Full Title

High-speed, long-term, 4D *in vivo* lifetime imaging in intact and injured zebrafish and mouse brains

by instant FLIM

Short Title

4D instant FLIM in intact and injured brains

Authors

Yide Zhang[1,6], Ian H. Guldner[2,4,5], Evan L. Nichols[2,3], David Benirschke[1], Cody J. Smith[2,3], Siyuan

Zhang[2,4,5], Scott S. Howard[1,4]*

Affiliations

[1]Department of Electrical Engineering, University of Notre Dame, Notre Dame, IN 46556, USA

[2]Department of Biological Sciences, University of Notre Dame, Notre Dame, IN 46556, USA

[3]Center for Stem Cells and Regenerative Medicine, University of Notre Dame, IN 46556, USA

[4]Mike and Josie Harper Cancer Research Institute, University of Notre Dame, IN 46556, USA

[5]Indiana University Melvin and Bren Simon Cancer Center, Indianapolis, IN 46202, USA

[6]Caltech Optical Imaging Laboratory, Andrew and Peggy Cherng Department of Medical

Engineering, California Institute of Technology, Pasadena, CA 91125, USA

*Corresponding author. Email: showard@nd.edu

Abstract

Traditional fluorescence microscopy is blind to molecular microenvironment information

that is present in fluorescence lifetime, which can be measured by fluorescence lifetime

imaging microscopy (FLIM). However, existing FLIM techniques are typically slow to

acquire and process lifetime images, difficult to implement, and expensive. Here, we present instant FLIM, an analog signal processing method that allows real-time streaming of fluorescence intensity, lifetime, and phasor imaging data through simultaneous image acquisition and instantaneous data processing. Instant FLIM can be easily implemented by upgrading an existing two-photon microscope using cost-effective components and our open-source software. We further improve the functionality, penetration depth, and resolution of instant FLIM using phasor segmentation, adaptive optics, and super-resolution techniques. We demonstrate through-skull intravital 3D FLIM of mouse brains to depths of 300 μm and present the first *in vivo* 4D FLIM of microglial dynamics in intact and injured zebrafish and mouse brains up to 12 hours.

Introduction

Imaging molecular contrast is essential to continued advances in cellular biology. Fluorescence microscopy has been a significant tool over the past decades in imaging cellular and sub-cellular molecular contrast (*1*). Traditional fluorescence microscopy typically obtains molecular contrast by labeling parts of cells with different fluorophores and imaging emission intensity. However, fluorescence emission contains a wealth of information on the molecular microenvironment that is not captured by the emission intensity but is present in the emission decay lifetime. By performing fluorescence lifetime imaging microscopy (FLIM), fluorophores with overlapping emission spectra can be differentiated, and physiological parameters such as pH, refractive index, ion concentration, dissolved gas concentration, and fluorescence resonance energy transfer (FRET) can be measured (*2*, *3*). When combined with multiphoton microscopy (MPM) (*4*, *5*), FLIM can provide lifetime measurements *in vivo* with high resolution, deep penetration, and reduced photodamage (*6*, *7*). Despite the biologically-relevant information provided by fluorescence

lifetime, the widespread use of FLIM in biomedical imaging has been limited due to its slow

image acquisition and processing speed, low signal-to-noise ratio (SNR), difficult

implementation, and high instrumentation cost (*8–13*).

State-of-the-art time-domain (TD) (*12–16*) and frequency-domain (FD) (*9*, *10*, *17–19*)

FLIM techniques have been developed to overcome the limitations above. The most widely

used and commercialized TD-FLIM technique is time-correlated single-photon counting

(TCSPC), which extracts the lifetime information from a histogram acquired by repetitively

recording the arrival time of each photon (*14–16*). Whereas state-of-the-art TCSPC systems

can acquire fluorescence decay data at around 10 μs/pixel, the processing for lifetime

information normally takes a much longer time through computationally extensive

procedures such as curve fitting and deconvolution. To reduce the data processing time, Ryu

et al. employed the analog mean-delay (AMD) method to extract the TD lifetime

information through numerical integration and realized real-time visualization of fixed

tissues (*12*). Besides TCSPC, Bower et al. utilized a high-frequency digitizer to directly

sample the TD fluorescence signal and achieved high-speed imaging of metabolic dynamics

in living cells (*13*). While both the AMD and the direct sampling methods reduced the pixel

dwell time to below 10 μs, they required expensive high-frequency digitizers (>$10,000),

and the limited computer memory and bandwidth prevented them from streaming lifetime

images without interruption due to the large amount of data sampled by the digitizers. On

the other hand, FD-FLIM techniques are less commonly used or commercialized compared

to TD-FLIM approaches due to their relatively difficult implementation and low SNR in

lifetime measurements (*8*, *11*). Conventional FD-FLIM techniques typically require

external modulation sources (usually sinusoidal modulation), high-voltage but imperfect

(less than 100% modulation degree) detector gain modulation, sequential phase shifting,

specialized electronics, and can achieve lifetime image acquisition and processing as fast as 40 μs/pixel (*9*, *10*, *17*, *18*). Recently, Raspe et al. demonstrated siFLIM, an FD-FLIM technique capable of video-rate (around 10 frames per second) lifetime imaging of living cells (*19*). However, siFLIM requires a dedicated camera, and it relies on a widefield microscope with no optical sectioning capabilities; therefore, it cannot be used to acquire 3D lifetime images. Overall, due to the limitations in acquisition or processing speed, SNR, or optical sectioning capabilities, so far, only a few existing FLIM systems have demonstrated 3D lifetime imaging; no systems, however, have demonstrated long-term, time-lapse 3D (i.e., 4D) *in vivo* FLIM through-skull deep in the brain, where useful ballistic photons are scarce due to severe scattering, and prolonged imaging time is not feasible because of animal movements (*20*).

Here, we demonstrate instant FLIM, a novel FD-FLIM technique that utilizes analog signal processing to simultaneously address the challenges in image acquisition and processing, SNR, implementation, and cost faced by existing FLIM methods. We present instant FLIM as a tool that provides real-time streaming of two-photon fluorescence intensity, lifetime, and phasor imaging data. The word "instant" refers to acquiring FLIM data simultaneously with instantaneous processing, where lifetime images and phasor plots (*3*, *21)* are instantaneously generated without recording the fluorescence decay curves, thus eliminating the limitations not only in the speed but also the computer memory and bandwidth faced by state-of-the-art FLIM techniques (*12*, *13*). We show that an instant FLIM system can be easily implemented as an upgrade to an existing two-photon laser scanning microscope for under $2,500 using cost-effective off-the-shelf components and our open-source, highly modularized, and user-friendly software packages. We also show that the imaging functionality, penetration depth, and resolution of an instant FLIM system

can be further improved using phasor segmentation (*22*), adaptive optics (*23*), and super-

resolution FLIM (*24*) techniques. Finally, employing an instant FLIM system, we

demonstrate intravital 3D lifetime imaging of mouse brains through-skull to depths of 300

μm, and present the first long-term, *in vivo* 4D lifetime imaging of microglial dynamics in

intact and injured larval zebrafish and adult mouse brains up to 12 hours.

Results

Instant FLIM system and principle

Built upon on our preliminary work presented in (*25*), instant FLIM uses a radio frequency

(RF) analog signal processing approach, where the two-photon excitation fluorescence

(2PEF) signal is split to four ways and mixed with the phase-shifted 80 MHz reference

signals from the Ti:sapphire laser in a multiplexing manner (Fig. 1A; see Fig. S1 and Fig.

S2 for details). It is essentially a homodyne FD-FLIM method to extract the lifetime

information from the first harmonic of the 80 MHz laser repetition in fluorescence. We

employed the reference signal from the laser because the laser repetition rate had a ± 1 MHz

variance so a fixed-frequency external reference signal could introduce errors, and the

implementation was cost-effective. In instant FLIM, the four paths of the fluorescence and

reference signals are operated independently and simultaneously during each measurement,

and the mixers' outputs are DC signals that can be digitized by almost any data acquisition

devices. The parallel, analog signal processing enabled simultaneous acquisition and

instantaneous processing of 2PEF intensity and lifetime images and phasor plots for single-

or multi-exponential decay analysis (Fig. 1B; see Section S1 and Section S2 for details).

Consequently, no additional acquisition time compared to conventional two-photon

intensity measurement was required in instant FLIM, and it was deconvolution-free and fit-

free, as lifetime images and phasor plots can be generated instantaneously through basic

matrix operations with no extra computation time or memory, eliminating the bottleneck of

state-of-the-art FLIM systems (*12*, *13*).

Fluorescence lifetime images alone are usually not enough to resolve the heterogeneity of

fluorophores with multi-exponential decays, as different fluorophore compositions could

result in the same lifetime measurements. Phasor plots, on the other hand, can resolve the

fluorophore heterogeneity because different fluorophore compositions can alter the phasor

components (horizontal coordinates *g* and vertical coordinates *s*) even if the average lifetime

might be unaltered (*21*). Conventionally, phasor plots are acquired by performing Fourier

transforms on fluorescence decay signals. Instant FLIM enables phasor plots generation at

the same speed as intensity images through simultaneous data acquisition and instantaneous

signal processing without computing Fourier transforms. To confirm the accuracy of phasor

measurements of the instant FLIM system, we acquired the phasor plots of four fluorophores

with single-exponential decays, which are usually used as fluorescence lifetime standards

as their lifetime values are stable and well-studied (*26*, *27*). As shown in Fig. 1C, the phasors

of these single-exponential fluorophores all located on the universal semicircle, and their

lifetime measurements matched the expected values. We then used the instant FLIM system

to acquire the intensity and lifetime images and phasor plots of heterogeneous fluorophore

mixtures consisting of fluorescein and rhodamine B: whereas the lifetimes of the mixtures

of different mole ratios of fluorescein and rhodamine B, e.g., 15:1 and 7.5:1, were hard to

distinguish (Fig. 1D), their difference in the phasor plot (Fig. 1E) was evident and could be

used to differentiate the two mixtures.

We next analyzed the SNR performance in lifetime measurements of an instant FLIM

system and compared it with conventional FD-FLIM techniques (see Section S3 for details).

The SNR performance was quantified using the *F*-value, i.e., photon economy, a widely used figure of merit to describe the sensitivity of FLIM techniques. The *F*-value is defined as the ratio of the uncertainties in lifetime and intensity measurements: a smaller *F*-value is desired as it represents a more accurate lifetime measurement with better SNR performance; there is, however, a lower limit of 1 on an *F*-value, which only exists in an ideal shot-noise-limited FLIM system where the available photons are utilized as efficiently as physically possible (*8*). Through Monte Carlo simulations and analytical error-propagation analyses, we showed that instant FLIM has a lower *F*-value, and therefore superior SNR performance, when compared to conventional FD-FLIM techniques for all fluorophores with a lifetime shorter than 4.5 ns. In fact, the *F*-value of instant FLIM approaches the ideal limit of 1, which equals to that of TCSPC. The superior SNR performance of instant FLIM was mainly achieved by efficiently utilizing the intrinsic 80 MHz mode-locked femtosecond laser pulses as the modulation source and employing the low-power external RF mixing, instead of the detector gain modulation used in conventional FD-FLIM systems (*8*, *11*).

With the simultaneous image acquisition, instantaneous data processing, and superior SNR performance, in this work, we demonstrated acquisition and processing of 2PEF intensity, lifetime, and phasor imaging data altogether in 12 µs/pixel using a pair of galvo scanners (Thorlabs GVS002) (Table S1). The 12 µs/pixel acquisition time in our instant FLIM system was mainly limited by the bandwidth of the galvo scanners, while the data processing time was around 2 ns/pixel running on an Intel Core i7-8750H 2.20 GHz laptop PC, which was orders of magnitude shorter than the image acquisition time. The pixel dwell time could be greatly reduced if resonant scanning mirrors were used to replace the galvo scanners (*13*), where the intensity of the excitation laser beam needed to be increased accordingly to compensate for the signal loss. We used galvo scanners, instead of resonant mirrors, mainly

because galvo scanners are the most widely used scanners in conventional two-photon laser scanning microscopes. Nevertheless, thanks to the modular design of the cost-effective hardware (Fig. S1) and our open-source software (*Instant-FLIM-Control* and *Instant-FLIM-Analysis*) (Fig. S5), modifications to an instant FLIM system such as replacing the galvo scanners with resonant mirrors can be easily implemented.

Instant FLIM with improved functionality, depth, and resolution

To make instant FLIM a powerful tool for 4D *in vivo* lifetime imaging in deep brains, we further improved its imaging functionality, depth, and resolution using phasor-based image segmentation, adaptive optics (AO), and super-resolution FLIM techniques, respectively. Phasor-based image segmentation techniques utilized phasor plots to segment pixels with similar phasor components (*g* and *s*) in a raw image to resolve fluorescence heterogeneity (*3*, *21*), thus improving the functionality of instant FLIM as an imaging tool. Here, we demonstrated two complementary approaches to implement phasor-based image segmentation: the manual phasor labeling (*21*) and the automatic phasor clustering techniques (*22*) (Fig. S6, A and B). In the phasor labeling approach, regions of interest (ROIs) were manually drawn on the phasor plot and the corresponding pixels in the raw image were labeled with different colors (*21*). Fig. 2A shows an example of how different cellular structures in a 3D instant FLIM stack of a fixed Cx3cr1-GFP/+ mouse brain could be segmented into different pseudo-colored groups by manually labeling their phasors with ROIs on the phasor plot in Fig. 2B (Movie S1). On the other hand, the phasor clustering approach segmented an instant FLIM image by applying an unsupervised machine learning approach, i.e., K-means clustering, to automatically cluster the phasors into a specified number of groups (e.g., K=3 as shown in Fig. S6B) and labeling the corresponding pixels in the raw image with different colors (*22*). The two segmentation methods are

complementary: the phasor labeling approach is flexible but could lead to biased results,

while the phasor clustering approach is unbiased and yet choosing a proper K value might

require multiple trials.

We also added a sensorless AO setup as an optional module to our instant FLIM system

(Fig. S1) to improve the penetration depth of our imaging system, which could be used to

compensate for the optical aberrations in *in vivo* through-skull imaging deep in mouse

brains (*23*). We used one of three optimization algorithms (see Section S4 for details) to

iteratively adjust the parameters of the wavefront shaping element, i.e., a deformable mirror

in our setup, to improve the image quality quantified by an optimization metric (*28*, *29*).

We acquired a 3D lifetime stack of the brain, through-skull, in a living Cx3cr1-GFP/+

mouse using the instant FLIM system combined with the AO setup, and compared it with

the 3D lifetime stack acquired from the same mouse but without AO (Movie S2). As shown

in Fig. 2C, when there was no AO, our instant FLIM system could only achieve a penetration

depth of 130 μm for through-skull 3D lifetime imaging in a living mouse brain; in

comparison, by adding a well-optimized AO module into our instant FLIM system, the

penetration depth for through-skull 3D FLIM in the same mouse was 300 μm, which was

more than twice deeper than the depth without AO.

Furthermore, we demonstrated super-resolution FLIM with our instant FLIM system using

generalized stepwise optical saturation (GSOS) microscopy (*24*), which used two instant

FLIM images acquired at different excitation powers to generate a super-resolution lifetime

image with preserved lifetime information and a $\sqrt{2}$-fold increase in spatial resolution (see

Section S5 for details). As shown in Fig. 2D, after linear combining two diffraction-limited

(DL) lifetime images acquired with excitation powers of 8.95 mW and 10.61 mW,

respectively, a super-resolution GSOS lifetime image of the same field-of-view can be

generated. Whereas we have utilized GSOS to generate 2D super-resolution FLIM images

of fixed cells like the ones in Fig. 2D (*24*), we could not demonstrate GSOS in 3D due to

the excessive time required to generate multiple 3D FLIM stacks under different excitation

powers using conventional FLIM systems. In instant FLIM, however, due to the analog

signal processing, 3D FLIM stacks could be generated at the same speed as 3D intensity

stacks. Therefore, by using GSOS in an instant FLIM system, generating a 3D super-

resolution FLIM stack only took twice the time of acquiring a 3D two-photon intensity

stack. In Fig. S8, we generated a 3D super-resolution FLIM stack by applying GSOS to a

pair of DL instant FLIM stacks of a fixed Cx3cr1-GFP/+ mouse brain acquired with

excitation powers of 12.31 mW and 13.44 mW, respectively. As shown in Movie S3 and

Fig. S8D, the cellular structures in the GSOS stack were better resolved with higher lateral

and axial resolutions compared to the ones in the DL stacks.

***In vivo* 4D instant FLIM imaging in intact zebrafish and mouse brains**

We characterized the *in vivo* performance of instant FLIM by measuring the fluorescence

lifetime and phasor components of green fluorescence protein (GFP) expressed in microglia

in living zebrafish and mouse brains, as microglia are critical for the functionality of the

brain in homeostatic and disease states (*30*, *31*). The GFP lifetime and the corresponding

phasor coordinates are indicators of the intracellular microenvironment and cellular status

(e.g., temperature (*32*), refractive index (*33*), stress (*34*), and apoptosis (*35*)). Before

measuring GFP lifetimes *in vivo*, we performed an *in vitro* instant FLIM experiment by

imaging GFP expressed in living MDA-MB-231-GFP cells under 18 different temperatures

from 18.1 °C to 46.7 °C (Fig. S6C). Whereas the intensity images showed no clear

distinctions under different temperatures, the fluorescence lifetimes decreased

monotonically as temperature increased, consistent with the results reported in (*32*). We

also used the phasor labeling (Fig. S6D) and phasor clustering (Fig. S6E) techniques to

segment the images and demonstrated that the GFP phasors under different temperatures

located differently on the phasor plot. The results confirmed that instant FLIM was able to

detect changes in the intracellular microenvironment through lifetime and phasor

measurements.

To test instant FLIM as an *in vivo* lifetime imaging modality, we first imaged *Tg(pu1:gfp)*

zebrafish at 4 days post fertilization (dpf) using regulatory sequences of *pu1* to express GFP

in myeloid cells including microglia and macrophages (Fig. 3A). So far, other than

anatomical locations, identifiable markers that distinctly label these cells are limited. To

determine if we could detect differences in GFP lifetimes within these cells, we imaged

neural regions where both central nervous system (CNS) and peripheral nervous system

(PNS) located myeloid cells could be detected and identifiable by their anatomical locations.

The instant FLIM measurement reported at least two distinct GFP lifetime profiles using

the phasor approach (Fig. 3, B-D). The phasors of PNS-located myeloid cells clustered

distinctly compared to that of CNS-located myeloid cells, which also segregated into at least

two distinct clusters by their *g* component, suggesting that lifetime could report

heterogeneity among myeloid cells. To investigate if lifetime differences were presented in

distinct subdomains of individual CNS-located myeloid cells over time, we performed 4D

instant FLIM by collecting 3D stacks every 15 minutes for 12 hours (Fig. 3, E and F). The

4D lifetime images in Fig. 3F show that the lifetimes of individual cellular subdomains

changed over time as the cells migrated (white arrowheads denote subdomains with

increased lifetimes over time). However, these changes largely occurred within the cellular

subdomains, whereas the average lifetimes of the cells remained stable during homeostasis

(Fig. 3E).

We repeated this analysis using skull-thinned Cx3cr1-GFP/+ adult mice whose microglia

were labeled with GFP (Fig. 4A). We also retro-orbitally injected Texas Red-Dextran into

the animal to distinguish blood vessels from microglia. These adult microglia displayed

dynamic and complex branching emanating from the cell body (Fig. 4B). Given that

microglia in larval zebrafish displayed distinct lifetime subdomains, we hypothesized that

adult microglia could also have distinct lifetimes in their cell bodies and surveilling

protrusions. To test this, we measured τ, g, and s and compared these values between the

cell bodies and protrusions. While we did not detect differences in g and s, the surveilling

protrusions displayed increased τ compared to that of the cell bodies (Fig. 4, C and D),

indicating that the protrusions had distinct changes in their microenvironment while

interacting with other neural cell types. We also employed 4D instant FLIM by taking 3D

stacks of the mouse microglia every two minutes for six minutes (Fig. 4, E and F). These

images demonstrated that while the microglia had dynamic processes, under homeostatic

conditions, the lifetimes of the cell bodies and surveilling protrusions were stable.

***In vivo* 4D instant FLIM imaging in injured zebrafish and mouse brains**

As the brain's immune cells, microglia sense injury by continuously surveying the

parenchyma with highly motile processes and converging to the site of injury to establish a

barrier between the healthy and injured brain tissue (*31*, *36*). We next used instant FLIM to

determine if we could detect lifetime changes in microglia when they responded to brain

injury. To do this, we created lesions in the larval *Tg(pu1:gfp)* zebrafish brain with the

femtosecond laser and acquired 4D instant FLIM movies of microglial response to the site

of injury by collecting 3D stacks every 15 minutes for 12 hours (Fig. 5A). Consistent with the injury response (*36*), microglia migrated to the site of injury (Fig. 5B; Movie S4). We investigated the phasors extracted from the 4D instant FLIM measurement. As shown in Fig. 5C, the phasors of pre-injury microglia clustered together; from 0 to 60 minutes post-injury (mpi), the phasors segregated into two clusters in opposite directions; this clustering continued after 60 mpi with few phasors resembling pre-injury ones. Meanwhile, in plotting average τ, g, and s values, we detected decreased s components in microglia after injury (Fig. 5D). We next analyzed the lifetimes of whole microglia and their individual cellular subdomains in response to injury (Fig. 5, E and F). After injury, both the microglia and subdomains adjusted their lifetimes, as denoted by the change in average lifetime values (Fig. 5E) and the increase of the number of red subdomains (red denoting longer lifetimes) (Fig. 5F), with continuing changes through 75 mpi. These observations demonstrated instant FLIM's capacity to detect lifetime changes *in vivo* after physiological challenges such as laser injury.

We then used instant FLIM to investigate if similar lifetime changes could be detected in adult mouse microglia when they responded to brain injury. We created lesions in the skull-thinned Cx3cr1-GFP/+ mouse brain with the femtosecond laser and acquired 4D instant FLIM movies of microglial dynamics in response to injury by collecting 3D stacks every two minutes for an hour (Fig. 6A). Adult mouse microglia were markedly more abundant than larval zebrafish microglia. Consistent with the observations reported in (*36*), the laser injury in the adult mouse brain parenchyma induced an instantaneous response from the microglia where processes were extended toward the site of injury (Fig. 6B; Movie S5). This was in contrast with microglia in larval zebrafish which utilized whole-cell migrations to the site of injury. Adult mouse microglial processes surrounded the lesion site similar to

the cloaking arrangement of macrophages in the PNS (*37*). We first compared lifetime

changes from before the injury (-2 mpi) to after the microglia have extended their processes

to the injury site (22 mpi) (Fig. 6C). To do this, we measured the lifetimes and phasor

components of the cell bodies, responding protrusions, and protrusion tips which were

migrating to the site of injury (Fig. 6D). These measurements did not detect changes in τ,

g, or *s* from -2 mpi to 22 mpi but did detect differences in τ and *g* between each of the

cellular subdomains. These data suggested that adult microglia maintained subcellular

lifetime and phasor differences while responding to injury (Movie S6). Further, we analyzed

lifetime dynamics throughout the process of protrusion extension to cloak the injury site

(Fig. 6, E and F). These measurements indicated that lifetimes and phasors in each

subdomain of the microglia remained relatively stable during early extension and cloaking

of the injury site (Fig. 6E). Considering the stability of lifetime and phasor information of

adult mouse microglia in response to injury, we used both the phasor labeling and phasor

clustering approaches to segment the 4D instant FLIM voxels into different cellular

structures (e.g., cell bodies, protrusions, protrusion tips, etc.) based on the similarity of their

phasors and distinguished their responses to the laser injury (Movie S7).

Taken together, these results demonstrate the capability of instant FLIM to delineate the

dynamics of lifetimes and phasors in diverse cellular subdomains in zebrafish and mouse

brains *in vivo*. They also highlight an important contrast in microglial responses to injury

early in development and adulthood: microglia in larval zebrafish demonstrated lifetime

changes after injury, while this effect was not observed in microglia in adult mice. Whereas

the fundamental causes of the GFP lifetime or phasor variations in microglial subdomains

are beyond the scope of this article, these variations measured by instant FLIM will be

beneficial to distinguish and label cellular subdomains in microglia and understand their

roles in the immune surveillance process (*31*).

Discussion

Through analog signal processing, we have demonstrated instant FLIM as a novel FD-FLIM

system that enables simultaneous acquisition and instantaneous processing of 2PEF

intensity, lifetime, and phasor imaging data. However, the performance does not come

without caveats. First, since instant FLIM utilizes the intrinsic femtosecond laser pulses as

the modulation source, the modulation frequency is fixed at 80 MHz; therefore, as shown

in Fig. S4C, the SNR performance in lifetime measurements, quantified by the *F*-value, will

become worse for fluorophores with longer lifetimes. As a result, instant FLIM will perform

best with short-lifetime fluorophores such as rhodamine B and indocyanine green (ICG)

(*38*); for long-lifetime fluorophores or samples consisting of a wide range of lifetime

components (*39*), the pixel dwell time for instant FLIM measurements should be increased

accordingly to compensate for the lower photon economy. Second, while it is advantageous

for instant FLIM to generate lifetime images and phasor plots directly without recording

fluorescence decay curves to eliminate limitations in computer memory and bandwidth,

users who are familiar with TD-FLIM systems may find it less intuitive or not

straightforward to interpret the lifetime results. This is a trade-off between functionality and

cost, as fluorescence decay curves can only be fully recorded using expensive TCSPC or

high-frequency digitizers. Third, due to the electronic and RF components required to

implement the analog signal processing in instant FLIM, additional electronic noise such as

thermal noise and electromagnetic interference from the environment could be introduced

to the lifetime measurement if the instruments were not well connected or shielded. In our

experience, however, using low-noise amplifiers and properly shielding the electronics

could successfully suppress the additional noise, and shot-noise limited measurements could

be achieved.

The four-phase analog signal processing in the current instant FLIM system can be further

improved. Theoretically, to extract lifetime information via homodyne FD-FLIM

measurements, minimally only three phase images are required, and the lifetime

measurement accuracy can be further improved if more phase images, e.g., 12, are employed

(*19*). In conventional FD-FLIM systems, these phase images need to be captured

sequentially, so acquiring more phase images requires a longer acquisition time. Meanwhile,

for more phase images, the processing for lifetime information becomes more complicated

and time-consuming, as complex trigonometry calculations or curve fittings are required. In

this work, we only acquired four phase images to reduce the cost of the system and the

complexity of lifetime and phasor calculations. Nevertheless, following the principle of

multiplexing analog signal processing, the current instant FLIM setup could be readily

expanded to allow simultaneous acquisition of 12 or more phase images, where the 2PEF

signal could be split to 12 or more paths and mixed with the phase-shifted reference signals

from the femtosecond laser; therefore, the lifetime measurement accuracy of instant FLIM

could be improved while no extra image acquisition time would be needed.

In conclusion, we have presented instant FLIM as a powerful tool for high-speed, long-term,

4D *in vivo* FLIM that allows real-time streaming of 2PEF intensity, lifetime, and phasor

imaging data. We have also demonstrated that an instant FLIM system could be combined

with phasor labeling and clustering, AO, and GSOS to provide versatile phasor-based image

segmentation, deep penetration depths, and super-resolution FLIM performances. In

addition, we have demonstrated 3D *in vivo* FLIM of mouse brains through-skull to depths

of 300 μm, and we have achieved, to our knowledge, the first long-term, *in vivo*, 4D lifetime imaging of microglia dynamics in intact and injured larval zebrafish and adult mouse brains up to 12 hours. Biologically, the identification of cellular subdomains with different fluorescence lifetime properties of a cytosolic fluorophore was surprising. These domains could be the result of a variety of phenomena such as distinct cell signaling hubs or organelle density. Regardless, these results were accomplished by upgrading a conventional two-photon laser scanning microscope using cost-effective off-the-shelf components with a total cost less than $2,500 and our fully open-source, highly modularized, and user-friendly software packages (*Instant-FLIM-Control* and *Instant-FLIM-Analysis*). As a result, instant FLIM can be easily accessed by many labs and has the potential to enable future discoveries in biology, including the mechanism of lifetime subdomains identified here, in addition to a wide variety of disciplines.

Materials and Methods

Experimental setup and analog signal processing

We implemented the instant FLIM system based on a custom-built two-photon laser scanning microscope (Fig. 1A; Fig. S1). The intensity of a mode-locked Ti:sapphire laser (Spectra-Physics Mai Tai BB, 710-990 nm, 100 fs, 80 MHz) is controlled by a neutral density filter (NDF), a motorized half-wave plate, and a polarizing beam splitter (PBS). A power meter is used to measure the excitation power by monitoring a small fraction of the laser beam reflected by a glass slide. A mechanical shutter (Thorlabs SHB1T) is used to block the laser beam when no imaging acquisition takes place. A sensorless adaptive optics (AO) setup consisting of a deformable mirror (Thorlabs DMP40-P01), a beam expander composed of two achromatic doublets (Thorlabs AC254-030-B, AC254-075-B), an achromatic quarter-wave plate (Thorlabs AQWP05M-980), and another PBS is utilized to

correct the wavefront of the excitation beam in order to improve the imaging depth (Section S4). The AO setup is optional and can be switched into and out of the optical path using a folding mirror. The laser beam is directed to a conventional two-photon microscopy setup consisting of a pair of galvo scanners (Thorlabs GVS002), a scan lens (Thorlabs AC254-040-B), a tube lens (Thorlabs AC254-200-B), an objective lens (Nikon CFI APO NIR, 40x, 0.8 NA, or Olympus XLPLN25XWMP2, 25x, 1.05 NA), and a motorized stage (Prior OptiScan III). A long pass filter is used to block ambient light from entering the objective. The 2PEF is epi-collected by the objective lens, reflected by a dichroic mirror, filtered through a set of bandpass and short pass filters to eliminate residual excitation, and detected by a photomultiplier tube (PMT) (Hamamatsu H7422PA-40) through a collection lens.

The analog signal processing module in instant FLIM utilizes the fluorescence signal from the PMT and the 80 MHz reference signal from the Ti:sapphire laser to generate the intensity, lifetime, and phasor data simultaneously. As shown in Fig. S2, the current signal from the PMT is amplified and converted to a voltage signal by a transimpedance amplifier (Aricorp DC-100), filtered by a low pass filter (LPF) (Mini-Circuits BLP-90+), and separated into DC and RF parts by a bias tee (Mini-Circuits ZFBT-282-1.5A+). The DC signal (V_{DC}) is acquired by a data acquisition (DAQ) card (National Instruments PCIe-6323) to reconstruct the intensity image. The RF signal is amplified by a low-noise amplifier (LNA) (Mini-Circuits ZX60-P103LN+) and split to four paths by a 4-way power splitter (Mini-Circuits ZSC-4-3+). Meanwhile, the 80 MHz reference signal from the laser, $v_{ref}(t)$, is filtered by an LPF to eliminate higher harmonics, amplified by an LNA, and split to four signal paths, $v_{80MHz}(t)$, also by a power splitter. A phase shift is introduced to each reference signal path by a pair of phase shifters (Mini-Circuits JSPHS-150 with TB-152+). Note that each phase shifter can introduce a phase shift within π to the 80 MHz signal; connecting

them in tandem introduces a total phase shift within 2π for each path. The phase shifts are independently controlled by the bias voltages generated by the DAQ card. The four phase-shifted reference signals are then amplified by LNAs and directed to four RF mixers (Mini-Circuits ZAD-3H+). Each mixer takes a reference signal path, $v_{LO}(t, \varphi)$, to its local oscillator (LO) port and a PMT signal path, $v_{RF}(t)$, to its RF port and generates a mixed signal, $v_{IF}(t, \varphi)$, on its intermediate frequency (IF) port. The IF signals from each mixer are then filtered to DC, i.e., $V_{IF}(\varphi)$, by an LPF (Thorlabs EF502) and measured by another DAQ card (National Instruments PCI-6110). In the end, for each intensity image (2D, 3D, or 4D) acquired, four corresponding mixer images are acquired simultaneously, so the data acquisition is intrinsically synchronized and effect of the PMT timing jitter is minimized. Fluorescence lifetime images as well as phasor plots are then instantaneously generated through basic matrix operations. The DAQ cards are also used to control the motorized half-wave plate, the shutter, and the galvo scanners during the imaging process. The motorized stage and the deformable mirror, on the other hand, are controlled directly by the computer through universal serial bus (USB) ports. Note that all electronic components in the instant FLIM system are impedance matched to 50 Ω to suppress signal reflections, and LNAs are used and the RF components are properly shielded to minimize additional electronic noise introduced to the measurement.

The parts and price list for the implementation of an instant FLIM system is presented in Table S2. The total cost to upgrade an existing two-photon laser scanning microscope (including data acquisition devices) to an instant FLIM system is less than $2,500.

Simultaneous acquisition and processing of intensity, lifetime, and phasor data

With the analog signal processing in instant FLIM, the fluorescence intensity, lifetime, and phasor data can be acquired simultaneously (Fig. 1B; Section S1). Specifically, the 2PEF intensity image is generated from the DC part of the PMT signal:

$$V_{DC} = \frac{BP^2 c}{T} + O_B, \tag{1}$$

where P is the excitation power, c is the fluorophore concentration, T is the modulation period of the Ti:sapphire laser, B and O_B are the conversion loss and offset from the bias tee's RF&DC to DC ports, respectively. The lifetime and phasor data, on the other hand, are obtained by applying basic mathematical operations on the outputs of the four mixers' IF ports:

$$V_{IF}(\varphi) = \frac{MP^2 c}{T} \sum_i a_i \frac{1}{1 + \tau_i \omega} [\sin(\varphi) + \tau_i \omega \cos(\varphi)] + O_M, \tag{2}$$

where φ is the phase shift introduced by the phase shifters, a_i is the intensity-weighted fractional contribution of the fluorophore with lifetime τ_i ($\sum_i a_i = 1$), ω is the angular modulation frequency, M and O_M are the conversion loss and offset from the mixer's RF to IF ports, respectively. The average (phase) lifetime (2) image is calculated as

$$\tau = \frac{1}{\omega} \frac{V_{IF}(0) - V_{IF}(\pi)}{V_{IF}(0.5\pi) - V_{IF}(1.5\pi)}, \tag{3}$$

and the components of the phasors are obtained as

$$
\begin{aligned}
g &= \frac{B}{2M} \frac{V_{IF}(0.5\pi) - V_{IF}(1.5\pi)}{V_{DC} - O_B} = \sum_i a_i \frac{1}{1 + (\tau_i \omega)^2}, \\
s &= \frac{B}{2M} \frac{V_{IF}(0) - V_{IF}(\pi)}{V_{DC} - O_B} = \sum_i a_i \frac{\tau_i \omega}{1 + (\tau_i \omega)^2},
\end{aligned} \tag{4}
$$

where M/B and O_B are calibrated before measurements using the procedures detailed in Section S2.

Image reconstruction and analysis

All image reconstructions and analyses were performed with our open-source *Instant-FLIM-Control* and *Instant-FLIM-Analysis* (Fig. S5) software developed for this work. Additional image processing and visualization were performed using ImageJ (US National Institutes of Health), Matlab (MathWorks), Imaris (Bitplane), or Illustrator (Adobe) software.

The raw intensity [Eq. (1)], *g*, and *s* [Eq. (4)] images from 2D, 3D, and 4D instant FLIM measurements were exported as 32-bit TIF files using the *Instant-FLIM-Control* program. Whereas the program allows the export of additional FLIM data, to reduce the consumption of the computer's storage space, we exported only the raw intensity, *g*, and *s* images, which can be used to reconstruct other types of FLIM data. We used the "Correct 3D Drift" ImageJ plugin (*40*) to register the 4D raw images to correct for the sample drift during time-lapse measurements. To perform the image registration simultaneously on the three raw images, we created a color image by merging the raw intensity, *g*, and *s* images as its red, green, and blue channels, respectively; then, as the 3D image registration was performed on the red (intensity) channel, the other channels were registered simultaneously. The registered image was cropped to remove the empty voxels generated from the registration process, and its channels were split into three separate images, which correspond to the registered intensity, *g*, and *s* images.

The intensity, *g*, and *s* images were then imported to the *Instant-FLIM-Analysis* program to generate other types of FLIM data. Since the raw FLIM data usually have a low SNR (*11*), we provided a filtering option in the program, such that one could apply a median filter (3×3 or 5×5 kernels) or a smoothing filter on the raw images, one or multiple times, to

increase the SNR; note that applying a median filter to the phasor images does not decrease

the image resolution (*21*). In this work, we applied a 3×3 median filter three times on the

raw phasor images for all *in vivo* measurements. The program could also uniformly scale

the *g* and *s* images by a constant ratio to effectively zoom-in or zoom-out the phasor plot

while keeping the calculated lifetime unaltered; a ratio between 0.7 to 1.0 was used in our

measurements to post-compensate for the inaccuracy in system calibration and make sure

that the majority of the phasor points fall inside the universal semicircle $[(g - 0.5)^2 + s^2 =$

0.25]. We then generated the phasor plot from the pre-processed *g* and *s* images. The phasor

plot was a 2D histogram of the phasor components, *g* and *s*, where the magnitude

(represented with a color map) of each grid (with a pre-defined size) in the 2D histogram

represented the number of phasor points located inside that grid. Note that the phasor plot

could be generated simultaneously with intensity and lifetime images in the *Instant-FLIM-*

Control program. In the *Instant-FLIM-Analysis* program, however, the phasor plot could be

further analyzed using phasor-based image segmentation techniques. To perform the phasor

analysis, the program allowed the user to either (a) manually draw ROIs on the phasor plot

and segment the pixels corresponding to the phasor points enclosed by the ROIs with

different colors (*21*), or (b) automatically group the phasors into *K* clusters using the K-

means clustering algorithm and segment the pixels corresponding to the phasor clusters with

different colors (*22*); both techniques could segment the raw image into structures with

different lifetime/phasor characteristics (Fig. S6). After the analysis described above, the

raw lifetime image (gray-scale image with pixel value as lifetime), composite lifetime image

(RGB image with pixel brightness as intensity, hue as lifetime), phasor plot (RGB image),

and segmented images based on phasor labeling or phasor clustering techniques (RGB

image) were generated and exported as 32-bit TIF files. For 3D images, the TIF files were

imported into ImageJ and the maximized z-projections of the stacks were generated. For 4D

measurements, the stacks were first converted to hyperstacks in ImageJ to facilitate the time-

lapse analysis, and a time-lapse maximized z-projection sequence could be generated. We

also used Imaris to visualize the 3D and 4D stacks (Fig. 2, A and C; Fig. S7 and Fig. S8;

Movie S1-Movie S5, Movie S7) and enhance the qualitative information of FLIM by surface

rendering the composite lifetime images (Fig. 5B; Movie S4).

To quantify the results of *in vivo* instant FLIM measurements (Fig. 3-Fig. 6), we extracted

the raw lifetime as well as *g* and *s* values from the TIF files exported by the *Instant-FLIM-*

Analysis program. Specifically, the files were opened in ImageJ, a single-plane ROI was

drawn around the cell of interest, and the mean value was measured within that ROI. The

plots representing the phasor locations of cells were generated using Illustrator (Fig. 3D,

Fig. 5C). Using the *Instant-FLIM-Analysis* program, ROIs were drawn on the phasor plots

to correspond with the pixels representing individual cells. Individual ROIs were drawn for

each cell analyzed. The locations for each of these ROIs were then recapitulated within the

universal phasor semicircle. These specific locations were determined by exporting each

phasor plot with the drawn ROIs and determining the coordinates of the ROIs within the

exported phasor plot image using ImageJ. The coordinates were then used to place

representations of each cell in the proper location within the universal phasor semicircle in

Illustrator. In Fig. 3-Fig. 6 separate statistical tests on τ, *g,* and *s* were performed to directly

compare lifetime measurements between experimental groups. This method allows for

determination of specific lifetime components which are different between samples or

experimental conditions.

Animal procedures and sample preparation

All animal studies were conducted in accordance with the University of Notre Dame Institutional Animal Care and Use Committee guidance. The acquisition parameters for all the images shown in this work are presented in Table S1.

Intravital imaging of the mouse brain was performed similarly to previously described (*41*). Briefly, Cx3cr1-GFP/+ mice (generated in-house by crossing Cx3cr1-GFP/GFP mice with wildtype C57Bl/6 mice) were anesthetized with ketamine and xylazine cocktail by intraperitoneal injection. The mouse's head was secured and fixed in place using a stereotaxic instrument (Stoelting Co), and the skull was exposed with a midline scalp incision. A high-speed microdrill (Ideal Microdrill) equipped with a 0.7 mm burr (Fine Science Tools, 19007-09) was used to thin the skull to approximately 30 μm in thickness, using light sweeping motions to thin the skull gradually without applying significant pressure to the brain. In some instances, dental cement was used to border the thinned skull to form a bowl-like barrier to help contain water for imaging. Following surgery, the anesthetized mouse was administered a retro-orbital injection of 70 kDa Texas Red-Dextran (Invitrogen D1864) to enable fluorescent detection of blood vessels. The mouse was placed on the stage for imaging and its heart rate, respiration rate, and toe-pinch reflex were monitored periodically to ensure that it was fully anesthetized and not under duress.

The transgenic zebrafish line used in this study was *Tg(pu1:gfp)*. All embryos were generated from pairwise matings and raised at 28 ℃ until imaging. Stable, germline transgenic zebrafish were used for all experiments. Embryos of either sex were used for all experiments. At 4 dpf, the embryos were dechorionated and anesthetized with 3-amino-benzoic acid ester. After anesthetization, embryos were mounted on their ventral side in

0.8% low-melting-point agarose in 35 mm Petri dishes with glass bottoms. Following

mounting, the embryos were imaged using the instant FLIM system described above.

To prepare a fixed mouse brain to image for select experiments, a living Cx3cr1-GFP/+

mouse was first deeply anesthetized with isoflurane. Next, the mouse's chest cavity was

opened to expose the heart, and the mouse was provided with a 100 μL injection of fixable

Dextran 594 directly into the heart. After allowing the dextran to circulate for 1 minute, the

mouse was perfused with 10 mL ice-cold 4% PFA to thoroughly fix the brain. Subsequently,

the brain was extracted and fixed in 4% PFA overnight at 4 ºC, and washed in 1x PBS, after

which point it was ready for imaging.

MDA-MB-231-EGFP cells were cultured in DMEM High Glucose supplemented with 10%

FBS and 1% Penicillin-Streptomycin in an incubator at 37 ºC, 5% CO_2. Prior to imaging,

the cells were grown to about 80% confluence for the imaging experiments. During

imaging, refrigerated or heated culture media were added to the cell culture to change the

microenvironment temperature, which was simultaneously monitored by a thermometer

placed in the media.

FluoCells prepared slide #1 (Invitrogen F36924) was used as a biological test slide to

evaluate the performance of the instant FLIM system. This test slide contained bovine

pulmonary artery endothelial (BPAE) cells labeled with multiple fluorescent dyes: the

mitochondria were stained with MitoTracker Red CMXRos, the F-actin was labeled with

Alexa Fluor 488 phalloidin, and the nuclei were labeled with DAPI.

Four lifetime standards, i.e., fluorophore solutions with known fluorescence lifetimes, were

prepared as previously described (*26*, *27*): 1 mM coumarin 6 in methanol (2.3 ns at 20 ℃),

1 mM coumarin 6 in ethanol (2.4 ns at 20 ℃), 1mM fluorescein in 0.1 M NaOH (4.0 ns at

20 ℃), and 1 mM rhodamine B in water (1.7 ns at 20 ℃). To prepare the standards, the

coumarin 6 (Sigma-Aldrich 546283) was dissolved in methanol (VWR BDH2029) and

ethanol (Millipore 818760), respectively; the fluorescein (Sigma-Aldrich F245-6) was

dissolved in NaOH 1.0N in aqueous solution (VWR BDH7222); and the rhodamine B (Alfa

Aesar A13572) was dissolved in water. The fluorophore mixtures were acquired by mixing

the fluorescein and rhodamine B lifetime standards described above with different mole

ratios.

Supplementary Materials

Supplementary material for this article is available.

Section S1. Principle of instant FLIM

Section S2. System calibration

Section S3. SNR analysis of instant FLIM

Section S4. Instant FLIM with adaptive optics

Section S5. Super-resolution instant FLIM with GSOS

Fig. S1. Detailed diagram and photos of an instant FLIM system.

Fig. S2. Analog signal processing in instant FLIM.

Fig. S3. Instant FLIM system calibration using a lifetime standard.

Fig. S4. SNR analysis of instant FLIM and conventional FD-FLIM techniques.

Fig. S5. Overview of the *Instant-FLIM-Control* and *Instant-FLIM-Analysis* software.

Fig. S6. Instant FLIM with phasor labeling and phaser clustering techniques.

References and Notes

1. J. W. Lichtman, J.-A. Conchello, Fluorescence microscopy. *Nat. Methods*. **2**, 910–919

(2005).

2. M. Y. Berezin, S. Achilefu, Fluorescence Lifetime Measurements and Biological Imaging.

Chem. Rev. **110**, 2641–2684 (2010).

3. Y. Sun, R. N. Day, A. Periasamy, Investigating protein-protein interactions in living cells

using fluorescence lifetime imaging microscopy. *Nat. Protoc.* **6**, 1324–1340 (2011).

4. W. Denk, J. H. Strickler, W. W. Webb, Two-photon laser scanning fluorescence microscopy.

Science. **248**, 73–6 (1990).

5. W. R. Zipfel, R. M. Williams, W. W. Webb, Nonlinear magic: multiphoton microscopy in

the biosciences. *Nat. Biotechnol.* **21**, 1369–1377 (2003).

6.   S. Sakadžić, E. Roussakis, M. a Yaseen, E. T. Mandeville, V. J. Srinivasan, K. Arai, S.

Ruvinskaya, A. Devor, E. H. Lo, S. a Vinogradov, D. a Boas, Two-photon high-resolution

measurement of partial pressure of oxygen in cerebral vasculature and tissue. *Nat. Methods*.

7, 755–759 (2010).

7.   S. S. Howard, A. Straub, N. G. Horton, D. Kobat, C. Xu, Frequency-multiplexed in vivo

multiphoton phosphorescence lifetime microscopy. *Nat. Photonics*. **7**, 33–37 (2012).

8.   J. Philip, K. Carlsson, Theoretical investigation of the signal-to-noise ratio in fluorescence

lifetime imaging. *J. Opt. Soc. Am. A*. **20** (2003), pp. 368–379.

9.   M. J. Booth, T. Wilson, Low-cost, frequency-domain, fluorescence lifetime confocal

microscopy. *J. Microsc.* **214**, 36–42 (2004).

10.   R. A. Colyer, C. Lee, E. Gratton, A novel fluorescence lifetime imaging system that

optimizes photon efficiency. *Microsc. Res. Tech.* **71**, 201–213 (2008).

11.   Y. Zhang, A. A. Khan, G. D. Vigil, S. S. Howard, Investigation of signal-to-noise ratio in

frequency-domain multiphoton fluorescence lifetime imaging microscopy. *J. Opt. Soc. Am.*

A. **33**, B1 (2016).

12.   J. Ryu, U. Kang, J. Kim, H. Kim, J. H. Kang, H. Kim, D. K. Sohn, J. Jeong, H. Yoo, B.

Gweon, Real-time visualization of two-photon fluorescence lifetime imaging microscopy

using a wavelength-tunable femtosecond pulsed laser. *Biomed. Opt. Express*. **9**, 3449 (2018).

13.   A. J. Bower, J. Li, E. J. Chaney, M. Marjanovic, D. R. Spillman, S. A. Boppart, High-speed

imaging of transient metabolic dynamics using two-photon fluorescence lifetime imaging

microscopy. *Optica*. **5**, 1290 (2018).

14.   W. Becker, A. Bergmann, M. A. Hink, K. König, K. Benndorf, C. Biskup, Fluorescence

lifetime imaging by time-correlated single-photon counting. *Microsc. Res. Tech.* **63**, 58–66

(2004).

15. M. C. Skala, K. M. Riching, D. K. Bird, A. Gendron-Fitzpatrick, J. Eickhoff, K. W. Eliceiri,

P. J. Keely, N. Ramanujam, In vivo multiphoton fluorescence lifetime imaging of protein-

bound and free nicotinamide adenine dinucleotide in normal and precancerous epithelia. *J.*

Biomed. Opt. **12**, 024014 (2007).

16. M. A. Yaseen, J. Sutin, W. Wu, B. Fu, H. Uhlirova, A. Devor, D. A. Boas, S. Sakadžić,

Fluorescence lifetime microscopy of NADH distinguishes alterations in cerebral metabolism

in vivo. *Biomed. Opt. Express*. **8**, 2368 (2017).

17. P. T. C. So, T. French, W. M. Yu, K. M. Berland, C. Y. Dong, Time-resolved fluorescence

microscopy using two-photon excitation. *Bioimaging*. **3**, 49–63 (1995).

18. E. Gratton, Fluorescence lifetime imaging for the two-photon microscope: time-domain and

frequency-domain methods. *J. Biomed. Opt.* **8**, 381 (2003).

19. M. Raspe, K. M. Kedziora, B. van den Broek, Q. Zhao, S. de Jong, J. Herz, M. Mastop, J.

Goedhart, T. W. J. Gadella, I. T. Young, K. Jalink, siFLIM: single-image frequency-domain

FLIM provides fast and photon-efficient lifetime data. *Nat. Methods*. **13**, 501–504 (2016).

20. F. Helmchen, W. Denk, Deep tissue two-photon microscopy. *Nat. Methods*. **2**, 932–940

(2005).

21. S. Ranjit, L. Malacrida, D. M. Jameson, E. Gratton, Fit-free analysis of fluorescence lifetime

imaging data using the phasor approach. *Nat. Protoc.* **13**, 1979–2004 (2018).

22. Y. Zhang, T. Hato, P. C. Dagher, E. L. Nichols, C. J. Smith, K. W. Dunn, S. S. Howard,

Automatic segmentation of intravital fluorescence microscopy images by K-means

clustering of FLIM phasors. *Opt. Lett.* **44**, 3928–3931 (2019).

23. N. Ji, Adaptive optical fluorescence microscopy. *Nat. Methods*. **14**, 374–380 (2017).

24. Y. Zhang, D. Benirschke, O. Abdalsalam, S. S. Howard, Generalized stepwise optical

saturation enables super-resolution fluorescence lifetime imaging microscopy. *Biomed. Opt.*

Express. **9**, 4077 (2018).

25.   Y. Zhang, I. H. Guldner, E. L. Nichols, D. Benirschke, C. J. Smith, S. Zhang, S. S. Howard,

in *Proc. SPIE 10882, Multiphoton Microscopy in the Biomedical Sciences XIX*, A.

Periasamy, P. T. So, K. König, Eds. (SPIE, 2019), p. 108822H.

26.   N. Boens, W. Qin, N. Basarić, J. Hofkens, M. Ameloot, J. Pouget, J.-P. Lefèvre, B. Valeur,

E. Gratton, M. VandeVen, N. D. Silva, Y. Engelborghs, K. Willaert, A. Sillen, G. Rumbles,

D. Phillips, A. J. W. G. Visser, A. van Hoek, J. R. Lakowicz, H. Malak, I. Gryczynski, A. G.

Szabo, D. T. Krajcarski, N. Tamai, A. Miura, Fluorescence Lifetime Standards for Time and

Frequency Domain Fluorescence Spectroscopy. *Anal. Chem.* **79**, 2137–2149 (2007).

27.   A. S. Kristoffersen, S. R. Erga, B. Hamre, Ø. Frette, Testing Fluorescence Lifetime

Standards using Two-Photon Excitation and Time-Domain Instrumentation: Rhodamine B,

Coumarin 6 and Lucifer Yellow. *J. Fluoresc.* **24**, 1015–1024 (2014).

28.   D. Debarre, M. J. Booth, T. Wilson, Image based adaptive optics through optimisation of

low spatial frequencies. *Opt. Express*. **15**, 8176 (2007).

29.   G. Palczewska, Z. Dong, M. Golczak, J. J. Hunter, D. R. Williams, N. S. Alexander, K.

Palczewski, Noninvasive two-photon microscopy imaging of mouse retina and retinal

pigment epithelium through the pupil of the eye. *Nat. Med.* **20**, 785–789 (2014).

30.   F. Peri, C. Nüsslein-Volhard, Live Imaging of Neuronal Degradation by Microglia Reveals

a Role for v0-ATPase a1 in Phagosomal Fusion In Vivo. *Cell*. **133**, 916–927 (2008).

31.   L. Bernier, C. J. Bohlen, E. M. York, B. Stevens, B. A. Barres, B. A. Macvicar, L. Bernier,

C. J. Bohlen, E. M. York, H. B. Choi, A. Kamyabi, Nanoscale Surveillance of the Brain by

Microglia via Article Nanoscale Surveillance of the Brain by Microglia via cAMP-Regulated

Filopodia. *Cell Rep.* **27**, 2895-2908.e4 (2019).

32.   P. Leiderman, D. Huppert, N. Agmon, Transition in the temperature-dependence of GFP

fluorescence: From proton wires to proton exit. *Biophys. J.* **90**, 1009–1018 (2006).

33.   H.-J. van Manen, P. Verkuijlen, P. Wittendorp, V. Subramaniam, T. K. van den Berg, D.

Roos, C. Otto, Refractive Index Sensing of Green Fluorescent Proteins in Living Cells Using

Fluorescence Lifetime Imaging Microscopy. *Biophys. J.* **94**, L67–L69 (2008).

34. T. Nakabayashi, I. Nagao, M. Kinjo, Y. Aoki, M. Tanaka, N. Ohta, Stress-induced

environmental changes in a single cell as revealed by fluorescence lifetime imaging.

Photochem. Photobiol. Sci. **7**, 671 (2008).

35. T. Ito, S. Oshita, T. Nakabayashi, F. Sun, M. Kinjo, N. Ohta, Fluorescence lifetime images

of green fluorescent protein in HeLa cells during TNF-α induced apoptosis. *Photochem.*

Photobiol. Sci. **8**, 763 (2009).

36. D. Davalos, J. Grutzendler, G. Yang, J. V. Kim, Y. Zuo, S. Jung, D. R. Littman, M. L. Dustin,

W.-B. Gan, ATP mediates rapid microglial response to local brain injury in vivo. *Nat.*

Neurosci. **8**, 752–758 (2005).

37. S. Uderhardt, A. J. Martins, J. S. Tsang, T. Lämmermann, R. N. Germain, Resident

Macrophages Cloak Tissue Microlesions to Prevent Neutrophil-Driven Inflammatory

Damage. *Cell*. **177**, 541-555.e17 (2019).

38. A. Gerega, N. Zolek, T. Soltysinski, D. Milej, P. Sawosz, B. Toczylowska, A. Liebert,

Wavelength-resolved measurements of fluorescence lifetime of indocyanine green. *J.*

Biomed. Opt. **16**, 067010 (2011).

39. D. M. Grant, J. McGinty, E. J. McGhee, T. D. Bunney, D. M. Owen, C. B. Talbot, W. Zhang,

S. Kumar, I. Munro, P. M. Lanigan, G. T. Kennedy, C. Dunsby, A. I. Magee, P. Courtney,

M. Katan, M. A. A. Neil, P. M. W. French, High speed optically sectioned fluorescence

lifetime imaging permits study of live cell signaling events. *Opt. Express*. **15**, 15656 (2007).

40. A. Parslow, A. Cardona, R. J. Bryson-Richardson, Sample Drift Correction Following 4D

Confocal Time-lapse Imaging. *J. Vis. Exp.*, 1–4 (2014).

41. J. Grutzendler, N. Kasthuri, W.-B. Gan, Long-term dendritic spine stability in the adult

cortex. *Nature*. **420**, 812–816 (2002).

42.   S. R. Kurtz, Mixers as Phase Detectors. *Watkins-Johnson Tech-Notes*. **5**, 1 (1978).

766
767
Acknowledgments

Funding: This work was supported by the University of Notre Dame, the Center for

Zebrafish Research and Center of Stem Cells and Regenerative Medicine at the University

of Notre Dame, the National Science Foundation under Grant No. CBET-1554516 (S.S.H.),

the National Institutes of Health R01 CA194697, R01 CA222405 (S.Z.), R01 NS107553

(C.J.S), the Elizabeth and Michael Gallagher Family (C.J.S.), the Alfred P. Sloan

Foundation (C.J.S.), and the Berry Family Foundation Graduate Fellowship of Advanced

Diagnostics & Therapeutics (AD&T) (Y.Z.).

Author contributions: Y.Z. and S.S.H. conceived and coordinated the project, designed

and built the microscope, wrote the control and image-processing software, and performed

the imaging experiments. I.H.G. and S.Z. performed the mouse surgery, acquired the

images, and analyzed the data. E.L.N. and C.J.S. prepared the zebrafish, performed the

zebrafish imaging experiments, and analyzed the data. D.B. assisted with the microscope

assembly and performed the temperature-dependent imaging experiment. S.S.H., S.Z., and

C.J.S. supervised the study. All authors contributed to the writing and editing of the

manuscript.

Competing interests: The authors declare that there are no competing interests.

Data and materials availability: The repositories of the open-source *Instant-FLIM-

Control* (https://github.com/yzhang34/Instant-FLIM-Control.git) and *Instant-FLIM-

Analysis* (https://github.com/yzhang34/Instant-FLIM-Analysis.git) software are hosted on

GitHub and they are freely available for academic use. Detailed protocols describing how

to use the two software packages are included within the repositories. All data needed to

evaluate the conclusions in this paper are present in the paper and/or the Supplementary

Materials. Additional data related to this paper may be requested from the authors.

Fig. 1. Instant FLIM system.

(**A**) Brief diagram of an instant FLIM system. Excitation (red) is generated by a

femtosecond laser and sent to a custom-built two-photon laser scanning microscope. Two-

photon excitation fluorescence (green) is collected by a photomultiplier tube (PMT), whose

signal is filtered and separated to two parts by a bias tee; the RF part is amplified, split to

four ways, and mixed with the split laser reference signals with different phases introduced

by four phase shifters; the filtered mixer signals and the bias tee's DC part are then

simultaneously digitized by a data acquisition card. (**B**) Left, raw analog signals acquired

simultaneously while imaging fixed BPAE cells. Right, lifetime, *g*, and *s* images and phasor

plots generated instantaneously through basic matrix operations. (**C**) Phasor plot of four

fluorescence lifetime standards. (**D**) Intensity and lifetime images of fluorophore solutions

mixed with different mole ratios of fluorescein and rhodamine B. (**E**) Phasor plot of the

fluorophore mixtures in (D). The red arrow indicates how the phasors shift when more

rhodamine B solution is added to the mixture. Scale bar, 20 μm.

Fig. 2. Instant FLIM with phasor labeling, adaptive optics, and super-resolution techniques.

(**A**) Maximized z-projections (top) and 3D reconstructions (bottom) of the 2PEF intensity, lifetime, and phasor labeled stacks of a fixed Cx3cr1-GFP/+ mouse brain acquired simultaneously with an instant FLIM system. (**B**) Demonstration of the phasor labeling technique, where ROIs are drawn on the phasor plot of the fixed mouse brain to label different cellular structures in the phasor labeled stack in (A). (**C**) 3D reconstructed lifetime stacks of the intact brain in a living Cx3cr1-GFP/+ mouse acquired with an instant FLIM system without (top) and with (bottom) the adaptive optics (AO) technique. (**D**) Demonstration of super-resolution FLIM by applying the generalized stepwise optical saturation (GSOS) technique in an instant FLIM system, where the super-resolution GSOS lifetime image of fixed BPAE cells is obtained by linear combining two diffraction-limited (DL) instant FLIM images acquired with different excitation powers. Insets, magnified views. Middle, line profiles of the normalized intensity and lifetime values at the positions of the white arrowheads in the DL and GSOS images. Scale bars, 20 μm.

Fig. 3. *In vivo* instant FLIM imaging in intact zebrafish brains.

(**A**) Larval *Tg(pu1:gfp)* zebrafish at 4 dpf were imaged with a 920 nm laser using instant

FLIM. (**B**) 2PEF intensity and lifetime maximized z-projection images of the CNS-located

and PNS-located myeloid cells in the zebrafish. (**C**) Graphs of average lifetime (τ) and

phasor (*g* and *s*) values in CNS-located (n=10 cells) and PNS-located (n=11 cells) myeloid

cells. CNS-located cells have a larger *g* phasor component. (**D**) Plot representing the phasor

locations of CNS-located (green) and PNS-located (blue) myeloid cells by their *g* and *s*

phasor components. Each shape represents a measurement taken from different individual

animals. (**E**) Average lifetime values of the zebrafish microglia over 150 minutes (n=8

cells). (**F**) 2PEF intensity and lifetime maximized z-projection images from a 12-hour 4D

instant FLIM movie of the zebrafish microglia. Bottom, surface projections representing

lifetime subdomains within the cell, where colors denote approximate lifetime values. White

arrowheads denote cellular subdomains with increased lifetimes. Scale bars, 10 μm. (C) uses

two-sided Student's t-tests. (E) uses one-way ANOVAs.

Fig. 4. *In vivo* instant FLIM imaging in intact mouse brains.

(**A**) Adult Cx3cr1-GFP/+ mice were imaged with a 920 nm laser using instant FLIM. (**B**)

2PEF intensity maximized z-projection image pseudo-colored to represent the temporal

dynamics of the microglia. The temporal scale is shown on the right. (**C**) 2PEF intensity

and lifetime maximized z-projection images of the mouse microglia. Bracket denotes the

microglial protrusion, arrowhead denotes the cell body, and their colors represent

approximate lifetime values. (**D**) Graphs of average lifetime (τ) and phasor (*g* and *s*) values

in microglial cell bodies (n=12) and protrusions (n=20). (**E**) Average lifetime values of

microglial cell bodies (green) and protrusions (blue) over 6 minutes (n=3 cells). (**F**) 2PEF

intensity and lifetime maximized z-projection images from a 4D instant FLIM movie of the

mouse microglia. Brackets denote microglial protrusions, arrowheads denote cell bodies,

and their colors represent approximate lifetime values. Scale bars, 10 μm. (D) uses two-

sided Student's t-tests. (E) uses one-way ANOVAs.

Fig. 5. *In vivo* **instant FLIM imaging in injured zebrafish brains.**

(**A**) Larval *Tg(pu1:gfp)* zebrafish at 4 dpf were imaged using instant FLIM following an injury induced by an 800 nm laser. (**B**) 2PEF intensity and lifetime maximized z-projection images from a 12-hour 4D instant FLIM movie in the zebrafish brain before and after laser injury. Mpi, minutes post-injury. Bottom, surface rendering of the lifetime images to better differentiate the cellular structures. Dashed yellow circle denotes the lesion site. Arrowheads denote approximate lifetime values. (**C**) Plot representing the phasor locations of microglia before injury (blue), 0-60 mpi (green), and 60+ mpi (orange). Each shape represents a measurement taken from different individual animals. (**D**) Graphs of average τ, *g*, and *s* values in microglia before injury (n=15 cells), 0-60 mpi (n=33 cells), and 60+

mpi (n=62 cells). (**E**) Average lifetime values of the microglia before and after injury (n=9

cells). (**F**) Lifetime maximized z-projection images from a 4-hour 4D instant FLIM movie

of the microglia before and after injury. Insets, surface representation of changing lifetime

subdomains within single microglia, where colors denote approximate lifetime values.

Dashed yellow circle denotes the lesion site. Arrowheads denote approximate lifetime

values. Scale bars, 10 µm. (D) and (E) use Tukey's HSD tests.

Fig. 6. *In vivo* instant FLIM imaging in injured mouse brains.

(**A**) Adult Cx3cr1-GFP/+ mice were imaged using instant FLIM following an injury induced

by an 800 nm laser. (**B**) 2PEF intensity maximized z-projection image pseudo-colored to

represent the temporal dynamics of the microglia in response to injury. The temporal scale

is shown on the right. Dashed yellow circle denotes the lesion site. (**C**) Intensity and lifetime

maximized z-projection images from a 4D instant FLIM movie in the mouse brain at -2 mpi

and 22 mpi. Dashed yellow circle denotes the lesion site. Arrowheads denote cell bodies,

brackets denote protrusions, and arrows denote protrusion tips. Colors denote approximate

lifetime values. Insets show magnified views of the protrusions. (**D**) Graphs of average τ,

g, and *s* values in cell bodies (n=5), protrusions (n=5), and protrusion tips (n=5) at -2 mpi

and 22 mpi. (**E**) Average lifetime values of cell bodies, protrusions, and protrusion tips

before and after injury (n=5 cells). (**F**) Intensity and lifetime maximized z-projection images

from a 30-min 4D instant FLIM movie of the microglia before and after injury. Annotations

are identical to the ones in (C). Scale bars, 10 µm. (D) uses two-way ANOVAs with multiple

comparisons. (E) uses one-way ANOVAs.

Supplementary Information

Section S1. Principle of instant FLIM

We first assume the fluorescence sample has a single-exponential decay with an impulse

response function $f(t) = \exp(-t/\tau)/\tau$, where τ is the fluorescence lifetime and the

function's integral on the time domain $(t \geq 0)$ is normalized to one. A mode-locked

Ti:sapphire laser which generates femtosecond pulses at 80 MHz is used as the excitation

source. Since the femtosecond pulses (100 fs) are orders of magnitude shorter than the

80 MHz modulation period (12.5 ns), we can consider these pulses as a Dirac comb with a

period of $T = 12.5$ ns. Mathematically, the excitation irradiance can be denoted as $I(t) =$

$P\delta_T(t)$, where P is a coefficient related to the average power of the laser beam. Based on

the quadratic nature of two-photon excitation, the fluorescence $F(t)$ is proportional to the

convolution of $I^2(t)$ and $f(t)$,

908
$$F(t) = cI^2(t) * f(t) = \frac{P^2 c}{\tau} \delta_T(t) * \exp\left(-\frac{t}{\tau}\right), \qquad (S1)$$

909   where c represents the fluorophore concentration. Since the fluorescence signal $F(t)$ is

910   periodic with an angular frequency of $\omega = 2\pi/T$, it can be written as a Fourier series,

911
$$F(t) = \sum_{k=-\infty}^{+\infty} q_k \exp(ik\omega t), \qquad (S2)$$

912   where the Fourier coefficients q_k are

913
$$q_k = \frac{1}{T} \int_0^T F(t) \exp(-ik\omega t)dt = \frac{P^2 c}{T} \frac{1}{1 + ik\tau\omega}. \qquad (S3)$$

915   We separate the fluorescence signal $F(t)$ detected by a PMT into DC and RF parts using a

916   bias tee. The DC part is linearly related to q_0 and can be written as

917
$$V_{\mathrm{DC}} = Bq_0 + O_B = \frac{BP^2 c}{T} + O_B, \qquad (S4)$$

where B is the conversion loss from the bias tee's RF&DC to DC ports, and O_B is the offset

that is invariant to the PMT signal variations. The RF part, on the other hand, is

$\sum_{k \neq 0} q_k \exp(ik\omega t)$. Since $q_k = q_{-k}^*$, it can also be written as

$$v_{\mathrm{RF}}(t) = 2 \sum_{k \in \mathbb{Z}^+} \mathrm{Re}\{q_k \exp(ik\omega t)\} = \frac{2P^2 c}{T} \sum_{k \in \mathbb{Z}^+} \frac{1}{1 + (k\tau\omega)^2} \left[\cos(k\omega t) + k\tau\omega \sin(k\omega t)\right]. \qquad (S5)$$

We use a homodyne detection method to extract the lifetime information from the first

harmonic (1ω) of $v_{\mathrm{RF}}(t)$. Specifically, we use RF mixers to mix the fluorescence signal with

the 80 MHz reference signal from the Ti:sapphire laser. The reference signal is low-pass

filtered and amplified such that it only contains the fundamental harmonic (1ω). For both

the fluorescence and reference signals, a 4-way power splitter is used to split the signal to

four paths. In instant FLIM, the four paths are operated independently and simultaneously

during imaging acquisition. For each reference signal path, a phase shifter is utilized to

introduce a voltage-controlled phase shift of φ (from 0 to 2π) to the signal. The reference

signals are sent to the local oscillator (LO) ports of the mixers and can be denoted as

$$v_{\mathrm{LO}}(t, \varphi) = \sin(\omega t + \varphi). \qquad (S6)$$

In instant FLIM, the four mixers take the PMT and reference signals to their RF and LO

ports, respectively. In theory, the output signal on the intermediate frequency (IF) ports can

be regarded as the product of the signals on its RF and LO ports; in practice, however, a DC

offset due to circuit imbalance also exists in the output (*42*). We denote this DC offset as

$$O_M = O(P_{\mathrm{RF}}) + d, \qquad (S7)$$

where $O(P_{\mathrm{RF}})$ is a function of the RF signal's power, P_{RF}, and d is a constant. The DC offset

O_M cannot be eliminated; it could be minimized by matching the powers of the RF and LO

signals (*42*), but in our setup P_{RF} is a variable related to the excitation power and the

fluorophore concentration, so the powers of RF and LO do not match. Considering the

existence of O_M, we model the output of the mixers as

$$v_{IF}(t,\varphi) = Mv_{LO}(t,\varphi)v_{RF}(t) + O_M, \tag{S8}$$

944 where M is the conversion loss from the mixer's RF to IF ports. The mixers' outputs are

945 then low-pass filtered to eliminate all the harmonics; therefore, the filtered signals are pure

946 DC voltages, as

$$\begin{aligned} V_{IF}(\varphi) &= \frac{1}{T}\int_0^T v_{IF}(t,\varphi)dt \\ &= \frac{P^2 Mc}{T}\frac{1}{1+(\tau\omega)^2}\left[\sin(\varphi) + \tau\omega\cos(\varphi)\right] + O_M \\ &= \frac{P^2 Mc}{T}\frac{1}{\sqrt{1+(\tau\omega)^2}}\sin\left[\varphi + \arctan(\tau\omega)\right] + O_M, \end{aligned} \tag{S9}$$

which are sampled by a DAQ card and used to calculate fluorescence lifetimes.

A calibration procedure described in Section S2 is required before measurement. When the

calibration is complete, we can control the phase shifts φ by applying corresponding bias

voltages to the phase shifters; we will also have the knowledge of M/B, a ratio between the

conversion losses of the mixer and the bias tee, that will be used for lifetime and phasor

calculations. The instant FLIM measurement is performed by applying four different phase

shifts, 0, 0.5π, π and 1.5π, respectively, to the four phase shifters on the reference signal

paths. Based on Eq. (S9), the measured mixer outputs are

$$\begin{aligned} V_{IF}(0) &= \frac{P^2 Mc}{T}\frac{\tau\omega}{1+(\tau\omega)^2} + O_M, \\ V_{IF}(0.5\pi) &= \frac{P^2 Mc}{T}\frac{1}{1+(\tau\omega)^2} + O_M, \\ V_{IF}(\pi) &= \frac{P^2 Mc}{T}\frac{-\tau\omega}{1+(\tau\omega)^2} + O_M, \\ V_{IF}(1.5\pi) &= \frac{P^2 Mc}{T}\frac{-1}{1+(\tau\omega)^2} + O_M. \end{aligned} \tag{S10}$$

958   Then, by taking the differences among them, we have

$$V_{\mathrm{IF}}(0) - V_{\mathrm{IF}}(\pi) = \frac{2P^2 Mc}{T} \frac{\tau\omega}{1+(\tau\omega)^2},$$

$$V_{\mathrm{IF}}(0.5\pi) - V_{\mathrm{IF}}(1.5\pi) = \frac{2P^2 Mc}{T} \frac{1}{1+(\tau\omega)^2},$$ (S11)

which are proportional to the imaginary and real parts of the first harmonic (1ω) Fourier

coefficient of the fluorescence, q_1, in Eq. (S3). Based on the measurements in Eq. (S11), it

is easy to extract the fluorescence lifetime by

$$\tau = \frac{1}{\omega} \frac{V_{\mathrm{IF}}(0) - V_{\mathrm{IF}}(\pi)}{V_{\mathrm{IF}}(0.5\pi) - V_{\mathrm{IF}}(1.5\pi)}.$$ (S12)

Next, we show that the instant FLIM method is also applicable for fluorophores with multi-

exponential decays by employing the phasor plot approach (21). Considering that the

fluorophore sample consists of multiple fluorophores with different lifetimes, τ_i, the

impulse response function becomes

$$f(t) = \sum_i a_i \frac{1}{\tau_i} \exp\left(-\frac{t}{\tau_i}\right),$$ (S13)

where a_i is the intensity weighted fractional contribution of the fluorophore with lifetime

τ_i, and $\sum_i a_i = 1$. Therefore, Eq. (S3) becomes

$$q_k = \frac{P^2 c}{T} \sum_i a_i \frac{1}{1+ik\tau_i\omega},$$ (S14)

and Eq. (S11) changes to

$$V_{\mathrm{IF}}(0) - V_{\mathrm{IF}}(\pi) = \frac{2P^2 Mc}{T} \sum_i a_i \frac{\tau_i\omega}{1+(\tau_i\omega)^2},$$

$$V_{\mathrm{IF}}(0.5\pi) - V_{\mathrm{IF}}(1.5\pi) = \frac{2P^2 Mc}{T} \sum_i a_i \frac{1}{1+(\tau_i\omega)^2}.$$ (S15)

On the other hand, the DC signal from the bias tee, Eq. (S4), does not change when we assume a multi-exponential decay model. If we divide Eq. (S15) by $2(V_{\mathrm{DC}} - O_B)$ in Eq. (S4) and the calibration coefficient M/B, we get

$$
\begin{aligned}
g &= \frac{V_{\mathrm{IF}}(0.5\pi) - V_{\mathrm{IF}}(1.5\pi)}{2(V_{\mathrm{DC}} - O_B)(M/B)} = \sum_i a_i \frac{1}{1 + (\tau_i \omega)^2}, \\
s &= \frac{V_{\mathrm{IF}}(0) - V_{\mathrm{IF}}(\pi)}{2(V_{\mathrm{DC}} - O_B)(M/B)} = \sum_i a_i \frac{\tau_i \omega}{1 + (\tau_i \omega)^2},
\end{aligned}
\tag{S16}
$$

where g and s are the horizontal and vertical components (coordinates) of phasors on a phasor plot (*21*). From the phasor components, we can obtain the average fluorescence (phase) lifetime of the multi-exponential decay by

$$
\tau = \frac{s}{g\omega} \approx \frac{\sum_i a_i \tau_i}{\sum_i a_i} = \sum_i a_i \tau_i.
\tag{S17}
$$

The average fluorescence lifetime alone cannot resolve the heterogeneity of multi-exponential decays, as different fluorophore compositions could result in the same average lifetime measurements. The phasor plot, on the other hand, can be used to resolve the heterogeneity because different fluorophore compositions can alter the phasor components even if the average lifetime might be unaltered.

Section S2. System calibration

A fluorescence sample with a known lifetime (e.g., 10^{-3} M coumarin 6 in methanol with a lifetime of 2.30 ns (*27*)) is required for system calibration. The calibration should be repeated for each excitation wavelength that will be used. Once the calibration is complete, the system is ready for imaging, and no more calibration is required. First, the relations between the phase shifts φ and the phase shifters' bias voltages V_b, i.e., $\varphi(V_b)$, should be calibrated for all four signal paths. Considering a fluorescence sample with a known lifetime

996 $\overline{\tau}$ (e.g., $\overline{\tau} = 2.3$ ns for coumarin 6 in methanol) and assuming that its concentration is $\overline{c}$, for

997 each bias voltage V_b, Eq. (S9) becomes

998
$$\overline{V}_{\mathrm{IF}}(V_b) = \frac{P^2 M \overline{c}}{T} \frac{1}{\sqrt{1+(\overline{\tau}\omega)^2}} \sin\left[\varphi(V_b) + \arctan(\overline{\tau}\omega)\right] + O_M. \tag{S18}$$

999 By changing V_b and measuring $\overline{V}_{\mathrm{IF}}$, we can obtain a curve, $\overline{V}_{\mathrm{IF}}(V_b)$, with maximal and

1000 minimal values:

1001
$$\overline{V}_{\mathrm{IF,max}} = \frac{P^2 M \overline{c}}{T} \frac{1}{\sqrt{1+(\overline{\tau}\omega)^2}} + O_M,$$
$$\overline{V}_{\mathrm{IF,min}} = \frac{P^2 M \overline{c}}{T} \frac{-1}{\sqrt{1+(\overline{\tau}\omega)^2}} + O_M. \tag{S19}$$

1002 We then have

1003
$$\overline{V}_{\mathrm{IF,max}} + \overline{V}_{\mathrm{IF,min}} = 2O_M,$$
$$\overline{V}_{\mathrm{IF,max}} - \overline{V}_{\mathrm{IF,min}} = \frac{2P^2 M \overline{c}}{T} \frac{1}{\sqrt{1+(\overline{\tau}\omega)^2}}. \tag{S20}$$

1004 Thus, from Eq. (S18), we can extract the phase calibration curve, $\varphi(V_b)$, as

1005
$$\varphi(V_b) = \arcsin\left[\left(\overline{V}_{\mathrm{IF}}(V_b) - O_M\right)\frac{T}{P^2 M \overline{c}}\sqrt{1+(\overline{\tau}\omega)^2}\right] - \arctan(\overline{\tau}\omega)$$
$$= \arcsin\left[\frac{2\overline{V}_{\mathrm{IF}}(V_b) - \left(\overline{V}_{\mathrm{IF,max}} + \overline{V}_{\mathrm{IF,min}}\right)}{\overline{V}_{\mathrm{IF,max}} - \overline{V}_{\mathrm{IF,min}}}\right] - \arctan(\overline{\tau}\omega). \tag{S21}$$

1006 Therefore, an arbitrary phase shift φ between 0 to 2π can be introduced to the system by

1007 applying the corresponding voltage V_b from the calibration curve $\varphi(V_b)$. Fig. S3 shows an

1008 example of $\overline{V}_{\mathrm{IF}}$ signals acquired from the four mixers' IF ports, as well as the phase

1009 calibration curve $\varphi(V_b)$ calculated using Eq. (S21), during the system calibration using a

1010 coumarin 6 lifetime standard.

1011

1012 Second, the coefficient M/B used in Eq. (S16) and the offset O_B in Eq. (S4) should be

1013 obtained during the calibration process. For the same fluorescence sample with a known

1014 lifetime $\bar{\tau}$, the DC signal from the bias tee, Eq. (S4), becomes

$$1015 \qquad \bar{V}_{\mathrm{DC}} = \frac{BP^2\bar{c}}{T} + O_B. \qquad (S22)$$

1016 The offset O_B can be obtained by turning off the laser beam ($P = 0$) while measuring $\bar{V}_{\mathrm{DC}}$.

1017 Therefore, based on Eqs. (S20) and (S22), we get

$$1018 \qquad \frac{M}{B} = \frac{\bar{V}_{\mathrm{IF,max}} - \bar{V}_{\mathrm{IF,min}}}{2(\bar{V}_{\mathrm{DC}} - O_B)} \sqrt{1 + (\bar{\tau}\omega)^2}, \qquad (S23)$$

1019 which is used for lifetime and phasor measurements.

1020

Note that in Fig. S3 the four mixers have almost identical electrical properties as the

calibration curves overlap with each other; therefore, it is valid to assume that the four

mixers have identical conversion losses M and DC offsets O_M. However, while the

conversion loss M is a design specification and can be guaranteed to be identical for the

same type of mixers, there is no guarantee that the DC offsets O_M are the same for all

mixers (*42*). Thus, an additional calibration for the DC offset difference may be needed. We

add a subscript i to denote the signals from the i-th mixer; the fluorescence signal from the

i-th mixer's IF port becomes

$$1029 \qquad \bar{V}_{\mathrm{IF}i}(V_b) = \frac{P^2 M\bar{c}}{T} \frac{1}{\sqrt{1 + (\bar{\tau}\omega)^2}} \sin\left[\varphi(V_b) + \arctan(\bar{\tau}\omega)\right] + O_{Mi}, \qquad (S24)$$

1030 where the i-th DC offset is

$$1031 \qquad O_{Mi} = O(P_{\mathrm{RF}}) + d_i. \qquad (S25)$$

1032 We found through experiments that $O(P_{\mathrm{RF}})$, as a function of the RF signal's power P_{RF},

1033 was identical for all four mixers, and that the DC offset difference was due to d_i. Therefore,

1034   we can compensate for such difference by calibrating the differences among d_i. To do that,

1035   we turn off the laser beam ($P = 0$) while measuring $\overline{V}_{\mathrm{IF}i}$ from the four mixers:

$$
\begin{aligned}
\overline{V}_{\mathrm{IF1}} &= O_{M1} = O(P_{\mathrm{RF}}) + d_1, \\
\overline{V}_{\mathrm{IF2}} &= O_{M2} = O(P_{\mathrm{RF}}) + d_2, \\
\overline{V}_{\mathrm{IF3}} &= O_{M3} = O(P_{\mathrm{RF}}) + d_3, \\
\overline{V}_{\mathrm{IF4}} &= O_{M4} = O(P_{\mathrm{RF}}) + d_4,
\end{aligned}
\tag{S26}
$$

1037   and we define two new calibration parameters, d_{13} and d_{24}, as

$$
\begin{aligned}
d_{13} &= d_1 - d_3 = \overline{V}_{\mathrm{IF1}} - \overline{V}_{\mathrm{IF3}}, \\
d_{24} &= d_2 - d_4 = \overline{V}_{\mathrm{IF2}} - \overline{V}_{\mathrm{IF4}}.
\end{aligned}
\tag{S27}
$$

1039   After the calibration, the DC offset differences among the mixers can be compensated by

1040   including d_{13} and d_{24} in FLIM measurements: Eq. (S12) becomes

$$
\tau = \frac{1}{\omega} \frac{V_{\mathrm{IF1}}(0) - V_{\mathrm{IF3}}(\pi) - d_{13}}{V_{\mathrm{IF2}}(0.5\pi) - V_{\mathrm{IF4}}(1.5\pi) - d_{24}},
\tag{S28}
$$

1042   and finally, the phasor components [Eq. (S16)] are now

$$
\begin{aligned}
g &= \frac{V_{\mathrm{IF1}}(0.5\pi) - V_{\mathrm{IF3}}(1.5\pi) - d_{13}}{2(V_{\mathrm{DC}} - O_B)(M/B)}, \\
s &= \frac{V_{\mathrm{IF2}}(0) - V_{\mathrm{IF4}}(\pi) - d_{24}}{2(V_{\mathrm{DC}} - O_B)(M/B)}.
\end{aligned}
\tag{S29}
$$

1044   Note that all the calibration procedures described in this section can be performed easily

1045   and completed automatically with our open-source *Instant-FLIM-Control* program.

1046

Section S3. SNR analysis of instant FLIM

We analyze the SNR performance of instant FLIM and compare it with conventional FD-

FLIM methods through Monte Carlo simulations and error-propagation analyses (*8*, *11*).

These FD-FLIM methods differ in the modulation waveforms of the excitation light, and

consequently, the detected fluorescence signals are also different, as shown in Fig. S4A.

These differences result in different sensitivity and SNR in lifetime measurements. Here,

we use the *F*-value, i.e., photon economy, a widely used figure of merit in FLIM, to quantify

and compare SNRs of FLIM measurements. It is defined as the ratio of the uncertainties in

lifetime (τ) and intensity (I) measurements:

1056
$$F = \frac{\sigma_\tau / \tau}{\sigma_I / I} = \sqrt{N_{\text{det}}}\, \frac{\sigma_\tau}{\tau}, \tag{S30}$$

where we denote $I = N_{\text{det}}$, the number of photons detected in a measurement, and use the

fact that N_{det} is shot-noise-limited, i.e., Poisson distributed, such that $\sigma_I = \sqrt{N_{\text{det}}}$. Note

that the shot-noise-limited performance is achieved using high-sensitivity PMTs and low-

noise amplifiers in a FLIM system. Since the *F*-value quantifies the uncertainty in lifetime

measurements, a smaller *F* means that the lifetime is measured more accurately, hence a

better SNR performance. Whereas a smaller *F* is desired, it is limited to $F > 1$ due to shot

noise; $F = 1$ only exists in an ideal shot-noise-limited FLIM system.

1064

We use Monte Carlo simulations and error-propagation analyses to acquire the *F*-values of

instant FLIM and conventional FD-FLIM methods. The Monte Carlo simulations are

performed by dividing each modulation period *T* (12.5 ns for 80 MHz modulation) into *L*

time units Δt (*8, 11*). In each Δt, a random number, *r*, that is uniformly distributed in [0, 1]

is generated and compared with the probability density described by the product of the

fluorescence signal $F(t)$ and the time unit Δt. If *r* is larger than $F(t)\Delta t$, the simulation

considers that a fluorescence photon is emitted and recorded by the detector. In the analysis

of instant FLIM, $F(t)$ is identical to Eq. (S1), while in other cases, $F(t)$ are analytically

calculated by convolving the corresponding excitation signal (Fig. S4A) with the impulse

response function, $f(t)$. A modulation period *T* is completed after the simulation goes

through all Δt in that period; then, another *T* is simulated likewise, and the emitted photons

are cumulatively recorded by the simulation. For a single lifetime measurement, *N*

modulation periods are simulated, and the lifetime τ is calculated based on the FD-FLIM

technique in use. This lifetime measurement process is then repeated for 1,000 times to

obtain the statistical properties (mean and variance) and consequently, the F-value, of the

lifetime measurement. A diagram summarizing the Monte Carlo simulation process is

shown in Fig. S4B.

1082

1083 The analytical error-propagation analysis is applicable when the lifetime can be written in

1084 the following form:

$$\tau = \frac{U}{V} = \frac{\mu_1 + \sigma_1 Y_1}{\mu_2 + \sigma_2 Y_2} = \frac{\mu_1}{\mu_2} \frac{1 + \delta_1 Y_1}{1 + \delta_2 Y_2}, \tag{S31}$$

where U and V are the random variables used in lifetime calculation with means, μ_1, μ_2,

standard deviations, σ_1, σ_2, and coefficients of variation, $\delta_1 = \sigma_1/\mu_1$, $\delta_2 = \sigma_2/\mu_2$; Y_1 and Y_2

are auxiliary random variables with zero means and unity variances. In practice, $\sigma_1^2 \approx$

$E[U^2]$ and $\sigma_2^2 \approx E[V^2]$ as $E[U]^2$ and $E[V]^2$ are negligible compared to $E[U^2]$

and $E[V^2]$. If the moments of third and higher orders are omitted, Eq. (S31) can be

expanded as

$$\tau = \frac{\mu_1}{\mu_2}\left(1 + \delta_1 Y_1 - \delta_2 Y_2 - \delta_1 \delta_2 Y_1 Y_2 + \delta_2^2 Y_2^2 + \cdots\right). \tag{S32}$$

1093 We then get the expected value of τ as

$$E[\tau] = \frac{\mu_1}{\mu_2}\left(1 - \rho \delta_1 \delta_2 + \delta_2^2\right), \tag{S33}$$

1095 where $\rho = E[Y_1 Y_2]$ is the correlation coefficient of U and V. We also have

$$E[\tau^2] = \left(\frac{\mu_1}{\mu_2}\right)^2 \left(1 + \delta_1^2 + 3\delta_2^2 - 4\rho \delta_1 \delta_2\right). \tag{S34}$$

1097 Therefore, the variance of τ can be calculated as

1098
$$\sigma_\tau^2 = E[\tau^2] - E[\tau]^2 = \left(\frac{\mu_1}{\mu_2}\right)^2 \left(\delta_1^2 + \delta_2^2 - 2\rho\delta_1\delta_2\right), \tag{S35}$$

1099 and the F-value can be calculated with Eq. (S30).

1100

1101 Based on the principle of instant FLIM in Section S1, the fluorescence signal $F(t)$ can be

1102 analytically calculated as

1103
$$F(t) = \frac{1}{\tau}\delta_T(t) * \exp\left(-\frac{t}{\tau}\right) = \frac{1}{\tau}\int_0^T \left[\sum_{k=0}^{\infty}\exp\left(-\frac{x+kT}{\tau}\right)\right]\delta_T(t-x)dx = \frac{1}{\tau}\frac{\exp(-t/\tau)}{1-\exp(-T/\tau)}, \tag{S36}$$

1104 where we scale the excitation power and the fluorophore concentration down to $P = 1$ and

1105 $c = 1$ such that on average only one photon is emitted during a modulation period T, i.e.,

1106 $\int_0^T F(t)dt = 1$. Thus, $F(t)$ can be regarded as the probability density function of detecting

1107 a photon, and the mathematical expectation of a random variable X related to detecting a

1108 photon is

1109
$$E[X] = \int_0^T X F(t)dt. \tag{S37}$$

1110 We denote the random processes corresponding to the four mixers' outputs [Eq. (S9)] in

1111 instant FLIM as X_1, X_2, X_3 and X_4. With Eqs. (S6) and (S8), Eq. (S9) becomes

1112
$$\begin{aligned}
V_{\text{IF}}(\varphi) &= \frac{1}{T}\int_0^T v_{\text{IF}}(t,\varphi)dt \\
&= \frac{1}{T}\int_0^T \left[M\sin(\omega t + \varphi)v_{\text{RF}}(t) + O_M\right]dt \\
&= \frac{M}{T}\int_0^T \sin(\omega t + \varphi)\left[F(t) - q_0\right]dt + O_M \\
&= \frac{M}{T}\int_0^T \sin(\omega t + \varphi)F(t)dt + O_M,
\end{aligned} \tag{S38}$$

1113 where we use the fact that $v_{\text{RF}}(t)$ and q_0 are the RF and DC parts of $F(t)$ and therefore

1114 $v_{\text{RF}}(t)$ can be written as $v_{\text{RF}}(t) = F(t) - q_0$. With Eqs. (S37) and (S38), we can write the

1115 random processes as

$$X_1 = \frac{M}{T}\sin(\omega t) + O_M,$$

$$X_2 = \frac{M}{T}\cos(\omega t) + O_M,$$

$$X_3 = -\frac{M}{T}\sin(\omega t) + O_M, \tag{S39}$$

$$X_4 = -\frac{M}{T}\sin(\omega t) + O_M.$$

Since Eq. (S12) follows the form of Eq. (S31), we have $U = V_{IF}(0) - V_{IF}(\pi)$ and $V = \omega\big[V_{IF}(0.5\pi) - V_{IF}(1.5\pi)\big]$. Considering that N_{det} photons are detected in a lifetime measurement, based on Eqs. (S3) and (S39), we get the means of U and V as

$$\mu_1 = N_{det}E[X_1 - X_3] = -2N_{det}M\,\mathrm{Im}\{q_1\} = N_{det}\frac{2M}{T}\frac{\tau\omega}{1+\tau^2\omega^2},$$

$$\mu_2 = \omega N_{det}E[X_2 - X_4] = 2\omega N_{det}M\,\mathrm{Re}\{q_1\} = \omega N_{det}\frac{2M}{T}\frac{1}{1+\tau^2\omega^2}. \tag{S40}$$

The variances and correlation coefficients of U and V can also be obtained as

$$\sigma_1^2 = N_{det}E[(X_1 - X_3)^2] = N_{det}\frac{2M^2}{T}[q_0 - \mathrm{Re}\{q_2\}] = N_{det}\frac{2M^2}{T^2}\frac{4\tau^2\omega^2}{1+4\tau^2\omega^2},$$

$$\sigma_2^2 = \omega^2 N_{det}E[(X_2 - X_4)^2] = \omega^2 N_{det}\frac{2M^2}{T}[q_0 + \mathrm{Re}\{q_2\}] = \omega^2 N_{det}\frac{2M^2}{T^2}\frac{2+4\tau^2\omega^2}{1+4\tau^2\omega^2}, \tag{S41}$$

$$\rho\sigma_1\sigma_2 = \omega N_{det}E[(X_1 - X_3)(X_2 - X_4)] = -\omega N_{det}\frac{2M^2}{T}\mathrm{Im}\{q_2\} = \omega N_{det}\frac{2M^2}{T^2}\frac{2\tau\omega}{1+4\tau^2\omega^2}.$$

Then, from Eq. (S35), the standard deviation of τ is

$$\sigma_\tau = \frac{\mu_1}{\mu_2}\sqrt{\frac{\sigma_1^2}{\mu_1^2} + \frac{\sigma_2^2}{\mu_2^2} - \frac{2\rho\sigma_1\sigma_2}{\mu_1\mu_2}} = \tau(1+\tau^2\omega^2)\sqrt{\frac{1+2\tau^2\omega^2}{N_{det}(1+4\tau^2\omega^2)}}. \tag{S42}$$

Consequently, we get the F-value of instant FLIM as

$$F = \sqrt{N_{det}}\frac{\sigma_\tau}{\tau} = (1+\tau^2\omega^2)\sqrt{\frac{1+2\tau^2\omega^2}{1+4\tau^2\omega^2}}, \tag{S43}$$

which is identical to the F-value of a two-photon (2P) FD-FLIM when the excitation is modulated as a Dirac comb (*11*); this is expected as instant FLIM uses a femtosecond pulse excitation in a 12.5 ns (80 MHz) modulation period, which can be seen as a Dirac comb.

We compare the SNR performances of instant FLIM and conventional FD-FLIM methods

(*11*), including 2P FD-FLIM with sinusoidal (1.0, 0.5 modulation degrees) and periodic

square wave (0.2, 0.5 duty cycles) modulations, as well as one-photon (1P) FD-FLIM with

sinusoidal modulation (1.0 modulation degree), by plotting their simulated (symbols) and

analytical (curves) F-values in Fig. S4C. Since the F-value is only dependent on the product

of the modulation frequency and the fluorescence lifetime (*8*), i.e., $\omega\tau$, and the modulation

frequency for instant FLIM is fixed at 80 MHz, for a fair comparison, we fix the modulation

frequency of all the methods to 80 MHz and vary the lifetime from 0 to 4.5 ns when we

investigate the F-values. The analytical results are in good agreement with the ones obtained

from Monte Carlo simulations. Our instant FLIM method has the smallest F-value ($F = 1$),

which is the shot noise limit and the best possible SNR performance a FLIM method can

achieve. In comparison, the 2P sinusoidal (1.0, 0.5 modulation degrees) and periodic square

wave (0.2, 0.5 duty cycles) modulations have their best SNR performances at $F = 2.62$,

$F = 4.07$, $F = 1.44$, and $F = 2.89$, respectively; the conventional 1P sinusoidal (1.0

modulation degree) case has its best F-value at $F = 3.67$. To illustrate the SNR difference

among these FD-FLIM methods, we select four targeted lifetime values (0.375 ns, 1.625 ns,

2.875 ns, and 4.125 ns) and plot the traces of 1,000 measurements of their values using

different FD-FLIM methods from the Monte Carlo simulations (Fig. S4D). A lifetime

histogram and the standard deviation (σ_τ) of the 1,000 lifetime measurements are plotted

next to each trace. In all four cases, the instant FLIM measurements have the smallest σ_τ

compared to conventional FD-FLIM methods. In summary, through Monte Carlo

simulations and error-propagating analyses, instant FLIM has been demonstrated to be

superior in SNR performance compared with conventional FD-FLIM techniques; in some

cases, instant FLIM can approach the shot noise limit ($F = 1$), the best possible SNR

performance of a FLIM measurement. This is achieved by the efficient utilization of the 80

MHz femtosecond pulsed laser in instant FLIM.

1157

Section S4. Instant FLIM with adaptive optics

Adaptive optics (AO) can be employed in instant FLIM to reduce the optical aberrations

induced by the imaging system or the sample, and potentially improve the imaging quality

and extend the penetration depth (*23*). We implemented AO as an optional module in instant

FLIM by introducing a deformable mirror to the setup. To reduce the system complexity

and cost, we employed sensorless AO, in which a wavefront sensor was not required, and

indirect wavefront sensing based on an optimization metric was used. Using the

optimization algorithms described below, the AO module iteratively adjusts the parameters

of the deformable mirror to improve the image-based optimization metric.

1167

Depending on the user's choice in the *Instant-FLIM-Control* program, the optimization

metric, *V*, can be the mean pixel value or the normalized variance of the image, where the

normalized variance is defined as the variance of all the pixel values divided by the square

of the mean pixel value. We employed Zernike modes to describe the optical aberrations as

well as the aberration compensation applied to the deformable mirror. The optimization

algorithms are performed in an *N*-dimensional aberration space generated by a base:

1174
$$\zeta = [z_1, z_2, \cdots, z_N]^T, \tag{S44}$$

1175   where $z_1, z_2, \cdots, z_N$ are Zernike polynomials. The deformable mirror (Thorlabs DMP40-

1176   P01) we used supports up to 12 Zernike modes (Z_2^{-2}, Z_2^0, Z_2^2, Z_3^{-3}, Z_3^{-1}, Z_3^1, Z_3^3,

1177 Z_4^{-4}, Z_4^{-2}, Z_4^0, Z_4^2, Z_4^4) in the optimization. The aberration compensation, Φ, can then

1178   be described in the aberration space spanned by ζ:

$$\Phi = \alpha^T \zeta = \sum_{n=1}^{N} a_n z_n,$$ (S45)

1179

where

$$\alpha = [a_1, a_2, \cdots, a_N]^T$$ (S46)

are the Zernike coefficients in which a_j represents the contribution of z_j to Φ. In practice,

an optimization algorithm iteratively monitors the image-based metric V and updates the

Zernike coefficients α that control the wavefront shaping elements (mirror segments) on the

deformable mirror; after multiple iterations, if the AO optimization is successful, the metric

V will be increased and the imaging quality will be improved.

1187

In the *Instant-FLIM-Control* program, we use three AO algorithms to optimize V and

imaging quality. The first one is a simple max search algorithm that sequentially searches

through each Zernike coefficient, from a_1 to a_N, until a maximized V is found for each one

of them. For example, to find the optimal value for a_j, the algorithm keeps all the other

Zernike coefficients unaltered while changing a_j from -1 to 1 with a step size defined by

the user, e.g., 0.2. This is valid due to the orthogonality of the Zernike modes. The optimal

a_j is found at the value where V is maximized from $-1 < a_j < 1$. This algorithm is easy and

straightforward, but it is time-consuming: for a step size of 0.2, full optimization of 12

Zernike modes requires the acquisition of 120 raw images. However, this is also the most

robust and reliable algorithm, as it guarantees that a global optimum or its proximity can be

found, whereas the other algorithms are likely to find a local optimum.

1199

1200   The second algorithm is a quadratic search algorithm (*28*) which approximates the metric V

1201   of the aberration Φ as a quadratic function of the Zernike coefficients α:

$$V(\Phi) \approx V_0 - \sum_{n=1}^{N} c_n a_n^2,$$ (S47)

where V_0 and c_n are constants and the metric has a paraboloidal shape around its maximum.

The goal of the optimization algorithm is to find the coordinates of α that maximizes V. This process can be decomposed into N independent one-dimensional parabolical optimization problem for each Zernike coefficient a_n, as Eq. (S47) can be written as

$$V(\Phi) \approx \left(V_0 - \sum_{l \neq n}^{N} c_l a_l^2\right) - c_n a_n^2.$$ (S48)

The optimal a_n that maximizes V can then be calculated by three measurements of V, i.e., $V(\Phi_0)$, $V(\Phi_0 + bz_n)$, and $V(\Phi_0 - bz_n)$ corresponding to $a_n = a_{n0}$, $a_n = a_{n0} + b$, and $a_n = a_{n0} - b$, respectively, where Φ_0 is the initial aberration, a_{n0} is the initial value of a_n ($a_{n0} = 0$ by default), and b is the bias amplitude used to search the parabolic maximum. With the three metrics obtained from the three raw images, the optimal a_n, i.e., a_{nx}, can be estimated using parabolic maximization as

$$a_{nx} = a_{n0} + \frac{V(\Phi_0 + bz_n) - V(\Phi_0 - bz_n)}{2V(\Phi_0) - V(\Phi_0 + bz_n) - V(\Phi_0 - bz_n)} \frac{b}{2}.$$ (S49)

In the algorithm, this one-dimensional optimization process is repeated for N times to calculate the optimal Zernike coefficients $a_{1x}, a_{2x}, \cdots, a_{Nx}$ that jointly maximizes V. Whereas each process requires three measurements, the metric for the initial image $V(\Phi_0)$ is common; therefore, to correct for N Zernike coefficients, the algorithm merely requires $2N + 1$ raw images. For our deformable mirror supporting 12 Zernike modes, the optimization needs only 25 raw images. Compared to the other AO optimization algorithms, the quadratic search one is the fastest and requires the least number of raw images to be captured. However, it is not always reliable as the approximation assumption in Eq. (S47) is only accurate for small aberration amplitudes, which may not be satisfied in practice.

1224   Therefore, this algorithm is recommended only if the speed is an essential requirement for

1225   AO optimization.

1226

The third algorithm in the program is based on the stochastic parallel gradient descent

(SPGD) method (29). In each SPGD iteration, after the metric V is acquired from a raw

image, the Zernike coefficients in α are perturbed in parallel by a small non-zero stochastic

value. In our program, the value is randomly chosen from [-0.05, -0.025, 0.025, 0.05].

During the m-th iteration, the Zernike coefficients applied to the $m+1$-th iteration is

calculated as

$$\alpha^{(m+1)} = \alpha^{(m)} - \eta[V(\Phi + \delta^T \zeta) - V(\Phi)]\delta, \qquad (S50)$$

where the superscripts in brackets are the indices of the iteration, η is the learning rate, Φ is

the aberration before the iteration, ζ is the Zernike base described in Eq. (S44), and δ is an

array consisting of the non-zero stochastic values. The learning rate η is negative in our case

(-0.01 by default) as the optimization is to maximize V. If η is chosen properly, the metric

V will be increased after each iteration. The algorithm is stopped when a maximal V is found

or the specified steps of iterations are reached. Compared to the previous algorithms, the

SPGD method updates the Zernike coefficients in parallel and it could acquire the optimal

coefficients more accurately. However, due to the stochastic nature of the method, the

algorithm usually takes much more iterations, hence imaging time, than the other methods,

and it could also easily fall into a local maximum. As a complement to the other algorithms,

the SPGD method is recommended when high precision is preferred in determining the

optimal Zernike coefficients.

1246

To demonstrate the performance of instant FLIM when the AO module is added, we

acquired through-skull 3D FLIM stacks of the intact brain in a living mouse with and

without AO. We used the simple max search algorithm for the AO optimization. With AO,

the instant FLIM system was able to generate 3D intensity, lifetime, and phasor labeled

stacks of the living mouse brain, through the skull, with a penetration depth up to 300 μm

(Fig. S7 and Movie S2). Note that the excitation power of the laser was gradually increased

from 8.53 mW to 21.13 mW during the imaging; the penetration depth limit was achieved

when further increasing the power could not increase the signal level. We then imaged the

animal with the same imaging condition but without the AO module. Specifically, we added

a folding mirror in front of the AO module to reflect the laser beam directly into the two-

photon microscope. As shown in Fig. S7, when the AO module was not used, we could only

achieve a penetration depth of 130 μm. In comparison, the penetration depth for instant

FLIM with a well-optimized AO module (300 μm) was more than double of that without

AO.

1261

Section S5. Super-resolution instant FLIM with GSOS

We show that the instant FLIM system can be used to generate super-resolution FLIM

images based on the recently demonstrated generalized stepwise optical saturation (GSOS)

technique (*24*). By linear combining M FLIM images obtained with different excitation

powers in the complex domain, a new FLIM image with a $\sqrt{M}$-fold increase in spatial

resolution can be obtained. Because the linear combination in GSOS is applied to the

complex Fourier coefficients, q_k, of the fluorescence, $F(t)$, we rewrite Eq. (S5) such that q_k

is explicitly shown in the equation:

$$v_{\mathrm{RF}}(t) = 2\sum_{k\in\mathbb{Z}^+}\mathrm{Re}\left\{q_k\exp(ik\omega t)\right\} = \sum_{k\in\mathbb{Z}^+}2\,\mathrm{Re}\{q_k\}\cos(k\omega t) - 2\,\mathrm{Im}\{q_k\}\sin(k\omega t). \qquad (S51)$$

Following the analog signal processing in instant FLIM, the output signals of the mixers

[Eq. (S9)] become

$$V_{IF}(\varphi) = \frac{1}{T}\int_0^T v_{IF}(t,\varphi)dt$$

1273
$$= \frac{1}{T}\int_0^T [M\sin(\omega t + \varphi)v_{RF}(t) + O_M]dt \qquad (S52)$$

$$= \frac{M}{T}\big[\text{Re}\{q_1\}\sin(\varphi) - \text{Im}\{q_1\}\cos(\varphi)\big] + O_M.$$

1274   Consequently, after introducing the phase shifts, the measured mixer outputs [Eq. (S10)]

1275   are

$$V_{IF}(0) = -\frac{M}{T}\text{Im}\{q_1\} + O_M,$$

$$V_{IF}(0.5\pi) = \frac{M}{T}\text{Re}\{q_1\} + O_M,$$

1276
$$(S53)$$

$$V_{IF}(\pi) = \frac{M}{T}\text{Im}\{q_1\} + O_M,$$

$$V_{IF}(1.5\pi) = -\frac{M}{T}\text{Re}\{q_1\} + O_M.$$

1277   Then, the differences among them [Eq. (S11)] are directly proportional to the real and

1278   imaginary parts of the Fourier coefficient:

$$V_{IF}(\pi) - V_{IF}(0) = \frac{2M}{T}\text{Im}\{q_1\},$$

1279
$$(S54)$$

$$V_{IF}(0.5\pi) - V_{IF}(1.5\pi) = \frac{2M}{T}\text{Re}\{q_1\}.$$

1280   Therefore, the magnitude and phase of the complex Fourier coefficient, q_1, can be extracted

1281   as

$$|q_1| \approx \sqrt{[V_{IF}(\pi) - V_{IF}(0)]^2 + [V_{IF}(0.5\pi) - V_{IF}(0.5\pi)]^2},$$

1282
$$\angle q_1 = \arctan\left[\frac{V_{IF}(\pi) - V_{IF}(0)}{V_{IF}(0.5\pi) - V_{IF}(0.5\pi)}\right], \qquad (S55)$$

1283   which are then combined as a complex value, $q_1 = |q_1|\exp(i\angle q_1)$.

1284

1285   In GSOS with M steps (M-GSOS), the measurement is repeated for M times with M different

1286   excitation powers, $I_{01}, I_{02}, \cdots, I_{0M}$, where $I_{01} < I_{02} < \cdots < I_{0M}$. Hence M images

1287   consisting of these complex Fourier coefficients, $q_{1,1}, q_{1,2}, \cdots, q_{1,M}$, are obtained based on

the measurements described above [Eqs. (S53)-(S55)]. The GSOS linear combination is then applied to these complex images,

$$q_{1,\text{M-GSOS}} = \sum_{m=1}^{M} c_m q_{1,m}, \tag{S56}$$

where the linear combination coefficients, c_m, are calculated based on the excitation powers, $I_{01}, I_{02}, \cdots, I_{0M}$. Here, we give the general expression to calculate c_m:

$$c_m = \begin{cases} 1 & \text{if } m = 1, \\ -\dfrac{I_{01}^N}{I_{02}^N}, & \text{if } m = 2 \text{ and } M = 2, \\ (-1)^{M-1} \dfrac{I_{01}^N}{I_{0m}^N} \displaystyle\prod_{j=2|j \neq m}^{M} \dfrac{I_{01}^N - I_{0j}^N}{I_{0j}^N - I_{0m}^N} & \text{otherwise,} \end{cases} \tag{S57}$$

where N is the number of excitation photons needed for a fluorophore to emit one photon ($N = 1$ for 1PEF, $N = 2$ for 2PEF). The result of the GSOS linear combination is a new image ($q_{1,\text{M-GSOS}}$) with complex pixel values, where its magnitude, $|q_{1,\text{M-GSOS}}|$, is a super-resolution image with a $\sqrt{M}$-fold increase in resolution over the diffraction limit, and its phase, $\angle q_{1,\text{M-GSOS}}$, is identical to that of the original Fourier coefficient, $\angle q_1$ (24). From the phase, a fluorescence lifetime image can be obtained by

$$\tau = -\frac{1}{\omega} \tan(\angle q_{1,\text{M-GSOS}}) = -\frac{1}{\omega} \tan(\angle q_1). \tag{S58}$$

As a result, by linear combining M complex images obtained with an instant FLIM system using the GSOS principle, we can obtain a super-resolution FLIM image where its intensity, $|q_{1,\text{M-GSOS}}|$, is enhanced by a factor of $\sqrt{M}$ and its lifetime information, $\tau = -\tan(\angle q_{1,\text{M-GSOS}})/\omega$, is preserved.

Instant FLIM can be used to generate super-resolution 3D FLIM stacks. Fig. S8 shows a side-by-side comparison between a diffraction-limited (DL) and a super-resolution (two-

step GSOS) 3D FLIM stacks of a fixed mouse brain. The DL stack was acquired with an

instant FLIM system at an excitation power of 12.31 mW. The two-step GSOS stack, on the

other hand, was generated by linear combining two DL instant FLIM stacks, $q_{1,1}$ and $q_{1,2}$,

measured at $I_1 = 12.31$ mW and $I_2 = 13.44$ mW, respectively. The GSOS linear

combination coefficients were calculated according to Eq. (S57) ($N = 2$ for 2PEF): $c_1 = 1$

and $c_2 = -I_{01}^2/I_{02}^2 = -0.8389$. The two-step GSOS stack, $q_{1,2\text{-GSOS}}$, was then generated

based on Eq. (S56), i.e., $q_{1,2\text{-GSOS}} = c_1 q_{1,1} + c_2 q_{1,2} = q_{1,1} - 0.8389 q_{1,2}$; its intensity,

$|q_{1,2\text{-GSOS}}|$, and fluorescence lifetime, $\tau = -\tan(\angle q_{1,2\text{-GSOS}})/\omega$, are plotted as brightness

and hue, respectively, to construct the 3D FLIM stack. The resolution improvement of the

GSOS stack compared to the DL stack can be seen in Fig. S8 (Movie S3), where the line

profiles of the normalized intensity values at the positions of the white arrowheads show

the features that are better resolved in the GSOS stack.

1320

1321

Fig. S1. Detailed diagram and photos of an instant FLIM system.

(**A**) Detailed diagram of the system configuration. NDF, neutral density filter; $\lambda/2$, half-

wave plate; PBS, polarizing beam splitter; $\lambda/4$, quarter-wave plate; DM, deformable mirror;

M, mirror; PMT, photomultiplier tube; TA, transimpedance amplifier; DAQ, data

acquisition; LPF, low pass filter; LNA, low-noise amplifier; PS, phase shifter. Three sets of

components are grouped together and highlighted as system modules. The two-photon

microscope module is a conventional two-photon laser scanning microscope setup; the

optional adaptive optics module can improve the imaging quality and penetration depth; the

analog signal processing module is the essential part of an instant FLIM system. (**B**) Photo

of an implementation of the optional adaptive optics module. (**C**) Photo of an

implementation of the conventional two-photon microscope module. (**D**) Photo of an

implementation of the instant FLIM analog signal processing module.

1334

1335

Fig. S2. Analog signal processing in instant FLIM.

(**A**) Diagram showing how analog signals are processed in instant FLIM. The signals are

labeled with numbers and their typical waveforms are shown in (B). (**B**) Waveforms of the

analog signals under real experimental conditions: excitation wavelength, 920 nm; sample,

coumarin 6 in methanol; excitation power, 3.6 mW. These signals are: 1, $v_{\mathrm{ref}}(t)$, the

reference signal from the mode-locked Ti:sapphire laser; 2, $v_{\mathrm{80MHz}}(t)$, the pure 80 MHz

signals after low pass filtering, amplifying, and splitting the reference signal; 3-6, $v_{\mathrm{LO}}(t, \varphi)$,

the phase-shifted reference signals directed to the mixers' LO ports; 7, $v_{\mathrm{RF}}(t)$, the low pass

filtered, amplified, and split PMT signals directed to the mixers' RF ports; 8, $v_{\mathrm{IF}}(t, \varphi)$, one

of the mixed signals generated on the mixers' IF ports; 9-12, $V_{\mathrm{IF}}(\varphi)$, the low pass filtered

(DC) mixed signals that are measured by a DAQ card. Unit, volts.

1347

Fig. S3. Instant FLIM system calibration using a lifetime standard.

(**A**) Raw calibration curves acquired from a lifetime standard (1 mM coumarin 6 in methanol)

by changing the bias voltage (V_b, stepping from 0 to 10V) applied to the four phase shifters

and measuring the voltages ($\overline{V}_{\mathrm{IF}}$) on the four mixers' IF ports. A set of calibration curves

should be measured for each excitation wavelength that will be used for imaging. Here we

show the curves for excitation wavelengths at 780 nm, 800 nm, 860 nm, and 920 nm. Unit,

volts. (**B**) Phase calibration curves, $\varphi(V_b)$, generated using Eq. (S21) based on the raw data

in (A). Unit, radians.

1357

Fig. S4. SNR analysis of instant FLIM and conventional FD-FLIM techniques.

(**A**) Excitation and fluorescence waveforms of the six FD-FLIM techniques in comparison:

instant FLIM, this work; Sin (1.0), two-photon (2P) sinusoidal (1.0 modulation degree)

modulation; Sin (0.5), 2P sinusoidal (0.5 modulation degree) modulation; Square (0.2), 2P

periodic square wave (0.2 duty cycle) modulation; Square (0.5), 2P periodic square wave

(0.5 duty cycle) modulation; 1P-FLIM, one-photon (1P) sinusoidal (1.0 modulation degree)

modulation. Modulation period, 12.5 ns (80 MHz). (**B**) Diagram summarizing the Monte

Carlo simulation process. (**C**) *F*-values as a function of fluorescence lifetimes with

modulation frequency fixed at 80 MHz for different FD-FLIM methods. The symbols and

curves are results of the numerical Monte Carlo simulation and the analytical error-

propagation analysis, respectively. (**D**) Simulated lifetime measurements extracted from

four different lifetime values in the Monte Carlo simulations for different FD-FLIM

methods. The histograms as well as the standard deviations of the lifetime measurements

are also shown.

1372

Fig. S5. Overview of the *Instant-FLIM-Control* and *Instant-FLIM-Analysis* software.

(**A**) "System calibration" module calibrates the instant FLIM system using a lifetime standard. "Fast scan" module allows fast acquisition (>1 frames per second using galvo scanners) of two-photon intensity images, which can be used to locate the focal position, to

find a ROI, and to generate image-based metrics for the AO optimization algorithms.

"Intensity imaging", "Lifetime imaging", and "Phasor plots" modules simultaneously

acquire and instantaneously generate intensity images, lifetime images, and phasor plots.

"3D and 4D measurements" module configures 3D and 4D instant FLIM measurements and

displays the results. "GSOS (super-resolution FLIM)" module permits two-step GSOS

super-resolution FLIM using two instant FLIM images of the same field-of-view captured

under different excitation powers. "Adaptive optics" module optimizes the Zernike

coefficients applied to the deformable mirror using the three AO optimization algorithms

described in Section S4. (**B**) Screenshot of the *Instant-FLIM-Analysis* program where the

3D intensity and phasor stacks of a living *Tg(sox10:megfp)* zebrafish embryo (2 dpf)

acquired with an instant FLIM system were imported and analyzed. (**C**) Maximized z-

projections of the exported 3D stacks segmented by the phasor labels (top) and the phasor

clusters (bottom, K=5) shown in (B).

1391

1392

Fig. S6. Instant FLIM with phasor labeling and phaser clustering techniques.

(**A**) Demonstration of the phasor labeling technique, where ROIs are manually drawn on the phasor plot of the fixed BPAE cells to label different cellular structures shown on the right. (**B**) Demonstration of the phasor clustering technique, where the phasors of the fixed BPAE cells are automatically clustered using the K-means clustering algorithm (K=3) to denote different cellular structures shown on the right. (**C**) Two-photon fluorescence intensity and lifetime images of MDA-MB-231-EGFP cells under 18 different temperatures acquired with an instant FLIM system. (**D**) Application of the phasor labeling technique to the instant FLIM results of the MDA-MB-231-EGFP cells in (C). (**E**) Application of the phasor clustering technique (K=18) to the instant FLIM results of the MDA-MB-231-EGFP cells in (C). As temperature increases, the GFP lifetimes decrease and the phasors shift from bottom-left to top-right of the phasor plot. Scale bar, 20 µm.

1405

Fig. S7. Instant FLIM with adaptive optics enabling through-skull *in vivo* lifetime imaging of intact mouse brains.

(**A**) *In vivo* two-photon fluorescence intensity and lifetime maximized x-projection 3D images of an intact Cx3cr1-GFP/+ mouse brain acquired with an instant FLIM system without (top) and with (bottom) the adaptive optics (AO) module. (**B**) Skull-excluded maximized z-projections (top) and skull-included 3D reconstructions (bottom) of the *in vivo* intensity, lifetime, and phasor labeled 3D stacks of the intact mouse brain acquired with an instant FLIM system with the AO module. The microglia were labeled with EGFP, and the blood vessels were injected with Texas Red-Dextran. The excitation power was gradually increased from 8.53 mW to 21.13 mW to compensate for the signal loss as the imaging depth increased. Scale bar, 20 μm.

1418

Fig. S8. Super-resolution instant FLIM enabled by GSOS.

1419

(**A**) 3D fluorescence lifetime stacks of a fixed Cx3cr1-GFP/+ mouse brain (microglia

1420

labeled with EGFP; blood vessel injected with Dextran 594) captured by an instant FLIM

1421

system conventionally and combined with the two-step GSOS technique. The conventional

1422

diffraction-limited (DL) stack was imaged at a power of 12.31 mW, and the GSOS stack

1423

was generated by linear combining two stacks imaged at 12.31 mW and 13.44 mW,

1424

respectively. (**B**) Maximized z-projections of the 3D stacks in (A). Insets: magnified views.

1425

(**C**) Maximized x-projections of the 3D stacks in (A). Insets: magnified views. (**D**) Line

1426

profiles of the normalized intensity values at the positions of the white arrowheads in the

1427

DL and GSOS stacks in (B) and (C). Norm., normalized. Scale bars, 20 μm.

1428

1429

1430 **Table S1. Acquisition parameters for all data.**

1431 A table showing the acquisition parameters for all the data used in this work.

Figure	Sample	Dwell time (μs)	Excitation wavelength (nm)	Excitation power (mW)	Image size (pixel/voxel)	Pixel size (nm)	Voxel depth (μm)	Time interval (s)	Notes
Figs. 1B, S6A, S6B	Fixed BPAE cells, mitochondria labeled with MitoTracker Red, F-actin with Alexa Fluor 488, nuclei with DAPI	12 (Average x20)	800	8.95	560 x 560	100	N/A	N/A	2D fixed sample
Fig. 1D	Mixture of fluorescein and rhodamine B	12	800	9.59	360 x 360	200	N/A	N/A	2D fluorophore solution
Fig. 2A, Movie S1	Fixed Cx3cr1-GFP/+ mouse brain, microglia labeled with EGFP, blood vessel injected with Dextran 594	12	920	8.53 to 21.13	540 x 540 x 350	200	0.5	N/A	3D fixed sample
Figs. 2C, S7, Movie S2	Live Cx3cr1-GFP/+ mouse, microglia labeled with EGFP, blood vessel injected with Texas Red-Dextran	12	920	8.53 to 21.13	AO: 360 x 360 x 600 No AO: 360 x 360 x 260	300	0.5	N/A	3D live animal
Fig. 2D	Fixed BPAE cells, mitochondria labeled with MitoTracker Red, F-actin with Alexa Fluor 488, nuclei with DAPI	12 (Average x20)	800	Step1: 8.95 Step2: 10.61	560 x 560	100	N/A	N/A	2D fixed sample; two-step GSOS
Fig. 3B, left	Live *Tg(pu1:gfp)* zebrafish, microglia labeled with EGFP	12	920	12.31	360 x 360 x 60	300	1	N/A	3D live animal
Fig. 3B, right	Live *Tg(pu1:gfp)* zebrafish, microglia labeled with EGFP	12	920	18.43	360 x 360 x 30	300	1	N/A	3D live animal
Fig. 3F	Live *Tg(pu1:gfp)* zebrafish, microglia labeled with EGFP	12	920	12.31	360 x 360 x 30 x 48	300	1	900	4D live animal
Figs. 4B	Live Cx3cr1-GFP/+ mouse, microglia labeled with EGFP, blood vessel injected with Texas Red-Dextran	12	920	12.31	520 x 520 x 20 x 15	200	2	120	4D live animal
Figs. 4C, 4F	Live Cx3cr1-GFP/+ mouse, microglia labeled with EGFP, blood vessel injected with Texas Red-Dextran	12	920	12.31	360 x 360 x 20 x 3	200	2	120	4D live animal
Fig. 5B, Movie S4	Live *Tg(pu1:gfp)* zebrafish, microglia labeled with EGFP, injury induced by 800 nm laser at 43.50 mW for 1 s	12	920	11.05	560 x 560 x 30 x 49	300	1.5	900	4D live animal
Fig. 5F	Live *Tg(pu1:gfp)* zebrafish, microglia labeled with EGFP, injury induced by 800 nm laser at 43.50 mW for 20 s	12	920	11.05	560 x 560 x 30 x 9	300	1.5	900	4D live animal
Figs. 6B, Movie S5	Live Cx3cr1-GFP/+ mouse, microglia labeled with EGFP, blood vessel injected with Texas Red-Dextran, injury induced by 800 nm laser at 43.50 mW for 120 s	12	920	12.31	520 x 520 x 20 x 29	200	2	120	4D live animal
Figs. 6C, 6F	Live Cx3cr1-GFP/+ mouse, microglia labeled with EGFP, blood vessel injected with Texas Red-Dextran, injury induced by 800 nm laser at 43.50 mW for 120 s	12	920	12.31	300 x 300 x 20 x 24	200	2	120	4D live animal
Figs. S6C-S6E	Live MDA-MB-231-EGFP cells imaged at a temperature between 18.1 and 46.7 °C	12 (Average x10)	920	8.53	360 x 360	200	N/A	N/A	2D live cells
Fig. S8, Movie S3	Fixed Cx3cr1-GFP/+ mouse brain, microglia labeled with EGFP, blood vessel injected with Dextran 594	12 (Average x5)	920	Step1: 12.31 Step2: 13.44	540 x 540 x 118	150	0.5	N/A	3D fixed sample; two-step GSOS
Movie S6	Live Cx3cr1-GFP/+ mouse, microglia labeled with EGFP, blood vessel injected with Texas Red-Dextran, injury induced by 800 nm laser at 43.50 mW for 120 s	12	920	12.31	300 x 300 x 20 x 6	200	2	120	4D live animal
Movie S7	Live Cx3cr1-GFP/+ mouse, microglia labeled with EGFP, blood vessel injected with Texas Red-Dextran, injury induced by 800 nm laser at 43.50 mW for 120 s	12	920	12.31	530 x 530 x 20 x 14	200	2	120	4D live animal

1432

1433 **Table S2. Parts and price list for instant FLIM.**

1434 A table showing the budget of all the components necessary for upgrading a conventional

1435 two-photon laser scanning microscope (including data acquisition devices) to an instant

1436 FLIM system.

Vendor	Part number	Qty	Price	Description and link
Instant FLIM components				
ThorLabs	EF502	4	$69.86	Low Pass Filter (LPF), DC-100 kHz, BNC Connector https://www.thorlabs.com/thorproduct.cfm?partnumber=EF502
Mini-Circuits	BLP-90+	2	$35.45	Low Pass Filter (LPF), DC-81 MHz, BNC Connector https://www.minicircuits.com/WebStore/dashboard.html?model=BLP-90%2B
Mini-Circuits	ZX60-P103LN+	6	$69.95	Low Noise Amplifier (LNA), 50-3000 MHz, SMA Connector https://www.minicircuits.com/WebStore/dashboard.html?model=ZX60-P103LN%2B
Mini-Circuits	ZSC-4-3+	2	$56.95	4-Way Power Splitter, 0.25-250 MHz, BNC Connector https://www.minicircuits.com/WebStore/dashboard.html?model=ZSC-4-3%2B
Mini-Circuits	JSPHS-150+	8	$34.95	Phase Shifter (PS), 100-150 MHz, Surface Mount https://www.minicircuits.com/WebStore/dashboard.html?model=JSPHS-150%2B
Mini-Circuits	TB-152+	8	$29.95	Board to Surface Mount Phase Shifters, SMA Connector https://www.minicircuits.com/WebStore/dashboard.html?model=TB-152%2B
Mini-Circuits	ZAD-3H+	4	$50.95	Level 17 Frequency Mixer, 0.05-200 MHz, BNC Connector https://www.minicircuits.com/WebStore/dashboard.html?model=ZAD-3H%2B
Mini-Circuits	ZFBT-282-1.5A+	1	$59.95	Bias Tee, 10-2800 MHz, SMA Connector https://www.minicircuits.com/WebStore/dashboard.html?model=ZFBT-282-1.5A%2B
Total cost:	**$1,666.89**			
Cables and adapters				
Mini-Circuits	141-24BM+	4	$19.45	24" Coaxial Cable, BNC Connector https://www.minicircuits.com/WebStore/dashboard.html?model=141-24BM%2B
Mini-Circuits	141-18BM+	18	$18.45	18" Coaxial Cable, BNC Connector https://www.minicircuits.com/WebStore/dashboard.html?model=141-18BM%2B
Mini-Circuits	086-6BM+	6	$15.75	6" Coaxial Cable, BNC Connector https://www.minicircuits.com/WebStore/dashboard.html?model=086-6BM%2B
Mini-Circuits	086-2SM+	8	$10.75	2" Coaxial Cable, BNC Connector https://www.minicircuits.com/WebStore/dashboard.html?model=086-2SM%2B
Mini-Circuits	SF-BF50+	6	$3.95	SMA-F to BNC-F Adapter https://www.minicircuits.com/WebStore/dashboard.html?model=SF-BF50%2B
Mini-Circuits	SM-BF50+	12	$3.95	SMA-M to BNC-F Adapter https://www.minicircuits.com/WebStore/dashboard.html?model=SM-BF50%2B
Mini-Circuits	SM-BM50+	6	$3.95	SMA-M to BNC-M Adapter https://www.minicircuits.com/WebStore/dashboard.html?model=SM-BM50%2B
Total cost:	**$685.20**			*Note: cheaper cables and adapters are available from other vendors*

1437

1438

Movie S1. Instant FLIM imaging of a fixed mouse brain.

Slices and 3D reconstructions of two-photon fluorescence intensity, lifetime, and phasor labeled stacks of a fixed Cx3cr1-GFP/+ mouse brain (microglia labeled with EGFP; blood vessel injected with Dextran 594) measured with an instant FLIM system. The stacks were captured from the surface to the depth of 175 μm inside the tissue.

Movie S2. Through-skull *in vivo* instant FLIM imaging of intact mouse brains with adaptive optics.

Slices and 3D reconstructions of two-photon fluorescence intensity and lifetime stacks of a living Cx3cr1-GFP/+ mouse brain acquired with an instant FLIM system without (left) and with (right) an adaptive optics (AO) module. The "No AO" and "AO" stacks were captured from the surface of the skull to 130 μm and 300 μm inside the brain, respectively. The excitation power was gradually increased from 8.53 mW to 21.13 mW to compensate for the signal loss as the imaging depth increased.

Movie S3. Super-resolution instant FLIM imaging of a fixed mouse brain.

3D reconstructed fluorescence lifetime stacks of a fixed Cx3cr1-GFP/+ mouse brain (microglia labeled with EGFP; blood vessel injected with Dextran 594) captured by an instant FLIM system conventionally (left) and combined with the two-step GSOS technique (right). The stacks were captured from the surface to the depth of 59 μm inside the tissue. The diffraction-limited (DL) conventional stack was imaged at a power of 12.31 mW, and the GSOS stack was generated by linear combining two stacks imaged at 12.31 mW and 13.44 mW, respectively.

Movie S4. 4D *in vivo* instant FLIM imaging in an injured zebrafish brain.

4D reconstructions of the two-photon fluorescence intensity, lifetime, and lifetime surface rendering stacks of the microglia in a living *Tg(pu1:gfp)* zebrafish brain at 4 dpf acquired with an instant FLIM system. The 4D stacks were captured every 15 minutes and the totally imaging session was 12 hours long. A laser injury was induced at $t = 30$ minutes by an 800 nm laser at 43.50 mW lasting for 1 second. The site of the injury is denoted with dashed yellow circles. The dynamics as well as the lifetime changes of the zebrafish microglia responding to the injury can be observed with the 4D movie.

Movie S5. 4D *in vivo* instant FLIM imaging in an injured mouse brain.

4D reconstructions of the two-photon fluorescence intensity and lifetime stacks of the microglia in a living Cx3cr1-GFP/+ mouse brain acquired with an instant FLIM system. The 4D stacks were captured every 2 minutes and the totally imaging session took 56 minutes. A laser injury was induced at $t = 4$ minutes by an 800 nm laser at 43.50 mW lasting for 120 seconds. The site of the injury is denoted with dashed yellow circles. The dynamics and the lifetime changes of the mouse microglia responding to the injury can be seen with the 4D movie.

Movie S6. 4D *in vivo* lifetime and phasor imaging in injured mouse brains.

Two-photon fluorescence intensity and lifetime maximized z-projections of the 4D stacks as well as their phasor plots for each time point of the microglia in a living Cx3cr1-GFP/+ mouse brain acquired with an instant FLIM system. A laser injury was induced at $t = 0$ by an 800 nm laser with a power of 43.50 mW lasting for 120 s. The sites of the injury are denoted with dashed yellow circles. The stacks were captured at 8 different injury sites from one of two mice.

1488

Movie S7. Phasor labeling and phasor clustering techniques applied to 4D _in vivo_ instant

FLIM stacks of an injured mouse brain.

Reconstructed 4D stacks of the microglia in a living Cx3cr1-GFP/+ mouse brain segmented

with the phasor labeling (left) and phasor clustering (K=5) (right) techniques. A laser injury

was induced at $t = 0$ by an 800 nm laser with a power of 43.50 mW lasting for 120 s. The

site of the injury is denoted with dashed yellow circles. The cellular structures segmented

by the phasor labels or clusters all responded to the injury.