Real-time suppression and amplification of frequency-specific neural activity using stimulation evoked oscillations

David Escobar Sanabria[a], Luke A. Johnson[a], Ying Yu[a], Zachary Busby[a], Shane Nebeck[a], Jianyu Zhang[a], Noam Harel[b], Matthew D. Johnson[c], Gregory F. Molnar[a], Jerrold L. Vitek[a*]

[a] Department of Neurology, University of Minnesota, Minneapolis, MN 55455, USA

[b] Department of Radiology, University of Minnesota, Minneapolis, MN 55455, USA

[c] Department of Biomedical Engineering, University of Minnesota, Minneapolis, MN 55455, USA.

* Correspondence should be addressed to Jerrold L. Vitek (vitek004@umn.edu)

Keywords

Closed-loop brain stimulation, neural oscillations, brain circuits, stimulation-evoked oscillations

Abstract

Background: Approaches to predictably control neural oscillations are needed to understand their causal role in brain function in healthy and diseased states and to advance the development of neuromodulation therapies. In this study, we present a closed-loop neural control and optimization framework to actively suppress or amplify low-frequency neural oscillations observed in local field potentials in real-time by using electrical stimulation.

Objective/Hypothesis: The rationale behind this control approach and our working hypothesis is that neural oscillatory activity evoked by electrical pulses can suppress or amplify spontaneous oscillations via destructive or constructive interference when stimulation pulses are continuously delivered with appropriate amplitudes and at precise phases of these oscillations in a closed-loop scheme.

Methods: We tested our hypothesis in two nonhuman primates that exhibited a robust increase in low-frequency (8-30 Hz) oscillatory power in the subthalamic nucleus (STN) following administration of the neurotoxin MPTP (1-methyl-4-phenyl-1,2,3,6-tetrahydropyridine). To test our neural control approach, we used electrode arrays and electrical stimulation waveforms similar to those used in humans chronically implanted with brain stimulation systems. Stimulation parameters that maximize the suppression or amplification of neural oscillations were predicted using mathematical models of the stimulation evoked oscillations.

Results: Our neural control and optimization approach was capable of actively and robustly suppressing or amplifying oscillations in the targeted frequency band in real-time in the studied subjects.

Conclusions: The results from this study support our hypothesis and suggest that the proposed neural control framework allows one to characterize in controlled experiments the functional role of circuit-level neural oscillations by using electrodes and stimulation waveforms currently being used in humans.

Introduction

Neuromodulation approaches that predictably control circuit-level neural dynamics in real-time will be of utility in neuroscience to deductively infer causal relationships between controlled changes in these dynamics and brain function. These control approaches could also help identify neural processes causally linked to the manifestation of brain conditions and inform the development of neuromodulation therapies. Neural oscillatory dynamics observed from local field potentials (LFPs) are of particular interest to the development of neuromodulation therapies with feedback given the long-term stability of LFP recordings in cortical and subcortical brain structures in human subjects[1,2]. Evidence from experimental studies and computer simulations suggest that LFP oscillations at low-frequency (<100 Hz) are generated predominantly by synchronized synaptic inputs to neuronal ensembles near the recording site[3,4]. Controlling synchronized synaptic activity in a targeted neuronal ensemble can therefore help modulate information flowing into the target, and thereby influence the information flowing out of the target. Feedback (closed-loop) control systems offer the ability to

control neural oscillatory activity by using LFP activity as a feedback signal and electrical stimulation for actuation[5].

Closed-loop stimulation systems being tested in human subjects deliver isochronal (fixed-frequency) electrical pulses on demand based upon neurophysiological signals extracted from LFP recordings. These on-demand systems have been used in patients with epilepsy[6] and Parkinson's disease (PD)[7–10] to minimize the amount of stimulation energy delivered to the brain and the likelihood of side effects that may occur with continuous stimulation as a result of current spread beyond the targeted region. Current on demand systems based on isochronal stimulation are, however, not capable of actively suppressing or amplifying neural oscillatory activity in specific frequency bands in real-time.

Stimulation based on the phase of neural oscillations has been proposed as a feedback signal to alter the dynamics of neuronal populations [11,12]. A recent experimental study has shown that brief administration of electrical pulses phase-locked to oscillations in cortical networks can alter plasticity in nonhuman primates[13]. A study with PD patients undergoing DBS implantation surgery suggests that open-loop, isochronal, low-frequency stimulation delivered dorsal to the subthalamic nucleus (STN) could alter the amplitude of low-frequency oscillations recorded in the STN, whenever consecutive stimulation pulses landed at specific phase angles of these oscillations[14]. A recent study with nonhuman primates has also shown that brief stimulation bursts of intra-cortical microstimulation aligned with the peaks or troughs of neural oscillations in the motor cortex can result in changes in the amplitude of LFP oscillations near the stimulating electrodes, neuronal firing, and motor performance when delivered during a neuro-feedback task[15]. While phase-locked stimulation is promising to modulate oscillatory activity within a neuronal ensemble, the rationale to actively suppress or amplify neural oscillations in the circuit-level by using implantable electrodes remains unclear. This rationale together with strategies to predictably optimize stimulation parameters based on neurophysiological data need to be developed if are to bring active neural control technologies to clinical studies.

In this study, we demonstrate that active suppression or amplification of spontaneous neural oscillations can be achieved in real-time by using destructive (or constructive) interference created with damped oscillations evoked by electrical pulses. The rationale behind this approach is that spontaneous oscillations associated with synaptic inputs to a targeted neuronal ensemble can be actively overwritten using stimulation-evoked oscillations. We employed a feedback control and optimization framework in which LFP measurements from chronically implantable electrodes are used for both sensing and delivering macro-stimulation. In this framework, active suppression or amplification of neural oscillations is achieved by continuously delivering stimulation pulses of adequate amplitude at precise phases of these oscillations in a closed-loop scheme. This strategy enables the use of stimulation waveforms with fixed amplitude similar to those used in humans chronically implanted with brain stimulation systems, making this technique feasible for human studies in the near future. We solved the experimentally intractable problem of finding optimal stimulation parameters to amplify or suppress neural oscillations by using mathematical models of stimulation evoked potentials and computer simulations of the closed-loop neuromodulation system. This neural control framework, referred to as Closed-Loop Stimulation-Evoked Interference (CL-SEI), was tested with two parkinsonian nonhuman primates, which exhibited a robust increase in the power of oscillations in the 8-30 Hz frequency band following administration of the neurotoxin MPTP (1-methyl-4-phenyl-1,2,3,6-tetrahydropyridine), similar to the oscillations observed in PD patients

and thought to underlie the development of PD motor signs[16,17]. We were able to actively suppress or amplify STN oscillations in the studied animals by delivering stimulation pulses in the internal segment of the globus pallidus (GPi). Our data also demonstrates that the mechanism by which CL-SEI exerts its modulatory effect is constructive or destructive interference between low-frequency oscillations evoked by stimulation and the spontaneous oscillations in the site targeted for modulation.

Material and Methods

Instrumentation and subjects. All procedures were approved by the University of Minnesota Institutional Animal Care and Use Committee (IACUC) and complied with United States Public Health Service policy on the humane care and use of laboratory animals. Two adult rhesus macaques (female Macaca mulatta) were used in this study, subjects: J (17 years), P (18 years). Each animal was implanted in both the STN and GPi with 8-contact scaled-down versions of human DBS leads (0.5 mm contact height, 0.5 mm inter-contact spacing, 0.625 mm diameter, NuMED, Inc.) as previously described[18]. DBS lead locations were approximated using fused pre-implantation MR and post-implantation CT images, histological reconstructions (**Fig. A.1**), and microelectrode mapping of the STN and GPi prior to implantation of the DBS leads. The animals were rendered parkinsonian by systemic-intramuscular and intra-carotid injections of the neurotoxin 1-methyl-4-phenyl-1,2,3,6 tetrahydropyridine (MPTP)[19].

Neural data acquisition. Neurophysiological data in the awake-resting state of the studied subjects were utilized to characterize how neural oscillations across frequencies changed in the STN from the normal to the parkinsonian condition and identify oscillations targeted for modulation using CL-SEI. Neural data were collected using a Tucker David Technologies (TDT, Alachua, FL, USA) workstation with a sampling rate of ~24 KHz. Signals were band-pass filtered (0.5-1400 Hz) to extract LFP data and down-sampled to ~3 KHz for analysis. LFPs were created by subtracting potentials from contacts estimated to be within the STN to suppress far field potentials. We verified that the animals were alert using video monitoring and image processing techniques[18]. The power of neural oscillations across frequencies was computed using power spectral densities (PSDs) and the Welch's method. The PSD curves were normalized with respect to the total power, which is the sum of PSD values over all frequencies. Oscillatory modes with the highest power across frequency were selected for modulation using CL-SEI. Analyses were performed using customized scripts in MATLAB (Mathworks, Natick, MA, USA).

Stimulation evoked potentials. Electrical stimulation was delivered in the GPi to modulate oscillations in the STN for two reasons. First, large evoked potentials were observed in the STN of both animals when stimulation (bipolar, biphasic) was delivered in the GPi. Second, stimulation in the GPi resulted in smaller stimulation-induced artifacts in the STN than those observed when stimulation was delivered within the STN itself, facilitating the suppression of artifacts in real-time. We characterized the temporal dynamics of stimulation-evoked potentials in the STN by delivering low-frequency (<4 Hz) anodal and cathodal stimulation to the GPi, computing stimulation triggered averages of the LFP time series in the STN for both anodal and cathodal stimulation ($X_a(t)$ and $X_c(t)$), and calculating the mean between the anodal and cathodal responses (($X_a(t) + X_c(t))/2$). This mean evoked response attenuates the stimulation artifacts while preserving the neural evoked potential[20]. The amplitude of the stimulation pulses used to characterize evoked potentials and implement the CL-SEI technique in animal J

and P was below 800 μA, which was in turn below the stimulation threshold at which we observed side effects associated with activating the internal capsule (e.g. muscle contractions).

Implementation of neural control approach. We implemented CL-SEI using a TDT neurophysiological recording and stimulation system (TDT, Alachua, FL, USA) and a computer fully dedicated to executing signal processing and control algorithms in real-time (Simulink Real-Time, Natick, MA, USA). LFP data were sampled at ~24 KHz in the neurophysiological recording system, amplified in the +/-10 V range, and transmitted to the control computer via analog channels. Stimulation was delivered using bipolar, charge-balanced, biphasic, symmetric stimulation pulses with pulse widths of 80 µsec. The cathode and anode of the stimulation system were connected to separate contacts in the DBS lead located within the GPi. This bipolar configuration was employed to minimize the size of artifacts in the recording site. The LFPs were digitized in the control computer at ~24 KHz to reconstruct the shape of electrical artifacts induced by stimulation and minimize the effect of antialiasing filters on the measured artifacts. Electrical artifacts were suppressed from the LFP data by holding for 2.3 ms the value of the LFP sample acquired before the stimulation pulse was triggered. The 2.3 ms holding period was longer than the duration of the artifact but short enough to avoid degrading information recorded at low-frequency. The artifact-suppressed LFP data were then band-pass filtered in the frequency band selected for modulation using second-order Butterworth filters and subsequently down-sampled at ~3 KHz. A frequency range of 6 Hz around the targeted center frequencies was selected for the implementation of CL-SEI to allow for variations in the frequency of oscillatory activity while attenuating information outside the frequency band of interest.

The instantaneous phase and amplitude of oscillations in the targeted frequency band were estimated using a Hilbert transformer filter[21]. The Hilbert filter introduced 16 samples of time delay (5.3 ms) to the closed-loop interconnection. A train of stimulation pulses, three for animal J and one for animal P, were delivered at specified phase angles. whenever the amplitude envelope of the oscillations was above the 25th percentile of the envelope computed in the off-stimulation state. A train of 3 pulses (165 Hz intra-burst rate) was used in animal J to enhance the modulatory effect of stimulation via temporal summation, with the first pulse of the train aligned to the targeted phase estimate. Stimulation was turned off when the envelope was below threshold to avoid delivering stimulation based on measurements with small signal to noise ratio. The total delay of the closed-loop interconnection, associated with hardware communication, was less than 1 ms.

Estimation of optimal stimulation parameters. Mathematical models of the stimulation evoked oscillations were developed to estimate the stimulation phase and amplitude that maximize the suppression or amplification of neural oscillations. Evoked potentials were characterized using linear, time-invariant differential equations and parameterized via system identification techniques[22]. A dead-zone operator was included in the models as evoked potentials were observed when the stimulation amplitude was greater than or equal to a non-zero value (lower bound). A more detailed description of the evoked potential characterization is presented in the **Appendix A**. By using these mathematical, numerical simulations were created in which the closed-loop algorithms were evaluated. The numerical simulations incorporated the same algorithms, filters, and time delays present in the real-time control computer to predict optimal stimulation amplitude and phase angles that suppress or amplify oscillations. In these computer simulations, evoked potential models as well as computer-generated sinusoidal oscillations (synthetic) or previously recorded LFP data were added to

obtain the modulated oscillations. We used sinusoids with an amplitude equal to the mean amplitude of experimentally recorded STN oscillations as a synthetic LFP signal in the computer simulation. Stimulation was delivered at various phase angles (-175, -170, 165, …, 180 deg) and stimulation amplitudes (300, 350….,750, 800 μA) in the computer simulations and a search was performed to calculate the optimal phases and amplitudes that resulted in maximum suppression or amplification of the oscillations in the targeted frequency band. The amplitude envelope of the modulated signal in the targeted frequency band was then used to quantify the degree of modulation achieved using CL-SEI in the simulation.

Quantification of neural modulation. We assessed whether the amplitude of neural oscillations changed when CL-SEI was delivered by using scalar measurements of the oscillations' amplitude envelope. The scalar measurements are equal to the average of the amplitude envelope over non-overlapping windows of one-second duration. The analytical amplitude of neural oscillations in the targeted frequency band was computed by filtering the raw data in this band, applying the Hilbert transform, and calculating the magnitude of the analytic signal obtained from the Hilbert transform. Pairwise differences between scalar measurements of the oscillations' amplitude in two different conditions were assessed via the Wilcoxon rank-sum test. The p-values resulting from this test were corrected for the number of comparisons via the Bonferroni method. We assumed that the difference between measurements in the two conditions was significant when $p < 0.05$. The comparisons made were stimulation off vs amplification and stimulation off vs suppression.

Results

Spontaneous neural activity can be modulated using CL-SEI. The studied animals exhibited a robust increase in the power of oscillations in the STN in the 8-30 Hz band following MPTP treatment. See PSD plots in **Figs. 1b,c**. The frequency bands with highest power and targeted for modulation were centered at around 11 Hz in animal J and 14 Hz in animal P (**Fig. 1b,c**). Potentials in the STN evoked by stimulation in the GPi exhibited short-latency, high-frequency oscillations as well as low-frequency oscillations (**Figs. 1d-g).** The low-frequency oscillations were used in the CL-SEI system to modulate the targeted spontaneous oscillations in both animals.

By continuously delivering CL-SEI, we were able to modulate targeted neural oscillations in the STN of both animals. The amplitude of neural oscillations in the targeted frequency bands was a function of the phase angle at which a train of stimulation pulses of fixed amplitude was delivered (**Figs. 2a-d**). The phase angles for which maximum amplification or suppression of neural oscillations were achieved at a fixed stimulation amplitude were unique, with a phase lag of 180 deg. The amplitude of oscillations in the modulated frequency band was significantly decreased (or increased) when stimulation was delivered at the optimal phase for suppression (or amplification) as compared to the amplitude when stimulation was turned off ($p < 0.05$). Boxplots that summarize the effect of suppression and amplification of neural oscillations are shown in **Fig. 3**. The degree of amplification was higher than the degree of suppression in the experiments. One reason for this difference is that stimulation was discontinued when the amplitude envelope of the oscillations was below the 25th percentile threshold (Methods section).

Modulation was local and not artifactual. In both subjects, the degree of modulation across different contact pairs in different regions inside and outside of the STN was not correlated with the size of the stimulation-induced artifacts, indicating that simulation-induced artifacts did not influence the observed modulation (**Figs. 2c,d**). Evoked potentials measured with electrodes estimated to be within the STN were larger than those outside the STN, suggesting that evoked neural activity was generated by neural sources and sinks located near electrodes located within the STN. Furthermore, spontaneous oscillations in the 8-30 Hz exhibited larger amplitudes inside the STN than outside (OFF state in **Fig. 2c,d**). The degree of amplification or suppression of these spontaneous oscillations achieved using CL-SEI was larger in electrodes located within the STN.

Modulation was mediated by low-frequency evoked oscillations. Short duration (<3 ms) and short latency (<3 ms) components of the evoked potentials, likely associated with antidromic activation of the STN by stimulation of the GPi, were observed in our data (**Figs. 1d,e**), but had a negligible effect on the spectral measurements at low-frequency bands due to their low power in these bands. When the short-duration and short-latency oscillations are blanked in the LFP time series, the modulation observed in **Fig. 2a,b** remains unchanged. The observed modulation (**Figs. 2a-d**) was therefore mediated by stimulation evoked oscillations at lower frequencies.

Optimal modulation parameters were estimated using data-driven models of the evoked potentials. The input-output relationship between the stimulation pulse and evoked potential

was accurately characterized by the mathematical models described in the Methods Section and **Appendix A** (**Figs. 4a,b** and **Fig. A2)**. A computer simulation of the experiment shown in **Fig. 4d** was created using LFP data in the stimulation-off condition and is shown in **Fig. 4e**. The computer-generated data reproduces the changes in oscillatory power as a function of stimulation phase observed in the in-vivo experiment (**Fig. 4d** vs **Fig. 4e**). This similarity provides evidence of the modulatory role of stimulation-evoked oscillations in the CL-SEI framework.

We applied the search approach described above to estimate the optimal stimulation phase and amplitude to suppress/amplify 11-17 Hz oscillations in animal P by using one single stimulation pulse. The optimization considered the mean amplitude of the oscillations' envelope measured in the resting, off-stimulation state of the animal. A map of the optimization search, with values of the mean amplitude of the oscillations' envelope after CL-SEI is applied in the computer simulations at different phases and amplitudes, is shown in **Fig. 5a**. The optimal phase and amplitude to suppress oscillations were found to be 35 deg and 600 μA, respectively. The optimal phase to amplify oscillations at the same amplitude ($600\mu A$) was found to be 145 deg. The optimal phase angles for both suppression (35 deg) and amplification (-145 deg) of oscillations at a fixed stimulation amplitude of 600 μA were the same as those found in the experiment depicted in **Figs. 2b** and **Fig. 3c.** This match suggests that the optimization approach can accurately predict the optimal stimulation parameters. Note that the optimal stimulation amplitude to <u>amplify oscillations</u> is equal to the maximum amplitude (upper bound) employed in the search since the size of the evoked oscillations is proportional to the stimulation amplitude[20,23]. The optimal amplitude to <u>suppress oscillations</u> is not necessarily equal to the optimal stimulation amplitude to amplify oscillations since evoked oscillations with high amplitude can create constructive interference even when delivering stimulation at phase angles at which suppression is achieved at lower stimulation amplitudes. The stimulation parameters found in the search algorithm were used in an experiment with the animal, in which we alternated between maximum suppression and amplification of neural oscillations (**Fig. 5b**). The results shown in **Fig. 5b** illustrate the capability of CL-SEI to actively suppress or amplify neural oscillations in real-time. The experiments also show that while we attempt to modulate neural oscillations in the 11-17 Hz band, there are changes in power in adjacent frequency bands.

Discussion

We developed an experimental approach and optimization framework capable of precisely suppressing or amplifying the amplitude of neural oscillations with the resolution and time-scale required to characterize the functional role of oscillatory dynamics in brain circuits. The optimization framework described in this article resolves the experimentally intractable problem of predicting phase angles and stimulation amplitudes that maximize the degree of suppression or amplification of targeted neural oscillations. Together these neural control and optimization approaches enable researchers to address questions regarding the role of circuit-level oscillatory dynamics in brain function in healthy and disease states. By improving our understanding of neural circuit dynamics in brain conditions, this closed-loop stimulation approach could also guide the development of subject specific neuromodulation therapies. While we deliver stimulation based on the phase of neural oscillations, it should be noted that the rationale behind using phase feedback is different to that of methods that are intended to induce phase desynchronization across interconnected neurons[11,12], alter short-term

plasticity[13], or modulate the balance between depolarization and hyperpolarization of neurons in the proximity of the stimulating electrodes[15]. The approach presented here differs in that it continuously overwrites the inputs of targeted neuronal populations to amplify or suppress oscillations via interference created with "new" oscillations evoked by electrical pulses. The main reason for employing phase-locking as a strategy to create neural interference is that it is more readily translated to clinical practice since one can use stimulation waveforms that do not change their amplitude, pulse-width, or shape in real-time. Phase-locked electrical stimulation with a fixed stimulation amplitude and pulse-width is, however, a suboptimal strategy to achieve interference because dynamic changes in the amplitude of neural oscillations are not considered in the optimization framework. Advanced feedback control algorithms that adapt to changes in the amplitude of oscillatory activity combined with stimulation systems that allow for instantaneous changes in stimulation parameters are more likely to produce better interference patterns and need to be developed if we are to achieve optimal control of pathological oscillatory activity in PD and other disorders via CL-SEI.

Modulation mechanisms of CL-SEI. The mechanism by which CL-SEI exerts its effect on neural oscillatory activity is likely secondary to its effect on synaptic inputs evoked by electrical stimulation and generated by activation of mono- or multi-synaptic connections to targeted neuronal populations[24–27]. We targeted oscillations in the 8-17 Hz band in the STN of two parkinsonian monkeys that exhibited an increase in power following MPTP administration. The mechanisms by which the amplitude of these oscillations increase in parkinsonian animals and are observed in PD patients is still being debated. Studies with the 6-OHDA mouse model of PD and computer simulations of the human STN indicate that a combination of synchronized inhibitory and excitatory synaptic inputs from the cerebral cortex and the external segment of the globus pallidus (GPe), innervating common neuronal ensembles contributes to the development of these oscillations in the STN[28,29]. In the experiments carried out in this study, we modulated neural oscillations in the STN in the 8-17 Hz band by delivering stimulation with appropriate amplitude in the GPi that was phase-locked to oscillations in the STN. The resultant modulation of oscillatory activity in the STN was mediated by low-frequency, stimulation-evoked oscillations during stimulation in the GPi. Although low-frequency damped oscillations in the STN evoked by GPi stimulation have not been previously characterized, they are likely associated with synaptic inputs to the STN[24–27]. Based on known anatomical connections, these evoked oscillations may emerge from a combination of one or more of the following: 1) antidromic activation of GPe followed by activation of collateral branches projecting to the STN[30]; 2) orthodromic activation of GPi-PPN-STN pathways, and 3) orthodromic activation of pallido-thalamo-cortico-subthalamic loops. Consequently, controlled changes in the amplitude of STN oscillations achieved via stimulation of the GPi may be mediated by simultaneous synaptic inputs to a number of different neuronal ensembles converging on the STN.

Limitations. We assumed that spontaneous and evoked LFP oscillations measured in the STN were associated with synaptic inputs innervating common STN neuronal ensembles. This is a reasonable assumption given that STN neurons simultaneously receive inputs from multiple structures, including the GPe and motor cortex. However, we acknowledge that spontaneous and evoked oscillations may be generated by inputs to adjacent but different populations of neurons, and modulations observed in the experiments may be caused by the superposition of currents from different neuronal ensembles. Recordings of synaptic activity (postsynaptic potentials) and/or neuronal activity in populations of STN neurons during periods of CL-SEI are needed to characterize how this stimulation approach exerts its effect at the cellular level. The experimental data shown in **Figs. 2a,b** and **Fig. 5b** indicate that CL-SEI alters oscillatory activity

in frequency bands not targeted for modulation. These alterations are, at least in part, due to the power content of the evoked neural activity in frequencies outside the band selected for modulation. Stimulation patterns different to fixed-amplitude pulse trains may be needed to reduce the activation of neural oscillatory activity in frequency bands outside that selected for modulation using CL-SEI. The experimental setup used in this study, with electrodes in both the STN and GPi, has been implemented in humans[31]; however, it is not standard practice as DBS leads are typically implanted in one brain target within the same cerebral hemisphere. In applications in which LFPs are recorded from and stimulation is delivered to the same brain region using a single electrode array (e.g. DBS for PD), hardware and/or software technologies that enable robust artifact removal are needed to rigorously implement CL-SEI. The relative benefit of CL-SEI compared to standard brain stimulation approaches using isochronal stimulation remains to be determined, but the potential utility of this technique for both improving current stimulation therapies and for understanding the pathophysiological basis underlying circuit disorders is compelling.

CRediT Authorship Contribution Statement

David Escobar Sanabria: Conceptualization, Methodology, Software, Formal analysis, Validation, Investigation, Visualization, Writing - Original Draft, Funding Acquisition. **Luke A. Johnson:** Resources, Investigation, Visualization, Writing - Review & Editing, Funding Acquisition. **Ying Yu:** Investigation (data collection). **Zachary Busby:** Investigation (data collection). **Shane Nebeck:** Investigation (data collection). **Jianyu Zhang:** Resources, Investigation. **Noam Harel:** Investigation (MR-CT image acquisition). **Matthew D. Johnson:** Writing - Review & Editing, Funding Acquisition. **Gregory F. Molnar:** Project administration, Supervision, Funding Acquisition. **Jerrold L. Vitek:** Conceptualization, Resources, Project administration, Supervision, Validation, Writing - Review & Editing, Funding Acquisition.

Funding source

Research reported in this publication was funded by the Wallin Discovery Fund, the Engdahl Family Foundation, the Kurt B. Seydow Dystonia Foundation, the National Institutes of Health, National Institute of Neurological Disorders and Stroke (P50-NS098573, R01-NS037019, R01-NS077657, R01-NS110613, R01-NS094206), the MN Research Evaluation and Commercialization Hub (MN-REACH), and the University of Minnesota's MnDRIVE (Minnesota's Discovery, Research and Innovation Economy) Initiative.

Acknowledgments

We thank Tay Netoff for the discussions regarding closed-loop brain stimulation techniques as well as Claudia Hendrix, Devyn Bauer and Ben Teplitsky for their help with histology processing.

Declaration of interest

J. L. Vitek has served as a consultant for Medtronic, Boston Scientific and Abbott. Noam Harel and Jerrold L. Vitek are shareholders of Surgical Information Sciences. Gregory F. Molnar has previously consulted for Abbott.

References

[1] Hanrahan SJ, Nedrud JJ, Davidson BS, Farris S, Giroux M, Haug A, et al. Long-Term Task- and Dopamine-Dependent Dynamics of Subthalamic Local Field Potentials in Parkinson's Disease. Brain Sci 2016;6. https://doi.org/10.3390/brainsci6040057.

[2] Staub F, Neumann W-J, Horn A, Schanda J, Schneider G-H, Brown P, et al. EP 4. Long term recordings of deep brain activity from the subthalamic nucleus in PD patients using PC+S. Clinical Neurophysiology 2016;127:e176. https://doi.org/10.1016/j.clinph.2016.05.199.

[3] Buzsáki G, Anastassiou CA, Koch C. The origin of extracellular fields and currents — EEG, ECoG, LFP and spikes. Nat Rev Neurosci 2012;13:407–20. https://doi.org/10.1038/nrn3241.

[4] Herreras O. Local Field Potentials: Myths and Misunderstandings. Front Neural Circuits 2016;10. https://doi.org/10.3389/fncir.2016.00101.

[5] Schiff SJ, Poggio TA, Sejnowski TJ. Neural Control Engineering: The Emerging Intersection Between Control Theory and Neuroscience. Cambridge, UNITED STATES: MIT Press; 2011.

[6] Morrell MJ, RNS System in Epilepsy Study Group. Responsive cortical stimulation for the treatment of medically intractable partial epilepsy. Neurology 2011;77:1295–304. https://doi.org/10.1212/WNL.0b013e3182302056.

[7] Little S, Pogosyan A, Neal S, Zavala B, Zrinzo L, Hariz M, et al. Adaptive deep brain stimulation in advanced Parkinson disease. Ann Neurol 2013;74:449–57. https://doi.org/10.1002/ana.23951.

[8] Arlotti M, Marceglia S, Foffani G, Volkmann J, Lozano AM, Moro E, et al. Eight-hours adaptive deep brain stimulation in patients with Parkinson disease. Neurology 2018;90:e971–6. https://doi.org/10.1212/WNL.0000000000005121.

[9] Velisar A, Syrkin-Nikolau J, Blumenfeld Z, Trager MH, Afzal MF, Prabhakar V, et al. Dual threshold neural closed loop deep brain stimulation in Parkinson disease patients. Brain Stimulation: Basic, Translational, and Clinical Research in Neuromodulation 2019;12:868–76. https://doi.org/10.1016/j.brs.2019.02.020.

[10] Swann NC, de Hemptinne C, Thompson MC, Miocinovic S, Miller AM, Gilron R, et al. Adaptive deep brain stimulation for Parkinson's disease using motor cortex sensing. J Neural Eng 2018;15:046006. https://doi.org/10.1088/1741-2552/aabc9b.

[11] Tass PA. Effective desynchronization with bipolar double-pulse stimulation. Phys Rev E Stat Nonlin Soft Matter Phys 2002;66:036226. https://doi.org/10.1103/PhysRevE.66.036226.

[12] Holt AB, Wilson D, Shinn M, Moehlis J, Netoff TI. Phasic Burst Stimulation: A Closed-Loop Approach to Tuning Deep Brain Stimulation Parameters for Parkinson's Disease. PLoS Comput Biol 2016;12. https://doi.org/10.1371/journal.pcbi.1005011.

[13] Zanos S, Rembado I, Chen D, Fetz EE. Phase-Locked Stimulation during Cortical Beta Oscillations Produces Bidirectional Synaptic Plasticity in Awake Monkeys. Current Biology 2018;28:2515-2526.e4. https://doi.org/10.1016/j.cub.2018.07.009.

[14] Holt AB, Kormann E, Gulberti A, Pötter-Nerger M, McNamara CG, Cagnan H, et al. Phase-Dependent Suppression of Beta Oscillations in Parkinson's Disease Patients. J Neurosci 2019;39:1119–34. https://doi.org/10.1523/JNEUROSCI.1913-18.2018.

[15] Peles O, Werner-Reiss U, Bergman H, Israel Z, Vaadia E. Phase-Specific Microstimulation Differentially Modulates Beta Oscillations and Affects Behavior. Cell Reports 2020;30:2555-2566.e3. https://doi.org/10.1016/j.celrep.2020.02.005.

[16] Brown P. Oscillatory nature of human basal ganglia activity: relationship to the pathophysiology of Parkinson's disease. Mov Disord 2003;18:357–63. https://doi.org/10.1002/mds.10358.

[17] Ray NJ, Jenkinson N, Wang S, Holland P, Brittain JS, Joint C, et al. Local field potential beta activity in the subthalamic nucleus of patients with Parkinson's disease is associated with improvements in bradykinesia after dopamine and deep brain stimulation. Experimental Neurology 2008;213:108–113. https://doi.org/10.1016/j.expneurol.2008.05.008.

[18] Escobar D, Johnson LA, Nebeck SD, Zhang J, Johnson MD, Baker KB, et al. Parkinsonism and Vigilance: Alteration in neural oscillatory activity and phase-amplitude coupling in the basal ganglia and motor cortex. J Neurophysiol 2017:jn.00388.2017. https://doi.org/10.1152/jn.00388.2017.

[19] Hashimoto T, Elder CM, Okun MS, Patrick SK, Vitek JL. Stimulation of the subthalamic nucleus changes the firing pattern of pallidal neurons. J Neurosci 2003;23:1916–23.

[20] Romeo A, Dubuc DM, Gonzalez CL, Patel ND, Cutter G, Delk H, et al. Cortical Activation Elicited by Subthalamic Deep Brain Stimulation Predicts Postoperative Motor Side Effects. Neuromodulation 2019;22:456–64. https://doi.org/10.1111/ner.12901.

[21] Oppenheim AV, Schafer RW, Buck JR. Discrete-time Signal Processing (2Nd Ed.). Upper Saddle River, NJ, USA: Prentice-Hall, Inc.; 1999.

[22] Ljung L. System Identification: Theory for the User. Upper Saddle River, NJ, USA: Prentice-Hall, Inc.; 1986.

[23] Li S, Arbuthnott GW, Jutras MJ, Goldberg JA, Jaeger D. Resonant antidromic cortical circuit activation as a consequence of high-frequency subthalamic deep-brain stimulation. J Neurophysiol 2007;98:3525–37. https://doi.org/10.1152/jn.00808.2007.

[24] Volkov IO. Unit responses in the cat auditory cortex to electrical stimulation of nerve fibers innervating receptor cells in different parts of the organ of corti. Neurophysiology 1982;14:317–23. https://doi.org/10.1007/BF01058742.

[25] Kumaravelu K, Oza CS, Behrend CE, Grill WM. Model-based deconstruction of cortical evoked potentials generated by subthalamic nucleus deep brain stimulation. J Neurophysiol 2018;120:662–80. https://doi.org/10.1152/jn.00862.2017.

[26] Kent AR, Grill WM. Neural origin of evoked potentials during thalamic deep brain stimulation. J Neurophysiol 2013;110:826–43. https://doi.org/10.1152/jn.00074.2013.

[27] Magill PJ, Sharott A, Bevan MD, Brown P, Bolam JP. Synchronous unit activity and local field potentials evoked in the subthalamic nucleus by cortical stimulation. J Neurophysiol 2004;92:700–14. https://doi.org/10.1152/jn.00134.2004.

[28] Wilson CJ, Bevan MD. Intrinsic dynamics and synaptic inputs control the activity patterns of subthalamic nucleus neurons in health and in Parkinson's disease. Neuroscience 2011;198:54–68. https://doi.org/10.1016/j.neuroscience.2011.06.049.

[29] Bevan MD, Magill PJ, Terman D, Bolam JP, Wilson CJ. Move to the rhythm: oscillations in the subthalamic nucleus–external globus pallidus network. Trends in Neurosciences 2002;25:525–31. https://doi.org/10.1016/S0166-2236(02)02235-X.

[30] Johnson MD, McIntyre CC. Quantifying the Neural Elements Activated and Inhibited by Globus Pallidus Deep Brain Stimulation. Journal of Neurophysiology 2008;100:2549–63. https://doi.org/10.1152/jn.90372.2008.

[31] Bilateral implantation in globus pallidus internus and in subthalamic nucleus in Parkinson's disease. - PubMed - NCBI n.d. https://www-ncbi-nlm-nih-gov.ezp3.lib.umn.edu/pubmed/22151377 (accessed January 23, 2020).

Figure Legends

Figure 1. Closed-loop stimulation evoked interference (CL-SEI) framework and concept. (a) Schematic of closed-loop neuromodulation framework in which stimulation-evoked activity is used to suppress or amplify spontaneous neural oscillations when stimulations pulses of appropriate amplitude are phase-locked to these oscillations. The power spectral density (PSD) plots of spontaneous LFP recordings in the STN of the studied animal J and P in the normal and parkinsonian conditions are shown in (b) and (c), respectively. Shaded regions represent interquartile ranges of the PSD curves at each frequency. The frequency bands targeted for modulation using CL-SEI are highlighted in gray. These frequency bands have a range of 6 Hz with center frequencies equal to the peak frequency of the PSD plots. Electric potentials in the STN of animal J and P evoked by stimulation pulses in the GPi are shown in (d) and (e), respectively. The evoked potentials displayed in this figure are the average response of a single pulse with an amplitude equal to 600 μA for animal J and 800 μA for animal P. Short-duration and short-latency evoked oscillations, depicted in (d) and (e), are associated with antidromic neural activation of the STN following the stimulus pulse. (f,g) Stimulation-evoked potentials in the targeted frequency bands for animal J and P are shown. The potentials in (f,g) illustrate the evolution of oscillations evoked by a single stimulation pulse in the frequency bands targeted for modulation using CL-SEI, responsible for the modulation observed when stimulation is delivered. Note that the time scale of the evoked potentials shown in (f-g) is different to that shown in (d-e).

Figure 2. Amplitude of oscillations as a function of stimulation phase. (a, b) Results of experiments in which CL-SEI was tested in animal J and P. The targeted (reference) phase angle for stimulation was varied by 10 degrees every 10 seconds, while the stimulation current delivered to the GPi was fixed at 600 μA in both animals. Spectrograms illustrating the power over time and frequencies for different phase angles in the OFF and ON stimulation state are shown in (a) and (b) for animal J and P, respectively. The spectrograms show data recorded using electrode pairs used to implement the closed-loop stimulation algorithm. The amplitude of neural oscillations as a function of the targeted phase angle and across electrode pairs is shown for animal J and P in (c) and (d), respectively. Electrodes C0-C2 in animal J and C4-C6 in animal P used for sensing are located within the STN. The artifacts and evoked potentials computed across electrode pairs are shown in (c) and (d) (center and right columns). Evoked potentials were calculated based on stimulation-triggered averages of LFPs by using both cathodal and anodal stimulation ($X_a(t)$ and $X_c(t)$). These evoked potentials were calculated as $((X_a(t) + X_c(t))/2)$.

Figure 3. Differences between the amplitude of oscillations when stimulation was OFF and when stimulation was delivered at the phase angles associated with maximum suppression/amplification. (a) Schematic of phase angles at which stimulation was delivered to achieve maximum suppression (blue arrow) or amplification (green arrow) of neural oscillations in the 8-14 Hz band for animal J and 11-17 Hz band for animal P, respectively. (b) Box plots illustrating the interquartile ranges and medians of 1-second segments of the amplitude envelope of LFP data filtered in the targeted frequency band in the OFF stimulation state and when stimulation was delivered at phase angles that achieved maximum suppression and amplification of oscillations. We assumed that the difference between measurements in the two

conditions was significant when p < 0.05. The p-values resulting from this test were corrected for the number of comparisons via the Bonferroni method. The number of data segments (n) the in the OFF stimulation, amplification, and suppression conditions for animal J were 143, 27, and 18, respectively; for animal P these numbers were 150, 20, and 20, respectively. The boxplots were created based on data from the experiment illustrated in **Fig. 2**.

Figure 4. Computer simulations of CL-SEI. (a, b) Stimulation-evoked potentials calculated using experimental data together with their corresponding mathematical models. The evoked potential mathematical models are computed through the convolution of an evoked potential transfer function obtained via system identification techniques and the stimulation pulse mathematical function. (c) Schematic of computer simulation in which pre-recorded or computer-generated (synthetic) oscillations are added to the evoked potential (EP) time series to model the steady-state of modulated oscillations. The evoked potential time series is computed through the mathematical model with an input equal to stimulation pulses phase-locked to the oscillations in the selected frequency band. (d) Experimental data with animal J in which phase angles were varied over time. (e) Computer simulation of CL-SEI created using STN LFP data (stimulation-free) from animal J and mathematical models of the stimulation-evoked potentials. The targeted phase angles in both experiments and computer simulation were varied over time, increasing the phase angle by ten degrees each ten seconds.

Figure 5. Optimization of stimulation parameters. (a) Optimization map to estimate optimal stimulation amplitudes and phases to suppress/amplify neural oscillations in the 11-17 Hz band with a mean amplitude of 1.95 μA in animal P by using CL-SEI. The color scale represents the mean amplitude of oscillations created in computer stimulations at different stimulation phases and amplitudes. The optimal phase and amplitude to suppress oscillations were found to be 35 deg and 600 μA, respectively. (b) Spectrogram of STN LFP data in which CL-SEI was delivered at stimulation amplitude found to be optimal for suppression of 11-17 Hz oscillations (600 μA). The stimulation phase was alternated between the optimal phase for suppression and the optimal phase for amplification at 600 μA, which is illustrated with the white curve on the spectrogram. The recordings shown in this figure are from the electrode pair that was used for sensing in the closed-loop stimulation system.

Figure 1.

a   Schematic of closed-loop brain stimulation framework

b   PSD of STN recordings in subject J

c   PSD of STN recordings in subject P

d   Stimulation evoked potential in the STN of subject J

e   Stimulation evoked potential in the STN of subject P

f   Evoked potential in targeted freq. band in subject J

g   Evoked potential in targeted freq. band in subject P

Figure 2.

Figure 3.

a

Subject J   Subject P

-180°   0°   180°   -180°   0°   180°

↑amplification ↓suppression

b

STN LFP amp. in 8-14 Hz (μV)

OFF   135°   -45°

* p<0.05

c

STN LFP amp. in 11-17 Hz (μV)

4
3
2
1

OFF   35°   -145°

Figure 4.

a
Stim. evoked potential model for animal J

— math model
-·-·- 600 uA

b
Stim. evoked potential model for animal P

— math model
-·-·- 800 uA scaled

c
Schematic of computer simulation

LFP recording

100 msec

Stim. pulses

100 msec

EP mathematical model

— Cathodal stim
— Meas. EP
-- Model EP

STN EP

2 msec

Simulation LFP + EP

100 msec

d
Experiment with animal J

OFF — Closed-loop system ON — OFF

Stim phase 180° 0° 180°

e
Computer simulation

OFF — Closed-loop system ON — OFF

Stim phase 180° 0° 180°

Figure 5.

a

Search for optimal stimulation parameters using computer simulation

b

Animal experiment with optimal stimulation parameters