The Series of a Four-node Motif and Coherent Type-1 Feed-forward Loop can Provide Sensitive Detection over Arbitrary Range of Input Signal, thereby Explain Weber's Law in Higher-Order Sensory Processes, and Compute Logarithm

Dinkar Wadhwa*

Department of Systems and Computational Biology

University of Hyderabad, Hyderabad - 500046, India

dinkar.wadhwa84@gmail.com

*The author did 90% of the work without an affiliation.

Abstract

Weber's law states that the ratio of the smallest perceptual change in an input signal and the background signal is constant. The law is observed across the perception of weight, light intensity, and sound intensity and pitch. Conventionally, two models of perception have been proposed to explain Weber's law, namely the logarithmic and the linear model. Later, another formulation of Weber's law was proposed which links it with exact adaptation. This paper argues in favour of the linear model, which requires the sensory system to generate linear input-output relationship over several orders of magnitude. To this end, a four-node motif (FNM) is constructed from first principles whose series provides almost linear relationship between input signal and output over arbitrary range of input signal. Mathematical analysis into the origin of this quasi-linear relationship shows that the series of coherent type-1 feed-forward loop (C1-FFL) is able to provide perfectly linear input-output relationship over arbitrary range of input signal. FNM also reproduces the neuronal data of numerosity detection study on monkey. The series of FNM also provides a mechanism for sensitive detection over arbitrary range of input signal when the output has an upper limit. Further, the series of FNM provides a general basis for a class of bow-tie architecture where the number of receptors is much lower than the range of input signal and the "decoded output". Besides (quasi-)linear input-output relationship, another example of this class of bow-tie architecture that the series of FNM is able to produce is absorption spectra of cone opsins of humans. Further, the series of FNM and C1-FFL, respectively, can compute logarithm over arbitrary range of input signal.

Keywords: Sensitive detection, Weber's law, linear model, bow-tie architecture, numerosity processing, human cone cell, logarithm

1. Introduction

Ernst Weber discovered that the ratio of the smallest noticeable difference in an input signal and the background signal is constant, a phenomenon now known as Weber's law [1]. Later, Fechner showed that Weber's law could be explained by assuming that the perception is proportional to the logarithm of the input signal (see the section *Weber's Law*) [2]. Another model which can also account for Weber's law is the linear model, according to which the output is equal to the input signal plus noise which is proportional to the input signal. In 1973, work of Mesibov et al. on bacterial chemotaxis suggested that *Escherichia coli* exhibits Weber's law, in that the bacterial response was dependent on the gradient of the logarithmic ligand concentration [3]. A theoretical study of a reduced model of *Escherichia coli*'s chemotaxis machinery showed that exact adaptation is necessary, though not sufficient, for the bacterial chemotaxis to exhibit Weber's law [4]. Later an experimental and theoretical modelling study using the reduced model demonstrated the presence of Weber's law in *E. coli*'s chemotaxis. [5].

Thus, inspired from the connection between Weber's law and exact adaptation in the bacterium, Weber's law was formulated as an exactly adapting system generating identical maximum amplitude as a response to an input signal if the ratio of the current input signal to the background signal is constant [6,7]. The formulation has been applied to explain modified versions of Weber-Fechner and Stevens laws found in human sensory systems [8]. However, it is doubtful that all higher-order sensory processes which show Weber's law exhibit scale-invariance with respect to the maximum amplitude. For example, consider the case of weight perception. Suppose the just noticeable difference (JND) for weight perception is 5% of the background, so that a subject holding a weight of 100 gm can feel the change in the weight if at least 5 gm of weight is added. The JND when the subject is holding 1 kg of weight is 50 gm. Although the ratio of the JND to the background signal is constant, the subject is able to sense the background weight and the additional weight in the absolute sense. The subject is not, if at all, just calculating the ratio between the two signals.

It has also been claimed that fold-change detection (FCD) entails Weber's law [6]. A system

capable of providing FCD also shows exact adaptation, in which the response to an input signal

returns to the resting value of the system even when the signal persists. That FCD implies exact

adaptation can be proven in the following way. Consider a system equilibrated at a stimulus

X_0. Its baseline output is Z_0. It generates a certain output when a stimulus X_1 is provided.

The ratio X_1/X_0 is the fold change, f. If the system does not show exact adaptation, the resting

output of the system, equilibrated at stimulus X_1 (or fX_0), will not be equal to Z_0 (scenario

I). If the system is capable of providing FCD, it will show identical response when the two

stimuli are replaced by kX_0 and kX_1, respectively, where k is a scalar. Clearly, the output of the

system equilibrated at stimulus kX_0 should be Z_0 (scenario II). If k is set equal to f, this leads

to a contradiction in a system which shows FCD but does not adapt exactly. That is, when the

stimulus is fX_0, the resting output of the system is Z_0 in the scenario II, whereas it is not equal

to Z_0 in the scenario I. Therefore, a system which shows FCD will also show exact adaptation.

Figure 1: Output of a type-1 incoherent feed-forward loop that lacks exact adaptation.

However, it is doubtful that all higher-order sensory processes which show Weber's law exhibit

exact adaptation. Again considering the case of weight perception, a subject holding a certain

amount of weight continues to sense the same amount of input signal; that is, the perception of

the weight does not come back to some resting value. The same argument applies also to the

perception of sound intensity and brightness.

Weber's law is also observed in size (length/area/volume) perception, for which two examples
are presented now. The first example demonstrates that a difference of 1 unit between two
rectangular strips of 5 and 6 units is perceptible to the human eye, whereas the same difference
between two rectangular strips of 40 and 41 units is not (Figure 2A). The second example
shows that the human eye can easily notice the difference of one disc between collections of 4
and 5 such identical discs at a quick glance, whereas doing so is virtually impossible between
collections of 24 ad 25 discs (Figure 2B). Weber's law is also observed in numerosity processing
[9]. As with weight perception, the perception of size and number does not come back to
some resting value. Because it is not clear how scale-invariance with respect to the maximum
amplitude or exact adaptation could be present in weight perception, size perception, and
numerosity processing; arguably, a general mechanism for Weber's law is needed which does
not involve either scale-invariance with respect to the maximum amplitude or exact adaptation.
Additionally, such a mechanism should be able to generate linear input-output relationship over
several orders of magnitude.

A   **B**

Figure 2: (**A**) Two pairs of rectangular strips which differ by the same length (20% of the smaller strip of the upper pair). (**B**) Two pairs of collection of discs numbering (i) 4 and 5; (ii) 24 and 25.

2. Results

2.1. (Quasi-)Linear Input-Output Relationship Over Arbitrary Range

In order for a system to respond sensitively throughout the whole range of input signal, ideal
relationship between an input signal and the output should be a straight line with the slope

equal to 1 and passing through the origin (i.e., the y-intercept equal to zero). Because sensory

systems operate over several orders of magnitude, the system should be able to generate linear

input-output relationship over several orders of magnitude. This is achieved in the following

way. Consider a collection of five receptors which bind a certain ligand, representing the input

signal, with the equilibrium dissociation constant (K_{da}) equal to 10^1, 10^2, 10^3, 10^4, and 10^5 arb.

units, respectively. The input signal, X, causes the Z producer (an imaginary generic form of

gene) to produce Z. In order to have sensitive detection, that receptor should contribute to the

output, Z, whose K_{da} is an order of magnitude larger than the strength of the input signal (the

concentration of X). Clearly, the output (i.e., the production rate of Z, β_1) of the receptor meant

to respond to an input signal of higher strength should be proportionally larger.

$$\frac{dZ}{dt} = \frac{\beta_1 \dfrac{X}{Kd_{XZ}}}{1 + \dfrac{X}{Kd_{XZ}}} - \alpha_1 Z \tag{1}$$

110 where, β_1 is the rate constant for production of Z by X. α_1 is the degradation rate of Z. Kd_{XZ} is

111 the equilibrium dissociation constant for the binding of X to the producer element (an imaginary

112 generic form of promoter) of Z, which causes Z production.

114 The equilibrium value of Z is

$$Z_{eq} = \left[\frac{\dfrac{\beta_1}{\alpha_1} \dfrac{X}{Kd_{XZ}}}{1 + \dfrac{X}{Kd_{XZ}}} \right] \tag{2}$$

115 Choosing appropriate values of β_1/α_1 and Kd_{XZ}, the total output from the N receptors is

$$Z_{eq} = \sum_{i=1}^{N} \left[\frac{10^i \dfrac{X}{10^i}}{1 + \dfrac{X}{10^i}} \right] \tag{3}$$

Let's assume that the input signal's value has the order of magnitude two. Arguably, the receptor

with Kd_{XZ} equal to 10^3 should generate output from the input signal of this value. However, the

receptors with Kd_{XZ} equal to 10^1 and 10^2 arb. units, respectively, largely saturated by the input

signal, also contribute to the output. Thus, output from the receptors whose Kd_{XZ} is either

equal to or less than the order of magnitude of the input signal should be removed. This is

achieved by adding to the motif a "negative arm": the input signal X engenders production of

the molecule Y which suppresses the output Z from such receptors. The input signal X and

the molecule Y bind to the producer element of Z in mutually exclusive manner. The resulting

motif is type-1 incoherent feed-forward loop. Parameters of the negative arm are such that it

suppresses the output mainly from the receptors whose Kd_{XZ} is either equal to or less than the

order of magnitude of the input signal.

$$\frac{dY}{dt} = \frac{\beta_2 \dfrac{X}{Kd_{XY}}}{1 + \dfrac{X}{Kd_{XY}}} - \alpha_2 Y \qquad (4)$$

$$\frac{dZ}{dt} = \left[\frac{\beta_1 \dfrac{X}{Kd_{XZ}}}{1 + \dfrac{X}{Kd_{XZ}}} \right] \cdot \left[\frac{1}{1 + \left(\dfrac{Y}{Kd_{YZ}} \right)^n} \right] - \alpha_1 Z \qquad (5)$$

127 where, β_2 is the rate constant for production of Y by X. α_2 is the degradation rate of Y. Kd_{XY} is

128 the equilibrium dissociation constant for the binding of X to the producer element of Y, which

129 causes Y production. Kd_{YZ} is the equilibrium dissociation constant for the binding of Y to the

130 producer element of Z, leading to suppression of Z production.

131 The equilibrium value of Y and Z are

$$Y_{eq} = \frac{\dfrac{\beta_2}{\alpha_2} \dfrac{X}{Kd_{XY}}}{1 + \dfrac{X}{Kd_{XY}}} \qquad (6)$$

$$Z_{eq} = \left[\frac{\frac{\beta_1}{\alpha_1} \frac{X}{Kd_{XZ}}}{1 + \frac{X}{Kd_{XZ}}} \right] \cdot \left[\frac{1}{1 + \left(\frac{\left(\frac{1}{Kd_{YZ}} \frac{\beta_2}{\alpha_2} \right) \frac{X}{Kd_{XY}}}{1 + \frac{X}{Kd_{XY}}} \right)^n} \right] \tag{7}$$

The expression in the second pair of brackets on the right hand side (RHS) of eq. 7, representing

suppression of the output by the input signal, reaches an asymptotic value because the denominator

in the expression reaches an asymptotic value. On the other hand, the formulation demands the

expression to keep decreasing with increasing X. That is, the expression should be of the form:

$1/(1 + X^n)$. This is achieved in the following way. The expression in the second pair of brackets

on the RHS of eq. 7 is approximately equal to the expression 8 (which is of the required form),

at least in the parameter range of interest (i.e., until X is not at least one order of magnitude

larger than Kd_{XZ}), if $Kd_{XY} \gg Kd_{XZ}$ and the order of magnitude of $(1/Kd_{YZ}) \cdot (\beta_2/\alpha_2)$ is at least

four (Figure 3A). This is because when $Kd_{XY} \gg Kd_{XZ}$, X/Kd_{XY} remains much less than 1 until

the saturation of the receptor has occurred. The rationale behind setting $(1/Kd_{YZ}) \cdot (\beta_2/\alpha_2)$ equal

to 10^4 is given in the Methods (part 1a).

$$\left[\frac{1}{1 + \left(\left(\frac{1}{Kd_{YZ}} \frac{\beta_2}{\alpha_2} \right) \frac{X}{Kd_{XY}} \right)^n} \right] \tag{8}$$

$$\left[\frac{1}{1 + \left(\frac{\left(\frac{1}{Kd_{YZ}} \frac{\beta_2}{\alpha_2} \right) \frac{X}{Kd_{XY}}}{1 + \frac{X}{Kd_{XY}}} \right)^n} \right] \approx \left[\frac{1}{1 + \left(\left(\frac{1}{Kd_{YZ}} \frac{\beta_2}{\alpha_2} \right) \frac{X}{Kd_{XY}} \right)^n} \right] \tag{9}$$

143 After applying the approximation, eq. 7 becomes

Figure 3: (**A**) The green curve represents the expression $1/(1 + 10^4((X/10^5)/(1 + (X/10^5))))$. The red curve: $1/(1 + (X/10))$. (**B**) The green curve represents the expression $10^4((X/10^5)/(1 + (X/10^5)))/(1 + 10^4((X/10^5)/(1 + (X/10^5))))$. The red curve: $(X/10)/(1 + (X/10))$.

$$Z_{eq} = \left[\frac{\frac{\beta_1}{\alpha_1}\frac{X}{Kd_{XZ}}}{1 + \frac{X}{Kd_{XZ}}}\right] \cdot \left[\frac{1}{1 + \left(\left(\frac{1}{Kd_{YZ}}\frac{\beta_2}{\alpha_2}\right)\frac{X}{Kd_{XY}}\right)^n}\right] \tag{10}$$

144 To fulfill the aforementioned demand on the value of parameters of the negative arm, $Kd_{YZ} \cdot (\alpha_2/\beta_2) \cdot Kd_{XY}$,

145 the effective equilibrium dissociation constant of this arm, is set equal to Kd_{XZ}. The total output

146 from the five receptors is

$$Z_{eq} = \sum_{i=1}^{N} \left[\frac{10^i \frac{X}{10^i}}{1 + \frac{X}{10^i}}\right] \cdot \left[\frac{1}{1 + \frac{X}{10^i}}\right] \tag{11}$$

147 The following is non-approximated form of the above eq.

$$Z_{eq} = \sum_{i=1}^{N} \left[\frac{10^i \frac{X}{10^i}}{1 + \frac{X}{10^i}}\right] \cdot \left[\frac{1}{1 + \frac{10^4 \frac{X}{10^{i+4}}}{1 + \frac{X}{10^{i+4}}}}\right] \tag{12}$$

However, an input signal can generate output Z from those receptors also whose Kd_{XZ} is larger

than the input signal by more than one order of magnitude. In the present case, this means

that the input signal of 10^2 arb. units being able to generate the output from the receptors

whose Kd_{XZ} is equal to 10^4 and 10^5 arb. units, respectively. Output Z_{eq} generated by each of

the two receptors is approximately equal to 10^2 arb. units, which is of the same order as Z_{eq}

generated by the receptor whose Kd_{XZ} is equal to 10^3 arb. units. The output from the receptors

whose Kd_{XZ} is larger than the input signal by more than one order of magnitude is removed by

adding to the motif a "positive arm": the input signal X engenders production of the molecule

V, which must also be bound along with X to the producer element of Z in order to engender Z

production. Parameters of the positive arm are such that it lets mainly those receptors generate

the output whose Kd_{XZ} is at most one order of magnitude larger than the input signal.

$$\frac{dV}{dt} = \frac{\beta_3 \dfrac{X}{Kd_{XV}}}{1 + \dfrac{X}{Kd_{XV}}} - \alpha_3 V \tag{13}$$

$$\frac{dY}{dt} = \frac{\beta_2 \dfrac{X}{Kd_{XY}}}{1 + \dfrac{X}{Kd_{XY}}} - \alpha_2 Y \tag{14}$$

$$\frac{dZ}{dt} = \left[\frac{\beta_1 \dfrac{X}{Kd_{XZ}}}{1 + \dfrac{X}{Kd_{XZ}}} \right] \cdot \left[\frac{\left(\dfrac{V}{Kd_{VZ}}\right)^m}{1 + \left(\dfrac{V}{Kd_{VZ}}\right)^m} \right] \cdot \left[\frac{1}{1 + \left(\dfrac{Y}{Kd_{YZ}}\right)^n} \right] - \alpha_1 Z \tag{15}$$

where, β_1, β_2, and β_3 are the rate constants for production of Z, Y, and V, respectively, by X.

α_1, α_2, and α_3 are the degradation rates of Z, Y, and V, respectively. Kd_{XZ}, Kd_{XY}, and Kd_{XV}

are the equilibrium dissociation constants for the binding of X to the element of Z, Y, and V,

respectively, which causes production of Z, Y, and V, respectively. Kd_{YZ} and Kd_{VZ} are the

equilibrium dissociation constants for the binding of Y and V, respectively, to the element of Z,

which causes Z production.

The equilibrium value of V, Y, and Z

$$V_{eq} = \frac{\dfrac{\beta_3}{\alpha_3}\dfrac{X}{Kd_{XV}}}{1 + \dfrac{X}{Kd_{XV}}} \tag{16}$$

$$Y_{eq} = \frac{\dfrac{\beta_2}{\alpha_2}\dfrac{X}{Kd_{XY}}}{1 + \dfrac{X}{Kd_{XY}}} \tag{17}$$

$$Z_{eq} = \left[\frac{\dfrac{\beta_1}{\alpha_1}\dfrac{X}{Kd_{XZ}}}{1 + \dfrac{X}{Kd_{XZ}}}\right] \cdot \left[\frac{\left(\dfrac{\left(\dfrac{1}{Kd_{VZ}}\dfrac{\beta_3}{\alpha_3}\right)\dfrac{X}{Kd_{XV}}}{1 + \dfrac{X}{Kd_{XV}}}\right)^m}{1 + \left(\dfrac{\left(\dfrac{1}{Kd_{VZ}}\dfrac{\beta_3}{\alpha_3}\right)\dfrac{X}{Kd_{XV}}}{1 + \dfrac{X}{Kd_{XV}}}\right)^m}\right] \cdot \left[\frac{1}{1 + \left(\dfrac{\left(\dfrac{1}{Kd_{YZ}}\dfrac{\beta_2}{\alpha_2}\right)\dfrac{X}{Kd_{XY}}}{1 + \dfrac{X}{Kd_{XY}}}\right)^n}\right] \tag{18}$$

The formulation demands that the expression in the second pair of brackets on the RHS of eq.

18, representing the generation of output Z_{eq} by the input signal X and the molecule V according

to the AND logic, should be of the form $X^n/(1 + X^n)$. This is achieved in the following way.

The expression in the second pair of brackets on the RHS of eq. 18 is approximately equal to

the expression 19 (which is of the required form), at least in the parameter range of interest (i.e.,

until X is not at least one order of magnitude larger than Kd_{XZ}), if $Kd_{XV} \gg Kd_{XZ}$ and the order

of magnitude of $(1/Kd_{VZ}) \cdot (\beta_3/\alpha_3)$ is at least four (Figure 3B). This is because when Kd_{XV}

$\gg Kd_{XZ}$, X/Kd_{XV} remains much less than 1 until the saturation of the receptor has occurred.

Again, the reasoning behind setting $(1/Kd_{VZ}) \cdot (\beta_3/\alpha_3))$ equal to 10^4 is given in the Methods

(part 1a).

$$\left[\frac{\left(\left(\dfrac{1}{Kd_{VZ}}\dfrac{\beta_3}{\alpha_3}\right)\dfrac{X}{Kd_{XV}}\right)^m}{1 + \left(\left(\dfrac{1}{Kd_{VZ}}\dfrac{\beta_3}{\alpha_3}\right)\dfrac{X}{Kd_{XV}}\right)^m}\right] \tag{19}$$

$$\left[\frac{\left(\dfrac{\left(\dfrac{1}{Kd_{VZ}}\dfrac{\beta_3}{\alpha_3}\right)\dfrac{X}{Kd_{XV}}}{1+\dfrac{X}{Kd_{XV}}}\right)^m}{1+\left(\dfrac{\left(\dfrac{1}{Kd_{VZ}}\dfrac{\beta_3}{\alpha_3}\right)\dfrac{X}{Kd_{XV}}}{1+\dfrac{X}{Kd_{XV}}}\right)^m}\right] \approx \left[\frac{\left(\left(\dfrac{1}{Kd_{VZ}}\dfrac{\beta_3}{\alpha_3}\right)\dfrac{X}{Kd_{XV}}\right)^m}{1+\left(\left(\dfrac{1}{Kd_{VZ}}\dfrac{\beta_3}{\alpha_3}\right)\dfrac{X}{Kd_{XV}}\right)^m}\right] \tag{20}$$

179   After applying the approximation, eq. 18 becomes

$$Z_{eq} = \left[\frac{\dfrac{\beta_1}{\alpha_1}\dfrac{X}{Kd_{XZ}}}{1+\dfrac{X}{Kd_{XZ}}}\right] \cdot \left[\frac{\left(\left(\dfrac{1}{Kd_{VZ}}\dfrac{\beta_3}{\alpha_3}\right)\dfrac{X}{Kd_{XV}}\right)^m}{1+\left(\left(\dfrac{1}{Kd_{VZ}}\dfrac{\beta_3}{\alpha_3}\right)\dfrac{X}{Kd_{XV}}\right)^m}\right] \cdot \left[\frac{1}{1+\left(\left(\dfrac{1}{Kd_{YZ}}\dfrac{\beta_2}{\alpha_2}\right)\dfrac{X}{Kd_{XY}}\right)^n}\right] \tag{21}$$

180   To fulfill the aforementioned demand on the value of parameters of the positive arm, $Kd_{VZ} \cdot (\alpha_3/\beta_3)\cdot$

181   Kd_{XV}, the effective equilibrium dissociation constant of this arm, is set equal to $Kd_{XZ}/10$. The

182   total output from the five receptors is

$$Z_{eq} = \sum_{i=1}^{N} \left[\frac{10^i \dfrac{X}{10^i}}{1+\dfrac{X}{10^i}}\right] \cdot \left[\frac{\dfrac{X}{10^{i-1}}}{1+\dfrac{X}{10^{i-1}}}\right] \cdot \left[\frac{1}{1+\dfrac{X}{10^i}}\right] \tag{22}$$

183   The following is non-approximated form of the above eq.

$$Z_{eq} = \sum_{i=1}^{N} \left[\frac{10^i \dfrac{X}{10^i}}{1+\dfrac{X}{10^i}}\right] \cdot \left[\frac{\dfrac{10^4 \dfrac{X}{10^{i+3}}}{1+\dfrac{X}{10^{i+3}}}}{1+\dfrac{10^4 \dfrac{X}{10^{i+3}}}{1+\dfrac{X}{10^{i+3}}}}\right] \cdot \left[\frac{1}{1+\dfrac{10^4 \dfrac{X}{10^{i+4}}}{1+\dfrac{X}{10^{i+4}}}}\right] \tag{23}$$

184   Hence, together the negative arm and the positive arm create a window which show maximum

185   response for an input signal of a particular order of magnitude and whose output declines

Figure 4: (**A**) FNM whose series can generate linear input-output relationship and compute logarithm. (**B**) The series for generating linear input-output relationship. (**C**) The series for computing logarithm.

progressively as the distance between the preferred order of magnitude and the order of magnitude

of input signal increases in either direction. Further, the input-output curve has positive skewness.

Figure 5 shows input-output relationship of a single four-node motif (FNM) with four combinations

of the Hill-coefficients. Increasing the value of m introduces steepness at the leftmost end of

the output, whereas increasing the value of n causes the output to have higher and sharper peak

and decline quickly.

Notably, because a) β_1/α_1 is equal to Kd_{XZ}, b) $Kd_{XY}=10^4 \cdot Kd_{XZ}$, c) $Kd_{XV}=10^3 \cdot Kd_{XZ}$, d) $(1/Kd_{YZ}) \cdot$

$(\beta_2/\alpha_2) = (1/Kd_{VZ}) \cdot (\beta_3/\alpha_3) = 10^4$, the value of Kd_{XZ} is sufficient to specify all other parameters

of FNM whose series produces linear input-output relationship. The last receptor should not

have the negative arm, otherwise a very large input signal will generate a very small output.

Thus, the eq. for the output should be:-

$$Z_{eq} = \sum_{i=1}^{N-1} \left[\frac{10^i \dfrac{X}{10^i}}{1 + \dfrac{X}{10^i}} \right] \cdot \left[\frac{\dfrac{X}{10^{i-1}}}{1 + \dfrac{X}{10^{i-1}}} \right] \cdot \left[\frac{1}{1 + \dfrac{X}{10^i}} \right] + \left[\frac{10^N \dfrac{X}{10^N}}{1 + \dfrac{X}{10^N}} \right] \cdot \left[\frac{\dfrac{X}{10^{N-1}}}{1 + \dfrac{X}{10^{N-1}}} \right] \tag{24}$$

198   The following is non-approximated form of the above eq.

$$Z_{eq} = \sum_{i=1}^{N-1} \left[\frac{10^i \dfrac{X}{10^i}}{1 + \dfrac{X}{10^i}} \right] \cdot \left[\frac{\dfrac{10^4 \dfrac{X}{10^{i+3}}}{1 + \dfrac{X}{10^{i+3}}}}{1 + \dfrac{10^4 \dfrac{X}{10^{i+3}}}{1 + \dfrac{X}{10^{i+3}}}} \right] \cdot \left[\frac{1}{1 + \dfrac{10^4 \dfrac{X}{10^{i+4}}}{1 + \dfrac{X}{10^{i+4}}}} \right] + \left[\frac{10^N \dfrac{X}{10^N}}{1 + \dfrac{X}{10^N}} \right] \cdot \left[\frac{\dfrac{10^4 \dfrac{X}{10^{N+3}}}{1 + \dfrac{X}{10^{N+3}}}}{1 + \dfrac{10^4 \dfrac{X}{10^{N+3}}}{1 + \dfrac{X}{10^{N+3}}}} \right] \tag{25}$$

Figure 5: (**A-D**) The output of FNM defined by the eq. $[10 \cdot (X/10)/(1 + X/10)] \cdot [(X/1)^m/(1 + (X/1)^m)] \cdot [1/(1 + (X/10)^n)]$ with different values of the Hill-coefficients m and n.

199   How well the expression on the RHS of eq. 21 approximates the expression on the RHS of eq.

200   18 was determined by analyzing how well the first term on the RHS of eq. 22 approximates the

201   first term on the RHS of eq. 23, using linear regression (see Methods, part 2a). As stated above,

Figure 6: The total output (Z_{eq}) from the first three FNM receptors for the approximated form (**A**) and non-approximated form (**B**) when m=1, n=1 (blue); m=1, n=2 (green); m=1, n=4 (red); m=1, n=8 (cyan); m=1, n=16 (pink). The total output (Z_{eq}) from the first three FNM receptors for the approximated form (**C**) and non-approximated form (**D**) when m=1, n=1 (blue); m=2, n=1 (green); m=4, n=1 (red); m=8, n=1 (cyan); m=16, n=1 (pink). The total output (Z_{eq}) from the first three FNM receptors for the approximated form (**E**) and non-approximated form (**F**) when m=1, n=1 (blue); m=2, n=2 (green); m=4, n=4 (red); m=8, n=8 (cyan); m=16, n=16 (pink).

in order to provide sensitive detection, ideal relationship between an input signal and the output

should be a straight line with the slope equal to 1 and the y-intercept equal to 0. Thus, in order

to assess if, given a range of Kd_{XZ}, there is a range of input signal in which the series of FNM

could generate linear input-output relationship, straight line was fitted with output Z_{eq} given by

eq. 25 (the non-approximated form) for various ranges of Kd_{XZ} and input signal (Table 1). See

Methods (part 3) for details of the fitting procedure.

Figure 7: (**A**) The green curve and red curve represent the first term on the RHS of eq. 23 and eq. 22, respectively. (**B**) The green curve and red curve represent the first term on the RHS of eq. 29 and eq. 28, respectively.

Table 1: Slope and goodness of fit (R^2) of linear regression of output Z_{eq} against the input values for various ranges of signal and Kd_{XZ}.

Signal Range (across) Kd_{XZ} Range (down)	10^0–10^2	10^{-1}–10^3	10^{-2}–10^4	10^{-3}–10^5	10^{-4}–10^6
10^{-2}–10^4	0.7383 (1.0000)	0.6891 (1.0000)	0.4606 (0.9976)	NA	NA
10^{-3}–10^5	0.7477 (1.0000)	0.7386 (1.0000)	0.6896 (1.0000)	0.4618 (0.9976)	NA
10^{-4}–10^6	0.7487 (1.0000)	0.7477 (1.0000)	0.7387 (1.0000)	0.6899 (1.0000)	0.4625 (0.9976)
10^{-5}–10^7	0.7489 (1.0000)	0.7488 (1.0000)	0.7478 (1.0000)	0.7387 (1.0000)	0.69 (1.0000)
10^{-6}–10^8	0.7489 (1.0000)	0.7489 (1.0000)	0.7488 (1.0000)	0.7478 (1.0000)	0.7388 (1.0000)

For the middle intervals, the slope of the input-output relationship converges to the value 0.7489

when the input signal is a multiple of 10. However, the limiting values of the slope are not

identical when the input signal is not powers of 10 (Figure 8A). The percentage difference

between the maximum value and the minimum value of the slope is 0.8250% and 0.8318%,

depending on whether the difference is normalized by the maximum value or the minimum

value of the slope, respectively. Although the slope of the line given by eq. 24/25 oscillates

between 0.7489 (when X is a multiple of 10) and 0.7551 (when X is 3 times the multiple of 10),

the difference is so small that the input-output relationship can be considered to be quasi-linear,

having the average slope of 0.75136. Further, the same results as presented in table 1 were

got when the range of Kd_{XZ} and concomitantly the range of input signal was shifted by the

factor of 0.01, 0.1, 10, and 100 (see Methods, part 3). However, if the number of receptors in a

series were such that, for a given range of input signal, the slope had reached its limiting value,

then as the range of Kd_{XZ} and input signal were multiplied by the factor of 0.01, 0.1, 10, and

100, the y-intercept of the fitted line turned out to be 0.01, 0.1, 10, and 100 times the previous

y-intercept, respectively. Thus, although the slope remains constant, the y-intercept increases

to 10^k (where k is a scalar) its previous value if the multiplicative factor, both for the range of

Kd_{XZ} and input signal, is 10^k with k>1. However, if the modified series (the series whose range

of Kd_{XZ} is multiplied by 10^k with k>1) is extended at both ends by k receptors, the y-intercept

goes back to its previous value. In general, if the number of receptors in a series are such that,

for a given range of input signal, the slope has reached its limiting value, then for the range of

input signal, the y-intercept reduces to 10^{-k} its value if the series is extended in both directions

by k receptors. Thus, the y-intercept can be reduced to arbitrary low values.

The average y-intercept for the ten values of X is 2.1601e-04 with the standard deviation equal

to 3.3083e-08. Taken together, if output Z_{eq} of this series is multiplied by the reciprocal of

0.75136, one gets an almost straight line passing through the origin and having the slope 1.

Because there is no limit on the number of the receptors, the series of FNM can generate

quasi-linear input-output relationship over arbitrary range of input signal. Note that in order to

provide the quasi-linear input-output relationship over the range 10^a-10^b (where, a < b and both

are integers), the series of receptors whose Kd_{XZ} ranges at least from 10^{a-5} to 10^{b+5} is required.

For the values of m and/or n being more than one, the output becomes oscillatory around the

output generated with m=1 and n=1 (Figure 6). This implies that V and Y molecules should

be present as monomers in a real system. Arguably, the output produced by eq. 24/25 needs to

be decoded by the brain in order to infer the input signal.

2.2. The Mathematical Basis of the Quasi-Linear Input-Output Relationship Provided by the Series of the Four-node Motif

Equation 24 provides quasi-linear input-output relationship. It differs from eq. 22 in that its last

receptor lacks the negative arm. However, this difference is inconsequential if a large number

of receptors flank the receptor which contributes the most to output Z_{eq} (i.e., whose Kd_{XZ}

is an order of magnitude higher than the input signal's value), as then output Z_{eq} of the last

receptor is negligible. In the analysis that follows, because the series of infinite FNM receptors

is considered, the output of eq. 22 and eq. 24 are practically identical, and thus eq. 22 is

considered. Equation 22 is equivalent to $Z_{eq} = m \cdot X$ (because the y-intercept is negligible) and

can be written as

$$Z_{eq} = X \cdot \left\{ \sum_{i=-\infty}^{i=\infty} \left[\frac{\frac{X}{10^{i-1}}}{1 + \frac{X}{10^{i-1}}} \right] \cdot \left[\frac{1}{1 + \frac{X}{10^{i}}} \right]^2 \right\} \qquad (26)$$

254 Equation 26 can be abbreviated in the following way:

$$Z_{eq} = X \cdot \left\{ \sum_{i=-\infty}^{i=\infty} g(X,i) \right\} \qquad (27)$$

Now it remains to be shown that the series in the curly brackets of eq. 26/27 converges in both

negative and positive direction to a value which, given an input value X, remains the same for

$10^{k} \cdot X$ (where is k is an integer). For very large positive values of i, $g(X,i) \approx X/10^{i-1}$, and for very

large negative values of i, $g(X,i) \approx (10^{i}/X)^2$. The two asymptotic forms of $g(X,i)$ are convergent

series, as the first one is the geometric series and the second one is the geometric series having

only the even powers. Now it is shown that given an input signal X, Z_{eq} remains the same for

$10^k \cdot X$ (k being an integer). Replacing X by $10^k \cdot X$ and doing the transformation i → i+k leaves

g(X,i) in eq. 26/27 unchanged. However, because i runs from minus infinity to plus infinity,

the transformation of i → i+k does not make any difference. Substituting $X/10^i$ with Y in eq.

26, and writing g(X,i) as p(Y)/q(Y), it can be seen that $\sum\limits_{i=-\infty}^{i=\infty}$ g(X,i)) converges in both directions

when the degree of q(Y) is at least one more than the degree of p(Y). This means that g(X,i) of

the form $[(X/10^{i-1})/(1+X/10^{i-1})] \cdot [1/(1+X/10^i)]$ (hereinafter called $g'(X,i)$) should also be able to

provide at least a quasi-linear input-output relationship. This is indeed the case: for very large

positive values of i, $g'(X,i) \approx X/10^{i-1}$, and for very large negative values of i, $g'(X,i) \approx (10^i/X)$.

Both are geometric series and hence convergent. Note that $g'(X,i)$ corresponds to coherent

type-1 feed-forward loop (C1-FFL); that is, FNM minus the negative arm. The following is the

eq. for the output of the series of C1-FFL receptors.

$$Z_{eq} = \sum_{i=1}^{N} \left[\frac{10^i \dfrac{X}{10^i}}{1 + \dfrac{X}{10^i}} \right] \cdot \left[\frac{\dfrac{X}{10^{i-1}}}{1 + \dfrac{X}{10^{i-1}}} \right] \tag{28}$$

272 The following is non-approximated form of the above eq.

$$Z_{eq} = \sum_{i=1}^{N} \left[\frac{10^i \dfrac{X}{10^i}}{1 + \dfrac{X}{10^i}} \right] \cdot \left[\frac{\dfrac{10^8 \dfrac{X}{10^{i+7}}}{1 + \dfrac{X}{10^{i+7}}}}{1 + \dfrac{10^8 \dfrac{X}{10^{i+7}}}{1 + \dfrac{X}{10^{i+7}}}} \right] \tag{29}$$

Note that $(1/Kd_{YZ}) \cdot (\beta_2/\alpha_2)$ and $(1/Kd_{VZ}) \cdot (\beta_3/\alpha_3))$ are set equal to 10^8 (unlike in eq. 23/25,

where the two quantities are set equal to 10^4). The rationale behind setting the two quantities

equal to 10^8 is given in the Methods (part 1b). As with FNM given in eq. 23/25, the value

of Kd_{XZ} is sufficient to specify all other parameters of C1-FFL whose series generates linear

input-output relationship. This is because a) β_1/α_1 is equal to Kd_{XZ}, b) $Kd_{XV}=10^7 \cdot Kd_{XZ}$, c)

$(1/Kd_{YZ}) \cdot (\beta_2/\alpha_2) = (1/Kd_{VZ}) \cdot (\beta_3/\alpha_3) = 10^8$.

Like for FNM, how well the first term on the RHS of eq. 28 approximates the first term on

the RHS of eq. 29 was determined using linear regression (see Methods, part 2b). As stated

above, in order to provide sensitive detection, ideal relationship between an input signal and

the output should be a straight line with the slope equal to 1 and the y-intercept equal to 0.

Thus, as previously, in order to assess if, given a range of Kd_{XZ}, there is a range of input signal

in which the series of C1-FFL could generate linear input-output relationship, straight line was

fitted with output Z_{eq} given by eq. 29 (the non-approximated form) for various ranges of Kd_{XZ}

and input signal (Table 2). See Methods (part 3) for details of the fitting procedure.

Table 2: Slope and goodness of fit (R^2) of linear regression of output Z_{eq} against the input values for various ranges of signal and Kd_{XZ}.

Signal Range (across) Kd_{XZ} Range (down)	10^0–10^2	10^{-1}–10^3	10^{-2}–10^4	10^{-3}–10^5	10^{-4}–10^6
10^{-2}–10^4	1.1 (1.0000)	1.008 (0.9999)	0.5513 (0.9933)	NA	NA
10^{-3}–10^5	1.11 (1.0000)	1.1 (1.0000)	1.009 (0.9999)	0.5535 (0.9933)	NA
10^{-4}–10^6	1.111 (1.0000)	1.11 (1.0000)	1.1 (1.0000)	1.01 (0.9999)	0.5549 (0.9933)
10^{-5}–10^7	1.111 (1.0000)	1.111 (1.0000)	1.11 (1.0000)	1.1 (1.0000)	1.01 (0.9999)
10^{-6}–10^8	1.111 (1.0000)	1.111 (1.0000)	1.111 (1.0000)	1.11 (1.0000)	1.1 (1.0000)

For the middle intervals, the slope of input-output relationship generated by the series of

C1-FFL converges to the value 1.111 (or 10/9). Also, the slope is independent of the input

signal's value (Figure 8B). Further, the same results as presented in table 2 were got when the

range of Kd_{XZ} and concomitantly the range of input signal were shifted by the factor of 0.01,

0.1, 10, and 100 (see Methods, part 3). However, if the number of receptors in a series were

such that, for a given range of input signal, the slope had reached its limiting value, then as

the range of Kd_{XZ} and input signal were multiplied by the factor of 0.01, 0.1, 10, and 100,

the y-intercept of the fitted line turned out to be 0.01, 0.1, 10, and 100 times the previous

y-intercept, respectively. Thus, although the slope remains constant, the y-intercept increases

to 10^k (where k is a scalar) its previous value if the multiplicative factor, both for the range of

Kd_{XZ} and input signal, is 10^k with k>1. However, if the modified series (the series whose range

of Kd_{XZ} is multiplied by 10^k with k>1) is extended at both ends by k receptors, the y-intercept

goes back to its previous value. In general, if the number of receptors in a series are such that,

for a given range of input signal, the slope has reached its limiting value, then for the range of

input signal, the y-intercept reduces to 10^{-k} its value if the series is extended in both directions

by k receptors. Thus, the y-intercept can be reduced to arbitrary low values.

The average y-intercept for the ten values of X is 2.1592e-04 with the standard deviation equal

to 3.3091e-08. Taken together, if output Z_{eq} of this series is multiplied by the reciprocal of

1.111, one gets a straight line passing through the origin and having the slope 1. Because there

is no limit on the number of the receptors, the series of C1-FFL can generate perfectly linear

input-output relationship over arbitrary range of input signal. Note that in order to provide the

linear input-output relationship over the range 10^a-10^b (where, a < b and both are integers), the

series of receptors whose Kd_{XZ} ranges at least from 10^{a-4} to 10^{b+4} is required. For the values of

m and/or n being more than one, the output becomes oscillatory around the output generated

with m=1 and n=1 (Figure 11). This implies that V and Y molecules should be present as

monomers in a real system. As with the series of FNM, the output produced by eq. 28/29

needs to be decoded by the brain in order to infer the input signal.

2.3.   Weber's Law

Now I present a formalism to get Weber's law from the series of FNM and the series of C1-FFL.

Equation 24/25, when multiplied by the factor of 1/0.75136, yields an input-output relationship

which, to a very good approximation, is linear for intermediate range of input signal (X); that

is, $Z_{eq} \approx X$. However, as shown above, because the deviation from linearity is minuscule,

the input-output relationship is assumed to be linear (i.e., $Z_{eq} = X$) for the purpose of the

analysis below. On the other hand, eq. 28/29, when multiplied by the factor of 1/1.111 (or

Figure 8: The limiting value of the slope from the linear regression of Z_{eq} against the input signal's value ($X \cdot 10^k$) for the series of FNM (**A**) and the series of C1-FFL (**B**). Note that the limiting value of the slope for the two series is equal to $\sum_{i=-\infty}^{i=\infty} g(X,i)$ and $\sum_{i=-\infty}^{i=\infty} g'(X,i)$, respectively

Figure 9: (**A**) The C1-FFL motif whose series can generate linear input-output relationship and compute logarithm. (**B**) The series for generating linear input-output relationship. (**C**) The series for computing logarithm.

Figure 10: (**A-D**) The output of FNM defined by the eq. $[10 \cdot (X/10)/(1+X/10)] \cdot [(X/1)^m/(1+(X/1)^m)]$ with different combinations of the value of the Hill-coefficients m and n.

Figure 11: The total output (Z_{eq}) from the first three C1-FFL receptors for the approximated form (**A**) and non-approximated form (**B**) when m=1 (blue); m=2 (green); m=4 (red); m=8 (cyan); m=16 (pink).

10/9), yields a perfectly linear input-output relationship for intermediate range of X; that is,

Z_{eq} = X. The following analysis is common for both the series. Given an input signal (X = μ),

the output (Z_{eq}) is considered to be the result of sampling from a Gaussian distribution with

mean equal to μ and standard deviation linearly proportional to μ; that is, $\sigma = f\mu$, where f is

the Weber fraction, the ratio of the smallest perceptual change in an input signal (ΔX_{min}) and

the background signal ($X_{background}$): $\Delta X_{min}/X_{background}$ = f. It is posited here that the subject

is able to perceive a change in the input signal when the ratio of the non-overlapping region,

towards the right, between the two Gaussians (shaded region in figure 12) and the area under

the Gaussian centered on μ_1 is above a certain threshold value. Because the Gaussians in the

consideration are normalized, the ratio is equal to the non-overlapping region on the right, R.

Figure 12: The Gaussian on the left has mean μ_1=10, and σ_1=10, and the Gaussian on the right has mean μ_2=15 and σ_2=15. The shaded portion is the non-overlapping region on the right, R

As is defined now, the region R is just below the threshold value when $\mu_2 - \mu_1 = \sigma_1$; that

is, when the difference between the mean of the current input signal and the mean of the

background signal is equal to the standard deviation of the background signal. In other words,

σ_1 is the just noticeable difference (JND). The region R is $F_1(p_2)$ - $F_2(p_2)$, where F(X) is

the cumulative distribution function of Gaussian distribution and p_2 is the farther point of

intersection of the two Gaussians when $\mu_2 - \mu_1 = \sigma_1$. That is, p_2 is the bigger-valued solution of

the quadratic eq. below. Note that the total output Z_{eq}, given by eq. 24/25, is the sum of Z_{eq} of

individual receptors. But that still does not affect the formalism above because the individual

outputs are independent, and thus the sum of the individual means is μ and the sum of the

individual standard deviations is σ. This is further corroborated by the stochastic simulation

later below

$$\frac{1}{\sqrt{2\pi\sigma_1^2}}e^{-\frac{(p-\mu_1)^2}{2\sigma_1^2}} = \frac{1}{\sqrt{2\pi\sigma_2^2}}e^{-\frac{(p-\mu_2)^2}{2\sigma_2^2}} \tag{30}$$

$$\ln\left|\frac{\sigma_2}{\sigma_1}\right| = \frac{(p-\mu_1)^2}{2\sigma_1^2} - \frac{(p-\mu_2)^2}{2\sigma_2^2} \tag{31}$$

$$\frac{\ln\left|\frac{\sigma_2}{\sigma_1}\right|}{\left(\frac{1}{\sigma_1} - \frac{1}{\sigma_2}\right)} = p\left[\left(\frac{1}{\sigma_1} + \frac{1}{\sigma_2}\right)p - \frac{2}{f}\right] \tag{32}$$

345 Setting $C = \dfrac{\ln\left|\frac{\sigma_2}{\sigma_1}\right|}{\left(\frac{1}{\sigma_1} - \frac{1}{\sigma_2}\right)}$, $A = \left(\frac{1}{\sigma_1} + \frac{1}{\sigma_2}\right)$, $B = \dfrac{2}{f}$

346 eq. 32 becomes

$$C = p[Ap - B] \quad \text{or} \quad Ap^2 - Bp - C = 0 \tag{33}$$

$$p_{1,2} = \frac{B \pm \sqrt{B^2 4AC}}{2A} \tag{34}$$

$$p_2 = \frac{\dfrac{2}{f} + \sqrt{\left(\dfrac{2}{f}\right)^2 + 4\left(\dfrac{1}{\sigma_1} + \dfrac{1}{\sigma_2}\right)\dfrac{\ln\left|\frac{\sigma_2}{\sigma_1}\right|}{\left(\dfrac{1}{\sigma_1} - \dfrac{1}{\sigma_2}\right)}}}{2\left(\dfrac{1}{\sigma_1} + \dfrac{1}{\sigma_2}\right)} \tag{35}$$

347 Setting $\dfrac{\sigma_2}{\sigma_1} = 1 + f$

$$p_2 = \frac{\mu_1 \left(1 + \sqrt{1 + f(2 + f)\ln|1 + f|}\right)}{\left(1 + \dfrac{1}{1 + f}\right)} \tag{36}$$

348 The eq. 36 can be written as $p_2 = \mu_1 g(f)$

349 The CDF of a Gaussian distribution with mean μ and variance σ^2 is

$$F(Y) = \frac{1}{2}\left[1 + \mathrm{erf}\left(\frac{Y - \mu}{\sigma\sqrt{2}}\right)\right]$$

350 Hence

$$R = \frac{1}{2}\left[1 + \mathrm{erf}\left(\frac{p_2 - \mu_1}{\sigma_1\sqrt{2}}\right)\right] - \frac{1}{2}\left[1 + \mathrm{erf}\left(\frac{p_2 - \mu_2}{\sigma_2\sqrt{2}}\right)\right] \tag{37}$$

351 Inserting the value of p_2 in eq. 37

$$R = \frac{1}{2}\left[1 + \mathrm{erf}\left(\frac{\mu_1 g(f) - \mu_1}{\sigma_1\sqrt{2}}\right)\right] - \frac{1}{2}\left[1 + \mathrm{erf}\left(\frac{\mu_1 g(f) - \mu_2}{\sigma_2\sqrt{2}}\right)\right] \tag{38}$$

$$R = \frac{1}{2}\left[\mathrm{erf}\left(\frac{g(f) - 1}{f\sqrt{2}}\right) - \mathrm{erf}\left(\frac{g(f)/(1 + f) - 1}{f\sqrt{2}}\right)\right] \tag{39}$$

352 Being a function of f alone, R can be written as $R = h(f)$. It also implies that the value of

353 R remains the same when the two means are multiplied by a scalar. This is because the two

354 Gaussians become flatter and the point p_2 goes farther. Hence, the region R stays constant

355 when the two signals are multiplied by a scalar, which is Weber' law. In the range of f from 0 to

356 1, R is a monotonically decreasing function of f (data not shown); hence $h^{-1}R$ is also a function.

$$\frac{\Delta X_{\min}}{X_{\mathrm{background}}} = \frac{\mu_2 - \mu_1}{\mu_1} = \frac{\sigma_1}{\mu_1} = f = h^{-1}(R) \tag{40}$$

358 In the formalism presented here (i.e., the linear model), Weber's law is the result of a Gaussian

359 internal noise whose standard deviation is proportional to the input signal. On the other hand,

360 Fechner's explanation is based on the assumption that the output is proportional to a logarithm

361 of the input signal, and JND therefore is a function of a constant increment in the output (eqs.

362 44 and 45).

$$Z_0 = \log(X_0) \tag{41}$$

$$Z_1 = \log(X_0 + \Delta X_{min}) \tag{42}$$

$$\Delta Z = Z_1 - Z_0 = \log\left(1 + \frac{\Delta X_{min}}{X_0}\right) \tag{43}$$

$$e^{\Delta Z} - 1 = \frac{\Delta X_{min}}{X_0} = f \tag{44}$$

366 For $\Delta Z \ll 1$, eq. 44 becomes

$$\Delta Z = \frac{\Delta X_{min}}{X_0} = f \tag{45}$$

However, Fechner's formulation does not provide a biological basis of the relation between

the Weber fraction and ΔZ (eqs. 44 and 45). Also, the output being logarithm of the input

signal does not seem natural. Two Wildebeests butting their head against each other should

not compute logarithm of the force that they receive from the other in the process. Otherwise,

a force four times as large will appear larger by only log4. With such a sensory system the

weaker animal will be much more injured at the end of the fight than if the sensory system

converted the input signal to an equally valued output.

The formalism for Weber's law presented in this paper assumes that output Z_{eq} given by eq.

25 (approximated as eq. 24) and eq. 29 (approximated as eq. 28), respectively, to be noisy

and thus considers the output to be a random sample from a Gaussian distribution whose mean

is the input signal's value and the standard deviation is the Weber fraction times the mean. In

order to validate this assumption, output Z_{eq} of eq. 25 and eq. 29, respectively, should be shown

to be a Gaussian distribution with mean equal to a constant times the input signal's value and

standard deviation equal to a constant times the Weber fraction times the mean when the output

generated by individual components of FNM and C1-FFL, respectively, is a random sample

from their corresponding Gaussian distributions (See Methods, part 4).

For the series of FNM: for the values of f up to 0.2, the average slope of the fitted line –for the

mean– was consistently 1.45 (standard deviation being of the order of magnitude -5 at worst),

the average y-intercept of the fitted line –for the mean– was very close to zero; that is, being

of the order of magnitude -4 at worst (with standard deviation being of the order of magnitude

-5 at worst). The average slope of the fitted line –for the standard deviation– was consistently

1.39 (standard deviation being of the order of magnitude -3 at worst), the average y-intercept

of the fitted line –for the standard deviation– was very close to zero; that is, being of the order

of magnitude -4 at worst (with standard deviation being of the order of magnitude -5 at worst).

And the average R^2 was equal to 1 (that is, standard deviation being zero) for both the mean

and standard deviation. For higher values of f (i.e., 0.5 and 1), the fit became progressively

poor (Supplementary Information, Table 8).

For the series of C1-FFL: for the values of f up to 0.2, the average slope of the fitted line –for the

mean– was consistently very close of 0.9 (standard deviation being of the order of magnitude

-4 at worst), the average y-intercept of the fitted line –for the mean– was very close to zero;

that is, being of the order of magnitude -3 at worst (with standard deviation being of the order

of magnitude -5 at worst). The average slope of the fitted line –for the standard deviation–

was consistently very close of 1.26 (standard deviation being of the order of magnitude -4 at

worst), the average y-intercept of the fitted line –for the standard deviation– was close to zero;

that is, being of the order of magnitude -2 at worst (with standard deviation being of the order

of magnitude -4 at worst). And the average R^2 for the mean was equal to 1 (that is, standard

deviation being zero) and average R^2 for the standard deviation was consistently 0.999 (with

standard deviation being of the order of magnitude -6 at worst). For higher values of f (i.e., 0.5

and 1), the fit was considerably poor (Supplementary Information, Table 9).

2.4. Explaining Numerosity Processing Data

In 2002, two studies [10,11], investigating parietal cortex and prefrontal cortex, respectively, observed the presence of neurons whose firing rate was tuned to a specific numerosity. In a study by Nieder and Miller [12], the activity of neurons from the lateral prefrontal cortex displayed a maximum at a preferred number and declined progressively as the numerical distance from that preferred number was increased, thereby forming numerosity filter function. The tuning curves, which had positive skewness on a linear scale, were plotted on nonlinear scales, namely a power function with an exponent of 0.5, a power function with an exponent of 0.33, and a logarithmic scale. The new distributions along with the original distribution (linear scale) were fitted with a Gaussian distribution. The mean goodness-of-fit (R^2) values were in ascending order when arranged from left to right for the linear scale, the power function with an exponent of 0.5, the power function with an exponent of 0.33, and the logarithmic scale. Additionally, on the logarithmic scale, the variance of numerosity filters was approximately constant with increasing preferred numerosity when the amplitude was kept constant .

As figure 10 shows, output Z_{eq} of C1-FFL is a monotonic function, and hence receptors based on C1-FFL cannot explain these experimental findings. FNM receptors considered in the present study so far produce the maximum output at values which are powers of ten (for example, receptors which constitute the series represented by eqs. 24/25 generate the maximum output at the values 10^1, 10^2, 10^3, and so on up to 10^N, respectively). Thus, in order to have the receptors produce the maximum output at integral values, such as 1, 2, 3, etc, (Figure 13) and also possess a certain mathematical property, a few combinations of the equilibrium dissociation constants and the Hill-coefficients were tried. The mathematical property that the expression for output Z_{eq} of the individual FNM receptors needed to possess is $f_{N+1}(X)$ = $f_N(X/C_N)$ when β_1/α_1 is kept constant. f_N and f_{N+1} are the expressions for output Z_{eq} of consecutive receptors, respectively, and C_N is a function of N in general but may also be constant. This property makes the output of the individual receptors with constant β_1/α_1 have

437   equal variance when plotted on a logarithm scale, as can readily be seen.

$$f_{N+1}(\exp(X)) = f_N(\exp(X - \ln C_N)) \tag{46}$$

438   The function f_{N+1} can be got from the function f_N by the transformation $X \to X\text{-}\ln C_N$ when

439   β_1/α_1 is kept constant; hence the standard deviation remains the same. The following function

440   turned out to satisfy both requirements

$$\left[\frac{N\frac{X}{N}}{1 + \frac{X}{N}}\right] \cdot \left[\frac{\frac{X}{N}}{1 + \frac{X}{N}}\right] \cdot \left[\frac{1}{1 + \left(\frac{X}{N}\right)^2}\right] \tag{47}$$

Note that for this function β_1/α_1 is equal to N and C_N is equal to (N+1)/N.

Like in the study [12], R^2 values of the Gaussian fit of the expression 47 having constant β_1/α_1

(i.e., set equal to 1) for N=1,2,3 plotted on the linear scale, the power function with an exponent

of 0.5, the power function with an exponent of 0.33, and the logarithmic scale were in ascending

order when arranged from left to right (See Methods, part 5, and Supplementary Information,

Table 5).

Notably, barring the last receptor (which does not possess the negative arm), FNM receptors

of the series which gives quasi-linear input-output relationship are related in the following way

when β_1/α_1 is kept constant: $f_{N+1}(X) = f_N(X/C_N)$, where f is the output function with β_1/α_1

set equal to one and N is the receptor's number. C_N for this function is independent of N and is

equal to 10. Thus, because output Z_{eq} of the FNM receptor whose series produces quasi-linear

input-output relationship follows the above-stated mathematical property when β_1/α_1 is kept

constant, the output has constant variance when plotted on a logarithm scale. R^2 values of the

Gaussian fit of the first, second, and third term on the RHS of eq. 22 having constant β_1/α_1

(i.e., set equal to 1) plotted on the linear scale, the power function with an exponent of 0.5, the

power function with an exponent of 0.33, and the logarithmic scale were in ascending order

when arranged from left to right (See Methods, part 5, and Supplementary Information, Table

6).

In their experiments, monkeys were shown a set of dots, and then, after a short delay, were

presented with another set of dots, which they had to distinguish from the first set. The

percentage of trials on which they judged the second number to be indistinguishable from

the first number, which varied between 2-6, was plotted as a function of the second number.

Monkeys' performance –percentage of trials on which they reported the two sets to be of the

same numerosity– declined progressively as the two sets became numerically more distant.

For larger numerosities, the two sets had to be proportionally larger in order to keep the level

of performance the same, thereby translating to Weber' law. The distributions of both monkey's

performance had positive skewness, but assumed a more symmetric shape when plotted on

nonlinear scales, namely a power function with an exponent of 0.5, a power function with an

exponent of 0.33, and a logarithmic scale. The mean goodness-of-fit values for the linear scale,

the power function with an exponent of 0.5, the power function with an exponent of 0.33, and

the logarithmic scale were 0.93, 0.97, 0.98, and 0.98, respectively. Further, the variance of the

distributions for each numerosity was constant when the data was plotted on a power function

scale with 0.33 exponent and the logarithmic scale.

C1-FFL based receptors could not explain the neuronal data, hence they cannot be considered

for the possibility of explaining the behavioural data. Because the above-stated formulation

of Weber's law requires the input-output relationship to be (quasi-)linear, the series of FNM

receptors which produce the maximum output at integral values must be able to produce (quasi-)linear

input-output relationship in order to explain behavioural data of the study by Nieder and Miller

[12]. To this end, a series of ten receptors (with the first receptor lacking the positive arm),

defined by the expression 47, whose N ranged from 1-10 was considered. The values of

β_1/α_1 of this series were determined by linear regression (See Methods, part 6). It turned

out that the values of β_1/α_1 varied over 7 orders of magnitude (R^2=0.9999), which does not

seem biologically plausible. When the series of twenty such receptors (again, with the first

receptor lacking the positive arm) were considered, the values of β_1/α_1 varied over 6 orders of

magnitude (R^2=1.0000). Thus, the present work is unable to explain the behavioural data.

Figure 13: Output Z_{eq} of the receptors which produce the maximum output at integral values. The expression 47 with constant β_1/α_1 for N=1,2,3,4,5, respectively, is plotted.

2.5. The Four-node Motif and a Class of Bow-Tie Architecture

As shown in the section *Quasi-linear Input-Output Relationship Over Arbitrary Range*, for the

series (of FNM) which generates quasi-linear input-output relationship (eq. 24/25 and figure

4B), b-a+11 receptors are required to provide quasi-linear input-output relationship over the

range 10^a-10^b. This implies that when a is non-negative and b-a is not too small, 10^b-10^a

$\gg$ b-a+11; and consequently, the generation of quasi-linear relationship between input signal

and decoded output becomes an example of bow-tie architecture. This gets more pronounced

as both b and a becomes large. For example, when a=0 and b=5, the range of the input

signal and decoded output (10^5-1) is four orders of magnitude larger than the number of

receptors (16). Similarly, as shown in the section *The Mathematical Basis of the Quasi-Linear*

Input-Output Relationship Provided by the Series of the Four-node Motif, for the series (of

C1-FFL) which generates linear input-output relationship (eq. 28/29 and figure 8B), b-a+9

receptors are required to provide linear input-output relationship over the range 10^a-10^b. Again,

this implies that when a is non-negative and b-a is not too small, 10^b-10^a $\gg$ b-a+9; and

consequently, the generation of linear relationship between input signal and decoded output

becomes an example of bow-tie architecture. This gets more pronounced as both b and a

becomes large. For example, when a=0 and b=5, the range of the input signal and decoded

output (10^5-1) is four orders of magnitude larger than the number of receptors (14). Therefore,

a class of bow-tie architecture can be defined: a class in which the number of receptors is much

smaller than the range of input signal and decoded output.

The range of output Z_{eq} generated by the series of FNM (eq. 24/25 and figure 4B) and the

series of C1-FFL (eq. 28/29 and figure 8B) are identical to the input signal's range. In contrast

to that, now I consider a hypothetical requirement of sensitive detection over wide range of

input signal when the output has an upper limit. Black line in figure 14A depicts that when

the output has an upper limit, sensitivity of a mechanism generating single linear input-output

relationship reduces as the input signal's range increases. But the sensitivity is maintained

if a mechanism generates multiple linear input-output relationships, each of which is from a

different receptor and covers corresponding limited range of input signal. The blue, green,

and red lines are ideal hypothetical outputs which together provide sensitive detection over a

wide range of input signal when the output has an upper limit. However, the outputs are not

biologically realistic, as they terminate abruptly at their maximum value. Figure 14B shows a

biologically plausible form of the outputs.

Figure 14C shows output Z_{eq} of a series of FNM which qualitatively matches figure 14B

and, thus, provides sensitive detection over arbitrary range of input signal when the output

has an upper limit. FNM in this series has the following properties: β_1/α_1 (K) is constant,

the Hill-coefficients m and n are equal to 2 and 8, respectively, all equilibrium dissociation

constants of a given receptor are equal, and the value of equilibrium dissociation constants of

a receptor are twice those of the preceding receptor. The expression 48 defines the general

form of this receptor. Z_{eq} of this FNM fits Gaussian distribution very well (See Methods,

part 7). R^2 for the Gaussian fit of the expression 48 for N=1,2,3,4,5 are 0.9965, 0.9955,

0.9954, 0.9953, and 0.9953, respectively. Although the output when m=2, n=10 and m=1,

m=8, respectively, for equilibrium dissociation constants equal to 1, give slightly better R^2

(Supplementary Information, Table 7), they are visibly less symmetric than the output when

m=2, n=8 (Figure 15).

$$\left[\dfrac{K\dfrac{X}{2^{N-1}}}{1+\dfrac{X}{2^{N-1}}}\right]\cdot\left[\dfrac{\left(\dfrac{X}{2^{N-1}}\right)^2}{1+\left(\dfrac{X}{2^{N-1}}\right)^2}\right]\cdot\left[\dfrac{1}{1+\left(\dfrac{X}{2^{N-1}}\right)^8}\right] \tag{48}$$

Because the expression 48, whose β_1/α_1 is already a constant, possesses the mathematical

property $f_{N+1}(X) = f_N(X/C_N)$, where C_N is independent of N and is equal to 2, the coefficient

of variation of Gaussians they are approximately equivalent to is constant. That is, the mean

and standard deviation of the output of a receptor is C_N times the mean and standard deviation

of the output of the preceding receptor. Further, between the mean of the output of the first

receptor and the antepenultimate receptor, the total output of the series of this receptor oscillates

with constant amplitude and decreasing frequency around a flat line. Note that the individual

outputs in figure 14B have constant width at half height (WAHH); whereas, because WAHH of

Gaussian distribution is equal to $4\cdot\ln2\cdot\sigma$, WAHH of the outputs in figure 14C are proportional

to the mean of the approximate Gaussians they are equivalent to. It should be noted that even

though the output's range has an upper limit, the range of the decoded output is still equal to the

input signal's range, just like for the series of FNM (eq. 24/25) and C1-FFL (eq. 28/29) which

generate (quasi-)linear input-output relationship. That's because for a given input signal, the

total output is a unique combination of the output of the individual receptors. Thus, for a given

input signal, a unique output can be decoded from the output of the individual receptors. Thus,

for the series of receptors that are defined by the expression 48, the decoded output is different

from output Z_{eq}, whereas for the series defined by eqn. 24/25 and 28/29, the two outputs are

equal. This implies that the biochemical nature of the output Z_{eq} of all receptors of the series

defined by eqn. 24/25 and 28/29 should be identical, whereas the biochemical nature of the

output Z_{eq} of receptors of the series whose terms are defined by the expression 48 should be

specific for every receptor. That is, in the latter series, Z_{eq} of a receptor decodes to a higher

value than Z_{eq} of the receptor that precedes it.

Assuming the equilibrium dissociation constant of the first and the last receptor to be 2^a and

2^b, respectively; arguably, the range in which an input signal can be detected sensitively is

$\mu_1 \cdot (2^b - 2^a) + (1/2) \cdot \sigma_1 \cdot (2^a + 2^b)$, where b > a and both are integers, and μ_1 (= 0.8461) and σ_1

(= 0.2748) are the mean and standard deviation of the Gaussian distribution which fits output

Z_{eq} of the receptor whose equilibrium dissociation constants are equal to 1 (i.e., K=5 and N=1

in the expression 48). The number of receptors in this series is equal to b-a+1. This implies

that when a is non-negative and b-a is not too small, $\mu_1 \cdot (2^b - 2^a) + (1/2) \cdot \sigma_1 \cdot (2^a + 2^b) \gg$ b-a+1;

and consequently, the linear relationship between input signal and decoded output becomes

an example of bow-tie architecture. This gets more pronounced as both b and a becomes

large. For example, when a=0 and b=10, the range of the input signal and decoded output

(1006.4) is two orders of magnitude larger than the number of receptors (11). Figure 14D

shows that, with an intuitive choice of parameters, a series of three such FNM receptors is

able to produce an input-output relationship which qualitatively matches absorption spectra of

three cone opsins of humans [13]. The defining expression of the three receptors are in the

figure's legend. This implies that FNM is likely to be involved in the perception of the visible

light spectrum in humans and presumably in other organisms as well. Note that this absorption

spectra is a bow-tie architecture: three cone opsins perceive a portion of the electromagnetic

spectrum. Because in many organisms sound frequency perception occurs over several orders

of magnitude [14], thereby forming a bow-tie architecture, FNM might be involved in the

perception of sound frequency also.

2.6.   The Four-node Motif and Logarithm Computation

When the ratio β_1/α_1 in the series of FNM defined by eq. 24 increases as powers of ten,

$Z_{eq}(X)$ is a straight line. And when the ratio β_1/α_1 increases linearly, the output of the same

series is a concave curve (Figure 16A). Thus it was suspected that with rational choice of

Figure 14: (**A**) The black line shows that, when the output has an upper limit, sensitivity of linear input-output relationship reduces with increase in the range of input signal. The blue, green, and red lines are minimal ideal hypothetical input-output relationship, i.e., which maintain sensitivity throughout the input signal's range. (**B**) Biologically realistic form of the ideal hypothetical input-output relationship. (**C-E**) Output Z_{eq} of the series of receptors which are defined by the expression 48 (with K=5) for various ranges of N. The individual outputs are approximately Gaussian and have constant coefficient of variation. (**F**) A series of three FNM receptors is able to qualitatively generate the absorption spectra of human cone cells. The expressions of the three receptors are: $[3.6 \cdot (X/4)/(1 + X/4)] \cdot [(X/8)^2/(1 + (X/8)^2)] \cdot [1/(1 + (X/8)^8)]$; $[5 \cdot (X/20)/(1 + X/20)] \cdot [(X/20)^2/(1 + (X/20)^2)] \cdot [1/(1 + (X/20)^8)]$; $[5 \cdot (X/24)/(1 + X/24)] \cdot [(X/24)^2/(1 + (X/24)^2)] \cdot [1/(1 + (X/24)^8)]$

Figure 15: (A-D) Output Z_{eq} of FNM defined by the expression $[5 \cdot (X/1)/(1 + X/1)] \cdot [(X/1)^m/(1 + (X/1)^m)] \cdot [1/(1 + (X/1)^n)]$ with different values of the Hill-coefficients m and n.

584 β_1/α_1, the output could be equal to the logarithm of the input signal. Because a series was

585 sought which could compute logarithm of input signal ranging between 1 and 10^4, series of

586 five FNM receptors (eq. 24) having Kd_{XZ} equal to 10^1, 10^2, 10^3, 10^4, and 10^5, respectively,

587 was considered. The values of β_1/α_1 of the series which compute logarithm with the base ten

588 and the natural logarithm were estimated by linear regression (See Methods, part 8). It turned

589 out that the series is able to compute logarithm of the input signal (Figure 17,18). The same

590 procedure was carried out on the series of C1-FFL (eq. 28), as its output also is a concave

591 curve when the ratio β_1/α_1 increases linearly (Figure 16B). It turned out that this series also

592 is able to compute logarithm of the input signal (Figure 19,20). The computation of logarithm

593 by the series of FNM and C1-FFL raised the possibility that, with rational choice of β_1/α_1, the

594 two series might also be able to compute the exponential of the input signal. As before, linear

595 regression was used to find out the values of β_1/α_1; however, none of the series was able to

596 generate the exponential of the input signal (See Methods, part 8).

Figure 16: Output Z_{eq} of the series of FNM (**A**) and C1-FFL (**B**), respectively, when β_1/α_1 of the five receptors are 1,2,3,4,5, respectively.

Figure 17: (**A-D**) Output of the series of FNM which computes $\log_{10}$. The total output (blue) of the first five receptors for various range of input signal plotted on $\log_{10}$-transformed abscissa. The straight line (red), which is the logarithm function plotted on a log-transformed abscissa, is drawn for comparison. The first receptor possesses the positive arm, with m=2, in order to dampen the output when the input signal is below one. The last receptor lacks the negative arm. β_1/α_1 of the five receptors were: 2.89, 6.299, 8.587, 12.36, 8.317, respectively. The R^2 was 0.9989.

Figure 18: (**A-D**) Output of the series of FNM which computes $\log_e$. The total output (blue) of the first five receptors for various range of input signal plotted on $\log_e$-transformed abscissa. As previously, the value of m of the first receptor's positive arm is set equal to 2 and the last receptor lacks the negative arm. β_1/α_1 of the five receptors were: 6.654, 14.5, 19.77, 28.47, 19.15, respectively. The R^2 was 0.9989.

Figure 19: (**A-D**) Output of the series of C1-FFL which computes $\log_{10}$. The total output (blue) of the first five receptors for various range of signal plotted on $\log_{10}$-transformed abscissa. The straight line (red), which is the logarithm function plotted on a log-transformed abscissa, is drawn for comparison. The first receptor possesses the positive arm, with m=2, in order to dampen the output when the input signal is below one. β_1/α_1 of the five receptors were: 1.97 0.292 1.697 0.3015 1.736, respectively. The R^2 was 0.9995.

Figure 20: (**A-D**) Output of the series of C1-FFL which computes $\log_e$. The total output (blue) of the first five receptors for various range of signal plotted on $\log_e$-transformed abscissa. As previously, the value of m of the first receptor's positive arm is set equal to 2. β_1/α_1 of the five receptors were: 4.536 0.6723 3.907 0.6941 3.996, respectively. The R^2 was 0.9995.

Table 3 and 4 depict how the parameters of different series based on FNM and C1-FFL scale with the receptor's number, respectively. The value of $(1/Kd_{YZ}) \cdot (\beta_2/\alpha_2)$ and $(1/Kd_{VZ}) \cdot (\beta_3/\alpha_3)$ for the series based on FNM and C1-FFL is equal to 10^4 and 10^8, respectively. Those equilibrium dissociation constants whose individual values are not known (i.e, which are lumped together with other parameters) are marked NA.

3. Methods

Part 1a

The rationale behind setting $(1/Kd_{YZ}) \cdot (\beta_2/\alpha_2)$ and $(1/Kd_{VZ}) \cdot (\beta_3/\alpha_3)$) for FNM equal to 10^4 is as follows.

Table 3: Type of Series based on FNM and the Values of its Parameters

Series Type	β_1/α_1	Kd_{XZ}	Kd_{XY}	Kd_{XV}	m	n
Linear input-output	Kd_{XZ}	Powers of 10	$10^4 \cdot Kd_{XZ}$	$10^3 \cdot Kd_{XZ}$	1	1
Numerosity Processing in Monkey	Kd_{XZ}	Integral values	NA	NA	1	2
Sensitive Detection when the Output has an Upper Limit	Constant	Powers of 2	NA	NA	2	8
Logarithm Computation	Determined by Linear Regression	Powers of 10	$10^4 \cdot Kd_{XZ}$	$10^3 \cdot Kd_{XZ}$	1	1

Table 4: Type of Series based on C1-FFL and the Values of its Parameters

Series Type	β_1/α_1	Kd_{XZ}	Kd_{XY}	Kd_{XV}	m	n
Linear input-output	Kd_{XZ}	Powers of 10	$10^8 \cdot Kd_{XZ}$	$10^7 \cdot Kd_{XZ}$	1	1
Logarithm Computation	Determined by Linear Regression	Powers of 10	$10^8 \cdot Kd_{XZ}$	$10^7 \cdot Kd_{XZ}$	1	1

$$S_1(X) = \sum_{i=-100}^{i=100} \left[\frac{10^i \frac{X}{10^i}}{1 + \frac{X}{10^i}} \right] \cdot \left[\frac{\frac{X}{10^{i-1}}}{1 + \frac{X}{10^{i-1}}} \right] \cdot \left[\frac{1}{1 + \frac{X}{10^i}} \right]$$

$$S_2(X) = \sum_{i=-100}^{i=100} \left[\frac{10^i \frac{X}{10^i}}{1 + \frac{X}{10^i}} \right] \cdot \left[\frac{\frac{10^m \frac{X}{10^{i+m-1}}}{1 + \frac{X}{10^{i+m-1}}}}{1 + \frac{10^m \frac{X}{10^{i+m-1}}}{1 + \frac{X}{10^{i+m-1}}}} \right] \cdot \left[\frac{1}{1 + \frac{10^m \frac{X}{10^{i+m}}}{1 + \frac{X}{10^{i+m-1}}}} \right]$$

That value of the two quantities were chosen for which $\sum_{X=1}^{X=10} (S_2(X) - S_1(X))^2 / S_1(X) < 10^{-10}$.

The minimum value of m turned out to be 4.

Part 1b

The rationale behind setting $(1/Kd_{YZ}) \cdot (\beta_2/\alpha_2)$ and $(1/Kd_{VZ}) \cdot (\beta_3/\alpha_3))$ for C1-FFL equal to 10^8

is as follows.

$$S_1'(X) = \sum_{i=-100}^{i=100} \left[\frac{10^i \frac{X}{10^i}}{1 + \frac{X}{10^i}} \right] \cdot \left[\frac{\frac{X}{10^{i-1}}}{1 + \frac{X}{10^{i-1}}} \right]$$

$$S_2'(X) = \sum_{i=-100}^{i=100} \left[\frac{10^i \frac{X}{10^i}}{1 + \frac{X}{10^i}} \right] \cdot \left[\frac{\frac{10^m \frac{X}{10^{i+m-1}}}{1 + \frac{X}{10^{i+m-1}}}}{1 + \frac{10^m \frac{X}{10^{i+m-1}}}{1 + \frac{X}{10^{i+m-1}}}} \right]$$

That value of the two quantities were chosen for which $\sum_{X=1}^{X=10} (S_2'(X) - S_1'(X))^2 / S_1'(X) < 10^{-10}$.

The minimum value of m turned out to be 8.

Part 2a

How well the first term on the RHS of eq. 22 approximates the first term on the RHS of eq.

23 was determined by regressing the output of the first term on the RHS of eq. 23 against the

first term on the RHS of eq. 22 multiplied by a coefficient (RHS of eq. 49). Note that the first

term on the RHS of eq. 22/23 defines the first receptor of the series of FNM which provides

quasi-linear input-output relationship. As stated above, this receptor is meant to perceive the

input signal (X) whose value is one order of magnitude less than Kd_{XZ} of the receptor. Also,

because Kd_{XZ} of the first receptor is equal to 10, its output peaks when X is equal to 10. Thus,

for the purpose of (linear) regression, the output of the first term on the RHS of eq. 23 was

evaluated up to one order of magnitude more than the Kd_{XZ}; that is, at the following values of

X: 1, 2, 5, 10, 20, 50, 100. At X equal to 100, the output has declined to 36% of its peak value.

$$Z_{eq} = C \cdot \left[\frac{10^i \frac{X}{10^i}}{1 + \frac{X}{10^i}} \right] \cdot \left[\frac{\frac{X}{10^{i-1}}}{1 + \frac{X}{10^{i-1}}} \right] \cdot \left[\frac{1}{1 + \frac{X}{10^i}} \right] \tag{49}$$

If the approximation is good, the value of the coefficient should turn out to be around one,

besides goodness-of-fit (r^2) being close to one. The value of the coefficient for all the combinations

of m and n was close to one. The goodness-of-fit was equal to one for all the combinations

(Supplementary Information, Tables 1-3). Specifically, for m and n equal to one, the value of

C was 1.0000.

Part 2b

How well the first term on the RHS of eq. 28 approximates the first term on the RHS of eq.

29 was determined by regressing the output of the first term on the RHS of eq. 29 against the

first term on the RHS of eq. 28 multiplied by a coefficient (RHS of eq. 50). As previously,

for the purpose of (linear) regression, the output of the first term on the RHS of eq. 29 was

evaluated up to one order of magnitude more than the Kd_{XZ}; that is, at the following values of

X: 1, 2, 5, 10, 20, 50, 100. At X equal to 100, the output is 90% of its maximum value (i.e., the

asymptotic output at a very large X).

$$Z_{eq} = C \cdot \left[\frac{10^i \dfrac{X}{10^i}}{1 + \dfrac{X}{10^i}} \right] \cdot \left[\frac{\dfrac{X}{10^{i-1}}}{1 + \dfrac{X}{10^{i-1}}} \right] \qquad (50)$$

If the approximation is good, the value of the coefficient should turn out to be around one,

besides goodness-of-fit (r^2) being close to one. The value of the coefficient for every m was

equal to one. The goodness-of-fit was equal to one for every m (Supplementary Information,

Table 4).

Part 3

Fitting straight line with output Z_{eq} given by eq. 25 (the non-approximated form) for various

ranges of Kd_{XZ} and input signal (Table 1). For a given range of input signal, the output was

generated at the input values which were powers of 10. For example, for the input signal's range

10^{-1}–10^3, the output was generated at the following values: 10^{-1}, 10^0, 10^1, 10^2, and 10^3. The

same procedure was carried out after shifting the range of Kd_{XZ} and input signal, shown in table

1, by the factor of 0.01, 0.1, 10, and 100. That is, for example, for the second case (factor=0.1)

the new ranges of Kd_{XZ} were 10^{-3}–10^3, 10^{-4}–10^4, 10^{-5}–10^5, 10^{-6}–10^6, and 10^{-7}–10^7. And

the new ranges of input signal were 10^{-1}–10^1, 10^{-2}–10^2, 10^{-3}–10^3, 10^{-4}–10^4, and 10^{-5}–10^5.

Similarly, for the third case (factor=10) the new ranges of Kd_{XZ} were 10^{-1}–10^5, 10^{-2}–10^6,

10^{-3}–10^7, 10^{-4}–10^8, and 10^{-5}–10^9. And the new ranges of input signal were 10^1–10^3, 10^0–10^4,

10^{-1}–10^5, 10^{-2}–10^6, and 10^{-3}–10^7. The same procedure was also carried out with output Z_{eq}

given by eq. 28 (the non-approximated form) for various ranges of Kd_{XZ} and input signal (Table

2), in order to determine if the series of C1-FFL could generate linear input-output relationship.

Part 4

The formalism of Weber's law presented in this paper; that is, the output Z_{eq} given by eq.

25 (approximated as eq. 24) and eq. 29 (approximated as eq. 28) is a random sample

from the Gaussian whose mean is equal to the input signal and standard deviation is equal

to the Weber fraction times the mean, is validated as follows. As stated above, in order to

validate this assumption, output Z_{eq} of eq. 25 and eq. 29, respectively, should be shown to

be a Gaussian distribution with mean equal to a constant times the input signal's value and

standard deviation equal to a constant times the Weber fraction times the mean when the output

generated by individual components of FNM and C1-FFL, respectively, is a random sample

from their corresponding Gaussian distributions. That is, given the input signal X (taken as

multiple of 10), the value of V and Y are generated from Gaussian distribution with mean

equal to $\dfrac{\beta_3}{\alpha_3}\dfrac{X}{Kd_{XV}}\bigg/\left(1 + \dfrac{X}{Kd_{XV}}\right)$ and $\dfrac{\beta_2}{\alpha_2}\dfrac{X}{Kd_{XY}}\bigg/\left(1 + \dfrac{X}{Kd_{XY}}\right)$ respectively, and standard deviation

equal to the Weber fraction times the respective mean.

Then, with the value of X, V and Y, Z_{eq} is generated from Gaussian with mean equal to

681
$$\left[\dfrac{\beta_1 \dfrac{X}{Kd_{XZ}}}{1 + \dfrac{X}{Kd_{XZ}}}\right] \cdot \left[\dfrac{\left(\dfrac{V}{Kd_{VZ}}\right)^m}{1 + \left(\dfrac{V}{Kd_{VZ}}\right)^m}\right] \cdot \left[\dfrac{1}{1 + \left(\dfrac{Y}{Kd_{YZ}}\right)^n}\right]$$

and standard deviation equal to the Weber fraction times the mean. Adding output Z_{eq} of all

receptors of the series and multiplying it by the reciprocal of 0.7489 (the limiting value of the

slope when the input signal is a multiple of 10) and 1.111 for the series of FNM and C1-FFL,

respectively, should turn out to be equivalent to sampling from a Gaussian with mean equal to

a constant times the input signal X and standard deviation equal to a constant times the Weber

fraction times the input signal X. As stated above, in order to get (quasi-)linear input-output

relationship over the range 10^a-10^b (where, a < b and both are integers) from the series of FNM

and C1-FFL, Kd_{XZ} of the receptors should range at least from 10^{a-5} to 10^{b+5} and 10^{a-4} to 10^{b+4},

respectively. Thus, the input-output relationship is (quasi-)linear only for the middle values of

input signal, and therefore the order of magnitude of X should be among the preferred order of

magnitude of the middle receptors.

The value of $(\beta_2/\alpha_2) \cdot (1/Kd_{YZ})$ and $(\beta_3/\alpha_3) \cdot (1/Kd_{VZ})$ were set equal to 10^4 (eqs. 9 and 20)

and 10^8 for FNM and C1-FFL, respectively, in order to carry out the approximations. However,

values of β_2/α_2 and β_3/α_3, required to generate the value of V and Y from the input signal X,

are not known individually. Therefore three combinations of β_2/α_2 and Kd_{YZ} were considered,

while keeping the value of the product of β_2/α_2 and $1/Kd_{YZ}$ equal to 10^4 and 10^8 for FNM and

C1-FFL, respectively. The combinations for FNM were $\beta_2/\alpha_2=10^4$ and $Kd_{YZ}=1$, $\beta_2/\alpha_2=10^2$

and $Kd_{YZ}=10^{-2}$, and $\beta_2/\alpha_2=1$, $Kd_{YZ}=10^{-4}$. The combinations for C1-FFL were $\beta_2/\alpha_2=10^8$

and $Kd_{YZ}=1$, $\beta_2/\alpha_2=10^4$ and $Kd_{YZ}=10^{-4}$, and $\beta_2/\alpha_2=1$, $Kd_{YZ}=10^{-8}$. The same was done with

β_3/α_3 and Kd_{VZ} for FNM and C1-FFL.

Given a value of the mean (equivalent to the input signal X) and the Weber fraction (f), ten

thousand values of Z_{eq} were generated from this sampling procedure and used to fit a Gaussian

distribution. This procedure was carried out for thirty times. For a given value of f, the average

of (thirty) means of the Gaussian fit for mean (the input signal X) equal to 0.1, 1, and 10 (and

therefore, standard deviation equal to f·0.1, f·1, and f·10, respectively) were linearly regressed

against the following values: 0.1, 1, and 10. Similarly, for a given value of f, the average

of (thirty) standard deviations got from the same procedure were linearly regressed against

the following values: f·0.1, f·1, and f·10. The values of f taken are as follows: 0.01, 0.02,

0.05, 0.1, 0.2, 0.5, and 1. This was done for all the nine combinations of $\beta_2/(\alpha_2 \cdot Kd_{YZ})$ and

$\beta_3/\alpha_3 \cdot Kd_{VZ})$. Table 8 and 9 of Supplementary Information show the average and standard

deviation of the slope, y-intercept, and R^2 of the straight line fitting of the average of thirty

means and standard deviations (derived from Gaussian fitting of Z_{eq}) for the series of FNM and

C1-FFL, respectively. The value of the average was truncated after two decimal places, and the

value of standard deviation was truncated after one decimal place.

Part 5

For the purpose of Gaussian fitting, the expression 47 for N=1,2,3, plotted on the linear scale,

the power function with an exponent of 0.5, the power function with an exponent of 0.33, and

the logarithmic scale, were evaluated at values of X which were uniformly spaced with the

interval of 0.25 and ranged from 0 to the value at which the output had declined to 0.01 times

the peak value. The same was done with the first three terms on the RHS of eq. 22, except

for the linear scale, for which the range taken was from 0 to the value at which the output had

declined to 0.5 times the peak value. This was done in order to reduce the number of data points

towards the right side of the peak. For both fittings (except for the special case mentioned),

reducing the interval further caused a minuscule change in the R^2 but did not change the result

qualitatively (Supplementary Information, Table 5 and 6, respectively).

Part 6

In order to get the series of FNM receptors which produce the maximum output at integral

values generate (quasi-)linear input-output relationship, the values of β_1/α_1 of this series were

determined by linearly regressing output Z_{eq} of the series of ten such receptors, defined by the

expression 47 with N ranging from 1-10, on the values of X which were uniformly spaced with

the interval of 0.25 and ranged from 0.25 to 10. The same was done with the series of twenty

such receptors, defined by the expression 47 with N ranging from 1-20. The positive arm of the

first receptor in both the series was removed, as its presence gave an uneven input-output curve

mostly towards its leftmost part.

Part 7

For the purpose of Gaussian fitting, the expression 48, with different combinations of m and n,

was evaluated at values of X which were uniformly spaced with the interval of 0.25 and ranged

from 0 to the value at which the output had declined to 0.01/K times the peak value. K was

set equal to 5. Reducing the interval further caused a minuscule change in the R^2 but did not

change the result qualitatively (Supplementary Information, Table 7).

Part 8

In order to determine β_1/α_1 for the computation of the logarithm by the series of FNM and

C1-FFL, the output of $\log_{10}(X)$ and $\log_e(X)$ were linearly regressed against the expression on

the RHS of eq. 51 and eq. 52, respectively. To this end, the functions $\log_{10}(X)$ and $\log_e(X)$

and the expressions were evaluated at values which were powers of 10, ranging from 10^0 to

10^6. For the range 10^0 to 10^5, the value of three out of five β_1/α_1 turned out to be negative for

both series. Note that at least five input values were needed for the regression procedure, as

the series of five receptors was considered. Because the logarithm of values that lie between 0

and 1 is negative, a biologically unrealistic scenario, the output in this range was suppressed.

This was done by setting the Hill-coefficient of the positive arm of the first receptor equal to

two (i.e., m=2). For the series of C1-FFL, it was observed that the first receptor with m=1

produced two negative β_1/α_1. If the maximum value of the range was more than 10^6 (at least

up to 10^{15}), the value of all β_1/α_1 remained positive for the series of FNM. However, the fitting

procedure returned at least one negative β_1/α_1 for the series of C1-FFL when the maximum

value of the range was more than 10^6 (at least up to 10^{15}). These two observations suggest that

the series of FNM is more robust in computing logarithm than the series of C1-FFL. In order

to determine β_1/α_1 for the computation of exponential by the series of FNM and C1-FFL, the

output of exp(X) was linearly regressed against the expression on the RHS of eq. 51 and eq.

52, respectively. To this end, the function exp(X) and the expressions were evaluated at values

which were square root of numbers ranging from 0 to 6.

$$Z_{eq} = \sum_{i=1}^{4} C_i \left[\frac{\frac{X}{10^i}}{1 + \frac{X}{10^i}} \right] \cdot \left[\frac{\frac{X}{10^{i-1}}}{1 + \frac{X}{10^{i-1}}} \right] \cdot \left[\frac{1}{1 + \frac{X}{10^i}} \right] + C_5 \left[\frac{\frac{X}{10^5}}{1 + \frac{X}{10^5}} \right] \cdot \left[\frac{\frac{X}{10^4}}{1 + \frac{X}{10^4}} \right] \tag{51}$$

$$Z_{eq} = \sum_{i=1}^{5} C_i \left[\frac{\frac{X}{10^i}}{1 + \frac{X}{10^i}} \right] \cdot \left[\frac{\frac{X}{10^{i-1}}}{1 + \frac{X}{10^{i-1}}} \right] \tag{52}$$

769 4. Discussion

Sensory systems need to respond to stimuli which vary over several orders of magnitude

in intensity and frequency. One way to achieve this is by "resetting" the system, that is,

by employing the mechanism of exact adaptation. A prominent example of this strategy is

Escherichia coli's chemotaxis. Tu and co-workers [4] presented a three-variable reduced model

of the bacterial chemotaxis, whose features are: 1) attractant ligand (L(t)) binding reduces the

average kinase activity (a(t)), 2) the kinase activates demethylation machinery (the time rate of

change in methylation must be a monotonically decreasing function of the kinase activity), and

3) attractant ligand binding affinity is a decreasing function of the average methylation level

(m(t)). Binding of an attractant ligand lowers the average kinase activity (and thus decreases

the tumbling frequency), leading to reduction of demethylation rate, and the resultant increased

level of methylation restores the average kinase activity back to its resting value.

The sensory mechanism presented in this work in order to explain Weber's law in higher-order

sensory processes differs fundamentally from the exact adaptation based mechanism, which

is responsible for Weber's law observed in E coli's chemotaxis. The two differences are as

follow. Firstly, in the latter mechanism an input signal is sensed relative to the background

signal, at which the system was equilibrated to. By contrast, in the former mechanism an

input signal is sensed in absolute manner. Secondly, in the latter mechanism it's the transient

response of the system that possesses information about the input signal, as the system's output

returns back to its resting value. On the other hand, in the former mechanism the equilibrium

state of the system possesses information about the input signal. Because higher-order sensory

processes such as weight perception, size perception, and numerosity processing sense an input

signal in absolute manner and should not involve exact adaptation (as argued in *Introduction*),

a sensory mechanism based on exact adaptation cannot explain Weber's law observed in the

three higher-order sensory processes. Thus the mechanism proposed here is, to the author's

knowledge, the only plausible mechanism which can explain Weber's law observed in the three

higher-order sensory processes.

Here the present author would like to speculate on the role of numeral systems. Arguably,

estimating the number of an entity without using a numeral system amounts to generating an

output which is the input signal plus noise which is proportional to the input signal; that is,

Weber's law. Thus, arguably, the function of a numeral system is to remove the noise and have

the brain generate an output which is equal to the input signal. However, because large numbers are considered in terms of their order of magnitude; arguably, the brain processes large numbers in accordance with Weber's law.

It should be noted that there has to be an upper limit on the production rate (β_1). However, because eq. 2 (and hence also eq. 18/21) is linear in β_1, the overall output can be increased by having the input signal engender the production from multiple Z producers. There also has to be an upper limit on the value of the equilibrium dissociation constants, so that the Gibbs energy of binding remains significantly larger than the thermal energy. Thus, some mechanism has to exist such that the apparent value of the equilibrium dissociation constants increases even when the equilibrium dissociation constants for the actual binding reach an upper limit. This can be achieved, for example, by having a mechanism in which the input signal has to occupy multiple producer elements of the producer Z at the same time in order to engender production of Z. An implication of these two considerations is that FNM and C1-FFL might be present in a hidden form in biological networks.

References

[1] Weber EH Tatsinn and Gemeingefuhl (Verlag von Wilhelm Englemann, Leipzig; 1905 Germany).

[2] Fechner GT Elements of Psychophysics, trans Adler HE (Holt, Rinehart, and Winston, New York); 1966

[3] Mesibov R, Ordal GW, and Adler J Range of attractant concentrations for bacterial chemotaxis and threshold and size of response over this range - Weber Law and related phenomena J. Gen. Physiol. 1973; 62 203–223.

[4] Tu Y, Shimizu TS, and Berg HC Modeling the chemotactic response of *Escherichia coli* to
time-varying stimuli PNAS 2008; 105:14855–14860.

[5] Kalinin YV, Jiang L, Tu Y, and Wu M Logarithmic Sensing in *Escherichia coli* Bacterial
Chemotaxis Biophysical Journal 2009; 96 2439–2448

[6] Shoval O, Goentoro L, Hart Y, Mayo A, Sontag E, and Alon U Fold-change detection and
scalar symmetry of sensory input fields PNAS 2010; 107(36) 15995–16000.

[7] Shoval O, Alon U, and Sontag E Symmetry Invariance for Adapting Biological Systems
SIAM J. Applied Dynamical Systems 2011; 10(3) 857–886.

[8] Adler M, Mayo A, and Alon U Logarithmic and Power Law Input-Output Relations in
Sensory Systems with Fold-Change Detection PLoS Comput Biol 2014; 10(8): e1003781

[9] Dehaene S The neural basis of the Weber–Fechner law: a logarithmic mental number line
TRENDS in Cognitive Sciences 2003; 7 145–147.

[10] Nieder A, Freedman DJ, Miller EK Representation of the quantity of visual items in the
primate prefrontal cortex Science 2002; 297 1708–1711.

[11] Sawamura H, Shima K, Tanji J Numerical representation for action in the parietal cortex
of the monkey Nature 2002; 415 918–922.

[12] Nieder A and Miller EK Coding of Cognitive Magnitude: Compressed Scaling of
Numerical Information in the Primate Prefrontal Cortex Neuron 2003; 37 149–157.

[13] Purves D, Augustine GJ, Fitzpatrick D, et al., Neuroscience. 2nd edition. Sunderland
(MA): Sinauer Associates; 2001

[14] Fay RR, Hearing in Vertebrates: A Psychophysics Databook. Winnetka, IL: Hill-Fay
Associates; 1988