Neural Flip-Flops II: Short-Term Memory and

Electroencephalography

Lane Yoder

Department of Science and Mathematics, retired

University of Hawaii, Kapiolani

Honolulu, Hawaii

LYoder@hawaii.edu

NeuralNanoNetworks.com

Abstract

The explicit neural flip-flops and oscillators proposed here suggest a resolution to the

longstanding controversy of whether short-term memory depends on neurons firing persistently

or in brief, coordinated bursts. Cascaded oscillators can generate the major phenomena of

electroencephalography by enabling the state changes of many neural structures simultaneously.

(The function of such oscillator-induced synchronization in information processing systems is

timing error avoidance.) For example, the hypothesis that cascaded oscillators produce

electroencephalographic phenomena implies that the boundary separating the alpha and beta

frequency bands is

$$125/\{\mu_d + \sqrt{[(\mu_d)^2 + (\sigma_d)^2 \ln(4)]}\} \text{ hertz,}$$

where μ_d and σ_d are the mean and standard deviation (in milliseconds) of delay times of neurons

that make up the initial oscillators in the cascades. With 4 and 1.5 ms being the best estimates

for μ_d and σ_d, respectively, this predicted boundary value is 14.9 Hz, which is within the range of

commonly cited estimates obtained empirically from electroencephalograms (EEGs). The delay

parameters $\mu_d = 4$ and $\sigma_d = 1.5$ also make predictions of the peaks and other boundaries of the

five major EEG frequency bands that agree well with empirically estimated values.

The cascaded oscillators hypothesis is supported by the available data for neuron delay times and

EEG frequencies; the micro-level explanations of macro-level phenomena; the number, diversity,

and accuracy of predictions of EEG phenomena; the simplicity of the oscillators and minimal

required neuron capabilities; the selective advantage of timing error avoidance that cascaded

oscillators can provide; and the implausibility of a fundamentally different mechanism producing

the phenomena.

1. Significance statement

Stripped of details such as redundancies and other error-correcting mechanisms, the basic organization of synaptic connections within some of the brain's building blocks is likely to be less complex than it appears. For some brain functions, the network architectures can even be quite simple.

The cascaded oscillators proposed here almost certainly show how neurons are connected to generate the periodic activity found in electroencephalograms (EEGs), commonly known as brainwaves. The evidence supporting this claim is quite strong.

Cascaded oscillators together with neural flip-flops suggest a resolution to the longstanding controversy of whether short-term memory depends on neurons firing persistently or in brief, coordinated bursts.

2. Introduction

This article is the fifth in a series of articles that show how neurons can be connected to process information. The first three articles [1-3] showed that a neural fuzzy logic decoder can produce the major phenomena of color vision and olfaction. The fourth article [4] showed that neurons can be connected to form Boolean neural flip-flops (NFFs) that are robust and generate the major phenomena of short-term memory. A flip-flop is a mechanism that can be set repeatedly to either one of two stable states, commonly labeled 0 and 1. Flip-flops are the basic building blocks of sequential logic systems, whose logic operations depend on both the current inputs and past sequence of inputs. Some of the material in [4] will be reviewed and used here.

The present article shows how neurons can be connected to produce the major phenomena of electroencephalography. This network and NFFs together suggest a resolution to the longstanding controversy of whether short-term memory depends on neurons firing persistently or in brief, coordinated bursts.

To accomplish this, a new NFF is presented here. It is composed of six neurons, and its

operation depends only on minimal neuron capabilities of excitation and inhibition. Its design is

a modification of a standard electronic flip-flop design. The NFF can be configured to function

as a toggle, i.e., a flip-flop with one input that inverts the memory state. It was shown in [2] that

a neuron can function as a logic inverter, whose output is the opposite of its single input.

The rest of this article's network designs are straightforward engineering: An odd

number of inverters connected in a circular sequence forms a ring oscillator. An oscillator

connected in sequence with several toggles forms a cascade of oscillators with different

frequencies. An oscillator can synchronize state changes in other networks by enabling them

simultaneously. The cascaded oscillators' properties and robust operation are demonstrated by

simulation, but the properties can be proven directly from the explicit network connections and

minimal neuron properties of excitation and inhibition.

The *cascaded oscillators hypothesis* states that the brain structures' matched periods of

neural activity that are found in EEGs are the result of the structures' synchronization by

cascades of neural oscillators. The main implication of the hypothesis is that the bands of

frequencies found in EEGs have the same distributions of frequencies as the cascaded oscillators.

All EEG phenomena predicted by the hypothesis follow from this one implication. It will be

shown here that cascaded oscillators' frequency distributions are determined by just two

parameters: the mean and variance of the delay times of neurons that make up the initial

oscillators in the cascades. With this property and samples of neuron delay times and EEG

frequencies, the main implication of the cascaded oscillators hypothesis can be tested simply and

rigorously with standard statistical tests for equal means and variances.

Two anomalous properties of EEG frequencies that have no apparent selective advantage

make it implausible that EEG phenomena are produced by a mechanism that is fundamentally

different from cascaded oscillators. The EEG gamma band has approximately the same

distribution of frequencies as three-neuron ring oscillators, and the ratios of peaks and

boundaries of the major EEG bands are approximately powers of two. These properties are by-

products of the cascaded oscillator solution to selective pressures for some information to be

processed as fast as possible and for a wide distribution of frequencies in the trade-off between

speed and accuracy.

Many neuroscientists believe that the specific connectivity of the brain largely determines

how information is processed, and that the brain's connectivity is one of the major open

questions in biology [5]. Little progress has been made in this area, possibly because a way

forward is not apparent. Many of the efforts to find connections between neuroscience and

artificial neural networks have been attempts to apply "brain-like" networks to artificial

intelligence and machine learning. One of the main problems with this approach has been the

lack of an accurate model of how the brain works [6].

This situation could change. Recognizing a neuron's simple logic capability makes a

useful connection between neuroscience and the field of logic circuit design in electronic

computational systems. It was shown in [2] that a neuron with excitatory and inhibitory input

can operate as a functionally complete logic primitive, meaning any logic function can be

performed by a network of such components. As demonstrated here and in [1-4], neuroscience

and logic circuit design can inform each other in how certain simple functions can be performed.

For higher-level cognitive functions, the methods of the brain and artificial intelligence are

currently vastly different. However, complex systems can consist of simple building blocks.

With the recognition that the two systems are likely to have similar logical design and essentially

the same building blocks, neuroscience and computer science may inform each other from the

ground up.

3. Materials and methods

3.1. Simulation materials and methods

The cascaded oscillators were simulated in MS Excel. For this simulation, the number t_i represents the time after i neuron delay times. The neurons' outputs were initialized in a stable state at time $t_0 = 0$. For i > 0, the output of each neuron at time t_i was computed as a function of the inputs at time t_{i-1}. Specific predicted probabilities of unusually large gamma band frequencies were approximated numerically from the initial oscillator's estimated frequency PDF with Converge 10.0, although this could also be done with a substitution of u = 1,000/x to convert the frequency PDF to a normal distribution of periods.

3.2. DEEP neural networks

The neural networks proposed here and in [1-4] are dynamic, explicit, evolutionary, and predictive (DEEP). The networks' dynamic operation means the only changes are the levels of neuron activity. No structural change is required, such as neurogenesis, synaptogenesis, or pruning, nor is any change required in the way neurons function, such as a change in synaptic strength or the strength of action potentials. All neurons, connections, and types of synapses are shown explicitly, and all assumptions of neuron capabilities are stated explicitly. Only minimal neuron capabilities are assumed, and no network capabilities are assumed. The networks are evolutionary in the sense that they demonstrate selective advantages for at least some of the phenomena they generate. This includes phenomena whose functions are apparently uncertain, such as the matched periods of neural activity found in EEGs. Finally, the networks are predictive of nervous system phenomena. That is, based on the explicit connections and neuron capabilities, it can be demonstrated that the models generate known nervous system phenomena, and they may make testable predictions of phenomena that are as yet unknown.

For most brain functions, the four DEEP properties are necessary for a model to show

how neurons are actually connected. The dynamic operation makes the network's speed

consistent with the "real time" of most brain functions (a few milliseconds). Explicitness means

the model is transparent, as opposed to a "black box" to which any property may be assigned.

An evolutionary model performs a useful function, as opposed to an ad hoc model that is

designed to produce a known phenomena without any apparent utility. A realistic model must

predict phenomena.

The dual purpose of this article is to call attention to the dearth of DEEP models in the

literature and to demonstrate that it is possible to design DEEP neural networks. DEEP models

are needed to make progress in discovering how synaptic connections are organized at the local

level.

3.3. Unexplained phenomena and alternative models

139   There is no consensus on the brain's organization of synaptic connections at the local

140   level. Consequently, many brain phenomena lack explicit explanations.

3.3.1. Short-term memory: persistent firing or brief, coordinated bursts?

Memory tests have shown that certain neurons fire continuously at a high frequency

while information is held in short-term memory [7, 8]. These neurons exhibit seven

characteristics associated with memory formation, retention, retrieval, termination, and errors.

One of the neurons in the NFFs proposed in [4] was shown to produce all of the characteristics.

In addition to neurons firing persistently, other neurons firing in brief, coordinated bursts

are also associated with short-term memory [9]. Which of these two phenomena actually

produces short-term memory has been a longstanding controversy [9, 10]. It will be shown that

neural oscillators and NFFs together suggest a resolution to this issue.

3.3.2. Electroencephalography

3.3.2.1. EEG phenomena and previous models

Electroencephalograms show widespread rhythms that consist of many neurons firing with matched periods. The spectrum of frequencies has been partitioned into bands according to the behavioral and mental state associated with the frequencies in each band. Five EEG frequency bands are considered here: gamma, beta, alpha, theta, and delta. Some researchers have found more bands or divided the bands into sub-bands depending on the focus of their research, but these five are discussed most often in the literature.

The distribution of frequencies within each of these bands is unimodal [11-14]. The ratios of consecutive band boundaries [15] and the ratios of consecutive band peak frequencies [11-14] are approximately 2. The gamma band peaks at about 40 Hz [11-14], although it contains frequencies of 100 Hz or more [16, 17]. Several estimated frequencies have been found for each boundary between bands.

The EEG phenomena raise several questions. What produces the widespread, synchronized, periodic firing? What is the function of this widespread synchronization? What produces and what is the function of the wide distribution of EEG frequencies in bands? What produces the unimodal distribution in each band and the octave relationships between the peaks and boundaries? What determines the specific frequencies of the peaks and boundaries? Why do gamma oscillations peak at about 40 Hz? Why does the gamma band contain frequencies that are considerably faster than 40 Hz? Why is there little agreement on the boundaries separating the EEG bands?

Answers to a few of these questions have been proposed, but there has been no explicit model that can explain more than one or two phenomena. Most models are based on "black box"

networks or broad assumptions of neuron capabilities. Below are two prominent examples of

proposed oscillator models.

Pacemaker cells are natural oscillators that cause involuntary muscles and other tissues to

contract or dilate. They are spontaneously active neurons with a specialized cell membrane that

allows sodium and potassium to cross and generate regular, slow action potentials (around 100

spikes per minute) [18, 19]. Modulating input controls the spike frequency. Except for

generating periodic signals, pacemaker cells do not offer answers to any of the questions above.

It is not clear, for example, how pacemaker cells could generate the wide distribution of EEG

frequencies, their unimodal distribution in bands, or the octave relationships of the bands. Also a

single spike would not be a good enabler of state changes because the duration of an enabling

input needs to be long enough to overlap the input that is being enabled.

The Kuramoto model [20] provides a widely accepted explanation of synchronized firing

found in EEGs. The model assumes, without supporting evidence and without an explanation of

a mechanism or function for any of these behaviors, that the neurons' signals oscillate naturally,

that these oscillations are nearly identical, and that each neuron is linked to all the others. The

model does not appear to answer any of the above questions besides how synchronization occurs.

The model is a macro-level explanation of a macro-level phenomenon. The EEG data are quite

distant from the micro-level explanation given here based on neuron delay times.

The cascaded oscillators model proposed here can produce the synchronized firing found

in EEGs by enabling neural structures' state changes simultaneously. It will be shown that the

model provides answers to all of the questions above.

3.3.2.2. Implausibility of alternative mechanisms

A natural question is whether the EEG phenomena listed above are actually produced by

a mechanism or mechanisms that are fundamentally different from the cascaded oscillators

proposed here. This is unlikely for at least three reasons.

First, it is unlikely that another mechanism that could produce all of the EEG phenomena

would be as simple as cascaded oscillators. Only two types of simple networks are required: a

three-neuron ring oscillator and a six-neuron NFF. The neurons require no special capabilities

other than excitation and inhibition. Second, nature has limits. Besides limitations on neuron

capabilities, evolutionary changes proceed in incremental steps with selective improvements at

each step. Even if all of the phenomena could be generated by a different mechanism, evolution

may not be able to produce it.

Perhaps most importantly, even if evolution could produce another mechanism that

generates the phenomena, selective pressure to do so is unlikely. Cascaded oscillators are a

possible response to two specific selective pressures. As side effects, cascaded oscillators imply

two anomalous characteristics of EEG frequencies that have no apparent function.

Toggles connected in sequence to function as oscillators are a possible response to a

selective pressure for a wide variety of frequencies in the trade-off between speed and accuracy

in processing different kinds of information. This would produce the octave relationship that has

been observed between EEG frequency bands. There is no apparent selective advantage in

distributions of frequencies with an octave relationship. If a mechanism other than cascaded

toggles evolved to produce oscillations with a wide variety of frequencies, it is unlikely that the

frequencies would be distributed in bands with the octave relationship.

A three-inverter ring oscillator is the fastest oscillator that can be constructed with logic

gates. A three-neuron ring oscillator as the cascade's initial oscillator is a possible response to a

selective pressure for some information to be processed as fast as possible. As shown below,

that distribution in the gamma band is consistent with available data. There is no apparent

selective advantage in that particular distribution of frequencies. If a different mechanism

evolved to produce fast oscillations, it would be unlikely to have the same distribution of

frequencies as three-neuron ring oscillators.

3.4. Analysis

3.4.1. Neuron signals

This section summarizes part of [4] that will be used here.

3.4.1.1. Binary neuron signals

Neuron signal strength, or intensity, is normalized here by dividing it by the maximum

possible intensity for the given level of adaptation. This puts intensities in the interval from 0 to

1, with 0 meaning no signal and 1 meaning the maximum intensity. The normalized number is

called the *response intensity* or simply the *response* of the neuron. Normalization is only for

convenience. Non-normalized signal strengths, with the highest and lowest values labeled Max

& Min rather than 1 and 0, would do as well. The responses 1 and 0 are collectively referred to

as binary signals and separately as high and low signals. If 1 and 0 stand for the truth values

TRUE and FALSE, neurons can process information contained in neural signals by functioning

as logic operators.

The strength of a signal consisting of action potentials, or spikes, can be measured by

spike frequency. A high signal consists of a burst of spikes at the maximum spiking rate. For a

signal that oscillates between high and low, the frequency of the oscillation is the frequency of

bursts, not the frequency of spikes.

For binary signals, the response of a neuron with one excitatory and one inhibitory input

is assumed to be as shown in Table 1.

Excitatory X	Inhibitory Y	Response
0	0	0
0	1	0
1	0	1
1	1	0

Table 1. Neuron response to binary inputs. Of the 16 possible binary functions of two

variables, this table represents the only one that is consistent with the customary meanings of

"excitation" and "inhibition." Table 1 is also a logic truth table, with the last column

representing the truth values of the statement X AND NOT Y.

The networks presented here require continuous, high input. In the figures, this input is

represented by the logic value "TRUE." For an electronic logic circuit, the high input is

normally provided by the power supply. If the components represent neurons, the high input can

be achieved by neurons in at least four ways. 1) A continuously high signal could be provided

by a neuron that has excitatory inputs from many neurons that fire independently [21]. 2) The

brain has many neurons that are active spontaneously and continuously without excitatory input

[22, 23]. A network neuron that requires a high excitatory input could receive it from a

spontaneously active neuron, or 3) the neuron itself could be spontaneously active. 4) The high

input could be provided by one of a flip-flop's outputs that is continuously high.

3.4.1.2. Additive noise in binary neuron signals

All binary results for the networks presented here follow from the neuron response in

Table 1. Analog signals (intermediate strengths between high and low) were considered in [4]

only to show how the NFFs in the figures can generate robust binary signals in the presence of

moderate levels of additive noise in binary inputs. The NFF simulation in [4] will not be

repeated here, but the same noise-reducing neuron response function will be used in the cascaded

oscillators simulation with additive noise. This function and the minimal conditions for adequate

noise reduction will be reviewed briefly in this section.

3.4.1.2.1. Noise reduction

Reduction of noise in both excitatory and inhibitory inputs can be achieved by a response

function of two variables that generalizes a sigmoid function's noise reducing features. The

noise reduction need only be slight because the proposed NFFs have feedback loops that

continually reduce the effect of noise.

Let $F(X, Y)$ represent a neuron's response to an excitatory input X and an inhibitory input

Y. The function must be bounded by 0 and 1, the minimum and maximum possible neuron

responses, and must satisfy the values in Table 1 for binary inputs. For other points (X, Y) in the

unit square, suppose F satisfies:

1. $F(X, Y) > X - Y$ for inputs (X, Y) near $(1, 0)$ and

2. $F(X, Y) < X - Y$ or $F(X, Y) = 0$ for inputs (X, Y) near the other three vertices of the

unit square.

Neurons that make up the networks proposed here are assumed to have these minimal noise-

reducing properties.

Conditions 1 and 2 are sufficient to suppress moderate levels of additive noise in binary

inputs and produce the NFF results found here. The level of noise that can be tolerated by the

NFFs depends on the regions in the unit square where conditions 1 and 2 hold. If a binary input

(X, Y) has sufficiently large additive noise to change the region in which it lies, an error can

occur.

3.4.1.2.2. Example of a neuron response that satisfies conditions 1 and 2

For any sigmoid function f from f(0) = 0 to f(1) = 1, the following function has the noise-reducing properties 1 and 2 and also satisfies Table 1:

F(X, Y) = f(X) - f(Y), bounded below by 0.

The function F is illustrated in Fig 1 for a specific sigmoid function f.

Fig 1. Noise-reducing AND-NOT function. The graph shows an example of a neuron response to analog inputs that reduces moderate levels of additive noise in binary inputs. **A.** A sigmoid function f(x) = (1/2)sin(π(x - 1/2)) + 1/2. **B.** Graph of a function that has the noise-reducing properties 1 and 2. The function is F(X, Y) = f(X) - f(Y), bounded by 0. The triangle lies in the plane Z = X - Y. The approximate intersection of the plane and the graph of the response function F is shown in red. The purple and blue regions in the unit square show approximately where conditions 1 and 2 hold, respectively.

3.4.2. Neural logic gates and flip-flops

For several reasons that were detailed in [4], the neural networks in the figures are illustrated with standard (ANSI/IEEE) logic symbols rather than symbols commonly used in neuroscience schematic diagrams. One of the reasons is that the symbols can be interpreted in

two ways. As a logic symbol, the rectangle with one rounded side in Fig 2A represents the AND

logic function, and the circle represents negation. The input variables X and Y represent truth

values TRUE or FALSE, and the output represents the truth value X AND NOT Y. Second, Fig

2A can also represent a single neuron, with a circle representing inhibitory input and no circle

representing excitatory input. If X and Y are binary inputs, the output is X AND NOT Y by

Table 1. Fig 2B shows that an AND-NOT gate with a continuously high input functions as a

NOT gate, or inverter.

Fig 2. Neural logic gates and flip-flops. A. A symbol for an AND-NOT logic gate, with output X AND NOT Y. The symbol can also represent a neuron with one excitatory input and one inhibitory input. **B.** An AND-NOT gate configured as a NOT gate, or inverter. **C.** An active low Set-Reset (SR) flip-flop. **D.** An active high SR flip-flop. **E.** An active high SR flip-flop enabled by input from an oscillator. **F.** A JK flip-flop or toggle. If S and R are high simultaneously, the flip-flop is inverted.

A flip-flop stores a discrete bit of information in an output with values usually labeled 0 and 1. This output variable is labeled M in Fig 2. The value of M is the flip-flop *state* or *memory*

bit. The information is stored by means of a brief input signal that activates or inactivates the

memory bit. Input S *sets* the state to M = 1, and R *resets* it to M = 0. Continual feedback

maintains a stable state. A change in the state *inverts* the state.

Two basic types of flip-flops are the Set-Reset (SR) and JK. Fig 2C shows an active low

SR flip-flop. The S and R inputs are normally high. A brief low input S sets the memory bit M

to 1, and a brief low input R resets it to 0. Adding inverters to the inputs produces the active

high SR flip-flop of Fig 2D. The S and R inputs are normally low. A brief high input S sets the

memory bit M to 1, and a brief high input R resets it to 0. The NFF in Fig 2D was simulated in

[4].

Fig 2E shows a flip-flop with an enabling input. The S and R inputs in Fig 2D have been

replaced by AND-NOT gates that allow the S or R input to be transmitted only when the

enabling input is low. In synchronized signaling systems, various logic circuits are enabled

simultaneously by an oscillator to avoid timing errors.

For the so-called JK flip-flop in Fig 2F, the enabling input in Fig 2E has been replaced by

input from the flip-flop outputs. A disadvantage of the SR flip-flop is that if S and R are

activating simultaneously, the outputs are unpredictable. The advantage of the JK flip-flop is

that if S and R are both high simultaneously, the flip-flop state is inverted because the most

recent inverting input is inhibited by one of the outputs. This means the JK flip-flop can be

configured as a toggle by linking the Set and Reset inputs, as illustrated by the single input T in

the figure.

A problem with the JK toggle is that it functions correctly only for a short duration of

high input. If the duration is too long, the outputs will oscillate. This problem is handled in the

oscillators section below.

341 3.4.3. Neural oscillators

342 3.4.3.1. Neural ring oscillators and toggles

An oscillator produces periodic bursts of a high signal followed a quiescent period of a

low signal. It is the basic element of a timing mechanism. A ring oscillator is a simple and

reliable oscillator. An odd number of three or more inverters connected sequentially in a ring

produces periodic bursts as each gate inverts the next one. The odd number of inverters makes

all of the inverter states unstable, so the states oscillate between high and low. All inverters in

the ring produce oscillations with the same frequency. Their phases are approximately uniformly

distributed over one cycle, and the high and low signal durations are approximately equal. Their

common period is twice the sum of the inverters' delay times. (The sum is doubled because each

component inverts twice per cycle.) A ring oscillator is the simplest type of oscillator that can be

implemented with logic gates, and the simplest and fastest ring oscillator consists of three

inverters.

As described in the introduction, an oscillator can be connected in sequence with toggles

to form a cascade of oscillators. Because two high inputs are required for each cycle of a toggle-

as-oscillator (one to set the memory state, another to reset it), a toggle produces a signal whose

period is exactly double that of the toggle's input.

The master-slave toggle is the customary choice for cascaded oscillators because of its

ability to invert no more than once regardless of the high input duration. The master-slave toggle

can be implemented with neurons by connecting two JK toggles in the standard way. However,

the problem of JK toggles inverting more than once with a long high input can be resolved by

using an early output in the JK toggle's signal pathway as the input to the next toggle. The JK

toggle's two initial neurons have the same pulse duration as the toggle's input. This means an

entire cascade can be composed of a ring oscillator and JK toggles, which require half as many

components as master-slave toggles. This configuration is illustrated in Fig 3. The use of JK

toggles as cascaded oscillators may be new to engineering.

Fig 3. Three cascaded neural oscillators. The cascade consists of a ring oscillator followed by

two JK toggles connected in sequence. The ring oscillator is composed of three inverters of Fig

2B, with an enabling first input. The toggles are as in Fig 2F. The input to each toggle comes

from one of the first gates in the previous toggle so that the duration of the high signal remains

the same throughout the cascade.

3.4.3.2. Cascaded neural oscillators simulation

A simulation of the cascaded oscillators in Fig 3 is shown in Fig 4. The simulation was

done in MS Excel.

Fig 4. Simulation of three cascaded neural oscillators. The simulation of the cascaded

oscillators in Fig 3 illustrates the main properties of cascaded oscillators: The period of the ring

oscillator's signal is twice the sum of three neuron delay times. In each toggle, the period of

every neuron's output is twice the period of the toggle's input. The pulse duration of each

toggle's two initial neurons is the same as the pulse duration of the toggle's input. Using one of

these signals as input to the next JK toggle in the cascade prevents it from inverting more than

once during the input's cycle. The effect of the moderate additive noise in the high inputs to all

seven inverters is negligible due to the neurons' noise reducing response.

The response function F(X, Y) in Fig 1 was used for the cascaded oscillator simulation as

follows. The number t_i represents the time after i neuron delay times. The neurons' outputs are

initialized in a stable state at time $t_0 = 0$. At time t_i for $i > 0$, the output Z_i of each neuron that has

excitatory and inhibitory inputs X_{i-1} and Y_{i-1} at time t_{i-1} is:

$$Z_i = F(X_{i-1}, Y_{i-1}) = \max\{0, [(1/2)\sin(\pi(X_{i-1} - 1/2)) + 1/2] - [(1/2)\sin(\pi(Y_{i-1} - 1/2)) + 1/2]\}.$$

Additive noise at each time t_i is simulated by a random number uniformly distributed

between 0 and 0.1. The Enabling input begins as baseline noise and transitions between 0 and 1

as a sine function plus noise. During the interval when the Enabling input is high, it is 1 minus

noise. All six TRUE inputs in Fig 3 are simulated as 1 minus noise. The noise is independent

for each time t_i and each input.

3.4.4. Distributions of neuron delay times and cascaded neural oscillators' frequencies

The distributions of cascaded neural oscillators' frequencies are determined by the mean and variance of neuron delay times of the cascades' initial oscillators.

3.4.4.1. Exact relationships between inverter delay times and cascaded oscillator frequencies

The interest here is in neural inverters and toggles, but the arguments in this section apply to any implementation of inverters and toggles, including electronic. These results may not be found in electronics texts because engineers are not normally concerned with the small variances in component performance.

3.4.4.1.1. Distributions of oscillator periods and frequencies

As noted earlier, each cycle time of a ring oscillator is the sum of the times it takes for each inverter to invert twice. If $X_1, \ldots, X_n$ are independent and identically distributed random variables representing the delay times of n inverters in a ring oscillator, the ring oscillator's period is:

$$3. \quad P = 2(X_1 + \ldots + X_n)$$

If toggles are connected in sequence with the oscillator, each cycle time of each toggle's output is the sum of two of the input's cycle times. Cascaded toggle number $k = 1, 2, \ldots$ has period:

$$4. \quad P_k = 2^k P$$

The mean and standard deviation of the delay times of inverters in ring oscillators are denoted by μ_d and σ_d. By equations 3 and 4 and the elementary properties of random variables, for $i = 1, 2, \ldots$ (with $i = 1$ representing the initial ring oscillator), the period of cascaded oscillator number i has mean and standard deviation:

5. $\mu_i = 2^i n \mu_d$, $\sigma_i = 2^i \sqrt{n} \sigma_d$

The factor 2^i shows the octave relationship between the oscillators' distributions of periods.

The oscillators' distributions of frequencies can be derived from the distributions of

periods by straightforward calculus. If periods and frequencies are measured in milliseconds and

hertz, respectively, then frequency = k/period for k = 1,000. If the probability density function

(PDF) of the period of oscillator i = 1, 2, … (i = 1 representing the initial ring oscillator) is $f_i(x)$,

then the PDF of the frequency of oscillator i is:

6. $g_i(x) = k f_i(k/x)/x^2$

Equation 6 shows the oscillator period and frequency distributions are different. For

example, it will be seen that if the periods are normally distributed, the frequency distributions

are skewed to the right. But the intersections of consecutive period PDFs (converted to

frequencies) are the same as the intersections of consecutive frequency PDFs because x^2 and the

initial constant k in equation 6 drop out of the equation $g_i(x) = g_{i+1}(x)$.

3.4.4.1.2. Normal distributions

If inverter delay times are normally distributed, then by equations 3 and 4 and the

elementary properties of normal distributions, the periods of ring oscillators and cascaded

toggles are also normally distributed.

The normal PDF with mean μ and standard deviation σ, whose graph is commonly

known as the bell curve, is:

7. $f(x) = \exp[-(x-\mu)^2/(2\sigma^2)]/\sqrt{(2\pi\sigma^2)}$

Equation 7 implies that a normal distribution is entirely determined by its mean and standard

deviation. By equations 5 and 6, this means cascaded oscillators' distributions of periods and

frequencies are entirely determined by the number of inverters n in the initial ring oscillators and

the inverter delay parameters μ_d and σ_d.

Substituting the cascaded oscillators' period parameters in equation 5 into equation 7 to

obtain the period PDFs $f_i(x)$, the intersections of each pair of consecutive period PDFs can be

found by elementary algebra. For i = 1, 2, …, (i = 1 representing the ring oscillator), the

intersection of $f_i(x)$ and $f_{i+1}(x)$ occurs at period:

8. $\text{Intersection}(i) = 2^i (2/3)\{n\mu_d + \sqrt{[(n\mu_d)^2 + 6n\sigma_d^2 \ln(2)]}\}$ ms

The factor 2^i shows the intersections also have the octave relationship.

By substituting the period PDFs f_i obtained from equations 5 and 7 into equation 6, the

peak frequency (mode) for PDF g_i can be found by calculus:

9. $\text{mode}(i) = \{250/(2^i n\sigma_d^2)\}\{-n\mu_d + \sqrt{[(n\mu_d)^2 + 8n\sigma_d^2]}\}$ Hz

Again, the factor 2^i shows the peak frequencies also have the octave property. These peak

frequencies are close to, but not the same as, the peak frequencies $1{,}000/\mu_i$ derived from the

means μ_i of the period's normal distributions in equation 5.

3.4.4.2. Neuron delay times

Since neuron delay times are determined by several factors, the delay times are

approximately normally distributed (by the central limit theorem). For small networks with

chemical synapses, nearly all of the delay occurs at the synapses. Several studies have measured

synapse delay times [e.g., 24, 25], but the literature apparently does not have empirical estimates

of the parameters (mean and variance) of the delay times' distribution. However, a description of

the range of synapse delay times is "at least 0.3 ms, usually 1 to 5 ms or longer" [22]. Although

the description is far from precise, delay time parameters can be estimated.

The description of the range has two parts. The first part "at least 0.3 ms" seems to refer

to all observations. The second part "usually 1 to 5 ms or longer" seems to describe the ranges of

typical samples, with "5 ms or longer" representing the ranges' right endpoints. In that case, the

interval [1 ms, 7 ms] is at least a reasonable, rough estimate of the range of a moderately sized

sample.

If only the range of a sample (minimum value, m, and maximum, M) is known, the

midpoint can be used as an estimate of the mean of a distribution. Simulations have shown that

(M - m)/4 is the best estimator of the standard deviation for moderately sized samples [26].

Based on this and the estimated range [1 ms, 7 ms], neuron delay times are estimated to have

distribution parameters:

10. $\mu_d = 4$ ms, $\sigma_d = 1.5$ ms

For a normal distribution with these parameters, about 99.3% of the distribution is at least 0.3

ms. This agrees well with the description "at least 0.3 ms." About 73% lies between 1 and 5 ms,

and 95% is between 1 and 7 ms. This agrees reasonably well with the description "usually 1 to 5

ms or longer."

3.4.4.3. Graphs of estimated neural oscillator frequency distributions

To produce oscillations for five EEG frequency bands, four toggles are needed in

addition to the initial ring oscillator. The hypothesis that cascaded oscillators produce EEG

frequencies implies the initial ring oscillator must have the minimum of three inverters, because

an oscillator with more inverters would be too slow to generate EEG oscillations in the gamma

band. This in turn implies, unsurprisingly, that the brain evolved to enable some information to

be processed as fast as possible.

As mentioned earlier, the outputs of a JK toggle (Fig 2F) with continually high input

oscillate. The period is six neuron delay times, the same as the three-neuron ring oscillator

(equation 3). Although a JK oscillator would suffice as the initial oscillator in a cascade and

would produce the same frequencies as a three-neuron ring oscillator, natural selection may have

chosen the ring oscillator because the JK oscillator requires twice as many neurons and has

somewhat more complexity in synaptic connections. A ring oscillator may also be more robust.

Apparently no other oscillator that can be constructed with neurons is faster or simpler than a

three-neuron ring oscillator.

To achieve lower frequency oscillations, ring oscillators with more neurons would

suffice. Selective pressure for a wide distribution of frequencies may have resulted in cascaded

toggles because their periods grow exponentially (doubling with each toggle by equation 4)

while a ring oscillator's period grows linearly with the number of neurons (equation 3). Other

toggles besides the JK would suffice, such as the master-slave mentioned above, but any toggle

would double the period of the input.

As before, the period PDFs $f_i(x)$ are obtained by substituting the period parameters in

equation 5 into equation 7. With the estimated delay parameters of equations 10 and $n = 3$

neurons, the estimated frequency PDFs $g_i(x)$ of five cascaded oscillators are obtained from

equation 6. Their graphs are shown in Fig 5. The four intersections of consecutive PDFs, shown

in blue, are found by converting the periods given by equation 8 to frequencies. The five PDF

modes, shown in yellow, are obtained from equation 9. Frequencies that are commonly cited

[11-14, 27-44] as partition points separating the EEG frequency bands and peak frequencies of

three of the bands are shown in red and green, respectively. Numbers in parentheses show how

many times each frequency was cited. (Estimates of peak frequencies apparently have not been

found for the lower frequency delta and theta bands.) The graphs illustrate several of the

implications of the cascaded oscillators hypothesis, which are discussed in the results section.

Fig 5. Estimated frequency distributions of cascaded neural oscillators and commonly cited EEG frequency band peaks and boundaries. The graphs are the estimated PDFs of the frequencies of a three-neuron ring oscillator and four cascaded toggles. All of the PDFs were determined by the estimated mean and variance of neuron delay times. The five intervals defined by the intersections of consecutive PDFs are labeled with Greek letters to distinguish them from EEG frequency bands, which are often written in the Roman alphabet. The intersections and modes are labeled in blue and yellow, respectively. Also shown in red and green are frequencies that are commonly cited as partition points separating the EEG frequency

bands and peak frequencies of three of the bands. Numbers in parentheses and numbers of data

points show how many times each frequency was found to be cited in a literature search.

3.4.5. Synchronization

The EEG frequency bands and associated behavioral and mental states are consistent with

the advantages of synchronous logic systems.

3.4.5.1. Synchronous logic systems

Logic systems have a timing problem in ensuring the various subcircuits change states in

the correct chronological sequence. Synchronous logic systems generally have simpler circuit

architecture and fewer errors than asynchronous systems. This is the reason nearly all electronic

logic systems are synchronized by an enabling pulse to each component circuit, so that whenever

any components change states, they change simultaneously. The enabling pulse in such systems

is usually produced by an oscillator. The enabling input in Fig 2E and the oscillators in Fig 3

illustrate how such synchronization is possible with neural networks.

Timing problems are greater in sequential logic than in combinational logic, and greater

in parallel processing than in serial processing. Much of the information processing in the brain

involves sequential logic and nearly all of it is parallel. The selective pressure for

synchronization in the brain would have been high, and the neural implementation proposed here

is quite simple.

The processing speed in a synchronous system depends largely on the enabling

oscillator's speed. A large system like the brain that performs many diverse functions may have

several different processing speed requirements. The trade-off for greater processing speed is a

higher error rate. Functions that can tolerate a few errors, and that need fast results with many

simultaneous small computations, require high processing speeds. Functions that are less

dependent on speed or massive computation, or that require few errors, or whose component

networks are large and complex and therefore slow to change state, call for slower processing.

3.4.5.2. Synchronization and EEG frequency bands

The EEG frequency bands and associated behavioral and mental states are consistent with

the function of multiple frequencies that was suggested in the preceding paragraph. Gamma

waves (high frequencies) are associated with vision [45, 46] and hearing [16], which make sense

out of massive data input in a few milliseconds. Beta waves are associated with purposeful

mental effort [22], which may involve less data input while requiring few errors and complex

operations. Alpha waves are associated with relaxed wakefulness [20], theta waves with

working memory and drowsiness [22, 47], and delta waves with drowsiness and sleep [22].

These categories require successively slower information processing, and they have

corresponding EEG bands of lower frequencies.

Cascaded oscillators can produce this neural activity. A neural oscillator can synchronize

state changes in neural structures by enabling them simultaneously. The enabling oscillator

pulse by itself does not produce any state changes. It only forces states to change simultaneously

when they do change. So the initial ring oscillator's high frequency signal could simply be

connected directly and permanently to the enabling gates (as illustrated in Fig 2E) of networks in

the visual and auditory cortexes, the first toggle's signal to networks in the prefrontal cortex for

purposeful mental effort, etc. A large number of neural structures synchronized in this way by

cascaded oscillators would exhibit the bands of matched periods found in EEGs.

4. Results and discussion

4.1. Explanations of known phenomena

4.1.1. Short-term memory controversy

Cascaded oscillators and NFFs suggest a resolution to the question of whether short-term

memory depends on neurons firing persistently or in brief, coordinated bursts [9, 10]: Memory

is stored by persistent firing in flip-flops [4], and the coordinated bursts observed along with the

persistent firing are due to the stored information being processed by several neural structures

whose state changes are synchronized by a neural oscillator. An example of such short-term

memory processing is a telephone number being reviewed in a phonological loop.

4.1.2. Electroencephalography

4.1.2.1. EEG frequency bands' peaks and boundaries

Fig 5 shows that the cascaded oscillators hypothesis is supported by the available data for

neuron delay times and EEG frequency band peaks and boundaries. The graphs in Fig 5 are the

estimated oscillator PDFs derived from a description of the range of neuron delay times. The

cascaded oscillators hypothesis implies that the EEG frequency band boundaries are the

intersections of consecutive oscillator frequency PDFs. The graphs show the intersections of the

estimated oscillator PDFs (in blue) are within the ranges of estimated EEG frequency band

boundaries (red). The hypothesis also implies the EEG band peaks are the same as the oscillator

PDF peaks. Fig 5 shows the available estimates of three EEG band peaks (green) are close to the

peaks of the estimated oscillator PDFs (yellow).

These close fits also show that the available data support the main implication of the

cascaded oscillators hypothesis (that the EEG bands have the same distributions of frequencies

as the cascaded oscillators) and the implication that the ratios of peaks and boundaries of the

major EEG bands are powers of two.

4.1.2.2. Answers to 15 questions raised by EEG phenomena

The cascaded oscillators hypothesis answers the EEG questions raised in the section on

unexplained phenomena.

What produces the widespread, synchronized, periodic firing? 1) The firing is periodic

because neural structures are being enabled by an oscillator. 2) The periodic firing is widespread

because many neural structures are being enabled. 3) The firing is synchronized because the

neural structures are being enabled by the same oscillator.

What is the function of this widespread synchronization? 4) The function of

synchronization is timing error avoidance in processing information.

What produces and what is the function of the wide distribution of EEG frequencies in

bands? 5) The frequencies occur in bands because each band is produced by a different

oscillator. 6) The wide distribution of frequencies is due to the octave relationship between

cascaded oscillators (100% exponential growth in periods with each successive oscillator by

equation 4) and five oscillators. 7) The distribution of frequencies within each band is

determined by the mean and variance of neuron delay times in the initial oscillators in the

cascades (equations 5). 8) The function of the wide distribution of frequencies is meeting the

widely different needs of different brain functions in the trade-off between speed and accuracy.

What produces the unimodal distribution in each band and the octave relationships

between the peaks and boundaries? 9) The unimodal distributions are due to the normal

distribution of neuron delay times in the initial ring oscillators in cascades of oscillators. This

makes the distribution of periods of each oscillator normal and the distributions of frequencies

unimodal. 10) The ratio of consecutive boundaries and peak locations is 2 because consecutive

cascaded oscillators increase the oscillation period by a factor of 2 (equations 4, 8, 9).

What determines the specific frequencies of the peaks and boundaries? The number of

neurons in the ring oscillators must be the minimum of 3 to produce the high frequencies in the

gamma band. Equations 8 and 9 show the EEG band 11) boundaries and 12) peaks are

determined by this number (n = 3), the ring oscillators' delay parameters μ_d and σ_d, and the

boundary or peak number i.

Why do gamma oscillations peak at about 40 Hz? 13) The three-neuron ring oscillator is

the fastest neural ring oscillator. The estimated peak frequency from equation 9 is 38.4 Hz

(illustrated in Fig 5).

Why does the gamma band contain frequencies that are considerably faster than 40 Hz?

The frequencies vary because of the variance in neuron delay times in the initial oscillators. 14)

As Fig 5 illustrates, all of the oscillator frequency distributions are skewed to the right, with the

initial oscillator producing frequencies substantially greater than 40 Hz. In the particular

estimate of Fig 5, 2% of the frequencies are greater than 75 Hz, and 0.4% are greater than 100

Hz.

Why is there little agreement on the boundaries separating the EEG bands? 15) The

oscillators hypothesis implies that the estimates of EEG band boundaries are estimates of the

intersections of the oscillators' PDFs. This makes estimating boundaries difficult for two

reasons.

The oscillators hypothesis implies that the probability of an EEG frequency being

observed has a local minimum near each intersection of consecutive oscillator PDFs. This

means that in a random sample of observed EEG frequencies, relatively few will be near the

intersections. A small number of data points has a negative effect on the accuracy of estimates.

The overlapping oscillator PDFs (Fig 5) imply the distributions of EEG frequencies

associated with the various behavioral and mental states have overlapping ranges rather than

discrete bands. Because two PDFs are equal at their intersection, a frequency near the

intersection of two PDFs is almost equally likely to be produced by either of two oscillators.

That is, an observed EEG frequency near a band "boundary" is almost equally likely to be

observed along with the behavioral and mental state that defines the band on either side of the

intersection. This makes obtaining accurate estimates of band "boundaries" especially difficult.

4.2. Testable predictions

4.2.1. Constructed neural networks

Any of the networks in the figures could be constructed with actual neurons and tested

for the predicted behavior. Constructing and testing NFFs was discussed in [4]. The ring

oscillator of Fig 3 may be simple to construct and test. The predicted behavior is oscillating

outputs for all three neurons with a period that is twice the sum of the neurons' delay times, and

phases uniformly distributed over one cycle.

4.2.2. A simple, rigorous, statistical test of the cascaded oscillators hypothesis

4.2.2.1. The data problem

Although the hypothesis that cascaded oscillators produce EEG phenomena is consistent

with available data, as illustrated in Fig 5, the data are too imprecise for a rigorous statistical test

of the hypothesis. The estimates found here for the neuron delay time parameters μ_d and σ_d were

based on a rough description of the range of synapse delay times. Available estimates of the

EEG frequency bands' peak frequencies are few and available only for three of the five major

frequency bands, estimates of band boundaries vary widely for reasons implied by the cascaded

oscillators hypothesis as explained above, and both types of estimates are routinely rounded to

whole numbers. Some researchers do not even attempt to estimate a boundary between bands,

instead giving a whole number frequency as the upper endpoint of one band and the next

consecutive whole number as the lower endpoint of the next band. Estimates of means and

variances of both neuron delay times and EEG frequency bands are apparently nonexistent.

4.2.2.2. A simple test of the cascaded oscillators hypothesis from sampling data

A simple, rigorous test of the cascaded oscillators hypothesis is possible. As stated in the

introduction, all predicted EEG phenomena follow from the main implication that the EEG bands

and cascaded oscillators have the same distributions of frequencies. This implication can be

tested statistically with random samples and the distribution relations of equations 5. As

discussed previously, neuron delay times should be approximately normally distributed by the

central limit theorem. This implies cascaded oscillator periods are also approximately normally

distributed. A normal distribution is completely determined by its mean and variance. So it

remains to be shown that EEG band periods are normally distributed and that EEG band periods

and oscillator periods have equal means and variances.

The neuron delay time parameters μ_d and σ_d can be estimated from a random sample of

neuron delay times. These estimates can be used to estimate the oscillator period distribution

parameters μ_i and σ_i from equations 5. The mean and variance of the periods of one or more

EEG bands can be estimated from a random sample of EEG periods (or frequencies). With

standard tests for equal means and variances, the EEG estimates can be compared to the

oscillator estimates of μ_i and σ_i. The EEG sampling data can also be used to test EEG band

periods for normal distributions. If the application of the central limit theorem to neuron delay

times may be questionable, neuron delay times can also be tested for a normal distribution with

the neuron delay time sampling data.

4.2.2.3. Caveats

Because the oscillators' frequency ranges overlap (Fig 5), the band to which an observed

EEG period or frequency is assigned should be determined by the observed behavioral and

mental state that defines a band, not by predetermined endpoints of bands. If EEG sampling data

are measured in frequencies, they must be converted to periods before computing the sample

mean and variance. (The period of the sample mean of frequencies is not the same as the sample

mean of periods.) Sampling data should not be rounded to whole numbers. In using equations 5

to find the estimated oscillator parameters, recall that the value of n must be the minimum of 3.

Sampling data for neuron delay times and EEG periods (or frequencies), or even estimates of

means and variances, may already be available in some database.

Although it is possible that EEG frequencies are produced by cascaded oscillators with

initial oscillators that are made up of specialized neurons whose delay times are different from

the general population of neurons, this appears to be unlikely. Fig 5 shows the EEG frequency

distributions are at least close to the values predicted by the general description of the range of

neuron delay times that was used here to estimate oscillator neuron delay time parameters.

Moreover, neurons in general and initial oscillator neurons in particular may have both evolved

under selective pressure to function as fast as possible.

5. Acknowledgements

The simulation was done with MS Excel. Network diagrams were created with

CircuitLab and MS Paint. Graphs were created with MS Excel, Converge 10.0, and MS Paint.

Predicted probabilities of large EEG frequencies were approximated with Converge 10.0. The

author would like to thank Duncan Watson, Arturo Tozzi, David Garmire, Paul Higashi, Anna

Yoder Higashi, Sheila Yoder, and especially Ernest Greene and David Burress for their support

and many helpful comments.

6. References

1. Yoder L. Relative absorption model of color vision. Color Research & Application. 2005 Aug 1;30(4):252-64.

2. Yoder L. Explicit Logic Circuits Discriminate Neural States. PloS one. 2009 Jan 7;4(1):e4154.

3. Yoder L. Explicit logic circuits predict local properties of the neocortex's physiology and anatomy. PloS one. 2010 Feb 16;5(2):e9227.

4. Yoder L. Neural Flip-Flops I: Short-Term Memory. bioRxiv. 2020 May 24:403196.

5. Seung S. Connectome: How the brain's wiring makes us who we are. HMH; 2012 Feb 7.

6. Schuman CD, Potok TE, Patton RM, Birdwell JD, Dean ME, Rose GS, Plank JS. A survey of neuromorphic computing and neural networks in hardware. arXiv preprint arXiv:1705.06963. 2017 May 19.

7. Fuster JM, Alexander GE. Neuron activity related to short-term memory. Science. 1971 Aug 13;173(3997):652-4.

8. Funahashi S, Bruce CJ, Goldman-Rakic PS. Mnemonic coding of visual space in the monkey's dorsolateral prefrontal cortex. Journal of neurophysiology. 1989 Feb 1;61(2):331-49.

9. Lundqvist M, Herman P, Miller EK. Working memory: delay activity, yes! persistent activity? Maybe not. Journal of Neuroscience. 2018 Aug 8;38(32):7013-9.

10. Constantinidis C, Funahashi S, Lee D, Murray JD, Qi XL, Wang M, Arnsten AF. Persistent spiking activity underlies working memory. Journal of Neuroscience. 2018 Aug 8;38(32):7020-8.

11. Posthuma D, Neale MC, Boomsma DI, De Geus EJ. Are smarter brains running faster?
Heritability of alpha peak frequency, IQ, and their interrelation. Behavior genetics. 2001 Nov
1;31(6):567-79.

12. Johnson L, Lubin A, Naitoh P, Nute C, Austin M. Spectral analysis of the EEG of dominant
and non-dominant alpha subjects during waking and sleeping. Electroencephalography and
Clinical Neurophysiology. 1969 Apr 30;26(4):361-70.

13. Baumgarten TJ, Oeltzschner G, Hoogenboom N, Wittsack HJ, Schnitzler A, Lange J. Beta
Peak Frequencies at Rest Correlate with Endogenous GABA+/Cr Concentrations in
Sensorimotor Cortex Areas. PloS one. 2016 Jun 3;11(6):e0156829.

14. Voss U, Holzmann R, Tuin I, Hobson JA. Lucid dreaming: a state of consciousness with
features of both waking and non-lucid dreaming. Sleep. 2009 Sep 1;32(9):1191-200.

15. Glassman RB. Hypothesized neural dynamics of working memory: Several chunks might be
marked simultaneously by harmonic frequencies within an octave band of brain waves. Brain
Research Bulletin. 1999 Sep 15;50(2):77-93.

16. Mably AJ, Colgin LL. Gamma oscillations in cognitive disorders. Current opinion in
neurobiology. 2018 Oct 1;52:182-7.

17. Uhlhaas PJ, Haenschel C, Nikolić D, Singer W. The role of oscillations and synchrony in
cortical networks and their putative relevance for the pathophysiology of schizophrenia.
Schizophrenia bulletin. 2008 Sep 1;34(5):927-43.

18. Campbell N, Reece J, Taylor M, Simon E. Biology: concepts & connections.
Pearson/Benjamin Cummings. San Francisco. 2006.

19. Weisbrod D, Khun SH, Bueno H, Peretz A, Attali B. Mechanisms underlying the cardiac

pacemaker: the role of SK4 calcium-activated potassium channels. Acta Pharmacologica

Sinica. 2016 Jan;37(1):82.

20. Kuramoto Y. Chemical oscillations, waves, and turbulence. Springer Science & Business

Media; 2012 Dec 6.

21. Okun M, Lampl I. Balance of excitation and inhibition. Scholarpedia. 2009 Aug

16;4(8):7467.

22. Kandel E, Schwartz J, Jessell T, Siegelbaum SA, Hudspeth AJ. Principles of neural science.

McGraw-Hill Professional. New York, NY. 2013:160, 178, 1119.

23. Eggermann E, Bayer L, Serafin M, Saint-Mleux B, Bernheim L, Machard D, Jones BE,

Mühlethaler M. The wake-promoting hypocretin–orexin neurons are in an intrinsic state of

membrane depolarization. Journal of Neuroscience. 2003 Mar 1;23(5):1557-62.

24. Adhikari BM, Prasad A, Dhamala M. Time-delay-induced phase-transition to synchrony in

coupled bursting neurons. Chaos: An Interdisciplinary Journal of Nonlinear Science. 2011

Jun;21(2):023116.

25. Katz B, Miledi R. The measurement of synaptic delay, and the time course of acetylcholine

release at the neuromuscular junction. Proceedings of the Royal Society of London B:

Biological Sciences. 1965 Feb 16;161(985):483-95.

26. Hozo SP, Djulbegovic B, Hozo I. Estimating the mean and variance from the median, range,

and the size of a sample. BMC Medical Research Methodology. 2005;5:13.

27. "System and method of measuring and correlating human physiological characteristics such

as brainwave frequency." U.S. Patent 3,875,930, issued April 8, 1975.

28. Nunez PL. A study of origins of the time dependencies of scalp EEG: I-theoretical basis.

IEEE Transactions on Biomedical Engineering. 1981 Mar(3):271-80.

29. Nunez PL. A study of origins of the time dependencies of scalp EEG: II-experimental

support of theory. IEEE Transactions on Biomedical Engineering. 1981 Mar(3):281-8.

30. Teplan M. Fundamentals of EEG measurement. Measurement science review. 2002;2(2):1-1.

31. David O, Friston KJ. A neural mass model for MEG/EEG:: coupling and neuronal dynamics.

NeuroImage. 2003 Nov 30;20(3):1743-55.

32. Ergenoglu T, Demiralp T, Bayraktaroglu Z, Ergen M, Beydagi H, Uresin Y. Alpha rhythm of

the EEG modulates visual detection performance in humans. Cognitive Brain Research. 2004

Aug 31;20(3):376-83.

33. Mormann F, Fell J, Axmacher N, Weber B, Lehnertz K, Elger CE, Fernández G.

Phase/amplitude reset and theta–gamma interaction in the human medial temporal lobe

during a continuous word recognition memory task. Hippocampus. 2005 Jan 1;15(7):890-

900.

34. König T, Prichep L, Dierks T, Hubl D, Wahlund LO, John ER, Jelic V. Decreased EEG

synchronization in Alzheimer's disease and mild cognitive impairment. Neurobiology of

aging. 2005 Feb 28;26(2):165-71.

35. Flagg RH, Barham WB, Stokes DA, Kotapish GE, inventors; Flagg Rodger H, Barham W

Bruce, assignee. Method and apparatus for magnetic brain wave stimulation. United States

patent US 6,978,179. 2005 Dec 20.

36. Herrmann CS, Demiralp T. Human EEG gamma oscillations in neuropsychiatric disorders.

Clinical neurophysiology. 2005 Dec 31;116(12):2719-33.

37. Palva S, Palva JM. New vistas for α-frequency band oscillations. Trends in neurosciences.

2007 Apr 30;30(4):150-8.

38. Jensen O, Colgin LL. Cross-frequency coupling between neuronal oscillations. Trends in

cognitive sciences. 2007 Jul 31;11(7):267-9.

39. Gireesh ED, Plenz D. Neuronal avalanches organize as nested theta-and beta/gamma-

oscillations during development of cortical layer 2/3. Proceedings of the National Academy

of Sciences. 2008 May 27;105(21):7576-81.

40. Lagopoulos J, Xu J, Rasmussen I, Vik A, Malhi GS, Eliassen CF, Arntsen IE, Sæther JG,

Hollup S, Holen A, Davanger S. Increased theta and alpha EEG activity during nondirective

meditation. The Journal of Alternative and Complementary Medicine. 2009 Nov

1;15(11):1187-92.

41. Poil SS, Hardstone R, Mansvelder HD, Linkenkaer-Hansen K. Critical-state dynamics of

avalanches and oscillations jointly emerge from balanced excitation/inhibition in neuronal

networks. Journal of Neuroscience. 2012 Jul 18;32(29):9817-23.

42. Thut G, Miniussi C, Gross J. The functional importance of rhythmic activity in the brain.

Current Biology. 2012 Aug 21;22(16):R658-63.

43. McConnell GC, So RQ, Hilliard JD, Lopomo P, Grill WM. Effective deep brain stimulation

suppresses low-frequency network oscillations in the basal ganglia by regularizing neural

firing patterns. Journal of Neuroscience. 2012 Nov 7;32(45):15657-68.

44. Basar E, Basar-Eroglu C, Guntekin B, Yener GG. Brain's alpha, beta, gamma, delta, and

theta oscillations in neuropsychiatric diseases: proposal for biomarker strategies. Suppl Clin

Neurophysiol. 2013;62(1).

45. Hughes JR. Responses from the visual cortex of unanesthetized monkeys. In International
review of neurobiology 1964 Jan 1 (Vol. 7, pp. 99-152). Academic Press.

46. Gold I. Does 40-Hz oscillation play a role in visual consciousness? Consciousness and
cognition. 1999 Jun 1;8(2):186-95.

47. Alekseichuk I, Turi Z, de Lara GA, Antal A, Paulus W. Spatial working memory in humans
depends on theta and high gamma synchronization in the prefrontal cortex. Current Biology.
2016 Jun 20;26(12):1513-21.