Article type: Research Article

Visualization of Phase-Amplitude Coupling Using Rhythmic High-Frequency Activity

Hiroaki Hashimoto. M.D., Ph.D.[1,2,3]*, Hui Ming Khoo. M.D., Ph.D.[4], Takufumi Yanagisawa. M.D., Ph.D.[4], Naoki Tani. M.D., Ph.D.[4], Satoru Oshino. M.D., Ph.D.[4], Haruhiko Kishima. M.D., Ph.D.[4], Masayuki Hirata. M.D., Ph.D.[1,3,4]

[1]   Department of Neurological Diagnosis and Restoration, Graduate School of Medicine, Osaka University, Suita 565-0871, Japan

[2]   Department of Neurosurgery, Otemae Hospital, Osaka, 540-0008, Japan

[3]   Endowed Research Department of Clinical Neuroengineering, Global Center for Medical Engineering and Informatics, Osaka University, Suita 565-0871, Japan

[4]   Department of Neurosurgery, Graduate School of Medicine, Osaka University, Suita 565-0871, Japan

* Correspondence:

Hiroaki Hashimoto, M.D., Ph.D.

Invited Researcher, Department of Neurological Diagnosis and Restoration, Graduate School of Medicine, Osaka University, Yamadaoka 2-2, Suita, Osaka, Japan

Tel.: +81-6-6210-8429

Fax: +81-6-6210-8430

E-mail: yousyou0720@gmail.com, h-hashimoto1986@otemae.gr.jp

Running title: Phase-amplitude coupling visualization

Number of characters in the title: 80

Number of characters in the running head: 38

Number of words in the abstract: 237

Number of words in the introduction: 379

Number of words in the discussion: 790

Number of words in the body of the manuscript: 4494

Number of color figures: 4

Number of tables: 1

Number of supplementary videos: 3

ORCID

Hiroaki Hashimoto: https://orcid.org/0000-0003-4057-4466

Hui Ming Khoo: https://orcid.org/0000-0002-4039-0520

Masayuki Hirata: https://orcid.org/0000-0002-9813-6728

Abstract

High-frequency activities (HFAs) and phase-amplitude coupling (PAC) are gaining attention as key neurophysiological biomarkers for studying human epilepsy. We aimed to clarify and visualize how HFAs are modulated by the phase of low-frequency bands during seizures. We used intracranial electrodes to record seizures of symptomatic focal epilepsy (15 seizures in seven patients). Ripples (80–250 Hz), as representative of HFAs, were evaluated along with PAC. The synchronization index (SI), representing PAC, was used to analyze the coupling between the amplitude of ripples and the phase of lower frequencies. The main low frequency band modulating ictal-ripple activities was the θ band (48 Hz), and after completion of ictal-ripple burst, δ (1–4 Hz)-ripple PAC occurred. We created a video in which the intracranial electrode contacts were represented by circles that were scaled linearly to the power changes of ripple. The video showed that fluctuation of the diameter of these circles indicated the rhythmic changes during significant high values of θ-ripple PAC. Moreover, clonic seizures were observed when values of δ-ripple PAC were significantly high. We inferred that ripple activities occurring during seizure evolution were modulated by θ rhythm, and ripple activities involved in clonic seizures were modulated by δ rhythm. In addition, we concluded that rhythmic circles' fluctuation presented in the video represents the PAC phenomenon. Our video is thus a useful tool for understanding how ripple activity is modulated by the low-frequency phase in relation with PAC.

Key Words: video-recorded seizures, phase-amplitude coupling, theta band, high-frequency, intracranial EEG

Introduction

Intracranial electroencephalograms (iEEG) allow acquisition of wideband waveforms, from slow shift to high-frequency activities (HFAs), at a high signal-to-noise ratio. Direct current (DC) shifts and infraslow activities, which are very slow-frequency components, appear in the seizure onset zone (SOZ) during a seizure [1-4]. HFAs can be physiological, i.e., those recorded during a task [5], or pathological, i.e., those observed during seizures or interictal period in epileptic patients [2, 6, 7]. High frequency oscillations (HFOs) are subgroup of HFAs and isolated oscillations standing out from the background, within the high frequency range usually above 80 Hz. Ictal HFOs occur in the SOZ [8, 9], and HFOs can be further classified into ripples (80–250 Hz) and fast ripples (250–500 Hz) [9]. Previous study reported that HFAs were useful for detection of seizures[10].

The amplitude of HFAs is modulated by the low-frequency oscillation phase [11]. Physiologically, this phase-amplitude coupling (PAC) has various functional roles in cortical processing such as motor execution [12] and sensory processing [13]. In the ictal state, PAC achieved high values in the SOZ [14, 15]. Moreover, it is reported that PAC between the infraslow phase and HFAs amplitude preceded the seizure onset (SO) [16].

PAC achieves high values in the SOZ during seizures; however, there is no consensus about the main low frequency band that modulates the amplitude of HFAs. Several low frequency bands have been reported like δ [15, 17, 18], θ [14], α [14], and β [19] bands. Furthermore, whereas dynamic HFAs changes in the ictal state have been visualized using topographic videos [6], dynamic PAC changes have not been visualized. The purpose of this study is twofold. One is to clearly identify the main low frequency band contributing to PAC during seizures. The other is to visualize the PAC phenomenon. Using the iEEG, we collected data from 15 seizures in seven patients with medically refractory focal epilepsy. First, we evaluated dynamic changes and characteristics of PAC from pre-ictal to late-ictal. Next, we created a video for each patient in which circles, corresponding to electrodes, change their diameters that correlate linearly with

the power of HFAs represented by ripples (Video S1–3). We hypothesized that PAC can be visualized using dynamic ripple power changes modulated by a low-frequency band.

Materials and Methods

Subjects

We included seven patients with drug-resistant focal epilepsy who underwent intracranial electrodes placement for presurgical invasive EEG study (six males and one female, 15–47 years of age, mean age: 26 ± 12.1 years) (Table 1) who were admitted to Osaka University Hospital from July 2018 to July 2019. This retrospective study was approved by the Ethics Committee of Osaka University Hospital (Suita, Japan) (approval no., 19193). Informed consent was obtained by the opt-out method on our center's website.

Intracranial electrodes and their location

Data on iEEG were acquired using a combination of subdural grids (10, 20, or 30 contacts), strips (four or six contacts), and depth electrodes (six contacts) (Unique Medical Co. Ltd., Tokyo, Japan), placed using conventional craniotomy. The diameter of each contact was 3 or 5 mm, and the inter-contact distance was 5, 7, or 10 mm for grid and strip electrodes. The diameter was 1.5 mm, and the inter-contact distance was 5 mm for depth electrodes. Three-dimensional (3D) brain renderings were created using FreeSurfer (https://surfer.nmr.mgh.harvard.edu) with the preoperative MRI images. Using Brainstorm (http://neuroimage.usc.edu/brainstorm/), the post-implantation CT images were overlaid onto the 3D brain renderings to obtain the position of contact for each electrode in the Montreal Neurological Institute coordinates system.

Data acquisition and preprocessing

Signals from the iEEG were acquired at a sampling rate of 1 kHz and a time constant of 10 s, using a 128-channel digital EEG system (EEG 2000; Nihon Kohden Corporation, Tokyo, Japan). The raw signals were then preprocessed using a low-pass filter at 333 Hz (to prevent aliasing) and a 60-Hz notch filter (to eliminate the AC line artifact) using the BESA Research 6.0 software (BESA GmbH, Grafelfing, Germany). Artifactual signals from electrodes were excluded from further analyses. For the purpose of signal analysis, iEEG signal of each electrode contact was digitally re-referenced to a common average of all electrode contacts in each patient. The digital EEG system was equipped with a set-up for simultaneous video capture in which the video was acquired at 30 frames per second (fps).

All the subsequent signal analysis was performed using MATLAB R2019b (MathWorks, Natick, MA, USA). Our iEEG data were saved every 60 min and thus each iEEG dataset contains a 60-min signal. A bandpass filter using a two-way least-squares finite impulse response filter (pop_eegfiltnew.m from the EEGLAB toolbox, https://sccn.ucsd.edu/eeglab/index.php) was applied to the preprocessed signals of the whole 60-min data to prevent edge-effect artifacts, before we extract iEEG segments for subsequent signal analysis.

High frequency activity power changes

The SO and the corresponding electrode contact (seizure onset electrode contact, SOEC) were determined by visual inspections of iEEG signals [20]. To simplify the analysis, we randomly selected one electrode contact that fulfil the condition that it was commonly involved at seizure onset across all seizures (for patients with more than one seizure). We analyzed the iEEG data acquired 5 minutes before and after the SO for each recorded seizure. We used the ripple band (80–250 Hz) to represent HFA. The time series of the HFA power on each contact was constructed every second from the preprocessed iEEG signal by using a band-pass filter (80–250 Hz) in combination with the Hilbert transformation [21]. The HFA power was then

normalized by dividing the power at each second by the average HFA power of the initial 60 s.

PAC analyses

We used synchronization index (SI) [21] to measure the strength of cross-frequency coupling between the amplitude of ripple and the phases of lower frequency bands, which include δ (1–4 Hz), θ (4–8 Hz), α (8–13 Hz), and β (13–30 Hz).

Hilbert transformation was performed on the bandpass filtered signals to obtain the complex-valued analytic signals of each frequency band, $Z_\omega(t)$ (ω means the frequency band). For each frequency band, the amplitude, $A_\omega(t)$, and phase, $\varphi_\omega(t)$, were calculated from the complex-valued signals using Equation 1.

$$Z_\omega (t) = A_\omega (t) \cdot \exp(i\, \phi_\omega (t)) \quad (1)$$

The phase of each lower frequency band, $\varphi_l(t)$, was obtained from the angle of the Hilbert transform of the bandpass filtered signal.

To obtain the surrogate signal that represent the time series of the ripple band amplitude, the amplitude of ripple band was first extracted using the squared magnitude of $Z_\gamma(t)$, the analytic signal calculated using the Hilbert transformation ($P_\gamma(t) = \text{real } [Z_\gamma (t)]^2 + \text{image } [Z_\gamma (t)]^2$); then the phase of this amplitude was computed using Hilbert transformation ($\varphi_\gamma(t) = \arctan (\text{image } [Z (P_\gamma(t))]/\text{real}[Z(P_\gamma(t))])$).

SI was calculated using Equation 2.

$$SI = \frac{1}{n} \times \sum_{t=1}^{n} e^i [\, \phi_l(t) - \phi_\gamma(t)] \quad (2)$$

We calculated SI for every 1-s time window, which sequentially shifted every 33 ms from 5 minutes before to 5 minutes after the SO. n is the number of time points within each 1-s time window. SI is a complex number; therefore, we used the magnitude of SI, referred to as SIm. SIm varies between 0 and 1, with 0 indicating that phases are completely desynchronized and 1 indicating that phases are perfectly synchronized.

Correlation analysis related to PAC

We computed the correlation between SIm and ripple normalized power using linear regression model for each electrode contact (total 1189 electrode contacts). We analyzed the correlation between SIm and ripple normalized power in the following three states in relation to seizure onset: pre-ictal (from -1.5 to 0 min before the SO), ictal (from 0 to 1.5 min after the SO), and late-ictal (from 1.5 to 3.0 min after the SO) states. Pearson correlation coefficients were calculated.

Phase-conditioned analysis

To identify the lower frequency phase to which ripple power was coupled, we computed the average oscillation of each lower frequency band on the SOEC across all seizures (15 seizures) and the average ripple normalized power on the SOEC. The phases of δ and θ band, were divided into 12 intervals of 30° without overlaps: $0° \pm 15°$, $30° \pm 15°$, …, $300° \pm 15°$, and $330° \pm 15°$, resulting in 12 phase bins. The reason for choosing these two bands is described in the result section. For each state (pre-ictal, ictal, and late-ictal), the ripple normalized power on the SOEC was averaged within each phase bin. Using signal from the SOEC instead of the average of all electrode contacts avoids averaging from obscuring the characteristics-of-interest.

Visualization of synchronized multimodal data

Multimodal data, including iEEG waveform, ripple normalized power, SIm, and video images, were synchronized and simultaneously displayed. To construct a power distribution map, we calculated the power of ripple using the periodogram. The period of 10 seconds before SO was defined as the baseline, and the baseline ripple power was obtained from the baseline segment. We calculated the ripple power within a 500-ms sequential time window every 33 ms (30 fps). The ripple power ratio was calculated by dividing the ripple power of the 500-ms time window

with baseline ripple power. We plotted red circles on the brain image to indicate the electrode locations, and the diameters were scaled linearly with ripple power ratio.

Statistics

The ripple normalized power and SIm values were averaged across all electrode contacts in each seizure, and then averaged ripple normalized power and averaged SIm values were averaged across all seizures (Fig. 1A, 1B, and 1C). SIm values were normalized using SIm values calculated from the data acquired five minutes before SO to allow comparison between different low frequency bands (Fig. 1B). In order to know if there is a difference between frequency band with the highest SIm and the others, we used single-sided Wilcoxon signed-rank test for pairwise comparison between frequency bands and Bonferroni correction for multiple comparisons (Fig. 1A, 1B, and 1D). To define the change of the power and SIm (Fig. 1C) compared to the background (the initial 10-s data), we used a permutation test for the comparison between the initial 10-s data and the next sequential 10-s data [22] and a familywise error (FWE)-corrected threshold for multiple comparisons. Each permutation test produces a set of differences between the initial 10-s data and the next sequential 10-s data. The maximum value of the differences from each permutation test were stored. The values at 95% of the distribution of these maximum values were taken as the FWE-corrected threshold. The values above the FWE-corrected threshold are statistically significant [23].

To assess the significant change in SIm, we used the boot-strapping technique (Fig. 2–4, and Video S1–S3). First, the phase of ripple power time series was shifted in time by a random amount. Then, this phase-shifted ripple power time series was used to calculate a SIm value for the purpose of bootstrapping (SImb). For each pair of ripple power and a lower frequency band amplitude, this procedure was repeated 1000 times to create the distribution of SImb [21]. To correct for multiple comparisons, we used the FWE-corrected threshold (95%) [23].

Data availability

All data that were generated by or analyzed in this study are available from the corresponding authors upon reasonable request and after additional ethics approvals regarding the data provision to individual institutions.

Results

Profile of ripple power and PAC changes related to seizures

We compared ripple normalized power between the pre-ictal and the ictal states. The ripple normalized power during seizures (ictal state) were significantly larger than that before seizures (pre-ictal state) (single-sided Wilcoxon signed-rank, $P = 3.1 \times 10^{-5}$) (Fig. 1A). Averaged time of seizures is 125.73 ± 55.1 s, and times of each seizure are shown in Table 1.

Among all seizures analyzed, SOEC that was determined by conventional visual inspection were concordant with the preceding ripple electrode contact (PREC, see case studies below) that was determined by ripple activities in 12/15 seizures (80%). When focusing on only focal to bilateral tonic-clonic seizures (FBTCS), SOEC matched PREC in all seizures (Table 1).

We compared SIm values calculated from the coupling between ripple band activity and each lower frequency band during the burst of ripple power within the seizure state. The normalized SIm of ripple-θ was the highest among all (single-sided Wilcoxon signed-rank with Bonferroni correction, θ-δ: corrected $P = 3.0 \times 10^{-3}$, θ-α: corrected $P = 1.3 \times 10^{-2}$, θ-β: corrected $P = 2.3 \times 10^{-3}$) (Fig. 1B). The main low frequency band coupled with ripple was the δ band in 2/15 seizures (13%), θ band in 12/15 seizures (80%), and α band in 1/15 seizures (7%) (Table 1).

Temporal profile of ripple power and PAC changes

Dynamic changes of ripple normalized power and PAC strength (represented by SIm value) between ripple and each lower frequency band from 5 min before to 5 min after SO are shown in Fig. 1C. A significant burst of ripple power was observed after SO, which was accompanied

by two different profiles of PAC with the lower frequency bands: (1) PAC changes with a peak (θ-, α-, and β-ripple coupling) and (2) PAC changes with a gradual increase and a plateau (δ-ripple coupling). For those with the first profile, the PAC for θ band after SO were the higher than those for α and β bands, which were also reflected in their differences shown in Fig. 1B. For the second profile, the PAC for δ band increased gradually and reached its maximum after ripple power burst, which was not reflected in the difference shown in Fig. 1B that was obtained from the data during the burst of ripple power within the seizure state. We focused on PAC for θ band (representing the first profile) and δ band (the second profile) in the following analyses. There was no significant difference between the time taken (since SO) to attain maximum ripple power (77.6 ± 38.9 s) and maximum θ PAC (73.7 ± 41.7 s); however, the time taken to achieve maximum value of δ PAC (117.7 ± 70.9 s) was significantly more than that for both ripple power and θ PAC (single-sided Wilcoxon signed-rank with Bonferroni correction, ripple power and δ PAC, corrected P = 1.6×10^{-3}, θ PAC and δ PAC, corrected P = 8.2×10^{-4}) (Fig. 1D). A time lag between θ and δ PAC was observed in 11/15 seizures (73.3%) (Table 1). The peak of δ PAC tends to occur later during the clonic phase following the tonic phase of the FBTCSs. One patient (P5) had FBTCSs without the clonic phase; therefore, the time lag between θ and δ PAC might not have been observed.

Due to the differences observed between PAC for θ and δ bands, we sought to clarify the differences in the following analyses.

Correlation between ripple normalized power and SIm

The correlation of ripple normalized power with the SIm of θ band was positive in all three states (pre-ictal, ictal and late-ictal), in which a statistical significance was reached in the ictal state. In contrast, the correlation with the SIm of δ band was positive in the pre- and late-ictal states and negative in the ictal state, in which a statistical significance was reached in all three states (Fig. 1E).

Phase-tuning ripple power

The oscillation of δ and θ bands showed a trough at 180° in all pre-ictal, ictal and late-ictal states (Fig. 1F). In the ictal state, in which θ-SIm increased (Fig. 1C), ripple normalized power peaked at the trough of the θ oscillation but not the δ oscillation (Fig. 1F). In the late-ictal state, in which δ-SIm increased (Fig. 1C), ripple normalized power peaked at the trough of the δ oscillation (Fig. 1F).

Case studies

During seizures, the ripple power increased and was coupled with the θ phase. After completion of ripple power burst, δ-ripple coupling occurred. We show the synchronized multimodal data including iEEG waveforms, ripple normalized power, SIm, ripple power distribution map, and video in the figure and videos of three illustrative cases. In Fig. 2, 3, and 4, significant θ-ripple SIm and representative electrodes are shown. In supplementary videos (Video S1–3), significant δ- and θ-ripple SIm and all electrodes are shown.

Case #1 (P1-S1 in Table 1)

A 28-year-old right-handed male patient with neither known history of perinatal and developmental problems, nor of febrile seizures, began suffering from seizures at the age of 25 years. The intractable seizures were focal impaired awareness seizures (FIAS), characterized by an aura of palpitation, followed by motionless staring and oral automatisms. These seizures were weekly and were sometimes followed by FBTCS. Interictal scalp EEG recorded spike-wave complexes over the right temporal region. Ictal scalp EEG could not be recorded. We placed intracranial electrodes with a total of 96 contacts, which included 24 contacts from 3 depth electrodes (A1–A24) that were inserted into the right medial temporal lobe, and 72 contacts from grid or strip electrodes in the right hemisphere (Fig. 2A). MRI images showed a

cystic lesion in the right mesial temporal lobe (MTL) (Fig. 2B).

We captured electroclinical seizures consisting of FIAS, followed by FBTCS (Fig. 2C and Video S1). Contact A2 on the depth electrode inserted in the right parahippocampal gyrus, showed initial infraslow activities, followed by low-voltage fast waves that changed into high-amplitude fast waves and spread to the other electrodes (Fig. 2D). Ripple power increases also began from A2 and spread to the other electrodes (Fig. 2E and 2G), and in this case, the SOEC was concordant with the PREC (Table 1). Significant θ-ripple SIm values were observed in the electrodes in which ripple power increased (Fig. 2F), and after that, significant δ-ripple SIm values were observed (Video S1). No motor symptom was observed until ripple power burst had propagated to the cortical surface along the Sylvian fissure. Clonic seizures were observed when δ-ripple SIm reached statistical significance. The time lag between θ and δ PAC was observed in this case. Ripple-band power (represented by the size of the red circle) fluctuated rhythmically at certain rhythms when θ-Sim reached statistical significance and this relationship was also observed for δ-band (Video S1).

We resected the right mesial temporal lobe including the cystic lesion and the parahippocampal gyrus. Histopathology revealed a dysembryoplastic neuroepithelial tumor. He was seizure-free at the 12-month follow-up.

Case #2 (P4-S2 in Table 1)

A 15-year-old right-handed female patient with neither known history of perinatal and developmental problems, nor of febrile seizures, began suffering from seizures at the age of 10 years. The intractable seizures were FIAS, characterized by motionless staring and oral automatisms. These seizures occurred weekly and were sometimes followed by FBTCS. Interictal scalp EEG recorded spike-wave complexes over the left frontotemporal region. Ictal scalp EEG recorded repetitive small activities from the left temporal region. We placed intracranial electrodes with a total of 72 contacts, which included 24 contacts from depth

electrodes (A1–A24) that were inserted into the left medial temporal lobe, and 48 contacts from grid or strip electrodes in the left hemisphere (Fig. 3A). MRI fluid-attenuated inversion recovery (FLAIR) images showed a high-intensity lesion in the left MTL (Fig. 3B).

We captured electroclinical seizures consisting of head turning to the right, followed by a vocalization, figure of four, and then a bilateral tonic-clonic movements (Fig. 3C and Video S2). Contact A13 on the depth electrodes, which were inserted in the left mesial temporal lesion, showed initial infraslow activities, followed by low-voltage fast waves that changed into high-amplitude fast waves and spread to the other electrodes (Fig 3D). Ripple power increases also began from A13 and propagated to other electrodes (Fig. 3E and 3G), and in this case, the SOEC was concordant with the PREC (Table 1). Significant θ-ripple SIm values were observed in contacts in which ripple power increased (Fig. 3F), and after that, significant δ-ripple SIm values were observed (Video S2). A time lag between θ and δ PAC was observed in this case (Table 1). No motor symptom was observed until ripple power burst had propagated to the cortical surface along the Sylvian fissure. Clonic seizures were observed when the δ-ripple SIm attained statistical significance. Rhythmic ripple-band activities were visualized in the power distribution map when the values of SIm were significantly high (Video S2).

We performed a left selective amygdalo-hippocampectomy that included the FLAIR high lesion. Histopathology revealed hippocampal sclerosis. She was seizure-free at the 12-month follow-up.

Case #3 (P5-S2 in Table 1)

A 15-year-old right-handed male patient with neither known history of perinatal and developmental problems, nor of febrile seizures, began suffering from seizures at the age of 13 years. The intractable seizures were focal aware seizure, characterized by blindness. These seizures were weekly and were sometimes followed by FBTCS. Interictal scalp EEG recorded spike-wave complexes over the right temporo-occipital region. Ictal scalp EEG recorded 8 Hz

rhythmic activities from the right occipital. We placed intracranial electrodes with a total of 62 contacts, which included 12 contacts from 3 depth electrodes (A1–A12) that were inserted around the right occipital lesion, and 50 contacts from grid or strip electrodes in the right hemisphere (Fig. 4A). MRI FLAIR images showed a high-intensity lesion in the right occipital lobe (Fig. 4B).

We captured electroclinical seizures consisting of his head turning to the left, followed by bilateral lower extremities stereotypies (FBTCS) (Fig. 4C and Video S3). The A32 and A37 electrodes, which were placed over the occipital lesion, showed initial infraslow activities, followed by low-voltage fast waves that changed into high-amplitude fast waves (Fig 4D). Ripple power increases also began from A32 and A37 electrodes and propagated to the other electrodes (Fig. 4E and 4G), and in this case, the SOEC was concordant with the PREC (Table 1). Significant θ-ripple SIm values started to appear in electrodes which were placed over the occipital lesion (Fig. 4F), and at that time, significant δ-ripple SIm values were also observed (Video S3). The time lag between θ and δ PAC was not observed in this case (Table 1). Motor symptom appeared immediately after the initial ripple power increase from the occipital lesion. Rhythmic ripple-band activities were visualized in the power distribution map when the values of SIm were significantly high (Video S3).

We performed a resection surgery of the right occipital lesion. Pathological findings showed diffuse glioma. He was seizure-free at the 12-month follow-up.

Discussion

This study demonstrated that a ripple power burst occurs during seizures, and the phase of θ band modulates ripple power involved in seizures. Our videos showed that when ripple power increased, the individual ripple power of each electrode contact (corresponded to the size of each red circle in the video) changes rhythmically. During such rhythmic fluctuation in the circles' size, a significant θ-ripple PAC was observed. Therefore, we inferred that the rhythmic

fluctuation in the circles' size (in the video) was modulated by the θ rhythm and this fluctuation represented the θ-ripple PAC phenomenon. Our video is a useful tool for understanding visually and comprehensively the PAC phenomenon related to ripple activities during seizures.

How HFAs were propagated during seizures has been visualized by topographic videos [6, 24], however, PAC changes involved in seizures have not been visualized. In our videos, the diameters of each circle that represents an implanted electrode contact changed with ripple power, and the videos also demonstrated the propagation of HFAs by dynamic changes of circles' diameters. Moreover, the rhythmic fluctuations of the diameter were observed in each contact. When δ- or θ-ripple PAC significantly increased, the rhythmic fluctuation of the circles' diameter became especially obvious. We inferred that this rhythmic fluctuation of the circles' diameter was tuned at δ- or θ rhythm, and concluded that this rhythmic fluctuation enabled the visualization of the PAC phenomenon.

HFAs have been observed during seizures [24, 25] and HFOs are suggested as useful biomarkers for detection of the SOZ [26, 27]. In this study, significant increase in ripple power was observed during seizures, and PREC which showed preceding ripple activities were demonstrated (Fig. 2E, 3E, and 4E, and supplementary videos). The SOEC was conventionally determined by visual inspection [20], and we demonstrated that in FBTCS, the SOECs were concordant with the PRECs. Therefore, we thought that ripple activities were useful for detection of the SOZ.

In line with a previous study [14], our study demonstrated that θ band was the main low frequency band modulating ictal-ripple activities and α- and β-ripple PAC showed the same tendency as the θ-ripple PAC with a weaker PAC though. Moreover, it is reported that coupling with θ waves and HFOs well discriminated normal brain regions from SOZ [28]. Therefore, we inferred that ripple activities occurring during early seizure evolution were modulated by θ rhythm. The

occurrence of maximal ripple power at the trough of the low frequency oscillation was concordant with a previous study[14]. In an interictal state, a positive correlation between coupling and ripple amplitude were known[29], and we showed the positive correlation between θ-ripple PAC and ictal-ripple power during the ictal state.

In contrary, we showed newly finding that δ-ripple PAC had a negative correlation with ripple power during ictal-ripple power burst, and increased after ictal-ripple power burst subsided. Coupling between HFAs and δ band were investigated in previous studies associated with epileptic spasm[18] and an interictal state[30]. Our videos brought a new insight that δ-ripple PAC significantly increased during clonic seizures in cases with FBTCSs. We inferred that ripple activities involved during the clonic phase later in seizures were modulated by δ rhythm. Our results suggested that δ- and θ-ripple PAC were caused by different mechanisms, and this explained the time lag between δ- and θ-ripple PAC.

This study had some limitations. Because intracranial EEG electrodes covers only a small portion of the brain, we can never be sure if the intracranial electrodes were placed in the actual SOZ, and thus the activities that we analyzed may not be the actual activities from the SOZ. To limit the effect of this uncertainty, we used the average ripple power and SIm from all electrodes because we could evaluate at least seizure-related changes which were propagated activities from the SOZ not focal activities of the SOZ. All the seizures were recorded after an extensive reduction of antiepileptic drugs, and thus, they might not represent the patients' usual seizures. However, our analysis were independent from this issue because reduction in medication does not affect the morphology of discharges at onset, and duration of contralateral spread [31]. Because this study included only patients with focal epilepsy, our findings may not be generalized to patients with generalized epilepsy.

In conclusion, by analyzing seizure evolution of focal epilepsy using ripple power and PAC, this study revealed that θ band is the main low frequency band modulating ripple power during ictal-ripple burst. The video we created, which the fluctuation in the sizes of circles represent the coupling between ripple power and lower frequency band, helps in the understanding of the PAC phenomenon during seizures. A better understanding in PAC between HFA and lower frequency band could potentially improve the diagnosis and subsequently the treatment of seizures.

Acknowledgements

This study was supported by the Grants-in-Aid for Scientific Research (A) (KAKENHI; grant no., 18H04166) and the Grants-in-Aid for Early-Career Scientists (KAKENHI; grant no., 18K18366), which are funded by the Japan Society for the Promotion of Science (JSPS; Tokyo, Japan).

Author Contributions

H.H. conceived the study, collected the data, created the MATLAB program, analyzed the data, created all figures and the video, and was primarily responsible for writing the manuscript. H.M.K., N.T., S.O., H.K., and M.H. performed the epileptic surgery. All authors clinically cared for and evaluated the patient. H.M.K., T.Y., and M.H. advised H.H. on scientific matters. H.M.K revised the manuscript. H.K. and M.H. supervised this study. All authors have reviewed the manuscript.

Conflict of Interests

None of the authors has any conflict of interest to disclose.

References

1.	Ikeda A, Taki W, Kunieda T, et al. Focal ictal direct current shifts in humanepilepsy as studied by subdural and scalp recording. Brain. 1999;122(5):827-38.

2.	Imamura H, Matsumoto R, Inouchi M, et al. Ictal wideband ECoG: direct comparison between ictal slow shifts and high frequency oscillations. Clinical Neurophysiology. 2011;122(8):1500-4.

3.	Kanazawa K, Matsumoto R, Imamura H, et al. Intracranially recorded ictal direct current shifts may precede high frequency oscillations in human epilepsy. Clinical Neurophysiology. 2015 Jan;126(1):47-59.

4.	Rodin E, Modur P. Ictal intracranial infraslow EEG activity. Clinical neurophysiology. 2008;119(10):2188-200.

5.	Hashimoto H, Hasegawa Y, Araki T, et al. Non-invasive detection of language-related prefrontal high gamma band activity with beamforming MEG. Sci Rep. 2017 Oct 27;7(1):14262.

6.	Akiyama T, Otsubo H, Ochi A, et al. Topographic movie of ictal high-frequency oscillations on the brain surface using subdural EEG in neocortical epilepsy. Epilepsia. 2006 Nov;47(11):1953-7.

7.	Zijlmans M, Jiruska P, Zelmann R, Leijten FS, Jefferys JG, Gotman J. High-frequency oscillations as a new biomarker in epilepsy. Annals of neurology. 2012;71(2):169-78.

8.	Jirsch J, Urrestarazu E, LeVan P, Olivier A, Dubeau F, Gotman J. High-frequency oscillations during human focal seizures. Brain. 2006;129(6):1593-608.

9.	Modur PN, Zhang S, Vitaz TW. Ictal high-frequency oscillations in neocortical epilepsy: implications for seizure localization and surgical resection. Epilepsia. 2011;52(10):1792-801.

10.	Ayoubian L, Lacoma H, Gotman J. Automatic seizure detection in SEEG using high frequency activities in wavelet domain. Medical engineering & physics. 2013;35(3):319-28.

11.	Canolty RT, Edwards E, Dalal SS, et al. High gamma power is phase-locked to theta oscillations in human neocortex. Science. 2006 Sep 15;313(5793):1626-8.

12.	Yanagisawa T, Yamashita O, Hirata M, et al. Regulation of Motor Representation by Phase-Amplitude Coupling in the Sensorimotor Cortex. Journal of Neuroscience. 2012 Oct 31;32(44):15467-75.

13.	Luo H, Poeppel DJN. Phase patterns of neuronal responses reliably discriminate speech in human auditory cortex. 2007;54(6):1001-10.

14.	Ibrahim GM, Wong SM, Anderson RA, et al. Dynamic modulation of epileptic high frequency oscillations by the phase of slower cortical rhythms. Experimental neurology. 2014;251:30-8.

15.	Iimura Y, Jones K, Takada L, et al. Strong coupling between slow oscillations and

wide fast ripples in children with epileptic spasms: Investigation of modulation index and occurrence rate. Epilepsia. 2018;59(3):544-54.

16.   Hashimoto H, Khoo HM, Yanagisawa T, et al. Coupling between infraslow activities and high-frequency oscillations precedes seizure onset. Epilepsia Open. 2020;00(n/a):1–6.

17.   Nonoda Y, Miyakoshi M, Ojeda A, et al. Interictal high-frequency oscillations generated by seizure onset and eloquent areas may be differentially coupled with different slow waves. Clin Neurophysiol. 2016 Jun;127(6):2489-99.

18.   Nariai H, Matsuzaki N, Juhász C, et al. Ictal high-frequency oscillations at 80–200 Hz coupled with delta phase in epileptic spasms. Epilepsia. 2011;52(10):e130-e4.

19.   Edakawa K, Yanagisawa T, Kishima H, et al. Detection of Epileptic Seizures Using Phase-Amplitude Coupling in Intracranial Electroencephalography. Sci Rep-Uk. 2016 May 5;6.

20.   Perucca P, Dubeau F, Gotman J. Intracranial electroencephalographic seizure-onset patterns: effect of underlying pathology. Brain. 2014 Jan;137(Pt 1):183-96.

21.   Cohen MX. Assessing transient cross-frequency coupling in EEG data. J Neurosci Methods. 2008 Mar 15;168(2):494-9.

22.   Maris E, Oostenveld R. Nonparametric statistical testing of EEG- and MEG-data. J Neurosci Methods. 2007 Aug 15;164(1):177-90.

23.   Cohen MX. Analyzing neural time series data: theory and practice: MIT press; 2014.

24.   Akiyama T, Chan DW, Go CY, et al. Topographic movie of intracranial ictal high-frequency oscillations with seizure semiology: epileptic network in Jacksonian seizures. Epilepsia. 2011 Jan;52(1):75-83.

25.   Ochi A, Otsubo H, Donner EJ, et al. Dynamic changes of ictal high-frequency oscillations in neocortical epilepsy: using multiple band frequency analysis. Epilepsia. 2007 Feb;48(2):286-96.

26.   Wang S, Wang IZ, Bulacio JC, et al. Ripple classification helps to localize the seizure-onset zone in neocortical epilepsy. Epilepsia. 2013;54(2):370-6.

27.   Wu S, Kunhi Veedu HP, Lhatoo SD, Koubeissi MZ, Miller JP, Lüders HO. Role of ictal baseline shifts and ictal high-frequency oscillations in stereo-electroencephalography analysis of mesial temporal lobe seizures. Epilepsia. 2014;55(5):690-8.

28.   Amiri M, Frauscher B, Gotman J. Interictal coupling of HFO s and slow oscillations predicts the seizure-onset pattern in mesiotemporal lobe epilepsy. Epilepsia. 2019.

29.   Weiss SA, Orosz I, Salamon N, et al. Ripples on spikes show increased phase-amplitude coupling in mesial temporal lobe epilepsy seizure-onset zones. Epilepsia. 2016;57(11):1916-30.

30.   Amiri M, Frauscher B, Gotman J. Phase-amplitude coupling is elevated in deep sleep and in the onset zone of focal epileptic seizures. Frontiers in human neuroscience. 2016;10:387.

31.   So N, Gotman J. Changes in seizure activity following anticonvulsant drug withdrawal. Neurology. 1990;40(3 Part 1):407-.

Figure legends

Figure 1 Characteristics of ripple power and PAC related to seizures. A. The ripple normalized power in ictal state was significantly greater than that in pre-ictal state. B. The normalized SIm during ripple power burst related to seizures achieved the significant highest values in θ band. C. Temporal plot of ripple normalized power, θ-, α-, and β-SIm increased and achieved the peak after the SO (0 min). δ-SIm achieved the peak after completion of ripple power burst. The FWE-corrected threshold is indicated as red dashed line. D. The time taken to achieve the maximum values was compared between ripple normalized power, θ-SIm (PAC), and δ-SIm (PAC). The time of δ PAC was significantly slower. E. During ictal state, significant positive correlation between ripple normalized power and θ-SIm and significant negative correlation between ripple normalized power and δ-SIm were observed. In late-ictal state, significant positive correlation between ripple normalized power and δ-SIm was observed. r: correlation coefficients, c.p: corrected p value with Bonferroni correction. F. Phase tuning δ and θ oscillation showed the trough at 180°. The phase-tuning ripple normalized power showed the peak at the trough with θ phase in ictal state, and with δ phase in late-ictal state. The error bars (EB) in 1A, 1B, and 1D indicate standard deviation. The EB in 1C, and 1F indicate 95%

confidence intervals.

Figure 2 Seizure profile in Patient 1 (P1)-Seizure 1 (S1). A. Depth electrodes A1–6, A7–12, A13–18, and A19–24 were targeting the parahippocampal gyrus, the anterior region of the tumor, the posterior region of the tumor, and the lingual gyrus, respectively. a. anterior; p. posterior; m. medial; l. lateral. B. The location of A2, A7, and A13 in relation the cystic tumor is shown on the T1-weighted MRI. C. Video images showing head turning to the left (71 s) followed by FBTCS (99 s). D. Intracranial electrodes' raw signals. Initial infraslow activities were observed on A2. E. The ripple normalized power started to increase after the SO, from the A2 and propagated to other contacts. F. Significant θ-ripple SIm shows the cluster in contacts in which ripple power increased. Here, 0 s corresponds to the SO determined visually and is indicated as dashed lines. G. Ripple power distribution map. The location of red circles corresponds to each contact's location, and those located within the semitransparent brain were depth electrode contacts. The size of red circles corresponds to ripple power. The ripple power started to increase in A2 (44 s) and propagated to other contacts on the cortex along the Sylvian fissure (71 s), and almost all other regions (99 s).

Figure 3 Seizure profile in P4-S2. A. Depth electrodes A1–24 were inserted into the left mesial temporal lobe. A13 was located in the lesion. B. The high-intensity lesion in the left mesial temporal lobe is shown on FLAIR MRI (red wedge arrows). C. She slept (3 s), growled (47 s), and had tonic seizures (FBTCS) (84 s). D. In A13, initial infraslow activities and low-voltage fast waves were observed. E. The ripple normalized power started to increase after the SO, from A13 and propagated to other contacts. F. Significant θ-ripple SIm shows the cluster in contacts in which ripple power increased. Here, 0 s corresponds to the SO determined visually and is indicated as dashed lines. G. Ripple power distribution map. The location of red circles corresponds to each contact's location, and those located within the semitransparent brain were depth electrode contacts. The size of red circles corresponds to ripple power. The ripple power started to increase in A13 (3 s) and propagated to other contacts on the cortex along the Sylvian fissure (47 s), and to the posterior middle temporal gyrus (84 s).

Figure 4 Seizure profile in P5-S2. A. Depth electrodes A1–12 were targeting around the right

occipital lesion. B. The high-intensity lesion in the right occipital lobe is shown on FLAIR

MRI (red wedge arrows). C. He slept (1 s). His head turned to the left (26 s) followed by

bilateral lower extremities stereotypies (46 s). D. In A32 and A37, initial infraslow activities

and low-voltage fast waves were observed. E. The ripple normalized power started to

increase after the SO, from the A32 and A37 and propagated to other electrodes. F.

Significant θ-ripple SIm shows the cluster in contacts in which ripple power increased. Here,

0 s corresponds to the SO determined visually and is indicated as dashed lines. G. Ripple

power distribution map. The location of red circles corresponds to each contact's location,

and those located within the semitransparent brain were depth electrode contacts. The size of

red circles corresponds to ripple power. The ripple power started to increase in A32 and A37

over the right occipital lesion (1 s) and propagated to the parietal lobe (46 s).

Common Legend for Video

Multimodal data are shown simultaneously, and each file includes video images, ripple (80–250 Hz) power distribution map, iEEG signals, ripple normalized power, θ-ripple PAC (SIm), and δ-ripple PAC (SIm). The video starts 10 s before the SO. In power distribution map, red circles, corresponding to intracranial electrode contacts, were scaled linearly with ripple power changes. The circles in the semitransparent brain indicate depth electrode contacts. The vertical bars indicating current-time are colored red in ECoG signals, white in ripple normalized power, and blue in PAC (SIm). SIm values scaled as black to red are statistically significant values to which the FWE-corrected threshold was applied. All implanted electrode contacts after removal of noisy contacts are shown in the vertical axes.

Legend for Video S1

The seizure in P1-S1 (Table 1) is shown. The rhythmic movement of red circles started from the A2 depth electrode contact, which were inserted into the right parahippocampal gyrus. The rhythmic fluctuations spread to the contacts over the cortex along the Sylvian fissure and that over the temporal base. During significantly high values of SIm, the fluctuation of red circles changed at certain rhythms. We inferred that the rhythmic fluctuations were tuned at θ or δ rhythm, and represented the PAC phenomenon. Time lag between θ and δ SIm were observed. The SO is 11:22:03. The 44 s, 71 s, and 99 s in Fig. 2 correspond to 11:22:47, 11:23:14, and 11:23:42 in respectively.

Legend for Video S2

The seizure P4-S2 (Table 1) were shown. The rhythmic movement of red circles started from the A13 depth electrode contact, which were inserted into the left mesial temporal lesion. The rhythmic movement spread to the contacts over the temporal tip cortex and that over the cortex along the Sylvian fissure and that over the posterior middle temporal gyrus. Time lag between

θ and δ SIm were observed. The SO is 4:15:56. The 3 s, 47 s, and 84 s in Fig. 3 correspond to 4:15:59, 4:16:43, and 4:17:20 in respectively.

Legend for Video S3

The seizure P5-S2 (Table 1) were shown. The rhythmic movement of red circles started from the A32 and 37 surface electrode contacts placed over the right occipital lesion. The rhythmic movement spread to the contacts over the parietal lobe. Time lag between θ and δ SIm were not observed. The SO is 8:28:53. The 1 s, 26 s, and 46 s in Fig. 4 correspond to 8:28:54, 8:29:19, and 8:29:39 in respectively.

PATIENTS NUMBER	SEX	AGE AT SURGERY	LATERALITY	PATHOLOGY	SEIZURE NUMBERS	SEIZURE TYPE	SEIZURE DURATION (S)	PRECEDING HFA	SOEC-PREC CONCORDANCE	COUPLING LOW FREQUENCY BAND	TIME LAG BETWEEN Δ AND Θ COUPLING
P1	Male	28	Right	MTLE DNT	S1	FIAS→FBTCS	154	Yes	concordant	θ	Yes
					S2	FIAS→FBTCS	144	Yes	concordant	θ	Yes
					S3	FIAS→FBTCS	156	Yes	concordant	α	Yes
					S4	FIAS→FBTCS	266	Yes	concordant	θ	Yes
					S5	FIAS→FBTCS	184	Yes	concordant	θ	Yes
P2	Male	47	Right	PLE Glial-cortical tissue with psammoma body-like lesion	S1	FIAS→FBTCS	49	Yes	concordant	δ	Yes
P3	Male	20	Left	OLE*	S1	FIAS→FBTCS	132	Yes	concordant	θ	Yes

						TCS					
P4	Female	15	Left	MTLE, HS	S1	FIAS→FBTCS	102	Yes	concordant	θ	Yes
					S2	FIAS→FBTCS	113	Yes	concordant	θ	Yes
P5	Male	15	Right	OLE Diffuse glioma	S1	FIAS→FBTCS	96	Yes	concordant	θ	No
					S2	FIAS→FBTCS	81	Yes	concordant	θ	No
					S3	FIAS→FBTCS	129	Yes	concordant	θ	No
P6	Male	37	Left	MTLE HS	S1	FAS	149	Yes	discordant	θ	No
P7	Male	20	Right	MTLE FCD	S1	FAS	67	Yes	discordant	θ	Yes
					S2	FAS	64	Yes	discordant	δ	Yes

Table 1 Clinical profile.

SOEC: seizure onset electrode contact, PREC: preceding ripple electrode contact, MTLE: mesial temporal lobe epilepsy, DNT: dysembryoplastic neuroepithelial tumor, PLE: parietal lobe epilepsy, FCD: focal cortical dysplasia, OLE: occipital lobe epilepsy, HS: hippocampal sclerosis, FIAS: focal impaired awareness seizure, FBTCS: focal to bilateral tonic-clonic seizure, FAS: focal aware seizure

*Focal resection surgery had not been performed because the detection of the seizure onset zone was impossible.