Title: **Paired feed-forward excitation with delayed inhibition allows high frequency computations across brain regions**

Abbreviated title: Paired feed-forward excitation/inhibition

Authors: Alex Cao[1,2], Stephen D. Van Hooser[1,2,3]
                1: Department of Biology
                2: Volen Center for Complex Systems
                3: Sloan-Swartz Center for Theoretical Neurobiology
                Brandeis University, Waltham, MA 02454 USA

Corresponding author:
        Stephen D. Van Hooser, vanhoosr@brandeis.edu
        Brandeis University, 415 South St. MS008, Waltham, MA 02453 USA

Impact statement: An archetypical feedforward projection pattern – excitation followed by a delayed inhibitory copy – can play the role of a clock-like trigger, allowing the organized processing of high frequency information within neural circuits.

Number of Pages: 35
Number of Figures and Tables: 8 Figures, 2 Tables
Number of words: Abstract: 150 words (250 max), Impact Statement: 31 words (15-30 suggested) Intro: 500 words (no max), Discussion: 1223 (no max)

Conflicts of interest: The authors declare no competing financial interests.

Acknowledgements: This work was funded by NIH EY022122 (SDV) and NIH DA033463. We thank Andrew Lipnick, whose undergraduate thesis on velocity tuning led us to consider feedforward transmission, Paul Miller for useful suggestions, and members of the Van Hooser lab for comments.

Contributions: AC performed modeling, AC and SDV designed the models, AC and SDV wrote the paper.

Keywords: feed-forward, timing, cross-area computing, striate cortex, area 17, LGN

Abstract

The transmission of high-frequency temporal information across brain regions is critical to perception, but the mechanisms underlying such transmission remain unclear. Long-range projection patterns across brain areas are often comprised of paired feedforward excitation followed closely by delayed inhibition, including the thalamic triad synapse, thalamic projections to cortex, and projections within hippocampus. Previous studies have shown that these joint projections produce a shortened period of depolarization, sharpening the timing window over which the postsynaptic neuron can fire. Here we show that these projections can facilitate the transmission of high-frequency computations even at frequencies that are highly filtered by neuronal membranes. Further, they can coordinate computations across multiple brain areas, even amid ongoing local activity. We suggest that paired feedforward excitation and inhibition provides a hybrid signal – carrying both a value and a clock-like trigger – to allow circuits to be responsive to input whenever it arrives.

Introduction

In digital electronics, computations are synchronized by the presence of a digital clock trigger signal that indicates when each digital component should examine its inputs and perform a computation. The digital clock offers several advantages for digital circuits. First, it allows digital circuits to have short integration times, because the components do not need to consider information that has arrived at its inputs long in the past. Second, this short integration time allows the digital circuit to operate at high temporal speeds (many computations per second). Third, the digital clock allows synchronization of computations across different layers of digital components, because the arrival of related inputs is coordinated by the digital clock.

In neuronal circuits, several properties would seem to make coordinated and precise high-speed computation across layers impossible: the apparent lack of an equivalent clock, the electrical filtering that is performed by the cell's membrane, and relatively slow synaptic time constants (von Neumann, 1963). However, we know that neural circuits do operate very quickly, as humans can make decisions within 200 milliseconds of the arrival of a visual stimulus (Thorpe et al., 1996; Sherwin et al., 2012). Further, in natural environments, stimuli may arrive at any time, at slow rates or fast rates, and circuitry must be ready to respond quickly regardless of when a previous stimulus arrived. Therefore, the brain must have mechanisms for quickly following high frequency inputs.

Many long-range connections across brain areas exhibit a peculiar motif: long-range feed-forward excitatory input is paired, after a short delay, with feed-forward inhibitory input. At the retinogeniculate synapse, this inhibitory input is produced at a specialized dendro-dendritic synapse (the triad synapse) so that each feed-forward excitatory input is followed by a very fast and local inhibitory copy (Cox et al., 1998; Chen and Regehr, 2000; Blitz and Regehr, 2003, 2005). In other connections, such as those from thalamus to cortex, across regions of the hippocampus, or interareal connections, feed-forward excitatory inputs project to both principal neurons and inhibitory interneurons, and the delayed inhibitory input onto principal neurons arises from the interneurons that received feed-forward excitation (Buzsaki, 1984; Agmon and Connors, 1991; Swadlow and Gusev, 2000; Porter et al., 2001; Swadlow, 2003; Gabernet et al., 2005; Pouille et al., 2009; Yang et al., 2013; Rock and Apicella, 2015; Bhatia et al., 2019).

It has been previously recognized that the coordinated arrival of excitatory synaptic drive followed by inhibitory drive can result in very temporally precise postsynaptic action potentials and short integration windows (Pouille and Scanziani, 2001; Wehr and Zador, 2003; Blitz and Regehr, 2005; Mittmann et al., 2005; Higley and Contreras, 2006; Cardin, 2018). Here in theoretical work we extend these findings to show that paired feedforward excitation and inhibition (FFEI) allows computation at very high temporal frequencies that "break" the membrane time constant barrier. Further, we show that this motif can synchronize computations across multiple hierarchical brain regions even when these brain regions have their own noisy ongoing local activity. Finally, we compare the limits of the temporal

computations that are permitted in a low fan-in situation (1 paired synaptic input, such as at the triad synapse) and in a high fan-in situation (such as in input to cortex).

We conclude that paired feedforward excitatory and delayed inhibitory input is a hybrid signal, providing information about the value of the input while at the same time imposing a clock-like trigger signal that shortens temporal integration in a manner that allows high frequency computation and synchronization across brain areas.

Results

Our goal was to understand if there was any potential advantage of the paired feedforward excitatory and inhibitory (FFEI) connections that are commonly observed in projections across brain regions. We analyzed the problem in two regimes. First, we analyzed a low convergence situation (N_{inputs} = ~1) such as is found at the triad retinogeniculate synapse in the LGN. Here, we discovered that FFEI projections allowed feed-forward computations at much higher frequencies than if feedforward excitatory (FFE) projections were employed alone. Then we examined a high convergence situation (N_{inputs} = ~50-150) such as is found at thalamocortical and intercortical projections.

In order to focus specifically on the difference between FFEI projections and FFE projections, we made our models as simple as possible. We did not include other parameters that likely contribute to the temporal qualities of synaptic transmission, such as synaptic depression or facilitation. While these features greatly impact the temporal dynamics of synaptic currents, we did not seek to vary them in our study of inhibition or to mimic specific connections or neuromodulatory states. These qualities have been the focus of many previous studies (Abbott et al., 1997; Tsodyks and Markram, 1997; Varela et al., 1997; Carandini et al., 2002; Swadlow et al., 2002; Boudreau and Ferster, 2005; Higley and Contreras, 2006). Therefore, we left synaptic depression and facilitation out completely so that we could focus on the specific contribution of inhibitory feedforward projections to area-to-area communication.

Paired feedforward excitatory and inhibitory inputs allow transmission of temporal information at high frequencies

We began with a simple model of the retina-LGN triad synapse. At these synapses, excitatory retinal input is provided to an LGN neuron and to an adjacent terminal bouton of the dendrite of an interneuron. The interneuron dendrite also contacts the LGN cell at very nearly the same location as the excitatory cell, providing an only slightly-delayed inhibitory input to the LGN neuron (Cox et. al, 1998). To build our model, we included a feedforward glutamatergic excitatory synaptic current with temporal dynamics that are between the fast-decaying AMPA current and the slower-decaying NMDA current observed at triad synapses (Chen et al., 2002). Fast GABAergic currents were included with a 1 ms delay, also following experimental measurements (Blitz and Regehr, 2003, 2005). While the total synaptic conductance was varied, the maximal conductances of the excitatory and inhibitory synapses were selected so that the

total conductance (the area under the curve) of excitation and inhibition were identical; that is, the total integrated conductance of excitation and inhibition were balanced.

To assess the transmission of temporal information in this model, we simulated the spiking responses of a leaky integrate-and-fire neuron to input spikes generated via a Poisson process with a rectified sinusoidal firing rate (**Fig. 1AB**). We examined transmission of the FFEI projection over a range of inhibitory synapse fall time constants that varied from 20 to 50 ms, and compared its transmission to the case where only feedforward excitatory (FFE) input was provided. Because changing the fall time constant of the inhibitory synaptic current, while keeping integrated E and I conductance fixed, alters the fraction of the excitatory conductance that arrives earlier in the postsynaptic response, the overall responsiveness of the cell also varies as we adjusted the inhibitory synapse fall time constant. To compare equally responsive models, we adjusted the feedforward synaptic weight so that each model generated a response of about 75 Hz when driven with an input modulating frequency of 5 Hz.

FFEI projections demonstrated a remarkable ability to transmit high frequency information. To measure transmission quality at each input frequency, we calculated the Fourier coefficient (FC) of the spiking response at the input modulation frequency (FC_F, **Fig. 1C**). Projections with only excitatory synapses were filtered strongly at input modulation frequencies ranging from 20 – 100 Hz. In contrast, FFEI projections with inhibitory time constants of 20 ms transmitted with nearly equal fidelity from 5 – 100 Hz, and did not reach a 50% reduction in Fourier coefficient responses until the input modulation frequency reached about 400 Hz.

While the Fourier coefficient at the input modulation frequency (FC_F) measures the output transmission at that single frequency, it did not provide information about how much of the total output of the cell was concentrated exclusively at the input modulation frequency. For example, if the output cell increased its overall response only tonically, then FC_F would still exhibit an increase. To examine the fraction of the output cell's total frequency response that was at the input modulation frequency, we divided FC_F by the average Fourier coefficient calculated all frequency (**Fig. 1D**) to produce a normalized frequency response measure (**Fig. 1E**). This analysis indicated that FFEI projections transmitted information that was highly specific to the input modulation frequency over a wide frequency range 5 – 100 Hz, while the specificity of information transmitted by excitatory-alone projections fell off rapidly with frequency.

The ability to provide specific output at the input modulation frequency was highly related to the inhibitory fall time constant. When the inhibitory fall time constant was short, then the advantage of the FFEI configuration was greater. We plotted the normalized output responses for input modulation frequencies of 50 and 100 Hz in **Fig. 1G**. For an inhibitory fall time constant of 20 ms, the postsynaptic neuron produced output at the input modulation frequency that was more than 12 times the amount of average output at other frequencies. As the inhibitory fall time constant was increased, the output neuron behaved more like the excitatory-only configuration, as one would expect. The ½ cutoff frequency – that is, the input

modulation frequency at which the normalized output dropped to ½ of the value it showed for a 5 Hz input – was also highly dependent on the inhibitory fall time constant (**Fig. 1H**).

It was possible that the relative advantage of FFEI transmission compared to FFE was not general, but instead was specific to the particular levels of synaptic input strengths that were chosen in order to drive output responses of about 75 Hz at a 5 Hz input modulation frequency. To examine this possibility, we compared FFEI and FFE models that were matched at 5 Hz input modulation but over a wide variety of output response levels (**Fig. 1F**). In all cases, the FFEI projection responses at the input modulation frequency were much stronger than those of the FFE projection over a wide range of input modulation frequencies. To quantify these changes, we examined the fold change of transmission of FFEI compared to FFE at input modulation frequencies of 50 or 100 Hz for these different levels of synaptic drive (**Fig. 1I**). For all of these levels of synaptic drive, the FFEI projection produced at least 2 times as much drive at 50 and 100 Hz compared to FFE alone. The ½ cutoff frequency was also more than 4 times higher for FFEI compared to FFE (**Fig. 1J**).

Paired feedforward excitatory and inhibitory inputs allow effective transmission at frequencies that are highly filtered by the output cell's membrane properties

The ability of the output cell to reliably follow very high input frequencies was surprising because the membrane properties of neurons act as a low-pass filter, and high frequency current fluctuations are not well transmitted to membrane voltage. We compared the ability of the output neuron to follow synaptic input provided through either FFEI or FFE projections with the ability of the output neuron to follow direct sinusoidal membrane current injections of a fixed amplitude (**Fig. 2**).

As before, we calibrated the output of the neuron to hit a target rate (75 Hz) at a 5 Hz input modulation frequency. For the FFEI and FFE simulations, we did this by setting the synaptic weight, and for the current injection simulations, we did this by setting the amplitude of the sinusoidal current injection. We compared the raw Fourier coefficient measured at the input modulation frequency (**Fig. 2B**), the overall response across all frequencies (**Fig. 2C**) and the normalized frequency response to measure the specificity of the output response to the input modulation frequency (**Fig 2D**). As expected, the cell followed the sinusoidal current injection well until a critical frequency was reached, after which the input fluctuations became too small to generate action potentials. This resulted in a rapid drop in the ability of the cell to follow the output frequencies. By contrast, FFEI inputs continued to drive responses at high frequencies, well beyond the point at which the sinusoidal current could drive spikes. While the critical frequency at which spiking stops for direct current injection does depend upon the amplitude of the current used, the take-home point here is that FFEI projections drive responses at higher input frequencies when responses to FFEI and direct current injections are matched at low frequencies.

At first glance, it seems almost paradoxical that inputs delivered via FFEI projections can apparently "break the limit" of the membrane time constant. To gain intuition into the

mechanism of action of FFEI projections, we examined synaptic currents generated by a 100 Hz train of input spikes when delivered either by FFE or FFEI projections (**Fig. 3A**). To study the influence of different amounts of inhibition on transmission, we also varied the relative weight (total area under conductance curve per presynaptic spike) of the inhibitory conductance to the excitatory conductance, and called this quantity α. The synaptic currents and postsynaptic potentials generated by excitatory-only projections were highly blurred in time and exhibited substantial temporal summation compared to those delivered by FFEI projections. FFEI projections delivered pulse-like current injections that were concentrated in time in a manner that varied with the total amount of inhibition α. Therefore, while inputs at high frequencies are highly filtered, the large, sharp current pulses produced by the FFEI input configuration allows spiking transmission at those high frequencies despite the high filtering.

To examine the optimal amount of feed-forward inhibition, we plotted the transmission of feed-forward signals as a function of input modulation frequency (**Fig. 3BCD**). As before, synaptic weights were set so that transmission at an input modulation of 5 Hz was equal to about 75 Hz. When no noise was introduced, transmission at high frequencies was most efficacious when α was between 1.5 and 3. Larger values of α suppressed transmission because the level of inhibition was too high.

In many neural circuits, ongoing activity provides a background input that might influence the feed-forward transmission of information. To investigate how these background signals might influence the level of inhibition needed for optimal feed-forward transmission, we modeled this background input as 50 noisy independent Poisson inputs, with varying excitatory synaptic input strengths. As the level of ongoing background input increased, relatively smaller weights were needed on the feed-forward inhibitory synapse for optimal transmission. Presumably, the higher background depolarization when background noise is introduced causes a larger inhibitory current for the same conductance, and the optimal inhibitory conductance is lower; higher values would suppress transmission as they do in the no-noise case. Therefore, in order to allow feed-forward drive, neural circuits could tune the strength of their feed-forward inhibition depending upon the amount of expected ongoing background activity.

Influence of inhibitory delay on feed-forward transmission

Another factor that should have a large influence on the temporal capabilities of feed-forward synapses is the delay between the feed-forward excitatory and inhibitory inputs. To examine this dependency, we varied the delay between excitation and inhibition systematically for a wide range of input modulation frequencies (**Fig. 4**). Shorter delays allowed transmission at much higher temporal frequencies, and a delay of 20 ms produced a transmission profile that was almost as slow as excitatory inputs alone. Therefore, a short delay between feed-forward excitation and feed-forward inhibition is necessary to achieve the high temporal frequency transmission characteristics reported here.

Paired feedforward excitatory and inhibitory inputs act as a clock or trigger that can organize feedforward computation across layers or areas

Neural circuits differ from conventional digital electronic circuits in that there is no external clock signal that tells neurons when they should begin evaluating their inputs. One classic idea suggests that neural circuits operate by attractor dynamics and therefore do not have a need for clocks (Hopfield and Tank, 1986; Miller, 2016). However, organisms are able to make extremely fast decisions in a few hundred milliseconds post-stimulus (Thorpe et al., 1996; Sherwin et al., 2012), and a feedforward trigger would be useful for such computations. Here we examined whether paired feedforward excitation and inhibition could provide temporal organization of their own input, in essence providing the feedforward input values and clock timing information in a single mechanism.

We studied transmission across 4 cells in successive brain areas in 3 different models. Each area was assumed to have local, ongoing excitatory activity that was modeled as 50 noisy Poisson inputs that were not related to the feedforward input. In one model, these 4 neurons were not connected at all, so that baseline activity of these neurons could be studied as a control. In another model, these neurons were connected using FFE projections. These connections represent the simplest feedforward cross-area computation that we could imagine, which is y = x. This computation was chosen because of its ease of evaluation, but these results should extend for any convergent feedforward computation where the output is a function of the inputs at a particular time. Finally, we examined a model where cross-area transmission was provided by FFEI synapses across the 4 model areas.

We assessed the temporal fidelity of the computation using the same frequency analysis that we performed in **Fig. 1**. We provided an input firing rate that was modulated at a particular frequency that was varied, and examined the Fourier coefficient (**Fig. 5B**), overall activity (**Fig. 5C**), and the normalized Fourier coefficients that indicated how specifically the output response followed the input frequency (**Fig. 5D**). When FFE projections were used, the area 4 output neuron did not efficaciously follow the input modulation frequency for frequencies greater than about 5 Hz. However, when FFEI projections were used, the area 4 output neuron followed the input very well at input modulation frequencies as high as 100 Hz. This difference between FFE and FFEI was robust over a variety of feedforward synaptic strengths (**Fig. 5E**). Even when feedforward firing rates were set so that the output neuron was driven at 20 Hz for 5 Hz input modulation, FFEI projections provided more than an 8-fold increase in transmission compared to FFE inputs modulated at 50 Hz, and differences were more pronounced for higher synaptic strengths (**Fig. 5F**). The ½ cutoff frequency for the same network was more than 5-fold greater (**Fig. 5G**).

Interestingly, when FFE projections were used, the Fourier coefficient of the area 4 output peaked several times at higher input frequencies (300-1000 Hz). This effect can likely be credited to over-excitation of the area 4 neuron, as seen in **Fig. 5A**. Indeed, at most frequencies, the area 4 neuron with FFE is likely firing at its maximum rate, due to the amplification of excitatory input over the circuit. As a result, high FC measurements at high input frequencies cannot necessarily be attributed to the circuit following the inputs, but may instead result from the physical features of the neuron allowing for maximal firing at these

rates. In either case, the Fourier coefficient peaks at these high input frequencies do not stand out from the overall power of the output response, as shown in **Fig. 5D**.

One may ask how much of these frequency responses could have arisen by chance due to the random activity that is provided to each area. The fold increase in Fourier coefficient responses at the input modulation frequency is shown in **Fig 5H**. Even at the lowest synaptic strength tested, FFEI projections provided responses that were at least 5 times those of the noise-only network, and this difference greatly increased when input strength was increased.

So far, we have only investigated how inputs of fixed modulation frequency are transmitted over multiple brain areas. While this addresses how different brain areas can exhibit synchronized activity, it does not directly confront how these brain areas can adapt to rapidly changing inputs. We therefore constructed a rectified sinusoidal Poisson input with a changing modulation frequency over time (**Fig. 5I**). We then provided this input to the FFE and FFEI models and examined the normalized FC spectrum over time (**Fig. 5JK**), which measured how closely the area 4 output followed a range of frequencies over the course of the input. With FFE projections, the area 4 output only noticeably followed the stepping input at low frequencies (5-10Hz). Meanwhile, with FFEI projections, the area 4 output followed the entire stepping input fairly well. Furthermore, the area 4 output did not exhibit significant residual power at frequencies represented earlier in the input, suggesting that the FFEI model was capable of quickly adapting to the changing input frequency.

Taken together, these results indicate that FFEI projections organize multi-level, hierarchical computations across brain areas that are also being driven by ongoing incidental activity. Further, FFEI projections allow these computations to occur with high fidelity even at high temporal frequencies. In this way, FFEI projections serve to deliver both a signal as well as the timing signal necessary to organize feedforward computation across areas.

Paired inputs of opposite sign can organize computation in neuromorphic circuits

We have already noted that paired feedforward excitation with slightly delayed inhibition is a common circuit motif in the brain, but the concept can be used more generally for computations with either sign. Although we are not presently aware of feedforward inhibition that is followed by delayed excitation in a neural circuit, this motif can be used in artificial circuits to organize feedforward computations at high speed.

We demonstrate the use of mixed feedforward inputs in a model LIF circuit that performs the exclusive-or (XOR) computation of 2 inputs (**Fig. 6**). In this computation, the output neuron should exhibit a response if either of the 2 inputs is positive, but it should be silent if there is no input or if both inputs are active. To transmit a positive postsynaptic signal, we used FFEI synapses employing excitation that was followed by identical but delayed inhibition (**Fig. 6A**). To transmit a negative signal, we employed inhibition that was followed by identical but delayed excitation. Input weights for cells in the first layer were set so that one input was positive and the other input was negative. Further, the input with a weight that was positive in

the first cell has a negative weight in the second cell. The neuron in the second layer will respond if either of the cells in the first layer responds.

Once again, we provided input at different modulation frequencies, although we shifted the two inputs so that they were 180° out of phase. Therefore, the XOR output should be produced at twice the input frequency (the cell should respond strongly when either input is at its positive phase, and weakly or not at all when the inputs are turned off). Once again, we found that the circuit with mixed FFEI projections could follow the XOR computation over high frequencies, while a comparison FFE circuit fell off rapidly with frequency. We compared another input case (with the 2 inputs shifted by 90°) in **Fig. 6 Supplement 1**.

We conclude that the concept of mirroring a feedforward input with a delayed negative copy can organize high frequency computations across multi-layer neuromorphic circuits in much the same way that a clock organizes computations across digital electronic circuits.

In principle, AMPA-only currents allow high frequency computations

Most excitatory synapses in the mammalian brain employ a combination of the AMPA and NMDA receptors. AMPA receptors respond rapidly and briefly to neurotransmitter, while NMDA receptors remain open for longer periods of time (50-150 ms). However, there are a few instances of excitatory synapses that primarily involve AMPA receptors. One example is the calyx of Held synapse in the mature mammalian auditory brain stem; notably, this region often processes high frequency temporal information in the form of auditory input (Nakamura and Cramer, 2011). This raises the question of whether neural circuits could, in principle, achieve the same fast computation as FFEI by using feedforward inputs that were comprised entirely of fast AMPA channels.

To address this question, we compared feedforward transmission in synapses that were comprised of AMPA receptors only, AMPA and NMDA receptors only (like FFE), and AMPA, NMDA, and GABA receptors (like FFEI) in **Fig. 7**. We again provided rectified sinusoidal input at an input modulation frequency, and examined the Fourier coefficient of the response at the input frequency (**Fig. 7B**), the average response across all frequencies (**Fig. 7C**), and the normalized output frequency (**Fig. 7D**). Unlike in previous simulations with feedforward excitatory transmission alone, accurate high-frequency transmission was possible when only fast-closing AMPA channels were present. However, when slow-closing NMDA channels were added, the excitatory conductance and the spiking response became blurred, leading to poor transmission of high-frequency information. High-frequency transmission was restored by inhibition via GABA channels.

To investigate the effects of local background activity on the ability of the synapses to follow high-frequency inputs, we provided 50 noisy Poisson inputs, modeled as in **Fig. 5**, and examined the output response (**Fig. 7EFG**). In the presence of excitatory noise, the FFEI synapse overall followed rectified sinusoidal inputs more effectively than the AMPA-only feedforward synapse.

These observations can be attributed to the overall output power, which was somewhat higher for the AMPA-only feedforward synapse than for the FFEI synapse (**Fig. 7F**).

These results suggest that AMPA-only feedforward synapses provide some of the benefits of FFEI with respect to high frequency computation. However, FFEI synapses are more effective than AMPA-only feedforward synapses when noisy inputs are also provided, suggesting that inhibitory GABA channels may play a role in filtering out excitatory noise and thus overriding ongoing computations.

Transmission is limited by inhibitory neuron time constants when FFEI is provided at the circuit level

While the FFEI motif is sometimes found in inputs onto individual neurons, such as in the retinogeniculate triad synapse, the FFEI motif is also commonly found in inputs to circuits such as in the hippocampus (Buzsaki, 1984; Pouille and Scanziani, 2001; Bhatia et al., 2019) or the cerebral cortex, both in inputs from thalamus (Agmon and Connors, 1991; Swadlow, 2003) and interareal projections (Yang et al., 2013). In these networks, excitatory projections from other areas make connections with separate populations of excitatory and inhibitory neurons, and the targeted inhibitory neurons provide rapid but slightly delayed inhibition onto the recipient excitatory neurons. Further, the excitatory and inhibitory neurons typically receive converging inputs from many cells, so that in principle the excitatory and inhibitory inputs to the local circuit may not be entirely matched. That is, the strong 1-to-1 relationship between each feedforward excitatory postsynaptic potential and each feedforward inhibitory postsynaptic potential that is found at the triad synapse is not present in circuit-level projections; instead, feedforward excitation and inhibition are more loosely related.

Before we begin studying how FFEI can impact temporal computations at the circuit level, it is worth pausing to consider whether all cortical circuits might take advantage of any properties that we uncover. In the thalamus, it is clear that visual, somatosensory, and auditory neurons can follow sensory inputs at high frequencies. However, in visual (Hawken et al., 1996), somatosensory (Chung et al., 2002), and auditory cortex (Creutzfeldt et al., 1980; Wehr and Zador, 2005), cortical neurons primarily respond to stimulation at much lower stimulus repetition frequencies (<20 Hz) than do thalamic neurons. That is, primary sensory cortex does not seem to segment responses to sensory stimulation at frequencies much higher than 20 Hz. However, in both sensory and higher cortical areas and in the hippocampal formation, 40 Hz activity (gamma activity) is prominent (Fries et al., 2007) and can be induced by driving feedforward interneurons (Cardin et al., 2009). It has been suggested that in hippocampal circuits, each gamma cycle might encode representations of individual items (Lisman and Idiart, 1995; Fries et al., 2007; Lisman and Jensen, 2013), and 40 Hz sensory stimulation has been reported to be protective against neurodegeneration (Iaccarino et al., 2016). So we feel it is worth considering whether circuit-level FFEI input can allow circuits to follow inputs at such high frequencies.

Here, we examined a model network with 100 feedforward excitatory inputs that arrived at an LIF excitatory cell and an LIF inhibitory cell (**Fig. 8A**). Following our previous methods, the firing rate of each input was modulated sinusoidally at an input modulation frequency. In this model, all inputs were driven at the same phase (**Fig. 8B**). We examined the Fourier coefficient of the output responses at the input modulation frequency (**Fig. 8C**), the average response across all frequencies (**Fig. 8D**), and the ratio of these quantities (**Fig. 8E**).

The circuit-level FFEI exhibited some similarities to and differences from the single FFEI input situation. One difference is that the circuit's I neuron receives excitatory input without a delayed inhibitory copy, and acts just like a neuron receiving FFE input. Therefore, the frequency responses of the inhibitory neuron are the same as the E-only case in **Fig. 8CDE**. If we look at these responses, we see that they fall off much like FFE input to the triad synapse: the response is much attenuated at about 25 Hz, for example. At input modulation frequencies greater than this, the I neuron will not respond strongly to the excitatory input (**Fig. 8B, right**), so the I neuron's contribution to the circuit is not present at high frequencies, and the circuit behaves like an FFE circuit. This means that the circuit-level FFEI projection has a much lower cut-off response frequency than a similarly-endowed triad-like FFEI projection.

We suspected that the membrane time constant of the inhibitory neuron would be a key parameter in determining the cut-off frequency for the circuit-level FFEI projection, so we compared responses in models where this parameter was varied. In this circuit network, the level of response output is very sensitive to the synaptic strengths of the inputs as well as the strength of the synapse from the inhibitory neuron onto the excitatory neuron. Because there were 2 non-linear ways to tune the responses to a particular input rate, we simply left the synaptic strengths unchanged while we altered the membrane time constant of the inhibitory neuron so that the models could be compared on the basis of that parameter.

In **Fig. 8F**, we show the normalized Fourier coefficient for these models but with the data scaled so that the output response for an input modulation of 5 Hz is equal to 1. Here it is apparent that the frequency response depends strongly on the inhibitory membrane time constant, with low values corresponding to high transmission at high input modulation frequencies. When the inhibitory time constant was 10 ms, which is consistent with experimental studies of cortical interneurons (Economo and White, 2012), the ½ frequency cut off was 40 Hz, indicating that the excitatory cell could follow input responses very effectively up to that frequency. This ½ cutoff frequency was 70% greater than the ½ cutoff frequency for a circuit with FFE projections alone.

Discussion

The motif of feedforward excitation and inhibition is present in a wide array of inter-area connections throughout the brain (Buzsaki, 1984; Agmon and Connors, 1991; Swadlow and Gusev, 2000; Porter et al., 2001; Swadlow, 2003; Yang et al., 2013; Rock and Apicella, 2015; Bhatia et al., 2019); as a result, one might expect that this motif serves some sort of

evolutionary benefit. By modeling paired E/I connections in simple feedforward networks, we have shown that FFEI inputs can enhance the transmission of high-frequency temporal information through neural circuits. We have also examined the features of FFEI circuits that influence high frequency transmission, such as the synaptic time constants, synaptic strengths, strength and delay of inhibition, and membrane time constants. Similar to the triad synapses in retinogeniculate projections, FFEI models with low input convergence and tightly paired E/I inputs exhibit robust temporal transmission over a wide range of frequencies up to ~100 Hz. Meanwhile, in circuits modeled after hippocampal and cortical projections, FFEI enhances high frequency transmission up to about 40 Hz, despite high input convergence (N = 100) and a looser association between excitatory and inhibitory inputs. Most strikingly, in circuit models crossing multiple hierarchical brain areas, we have found that FFEI projections not only reliably transmit high frequency signals, but also organize activity across brain areas over time, essentially acting as a feedforward clock trigger. Thus, FFEI projections can act as a hybrid input, conveying both information about input value and imposing a clock-like trigger to initiate rapid computation.

FFEI allows computation at high temporal frequencies that "break the limit" of the membrane time constant

The pairing of excitation with delayed inhibition produces a narrow time window during which spiking can occur; as a result, FFEI inputs can enhance the temporal fidelity of neural circuit outputs, as shown in experiments in hippocampal CA1 (Pouille and Scanziani, 2001; Bhatia et al., 2019). Given the high temporal precision of networks containing FFEI projections, it follows that such networks would accurately transmit high-frequency temporal information, as well. This effect can largely be attributed to the narrow spiking time window generated by paired E/I inputs, as was previously described (Pouille and Scanziani, 2001; Wehr and Zador, 2003; Blitz and Regehr, 2005; Mittmann et al., 2005; Higley and Contreras, 2006; Cardin, 2018). Here we show that the residual inhibition following each input spike does not suppress the cell for long, and the cell is quickly ready to respond to subsequent FFEI inputs (**Figure 3A**).

Network communications among areas that contain feed-forward excitatory-only projections have been studied for many years. Networks of this design that propagate signals or computations with high temporal fidelity have been called synfire chains (Abeles, 1991). We have shown here that, with excitatory-only feed-forward input, networks can produce reliable computation only at relatively low temporal frequencies. Excitatory-only feed-forward networks can reliably and quickly transmit firing rate information (without single spike temporal precision) if each area receives ongoing balanced excitatory and inhibitory internal noisy input (Shadlen and Newsome, 1998; van Rossum et al., 2002; Murphy and Miller, 2009; Hennequin et al., 2017). Here we have shown that this transmission is possible with FFEI projections even if the random local input that a local area experiences is not balanced.

The FFEI models we have discussed are capable of maintaining precise output timing, even when presented with inputs at fairly high temporal frequencies. In most real circuits, synaptic transmission is also influenced by short-term synaptic dynamics such as synaptic facilitation and

depression (Deisz and Prince, 1989; Thomson and West, 1993; Markram and Tsodyks, 1996; Abbott et al., 1997; Varela et al., 1997) in a manner that varies from circuit to circuit. If synapses exhibited moderate synaptic depression, then transmission could be much better after pauses in activity of a few hundred milliseconds in duration (Swadlow et al., 2002; Swadlow et al., 2005). Still, if steady-state synaptic depression did not differ greatly between excitatory and inhibitory synapses, high frequency computation via FFEI would still be possible. Compatible synaptic depression among excitatory and inhibitory inputs to cortical circuits has been reported experimentally, as examination of input to somatosensory cortex showed that time delays between excitatory and inhibitory postsynaptic currents were maintained across long trains of input stimulation (Higley and Contreras, 2006).

FFEI as a feedforward "clock" trigger mechanism

The absence of a synchronizing clock or trigger signal to organize the activity of neurons would seem to imply that neuronal circuits would be limited to performing computations that do not require such a trigger, such as attractor networks or integrators (Hopfield, 1982; Seung et al., 2000; Miller et al., 2003; Miller, 2016). FFEI acts much like a feed-forward synchronizing trigger that forces computation to occur within a short window (Buzsaki, 1984; Agmon and Connors, 1991; Swadlow and Gusev, 2000; Porter et al., 2001; Swadlow, 2003; Rock and Apicella, 2015; Bhatia et al., 2019).

Here we showed that FFEI, when used in projections across brain areas or layers, can organize computation across these regions, even when these regions are experiencing ongoing local activity (**Fig. 5**). Unlike a digital computer, where the clock trigger runs at a fixed rate, FFEI allows the trigger signal to be generated at any time (**Fig. 5IJK**) and at many rates, up to 100 Hz for triad-like synapses and up to about 40 Hz for circuit-level FFEI inputs. In low-level areas, these triggers would be generated when sensory input arrives, and computation could proceed at the speed of the sensory input. In higher-level areas, computation across two areas could proceed whenever the input area generates output, and could underlie coordination of high frequency oscillations across areas (Lisman and Idiart, 1995; Lisman and Jensen, 2013).

The degree to which high frequency information actually travels throughout the brain varies depending upon area and channel, and has been well studied in the visual system. In recordings that examined velocity tuning to single bar sweeps in both retina and LGN of X and Y cells in the cat, peak velocity tuning was slightly lower in the LGN for X cells, but very comparable in retina and LGN for Y cells, with preferred velocities that ranged from about 20°/s to 100°/s (Frishman et al., 1983), indicating that spike timing information can be precisely transmitted across the triad synapse. Consistent with this idea, retinal inputs activate LGN cells with high efficacy (Usrey et al., 1998), indicating that LGN neurons follow retinal ganglion inputs with high reliability.

Evidence from sensory cortex, however, suggests that the thalamocortical connection does not take full advantage of the potential FFEI speeds. There is a strong drop-off in peak temporal frequency tuning between LGN and cortex, with most LGN cells exhibiting strong firing for many

frequencies, including those greater than 16 Hz, while few cortical neurons exhibit strong firing at 16 Hz or greater (Hawken et al., 1996; Van Hooser et al., 2003; Heimel et al., 2005; Van Hooser et al., 2013). In principle, if FFEI were the only factor, we would predict that transmission should be quite robust at 20 Hz (**Fig. 8**), but visual cortex attenuates these frequencies quite strongly on average. The same drop in responses to repeated sensory stimulation occurs in the somatosensory (Ahissar et al., 2001; Chung et al., 2002) and auditory systems (Creutzfeldt et al., 1980). Synaptic depression or other cortical circuit mechanisms may underlie this filtering (Chung et al., 2002; Swadlow, 2002; Boudreau and Ferster, 2005; Swadlow et al., 2005; Wehr and Zador, 2005).

Nevertheless, many cortical regions exhibit strong modulation and resonance at around 40 Hz, also known as the gamma frequency (Fries et al., 2007; Cardin et al., 2009; Lisman and Jensen, 2013). If responses at 40 Hz in one area are to be intelligible in another cortical or hippocampal area, then it is necessary for these circuits to be able to follow inputs at these frequencies. Here we showed that circuit-level FFEI inputs can in principle allow such rapid communication.

Predictions

The FFEI models make a simple prediction: the absence of inhibition at cells receiving FFEI inputs should limit the ability of these cells to follow inputs at high temporal frequencies. To provide evidence in support of (or against) the model, the ability of the retinogeniculate synapse to follow high frequency inputs could be experimentally evaluated. An optogenetics approach could be used to control the activation of retinal ganglion cells (RGC) with high temporal precision, and the activity of LGN relay cells in response to RGC action potentials could then be measured. According to the model presented in **Figure 1**, a GABAzine infusion to block inhibition in the LGN would limit the ability of LGN relay cells to follow RGC inputs at high temporal frequencies. A similar experiment could be performed at thalamocortical slices in somatosensory cortex (Agmon and Connors, 1991) in order to test the high-convergence regime. While we have noted that there is a high degree of synaptic depression in thalamocortical synapses (Chung et al., 2002; Higley and Contreras, 2006), the data from an experiment should exhibit a strong shift, as shown in **Figure 8**, from the FFEI dynamics towards E-only dynamics.

Conclusion

We now know that feed-forward pairing of excitatory and inhibitory connections provides several functions for neural circuits. It helps to linearize computations that are impacted by rectification in the retina (Werblin, 2010), LGN, and cortex (Hirsch et al., 2015). It sharpens stimulus tuning and spike timing (Pouille and Scanziani, 2001; Wehr and Zador, 2003; Blitz and Regehr, 2005; Mittmann et al., 2005; Higley and Contreras, 2006; Cardin, 2018), and allows neurons to respond to weak inputs without saturating for strong inputs (Pouille et al., 2009). And in hippocampal CA3-CA1 paired E/I projections, it has been found that the delay between excitation and inhibition shortens with stronger CA3 inputs, producing smaller changes in CA1 membrane potential (Bhatia et al., 2019). Therefore feedforward excitation and inhibition

allows neurons to accommodate a dynamic range of inputs before firing, providing a mechanism of gain control to these circuits (Pouille et al., 2009; Bhatia et al., 2019). Here we add that it provides a dual signal – the value of its input on the one hand and a clock-like trigger on the other – that allows high frequency feed-forward computation that is synchronized across brain areas.

Materials and Methods

Neural circuit simulations were performed in MATLAB (MathWorks, Natick, MA). Leaky integrate and fire neurons were modeled with the following differential equation, using the forward Euler method with a 0.1 ms time step (Lapicque, 1907; Abbott, 1999):

$$\frac{dV_m}{dt} = -\frac{(V_m - V_e)}{\tau_m} - \frac{R_m}{\tau_m}\sum_n \alpha_n P_n(t)(V_m - V_{syn,n})$$

where V_m is the membrane potential of the neuron, V_e is the leak potential, τ_m is the membrane time constant, R_m is the membrane resistance, $P_n(t)$ is the synaptic conductance from synaptic input n, and $V_{syn,n}$ is the resting potential at the synapse for input n, and α_n (= 1 for excitatory synapses) is a scaling coefficient for the synaptic current from input n. When V_m reaches the threshold potential V_{thresh}, the model neuron generates a spike and V_m is set to the reset potential V_{reset} (see Tables 1 and 2 for values).

Synapses were modeled as a difference of exponentials, with two time constants (Dayan and Abbott, 2001):

$$P_n(t) = \sum_j P_{max,n} B_n \left(\exp\left(-\frac{\Delta t_j}{\tau_{fall,n}}\right) - \exp\left(-\frac{\Delta t_j}{\tau_{rise,n}}\right) \right)$$

$$B_n = \left(\left(\frac{\tau_{rise,n}}{\tau_{fall,n}}\right)^{\left(\frac{\tau_{rise,n}}{\tau_{fall,n}-\tau_{rise,n}}\right)} - \left(\frac{\tau_{rise,n}}{\tau_{fall,n}}\right)^{\left(\frac{\tau_{fall,n}}{\tau_{fall,n}-\tau_{rise,n}}\right)} \right)^{-1}$$

where $P_{max,n}$ is the maximum conductance of the synapse, B_n is a normalization factor to ensure that the peak value of $P_n(t)$ is $P_{max,n}$, Δt_j is the time between t and the jth spike of synaptic input n, $\tau_{fall,n}$ is the fall time constant, and $\tau_{rise,n}$ is the rise time constant. (see Tables 1 and 2 for values).

Simulating inputs to neural circuits
Temporal information was generated using a Poisson process with a rectified sinusoidal firing rate:

$$r(t) = rectify(PR \sin(2\pi Ft))$$

where PR is the peak firing rate set to 100 Hz for all simulations, F is the input modulation frequency, and rectify(x) = 0 if x < 0, and rectify(x) = x for x≥0. For each set of simulations, temporal information was presented to our simulated neural circuits for a fixed length of time, independent of F.

In some of our simulations, we provided random background activity as an additional excitatory synaptic input. This activity was modeled as N_{inputs} noisy Poisson inputs with a uniform firing rate FR (see Table 1 for values). FR was calculated such that, for each noisy input, the probability of seeing 1 background spike during an input cycle is equal to the probability of a feedforward input spike over one cycle (that is, the mean firing rate of the feedforward inputs and each noisy input were balanced):

$$FR = \frac{PR}{\pi}$$

Calculating the power of spiking responses at a particular frequency
Spiking responses were converted to a firing rate per time step (Hz), and the following equation was used to calculate the Fourier coefficient magnitude at a particular frequency (Crawford, 1968):

$$FC_F = \left| \frac{2\Delta t}{L} * \sum_{t_{index}=0}^{L/\Delta t} R(t) \exp(-2\pi i * F * t) \right|, t = t_{index}\Delta t$$

where Δt is the time step size in seconds, L is the length of the spiking response in seconds, t_{index} is time as an integer index, $R(t)$ is the spiking response in Hz, and F is a particular frequency.

To normalize the power of spiking responses at a particular frequency, we used the average power calculated over all frequencies (FC_{avg}) as a normalization factor. For a time interval of length L in time steps of Δt, $1/\Delta t$ and $1/L$ are the maximum and minimum frequencies that can be represented, respectively. Therefore, FC_{avg} was determined by averaging FC_F over $F = \left[0, \frac{1}{\Delta t}\right]$ in intervals of $1/L$. The normalized frequency response was then expressed as FC_F/FC_{avg}. In cases where FC_{avg} = 0, the normalized frequency response was set to 0.

Unless otherwise stated, FC_F, FC_{avg}, and FC_F/FC_{avg} were each averaged over 10 trials for each model.

Balancing excitation and inhibition in triad synapse models
When varying the inhibitory fall time constant ($\tau_{fall,i}$) in our triad synapse models, we scaled $P_{max,i}$ relative to $P_{max,e}$, such that the total excitation and inhibition are balanced:

$$P_{max,i} = P_{max,e} \frac{B_e}{B_i} \frac{\tau_{fall,e} - \tau_{rise,e}}{\tau_{fall,i} - \tau_{rise,i}}$$

The above equation was derived by first integrating $P_e(t)$ and $P_i(t)$ for a single spike at $t = 0$ over the interval $t = [0, \infty]$, as a measure of the total conductance due to a single spike. $P_{max,i}$ values were then obtained by setting the total excitation equal to the total inhibition, and then solving for $P_{max,i}$ given a set of time constants and excitatory parameters.

Determining the expected output of an exclusive-or computation
In Figure 6, we examine the output of a circuit designed to perform an exclusive-or (XOR) computation of 2 inputs. The expected output of the circuit was determined by performing the XOR computation on sliding windows of length t_{bin} = 10 ms or 5 ms. If only one of the inputs fires during the time interval $[t - \frac{t_{bin}}{2}, t + \frac{t_{bin}}{2}]$, then output is expected at time t.

Key Resources Table

Reagent type (species) or resource	Designation	Source or reference	Identifiers	Additional information
Software, algorithm	Matlab	The MathWorks, Natick, MA	RRID:SCR_001622	
Software, algorithm	GitHub	GitHub	RRID:SCR_002630	

Sex as a variable

The computational models studied here have neither sex nor gender.

Table 1. Parameters for triad synapse simulations

Default model parameters: dt = 0.1 ms					
Leaky integrate and fire neuron		Synaptic transmission, paired feed-forward E/I		Synaptic transmission, feed-forward E	
Parameter	Value	Parameter	Value	Parameter	Value
τ_m	10 ms[§]	$P_{max,e}$	1.21 µS[¶]	P_{max}	0.080 µS[¶]
R_m	10 MΩ[§]	$P_{max,i}$	1.21 µS[¶]	V_{syn}	0 mV[§]
V_e	−75 mV[§]	$V_{syn,e}$	0 mV[§]	τ_{fall}	20 ms[‖]
V_{reset}	−80 mV[§]	$V_{syn,i}$	-80 mV[§]	τ_{rise}	1 ms[‖]
V_{thresh}	−40 mV[§]	$\tau_{fall,e}$	20 ms[‖]		
		$\tau_{fall,i}$	20 ms[‖]		
		$\tau_{rise,e}$	1 ms[‖]		
		$\tau_{rise,i}$	1 ms[‖]		
		Δ	1 ms[†]		
		α	1.25		

Figure 1 modifications:		
Panels C-E: Paired feed-forward E/I:		
$\tau_{fall,i}$	$P_{max,e}$	$P_{max,i}$
25 ms	0.883 µS[¶]	0.723 µS[¶]
30 ms	0.581 µS[¶]	0.403 µS[¶]
50 ms	0.222 µS[¶]	0.096 µS[¶]
Panel F:		
Paired feed-forward E/I		Feed-forward E
$P_{max,e}$	$P_{max,i}$	P_{max}
0.498 µS[¶]	0.498 µS[¶]	0.032 µS[¶]
0.911 µS[¶]	0.911 µS[¶]	0.054 µS[¶]
1.21 µS[¶]	1.21 µS[¶]	0.080 µS[¶]
1.46 µS[¶]	1.46 µS[¶]	0.120 µS[¶]
1.59 µS[¶]	1.59 µS[¶]	0.160 µS[¶]

Figure 3 modifications:		
Default noisy input parameters		
Parameter	Value	
N_{inputs}	50	
FR	31.83Hz[††]	
$P_{max,noise}$	2.26 nS[§§]	
$\tau_{fall,noise}$	20 ms[‖]	
$\tau_{rise,noise}$	1 ms[‖]	
Panels B-E: Paired feed-forward E/I: dt = 0.02 ms		
α	$P_{max,e}$	$P_{max,i}$
1	0.597 µS[¶]	0.597 µS[¶]
1.25	1.67 µS[¶]	1.67 µS[¶]
1.5	3.19 µS[¶]	3.19 µS[¶]

1.75	4.78 µS¶	4.78 µS¶
2	5.58 µS¶	5.58 µS¶
3	4.46 µS¶	4.46 µS¶
5	3.78 µS¶	3.78 µS¶
7	2.87 µS¶	2.87 µS¶
10	2.11 µS¶	2.11 µS¶

Panel F: Paired feed-forward E/I (noise): dt = 0.02 ms

	α	1	1.25	1.5	1.75	2	3	5	7	10
Noise × 0.5: $P_{max,noise}$ = 1.13 nS	$P_{max,e}$ = $P_{max,i}$	0.538 µS¶	1.63 µS¶	3.19 µS¶	4.82 µS¶	5.53 µS¶	4.94 µS¶	3.72 µS¶	2.79 µS¶	2.23 µS¶
Noise × 1: $P_{max,noise}$ = 2.26 nS	$P_{max,e}$ = $P_{max,i}$	0.478 µS¶	1.59 µS¶	3.19 µS¶	4.78 µS¶	5.46 µS¶	5.02 µS¶	3.74 µS¶	2.91 µS¶	2.11 µS¶
Noise × 1.5: $P_{max,noise}$ = 3.40 nS	$P_{max,e}$ = $P_{max,i}$	0.259 µS¶	1.41 µS¶	1.99 µS¶	3.19 µS¶	3.82 µS¶	4.66 µS¶	3.51 µS¶	2.79 µS¶	2.11 µS¶
Noise × 2: $P_{max,noise}$ = 4.53 nS	$P_{max,e}$ = $P_{max,i}$	0.159 µS¶	1.31 µS¶	0.956 µS¶	1.59 µS¶	2.39 µS¶	4.46 µS¶	3.58 µS¶	2.67 µS¶	2.15 µS¶
Noise × 5: $P_{max,noise}$ = 11.3 nS	$P_{max,e}$ = $P_{max,i}$	0.120 µS¶	0.836 µS¶	0.291 µS¶	0.179 µS¶	0.127 µS¶	0.052 µS¶	0.024 µS¶	0.014 µS¶	0.010 µS¶

Figure 4 modifications:

Panels B-D: Paired feed-forward E/I:

Δ	$P_{max,e}$	$P_{max,i}$
2 ms	0.671 µS¶	0.671 µS¶
5 ms	0.328 µS¶	0.328 µS¶
10 ms	0.204 µS¶	0.204 µS¶
20 ms	0.132 µS¶	0.132 µS¶

Figure 5 modifications (noise):

Panel A:

Paired feed-forward E/I	$P_{max,e}$ = $P_{max,i}$ = 0.359 µS¶
Feed-forward E	P_{max} = 0.016 µS¶
Noise only	P_{max} = 0

Panels B-D, J-K:

Paired feed-forward E/I	$P_{max,e}$ = $P_{max,i}$ = 0.717 µS¶
Feed-forward E	P_{max} = 0.032 µS¶
Noise only	P_{max} = 0

Panel E:

Paired feed-forward E/I		Feed-forward E
$P_{max,e}$	$P_{max,i}$	P_{max}
0.359 µS¶	0.359 µS¶	0.016 µS¶

0.595 µS[¶]	0.595 µS[¶]		0.024 µS[¶]
0.717 µS[¶]	0.717 µS[¶]		0.032 µS[¶]
0.799 µS[¶]	0.799 µS[¶]		0.047 µS[¶]
0.835 µS[¶]	0.835 µS[¶]		0.055 µS[¶]

Figure 6 modifications: dt = 0.02 ms

Paired feed-forward mixed-sign	$P_{max,e} = P_{max,i} = 1.31$ µS[¶]
Feed-forward single-sign	$P_{max} = 0.066$ µS[¶]

Figure 6 supplement 1 modifications: dt = 0.02 ms

Paired feed-forward mixed-sign	$P_{max,e} = P_{max,i} = 1.20$ µS[¶]
Feed-forward single-sign	$P_{max} = 0.068$ µS[¶]

Figure 7 modifications:

Default AMPA+NMDA/GABA parameters

Parameter	AMPA	AMPA+NMDA	AMPA+NMDA/GABA
$P_{max,AMPA}$	0.679 µS[¶]	0.051 µS[¶]	0.798 µS[¶]
$\tau_{fall,AMPA}$	0.72 ms[†]	0.72 ms[†]	0.72 ms[†]
$\tau_{rise,AMPA}$	0.7 ms[†]	0.7 ms[†]	0.7 ms[†]
$P_{max,NMDA}$		0.026 µS[¶]	0.399 µS[¶]
$\tau_{fall,NMDA}$		100 ms[‡]	100 ms[‡]
$\tau_{rise,NMDA}$		3.2 ms[‡]	3.2 ms[‡]
Δ			1 ms[†]

Table 1: Parameters of the single input FFEI / FFE models. [†]: (Blitz and Regehr, 2005). [‡]: (Blitz and Regehr, 2005). [§]: (Blitz and Regehr, 2005). [¶]: For each set of simulations, synaptic input strengths were chosen to balance the response at F = 5Hz between different parameter sets. [‖]: Excitation at biological triad synapses involves a combination of a fast-decaying AMPA current (Blitz and Regehr, 2005; Chen et al., 2002) and a slow-decaying NMDA current (Chen et al., 2002), resulting in a complex excitatory conductance (Chen et al., 2002). In order to simplify the analysis of this circuit motif, synaptic time constants were chosen to produce a single excitatory current with a medium decay. [††]: The background noise firing rate was adjusted such that the mean firing rates of the feedforward inputs and each noisy input were balanced. [§§]: The strength of noisy input was adjusted such that the total noise was comparable to the feedforward input.

Table 2: Parameters for LGN-cortex simulations

Default model parameters: dt = 0.1 ms

Leaky integrate and fire neurons

Parameter	Interneuron (I)	Cortical neuron (E)
τ_m	10 ms[§]	10 ms[§]
R_m	10 MΩ[§]	10 MΩ[§]
V_e	−75 mV[§]	−75 mV[§]
V_{reset}	−80 mV[§]	−80 mV[§]
V_{thresh}	−48 mV[◊]	−40 mV[§]

Synaptic transmission

Parameter	Paired feed-forward E/I			Feed-forward E
	LGN input to (E)	LGN input to (I)	(I) to (E)	LGN input to (E)
P_{max}	2 nS	0.6 nS	100 nS	0.8 nS
V_{syn}	0 mV[§]	0 mV[§]	-80 mV[§]	0 mV[§]
τ_{fall}	20 ms[#]	20 ms[#]	20 ms[#]	20 ms[#]
τ_{rise}	1 ms[#]	1 ms[#]	1 ms[#]	1 ms[#]
N_{inputs}	100	100	1	100
α			1.25	

Figure 8 modifications:

Panels C-E: (I): τ_m = [5 ms, 6 ms, 10 ms, 20 ms, 50 ms, 100 ms]

Table 2: Parameters of the many input FFEI / FFE models. [#]: (Blitz and Regehr, 2005). [◊]: The firing threshold of inhibitory interneurons was lowered, in order to represent the increased excitability of these neurons compared to other neurons in cortex (McCormick et al., 1985). See additional annotations for constants chosen in Table 1 caption.

Figure 1. Paired feedforward excitation and delayed inhibition in a triad synapse model allows transmission of higher frequencies than feedforward excitation alone. (A) Top: A feedforward excitatory (E) model circuit with a single RG cell (light green) providing excitatory input to an LGN neuron (blue). **Bottom**: A 0.5 s simulation of the model circuit with a rectified sinusoidal input firing rate (yellow) with a peak rate (PR) of 100 Hz and an input modulation frequency (F) of 50 Hz; presynaptic spikes were generated with a Poisson process (dark green). The postsynaptic conductance (light green) and the membrane potential of the LGN cell (blue) are simulated in response to the RG input. LGN firing times are marked (red x), and the postsynaptic response is compared to the underlying input characteristics (dashed yellow). **(B)** Same, but for a paired feedforward excitatory/inhibitory (E/I) model circuit with a single RG cell (light green) providing excitatory input to an LGN neuron (blue) and to an interneuron (gray), which in turn provides delayed inhibitory input (1 ms) to the LGN neuron. **(C)** For a range of input modulation frequencies F, the Fourier coefficient of the output at F (FC_F) was averaged over 10 trials for triad synapse models with different inhibitory conductance characteristics. Legend entries indicate the length of the inhibitory time constant $\tau_{fall,I}$ for each paired feedforward E/I model; "excitatory" indicates the feedforward E model. Synaptic strengths were adjusted so that Fourier coefficients at input modulation 5 Hz were approximately 75 Hz. **(D)** Mean Fourier coefficient of the output over all frequencies. **(E)** Fourier coefficient of the output at F divided by the mean overall power (FC_F/FC_{avg}). Dashed line indicates FC_F/FC_{avg} = 1. **(F)** Same as C, except that synaptic strength P_{max} was adjusted to produce a range of Fourier coefficient values at an input modulation frequency at 5 Hz (weak to strong: red to dark blue). Solid lines indicate the feedforward E/I model, and dashed lines indicate the feedforward E model. In all cases, paired E/I input resulted in greater transmission at high input modulation frequencies than E input alone. **(G)** The influence of the inhibitory synaptic fall-off time constant $\tau_{fall,I}$ on transmission FC_F/FC_{avg}, measured at F = 50Hz (triangles) and 100Hz (squares). Dashed lines indicate feedforward E model at 50Hz (top) and 100Hz (bottom). The paired E/I configuration exhibits greater transmission over a range of inhibitory synaptic time constants. **(H)** The influence of the inhibitory synaptic fall-off time constant $\tau_{fall,I}$ on the input modulation frequency at which FC_F/FC_{avg} is ½(FC_F/FC_{avg} at F = 5Hz). Dashed line indicates the ½ cutoff for the feedforward E model. **(I)** For each paired feedforward E/I model shown in (F), the FC_F fold change with respect to the feedforward E model of matching response at F = 5Hz for F = 50Hz (triangles) and F = 100Hz (squares). Dashed line indicates a fold change of 1. **(J)** For each paired feedforward E/I model shown in (F), the ½ cutoff fold change with respect to the feedforward E model of matching output power (denoted by line style and FC_F at F = 5Hz) was calculated as FFEI/FFE. For the lowest firing rates, ½ cutoff was greater than 1000 Hz in the FFEI case (out of range). Dashed line indicates a fold change of 1. In all, paired E/I input allowed transmission of higher input modulation frequencies over a wide range of inhibitory synaptic time constants and for a wide range of synaptic input strengths.

Figure 2. Paired feed-forward E/I inputs allows transmission of higher input modulation frequencies compared to direct sinusoidal current injection. (A) Left: A model cell receiving direct injections of rectified sinusoidal currents at various frequencies. As input modulation frequency increases, the ability of the cell to follow the input decreases, and the cell is totally unable to spike in response to the input modulation frequency of 100 Hz. **(B)** Fourier coefficient of spiking output for a range of input modulation frequencies F for direct current injections (magenta), paired feedforward E/I model with $\tau_{fall,I}$ = 20ms (blue), and for the feedforward E model (red). **(C)** Same, except mean responses over all Fourier frequencies is shown (FC_{avg}). **(D)** The normalized output response (FC_F/FC_{avg}). Dashed line indicates FC_F/FC_{avg} = 1. When firing rates are matched at input modulation frequency of 5Hz, direct current injections provide more selective transmission for lower frequencies but paired feedforward E/I connections allow the cell to follow signals at higher frequencies than direct current injection.

Figure 3. The transmission of paired feedforward E/I inputs is dependent on the strength of inhibition. (A) 0.1 s simulations of single-input model circuits in response to a 100Hz spike train (topmost), in which the model LGN neuron is prevented from spiking. From left to right: feedforward E, paired feedforward E/I with inhibitory current scaled by α = 1, 1.25, 2, 5. The postsynaptic conductance, synaptic current, and membrane potential of the LGN neuron are simulated in response to the spike train input. Each simulation is shown 0.1s after the onset of spiking inputs. As the scaling on the inhibitory input increases, the inward current produced by each spike shortens in duration. **(B)** Fourier coefficient of spiking output for a range of input modulation frequencies F. Legend entries indicate the inhibitory current scaling coefficient α for each paired feedforward E/I model; "E only" indicates the feedforward E model. **(C)** Mean Fourier coefficient over all frequencies (FC_{avg}). **(D)** Normalized output response over a range of frequencies F. Dashed line indicates FC_F/FC_{avg} = 1. **(E)** The influence of scaling the inhibitory current by α on transmission FC_F/FC_{avg}, measured at F = 50Hz (triangles) and 100Hz (squares). Dashed lines indicate feedforward E model at 50Hz (top) and 100Hz (bottom). The paired feedforward E/I model exhibits greater transmission with stronger inhibition, plateauing at α = 1.5. **(F)** The influence of excitatory background noise on transmission FC_F/FC_{avg} with different levels of inhibitory scaling α, measured at F = 50Hz. Legend entries indicate relative background current strength. **(G)** Inhibitory scaling coefficients α that produced the strongest transmission for each background noise level shown in (F). For these models, moderate inhibition ($1.5 \leq \alpha \leq 2$) produces greater transmission when excitatory background noise is weak. As background noise becomes stronger, the model performs best with slightly scaled inhibition (α = 1.25).

Figure 4. The transmission of paired feedforward inputs is dependent on the timing of inhibition. (A) 3 single-input model circuits, in which the LGN neuron receives feedforward E/I inputs with different inhibitory delays Δ. Each model is simulated for 0.5s with input parameters F = 50Hz, PR = 100Hz. Postsynaptic conductance (excitatory: light green, inhibitory: gray) and the membrane potential of the LGN cell (blue) are simulated in response to RG and interneuron input. LGN firing times (red x) and postsynaptic response is compared to the underlying input characteristics (dashed yellow). From left to right: Δ = 1ms, 5ms, 20ms. **(B)** Fourier coefficient of spiking output for a range of input modulation frequencies F. Legend entries indicate the inhibitory delay for each paired feedforward E/I model; "E only" indicates the feedforward E model. **(C)** Mean responses over all Fourier frequencies (FC_{avg}). **(D)** The normalized output response (FC_F/FC_{avg}). Dashed line indicates FC_F/FC_{avg} = 1. **(E)** the input modulation frequency at which FC_F/FC_{avg} is ½(FC_F/FC_{avg} at F = 5Hz). Dashed line indicates the ½ cutoff for the feedforward E model. With a shorter inhibitory delay, the paired feedforward E/I model reliably transmits information at higher frequencies.

Figure 5. Paired feedforward E/I input allows time-locked high frequency computation across multiple brain layers or areas in the absence of an explicit external clock. (A) 3 model circuits exhibiting different forms of y=x transmission over 4 areas (A1-A4): no connections between areas (NC), feedforward E-only (FFE) connections, and paired feed-forward E/I (FFEI) connections. Each circuit receives the same Poisson input (yellow) at A1, with input firing rate a rectified sine wave of frequency F and amplitude PR (dark yellow). The circuits also receive 50 "internal" noisy Poisson excitatory inputs at A1-A4 (gray, left). Simulations (NC: green, FFE: red, FFEI: blue) with input parameters F = 5Hz, PR = 100Hz shown (repeated at bottom). **(B)** For a range of input modulation frequencies F, the Fourier coefficient of the A4 output at F (FC_F) was substantially higher for FFEI connections than for FFE connections. **(C)** Mean Fourier coefficient of the A4 output over all frequencies (FC_{avg}). **(D)** Normalized Fourier output for a range of input modulation frequencies F. Dashed line indicates $FC_F/FC_{avg} = 1$. FFEI allows the areas to follow computations at higher frequencies than FFE. **(E)** Same as C, except that synaptic strength P_{max} was adjusted to produce a range of Fourier coefficient values at an input modulation frequency at 5 Hz (weak to strong: red to dark blue). Solid lines indicate the feedforward E/I model, and dashed lines indicate the feedforward E model. **(F)** Summary data from E, showing fold change advantage of FFEI over FFE at F = 50 Hz (triangles) and F = 100 Hz (squares) for various synaptic strengths (FC_F at 5 Hz shown on x axis). Dashed line indicates 1. **(G)** Same, but fold change in the ½ cutoff shown. The ½ cutoff fold change could not be measured for the weakest FFEI/FFE pair in **(E)**, as the paired feedforward E/I model does not have a ½ cutoff within the range of considered F values. **(H)** For each paired feedforward E/I model shown in **(E)**, the FC_F fold change with respect to the model with no connections (noise only) is shown. Dashed line indicates a fold change of 1. **(I)** Over a 20 second trial, a rectified sinusoidal Poisson input with a changing input modulation frequency was provided to the circuits exhibiting FFE and FFEI connections. **(J)** The normalized Fourier spectrum of the A4 output with FFEI connections, averaged over 1 second bins. Spectrum is averaged over 50 trials. **(K)** Same as **(J)**, but with FFE connections, which cannot follow high frequencies.

Figure 6. Paired feedforward E/I allows high frequency computation in artificial neuromorphic circuits. (A) Model circuits utilizing either feedforward single-sign inputs only (center, top) or paired mixed-sign inputs (center, bottom) to perform an exclusive-or (XOR) computation. The cell in layer A2 fires only when either Poisson input i_1 or i_2 (dark yellow) is active, but not both. A 0.6s simulation of each model circuit with inputs driven out-of-phase (π) is shown with input parameters F = 5Hz, PR = 100Hz. The simulated output spikes of cells 1 and 2 in A1 and the cell in A2 are shown to the right for each model circuit (single-sign: red, mixed-sign: blue). The expected output of the XOR computation between i_1 and i_2 (purple), calculated in 10ms or 5ms windows, is shown below for comparison with A2 outputs. **(B)** A2 output Fourier coefficient at 2xF (FC_F) for a range of input modulation frequencies F. **(C)** A2 output mean Fourier coefficient. **(D)** A2 output normalized Fourier coefficient. Dashed line indicates FC_F/FC_{avg} = 1.

Figure 6 Supplement 1. Paired feedforward E/I in an XOR circuit, with $\pi/2$ phase-shifted inputs. (A) A simulation of each XOR model circuit described in Figure 6A is shown with inputs modeled as in Figure 6A, but with a $\pi/2$ phase shift instead of a π phase shift, which should result in output at the stimulus frequency F (instead of 2 x F when the phase shift is π). **(B)** For a range of input modulation frequencies F, the Fourier coefficient of the A2 output at F (FC_F) was averaged over 10 trials for the two XOR circuit models shown in **(A)**. **(C)** For a range of input modulation frequencies F, the mean power of the A2 output over all frequencies (FC_{avg}). **(D)** For a range of input modulation frequencies F, the normalized Fourier coefficient of the A2 output is shown. Dashed line indicates $FC_F/FC_{avg} = 1$.

Figure 7. Feedforward excitatory input that is restricted to AMPA channels allows high frequency computation but is less robust to noise compared to FFEI inputs. (A) 3 triad synapse models, in which the LGN neuron receives inputs via different sets of synaptic channels. Each model is simulated for 0.5s with input parameters F = 50Hz, PR = 100Hz. Postsynaptic conductance (excitatory: light green, inhibitory: gray) and the membrane potential of the LGN cell (blue) are simulated in response to RG and interneuron input. LGN firing times (red x) and postsynaptic response is compared to the underlying input characteristics (dashed yellow). Left: inputs are transmitted via AMPA channels only. Center: inputs are transmitted via AMPA and NMDA channels. Right: inputs are transmitted via AMPA, NMDA, and GABA channels. **(B)** Fourier coefficients (FC_F) for a range of input modulation frequencies F. **(C)** Fourier coefficients averaged over all response frequencies (FC_{avg}) for a range of input modulation frequencies F. **(D)** Normalized Fourier coefficients (FC_F/FC_{avg}). Dashed line indicates FC_F/FC_{avg} = 1. AMPA-only synapses, with their shorter time constants, allow transmission at higher frequencies than synapses with both AMPA and NMDA, and are comparable to AMPA-NMDA-GABA synapses for frequencies less than about 20 Hz. **(E)** In addition to the rectified sinusoidal Poisson input, the LGN cell receives 50 noisy Poisson excitatory inputs. Fourier coefficients (FC_F) are shown for a range of input modulation frequencies F; "noise only" denotes the absence of rectified sinusoidal input. **(F)** Same as **(C)**, but in the presence of LGN noise. **(G)** Same as **(D)**, but in the presence of LGN noise. FFEI slightly enhances transmission in the presence of noise compared to FFE with AMPA synapses alone.

Figure 8. Paired feedforward E/I in a multi-input model allows computations that are frequency-limited by the membrane time constant of the feedforward inhibitory neuron. (A) A paired feedforward E/I model circuit with 100 input cells (light green) providing excitatory input to a cortical neuron E (blue) and to an interneuron I (gray), which in turn provides inhibitory input to the cortical neuron. **(B)** 0.6s simulations of the model circuit with Poisson input parameters F = 5Hz (left), 20Hz (center), and 90Hz (right), and PR = 100Hz. The excitatory postsynaptic conductance (light green) in the I and E cells are simulated in response to the summed input. This excitatory input produces spiking of the I cell (dark gray), resulting in an inhibitory postsynaptic conductance in the E cell (light gray). The combination of excitatory and inhibitory inputs produces the observed spiking in the E cell (blue). Notably, there is an absence of inhibitory input to the E cell at 90Hz. **(C)** Fourier coefficient at input frequency F (FC_F) for a range of input modulation frequencies. Legend entries indicate the value of the interneuron membrane time constant $\tau_{m,I}$ for each paired feedforward E/I model; "E-only" indicates a feedforward E model, in which the interneuron is not present. **(D)** Fourier coefficients averaged over all response frequencies (FC_{avg}) for a range of input modulation frequencies F. **(E)** Normalized Fourier coefficients (FC_F/FC_{avg}). Dashed line indicates FC_F/FC_{avg} = 1. **(F)** Scaled FC_F/FC_{avg} values from (E) such that FC_F/FC_{avg} = 1 for F = 5Hz. The dashed line indicates FC_F/FC_{avg} = 0.5, and intersects with each FC_F/FC_{avg} curve at the ½ cutoff. **(G)** The $\tau_{m,I}$ dependence of the ½ cutoff. Dashed line indicates the ½ cutoff for the feedforward E model. **(H)** Percent difference in the ½ cutoff relative to the feedforward E model as a function of $\tau_{m,I}$. Circuit-level feedforward E/I input allows excitatory neurons to follow higher temporal frequencies than those receiving feedforward excitatory input alone, but the cut off frequency values are smaller than for the triad synapse, where the interneuron cell body integration does not intervene.

References

Abbott LF (1999) Lapicque's introduction of the integrate-and-fire model neuron (1907). Brain Res Bull 50:303-304.

Abbott LF, Varela JA, Sen K, Nelson SB (1997) Synaptic depression and cortical gain control. Science 275:220-224.

Abeles M (1991) Corticonics: Neural circuits of the cerebral cortex: Cambridge University Press.

Agmon A, Connors BW (1991) Thalamocortical responses of mouse somatosensory (barrel) cortex in vitro. Neuroscience 41:365-379.

Ahissar E, Sosnik R, Bagdasarian K, Haidarliu S (2001) Temporal frequency of whisker movement. II. Laminar organization of cortical representations. J Neurophysiol 86:354-367.

Bhatia A, Moza S, Bhalla US (2019) Precise excitation-inhibition balance controls gain and timing in the hippocampus. eLife 8.

Blitz DM, Regehr WG (2003) Retinogeniculate synaptic properties controlling spike number and timing in relay neurons. J Neurophysiol 90:2438-2450.

Blitz DM, Regehr WG (2005) Timing and specificity of feed-forward inhibition within the LGN. Neuron 45:917-928.

Boudreau CE, Ferster D (2005) Short-term depression in thalamocortical synapses of cat primary visual cortex. J Neurosci 25:7179-7190.

Buzsaki G (1984) Feed-forward inhibition in the hippocampal formation. Prog Neurobiol 22:131-153.

Carandini M, Heeger DJ, Senn W (2002) A synaptic explanation of suppression in visual cortex. J Neurosci 22:10053-10065.

Cardin JA (2018) Inhibitory Interneurons Regulate Temporal Precision and Correlations in Cortical Circuits. Trends Neurosci 41:689-700.

Cardin JA, Carlen M, Meletis K, Knoblich U, Zhang F, Deisseroth K, Tsai LH, Moore CI (2009) Driving fast-spiking cells induces gamma rhythm and controls sensory responses. Nature 459:663-667.

Chen C, Regehr WG (2000) Developmental remodeling of the retinogeniculate synapse. Neuron 28:955-966.

Chen C, Blitz DM, Regehr WG (2002) Contributions of receptor desensitization and saturation to plasticity at the retinogeniculate synapse. Neuron 33:779-788.

Chung S, Li X, Nelson SB (2002) Short-term depression at thalamocortical synapses contributes to rapid adaptation of cortical sensory responses in vivo. Neuron 34:437-446.

Cox CL, Zhou Q, Sherman SM (1998) Glutamate locally activates dendritic outputs of thalamic interneurons. Nature 394:478-482.

Crawford FS (1968) Waves (Berekely Physics Course, Vol. 3): McGraw-Hill.

Creutzfeldt O, Hellweg FC, Schreiner C (1980) Thalamocortical transformation of responses to complex auditory stimuli. Exp Brain Res 39:87-104.

Dayan P, Abbott LF (2001) Theoretical Neuroscience. Cambridge, MA: MIT Press.

Deisz RA, Prince DA (1989) Frequency-dependent depression of inhibition in guinea-pig neocortex in vitro by GABAB receptor feed-back on GABA release. J Physiol 412:513-541.

Economo MN, White JA (2012) Membrane properties and the balance between excitation and inhibition control gamma-frequency oscillations arising from feedback inhibition. PLoS Comput Biol 8:e1002354.

Fries P, Nikolic D, Singer W (2007) The gamma cycle. Trends Neurosci 30:309-316.

Frishman LJ, Schweitzer-Tong DE, Goldstein EB (1983) Velocity tuning of cells in dorsal lateral geniculate nucleus and retina of the cat. J Neurophysiol 50:1393-1414.

Gabernet L, Jadhav SP, Feldman DE, Carandini M, Scanziani M (2005) Somatosensory integration controlled by dynamic thalamocortical feed-forward inhibition. Neuron 48:315-327.

Hawken MJ, Shapley RM, Grosof DH (1996) Temporal-frequency selectivity in monkey visual cortex. Vis Neurosci 13:477-492.

Heimel JA, Van Hooser SD, Nelson SB (2005) Laminar organization of response properties in primary visual cortex of the gray squirrel (Sciurus carolinensis). J Neurophysiol 94:3538-3554.

Hennequin G, Agnes EJ, Vogels TP (2017) Inhibitory Plasticity: Balance, Control, and Codependence. Annu Rev Neurosci 40:557-579.

Higley MJ, Contreras D (2006) Balanced excitation and inhibition determine spike timing during frequency adaptation. J Neurosci 26:448-457.

Hirsch JA, Wang X, Sommer FT, Martinez LM (2015) How inhibitory circuits in the thalamus serve vision. Annu Rev Neurosci 38:309-329.

Hopfield JJ (1982) Neural Networks and Physical Systems with Emergent Collective Computational Abilities. Proc Natl Acad Sci USA 79:2554-2558.

Hopfield JJ, Tank DW (1986) Computing with Neural Circuits: A Model. Science 233:625-633.

Iaccarino HF, Singer AC, Martorell AJ, Rudenko A, Gao F, Gillingham TZ, Mathys H, Seo J, Kritskiy O, Abdurrob F, Adaikkan C, Canter RG, Rueda R, Brown EN, Boyden ES, Tsai LH (2016) Gamma frequency entrainment attenuates amyloid load and modifies microglia. Nature 540:230-235.

Lapicque L (1907) Recherches quantitatives sur l'excitation électrique des nerfs traitée comme une polarization. J Physiol Pathol Gen 9:620–635.

Lisman JE, Idiart MA (1995) Storage of 7 +/- 2 short-term memories in oscillatory subcycles. Science 267:1512-1515.

Lisman JE, Jensen O (2013) The theta-gamma neural code. Neuron 77:1002-1016.

Markram H, Tsodyks M (1996) Redistribution of synaptic efficacy between neocortical pyramidal neurons. Nature 382:807-810.

McCormick DA, Connors BW, Lighthall JW, Prince DA (1985) Comparative electrophysiology of pyramidal and sparsely spiny stellate neurons of the neocortex. J Neurophysiol 54:782-805.

Miller P (2016) Dynamical systems, attractors, and neural circuits. F1000Res 5.

Miller P, Brody CD, Romo R, Wang XJ (2003) A recurrent network model of somatosensory parametric working memory in the prefrontal cortex. Cereb Cortex 13:1208-1218.

Mittmann W, Koch U, Hausser M (2005) Feed-forward inhibition shapes the spike output of cerebellar Purkinje cells. J Physiol 563:369-378.

Murphy BK, Miller KD (2009) Balanced amplification: A new mechanism of selective amplification of neural activity patterns. Neuron 61:635-648.

Nakamura PA, Cramer KS (2011) Formation and maturation of the calyx of Held. Hear Res 276:70-78.

Porter JT, Johnson CK, Agmon A (2001) Diverse Types of Interneurons Generate Thalamus-Evoked Feedforward Inhibition in the Mouse Barrel Cortex. J Neurosci 21:2699-2710.

Pouille F, Scanziani M (2001) Enforcement of temporal fidelity in pyramidal cells by somatic feed-forward inhibition. Science 293:1159-1163.

Pouille F, Marin-Burgin A, Adesnik H, Atallah BV, Scanziani M (2009) Input normalization by global feedforward inhibition expands cortical dynamic range. Nat Neurosci 12:1577-1585.

Rock C, Apicella AJ (2015) Callosal projections drive neuronal-specific responses in the mouse auditory cortex. J Neurosci 35:6703-6713.

Seung HS, Lee DD, Reis BY, Tank DW (2000) Stability of the memory of eye position in a recurrent network of conductance-based model neurons. Neuron 26:259-271.

Shadlen MN, Newsome WT (1998) The variable discharge of cortical neurons: implications for connectivity, computation, and information coding. J Neurosci 18:3870-3896.

Sherwin J, Muraskin J, Sajda P (2012) You Can't Think and Hit at the Same Time: Neural Correlates of Baseball Pitch Classification. Frontiers in neuroscience 6:177.

Swadlow HA (2002) Thalamocortical control of feed-forward inhibition in awake somatosensory 'barrel' cortex. Philos Trans R Soc Lond B Biol Sci 357:1717-1727.

Swadlow HA (2003) Fast-spike interneurons and feedforward inhibition in awake sensory neocortex. Cereb Cortex 13:25-32.

Swadlow HA, Gusev AG (2000) The influence of single VB thalamocortical impulses on barrel columns of rabbit somatosensory cortex. J Neurophysiol 83:2802-2813.

Swadlow HA, Gusev AG, Bezdudnaya T (2002) Activation of a cortical column by a thalamocortical impulse. J Neurosci 22:7766-7773.

Swadlow HA, Bezdudnaya T, Gusev AG (2005) Spike timing and synaptic dynamics at the awake thalamocortical synapse. Prog Brain Res 149:91-105.

Thomson AM, West DC (1993) Fluctuations in pyramid-pyramid excitatory postsynaptic potentials modified by presynaptic firing pattern and postsynaptic membrane potential using paired intracellular recordings in rat neocortex. Neurosci 54:329-346.

Thorpe S, Fize D, Marlot C (1996) Speed of processing in the human visual system. Nature 381:520-522.

Tsodyks MV, Markram H (1997) The neural code between neocortical pyramidal neurons depends on neurotransmitter release probability. Proc Natl Acad Sci USA 94:719-723.

Usrey WM, Reppas JB, Reid RC (1998) Paired-spike interactions and synaptic efficacy of retinal inputs to the thalamus. Nature 395:384-387.

Van Hooser SD, Heimel JA, Nelson SB (2003) Receptive field properties and laminar organization of lateral geniculate nucleus in the gray squirrel (Sciurus carolinensis). J Neurophysiol 90:3398-3418.

Van Hooser SD, Roy A, Rhodes HJ, Culp JH, Fitzpatrick D (2013) Transformation of receptive field properties from lateral geniculate nucleus to superficial V1 in the tree shrew. J Neurosci 33:11494-11505.

van Rossum MC, Turrigiano GG, Nelson SB (2002) Fast propagation of firing rates through layered networks of noisy neurons. J Neurosci 22:1956-1966.

Varela JA, Sen K, Gibson J, Fost J, Abbott LF, Nelson SB (1997) A quantitative description of short-term plasticity at excitatory synapses in layer 2/3 of rat primary visual cortex. J Neurosci 17:7926-7940.

von Neumann J (1963) The computer and the brain: Yale University Press.

Wehr M, Zador AM (2003) Balanced inhibition underlies tuning and sharpens spike timing in auditory cortex. Nature 426:442-446.

Wehr M, Zador AM (2005) Synaptic mechanisms of forward suppression in rat auditory cortex. Neuron 47:437-445.

Werblin FS (2010) Six different roles for crossover inhibition in the retina: correcting the nonlinearities of synaptic transmission. Vis Neurosci 27:1-8.

Yang W, Carrasquillo Y, Hooks BM, Nerbonne JM, Burkhalter A (2013) Distinct balance of excitation and inhibition in an interareal feedforward and feedback circuit of mouse visual cortex. J Neurosci 33:17373-17384.

Figure 1

Figure 2

Figure 3

Figure 4

Figure 5

Figure 6

Figure 6 Supplement 1

Figure 7

Figure 8