1 A State Space Modeling Approach to

2 Real-Time Phase Estimation

3 Authors: Anirudh Wodeyar[1], Mark Schatza[2], Alik S. Widge[2,3], Uri T. Eden[1,4], Mark A. Kramer[1,4]

5 1. Department of Mathematics and Statistics, Boston University

6 2. Department of Psychiatry, University of Minnesota

7 3. Department of Neuroscience, University of Minnesota

8 4. Center for Systems Neuroscience, Boston University

9 Abstract

Brain rhythms have been proposed to facilitate brain function, with an especially important role
attributed to the phase of low frequency rhythms. Understanding the role of phase in neural
function requires interventions that perturb neural activity at a target phase, necessitating
estimation of phase in real-time. Current methods for real-time phase estimation rely on
bandpass filtering, which assumes narrowband signals and couples the signal and noise in the
phase estimate, adding noise to the phase and impairing detections of relationships between
phase and behavior. To address this, we propose a state space phase estimator for real-time
tracking of phase. By tracking the analytic signal as a latent state, this framework avoids the
requirement of bandpass filtering, separately models the signal and the noise, accounts for
rhythmic confounds, and provides credible intervals for the phase estimate. We demonstrate in
simulations that the state space phase estimator outperforms current state-of-the-art real-time
methods in the contexts of common confounds such as broadband rhythms, phase resets and
co-occurring rhythms. Finally, we show applications of this approach to in vivo data. The method
is available as a ready-to-use plug-in for the OpenEphys acquisition system, making it widely
available for use in experiments.

25 Introduction

Rhythms, consistently periodic voltage fluctuations, are an ubiquitous phenomenon
observed in brain electrophysiology across scales and species. Many studies have described a
relationship between rhythms and behavior (Buzsáki, 2006; Haegens & Zion Golumbic, 2018;
VanRullen, 2016). A prominent feature of rhythms proposed as relevant for neural processing is
the phase. Phase has been proposed to coordinate neural spiking locally and potentially,
through coherent networks, even globally (Fries, 2015; Maris et al., 2016). For example, the
phase of slow rhythms (3-15 Hz) has shown relationships to dynamics in perception (Busch et

al., 2009; Gaillard et al., 2020; Gregoriou et al., 2009; Helfrich et al., 2018). Phase-amplitude
synchrony is common (Canolty & Knight, 2010; Hyafil et al., 2015), and has been suggested to
change in neurodegenerative disease (Hemptinne et al., 2013). Cross-regional, low frequency
phase synchrony is consistently observed as a correlate of top-down executive control (Widge
et al., 2019). Most work examining the importance of phase for neural dynamics and behavior
has been correlative in nature. To better understand the functional relevance of the phase of a
rhythm requires an ability to monitor and perturb phase relationships in real-time.

Several methods exist to estimate phase in real-time (Blackwood et al., 2018; L. L. Chen
et al., 2013; Mansouri et al., 2017; Rivero & Ditterich, 2021; Rutishauser et al., 2013; Siegle &
Wilson, 2014; Zrenner et al., 2020). At their core, these methods rely on bandpass filtering, a
mechanism to forward predict data (using autoregressive models or linear extrapolation of
phase) and the Hilbert transform to estimate the phase. Brain rhythms are often non-sinusoidal
(Cole & Voytek, 2017) and broadband (Buzsaki, 2004; Roopun et al., 2008), making
development of an accurate bandpass filter difficult. While the contemporary modeling approach
using filters accurately estimates the phase across a range of contexts, several limitations exist
that limit the phase estimate accuracy (Matsuda & Komaki, 2017; Siegle & Wilson, 2014): (i) By
depending on bandpass filters, existing real-time phase estimators are susceptible to non-
sinusoidal distortions of the waveform, and inappropriate filter choices may miss the center
frequency or total bandwidth of the rhythm. (ii) Phase resets, moments when the phase slips
because of stimulus presentation or spontaneous dynamics, cannot be tracked using filters,
which control the maximum possible instantaneous frequency. (iii) By filtering the observed data
directly, these approaches do not model signal and noise processes separately. Phase
estimates thus represent signal and noise phase together. (iv) Many existing approaches
depend on buffered processing (e.g., Fourier or related transforms), meaning that current phase
estimates are delayed in ways that may not support real-time intervention. Further, buffer-based
processing is susceptible to edge effects that are not of concern in traditional, offline analysis.
(v) Contemporary approaches do not define a measure of confidence in the phase estimate.
Despite these limitations, real-time phase simulations using current techniques have produced
interesting results (Cagnan et al., 2017; Desideri et al., 2019; Hyman et al., 2003; Kundu et al.,
2014; Schaworonkow et al., 2018; Siegle & Wilson, 2014; Zrenner et al., 2018), motivating the
value of generating better methods to estimate phase causally.

To address the limitations of existing approaches, we implement here a dynamical
systems approach to real-time phase estimation. Rather than filtering the data to identify the
rhythm of interest, we focus on tracking the analytic signal (a complex valued entity,
representing the amplitude and phase of a rhythm (Kramer & Eden, 2016)) as a latent process
in the observed time series using a model proposed by (Matsuda & Komaki, 2017). In doing so,
we remove the requirement of bandpass filtering, and instead model the signal as a state space
harmonic oscillator (or combination of such oscillators) driven by noise. This modeling approach
allows: (1) a separate estimate of observation noise, (2) a procedure to model and reduce the
confounding activity of other rhythms, and (3) a principled method for assessing uncertainty in
the real-time phase estimates. After first fitting parameters of the state space harmonic oscillator
model acausally, the method then tracks the phase in real-time assuming spectral stationarity.
We call this approach the State Space Phase Estimate (SSPE).

To benchmark the SSPE technique against the current state-of-the-art methods of real-time phase estimation, we design several simulations and analyze case studies of *in vivo* data. We limit our comparison to the real-time methods proposed in Zrenner et al. (2020) and Blackwood et al. (2020), methods which provide an estimate of phase on receipt of each new sample of data and have readily available reference code. We additionally apply a standard method for non-real-time phase estimation (an acausal finite impulse response (FIR) filter followed by a Hilbert transform (Lepage et al., 2013)). We note that these and other existing real-time phase estimation techniques (L. L. Chen et al., 2013; Mansouri et al., 2017; Rivero & Ditterich, 2021; Rutishauser et al., 2013; Siegle & Wilson, 2014) apply a bandpass filter and forecasting technique, and, by that measure, the acausal FIR approach by utilizing more information suggests the room for improvement available for these estimators. We test the ability of these different methods to track the phase of rhythms with different spectral profiles - including narrowband rhythms, broadband rhythms, multiple rhythms, and rhythms with phase resets, and in different signal-to-noise settings. We show that the SSPE method outperforms the existing real-time phase estimation methods in almost all cases. Finally, we illustrate the application of the SSPE method to *in vivo* LFP and EEG recordings, demonstrate the utility of SSPE for predicting behavior, and introduce a plug-in of the SSPE method for OpenEphys (Siegle et al., 2017), making the method widely available for use in real-time experiments. Our work demonstrates that the SSPE method improves the ability to track phase accurately, in real-time, across a diverse set of contexts encountered in data.

Methods

State Space Model Framework

To estimate phase in real-time, we utilize a data-driven model (Matsuda & Komaki, 2017) that operates based on principles from dynamical systems and Markov models. This type of model (called a state space model) separates what is observed (called the observation equation) from what we wish to estimate (called the state equation). The state equation attempts to capture the underlying, unobserved dynamics of the system, while the observation equation transforms the state into the observed signal. We generate an optimal prediction for the state using a Kalman filter that compares the initial prediction of the observation with the actual observed value.

Each state variable represents an oscillator with a fixed frequency that undergoes small random perturbations. As these perturbations accumulate, the instantaneous phase and frequency of the oscillator become more uncertain, since the oscillator is not directly observed. We assume that the observed data are noisy versions of these oscillators. The state space model framework combines information from two models: 1) a state model that describes the oscillator dynamics, and 2) an observation model that describes how the oscillator generates the data. The methods we develop use both of these sources of information to optimally estimate the instantaneous frequency and phase of each oscillator at every moment in time.

We implement a linear state equation that models the *real* and *imaginary* part of the
complex valued analytic signal of rhythms present in the neural data. For each rhythm modeled,
the state equation dynamics rotate the analytic signal at that rhythm's frequency. The
observation equation sums the *real* part of the analytic signals of every modeled rhythm to
predict the observed neural activity. We treat as real-valued the real and imaginary parts of the
complex valued analytic signal for ease of analysis and interpretation. This state space model
structure allows us to derive the amplitude and phase of each modeled rhythm, and estimate
the analytic signal in the temporal domain, thus avoiding complications associated with
windowing (i.e., the need to choose large enough window sizes to support sufficient frequency
resolution and the associated unavoidable temporal delay in phase estimates) that occur in
related frequency domain approaches (Kim et al., 2018).

The state space model is linear in the state evolution (dynamics of state transitions) and
observation equations. Further, the covariance for the state (which determines the bandwidth for
the rhythms) and noise for the observation is Gaussian (white noise). These assumptions
(linearity and Gaussianity) imply that we can use the Kalman filter to correct the state estimate
based on the true observation (i.e., to filter the state) (Kalman, 1960). This type of modeling
approach has been successfully applied in many contexts to track latent structure from observed
data while accounting for state and observation noise effects (Brockwell et al., 2004; Eden et al.,
2018; Galka et al., 2004; Yousefi et al., 2019).

To illustrate this approach, we first consider the case of tracking a single, 6 Hz rhythm.
The state equation for this scenario is,

140
$$x_t = aO(\omega_j)x_{t-1} + u_t, u_t \sim N(0, Q)$$

141 where x_t has both a real and imaginary part. At time instant t-1, the modeled rhythm is in state
142 x_{t-1}, that is, the rhythm is at some point along its trajectory. The state equation provides a
143 prediction for the next point along this trajectory (x_t) by rotating the current state (x_{t-1}) and adding
144 noise (u_t). The rotation matrix $O(\omega)$ rotates the real and imaginary parts of the state by the amount
145 ω appropriate for a 6 Hz rhythm:

$$O(\omega) = \begin{pmatrix} \cos(\omega) & -\sin(\omega) \\ \sin(\omega) & \cos(\omega) \end{pmatrix}$$
147

148
$$\omega = 2\pi(6/Fs)$$

149 where Fs is the sampling frequency in Hz. After rotation, the state is scaled (or rather, damped)
150 by a factor a, and then Gaussian noise (with mean zero and variance Q) is added. We estimate
151 the observation at time t (y_t) as the real-part of the state at time t with additive noise:

152
$$y_t = Real(x_t) + \nu$$

where ν is Gaussian noise with mean 0 and variance σ^2. Note that this model for the state is akin
to a damped harmonic oscillator driven by noise, a model that has been shown to be relevant and
useful for gamma rhythms in the visual cortex (Burns et al., 2010; Spyropoulos et al., 2020) and
also for EEG (Franaszczuk & Blinowska, 1985).

To model N rhythms, we define **X** as the state variable, a *2N x T* matrix over total time *T*.
An individual time point with state X_t (*2N x 1* vector) is rotated according to each rhythm's (x_j^t, a
2 x 1 complex vector for rhythm *j*) central frequency ($\omega_j = 2\pi f_j \Delta t \in (0, \pi)$, where f_j is frequency
in Hz and Δt is sampling interval) and damped by a constant (a_j). For each rhythm x_j^t we define
θ_j^t as a scalar quantity tracking the phase, and **Θ** as a *N x T* matrix of phase values for all rhythms
over all time. For the N rhythms, **O** is the rotation matrix, a *2N x 2N* and block diagonal matrix,
defined by the central frequency of each rhythm. **A** is the scaling matrix, a diagonal *2N x 2N*
matrix, with scaling factor $a_j \in (0,1)$ to ensure stability, the same for each rhythm, and different
across rhythms. The driving noise for the state U is Gaussian, a *2N x T* matrix with covariance
structure **Q,** a *2N x 2N* diagonal matrix with the same variance for the real and imaginary parts of
each rhythm. The state is collapsed into the observation *Y*(a *T x 1* vector) through M (a *1 x 2N*
vector) which summates the real parts of the analytic signals of all rhythms. For any time point,
the observation y_t is a scalar. The noise for the observation v_t is Gaussian with covariance σ_R^2.
The model equations are:

$$X_t = [(x_t^1)^T, ..., (x_t^N)^T]$$

$$\tag{1}$$

$$x_t^j = a_j O(\omega_j) x_{t-1}^j + u_t^j, u_t^j \sim N(0, Q_j)$$

$$\theta_j^t = arg(x_j^t) \tag{2}$$

$$O(\omega_j) = \begin{pmatrix} \cos(\omega_j) & -\sin(\omega_j) \\ \sin(\omega_j) & \cos(\omega_j) \end{pmatrix} \quad Q_j = \begin{pmatrix} \sigma_j^2 & 0 \\ 0 & \sigma_j^2 \end{pmatrix} \tag{3}$$

$$y_t = MX_t + v_t, v_t \sim N(0, \sigma_R^2) \tag{4}$$

$$M = [1, 0, 1, 0, ...] \tag{5}$$

We note that the state (Q) and observation (σ_R^2) covariance matrices are estimated from
the data, as described below. While we term $x_j{}^t$ as tracking the analytic signal, this nomenclature
differs from the signal processing literature. In signal processing, the analytic signal is defined as
a signal that has zero power at negative frequencies. However, given the stochastic frequency
modulation permitted in the state vector $x_j{}^t$, we cannot guarantee that $x_j{}^t$ has zero power at
negative frequencies. Nevertheless, since for sufficiently complex signals there are (potentially)
several ways one could represent the dynamics of the amplitude and phase (Boashash, 1991;
Rosenblum et al., 1997), we use the term *analytic signal* here for ease of understanding our intent
with this model and comparing it to classical Hilbert-based methods.

Real-time Phase Estimation

We perform real-time estimation of phase as follows. First, we use an existing interval of
data to acausally fit the parameters of the state space model a_j, ω_j, Q_j, σ_R^2 using an
expectation-maximization (EM) algorithm as proposed by (Soulat et al., 2019); for details see
the Supplementary Information in (Soulat et al., 2019). Under the EM approach, optimization of
parameters follows a two step process. First, initial values for parameters are selected, usually
from prior knowledge such as an examination of the power spectrum of an initial data sample.
This allows the algorithm to estimate the expectations for the state and the observation.
Second, using the state and observation estimates, an analytic solution exists (Shumway &
Stoffer, 1982) for the parameters that maximizes the likelihood. We repeat the expectation and
maximization procedures until the parameter estimates do not change between two iterations
beyond a threshold. The rate of convergence of the EM algorithm (speed of computation)
depends on the initial parameter estimates and the signal-to-noise ratios of the rhythms present
in the signal.

In simulations, unless otherwise specified, we use the first 2 s of data to fit the model
parameters. With these model parameters estimated and fixed, we then apply a Kalman filter to
predict and update the state estimates, and estimate the phase and amplitude for each
oscillator, each representing a different rhythm, for every sample (Figure 1). We note that the
Kalman filter is an optimal filter, i.e., in the presence of Gaussian noise, the Kalman filter
achieves minimum error and is an unbiased estimate of the mean phase. However, if the noise
is not Gaussian, the Kalman filter remains the optimal linear filter for phase estimation under this
model. Given the stochastic frequency modulation that is possible under the model, the Kalman
filter is robust to small shifts in the central frequency of the rhythm.

We now define the stages of Kalman filtering. The state is initialized with zeros and the
state covariance to a diagonal matrix with 0.001 along the diagonal. To predict the future state
and state estimation error at time t prior to filtering (x_t^{t-1} and P_t^{t-1}) given the filtered state and
estimation error (x_{t-1}^{t-1} and P_{t-1}^{t-1}) from the previous sample (t-1), we compute:

$$x_t^{t-1} = aO(\omega)x_{t-1}^{t-1} \tag{6}$$

$$P_t^{t-1} = aO(\omega_j)P_{t-1}^{t-1}(aO(\omega_j))^T + Q \tag{7}$$

209   We then estimate the Kalman gain for the current sample (t):

$$K_t = P_t^{t-1}M^T(MP_t^{t-1}M^T + R)^{-1} \tag{8}$$

210   Finally, we filter the current sample using the Kalman gain to compute filtered state (x_t^t) and
211   state estimation error (P_t^t) at time t:

$$x_t^t = x_t^{t-1} + K_t(y_t - Mx_t^{t-1}) \tag{9}$$

$$P_t^t = P_t^{t-1} - K_t M P_t^{t-1}.\qquad\qquad(10)$$

The SSPE method also tracks the state estimation error (P_t^t), which allows estimation of
confidence in the mean phase estimates. To do so, we sample 10,000 samples from the
posterior distribution of each state *j*, and from this estimate the width of the 95% credible
intervals for the phase. The credible intervals are derived from the posterior distribution of the
state, which is Gaussian; however, following their transformation into angles, the intervals are
not constrained to be symmetric. Note that, alternatively, one could attempt to define a closed
form for the phase distribution to estimate confidence bounds, as we estimate the posterior
distribution for the analytic signal under the Kalman filter. However, this strategy requires an
expectation of asymptotic convergence and the assumption of independence of amplitude and
phase (Withers & Nadarajah, 2013).

AR-based Forecasting to Estimate Phase

While current techniques depend upon filtering to isolate a narrow band rhythm from which
to estimate phase, different methods exist to forecast the phase. One category of methods
forecasts the phase as a linear extrapolation from the current moment while assuming a singular
central frequency, which is estimated from the data (Rivero & Ditterich, 2021; Rutishauser et al.,
2013). Other methods estimate phase by using an autoregressive (AR) model. After estimating
the AR parameters (either asynchronously or synchronously), these methods forecast data to
limit filter edge effects, then use a filter and Hilbert transform to estimate phase (see Blackwood
et al., 2018 and Zrenner et al., 2020). We compare the SSPE to this latter set of techniques as
these are more flexible to variability in rhythms than methods that assume a constant central
frequency when estimating phase. We implement the version of the Zrenner et al. (2020)
algorithm accessible at https://github.com/bnplab/phastimate and term this method as *Zrenner*.
Please refer to Zrenner et al. (2020) for algorithm details. The Zrenner algorithm uses an FIR
filter (applied forward and backward) and the Hilbert transform as the core phase estimation
technique. The AR model used to forecast the data and allow real-time phase estimation (by
expanding the window for the FIR filter) is fitted to the 30th order and efficiently updated on every
new sample. Compared to the default settings, we set the algorithm to track a 6 Hz rhythm by
increasing the window size for the FIR filter to 750 ms, the filter order to 192, and the frequency
band to 4 to 8 Hz. We utilize the implementation of the Blackwood et al. (2018) algorithm as
provided by the authors. In Blackwood et al (2018), the authors develop a forward bandpass filter
- AR-based (5th order AR model whose parameters are fit every second) forecasting and then
the Hilbert transform - to compute the phase. Here, we instead apply a Hilbert transformer (of
order 18) that estimates the phase by directly computing the Hilbert transform while filtering the
data as implemented in (Blackwood, 2019). We do so because this implementation is more
computationally efficient, functionally equivalent to the original method, and the code is made
widely available. We verified in sample data that application of the original and modified
Blackwood methods produced consistent phase estimates. We refer to this method as
Blackwood.

Figure 1*: **Illustration of State Space Phase Estimate (SSPE) procedure.** Given an observation (**A**, red), we estimate model parameters in an initial interval of data. At subsequent times, we use the*

*observed data to (**B**) predict and update the state estimate (purple), and (**C**) the phase and credible intervals, causally estimated. Note that prediction can be done for any time after parameter estimation; here we show a representative time interval. (**D**) Conceptual diagram of the steps involved in the SSPE method.*

Non-Causal Phase Estimation

Existing studies compare causal, real-time phase estimation approaches to an acausal
estimate of phase computed by applying an (acausal) FIR filter and the Hilbert transform
(Blackwood et al., 2018; L. L. Chen et al., 2013; Zrenner et al., 2020). To maintain consistency
with the existing literature, we do so here and apply a least-squares linear-phase FIR filter of
order 750, with bandpass 4 to 8 Hz. After forward and backward filtering of the data (using
MATLAB's *filtfilt* function), we apply the Hilbert transform to compute the analytic signal (using
MATLAB's *hilbert* function). We estimate phase using the four-quadrant arctan function
implemented by MATLAB's *angle* function and estimate the amplitude envelope using
MATLAB's *abs* function. We use the *angle* function throughout the analysis to estimate the
phase from a complex valued analytic signal. This acausal estimate of phase has been
proposed to serve as a lower-bound in phase estimation error for methods that apply a filter-
based approach to real-time phase estimation (Zrenner et al., 2020).

Defining Error as Circular Standard Deviation

265   Identifying a common error metric across alternative algorithms to causally estimate
266   phase is crucial for accurate comparison. We follow Zrenner et al. (2020) and use the circular
267   standard deviation of the difference between the estimated phase and true phase:

$$CircSD = \sqrt{-2\log(|\exp\left(\frac{1}{n}\sum_{k=1}^{n}(i\theta - i\hat{\theta})\right)|)} \tag{11}$$

270   where *n* is number of samples, θ is true phase, $\hat{\theta}$ is the phase estimate, and | | indicates the
271   absolute value. We transform the final result from radians to degrees. The circular standard
272   deviation (a transformed version of the phase locking value) captures the variance in the circular
273   error for the phase estimate and ignores any potential bias (non-zero mean shift).

Simulated data

Narrow Band to Broad Band Rhythms

Our initial simulation tests the capability of different real-time phase estimators to track
different frequency band profiles. We shift the bandwidth of the target rhythm from narrow
(sharply peaked in the spectral domain at 6 Hz) to wide (broadly peaked in the spectral domain;

peak bandwidth 4 - 8 Hz). We simulate all rhythms for 10 s at a sampling rate of 1000 Hz, with a
central frequency of 6 Hz. For each simulated rhythm, we apply each phase estimation method,
as described in Results.

The first type of rhythm we simulate is a pure sinusoid with added white noise:

$$Y = 10\cos(2\pi * 6 * T) + \epsilon_1$$

$$\epsilon_1 \sim N(0, 1)$$

(12)

286   where T is time, and $N(0,1)$ indicates a standard normal distribution. The second type of rhythm
287   we simulate is a pure sinusoid with added pink noise, i.e., the power spectral density (PSD) of
288   the noise decreases with the reciprocal of frequency (f):

$$Y = 10\cos(2\pi * 6 * T) + \epsilon_1$$

$$PSD(\epsilon_1(f)) \sim \frac{1}{f^{1.5}}.$$

(13)

The third type of rhythm we simulate is filtered pink noise with added pink noise. To
create a broadband spectral peak, we apply the same FIR filter utilized in the acausal phase
estimation analysis (see *Methods: Non-Causal Phase Estimation*) to pink noise ($PSD \sim 1/f^{1.5}$),
normalizing by the standard deviation and amplifying the resulting signal 10-fold. The resulting
signal consists of a broad spectral peak centered at 6 Hz. To this broadband signal we again
add independent pink noise (ϵ_1) as in Equation (13).

For the final rhythm we simulate a signal y_t from the SSPE model (see *Methods: State
Space Model Framework*) which is non-sinusoidal and broadband. The state in the state space
model is an auto-regressive model of order 2 (West 1997a) (equivalently, a damped harmonic
oscillator driven by noise), which has been proposed to capture features of gamma rhythms in
visual cortex and rhythms in EEG (Franaszczuk and Blinowska 1985, Xing et al., 2012, Burns et
al. 2010, Spyropoulos et al. 2020). The addition of observation noise under the state space
model can be analogized to measurement noise. Thus, the State Space Model provides a
simple possible model for brain rhythms observed in electrophysiological data. For the model,
we fix one latent state (j=1) with frequency 6 Hz ($\omega_j = 6$), and set *a* (scaling factor) = *0.99*,
variance *Q = 10,* and observation noise variance (σ_R^2) to 1. For this rhythm, phase was

estimated from the state directly as described in *Methods: State Space Model Framework*. We
show example instances of all four simulated rhythm types in Figure 2A.

Two Simultaneous Rhythms With Nearby Frequencies

In many physiologic use cases (Tort et al., 2010; VanRullen, 2016), we may wish to
track one rhythm while ignoring another at a nearby frequency. This may occur because of low
spatial resolution (e.g., from mixing of signals due to volume conduction (Nunez & Srinivasan,
2006)) or because there exist overlapping neural populations expressing different rhythms
(Kocsis et al., 1999). To simulate this case, we consider two sinusoids. We define the target
rhythm to track as a 6 Hz sinusoid with consistent amplitude. We define the confounding rhythm
as a sinusoid with varying frequency and amplitude. We define the observation (signal plus
noise) as:

$$Y = 25\cos(2\pi * 6 * T) + A * 25\cos(2\pi * F * T + \frac{\pi}{4}) + \epsilon_1 \tag{14}$$

$$\epsilon_1 \sim N(0, 0.5)$$

322   where $A \in [0.2, 2]$ and $F \in [1, 11]$. The confounding rhythm frequency assumes a range of
323   integer values from 1 to 11 Hz. The confounding rhythm amplitude ranges from 0.2 to 2 times
324   the amplitude of the target rhythm, in increments of 0.2.

Phase Reset

Ongoing slow rhythms in the brain occasionally undergo a sudden shift in phase. This
can occur both in response to a stimulus or as a result of ongoing spontaneous neural dynamics
(Voloh & Womelsdorf, 2016). To simulate sudden changes in a rhythm's phase, we implement a
pure sinusoid (6 Hz) with additive pink noise and impose phase slips at four distinct time points,
separated by at least 1 s. We fix the extent of phase slip, relative to the previous phase, at $\pi/2$.
However, the phase at which the slip occurs differs across the four time points (see example in
Figure 4A). We simulate the signal in five intervals, as follows:

$$Y(0 < T < 3.5) = 10\cos(2\pi * 6 * T) + \epsilon_1$$

$$Y(3.5 < T < 4.75) = 10\cos(2\pi * 6 * (T - 3.5) + \frac{\pi}{2}) + \epsilon_1 \tag{15}$$

$$Y(4.75 < T < 6.5) = 10\cos(2\pi * 6 * (T - 4.75)) + \epsilon_1$$

$$Y(6.5 < T < 8.75) = 10\cos(2\pi * 6 * (T - 6.5) + \frac{\pi}{2}) + \epsilon_1$$

$$Y(8.75 < T < 10) = 10\cos(2\pi * 6 * (T - 8.75)) + \epsilon_1$$

$$PSD(\epsilon_1(f)) \sim \frac{1}{f^{1.5}}$$

Signal to Noise Ratio

335　　　To investigate the impact of signal-to-noise ratio (SNR) on phase estimation, we again
336　simulate a filtered pink noise signal (centered at 6 Hz) with added pink noise (the third type of
337　rhythm simulated in *Methods: Narrow Band to Broad Band Rhythms*). To modulate the SNR, we
338　first compute,

340
$$\mathrm{SNR}_0 = \sigma_\mathrm{signal} / \sigma_\mathrm{noise}$$

342　where σ_signal (σ_noise) is the standard deviation of the filtered pink noise signal (added pink
343　noise). We then divide the filtered pink noise signal by SNR_0, multiply the filtered pink noise
344　signal by the chosen SNR (1, 2.5, 5, 7.5, 10), and add this scaled signal to the pink noise.

In vivo Data

We consider two datasets to demonstrate how the SSPE method performs *in vivo*. The
first dataset consists of local field potential (LFP) activity collected from the infralimbic cortex in
rats. LFP were acquired continuously at 30 kHz (OpenEphys, Cambridge, MA, USA). An
adaptor connected the recording head stage (RHD 2132, Intan Technologies LLC, Los Angeles,
CA, USA) to two Mill-max male-male connectors (8 channels each, Part number: ED90267-ND,
Digi-Key Electronics, Thief River Falls, MN, USA). For additional details on data collection,
please refer to (Lo et al., 2020). We analyze here 250 s of LFP data from one channel. Before
real-time phase estimation, we downsample the data to 1000 Hz (with a low pass filter at 100
Hz to prevent aliasing) for computational speed. To model these data, we fit three oscillators
with the SSPE method, with the goal of tracking a target theta rhythm (defined as 4 - 11 Hz).
Motivated by an initial spectral analysis of these data, we choose one oscillator to capture low
frequency delta band activity ($\omega_j = 1$ Hz, based on spectral peak), one to capture the theta band
rhythm of interest ($\omega_j = 7$ Hz), and a final oscillator to track high frequency activity ($\omega_j = 40$ Hz).
We estimate these model parameters (so center frequencies may change) using the first 10 s of
LFP data, and then fix these model parameters to estimate future phase values (up to 250 s). In
doing so, we assume that the same oscillator models in the SSPE method remain appropriate
for the entire duration of the LFP recording.

The second dataset was derived from the publicly available data in Zrenner et al. (2020).
The data consist of spatially filtered and downsampled scalp electroencephalogram (EEG)
recordings from electrode C3 (over central areas), which records a strong somatosensory mu
rhythm (8-13 Hz). For details on data collection and preprocessing, see Zrenner et al. (2020).
We analyze 250 s of data from a single participant for demonstration purposes. For these data,
before the real-time phase estimation step, we first apply a moving average causal filter (using 3
s of past data for each new data point) to remove slow drifts. We again track three oscillators in
the SSPE method, with the goal of estimating phase from the mu rhythm: one in the delta band
($\omega_j = 2$ Hz), one centered at the mu rhythm ($\omega_j = 10$ Hz), and one in the beta band ($\omega_j = 22$
Hz). We note that these frequency values initialize the model, and are then tracked in time. In
analyzing the mu rhythm, we ensured that phase was estimated from an oscillator whose
frequency was in the mu rhythm range, i.e., 8-12 Hz.

For the *in vivo* data, the true phase is unknown. To estimate phase error, we define the
true phase as follows: first, we select a 10 s segment centered on the 1 s interval of the phase
estimate. We then fit the state space model (Equations (1)-(4)) acausally to this 10 s segment
and estimate the phase in the 1 s interval at the segment's center. We note that here, the phase
estimate is acausal because we use forward and backward smoothing of the state estimate
when estimating the analytic signal. We also note that, in some segments, the frequency band
of interest may not be identified through EM due to low signal strength. When this occurred, we
omit error in the phase estimates, as these intervals lack the frequency of interest.

Real-time Implementation in TORTE

To make SSPE more broadly available, we implemented SSPE into the real-time
TORTE (Toolkit for Oscillatory Real-time Tracking and Estimation) system
(https://github.com/tne-lab/phase-calculator, 10.5281/zenodo.2633295). TORTE is built upon
the Open Ephys platform (https://open-ephys.org/), and can be used with a broad range of
electrophysiologic acquisition devices. Phase outputs and triggers from the system can be used
to drive presentation of psychophysical stimuli or delivery of optical/electrical/magnetic
stimulation. We directly integrated the MATLAB based SSPE algorithm described above into
C++ for improved efficiency. TORTE uses a buffer based approach to receive data, based on
the buffered approach of the underlying Open Ephys system. New buffers are repeatedly
received by TORTE containing the most recent neural data. These buffers are subject to system
latency causing a delay between activity in the brain being received by the toolkit. Both the
buffer size and latency individually vary from microseconds to a few milliseconds depending on
the acquisition system used. The phase of each sample within the buffer is estimated using
SSPE. A detector continuously monitors the estimated phase and can trigger output logic at any
desired phase. We note that the observation noise parameter (Q) is defaulted to 50, but should
be updated by the user to the square root of the amplitude. Two modifications were needed to
integrate SSPE into TORTE. For computational efficiency, data were downsampled before
application of the SSPE algorithm, and then the resulting phase estimates were upsampled
back to the native sampling rate. The Open Ephys system can provide buffer sizes that are not
exactly divisible into downsampled buffers. When this occurs, the phase estimates at the end of
the upsampled buffer cannot be generated from the downsampled SSPE result. To account for
this, an additional predicted state sample (with credible intervals) is computed by forward

filtering using equations 6 and 7. This extra value is inserted at the end of the downsampled
buffer. This provides an extra data point in the SSPE result that can be used to generate the
remainder of samples for the upsampled phase output buffer. The second modification results
from the real-time data acquisition by TORTE. In this case, low pass filtering must be causal,
not the acausal (i.e., forward-backward filtering) used in the MATLAB implementation. To
account for the consistent phase shift introduced in a real-time system, TORTE includes an
online learning algorithm that adjusts target phase thresholding to improve event timings in
closed loop applications. We test the real-time implementation on an AMD FX-8350 CPU with
16GB RAM.

Code availability

418   The code to perform this analysis is available for reuse and further development at
419 (MATLAB) https://github.com/wodeyara/stateSpacePhasePredictor and (OpenEphys)
420 https://github.com/tne-lab/phase-calculator.

Results

We first examine in simulations the viability of different causal phase estimation
algorithms, and how these existing methods compare to the proposed method - the state space
phase estimator (SSPE). In these simulations, we vary the nature of the underlying rhythm of
interest - either the spectral bandwidth or the noise/confounding signal present. Through these
simulations, we examine the assumptions under which different methods perform best at
estimating the phase in real-time. We then illustrate the application of the SSPE method to *in vivo*
data in two case studies: a rodent local field potential, and a human electroencephalogram (EEG).

SSPE accurately tracks the phase of a single oscillation

To test the accuracy of causal estimates of phase, we simulate rhythms with different
spectral profiles in four different ways. For the first two rhythms, we simulate a 6 Hz sinusoid and
add either white noise (constant power spectrum, "Sine in White Noise", Figure 2A.i) or pink noise
(power spectrum decreases with the reciprocal of frequency, "Sine in Pink Noise", Figure 2A.ii).
For the next simulation scenario, to generate a broadband spectral peak, we filter pink noise into
the band of interest using an FIR filter (4-8 Hz, "Filtered Pink Noise", see *Methods*), amplify this
signal, and then add additional (unfiltered) pink noise (Figure 2A.iii). For the last simulation, to
generate the signal of interest we sample data from the model underlying the SSPE method. The
state space harmonic oscillator model ("State Space Model") consists of a damped harmonic
oscillator driven by noise (the signal) with additive white noise (Figure 2A.iv). We note that, for
the first two simulation approaches in which the signal is a pure sinusoid, the true phase is known.
For the "Filtered Pink Noise" simulation, we estimate the phase by applying the Hilbert transform
to the signal before adding noise (see *Methods*). For the "State Space Model" simulation, we
determine phase directly from the model (see *Methods*). Thus, in all simulation scenarios, we
have an independent measure of the true phase.

We repeat each simulation 1000 times with different noise instantiations, and calculate
error as the circular variance of the difference between the estimated phase and true phase (see
Methods). We find that for rhythms with narrowband spectral peaks (Sine in White Noise and Sine
in Pink Noise, Figure 2B,C), all estimators perform well, and those estimators that presume a
narrow band signal (i.e., the filter based approaches) perform best. However, for rhythms with
broad spectral peaks (Filtered Pink Noise and State Space Model, Figure 2B,C), the SSPE
method outperforms the other causal approaches. Moreover, the SSPE method performs as well
as (Filtered Pink Noise), or better than (State Space Model), the acausal FIR method. In what
follows, we further explore the implications of this result, and the impact on assessment of phase
estimator performance. We conclude that the SSPE method performs well in all four simulation
scenarios, and outperforms existing causal phase estimation methods in two instances with broad
spectral peaks.

Figure 2: Wide band rhythm's phase better tracked with SSPE. ***(A)*** *Example 2 s of simulated
observed data (thick curves) and the true phase (thin blue curves) for each scenario.* ***(B)*** *For each
scenario, example spectra of (B.i) the signal, and (B.ii) the observation (i.e., signal plus noise). Spectra
were estimated for 10 s segments using the function "pmtm" in MATLAB, to compute a multitaper
estimate with frequency resolution 1 Hz and 9 tapers.* ***(C)*** *The phase error for each estimation method
(see legend) and simulation scenario. In each box plot, the central mark indicates the median; the
bottom and top edges of the box indicate the 25th and 75th percentiles, respectively; the whiskers
indicate the most extreme data points not considered outliers.*

SSPE accurately tracks the phase of two simultaneous oscillations.

To replicate a situation that has been documented in EEG (e.g., multiple alpha rhythms coexisting) (VanRullen, 2016) and in LFP (e.g., multiple theta/alpha rhythms in hippocampus) (Tort et al., 2010), we simulate two rhythms with similar frequencies. In this situation, phase estimation requires an approach to identify the presence of two rhythms and target the rhythm of interest. This simulation examines the impact of choosing a specific, previously specified, frequency response to isolate the rhythm of interest, as required by the two comparative causal phase estimation methods implemented here. In some cases, a finely tuned bandpass filter may separate the two rhythms, although such a filter requires sufficient prior knowledge and may be difficult to construct, particularly if the center frequencies are not perfectly stationary. The SSPE method provides an alternative approach to identify the two (or potentially more) rhythms without filtering and then allows tracking of the appropriate target rhythm. Further, while we focus on the phase of the target rhythm here, we note that the SSPE method provides estimates of the amplitude and phase of all modeled rhythms.

To illustrate this scenario, we simulate two slow rhythms at different frequencies. We set the target rhythm as a 6 Hz sinusoid with fixed amplitude, and the confounding rhythm as a 5 Hz sinusoid with 1.5 times the 6 Hz amplitude (Figure 3A). The observed signal consists of the combined target and confounding rhythms, plus white noise, simulated for 15 seconds. We apply each phase estimation method to the observed signal, and estimate the phase of the target rhythm after fitting parameters with 5 seconds of initial data. Visual inspection for this example (Figure 3B) suggests that only the SSPE method accurately tracks the target phase.

Repeating this analysis with the confounding amplitude and frequency varied across a range of values (frequencies 1-11 Hz, and amplitudes 20% to 200% of the target rhythm; see *Methods*) we find consistent results. For all methods, the error increases as the frequency of the confounding rhythm approaches the frequency of the target rhythm (6 Hz, Figure 3C). However, the increased error is restricted to a narrower frequency interval for the SSPE method. For the existing causal phase estimators, the error likely reflects choices in the filtering procedure (i.e., type of filter, features of passband and stopband, window size, see (Sameni & Seraj, 2017)) and modeling procedure (i.e., AR order, number of samples forecasted (L. L. Chen et al., 2013; Zrenner et al., 2020)). Similarly, for the acausal FIR estimator, the error likely reflects the filter passband of 4-8 Hz, with increasing error as the confounding rhythm nears the 6 Hz target rhythm. For the existing causal and acausal methods, error also increases as the confounding oscillation amplitude increases (Figure 3C).

Previously, we showed that all estimation methods performed well for a signal consisting of a single sinusoid in white noise (see Figure 2, Sine in White Noise). Here, we show that for a signal consisting of two sinusoids in white noise, the SSPE method outperforms the existing methods. Unlike these existing methods, the SSPE method estimates parameters for both the

503   target and confounding rhythms, and tracks each oscillation independently. By doing so, the
504   SSPE method accounts for the confounding effect of the nearby oscillation, and allows more
505   accurate tracking of the target rhythm. We conclude that the SSPE method outperforms these
506   existing methods in the case of two simultaneous rhythms with nearby frequencies.

Figure 3. SSPE performs well when two oscillations exist at nearby frequencies. (A)
Example observed signal (black) and phase for two simulated rhythms, the confounding
rhythm at 5 Hz (blue) and the target rhythm at 6 Hz (red). ***(B)*** *Example phase estimates for*

*the target rhythm in (A) using four different approaches (see legend). **(C)** Estimation error (circular standard deviation, see scale bars) for each estimation method as a function of frequency and amplitude of the confounding oscillation. In all cases the error increases as the frequency of the confounding oscillation approaches 6 Hz (the frequency of the target oscillation), and as the amplitude of the confounding oscillation increases.*

Phase estimation following phase reset

Phase resets are defined as consecutive samples of data that show a sudden shift in the oscillatory phase, proposed to represent the presence of synchronization of a neural mass in response to a stimulus, for example (Lakatos et al., 2009). Phase resets are common and well documented in electrophysiological recordings (Fiebelkorn et al., 2011; Makeig et al., 2004). Recent work delivering electrical stimulation based on phase of the theta rhythm has been forced to avoid segments with phase resets to reduce error in real-time phase estimation (Gordon et al., 2021). Further, accurate tracking of phase resets would provide better evidence for the relevance of phase resetting in generating event related potentials (Sauseng et al., 2007) - an analysis that could also be performed acausally. We examine the performance of each phase estimation method in the presence of simulated phase resets.

To do so, we simulate phase reset as a shift in the phase of a 6 Hz sinusoid by 90 degrees at four points in a 10 s signal (example in Figure 4A). We then compute the error of each phase estimation method in the 167 ms (one period of a 6 Hz rhythm) following the phase reset. Visual inspection of an example phase reset (Figure 4B) suggests that only the SSPE method accurately tracks the phase in the interval following the reset. We note that we fit SSPE parameters using an initial 2 s interval containing no phase resets (Eq. 15). Repeating this analysis for 1000 simulated signals (4000 total phase resets), we find consistent results; the error of the SSPE method is significantly lower than the error of the other methods (p ~ 0 in all cases using two-sided t-test, see Table 1). These results demonstrate that the existing causal and acausal methods implemented here are unable to estimate the phase accurately immediately after a phase reset. To determine how quickly each method returned to accurate phase estimation, we first estimated the pre-stimulus average error for each method, prior to the first phase reset, over a 500 ms interval. We then determined the time between each subsequent phase reset and the moment when the error reduced to 1.5 times the pre-stimulus error. Note that the level of pre-stimulus error differs across methods, so, for example, we determine when the SSPE converges to a lower error than the Blackwood method. We find that each method eventually converged to accurate phase estimation after a phase reset, with the SSPE method converging most rapidly (Table 1). The differences between methods likely result from the windowing used by each method when estimating the phase; smaller windows will lead to less impact of the phase reset on the error (as seen with the Blackwood approach converging more quickly than the Zrenner method), with the SSPE needing a window of a single sample.

We note that these existing methods all require a bandpass filtering step, which limits the fastest rate at which the phase can change (instantaneous frequency (Boashash, 1991)). The SSPE method, however, does not require the phase change within a limited range of instantaneous frequencies, and therefore can track rapid changes in phase. We conclude that the

545   SSPE method is able to most rapidly track the true phase after a phase reset, and thus provides
546   the most accurate estimate.

	SSPE	**Blackwood**	**Zrenner**	**acausal FIR**
Error (Std. Dev)	2.85 (0.89)***	62.08 (0.38)	44.68 (0.38)	15.04 (0.23)
Time to Convergence (Std. Dev.)	*34 ms (162)*	*190 ms (33)*	*747 ms (22)*	*555 ms (206)*

*** p~0 compared to all other methods

Table 1: Error following phase reset for different phase estimation methods. *The SSPE method tracks phase resets with error near zero,* and rapidly converges to accurate phase estimation following a phase reset*.*

Figure 4. The SSPE accurately tracks phase following a phase reset. (A) Example phase of a 6 Hz sinusoid (blue) with 4 phase resets (red dashed lines). (B) Example phase estimates (thin curves) and the true phase (thick blue curve) at the indicated phase reset in (A). The SSPE method (in green) tracks the true phase much more closely than other methods following a phase reset.

Phase estimation with different signal-to-noise ratios

To demonstrate the impact of noise on phase estimation we simulate signals with different signal-to-noise ratios. To generate a signal we filter pink noise into the band of interest (see *Methods: Signal to Noise Ratio*), and then add additional (unfiltered) pink noise. The ratio

of the standard deviations of the signal and noise defines the signal-to-noise ratio (SNR); we
modulate the standard deviation of the signal to achieve the desired SNR. Finally, we normalize
the full observation so that amplitudes across simulations are consistent. In these simulations
the SNR varies from 1 (signal and noise have the same total power) to 10 (signal has 100 times
the total power of the noise); see example traces of the observation under each SNR in Figure
5A.i - iv. We repeat each simulation 1000 times with different noise instantiations for each signal
to noise ratio.

We compute two metrics to characterize the impact of signal-to-noise on phase
estimation. First, we consider the credible intervals estimated by the SSPE, here measured as
the average credible interval width throughout a simulation. As expected, the credible intervals
track with the SNR (Figure 5B.i); signals with higher SNR correspond to smaller credible
intervals. Computing the average amplitude (as derived from the acausal FIR, see *Methods:*
Non-Causal Phase Estimation) throughout each simulation, we find no overlap between the
distributions of amplitudes at SNR=1 and SNR=2.5 (5B.ii), while the distributions of credible
intervals overlap. This suggests that, at low SNR, an arbitrary amplitude threshold (e.g.,
amplitude > 1) would eliminate all data at SNR=1 and preserve all data at SNR=2.5.
Alternatively, using the credible interval width allows identification of transient periods of
confidence (e.g., credible interval width < 40 degrees) at both SNR values. We also note that
the credible interval width - in units of degrees - provides a more intuitive threshold than the
amplitude, whose intrinsic meaning at any particular value is only understood relatively. These
results suggest that, in this simulation study, amplitude serves as a less accurate criterion for
confidence in phase compared to the credible interval width.

Second, we consider the error in phase estimates using four different phase estimation
methods (Figure 5C). We find that the error for the SSPE method reduces more quickly than for
the other methods, and at a SNR of 1, the SSPE method is comparable to or better than the
contemporary methods of real-time phase estimation. At SNR = 10, the error in the SSPE phase
estimation is comparable to the acausal FIR, while the alternative real-time algorithms continue
to perform with error similar to an SNR of 1. These results suggest that, for the two existing real-
time phase estimation methods, broadband rhythms are difficult to track even with high SNR,
consistent with Figure 2C.

Figure 5: SSPE tracks an oscillatory signal with less error across a range of signal to
noise ratios. **(A)** *Example 2 s of simulated observed data (thick curves) and true phase (thin blue*
*curves) for each SNR value. **(B)** For each SNR, (i) the average credible interval width (colored circles) of*
the SSPE method for all simulation iterations, and (ii) the average amplitude of the estimated signal
(colored circles) for all simulation iterations. White circles (horizontal gray lines) indicate median (25th and
*75th percentiles) values for each SNR. **(C)** The phase error for each estimation method (see legend) and*
simulation SNR. In each box plot, the central mark indicates the median; the bottom and top edges of the
box indicate the 25th and 75th percentiles, respectively; the whiskers indicate the most extreme data
points not considered outliers.

Example *in vivo* application: rodent LFP

Having confirmed the SSPE method performs well in simulation, we now illustrate its
performance in example *in vivo* recordings. We first apply the SSPE method to an example LFP
recording from rodent infralimbic cortex (see *Methods*), which contains frequent intervals of theta
band (4-8 Hz) activity. Unlike the simulated data considered above, in the *in vivo* signal, the target
rhythm changes in time (e.g., time intervals exist with, and without, the theta rhythm). Accurate
application of the SSPE method requires accurate estimation of the parameters defining the

oscillators in the SSPE model. In the simulated data, the stationary target rhythm allowed
consistent SSPE model parameter estimation from (any) single interval in time; in those
simulations, we estimated the SSPE model parameters from a single, early time interval (see
Methods), and then used those (fixed) model parameters for future causal phase estimates.

For the *in vivo* data, in which the target rhythm may change in time, model estimates from
an initial time may be inappropriate - and produce inaccurate phase estimates - at a later time.
However, comparing the estimated phase to the true phase (see *Methods*), we find that the phase
error tends to remain consistent in time (blue curve in Figure 6A; circular standard deviation 95
percent interval = [33.11, 75.39]; for error of phase estimates computed using alternative
methods, see Figure 6 - Figure Supplement 1). We find no evidence of a linear trend in error with
time (linear fit, slope = 0.01, p = 0.53); i.e., we find no evidence that the error increases in time.
Instead, visual inspection suggests that the error increases when the spectral content of the LFP
changes (e.g., near 120 s in Figure 6B). We note that the error bounds are within the bounds of
the range expected for real-time phase estimates in (Zrenner et al., 2020). Finally, we note that
visual inspection of the power spectral density (Figure 6C) demonstrates that the theta band
power appears more closely matched by a broad band peak, rather than a narrow band peak.

An alternative approach is to re-estimate the SSPE model parameters over time. By
allowing the parameters of the model oscillators to change in time, this approach may improve
the accuracy of the phase estimates. To examine this in the *in vivo* data, we refit the SSPE model
parameters in each 10 s interval of the LFP data. More specifically, we refit model parameters in
every 10 s interval of the 250 s recording, incrementing the 10 s interval by 1 s, to create 240
models. We then use each of these models to causally estimate the phase for all future times.
For example, we use the SSPE model with parameters estimated from the interval 40-50 s to then
estimate the phase for data after 50 s. We compute the error in the phase estimates for all 240
models to assess whether refitting the SSPE model parameters impacts future phase estimates.
We find no evidence that the distribution of phase errors changes for the refit models compared
to the original fixed parameter model for the immediate 30 seconds that followed (p=0.21,
Wilcoxon Rank Sum test) or for the entire time period analyzed (red interval in Figure 6A, circular
standard deviation 95 percent interval = [30.68, 88.7] degrees; p = 0.35 using Wilcoxon Rank
Sum test). The original fixed parameter SSPE model (fit using the first 10 s of data; blue curve in
Figure 6A) performs as well as the models refit with future data. We conclude that, under the
assumption that parameters for the frequency band of interest are stable, we are able to estimate
the SSPE model parameters whenever there exists a consistent rhythm of interest and then apply
this model to estimate phase at future times (here on the scale of hundreds of seconds). In other
words, for these data, any 10 s interval with sufficiently strong theta rhythm can be used to fit
parameters before the model is applied causally. This result has an important practical implication;
the SSPE model parameters can be fit using an initial segment of data, and then applied to derive
causal estimates of future phase values. In other words, the model has robust estimation
properties; parameters estimated early in the recording remain appropriate for future
observations.

In addition, these results allow a novel insight into the rhythmic activity of the data, beyond
those available using traditional methods. Typical analysis of neural rhythms either presumes the
presence of a rhythm (for subsequent filtering) or operates in the frequency domain using the
power spectral density and statistical testing to identify significant rhythms. Here, through direct
fitting of the state space model to the time series data, we find consistent model parameters that
accurately track the observed theta rhythm. This consistency is maintained through variations in
the rhythm's amplitude. These observations suggest that the theta rhythm in infralimbic LFP
maintains a consistent underlying rhythmic structure over the entire duration of the observation.

Confidence in the Phase Estimate

Past approaches to causally estimate phase have not attempted to quantify confidence in
the phase estimate beyond utilizing the amplitude as a surrogate (Zrenner et al., 2020). However,
using the amplitude assumes a monotonic linear relationship between the phase confidence
bounds and the amplitude, which may not be true (e.g., for an AR(2) process with complex roots,
Spyropoulos et al., 2019). Unlike existing methods, the SSPE method provides real-time
estimates of the credible interval estimates for the phase (resulting from estimating the
parameters of the SSPE model and tracking the phase using the Kalman filter; see *Methods*). To
illustrate this, we show the phase and credible interval estimates of the SSPE method for an
example 3 s interval of the LFP data (Figure 7; for comparison to phase estimates computed using
alternative methods, see Figure 7 - Figure Supplement 1). We note that, during a prominent theta
rhythm, the credible intervals tightly track the mean phase estimate; at other times - when the
theta rhythm is less obvious - the credible intervals expand. We can restrict error in the phase
estimate by examining only samples with small CI width. When thresholding at 10 degrees of
credible interval width, we find that the error decreases from (mean) 46.9 (s.e. 0.89) degrees to
26.91 (s.e. 1.07) degrees, while still retaining 27 percent of the data. This is within the current
state-of-the-art in phase estimation with minimum of 20 to 40 degrees error as a function of SNR
(when applying a sufficiently high amplitude threshold, Zrenner et al., 2020).

Previous studies have proposed a relationship between the theta amplitude envelope,
estimated using the traditional approach of narrow band filtering followed by a Hilbert transform,
and confidence in the phase (Zrenner et al., 2020); when the theta signal is strong (i.e., the
amplitude is large), the theta phase estimate improves. To examine this relationship here, we plot
the theta amplitude envelope versus the phase credible intervals derived from the SSPE method
(Figure 7C.i). Visual inspection reveals that, when the amplitude is large, small decreases in
amplitude coincide with increased credible intervals, as expected. However, if we choose to
approximate certainty in the phase estimate through thresholding the amplitude, we find that fixed
amplitude thresholds produce wide ranges of credible intervals (Figure 7C.ii). This is especially
apparent at lower amplitude thresholds; choosing a threshold of 65% results in credible intervals
that range from 2.29 (minimum) to 174.75 (maximum) degrees. Therefore, a fixed amplitude
threshold does not guarantee an accurate phase estimate. Instead, we propose that inspection
of the credible intervals better guides certainty in the phase estimate. These credible intervals are
directly derived from the modeling procedure, as opposed to surrogate measures of confidence
in the phase estimate, such as amplitude. In addition, credible intervals are directly interpretable
unlike amplitude thresholds, which depend on the measurement scale (e.g., a credible interval
threshold of 10 degrees versus an amplitude threshold of 10 millivolts. We conclude that

amplitude is linked to confidence in the phase, however, a fixed amplitude threshold is not directly
interpretable and encompasses a wide range of credible interval values.

Figure 6: Any interval with a prominent rhythm of interest (here: theta) can be used to fit SSPE parameters. (A) The phase error for a single instance of the model fit (using data at times 10-20 s, blue curve), and the 90 percent interval for phase error (red bands) at time t derived using parameter estimates from all models estimated with data prior to t. The moments where no error is reported are moments when an acausal approach failed to detect the theta band rhythm. Right: a histogram of circular deviation across all time demonstrating that error remains below 60 degrees in the majority of cases. (B) Corresponding spectrogram of the rodent LFP data (multi-taper method with window size 10 s, window overlap 9 s, frequency resolution 2 Hz, and 19 tapers). (C) Average power spectral density (PSD) of (B) over all times with theta band oscillator identified in (A). The mean PSD (dark blue) and 95% confidence intervals (light blue) reveal a broadband peak in the theta band.

Figure 6 - figure supplement 1: The SSPE method performs optimally across algorithms when tracking LFP theta. *The error (circular deviation) in performance of each algorithm across all LFP data. Each dot represents the error computed for one second of data. To compute the error, we compare the real-time phase estimate of each method to an acausally derived estimate of the phase by fitting the state space model (see Methods: In Vivo Data). The SSPE method shows performance comparable to the acausal FIR.*

***Figure 7. SSPE tracks in vivo credible intervals for the phase. (A)** Example rodent LFP data (red, solid) with a consistent broadband peak in the theta band (4-8 Hz). The estimated state of the SSPE method (purple, dashed) tracks the observed LFP. **(B)** Phase estimates (purple, dashed) and credible intervals (red, shaded) for the example LFP data in (A). When the rhythm appears (yellow shaded region) the credible intervals approach the mean phase; when the rhythm drops out, the credible intervals expand. **(C.i)** Phase credible intervals versus theta rhythm amplitude for each time point (gray dot). (Lower) Example cycles of a rhythm with credible intervals, see x-axis of (C.ii) for numerical values of credible intervals. **(C.ii)** Violin plot of credible intervals for thresholds set at the 65th, 80th and 95th percentile of the distribution of amplitude. The distribution of credible intervals increases with reduced amplitude threshold, and all amplitude thresholds include times with large credible intervals.*

Note that the phase and amplitude estimates are auto-correlated in time so that each gray dot is not independent of every other dot.

Figure 7 - figure supplement 1: All methods produce similar phase estimates during segments of the theta rhythm with high signal-to-noise ratio (SNR). (A.i.) *Example rodent LFP data. (**A.ii**) Phase estimates from each method (see legend) are consistent when the SNR of the theta rhythm is high.*

Example *in-vivo* application: human EEG

To illustrate application of the SSPE method in another data modality, we analyze an
example EEG recording of the mu rhythm (8-13 Hz) from (Zrenner et al., 2020). To do so, we
apply the SSPE method to track three oscillators (1, 10, 22 Hz) in 10 s intervals (see
Methods),and examine the phase estimates of the 8-12 Hz oscillator. Consistent with the rodent
LFP data, we find that re-fitting of the SSPE model parameters is not required. Instead, the
SSPE model parameters estimated from an initial 10 s segment of the EEG produce phase
estimation errors consistent with SSPE models refit at future times (Figure 8A). Like the theta
rhythm in the LFP rodent data, the mu rhythm in the human EEG data maintains a consistent
spectral profile in time (Figure 8B) and further, it appears to be narrow-band (Figure 8C).
Therefore, estimating SSPE model parameters early in the data accurately captures the mu
rhythm tracked later in the data, and there is no need to perform the (computationally
expensive) refitting of the model.

The phase estimates and credible intervals for the mu rhythm reveal how this rhythm
waxes and wanes in time (example in Figure 8D,E; for comparison to phase estimates
computed using the alternative methods, see Figure 8 - Figure Supplements 1 and 2). When a
strong mu rhythm emerges, tight credible intervals surround the mean phase estimate tracking
the rhythm of interest; as the mu rhythm wanes, the credible intervals expand. When we restrict
analysis to samples with credible interval width less than 25 degrees, the error drops from 40.5
(s.e. 1.1) to 11.2 (s.e. 0.46) degrees while still retaining 16.4 percent of the data. As with the
LFP, we are able to assess certainty in our phase estimates using the credible intervals. Finally,
we note that computing the state estimate including both the 10 Hz and 22 Hz components of
the model better approximates the non-sinusoidal waveform of the mu rhythm (Figure 8 - Figure
Supplement 3).

Pre-stimulus Mu Rhythm Phase Predicts MEP amplitude

To illustrate the utility of real-time phase estimation, we again analyze an example EEG
recording from (Zrenner et al., 2020) in which the authors stimulate a subject at random
intervals using transcranial magnetic stimulation (TMS) to elicit a motor evoked potential (MEP)
from the right abductor pollicis brevis muscle. We analyze the MEP amplitude to assess the
influence of pre-stimulus mu rhythm phase on the response (replicating the analysis performed
by Zrenner et. al. 2020). We estimate mu rhythm phase using the SSPE method with model
parameters derived from a different subject. We find that the pre-stimulus phase of the mu
rhythm, at the instant immediately prior to stimulation, predicts (using circular linear regression)
13 percent of the log-transformed MEP amplitude (Figure 9A). Furthermore, thresholding the
trials using credible interval width, we find improved prediction of the MEP amplitude. When
using trials with CI width less than 50 degrees, the mu rhythm phase explains 30% of the
variance in the MEP amplitude (Figure 9B), and with CI width less than 25 degrees, 48% of the
variance (Figure 9C). These results show that modulation of the MEP amplitude depends on the
pre-stimulus phase of the mu rhythm, and suggest that accurate estimation of the mu rhythm
(e.g., using the SSPE method with narrow CI width) may enhance the evoked motor response.

Figure 8: SSPE parameters can be estimated from any interval of EEG mu rhythm and credible intervals for mu rhythm phase indicate periods of confidence. (A) *Phase error for a model fit using data from the first 10 seconds (blue curve), and the 95% confidence*

*intervals (red) in the error for phase estimates at time t using models fit at times prior to time t. Right: histogram of error showing that error remains below 60 degrees in most cases. **(B)** Corresponding spectrogram for the EEG data (multi-taper method with window size 10 s, window overlap 9 s, frequency resolution 1 Hz, and 19 tapers). **(C)** Average power spectral density (PSD) of (B) over all times in (A). The mean PSD (dark blue) and 95% confidence intervals (light blue) reveal a peak in the mu rhythm near 11 Hz. **(D)** Example human EEG data (red, solid) with a consistent peak in the mu rhythm (8-13 Hz). The estimated state of the SSPE method (purple, dashed) tracks the observed mu rhythm. **(E)** Phase estimates (purple, dashed) and credible intervals (red, shaded) for the example EEG data in D. When the rhythm appears (yellow shaded region) credible intervals approach the mean phase; when the rhythm drops out the credible intervals expand.*

Figure 8 - figure supplement 1: All methods produce similar phase estimates during segments of the mu rhythm with high signal-to-noise ratio (SNR). (A.i.) *Example mu rhythm clearly visible in the early portion of the EEG trace.* **(A.ii)** *Phase estimates from each method (see legend) are consistent when the SNR of the mu rhythm is high.*

***Figure 8 - figure supplement 2: The SSPE method performs optimally across
algorithms when tracking the EEG mu rhythm.*** *The error (circular deviation) in
performance of each algorithm across all EEG data. Each dot represents the error computed
for one second of data. To compute the error, we compare the real-time phase estimate of
each method to an acausally derived estimate of the phase by fitting the State Space Model
(see Methods: In Vivo Data). The SSPE method shows performance comparable to the
acausal FIR.*

A.i.

A.ii.

Figure 8 - figure supplement 3: SSPE captures non-sinusoidality of the mu rhythm.
*(**A.i.**) The observed data (orange) is well tracked by the (summed) state estimate (purple, dotted) of the 10 Hz and 22 Hz oscillators. (**A.ii.**) Phase estimates for the 10 Hz (blue, dotted) and 20 Hz (orange, dotted) oscillators are tracked simultaneously.*

Figure 9: Motor evoked potential (MEP) amplitude is predicted by the pre-stimulus

SSPE estimated mu rhythm phase. (A) Log-transformed MEP amplitude versus phase with no threshold applied to the credible interval width. White dot indicates the median of the MEP amplitude. Yellow line is the best fit circular linear regression line (a phase offset sinusoid) showing that the MEP amplitude is maximum at mu rhythm trough (phase = +/- π). (B,C) Including only trials with CI width (B) less than 50 degrees, or (C) less than 25 degrees more clearly demonstrates the MEP amplitude maxima at the mu rhythm trough.

Speed and Accuracy of TORTE Real-time Implementation

To assess the validity of the integration of SSPE into TORTE (Figure 10A), we
generated a 5 Hz sine wave with no additive noise and estimated the phase using the MATLAB
and C++ implementations. The parameter estimates for the fitted model were computed on the
first ten seconds of the data. The computed parameters were nearly identical between the two
implementations and the time to estimate the parameters (which, as above, would need to be
done only once per experiment) ranged from 2 s to 100 s. The phase estimates of the two
implementations have a mean circular difference of 2.06 deg (Figure 10B) with a circular
standard deviation of 0.65 deg; this variation in phase estimates likely arises from differences in
filtering in the TORTE real-time (causal filtering on individual buffers) implementation and the
offline MATLAB real-time (acausal filtering across all data) implementation. Further, given that it
is a near constant shift in phase, the online learning algorithm in TORTE will correct for the
biased phase estimates. We also examined the speed of evaluating different sized buffers with
SSPE within TORTE. Across five buffer sizes from 420 to 1700 samples (encompassing 9 to 37
ms of data, see Figure 10C), estimating phase with SSPE took less than 0.35 ms in the worst
case. We note that the system latency of TORTE is in the range of a few milliseconds (driven
mainly by the USB-based implementation of the current Open Ephys system), whereas the
buffers were evaluated on the scale of microseconds. That is, the real-time bottleneck lies in
signal amplification and digitization, not this processing. In conclusion, we present a real-time
implementation of SSPE that could be easily deployed in various experimental setups.

Figure 10: SSPE implementation in TORTE is accurate, with negligible latency. ***(A)***
OpenEphys GUI for using SSPE. The user specifies the number of frequencies to track, the
center frequencies to track, the frequencies of interest for phase calculation and output (FOI),
variance for the FOI, and the observation error. Observation error determines the effective
bandwidth for each frequency. ***(B)*** *Histogram of the circular standard deviation between*
MATLAB (offline) and TORTE (real-time) implementations of the SSPE. Small variation
results from causal low-pass filtering in TORTE and acausal filtering in the offline phase
estimates. ***(C)*** *Time to evaluate phase versus buffer size. Longer buffer sizes from TORTE*
require longer calculation time for application of SSPE. However, the calculation time is
approximately two orders of magnitude smaller than the buffer size.

Discussion

We have introduced a real-time phase estimator derived from a time series state space model. This approach - the SSPE method - addresses limitations of existing methods (namely, the requirements associated with bandpass filtering in phase estimation) and provides a real-time estimate of confidence in the phase estimate. We demonstrated the benefits of the SSPE method in simulations with varying breadth of the peak rhythm frequency and signal-to-noise ratios, a confounding rhythm with a nearby frequency, and phase resets. In two case studies of *in vivo* data, we showed that re-estimation of model parameters is unnecessary and that the SSPE method provides clear estimates of confidence in phase estimates. We propose that the SSPE serves as a useful tool for real-time phase applications, e.g., real-time phase-locked stimulation or real-time phase-amplitude synchrony estimation.

Narrow-band vs Broadband Signals

While brain rhythms tend to be broadband (Buzsaki, 2004; Roopun et al., 2008), the most common methods in neuroscience to track a rhythm's phase generally expect a narrowband oscillation. However, real-time methods that require a narrowband oscillation struggle to capture the phase accurately for broadband rhythms (e.g., Figure 2). Moreover, when the broadband rhythm has non-negligible power across all frequencies, the standard non-real-time approach (acausal FIR and Hilbert transform) tracks the phase with limited accuracy. For forecasting needed in real-time analyses, implementing the same assumption (of a broadband peak) in the model may improve phase estimation accuracy. In the SSPE method, the assumption of a narrowband oscillation is not required, as the covariance allows flexibility in modelling peaks of different bandwidths.

Noise in the Signal

By applying a bandpass filter directly on the observed signal, existing real-time phase estimators do not disambiguate the signal and the noise, thus folding the noise into the phase estimate. The impact of structured noise (e.g., a competing rhythm or sudden phase shift) is particularly visible in Figure 3 and in Figure 4. To address this, the SSPE approach explicitly separates the signal and noise, and models two separate components of noise: state noise and observation noise. The SSPE state consists of harmonic oscillators driven by (white) noise. The resulting spectrum consists of broadband peaks at the oscillator frequencies upon a brown aperiodic component, similar to spectra observed in neural field activity. Confounding rhythms (a particular type of noise) can be explicitly modeled and accounted for in the SSPE approach. We consider the observation noise as additive white noise (flat spectrum) due to unknown noise in the measurement process. This model structure is more flexible than methods reliant on bandpass filters, allowing different expectations for the noise (e.g., modeling a confounding rhythm as a pure harmonic oscillator) or adding additional model elements to account for power at higher frequencies (e.g., adding moving average terms c.f. (Matsuda & Komaki, 2017)).

Detecting a Rhythm for Phase Estimation

To estimate phase for a target rhythm, there should be evidence that the rhythm exists in the data. A few contemporary real-time phase estimators tackle this problem by using an amplitude threshold to decide when a rhythm is present (Rivero & Ditterich, 2021; Rutishauser et al., 2013). An amplitude criterion depends on accurate knowledge of the distribution of amplitudes possible for the data, relative to the background noise. The SSPE method, in contrast, directly represents the presence/absence of a rhythm in the credible intervals for the phase, as demonstrated for the *in vivo* data. The result is directly interpretable, and permits a more intuitive decision metric (e.g., a threshold depending on the credible interval width) than an arbitrary amplitude criterion. Further, while we expect a central frequency for a rhythm estimated from the data, the Gaussian assumptions of the harmonic oscillator driven by noise allow for the instantaneous frequency to be stochastic. This permits greater flexibility in tracking a rhythm's central frequency compared to prior phase estimators and supports analysis of broadband rhythms with drifting central peaks, and abrupt changes in phase of a fixed rhythm (e.g., Figure 4). However, the SSPE method does require identification of target and confounding rhythms for accurate estimation. If details about the rhythms (central frequencies and bandwidth) are unknown, or the target rhythm is known to exist only for short intervals in a long recording, then alternative methods that allow real-time visualization and user-directed intervention in estimation may be pursued (Rivero & Ditterich, 2021; Rutishauser et al., 2013).

Computational Speed

For real-time phase applications, speed of estimation is critical. We focus here on algorithmic speed as opposed to hardware speed, which is a function of the computing device. Algorithmic speed can be measured at two different points: parameter estimation and application. In the SSPE method and other real-time phase estimators (L. L. Chen et al., 2013; Zrenner et al., 2020), the parameter estimation stage is the slower aspect of phase estimation. Past work has required 10s of minutes for parameter estimation (L. L. Chen et al., 2013). Here, for the SSPE method using a window size of 10 s and a sampling rate of 1 kHz, we find that parameter estimation time rarely exceeds a minute or two. In the application stage, we find that speed is orders of magnitude faster than the sampling rate (Figure 8), considerably improving on the algorithmic delays present in existing algorithms (Rivero & Ditterich, 2021; Rutishauser et al., 2013).

Limitations and Future Directions

Like all real-time phase estimators, the proposed method possesses specific limitations and opportunities for future improvement. First, the SSPE method treats the generative model for any rhythm as a harmonic oscillator driven by noise. A pure sinusoid is outside this model class, and as such the SSPE method performs slightly worse than filter-based algorithms at tracking the phase of a pure sine. Nonetheless, the error remains small for the SSPE tracking a

pure sinusoid in noise (Figure 2). We note that a simple alteration in the SSPE model (removing
the state covariance *Q*) would allow more accurate tracking of a sinusoid, but not the broadband
rhythms more commonly observed *in vivo*. Second, slow drifts (< 0.1 Hz) in the baseline of the
data can impair the ability of the SSPE method to track the phase. Slow drifts could be modeled
as an additional confounding oscillator, however, estimating its presence would require long
segments of time (possibly exceeding 40 s). Alternatively, the SSPE model could be updated to
include a model of the slow drift dynamics (perhaps as a piecewise linear term), or a moving
average mean trend could be causally removed as we demonstrated with the *in vivo* EEG
analysis. Third, in applying the SSPE method, we assume that the model we estimate for a
rhythm remains appropriate for the extent of the experimental duration. While we showed in two
in vivo case studies that this assumption may be reasonable, in other cases this assumption
may fail. Rhythms, observed over time, may be better represented by models with changing
parameters. Indeed, non-stationarity is an important issue to consider when tracking brain
rhythms. The SSPE method is robust (by virtue of the model structure and application of the
Kalman Filter) to small changes in the central frequency or the bandwidth of a rhythm (e.g.,
Figure 2). However, non-stationary rhythms require new algorithms to be developed (such as
the PLSO method in Song et al., 2020). An extension of the SSPE method that could potentially
track changing central frequencies is to apply an extended Kalman filter (Schiff, 2012) that
simultaneously estimates the frequencies of interest while filtering the state. Alternatively, the
SSPE method could also be extended to implement a switching model that utilizes multiple sets
of parameters and switches between parameter sets as necessary, or by refitting the SSPE
model as time evolves. Finally, we note that data sampled at a high rate can reduce
computational efficiency when fitting parameters for SSPE. To address this, a quasi-Newton
optimization - instead of expectation maximization, as implemented here - may improve
performance, as suggested in Matsuda and Komaki (2017). Determining the optimization
framework best suited for practical use remains an important direction for future work.

Conclusion

We introduced a new algorithm - the SSPE method - to track phase in real-time that
addresses several limitations of current methods. We demonstrated in simulation that SSPE
performs better than current state-of-the art techniques for real-time phase estimation and
comparably, or better, than a commonly used acausal FIR approach. We showed in *in vivo* data
that we can estimate SSPE model parameters and apply them for hundreds of seconds without
re-estimation. Finally, we showed how credible intervals from the SSPE method track
confidence in the real-time phase estimate, and may provide an intuitive, user-determined
decision metric for stimulation at a particular phase. We have provided reference
implementations suitable for immediate incorporation into phase-aware *in vivo* experiments.
Future work using the SSPE method in practice may help provide critical evidence on the
potential functional importance of phase in neural dynamics.

Source Data Files

Figure 2 Source Data 1: Circular Standard Deviation for all methods.

Figure 3 Source Data: Circular Standard Deviation for all methods on two simultaneous oscillations simulation.

Figure 5 Source Data: Circular Standard Deviation for all methods on SNR simulation.

Figure 6 Source Data: Error and Spectrogram for *in vivo* LFP data

Figure 7C Source Data: Amplitude and Credible Interval Widths for LFP data

Figure 8 Source Data 1: Error and spectrogram for *in vivo* EEG analysis

Table 1 Source Data: Circular standard deviation and convergence time information for Phase Reset simulation

References

Blackwood, E., Lo, M., & Widge, A. S. (2018). Continuous Phase Estimation for Phase-Locked

    Neural Stimulation Using an Autoregressive Model for Signal Prediction*. *2018 40th*

    Annual International Conference of the IEEE Engineering in Medicine and Biology

    Society (EMBC), 4736–4739. https://doi.org/10.1109/EMBC.2018.8513232

Boashash, B. (1991). *Estimating and Interpreting The Instantaneous Frequency of a Signal-Part*

    1: Fundamentals. 19.

Brockwell, A. E., Rojas, A. L., & Kass, R. E. (2004). Recursive bayesian decoding of motor

    cortical signals by particle filtering. *Journal of Neurophysiology*, *91*(4), 1899–1907.

    https://doi.org/10.1152/jn.00438.2003

Burns, S. P., Xing, D., Shelley, M. J., & Shapley, R. M. (2010). Searching for Autocoherence in

    the Cortical Network with a Time-Frequency Analysis of the Local Field Potential.

    Journal of Neuroscience, *30*(11), 4033–4047.

Busch, N. A., Dubois, J., & VanRullen, R. (2009). The Phase of Ongoing EEG Oscillations

Predicts Visual Perception. *Journal of Neuroscience*, *29*(24), 7869–7876.

https://doi.org/10.1523/JNEUROSCI.0113-09.2009

Buzsaki, G. (2004). Neuronal Oscillations in Cortical Networks. *Science*, *304*(5679), 1926–1929.

https://doi.org/10.1126/science.1099745

Buzsáki, G. (2006). *Rhythms of the Brain*. Oxford University Press.

https://doi.org/10.1093/acprof:oso/9780195301069.001.0001

Cagnan, H., Pedrosa, D., Little, S., Pogosyan, A., Cheeran, B., Aziz, T., Green, A., Fitzgerald,

J., Foltynie, T., Limousin, P., Zrinzo, L., Hariz, M., Friston, K. J., Denison, T., & Brown,

P. (2017). Stimulating at the right time: Phase-specific deep brain stimulation. *Brain*,

140(1), 132–145. https://doi.org/10.1093/brain/aww286

Canolty, R. T., & Knight, R. T. (2010). The functional role of cross-frequency coupling. *Trends in*

Cognitive Sciences, *14*(11), 506–515. https://doi.org/10.1016/j.tics.2010.09.001

Chen, L. L., Madhavan, R., Rapoport, B. I., & Anderson, W. S. (2013). Real-Time Brain

Oscillation Detection and Phase-Locked Stimulation Using Autoregressive Spectral

Estimation and Time-Series Forward Prediction. *IEEE Transactions on Biomedical*

Engineering, *60*(3), 753–762. https://doi.org/10.1109/TBME.2011.2109715

Cole, S. R., & Voytek, B. (2017). Brain Oscillations and the Importance of Waveform Shape.

Trends in Cognitive Sciences, *21*(2), 137–149. https://doi.org/10.1016/j.tics.2016.12.008

Desideri, D., Zrenner, C., Ziemann, U., & Belardinelli, P. (2019). Phase of sensorimotor μ-

oscillation modulates cortical responses to transcranial magnetic stimulation of the

human motor cortex. *The Journal of Physiology*. https://doi.org/10.1113/JP278638

Eden, U. T., Frank, L. M., & Tao, L. (2018). Characterizing Complex, Multi-Scale Neural

Phenomena Using State-Space Models. In Z. Chen & S. V. Sarma (Eds.), *Dynamic*

Neuroscience (pp. 29–52). Springer International Publishing.

https://doi.org/10.1007/978-3-319-71976-4_2

Ethan Blackwood. (2019). *tne-lab/phase-calculator: Phase calculator with fixed visualization and*

structs for channel info. Zenodo. https://doi.org/10.5281/zenodo.2633295

Fiebelkorn, I. C., Foxe, J. J., Butler, J. S., Mercier, M. R., Snyder, A. C., & Molholm, S. (2011).

Ready, Set, Reset: Stimulus-Locked Periodicity in Behavioral Performance

Demonstrates the Consequences of Cross-Sensory Phase Reset. *Journal of*

Neuroscience, *31*(27), 9971–9981. https://doi.org/10.1523/JNEUROSCI.1338-11.2011

Franaszczuk, P. J., & Blinowska, K. J. (1985). Linear model of brain electrical activity—EEG as

a superposition of damped oscillatory modes. *Biological Cybernetics*, *53*(1), 19–25.

https://doi.org/10.1007/BF00355687

Fries, P. (2015). Rhythms for Cognition: Communication through Coherence. *Neuron*, *88*(1),

220–235. https://doi.org/10.1016/j.neuron.2015.09.034

Gaillard, C., Ben Hadj Hassen, S., Di Bello, F., Bihan-Poudec, Y., VanRullen, R., & Ben Hamed,

S. (2020). Prefrontal attentional saccades explore space rhythmically. *Nature*

Communications, *11*(1), 925. https://doi.org/10.1038/s41467-020-14649-7

Galka, A., Yamashita, O., Ozaki, T., Biscay, R., & Valdés-Sosa, P. (2004). A solution to the

dynamical inverse problem of EEG generation using spatiotemporal Kalman filtering.

NeuroImage, *23*(2), 435–453. https://doi.org/10.1016/j.neuroimage.2004.02.022

Gordon, P. C., Dörre, S., Belardinelli, P., Stenroos, M., Zrenner, B., Ziemann, U., & Zrenner, C.

(2021). Prefrontal Theta-Phase Synchronized Brain Stimulation With Real-Time EEG-

Triggered TMS. *Frontiers in Human Neuroscience*, *15*, 691821.

https://doi.org/10.3389/fnhum.2021.691821

Gregoriou, G. G., Gotts, S. J., Zhou, H., & Desimone, R. (2009). High-frequency, long-range

coupling between prefrontal and visual cortex during attention. *Science (New York,*

N.Y.), *324*(5931), 1207–1210. https://doi.org/10.1126/science.1171402

Haegens, S., & Zion Golumbic, E. (2018). Rhythmic facilitation of sensory processing: A critical

review. *Neuroscience & Biobehavioral Reviews*, *86*, 150–165.

https://doi.org/10.1016/j.neubiorev.2017.12.002

Helfrich, R. F., Fiebelkorn, I. C., Szczepanski, S. M., Lin, J. J., Parvizi, J., Knight, R. T., &

Kastner, S. (2018). Neural Mechanisms of Sustained Attention Are Rhythmic. *Neuron*,

99(4), 854-865.e5. https://doi.org/10.1016/j.neuron.2018.07.032

Hemptinne, C. de, Ryapolova-Webb, E. S., Air, E. L., Garcia, P. A., Miller, K. J., Ojemann, J. G.,

Ostrem, J. L., Galifianakis, N. B., & Starr, P. A. (2013). Exaggerated phase–amplitude

coupling in the primary motor cortex in Parkinson disease. *Proceedings of the National*

Academy of Sciences, *110*(12), 4780–4785. https://doi.org/10.1073/pnas.1214546110

Hyafil, A., Giraud, A.-L., Fontolan, L., & Gutkin, B. (2015). Neural Cross-Frequency Coupling:

Connecting Architectures, Mechanisms, and Functions. *Trends in Neurosciences*,

38(11), 725–740. https://doi.org/10.1016/j.tins.2015.09.001

Hyman, J. M., Wyble, B. P., Goyal, V., Rossi, C. A., & Hasselmo, M. E. (2003). Stimulation in

Hippocampal Region CA1 in Behaving Rats Yields Long-Term Potentiation when

Delivered to the Peak of Theta and Long-Term Depression when Delivered to the

Trough. *Journal of Neuroscience*, *23*(37), 11725–11731.

https://doi.org/10.1523/JNEUROSCI.23-37-11725.2003

Kalman, R. E. (1960). A New Approach to Linear Filtering and Prediction Problems. *Journal of*

Basic Engineering, *82*(1), 35–45. https://doi.org/10.1115/1.3662552

Kim, S.-E., Behr, M. K., Ba, D., & Brown, E. N. (2018). State-space multitaper time-frequency

analysis. *Proceedings of the National Academy of Sciences*, *115*(1), E5–E14.

https://doi.org/10.1073/pnas.1702877115

Kocsis, B., Bragin, A., & Buzsáki, G. (1999). Interdependence of multiple theta generators in the

hippocampus: A partial coherence analysis. *The Journal of Neuroscience: The Official*

Journal of the Society for Neuroscience, *19*(14), 6200–6212.

Kramer, M. A., & Eden, U. T. (2016). *Case Studies in Neural Data Analysis: A Guide for the*

Practicing Neuroscientist. MIT Press.

Kundu, B., Johnson, J. S., & Postle, B. R. (2014). Prestimulation phase predicts the TMS-

evoked response. *Journal of Neurophysiology*, *112*(8), 1885–1893.

https://doi.org/10.1152/jn.00390.2013

Lakatos, P., O'Connell, M. N., Barczak, A., Mills, A., Javitt, D. C., & Schroeder, C. E. (2009).

The Leading Sense: Supramodal Control of Neurophysiological Context by Attention.

Neuron, *64*(3), 419–430. https://doi.org/10.1016/j.neuron.2009.10.014

Lepage, K. Q., Kramer, M. A., & Eden, U. T. (2013). Some Sampling Properties of Common

Phase Estimators. *Neural Computation*, *25*(4), 901–921.

https://doi.org/10.1162/NECO_a_00422

Lo, M.-C., Younk, R., & Widge, A. S. (2020). Paired Electrical Pulse Trains for Controlling

Connectivity in Emotion-Related Brain Circuitry. *IEEE Transactions on Neural Systems*

and Rehabilitation Engineering: A Publication of the IEEE Engineering in Medicine and

Biology Society, *28*(12), 2721–2730. https://doi.org/10.1109/TNSRE.2020.3030714

Makeig, S., Debener, S., Onton, J., & Delorme, A. (2004). Mining event-related brain dynamics.

Trends in Cognitive Sciences, *8*(5), 204–210. https://doi.org/10.1016/j.tics.2004.03.008

Mansouri, F., Dunlop, K., Giacobbe, P., Downar, J., & Zariffa, J. (2017). A Fast EEG

Forecasting Algorithm for Phase-Locked Transcranial Electrical Stimulation of the

Human Brain. *Frontiers in Neuroscience*, *11*. https://doi.org/10.3389/fnins.2017.00401

Maris, E., Fries, P., & van Ede, F. (2016). Diverse Phase Relations among Neuronal Rhythms

and Their Potential Function. *Trends in Neurosciences*, *39*(2), 86–99.

https://doi.org/10.1016/j.tins.2015.12.004

Matsuda, T., & Komaki, F. (2017). Time Series Decomposition into Oscillation Components and

Phase Estimation. *Neural Computation*, *29*(2), 332–367.

https://doi.org/10.1162/NECO_a_00916

Nunez, P. L., & Srinivasan, R. (2006). *Electric Fields of the Brain: The Neurophysics of EEG*.

Oxford University Press.

Rivero, C. R., & Ditterich, J. (2021). A user-friendly algorithm for adaptive closed-loop phase-

locked stimulation. *Journal of Neuroscience Methods*, 13.

Roopun, A. K., Kramer, M. A., Carracedo, L. M., Kaiser, M., Davies, C. H., Traub, R. D., Kopell,

N. J., & Whittington, M. A. (2008). Temporal interactions between cortical rhythms.

Frontiers in Neuroscience, *2*. https://doi.org/10.3389/neuro.01.034.2008

Rosenblum, M. G., Pikovsky, A. S., & Kurths, J. (1997). Phase synchronization in driven and

coupled chaotic oscillators. *IEEE Transactions on Circuits and Systems I: Fundamental

Theory and Applications*, *44*(10), 874–881. https://doi.org/10.1109/81.633876

Rutishauser, U., Kotowicz, A., & Laurent, G. (2013). A method for closed-loop presentation of

sensory stimuli conditional on the internal brain-state of awake animals. *Journal of*

Neuroscience Methods, *215*(1), 139–155.

https://doi.org/10.1016/j.jneumeth.2013.02.020

Sameni, R., & Seraj, E. (2017). A robust statistical framework for instantaneous

electroencephalogram phase and frequency estimation and analysis. *Physiological*

Measurement, *38*(12), 2141–2163. https://doi.org/10.1088/1361-6579/aa93a1

Sauseng, P., Klimesch, W., Gruber, W. R., Hanslmayr, S., Freunberger, R., & Doppelmayr, M.

(2007). Are event-related potential components generated by phase resetting of brain

oscillations? A critical discussion. *Neuroscience*, *146*(4), 1435–1444.

https://doi.org/10.1016/j.neuroscience.2007.03.014

Schaworonkow, N., Caldana Gordon, P., Belardinelli, P., Ziemann, U., Bergmann, T. O., &

Zrenner, C. (2018). μ-Rhythm Extracted With Personalized EEG Filters Correlates With

Corticospinal Excitability in Real-Time Phase-Triggered EEG-TMS. *Frontiers in*

Neuroscience, *12*. https://doi.org/10.3389/fnins.2018.00954

Schiff, S. J. (2012). *Neural control engineering: The emerging intersection between control*

theory and neuroscience. MIT Press.

Shumway, R. H., & Stoffer, D. S. (1982). An Approach to Time Series Smoothing and

Forecasting Using the Em Algorithm. *Journal of Time Series Analysis*, *3*(4), 253–264.

https://doi.org/10.1111/j.1467-9892.1982.tb00349.x

Siegle, J. H., López, A. C., Patel, Y. A., Abramov, K., Ohayon, S., & Voigts, J. (2017). Open

Ephys: An open-source, plugin-based platform for multichannel electrophysiology.

Journal of Neural Engineering, *14*(4), 045003. https://doi.org/10.1088/1741-2552/aa5eea

Siegle, J. H., & Wilson, M. A. (2014). Enhancement of encoding and retrieval functions through

theta phase-specific manipulation of hippocampus. *ELife*, *3*, e03061.

https://doi.org/10.7554/eLife.03061

Song, A. H., Ba, D., & Brown, E. N. (2020). PLSO: A generative framework for decomposing

nonstationary timeseries into piecewise stationary oscillatory components. arXiv preprint

arXiv:2010.11449.

Soulat, H., Stephen, E. P., Beck, A. M., & Purdon, P. L. (2019). *State Space Methods for Phase*

Amplitude Coupling Analysis [Preprint]. Neuroscience. https://doi.org/10.1101/772145

Spyropoulos, G., Dowdall, J. R., Schölvinck, M. L., Bosman, C. A., Lima, B., Peter, A., Onorato,

I., Klon-Lipok, J., Roese, R., Neuenschwander, S., Singer, W., Vinck, M., & Fries, P.

(2019). *Spontaneous variability in gamma dynamics described by a linear harmonic*

oscillator driven by noise [Preprint]. Neuroscience. https://doi.org/10.1101/793729

Tort, A. B. L., Fontanini, A., Kramer, M. A., Jones-Lush, L. M., Kopell, N. J., & Katz, D. B.

(2010). Cortical Networks Produce Three Distinct 7–12 Hz Rhythms during Single

Sensory Responses in the Awake Rat. *The Journal of Neuroscience*, *30*(12), 4315–

4324. https://doi.org/10.1523/JNEUROSCI.6051-09.2010

VanRullen, R. (2016). Perceptual Cycles. *Trends in Cognitive Sciences*, *20*(10), 723–735.

https://doi.org/10.1016/j.tics.2016.07.006

Voloh, B., & Womelsdorf, T. (2016). A Role of Phase-Resetting in Coordinating Large Scale

Neural Networks During Attention and Goal-Directed Behavior. *Frontiers in Systems*

Neuroscience, *10*, 18. https://doi.org/10.3389/fnsys.2016.00018

West, M. (1997a) Time series decomposition. Biometrika, 84, 489-494

Widge, A. S., Heilbronner, S. R., & Hayden, B. Y. (2019). Prefrontal cortex and cognitive control:

New insights from human electrophysiology. *F1000Research*, *8*.

https://doi.org/10.12688/f1000research.20044.1

Withers, C. S., & Nadarajah, S. (2013). The distribution of the amplitude and phase of the mean

of a sample of complex random variables. *Journal of Multivariate Analysis*, *113*, 128–

152. https://doi.org/10.1016/j.jmva.2012.05.017

Xing, D., Shen, Y., Burns, S., Yeh, C.-I., Shapley, R., & Li, W. (2012). Stochastic Generation of

Gamma-Band Activity in Primary Visual Cortex of Awake and Anesthetized Monkeys.

Journal of Neuroscience, *32*(40), 13873–13880a.

https://doi.org/10.1523/JNEUROSCI.5644-11.2012

Yousefi, A., Basu, I., Paulk, A. C., Peled, N., Eskandar, E. N., Dougherty, D. D., Cash, S. S.,

Widge, A. S., & Eden, U. T. (2019). Decoding Hidden Cognitive States From Behavior

and Physiology Using a Bayesian Approach. *Neural Computation*, *31*(9), 1751–1788.

https://doi.org/10.1162/neco_a_01196

Zrenner, C., Desideri, D., Belardinelli, P., & Ziemann, U. (2018). Real-time EEG-defined

excitability states determine efficacy of TMS-induced plasticity in human motor cortex.

Brain Stimulation, *11*(2), 374–389. https://doi.org/10.1016/j.brs.2017.11.016

Zrenner, C., Dragana Galevska, Jaakko O. Nieminen, David Baur, MariaIoanna Stefanou, & Ulf

Ziemann. (2020). *The shaky ground truth of real-time phase estimation*. 21.

1100