Peripheral Nerve Magnetoneurography with Optically Pumped Magnetometers

Yifeng Bu[1], Jacob Prince[1], Hamed Mojtahed[1], Donald Kimball[1], Vishal Shah[2], Todd Coleman[3], Mahasweta Sarkar[4], Ramesh Rao[1], Mingxiong Huang[5], Peter Schwindt[6], Amir Borna[6], Imanuel Lerman[1, 7*]

[1]Jacob School of Engineering, Electrical and Computer Engineering, University of California, San Diego, United States, [2]QuSpin Inc., United States, [3]Department of Bioengineering, Stanford unviersity, United States, [4]Electrical and Computer Engineering Department, San Diego State University, United States, [5]Department of Radiology, Radiology Imaging Laboratory, University of California, San Diego, United States, [6]Quantum Information Sciences, Sandia National Laboratories, United States, [7]Department of Anesthesiology, Center for Pain Medicine, University of California, San Diego, United States

Conflict of interest statement

The authors declare a potential conflict of interest and state it below

VS is the founding director of QuSpin, the commercial entity selling the OPM magnetometers used in the study.
All other authors declare that the research was conducted in the absence of any commercial or financial relationships that could be construed as a potential conflict of interest.

Author contribution statement

IL proposed the experimental concept. IL, YB, JP, AB, and PS designed the methodology and experiments. AB, PS, HM, RR, DK, VS, MS, TC, MH, and IL suggested experimental improvements. IL, YB, JP, and HM performed the experiments. YB and JP processed and analysed the experimental data. AB provided key suggestions for the appropriate analysis the OPM sensor characterization data. IL, YB, and JP wrote the primary content of the paper. All other authors participated in the editing of the final manuscript.

Keywords

Optically pumped magnetometer (OPM), Magnetoneurography (MNG), Magnetoencephalography (MEG), H-Reflex, Sensory Nerve Action Potentials (SNAP), magnetospinoography (MSG), Super conducting quantum interference devices (SQUID)

Abstract

Word count: 179

Electrodiagnosis is routinely integrated into clinical neurophysiology practice for peripheral nerve disease diagnoses such as neuropathy, demyelinating disorders, nerve entrapment/impingement, plexopathy or radiculopathy. Measured with conventional surface electrodes, the propagation of peripheral nerve action potentials along a nerve is the result of ionic current flow which, according to Ampere's Law, generates a small magnetic field that is also detected as an "action current" by magnetometers such as superconducting quantum interference device (SQUID) Magnetoencephalography (MEG) systems. Optically pumped magnetometers (OPMs) are an emerging class of quantum magnetic sensors with a demonstrated sensitivity at the 1 fT/$\sqrt{\text{Hz}}$ level, capable of cortical action current detection. But, OPMs were ostensibly constrained to low bandwidth therefore precluding their use in peripheral nerve electrodiagnosis. With careful OPM bandwidth characterization, we hypothesized OPMs may also detect compound action current signatures consistent with both Sensory Nerve Action Potential (SNAP) and the Hoffmann Reflex (H-Reflex). In as much, our work confirms OPMs enabled with expanded bandwidth can detect the magnetic signature of both the SNAP and H-Reflex. Taken together, OPMs now show potential as an emerging electrodiagnostic tool.

Contribution to the field

Electrodiagnosis is routinely integrated into clinical neurophysiology practice for peripheral nerve disease diagnoses such as neuropathy, demyelinating disorders, nerve entrapment/impingement, plexopathy or radiculopathy. Well established in clinical neurophysiology practice, surface electrode electrodiagnostics routinely identify peripheral neuropathy, and nerve entrapment with the Sensory Nerve Action Potential (SNAP); whereas plexopathy, demyelinating disease and radiculopathy are identified with the Hoffmann Reflex (H-Reflex). The propagation of peripheral nerve action potentials along a peripheral nerve are the result of ionic current flow which, according to Ampere's Law, generates a small magnetic field (action current). Termed magnetoneurography, superconducting quantum interference devices (SQUID) are capable of peripheral action current detection. Optically pumped magnetometers (OPMs) are an emerging class of quantum magnetic sensors with a demonstrated sensitivity at the 1 fT/$\sqrt{\text{Hz}}$ level, capable of cortical action current detection. Based on these capabilities we hypothesized OPM may also detect peripheral nerve action current signatures. With careful OPM bandwidth characterization, we provide compelling evidence that OPMs can detect peripheral nerve action current (SNAP and H-Reflex) equivalents consequently confirmed with conventional surface electrode measures. Taken together, our results warrant further OPM sensor electrodiagnostic investigation in clinical disease cohorts.

Funding statement

This work is funded by the Biological Advanced Research and Development Authority (BARDA) Contract #75A50119C00038, and the David and Janice Katz Neural Sensor Research Fund in Memory of Allen E. Wolf.

Ethics statements

Studies involving animal subjects
Generated Statement: No animal studies are presented in this manuscript.

Studies involving human subjects
Generated Statement: The studies involving human participants were reviewed and approved by UCSD IRB 171154. The patients/participants provided their written informed consent to participate in this study.

Inclusion of identifiable human data
Generated Statement: No potentially identifiable human images or data is presented in this study.

Data availability statement

Generated Statement: The raw data supporting the conclusions of this article will be made available by the authors, without undue reservation.

Peripheral Nerve Magnetoneurography with Optically Pumped Magnetometers

Yifeng Bu[1] †, Jacob Prince[1] †, Donald Kimball[1], Vishal Shah[2], Todd Coleman[3], Ramesh Rao[1],
Mingxiong Huang[4], Peter Schwindt[5], Amir Borna[5], Imanuel Lerman[1,6,7] *

[1] Jacob School of Engineering, Electrical and Computer Engineering, University of California San
Diego, San Diego, CA, USA

[2] QuSpin Inc., Boulder, CO, USA

[3] Department of Bioengineering, Stanford University, Stanford, CA, USA

[4] Department of Radiology, Radiology Imaging Laboratory, University of California San Diego, San
Diego, CA, USA

[5] Quantum Information Sciences, Sandia National Laboratories, Albuquerque, NM, USA

[6] Department of Anesthesiology, Center for Pain Medicine, University of California San Diego, San
Diego, CA, USA

[7] Veterans Health Administration, VA San Diego, Center for Stress and Mental Health, San Diego,
CA, USA

† These authors have contributed equally to this work and share first authorship
15

* Correspondence:
Imanuel Lerman

ilerman@health.ucsd.edu

Keywords: Optically Pumped Magnetometer (OPM), Magnetoneurography (MNG),
Magnetospinoography (MSG), Super conducting quantum interference devices (SQUID),
Magnetoencephalography (MEG), H-Reflex, Sensory Nerve Action Potentials (SNAP), Action
Currents

Abstract

Electrodiagnosis is routinely integrated into clinical neurophysiology practice for peripheral nerve
disease diagnoses such as neuropathy, demyelinating disorders, nerve entrapment/impingement,
plexopathy or radiculopathy. Measured with conventional surface electrodes, the propagation of
peripheral nerve action potentials along a nerve is the result of ionic current flow which, according to
Ampere's Law, generates a small magnetic field that is also detected as an "action current" by
magnetometers such as superconducting quantum interference device (SQUID)
Magnetoencephalography (MEG) systems. Optically pumped magnetometers (OPMs) are an emerging
class of quantum magnetic sensors with a demonstrated sensitivity at the 1 fT/√Hz level, capable of
cortical action current detection. But OPMs were ostensibly constrained to low bandwidth therefore

precluding their use in peripheral nerve electrodiagnosis. With careful OPM bandwidth
characterization, we hypothesized OPMs may also detect compound action current signatures
consistent with both Sensory Nerve Action Potential (SNAP) and the Hoffmann Reflex (H-Reflex). In
as much, our work confirms OPMs enabled with expanded bandwidth can detect the magnetic signature
of both the SNAP and H-Reflex. Taken together, OPMs now show potential as an emerging
electrodiagnostic tool.

1   Introduction

The human peripheral nervous system is composed of an intricate network of motor, sensory and
autonomic neural structures (Barr, 1974;Sulaiman et al., 2001;Mai and Paxinos, 2011) that if injured
can result in peripheral neuropathic pain. Electrodiagnosis augments the clinicians' ability to gauge the
severity of the neuropathy, and the distribution of neuropathic dysfunction, that consequently guide
clinical pharmacologic, minimally invasive or invasive surgical interventions (Do Campo, 2021). Well
established in clinical neurophysiology practice, conventional (surface electrode) electrodiagnostic,
routinely identify peripheral neuropathy, and peripheral nerve entrapment with the Sensory Nerve
Action Potential (SNAP); whereas plexopathy, demyelinating disease and radiculopathy are identified
with the Hoffmann Reflex (H-Reflex). SNAP measures electrically evoked sensory nerve fiber action
potentials of the upper and lower extremities; while the H-Reflex, an electrically evoked sensory-motor
mono-synaptic spinal reflex, may be recorded from any surface muscle with an accessible nerve (Burke
et al., 1989; Pierrot-Deseilligny and Burke, 2005). Abnormal (delayed 3-4 ms) H-Reflexes are known
to occur at the onset of nerve root compression at the very early stage of nerve root injury even when
imaging is normal and remain abnormal until the compression ceases (i.e., with selective nerve root
injection or corrective surgical intervention)(Jin et al., 2010;Zheng et al., 2014). Further H-Reflexes
are absent in acute inflammatory demyelinating polyneuropathy (Guillain–Barré syndrome)(Bamford
and Davis, 2020). Abnormal SNAP measures (delay or amplitude decrement) are regularly identified
early in peripheral nerve entrapment and are pathognomonic in peripheral neuropathy (Krarup,
2004;Yang et al., 2021). Although surface electrode SNAP and H-Reflexes are proven integral
electrodiagnostic measures; novel nascent magnetoneurography techniques are in development,
capable of compound action current measurement in the peripheral nerve and muscle.

Super conducting quantum interference devices (SQUID) sensor arrays are a non-invasive
diagnostic employed to detect cortical neuronal action potentials with magnetoencephalography
(MEG). Peripheral nerve action currents in the human upper extremity (median and ulnar nerve)
(termed magnetoneurography) (Hari et al., 1989;Hashimoto et al., 1994;Lang et al., 1998) and, more
recently, in the dorsal root ganglion and spinal cord (termed magnetospinography) have successfully
been detected with SQUID sensor arrays (Adachi et al., 2009). However, conventional SQUID sensor
use is highly limited, as they require cryogenic temperature provided with liquid helium (4 K or -269
°C) and magnetically shielded rooms (MSRs). Moreover, SQUID sensors are housed in a rigid Dewar
which prohibit adjacent placement to the sensory, motor nerve or the target muscle that inherently
requires highly mobile and conformal sensor arrays.

QuSpin OPM sensors are conformal with a 6.5 mm sensor stand-off that in aggregate contribute
to an improved magnetic signal-to-noise ratio therefore capable of surpassing current SQUID sensor
technology due to closer proximity to the neuronal source (Iivanainen et al., 2017;Hill et al., 2020).
Recently Broser et.al., (Broser et al., 2018;Broser et al., 2020) showed that commercial Gen-1 OPMs
(QuSpin Inc, CO, USA) detect compound muscle action currents consistent with motor neuron
activation. Expounding on this work, we employed the commercially available Gen-2 OPM (QuSpin
Inc, CO, USA) with the aim to measure upper extremity action currents equivalent to the SNAP and

H-Reflex. To achieve this aim we meticulously: 1) characterized the frequency response, phase
response, and sensitivity of the OPM sensor, and 2) validated the temporal resolution of the OPM's
recording of upper extremity action currents (equivalents of SNAP and H-Reflex) when equated to
conventional surface electrodes. In concert, these results demonstrate preliminary potential for OPM
as a peripheral nerve electrodiagnostic tool.

2   **Methods**

2.1   **OPM Operational Bandwidth**

QuSpin Gen2 OPMs were used to measure median nerve compound action currents. In
comparison to the Gen-1 OPM (dimensions: $13.0 \times 19.0 \times 110.0$ mm^3), Gen-2 OPMs have a significantly
smaller footprint ($12.4 \times 16.6 \times 24.4$ mm^3) that improves conformal placement of the OPM array. Gen-2
OPMs demonstrate improved sensitivity (7-10 fT/$\sqrt{Hz}$ in ideal conditions) and have an extended
tolerance to background magnetic field (up to 200 nT) while maintaining ±5 nT dynamic range (Shah
and Romalis, 2009). The OPM integrates a sixth-order digital filter at 500 Hz to eliminate residual
response above this frequency.

QuSpin OPM sensor response capability of magnetic field frequencies (up to 500 Hz) was
identified with response to a frequency chirp function. The voltage chirp function (swept linearly from
1 Hz to 700 Hz over a 2 second period) was converted into a proportional magnetic chirp by a copper-
wire Helmholtz Coil (two 7.5 cm radius loops with 5 coils per loop at 7.5 cm separation) and associated
current supply circuit (**Supplemental Figure 1**). Based on electromagnetic theory, the amplitude of
the current running through the Helmholtz coil is directly proportional to the amplitude of the magnetic
field generated at the center of the two coils (Bronaugh, 1995;Wang et al., 2002;Cvetkovic and Cosic,
2007;de Melo et al., 2009). Accordingly, the current supply was controlled to generate a 600 pT peak-
to-peak (pk-pk) alternating magnetic field at the OPM's central location. Using the OPM recordings
of repeated (N=11) chirp functions, the OPM magnitude and phase response was then calculated.
Additionally, the sensitivity of the sensor was calculated by computing the power spectral density of
an empty room recording and dividing this value by the normalized frequency response curve. Before
the creation of the sensitivity plot, the OPM signal was filtered for powerline sources (i.e., 60 Hz and
its harmonics) that allowed for removal of these the sensitivity spikes. Finally, using the same
Helmholtz Coil setup with a varying input current amplitude, the OPM response to a 73 Hz sinusoidal
magnetic field input was recorded at amplitudes measured between 15 and 1,500 pT. Magnetic
recordings from this experiment were used to calculate the total harmonic distortion of the OPM at
multiple measured signal amplitudes.

2.2   **Experimental Setup and Procedures**

The Institutional Review Board at the University of California San Diego (UCSD) Health
Systems approved the experimental protocol (UCSD IRB:171154). Three healthy male subjects (age:
40±12 years) without history, signs, or symptoms of peripheral neuropathy, nerve entrapment
syndrome or radiculopathy, gave their written consent. On the visit day, surface electrode and OPM-
based peripheral nerve measurements were carried out within the UCSD Radiology Imaging
Laboratory's six-layer MSR (IMEDICO, Switzerland), to minimize the effects of powerline noise and
the Earth's magnetic field. The employed MSR has a shielding factor of 65-160 dB for the 0.01 Hz-10
Hz frequency range. Subjects were asked to remove all electronic equipment and metal accessories
before entering the MSR to avoid magnetic noise and sensor saturation.

2.2.1 Median Nerve Sensory Nerve Action Potential and Current Measure

The subject (N=1) was centered in the middle of the MSR in the supine position. A pillow was
positioned below the subject's left elbow to ensure comfortable yet maximal extension of the upper
arm above the head. The median nerve SNAP and sensory nerve action current was measured between
the brachialis and the biceps brachii. A 20 MHz portable ultrasound transducer (Butterfly IQ, Palo
Alto, USA) was used to measure the median nerve depth, circumference, and area at both proximal
bicep and distal bicep sites. Stimulating electrodes with cathode-anode distance of 1.5 cm were secured
(with a Velcro strap) longitudinally over the left median nerve at the wrist with cathode proximal to
anode. Two pairs of active and reference electrodes were localized (via ultrasound image guidance)
over the median nerve separated by a 2 cm, 4 cm and 6 cm distance while the ground electrode was
placed between the stimulator and the active electrode (**Figure 2A**). In all measurements, the skin was
carefully abraded with the Nuprep skin prep gel (Weaver and Company, CO, USA) and the EC3 Grass
conductive adhesive gel (Natus, Pleasanton, CA, USA) was applied to each electrode cup with
assurance of impedance maintenance at 5000 Ω or less. Subjects then underwent left median nerve
supramaximal stimulation with the DS7AH constant stimulator (Digitimer Ltd, UK) using a 0.23 Hz,
500 µs pulse-width, monopolar square-wave.

2.2.2 Median Nerve Hoffman Reflex

The H-reflex response was elicited in the Flexor Carpi Radialis muscle (FCR) by stimulator
placement along the antecubital fossa longitudinal axis directly over the left median nerve on two
subjects. The recording techniques employed for H-Reflex generally followed the methodologies of
two studies (Christie et al., 2005;Khosrawi et al., 2015). Briefly, the active electrode was placed over
the muscle belly of the FCR located one-third of the distance between the medial epicondyle and radial
styloid while the reference electrode was placed over the FCR tendon insertion site at the wrist (**Figure
3A**). Isometric contraction of the FCR muscle was used to facilitate the reflex response. Stimulation
intensity was incrementally increased by 0.2 mA until a clear H-Reflex was elicited followed by
amplitude decreased with subsequent maximal M-wave (Stowe et al., 2008).

To match surface electrode time-locked measurements of the SNAP and the H-Reflex, a single
OPM was positioned (with conformal Velcro strap) at the identical sites of the active electrode (at
either the proximal or distal site) in the above experiments (**Figure 2E, 3D**). In all measures, the z-
direction of the OPM was adjusted normal to the skin surface in the longitudinal direction along the
nerve. The y-axis of the OPM was used for measurement and the OPM were operated in single-axis
mode.

To further confirm the source of the detected signals and to measure the spatial fall-off of the
H-Reflex. 3 OPM sensors were placed in transverse orientation to the FCR at the one-third (proximal
FCR) and one-half (distal FCR) distance between the medial epicondyle and radial styloid (**Figure 4A,
4B**). The proximal and distal OPM sensors were separated longitudinally by 4.5 cm. The central OPM
sensor was placed directly over the FCR muscle. At the equipotential level, the two remaining OPMs
were positioned radially 0.5 cm lateral and medial to the central OPM sensor.

2.3   Processing Pipeline

The recorded surface electrode signal was amplified and bandpass filtered from 3-1000 Hz using
a Digitimer D360 isolated amplifier (Digitimer Ltd, UK) with a gain setting of 1000 for SNAP
measurement and 200 for H-Reflex measurement (Christie et al., 2005). The signal was sampled by a
CED Micro1401 device at 10 kHz and recorded by Signal 8.19a software (Cambridge Electronic

Design, Cambridge, UK). All stimuli were repeated with a time-locked trigger to enable trial averaging
while no trial rejection was necessary due to high signal to noise ratio.

Prior to OPM Neuronal recordings, each OPM was tuned and calibrated in an absolute zero
magnetic field environment in the closed door MSR with the OPM gain set to 2.7 V/nT. Of note the
OPM 6[th] order hardware digital filter at 500 Hz is known to generate up to a 15 ms ringing effect post
electric stimulation (**Supplemental Figure 3**). In our measurements, stimulation artifact was post-
calibrated to 0 s to eliminate intrinsic OPM and analog digital converter delay. To reduce ringing effect
data contamination, both stimulation artifact and subsequent ringing effect curves were regressed as a
sinc function by non-linear least squares method and subtracted from the averaged data. A second order
20-500 Hz bandpass filtered was then applied. All post processing was carried out with MATLAB
software (MathWorks Inc, MA, USA). The same processing technique was applied on all physiological
OPM measurements. To compare OPM and surface electrode neural signal bandwidth, time-frequency
analysis (1-500 Hz) was computed by convolving the time-locked averaged data with complex
Morlets' wavelet (Kronland-Martinet et al., 1987) as prior described by Cohen et.al. (Cohen, 2014).

3   Results

3.1   OPM Frequency response and sensitivity

The averaged OPM normalized magnitude response (over 11 chirps) decreased as frequency was
incrementally increased (**Figure 1A).** For the bandwidth between 1 Hz to 135 Hz (**Figure 1A** green
shaded area), the magnitude response decreased minimally. Above 135 Hz, the magnitude response
moderately decreased, and a reduced response was recorded up 500 Hz (**Figure 1A** yellow shaded
area). Above 500 Hz a large reduction in response is noted as a direct effect of the Gen2 OPM hardware
digital filter in the electronic module (**Figure 1A** red shaded area). Major spikes at multiples of 60 Hz
in both the magnitude response and phase response plot (**Figure 1A, 1B**) are a result of the powerline
noise and its harmonics.

The OPM phase response curve is approximately linear up to 500 Hz (**Figure 1B** green and
yellow shaded area), indicating a relatively constant phase delay across these frequencies. A direct
calculation of the average phase delay from 5 to 500 Hz is 3.77 ± 0.078 ms. In our neurophysiological
measurements below, we eliminated the delay introduced by this phase response by setting the start of
the stimulation artifact to time zero, so that the temporal characteristics of our OPM measurements
could be directly compared to the electrode measurements.

The OPM sensitivity was divided into three segments: below 135 Hz (**Figure 1C** green shaded
area), from 135 to 500 Hz (**Figure 1C** yellow shaded area), and from 500 to 700 Hz (**Figure 1C** red
shaded area). Ignoring outlier frequencies caused by powerline and other technical noise sources, our
measured sensitivities in the three segments are: 17.7 ± 3.5 fT/√Hz below 135 Hz, 20.8 ± 3.8 fT/√Hz
from 135-500 Hz, and 101.6 ± 85.6 fT/√Hz above 500 Hz. Filtering at 60 Hz and its harmonics aimed
to remove powerline noise inherently resulted in downward spikes at multiples of 60 Hz while
environmental noise sources lowered sensitivity below 65 Hz (**Figure 1B**). The OPM total harmonic
distortion ranged from -25 dBc to -60 dBc for measured input amplitudes between 15 and 1,500 pT.

3.2   Ultrasound Neural Imaging Measurements

202 Using high resolution B-mode ultrasound imaging, we accurately measured the median nerve
203 circumference, area, and depth at the distal bicep and proximal bicep, The median nerve at two
204 measurement sites was similar in circumference (1.78 cm and 1.7 cm, respectively) and area (0.22 cm^2

205 and 0.21 cm^2, respectively), but was located deeper at the proximal bicep (0.64 cm) when compared to
206 the distal bicep (0.43 cm), (**Supplemental Figure 4).**

3.3   Optically Pumped Magnetometer Electrodiagnostic Measurements

3.3.1 Sensory Nerve Action Potential and Current

We first verified OPM-based detection of afferent sensory nerve action current when
compared to surface electrode SNAP in median nerve. We observed identical surface electrode and
OPM 0.8 ms peak latency temporal dispersion **(Figure 2B, 2F)** and demonstrated nerve conduction
velocity of 50 m/s largely in line with reported median nerve (large fiber) orthodromic sensory
conduction velocities (Shehab, 1998;Valls-Sole et al., 2016). Additionally, surface electrode (inter-
electrode distance of 6 cm) action potential (time frequency derived) center frequencies, were
largely equivalent (260 Hz) when compared to OPM (200 Hz) **(Figure 2C-D, 2G-H)**. Of note,
surface electrode (inter-electrode distance of 2 cm and 4 cm) action potentinal (time frequency
derived) center frequencies (460 Hz and 300 Hz) were greater than the OPM center frequency
(Supplemental Figure 2).
218

219   The effective current density of the nerve was simulated and back-calculated by the Biot-
220 Savart magnetic MATLAB toolbox (Loic, 2015) by employing the detected B-field action
221 current and median-nerve-depth-to-vapor-cell distance (including the 6.5 mm sensor standoff).
222 The nerve was simulated as a straight wire. The estimated total current was 0.195 μA and 0.19 μA
223 from the median nerve at proximal and distal bicep, respectively. The current density was calculated
as 0.92 μA/cm^2 and 0.91 μA/cm^2 at the proximal and distal bicep, respectively.
224

3.3.2 Flexor Carpi Radialis Hoffman-Reflex
225
Two experiments were conducted to verify accurate OPM-based detection of M-wave and H-
Reflex of the FCR muscle. In our first experiment, stimulation intensity was gradually increased to
elicit conserved standard M and H-Reflex characteristics: 1) there was conserved incremental
increases in M-wave amplitude until a maxima was reached, while 2) incremental increases in H-
Reflex reach maxima, known to subsequently diminish. Four demonstrative traces observed with
incremental increases in stimulation intensity (Figure 3B, 3E). We compared the electromyography
response and the reflex reaction of the FCR muscle between the gold standard surface electrode
measures and the OPM. In subjects (N=2) we observed conserved standard M and H-Reflex
characteristics with stimulation intensity increases in all measurements (OPM and surface
electrodes). M-Wave (3.1 ms) and H-Reflex (17.6 ms) onset latencies were identical for surface
electrode and OPM measurements **(Figure 3B, 3E, Supplemental Table 1)**. M wave and H-
reflex time frequency analysis center frequency of 80 Hz was highly conserved across OPM and
surface electrode measurements **(Figure 3C, 3F)** and M-wave general shape was conserved (Merletti
238 et al., 1995).
239

240   In the second experiment, three radially placed OPMs were positioned at the one third
241 (proximal FCR) and one half (distal FCR) distance between the medial epicondyle and radial styloid.
242 At the proximal FCR, all three OPM successfully detected M-wave and H-Reflex activities. The
243 central OPM had the largest H-Reflex pk-pk amplitude among the three measurements and the medial
244 OPM showed reversed polarity. At the distal FCR, where the muscle spindle gets thinner, the central
OPM measurements again showed larger H-Reflex activities compared with the lateral sensor. The
245 medial OPM that **4 Discussion** was placed closer to the palmaris longus muscle only detected muscle activity
(Figure 4C).

Widely adopted by clinical Neurophysiologists, conventional surface electrode electrodiagnostic
measures (i.e., SNAP and H-Reflex) are routinely deployed to measure functional and dysfunctional
neural physiology. Our work demonstrate, QuSpin Gen2 OPM can measure frequencies up to 500 Hz
with a sensitivity capable of action current detection (SNAP and H-Reflex equivalent) confirmed with
conventional surface electrode measures.

The presented frequency response curve and frequency dependent sensitivity (**Figure 1)**
indicate that the OPM sensor can measure frequencies: 1) above the reported bandwidth (135 Hz), and
2) within range of peripheral nerve action current frequencies (up to 500 Hz), but 3) with a reduced
sensitivity in this range (135-500 Hz). Generally, the sensitivity of the OPM from 0 to 500 Hz is below
30 fT/√Hz (**Figure 1C**). A 30 fT/√Hz threshold of detection is well below the magnetic nerve action
current signals detected throughout the study, which were on the range of or greater than one pT (1,000
fT). As such, the evoked magnetic activities observed throughout this report are above the minimum
detection amplitude of the commercially available Gen2 OPM sensor and within its current capabilities.

The OPM linear phase response (between 0 and 500 Hz) indicate preservation of the phase
relationships of different frequency components below 500 Hz necessary for peripheral nerve action
current detection (**Figure 1B**). The observed nominal total OPM harmonic distortion (less than -25
dBc) indicate physiologic signals do not significantly distort nerve action current measures.

After sensor characterization, OPM fast fiber sensory nerve action current detection was
confirmed with conventional surface electrode measurements. Identical SNAP temporal dispersion was
measured with OPM surface electrode SNAP recordings. In both sensors, temporal dispersion derived
nerve conduction velocities match expected large fiber 50 m/s conduction velocity. To our knowledge,
this is the first measure of peripheral nerve action current with OPM.

It should be noted that with 6 cm surface electrode separation center frequencies of the action
potential and action current were largely equivalent albeit with a nominal 60 Hz difference (**Figure 2C,
2D, 2G, 2H**). But with decreased surface inter-electrode distance (4 cm and 2 cm active to reference),
we observed an incrementally increased action potential width and action current center frequency
difference (100 Hz at 4 cm and 260 Hz at 2 cm) when compared to OPM (**Supplemental Figure 2**).
These differences are due to a combination of factors. Because it takes a finite time (0.8 ms) for a
peripheral large fiber sensory nerve action potential to travel from onset to maxima, the traveling action
potential spatial distribution is calculated as approximately 4 cm with a concomitant nerve conduction
velocity of 50 m/s (Dumitru et al., 2010). To accurately measure the full action potential signal, a
minimum of 4 cm inter-electrode distance is required. But the closer the electrodes are placed (less
than 4 cm), the more of the signal will be eliminated and hence the smaller it will appear (i.e., action
potential amplitude and duration) (Dumitru et al., 2010). In line, we detected a decrease in surface
electrode center frequency with larger inter-electrode distances (460 Hz at 2cm, 300 Hz at 4 cm, and
260 Hz at 6 cm) (**Supplemental Figure 2, Figure 2C, 2D**). Precisely positioned over the active
electrode site, the OPM acts as a single sensor with a fixed effective distance, (i.e., circumferential
diameter at which the median nerve propagating action current is detected), that likely contributes to
the observed 200 Hz center frequency. In addition to the OPM fixed effective distance that potentially
widened the action current, the qualitative amplitude reduction of high frequency action current
components is most likely due to the OPMs intrinsic low pass filter, but other as yet identified factors
may also contribute. Nonetheless, the OPM was capable of peripheral nerve action current detection
(albeit with reduced response), that inevitably preserved the equivalent (0.8 ms) surface electrode
derived temporal dispersion. In sum, OPM accurately measures sensory nerve action current latency,
however the above-described factors may result in relative amplitude blunting due to a fixed effective

distance, intrinsic sensitivity, qualitative filtering and other undetermined factors. When considering
OPM sensory nerve action current measures as a clinical diagnostic adjuvant, further work is
essential in clinical disease populations (i.e., axonal neuropathy) where relative amplitude
comparison between upper, lower, right and left limbs is requisite.

Of note the signals from surface electrodes and OPM are similar because they fundamentally
arise from the same moving source (i.e., the median nerve propagating action potential or current).
However, there are important distinctions. The OPM magnetometer measures the field vector while
the surface measures a scalar quantity. Inherently, more information is captured (i.e., direction of the
field) with OPM when compared to electrodes, that may improve nerve action source localization
with expanded N=10 OPM sensor arrays. Moreover, we observed equivalent current densities: 1)
0.92 μA/cm^2 (0.64 cm median nerve depth at proximal position) and 2) 0.91 μA/cm^2 (0.43 cm
median nerve depth at distal position), that in aggregate evince a capability to identify depth
independent median nerve action currents. In the near future, OPM depth independent current density
equivalents may: 1) expedite peripheral nerve source localization and peripheral nerve
differentiation critical for both neural recording as well as targeted stimulation, and 2) may
supersede spatial resolution obtained with conventional electrode based finite element modeling.
Clinically, (if developed) these depth independent current density algorithms may better
identify neural root, trunk, division, cord, and branch dysfunction in plexopathies where multiple
neural structures are in close proximity.
309

310   Analagous to SNAP measures, OPM M-wave and H-Reflex were verified when compared to
311 gold standard surface electrode measures. Time-locked OPM derived M-wave and H-reflex
312 responses demonstrated the same temporal latency and center frequency when compared to those
313 from the surface electrode measurement. Additionally, as we increased the stimulation amplitude, we
314 observed an initial increase and then decrease in the H-Reflex amplitude, highly
characteristic of an H-Reflex signal(Christie et al., 2005;Stowe et al., 2008).
315

Next, we identified a maximal peripheral FCR H-Reflex current source by distributing three
separate OPM sensors within an equipotential line at both proximal and distal FCR. At both
transverse levels, the centrally placed OPM (directly over the FCR) exhibited the largest H-
Reflex pk-pk amplitude compared to the two radially placed OPM sensors. At the proximal FCR
site, the lateral and medial OPM showed reverse polarity, demonstrating the propagation direction
and the center location of the propagating action current. Collectively, this location dependent
pattern of OPM signal magnitude (i.e., largest H-Reflex action current identified with Central
OPM sensor placed directly over the FCR) supports peripheral nerve action current identification
with OPM multi-sensor array methodology. Reliability of conventional FCR H-Reflex
identification is low (Christie et al., 2005). Based on these preliminary results, OPM arrays
distributed over the forearm area (4-10 OPMs) may expedite and improve reliable and objective
326 identification of the FCR H-Reflex response.
327

328   Similar to single sensor, multi-OPM peak latencies were measured within typical range of
329 conventional gold standard surface electrode FCR H-Reflex latency (17-18 ms) (Jabre, 1981;Christie
330 et al., 2005;Khosrawi et al., 2015). Future clinical cohort studies are planned in patients with known
demyelinating disease, plexopathy or radiculopathy with the aim to identify pathological absent or
331 slowed H-Reflex measured with OPM.
332

333   While our OPM action current recordings are encouraging, our work is not without limitations.
334 First, the OPM is only operational within a MSR which limits general use in the open conventional
clinic setting. Future work will focus on the development of open field capable small single limb
(arm or leg) magnetic shielding devices that may afford convenient in office OPM electrodiagnostic
(SNAP

and H-Reflex) characterization, that inherently may lower costs when compared to conventional MSR.
Second, post-hoc stimulation artifact and ringing effect removal was required to obtain early SNAP
measures. Future automated, optimization of OPM filtering techniques applied to the transimpedance
amplifier interaction with the lock-in amplifier are planned; this together may minimize the ringing
effect. Additionally, accurate OPM neuronal action potential measurement requires informed
placement of each sensor, i.e., B-mode median nerve and Flexor Carpi Radialis imaging. Employing a
multiarray 4-10 OPM sensor solution has the potential to circumvent the requirement for B-mode
ultrasound scanning and therefore may improve SNAP and FCR H-Reflex reliability. As prior
mentioned, OPM intrinsic sensitivity and filtering may result in amplitude blunting of fast component
sensory nerve action currents. Future clinical cohort studies may define OPM sensory nerve action
current amplitude characteristic accuracy and reliability as a clinical electrodiagnostic.

In summary, we demonstrate two major findings: 1) the commercially available QuSpin Gen2
OPM is capable of measuring signals at a frequency above 135 Hz (up to 500 Hz) with a sensitivity
and phase response appropriate for the detection of peripheral nerve action current (SNAP and H-
Reflex) equivalents, and 2) OPM has comparable temporal resolution when measuring SNAP and H-
Reflex equivalents consequently compared to gold standard surface electrodes. Taken together, our
results warrant further OPM sensor electrodiagnostic investigation in clinical disease cohorts.

5   Conflict of Interest

353 VS is the founding director of QuSpin, the commercial entity selling the OPM magnetometers used
354 in the study.

355 All other authors declare that the research was conducted in the absence of any commercial or
356 financial relationships that could be construed as a potential conflict of interest.

6   Author Contributions

IL proposed the experimental concept. IL, YB, JP, AB, and PS designed the methodology and
experiments. AB, PS, RR, DK, VS, TC, MH, and IL suggested experimental improvements. IL, YB,
JP performed the experiments. YB and JP processed and analysed the experimental data. AB
provided key suggestions for the appropriate analysis the OPM sensor characterization data. IL, YB,
and JP wrote the primary content of the paper. All other authors participated in the editing of the final
manuscript.

7   Funding

365 This work is funded by the Biological Advanced Research and Development Authority (BARDA)
366 Contract *#75A50119C00038,* and the David and Janice Katz Neural Sensor Research Fund in
367 Memory of Allen E. Wolf.

8   Data Availability Statement

369 Data is available at the authors' discretion upon direct request.

9   References

Adachi, Y., Kawai, J., Miyamoto, M., Ogata, H., Tomori, M., Kawabata, S., Sato, T., and Uehara, G. (2009). A SQUID system for measurement of spinal cord evoked field of supine subjects. *IEEE transactions on applied superconductivity* 19**,** 861-866.

Bamford, J.A., and Davis, S.F. (2020). "The H-Reflex and F-Response," in *Principles of Neurophysiological Assessment, Mapping, and Monitoring*. Springer), 171-179.

Barr, M.L. (1974). *The human nervous system: An anatomical viewpoint.* Harper & Row.

Bronaugh, E.L. (Year). "Helmholtz coils for calibration of probes and sensors: limits of magnetic field accuracy and uniformity", in: *Proceedings of International Symposium on Electromagnetic Compatibility*: IEEE), 72-76.

Broser, P., Middelmann, T., Sometti, D., and Braun, C. (2020). Optically pumped magnetometers disclose magnetic field components of the muscular action potential. *bioRxiv*.

Broser, P.J., Knappe, S., Kajal, D.-S., Noury, N., Alem, O., Shah, V., and Braun, C. (2018). Optically pumped magnetometers for magneto-myography to study the innervation of the hand. *IEEE Transactions on Neural Systems and Rehabilitation Engineering* 26**,** 2226-2230.

Christie, A.D., Inglis, J.G., Boucher, J.P., and Gabriel, D.A. (2005). Reliability of the FCR H-reflex. *Journal of Clinical Neurophysiology* 22**,** 204-209.

Cohen, M.X. (2014). *Analyzing neural time series data: theory and practice.* MIT press.

Cvetkovic, D., and Cosic, I. (Year). "Modelling and design of extremely low frequency uniform magnetic field exposure apparatus for in vivo bioelectromagnetic studies", in: *2007 29th Annual International Conference of the IEEE Engineering in Medicine and Biology Society*: IEEE), 1675-1678.

De Melo, C.F., Araújo, R.L., Ardjomand, L.M., Quoirin, N.S.R., Ikeda, M., and Costa, A.A. (2009). Calibration of low frequency magnetic field meters using a Helmholtz coil. *Measurement* 42**,** 1330-1334.

Do Campo, R.V. (2021). Electrodiagnostic Assessment of Polyneuropathy. *Neurologic clinics* 39**,** 1015-1034.

Dumitru, D., Nandedkar, S.D., and Netherton, B. (Year). "Neurophysiology and instrumentation", in: *AANEM 57th Annual Meeting, Québec, Canada*).

Hari, R., Hällström, J., Tiihonen, J., and Joutsiniemi, S.-L. (1989). Multichannel detection of magnetic compound action fields of median and ulnar nerves. *Electroencephalography and clinical neurophysiology* 72**,** 277-280.

Hashimoto, I., Mashiko, T., Mizuta, T., Imada, T., Iwase, K., and Okazaki, H. (1994). Visualization of a moving quadrupole with magnetic measurements of peripheral nerve action fields. *Electroencephalography and Clinical Neurophysiology/Evoked Potentials Section* 93**,** 459-467.

Hill, R.M., Boto, E., Rea, M., Holmes, N., Leggett, J., Coles, L.A., Papastavrou, M., Everton, S.K., Hunt, B.A., and Sims, D. (2020). Multi-channel whole-head OPM-MEG: Helmet design and a comparison with a conventional system. *NeuroImage* 219**,** 116995.

Iivanainen, J., Stenroos, M., and Parkkonen, L. (2017). Measuring MEG closer to the brain: Performance of on-scalp sensor arrays. *NeuroImage* 147**,** 542-553.

Jabre, J.F. (1981). Surface recording of the H-reflex of the flexor carpi radialis. *Muscle & Nerve: Official Journal of the American Association of Electrodiagnostic Medicine* 4**,** 435-438.

Jin, X., Zhu, Y., Lu, F.Z., Wu, X.D., Zhu, D.Q., Weber, R., Dunn, B., and Jiang, J.Y. (2010). H-reflex to S1-root stimulation improves utility for diagnosing S1 radiculopathy. *Clinical neurophysiology* 121**,** 1329-1335.

Khosrawi, S., Taheri, P., and Hashemi, S.H. (2015). Proposed equation between flexor carpi radialis H-reflex latency and upper limb length. *Iranian journal of neurology* 14**,** 41.

Krarup, C. (2004). Compound sensory action potential in normal and pathological human nerves. *Muscle & Nerve: Official Journal of the American Association of Electrodiagnostic Medicine* 29**,** 465-483.

Kronland-Martinet, R., Morlet, J., and Grossmann, A. (1987). Analysis of sound patterns through wavelet transforms. *International journal of pattern recognition and artificial intelligence* 1**,** 273-302.

Lang, G., Shahani, U., Weir, A., Maas, P., Pegrum, C., and Donaldson, G. (1998). Neuromagnetic recordings
of the human peripheral nerve with planar SQUID gradiometers. *Physics in Medicine & Biology* 43**,**
2379.
Loic, Q. (2015). Biot Savart magnetic Toolbox. *Tech. report, Dept. Elect. Eng., University of Applied Sciences*
Düsseldorf, Germany.
Mai, J.K., and Paxinos, G. (2011). *The human nervous system.* Academic Press.
Merletti, R., Conte, L.L., and Sathyan, D. (1995). Repeatability of electrically-evoked myoelectric signals in
the human tibialis anterior muscle. *Journal of Electromyography and Kinesiology* 5**,** 67-80.
Shah, V., and Romalis, M.V. (2009). Spin-exchange relaxation-free magnetometry using elliptically polarized
light. *Physical Review A* 80**,** 013416.
Shehab, D.K. (1998). Normative data of nerve conduction studies in the upper limb in Kuwait: Are they
different from the western data? *Medical principles and practice* 7**,** 203-208.
Stowe, A.M., Hughes-Zahner, L., Stylianou, A.P., Schindler-Ivens, S., and Quaney, B.M. (2008). Between-
day reliability of upper extremity H-reflexes. *Journal of neuroscience methods* 170**,** 317-323.
Sulaiman, H., Gabella, G., Davis, C., Mutsaers, S.E., Boulos, P., Laurent, G.J., and Herrick, S.E. (2001).
Presence and distribution of sensory nerve fibers in human peritoneal adhesions. *Annals of surgery*
234**,** 256.
Valls-Sole, J., Leote, J., and Pereira, P. (2016). Antidromic vs orthodromic sensory median nerve conduction
studies. *Clinical neurophysiology practice* 1**,** 18-25.
Wang, J., She, S., and Zhang, S. (2002). An improved Helmholtz coil and analysis of its magnetic field
homogeneity. *Review of scientific instruments* 73**,** 2175-2179.
Yang, J., Chen, K., Liu, Y., and Yang, Y. (2021). Prolonged median distal sensory nerve action potential
duration in carpal tunnel syndrome. *Muscle & Nerve* 63**,** 710-714.
Zheng, C., Zhu, Y., Lv, F., Ma, X., Xia, X., Wang, L., Jin, X., Weber, R., Jiang, J., and Anuvat, K. (2014).
Abnormal flexor carpi radialis H-reflex as a specific indicator of C7 as compared with C6
radiculopathy. *Journal of Clinical Neurophysiology* 31**,** 529-534.

FIGURE 1| OPM frequency response and sensitivity characterization. **Panel A:** OPM magnitude response decreased as frequency increased, particularly above 135 Hz (**green shaded area**), while a reduced frequency response was recorded up to 500 Hz (**yellow shaded area**). Above 500 Hz a large reduction in response is noted as a direct effect of the Gen2 OPM hardware digital filter in the electronic module (**red shaded area**). **Panel B:** OPM Phase response is approximately linear (**green and yellow shaded area**) up to 500 Hz (**red shaded area**). **Panel C:** Sensitivity response of the OPM. OPM sensitivity was divided into three segments: below 135 Hz (**green shaded area**), from 135 to 500 Hz (**yellow shaded area**), and from 500 to 700 Hz (**red shaded area**). A decrease in sensitivity is noted above 500 Hz. (OPM=Optically Pumped Magnetometer, Hz= Hertz, fT= femtotesla)

FIGURE 2 | Panel A, E: Measurement setup of Median nerve SNAP with surface electrode **(A)** and equivalent action current by OPM **(E)**. **Panel B and F:** Time-locked average comparison (from two sites; distal bicep=blue line and proximal bicep=red line) between surface electrode (6m interelectrode distance) **(B)** and OPM **(F)** demonstrate identical 0.8 ms temporal dispersion for both modalities. SNAP action potential/currents are marked in the magenta shaded area. **Panel C and D**: Surface electrode time-frequency analysis for SNAP measured by at distal bicep **(C)** and proximal bicep **(D)**. **Panel G and H**: OPM time-frequency analysis for SNAP measured at distal bicep **(G)** and proximal bicep **(H)**. (OPM = Optically Pumped Magnetometers, SNAP= Sensory Nerve Action Potential, μV = microvolt, pT=picoTesla, ms=milliseconds)

FIGURE 3 | Panel A and D: Measurement setup of FCR M-wave and H-Reflex responses measured by surface electrode **(A)** and OPM **(D)** from the same subject. **Panel B and E:** Time-locked averages with incremental increase in stimulation intensity from top to bottom traces by surface electrode **(B)** and OPM **(E)**. The M-wave and the H-Reflex responses are highlighted green and yellow respectively. Conserved standard M and H-Reflex characteristics: 1) there was conserved incremental increases in M-wave amplitude until a maxima was reached, while 2) incremental increases in H-Reflex reach maxima, known to subsequently diminish, were observed in all measurements (**surface electrodes in B and OPM in D**). **Panel C**: Surface electrode time-frequency analysis of FCR M-wave and maximal H-Reflex recorded. **Panel D**: OPM time-frequency analysis of FCR M-wave and maximal H-Reflex recorded. (OPM = Optically Pumped Magnetometers, FCR=Flexor Carpi Radialis, mV = millivolt, pT=picoTesla, ms=milliseconds, TF=Time Frequency)

FIGURE 4 | Panel A and B: Three OPMs were transversely placed at an equipotential level on the proximal FCR **(A)** and distal FCR **(B)**. **Panel C:** The centrally placed OPM (directly over the FCR) exhibited the largest H-Reflex pk-pk amplitude compared with the two radially placed OPM sensors. At the proximal FCR, the lateral and the medial OPM showed reverse polarity. At the distal FCR, where the muscle spindle is thin, the medial OPM placed only detected M-Wave activity. The M-wave and the H-Reflex responses are highlighted green and yellow respectively. (OPM = Optically Pumped Magnetometers, FCR=Flexor Carpi Radialis, pT=picoTesla, ms=milliseconds).

Figure 1.JPEG

Figure 3.JPEG

Figure 4.JPEG

Supplementary Material

1   Supplemental Figures

1.1   Helmholtz Coils setup.

Supplemental Figure 1: OPM frequency response and sensitivity characterization setup. A single Gen-2 OPM was placed between two copper wire Helmholtz Coils (coiled red lines are 7.5 cm radius loops with 5 coils per loop) at 7.5 cm separation. Based on electromagnetic theory, the amplitude of the magnetic field in the direction of the x-axis at the center of the two coils, is given by the equation: $B_{axis} = \frac{\left(\frac{5}{4}\right)^{-\frac{3}{2}}\mu_0 \cdot N \cdot i}{r}$, where r is the radius of the coils, μ_0 is the relative permittivity of air, N is the number of wire loops in each coil, and i is the current running through the coils. Once the response of the OPM to several chirp functions (N=11) was recorded, the frequency response of the sensor was calculated by performing a fast Fourier transform of sensor response to each chirp and averaging each response to reduce the effects of noise. Then this Fourier transform was normalized to frequency content from the input voltage chirp. This process can be summarized mathematically with the equation: $H(jw) = \frac{\bar{x}[\mathcal{F}\{y(t)\}]}{\bar{x}[\mathcal{F}\{x(t)\}]}$, where $H(jw)$ is the frequency response, $y(t)$ is the signal recorded by the OPM, and $x(t)$ is the voltage chirp function, $\bar{x}$ denotes calculation of the mean, and $\mathcal{F}\{y(t)\}$ is the Fourier transform computed using the Fast Fourier transform algorithm. The OPM response at 5 Hz, was well within the manufactures listed bandpass of 3-125 Hz, was set to unity to create the final frequency response curve.

1.2 Surface electrode SNAP measurement

Supplemental Figure 2: Panel A and D: Time-locked average comparison from surface electrode with 2 cm **(A)** and 4 cm **(D)** inter-electrode distance for median nerve SNAP measurement demonstrated 0.8 ms temporal dispersion. SNAP action potential is marked in the magenta shaded area. **Panel B and C**: 2cm inter-electrode distance time-frequency analysis for SNAP measured at distal bicep **(B)** and proximal bicep **(C)**. Distal bicep **(B)** and proximal bicep **(C)** demonstrate equal center frequencies of 460 Hz. Distal bicep residual low frequency components **(C)** are due to triphasic action potential measured from the superficial median nerve. **Panel E and F**: 4cm inter-electrode distance time-frequency analysis for SNAP measured at distal bicep **(E)** and proximal bicep **(F)**. Distal bicep **(E)** and proximal bicep **(F)** demonstrate equal center frequencies of 300 Hz. (SNAP= Sensory Nerve Action Potential, μV = microvolt, ms=milliseconds)

1.3   OPM SNAP Raw Measurement

Supplemental Figure 3: **Panel A**: OPM SNAP raw measurements from median nerve at distal bicep and proximal bicep. The OPM internal hardware digital filter at 500 Hz generate up to a 15 ms ring effect post stimulation. **Panel B and C**: Time-frequency analysis for SNAP measured by OPM before artifact removal at distal bicep **(B)** and proximal bicep **(C).** The stimulation artifact and its ringing effect distort accurate signal acquisition of the SNAP center frequency. To reduce ringing effect data contamination, both stimulation artifact and subsequent ringing effect curves were regressed as a *sinc* function by non-linear least squares method and subtracted from the averaged data. Finally, a second order 20-500 Hz bandpass filtered was applied effectively removing stimulation artifact ring effects **presented in Figure 2F.** (OPM = Optically Pumped Magnetometers, SNAP= Sensory Nerve Action Potential, pT=picoTesla, ms=milliseconds)

1.4   Ultrasound Neural Imaging Measurements

Supplemental Figure 4: Using high resolution B-mode ultrasound imaging, we accurately measured the median nerve circumference, area, and depth at the distal (**Panel A)** and proximal (**Panel B)** bicep. The median nerve at two measurement sites was similar in circumference (1.72 cm and 1.7 cm, respectively) and area (0.21 cm^2 for both) (**Panel A & B**). Compared to the median nerve localized at the distal bicep (0.43 cm) (**Panel A**) it was localized deeper at the proximal bicep (0.64 cm) (**Panel B**).

2   Supplemental Table

	Surface M-Wave	OPM M-Wave	Surface H-Reflex	OPM H-Reflex
Subject1	4.36 ± 0.11 ms	4.36 ± 0.24 ms	17.68 ± 0.30 ms	17.82 ± 0.37 ms
Subject2	3.06 ± 0.13 ms	3.13 ± 0.15 ms	17.52 ± 0.18 ms	17.6 ± 0.4 ms

Supplemental Table 1: Onset latency statistic comparison for M-wave and H-Reflex measurements between Surface electrode and OPM from two subjects.