Nonlinearities and Timescales in Temporal Interference Stimulation

Tom Plovie [1,*], **Ruben Schoeters** [1], **Thomas Tarnaud** [1], **Luc Martens** [1], **Wout Joseph** [1] **and Emmeric Tanghe** [1]

[1]*WAVES, Department of Information Technology (INTEC), Ghent University/IMEC, Ghent, Belgium*

Correspondence*:
Tom Plovie
tom.plovie@UGent.be

2 ABSTRACT

In temporal interference (TI) stimulation, neuronal cells react to two interfering sinusoidal electric fields with a slightly different frequency. It was previously seen that for the same input intensity, the neurons do not react to a purely sinusoidal signal. This study aims to get a better understanding of the mechanism underlying TI neuromodulation, which is largely unknown. To this end, single-compartment models are used to simulate computationally the response of neurons to the sinusoidal and TI waveform. This study compares different neuron models to get insight into which models are able to reproduce the experimental observations. It was found that integrate-and-fire models do not entirely reflect the experimental behavior while the Hodgkin-Huxley and Frankenhaeuser-Huxley model do reflect this behavior. Changing the characteristics of the ion gates in the Frankenhaeuser-Huxley model alters the response to both the sinusoidal and TI signal, possibly reducing the firing threshold of the sinusoidal input below that of the TI input. The model results show that TI stimulation is not qualitatively impacted by nonlinearities in the current-voltage relation. In contrast, ion channels have a significant impact on the neuronal response. This paper makes advances both in terms of biophysical insight into the neuron as well as the insight in computational modelling of TI stimulation.

Keywords: Computational neuron models, ion gates, nonlinearities, temporal interference stimulation, point neurons

1 INTRODUCTION

Nowadays, many applications for brain stimulation exist. One of these applications is deep brain stimulation (DBS) that was mainly developed to treat movement disorders, such as Parkinson's Disease (PD). However, it has an important disadvantage: it is invasive and can cause complications (e.g. bleeding in the brain, stroke, infection) (Aum and Tierney, 2018). Because of this, a new technique is being developed named temporal interference (TI) stimulation. With this technique, two sinusoidal electric fields, oscillating at a high but slightly different frequency, are applied to the brain by two cathode-anode pairs. At the place where they temporally interfere, an amplitude-modulated signal is created. This is illustrated in Figure 1. The frequency at which the envelope repeats is called the beat frequency. Grossman et al. (2017, 2018) has found from experiments on mice that cortical and hippocampal neurons respond to this interference pattern but not to the constituting sinusoids separately. Therefore, TI stimulation is a non-invasive alternative to the conventional, invasive DBS techniques. Furthermore, instead of using electrodes to create an amplitude modulated electric field inside the brain, it is also possible to use transcranial magnetic stimulation (TMS) coils, creating a magnetic field and inducing an electric field. It is possible to achieve a TI waveform by

using the same technique of applying multiple frequencies to the brain (Sorkhabi et al., 2020; Xin et al., 2021). Although promising, there are still some limitations to overcome before TI stimulation can be used for humans and can replace conventional DBS. A first limitation is that the technique has only been extensively tested on rodents, while very few studies are performed with experiments on humans. One study reports TI stimulation of the human hippocampus with improved episodic memory accuracy as a result (Violante et al., 2022). Another study used TI stimulation to show an increase in activity in the striatum and in its functional brain network. This resulted in a better performance in a motor learning task, with a prominent improvement for healthy older subjects Wessel et al. (2022). Furthermore, Vassiliadis et al. (2022) showed the importance of the striatum in reinforcement learning processes via the use of TI stimulation. A second limitation is that the mechanism in the neuron that allows this type of stimulation is unknown. It is thus very hard to predict how different neuron types will react to the stimulation and thus how exactly the human brain responds to TI stimulation.

Other experiments in mice have shown that it is possible to cause eye movements at the beat frequency of the TI signal (Song et al., 2021), confirming the importance of the beat frequency. It should be noted that TI stimulation is not only used in the brain. It was shown in rats that TI stimulation can activate spinal motor neurons in the neck to restore breathing after opioid overdose. Again it was shown that a single sine waveform is not able to cause stimulation (Sunshine et al., 2021). Furthermore, TI has been studied for retinal stimulation (Su et al., 2021).

To get more insight into the electric field distribution of TI stimulation in the human brain, finite element method (FEM) simulations have been performed. In these studies, TI stimulation has been compared to a conventional technique like transcranial alternating current stimulation (tACS). This showed that when the same electric field strength is achieved inside the focus, TI induces a smaller maximal electric field outside this focus than tACS (von Conta et al., 2021). In contrast to the traditional DBS technique, it is easier to steer the stimulation site with TI stimulation. This can be done by changing the electrode positions or by adjusting the relative amplitudes of the current at the different electrode pairs (Rampersad et al., 2019; von Conta et al., 2021; Gomez-Tames et al., 2021). With these degrees of freedom, it possible to find the optimal electrode positions for targeting focality. This optimal electrode positioning is very person-specific. With the same electrode positioning, high variations are possible in the simulated electric fields for different people (von Conta et al., 2021). Huang and Parra (2019) argue that it is possible to achieve sufficiently high electric fields in deep brain regions using tACS. To achieve this, the electrode positioning becomes more important because it makes use of the cerebrospinal fluid as a conductor for the electric field. It is thus even more challenging to obtain a patient-specific electrode position. They do mention that the focality is still worse with this technique than with TI stimulation (Huang and Parra, 2019). The focality in TI stimulation is in the centimeter range (Huang et al., 2020). Lee et al. (2022) proposed epidural TI stimulation, where the electrodes are placed under the skull, in order to avoid stimulation in cortical regions. They validated their FEM simulations with phantom experiments. Furthermore, the feasibility of TI stimulation in humans is investigated by Acerbo et al. (2022) with the use of mice models and human cadavers in combination with simulations for the optimal electrode positioning.

It was found in silico and in vivo that increasing the carrier frequency of the TI signal increases the threshold of the input needed to cause stimulation. Changing the beat frequency did not seem to have an influence on the threshold according to Grossman et al. (2017) and Gomez-Tames et al. (2021). On the other hand, Mirzakhalili et al. (2020) and Howell and McIntyre (2021) do mention the importance of the beat frequency for the activation threshold. Furthermore, Plovie et al. (2022) showed that for a reduced Hodgkin-Huxley model, the excitation threshold changes with both carrier and beat frequency. To model TI stimulation, it

was found that integrate-and-fire (IF)-neurons are not sufficient to reproduce the experimental behavior on
single neuron level (Cao et al., 2020). However, when IF-neurons are placed in a network and GABA_b
postsynaptic inhibition is included, the computational results were in line with experimental observations
of TI stimulation (Esmaeilpour et al., 2021). Further on, for point neurons, it is possible to have neurons
exhibiting TI stimulation when using the FitzHugh-Nagumo model or the Hodgkin-Huxley model. It
was also seen that not all mammalian cells exhibit TI (Cao and Grover, 2018; Cao et al., 2020). Howell
and McIntyre (2021) argues that because of the large dimensions of a human head, TI stimulation seems
unfeasible. However, it is suggested that subthreshold TI stimulation can be used to synchronise the firing
of neurons to the TI signal. Next to the immediate effect on the neuron, TI stimulation could also, like
other electrical stimulation methods, impact the plasticity and the interconnectivity of neurons (Howell and
McIntyre, 2021). Up to now, it was said that high-frequency signals do not cause stimulation. This is not
entirely true: there are actually three ways for a neuron to respond to a high-frequency signal. There can be
either one action potential (AP) at the signal onset, continuous firing or depolarization block. It may be
impossible to stimulate the deep regions of the brain without also causing a conduction block in other parts
of the brain (Mirzakhalili et al., 2020). This conduction block occurs at higher input intensities and could
lead to an upper limit for the use of TI stimulation (Grossman et al., 2017). The conduction block was
also seen in Wang et al. (2022), with morphologically-realistic neuron models at amplitudes that were an
order of magnitude larger than the amplitude for activation. This again shows the difficulty with off-target
regions during TI stimulation (Wang et al., 2022).

Regarding the underlying mechanism at the neuron level that enables this stimulation type, one of the
earliest hypotheses was that TI stimulation can be explained in terms of the intrinsic low-pass filter property
of a neuron together with a nonlinear component. For example, in the Hodgkin-Huxley framework, the
cell membrane is modeled by a parallel RC circuit, thus implementing a low-pass filter when driven by a
current source Hodgkin and Huxley (1952). Here, a first nonlinearity is introduced in the time-dependent
resistor, through the ion channel dynamics. Indeed, the channel opening and closing rate functions depend
nonlinearly on the membrane potential. Furthermore, subsequent work has generalized the Ohmic current-
voltage relation in the Hodgkin-Huxley model to account for the nonlinear distribution of electrolyte
concentration along the ion channel Frankenhaeuser and Huxley (1964). The resulating Goldman-Hodgkin-
Katz current-voltage relation introduces a second nonlinearity to the equation set. Because of the low-pass
filter property, the neuron cannot react to the high-frequency oscillations and therefore responds to the
low-frequency envelope of the TI signal (Grossman et al., 2017, 2018). It is clear that the low-pass filter
property cannot be the single explanation because with only the properties of a low pass filter, the envelope
could not be extracted by the neuron and it would not respond to the beat frequency. This is because the TI
waveform, as a sum of two high-frequency sines, does not contain spectral content at the beat frequency.
As a result, a pure low-pass filter will not give spectral components at the beat frequency. Alternatively,
by first rectifying the signal and then low-pass filtering, which comes down to an envelope detection of
the TI signal, the beat frequency is extracted. In fact, a rectification process is needed in order to have a
response to the TI-stimulus. However, the neuronal membrane cannot be a perfect demodulator because
high-frequency oscillations can still be found in the membrane potential response (Mirzakhalili et al., 2020;
Cao and Grover, 2018).

The first finding of this paper is the demonstration that the nonlinearity of the Goldman-Hodgkin-Katz
(GHK) equation in the Frankenhaeuser-Huxley model is not strictly required to demonstrate the effect of
TI stimulation found in Grossman et al. (2018). Consequently, our model results indicate that envelope
detection can be realized at the membrane level through the nonlinearity intrinsic to ion channel gating.
From the comparison of biologically inspired models (Frankenhaeuser-Huxley and Hodgkin-Huxley) and

different IF models, a second finding is the required aspects in a computational neuron model to show the
effect of TI stimulation. The third novel aspect is a thorough investigation of the different influences of
both the time constants and the steady-state parameters of the gates to obtain a biophysical explanation of
the neuronal response to TI stimulation. It was already mentioned by Mirzakhalili et al. (2020) and Cao
et al. (2020) that the time constants influence the excitation threshold. In this study, this is investigated in
more detail.

2   METHODS

2.1   Neuron models

In this study, single-compartment models are used. This means that the morphology of the neuron is not
taken into account. This can be justified as the idea is to investigate the influence of nonlinearities on the
neuronal response to sinusoidal signals and TI signals. The longitudinal direction of the neuron does not
add any nonlinearities and is thus not thought to have a big influence on the underlying mechanism of TI
stimulation. The five existing models that are used are the Hodgkin-Huxley (HH) (Hodgkin and Huxley,
1952), Frankenhaeuser-Huxley (FH) (Frankenhaeuser and Huxley, 1964), leaky integrate-and-fire model
(LIF), exponential integrate-and-fire (EIF) and the adaptive and exponential integrate-and-fire (AdEx)
model. The first two are described by the following equations:

$$C_{\mathrm{M}}\frac{dV}{dt} = I_{\mathrm{e}} - \left(I_{\mathrm{l}} + \sum_{X} I_{\mathrm{X}}\right) \tag{1}$$

$$\tau_{\mathrm{x}}(V)\frac{\mathrm{d}x}{\mathrm{d}t} = x_{\infty}(V) - x \tag{2}$$

where C_{M} is the membrane capacitance, V is the membrane potential, I_{e} is the input current, I_{l} is the
leak current and I_{X} are the currents linked to voltage-dependent gates, where X can be Na, K or p
(sodium, potassium and a non-specific current, respectively). The values for all of the constants are taken
from Hodgkin and Huxley (1952) and Frankenhaeuser and Huxley (1964). In (2), x can be m, h, n or
p. These are the open probabilities of the respective gates. p is only used in the FH-model. $\tau_x(V)$ and
$x_{\infty}(V)$ are the time constant and the steady-state value characterising the gates. These are again retrieved
from Hodgkin and Huxley (1952) and Frankenhaeuser and Huxley (1964). For TI, I_{e} is of the form
$I_{\mathrm{e}} = \frac{A}{2}(\sin(2\pi f_1 t) + \sin(2\pi f_2 t)) = A\cos(\pi f_b t)\sin(2\pi f_c t)$, where f_b is the beat frequency and f_c is
the carrier frequency. The ion currents of the FH-model and HH-model are of the form of (3) and (4),
respectively.

$$I_X = m^a h^b n^c p^d P_X \frac{VF^2}{R_{\mathrm{g}}T} \frac{[X]_o - [X]_i \exp(\frac{VF}{R_{\mathrm{g}}T})}{1 - \exp(\frac{VF}{R_{\mathrm{g}}T})} \tag{3}$$

$$I_X = m^e h^f n^k g_X(V - E_X) \tag{4}$$

The part of (3) after the gates (m, h, n and p) is known as the Goldman-Hodgkin-Katz (GHK) flux equation.
P_X is the ion-specific permeability, F is the Faraday constant, R_{g} is the ideal gas constant and T is
the temperature. The exponents a, b, c, d, e, f and k are the number of gates of the respective channel

and depend on both the model and the ion type. $[X]_o$ and $[X]_i$ are the extracellular and intracellular
concentrations of the ion X, respectively. The HH- and FH-model are made for the squid giant axon and
the myelinated nerve fibre of Xenopus laevis, respectively. However, mammalian neurons function in a
similar way. As this study focuses on the qualitative behavior of neurons, these models are well suited for
the aims of this study.

The LIF-model is described by:

$$\tau_m \frac{dV}{dt} = RI_e - (V - V_r) \tag{5}$$

155 and the EIF-model is described by:

$$\tau_m \frac{dV}{dt} = RI_e - (V - V_r) - \Delta_T \exp\left(\frac{V - V_T}{\Delta_T}\right) \tag{6}$$

156 where τ_m is the membrane time constant, R is the membrane resistance, V_r is the resting potential, Δ_T
157 is the slope factor that determines the sharpness of the threshold and V_T is the model intrinsic spike
158 threshold. When the threshold V_{thresh} is reached, the potential resets to V_{reset}. Note that the LIF-model is
159 the EIF-model in the limit of $\Delta_T \to 0$. The AdEx-model is very similar but has an additional differential
160 equation. It is described by:

$$\tau_m \frac{dV}{dt} = RI_e - (V - V_r) - \Delta_T \exp\left(\frac{V - V_T}{\Delta_T}\right) - RW \tag{7}$$

$$\tau_w \frac{dW}{dt} = a_0(V - V_r) - W \tag{8}$$

161 where the additional parameter a_0 determines the level of subthreshold adaptation. Again when a threshold
162 V_{thresh} is reached, the potential is reset to V_{reset} while W is changed into $W + b_0$ (Brette and Gerstner,
163 2005). The parameters used for the presented results of the IF-models are given in Table 1 unless stated
164 otherwise. The IF-models are mainly added in order to investigate which characteristics are needed in
165 neuron models to make the neuron spike at lower inputs for a TI signal than for a sinusoidal signal.

2.2 Neuron model extensions

167 To investigate the influence of the nonlinearity of the GHK-equation, two new models are constructed
168 from the HH- and FH-model. A partly linearized version of the FH-model (FH1) is obtained by replacing
169 the GHK-factor of (3) by its first-order Taylor expansion for I_K, I_{Na} and I_p. In (9), this is shown more
170 specifically by the transition from left to right.

$$I_X = m^a h^b n^c p^d A_X x \frac{B_X - C_X \exp(x)}{1 - \exp(x)} \longleftrightarrow I_X = \left(I_X(x_{X,0}) + \frac{dI_X}{dx}(x_{X,0})(x - x_{X,0})\right) \tag{9}$$

where $x = \frac{F}{RT}V$, $A_X = P_X \frac{F^2}{R_g T}$, $B_X = [X]_o$, $C_X = [X]_i$ and $x_{X,0} = \frac{F}{R_g T}V_{X,0}$. In this transition, the
gates remain the same as in the original models. The ion currents are thus still nonlinear because of the
gate equations, only the part representing the GHK-equation is linearized for FH1. For the HH-model, the

opposite is done. It is assumed that the HH-model is the first-order Taylor expansion of a more general
model. This more general model is then of the form of (3) and is called the gHH-model. In (9), this
corresponds to the transition from right to left. In order to obtain these new models, the right expansion
points $((V_{Na,0}, V_{K,0})$ and $(V_{Na,0}, V_{K,0}, V_{p,0}))$ for this Taylor series should be found for the gHH and FH1
model, respectively. Two methods are followed to realise this, resulting in four derived models: gHHv1,
FH1v1 (method 1) and gHHv2, FH1v2 (method 2).

The first method consists of calculating the reversal potentials for the ion currents (i.e. the Nernst potentials)
and taking these as the expansion points. In the second method, a sweep is done over several combinations
of possible Taylor expansion points. For each set, several combinations of duration and intensity of a
rectangular input signal are tested. The values for the input amplitudes are ten uniformly distributed values
between $300 \frac{\mu A}{cm^2}$ and $800 \frac{\mu A}{cm^2}$ for the FH-model and between $0 \frac{\mu A}{cm^2}$ and $100 \frac{\mu A}{cm^2}$ for the HH-model. For
the stimulation duration, ten uniformly distributed values between 0.05 ms and 2.00 ms are chosen for
both models. For every combination, the correlation between the membrane response of the original and
the new model is calculated. The correlations of the different duration-intensity combinations are averaged.
The $(V_{Na,0}, V_{K,0})$-combination with the highest average correlation is chosen for the new model. For the
FH1 models, it is assumed that $V_{p,0} = V_{Na,0}$.

2.3 Gates

191 To investigate the influence of the time constants, a small adaptation is made to (2). A parameter k_x is
192 introduced to scale the time constant of the gates so that

$$\tau_{x,new} = k_x \tau_{x,original} \qquad [\text{s}] \tag{10}$$

193 Lastly the steady-state values of the gates are investigated in more detail. The equations for the steady-
194 state values are replaced by a logistic function like (11), while the original time constant equations are
195 maintained.

$$x_\infty = \frac{1}{1 + \exp(-a(V - V_r - b))} \tag{11}$$

196 The influence of the parameters a and b on the TI-effects can then be investigated. The goal of this approach
197 is to get insight into how the behavior changes with changing parameters and not to approximate the real
198 behavior of the neuron globally. V_r is the rest potential and is equal to -70 mV.

2.4 behavior analysis

The analysis of the results was done based on the firing rate (FR) and the new energy metric defined
below in (13). To obtain the firing rate, first the action potentials (APs) need to be determined. For the
IF-models, an AP is counted every time the threshold V_{thresh} is exceeded. For the HH-like models, an AP
was detected based on the m-gate. The m-gate, that is responsible for the Na^+-influx that initiates the AP,
needs to cross a threshold value of 0.75 for an AP to be counted. This definition is preferred because the
membrane potential oscillates with the carrier frequency, while the m-gate is more robust. An additional
rule is set that the m-gate needs to drop below 0.10 before a new AP can be counted, in order to avoid
miscounts when the m-gate oscillates around 0.75. To cancel out the influence of transient behaviors caused
by the onset of the input current, only a certain time window is considered to determine the FR. This time

window is from $100\,\mathrm{ms}$ after the stimulation onset until $100\,\mathrm{ms} + \frac{20}{f_b}$ after the stimulation onset, where f_b
is the beat frequency. In this way, 20 periods of the envelope are included. Then the FR is calculated with:

$$\mathrm{FR} = \frac{N}{t_{\mathrm{window}}} \qquad [\mathrm{Hz}] \tag{12}$$

where N is the number of APs counted and t_{window} is the duration of the stimulation in the investigated
time window, being $\frac{20}{f_b}$.

A disadvantage of the FR metrix is that it depends on the arbitrary lower and upper excitation threshold
values of 0.10 and 0.75. Because it is not ideal that the results depend on the choice of these values, a
metric based on the energy of the signal is introduced for extra analysis. This metric pTI (percentage of TI)
is defined as:

$$\mathrm{pTI} = \frac{E_{\mathrm{TI,b}}}{E_{\mathrm{TI,tot}}} \qquad [-] \tag{13}$$

217 where $E_{\mathrm{TI,b}}$ is the sum of the energy at the beat frequency and the first harmonic of the beat frequency in
218 the frequency spectrum of the membrane potential in response to the TI signal. $E_{\mathrm{TI,tot}}$ is the total energy in
219 the membrane response to the TI signal (i.e. the sum of the magnitudes at all frequencies). The total energy
220 is restricted to energies at frequencies higher than $0\,\mathrm{Hz}$ in the frequency spectrum. The DC-component is
221 thus not taken into account, to ensure that pTI is independent of the resting potential.

2.5 Software

The programming, analysis and simulations were performed in MATLAB R2021b. The ode45, ode15s
and ode4 solvers of Matlab were used to calculate the neuronal response numerically (Shampine and
Reichelt, 1997). For example, the fixed step ode4-solver was needed for transforming the signals to the
frequency spectrum. The variable step variable order solvers, ode45 and ode15s were used to speed up the
simulations when no frequency information was needed. The principle of the ode45 and ode15s solvers is
explained in Ashino et al. (2000).

3 RESULTS

229 A summary of the most important results is given in Tables 2 and 3. Table 2 shows for which of the
230 discussed models it is possible to get a TI zone. The TI zone is defined as the range of input intensities for
231 which the TI signal causes regular firing and the sine input with the same carrier frequency does not cause
232 regular firing. Regular firing is defined as the neuron having more than one spike during the considered
233 time window explained in section 2.4.

3.1 IF-models

Figure 2 shows the threshold for regular firing, induced by a TI waveform (solid lines) and by a single
sinusoid at the same carrier frequency (dashed lines). The input current is divided by an area of $1\,\mathrm{cm}^2$ to
get a measure in $\frac{\mu\mathrm{A}}{\mathrm{cm}^2}$. In the case of the LIF model, the TI signal causes APs at a lower threshold than the
sinusoidal signal. The LIF model thus shows a TI zone. However, the width of this zone is on average only
0.0646% of the threshold of the TI signal. For both EIF models, the single sinusoid causes regular firing at

a lower threshold than the TI signal. The TI threshold is 1.13 and 1.18 times higher than the sine threshold
for the EIF1 and EIF2 model, respectively.

For the AdEx-model, the TI signal again causes firing at higher intensities (approximately 1.12 times higher
for a TI signal than for a sinusoidal signal). For all models and all signals, it is clear that for a higher carrier
frequency, a higher input is needed to achieve stimulation. None of the IF models showed a depolarization
block over the range of $1\,\text{kHz} - 4\,\text{kHz}$.

3.2   Effect of nonlinearity in current equations

Two methods are used to determine the Taylor expansion points for the gHH and FH1 models, as
described in section 2.2. For the first method, the expansion points are chosen equal to the Nernst reversal
potentials of the ion currents. For the HH-model, this results in $V_{Na,0} = 45\,\text{mV}$ and $V_{K,0} = -82\,\text{mV}$. For
the FH-model this results in $V_{Na,0} = 53.53\,\text{mV}$, $V_{K,0} = -97.74\,\text{mV}$ and $V_{p,0} = 53.53\,\text{mV}$.

For the second method, the average correlations are calculated as described in section 2.1. The maximum
for the FH1v2-model can be found at $(V_{Na,0} = -30.69\,\text{mV}, V_{K,0} = -37.24\,\text{mV})$ and is equal to
0.994. The average correlation for the FH1v1-model is 0.924. For the gHHv2-model, the maximum is at
$(V_{Na,0} = 0.34\,\text{mV}, V_{K,0} = -78.6\,\text{mV})$ and is equal to 0.971. The average correlation for the gHH1v1-
model is 0.785. Figure S1 in the supplementary information shows the average correlation as function of
the Taylor expansion points for the gHHv2 and FH1v2 models. Some examples of voltage traces are shown
in Figure S2.

3.2.1   FH vs FH1

Figures 3A-C show the energy plot of the FH-model and the difference with the energy of the FH1-models
$(\text{pTI}_{\text{FH1}} - \text{pTI}_{\text{FH}})$ as a comparison. In Figure 3A it can be seen that for a higher f_c value, there is a larger
range of input intensities for which the neuron reacts at the beat frequency of the TI-input. Also for a
higher f_c, a higher input is needed to achieve spiking. Moreover, it can be seen that the behavior of the
FH1-models is very similar to the original FH-model (Figures 3B-C). Here, FH1v2 is a closer match than
FH1v1 to the original FH-model. The only difference is that the FH1-models get high energies at the beat
frequency at higher input intensities.

The plots of the threshold lines can be used to compare the models as well. These results are shown in
Figures 3D-I. From the threshold lines, the TI zone can be deduced. Again it can be seen that the models
are very alike with some minor differences (maximal relative difference between thresholds of $15.03\,\%$
and $3.49\,\%$ for FH1v1 and FH1v2 with respect to FH, respectively). Comparing the two solid lines, the
FH model and FH1 models have a TI zone in the whole range of the carrier frequency from $1\,\text{kHz}$ to
$4\,\text{kHz}$. The maximal width of the TI zone is $30.52\,\frac{\mu\text{A}}{\text{cm}^2}$, $35.46\,\frac{\mu\text{A}}{\text{cm}^2}$ and $29.72\,\frac{\mu\text{A}}{\text{cm}^2}$ for the FH, FH1v1 and
FH1v2 model, respectively. The FH1v2-model again shows the best match to the FH-model over the whole
f_c-range. Considering the fact that these TI zones are very small, an example is shown in the supplementary
information with a larger TI zone (Figure S3). In this case, the a and b parameters of the logistic function
are changed (cf. (11)). The influence of these parameters are discussed in sections 3.3.2 and 4.4.2.

Moreover, it can be seen that higher intensities are needed to obtain firing at the beat frequency, compared
to regular firing. For the FH model the additional intensity needed is $5.37\,\frac{\mu\text{A}}{\text{cm}^2}$ up to $13.00\,\frac{\mu\text{A}}{\text{cm}^2}$ in the range
of $1\,\text{kHz}$ to $4\,\text{kHz}$. Finally it is interesting to consider the FR for the sine at regular firing. For $f_c > 1.2\,\text{kHz}$,
these FRs are always above $80\,\text{Hz}$.

3.2.2 HH vs gHH

The results for the energy metric and the firing thresholds for the HH and gHH models are shown in
Figure 4. From the energy plots it seems that the models again react very similar with only some minor
differences due to the approximation. The firing thresholds however suggest that there are big differences
for a sinusoidal input. For the sinusoidal input in the HH model, the neuron never spikes above a carrier
frequency equal to $1.74\,\mathrm{kHz}$, while for the gHH-model spiking is seen over the whole f_c-range. It is thus
possible that the GHK-nonlinearity assures more robustness for quickly oscillating signals. Regarding the
TI zone, it is visible that in the whole range in which the pure sine is able to cause APs, the TI signal has a
lower threshold. For the gHHv1 model, there is only a TI zone for $f_c > 1.65\,\mathrm{kHz}$. The gHHv2 model again
shows a TI zone over the whole f_c-range between $1\,\mathrm{kHz}$ and $3\,\mathrm{kHz}$. The maximal width of the TI zone is
$285.79\,\frac{\mu\mathrm{A}}{\mathrm{cm}^2}$, $226.14\,\frac{\mu\mathrm{A}}{\mathrm{cm}^2}$ and $911.04\,\frac{\mu\mathrm{A}}{\mathrm{cm}^2}$ for the HH, gHHv1 and gHHv2 model, respectively. Interesting is
the threshold for firing at the beat frequency. This threshold of the sinusoidal input is lower than that of
the TI input for certain parameter choices. This applies for the HH model for $f_c < 1.4\,\mathrm{kHz}$, in the whole
tested f_c range for the gHHv1 model and for $f_c < 2.63\,\mathrm{kHz}$ for the gHHv2 model.

3.3 Gates

3.3.1 Time constants

Figure 5 shows the influence on the firing thresholds for the different k-parameters. For the m-gate
(Figure 5A), a logarithmic trend is followed. The thresholds increase with increasing k_m-values until
it reaches a plateau. Moreover, the blue and red lines cross around $k_m = 1.57$, meaning the TI zone
disappears for higher k_m-values.

For very low values of k_h (< 0.7), the input intensity needed to achieve spiking increases rapidly for both
the TI and sine signal for decreasing k_h values. When $k_h < 0.1$, it is not possible anymore to create APs.
For $k_h > 0.7$, the threshold lines increase for firing at the beat frequency but stay approximately constant
for regular firing.

Similar results are found for the n-gate: for very low k_n-values ($k_n < 1$), all input thresholds increase,
while for high k_n-values the thresholds stay more or less constant except for firing at the beat frequency.

Furthermore, it can be seen that the TI signal is able to cause regular firing at lower input intensities than
needed for firing at the beat frequency. For low k-values, the solid and dashed blue line in Figure 5 are
almost equal. In contrast, a gap of $16.92\,\frac{\mu\mathrm{A}}{\mathrm{cm}^2}$, $116.45\,\frac{\mu\mathrm{A}}{\mathrm{cm}^2}$ and $40.64\,\frac{\mu\mathrm{A}}{\mathrm{cm}^2}$ arises for $k_m = 4$, $k_h = 4$ and
$k_n = 4$, respectively.

Finally, it can again be seen that for certain k values the threshold for firing at the beat frequency is higher
for the TI signal than for the sinusoidal signal. This is the case for $k_m > 1.18$, $k_h > 1.22$ and $k_n > 2.09$.

3.3.2 Steady-state values

The effect of changing the slope of the m-gate's membrane potential dependency is shown in Figure 6A.
A higher a-value shifts the TI zone to higher input currents. The influence of the b-value (i.e. shifting the
logistic function along the x-axis) of the m-gate is similar (Figure 6B). A small increase in the b-value
makes the threshold lines shift to higher input currents. Moreover, a plateau is observed for $b < 27\,\mathrm{mV}$
where the neuron fires spontaneously.

For the h-gate, a similar but opposite effect is seen. An increase in b-value shifts the thresholds, and thus
the TI zone, to lower input currents (Figure 6D). It has to be noted that this effect is less pronounced.

While for the m-gate, a slight change in b-value causes a big shift along the y-axis, for the h-gate a bigger
change in b-value is needed to accomplish the same shift. Increasing the a-parameter of the h-gate increases
the threshold for spiking activity. In contrast to the m-gate, it increases in a convex way. An interesting
observation is that the threshold for the TI input increases faster than for the sine-input with an intersection
of the two dashed lines at $a_h = -0.15 \frac{1}{\text{mV}}$. Also for the b-parameter, an intersection of the dashed blue and
red line can be seen at $b_h = 11.48 \, \text{mV}$.

In case of the n-gate, increasing the a-value shifts the threshold lines to lower input currents. The TI zone
spans over the whole a_n and b_n ranges, but there are intersections of the dashed lines for $a_n = 0.18 \frac{1}{\text{mV}}$
and $b_n = 34.48 \, \text{mV}$ (Figure 6E-F).

The dependency of the existence of a TI zone on the steady state values and time constants is summarized
in Table 3.

4   DISCUSSION

4.1   IF models

Besides the LIF model, for all investigated IF models it was seen that no TI-behavior is present (Figure 2).
Although the LIF model does not contain any nonlinearities, it is still possible to get a TI zone, despite
being small. The reason for this is that the TI signal contains both the f_1 and f_2 frequencies, while the sine
only contains the f_c frequency. Because $f_1 < f_c$, the threshold is slightly lower for the TI signal than for
the pure sinusoid. This is further explained with the analytical result in the supplementary information
(section S2). From the transition from LIF to EIF it is clear that adding a nonlinearity makes the TI zone
disappear. The transition from EIF to AdEx did not show major differences. However, in Esmaeilpour
et al. (2021), AdEx neurons did show correspondence with the experiments of Grossman et al. (2017). In
that study, they used a network of neurons rather than a single neuron. They also state that the effect was
probably seen because they added the slow GABA_b channels to the network, while isolated AdEx neurons
are unlikely to exhibit the TI behavior.

4.2   FH and HH model

Two conclusions can already be drawn from the FH and HH models. First, the threshold for the neuron to
exhibit regular firing or to fire at the beat frequency is not equal. Second, the FR for a sinusoidal input is
around $100 \, \text{Hz}$ in most cases. The reason for the first conclusion will be discussed more in depth in the
next sections. The second conclusion points out the importance of TI stimulation. When applying a TI
input, it much easier to control the FR of the neurons than for a sinusoidal input, for which the FR changes
much faster with the input intensity. For pure sines, lower FRs can then only be reached when the current
is applied in a pulsed way. If indeed the difference between the excitation thresholds of a TI signal and a
sinusoidal signal is very small, the controllability of the FR with the TI signal can still be an advantage for
TI stimulation as in Howell and McIntyre (2021) and Wessel et al. (2022), where it is proposed to use a
subthreshold TI signal.

4.3   Importance of the GHK nonlinearity

From the comparison between the FH and FH1 models it became clear that linearising the GHK-equation
of the ion currents has a minor effect on the neuronal response. However, the TI zone does not disappear as
seen with the IF-models. Instead, the TI zone behaves as an approximation of the more complex model
without losing its most important characteristics. Simply adding a nonlinearity in the differential equation

of the membrane potential is thus not sufficient to fully change the behavior of the neuron model. The shift
of the pTI-metric to higher input intensities is explained by the observation that the Na^+-current is lower
in magnitude for the FH1-models, so a higher input is needed to achieve firing. This is supported by the
fact that the FH1v2-model is a better approximation in which the magnitude of the Na^+-current is higher,
especially at lower membrane potentials.

The comparison of the HH and gHH models shows larger differences. For example, it is less straightforward
to determine which linearised model better approximates the behavior of the HH-model. However, with
both models it is possible to achieve a TI zone. From this it can be concluded that the GHK nonlinearity is
not the main reason for a neuron model to show a TI zone.

4.4   Gates

The effect of the different characteristics of the gates will be explained in this section, but the mechanism
of TI can be best explained with Figure 7. Figure 7 shows that a TI signal can elicit an AP at every other
beat, while the sinusoidal signal with the same carrier frequency can only elicit an AP at the stimulation
onset. An explanation for this behavior can be found by examining the gates. For the response to a
sinusoidal signal, all the gates reach a state of small-amplitude oscillations about a quasi-equilibrium value.
However, the values around which they oscillate are not favorable for neuronal excitation (a higher h-value
and a lower n-value would be better). Comparing this to the TI signal (Figure 7A), it can be seen that
because this input signal drops to lower values for a longer period, the n- and h- gates are able to return
to values that are more favorable to create an AP. This is further illustrated by the observation that no
AP is induced by the second beat in Figure 7A, because the h-gate value is still too low. However, at the
subsequent beat, further opening of the h-gate results in an AP.

4.4.1   Time constants

The results in Figure 5A show that the m-gate time constant has the most influence on the behavior of the
neuron. For lower time constants, the neuron starts to fire at lower amplitudes of the input current. This can
be explained by the fact that the fast reaction of the m-gate is responsible for the initiation of an AP. If the
m-gate would react infinitely fast, an AP would be created at the moment that a certain threshold of the
membrane potential is reached. When the m-gate reacts with a certain lag, a higher membrane potential
should be reached to create an AP, as the m-gate needs some time to get to a value that is high enough to
push the membrane potential into an AP. However, if the potential starts decreasing again shortly after its
maximum is reached and the m-gate starts decreasing as well, no AP will be created. Because of this, the
firing thresholds increase proportional to the m-gate time constant (cf. Figure 5A). Above $k_m = 1$, the
threshold for regular firing of the sine decreases slightly. This is due to an interplay of the closing and
opening of the m-gate over multiple periods of the sine.

For the h-gate it was seen that both very low and very high time constants increase the threshold current for
firing at the beat frequency (Figure 5B). In the case of a very low time constant, this is because the h-gate
closes too fast (Figure 8A). In contrast, high time constants result in reduced h-gate opening after a first
action potential, resulting in higher excitation thresholds (Figure 8B). This also explains why from a certain
point, increasing k_h only has an influence on the threshold for firing at beat frequency of the TI signal
(dashed blue line). The slower the h-gate reacts, the more beats are skipped and the higher the input current
has to be to force the neuron to respond to every beat. This will not affect the regular firing threshold of the

TI signal because the effect is only on the time between spikes. When the h-gate has reopened, the rapid
response of the m-gate will always be able to initiate a new AP, only the FR will be lower. For sine-input,
the same reasoning can be made: waiting long enough for the h-gate to reopen will always lead to a new
AP, only with a lower FR.

The reasoning for the n-gate is very similar to that of the h-gate. Opening of the n-gates causes an outflow
of K^+-ions resulting in a decrease of the membrane potential. Both gates can thus counteract the formation
of an AP with the only difference that the effect of the h-gate is present in the form of a multiplication
with the m-gate, while the effect of the n-gate is present in the addition of the K^+-current. Therefore, a
fast-reacting n-gate (low k_n) makes it harder to create an AP and thus a higher input current is needed to
achieve spiking (cf. Figure 5C). For a slower n-gate (high k_n), the K^+-outflow will still be too high to
initiate a new AP at the next beats. The reasoning why the threshold for firing at the beat frequency of the
TI signal changes most with increasing k_n is the same as with increasing k_h.

The threshold for firing at the beat frequency is lower for a sine input than for a TI input for $k_{\mathrm{m}} > 1.18$,
$k_{\mathrm{h}} > 1.22$ or $k_{\mathrm{n}} > 2.09$. This is because increasing the input intensity above the threshold for spiking for a
sine will increase the FR in a continuous way. In contrast, increasing the intensity above the threshold for
a TI signal will not immediately increase the FR. The FR will only increase when more beats can cause
an AP. Therefore, the FR will make a discrete jump when increasing the input intensity. Moreover, at
the theshold, the neuron is expected to fire around the trough of the envelope. When the input is just too
low, it is possible that some beats do not elicit an AP, because the states of the gates were not right in the
short time frame around the top of the beat. In this way, it is possible that the sine causes firing at the beat
frequency of the TI signal it is compared to, but the TI signal needs a higher intensity to fire at its beat
frequency.

421   4.4.2   Steady-state values

From the discussion above, it has become clear that the values of the gates play an important role.
The time constants that were discussed play a role in how fast the gates can reach a certain value. The
steady-state characteristic then determines to which value the gates evolve. This is investigated in this study
by changing the a- and b-parameters in the logistic function approximation of the gates.

Starting with the m-gate (Figures 6A and 6B), a TI zone is present for all the investigated a-values.
Increasing the steady-state values shifts the TI zone to higher input currents. For a higher b-value, a TI
zone appears, while for the a-value, the TI zone becomes smaller. The reason for the shift of the threshold
to higher input currents is that for higher a- or b-values, the m-gate is in a more closed state at lower
membrane potentials. Interestingly, for values of $b < 27$ mV, the neuron fires spontaneously. In other
words, the open probability of the m-gate is high enough at low membrane potentials so the neuron can
always enter the positive feedback loop to form an AP.

For the h-gate, the behavior for different values of a and b can be explained by the fact that for higher
a-values or lower b-values, the h-value around the resting potential is lower. The h-gate is thus already in a
more closed state resulting in a lower Na^+-current and a higher input current needed to cause firing.

Useful for the application of TI stimulation is that the steepness of the threshold is not the same for the
TI-input and the sinusoidal input. For low b_h-values, this causes a substantial TI zone. The reason for
this is the following. When the threshold input is plotted with respect to the beat frequency (Figure 9), it

can be seen that a global minimum exists and thus there is an optimal beat frequency for TI stimulation.
When the characteristic parameters a, b and k of the gates are altered, the minimum shifts to other beat
frequencies. The beat frequency at the minimal threshold current is shown in Figures 9B-G. For example,
increasing the a_h- and b_h-parameter generally shifts the optimal beat frequencies to lower values, with a
local maximum at $b_h = 10$ mV. Hence, the optimal f_b comes closer to 0 Hz and goes further from the case
of $f_b = 100$ Hz with increasing a_h-value. Because the TI signal approximates a sine for $f_b \rightarrow 0$ Hz, a sine
can be seen as a TI signal with $f_b = 0$ Hz, with increasing a_h-value, the threshold for a sine increases less
steep than the threshold for the TI signal (Figure 6C). The same holds for the increasing b_h parameter in
Figure 6D. In this case, the decrease of the red lines is steeper because the sine comes closer to the optimal
beat frequency with increasing b_h. On the other hand, the h-value at low membrane potentials increases
which is in turn more favorable to create an AP. This means that there is a double effect for the decreasing
threshold. For the 100 Hz beat frequency TI-input, the increase in h-value at low membrane potentials for
increasing b_h-value again causes a decrease in threshold but because the optimal beat frequency shifts to
lower values, the decrease in threshold is less steep.

Similarly, the dependency if the optimal f_b on a_X and b_X explains the difference in steepness of the
thresholds for the sine and the TI signal for the m- and h-gate. The reasoning can also be followed for the
k-values. In this case, the effect can be best seen for higher k-values in Figure 5: the optimal beat frequency
is inversely proportional with k.

The reason for the existence of an optimal beat frequency is because of the following: when the beat
frequency is too high, some of the gates might not be restored to a value that is sufficient to create a new
AP. Because of this, some beats might be skipped in the neuronal response to the TI waveform. When the
beat frequency is too low, the TI waveform envelope builds up too slow. Because of this slow build-up, the
h-gate tends to close too fast while the n-gate opens too fast. Because of this the input current needed to
create an AP is higher.

Equation (17) can be used to get more insight into the relation between the optimal beat frequency and the
membrane channel dynamics. To derive (17), it is assumed that two phases can be distinguished. In each
phase τ_x and x_∞ are constant. In the first phase, the gate characteristics take their values at the membrane
potential at the peak of the AP. In the second phase, the gate characteristics take their values at the resting
potential. This assumption might not be acceptable for the m-gate, which can be approximated as an
instantaneous function $m = m_\infty(V)$ due to its fast nature. A second assumption is that when looking at
threshold values, the AP is induced at the top of the beat and the gates should be restored around the node
of the TI signal. A third assumption is that x does not change much in the half period before the AP. This
means these two phases should be ran through in a half period of the envelope ($= \frac{1}{2f_b}$). This assumption is
supported by our observation in a simplified HH-model, that the h-gate is opened at the envelope node for
beat-locked spiking Plovie et al. (2022).

The starting point in the derivation is (2). With the assumption of a constant τ_x and x_∞, the solution for x
during the first and second phase is shown in (14) and (15), respectively.

$$x(t) = (x_0 - x_{\infty,1})\exp\left(-\frac{t}{\tau_{x,1}}\right) + x_{\infty,1} \tag{14}$$

$$x(t) = (x_1 - x_{\infty,2})\exp\left(-\frac{t}{\tau_{x,2}}\right) + x_{\infty,2} \tag{15}$$

The next step is to solve $x(t_1) = x_1$ for t_1 and $x(t_2) = x_2$ for t_2. The total time is then the sum of t_1 and t_2:

$$\Delta t = t_1 + t_2 = -\tau_{x,1} \ln \left(\frac{x_1 - x_{\infty,1}}{x_0 - x_{\infty,1}} \right) - \tau_{x,2} \ln \left(\frac{x_2 - x_{\infty,2}}{x_1 - x_{\infty,2}} \right) \tag{16}$$

where x can be h or n. Here, x_0, x_1 and x_2 are the gate parameters at the crest, somewhere between crest and trough (at the minimum of the h-gate or the maximum of the n-gate), and at the trough of the envelope, respectively. The optimal beat frequency then becomes:

$$f_{b,opt} = -\frac{1}{2\left(\tau_{x,1} \ln \left(\frac{x_1 - x_{\infty,1}}{x_0 - x_{\infty,1}} \right) + \tau_{x,2} \ln \left(\frac{x_2 - x_{\infty,2}}{x_1 - x_{\infty,2}} \right) \right)} \tag{17}$$

Because k_x is directly related to the time constant (see (10)), a slower gate means that a lower beat frequency is better. This shows the inverse proportionality of the optimal beat frequency with k_x. With this equation, there is an optimal beat frequency for every gate but of course there is only one optimal beat frequency for the whole system. This should be a combination of the different optima for the different gates. Still, (17) gives some mathematical insight into why there is an optimal beat frequency and how it depends on the different gate parameters. As an illustration, when the parameters ($h_0 = 0.75$, $h_1 = 0.025$, $h_2 = 0.75$, $h_{\infty,1} = 0$, $h_{\infty,2} = 0.80$, $n_0 = 0.05$, $n_1 = 0.56$, $n_2 = 0.05$, $n_{\infty,1} = 1$ and $n_{\infty,2} = 0.025$) are filled in (17) in the case of spiking at the beat frequency, the resulting optimal beat frequency is 51.1 Hz for the h-gate and 119.3 Hz for the n-gate. From the simulations it was found to be 52.7 Hz for the whole system. When $k_n = 3$, the optimal beat frequency for the n-gate according to (17) changes to 39.8 Hz while the optimal beat frequency from the simulations is 45.8 Hz. For $k_h = 3$, the optimal beat frequency for the h-gate according to (17) changes to 17.0 Hz while the simulation gives 23.2 Hz. The optimum is thus inbetween the optimal values of the n-gate and h-gate. The existence of the optimal beat frequency is in line with the concept of resonance in neurons Hutcheon and Yarom (2000). This discussion shows that the resonant beat frequency does not only depend on the time constant of the gates, but also on their steady-state characteristics.

4.5 Limitations and future work

Because TI neuromodulation has only recently gained attention, the technique itself can still be improved. For example, the focality of TI stimulation is still in the order of centimeters. This can be improved by adding extra electrode pairs or by using a lensing effect Cao and Grover (2020). Multiple focal points can be achieved by adding extra electrode pairs or by using multiple frequencies in the present electrode pairs. In this way, two TI signals are generated with different carrier frequencies Zhu et al. (2019). Finally, in classic TI stimulation, a reference electrode is placed at the chest. Orientation-tunable temporal interference (ot-TI) is a different method where the reference is chosen locally on the scalp. This heavily influences the electric field lines. With this method, the importance of the direction of the electric field can be shown (Missey et al., 2021).

A first limitation of this study of the underlying mechanism of TI stimulation is that the spatial properties of the electric field are not taken into account in the cell models. Other authors have used morphologically correct neuron models, to investigate the neuronal response to TI modulation Wang et al. (2022). However, axial coupling in these spatially extended models is linear and as a result is not expected to influence

the qualitative results obtained in this paper (i.e. dependency of the existence of a TI zone on the GHK nonlinearity and gating dynamics). Nevertheless, morphologically realistic models are interesting to obtain quantitative insights into the activation and conduction block thresholds. Moreover, a limitation of point neurons is that it is not always certain if the detected APs can propagate. A second limitation of this study, is that the TI-modulated point neurons are isolated, while neuronal network simulations have demonstrated the importance of network adaptation Esmaeilpour et al. (2021). As future work, it would be interesting to investigate the influence of synaptic time constants on the TI zone. The underlying mechanism of TI stimulation can thus be found in a lot of aspects of the neural system and may be a combined effect of several factors. Therefore, the investigation in this study of the nonlinearities and time constants in point neurons is a first step in the direction of a comprehensive understanding of neuromodulation by temporal interference.

5 CONCLUSION

This study consists of two major parts. First, the discussion of the complexity of neuron models needed to be able to model the experimentally observed responses to TI-DBS. Second, the time dynamics of the ion gates in relation to TI stimulation.

From the first part, it can be concluded that the nonlinearity in the GHK-equation alone is not able to explain the underlying mechanism of TI-DBS. For the FH-model, the linearisation causes minor differences in the neuronal response, that are not sufficient to describe the TI underlying mechanism. For the HH-model, the differences caused by the GHK nonlinearity are bigger. However, the Hodgkin-Huxley TI zone is actually larger in the linearised model, confirming that the GHK nonlinearity is not necessary in order to observe neuronal sensitivity to a beating sine. It should be noted that the choice of the expansion points has a big influence on the neuronal behavior as well. From the investigation of the IF-models it can also be concluded that the introduction of a nonlinear term in the differential equations is not able to shift the threshold of the TI-input beneath that of the sinusoidal input.

From the second part, it can be concluded that the nonlinearities intrinsic to the gating dynamics have a big influence on how the neurons react to the TI and sine input. The mechanism is a complex interplay between the gates that is driven by the gate characteristics in terms of the time constants and steady-state values. This paper showed that changing the gates' opening and closing rates can influence the existence and the width of the TI zone. A TI zone can appear with increasing b_m values or with a decrease of the k_m, a_m or b_h parameter. It was also shown that for a certain neuron, it is possible to find the optimal stimulation parameters to increase the TI zone. This is an interesting finding for the optimization of TI stimulation, for which there is a combination of different neuron types at different locations throughout the brain or nerves.

CONFLICT OF INTEREST STATEMENT

The authors declare that the research was conducted in the absence of any commercial or financial relationships that could be construed as a potential conflict of interest.

AUTHOR CONTRIBUTIONS

TP, RS, TT, LM, WJ and ET contributed to the study design. TP performed the simulations and wrote the manuscript with major suggestions of all other authors. RS and TT had a great deal of input into the ideas for simulations. ET supervised the work. All authors read and approved the submitted manuscript.

FUNDING

547 This research was funded by the FWO-project G019121N. T Tarnaud is a postdoctoral Fellow of the
548 FWO-V (Research Foundation Flanders, Belgium). R Schoeters is a Ph.D. Fellow of the FWO-V (Research
549 Foundation Flanders, Belgium).

ACKNOWLEDGMENTS

550 We want to thank Michiel De Kesel for the exploratory work and discovering the possible importance of
551 the nonlinearity of the GHK-equation.

REFERENCES

Acerbo, E., Jegou, A., Luff, C., Dzialecka, P., Botzanowski, B., Missey, F., et al. (2022). Focal non-invasive
deep-brain stimulation with temporal interference for the suppression of epileptic biomarkers. *Frontiers*
in Neuroscience 16. doi:10.3389/fnins.2022.945221

Ashino, R., Nagase, M., and Vaillancourt, R. (2000). Behind and beyond the matlab ode suite. *Computers*
and Mathematics with Applications 40, 491–512

Aum, D. J. and Tierney, T. S. (2018). Deep brain stimulation: foundations and future trends. *Frontiers In*
Bioscience 23, 162–182

Brette, R. and Gerstner, W. (2005). Adaptive exponential integrate-and-fire model as an effective description
of neuronal activity. *Journal of Neurophysiology* 94, 3637–3642. doi:10.1152/jn.00686.2005

Cao, J., Doiron, B., Goswami, C., and Grover, P. (2020). The mechanics of temporal interference
stimulation doi:10.1101/2020.04.23.051870

Cao, J. and Grover, P. (2018). Do single neuron models exhibit temporal interference stimulation? (Institute
of Electrical and Electronics Engineers Inc.). doi:10.1109/BIOCAS.2018.8584745

Cao, J. and Grover, P. (2020). Stimulus: Noninvasive dynamic patterns of neurostimulation using spatio-
temporal interference. *IEEE Transactions on Biomedical Engineering* 67, 726–737. doi:10.1109/TBME.
2019.2919912

Esmaeilpour, Z., Kronberg, G., Reato, D., Parra, L. C., and Bikson, M. (2021). Temporal interference
stimulation targets deep brain regions by modulating neural oscillations. *Brain Stimulation* 14, 55–65.
doi:10.1016/j.brs.2020.11.007

Frankenhaeuser, B. and Huxley, A. F. (1964). The action potential in the myelinated nerve fibre of xenopus
laevis as computed on the basis of voltage clamp data. *J. Phy8iol* 171, 302–315

Gomez-Tames, J., Asai, A., and Hirata, A. (2021). Multiscale computational model reveals nerve
response in a mouse model for temporal interference brain stimulation. *Frontiers in Neuroscience* 15.
doi:10.3389/fnins.2021.684465

Grossman, N., Bono, D., Dedic, N., Kodandaramaiah, S. B., Rudenko, A., Suk, H. J., et al. (2017).
Noninvasive deep brain stimulation via temporally interfering electric fields. *Cell* 169, 1029–1041.e16.
doi:10.1016/j.cell.2017.05.024

Grossman, N., Okun, M. S., and Boyden, E. S. (2018). Translating temporal interference brain stimulation
to treat neurological and psychiatric conditions. *JAMA Neurology* 75, 1307–1308. doi:10.1001/
jamaneurol.2018.2760

Hodgkin, A. L. and Huxley, A. F. (1952). I952) i i7. *J. Physiol* , 500–544

Howell, B. and McIntyre, C. C. (2021). Feasibility of interferential and pulsed transcranial electrical stimulation for neuromodulation at the human scale. *Neuromodulation* 24, 843–853. doi:10.1111/ner.13137

Huang, Y., Huang, Y., Datta, A., and Parra, L. C. (2020). Optimization of interferential stimulation of the human brain with electrode arrays. *Journal of Neural Engineering* 17. doi:10.1088/1741-2552/ab92b3

Huang, Y. and Parra, L. C. (2019). Can transcranial electric stimulation with multiple electrodes reach deep targets? *Brain Stimulation* 12, 30–40. doi:10.1016/j.brs.2018.09.010

Hutcheon, B. and Yarom, Y. (2000). Resonance, oscillation and the intrinsic frequency preferences of neurons. *Trends in neurosciences* 23, 216–222

Iacono, M. I., Neufeld, E., Akinnagbe, E., Bower, K., Wolf, J., Vogiatzis Oikonomidis, I., et al. (2015). Mida: a multimodal imaging-based detailed anatomical model of the human head and neck. *PloS one* 10, e0124126

Lee, S., Park, J., Choi, D. S., Lim, S., Kwak, Y., Jang, D. P., et al. (2022). Feasibility of epidural temporal interference stimulation for minimally invasive electrical deep brain stimulation: Simulation and phantom experimental studies. *Journal of Neural Engineering* 19. doi:10.1088/1741-2552/ac8503

Mirzakhalili, E., Barra, B., Capogrosso, M., and Lempka, S. F. (2020). Biophysics of temporal interference stimulation. *Cell Systems* 11, 557–572.e5. doi:10.1016/j.cels.2020.10.004

Missey, F., Rusina, E., Acerbo, E., Botzanowski, B., Trébuchon, A., Bartolomei, F., et al. (2021). Orientation of temporal interference for non-invasive deep brain stimulation in epilepsy. *Frontiers in Neuroscience* 15. doi:10.3389/fnins.2021.633988

Plovie, T., Schoeters, R., Tarnaud, T., Martens, L., Joseph, W., and Tanghe, E. (2022). Influence of temporal interference stimulation parameters on point neuron excitability (Institute of Electrical and Electronics Engineers Inc.), vol. 2022-July, 2365–2368. doi:10.1109/EMBC48229.2022.9871641

Rampersad, S., Roig-Solvas, B., Yarossi, M., Kulkarni, P. P., Santarnecchi, E., Dorval, A. D., et al. (2019). Prospects for transcranial temporal interference stimulation in humans: A computational study. *NeuroImage* 202. doi:10.1016/j.neuroimage.2019.116124

Shampine, L. F. and Reichelt, M. W. (1997). The matlab ode suite. *SIAM journal on scientific computing* 18, 1–22

Song, S., Zhang, J., Tian, Y., Wang, L., and Wei, P. (2021). Temporal interference stimulation regulates eye movements and neural activity in the mice superior colliculus. In *2021 43rd Annual International Conference of the IEEE Engineering in Medicine & Biology Society (EMBC)* (IEEE), 6231–6234

Sorkhabi, M. M., Wendt, K., and Denison, T. (2020). Temporally interfering tms: Focal and dynamic stimulation location (Institute of Electrical and Electronics Engineers Inc.), vol. 2020-July, 3537–3543. doi:10.1109/EMBC44109.2020.9176249

Su, X., Guo, J., Zhou, M., Chen, J., Li, L., Chen, Y., et al. (2021). Computational modeling of spatially selective retinal stimulation with temporally interfering electric fields. *IEEE Transactions on Neural Systems and Rehabilitation Engineering* 29, 418–428. doi:10.1109/TNSRE.2021.3055203

Sunshine, M. D., Cassarà, A. M., Neufeld, E., Grossman, N., Mareci, T. H., Otto, K. J., et al. (2021). Restoration of breathing after opioid overdose and spinal cord injury using temporal interference stimulation. *Communications Biology* 4. doi:10.1038/s42003-020-01604-x

Vassiliadis, P., Beanato, E., Popa, T., Windel, F., Morishita, T., Neufeld, E., et al. (2022). Campus biotech, room h4.3.132.084 chemin des mines 9 , 1202doi:10.1101/2022.11.07.515477

Violante, I. R., Alania, K., Cassarà, A. M., Neufeld, E., Acerbo, E., Carron, R., et al. (2022). Non-invasive temporal interference electrical stimulation of the human hippocampus foundation for research on information technologies in society (it'is) doi:10.1101/2022.09.14.507625

von Conta, J., Kasten, F. H., Ćurčić Blake, B., Aleman, A., Thielscher, A., and Herrmann, C. S. (2021).
Interindividual variability of electric fields during transcranial temporal interference stimulation (ttis).
Scientific Reports 11. doi:10.1038/s41598-021-99749-0
Wang, B., Aberra, A. S., Grill, W. M., and Peterchev, A. V. (2022). November 2022 i responses of
model cortical neurons to temporal interference stimulation and related transcranial alternating current
stimulation modalities doi:10.1101/2022.05.04.490540
Wessel, M. J., Beanato, E., Popa, T., Windel, F., Vassiliadis, P., Menoud, P., et al. (2022). Ltp-like
noninvasive striatal brain stimulation enhances striatal activity and motor skill learning in humans
foundation for research on information technologies in society (it's) doi:10.1101/2022.10.28.514204
Xin, Z., Kuwahata, A., Liu, S., and Sekino, M. (2021). Magnetically induced temporal interference for focal
and deep-brain stimulation. *Frontiers in Human Neuroscience* 15. doi:10.3389/fnhum.2021.693207
Zhu, X., Li, Y., Zheng, L., Shao, B., Liu, X., Li, C., et al. (2019). Multi-point temporal interference
stimulation by using each electrode to carry different frequency currents. *IEEE Access* 7, 168839–168848.
doi:10.1109/ACCESS.2019.2947857

FIGURE CAPTIONS

Figure 1. Schematic illustration of the concept of TI-DBS in the MIDA brain(Iacono et al., 2015). The red and blue electric field oscillate at a different frequency. At the place where they temporally interfere, the pink amplitude modulated signal is created.

Table 1. Parameters for the IF-models

V_{r}	-70 mV
V_{reset}	-70 mV
V_{thresh}	-40 mV
R	$0.5 \cdot 10^6$ kΩ
τ_{m}	5 ms
Δ_{T}	2 mV
V_{T}	-50 mV
τ_{w}	100 ms
a_0	$2 \cdot 10^{-9}$ mS
b_0	$8 \cdot 10^{-6}$ μA

Figure 2. Threshold lines for regular firing with a TI input (solid lines) and a sinusoidal signal (dashed lines) with carrier frequency f_c and a beat frequency of 100 Hz. The thresholds are shown for the leaky integrate-and-fire (LIF), exponential integrate-and-fire with $\Delta_T = 2$ mV (EIF1), exponential integrate-and-fire with $\Delta_T = 15$ mV (EIF2) and adaptive and exponential integrate-and-fire (AdEx) neuron. **A**: overview of all IF models. **B**: detail of the LIF model.

Figure 3. Comparison of the FH- and FH1-model with a beat frequency $f_b = 100$ Hz. **A**: 2D plot of the energy metric for the FH model **B-C**: Difference between the energy metric of the FH1v1 and FH1v2 model with respect to the FH model, respectively. **D-F**: Absolute threshold lines for TI and sinusoidal stimulation to obtain regular firing (RF) and firing at the beat frequency (f_b) in the FH, FH1v1 and FH1v2 models, respectively. **G-I**: Relative threshold lines with respect to the threshold line of regular firing (RF) of the TI-input in the FH, FH1v1 and FH1v2 models, respectively.

Figure 4. Comparison of the HH- and gHH-model with a beat frequency $f_b = 100$ Hz. **A**: 2D plot of the energy metric for the HH model. **B-C**: Difference between the energy metric of the gHH1v1 and gHH1v2 model with respect to the HH model, respectively. **D-F**: Threshold lines for regular firing (RF) and firing at the beat frequency (f_b) of the HH, gHHv1 and gHHv2 models, respectively.

Figure 5. Comparison of the threshold lines for regular firing (RF) and firing at the beat frequency $f_b = 100$ Hz for different k_x-values for the FH model ($f_c = 3$ kHz). **A**: m-gate. **B**: h-gate. **C**: n-gate.

Figure 6. Results for the threshold lines for the FH model with x_∞ as a logistic function with a varying a-parameter and constant b-parameter (left) and a varying b-parameter and constant a-parameter (right) with $f_c = 3$ kHz and $f_b = 100$ Hz. **A-B**: m-gate. **C-D**: h-gate. **E-F**: n-gate.

Figure 7. Illustration of the different responses of an FH-neuron to a TI signal ($f_b = 100$ Hz, $f_c = 3$ kHz and $I_e = 970 \frac{\mu A}{cm^2}$) and a sinusoidal signal ($f = 3$ kHz and $I_e = 970 \frac{\mu A}{cm^2}$). **A**: TI-input. **B**: sinusoidal input.

Figure 8. Illustration of the different responses of an FH-neuron to a TI signal ($f_b = 100$ Hz, $f_c = 3$ kHz and $I_e = 970 \frac{\mu A}{cm^2}$) with different k_h-values. **A**: $k_h = 0.5$. **B**: $k_h = 3$.

Figure 9. **A**: Illustration of the threshold-beat frequency relation for regular firing (solid line) and firing at the beat frequency (dashed line) for the FH-model with $f_c = 3$ kHz. **B-G**: Minimal beat frequency for different values of the a and b parameters, where the steady state value of a single gate (x = m, h or n) is substituted by a logistic function. The optimum was found through curve fitting of a fourth order polynomial on the minimum of the simulation and its three closest neighbouring datapoints on each side.

Table 2. Summary of the existence of a TI zone for the discussed models. EIF includes both the EIF1 and EIF2 model.

	yes	no
LIF	x	
EIF		x
AdEx		x
HH	x	
FH	x	
gHH	x	
FH1	x	

Table 3. Summary of the gate parameter values, for which there is a TI zone in the FH model with a carrier frequency of 3 kHz and a beat frequency of 100 Hz.

	a [1/mV]	b [mV]	k [-]
m	whole range	>27.8	<1.58
h	whole range	<18.7	whole range
n	whole range	whole range	whole range