System identification reveals multiple interacting states in visuomotor adaptation

Priscilla Balestrucci[1,*], Marc Ernst[1]

Ulm University, Ulm, Germany

*Corresponding author: priscilla.balestrucci@uni-ulm.de

Abstract

Many characteristics of sensorimotor adaptation are well predicted by the Kalman filter, a relatively simple learning algorithm for the optimal estimation of dynamic variables given noisy measurements. Yet not all Kalman filter predictions are confirmed empirically, suggesting that the model might not be sufficient to describe the observed behavior. In our study, we propose that sensorimotor adaptation can be modeled with multiple interacting states, each one described as a Kalman filter, to better reflect the architecture plant of the physical system implementing the behavior (i.e., the different motor and sensory components involved in adaptation). To test our hypothesis, we measured motor error in a series of rapid reaching tasks in which we introduced different conditions of feedback uncertainty and systematic perturbations. We then applied system identification procedures to the resulting adaptation response to test which system architecture would best fit the data. We considered three possible architectures: one with a single Kalman filter, with two filters in series, or two filters in parallel. We found that this latter structure consistently provided a significantly better fit than the others. When evaluating the identified system parameters, we found that the learning rates of both states decreased under higher uncertainty, while the weight assigned to the

slower state increased. Moreover, the dual-state parallel system accounted for the

presence of a constant residual bias in the adaptation to a step offset, which has been

repeatedly reported but is in disaccord with the predictions of the single Kalman filter.

We propose that the identified system architecture reflects how the error is assigned to

different components of the physical plant responsible for adaptation: namely, as

uncertainty increases, the controller assigns a larger contribution in error reduction to

the slower state, which is more likely to have been responsible for the measured error.

Introduction

We constantly adjust and recalibrate the motor plan of our actions over subsequent

attempts, based on the difference between desired and perceived outcome. This error

correction process is referred to as sensorimotor adaptation, and it is necessary to

maintain adequate levels of performance despite changes in the environment, such as

those occurring when adjusting to the characteristics of a new tool, and to our own body,

for example because of muscle fatigue or body transformations during development (1–

3). Short-term adaptation allows us to maintain a highly flexible control of generated

movements in different conditions, and it is a strategy used by the nervous system in all

kinds of movements, e.g. arm reaching (4), walking (5), eye saccades (6), or speech

production (7,8).

Typically, experimental paradigms used to investigate properties of sensorimotor

adaptation of arm reaching and pointing movements—which are the focus of the current

study—consist in measuring the response to an applied perturbation. Experimental

perturbations can consist of a change of the visual feedback displacement associated with

the performed movement (9–12), or of the alteration of the motion dynamics obtained

by applying a force field via a robotic effector (13–15). When a perturbation is introduced,

adaptation is usually fairly rapid, but not instantaneous, as error is reduced incrementally

over different trials and not in one single attempt. The fraction of the error corrected from

one trial to the next, i.e. the rate of error reduction, is a measure often used to describe

and model sensorimotor adaptation (16). Several studies showed that adaptation rate is

not constant, instead it depends on many different factors, such as the reliability of the

error signal (10,17), the rate of change of environmental statistics (9,10,18), and prior

experience with a given perturbation (19–22). Other factors do not seem to have an effect

on adaptation rate, in particular movement or perturbation variability (10,23).

Different computational approaches have been applied to describe and predict changes

in the adaptation rate. The mathematical formalization used for modeling dynamic, linear

time-invariant (LTI) systems is widely used in studies investigating the properties of

adaptation from the point of view of motor control (24). In the state-space representation

of LTI systems, the input is the sensory error signal induced by the mapping perturbation,

the output is the motor adaptation signal, and the hidden states correspond to the

estimation of the change that occured to the mapping. While the state-space formalization

is very effective in capturing many characteristics of sensorimotor adaptation (21,25,26),

it is primarily a descriptive approach, which does not contribute to providing answers to

fundamental questions about the characteristics of adaptation (16). In particular, we are

interested in understanding, *why* does adaptation rate change instead of being a fixed

parameter for an individual? Even more fundamentally, why should there be a rate of

adaptation, and error is not completely removed as soon as it is encountered? By

adopting a normative rather than descriptive perspective, Bayesian models provide a

framework which is better suited to explore such aspects of adaptation. Bayesian models

build on the premise that the parameters of adaptation are set and change optimally,

based on the knowledge of the statistics of the environment and the uncertainty

associated with sensorimotor information (27–29). Since adaptation requires tracking

dynamic states and updating the estimation over time given noisy observations, for

comparing human behavior to that of an optimal observer, typically a Kalman filter

algorithm is applied to model empirical data (9,10,30). In several cases, the predictions

of the Kalman filter were confirmed by the experiments. However, not all predictions

were validated when comparing human and optimal observer behavior. For example, the

Kalman filter predicts that when a constant perturbation is introduced, the error

decreases exponentially until it is fully compensated. Instead, several studies showed that

adaptation to a constant perturbation is incomplete (10,31,32). Furthermore, movement

variability and adaptation rate should be correlated according to the algorithm's

prediction, but such a relation has not been found empirically (10,23).

Figure 1: Possible system architectures and relative biological plant. **A)** Single-state system. There is a single stage of adaptation with rate *K.* **B)** Dual-state serial system. Adaptation is the result of two independent states arranged in series, possibly representing the motor system adapting at different joints. **C)** Dual-state parallel system. Two independent states are arranged in parallel, possibly representing different sensory and motor components.

Despite the fundamental differences between descriptive approaches such as state-space

models and normative approaches such as the Kalman filter, their formalizations are

nearly identical (2). Using the state-space representation, the Kalman filter can in fact be

represented as a dynamic system with a single state, fully described by one free

parameter (i.e. the Kalman gain K) which varies according to the statistics of the

environment (Fig. 1A). However, given the complexity of the processes underlying

sensorimotor adaptation, it is possible that such a model with only a single free

parameter is too simple for predicting the behaviors implemented by the physical plant,

i.e. the body, responsible for adaptation. Therefore, it is likely that a more articulated

representation of the components of the system can instead provide predictions that are

better confirmed by empirical data. The idea that multiple free parameters are necessary

to describe the characteristics of sensorimotor adaptation has been proposed and

successfully validated in multiple studies using the state-space model formalization e.g.

(33,34). Smith and colleagues (21) first proposed the existence of at least two interacting

adaptive processes, each one operating at different timescales, which could capture

several complex adaptation phenomena such as savings (i.e. the faster adaptation

occurring when a perturbation is experienced a second time) (35), anterograde

interference (the slower adaptation occurring after adapting to a different perturbation)

(36), rapid unlearning (extinction of the adaptation effect once the perturbation is

removed) (37). Typically, models including multiple interacting states assume that each

state is characterized by different learning and forgetting rates, but no hypotheses are

proposed concerning the origin of such parameters.

In our study, we hypothesize that the biological plant responsible for adaptation can be

modeled with a linear dynamic system composed of multiple interacting states, where

each state is described as a Kalman filter. According to this view, the measured adaptation

response would depend on changes in the statistics of the environment, as well as on the

physical organization of the system itself. In particular, we considered two possible

configurations including two independent states: one with a serial architecture, the other

with a parallel architecture. In principle, adaptation could be accomplished by

implementing either type of system. On the one hand, a system with two (or more) states

arranged in series could stand for the articulated motor system adapting at different

joints serially aligned along the motor plant (e.g. the shoulder and elbow joints of the arm,

Fig. 1B). On the other hand, a system with states operating in parallel would represent

different sensory and motor components of the total plant (Fig. 1C), each adapting at its

own rate, such as the contribution to the error of the visual system on the one side and

the proprioceptive/motor system of the arm on the other. Obviously when introducing

multiple adapting states, a possible interaction between them emerges.

In order to test our hypothesis, we measured adaptation in fast reaching movements

under different conditions of uncertainty of the visual feedback location. Uncertainty was

modulated by applying Gaussian blurs with different standard deviations to the visual

feedback. Next, we applied system identification algorithms to assess which of the system

architectures introduced above provided the best fit of the experimental data. In order to

measure the adaptation response to systematic perturbations of the mapping between

motor reach and endpoint location of the feedback, following the method introduced by

Hudson and Landy (38), we applied sinusoidal perturbations with different frequencies

instead of an impulse-like step-offset perturbation. In their study, they demonstrated the

advantage of using sinusoidal perturbations over the more commonly used step-function:

Using both empirical and simulated data, they showed that the adaptive response

associated with sinusoidal perturbations provide a better signal-to-noise ratio compared to that from step offsets, already with small perturbation amplitudes. As it is possible to use sinusoidal offset functions with small amplitudes, and the change in mapping occurs gradually from one trial to the next, perturbations are less likely to be overtly detected, allowing for less reliance on cognitive strategies to correct errors when participants perform the task. Moreover, while in the case of adaptation to a step function it is necessary to fit an exponential function to the response, we can apply linearized methods for analyzing the response to a sinusoid, thus allowing us to easily use a parametric model to fit the response. In our application of the proposed method, introducing sinusoidal perturbations with multiple frequencies provided an additional advantage: Namely, for each level of feedback uncertainty, we could construct the response of the system in the frequency domain by putting together the parameters extracted from the adaptation signals associated to the different sinusoidal inputs. The response of a system in the frequency domain is mathematically equivalent to that in the time domain (i.e. the impulse response obtained when measuring the adaptation to as step offset) (39). However, by using the former, we could rely on the parameters extracted from multiple experimental runs (one for each sinusoidal frequency) for constructing the overall system response.

Model Architectures and Simulations

In order to model the different system architectures under consideration for adaptation, we consider the case provided in the experimental task, in which in every trial t a systematic perturbation P_t is applied to the endpoint visual feedback (F_t) of the reaching hand movement towards a displayed target (see Fig. 5C):

$$F_t = H_t + P_t \tag{1}$$

155 The error on trial t results from the distance between feedback and target:

$$E_t = F_t - T_t \tag{2}$$

156 To minimize the error in this task, participants should estimate the visuomotor mapping
157 perturbation based on the performance in previous trials, and make a reaching
158 movement accordingly:

$$H_t = T_t - \hat{X}_t \tag{3}$$

159 In such conditions, the optimal estimation is provided by the Kalman filter (9,10):

$$\hat{X}_{t+1} = \hat{X}_t + K(E_t) \tag{4},$$

160 where the Kalman gain K defines the speed of the estimation update from one trial to the
161 next, i.e. the rate of adaptation.

162 Given the identities above (Eq. 1-3), the error can be rewritten as:

$$E_t = P_t - \hat{X}_t \tag{5}$$

163 which for the optimal estimation yields:

$$\hat{X}_{t+1} = (1 - K)\hat{X}_t + KP_t \tag{6}.$$

164 This notation closely resembles the state update of a discrete, LTI state-space system,
165 which is canonically in the form of the difference equation:

$$x(t+1) = Ax(t) + Bu(t) \tag{7}$$

166 where the input signal $u(t)$ is the feedback perturbation P_t, and the state update $x(t)$ is the

167 mapping estimation $\hat{X}_t$.

168 For the second equation of the state-space system:

$$y(t) = Cx(t) + Du(t) \tag{8}$$

169 we consider the output of the system as the endpoint error of the hand reaching

170 movement:

$$Y_t = H_t - T_t \tag{9}$$

171 which yields

$$Y_t = -\hat{X}_t \tag{10}$$

corresponding to the second difference equation of the state-space model where $C = -1$,

$D = 0$.

In the case of a system like the one in Eq. 6, the characteristics of the adaptation response

depend on the free parameter of the model, the gain K. Such a model resembles a low-

pass filter and thus reacts to different input perturbations accordingly: If the input

perturbation P_t consists of a constant offset, the model predicts that the adaptation

response has the form of an exponential decay with asymptote to 0, while the time

constant of the exponential function is given by the Kalman gain K (Fig. 2B). For a

sinusoidal perturbation, the model predicts that the response has the same frequency,

but reduced amplitude and delayed phase with respect to the perturbation. Moreover,

the response depends on the free parameter of the model as well as on the speed of the

perturbation (i.e. its frequency). The relationship between input and output of a system

across frequencies is typically described by the Bode plot of the response in the frequency

domain (Fig. 2C). The Bode plot provides the representation of the relative amplitude

between input and output expressed in dB (Fig. 2C, top panel) and that of their phase shift

in degrees (Fig. 2C, bottom panel).

Since in our study we measure adaptation to sinusoidal offsets and use such responses to

characterize the underlying processes, we will only show simulations of the responses in

the frequency domain in the next sections. We used the Matlab's Control System Toolbox

(40) to define the system and to simulate the relative responses in the frequency domain.

Figure 2: **A)** Single-state system representation. **B)** Response to a step perturbation of a single-state system in the time domain, for varying values of *K*. **C)** Response to sinusoidal perturbations of the same system for varying values of K, in the frequency domain (Bode plot).

Dual-state systems

193   In case of a system with two independent states arranged in **series**, the estimation made

194   by the first state provides the input signal for the second, cascading state (Fig. 3A). The

195   estimation updated by the latter, in turn, provides the adaptation output of the overall

196   system. The model is represented by the following system of difference equations:

$$\hat{X}_{1,t+1} = (1 - K_1)\hat{X}_{1,t} + K_1 P_t$$
$$\hat{X}_{2,t+1} = (1 - K_2)\hat{X}_{2,t} + K_2 \hat{X}_{1,t} \tag{11}$$
$$Y_t = -\hat{X}_{2,t}$$

The free parameters of the model are the two Kalman gains K_1, K_2. While the response of

such a system is qualitatively similar to that of a single-state system, they are clearly

different from each other when considering their frequency responses. In particular, the

response of a dual system with two identical states in series is well distinguishable from

that of a single state with the same gain (Fig. 2C, 3B-top panel). Moreover, it is not possible

to obtain a serial system to a single-state system by setting one of the gains to 0 or 1: In

the former case, the response of the serial system is a null response for all frequencies; in

the latter, the response of a serial system with gains K and 1 differs from that of a single

state with gain K for a shift in the phase of the response. Note also that the response of

the overall system does not depend on the order of each individual state (Fig. 3B, bottom

panel).

Figure 3: **A)** Representation of a dual-state serial system. **B)** Simulations of the system's frequency response, for varying values of the two adaptation rates K_1 and K_2.

210 In a dual system with a **parallel** architecture, each individual state processes part of the

211 input, and the overall output is given by the sum of the estimates performed by each state

212 (Fig. 4A). The system of difference equations describing the model are the following:

$$\hat{X}_{1,t+1} = (1 - K_1)\hat{X}_{1,t} + wK_1 P_t$$
$$\hat{X}_{2,t+1} = (1 - K_2)\hat{X}_{2,t} + (1 - w)K_1 P_t \qquad (12)$$
$$Y_t = -(\hat{X}_{1,t} + \hat{X}_{2,t})$$

In this case, the system has three independent parameters, namely the two state gains K_1

and K_2, and the relative weight assigned to each state w (Fig. 4B).

Unlike for a serial system, assigning the same weight to both states in a parallel system

yields the same response of the corresponding single-state system, regardless of which

weight is assigned to either state. Similarly, if the weighting parameter has the value of w

= 1 or w = 0, the resulting response is that of a single-state system with gain K_1 or K_2,

respectively. Note that the two states of the system are symmetrical: therefore, the

response of a system with parameters K_1, K_2, w will be identical to that of a system with

parameters K_2, K_1, 1–w, i.e. where the gain of each branch is inverted and the weight

assigned to the first state is 1–the original weight (Fig. 4B).

Figure 4: **A)** Representation of a dual-state parallel system. **B)** Simulations of the system's frequency response, for varying values of the free parameters—namely, adaptation rates K_1 and K_2, and weight w.

Materials and methods

Experimental procedure

In order to obtain the empirical data to be used in the system identification procedure, we measured participants' motor error in a series of rapid reaching tasks, in which they were exposed to different conditions of measurement uncertainty coupled with sinusoidal perturbations of varying frequency. Prior to that, we conducted an experiment using an alternative forced choice localization task to determine the uncertainty associated with various levels of visual blur. The results of the localization task were used to select the blur of the visual feedback in the different uncertainty conditions of the adaptation task.

Participants: Seven participants (4 females, 3 males, age 26.3 ± 6 years, 6/1 right/left-handed) took part in the localization task. The sample size was chosen based on a priori power analysis conducted with the G*Power application version 3.1.9.6 (41), as it would achieve 80% power for detecting a medium effect at a significance level of $\alpha = 0.05$. Ten participants (5 females, 5 males, age 22.1 ± 2 years, all right-handed) volunteered in the adaptation task. They were all informed of the general purpose of the experiment but were naïve with respect to the specific research questions, and received 7,50 €/h compensation or course credit for their participation. They all had normal or corrected-to-normal vision and no motor impairment. The study was approved by the ethics committee of the University of Ulm and conducted in accordance with the Declaration of Helsinki.

Setup: Visual stimuli were presented on a large LCD display (Sony 65X8505B, dimensions 144 x 81 cm, 1920 x 1080 pixels), placed at a distance of 85 cm from the sitting participant, in an otherwise dark room. The desk between screen and participant was

249 customized so that on top of it was a scaffold holding a chin rest, and a black rigid cloth

250 that prevented participants from seeing their own hand (Fig. 5A). Stimuli were

251 programmed in Matlab R2017a and Psychtoolbox (42,43).

Localization task

Visual stimuli consisted of a vertical white line on a black background, as tall as the

screen, and blurred along the horizontal direction with a Gaussian filter with varying

standard deviations, starting from 0° visual angle (no blur), 8°, 12°, 16°, to 20°, resulting

in 5 blur levels. The non-blurred stimulus consisted of a white vertical line of 0.5° width.

Two identical stimuli were presented in rapid temporal succession (Fig. 5B; presentation

time for each stimulus: 500 ms; inter-stimulus-interval: 500 ms). The first stimulus

appeared at a random horizontal location on the screen within an area of width 8°

centered in the middle of the screen. The second stimulus appeared on one of eight fixed

distances to the left or right with respect to the first. The distance between stimuli varied

linearly in a range of ±4.6° for all the blur levels except 0° where it was ±1.2°. Participants

had to respond on which side they perceived the second stimulus to have appeared with

respect to the first by pressing the corresponding arrows on a keyboard. Each of the eight

distances of the comparison stimulus was repeated 20 times, resulting in a total of 160

forced-choice trials for each blur level condition. All trials of a given blur level were

presented en bloc with a randomized order. To avoid fatigue, a non-mandatory break

after every 20 trials was signaled by the appearance of a gray screen between trials.

Data analysis: Participants' responses in the localization task were analyzed with a

Generalized Linear Mixed Model (GLMM) to estimate the just noticeable difference (JND)

associated with each blur condition (44). The model was fitted with R version 4.0.2 using

the `lme4` package (45). We then calculated JND estimates and their bootstrap-based

confidence intervals using the `MixedPsy` package Moscatelli et al., 2012; (46).

Figure 5: **A)** Experimental setup. **B)** Trial procedure for the localization task. **C)** Trial procedure for the adaptation task. **D)** Representation of perturbation functions (red lines) and relative adaptation responses (blue lines). Each perturbation is characterized by its frequency, i.e. the number of period repetition per run of 256 trials. The adaptation response associated with each perturbation has the same frequency, but a difference in amplitude and a phase delay. The responses associated with all tested frequencies define the frequency response, or response in the frequency domain, of the system under investigation (black line). **E)** Definition of amplitude of and phase lag of the response (blue line) with respect to the

perturbation (red line).

Adaptation task

In each trial, a red target line (width 0.5°) appeared on the screen at a random horizontal

location within an 8° wide area centered in the middle of the screen. Participants were

instructed to point on a graphics tablet (WACOM Intuos3 A3; active area 48.8 cm x 30.5

cm). They had to point to the location they perceived as corresponding to that of the

target on the screen as accurately as possible (Fig. 5C). That is, their task was to minimize

the distance between target and feedback position (i.e. the feedback error E_t, Eq. 5). The

pointing movement was done with a stylus held in their preferred hand. The feedback

stimulus consisted of a white vertical line blurred along the horizontal dimension,

identical to the one described for the localization task. Only a subset of the blurs tested in

the localization experiment was used in the adaptation experiment, namely: 0° (no blur),

12° (intermediate blur) and 20° (large blur).

The experiment included separate runs consisting of 256 trials each. The mapping

between tablet and screen coordinate changed on every trial within a run along the

horizontal direction, according to a sinusoidal perturbation function in the form:

$$P_t = -A_0 \sin\left[\frac{2\pi f}{T}(t-1)\right] \tag{13}$$

where A_0 was the perturbation amplitude set to 3°, T was the total number of trials within

a run (T = 256), and f was the frequency of the sinusoidal perturbation, corresponding to

the number of times that the full period of the sinusoidal function was repeated within a

run. Following the method proposed by Hudson and Landy (38), the negative sign in Eq.

(13) was chosen out of convenience for subsequent analysis, so that the adaptation

response would follow a positive sinusoidal function (Fig. 5E). Also, a lag of 1 trial was

introduced so that the first trial of each run would have no perturbation. We presented 7

sinusoidal frequencies, chosen as integer powers of 2 and ranging between $2^0 = 1$ and 2^6

$= 64$ cycles/run (Fig. 5D). We tested every sinusoidal frequency with each of the three

blur levels (i.e. 3 blurs x 7 frequencies), resulting in 21 runs of 256 trials. All 7 frequencies

of a given blur level were tested en bloc in randomized order, with each blur level tested

on a different day. At the beginning of each testing day participants performed 100

training trials of the reaching task without any perturbation, but with a feedback blur

consistent with that of the rest of the day. The order in which the blur levels were tested

across days was counterbalanced between participants.

Every reaching movement began in a small area at the center/bottom of the tablet,

delimited by a plastic half-circle ridge of diameter 3.5 cm (Fig. 5C). In order to trigger the

presentation of a new target, participants pressed a button on the grip of the stylus while

holding its tip inside the ridged half-circle (starting area). They were allowed to keep

their non-preferred hand on the ridge in order to find the starting area more easily. While

participants kept the stylus within the starting area, the target was visible on screen for

a maximum of 500 ms. Once the stylus left the starting position, participants needed to

make a fast reaching movement towards the upper half of the tablet. The endpoint

position where the stylus first touched the tablet counted as the response; however, it did

not count as valid unless the stylus moved at least 9 cm away from the starting position

along the sagittal plane. If the position of the stylus passed this limit, a feedback stimulus

appeared and remained on the screen for 500 ms. Otherwise, no feedback appeared and

the trial had to be repeated.

The tablet's coordinates mapped univocally to the coordinates of the screen, with the

tablet's boundaries corresponding to those of the screen. Although the devices did not

share the same dimensions, no participants demonstrated difficulties in understanding

the applied scaling.

Data analysis: Since no perturbation occurred along the vertical axis of the screen, we did

not analyze data relative to the vertical endpoint coordinate of the reaching movement.

To evaluate the adaptation signal in response to a sinusoidal perturbation, we considered

the motor error Y_t, defined as the difference between the target coordinate and the

horizontal coordinate of the reaching endpoint position in the unperturbed mapping. We

assumed that the adaptation response to a sinusoidal perturbation with frequency f

would have the same frequency but a smaller amplitude and a delay, i.e. a phase

difference with respect to the perturbation (Fig. 5D-E). The adaptation response was

modeled accordingly (38):

$$Y_t = A \sin\left[\frac{2\pi f}{T}(t-1) + \phi\right]$$ (14),

331   where A is the amplitude ($0 \leq A \leq A_0$) and φ is the phase of the adaptation response ($0 \leq$

332    $\varphi < 2\pi$).

333   Eq. (14) can be rewritten in analogous terms by the properties of trigonometric functions

334   as follows:

$$A \sin(\gamma_t + \phi) = A \cos(\phi) \sin(\gamma_t) + A \sin(\phi) \cos(\gamma_t)$$ (15)

335   with $\gamma_t = \dfrac{2\pi f}{T}(t-1)$.

336   The identity in Eq. (15) allows to quantify the amplitude and phase of the response by

337   fitting the adaptation response with a linear mixed model (LMM) in the following form,

338   for each combination of frequency and visual blur:

$$Y_t = \beta_0 + \beta_1 \sin(\gamma_t) + \beta_2 \cos(\gamma_t) + Zu$$

(16).

339   Where β_0, β_1, β_2 represent the fixed-effect parameters of the model, and Zu accounts for

340   the random effects. Of the fixed-effect parameters, β_0 describes the constant response

341   bias associated with the response, and is expected to vary randomly for each participant

342   (38). In line with Eq. (15), parameters β_1 and β_2 can be rewritten as:

$$\beta_1 = A\cos(\phi)$$

$$\beta_2 = A\sin(\phi)$$

(17)

343   In this way, we can extract amplitude and phase parameters (A and φ in Eq. 14) given the

344   linear predictors β_1 and β_2, by arranging and combining them in light of basic

345   trigonometric identities. For the amplitude, we have:

$$\beta_1^2 + \beta_2^2 = A^2[\cos^2(\phi) + \sin^2(\phi)]$$

(18)

346   which yields

$$A = \sqrt{\beta_1^2 + \beta_2^2}$$

(18)

347   given the Pythagorean identity: $\cos^2(\phi) + \sin^2(\phi) = 1$.

348   For the phase shift, by considering the definition of the angle's tangent: $\tan(\phi) = \dfrac{\sin(\phi)}{\cos(\phi)}$

349   , we obtain:

$$\phi = \tan^{-1}\left(\frac{\beta_2}{\beta_1}\right)$$

(20).

The intercept parameter β_0 represents a constant bias in the response. Since such
constant bias, which is small and variable across participants, does not affect the
frequency response or the amplitude of adaptation, it was removed from the data and
excluded from further analysis, without affecting the other model parameters.

LMMs for each blur and frequency (21 models in total) were fitted in R with the `lme4`
package. Amplitude and phase parameters for individual participants were extracted
from the combination of fixed and random effects of each coefficient of the LMMs. We
calculated Bootstrap-based confidence intervals for estimating parameters at the
population level using the `MixedPsy` package. Finally, the amplitude of the response
(both at the individual and sample level) was transformed in magnitude, i.e. it was
normalized with respect to the amplitude of the input perturbation and expressed in
decibel (dB): $A_{dB} = 20\log\left(\frac{A}{A_0}\right)$.

Magnitude and phase fully describe the adaptation response to a given sinusoidal
perturbation in the frequency domain (39). Taken together, these parameters provided
the frequency response of adaptation in the frequency range of the presented
perturbations for each level of feedback uncertainty (Fig. 5D).

System Identification

Given the frequency responses extracted from the adaptation signals, we used the state-
space parametrizations for the model architectures described in the previous section to
estimate the corresponding best fitting models. The state-space model estimation was
performed in Matlab R2017a using functions from the System Identification Toolbox

(40). In particular, we used the function `greyest`, which performs a grey-box estimation

of a LTI system given the frequency response of the empirical data and the specific

relations between system parameters.

For each participant and condition of measurement uncertainty, we estimated the

following possible models from the associated frequency response:

● a one-state system (Eq. 6) characterized by the single adaptation rate K;

● a dual-state system with serial architecture (Eq. 11), described by two adaptation

rates K_1 and K_2;

● a dual-state system with parallel architecture (Eq. 12), described by the

adaptation rates K_1 and K_2, and the relative weight w assigned to each state.

Without loss of generality, in the dual-state configurations, we always assigned K_1 to the

faster, and K_2 to the slower rate. Accordingly, for the system with a parallel architecture,

the weighting factor w refers to the weight assigned to the state with faster rate and *(1-*

w) to the state with the slower rate.

In the system identification function, we constrained every parameter to be limited

between 10^{-15} and 1. The small bias added to the lower threshold was included to avoid

undefined results in subsequent analyses in case parameters were estimated at exactly 0.

In order to evaluate which of the three considered systems was best at fitting the

adaptation response, we used the Bayesian information criterion (BIC) to compare the

models. For each frequency response we selected the model with the lowest BIC score

and evaluated the goodness of fit relative to the other models in terms of the difference

between BIC values (ΔBIC). Models with ΔBIC between 0 and 2 were not considered

different from each other; models with ΔBIC between 3 and 10 were classified as little

though still significantly different; models with ΔBIC greater than 10 were considered

strongly different from each other (47,48).

Effect of uncertainty on identified parameters

Once we identified the parameters of the three system architectures, we evaluated how

the JND associated with the visual blur of the feedback (i.e. their measurement

uncertainty) affected the parameter values. Since the system with two states in parallel

provided the best fit of the three, we selected this model for further considerations. In

general, we expected that the system, regardless of its structure, would adapt slower as

an effect of the increase in feedback uncertainty. In case of a dual-state system with a

parallel architecture, this could be achieved in two ways: (1) by decreasing one—or

both—adaptation rates, and/or (2) by assigning more weight to the state with the lower

adaptation rate. We fitted LMMs to adaptation rates and relative weight in order to test

our hypotheses.

Adaptation rates: We expected that adaptation rates, if they changed, would become

smaller as the uncertainty associated with visual feedback increased. We modeled this

relationship with an exponential decay in the form:

$$K = a \cdot e^{\lambda \cdot JND} \tag{21}.$$

411   We applied a logarithmic transformation to both elements in Eq. 21 in order to fit a LMM

412   as follows:

$$\log(K) = \delta_0 + \delta_1 JND + Zu \tag{22}$$

where $\delta_0 = \log(a)$ and $\delta_1 = \lambda$.

The model in Eq. 22 was applied to both rates, K_1 and K_2 of the systems. Significance of

the fixed-effect parameters was set at 0.05 and evaluated with likelihood ratio (LR) tests.

Relative weight: We expected the weight assigned to the faster state w to decrease as a

function of feedback JND. As a first approximation, we evaluated whether such decrease

could be described as a linear function with a negative slope in the form:

$$w = \zeta_0 + \zeta_1 JND + Zu \qquad (23)$$

419   Since the weight is bound to change between 0 and 1, the model in Eq. (13) is not

420   appropriate to fully describe the relationship between weight and feedback JND, hence it

421   must be considered as a local approximation for the considered JND interval.

Results

Localization task

In the localization task, the JND increased monotonically and non-linearly as a function

of the standard deviation of the gaussian blur applied in the different conditions (Fig. 6).

In other words, an increase in blur of the visual feedback was associated with an increase

of measurement uncertainty. To provide visual feedback in the adaptation task, we chose

the three values of visual blur (0, 12, & 20°) for which the confidence intervals of the JND

estimates were not overlapping (Table S1 in Supplementary Materials).

Figure 6: JND associated with all the blurred stimuli presented in the localization task.

Adaptation task

The model in Eq. (16) was applied to the motor response Y_t in each condition of perturbation frequency and measurement uncertainty. Fig. 7 shows the sinusoidal perturbation together with averaged response across participants. As expected, the adaptation response generally followed a sinusoidal pattern with the same frequency, but a reduction in amplitude and a phase delay with respect to the imposed perturbation. The summary of magnitude and phase values of the adaptation response as a function of frequency is shown in Fig. 8A in a Bode plot.

A first qualitative observation from visual inspection showed that the amplitude of the adaptation response was smaller for higher frequencies and increasing measurement uncertainty, while the phase lag increased for higher frequencies but tended to be similar across different conditions of uncertainty.

Figure 7: Sinusoidal fit and adaptation response averaged across participants (n = 10). The offset perturbation for each frequency condition is shown in red. Amplitude and phase of the sinusoidal curves in gray are calculated from to the fixed-effect parameters of the model in Eq. (16) through the identities in Eq. (17). In this representation, perturbations are inverted to allow the reader to visually evaluate the difference between input and response, by comparing the peaks of the two signals.

System identification

The parameters resulting from the estimation of the three system architectures (i.e. a single state, two states in series, and two states in parallel) are summarized in Table 1.

As is apparent from Fig. 8A, the system with a parallel architecture was the most effective in capturing the characteristics of the frequency response for all conditions of measurement uncertainty. Accordingly, it had the lowest BIC score 27 out of 30 times (Fig. 8B). In four cases, the single-state system was indistinguishable from the system in parallel or provided a better fit, with a small but significant difference (ΔBIC between 3 and 10). The system with a serial architecture was the one consistently providing the worst fit, and accordingly, the one with the largest BIC scores in all cases.

Table 1: Parameters of the best fitting systems (Median and IQR) for each condition of visual blur σ.

| σ (deg) | One-state | Serial | | Parallel | | |
	K	K_1	K_2	K_1	K_2	w
0	0.145 (0.066)	1.00 (0.605)	0.101 (0.200)	0.313 (0.142)	0.015 (0.014)	0.616 (0.214)
12	0.005 (0.007)	1.00 (0.00)	0.00 (0.00)	0.226 (0.094)	0.001 (0.002)	0.234 (0.141)
20	0.003 (0.005)	1.00 (0.00)	0.00 (0.00)	0.073 (0.105)	0.00 (0.001)	0.233 (0.285)

Figure 8: **A)** Bode plot: Comparison between frequency response for the population sample (estimate and bootstrap-based confidence intervals) and response associated with median identified parameters for the three system architectures under consideration. **B)** Model comparison according to the BIC criterion for individual fittings.

Effect of uncertainty on identified parameters

After having identified the free parameters for each of the three considered system architectures, and having established that the parallel system was the best amongst the candidate models, we focused on the relationship between measurement uncertainty (i.e. the feedback JND) and the identified parameters only for this parallel model.

Adaptation rates: The LMM fitted to the fast learning rate K_1 (Eq. (22); Fig. 9A, black symbols) revealed an intercept of 0.334 (95% CI: [0.259, 0.43]) and a decay constant $\lambda =$ −0.297 (95% CI: [−0.496, −0.096]) indicating that the fast adaptation rate became slower with increasing blur. The fixed effect accounting for the decay of the fast adaptation rate as a function of JND was significant ($\chi_1 = 6.922$, p = 0.009). For K_2 (Fig. 9A, gray symbols), the intercept was very close to 0 ($\sim 10^{-4}$, 95% CI: [10^{-7}, 1.361]). Still the decay constant, albeit small, was significantly different from 0 ($\lambda = −4.66$, 95% CI: [−7.901, −1.284]; $\chi_1 =$ 7.334, p = 0.007).

Weighting factor: For parameter w (Fig. 9B) the model in Eq. (23) had a negative slope ($\zeta_1 = -0.099$, 95% CI: [−0.135, −0.062]. $\chi_1 = 16.709$, p < 0.001) indicating that the weight assigned to the faster state decreases with increasing uncertainty (i.e. the slower state was weighted more as feedback JND increased).

Figure 9: **A)** Values and fitted models of learning rate parameters K_1 and K_2 for the system with two states in parallel, as a function of feedback JND. **B)** Weight (values and fitted model) assigned to the fast learning state (K_1) in the parallel system as a function of feedback JND.

Discussion

We investigated visuomotor adaptation of pointing movements under different conditions of sinusoidal perturbation and feedback uncertainty, and applied system identification techniques to determine which system architecture provided the best fit to the empirical data.

Our results confirm and extend those of previous studies: Adaptation responses were successfully fitted by sinusoidal functions having the same frequency, but different

amplitude and phase with respect to the perturbation (38). This indicates that

participants were able to adapt to sinusoidal offsets at various speeds. In particular, the

response had higher amplitude and smaller delay at lower frequencies and tended to

degrade for higher frequencies, in accordance with the prediction that adaptation to

systematic perturbations resembles the response of a passive low-pass filter. Moreover,

adaptation performance was affected by the modulation of the feedback's visual blur,

with higher uncertainty (i.e. larger blur) associated with less complete, slower adaptation

(10).

When applying system identification procedures to the adaptation response expressed in

the frequency domain, we found that a dual system with a parallel architecture provided

the best fit to our data for all levels of feedback uncertainty. The parallel architecture

provided a better fit than the dual-state system with a serial architecture 100% of the

time. 90% of the time the parallel architecture was better than a single-state system

taking also model complexity into account. In the remaining 10% of cases in which the

single-state system outperformed the parallel system, the best fitting parameters were

such that the two systems were hardly distinguishable: namely, the assigned weight in

the parallel system architecture was close to either 0 or 1. Such result indicates that in

the majority of cases the system identification algorithm converged to a solution well

distinguishable from that of a single-state system: Namely, the learning rate of the two

independent states differed from each other, and both states were assigned a non-zero

contribution.

As an effect of increasing feedback uncertainty, the values of all three identified

parameters (i.e. the two adaptation rates K_1, K_2, and the weight assigned to the faster state

w) decreased significantly, even though the adaptation rate of the slower state K_2 was

close to zero in all uncertainty conditions (Table 1, Fig. 10). Nevertheless, not only was

the weight assigned to its contribution (i.e. *1–w*) significantly different from zero in all

conditions, but it also increased for larger feedback blurs.

To better understand the implications of this aspect of the identified model, let us

consider the simulations of the response to a step offset associated with both the single-

state and the parallel system (Fig. 10). For a single-state system (Fig. 10, green lines), the

error decreases according to an exponential decay function, whose time constant is

defined by the value of the free parameter K. Since the identified values of K under

medium and high uncertainty tend to zero (Table 1, Fig. 1S), the rate of decay of the error

is very slow in these two conditions, and can be even approximated by a linear decrease

in the displayed interval of 120 trials (Fig. 10, middle and right panel). Regardless, at the

end of the exponential decay, error is fully eliminated and performance returns to

baseline levels in all cases (given enough trials), as is predicted by the Kalman filter

model. The response of a dual-state parallel system (Fig. 10, purple lines) differs

qualitatively from that of a single Kalman filter. For the condition under lower

uncertainty (Fig. 10, left panel), the error does tend to revert to baseline, although after a

large number of trials, and with a decay profile dependent not only on the faster rate, but

also on the slower rate as well as their relative weight. Yet, since the slow adaptation rate

K_2 is several times smaller than the fast adaptation rate K_1 (Table 1), the latter dominates

for the larger part of the adaptation response in the considered interval. In conditions of

medium and high uncertainty, the value of the slow gain K_2 is even smaller, to the point

that it can be approximated to zero without a significant decrement in the fitting accuracy.

As a result, the rate of the error's exponential decay is defined by the value of the fast gain

K_1, while the relative weight w determines the asymptote of the decay. Notably, this

prediction of the parallel dual-system is highly consistent with the empirical results

obtained by Burge and colleagues (10). In their study, results showed the presence of an

incomplete compensation in the adaptation response, i.e. an asymptote of the exponential

error decay larger than zero, which increased in conditions of higher uncertainty. Such

residual error bias was nevertheless excluded from the proposed model, because it did

not appear to affect the estimate of the adaptation rate (10,24). The presence of a

constant residual error has been described in several studies on visuomotor adaptation

e.g. (10,31,32,49–51), in full disaccord with the predictions of the Kalman filter model.

Instead, state-space models can account for incomplete offset compensation, by

introducing a forgetting factor which describes the tendency for the system to return to

a baseline, unperturbed state on every trial (32). In this framework, incomplete

adaptation is interpreted as the effect of the balancing between multiple retention and

learning processes (described by parameter A and B in the state estimation update

equation, respectively; cf. Eq. 7) operating at different rates (31). In their study, van der

Kooij and colleagues (31) proposed that this phenomenon is not a fallibility of the

adaptation system, instead it is a mechanism by which the system can react in a

conservative fashion to possibly transient changes in the environment (e.g. unstable

external perturbations or fatigue) while being able to adjust effectively to more

permanent changes, such as body modifications following development. Nevertheless, it

is unclear from modeling studies within the state-space framework how such a

combination of learning and retention factors are actually implemented in the physical

plant of the system responsible for adaptation. Our results suggest that incomplete

adaptation is the result of two concurrent mechanisms: On the one hand, the states of the

system contributing to adaptation in parallel respond to the perturbation with different

rates, which are sensitive to the change in the environmental statistics and therefore

decrease their learning rate in presence of higher feedback uncertainty, thus slowing

down the overall adaptation; On the other hand, the contribution to adaptation assigned

to either state also changes, so that with increasing uncertainty, the response of slower

state determines the larger part of the system's response. As the learning rate of the slow,

dominating state tends to zero, this translates into little or no adaptation once the

contribution of the faster state is extinguished, and therefore to a residual error bias. It is

likely that the weight assigned to each state of the system, just like the learning rates

assigned to the states themselves, is optimally tuned to the statistics of the environment.

However, further research is needed to investigate the statistical determinants of

contribution assignment in adaptation.

By showing evidence supporting the hypothesis that multiple estimators act like optimal

observers, each one contributing to the adaptation response by processing the input

information in parallel, we can provide a better insight on the mechanisms of

sensorimotor adaptation, as well as the way they are physically implemented. On every

trial, a motor plan is actuated based on the mapping estimated from error in previous

trials, and a new error is perceived in the form of a visual displacement with respect to

the intended target. Given this error signal, the controller must establish which one of the

systems involved is more likely to have caused the perturbation. On the one hand, the

error can be attributed to an incorrect action plan performed by the motor system; on the

other hand, the cause of error can be imputed to a misperception of the input signal by

the visual system. Following error assignment, the controller must establish which part

of the system is responsible for correcting the perturbation error in subsequent trials, in

order to update the state estimation with one more appropriate for the current

environmental conditions. In scenarios of error reduction tasks under ambiguous,

redundant conditions, the controller typically assigns error reduction to the component

that is considered as more likely to have caused the error (52). In their study, White and

Diedrichsen (52) showed that, in bimanual motor tasks, right-handed participants

corrected the perceived error induced by a perturbation more with their left hand, even

if the right hand was generally able to correct for error faster in non-redundant tasks. In

analogy with this phenomenon, in visuomotor adaptation tasks like the one in our study,

the decision regarding which estimator is more likely to have caused the error should

result in the appropriate contribution to error reduction, i.e. the selection of weight

attributed to the different states of the system. Our results show that, under conditions

of higher uncertainty, the controller assigns the task of error reduction to the state known

to be slower in learning. This finding is in line with the idea that error correction is

performed by the state that is more likely to have caused the error in the first place.

It is likely that reducing the entire plant of sensorimotor adaptation to two distinct

systems is an oversimplification (21,33). By extending the model proposed here, we can

test increasingly complex implementations of the adaptaing system that takes into

account the constraints imposed by the physical plant of the sensorimotor system. For

example, we can test a more articulated implementation of the system by adding other

states to the parallel system, either in series or in parallel. Such configurations would

account for the contribution of different sensory and motor components, together with

the internal complexity of each individual component. Since such an approach would

result in a rapid increase of the free parameters of the model, with the risk of incurring

in model overfitting with our current dataset, we limited our investigation to systems

including only two independent states.

In conclusion, our results show that the adaptation response to visuomotor perturbations

is well approximated by a linear time-invariant system with two states in parallel. Unlike

the more commonly used model with one single Kalman filter, such an architecture

captures an often described characteristic of adaptation, namely incomplete error

compensation in response to a constant offset, which results in a nearly constant residual

bias. Under conditions of increasing feedback uncertainty, the learning rate of both states

slows down, while the weight assigned to the slower state increases, suggesting that the

controller assigns a larger contribution in error reduction to the system which is more

likely to have caused the error. Such an explanation is consistent with the scenario in

which the motor system adapts quickly, while the visual system adapts slowly.

Figure 10: Simulations of the impulse response to a constant perturbation under different conditions of feedback uncertainty. The simulations are relative to the systems with one state (green lines) and two states in parallel (magenta lines) identified from the frequency responses obtained in the sinusoidal adaptation experiment.

Acknowledgments

621 We thank Lynn Matits for assistance in data collection, and Chris Geekie for suggestions

622 on language and style of the manuscript. Funded by the Deutsche

623   Forschungsgemeinschaft (DFG, German Research Foundation) – Projektnummer

624   251654672 – TRR 161.

References

626
1.   Körding KP, Tenenbaum JB, Shadmehr R. The dynamics of memory as a
consequence of optimal adaptation to a changing body. Nat Neurosci.
2007;10(6):779–86.
2.   Krakauer JW, Hadjiosif AM, Xu J, Wong AL, Haith AM. Motor learning. Compr
Physiol. 2019;9(2):613–63.
3.   Shadmehr R, Smith MA, Krakauer JW. Error Correction, Sensory Prediction, and
Adaptation in Motor Control. Annu Rev Neurosci. 2010 Jun;33(1):89–108.
4.   Krakauer JW, Mazzoni P. Human sensorimotor learning: adaptation, skill, and
beyond. Curr Opin Neurobiol. 2011 Aug;21(4):636–44.
5.   Torres-Oviedo G, Vasudevan E, Malone L, Bastian AJ. Locomotor adaptation. In:
Progress in Brain Research [Internet]. Elsevier; 2011 [cited 2022 Feb 15]. p. 65–74.
Available from:
https://linkinghub.elsevier.com/retrieve/pii/B9780444537522000138
6.   Pélisson D, Alahyane N, Panouillères M, Tilikete C. Sensorimotor adaptation of
saccadic eye movements. Neurosci Biobehav Rev. 2010 Jul;34(8):1103–20.
7.   Houde JF, Jordan MI. Sensorimotor Adaptation in Speech Production. Science.
1998;279(5354):1213–6.
8.   Keough D, Hawco C, Jones JA. Auditory-motor adaptation to frequency-altered
auditory feedback occurs when participants ignore feedback. BMC Neurosci.
2013;14.
9.   Baddeley RJ, Ingram H a, Miall RC. System identification applied to a visuomotor
task: near-optimal human performance in a noisy changing task. J Neurosci Off J
Soc Neurosci. 2003 Apr;23(7):3066–75.
10.   Burge J, Ernst MO, Banks MS. The statistical determinants of adaptation rate in
human reaching. J Vis. 2008 Apr 23;8(4):20.
11.   Krakauer JW. Motor Learning and Consolidation: The Case of Visuomotor Rotation.
In: Adv Exp Med Biol [Internet]. 2009. p. 405–21. Available from:
http://www.springerlink.com/index/10.1007/978-0-387-77064-2
http://link.springer.com/10.1007/978-0-387-77064-2{_}21
12.   van Beers RJ. How Does Our Motor System Determine Its Learning Rate? PLoS ONE.
2012;7(11).
13.   Krakauer JW, Ghilardi M felice, Ghez C. Independent learning of internal models for
kinematic and dynamic control of reaching. Nat Neurosci. 1999;2(11).
14.   Lackner JR, DiZio P. Motor control and learning in altered dynamic environments.
Curr Opin Neurobiol. 2005;15(6):653–9.
15.   Shadmehr R, Mussa-Ivaldi F a. Adaptive representation of dynamics during
learning of a motor task. J Neurosci Off J Soc Neurosci. 1994 May;14(5 Pt 2):3208–
24.
16.   Haith AM, Krakauer JW. Motor learning: The great rate debate. Curr Biol.
2014;24(10):R386–8.

17.   Wei K, Körding KP. Uncertainty of feedback and state estimation determines the
668   speed of motor adaptation. Front Comput Neurosci. 2010;4(May):1–9.
669   18.   Gonzalez Castro LN, Hadjiosif AM, Hemphill MA, Smith MA. Environmental
670   consistency determines the rate of motor adaptation. Curr Biol.
671   2014;24(10):1050–61.
672   19.   Huang VS, Haith A, Mazzoni P, Krakauer JW. Rethinking Motor Learning and
673   Savings in Adaptation Paradigms: Model-Free Memory for Successful Actions
674   Combines with Internal Models. Neuron. 2011 May;70(4):787–801.
675   20.   Martin TA, Keating JG, Goodkin HP, Bastian AJ, Thach WT. Throwing while looking
676   through prisms I. Focal olivocerebellar lesions impair adaptation. Brain.
677   1996;119(4):1183–98.
678   21.   Smith MA, Ghazizadeh A, Shadmehr R. Interacting Adaptive Processes with
679   Different Timescales Underlie Short-Term Motor Learning. PLoS Biol.
680   2006;4(6):e179.
681   22.   van Dam LCJ, Hawellek DJ, Ernst MO. Switching between visuomotor mappings:
682   Learning absolute mappings or relative shifts. J Vis. 2013 Jan;13(4):1–12.
683   23.   He K, Liang Y, Abdollahi F, Fisher Bittmann M, Kording K, Wei K. The Statistical
684   Determinants of the Speed of Motor Learning. PLoS Comput Biol. 2016;12(9):1–20.
685   24.   Cheng S, Sabes PN. Modeling sensorimotor learning with linear dynamical systems.
686   Neural Comput. 2006;18(4):760–93.
687   25.   Raibert MH. Motor control and learning by the state space model [PhD Thesis].
688   Massachusetts Institute of Technology; 1977.
689   26.   Thoroughman KA, Shadmehr R. Learning of action through adaptive combination
690   of motor primitives. Nature. 2000;407(6805):742–7.
691   27.   Ernst MO, Banks MS. Humans integrate visual and haptic information in a
692   statistically optimal fashion. Nature. 2002 Jan;415(6870):429–33.
693   28.   Wolpert DM, Ghahramani Z, Jordan MI. An internal model for sensorimotor
694   integration. Science. 1995;269(5232):1880–2.
695   29.   Yuille AL, Bülthoff HH. Bayesian decision theory and psychophysics. 1993;
696   30.   Vilares I, Kording K. Bayesian models: The structure of the world, uncertainty,
697   behavior, and the brain. Ann N Y Acad Sci. 2011;1224(1):22–39.
698   31.   Van Der Kooij K, Brenner E, Van Beers RJ, Smeets JBJ. Visuomotor adaptation: How
699   forgetting keeps us conservative. PLoS ONE. 2015;10(2):1–13.
700   32.   Vaswani PA, Shmuelof L, Haith AM, Delnicki RJ, Huang VS, Mazzoni P, et al.
701   Persistent residual errors in motor adaptation tasks: Reversion to baseline and
702   exploratory escape. J Neurosci. 2015;35(17):6969–77.
703   33.   Huberdeau DM, Krakauer JW, Haith AM. Dual-process decomposition in human
704   sensorimotor adaptation. Curr Opin Neurobiol. 2015;33:71–7.
705   34.   Inoue M, Uchimura M, Karibe A, O'Shea J, Rossetti Y, Kitazawa S. Three timescales
706   in prism adaptation. J Neurophysiol. 2015;113(1):328–38.
707   35.   Coltman SK, Cashaback JGA, Gribble PL. Both fast and slow learning processes
708   contribute to savings following sensorimotor adaptation. J Neurophysiol.
709   2019;121(4):1575–83.
710   36.   Sing GC, Smith MA. Reduction in learning rates associated with anterograde
711   interference results from interactions between different timescales in motor
712   adaptation. PLoS Comput Biol. 2010;6(8).
713   37.   Kitago T, Ryan SL, Mazzoni P, Krakauer JW, Haith AM. Unlearning versus savings in
714   visuomotor adaptation: Comparing effects of washout, passage of time and removal
715   of errors on motor memory. Front Hum Neurosci. 2013;7(JUN):1–7.

38. Hudson TE, Landy MS. Measuring adaptation with a sinusoidal perturbation
function. J Neurosci Methods. 2012 Jun;208(1):48–58.
39. Ljung L. System identification-theory for the user 2nd edition ptr prentice-hall. Up
Saddle River NJ. 1999;
40. Ljung L. System identification toolbox: User's guide. Citeseer; 1995.
41. Faul F, Erdfelder E, Lang AG, Buchner A. G* Power 3: A flexible statistical power
analysis program for the social, behavioral, and biomedical sciences. Behav Res
Methods. 2007;39(2):175–91.
42. Brainard DH, Vision S. The psychophysics toolbox. Spat Vis. 1997;10(4):433–6.
43. Kleiner M, Brainard D, Pelli D. What's new in Psychtoolbox-3? 2007;
44. Moscatelli A, Mezzetti M, Lacquaniti F. Modeling psychophysical data at the
population-level: The generalized linear mixed model. J Vis. 2012 Oct
25;12(11):26–26.
45. Bates D, Mächler M, Bolker B, Walker S. Fitting Linear Mixed-Effects Models using
lme4. ArXiv14065823 Stat [Internet]. 2014 Jun 23 [cited 2021 Sep 24]; Available
from: http://arxiv.org/abs/1406.5823
46. Moscatelli A, Balestrucci P. Psychophysics with R: The R package MixedPsy. 2017.
47. Forano M, Franklin DW. Timescales of motor memory formation in dual-
adaptation. Haith AM, editor. PLOS Comput Biol. 2020 Oct;16(10):e1008373.
48. Kass RE, Raftery AE. Bayes Factors. J Am Stat Assoc. 1995;90(430):773–95.
49. Galea JM, Vazquez A, Pasricha N, Orban De Xivry JJ, Celnik P. Dissociating the roles
of the cerebellum and motor cortex during adaptive learning: The motor cortex
retains what the cerebellum learns. Cereb Cortex. 2011;21(8):1761–70.
50. Krakauer JW, Mazzoni P, Ghazizadeh A, Ravindran R, Shadmehr R. Generalization
of motor learning depends on the history of prior action. PLoS Biol.
2006;4(10):1798–808.
51. Tseng YW, Diedrichsen J, Krakauer JW, Shadmehr R, Bastian AJ. Sensory prediction
errors drive cerebellum-dependent adaptation of reaching. J Neurophysiol.
2007;98(1):54–62.
52. White O, Diedrichsen J. Responsibility assignment in redundant systems. Curr Biol.
2010;20(14):1290–5.
747

748 ## Supplementary material

Blur	JND Estimate [95% CI]
0°	0.273 [0.220, 0.334]
8°	1.159 [0.968, 1.393]
12°	1.878 [1.494, 2.650]
16°	2.479 [2.139, 2.846]
20°	3.874 [2.937, 5.634]

Table S1: Estimate and confidence intervals of JND in the localization experiment, in degrees of visual angle. Rows with gray background are those used in the adaptation task.

751 Figure 1S: *Single-state system:* For the single-state and the parallel system, learning rates
752 followed an exponential decay as a function of the JND of the visual feedback. The
753 learning rate (Fig. S1) had a starting value of 0.19 (95% CI: [0.003, 3.319]) and decreased
754 with a decay constant λ = −1.846 (95% CI: [−2.913, −0.355]). The fixed effect accounting
755 for the decay of the learning rate was statistically significant (χ_1 = 6.724, p = 0.01).

756