A physical neural mass model framework for the analysis of oscillatory generators from laminar electrophysiological recordings

Roser Sanchez-Todo[1], André M. Bastos [2], Edmundo Lopez Sola[1], Borja Mercadal[1], Emiliano Santarnecchi[3], Earl K. Miller[4,5], Gustavo Deco[6,7,8,9] and Giulio Ruffini[1,10,11]

[1] Department of Brain Modeling, Neuroelectrics SL, Av. Tibidabo 47b, 08035 Barcelona, Spain

[2] Department of Psychology and Vanderbilt Brain Institute, Vanderbilt University, Nashville, TN, United States

[3] Precision Neuroscience & Neuromodulation Program, Gordon Center for Medical Imaging, Department of Radiology, Massachusetts General Hospital, Harvard Medical School, Boston, MA, USA

[4] The Picower Institute for Learning and Memory, Massachusetts Institute of Technology, Cambridge, MA 02139

[5] Department of Brain and Cognitive Sciences, Massachusetts Institute of Technology, Cambridge, MA 02139

[6] Institució Catalana de Recerca i Estudis Avançats (ICREA), Universitat Pompeu Fabra, Computational Neuroscience, Barcelona, Spain

[7] Institució Catalana de la Recerca i Estudis Avançats (ICREA), Passeig Lluís Companys 23, Barcelona, 08010, Spain

[8] Department of Neuropsychology, Max Planck Institute for Human Cognitive and Brain Sciences, 04103 Leipzig, Germany

[9] School of Psychological Sciences, Monash University, Melbourne, Clayton, VIC 3800, Australia

[10] Starlab Barcelona, Av. Tibidabo 47b, 08035 Barcelona, Spain

[11] Haskins Laboratories, 300 George Street, New Haven, CT, 06511, USA

E-mail: `giulio.ruffini@neuroelectrics.com`, rev. 19 July 2022

Abstract. Cortical function emerges from the interactions of multi-scale networks that may be studied at a high level using neural mass models (NMM), which represent the mean activity of large numbers of neurons. In order to properly reproduce experimental data, these models require the addition of further elements. Here we provide a framework integrating conduction physics that can be used to simulate cortical electrophysiology measurements, in particular those obtained from multicontact laminar electrodes. This is achieved by endowing NMMs with basic physical properties, such as the average laminar location of the apical and basal dendrites of pyramidal cell populations. We call this framework laminar NMM, or LaNMM for short. We then employ this framework to infer the location of oscillatory generators from laminar-resolved data collected from the prefrontal cortex in the macaque monkey. We define, based on the literature of columnar connectivity, a minimal neural mass model capable of generating amplitude and phase coupled slow (alpha, 4–22 Hz) and fast (gamma, 30–250 Hz) oscillations. The synapse layer locations of the two pyramidal cell populations are treated as optimization parameters, together with two more LaNMM-specific parameters, to compare the models with the multicontact recordings. We rank the candidate models using an optimization function that evaluates the match between the functional connectivity of the model and data, where the FC is defined by the covariance between bipolar voltage measurements at different cortical depths. The family of best solutions reproduces the FC of the observed electrophysiology while selecting locations of pyramidal cells and their synapses that result in the generation of fast activity at superficial layers and slow activity across most depths, in line with recent literature proposals.

Keywords: laminar NMM, local field potentials, bipolar LFP, current source density, relative power

1. Introduction

Brain function is the result of interactions between specialized, spatially-distributed areas of brain networks [4]. For this reason, to explore the relationship between function and the underlying structure, the brain can be modeled as a complex and dynamic multi-scale network (for a review see [3, 1]). Along these lines, several computational studies rely on large-scale networks of neural mass models (NMM) to obtain insights about brain physiology and its underlying mechanisms [32, 23, 43, 6].

Jansen and Rit's NMM [19] is an effective *lumped* mesoscale model of neuronal populations based on the work of Lopes Da Silva and van Rotterdam in the 1970s [27, 28, 42]. It describes cortical column dynamics by capturing relevant physiological features at the mesoscale, but in its original form it has some limitations. For example, it can represent oscillations only in one specific frequency band for each parameter configuration [14], which limits its usefulness to model disorders with multifrequency alterations such as Alzheimer's disease [40]. This can be remedied by adding extra neuronal populations to the original model [45], as we do here. Furthermore, NMMs cannot *per se* generate measurements such as local field potentials (LFP) or derived quantities such as current source density (CSD), since these models are not mathematically embedded in a physical medium. They do, however, provide a handle on synaptic current sources and membrane potentials, where physics modeling can begin. While membrane potential may be sufficient for comparison with patch-clamp experiments, adding further physical structure is necessary to contrast model outputs with electrophysiological recordings such as LFPs, stereotactic EEG (SEEG), or, in whole brain network models, scalp electro- or magnetoencephalography (EEG or MEG).

The raw outputs of NMMs are the membrane potential alterations induced by each synapse and the consequent firing rates of each of the populations in the model, and is determined by a set of parameters describing, e.g., the dynamics of post-synaptic potentials, the relationship between membrane potential alteration and firing rate, population connectivity, and external inputs. Several studies have employed rodent multi-unit activity (MUA), LFP and CSD measurements to estimate or fit some of these parameters [46, 7, 25, 36]. To relate model outputs with CSD measurements, the sum of the average membrane potential of the populations of each layer was used in [46], while the average membrane potential or firing rates of the pyramidal populations is typically used as a proxy for MUA [7], LFP [36] or CSD [25] measurements. Whole-brain computational studies use similar methods to simulate macroscopic electrophysiological recordings (e.g., EEG) in humans [32, 23, 37]. However, as we discuss here, the connection between NMM membrane potential or firing rates with electrophysiology is not well defined. Unlike detailed neuron compartment models [24, 18], the modeling framework in these studies does not use the physical laws of volume conduction (Poisson's equation) to realistically predict measurements.

The first objective of this study is to create a framework for modeling cortical

column physics by embedding NMMs in a physical medium. Since synaptic and associated return currents in pyramidal cells are the main LFP generators [39, 13], we will assign spatial coordinates to apical and basal dendrites of the pyramidal populations corresponding to the locations where the flow of ions across the membrane takes place. Then, using Poisson's equation (which governs the distribution of electrostatic potential in biological media) in a layered medium, we can realistically calculate the LFP profiles, bipolar LFPs and CSD. We call this framework *laminar neural mass modeling*, or LaNMM for short, to emphasize its spatial and physical representation features.

As a first application of this approach, we explore a LaNMM adapted to simulate fast (gamma band) and slow dynamics (alpha band), and we fit the model parameters to simulate multicontact LFP recordings collected from the prefrontal cortex (PFC) of two macaque monkeys performing a working memory task. This previously collected dataset is described in Bastos et al. (2018) [5]. There, it was found that LFP power in the gamma band (30–250 Hz) was strongest at superficial layers and in the alpha/beta band (4–22 Hz) at deep layers, and that the phase and amplitude from deep alpha drove the phase and amplitude of superficial gamma dynamics.

These findings are in line with other studies of the visual cortex of non-human primates [8, 12, 29, 47, 49, 22, 21]. However, there are discrepancies with some studies, which may be associated with the location of the recording site (e.g., visual vs. non-visual cortex) or the type of measurement employed (e.g., CSD vs LFP). Bollimunta et al. (2008) [9], using bipolar LFP and CSD measurements, found primary alpha power generators in the deep layers of the visual areas. However, in the inferior temporal gyrus (IT) alpha generators were located in superficial layers, and superficial to deep layer driving of alpha was found. Ninomyia et al. (2015) [38], also using bipolar LFP and CSD measurements, replicated the findings of Bastos et al. (2018) [5] in visual areas but not in the Supplementary Eye Field area. Finally, Haegens et al. (2015) [17] found maximal LFP alpha power in deep layers but a shift towards superficial layers using CSD. See Appendix A for a literature review summary of studies with different recording areas and measurement types.

A potential explanation for these discrepancies is that the LFP is calculated as the spatial line integral (along an arbitrary path) of the electric field from a (potentially remote) reference electrode to the recording site ($\Delta V = V_b - V_a = -\int_a^b E \cdot dl$, with the current density $J = \sigma E$). Thus, LFPs are strongly susceptible to the selection of the reference point and to currents potentially far from the measurement point. This can affect the power distribution and coupling measurements (e.g. Granger causality). Using the recorded data, we study the impact of the choice of reference or measurement type on the power profiles. Ultimately, it would be desirable to avoid the ambiguity induced by LFPs by estimating more local quantities such as an electric field component— approximated as the first spatial derivative of the voltage along the linear array, or bipolar LFP, which removes the referencing ambiguity but not volume conduction confounds—or the CSD—approximated as the second spatial derivative of the voltage multiplied by the tissue conductivity, which deals with both problems. CSD analysis

reveals the location, direction (inwards or outwards) and strength of the flow of ions, and is widely used to calibrate the laminar location of recording sites [30, 5, 15]. However, computation of derivatives (differences) can also decrease signal to noise ratio.

Our second objective is to use our modeling framework to carry out a model-driven analysis of the data and disentangle the slow and fast sources of activity. By adjusting model parameters such as pyramidal synapse locations, we can adjust the LFP voltage, bipolar LFP and CSD power profile distributions, and voltage correlations across the PFC laminae, and compare them with the recordings collected in macaque monkeys by Bastos et al. (2018) [5]. To define a quantitative loss function for parameter fitting while avoiding referencing issues, we use the complete set of bipolar voltage correlations as the simulation target to maximize the correlation with the multicontact data. With this loss function, we deduce a family of laminar models, mainly composed of a population of neurons in superficial layers oscillating in gamma and a population of neurons in deep layers oscillating in the alpha band. The optimized architectures provide a mechanistic interpretation of the generation of slow and fast oscillations in the animal model and approximate the measured LFP and CSD power profiles.

Figure 1. Multicontact laminar recordings. A) Recordings from the ventrolateral prefrontal cortex (VLPFC) (4 electrodes) and area 8a (2 electrodes) referenced to the PFC electrode chamber. B) Visual search task. The macaque had to make a saccade to the match after the delay period (0.5–1.2 s). C) Sample LFP (referenced to ground in electrode chamber) recordings of the delay period for one of the trials. D) Sample power spectrum across depth (gradient from superficial-black to deep-white contacts). E) Sample in A) filtered in slow (4—22 Hz, blue) and fast (50—250 Hz) frequencies. F) Relative power across depth for the slow and fast frequencies.

2. Methods

2.1. Multicontact laminar recordings

The multicontact dataset used in this study was collected in experiments described in Bastos et al. (2018) [5]. LFPs from the prefrontal cortex (ventrolateral prefrontal cortex, VLPFC) and area 8a of two macaque monkeys (*Macaca mulatta*) were recorded using a linear array of multicontact laminar probes (16 contacts, 0.2 mm separation) while the animals were performing a search task (Figure 1A and 1B). For our analysis, we selected the delay period (0.5—1s) of the successful memory encoding trials (see Appendix B for more details). The reference (ground) of the LFP recordings was located on the prefrontal cortex electrode chamber. In order to define which contacts belong to the superficial and deep layers, we aligned the electrode contacts where the cerebrospinal fluid (CSF) ends and the white matter (WM) begins. Our final selection included a total of 11 contacts spanning 2 mm of grey matter (GM), the first 5 contacts (0.8 mm) belonging to the superficial layers and the rest in deep layers (1.2 mm), see Figure 1C and Figure 1E [5].

Figure 1D displays the power spectrum across depth; there is a clear bump in slow frequencies (4–22 Hz), with higher power in deep layers, and broadband gamma activity

in fast frequencies (30–250 Hz, just until 120 Hz shown), with higher power in superficial layers. We then filtered the data in these slow/fast frequency bands (Figure 1E) and computed the relative power across depth (Figure 1F). We found higher power in the fast band in superficial layers, and in the slow band in deep layers, as reported in Bastos et al. (2018) [5].

2.2. Synapse-driven formulation of NMM

Neural mass models (NMM) are mathematical representations of the dynamics of the average membrane potential and firing rate of a population of neurons in a cortical column [28]. In essence, a second order differential equation describes the average membrane perturbation that a neuronal population m experiences at each of the synapses where it receives inputs from another population n. The synapse equation represents the conversion from an input presynaptic mean firing rate φ_n to a perturbation of the mean membrane potential $u_{m\leftarrow n}$ of the postsynaptic neuron population. We represent this relation here with the integral operator $\hat{L}_{m\leftarrow n}^{-1}$ (a linear temporal filter), the inverse of which is a differential operator $\hat{L}_{m\leftarrow n}$,

$$u_{m\leftarrow n}(t) = \hat{L}_{m\leftarrow n}^{-1}[C_{m\leftarrow n}\,\varphi_n(t)]$$
$$\hat{L}_{m\leftarrow n}[u_{m\leftarrow n}(t)] = C_{m\leftarrow n}\,\varphi_n(t) \tag{1}$$

where $C_{m\leftarrow n}$ is the connectivity constant between the populations. The operator $\hat{L}_{m\leftarrow n}^{-1}$ can be expressed as a convolution of the input signal with a kernel of the form $h(t) = Aat\exp[-at]$ for $t > 0$ [16], and satisfies the Green's function equation $\hat{L}_{m\leftarrow n}[h(t-t')] = \delta(t-t')$ with appropriate causality boundary conditions.

For simplicity, we will use single index notation (s) to represent the connection/synapse from one neuronal population to another, such that the set of the synapse transmembrane potential perturbations is $\{s\} \equiv \{m\leftarrow n\colon C_{m\leftarrow n} \neq 0\}$.

The linear operator that describes the dynamics of synapse s is defined as

$$\hat{L}_s[u_s(t)] = \frac{1}{A_s}\left(\frac{1}{a_s}\frac{d^2}{dt^2} + 2\frac{d}{dt} + a_s\right)u_s(t) \tag{2}$$

where A_s is the average excitatory/inhibitory synaptic gain and a_s is the rate constant of the synapse ($a_s = 1/\tau_s$, τ_s being the synaptic time constant).

Each neuronal population converts the sum v_m of the membrane perturbations from each of the incoming synapses or external perturbations to an output firing rate (φ_m) non-linearly by a sigmoid function,

$$v_m(t) = \sum_s u_s(t) \tag{3}$$

$$\varphi_m(t) = \sigma_m(v_m(t)) = \frac{2\varphi_0}{1 + e^{r(v_0 - v_m(t))}} \tag{4}$$

where φ_0 is half of the maximum firing rate of each neuronal population, v_0 is the value of the potential when the firing rate is φ_0 and r determines the slope of the sigmoid at

Figure 2. NMM for the macaque data. A) Diagram of the model equations. B) Illustration of the neuronal populations and the connectivity between them. Top, PING model, bottom, Jansen and Rit model. Rounded shapes in A) and B) represent inhibitory populations, the rest, excitatory. C) Top, membrane potential of the Pyramidal populations; bottom, power spectral density.

the central symmetry point (v_0, φ_0). We call this rewrite of the neural mass equations [19, 16] a synapse-driven formulation of a NMM. See Appendix C for more details.

2.3. Neural Mass Model

In order to generate the dynamics described in previous experimental studies [5, 29, 12, 47, 38, 10, 21], where slow oscillations were observed to drive fast activity, we have combined two well-known NMMs. Slow oscillations in the alpha band (10 Hz) are produced by the Jansen and Rit model [19], and fast oscillations in the gamma band (40 Hz) by a variation of the PING model [11, 35].

The Jansen-Rit model (Figure 2) consists of a population P_1 of pyramidal neurons, a population SS of excitatory cells (e.g., spiny stellate cells), and a population SST representing slow inhibitory interneurons (e.g., somatostatin-expressing cells, such as Martinotti cells). The PING model (Figure 2) consists of two populations: a pyramidal population P_2, and a fast oscillatory interneuron population PV (e.g. parvalbumin-

Figure 3. Laminar framework. A) Schematic of the geometry used to simulate LFPs. For simplicity, we have removed the time variable. B) Representation of the return currents for an apical synapse (top) and a basal synapse (bottom). C) Example of a biologically informed architecture (only the synapses to pyramidal populations are shown). D) LFPs generated by the architecture in C) for a probe distance $\rho = 0.6$ mm. E) LFP shown in D) filtered in slow and fast frequency bands. F) Relative power across depth for the LFPs shown in D) for the fast and slow frequency bands.

positive cells, such as basket cells). The connectivity between these models is set so that there is a positive cross frequency coupling and a negative power correlation from slow-to-fast frequencies, as is observed in experimental work [5].

The model equations are represented in Figure 2A, and described in detail, together with the parameters used, in Appendix D. Figure 2C shows the membrane potential and power spectra of the two pyramidal populations of the model.

2.4. Physical environment

In the laminar framework, we embed the NMM into a physical medium composed of two isotropic media—grey matter and CSF. We assume that the grey matter layers have a uniform width across depth, spanning from 0 to 2 mm. To produce electrophysiological measurements from the model, we assume that synapses to pyramidal cells are the main current generators, given the anatomy of these cells (an elongated form factor), organization (perpendicular to the grey matter surface) and temporal coherence [39, 13].

The apical and basal dendrites of the pyramidal populations, with locations across the vertical z axis (Figure 3A, z_l with layer $l \in [1, 6]$) provide the location of the input/output currents of each of the synapses (sinks and sources, respectively) (for a detailed geometrical representation of the locations of the synapses and the probe contacts see Appendix E). Since each synapse perturbation u_s has its own location in

space (z_l), it will produce a flow of ions across the membrane and therefore a synaptic current I_s. We assume that the population membrane perturbation u_s is linearly related to the injected current by a scaling factor that depends on the neuron population type and represents several aspects of the population such as cell density and cell morphology. We capture this in a scaling factor—the *gain parameter* g_n —and write

$$I_s(z_l) = \begin{cases} g_n u_s(z_l), & \text{if } z_l \text{ is the location of } s \\ 0 & \text{otherwise} \end{cases} \qquad (5)$$

For simplicity, the time variable t is omitted here and in the following equations.

In the model, each injected current is accompanied by a capacitive return current (charge conservation) supplied by charges accumulated in the membrane. The precise flow of this current depends on cell morphology and electrical properties and is a subject of current study [31]. Based on previous studies [26], here we assume that inputs to apical dendrites (layer location z_a) create a return CSD contribution at two locations on the basal dendrites, layer z_b and z_{b+1}, each with half contribution, since there are large dendritic ramifications at the soma of pyramidal neurons (Figure 3B). On the other hand, inputs to the basal dendrites (z_b) create a return at the layer above (z_{b+1}). Thus, for each pyramidal cell, the total current generated at apical $(\mathcal{I}_a)$ and basal locations $(\mathcal{I}_b$ and $\mathcal{I}_{b+1})$ is

$$\mathcal{I}_a = \sum_s I_s(z_a)$$

$$\mathcal{I}_b = \sum_s I_s(z_b) - \frac{1}{2} \sum_s I_s(z_a) \qquad (6)$$

$$\mathcal{I}_{b+1} = -\sum_s I_s(z_b) - \frac{1}{2} \sum_s I_s(z_a)$$

Once the current sources are specified, we can compute the electric potential and derived quantities. We model the potential field generated by each pyramidal cell by assuming there exist two isotropic media with conductivities $\sigma_1 = 0.40$ S/m (GM) and $\sigma_2 = 1.79$ S/m (CSF) [33] and a common planar boundary (Figure 3A). Then, the potential induced by a set of synaptic point current sources in GM is [39]

$$V(z) = \frac{1}{4\pi\sigma_1} \sum_s \left[\frac{I_s(z_l)}{R_s(z)} + \left(\frac{\sigma_1 - \sigma_2}{\sigma_1 + \sigma_2}\right) \frac{I_s(z_l)}{R_{s'}(z)} \right] \qquad (7)$$

Here, $R_s(z)$ and $R_{s'}(z)$ are the distances from the current source and mirror current source to the recording point (z), respectively (Figure 3A). These distances depend on the parameter ρ, which represents the distance from the point source to the probe.

The normal component of the electric field can be computed from the gradient of the potential. We can simulate the experimentally measured "normal component" of CSD (A/m^3) from the electric potential using

$$\text{CSD}(z) = -\frac{\sigma}{(\delta z)^2} \Big(V(z + \delta z) - 2V(z) + V(z - \delta z) \Big) \qquad (8)$$

where σ (S/m) is the tissue conductivity [34, 41]. The values at the boundary layers are not evaluated.

2.5. Optimization function for model fitting

In order to compare model and data and find optimal parameters, we computed the matrix of cross-contact correlations for the slow and fast frequency bands. The optimization process is represented in Figure 4 and described hereafter.

Figure 4. Overview of the optimization function for model fitting. The shaded box (top-left) shows the process from LFP data to the creation of the two point function matrix, or functional connectivity matrix (FC, normalized by the standard deviation). To fit the model FC to the data, we adjusted three different parameters: the distance to the probe ρ, the model architectures (a total of 44,100, just three samples represented), and the relative gain η (just one sample fit shown here).

Let V_a be the real, physical, filtered measurement at a contact a referenced to ground. We then create the list of all bipolar combinations

$$(\boldsymbol{\Delta}_a)_i = (\boldsymbol{V})_i - V_a \tag{9}$$

To avoid redundancy, in what follows, $i > a$. Then, to get a generalized reference-free functional connectivity representation ($\boldsymbol{FC}$) matrix between all pairs of bipolar channels in the data, we compute the two point function

$$(\boldsymbol{FC})_{ai,bj} = \langle (\boldsymbol{\Delta}_a)_i (\boldsymbol{\Delta}_b)_j \rangle \tag{10}$$

where the brackets denote time average. Note that the two-point matrix $\boldsymbol{FC}$ includes as a subset the voltage power profiles referenced to any choice of reference electrode.

As with real data, we can produce the two point matrix from our model, $\boldsymbol{FC}_\theta$, that will depend on the parameters θ. We select the best model parameters by maximizing the Pearson correlation coefficient (r) between the flattened data $\boldsymbol{FC}_\theta$ and model $\boldsymbol{FC}$

matrices (only their diagonal and upper diagonal entries because they are symmetric) averaged over the two frequency bands, i.e., $\theta^* = \arg\max_\theta \chi(\theta)$ with

$$\chi(\theta) = \frac{1}{2} \left\{ r(\boldsymbol{FC}_\theta^{slow}, \boldsymbol{FC}_{data}^{slow}) + r(\boldsymbol{FC}_\theta^{fast}, \boldsymbol{FC}_{data}^{fast}) \right\} \tag{11}$$

The results discussed below are provided as the percent match between model and data $(\chi(\theta) * 100)$.

We adjusted the model using three different sets of parameters (represented by θ): the distance to probe ρ, the model architecture, and the relative gain η between the slow and fast population. We explored a total of 11 different ρ values, from 0.4 mm to 1.4 mm, with a size step of 0.1 mm (see Figure 4, for simplicity just 4 values are shown). We also explored all possible model architectures by varying the location of every synapse to the pyramidal populations (a binary choice of either apical or basal location) and, thus, the location and layer-span of the pyramidal populations. Figure 4 presents three examples of the different architectures. Each pyramidal population receives a total of 4 synapses to be assigned to one of six layers with the restriction that not all synapses in a population can be assigned to the same layer, so the analysis of combinations results in a total of $\left((6 \cdot 5/2) \left(2^4 - 2 \right) \right)^2 = 44{,}100$ possibilities. Here $6 \cdot 5/2$ is the number of possible apical/basal location pairs for a pyramidal cell population, while $2^4 - 2$ is the number of possible synapse assignments to each location excluding the two cases where all the synapses are assigned to the same location (this ensures that a pyramidal population always spans two different locations). Finally, for each ρ and synaptic architecture choice, the relative gain factor between the slow and fast populations ($\eta = g_{P_1}/g_{P_2}$) was adjusted to maximize the optimization function. The *SciPy* library method *optimize* [48] was used for fitting the model parameters.

3. Results

3.1. Optimization results

In order to assess the model's ability to simulate the power profiles for different LFP-derived measurements, we first need to adjust model parameters. The optimization function for model fitting is a generalization of the power profiles, namely the covariance of arbitrary differential voltage measurements (the two-point functions derived from bipolar voltages, see Methods section 2.5). We explored different model parameters in order to obtain the desired cross-correlation profiles.

The NMM parameters associated with intrinsic dynamics were fixed to produce representative fast (gamma) and slow (alpha) oscillations. We focused the fitting on laminar parameters directly influencing measurable quantities, namely the distance to probe (ρ), the location of the synapses (architectures), and the relative synaptic gain η (Figure 4 and F1). The laminar architecture parameters specify not only information about the location of the synapses in the pyramidal cells (apical vs. basal), but also the location of the apical and basal dendrites across the layers (I-VI).

The family of models that best fit the data is described in Figure 5. Figure 5A displays the percentage match with real data for different distances to probe ρ and the architectures ordered from worst to best match, for an optimized relative gain (η). For the majority of architectures, the best match happens with $\rho = 1.4$ mm, but if we zoom in to the 44 best architectures (0.1% of the total), we can see that the best fit happens with $\rho = 1.0$ mm. The fit of the model to the data degrades for $\rho > 1.0$ mm. It it noteworthy that the optimization function does not flatten out near the optimum, so the best solutions are sharply defined.

Then, we analyzed the statistics of the resulting number of synapses per layer of the 0.1% best architectures (Figure 5B) for $\rho = 1.0$ mm, and the optimized relative gain (Figure F1). For the fast circuit, most of the synapses appear located in the superficial layers I–III, whereas the synapses of the slow circuit span layers I–V. The synapses to the basal dendrites for the slow population are located in layers IV and V, and in the fast circuit, the majority happen in layer III. In both the sum as well as each individual connectivity plot, the peak synaptic activity for the slow population is always deeper than the fast population. Although layer VI was included in the model, it was never the primary layer providing the synaptic currents in the top 0.1% architectures. See Figure F1 for the optimized gains for the 0.1% best architectures.

3.2. Influence of the reference location in LFP measurements and model fit

To explore the effect of the electrical reference location on LFP measurements, we computed the LFP power profile using different electrical reference points: the ground in the prefrontal cortex chamber, a point distant to the sources (LFP_{dist}), and the first contact in the gray matter (LFP_0). In order to mitigate the impact of possible far-field sources and referencing artifacts, we also evaluated the relative power of the fast and

Figure 5. A) Percentage match with the real data for the different distances to probe ρ and ordered architectures from worst to best. B) Histograms of the number of synapses per layer among the best 0.1% architectures for each connection in the model with the best distance to probe ($\rho = 1.0$ mm). Synapses to the fast population are shown on the top row, and synapses to the slow population are shown on the bottom. Dark colors denote apical synapses and light colors basal synapses. The sum of the histograms for the synapse locations for both populations is shown for reference in black. C) Sum over all the synapses for both slow and fast populations.

slow frequency bands for the bipolar LFP and CSD measurements (Figure 6A).

Given the definition of voltage as an integral of the field or currents and the results obtained from bipolar LFP and CSD measurements, we infer that the low frequency LFP power data can be explained by currents generated by a long dipole spanning most of the cortex, with the high frequency components generated by a shorter dipole in more superficial layers. Moreover, the LFP_0 profiles in superficial layers display a rapid increase in power with depth compared with deep layers, where it slowly plateaus, which differs from the LFP_{dist} case, where the profiles remain more stable across layers for the fast frequency band, probably due to effects from more remote brain areas near the ground. This suggests that the spatial integral of the field along the vertical axis sums signals more coherently between the contacts in superficial layers than in deep layers, i.e., there is more spatial coherence of the electric field in superficial than deep layers. Moreover, the power peak of bipolar LFPs and CSD measurements occurs in superficial layers as well.

We next computed the average relative power depth profile for the best 0.1% of architectures with $\rho = 1.0$ mm for each of the different measurements (Figure 6B). These models also predict the rapid increase in power in the superficial layers for the LPF_0, and the plateau in deep layers for both fast and slow frequencies, with a more superficial peak for the fast frequencies as observed in the empirical data (Figure 6A). Moreover, the models also replicate the peak in superficial layers for both bipolar LFP and CSD. The resulting density of all the synapses estimate (Figure 5 C) is seen to reflect the associated CSD profiles from the model, with a peak in layer III (Figure 6 B,

Figure 6. A) Relative power across depth for the real data. B) Relative power across depth for the average of the 0.1% best solutions in Figure 5. Each column shows the relative power profile for each of the different measurements: LFP with a distant reference (LPF_{dist}, not present in the model), LFP with the reference in the first contact (LFP_0), bipolar LFP, and CSD. The dashed lines show the relative power of the best fit (architecture shown at the left). Filled areas show one standard error of the mean. C) Normalized FC of the data and D) of the best model fit for the slow and fast frequency bands.

CSD).

The best solution is also shown in Figure 6B (best fit), in dashed lines, and together with the FC_{data} used for the model fitting (Figure 6C) as the best FC_{model} solution (Figure 6D). We observe that the model fits the slow frequency FC_{data} better than the fast frequency FC_{data}. We also explored the power correlation and the modulation index of the model in Appendix G. We find similar patterns to those described in Bastos et al. (2018) [5], namely a bottom-up coupling of phase and amplitude and anticorrelation of fast and slow frequency power.

Altogether, we conclude from fitting the data that the main fast oscillatory synapses in our model are located in superficial layers. This is consistent with the results of the optimization in Figure 5B, where most of the synapses were present in superficial layers in the fast frequency subcircuit. In the slow population model fit, the synapses are located in significantly lower layers than the fast ones. Moreover, they are spanning across almost almost all layers, and peaking in layer IV with considerable activity also in layer V, which is completely absent from the fast population.

4. Discussion

4.1. The relative power distribution across layers depends on the choice of the measurement

In addition to the importance of taking into account the reference point when studying data in LFP space, Figure 6A demonstrates that the distributions of the relative power vary significantly depending on the type of measurement. The CSD or bipolar LFP for the slow band peak shifts to superficial layers as compared to voltage profiles, in agreement with other existing studies [8, 17]. We note that most of the studies that find the peak of slow oscillations in deep layers are based on monopolar LFP voltage recordings (LFP_{dist} here), with a remote reference far from the electrode contacts [5, 29, 12, 44, 22].

The referencing issue can in part be addressed by re-referencing the data to local electrode contacts [38, 22, 17]. It can be further mitigated by using bipolar measurements (bipolar LFP, related to the local electric field and current density) or CSD estimates. Monopolar measurements (LFP) and bipolar LFPs, unlike CSD measurements, are susceptible to volume conduction from remote sources since they are calculated as the spatial integral of the electric field between the measurement and reference point. In order to gain more information about the synaptic currents underlying LFP measurements, it is important to take into account more local types of measurements such as the bipolar potential or CSD [9, 17, 18] (see Figure A1).

It is important to note that other factors may influence the power profiles across layers: recording area [17, 38, 9], experimental task [22, 8, 17, 21], and experimental procedures such as electrode placement [38]. The proper identification of the transition between superficial and deep layers, that should also depend on the recording site [15, 12, 38], can also be a confound when comparing across studies. Future work should consider all these factors while trying to establish a golden standard for the experimental procedures (as suggested in [38]). The current availability of massively dense depth probe electrodes should shed light on theses issues in the coming years.

4.2. Mesoscale laminar models can represent physical measurements of cortical rhythms across the laminae

In this study we showed that our modeling framework is able to produce different oscillatory rhythms across layers and couplings as well as different types of laminar measurements extracted from multi-contact electrodes in a physically realistic manner (Figure 6).

A model-driven interpretation of the role of synaptic currents can shed some light on disagreements in the literature with regard to the location of oscillatory "generators"— a loose term we have purposefully avoided until now that may be conflated with the location of the soma of main cells. Electrophysiological recordings are driven by the location of synapses, which may occur at distant locations from the projecting cell

bodies.

4.3. Limitations

There are several limitations regarding the physical modeling framework we propose in this study. First, when estimating the voltage of the cortical column model (Equation 7), we assume the column can be represented as a set of monopoles and that the measurement point is relatively far from it. In reality, there is a field of dipoles in the cortical surface/patch, and the measurement contact can be placed exactly where the main dipole is located [13]. More realistic modeling approaches, such as describing the sources as a homogeneous density distributed in the the horizontal plane, can be explored [31]. Additionally, as is often done in experimental work using depth probes, in our estimation of CSD from data, we implicitly assume that all currents occur in the vertical plane. In order to properly extract the CSD, we need measurements in 3D space. This assumption may be supported by symmetry arguments derived from the fact that pyramidal cells are mostly homogeneously oriented perpendicular to the surface [13, 39].

Another limitation of this work is the relative simplicity of the presented NMM, with just two pyramidal populations oscillating in alpha and gamma bands, respectively. This simple model architecture inspired by the experimental work of Bastos et al. (2018) [5], however, has allowed us to explore all its combinations of pyramidal synapses. The LaNMM only allows for two synapse locations (apical and basal dendrites), but there is recent work that has addressed this limitation along with improving the model of return currents [31], which is also simplified in the present work.

5. Conclusions

In this study, we first extend the neural mass modeling formalism to include multiple oscillatory circuits and simulate realistic electrophysiological signals. We then use it to analyze data collected from multicontact laminar measurements in the macaque. The analysis is performed with a simple laminar model whose connections are derived from literature and that is designed to produce coupled fast and slow oscillatory activity. We fit model parameters and the location of synapses by matching voltage statistics in the alpha/beta and gamma bands, leading to a solution with slow frequency components generated by synapses spanning most cortical layers and fast oscillations in superficial layers. The laminar modeling framework developed here can be helpful for understanding the neural mechanisms of electrophysiological signals and shed some light on controversial issues regarding discrepancies in LFP, bipolar LFP and CSD measurements. The modeling framework may also help establish a firmer connection between neural mass models and EEG/MEG data and can be easily extended for the analysis of future data collected with dense probes.

Appendix A. Literature review

Figure A1. Summary of literature review of the slow (alpha/beta) and fast (gamma) cortical generators.

Figure A1 provides a graphical summary of the literature review performed of the different measurement types (rows) used in the study. It also shows the different results obtained for the different areas recorded. When using LFPs without taking into account reference location, most studies conclude that the fast activity is in upper layers and slow activity in lower layers. The conclusions change with other, more local measurement types (bipolar LFPs and CSD).

Appendix B. LFP data analysis

The multicontact dataset used in this study was collected in experiments described in Bastos et al. (2018) [5]. We analyzed the data from 2 monkeys (L, S) for six different sessions and brain areas (VLPFC and 8a). In Figure B1, the average across the correct trials for each sessions is shown. The delay period of monkey-L was fixed (1s), but for monkey-S it varied from 0.5 s to 1 s.

Appendix C. Jansen and Rit model in synapse-driven formulation

Appendix C.1. Jansen and Rit model description

In 1993 Jansen and Rit [20] developed a model of a cortical column which consists of three different neural populations: pyramidal neurons (P), inhibitory interneurons (I) and excitatory interneurons (E). The state variables of the model are the membrane

Figure B1. Average LPFs across trials, N, for the different monkeys and different sessions. The delay period is in between the 'sampleOff' and 'testOn' mark, in pink, which varies in time for monkey S (mean shown for the 'testOn', standard deviation in dashed lines). Each trace represent a different contact.

potential and the firing rate of the neuron populations, and they are linked by two different transformations that shape the classical properties of neurons: the pulse-to-wave $h(t)$ and wave-to-pulse $\sigma(v)$ functions [16, 2].

The $\sigma(v)$ operator, also called "wave-to-pulse", introduces a nonlinear component that transforms the average membrane potential of a population $v(t)$ (mV) into an average firing rate $\varphi(t)$ (Hz)

$$\varphi(t) = \sigma(v(t)) = \frac{2\varphi_0}{1 + e^{r(v_0 - v(t))}} \tag{C.1}$$

where φ_0 is half of the maximum firing rate of each neuronal population, v_0 is the value of the potential when the firing rate is φ_0 and r determines the slope of the sigmoid at the central symmetry point (v_0, φ_0). See Table C1 for the standard parameter values of the model equations.

The $h(t)$ operator, also called "pulse-to-wave", converts the average rate of action potentials into an average post-synaptic potential, either excitatory $h_{0,1}(t)$ or inhibitory $h_2(t)$. The transformation is done by a second order linear differential operator whose impulse response is given by

$$h(t) = \begin{cases} aA\,te^{-t} & t \geq 0 \\ 0 & t < 0 \end{cases} \tag{C.2}$$

where A is the synaptic gain (in potential units, e.g., mV) and a (with units of time, s^{-1}) is the rate constant (and its reciprocal τ the time constant) of the synapse. Each

Table C1. Parameters, description and standard values of the JR synapse model. Values taken from [19]. Note that the sigmoid parameters in this model (v_0, φ_0, r) are common to all neuron populations.

Parameter	Description	Value
A_s	Average excitatory and inhibitory synaptic gain	$A_{1,3,4,5} = 3.25$ mV $A_2 = -22$ mV
a_s	Time rate constant of average excitatory and inhibitory post synaptic potentials	$a_{1,3,4,5} = 100$ s^{-1} $a_2 = 50$ s^{-1}
C_s	Average number of synaptic contacts between population types	$C_1 = 108$ $C_2 = 33.7$ $C_3 = 1$ $C_4 = 135$ $C_5 = 33.75$
v_0	Potential when 50% of the firing rate is achieved	6 mV
φ_0	Half of the maximum firing rate	2.5 Hz
r	Slope of the sigmoid function at v_0	0.56 mV^{-1}

of these post-synaptic boxes corresponds to solving a differential equation of the form

$$\ddot{u}(t) + a\dot{u}(t) + a^2 u(t) = aA\,\varphi(t) \tag{C.3}$$

where $\varphi(t)$ is the output of the sigmoid function (average firing rate of a population, in Hz) and $u(t)$ is the membrane potential alteration in each of the synapses. The function $h(t)$ is the equation's Green's function or impulse response, i.e., the solution with $\varphi = \delta(t)$ and appropriate boundary conditions. The parameters A and $\tau = 1/a$ represent the maximal amplitude of excitatory or inhibitory post-synaptic potential and the average time constant for each synapse type, respectively.

This second order differential equation can be decomposed in a system of two equations,

$$\begin{aligned}\dot{u}(t) &= z(t)\\ \dot{z}(t) &= aA\,\varphi(t) - 2a\,z(t) - a^2 u(t)\end{aligned} \tag{C.4}$$

There are thus three main state variables in the model: the total average membrane potential alteration of each of the subpopulations of the system: $v_P(t)$ for the pyramidal cells, and $v_E(t)$, $v_I(t)$ for the excitatory and inhibitory interneurons, respectively. The membrane potential alteration v_P of the pyramidal population has been typically used as a proxy source of electrophysiological signals such as LFPs and EEG (dipole generator). This first-order approximation is abandoned in the LaNMM framework.

The Jansen and Rit model can be described with a set of six differential equations

Figure C1. Jansen and Rit model. A) Schematics of the connections between the different populations: P—Pyramidal, I—Inhibitory interneuron and E—Excitatory interneuron
. B) simplified wired diagram exploiting the presence of common synapse types, c) full synapse-driven wiring diagram with all synapses explicitly represented.

with each pair corresponding to a population,

$$
\begin{aligned}
\dot{u}_0(t) &= u_3(t) \\
\dot{u}_3(t) &= a_0 A_0 \Big[\sigma_P(u_1(t) - u_2(t)) \Big] - 2a_0\, u_3(t) - a_0^2 u_0(t) \\
\dot{u}_1(t) &= u_4(t) \\
\dot{u}_4(t) &= a_1 A_1 \Big[\varphi_{ext}(t) + C_2 \sigma_E(C_1 u_0(t)) \Big] - 2a_1\, u_4(t) - a_1^2 u_1(t) \\
\dot{u}_2(t) &= u_5(t) \\
\dot{u}_5(t) &= a_2 A_2 \Big[C_4 \sigma_I(C_3 u_0(t)) \Big] - 2a_2\, u_5(t) - a_2^2 u_2(t)
\end{aligned}
\tag{C.5}
$$

For an illustrative description of the model equations see Figure C1 A) and B). In this cortical column configuration, the membrane potential of the pyramidal population is $v_P(t) = u_1(t) - u_2(t)$, the membrane potential of the inhibitory interneuron population is $v_I = C_3 u_0$ and of the excitatory interneuron population is $v_E = C_1 u_0$.

Appendix C.2. Derivation of the synapse-driven formulation from Jansen and Rit equations

We can rewrite the Jansen and Rit NMM focusing on the dynamics each of the synapses independently, which will allow us to generalize the equations and simplify the definition of the neural dynamics for the development of more complex models. We will define a new linear operator, $\hat{L}^{-1}[\cdot]$, to transform the pre-synaptic average firing rate of neuron n φ_n into a post-synaptic membrane perturbation of neuron m $u_{m \leftarrow n}$:

$$
\begin{aligned}
u_{m \leftarrow n}(t) &= \hat{L}_{m \leftarrow n}^{-1}[C_{m \leftarrow n}\, \varphi_n(t)] \\
\hat{L}_{m \leftarrow n}[u_{m \leftarrow n}(t)] &= C_{m \leftarrow n}\, \varphi_n(t)
\end{aligned}
\tag{C.6}
$$

The inverse of the $\hat{L}(\cdot)$ operator and can be expressed as an integral (convolution) operator using the typical $h(t)$ kernel,

$$\hat{L}^{-1}[f(t)] = \int_{-\infty}^{\infty} dt' \, h(t-t')f(t') \tag{C.7}$$

Note that, for simplicity, the index s will represent the connection/synapse from one neuronal population to another $m \leftarrow n$, where $n, m \in [P, E, I, ext]$ and (m, n): $C_{m \leftarrow n} \neq 0$. Then, we can define the linear operator that captures the synapse dynamics $\hat{L}_s(\cdot)$ as

$$\hat{L}_s[u_s(t)] = \frac{1}{A_s}\left(\frac{1}{a_s}\frac{d^2}{dt^2} + 2\frac{d}{dt} + a_s\right)u_s(t) \tag{C.8}$$

The sum of each pre-synaptic perturbation into neuron n is the overall membrane potential perturbation of the post-synaptic neuron, v_m,

$$v_m(t) = \sum_s u_s(t) \tag{C.9}$$

and the average firing rate of the neural population, φ_m, is the output of the non-linear function,

$$\begin{aligned}\varphi_m(t) &= \sigma_m(v_m(t)) \\ \sigma_m(v_m(t)) &= \frac{2\varphi_0}{1 + e^{r(v_0 - v_m(t))}}\end{aligned} \tag{C.10}$$

Finally, the set of equations, one for each synapse (m, n) and neuron m,

$$\begin{aligned}u_{m \leftarrow n}(t) &= \hat{L}_{m \leftarrow n}^{-1}[C_{m \leftarrow n}\,\varphi_n(t)] \\ v_m(t) &= \sum_{n: C_{m \leftarrow n} \neq 0} u_{m \leftarrow n}(t) \\ \varphi_m(t) &= \sigma_m(v_m(t))\end{aligned} \tag{C.11}$$

which we call the synapse-driven reformulation of the Jansen-Rit that can be easily be extended to other, more complex NMMs.

Rewritten using the synapse-driven formalism, the Jansen and Rit equations specify the dynamics as a function of the average firing rate for each neural population φ_n, the average membrane potential for each population v_n and the membrane perturbation per each synapse u_s,

$$\begin{aligned}\hat{L}_1[u_1(t)] &= C_1\varphi_P = C_1\sigma(v_P) = C_1\sigma(u_2(t) + u_5(t) + u_4(t)) \\ \hat{L}_2[u_2(t)] &= C_2\varphi_E = C_2\sigma(v_E) = C_2\sigma(u_1(t)) \\ \hat{L}_3[u_3(t)] &= C_3\varphi_P = C_3\sigma(v_P) = C_3\sigma(u_2(t) + u_5(t) + u_4(t)) \\ \hat{L}_4[u_4(t)] &= C_4\varphi_I = C_4\sigma(v_I) = C_4\sigma(u_3(t)) \\ \hat{L}_5[u_5(t)] &= C_5\varphi_{ext}(t)\end{aligned} \tag{C.12}$$

Figure C1 C) provides the diagram and dynamics of the Jansen and Rit NMM in the Synapse-driven implementation.

Appendix D. Model parameters and equations

The parameters of the model are described in Table D1 and the equations are the following:

$$
\begin{aligned}
\hat{L}_1[u_1(t)] &= C_1\,\sigma_{SS}(v_{SS})\\
\hat{L}_2[u_2(t)] &= C_2\,\sigma_{SST}(v_{SST})\\
\hat{L}_3[u_3(t)] &= C_3\,\varphi_{e1}\\
\hat{L}_4[u_4(t)] &= C_4\,\sigma_{P_1}(v_{P_1})\\
\hat{L}_5[u_5(t)] &= C_5\,\sigma_{P_1}(v_{P_1})\\
\hat{L}_6[u_6(t)] &= C_6\,\sigma_{P_2}(v_{P_2})\\
\hat{L}_7[u_7(t)] &= C_7\,\sigma_{PV}(v_{PV})\\
\hat{L}_8[u_8(t)] &= C_8\,\varphi_{e2}\\
\hat{L}_9[u_9(t)] &= C_9\,\sigma_{P_2}(v_{P_2})\\
\hat{L}_{10}[u_{10}(t)] &= C_{10}\,\sigma_{PV}(v_{PV})\\
\hat{L}_{11}[u_{11}(t)] &= C_{11}\,\sigma_{P_2}(v_{P_2})\\
\hat{L}_{12}[u_{12}(t)] &= C_{12}\,\sigma_{P_1}(v_{P_1})\\
\hat{L}_{13}[u_{13}(t)] &= C_{13}\,\sigma_{P_1}(v_{P_1})
\end{aligned}
\tag{D.1}
$$

with neuronal population membrane potentials given by:

$$
\begin{aligned}
v_{P_1} &= u_1 + u_2 + u_3 + u_{11}\\
v_{SS} &= u_4\\
v_{SST} &= u_5\\
v_{P_2} &= u_6 + u_7 + u_8 + u_{12}\\
v_{PV} &= u_9 + u_{10} + u_{13}
\end{aligned}
\tag{D.2}
$$

Appendix E. Geometrical representation of the laminar model

In this section we show the geometrical model used in the LaNMM (Figure E1). The cortical depth (2 mm) is shown in the shaded area, where all the sources and contacts are located. The sources (N=6) and contacts (N=11) are equally distributed in the cortical space. We also show the different distance to probes ρ used in the model fitting.

Appendix F. LaNMM contact couplings

The median relative gain of the 0.1% best architectures for $\rho = 1.0$ mm is 0.13, meaning that the gain of the fast circuit g_{P_2} is approximately seven times higher than the gain of the slow circuit g_{P_1}, $\eta = g_{P_1}/g_{P_2}$. This might be due to the fact that the

Table D1. Parameters, description and standard values the model. Values taken from [19] and [35]. Note that the sigmoid parameters in this model (v_0, φ_0, r) are common to all neuron populations. Moreover, excitatory synapses have the same synapse dynamics, $(A, a)_{AMPA} = (A, a)_{1,3,4,5,6,8,9,11,12,13}$, and inhibitory synapses have either fast dynamics, $(A, a)_{GABA_{fast}} = (A, a)_{7,10}$, or slow, $(A, a)_{GABA_{slow}} = (A, a)_2$.

Parameter	Description	Value
A_s	Average excitatory and inhibitory synaptic gain	$A_{AMPA} = 3.25$ mV $A_{GABA_{slow}} = -22$ mV $A_{GABA_{fast}} = -30$ mV
a_s	Time rate constant of average excitatory and inhibitory post synaptic potentials	$a_{AMPA} = 100$ s^{-1} $a_{GABA_{slow}} = 50$ s^{-1} $a_{GABA_{fast}} = 220$ s^{-1}
C_s	Average number of synaptic contacts between population types	$C_1 = 108, C_2 = 33.7$ $C_3 = 1, C_4 = 135$ $C_5 = 33.75, C_6 = 70$ $C_7 = 550, C_8 = 1$ $C_9 = 200, C_{10} = 100$ $C_{11} = 80, C_{12} = 200$ $C_{13} = 30$
v_0	Potential when 50% of the firing rate is achieved	6 mV except for $P_2 : 1$mV
φ_0	Half of the maximum firing rate	2.5 Hz
r	Slope of the sigmoid function at v_0	0.56 mV^{-1}
φ_e	External input	φ_{e1}: pink noise with mean 200 Hz and standard deviation 30 Hz $\varphi_{e2} = 90$ Hz

intrinsic power of gamma oscillations in our model is one order of magnitude lower than the power of alpha oscillations (Figure F1).

Appendix G. LaNMM contact couplings

Here we show the power correlations and the modulation index (MI) for the model LFP data. The power correlation is computed by extracting the amplitude of the band-passed signals using the Hilbert transform and then computing the Spearman correlation of the envelopes. The MI is computed as the entropy of the phase-amplitude histogram, with phase measured in the slow band and amplitude in the gamma band.

We show in Figure G1 that there are always negative power correlations between the contacts. The most negative peak happens between the deep slow band and the superficial fast band for the best fit model parameters (box 4), and for the average over the best 0.1% model parameters from superficial to superficial layers (box 1).

Figure E1. Schematic of the locations of the sources in every layer and the probe contacts for the different distances to probe (ρ) in the grey matter (2 mm).

Figure F1. Box plot of the optimized relative gain η with the median of the distribution in green for the best 0.1% architectures in Figure 5.

In the case of the MI, the model always displays a positive MI through all the contacts, with the peak in box 1, from superficial slow frequencies to superficial fast ones.

Figure G1. Power correlation (left) and modulation index (right) for the best model fit (top) and averaged over the best 0.1% model results. The dashed lines refer to the transitions between superficial and deep layers.

Acknowledgments

This work has received funding from FET European Union's Horizon 2020 research and innovation programme (grant agreement No 101017716). The authors wish to thank Esteban Félez and Kyra Kadhim for revising the document, and Fabrice Wendling for useful discussions.

References

[1]   Hannelore Aerts et al. "Brain networks under attack: robustness properties and the impact of lesions". In: *Brain: A Journal of Neurology* 139 (Pt 12 Dec. 2016), pp. 3063–3083. ISSN: 1460-2156. DOI: `10.1093/brain/aww194`.

[2]   Saeed Ahmadizadeh et al. "Bifurcation analysis of two coupled Jansen-Rit neural mass models". In: *PloS One* 13.3 (2018), e0192842. ISSN: 1932-6203. DOI: `10.1371/journal.pone.0192842`.

[3]   Kanika Bansal, Johan Nakuci, and Sarah Feldt Muldoon. "Personalized brain network models for assessing structure-function relationships". In: *Current Opinion in Neurobiology* 52 (Oct. 2018), pp. 42–47. ISSN: 1873-6882. DOI: `10.1016/j.conb.2018.04.014`.

[4]   Danielle S. Bassett and Olaf Sporns. "Network neuroscience". In: *Nature Neuroscience* 20.3 (2017), pp. 353–364. ISSN: 15461726. DOI: `10.1038/nn.4502`.

[5]   André M. Bastos et al. "Laminar recordings in frontal cortex suggest distinct layers for maintenance and control of working memory". In: *Proceedings of the National Academy of Sciences* 115.5 (2018), pp. 1117–1122. ISSN: 1091-6490. DOI: `10.1073/pnas.1710323115`. URL: `http://dx.doi.org/10.1073/pnas.1710323115`.

[6]   Siouar Bensaid et al. "COALIA: A Computational Model of Human EEG for Consciousness Research". In: *Frontiers in Systems Neuroscience* 13 (2019), p. 59. ISSN: 1662-5137. DOI: `10.3389/fnsys.2019.00059`.

[7]   Patrick Blomquist et al. "Estimation of Thalamocortical and Intracortical Network Models from Joint Thalamic Single-Electrode and Cortical Laminar-Electrode Recordings in the Rat Barrel System". In: *PLOS Computational Biology* 5.3 (Mar. 2009), e1000328. ISSN: 1553-7358. DOI: `10.1371/journal.pcbi.1000328`. URL: `https://journals.plos.org/ploscompbiol/article?id=10.1371/journal.pcbi.1000328` (visited on 08/11/2020).

[8]   Anil Bollimunta et al. "Neuronal mechanisms and attentional modulation of corticothalamic alpha oscillations". In: *The Journal of Neuroscience: The Official Journal of the Society for Neuroscience* 31.13 (Mar. 2011), pp. 4935–4943. ISSN: 1529-2401. DOI: `10.1523/JNEUROSCI.5580-10.2011`.

[9] Anil Bollimunta et al. "Neuronal mechanisms of cortical alpha oscillations in awake-behaving macaques". In: *The Journal of Neuroscience: The Official Journal of the Society for Neuroscience* 28.40 (Oct. 1, 2008), pp. 9976–9988. ISSN: 1529-2401. DOI: `10.1523/JNEUROSCI.2699-08.2008`.

[10] J.J. Bonaiuto et al. "Lamina-specific cortical dynamics in human visual and sensorimotor cortices". In: *eLife* 7 (e33977 2018).

[11] C. Borgers, S. Epstein, and N. J. Kopell. "Gamma oscillations mediate stimulus competition and attentional selection in a cortical network model". In: *Proceedings of the National Academy of Sciences* 105.46 (Nov. 18, 2008), pp. 18023–18028. ISSN: 0027-8424, 1091-6490. DOI: `10.1073/pnas.0809511105`. URL: `http://www.pnas.org/cgi/doi/10.1073/pnas.0809511105` (visited on 08/03/2020).

[12] Elizabeth A. Buffalo et al. "Laminar differences in gamma and alpha coherence in the ventral stream". In: *Proceedings of the National Academy of Sciences of the United States of America* 108.27 (July 2011), pp. 11262–11267. ISSN: 1091-6490. DOI: `10.1073/pnas.1011284108`.

[13] György Buzsáki, Costas A. Anastassiou, and Christof Koch. "The origin of extracellular fields and currents — EEG, ECoG, LFP and spikes". In: *Nature Reviews Neuroscience* 13 (2012), p. 407.

[14] Olivier David and Karl J. Friston. "A neural mass model for MEG/EEG:: coupling and neuronal dynamics". In: *NeuroImage* 20.3 (Nov. 1, 2003), pp. 1743–1755. ISSN: 1053-8119. DOI: `10.1016/j.neuroimage.2003.07.015`. URL: `https://www.sciencedirect.com/science/article/pii/S1053811903004579` (visited on 06/28/2022).

[15] David C. Godlove et al. "Microcircuitry of agranular frontal cortex: testing the generality of the canonical cortical microcircuit". In: *The Journal of Neuroscience: The Official Journal of the Society for Neuroscience* 34.15 (Apr. 2014), pp. 5355–5369. ISSN: 1529-2401. DOI: `10.1523/JNEUROSCI.5127-13.2014`.

[16] F. Grimbert and Olivier Faugeras. "Analysis of Jansen's model of a single cortical column". In: *INRIA* RR-5597 (June 2006), p. 34.

[17] Saskia Haegens et al. "Laminar Profile and Physiology of the alpha Rhythm in Primary Visual, Auditory, and Somatosensory Regions of Neocortex". In: *The Journal of Neuroscience: The Official Journal of the Society for Neuroscience* 35.42 (Oct. 2015), pp. 14341–14352. ISSN: 1529-2401. DOI: `10.1523/JNEUROSCI.0600-15.2015`.

[18] Espen Hagen et al. "Multimodal Modeling of Neural Network Activity: Computing LFP, ECoG, EEG, and MEG Signals With LFPy 2.0". In: *Frontiers in Neuroinformatics* 12 (2018). ISSN: 1662-5196. DOI: `10.3389/fninf.2018.00092`. URL: `https://www.frontiersin.org/articles/10.3389/fninf.2018.00092/full` (visited on 01/03/2020).

[19] B. H. Jansen and V. G. Rit. "Electroencephalogram and visual evoked potential generation in a mathematical model of coupled cortical columns". In: *Biol Cybern* 73.4 (1995), pp. 357–66.

[20] B. H. Jansen, G. Zouridakis, and M. E. Brandt. "A neurophysiologically-based mathematical model of flash visual evoked potentials". In: *Biol Cybern* 68.3 (1993), pp. 275–83.

[21] Kevin Johnston et al. "Alpha Oscillations Modulate Preparatory Activity in Marmoset Area 8Ad". In: *Journal of Neuroscience* 39.10 (Mar. 2019), pp. 1855–1866. ISSN: 0270-6474, 1529-2401. DOI: `10.1523/JNEUROSCI.2703-18.2019`. URL: `https://www.jneurosci.org/content/39/10/1855` (visited on 12/27/2019).

[22] Timo van Kerkoerle et al. "Alpha and gamma oscillations characterize feedback and feedforward processing in monkey visual cortex". In: *Proceedings of the National Academy of Sciences* 111.40 (Oct. 2014), p. 14332. DOI: `10.1073/pnas.1402773111`. URL: `http://www.pnas.org/content/111/40/14332.abstract`.

[23] Tim Kunze et al. "Transcranial direct current stimulation changes resting state functional connectivity: A large-scale brain network modeling study". In: *NeuroImage* 140 (2016), pp. 174–187. ISSN: 10959572. DOI: `10.1016/j.neuroimage.2016.02.015`. URL: `http://dx.doi.org/10.1016/j.neuroimage.2016.02.015`.

[24] Shane Lee and Stephanie R. Jones. "Distinguishing mechanisms of gamma frequency oscillations in human current source signals using a computational model of a laminar neocortical network". In: *Frontiers in Human Neuroscience* 7 (Dec. 2013). ISSN: 1662-5161. DOI: `10.3389/fnhum.2013.00869`. URL: `https://www.ncbi.nlm.nih.gov/pmc/articles/PMC3866567/` (visited on 01/03/2020).

[25] Pierre Lefebvre, Philip Merrigan, and Matthieu Verstraete. "Dynamic labour supply effects of childcare subsidies: Evidence from a Canadian natural experiment on low-fee universal child care". In: *Labour Economics* 16.5 (2009). Publisher: Elsevier, pp. 490–502. ISSN: 0927-5371. URL: `https://econpapers.repec.org/article/eeelabeco/v_3a16_3ay_3a2009_3ai_3a5_3ap_3a490-502.htm` (visited on 06/24/2022).

[26] S Leski et al. "Inverse current source density method in two dimensions: inferring neural activation from multielectrode recordings." In: *Neuroinformatics* 9.4 (Dec. 2011), pp. 401–25.

[27] FH Lopes da Silva et al. "Model of brain rhythmic activity: the alpha rhythm of the thalamus". In: *Kybernetik* 15.1 (1974), pp. 27–37.

[28] FH Lopes da Silva et al. "Model of neuronal populations: the basic mechanism of rhythmicity". In: *Prog Brain Res* 45 (1976).

[29] Alexander Maier et al. "Distinct superficial and deep laminar domains of activity in the visual cortex during rest and stimulation". In: *Frontiers in Systems Neuroscience* 4 (2010). ISSN: 1662-5137. DOI: `10.3389/fnsys.2010.00031`.

[30] Nikolaus Maier, Volker Nimmrich, and Andreas Draguhn. "Cellular and Network Mechanisms Underlying Spontaneous Sharp Wave–Ripple Complexes in Mouse Hippocampal Slices". In: *The Journal of Physiology* 550.3 (2003). _eprint: https://onlinelibrary.wiley.com/doi/pdf/10.1113/jphysiol.2003.044602, pp. 873–887. ISSN: 1469-7793. DOI: `10.1113/jphysiol.2003.044602`. URL: `https://onlinelibrary.wiley.com/doi/abs/10.1113/jphysiol.2003.044602` (visited on 06/24/2022).

[31] Borja Mercadal et al. *Towards a mesoscale physical modeling framework for stereotactic-EEG recordings.* July 2022. URL: `https://www.biorxiv.org/content/10.1101/2022.07.06.498826v2`.

[32] Isabelle Merlet et al. "From Oscillatory Transcranial Current Stimulation to Scalp EEG Changes: A Biophysical and Physiological Modeling Study". In: *PLoS ONE* 8.2 (2013), pp. 1–12. ISSN: 19326203. DOI: `10.1371/journal.pone.0057330`.

[33] Pedro Cavaleiro Miranda et al. "The electric field in the cortex during transcranial current stimulation". In: *Neuroimage* 70 (2013), pp. 45–58.

[34] U. Mitzdorf. "Current source-density method and application in cat cerebral cortex: investigation of evoked potentials and EEG phenomena". In: *Physiological Reviews* 65.1 (Jan. 1985), pp. 37–100. ISSN: 0031-9333. DOI: `10.1152/physrev.1985.65.1.37`.

[35] Behnam Molaee-Ardekani et al. "Computational modeling of high-frequency oscillations at the onset of neocortical partial seizures: from 'altered structure' to 'dysfunction'." In: *Neuroimage* 52.3 (2010), pp. 1109–22.

[36] R.J. Moran et al. "Bayesian estimation of synaptic physiology from the spectral responses of neural masses". In: *NeuroImage* 42.1 (Aug. 1, 2008), pp. 272–284. ISSN: 1053-8119. DOI: `10.1016/j.neuroimage.2008.01.025`. URL: `https://www.ncbi.nlm.nih.gov/pmc/articles/PMC2644419/` (visited on 06/25/2022).

[37] Sarah Feldt Muldoon et al. "Stimulation-Based Control of Dynamic Brain Networks". In: *PLoS Computational Biology* 12.9 (2016). ISSN: 15537358. DOI: `10.1371/journal.pcbi.1005076`.

[38] Taihei Ninomiya et al. "Microcircuitry of agranular frontal cortex: contrasting laminar connectivity between occipital and frontal areas". In: *Journal of Neurophysiology* 113.9 (May 2015), pp. 3242–3255. ISSN: 1522-1598. DOI: `10.1152/jn.00624.2014`.

[39] P. L. Nunez and R. Srinivasan. *Electric Fields of the Brain: theNeurophysics of EEG.* Oxford University Press, USA, 2006.

[40] Jorge J. Palop and Lennart Mucke. "Network abnormalities and interneuron dysfunction in Alzheimer disease". In: *Nature Reviews Neuroscience* 17.12 (Dec. 2016), pp. 777–792. ISSN: 1471-0048. DOI: `10.1038/nrn.2016.141`. URL: `https://www.nature.com/articles/nrn.2016.141` (visited on 08/23/2020).

[41] Charles Quairiaux et al. "Functional development of large-scale sensorimotor cortical networks in the brain". In: *The Journal of Neuroscience: The Official Journal of the Society for Neuroscience* 31.26 (June 29, 2011), pp. 9574–9584. ISSN: 1529-2401. DOI: 10.1523/JNEUROSCI.5995-10.2011.

[42] A van Rotterdam et al. "A model of the spatial-temporal characteristics of the alpha rhythm". In: *Bulletin of Mathematical Biology* 44.2 (1982), pp. 283–305. ISSN: 1522-9602. DOI: 10.1007/BF02463252. URL: https://doi.org/10.1007/BF02463252.

[43] R. Sanchez-Todo et al. *Personalization of hybrid brain models from neuroimaging and electrophysiology data.* Pages: 461350 Section: New Results. Nov. 4, 2018. DOI: 10.1101/461350. URL: https://www.biorxiv.org/content/10.1101/461350v1 (visited on 06/25/2022).

[44] Matthew A. Smith et al. "Laminar dependence of neuronal correlations in visual cortex". In: *Journal of Neurophysiology* 109.4 (Feb. 2013), pp. 940–947. ISSN: 1522-1598. DOI: 10.1152/jn.00846.2012.

[45] Roberto C. Sotero. "Topology, Cross-Frequency, and Same-Frequency Band Interactions Shape the Generation of Phase-Amplitude Coupling in a Neural Mass Model of a Cortical Column". In: *PLOS Computational Biology* 12.11 (Nov. 2016), e1005180. ISSN: 1553-7358. DOI: 10.1371/journal.pcbi.1005180. URL: https://journals.plos.org/ploscompbiol/article?id=10.1371/journal.pcbi.1005180 (visited on 01/03/2020).

[46] Roberto C. Sotero et al. "Anatomically-constrained effective connectivity among layers in a cortical column modeled and estimated from local field potentials". In: *Journal of Integrative Neuroscience* 09.4 (Dec. 2010), pp. 355–379. ISSN: 0219-6352. DOI: 10.1142/S0219635210002548. URL: https://www.worldscientific.com/doi/abs/10.1142/S0219635210002548 (visited on 08/11/2020).

[47] Eelke Spaak et al. "Layer-specific entrainment of gamma-band neural activity by the alpha rhythm in monkey visual cortex". In: *Current biology: CB* 22.24 (Dec. 2012), pp. 2313–2318. ISSN: 1879-0445. DOI: 10.1016/j.cub.2012.10.020.

[48] Pauli Virtanen et al. "SciPy 1.0: fundamental algorithms for scientific computing in Python". In: *Nature Methods* 17.3 (Mar. 2, 2020), pp. 261–272. ISSN: 1548-7091, 1548-7105. DOI: 10.1038/s41592-019-0686-2. URL: http://www.nature.com/articles/s41592-019-0686-2 (visited on 06/28/2022).

[49] Dajun Xing et al. "Laminar analysis of visually evoked activity in the primary visual cortex". In: *Proceedings of the National Academy of Sciences* 109.34 (Aug. 2012), pp. 13871–13876. ISSN: 0027-8424, 1091-6490. DOI: 10.1073/pnas.1201478109. URL: https://www.pnas.org/content/109/34/13871 (visited on 12/27/2019).