Subcortical Auditory Model including Efferent Dynamic Gain Control

with Inputs from Cochlear Nucleus and Inferior Colliculus

Afagh Farhadi,[1] Skyler G. Jennings,[2] Elizabeth A. Strickland,[3] and Laurel H. Carney[4,a]

[1] Department of Electrical and Computer Engineering, University of Rochester, Rochester, New York 14642, USA

[2]Department of Communication Sciences and Disorders, University of Utah, Salt Lake City, Utah 84112, USA

[3] Department of Speech, Language, and Hearing Sciences, Purdue University, West Lafayette, Indiana 47907,

USA

[4] Departments of Biomedical Engineering and Neuroscience, University of Rochester, Rochester, New York 14642,

USA

Abstract

We developed an auditory model with a time-varying, gain-control signal based on the physiology of the

efferent system and the sub-cortical neural pathways. The medial olivocochlear (MOC) efferent stage of the

model receives excitatory projections from both fluctuation-sensitive model neurons of the inferior colliculus

(IC) and wide-dynamic-range model neurons of the cochlear nucleus. The response of the model MOC stage

dynamically controls the gain of simulated cochlear outer hair cells. In response to amplitude-modulated

(AM) noise, firing rates of most IC neurons with band-enhanced modulation transfer functions in awake

rabbits increase over a time course consistent with the dynamics of the MOC efferent feedback. These

changes in the rates of IC neurons in awake rabbits were employed to adjust the parameters of the efferent

stage of the proposed model. Responses of the proposed model to AM noise were able to simulate the

increasing IC rate over time, while the model without the efferent system did not show this trend. The

proposed model with efferent gain control provides a powerful tool for testing hypotheses, shedding insight

on mechanisms in hearing, specifically those involving the efferent system.

[a] Laurel_Carney@URMC.Rochester.edu

I.   INTRODUCTION

The descending auditory pathway, or efferent system, is as large as the ascending pathway in terms of number of projections, but this part of the system not been as extensively studied as the ascending pathway. The efferent system consists of several feedback projections (Guinan, 2006; Warr, 1992) spanning all levels of the auditory pathway, from the auditory cortex to the cochlea. The focus of this study is the medial olivocochlear (MOC) system, which includes projections from MOC neurons to the outer hair cells, which directly control cochlear gain. Although several studies suggest the critical role of the MOC efferent system for interpreting data from psychoacoustic measures (Lopez-Poveda, 2018; Jennings, 2021; Lauer et al., 2022), it is still unclear the extent to which the gain control by the MOC efferent system is involved in hearing. Understanding the role of the efferent system in auditory processing is essential to gain a comprehensive understanding of auditory function. In this study, we develop a computational model for the sub-cortical auditory system, providing a tool for exploring efferent mechanisms of cochlear gain control.

Despite several studies of the physiology of the efferent system (Guinan, 2006; Gummer et al., 1988; Liberman & Guinan, 1998), many aspects of this system are not well understood, such as the effects of anesthesia, the role of higher-level projections, and the independent effects of the MOC and middle-ear muscle reflexes. This gap in understanding is potentially explained by its complexity and the limited experimental methods for understanding the efferent system (Schofield, 2011). Most of the information available is based on a relatively small number of recordings from single neurons located deep in the brainstem in anesthetized animals (Guinan, 2018); however, anesthesia suppresses MOC responses (Aedo et al., 2015; A. R. Chambers et al., 2012; Guitton et al., 2004). Noninvasive methods used to study MOC effects on cochlear gain include measurements of either otoacoustic emissions (OAEs) (Guinan, 2006) or the cochlear microphonic (Jennings & Aviles, 2023; Jamos et al., 2020, 2021; Lichtenhan et al. 2016; Smith et al., 2017), with and without

MOC activation by electrical stimulation or contralateral broadband noise. These methods provide

useful insights about the efferent system; however, they do not provide information about higher-

level projections in the pathway, such as those from the IC or auditory cortex to the MOC (Delano

et al, 2007). Furthermore, care must be taken to separate effects of the middle-ear muscle reflex on

OAEs (Sun, 2008, Guinan, 2018). Here we propose a model of the MOC efferent system that can

help in designing future physiological and psychophysical experiments for studying efferent function.

A new framework for auditory coding proposes an explicit role for the efferent system.

Carney (2018) suggests that low-frequency temporal fluctuations in auditory-nerve (AN) responses

can be a reliable cue for auditory perception. It is often assumed that AN average-rate profiles

encode the spectrum of complex sounds; however, the majority of AN fibers, the high-spontaneous-

rate (HSR) fibers, have average rates that are saturated at conversational speech levels (55–65 dB

SPL, Olsen, 1998). Therefore, in many conditions, average discharge rates of HSR AN fibers do not

contain enough information to explain perception of complex sounds (Bharadwaj et al., 2014;

Carney, 2018; Liberman, 1978). On the other hand, temporal fluctuations of HSR AN responses,

referred to as neural fluctuations, have robust information at conversational speech levels,

potentially encoding peaks and valleys in the stimulus spectrum because the fluctuation depths are

smaller for AN fibers tuned near peak frequencies and larger for other frequency channels (Carney

et al., 2015; Carney, 2018). If neural fluctuations play a key role in encoding complex sounds, then

these fluctuations should be involved in the efferent gain-control system to maintain contrasts in the

neural-fluctuation profile. Interestingly, neurons in the auditory midbrain (inferior colliculus, IC) are

sensitive to low-frequency (i.e., <100Hz) fluctuations of their inputs, and the IC projects to MOC

neurons (Joris et al. 2004; Huffman & Henson 1990; Krishna & Semple, 2000).

The MOC efferent system receives several convergent inputs; the model presented here

focuses on subcortical pathways, specifically inputs from the IC and cochlear nucleus (CN). MOC

neurons receive descending projections from IC cells in the midbrain and exhibit band-pass

modulation transfer functions (MTFs) that are possibly inherited from these inputs (Gummer et al.,

1988a; Huffman & Henson, 1990; Schofield, 2011). MOC neurons also receive ascending

projections from cells types in the CN that have wide dynamic ranges (WDR), including T-stellate

cells (Blackburn & Sachs, 1990; Guinan, 2018; Romero & Trussell, 2021) and neurons in the small

cell cap, which receive low- and medium-spontaneous-rate AN inputs (Ye et al., 2000; Fekete et al.,

1984) (Fig. 1). For the proposed model, IC projections to the MOC provide neural-fluctuation

information to the MOC gain-control system, as follows: 1) IC neurons that are excited by

fluctuations (band-enhanced (BE) IC cells) reduce cochlear gain in response to fluctuating inputs, 2)

this reduction in cochlear gain increases AN fluctuation depth by reducing inner-hair-cell saturation,

3) this increase in AN fluctuation depth results in a further increase in IC activity until the gain stops

decreasing, either because a minimum cochlear gain is reached or when fluctuation-driven feedback

is balance by WDR driven feedback (described below). This fluctuation-driven feedback loop, in

which IC activity ultimately reinforces IC activity, is effectively a positive feedback loop. Note that, a

decrease in AN fluctuation depth results in positive feedback in the opposite direction, that is a

reduction in IC responses ultimately leads to a further reduction in IC responses.

The positive-feedback mechanism described above could contribute to spectral coding of

complex sounds, as follows (see Carney, 2018): 1) AN frequency channels tuned near local peaks in

the stimulus spectrum have responses that are "captured" by the spectral peak, and thus have

relatively small fluctuations (Deng et al., 1987; Delgutte and Kiang, 1984; Young and Sachs, 1979).

Consequently, for these frequency channels, BE IC cells would have lower response rates. Activity

of MOC neurons reduces cochlear gain in a frequency/place-specific manner (Guinan, 2018);

therefore, input to the MOC from BE IC channels near a spectral peak would be relatively small, as compared to that from channels driven by large fluctuations. The relatively higher cochlear gain for channels near spectral peaks would drive IHCs closer to saturation, resulting in further reduction in the neural fluctuations in AN HSR responses over time (i.e., positive feedback). 2) For frequency channels tuned away from spectral peaks, AN fluctuations are larger and BE IC cells therefore have higher response rates. The higher rates in the BE IC input to the MOC would result in a reduction in cochlear gain, reducing IHC saturation and further increasing fluctuation amplitudes in the AN response. Overall, the IC input to MOC neurons provides a positive feedback that would enhance the fluctuation contrast across AN channels tuned near spectral peaks, and thus the rate contrast across IC channels. This feedback potentially enhances the neural representation of spectral peaks and valleys at the level of the IC (see Figs. 2 and 3 in Carney, 2018).

In the proposed model, the other input to the MOC stage is from the WDR neurons in the CN, which carry the stimulus sound-level information. This level-dependent input to the MOC acts as a negative feedback system, i.e., an increase in stimulus level would increase activity of the WDR neurons which excite MOC neurons, ultimately reducing cochlear gain. This negative feedback is hypothesized to keep the operating point of the saturating IHC transducer function near its knee point, to ensure sufficient baseline fluctuation contrast across frequency channels. The IC feedback signal, described above, would then enhance this baseline contrast. If there were no contribution to gain control from the WDR cells, the AN channels could all have fluctuating or flat responses when exposed to stimuli with low or high levels, respectively, regardless of the peaks and valleys in the stimulus spectrum. Both extremes would reduce the contrast in fluctuation depth across IC frequency channels.

According to the neural-fluctuation profile framework and the feedback mechanisms of the

MOC efferent system described above, sustained fluctuations in a stimulus could cause a progressive

decrease in cochlear gain over time. As a result, in response to amplitude-modulated (AM) noise, the

average rate of BE IC neurons is expected to increase over a time course of 100-200 ms due to the

MOC-related reduction in cochlear gain. The rationale for this prediction is that the low-frequency

fluctuations of AN fiber responses to modulated noise stimuli excite IC neurons with BE MTFs. BE

IC neurons are assumed to excite MOC cells, and MOC activity decreases cochlear gain. Reduction

in cochlear gain effectively decreases the slope of the IHC transduction nonlinearity and therefore

increases the effective modulation depth at the output of the IHC (Fig. 2), ultimately increasing the

BE IC response. Thus, IC rates would increase over time until the efferent control system is

stabilized. Interestingly, re-examination of IC responses to AM noise in awake rabbits (Carney et al.,

2014) supported this hypothesis and revealed rates that increased over a time course that is

consistent with the dynamics of MOC efferent gain control (Farhadi et al., 2021). This increase in IC

rate is an unexpected effect in neural responses, which typically adapt and therefore exhibit a

decrease, rather than increase, in the neural rate over time. We quantified the increase in IC average

rate over the time course of responses to AM noise, and used that information to tune the

parameters of the MOC efferent model proposed in this work.

Here, we refine and test an AN and subcortical model with both fluctuation- and wide-

dynamic-range-driven gain control (Farhadi et al., 2021). We first introduce the novel control system

used to implement the MOC efferent pathway. Next, we describe how the parameters of the MOC

efferent model were adjusted based on a physiological dataset from a previous study of IC responses

to AM noise from awake rabbits (Carney et al., 2014). We then show that the model with efferents

outperforms a model without efferents in simulating the dynamics of physiological responses in the

IC response to AM noise stimuli. This finding supports the hypothesis that the efferent system is

potentially the underlying mechanism for the increase in rate of IC cells over the time course of AM

noise. Implications of the proposed model for responses to other sounds, and interactions with

other neural mechanisms involved in long-term changes in response rates, will be discussed.

II.   **METHODS**

We adapted existing models that were designed to simulate responses of AN fibers (Zilany et al.,

2009, 2014) and IC cells (Mao et al., 2013) to implement the proposed model with MOC efferent

gain control. First, we briefly introduce the original AN and IC models. Then, we describe the

modifications that were applied, including changes to the structure of the existing models and new

extensions added to simulate the MOC efferent system. Finally, we introduce the methods used to

estimate the MOC efferent-system model parameters.

A. Existing models

For the original Zilany et al. (2009, 2014) AN model, the stimulus first passes through a filter

that simulates the middle-ear transfer function. The output of the middle-ear filter is the input to the

cochlear-model stage (Fig. 3). Cochlear tuning is modeled using two filters, a relatively sharp

chirping filter in the signal path tuned at the characteristic frequency (CF) and a wider bandpass

filter in the feedforward control path tuned slightly higher than CF (Zhang et al., 2001; Tan &

Carney, 2003; Zilany & Bruce, 2006). The output of the control-path filter and OHC model stage

adjusts the time constant (and thus the gain and bandwidth) of the chirping filter. The cochlear-gain

parameter (C_{OHC}) in this model can be varied from 1 (normal OHC function) to 0 (completely

impaired OHC function) to simulate hearing loss related to OHC impairment. The IHC is modeled

with a nonlinear transduction function followed by a low-pass filter. Hearing loss from decreased

IHC sensitivity is implemented by varying the C_{IHC} parameter between 1 (normal IHC function) and

0 (completely impaired IHC function).

We used the BE IC model from Mao et al. (2013), which consisted of a band-pass filter centered

at the best modulation frequency (BMF) of the IC cell. The response of a simulated HSR AN model

was the input to the IC model; this structure is a simplified version of an IC model for   AM tuning

that also included a CN stage (Nelson and Carney, 2004).

B. Proposed model with MOC efferents

One of the challenges of including the efferent system in the computational AN model was to

reconfigure the implementation of the model to work sample by sample. In previous IC model

implementations (e.g., Mao et al., 2013), the AN model output for the entire stimulus waveform

served as the input to the IC stage. In the sample-by-sample configuration of the proposed efferent

model (Fig. 3), a new value of COHC(t) was applied to each sample to adjust cochlear gain based on

the output of a new stage: the model MOC (Fig. 3, dashed red box). The dynamics of the MOC

system were modeled with a first-order low-pass filter, thus the output of the MOC model was a

function of the current and previous time samples of the MOC input signal, which was a

combination of the IC-model rate function (time-varying rate, in spikes/sec) and the CN WDR

response provided by a LSR AN-model rate-function. For simplicity, we used the LSR AN model

response to represent all WDR inputs to the MOC, such as the T-stellate cells in the anteroventral

cochlear nucleus (Oertel et al., 2011; Romero & Trussell, 2021) and cells in the small cell cap of the

CN that receive exclusive inputs from LSR and MSR AN fibers (Fekete et al., 1984; Ryugo, 2008).

In the sample-by-sample implementation, the previous states of all the filters of the AN model were

preserved in order to process each time sample of the simulated model response.

In the proposed model, the output of the MOC efferent stage controlled the gain parameter

based on the current and previous samples of the neural signals at the input to this stage.

Specifically, the output of the MOC stage, a scaler between 0 to 1, was multiplied by the OHC gain

parameter (COHC) to modulate the cochlear gain. This multiplication occurred for every time

sample. The model with this new sample-by-sample configuration was tested to ensure that it

matched the response of the original model when the efferent stage was deactivated.

The two inputs to the proposed MOC model (Fig. 3, red) were the descending IC feedback

signal and the ascending WDR signal, which were combined to determine the degree of cochlear

gain reduction. Specifically, the excitatory input to the MOC stage was the sum of the IC and the

WDR rate functions. A constant scalar, KIC, was applied to the IC rate signal to approximately

balance the amplitudes of the two inputs to the MOC (Table 1). The MOC system was modeled

with a low-pass filter representing dynamics of the MOC efferent system, followed by a decaying

rational function (Eqn. 1) that mapped the MOC inputs to an output signal that modulated the

cochlear-gain parameter, C_{OHC}, on a sample-by-sample basis. The rational function, chosen to be

second-order to ensure asymptotic behavior for both small and large input signals, was described by

$$M_{out}(t) = \frac{1}{1 + (B \times (M_{in}(t))^2)} \qquad , \qquad (Eqn.\,1)$$

where $M_{in}(t)$ is the sum of the responses from the WDR and IC paths to the MOC unit after low-

pass filtering, and B is a constant that adjusts the shape of MOC input-output function (Fig. 3). The

optimization of the value of parameter B is discussed later (Section C of the Methods). Figure 4

shows the intermediate responses at each level of the composite model to a tone-in-noise stimulus.

The first 200 ms of the stimulus is noise only (Fig. 4, black). The BE IC response to this initial noise

is robust (Fig. 4, purple); because of the fluctuation in AN HSR rates (Fig. 4, blue), thus driving the

MOC model and decreasing the cochlear gain (Fig. 4, green). Between 200 and 500 ms, a tone at the

model CF (5 kHz) was added to the noise, resulting in saturation of the IHC (not shown) and

flattening the neural fluctuations in the AN HSR response. As a result of the reduced AN HSR

neural fluctuations, the BE IC rate response decreased. The reduced IC rate resulted in a weaker

MOC input and thus a relative increase in cochlear gain (Fig. 4, green). Note that the mean rate of

the AN HSR fiber was not changed appreciably by the addition of the tone, due to rate saturation;

however, the model WDR rate function increased during presentation of the tone. After the tone

ended, the IHC was no longer saturated, AN fluctuations reappeared, and the IC response increased.

The increase in the IC response excited the MOC stage, which resulted in a reduction in cochlear

gain. The changes in the WDR response rate (Fig.4, red) also influenced cochlear gain; as described

above, the WDR signal maintains the IHC operating point such that the IC response has an effect

on cochlear gain. In contrast to the CF channel tuned to the tone frequency (Fig. 4), AN fibers

tuned away from the tone would have responses that were dominated by the noise masker; at

moderate sound levels, these responses would have strong fluctuations. In summary, a flat AN

response flanked by fluctuating responses provides a cue for detecting a tone in noise.

Model code will be made freely available as downloadable files.

C. Adjusting the parameters of the MOC efferent model

Parameters of the MOC efferent model include those of the MOC input/output function, B

(Eqn.1, Fig.4), the scaler constant for IC rate (K_{IC}), and the low-pass filter (LPF) time constant (cut-

off frequency). We adjusted these parameters based on an existing physiological dataset that

contained IC responses in awake rabbits to AM wideband noise (Carney et al., 2014).

1. Stimuli

The stimulus for both the physiological dataset and the model simulation during the parameter

fits was a sinusoidally amplitude-modulated (SAM) wideband noise (100 Hz to 20 kHz) with

modulation depths that varied from -30 to 0 dB (fully modulated) in 5 dB steps, and an

unmodulated wideband noise with the same bandwidth. The modulation frequency was matched to

the best modulation frequency (BMF) of the recorded cells, and was in a ranging from 50 to 100 Hz.

The stimulus spectrum level was 36 dB re 20µPa (RMS: 76 dB SPL overall level). The duration of

the stimuli was 500 ms, including 50-ms raised-cosine ramps.

2. Physiological data and analysis

The physiological dataset included previously published extracellular, tetrode recordings of

responses in the central nucleus of the IC in three awake rabbits. Stimuli were presented to the

contralateral ear. Details of the physiological methods can be found in Carney et al. (2014). Briefly,

IC cells were classified based on their MTFs into BE, band-suppressed (BS), hybrid, flat and unusual

types (Kim et al., 2015, 2020) (Fig. 5). BE IC cells are excited over a band of modulation

frequencies, whereas IC BS cells are suppressed over a band of modulation frequencies (Kim et al.,

2020). Hybrid cells have rates that are enhanced over one band of modulation frequencies, and

suppressed over another range (Kim et al., 2020). The focus of this study was on BE cells because

this IC MTF type was hypothesized by Gummer et al., (1988b) to project to MOC neurons, based

on the BE MTFs reported for MOC neurons. MTF shapes were classified similar to Kim et al.

(2020), using a criterion ratio of 1.2 peak MTF rate to the reference rate response to an unmodulated

wideband noise which yielded approximately equal numbers of BE and BS MTFs (Fig. 5). The

frequency of the peak rate in the MTF identifies the cell's BMF. The physiological responses used

in this study had stimulus modulation frequency that was within an octave of the recorded cell's

BMF.

To analyze the physiological responses to AM noise, a Gaussian filter was used to smooth the

spike trains to avoid aliasing introduced by PSTH bin-widths (Lehky, 2010). The standard deviation

of the Gaussian filter was inversely proportional to each cell's BMF; the number of points in the

filter was six times the standard deviation of the Gaussian window. Responses were averaged over

50 repetitions of the stimulus.

Trends in firing rate over the course of the response, after an initial 200 ms which included the

onset response, were characterized using a simple linear regression. Based on the efferent model

framework, the BE IC rates were hypothesized to increase over time as a result of reduction in

cochlear gain and increase in the temporal fluctuation depths in AN responses. The sign of the

linear model's slope indicated whether the response increased or decreased over time. BE IC

responses with rates that increased over time were used to find the parameters in the MOC efferent

model by maximizing the correlation between the BE IC spiking rate and the model responses to a

stimulus with a modulation depth of -10 dB. A modulation depth of -10 dB was chosen here

because the majority of the IC neurons had strong increases in rate over time at this modulation

depth as compared to higher modulation depths, for which IC rates sometimes saturated. A brute-

force method was used to search a reasonable range of parameters and find a set of parameters

values that maximized the correlation between the model response and the physiological data over

the analysis window. Parameters were estimated for each neuron in the dataset. We simultaneously

fit the time constant, τ_{MOC}, the rational function parameter, B (Eqn. 1), and the IC constant scaler,

K_{IC}. A 300-ms -duration analysis window was used for both physiological and model responses. The

analysis window started 200 ms after stimulus onset and continued until the end of stimulus.

Properties of the model such as CF, BMF, and modulation frequency were matched to each cell in

the physiological dataset. Based on the parameter value fits for each of the 33 neurons in the dataset,

a distribution of the parameters was established, and the means of the distributions were chosen for

the final model parameter values. The sensitivity of the model to the parameter values was studied

by comparing the average correlation between the physiological and the model responses when each

model parameter was either set to the value fit to each neuron or to the mean parameter value for

the population.

III.   RESULTS

Section A below reviews our hypothesis regarding the MOC efferent model response to AM noise stimuli, analysis of the physiological dataset in response to AM noise, and implementation of the MOC efferent model with its parameters (K_{IC}, B, and τ_{MOC}). Section B describes the distribution of the optimum parameters in the dataset and compares the responses of models with and without the MOC efferent control system to physiological data. In section C we use the new model with MOC efferent control to simulate responses to a few different stimuli and compare these responses with physiological data from the literature.

A. The physiological dataset

Consistent with our hypothesis, the IC rates increased over time in most IC neurons with BE MTFs. Figure 6 presents six examples of BE IC neuron responses that illustrate the trend of increasing rate over time; these examples were chosen as they have different BMFs and CFs. The left panel in each example in Fig. 6 is the rate MTF, and the right panel is the IC response to AM noise modulated at a frequency near the neuron's BMF, with a range of modulation depths (different colored lines). The gray time range is the time window after the onset response over which we analyzed the increase in rate. All of the examples in Fig. 6 had increasing rate over time during the analysis window, especially in response to lower modulation depths. In some neurons (e.g., Fig. 6B) the rate was nearly constant over time in response to fully modulated noise, but the IC rate was high for this modulation depth from the beginning of the analysis window. In the framework of our hypothesis, this observation suggests that because of the strong modulation in the stimulus, the fluctuation in AN PSTHs was large enough to maximize the IC rate, such that a change in cochlear gain as a result of MOC efferent activity could not further increase the IC rate. In these examples, the PSTHs in response to the unmodulated noise stimulus also showed an increasing trend in rate. This trend in the noise responses could also be explained by efferent-system activity, because

unmodulated wideband noise includes inherent temporal fluctuations after peripheral filtering,

which would increase IC rate and lower the cochlear gain.

The trend of increasing rate over time (See Methods Section C) occurred in approximately 80%

of neurons with BE MTFs in response to modulation depths less than -15 dB (Fig. 7). This

percentage decreased at high modulation depths (see Fig. 6). As described above, the decrease at

high modulation depths can be explained by a ceiling effect on the IC rate. In general, neural

response rates are typically expected to decrease over time during sustained stimuli, as a result of rate

adaptation, making this increase in rate particularly striking. The finding that 80% of the BE IC cells

had rates that increased over the time course of the AM noise stimuli is consistent with the

hypothesis that MOC efferent activity results in an increase in BE IC rates over time.

B. Adjusting model parameters

The distribution of the optimized parameters for neurons in this study was very broad (Fig.8).

The median of the distribution for each parameter was used as the final value for that parameter

(K_{IC}=30, τ_{MOC}=260 ms, B=0.01) (Eqn.1). The median of the estimated time constant distribution

was 260 ms, which was used to determine the cutoff frequency of the LPF in the MOC's model,

τ_{MOC}. This value agrees with values of the time constant that have been suggested for the MOC

efferent system based on other types of physiological and psychophysical measurements (Backus &

Guinan, 2006; Roverud & Strickland, 2010; Warren & Liberman, 1989).

The median correlation between the model and physiological responses during the analysis time

window was calculated for models with and without the efferent feedback system (Fig. 9). The low

median correlation of 0.025 between data and the model without efferent response (Fig. 9-A)

demonstrates that the model without efferents did not simulate the increasing trend in rate over time

in the physiological dataset; instead, the response of that model showed a decrease in rate consistent

with neural adaptation that arises in the AN model responses (Zilany et al., 2014). Simulations using

a MOC efferent model with parameters identified for each neuron resulted in a correlation of 0.98

between the data and model responses (Fig. 9-B). The correlation reduced to 0.68 after replacing the

individual values with the median values of the distributions estimated for each parameter, and some

of the correlations in this condition are negative, consistent with the wide distribution of the

optimum parameters for each neuron (Fig. 9-C). This result shows that the model was sensitive to

the parameter values, but still simulated the increased rate in response to AM noise using median

parameters values.

Figure 10 shows responses to AM noise for three representative BE IC cells (left column),

for models without MOC efferents (middle column), and for the model with efferents, using the

mean values for the model parameters (right column). The models had BMFs and CFs that matched

the example neurons. The model with MOC efferent feedback simulated the increase in rate over

time, consistent with the hypothesis that a model with the MOC efferent system could simulate the

response to AM noise more accurately than the model without efferents.

C. Validating the proposed model responses

Model responses to tone stimuli were compared to responses of the previous model to verify

that introducing the efferent gain-control pathways did not adversely affect the model's ability to

predict AN responses to basic stimuli. It is important to note that the physiological data used for

comparison were recorded from ANs of anesthetized animals, in which the MOC efferent system

was likely suppressed (Guitton et al., 2004). Thus, complete agreement between the physiological

responses of AN fibers in anesthetized animals and the responses of the AN stage of the model with

MOC efferents was not expected, especially for complex stimuli (such as AM tones). However, for

pure-tone stimuli, Rhode and Kettner (1987) and May and Sachs (1992) showed that anesthesia does

not significantly affect post-stimulus time histograms (PSTHs) or rate-level functions of primary-like

neurons in the cochlear nucleus (and one presumed AN fiber). Therefore, we validated the proposed

model by comparing simulated responses to some baseline stimuli in physiological examples.

Model Response to pure tones and recovery of spontaneous rate

Figure 11 shows data and simulated responses to a 500-ms tone at CF followed by 500-ms of

silence. The purpose of this task was to study both the tone response and the AN model's recovery

to spontaneous rate. Recovery of spontaneous activity depends on stimulus level and on the

spontaneous rate of the fiber (Kiang, 1965). Here we compare model responses to physiological

recordings from two HSR fibers with CFs of 1.82 and 10.34 kHz from Kiang (1965) (Fig. 11). The

model response during the tone is comparable to the physiological examples, and the model shows

the same initial pause and time course of recovery after the stimulus as in the physiological

responses. Note that the response to a pure tone would primarily activate the CN input to MOC

efferent pathway. The IC stage of the model would mainly respond at the onset and offset of the

tone, when the onset/offset ramps form a fluctuation in the stimulus envelope and therefore elicit a

response from the fluctuation-sensitive IC neurons.

Model response to an increment in tone level

One of the paradigms tested in Zilany et al. (2009) was the model response to an increment in

tone level. The purpose of this example is to evaluate the response to an increment in a tonal

pedestal. In the physiological data (Westerman & Smith, 1987) the AN fiber response to a tone at

the fiber's CF (5.99 kHz, HSR) was recorded in anesthetized cat. Over the first 300 ms of the

stimulus, the tone level was 5, 10, 15, or 20 dB above threshold, and for the second 300 ms, the tone

level increased to 43 dB above threshold. In the physiological responses, the transient response to

the pedestal increased with pedestal level, but the transient response to the increment decreased with

increasing pedestal level. The same trend was observed in the response of the AN model with and

without MOC efferents. The increase in rate over time that followed the first transient response was

observed for the model with MOC efferents (Fig. 12C, for initial tone levels of +5 and +10 dB), but

not for physiological responses in the anesthetized gerbil (Fig. 12A). This discrepancy between the

MOC model predictions and the physiological data may be due to the effects of anesthesia on the

empirical AN recordings. The increase in rate during the low-level tones (Fig. 12-c, +5 and +10 dB)

reflects the recovery of cochlear gain after an initial decrease in response to the onset of the

stimulus. Responses in unanesthetized animals are not available for these stimuli, therefore, it is not

possible to confirm this interpretation at this time.

Model response to AM stimuli

Here the model response was compared to the response of an HSR AN fiber with CF of 20.2

kHz to an AM tone with a carrier frequency at CF (Joris & Yin, 1992). The effect of modulation

depth on the synchrony to modulation frequency was studied for modulation depths ranging from 0

to 1. The modulation frequency was 100 Hz and level was 49 dB SPL. A comparison of

synchronization to AM frequency as a function of modulation depth showed that the model with

MOC efferents had increased synchrony with modulation depth. However, the synchrony of the

model response was weaker than that observed physiologically because of the reduction in cochlear

gain as a result of MOC efferent activity. Complications for comparison exist due to the difference

between dynamic ranges of the model and this physiological example, as noted by Zilany et al.,

(2009) (Fig. 13-A). Furthermore, model responses to AM tones, which consist of both carrier and

sideband frequencies, may be shaped by the effective bandwidths of MOC projections, discussed

below. AM responses of the model with efferents, however, cannot be directly compared to

physiological responses, which are not available for AN fibers in unanesthetized animals. However,

we do have access to IC responses to AM noise in awake rabbit. Figure 13 B compares the

synchrony to AM noise for the IC stage of the model with MOC efferents to actual responses from

an IC cell in awake rabbit (Carney et al., 2014). This result confirms that, for the model with

efferents, the increase in synchrony in the AN model with increasing modulation depth results in

appropriate synchrony at the level of the model IC.

IV. **DISCUSSION**

In this work, we modified an existing model of the peripheral auditory system to simulate both

the ascending pathway and MOC efferent feedback with both CN and IC inputs. The physiological

data and simulation results are consistent with the hypothesis that the MOC efferent system

influences neural fluctuations over time (Carney, 2018), as observed here by the increasing responses

of BE IC cells over the time course of an AM noise. The simulation results support the hypothesis

that a sub-cortical model with MOC efferent gain control better simulates IC responses to AM noise

compared to a model without efferents.

One of the components of the proposed model is a LPF that was implemented to simulate the

dynamics of the MOC efferent system. The time constant (or cut-off frequency) of this filter was

adjusted based on the physiological dataset. The dynamics of the MOC efferent system based on the

fit parameter agree with the reported dynamics in the literature for the MOC efferent fast effect.

Backus and Guinan (2006) used stimulus-frequency otoacoustic emission (SFOAE) measurements

to estimate the human MOC-reflex time constant. They reported an overall onset time constant of

277±62 ms and decay time constant of 159±54 ms. Warren and Liberman (1989) estimated the

MOC response to have a time constant of 250 ms in barbiturate-anesthetized cats. Roverud and

Strickland (2010) used an optimized psychophysical technique to estimate the time course of

cochlear-gain reduction. They estimated an average exponential decay of 100 ms, which is faster

than the time constant estimated by Backus and Guinan. Yasin et al. (2020) used a computational

model of human hearing that included MOC efferent feedback and evaluated the model's speech

recognition for different MOC efferent time constants. Their results suggest the improvement in

recognition of speech in AM noise is highest for a MOC efferent time constant of 200 ms. In

general, all of the time constants suggested in the literature for the MOC efferent system are in the

same range as our results based on rabbit midbrain physiology. However, the MOC efferent system

time constant could differ between rabbits and humans. Using the proposed MOC efferent model to

simulate human psychoacoustic experiments could better inform our understanding of the time

constant for human listeners.

The dynamics of the efferent system support its potential role in improving speech perception

(Yasin et al., 2018). Specifically, the latency and time constant of the MOC efferent system (Backus

& Guinan, 2006; Roverud & Strickland, 2010; Warren III & Liberman, 1989) are comparable to

typical phonemic durations (Jacewicz et al., 2007; Umeda, 1977). Therefore, the MOC efferent

system would presumably affect auditory neural responses, both within the time course of

phonemes and also in running speech, for which the perception of a phoneme would be influenced

by the previous phoneme (co-articulation) (Chambers et al., 2017; Recasens, 1984, 2018).

Another important component of the proposed model MOC efferent system was the input-

output function that maps the MOC input to a gain factor that scales the cochlear-gain coefficient

between 0 and 1. The second-order rational function used in this model was chosen based on its

asymptotic behavior at low and high input levels. The direct input-output function of MOC neurons

is not known, but several related functions have been reported. The shape of the proposed input-

output function was similar to the MOC efferent attenuation as a function of input sound level

shown in Russell and Murugasu (1997). Also, the asymptotic trend of this function for higher values

is similar to the asymptotic responses shown in Liberman (1988) for MOC efferent activity as a

function of input sound level. Finally, the proposed function is similar to the relationship between

stimulus level and OHC power gain, which would be modulated by MOC signals, in an electrical-

mechanical model for OHCs (Rabbitt & Bidone, 2023; Rabbitt, 2023).

Comparing the Proposed model with previous AN models that included the efferent system

Several previous AN models include efferent signals driven by the periphery (Clark et al., 2012;

Giguere & Woodland, 1994; Kwan et al., 2019; Smalt et al., 2014; Yasin et al., 2020). In some of

these previous implementations, cochlear gain was set to remain constant over time, omitting the

dynamics of MOC efferents (Brown et al., 2010; Ferry & Meddis, 2007; Giguere & Woodland, 1994;

Jennings et al., 2011). Smalt et al. (2014) proposed a model based on the Zilany et al. (2014) AN

model, but with an efferent system modeled by a time-varying gain-control feedback system.

However, in this model, a local gain-control system was implemented based on the output of model

OHCs, which is inconsistent with the overall structure of the MOC efferent system, which depends

on outputs from the OHCs, IHC, AN, CN, IC, and other structures (Smalt et al., 2014; Schofield,

2011). None of these models simulated the descending input to the MOC efferent system from the

midbrain. The focus of the current study was to include both peripheral and midbrain inputs to a

dynamic MOC efferent system in a model for AN and BE IC responses.

Limitations and Future directions

Other physiological and psychoacoustic studies can be used to further fine tune the model's

parameters and structure. For example, forward-masking studies with long-duration maskers would

be expected to activate the MOC efferent system (Krull and Strickland, 2008; Brennan et al., 2023).

At the level of the IC, further animal studies of the temporal properties of responses to complex

sounds would contribute to this modeling effort, such as investigating the changes in synchrony of

IC responses to the envelope of AM stimuli over time. Another direction for future work is to study

the influence of efferent activity on the responses of other MTF types in the IC, such as BS or

Hybrid MTFs. Here we focused on BE MTFs, as their increase in their rate over the time course of

AM stimuli cannot be confused with rate adaptation.

The peripheral model studied here is a monaural model, with "one-sided" brainstem and

midbrain stages. A binaural model would be a powerful tool for studying the crossed and uncrossed

effects of the efferents. The proposed model in this study consists of a single CF channel, and MOC

controls for each frequency influence the gain of the related CF channel. However, studies have

shown that some projections from MOC neurons to OHCs have a broad distribution across CF

channels (Brown, 2014; Lee & Lewis, 2023). To move towards a more comprehensive model, a

future direction of research could be to explore a cross-frequency projection of the MOC control

system that affects a range of CFs. A broader distribution of MOC projection could benefit

simulations of the neural response to complex stimuli such AM noise and also speech signals.

Another direction for future work on this model is inclusion of a more advanced IC model, instead

of the simple bandpass filter used for modulation filtering in BE IC neurons in the current model.

In general, recording from AN fibers requires an anesthetized animal preparation, but

anesthesia suppresses MOC efferent activity (Guitton et al., 2004). As a result, there are no examples

in the AN physiological literature for comparison to the AN model response with active MOC

efferents. However, recording from more accessible levels of the auditory pathway, such as the IC in

awake animals, could provide further information regarding the MOC efferent system. Recording

from the CN in awake animals or recording from AN fibers in decerebrate animals could also

potentially be beneficial for studying the MOC efferent system (Kim et al., 1990a, 1990b; Kawase et

al., 1993).

Other phenomena could explain the increase in IC response rates over time in response to AM

noise, either in addition to or instead of efferent activity. For instance, adaptation of inhibition

(Viemeister & Bacon, 1982) could be an alternative explanation for the increase in rate we observed

in IC responses to AM noise. Adaptation of inhibition has been suggested as an explanation for

auditory enhancement, in which a target signal embedded in a masker is preceded by the same

masker but without the target frequency. Adaptation of inhibition could explain an improvement in

the threshold of detecting the tone (Byrne et al., 2011). However, neural mechanisms underlying

adaptation of inhibition are not clear. Enhancement effects and its properties, such as time constant

and level-dependence, may be further examined using the MOC efferent model in the future to see

if such effects are consistent with MOC feedback. Preliminary results suggest that the subcortical

model with efferent feedback can also explain several aspects of auditory enhancement (Farhadi et

al., 2023).

V.　**ACKNOWLEDGMENTS**

This work was supported by NIH-R01-DC010813 (AF, LHC), NIH-R01-DC008327 (EAS), and

K23 DC014752 (SGJ).

REFERENCES

Aedo, C., Tapia, E., Pavez, E., Elgueda, D., Delano, P. H., & Robles, L. (2015). Stronger

efferent suppression of cochlear neural potentials by contralateral acoustic stimulation in awake than

in anesthetized chinchilla. Frontiers in Systems Neuroscience, 9, 21.

Backus, B. C., & Guinan Jr, J. J. (2006). Time-course of the human medial olivocochlear reflex.

The Journal of the Acoustical Society of America, 119(5), 2889–2904.

Bharadwaj, H. M., Verhulst, S., Shaheen, L., Liberman, M. C., & Shinn-Cunningham, B. G.

(2014). Cochlear neuropathy and the coding of supra-threshold sound. Frontiers in Systems

Neuroscience, 8, 26.

Blackburn, C. C., & Sachs, M. B. (1990). The representations of the steady-state vowel

sound/e/in the discharge patterns of cat anteroventral cochlear nucleus neurons. Journal of

Neurophysiology, 63(5), 1191–1212.

Brennan, M. A., Svec, A., Farhadi, A., Maxwell, B. N., & Carney, L. H. (2023). Inherent

envelope fluctuations in forward masking: Effects of age and hearing loss. The Journal of the

Acoustical Society of America, 153(4), 1994-2005.

Brown, M. C. (2014). Single-unit labeling of medial olivocochlear neurons: the cochlear

frequency map for efferent axons. *Journal of neurophysiology*, *111*(11), 2177-2186.

Brown, G. J., Ferry, R. T., & Meddis, R. (2010). A computer model of auditory efferent

suppression: Implications for the recognition of speech in noise. The Journal of the Acoustical

Society of America, 127(2), 943–954. https://doi.org/10.1121/1.3273893

Byrne, A. J., Stellmack, M. A., & Viemeister, N. F. (2011). The enhancement effect: evidence for

adaptation of inhibition using a binaural centering task. The Journal of the Acoustical Society of

America, 129(4), 2088–2094.

Carney, L. H. (2018). Supra-threshold hearing and fluctuation profiles: implications for

sensorineural and hidden hearing loss. Journal of the Association for Research in Otolaryngology,

19(4), 331–352.

Carney, L. H., Li, T., & McDonough, J. M. (2015). Speech coding in the brain: representation of

vowel formants by midbrain neurons tuned to sound fluctuations. Eneuro, 2(4).

Carney, L. H., Zilany, M. S. A., Huang, N. J., Abrams, K. S., & Idrobo, F. (2014). Suboptimal

use of neural information in a mammalian auditory system. Journal of Neuroscience, 34(4), 1306–

1313.

Chambers, A. R., Hancock, K. E., Maison, S. F., Liberman, M. C., & Polley, D. B. (2012).

Sound-evoked olivocochlear activation in unanesthetized mice. Journal of the Association for

Research in Otolaryngology, 13(2), 209–217.

Chambers, C., Akram, S., Adam, V., Pelofi, C., Sahani, M., Shamma, S., & Pressnitzer, D. (2017).

Prior context in audition informs binding and shapes simple features. Nature Communications, 8(1),

1–11.

Clark, N. R., Brown, G. J., Jürgens, T., & Meddis, R. (2012). A frequency-selective feedback

model of auditory efferent suppression and its implications for the recognition of speech in noise.

The Journal of the Acoustical Society of America, 132(3), 1535–1541.

https://doi.org/10.1121/1.4742745

Delgutte, B., & Kiang, N. Y. (1984). Speech coding in the auditory nerve: I. Vowel-like sounds.

The Journal of the Acoustical Society of America, 75(3), 866-878.

Delano, P. H., Elgueda, D., Hamame, C. M., & Robles, L. (2007). Selective attention to visual

stimuli reduces cochlear sensitivity in chinchillas. Journal of Neuroscience, 27(15), 4146-4153.

Deng, L., Geisler, C. D., & Greenberg, S. (1987). Responses of auditory-nerve fibers to multiple-

tone complexes. The Journal of the Acoustical Society of America, 82(6), 1989-2000.

Farhadi, A., Agarwalla, S. & Carney, L. H. (2023). A Subcortical Auditory Model With Efferent

Gain Control Explains Perceptual Enhancement. Abstract, Association for Research in

Otolaryngology, SU198, pg.449.

Farhadi, A., Jennings, S. G., Strickland, E. A., & Carney, L. H. (2021). A Closed-Loop Gain-

Control feedback model for the medial efferent system of the descending auditory pathway.

In ICASSP 2021-2021 IEEE International Conference on Acoustics, Speech and Signal Processing

(ICASSP) (pp. 291-295). IEEE.

Fekete, D. M., Rouiller, E. M., Liberman, M. C., & Ryugo, D. K. (1984). The central projections

of intracellularly labeled auditory nerve fibers in cats. Journal of Comparative Neurology, 229(3),

432-450.

Ferry, R. T., & Meddis, R. (2007). A computer model of medial efferent suppression in the

mammalian auditory system. The Journal of the Acoustical Society of America, 122(6), 3519–3526.

https://doi.org/10.1121/1.2799914

Giguere, C., & Woodland, P. C. (1994). A computational model of the auditory periphery for

speech and hearing research. II. Descending paths. Journal of the Acoustical Society of America,

95(1), 343–349. https://doi.org/10.1121/1.408367

Guinan Jr, J. J. (2006). Olivocochlear efferents: anatomy, physiology, function, and the

measurement of efferent effects in humans. Ear and Hearing, 27(6), 589–607.

Guinan Jr, J. J. (2018). Olivocochlear efferents: Their action, effects, measurement and uses, and

the impact of the new conception of cochlear mechanical responses. Hearing Research, 362, 38–47.

Guitton, M. J., Avan, P., Puel, J.-L., & Bonfils, P. (2004). Medial olivocochlear efferent activity in

awake guinea pigs. Neuroreport, 15(9), 1379–1382.

Gummer, M., Yates, G. K., & Johnstone, B. M. (1988a). Modulation transfer function of

efferent neurones in the guinea pig cochlea. Hearing Research, 36(1), 41–51.

https://doi.org/10.1016/0378-5955(88)90136-0

Gummer, M., Yates, G. K., & Johnstone, B. M. (1988b). Modulation transfer function of

efferent neurones in the guinea pig cochlea. Hearing Research, 36(1), 41–51.

Huffman, R. F., & Henson Jr, O. W. (1990). The descending auditory pathway and

acousticomotor systems: connections with the inferior colliculus. Brain Research Reviews, 15(3),

295–323.

Jacewicz, E., Fox, R. A., & Salmons, J. (2007). Vowel duration in three American English

dialects. American Speech, 82(4), 367–385.

Jamos, A. M., Kaf, W. A., Chertoff, M. E., & Ferraro, J. A. (2020). Human medial olivocochlear

reflex: contralateral activation effect on low and high frequency cochlear response. Hearing

Research, 389, 107925.

Jamos, A. M., Hosier, B., Davis, S., & Franklin, T. C. (2021). The role of the medial

olivocochlear reflex in acceptable noise level in adults. Journal of the American Academy of

Audiology, 32(03), 137-143.

Jennings, S. G., & Aviles, E. S. (2023). Middle ear muscle and medial olivocochlear activity

inferred from individual human ears via cochlear potentials. The Journal of the Acoustical Society of

America, 153(3), 1723-1732.

Jennings, S. G. (2021). The role of the medial olivocochlear reflex in psychophysical masking

and intensity resolution in humans: a review. Journal of Neurophysiology, 125(6), 2279–2308.

Jennings, S. G., Heinz, M. G., & Strickland, E. A. (2011). Evaluating adaptation and

olivocochlear efferent feedback as potential explanations of psychophysical overshoot. JARO -

Journal of the Association for Research in Otolaryngology, 12(3), 345–360.

https://doi.org/10.1007/s10162-011-0256-5

Joris, P X, Schreiner, C. E., & Rees, A. (2004). Neural processing of amplitude-modulated

sounds. Physiological Reviews, 84(2), 541–577.

Joris, Philip X, & Yin, T. C. T. (1992). Responses to amplitude-modulated tones in the auditory

nerve of the cat. The Journal of the Acoustical Society of America, 91(1), 215–232.

Kawase, T., Delgutte, B., & Liberman, M. C. (1993). Antimasking effects of the olivocochlear

reflex. II. Enhancement of auditory-nerve response to masked tones. Journal of neurophysiology,

70(6), 2533-2549.

Kiang, N. Y. S., Watanabe, T., Thomas, E. C., & Clark, L. F. (1965). *Discharge patterns of single*

fibers in the cat's auditory nerve. Cambridge, MA: MIT Press.

Kim, D. O., Carney, L., & Kuwada, S. (2020). Amplitude modulation transfer functions reveal

opposing populations within both the inferior colliculus and medial geniculate body. Journal of

Neurophysiology, 124(4), 1198–1215.

Kim, D. O., Zahorik, P., Carney, L. H., Bishop, B. B., & Kuwada, S. (2015). Auditory distance

coding in rabbit midbrain neurons and human perception: monaural amplitude modulation depth as

a cue. Journal of Neuroscience, 35(13), 5360-5372.

Kim, D. O., Sirianni, J. G., & Chang, S. O. (1990). Responses of DCN-PVCN neurons and

auditory nerve fibers in unanesthetized decerebrate cats to AM and pure tones: analysis with

autocorrelation/power-spectrum. Hearing research, 45(1-2), 95-113.

Kim, D. O., Chang, S. O., & Sirianni, J. G. (1990). A population study of auditory-nerve fibers in

unanesthetized decerebrate cats: Response to pure tones. The Journal of the Acoustical Society of

America, 87(4), 1648-1655.

Krishna, B. S., & Semple, M. N. (2000). Auditory temporal processing: responses to sinusoidally

amplitude-modulated tones in the inferior colliculus. Journal of Neurophysiology, 84(1), 255–273.

Krull, V., & Strickland, E. A. (2008). The effect of a precursor on growth of forward

masking. The Journal of the Acoustical Society of America, 123(6), 4352-4357.

Kwan, T. J. M., Zilany, M. S. A., Davies-Venn, E., & Abdul Wahab, A. K. (2019). Modeling the

effects of medial olivocochlear efferent stimulation at the level of the inferior colliculus.

Experimental Brain Research, 237(6), 1479–1491. https://doi.org/10.1007/s00221-019-05511-4

Lehky, S. R. (2010). Decoding poisson spike trains by gaussian filtering. Neural Computation,

22(5), 1245–1271.

Lauer, A. M., Jimenez, S. V., & Delano, P. H. (2022). Olivocochlear efferent effects on

perception and behavior. Hearing Research, 419, 108207.

Lee, D., & Lewis, J. D. (2023). Inter-Subject Variability in the Dependence of Medial-

Olivocochlear Reflex Strength on Noise Bandwidth. Ear and Hearing, 44(3), 544-557.

Liberman, M. C. (1988). Response properties of cochlear efferent neurons: monaural vs. binaural

stimulation and the effects of noise. Journal of neurophysiology, 60(5), 1779-1798.

Liberman, M. C. (1978). Auditory-nerve response from cats raised in a low-noise chamber. The

Journal of the Acoustical Society of America, 63(2), 442–455.

Liberman, M. C., & Guinan Jr, J. J. (1998). Feedback control of the auditory periphery: anti-

masking effects of middle ear muscles vs. olivocochlear efferents. Journal of Communication

Disorders, 31(6), 471–482.

Lichtenhan, J. T., Wilson, U. S., Hancock, K. E., & Guinan Jr, J. J. (2016). Medial olivocochlear

efferent reflex inhibition of human cochlear nerve responses. Hearing research, 333, 216-224.

Lopez-Poveda, E. A. (2018). Olivocochlear efferents in animals and humans: from anatomy to

clinical relevance. Frontiers in neurology, 9, 197.

Mao, J., Vosoughi, A., & Carney, L. H. (2013). Predictions of diotic tone-in-noise detection

based on a nonlinear optimal combination of energy, envelope, and fine-structure cues. The Journal

of the Acoustical Society of America, 134(1), 396–406.

May, B. J., & Sachs, M. B. (1992). Dynamic range of neural rate responses in the ventral cochlear

nucleus of awake cats. Journal of neurophysiology, 68(5), 1589-1602.

Nelson, P. C., & Carney, L. H. (2004). A phenomenological model of peripheral and central

neural responses to amplitude-modulated tones. The Journal of the Acoustical Society of

America, 116(4), 2173-2186.

Oertel, D., Wright, S., Cao, X.-J., Ferragamo, M., & Bal, R. (2011). The multiple functions of T

stellate/multipolar/chopper cells in the ventral cochlear nucleus. Hearing Research, 276(1–2), 61–

69.

Olsen, W. O. (1998). Average speech levels and spectra in various speaking/listening conditions.

American Journal of Audiology, 7:21-25.

Rabbitt, R. (2023) The MOC efferent system acts as a control parameter for outer hair cell

dynamic stability and power output. Abstract, ARO, 46:544.

Rabbitt, R., and Bidone, T.C. (2023) A parametric blueprint for optimum cochlear outer hair cell

design, Journal of the Royal Society Interface, 20(199) 20220762.

Rahman, M., Willmore, B. D. B., King, A. J., & Harper, N. S. (2019). A dynamic network model

of temporal receptive fields in primary auditory cortex. PLoS Computational Biology, 15(5),

e1006618.

Recasens, D. (1984). Vowel-to-vowel coarticulation in Catalan VCV sequences. The Journal of

the Acoustical Society of America, 76(6), 1624–1635.

Recasens, D. (2018). Coarticulation. In Oxford Research Encyclopedia of Linguistics.

https://doi.org/10.1093/acrefore/9780199384655.013.416.

Rhode, W. S., & Kettner, R. E. (1987). Physiological study of neurons in the dorsal and

posteroventral cochlear nucleus of the unanesthetized cat. Journal of neurophysiology, 57(2), 414-

442.

Romero, G. E., & Trussell, L. O. (2021). Distinct forms of synaptic plasticity during ascending

vs descending control of medial olivocochlear efferent neurons. Elife, 10, e66396.

Roverud, E., & Strickland, E. A. (2010). The time course of cochlear gain reduction measured

using a more efficient psychophysical technique. The Journal of the Acoustical Society of America,

128(3), 1203–1214.

Russell, I. J., & Murugasu, E. (1997). Medial efferent inhibition suppresses basilar membrane

responses to near characteristic frequency tones of moderate to high intensities. The Journal of the

Acoustical Society of America, 102(3), 1734-1738.

Ryugo, D. K. (2008). Projections of low spontaneous rate, high threshold auditory nerve fibers

to the small cell cap of the cochlear nucleus in cats. Neuroscience, 154(1), 114–126.

Schofield, B. R. (2011). Central descending auditory pathways. In Auditory and vestibular

efferents (pp. 261–290). Springer.

Smalt, C. J., Heinz, M. G., & Strickland, E. A. (2014). Modeling the time-varying and level-

dependent effects of the medial olivocochlear reflex in auditory nerve responses. JARO - Journal of

the Association for Research in Otolaryngology, 15(2), 159–173. https://doi.org/10.1007/s10162-

013-0430-z

Smith, S. B., Lichtenhan, J. T., & Cone, B. K. (2017). Contralateral inhibition of click-and chirp-

evoked human compound action potentials. Frontiers in neuroscience, 11, 189.

Sun, X.-M. (2008). Contralateral suppression of distortion product otoacoustic emissions and the

middle-ear muscle reflex in human ears. Hearing Research, 237(1–2), 66–75.

Tan, Q., & Carney, L. H. (2003). A phenomenological model for the responses of auditory-nerve

fibers. II. Nonlinear tuning with a frequency glide. The Journal of the Acoustical Society of America,

114(4), 2007–2020.

Umeda, N. (1977). Consonant duration in american english. The Journal of the Acoustical

Society of America, 61(3), 846–858.

Viemeister, N. F., & Bacon, S. P. (1982). Forward masking by enhanced components in

harmonic complexes. The Journal of the Acoustical Society of America, 71(6), 1502–1507.

Warr, W. B. (1992). Organization of olivocochlear efferent systems in mammals. The

Mammalian Auditory Pathway: Neuroanatomy, 410–448.

Warren III, E. H., & Liberman, M. C. (1989). Effects of contralateral sound on auditory-nerve

responses. I. Contributions of cochlear efferents. Hearing Research, 37(2), 89–104.

Westerman, L. A., & Smith, R. L. (1984). Rapid and short-term adaptation in auditory nerve

responses. Hearing Research, 15(3), 249–260.

Westerman, L. A., & Smith, R. L. (1987). Conservation of adapting components in auditory-

nerve responses. The Journal of the Acoustical Society of America, 81(3), 680–691.

Yasin, I., Drga, V., Liu, F., Demosthenous, A., & Meddis, R. (2020). Optimizing Speech

Recognition Using a Computational Model of Human Hearing: Effect of Noise Type and Efferent

Time Constants. IEEE Access, 8, 56711–56719. https://doi.org/10.1109/ACCESS.2020.2981885

Yasin, I., Liu, F., Drga, V., Demosthenous, A., & Meddis, R. (2018). Effect of auditory efferent

time-constant duration on speech recognition in noise. The Journal of the Acoustical Society of

America, 143, EL112-EL115

Ye, Y., Machado, D. G., & Kim, D. O. (2000). Projection of the marginal shell of the

anteroventral cochlear nucleus to olivocochlear neurons in the cat. Journal of Comparative

Neurology, 420(1), 127–138.

Young, E. D., & Sachs, M. B. (1979). Representation of steady-state vowels in the temporal

aspects of the discharge patterns of populations of auditory-nerve fibers. The Journal of the

Acoustical Society of America, 66(5), 1381-1403.

Zhang, X., Heinz, M. G., Bruce, I. C., & Carney, L. H. (2001). A phenomenological model for

the responses of auditory-nerve fibers: I. Nonlinear tuning with compression and suppression. The

Journal of the Acoustical Society of America, 109(2), 648-670.

Zilany, M. S. A., & Bruce, I. C. (2006). Modeling auditory-nerve responses for high sound

pressure levels in the normal and impaired auditory periphery. The Journal of the Acoustical Society

of America, 120(3), 1446–1466.

Zilany, M. S. A., Bruce, I. C., & Carney, L. H. (2014). Updated parameters and expanded

simulation options for a model of the auditory periphery. The Journal of the Acoustical Society of

America, 135(1), 283–286.

Zilany, M. S. A., Bruce, I. C., Nelson, P. C., & Carney, L. H. (2009). A phenomenological model

of the synapse between the inner hair cell and auditory nerve: long-term adaptation with power-law

dynamics. The Journal of the Acoustical Society of America, 126(5), 2390–2412.

FIG. 1. (color online) Schematic illustration of the peripheral afferent (black arrows) and MOC efferent (red arrows) pathways. Here for a simple presentation we have shown the afferent pathways on the left side and the efferent pathways on the right side, but anatomically both pathways exist on both sides of the brainstem.

FIG. 2. (color online) Effect of MOC efferent activity on IHC input-output function. Left panel: The effective modulation depth in IHC output voltage is limited due to the saturation. Right panel: with the same input pressure, effective modulation depth is increased due to the MOC efferent activity and decrease in gain.

FIG. 3. (color online) Schematic illustrating overall structure of the new model components (red) with respect to the Zilany et al. (2014) AN model and Mao et al. (2013) IC/CN model (black). After (Zilany et al., 2009) and (Farhadi et al., 2021). The new model components include the two feedback signals from IC and WDR cells to the MOC unit (dashed red box), where the two input signals are scaled and summed before going through a first-order low-pass filter. The low-pass filtered signal goes to the rational input-output MOC function, which maps the input signal to a cochlear-gain scaler between 0 and 1, for that time sample.

FIG. 4. (color online) The MOC efferent model diagram with intermediate responses at different levels of auditory periphery in response to tone-in-noise stimulus. The stimulus (black) is initially a wide band noise; after 200 ms a tone is added to the noise for a duration of 300 ms. The response of the model AN (HSR) stage (blue) shows that during the noise-only stimulus (first 200 ms) the fluctuation depth increases over time as the gain decreases (green), and as a result the IC (purple) rate increases. After the addition of the tone (200 -500 ms) the fluctuation depths in the AN HSR response is reduced, resulting in a drop in IC response rate. As the In1 input to the MOC block (on the right side of this figure) decreases, the gain starts to recover (green). After the offset of the tone (500-700 ms) the gain decreases again, and the AN fluctuations and IC rate increase.

FIG. 5. (color online) Distribution of MTF classes of the IC neurons in the physiological dataset (Carney et al., 2014) using the MTF-categorization method of Kim et al. (2020) (D. O. Kim et al., 2020)

FIG. 6. (color online) A-F) Six examples of BE IC neuron smoothed responses to AM noise stimulus. The left-hand panel in each example is the MTF for AM noise stimuli; the vertical green lines indicate BMF. The right-hand panels show smoothed PSTHs that illustrate the time course of the rate during responses to AM noise stimuli with a modulation frequency near each neuron's BMF and a range of modulation depths (see legend).

FIG. 7. Percentage BE IC neurons with increasing rate over the time course of wideband AM

noise stimuli.

FIG. 8. (color online) Distribution of the fit values of, A) time constant (τ_{MOC}), B) the rational

function parameter (B), and C) the IC scaler (K_{IC}) for the model for 29 neurons in this study for which

the rates increased during the SAM stimuli, the MTF type was BE, and the modulating frequency of the

stimulus matched the BMF of the cell.

FIG. 9. (color online) Correlations between the physiology and models A) without efferents, B) with

efferents, with all parameters individually identified for each neuron, and C) with efferent parameters

fixed at the median of the distributions.

FIG. 10. A) Physiological data from a BE IC cell in awake rabbit, and IC model responses to AM noise with modulation depth of -10 dB B) without and C) with efferent activation. The CF and BMF of the model were matched to the example neuron (BMF is 50 Hz and CF is 3650 Hz in this example neuron) the median value for the model parameters were used (Fig. 9-C).

FIG. 11. AN and model responses to tones at CF: A) Unit 43 : CF = 1.82 kHz, 55 dB SPL, SR = 60.6

s/sec; B) Unit 41: CF = 10.34 kHz, 30 dB SPL, SR = 51.7 s/sec; C, D) Responses to the same tones for

the model without efferents, and E, F) with MOC efferents. For all model simulations (C to F) the AN

model type was HSR with CFs matching the AN fibers in the physiological study. The stimulus sound

level was matched to stimuli for the physiological data from Kiang (1965, permission requested.)

FIG. 12. A) Actual neuron physiological data from gerbil from Westerman and Smith (1987, with permission) in response to increase in tone level. The AN model response to the amplitude increment response paradigm B) without efferent system C) with MOC efferent system

FIG. 13. (color online) A) Synchrony to the envelope of an AM tone at CF for an AN fiber with CF = 20 kHz (Joris & Yin, 1992; permission requested) and for an HSR model fiber with matching CF with and without efferent activation. Modulation frequency of 100 Hz; level = 49 dB SPL. B) IC model with and without activation of the MOC efferent system and IC physiology synchronization-modulation depth plots for responses to AM noise stimulus at CF 5330 Hz, BMF 80 Hz, modulation frequency 64 Hz and stimulus level 36 dB SPL.