Subcortical Auditory Model including Efferent Dynamic Gain Control

with Inputs from Cochlear Nucleus and Inferior Colliculus

Afagh Farhadi,[1] Skyler G. Jennings,[2] Elizabeth A. Strickland,[3] and Laurel H. Carney[4,a]

[1] Department of Electrical and Computer Engineering, University of Rochester, Rochester, New York 14642, USA

[2] Department of Communication Sciences and Disorders, University of Utah, Salt Lake City, Utah 84112, USA

[3] Department of Speech, Language, and Hearing Sciences, Purdue University, West Lafayette, Indiana 47907,

USA

[4] Departments of Biomedical Engineering and Neuroscience, University of Rochester, Rochester, New York 14642,

USA

Abstract

We developed an auditory model with a time-varying, gain-control signal based on the physiology of

the efferent system and the sub-cortical neural pathways. The medial olivocochlear (MOC) efferent

stage of the model receives excitatory projections from both fluctuation-sensitive model neurons of

the inferior colliculus (IC) and wide-dynamic-range model neurons of the cochlear nucleus. The re-

sponse of the model MOC stage dynamically controls cochlear gain via simulated outer hair cells. In

response to amplitude-modulated (AM) noise, firing rates of most IC neurons with band-enhanced

modulation transfer functions in awake rabbits increase over a time course consistent with the dy-

namics of the MOC efferent feedback. These changes in the rates of IC neurons in awake rabbits

were employed to adjust the parameters of the efferent stage of the proposed model. Responses of

the proposed model to AM noise were able to simulate the increasing IC rate over time, while the

model without the efferent system did not show this trend. The proposed model with efferent gain

    [a] Laurel_Carney@URMC.Rochester.edu

23 control provides a powerful tool for testing hypotheses, shedding insight on mechanisms in hearing,

24 specifically those involving the efferent system.

I.   INTRODUCTION

The descending auditory pathway, or efferent system, is as large as the ascending pathway in

terms of number of projections, but this part of the system not been as extensively studied as the

ascending pathway. The efferent system consists of several feedback projections (Guinan, 2006;

Warr, 1992) spanning all levels of the auditory pathway, from the auditory cortex to the cochlea. The

focus of this study is the medial olivocochlear (MOC) system, which includes projections from

MOC neurons to the outer hair cells and directly controls cochlear gain. Although several studies

suggest the critical role of the MOC efferent system for interpreting data from psychoacoustic

measures (Lopez-Poveda, 2018; Jennings, 2021; Lauer et al., 2022), it is still unclear the extent to

which gain control by the MOC efferent system is involved in hearing. Understanding the role of

the efferent system in auditory processing is essential to gain a comprehensive understanding of au-

ditory function. In this study, we develop a computational model for the sub-cortical auditory sys-

tem, providing a tool for exploring efferent mechanisms of cochlear gain control.

Despite several studies of the physiology of the efferent system (Guinan, 2006; Gummer et

al., 1988; Liberman & Guinan, 1998), many aspects of this system are not well understood, such as

the effects of anesthesia, the role of higher-level projections, and the independent effects of the

MOC and middle-ear muscle reflexes. This gap in understanding is potentially explained by its com-

plexity and the limited experimental methods for understanding the efferent system (Schofield,

2011). Most of the information available is based on a relatively small number of recordings from

single neurons located deep in the brainstem in anesthetized animals (Guinan, 2018); however, anes-

thesia suppresses MOC responses (Aedo et al., 2015; Chambers et al., 2012; Guitton et al., 2004).

Noninvasive methods used to study MOC effects on cochlear gain include measurements of either

otoacoustic emissions (OAEs) (Guinan, 2006),the cochlear microphonic (Jennings & Aviles, 2023;

Jamos et al., 2020, 2021), or the compound action potential (Lichtenhan et al. 2016; Smith et al.,

2017), with and without MOC activation by contralateral broadband noise. These methods provide

useful insights about the efferent system; however, they do not provide details about the contribu-

tions of higher-level projections in the pathway, such as those from the IC or auditory cortex to the

MOC (Delano et al, 2007). Furthermore, care must be taken to separate effects of the middle-ear

muscle reflex on OAEs when studying the MOC efferent system (Sun, 2008, Guinan, 2018). Here

we propose a model of the MOC efferent system that can help in designing future physiological and

psychophysical experiments for studying efferent function.

A new framework for auditory coding proposes an explicit role for the efferent system. Car-

ney (2018) suggests that low-frequency temporal fluctuations in auditory-nerve (AN) responses can

be a reliable cue for auditory perception. It is often assumed that AN average-rate profiles encode

the spectrum of complex sounds; however, the majority of AN fibers, the high-spontaneous-rate

(HSR) fibers, have average rates that are saturated at conversational speech levels (55–65 dB SPL,

Olsen, 1998). Therefore, in many conditions, average discharge rates of HSR AN fibers do not con-

tain enough information to explain perception of complex sounds (Bharadwaj et al., 2014; Carney,

2018; Liberman, 1978). On the other hand, temporal fluctuations of HSR AN responses, referred to

as neural fluctuations, have robust information at conversational speech levels, potentially encoding

peaks and valleys in the stimulus spectrum because the fluctuation depths are smaller for AN fibers

tuned near peak frequencies and larger for other frequency channels (Carney et al., 2015; Carney,

2018). If neural fluctuations play a key role in encoding complex sounds, then these fluctuations may

be involved in the efferent gain-control system to maintain contrasts in the neural-fluctuation pro-

file. Interestingly, neurons in the auditory midbrain (inferior colliculus, IC) are sensitive to low-fre-

quency (i.e., < 100Hz) fluctuations of their inputs (Joris et al. 2004; Krishna & Semple, 2000), and

the IC projects to MOC neurons (Huffman & Henson 1990; Delano et al., 2007).

The MOC efferent system receives several convergent inputs; the model presented here fo-

cuses on subcortical pathways, specifically inputs from the IC and cochlear nucleus (CN). MOC

neurons receive descending projections from IC cells in the midbrain and exhibit band-pass modula-

tion transfer functions (MTFs) that are possibly inherited from these inputs (Gummer et al., 1988a;

Huffman & Henson, 1990; Schofield, 2011). MOC neurons also receive ascending projections from

cell types in the CN that have wide dynamic ranges (WDR), including T-stellate cells (Blackburn &

Sachs, 1990; Guinan, 2018; Romero & Trussell, 2021) and neurons in the small cell cap, which re-

ceive low- and medium-spontaneous-rate AN inputs (Ye et al., 2000; Fekete et al., 1984) (Fig. 1).

Although some CN neurons have bandpass MTFs, they tend to have broad, shallow peaks and best

FIG. 1. (color online) Schematic illustration of the peripheral afferent (black arrows) and MOC efferent (red arrows) pathways. Here for a simple presentation we have shown the afferent pathways on the left side and the efferent pathways on the right side, but both pathways exist on both sides of the brainstem.

modulation frequencies (BMFs) that are higher than BMFs for neurons in the IC (Nelson and Car-

ney, 2004; Rhode and Greenberg, 1994). Either source (i.e., IC or CN) of modulation tuning, or

even modulation tuning that could arise *de novo* at the level of the MOC, could contribute to the

MOC sensitivity to fluctuations. Nevertheless, a parsimonious explanation is that MOC neurons in-

herit their bandpass MTFs from IC inputs rather than from CN inputs. For the proposed model, IC

projections to the MOC provide neural-fluctuation information to the MOC gain-control system, as

follows: 1) IC neurons that are excited by fluctuations (band-enhanced (BE) IC cells) effectively re-

duce cochlear gain in response to fluctuating inputs, 2) this reduction in cochlear gain increases AN

fluctuation depth by effectively increasing the IHC dynamic range , 3) this increase in AN fluctua-

tion depth results in a further increase in IC activity until the gain stops decreasing, either because a

minimum cochlear gain is reached or when fluctuation-driven feedback is balanced by WDR driven

feedback (described below). This fluctuation-driven feedback loop, in which BE IC activity ulti-

mately reinforces BE IC activity, is effectively a positive feedback loop. Note that, a decrease in AN

fluctuation depth results in positive feedback that works in the opposite direction, that is, a reduc-

tion in IC responses ultimately leads to a further reduction in IC responses.

The positive-feedback mechanism described above could contribute to spectral coding of

complex sounds, as follows (see Carney, 2018): 1) AN frequency channels tuned near local peaks in

the stimulus spectrum have responses that are "captured" by the spectral peak, and thus have rela-

tively small fluctuations (Deng et al., 1987; Delgutte and Kiang, 1984; Young and Sachs, 1979). Con-

sequently, for these frequency channels, BE IC cells would have lower response rates than adjacent

channels tuned to spectral troughs. Activity of MOC neurons reduces cochlear gain in a fre-

quency/place-specific manner (Guinan, 2018); therefore, input to the MOC from BE IC channels

near a spectral peak would be relatively small, as compared to that from channels within spectral

troughs that are driven by large fluctuations. The relatively higher cochlear gain for channels near

spectral peaks would drive IHCs closer to saturation, resulting in further reduction in the neural

fluctuations in AN HSR responses over time (i.e., positive feedback). 2) For frequency channels

tuned away from spectral peaks, AN fluctuations are larger and BE IC cells therefore have higher

response rates. The higher rates in the BE IC input to the MOC would result in a reduction in coch-

lear gain, reducing IHC saturation and further increasing fluctuation amplitudes in the AN response

in the frequency channels tuned away from spectral peaks. Overall, the IC input to MOC neurons

provides a positive feedback that would enhance the fluctuation contrast across AN channels by de-

creasing the fluctuating amplitude in frequency channels near spectral peaks and increasing the fluc-

tuations in other channels. This feedback potentially enhances the neural representation of spectral

peaks and valleys at the level of the IC (see Figs. 2 and 3 in Carney, 2018).

In the proposed model, the other input to the MOC stage is from the WDR neurons in the

CN, which carry the stimulus sound-level information. This level-dependent input to the MOC acts

as a negative feedback system, i.e., an increase in stimulus level would increase activity of the WDR

neurons which excite MOC neurons, ultimately reducing cochlear gain. This negative feedback is hy-

pothesized to keep the operating point of the saturating IHC transducer function near its knee

point, to ensure sufficient baseline fluctuation contrast across frequency channels. The IC feedback

signal, described above, would then enhance this baseline contrast. If there were no contribution to

gain control from the WDR cells, the AN channels could all have fluctuating or flat responses when

exposed to stimuli with low or high levels, respectively, regardless of the peaks and valleys in the

stimulus spectrum. Both extremes would reduce the contrast in fluctuation depth across IC fre-

quency channels.

According to the neural-fluctuation profile framework and the feedback mechanisms of the

MOC efferent system described above, sustained fluctuations in a stimulus could cause a progressive

decrease in cochlear gain over time. As a result, in response to amplitude-modulated (AM) noise, the

average rate of BE IC neurons is expected to increase over a time course of 100-200 ms due to the

MOC-related reduction in cochlear gain. The rationale for this prediction is that the low-frequency

fluctuations of AN fiber responses to modulated noise stimuli excite IC neurons with BE MTFs. BE

IC neurons are assumed to excite MOC cells, and MOC activity decreases cochlear gain. Reduction

in cochlear gain effectively decreases the slope of the IHC transduction nonlinearity and therefore

increases the effective modulation depth at the output of the IHC (Fig. 2), ultimately increasing the

BE IC response. Thus, IC rates would increase over time until the efferent control system is stabi-

lized. Interestingly, re-examination of IC responses to AM noise in awake rabbits (Carney et al.,

2014) supported this hypothesis and revealed rates that increased over a time course that is con-

sistent with the dynamics of MOC efferent gain control (Farhadi et al., 2021). This increase in IC

FIG. 2. (color online) Effect of MOC efferent activity on IHC input-output function. Left panel: The effective modulation depth in IHC output voltage is limited due to the saturation. Right panel: with the same input pressure, effective modulation depth is increased due to the MOC efferent activity and decrease in gain.

rate is an unexpected effect in neural responses, which typically adapt and therefore exhibit a de-

crease, rather than increase, in the neural rate over time. We quantified the increase in IC average

rate over the time course of responses to AM noise and used that information to adjust the parame-

ters of the MOC efferent model proposed in this work.

Here, we refine and test an AN and subcortical model with both fluctuation- and WDR-driven gain

control (Farhadi et al., 2021). We first introduce the novel control system used to implement the

MOC efferent pathway. Next, we describe how the parameters of the MOC efferent model were ad-

justed based on a physiological dataset from a previous study of IC responses to AM noise from

awake rabbits (Carney et al., 2014). We then show that the model with efferents outperforms a

model without efferents in simulating the dynamics of the IC response to AM noise stimuli. This

finding supports the hypothesis that the MOC efferent system is a potential mechanism underlying

the increase in rate of IC cells over the time course of AM noise. Implications of the proposed

model for responses to other sounds, and interactions with other neural mechanisms involved in

long-term changes in response rates, will be discussed.

II.   **METHODS**

We adapted existing models that were designed to simulate responses of AN fibers (Zilany et al.,

2009, 2014) and IC cells (Mao et al., 2013) to implement the proposed model with MOC efferent

gain control. First, we briefly introduce the original AN and IC models. Then, we describe the modi-

fications that were applied, including changes to the structure of the existing models and new exten-

sions added to simulate the MOC efferent system. Finally, we introduce the methods used to esti-

mate the MOC efferent-system model parameters.

A. Existing models

For the original Zilany et al. (2009, 2014) AN model, the stimulus first passes through a filter that simulates the middle-ear transfer function. The output of the middle-ear filter is the input to the cochlear-model stage (Fig. 3). Cochlear tuning is modeled using two filters, a relatively sharp chirping filter in the signal path tuned at the characteristic frequency (CF) and a wider bandpass filter in the feedforward control path tuned slightly higher than CF (Zhang et al., 2001; Tan & Carney, 2003; Zilany & Bruce, 2006). The output of the control-path filter and following OHC model stage adjusts the time constant (and thus the gain and bandwidth) of the chirping filter. The cochlear-gain parameter (C_{OHC}) in the original model is set to one to simulate normal hearing. The IHC is modeled with a nonlinear transduction function followed by a low-pass filter. IHC sensitivity (C_{IHC}) is set to 1 to simulate normal-hearing IHC function. The AN model is based on human Q10 values (Shera et al., 2002).

We used the BE IC model from Mao et al. (2013), which consists of a band-pass filter centered at the BMF of the IC cell. The response of a simulated HSR AN model was the input to the IC model; this structure is a simplified version of an IC model for AM tuning that also included a CN stage (Nelson and Carney, 2004).

B. Proposed model with MOC efferents

One of the challenges of including the efferent system in the computational AN model was to reconfigure the implementation of the model to work sample by sample. In previous IC model implementations (e.g., Mao et al., 2013), the AN model output for the entire stimulus waveform served as the input to the IC stage. In the sample-by-sample configuration of the proposed efferent model (Fig. 3), a new value of $C_{OHC}(t)$ was applied to each sample to adjust cochlear gain based on the output of a new stage: the model MOC (Fig. 3, dashed red box). The dynamics of the MOC system were modeled with a first-order low-pass filter, thus the output of the MOC model was a function of the current and previous time samples of the MOC input signal, which was a combination of the

IC-model rate function (time-varying rate, in spikes/sec) and the CN WDR response provided by a

LSR AN-model rate-function. For simplicity, we used the LSR AN model response to represent all

WDR inputs to the MOC, such as the T-stellate cells in the anteroventral cochlear nucleus (Oertel et

al., 2011; Romero & Trussell, 2021) and cells in the small cell cap of the CN that receive exclusive

inputs from LSR and MSR AN fibers (Fekete et al., 1984; Ryugo, 2008). In the sample-by-sample

implementation, the previous states of all the filters of the AN model were preserved in order to

process each time sample of the simulated model response.

In the proposed model, the output of the MOC efferent stage controlled the gain parameter

based on the current and previous samples of the neural signals at the input to this stage. Specifi-

FIG. 3. (color online) Schematic illustrating overall structure of the new model components (red) with respect to the Zilany et al. (2014) AN model and Mao et al. (2013) IC/CN model (black) (adapted from Zilany et al., 2014, with permission of Acoustical Society of America.). The Zilany model includes the feedforward blocks simulating middle-ear filter, cochlear filtering (labeled C1, C2, and Control Path Filters) and two stages consisting of filters and nonlinearities for simulation IHC and OHC units (boxes marked by black dashed lines). The new model components include the two feedback signals from IC and WDR cells to the MOC stage (dashed red box), where the two input signals are scaled and summed before going through a first-order low-pass filter. The low-pass filtered signal goes to the rational input-output MOC function, which maps the input signal to a cochlear-gain scaler between 0 and 1, for that time sample.

cally, the output of the MOC stage, a scaler between 0 to 1, was multiplied by the OHC gain param-

eter (C$_{OHC}$) to modulate the cochlear gain. This multiplication occurred for every time sample. The

model with this new sample-by-sample configuration was tested to ensure that it matched the re-

sponse of the original model when the efferent stage was deactivated.

The two inputs to the proposed MOC model (Fig. 3, red) were the descending IC feedback sig-

nal and the ascending WDR signal, which were combined to determine the degree of cochlear gain

reduction. Specifically, the excitatory input to the MOC stage was the sum of the IC and the WDR

rate functions. A constant scalar, K$_{IC}$, was applied to the IC rate signal to approximately balance the

amplitudes of the two inputs to the MOC. The AN model has higher average rates than the IC

model, and combining these signals without scaling would result in an input signal to MOC that

would not be not sensitive to changes in the IC model response. The MOC system was modeled

with a low-pass filter representing dynamics of the MOC efferent system, followed by a decaying ra-

tional function (Eqn. 1) that mapped the MOC inputs to an output signal that modulated the coch-

lear-gain parameter, C$_{OHC}$, on a sample-by-sample basis. The rational function, chosen to be second-

order to ensure asymptotic behavior for both small and large input signals, was described by

$$M_{out}(t) = \frac{1}{1 + [B \times \{M_{in}(t)\}^2]} \quad , \qquad (Eqn.\,1)$$

where $M_{in}(t)$ is the sum of the responses from the WDR and IC paths to the MOC unit after low-

pass filtering, and B is a constant that adjusts the shape of MOC input-output function (Fig. 3). The

optimization of the value of parameter B is discussed later (Section C of the Methods).

Figure 4 (upper panel) shows the intermediate responses at each level of the composite

model to a tone-in-noise stimulus. The first 200 ms of the stimulus is noise only (Fig. 4, black). The

BE IC response to this initial noise is robust (Fig. 4, purple); because of the fluctuation in AN HSR

rates (Fig. 4, blue), thus driving the MOC model and decreasing the cochlear gain (Fig. 4, green).

During the first 200 ms the gain decreases over time and as a result the fluctuations in the AN HSR

response increase over time (Fig. 4, blue- see also Fig 4A-D for zoomed-in views of AN HSR re-

sponses corresponding to labelled portions in Fig. 4, upper panel). The increase in depth of fluctua-

tions in the AN HSR response over time (Figs. 4C, D) resulted in an effective decrease in cochlear

gain from the MOC stage and subsequent increase in IC rate over time (Fig. 4, purple). Between 200

and 500 ms, a tone at the model CF (4 kHz) was added to the noise, resulting in saturation of the

IHC (not shown) and flattening the neural fluctuations in the AN HSR response (Fig. 4, blue). As a

result of the reduced AN HSR neural fluctuation depths, the BE IC rate response decreased. The

reduced IC rate resulted in a weaker MOC input and thus a relative increase in cochlear gain (Fig. 4,

green). Note that the mean rate of the AN HSR fiber was not changed appreciably by the addition

of the tone, due to rate saturation; however, the model WDR rate function increased during presen-

tation of the tone. This increase in rate of the WDR response over the time course of the tone oc-

curred because the average rate was not saturated for WDR neurons. After the tone ended, the IHC

was no longer saturated, AN fluctuations reappeared, and the IC response increased. The increase in

the IC response excited the MOC stage, which resulted in a reduction in cochlear gain. The changes

in the WDR response rate (Fig.4, red) also influenced cochlear gain. As described above, the WDR

signal maintains the IHC operating point such that the IC response has an effect on increasing spec-

tral contrast via changes in cochlear gain. In contrast to the CF channel tuned to the tone frequency

(Fig. 4), AN fibers tuned away from the tone would have responses that were dominated by the

noise masker; at moderate sound levels, these responses would have strong fluctuations. In sum-

mary, the introduction of a tone in an ongoing noise results in a flat AN response that is temporally

flanked by fluctuating responses and thereby may provide a cue for detecting a tone in noise. The

responses of the model without efferent gain control did not show changes over time during each

portion of the stimulus, as expected (Fig.4, upper panel left, and Figs. 4A, B).

FIG. 4. (color online) The MOC efferent model diagram with intermediate responses at different levels of auditory periphery in response to tone-in-noise stimulus. The stimulus (black) is initially a wide band noise; after 200 ms a tone is added to the noise for a duration of 300 ms. The response of the model AN (HSR) stage (blue) shows that during the noise-only stimulus (first 200 ms) the fluctuation depth increases over time as the gain decreases (green), and as a result the IC (purple) rate increases. After the addition of the tone (200 -500 ms) the fluctuation depth in the AN HSR response is reduced, resulting in a drop in IC response rate. As the In1 input to the MOC block (on the right side of this figure) decreases, the gain starts to recover (green). After the offset of the tone (500-700 ms) the gain decreases again, and the AN fluctuations and IC rate increase.

C. Adjusting the parameters of the MOC efferent model

Parameters of the MOC efferent model include those of the MOC input/output function, B

(Eqn.1, Fig. 4), the scaler constant for IC rate (K_{IC}), and the low-pass filter (LPF) time constant (cut-

off frequency). We adjusted these parameters based on an existing physiological dataset that con-

tained IC responses in awake rabbits to AM wideband noise (Carney et al., 2014).

Stimuli

The stimulus for both the physiological dataset and the model simulation during the parameter

fits was a sinusoidally amplitude-modulated (SAM) wideband noise (100 Hz to 20 kHz) with modu-

lation depth that varied from -30 to 0 dB (fully modulated) in 5 dB steps, and an unmodulated wide-

band noise with the same bandwidth. The modulation frequency was matched to the best modula-

tion frequency (BMF) of the recorded cells, which ranged from 50 to 100 Hz. The stimulus spec-

trum level was 36 dB re 20μPa (RMS: 76 dB SPL overall level). The duration of the stimuli was 500

ms, including 50-ms raised-cosine ramps.

Physiological data and analysis

The physiological dataset included previously published extracellular, tetrode recordings of re-

sponses in the central nucleus of the IC in three awake rabbits. Stimuli were presented to the contra-

lateral ear. Details of the physiological methods can be found in Carney et al. (2014). Briefly, IC cells

were classified based on their MTFs into BE, band-suppressed (BS), hybrid, flat, and unusual types

(Kim et al., 2015, 2020) (Fig. 5). BE IC cells are excited over a band of modulation frequencies,

whereas IC BS cells are suppressed over a band of modulation frequencies (Kim et al., 2020). Hybrid

cells have rates that are enhanced over one band of modulation frequencies, and suppressed over

another range (Kim et al., 2020). The focus of this study was on BE cells because this IC MTF type

was hypothesized by Gummer et al., (1988b) to project to MOC neurons, based on the BE MTFs

reported for MOC neurons. MTF shapes were classified similar to Kim et al. (2020), using a crite-

rion ratio of 1.2 peak MTF rate to the reference rate response to an unmodulated wideband noise

which yielded approximately equal numbers of BE and BS MTFs (Fig. 5). The frequency of the peak

rate in the MTF identifies the cell's BMF. The physiological responses used in this study had stimu-

lus modulation frequencies that were within an octave of the recorded cell's BMF.

To analyze the physiological responses to AM noise, a Gaussian filter was used to smooth the

spike trains to avoid aliasing introduced by PSTH binwidth (Lehky, 2010). The standard deviation of

the Gaussian filter was inversely proportional to each cell's BMF; the number of points in the filter

was six times the standard deviation of the Gaussian window. Responses were averaged over 50 rep-

etitions of the stimulus.

FIG. 5. (color online) Distribution of MTF classes of the IC neurons (N=193) in the physiological dataset

(Carney et al., 2014) using the MTF-categorization method of Kim et al. (2020) (D. O. Kim et al., 2020)

Trends in firing rate over the course of the response, after an initial 200 ms to exclude the onset

response, were characterized using a simple linear regression. Based on the efferent model frame-

work, the BE IC rates were hypothesized to increase over time as a result of reduction in cochlear

gain and increase in the temporal fluctuation depths in AN responses. The sign of the linear model's

slope indicated whether the response increased or decreased over time. BE IC responses with rates

that increased over time were used to find the parameters in the MOC efferent model by maximiz-

ing the correlation between the BE IC spiking rate and the model responses to a stimulus with a

modulation depth of -10 dB. A modulation depth of -10 dB was chosen here because the majority of

the IC neurons had strong increases in rate over time at this modulation depth as compared to

higher modulation depths, for which IC rates sometimes saturated. A brute-force method was used

to search a reasonable range (K_{IC} between 1 to 50, B between 0.001 to 0.1, and τ_{MOC} between 10 ms

to 500 ms) of parameter values and find a set of values that maximized the correlation between the

model response and the physiological data over the analysis window. Parameters were estimated for

each neuron in the dataset. We simultaneously fit the time constant, τ_{MOC}, the rational function pa-

rameter, B (Eqn. 1), and the IC constant scaler, K_{IC}. A 300-ms -duration analysis window was used

for both physiological and model responses. The analysis window for model responses started at 200

ms in order to exclude the onset response, as was done for the physiological responses, and contin-

ued until the end of stimulus. Properties of the model such as CF, BMF, and modulation frequency

were matched to each cell in the physiological dataset. Based on the parameter value fits for each of

the 33 neurons in the dataset, a distribution of the parameters was established, and the medians of

the distributions were chosen for the final model parameter values. The sensitivity of the model to

the parameter values was studied by comparing the average correlation between the physiological

and the model responses when each model parameter was either set to the value fit to each neuron

or to the median parameter value for the population.

III.   RESULTS

Section A below reviews our hypothesis regarding the MOC efferent model response to AM noise stimuli, analysis of the physiological dataset in response to AM noise, and implementation of the MOC efferent model with its parameters (K_{IC}, B, and τ_{MOC}). Section B describes the distribution of the optimum parameters in the dataset and compares the responses of models with and without the MOC efferent control system to physiological data. In section C we use the new model with MOC efferent control to simulate responses to a few different stimuli and compare these responses with physiological data from the literature.

A. The physiological dataset

Consistent with our hypothesis, the IC rates increased over time in most IC neurons with BE MTFs. Figure 6 presents six examples of BE IC neuron responses that illustrate the trend of increasing rate over time; these examples were chosen as they have different BMFs and CFs. The left panel in each example in Fig. 6 is the rate MTF, and the right panel is the IC response to AM noise modulated at a frequency near the neuron's BMF, with a range of modulation depths (different colored lines). The gray time range is the time window after the onset response over which we analyzed the increase in rate. All of the examples in Fig. 6 had increasing rate over time during the analysis window, especially in response to lower modulation depths. In some neurons (e.g., Fig. 6B) the rate was nearly constant over time in response to fully modulated noise, but the IC rate was high for this modulation depth from the beginning of the analysis window. In the framework of our hypothesis, this observation suggests that because of the strong modulation in the stimulus, the fluctuation in AN PSTHs was large enough to maximize the IC rate, such that a change in cochlear gain as a result of MOC efferent activity could not further increase the IC rate. In these examples, the PSTHs in response to the unmodulated noise stimulus also showed an increasing trend in rate. This trend in the noise responses could also be explained by efferent-system activity, because unmodulated wideband

noise includes inherent temporal fluctuations after peripheral filtering, which would increase IC rate

and lower the cochlear gain.

The trend of increasing rate over time (See Methods Section C) occurred in the majority of the

neurons with BE MTFs in response to modulation depths less than 0 dB (i.e. most symbols in Fig. 7

fall above the horizontal line at 0). The percentage of neurons with positive slopes decreased at high

modulation depths (see Fig. 6). As described above, the decrease at high modulation depths can be

explained by a ceiling effect on the IC rate. In general, neural response rates are typically expected to

FIG. 6. (color online) A-F) Six examples of BE IC neuron smoothed responses to AM noise stimulus. The left-hand panel in each example is the MTF for AM noise stimuli; the vertical green lines indicate BMF. The right-hand panels show smoothed PSTHs that illustrate the time course of the rate during responses to AM noise stimuli with a modulation frequency near each neuron's BMF and a range of modulation depths (see legend).

331   decrease over time during sustained stimuli, as a result of rate adaptation, making this increase in rate

332   particularly striking. The finding that that majority of the BE IC cells had rates that increased over

333   the time course of the AM noise stimuli is consistent with the hypothesis that MOC efferent activity

334   results in an increase in BE IC rates over time.

FIG. 7. Percentage increase in rate of BE IC neurons, referenced to the rate at the end of

the onset response. The majority of 35 studied BE neurons had rates that increased over

the steady-state time course of wideband AM noise stimuli.

B. Adjusting model parameters

The distributions of the optimized parameters for neurons in this study were broad (Fig.8). The median of the distribution for each parameter was used as the final value for that parameter (K_{IC}=20, τ_{MOC}=260 ms, B=0.01) (Eqn.1). The median of the estimated time constant distribution was 260 ms, which was used to determine the cutoff frequency of the LPF in the MOC model, τ_{MOC}. This value is consistent with values of the time constant that have been suggested for the MOC efferent system based on other types of physiological and psychophysical measurements (Backus & Guinan, 2006; Roverud & Strickland, 2010; Warren & Liberman, 1989). The median of the distribution of correlations between the model responses and each of the IC neuron responses in the physiological dataset was 0.025 for models without efferent feedback. These correlations illustrate that the model without efferents did not simulate the increasing trend in rate over time in the physiological

FIG. 8. (color online) Distribution of the fit values of, A) time constant (τ_{MOC}), B) the rational function parameter (B), and C) the IC scaler (K_{IC}) for the model for 29 neurons in this study for which the rates increased during the SAM stimuli, the MTF type was BE, and the modulating frequency of the stimulus matched the BMF of the cell.

dataset. The response of the model without efferents had a decrease in rate consistent with neural

adaptation that arises in the AN model responses (Zilany et al., 2014). Simulations using a MOC ef-

ferent model with parameters identified for each neuron resulted in a correlation of 0.89 between

the data and model responses. The correlation reduced to 0.43 after replacing the individual values

with the median values of the distributions estimated for each parameter. Some of the correlations

in this condition were negative, consistent with the wide distribution of the optimum parameters for

each neuron. We performed cross-validation analysis with 30 validation neurons and 5 test neurons,

using a bootstrap analysis and 100 repetitions with replacement. The median of the test correlation

FIG. 9. (color online) Correlations between the IC responses and model simulations for various model parameter combinations. Each panel shows the correlation with the changing parameters 'B' and 'τ' while K_{IC} is held constant at the values displayed at the panel title. All correlations below zero are shown as blue.

was 0.2 while the validation correlation was 0.43. This result showed that the model was sensitive to

the parameter values, but still simulated the increased rate in response to AM noise using the median

parameter values. To test the chosen values for the model parameters, we show the median correla-

tions between the physiology and the model responses for the values in the optimization search win-

dow and evaluate the effect of each of these parameters on this correlation (Fig. 9A). The final val-

ues for the model parameter ($K_{IC} = 20$, $\tau_{MOC} = 260$ ms, B = 0.01) had the highest correlation value

points on the surface plots in Fig. 9, supporting the validation of these values.

For a better understanding of the effect of each of the parameters on the model IC response to

AM noise stimuli, Fig. 10 illustrates model responses over time for different combinations of param-

eter values. Each panel shows responses for the model with the value of one parameter set to five

FIG. 10. (color online) Effect of changing each of the efferent model parameters on IC model responses to AM noise stimuli over time. A) the time constant parameter (τ_{MOC}) was varied, while the other two parameters (B and K_{IC}) were fixed to the median values of the best-fit parameter-value distributions (Fig. 8B. B, C) Model responses for five values of the parameters B and K_{IC}, respectively.

values within the optimization search window, while keeping the other two parameters set to the

median of the distributions in Fig.8. For instance, in Fig. 10A, the parameters B and K_{IC} were set to

0.01 and 20, respectively, while the time constant, τ_{MOC}, was varied between 10 to 460 ms. For lower

values of the time constant, the increase in rate over time evident in the physiological dataset, was

not present in the model response. When the time constant was increased to 260 ms - the mean of

the distribution in Fig. 8 - an increase in rate over time was observed for the model responses. Fur-

ther increase in the value of the time constant resulted in a decrease in the slope of the rate increase.

Similarly, model responses for a range of values of the parameters B (Fig. 10B) and K_{IC} (Fig. 10C)

illustrate how the change in response rate over time was influenced by a range of parameter values.

These responses illustrate the sensitivity of the model to the parameter values, and further validate

the parameter values chosen to match the physiological responses. Figure 11 shows responses to

AM noise for three representative BE IC cells (left column), for models without MOC efferents

(middle column), and for the model with efferents, using the median values for the model parame-

ters (right column). The models had BMFs and CFs that matched the example neurons. The model

with MOC efferent feedback simulated the increase in rate over time, consistent with the hypothesis

that a model with the MOC efferent system could simulate the response to AM noise more accu-

rately than the model without efferents.

C. Validating the proposed model responses

Model responses to tone stimuli were compared to responses of the previous AN model to

verify that introducing the efferent gain-control pathways did not adversely affect the model's ability

to predict AN responses to basic stimuli. It is important to note that the physiological data used for

comparison were recorded from ANs of anesthetized animals, in which the MOC efferent system

was likely suppressed (Guitton et al., 2004). Thus, complete agreement between the physiological re-

sponses of AN fibers in anesthetized animals and the responses of the AN stage of the model with

FIG. 11. A-C) Examples of physiological data from three BE IC cells in awake rabbit (left panels), with simulated IC responses to AM noise with modulation depth of -10 dB without (center) and with (right) efferent activation. The CF and BMF of each model neuron were matched to the example neuron. Median values (K_{IC}=30, τ_{MOC}=260 ms, and B=0.01) for the model parameters were used. The CFs for these cells were 3.5, 4, 2 kHz, respectively, and the BMFs were all approximately 80 Hz.

MOC efferents was not expected, especially for complex stimuli (such as AM tones). However, for

pure-tone stimuli, Rhode and Kettner (1987) and May and Sachs (1992) showed that anesthesia does

not significantly affect post-stimulus time histograms (PSTHs) or rate-level functions of primary-like

neurons in the cochlear nucleus (and one presumed AN fiber). Therefore, we validated the proposed

model by comparing simulated responses to some baseline stimuli in physiological examples.

Model Response to pure tones and recovery of spontaneous rate

Figure 12 shows data and simulated responses to a 500-ms tone at CF followed by 500-ms of

silence. The purpose of this task was to study both the tone response and the AN model's recovery

to spontaneous rate. Recovery of spontaneous activity depends on stimulus level and on the sponta-

neous rate of the fiber (Kiang et al., 1965). Here we compare model responses to physiological re-

cordings from two HSR fibers with CFs of 1.82 and 10.34 kHz from Kiang et al. (1965) (Fig. 12).

The model response during the tone is comparable to the physiological examples, and the model

shows the same initial pause and time course of recovery after the stimulus as in the physiological

responses. Note that the response to a pure tone would primarily activate the CN input to the MOC

efferent pathway. The IC stage of the model would mainly respond at the onset and offset of the

tone, when the onset/offset ramps form a fluctuation in the stimulus envelope and therefore elicit a

response from the fluctuation-sensitive IC neurons (Fig. 12.G).

FIG. 12. AN and model responses to tones at CF: A) Unit 43: CF = 1.82 kHz, 55 dB SPL, SR = 60.6 s/sec; B) Unit 41: CF = 10.34 kHz, 30 dB SPL, SR = 51.7 s/sec; Panels A, B adapted from Kiang, Nelson Yuan-Sheng. with the assistance of Takeshi Watanabe, Eleanor C. Thomas, and Louise F. Clark., Discharge Patterns of Single Fibers in the Cat's Auditory Nerve, Fig 6.1 (p. 69), © 1966 Massachusetts Institute of Technology, by permission of The MIT Press. C, D) Responses to the same tones for the model without efferents, and E, F) with MOC efferents. G) The gain factor variation over time for the model with efferents (gain factor for plot E). For all model simulations (C to F) the AN model type was HSR with CFs matching the AN fibers in the physiological study. The stimulus sound level was matched to stimuli for the physiological data.

 Model response to an increment in tone level

One of the paradigms tested in Zilany et al. (2009) was the model response to an increment in

tone level. In the physiological data (Westerman & Smith, 1987) the AN fiber response to a tone at

the fiber's CF (5.99 kHz, HSR) was recorded in anesthetized cat. Over the first 300 ms of the stimu-

lus, the tone level was 5, 10, 15, or 20 dB above threshold, and for the second 300 ms, the tone level

increased to 43 dB above threshold. In the physiological responses, the transient response to the

pedestal increased with pedestal level, but the transient response to the increment decreased with in-

creasing pedestal level. The same trend was observed in the response of the AN model with and

without MOC efferents. The increase in rate over time that followed the first transient response was

observed for the model with MOC efferents (Fig. 13C, for initial tone levels of +5 and +10 dB), but

not for physiological responses in the anesthetized gerbil (Fig. 13A). This discrepancy between the

MOC model predictions and the physiological data may be due to the effects of anesthesia on the

FIG. 13. A) Physiological data from gerbil (adapted from Westerman and Smith (1987) with permission of Acoustical Society of America) in response to an increase in level during a tone. The AN model response to the amplitude increment response paradigm B) without efferent system C) with MOC efferent system.

empirical AN recordings. The increase in rate during the low-level tones (Fig. 13-c, +5 and +10 dB)

reflects the recovery of cochlear gain after an initial decrease in response to the onset of the stimu-

lus. Responses in unanesthetized animals are not available for these stimuli, therefore, it is not possi-

ble to confirm this interpretation at this time.

Model response to AM stimuli

Here the model response was compared to the response of an HSR AN fiber with CF of 20.2

kHz to an AM tone with a carrier frequency at CF (Joris & Yin, 1992). The effect of modulation

depth on the synchrony to modulation frequency (Fm) was studied for modulation depths ranging

from 0 to 1 (Fig. 14A). The modulation frequency was 100 Hz and level was 49 dB SPL. A compari-

son of synchronization to AM frequency as a function of modulation depth showed that the model

with MOC efferents had increased synchrony with modulation depth. However, the synchrony of

the model response was weaker than that observed physiologically because of the reduction in coch-

lear gain as a result of MOC efferent activity. Complications for comparison exist due to the differ-

ence between dynamic ranges of the model and this physiological example, as noted by Zilany et al.,

(2009). Furthermore, model responses to AM tones, which consist of both carrier and sideband fre-

quencies, may be shaped by the effective bandwidths of MOC projections, discussed below. AM re-

sponses of the model with efferents, however, cannot be directly compared to physiological re-

sponses, which are not available for AN fibers in unanesthetized animals. However, we do have ac-

cess to IC responses to AM noise in awake rabbit. Figure 14B compares the synchrony to AM noise

for the IC stage of the model with MOC efferents to actual responses from a single-unit recording

in the IC of awake rabbit (Carney et al., 2014). This result confirms that, for the model with effer-

ents, the increase in synchrony in the AN model with increasing modulation depth results in appro-

priate synchrony at the level of the model IC.

FIG. 14. (color online) A) Synchrony to the envelope of an AM tone at CF for an AN fiber with CF = 20 kHz (AN Physiology data from Joris & Yin, 1992) and for an HSR model fiber with matching CF with and without efferent activation. Modulation frequency of 100 Hz; level = 49 dB SPL. B) IC model with and without activation of the MOC efferent system and IC physiology synchronization-modulation depth plots for responses to AM noise stimulus at CF 5500 Hz, BMF 100 Hz, modulation frequency 64 Hz and stimulus level 36 dB SPL.

IV. DISCUSSION

In this work, we modified an existing model of the peripheral auditory system to simulate both the ascending pathway and MOC efferent feedback with both CN and IC inputs. The physiological data and simulation results are consistent with the hypothesis that the MOC efferent system influences neural fluctuations over time (Carney, 2018), as observed here by the increasing responses of BE IC cells over the time course of an AM noise. The simulation results support the hypothesis that a sub-cortical model with MOC efferent gain control better simulates IC responses to AM noise compared to a model without efferents.

One of the components of the proposed model is a LPF that was implemented to simulate the dynamics of the MOC efferent system. The time constant (or cut-off frequency) of this filter was

adjusted based on the physiological dataset. The dynamics of the MOC efferent system based on the

fit parameter agree with the reported dynamics in the literature for the MOC efferent fast effect.

Backus and Guinan (2006) used stimulus-frequency otoacoustic emission (SFOAE) measurements

to estimate the human MOC-reflex time constant. They reported an overall onset time constant of

277 ± 62 ms and decay time constant of 159 ± 54 ms. Warren and Liberman (1989) estimated the

MOC response to have a time constant of 250 ms in barbiturate-anesthetized cats. Roverud and

Strickland (2010) used an optimized psychophysical technique to estimate the time course of coch-

lear-gain reduction. They estimated an average exponential decay of 100 ms, which is faster than the

time constant estimated by Backus and Guinan. Yasin et al. (2020) used a computational model of

human hearing that included MOC efferent feedback and evaluated the model's speech recognition

for different MOC efferent time constants. Their results suggest the improvement in recognition of

speech in AM noise is highest for a MOC efferent time constant of 200 ms. In general, all of the

time constants suggested in the literature for the MOC efferent system are in the same range as our

results based on rabbit midbrain physiology. However, the MOC efferent system time constant

could differ between rabbits and humans. Using the proposed MOC efferent model to simulate hu-

man psychoacoustic experiments could better inform our understanding of the time constant for hu-

man listeners.

The dynamics of the efferent system support its potential role in improving speech perception

(Yasin et al., 2018). Specifically, the latency and time constant of the MOC efferent system (Backus

& Guinan, 2006; Roverud & Strickland, 2010; Warren III & Liberman, 1989) are comparable to typi-

cal phonemic durations (Jacewicz et al., 2007; Umeda, 1977). Therefore, the MOC efferent system

would presumably affect auditory neural responses, both within the time course of phonemes and

also in running speech, for which the perception of a phoneme would be influenced by the previous

phoneme (co-articulation) (Chambers et al., 2017; Recasens, 1984, 2018).

Another important component of the proposed model MOC efferent system was the input-

output function that maps the MOC input to a gain factor that scales the cochlear-gain coefficient

between 0 and 1. The second-order rational function used in this model was chosen based on its as-

ymptotic behavior at low and high input levels. The direct input-output function of MOC neurons is

not known, but several related functions have been reported. The shape of the proposed input-out-

put function was similar to the MOC efferent attenuation as a function of input sound level shown

in Russell and Murugasu (1997). Also, the asymptotic trend of this function for higher values is simi-

lar to the asymptotic responses shown in Liberman (1988) for MOC efferent activity as a function of

input sound level. Finally, the proposed function is similar to the relationship between stimulus level

and OHC power gain, which would be modulated by MOC signals, in an electrical-mechanical

model for OHCs (Rabbitt & Bidone, 2023; Rabbitt, 2023).

A. Comparing the Proposed model with previous AN models that included the efferent sys-

tem

Several previous AN models include efferent signals driven by the periphery (Clark et al., 2012;

Giguere & Woodland, 1994; Kwan et al., 2019; Smalt et al., 2014; Yasin et al., 2020). In some of

these previous implementations, cochlear gain was set to remain constant over time, omitting the

dynamics of MOC efferents (Brown et al., 2010; Ferry & Meddis, 2007; Giguere & Woodland, 1994;

Jennings et al., 2011). Smalt et al. (2014) proposed a model based on the Zilany et al. (2014) AN

model, but with an efferent system modeled by a time-varying gain-control feedback system. How-

ever, in this model, a local gain-control system was implemented based on the output of model

OHCs, which is inconsistent with the overall structure of the MOC efferent system, which depends

on outputs from the OHCs, IHC, AN, CN, IC, and other structures (Smalt et al., 2014; Schofield,

2011). None of these models simulated the descending input to the MOC efferent system from the

midbrain. The focus of the current study was to include both peripheral and midbrain inputs to a

dynamic MOC efferent system in a model for AN and BE IC responses.

B. Limitations and Future directions

Other physiological and psychoacoustic studies can be used to further fine tune the model's

parameters and structure. For example, forward-masking studies with long-duration maskers would

be expected to activate the MOC efferent system (Krull and Strickland, 2008; Brennan et al., 2023).

At the level of the IC, further animal studies of the temporal properties of responses to complex

sounds would contribute to this modeling effort, such as investigating the changes in synchrony of

IC responses to the envelope of AM stimuli over time. Another direction for future work is to study

the influence of efferent activity on the responses of other MTF types in the IC, such as BS or hy-

brid MTFs. Here we focused on BE MTFs, as the increase in their rate over the time course of AM

stimuli cannot be confused with rate adaptation. Phase of AM coding could be an important aspect

for studying speech. AM phase was not explored in this study due to the relatively short stimulus du-

ration used and the limited number of repetitions of the stimuli in the available dataset. Physiological

experiments designed to study the effect of the efferent system on the phase of AM coding is an in-

teresting future direction.

The peripheral model studied here is a monaural model, with "one-sided" brainstem and

midbrain stages. A binaural model would be a powerful tool for studying the crossed and uncrossed

effects of the efferents. The proposed model in this study consists of a single CF channel, and MOC

controls for each frequency influence the gain of the related CF channel. However, studies have

shown that some projections from MOC neurons to OHCs have a broad distribution across CF

channels (Brown, 2014; Lee & Lewis, 2023). To move towards a more comprehensive model, a fu-

ture direction of research is to explore a cross-frequency projection of the MOC control system that

affects a range of CFs. A broader distribution of MOC projections could benefit simulations of the

neural response to complex stimuli, such AM noise and also speech signals. Another direction for

future work on this model is inclusion of a more advanced IC model, instead of the simple bandpass

filter used for modulation filtering in BE IC neurons in the current model.

In general, recording from AN fibers requires an anesthetized animal preparation, but anes-

thesia suppresses MOC efferent activity (Guitton et al., 2004). As a result, there are no examples in

the AN physiological literature for comparison to the AN model response with active MOC effer-

ents. However, recording from more accessible levels of the auditory pathway, such as the IC in

awake animals, could provide further information regarding the MOC efferent system. Recording

from the CN in awake animals or recording from AN fibers in decerebrate animals could also po-

tentially be beneficial for studying the MOC efferent system (Kim et al., 1990a, 1990b; Kawase et al.,

1993).

Other phenomena could explain the increase in IC response rates over time in response to AM

noise, either in addition to or instead of efferent activity. For instance, adaptation of inhibition (Vie-

meister & Bacon, 1982; Oberle et al., 2023) could be an alternative explanation for the increase in

rate we observed in IC responses to AM noise. Adaptation of inhibition has been suggested as an

explanation for auditory enhancement, in which a target signal embedded in a masker is preceded by

the same masker but without the target frequency. Adaptation of inhibition could explain an im-

provement in the threshold of detecting the tone (Byrne et al., 2011). However, neural mechanisms

underlying adaptation of inhibition are not clear. Enhancement effects and its properties, such as

time constant and level-dependence, may be further examined using the MOC efferent model in the

future to see if such effects are consistent with MOC feedback. Preliminary results suggest that the

subcortical model with efferent feedback can also explain several aspects of auditory enhancement

(Farhadi et al., 2023a).

In addition to subcortical projections, there are significant descending projections from the audi-

tory cortex and thalamus to the IC (Schofield, 2011). The descending projection to the central nu-

cleus of the IC (ICc) could potentially contribute to the observed trend in the physiology dataset.

However, studies indicate that in animal models (except for rats), the projections from the auditory

cortex and medial geniculate nucleus (MG) in the thalamus terminate in the external cortex of the IC

(ICx) and dorsal cortex of the IC (ICd), and the projection to ICc is described as much less dense

than ICd or ICx (Schofield, 2011). These projections were not included in the proposed subcortical

model, but they may influence responses of IC cells.

V.   ACKNOWLEDGMENTS

This work was supported by NIH-R01-DC010813 (AF, LHC), NIH-R01-DC008327 (EAS), and

K23 DC014752 (SGJ).

VI.   AUTHOR DECLARATIONS

The authors have no conflicts of interest to disclose.

VII.   DATA AVAILABILITY

Model code will be made freely available as downloadable files (Farhadi et al., 2023) from the

Open Science Framework, DOI 10.17605/OSF.IO/UZYW4.

VIII.   REFERENCES

Aedo, C., Tapia, E., Pavez, E., Elgueda, D., Delano, P. H., & Robles, L. (**2015**). "Stronger effe-

rent suppression of cochlear neural potentials by contralateral acoustic stimulation in awake than in

anesthetized chinchilla," Frontiers in Systems Neuroscience **9**, 21.

Backus, B. C., & Guinan Jr, J. J. (**2006**). "Time-course of the human medial olivocochlear re-

flex," J. Acoust. Soc. Am. **119**, 2889–2904.

Bharadwaj, H. M., Verhulst, S., Shaheen, L., Liberman, M. C., & Shinn-Cunningham, B. G.

(**2014**). "Cochlear neuropathy and the coding of supra-threshold sound," Frontiers in Systems Neu-

rosci. **8**, 26.

Blackburn, C. C., & Sachs, M. B. (**1990**). "The representations of the steady-state vowel

sound/e/in the discharge patterns of cat anteroventral cochlear nucleus neurons," J. Neurophys. **63**,

1191–1212.

Brennan, M. A., Svec, A., Farhadi, A., Maxwell, B. N., & Carney, L. H. (**2023**). "Inherent enve-

lope fluctuations in forward masking: Effects of age and hearing loss," J. Acoust. Soc. Am. **153**,

1994-2005.

Brown, M. C. (**2014**). "Single-unit labeling of medial olivocochlear neurons: the cochlear fre-

quency map for efferent axons," J. Neurophys. **111***, 2177-2186.

Brown, G. J., Ferry, R. T., & Meddis, R. (**2010**). "A computer model of auditory efferent

suppression: Implications for the recognition of speech in noise," J. Acoust. Soc. Am. **127**, 943–954.

Byrne, A. J., Stellmack, M. A., & Viemeister, N. F. (**2011**). "The enhancement effect: evidence for

adaptation of inhibition using a binaural centering task," J. Acoust. Soc. Am. **129**, 2088–2094.

Carney, L. H. (**2018**). "Supra-threshold hearing and fluctuation profiles: implications for sensori-

neural and hidden hearing loss," JARO **19**, 331–352.

Carney, L. H., Li, T., & McDonough, J. M. (**2015**). "Speech coding in the brain: representation of

vowel formants by midbrain neurons tuned to sound fluctuations," Eneuro **2**, 4.

Carney, L. H., Zilany, M. S. A., Huang, N. J., Abrams, K. S., & Idrobo, F. (**2014**). "Suboptimal

use of neural information in a mammalian auditory system," J. Neurosci. **34**, 1306–1313.

Chambers, A. R., Hancock, K. E., Maison, S. F., Liberman, M. C., & Polley, D. B. (**2012**).

"Sound-evoked olivocochlear activation in unanesthetized mice," JARO **13**, 209–217.

Chambers, C., Akram, S., Adam, V., Pelofi, C., Sahani, M., Shamma, S., & Pressnitzer, D. (**2017**).

"Prior context in audition informs binding and shapes simple features," Nat. Comm. **8**, 1–11.

Clark, N. R., Brown, G. J., Jürgens, T., & Meddis, R. (**2012**). "A frequency-selective feedback

model of auditory efferent suppression and its implications for the recognition of speech in noise,"

J. Acoust. Soc. Am. **132**, 1535–1541.

Delgutte, B., & Kiang, N. Y. (**1984**). "Speech coding in the auditory nerve: I. Vowel-like

sounds," J. Acoust. Soc. Am. **75**, 866-878.

Delano, P. H., Elgueda, D., Hamame, C. M., & Robles, L. (**2007**). "Selective attention to visual

stimuli reduces cochlear sensitivity in chinchillas," J. Neurosci. **27**, 4146-4153.

Deng, L., Geisler, C. D., & Greenberg, S. (**1987**). "Responses of auditory-nerve fibers to multi-

ple-tone complexes," J. Acoust. Soc. Am. **82**, 1989-2000.

Farhadi, A., Agarwalla, S. & Carney, L. H. (**2023a**). "A Subcortical Auditory Model With Effe-

rent Gain Control Explains Perceptual Enhancement," Abstract, Assoc. Res. Otolaryngol. **46**:449.

Farhadi, A., Jennings, S. G., Strickland, E. A., & Carney, L. H. (**2023b**). Downloadable

MATLAB/C Code for "Subcortical Auditory Model including Efferent Dynamic Gain Control with

Inputs from Cochlear Nucleus and Inferior Colliculus" from OSF: https://osf.io/uzyw4/, DOI

10.17605/OSF.IO/UZYW4, Software.

Farhadi, A., Jennings, S. G., Strickland, E. A., & Carney, L. H. (**2021**). "A Closed-Loop Gain-

Control feedback model for the medial efferent system of the descending auditory pathway,"

In ICASSP 2021-2021 IEEE Intl. Conf. Acoust. Speech Signal Proc. (ICASSP) (pp. 291-295).

Fekete, D. M., Rouiller, E. M., Liberman, M. C., & Ryugo, D. K. (**1984**). "The central projections

of intracellularly labeled auditory nerve fibers in cats," J. Comp. Neurol. **229**, 432-450.

Ferry, R. T., & Meddis, R. (**2007**). "A computer model of medial efferent suppression in the mammalian auditory system," J. Acoust. Soc. Am. **122**, 3519–3526.

Giguere, C., & Woodland, P. C. (**1994**). "A computational model of the auditory periphery for speech and hearing research. II. Descending paths," J. Acoust. Soc. Am. **95**, 343–349.

Guinan Jr, J. J. (**2006**). "Olivocochlear efferents: anatomy, physiology, function, and the measurement of efferent effects in humans," Ear Hear. **27**, 589–607.

Guinan Jr, J. J. (**2018**). "Olivocochlear efferents: Their action, effects, measurement and uses, and the impact of the new conception of cochlear mechanical responses," Hear. Res. **362**, 38–47.

Guitton, M. J., Avan, P., Puel, J.-L., & Bonfils, P. (**2004**). "Medial olivocochlear efferent activity in awake guinea pigs," Neuroreport **15**, 1379–1382.

Gummer, M., Yates, G. K., & Johnstone, B. M. (**1988a**). "Modulation transfer function of efferent neurones in the guinea pig cochlea," Hear. Res. **36**, 41–51.

Gummer, M., Yates, G. K., & Johnstone, B. M. (**1988b**). "Modulation transfer function of efferent neurones in the guinea pig cochlea," Hear. Res. **36**, 41–51.

Huffman, R. F., & Henson Jr, O. W. (**1990**). "The descending auditory pathway and acoustico-motor systems: connections with the inferior colliculus," Brain Res. Rev. **15**, 295–323.

Jacewicz, E., Fox, R. A., & Salmons, J. (**2007**). "Vowel duration in three American English dialects," American Speech **82**, 367–385.

Jamos, A. M., Kaf, W. A., Chertoff, M. E., & Ferraro, J. A. (**2020**). "Human medial olivocochlear reflex: contralateral activation effect on low and high frequency cochlear response," Hear. Res. **389**, 107925.

Jamos, A. M., Hosier, B., Davis, S., & Franklin, T. C. (**2021**). "The role of the medial olivocochlear reflex in acceptable noise level in adults," J. Am. Acad. Audiol. **32**, 137-143.

Jennings, S. G., & Aviles, E. S. (**2023**). "Middle ear muscle and medial olivocochlear activity infe-

rred from individual human ears via cochlear potentials." J. Acoust. Soc. Am. **153**, 1723-1732.

Jennings, S. G. (**2021**). "The role of the medial olivocochlear reflex in psychophysical masking

and intensity resolution in humans: a review," J. Neurophys. **125**, 2279–2308.

Jennings, S. G., Heinz, M. G., & Strickland, E. A. (**2011**). "Evaluating adaptation and olivococh-

lear efferent feedback as potential explanations of psychophysical overshoot," JARO **12**, 345–360.

Joris, P. X., Schreiner, C. E., & Rees, A. (**2004**). "Neural processing of amplitude-modulated

sounds," Phys. Rev. **84**, 541–577.

Joris, P. X., & Yin, T. C. T. (**1992**). "Responses to amplitude-modulated tones in the auditory

nerve of the cat," J. Acoust. Soc. Am. **91**, 215–232.

Kawase, T., Delgutte, B., & Liberman, M. C. (**1993**). "Antimasking effects of the olivocochlear

reflex. II. Enhancement of auditory-nerve response to masked tones," J. Neurophys. **70**, 2533-2549.

Kiang, N. Y. S., Watanabe, T., Thomas, E. C., & Clark, L. F. (**1965**). *Discharge patterns of single fibers*

in the cat's auditory nerve. Cambridge, MA: MIT Press.

Kim, D. O., Carney, L., & Kuwada, S. (**2020**). "Amplitude modulation transfer functions reveal

opposing populations within both the inferior colliculus and medial geniculate body," J. Neurophys.

124, 1198–1215.

Kim, D. O., Zahorik, P., Carney, L. H., Bishop, B. B., & Kuwada, S. (**2015**). "Auditory distance

coding in rabbit midbrain neurons and human perception: monaural amplitude modulation depth as

a cue," J. Neurosci. **35**, 5360-5372.

Kim, D. O., Sirianni, J. G., & Chang, S. O. (**1990**). "Responses of DCN-PVCN neurons and au-

ditory nerve fibers in unanesthetized decerebrate cats to AM and pure tones: analysis with autocorre-

lation/power-spectrum," Hear. Res. 45**,** 95-113.

Kim, D. O., Chang, S. O., & Sirianni, J. G. (**1990**). "A population study of auditory-nerve fibers in unanesthetized decerebrate cats: Response to pure tones," J. Acoust. Soc. Am. **87**, 1648-1655.

Krishna, B. S., & Semple, M. N. (**2000**). "Auditory temporal processing: responses to sinusoidally amplitude-modulated tones in the inferior colliculus," J. Neurophys. **84**, 255–273.

Krull, V., & Strickland, E. A. (**2008**). "The effect of a precursor on growth of forward masking," J. Acoust. Soc. Am. **123**, 4352-4357.

Kwan, T. J. M., Zilany, M. S. A., Davies-Venn, E., & Abdul Wahab, A. K. (**2019**). "Modeling the effects of medial olivocochlear efferent stimulation at the level of the inferior colliculus," Exp. Brain Res. **237**, 1479–1491.

Lehky, S. R. (**2010**). "Decoding poisson spike trains by gaussian filtering," Neural Comp. **22**, 1245–1271.

Lauer, A. M., Jimenez, S. V., & Delano, P. H. (**2022**). "Olivocochlear efferent effects on perception and behavior," Hear. Res. **419**, 108207.

Lee, D., & Lewis, J. D. (**2023**). "Inter-Subject Variability in the Dependence of Medial-Olivocochlear Reflex Strength on Noise Bandwidth," Ear Hear. **44**, 544-557.

Liberman, M. C. (**1988**). "Response properties of cochlear efferent neurons: monaural vs. binaural stimulation and the effects of noise," J. Neurophys. **60**, 1779-1798.

Liberman, M. C. (**1978**). "Auditory-nerve response from cats raised in a low-noise chamber," J. Acoust. Soc. Am. **63**, 442–455.

Liberman, M. C., & Guinan Jr, J. J. (**1998**). "Feedback control of the auditory periphery: anti-masking effects of middle ear muscles vs. olivocochlear efferents," J. Comm. Dis. **31**, 471–482.

Lichtenhan, J. T., Wilson, U. S., Hancock, K. E., & Guinan Jr, J. J. (**2016**). "Medial olivocochlear efferent reflex inhibition of human cochlear nerve responses," Hear Res. **333**, 216-224.

Lopez-Poveda, E. A. (**2018**). "Olivocochlear efferents in animals and humans: from anatomy to

clinical relevance," Frontiers Neurol. **9**, 197.

Mao, J., Vosoughi, A., & Carney, L. H. (**2013**). "Predictions of diotic tone-in-noise detection ba-

sed on a nonlinear optimal combination of energy, envelope, and fine-structure cues," J. Acoust.

Soc. Am. **134**, 396–406.

May, B. J., & Sachs, M. B. (**1992**). "Dynamic range of neural rate responses in the ventral coch-

lear nucleus of awake cats," J. Neurophys. **68**, 1589-1602.

Nelson, P. C., & Carney, L. H. (**2004**). "A phenomenological model of peripheral and central

neural responses to amplitude-modulated tones," J. Acoust. Soc. Am. **116**, 2173-2186.

Oberle, H. M., Ford, A. N., Czarny, J. E., Rogalla, M. M., & Apostolides, P. F. (**2023**, in press).

"Recurrent circuits amplify corticofugal signals and drive feedforward inhibition in the inferior co-

lliculus," J. Neurosci.

Oertel, D., Wright, S., Cao, X.-J., Ferragamo, M., & Bal, R. (**2011**). "The multiple functions of T

stellate/multipolar/chopper cells in the ventral cochlear nucleus," Hear. Res. **276**, 61–69.

Olsen, W. O. (**1998**). "Average speech levels and spectra in various speaking/listening condi-

tions," Am. J. Audiol. **7**, 21-25.

Rabbitt, R. (**2023**) "The MOC efferent system acts as a control parameter for outer hair cell dy-

namic stability and power output," Abstract, Assoc. Res. Otolaryngol. **46**, 544.

Rabbitt, R., and Bidone, T.C. (**2023**). "A parametric blueprint for optimum cochlear outer hair

cell design," J. Roy. Soc. Interface **20**, 20220762.

Rahman, M., Willmore, B. D. B., King, A. J., & Harper, N. S. (**2019**). "A dynamic network model

of temporal receptive fields in primary auditory cortex," PLoS Comp. Biol. **15**, e1006618.

Recasens, D. (**1984**). "Vowel-to-vowel coarticulation in Catalan VCV sequences," J. Acoust. Soc.

Am. **76**, 1624–1635.

Recasens, D. (**2018**). "Coarticulation," In *Oxford Research Encyclopedia of Linguistics*.

https://doi.org/10.1093/acrefore/9780199384655.013.416.

Rhode, W. S., & Greenberg, S. (**1994**). "Encoding of amplitude modulation in the cochlear nu-

cleus of the cat," J. Neurophys. **71**, 1797-1825.

Rhode, W. S., & Kettner, R. E. (**1987**). "Physiological study of neurons in the dorsal and poste-

roventral cochlear nucleus of the unanesthetized cat," J. Neurophys. **57**, 414-442.

Romero, G. E., & Trussell, L. O. (**2021**). "Distinct forms of synaptic plasticity during ascending

vs descending control of medial olivocochlear efferent neurons," Elife **10**, e66396.

Roverud, E., & Strickland, E. A. (**2010**). "The time course of cochlear gain reduction measured

using a more efficient psychophysical technique," J. Acoust. Soc. Am. **128**, 1203–1214.

Russell, I. J., & Murugasu, E. (**1997**). "Medial efferent inhibition suppresses basilar membrane

responses to near characteristic frequency tones of moderate to high intensities," J. Acoust. Soc. Am.

102, 1734-1738.

Ryugo, D. K. (**2008**). "Projections of low spontaneous rate, high threshold auditory nerve fibers

to the small cell cap of the cochlear nucleus in cats," Neurosci. **154**, 114–126.

Schofield, B. R. (**2011**). "Central descending auditory pathways," In *Auditory and vestibular efferents*

(pp. 261–290). Springer.

Shera, C. A., Guinan Jr, J. J., & Oxenham, A. J. (**2002**). "Revised estimates of human cochlear

tuning from otoacoustic and behavioral measurements, " PNAS **99**, 3318-3323.

Smalt, C. J., Heinz, M. G., & Strickland, E. A. (**2014**). "Modeling the time-varying and level-de-

pendent effects of the medial olivocochlear reflex in auditory nerve responses," JARO **15**, 159–173.

Smith, S. B., Lichtenhan, J. T., & Cone, B. K. (**2017**). "Contralateral inhibition of click-and chirp-

evoked human compound action potentials," Frontiers Neurosci. **11**, 189.

Sun, X.-M. (**2008**). "Contralateral suppression of distortion product otoacoustic emissions and the middle-ear muscle reflex in human ears," Hear. Res. **237**, 66–75.

Tan, Q., & Carney, L. H. (**2003**). "A phenomenological model for the responses of auditory-nerve fibers. II. Nonlinear tuning with a frequency glide," J. Acoust. Soc. Am. **114**, 2007–2020.

Umeda, N. (**1977**). "Consonant duration in american english," J. Acoust. Soc. Am. **61**, 846–858.

Viemeister, N. F., & Bacon, S. P. (**1982**). "Forward masking by enhanced components in harmonic complexes," J. Acoust. Soc. Am. **71**, 1502–1507.

Warr, W. B. (**1992**). "Organization of olivocochlear efferent systems in mammals," In *The Mammalian Auditory Pathway: Neuroanatomy*, pp. 410–448. Springer.

Warren III, E. H., & Liberman, M. C. (**1989**). "Effects of contralateral sound on auditory-nerve responses. I. Contributions of cochlear efferents," Hear. Res. **37**, 89–104.

Westerman, L. A., & Smith, R. L. (**1984**). "Rapid and short-term adaptation in auditory nerve responses," Hear. Res. **15**, 249–260.

Westerman, L. A., & Smith, R. L. (**1987**). "Conservation of adapting components in auditory-nerve responses," J. Acoust. Soc. Am. **81**, 680–691.

Yasin, I., Drga, V., Liu, F., Demosthenous, A., & Meddis, R. (**2020**). "Optimizing Speech Recognition Using a Computational Model of Human Hearing: Effect of Noise Type and Efferent Time Constants," IEEE Access **8**, 56711–56719.

Yasin, I., Liu, F., Drga, V., Demosthenous, A., & Meddis, R. (**2018**). "Effect of auditory efferent time-constant duration on speech recognition in noise," J. Acoust. Soc. Am. **143**, EL112-EL115

Ye, Y., Machado, D. G., & Kim, D. O. (**2000**). "Projection of the marginal shell of the anteroventral cochlear nucleus to olivocochlear neurons in the cat," J. Comp. Neurol. **420**, 127–138.

Young, E. D., & Sachs, M. B. (**1979**). "Representation of steady‑state vowels in the temporal as-

pects of the discharge patterns of populations of auditory‑nerve fibers," J. Acoust. Soc. Am. **66**,

1381-1403.

Zhang, X., Heinz, M. G., Bruce, I. C., & Carney, L. H. (**2001**). "A phenomenological model for

the responses of auditory-nerve fibers: I. Nonlinear tuning with compression and suppression." J.

Acoust. Soc. Am. **109**, 648-670.

Zilany, M. S. A., & Bruce, I. C. (**2006**). "Modeling auditory-nerve responses for high sound pres-

sure levels in the normal and impaired auditory periphery," J. Acoust. Soc. Am. **120**, 1446–1466.

Zilany, M. S. A., Bruce, I. C., & Carney, L. H. (**2014**). "Updated parameters and expanded simu-

lation options for a model of the auditory periphery," J. Acoust. Soc. Am. **135**, 283–286.

Zilany, M. S. A., Bruce, I. C., Nelson, P. C., & Carney, L. H. (**2009**). "A phenomenological mo-

del of the synapse between the inner hair cell and auditory nerve: long-term adaptation with power-

law dynamics," J. Acoust. Soc. Am. **126**, 2390–2412.