Mechanisms of masking by Schroeder-phase harmonic tone complexes in the budgerigar

(*Melopsittacus undulatus*)

Kenneth S. Henry [a,b,c,*], Yingxuan Wang [b], Kristina S. Abrams [c], Laurel H Carney [b,c]

Departments of [a] Otolaryngology, [b] Biomedical Engineering, and [c] Neuroscience, University of

Rochester, Rochester, NY 14642, USA

* Corresponding author

E-mail addresses: kenneth_henry@urmc.rochester.edu (K.S. Henry),

laurel_carney@urmc.rochester.edu (L.H. Carney).

Abstract

Schroeder-phase harmonic tone complexes can have a flat temporal envelope and either rising

or falling instantaneous-frequency sweeps within periods of the fundamental frequency (F0),

depending on the phase-scaling parameter C. Human thresholds for tone detection in a

concurrent Schroeder masker are 10-15 dB lower for positive C values (rising frequency

sweeps) compared to negative (falling sweeps), potentially due to the impulse response of

cochlear filtering, though this hypothesis remains controversial. Birds provide an interesting

animal model for studies of Schroeder masking because prior reports suggest less behavioral

threshold difference between maskers with opposite C values. However, most behavioral

studies focused on relatively low masker F0s, and neurophysiological mechanisms in birds have

not been explored. We performed behavioral Schroeder-masking experiments in budgerigars

(*Melopsittacus undulatus*) using a wide range of masker F0 and C values. The signal frequency

was 2800 Hz. Neural recordings at the midbrain processing level characterized encoding of

behavioral stimuli in awake animals. Behavioral thresholds increased with increasing masker F0

and showed minimal difference between opposite C values, consistent with prior studies. Neural

recordings showed prominent temporal and rate-based encoding of Schroeder F0, and in many

neurons, marked response asymmetry between Schroeder stimuli with opposite C values.

Neural thresholds for Schroeder-masked tone detection were (1) in most cases based on a

response decrement compared to the masker alone, consistent with prominent modulation

tuning in midbrain neurons, and (2) generally similar between opposite masker C values. These

results highlight the likely importance of envelope cues in behavioral studies of Schroeder

masking.

Keywords: Budgerigar; Envelope encoding; Inferior colliculus; Operant conditioning; Schroeder

masking

1. Introduction

Schroeder's algorithm can produce harmonic tone complexes (HTCs) with a flat temporal

envelope and either upward- or downward-sloping instantaneous frequency sweeps within

periods of the fundamental frequency (F0), depending on the polarity of the phase-scaling

parameter C (Schroeder, 1970) (Fig. 1). Early on, it was discovered that HTCs generated with

positive (downward-sweeping frequency) and negative (upward-sweeping frequency) C values

differ in the extent to which they mask behavioral thresholds for pure-tone detection in humans,

with lower thresholds by up to 20 dB for the positive C value compared to negative (Kohlrausch

and Sander, 1995; Smith et al., 1986). Less masking by Schroeder HTCs with positive C values

is not explainable by traditional power-spectrum models of masking (Fletcher, 1940) because

Schroeder HTCs generated with opposite C values have identical magnitude spectra; these

signals share the same waveform when one signal is time reversed.

Fig. 1. Waveforms of Schroeder-phase harmonic tone complexes (HTCs) produced with the same fundamental frequency (F0; 100 Hz) and values of the phase-scaling parameter, C, ranging from -1 to 1. Positive C values (right column) produce downward-sloping instantaneous frequency sweeps within F0 periods whereas negative C values (left column) produce upward-sloping frequency sweeps. Lower absolute C value decreases the duty cycle of the waveform, with C of zero (bottom panel; all components in cosine phase) producing an impulse train.

57
58
The underlying reason for masking differences between Schroeder C polarities remains
uncertain. One hypothesis is that the difference originates from asymmetry of mechanical
filtering by the mammalian cochlea (Smith et al., 1986). Specifically, recordings of basilar
membrane motion in response to clicks show that the impulse response of the cochlea exhibits
an upward-sweeping instantaneous frequency glide in response to clicks – a property
associated with asymmetry in the shape of pure-tone frequency tuning curves (Recio et al.,
1998; Strube, 1985). Filters with an upward-gliding impulse response are expected to produce
more prominent response envelope fluctuations (i.e., "peakier" temporal-response profiles) for
Schroeder HTCs with positive C values compared to negative. The deeper and longer low-
amplitude periods in the cochlear response to maskers with positive C value could potentially
provide opportunities for detection of an added low-level tone, thereby leading to the observed
lower masked threshold for the positive-C condition.
Animal models have been used to test the hypothesized contribution of cochlear filtering
asymmetries to Schroeder-masking differences between opposite C polarities, but so far have
yielded an incomplete understanding of underlying mechanisms. Studies in chinchilla and
guinea pig recorded basilar membrane motion in response to Schroeder HTCs to test for the
predicted difference in response envelope fluctuations between opposite C polarities (Recio and
Rhode, 2000; Summers et al., 2003). Results were partly consistent with an explanation based
on cochlear impulse responses, showing the expected larger fluctuations for responses to

Schroeder HTCs with positive C values compared to negative. However, measurements were

restricted to basal cochlear regions with characteristic frequencies (CFs) above the frequency

range of target signals typical of human behavioral studies. Note that for CFs below 1 kHz, the

mammalian cochlea appears to transition to downward-sweeping frequency glides of the

impulse response based on auditory-nerve-fiber recordings (Carney et al., 1999; Recio-Spinoso

et al., 2005). Filters with downward-gliding impulse responses should theoretically produce a

peakier response to Schroeder HTCs with negative C values rather than positive, and

consequently less masking for the negative-C condition. However, less masking by Schroeder

HTCs with negative C values has not been observed in any human behavioral study

(Kohlrausch and Sander, 1995; Smith et al., 1986). While it remains possible that chinchillas or

guinea pigs show lower thresholds for the negative-C Schroeder masking condition at test

frequencies below 1 kHz, animal behavioral studies of Schroeder masking have not been

conducted in any other nonhuman mammal to our knowledge. Consequently, it remains unclear

whether asymmetry of cochlear filtering can explain observed behavioral masking differences

between Schroeder C polarities.

Birds provide an interesting animal model for studies of Schroeder masking because

many species use vocalizations containing rapid frequency changes as part of their social

communication system and can perform complex auditory detection and discrimination tasks

(Dooling et al., 2000). In contrast with human results, the few behavioral studies of Schroeder

masking in birds have found minimal threshold differences for tones masked by Schroeder

HTCs with opposite C values. In budgerigars, thresholds were determined for detection of 1,

2.8, and 4-kHz tones masked by Schroeder HTCs with positive or negative C values, for

comparison with human thresholds determined using the same stimuli (Leek et al., 2000).

Whereas human subjects showed the expected lower threshold of up to 15-20 dB for positive-C

Schroeder maskers compared to negative C values, budgerigar thresholds were either similar

between opposite C values or slightly lower for maskers with negative C values. In two follow-up

studies, budgerigars, zebra finches, and canaries were tested across a wider range of stimulus

conditions including higher F0s up to 400 Hz (Dooling et al., 2001), and multiple, intermediate C

values between -1 and +1 (Lauer et al., 2006). Note that lower absolute C values produce

stimuli with reduced duty cycles and, consequently, faster instantaneous frequency sweeps

within F0 periods, with C of zero producing an impulse train associated with all components in

cosine phase (Fig. 1). Even over this wider range of conditions, which included faster rates of

instantaneous frequency change that were potentially better suited to the mechanics of the

avian inner ear, birds showed little appreciable difference in masking between Schroeder HTCs

generated with opposite C values (Dooling et al., 2001; Lauer et al., 2006).

The reason for less masking difference between Schroeder HTCs of opposite C polarity

in birds compared to humans is unclear due to limited physiological investigations. One

possibility is that the avian cochlea differs from that of mammals in its impulse response,

perhaps lacking a prominent instantaneous frequency glide [see barn owl auditory-nerve

recordings potentially consistent with this interpretation (Fontaine et al., 2015)], or perhaps

showing a glide that is faster than the rate of frequency change found in Schroeder maskers

from existing behavioral studies. Despite basic physiological similarities between birds and

mammals in auditory-nerve frequency tuning, phase-locking limits, and other response

properties of auditory-nerve fibers (Manley et al., 1985; Sachs et al., 1974), the sensory

epithelium in birds is considerably shorter and wider than in mammals, with dozens of hair cells

spanning its width in apical low-CF regions (Takasaka and Smith, 1971). If these anatomical

differences result in a cochlear impulse response without a prominent frequency glide (see

Fontaine et al., 2015), this could explain less masking difference between Schroeder HTCs of

opposite polarity. While Dooling and colleagues found stronger compound auditory-nerve action

potentials for negative-C Schroeder HTCs in several bird species (Dooling et al., 2002), these

gross potentials are strongly influenced by cross-channel neural synchrony and are therefore

not directly relatable to current hypotheses for human masking asymmetry, based on a single-

channel framework.

To gain further insight into mechanisms of Schroeder masking, and into possible

reasons for minimal Schroeder masking asymmetry in birds, we performed parallel behavioral

and neurophysiological experiments in budgerigars using tones masked by Schroeder HTCs. In

the first experiment, behavioral studies were conducted in animals trained using operant-

conditioning procedures over a wide range of F0 and C values, to improve the possibility of

detecting masking differences between Schroeder C polarities if they exist. To expand upon

prior studies, masking conditions included previously untested C values of ±0.5 at F0s of 200

and 400 Hz. Furthermore, stimuli were presented using a roving-level paradigm for which the

overall masker level was randomly selected on each trial from a 20-dB range centered on 80 dB

SPL (a typical level used in prior studies), thereby diminishing the extent to which overall

loudness and/or single-channel energy cues could be used to perform the task. In the second

neurophysiological experiment, we made recordings in awake passively listening animals of

extracellular activity in the central nucleus of the avian inferior colliculus (IC), which is a large

and nearly obligatory midbrain processing center in the ascending auditory pathway. The IC

shows pronounced temporal and rate-based encoding of acoustic-envelope fluctuations at

amplitude-modulation frequencies up to several hundred Hz (Henry et al., 2017a; Joris et al.,

2004), encompassing the range of envelope frequencies found in Schroeder HTCs. Moreover, a

recent study of gerbil IC revealed neural selectivity for C polarity of Schroeder HTCs based on

average discharge rate and spike timing (Steenken et al., 2022). The present study obtained

budgerigar IC neural responses to Schroeder HTCs across widely ranging F0 and C values and

evaluated the changes in neural activity that occur upon addition of a tone increment to

Schroeder maskers, providing insight into potential neural cues used by animals to perform the

behavioral masked-detection task.

2. Methods

2.1. Behavioral experiments

Behavioral experiments were conducted in four adult budgerigars of either sex (2 male; 2

female) using previously described operant conditioning procedures (Henry and Abrams, 2021;

Henry et al., 2017a; Henry et al., 2020; Henry et al., 2017b; Henry et al., 2016; Wang et al.,

2021; Wong et al., 2019). All procedures were approved by the University of Rochester

Committee on Animal Resources.

2.1.1. Stimuli

Stimuli in the behavioral experiments were Schroeder-phase HTCs presented with or without a

simultaneously-gated 2.8-kHz tone signal. Schroeder HTCs were generated with component

phases scaled according to Schroeder's (1970) algorithm,

$$\theta_n = C\pi n(n + 1)/N$$

where θ_n is the phase of the nth harmonic, N is the total number of harmonics, and C is a scaling

parameter. Harmonic components ranged in frequency from 2F0 to 5000 Hz and were

presented with equal level. The overall level of the masker was 80 dB SPL prior to application of

random level variation for some conditions (i.e., roving-level paradigm; see below).

Consequently, for F0s of 100, 200, and 400 Hz, the number of components included in the

Schroeder masker was 49, 24, and 11, respectively, and the level of individual masker

components prior to roving was 63.10, 66.20, and 69.59 dB SPL, respectively.

Schroeder maskers and pure-tone targets were simultaneously gated on target trials

(50% of all trials) and had a duration of 260 ms, including 20-ms raised-cosine onset and offset

ramps. The phase of the 2.8-kHz pure tone target was equal to that of the masker frequency

component at the same frequency. The masker alone was presented on standard trials.

Threshold signal-to-masker ratios for tone detection are expressed in dB relative to the level of

single masker components, as in previous studies (Kohlrausch and Sander, 1995; Lauer et al.,

2006; Smith et al., 1986).

The first behavioral experiment assessed Schroeder masking in three animals over a

wide range of masking conditions using F0s of 100, 200 and 400 Hz and C values of 0, ±0.5,

and ±1. Testing was conducted using a roving-level paradigm for which the overall stimulus

level on each trial was randomly varied with respect to the mean level based on a uniform

distribution spanning -10 to +10 dB with 1-dB resolution. A second behavioral experiment

compared Schroeder-masked thresholds between fixed-level and roving-level test conditions in

four animals, using F0 of 100 Hz and C values of 0 and ±1. Testing alternated between fixed-

and roving-level conditions within tracking sessions, as described in detail below, to assess the

effect of the roving-level paradigm.

2.1.3. Apparatus

Behavioral experiments were conducted in four identically constructed small-animal acoustic

isolation chambers (0.3 m^3) lined with sound-absorbing foam. Chambers contained a house

light, overhead loudspeaker (Polk Audio MC60; Baltimore, MD), seed dispenser (ENV-203 mini;

Med Associates, St. Albans, VT), feeding trough, small wire-mesh cage with a perch, and three

illuminated response switches. The loudspeaker was positioned 20 cm above the location of the

animal's head during observing responses (see below). Behavioral tests were controlled using

custom MATLAB software (The MathWorks, Natick, MA) running on a PC. Stimulus waveforms

were generated digitally with 50-kHz sampling frequency and converted to analog signals

(National Instruments PCI-6151; Austin, TX) before power amplification (Crown D-75A).

Custom-built electronic equipment was used to process input from the response switches and

control the house light and seed dispenser. Stimuli were calibrated using a pre-emphasis filter

generated based on the output of a ½" precision microphone (Brüel and Kjær type 4134,

Marlborough, MA) in response to 249 log-spaced tone frequencies from 50-15,100 Hz. The pre-

emphasis filter corrected the stimulus spectrum for the frequency response of the loudspeaker

system prior to analog conversion.

2.1.4. Procedure

Budgerigars were trained using operant-conditioning procedures to perform a single-interval,

two-alternative, auditory discrimination task. Birds initiated a trial by pecking the center

observing-response switch, resulting in presentation of a single stimulus. The stimulus was

either a standard Schroeder HTC masker or target with a tone signal added to the masker.

Standard and target stimuli were presented with equal probability of 0.5. The correct response

to the standard stimulus was the right switch and the correct response to the target stimulus

was the left switch. Animals had 3 seconds to report a response following stimulus onset.

Correct responses were reinforced with delivery of hulled millet seeds, whereas incorrect

responses resulted in a 5-s timeout during which the house light was turned off. The trial was

aborted in rare instances for which animals did not report a response (<0.2% of trials). The

number of millet seeds was adaptively varied (1 or 2 seeds) using an automated procedure to

control response bias. Bias was calculated based on the most recent 50 trials as 0.5 times the

sum of the Z scores of the hit and false-alarm rates (Macmillan and Creelman, 1991). Bias was

controlled to stay near zero by delivering additional seeds for correct responses made with the

switch the animal was biased against. Testing was conducted 6-7 days per week during

morning and afternoon blocks separated by four hours, and consisting of several hundred trials

each.

233   Animals were initially trained to behaviorally discriminate the target stimulus from the

standard at a relatively high signal level of 10 dB re: masker component level. Once 90%

correct discrimination performance was attained, masked thresholds were tested repeatedly

using two-down one-up adaptive-tracking procedures (Levitt, 1971). Behavioral-tracking

sessions began at a signal level of 10 dB re: masker component level. The signal level was

reduced following every two consecutive correct responses to target trials (hits) with the same

signal level, and increased following every incorrect response to a target trial (miss). Responses

on standard trials (false alarms and correct rejections) were reinforced but did not affect the

signal level of the track. The step size of the tracking procedure was varied based on the

number of reversals (upward to downward or vice versa) of the signal-level track across target

trials. The initial step size of 3 dB was decreased to 2 dB after 2 reversals and to 1 dB after 4

reversals. Tracks continued for at least 15 reversals until the signal level of the final eight track

reversal met two stability criteria. Both (1) the standard deviation of the final eight reversal

values and (2) the difference between the means of the first and second sets of four reversals in

the final eight were required to be less than 3 dB (i.e., the track had to be consistent, without an

upward or downward trend of the final reversal points). Tracks for which the overall absolute

bias exceeded 0.3 were excluded from further analysis.

For the first experiment, the mean of the final eight reversal values was taken as the

track threshold. For the second experiment, extended-duration tracks (Wang et al., 2021) were

used to evaluate the effect of roving stimulus level on Schroeder-masked tone detection within

sessions, and fewer tracks were completed daily. For extended tracks, the masker level

remained fixed at 80 dB SPL until the stability criteria described above were satisfied. This initial

portion of the track provided reversal points for calculation of the fixed-level masked threshold.

Thereafter, the track was continued (without resetting the signal level) for an additional 10

reversals under the roving-level condition (±10 dB across-trial variation in masker level with

respect to the fixed masker level from the first part of the track) until the track stability criteria

were once again satisfied. This second portion of the track was used to calculate the roving-

level threshold (based on the final eight reversal points as above).

For both experiments, tracking sessions were conducted repeatedly on the same

stimulus condition until at least 13 unbiased thresholds (or threshold pairs for experiment 2)

were obtained, with absolute response bias less than 0.3, and two across-track stability criteria

were satisfied. Both (1) the standard deviation of the final six unbiased track thresholds and (2)

the mean difference between the first and second half of the final six unbiased thresholds were

required to be less than 3 dB. For both experiments, stimulus conditions were tested in different

random sequences across animals. Animals were tested 2-4 times on each condition, with each

testing period separated by testing on the other conditions.

2.1.4. Analysis

The last 25 unbiased-track thresholds were averaged to calculate masked thresholds of

individual animals on each condition. Thresholds were analyzed in R (v. 4.1.3) using linear

mixed-effect models (Bates et al., 2015). Models incorporated random intercepts for each

animal subject, to account for repeated observations, and included fixed effects of F0, C, and

roving level (for experiment two). Two-way interactions were included and dropped when not

significant ($p > 0.05$) in order of decreasing p value. Degrees of freedom for post-hoc t-tests

were calculated based on the Satterthwaite approximation.

2.2 Neurophysiological recordings

Neurophysiological recordings were made from the IC in four adult budgerigars of either sex

(two male; two female) using previously reported procedures (Henry et al., 2017a; Henry et al.,

2016; Wang et al., 2021). Different animals were used for neural recordings than those from the

behavioral experiments. All procedures were approved by the University of Rochester

Committee on Animal Resources.

2.2.1 Neural implantation procedure

A probe assembly consisting of 1-2 microelectrodes mounted to a miniature microdrive was

implanted into the right IC under anesthesia using a stereotaxic approach. Microelectrodes were

either single pure iridium wires or four-channel silicon probes with impedance ranging from 1.5-

3 MΩ. Anesthesia was induced with subcutaneous injection of ketamine (3-5 mg/kg) and

dexmedetomidine (0.08-0.1 mg/kg), and maintained throughout the 2-3 h implantation surgery

with slow subcutaneous infusion of the same agents (ketamine: 6-10 mg/kg/h;

dexmedetomidine: 0.16-0.27 mg/kg/h) in lactated ringers solution. When possible, electrodes

were initially implanted superficially in the dorsal region of the IC tuned to low frequencies. This

method allowed sampling of response regions tuned to higher CFs by advancing the electrodes

deeper into the IC across recording sessions with the microdrive control screw. Electrodes were

typically advanced 30 um between recording sessions. In total, recordings were made from 142

multi-unit sites and 8 sites with well-isolated single-unit activity (criteria described below).

2.2.2. Apparatus

Neurophysiological recordings were made with animals perched in a small wire-mesh cage

located inside a walk-in acoustic isolation chamber. The chamber was lined with sound-

absorbing foam and contained a loudspeaker (MC60, Polk Audio) positioned 45 cm from the

normal location of the animal's head in the same horizontal plane. A closed-circuit video system

was monitored to ensure that animals remained perched and facing the loudspeaker throughout

recording sessions.

Stimuli were generated in MATLAB with a sampling frequency of 50 kHz and converted

to analog at full scale using a data acquisition card (±10V; PCIe-6251, National Instruments).

Signals were then attenuated to the specified level (PA5; Tucker-Davis Technologies) followed

by power amplification (D-75A, Crown Audio). Stimulus calibration was accomplished with a

digital "pre-emphasis" filter that compensated for the frequency response of the system. The

filter was designed based on the output of a 0.25" precision microphone (type 4938, Brüel &

Kjær) placed at the location of the animal's head in response to 249 log-space tone pips ranging

in frequency from 0.05-15.1 kHz.

Neural recordings were made using a multi-channel recording system (RHD2132

amplifier chip and C3100 USB interface board, Intan Technologies), referenced to one of the

anchor screws for the microdrive assembly. Recordings were high-pass filtered at 150 Hz and

sampled on the amplifier chip at 30 kHz for storage on the computer hard drive. In post

processing, recordings were resampled at 50 kHz and band-pass filtered from 0.75-10 kHz

(1000-point finite impulse response) to reduce local field potentials. Thereafter, a third-order

Teager-energy operation (Choi et al., 2006; Wang et al., 2021) was applied for spike detection

based on a visually determined threshold criterion. Sessions with consistent spike shape and

spike amplitude through the recording period and less than 1% of inter-spike intervals less than

1 ms were classified as single-unit sessions. Both single- and multi-unit recordings were

analyzed, as described below.

2.3.3. Stimuli

Stimuli used in neurophysiological recordings were pure tones for determination of the

frequency response map, sinusoidally amplitude-modulated (SAM) tones, Schroeder-phase

HTCs, and Schroeder-phase HTCs with an added tone. The frequency response map shows

average discharge rate as a function of stimulus frequency and level. Tone stimuli for the

response map ranged in frequency from 0.25-8.0 kHz with 8 steps per octave, and were

presented at levels from 15-75 dB SPL in 10-dB steps. Tone duration was 100 ms including 10-

ms raised-cosine onset and offset ramps. Stimuli were presented in random sequence with

three repetitions of each frequency-level combination, and 250-ms of silence between

successive stimuli.

SAM tones were used to characterize modulation tuning of each recording site with a

modulation-transfer-function (MTF) approach. The MTF shows average discharge rate as a

function of stimulus modulation frequency. Stimuli had modulation frequencies ranging from 4 to

1024 Hz with 3 steps per octave and carrier frequency equal to the estimated CF. Overall level

was 65 dB SPL and the depth of modulation was 0 dB (100%), except for the case of an

unmodulated CF tone also included in the stimulus set. Stimulus duration was 800 ms including

50-ms raised-cosine onset and offset ramps. MTF stimuli were presented in random sequence
for 5 or 10 repetitions with 350-ms of silence between stimuli.

Responses to Schroeder HTCs were obtained for F0s of 50, 100, 200, and 400 Hz and
C values from -1 to +1 with a step size of 0.25. Harmonic frequency components between 250
Hz and 5000 Hz (inclusive) were included in the stimulus, and overall level was scaled to 60 dB
SPL. Stimuli were 400 ms in duration, including 25-ms raised-cosine onset and offset ramps,
presented for 20 repetitions in random sequence with 200 ms of silence between stimuli.

Responses to Schroeder-maskers with an added tone signal were obtained for masker
F0s of 100, 200, and 400 Hz and C values from -1 to +1 with a step size of 0.5. Frequency
components between 200 Hz and 5000 Hz (inclusive) were included in the masker, tone
frequency was equal to that of the nearest masker component to CF, and tone phase was equal
to that of the masker component at the same frequency. Tone and masker were simultaneously
gated with a duration of 260 ms, 20-ms onset and offset ramps, and 250 ms of silence between
stimuli. Signal level re: single masker components ranged from -33 to 0 dB, spanning the
observed range of behavioral thresholds, and included a masker with no added tone signal to
allow estimation of masked neural detection thresholds (see below). The overall level of the
masker was 60 dB SPL. Stimuli were presented in random sequences, with 20 repetitions of
each stimulus condition.

2.3.4. Analyses

CF was determined from frequency response maps as the stimulus frequency at which the
neural response was most sensitive (i.e., responded at the lowest sound level). Best modulation
frequency was defined as the modulation frequency of the MTF peak, and the amplitude of
modulation tuning was estimated as the percent difference between the peak MTF rate and the
response rate for the unmodulated stimulus.

Neural responses to Schroeder HTCs were quantified with both an average-rate analysis
and a temporal metric calculated as the peak-to-peak amplitude of single-trial period
histograms. The temporal metric quantifies the mean amplitude of instantaneous rate
fluctuations at F0 and is hereafter called "rate fluctuation" for brevity. Rate fluctuation was
calculated after first integrating each single-trial spike-train response over a duration equal to
$1/25^{th}$ of the F0 period for F0s up to 200 Hz (50 Hz: 0.8 ms; 100 Hz: 0.4 ms; 200 Hz: 0.2 ms)
and over 0.2 ms for F0 of 400 Hz. Schroeder bias was calculated for both average rate and rate
fluctuation as the mean response difference between positive and negative Schroeder polarities

divided by the pooled standard deviation. Hence, positive (negative) values indicate a greater

response amplitude for the positive (negative) Schroeder stimulus and the magnitude of bias

metric relates to separation between the means in terms of standard deviation, as in a d-prime

analysis (Egan, 1975).

Neural thresholds for detection of a CF tone added to a Schroeder HTC were estimated

from neurophysiological data using receiver-operating characteristic (ROC) analysis (Egan,

1975). For each tone level presented, the discrimination performance of the neuron was

calculated as the area under the ROC curve between the response distribution observed for the

masker alone and the distribution for the tone-plus-masker stimulus. Area under the ROC curve

corresponds to the percent separation (100 – percent overlap) between the response

distributions. Response distributions were based on 20 stimulus repetitions. The function

describing discrimination performance across signal levels was linearly interpolated with 0.1-dB

resolution and inverted (i.e., 100 – discrimination performance) in cases for which performance

at the highest signal-to-masker ratio was less than 50% correct. Threshold was defined as the

highest signal-to-masker ratio above which discrimination performance consistently exceeded

70.7% correct, which is the average correct performance of an unbiased theoretical observer

performing a two-down one-up track (Levitt, 1971).

3. Results

3.1. Behavioral Results

3.1.1. Effects of F0 and C on Schroeder-masked thresholds

Budgerigars were trained with operant-condition procedures to detect a 2.8-kHz tone added to a

Schroeder HTC masker. Masked detection thresholds were tested in three animals using two-

down one-up tracking procedures (Fig. 2A) and a ±10-dB roving-level paradigm that reduces the

utility of single-channel energy cues for performing the task. Maskers had F0 of 100, 200, or 400

Hz and C values of -1, -0.5, 0, +0.5, or 1 (15 conditions). Each animal completed the experiment

over a period of 8-9 months consisting of 850-950 test sessions.

Fig. 2. Representative results of two-down one-up tracking sessions in trained budgerigars. Tracks show variation in signal level across trials.. Roving-level tracks (A) are obtained with ±10-dB random variation in stimulus level across trials that reduces the utility of single-channel energy cues for performing the task. Extended tracks (B) transition from a fixed- (black) to the roving-level (blue) test procedure within sessions. Crosses indicate final reversal points used to calculate track thresholds, given above each track in dB. F0 is 100 Hz and C is +1.

Schroeder-masked behavioral thresholds of individual animals were obtained for each

condition (Fig. 3A) based on the final 25 unbiased tracks. Masked thresholds increased for

higher F0 values and for greater absolute C values, with C values of ±0.5 producing

intermediate thresholds between C of zero, for which thresholds were lowest, and C of ±1, for

which thresholds were highest. A mixed-effects model analysis of masked thresholds showed

significant effects of F0 ($F_{2,28}$=34.14, p<0.0001), C ($F_{4,28}$=17.59, p<0.0001), and the F0-by-C

interaction ($F_{8,28}$=2.76, p=0.0220). The interaction was due to greater elevation of thresholds

with increasing F0 for C of zero and ±0.5 compared to ±1. No significant differences in threshold

were observed between negative and positive polarities of the same C value at F0s of 100 Hz

(C ±1: -1.77 ±1.85 dB; t_{28}=-0.96, p=0.35; C ±0.5: -2.55 ±1.85 dB; t_{28}=-1.38, p=0.18), 200 Hz (C

±1: 2.02 ±1.85 dB; t_{28}=1.09, p=0.28; C ±0.5: 1.39 ±1.85 dB; t_{28}=0.75, p=0.46), or 400 Hz (C ±1:

1.12 ±1.85 dB; t_{28}=0.60, p=0.55; C ±0.5: -0.46 ±1.85 dB; t_{28}=-0.25, p=0.80; least-squared mean

difference ±1 SE and pairwise comparisons of least-squared means). These results indicate no

asymmetry of tone masking by Schroeder HTCs in the budgerigar.

Fig. 3. Behavioral thresholds of individual budgerigars for detection of a tone signal masked by a Schroeder HTC (A). Trend lines and error bars are means and across-subject standard deviations, respectively. Budgerigar Schroeder-masked tone thresholds increase for higher F0s, increase for higher absolute C values, and are similar between opposite polarities of the same C value. Mean thresholds from the current study compared to previously published results from humans and other budgerigar studies (B). Budgerigars show less masking difference between positive and negative C value than humans.

Several previous studies quantified Schroeder masking in budgerigars and humans

using similar stimulus parameters (Fig 3B). Studies by Dooling et al. (2001; budgerigars) and

Lauer et al. (2006; budgerigars and humans) used the same tone frequency of 2.8 kHz as in the

present study, whereas Kohlrausch and Sander (1995; humans) used tone frequencies of 2.2

and 4.4 kHz. In general, the budgerigar thresholds reported previously for F0 of 100 Hz (Dooling

et al., 2001; Lauer et al., 2006) appear similar to those from the present study, showing the

same V-shaped pattern with a minimum at C of approximately zero (Fig. 3B; blue symbols, left

column). In contrast, prior budgerigar thresholds at 200 Hz (Fig. 3B, middle column) and 400 Hz

(Fig. 3B, right column) are considerably higher and lower (Dooling et al., 2001), respectively,

than those of the present study. Compared to previously published human results (Kohlrausch

and Sander, 1995; Lauer et al., 2006) (Fig. 3B, red symbols), our findings suggest less

threshold difference in budgerigars between Schroeder maskers with opposite C values.

Furthermore, budgerigars in the present study showed less increase in masked thresholds for

higher F0 values than has been reported in humans, and intriguingly, appear substantially more

sensitive than human subjects for F0 of 400 Hz and at all C values except +1 for F0 of 200 Hz.

3.1.2. Roving-level paradigm

One difference between our study and previous studies of masking by Schroeder HTCs is that

we used a roving-level paradigm for which a ±10 dB perturbation was applied to the stimulus

level on each single-interval trial, while previous studies fixed the masker level, often at 80 dB

SPL. A second experiment was conducted in four animals to evaluate the extent to which roving

stimulus level impacted behavioral thresholds. C values of -1, zero, and +1 were tested using

F0 of 100 Hz. The rove effect was assessed by transitioning from a fixed-level (80 dB SPL

masker level) to roving-level test procedure (70-90 dB SPL masker level) partway through

individual tracking sessions (Fig. 2B). Each animal completed the experiment over 2-3 months

and 200-300 sessions.

Fig. 4. Behavioral Schroeder-masking thresholds of budgerigars from the second experiment comparing
performance under fixed- and roving-level test conditions. Trend lines and error bars indicate means and cross-
subject standard deviations, respectively. F0 is 100 Hz. Budgerigars showed little of no effect of roving stimulus level
on Schroeder masking thresholds.

Behavioral tracks showed decreasing tone level over the first 10-20 trials before
stabilizing at the animal's fixed-level thresholds, similar to roving-level tracks described above.
Furthermore, most tracks showed no apparent change in tone level following the onset of the
roving-level test period (Fig. 2B). Fixed-level masked thresholds calculated based on the final
25 unbiased tracking sessions (i.e., from portions of tracks prior to the rove onset) were lower
for C of zero than for C of ±1 and similar between C values of -1 and 1 (Fig. 4A). These findings
are consistent with results of the first behavioral experiment. Masked thresholds calculated from
the roving-level part of tracks showed essentially the same pattern (Fig. 4B), suggesting minimal
impact of this stimulus perturbation that makes single-channel energy cues less informative.
Finally, roving-level threshold shifts calculated from individual test sessions were generally near
zero (Fig. 4C), though one animal (B34) showed a mean roving-level shift of 4 dB for C of zero
only.

A mixed-effects model analysis of fixed- and roving-level thresholds showed a significant
effect of C value ($F_{2,15}$=69.57, p<0.0001) but no significant impact of roving level ($F_{1,15}$=0.12,
p=0.74) or the C value by roving-level interaction ($F_{2,15}$=0.054, p=0.95). Thresholds were lower
for C of zero than for C of -1 (-11.15 ±1.14 dB; t_{15}=-9.82, p<0.0001) or +1 (-12.00 ±1.14 dB; t_{15}=-
10.57, p<0.0001; pairwise comparison of least-squared means ±1 SE), and similar between C
values of -1 and +1 (-0.85 ±0.75 dB; t_{15}=-0.75, p=0.47). The estimated effect of roving stimulus
level was -0.32 ±0.93 dB (i.e., not significant; t_{15}=-0.34, p=0.74). An ANOVA of within-track
threshold shifts during the roving-level portion of tracks showed no significant intercept (-0.42
±0.90 dB; $t_{8.9}$=-0.46, p=0.65; i.e., mean roving-level shifts were not significantly different than
zero) or effect of C ($F_{2,6}$=0.18, p=0.84), consistent with results of the mixed-model analysis.

In summary, results from the two behavioral experiments support prior findings that
Schroeder HTCs generated with positive and negative C values produce similar masking of a
simultaneously presented tone signal in budgerigars. This result contrasts with prior human
studies showing lower thresholds for Schroeder HTCs generated with positive C values
(Kohlrausch and Sander, 1995; Lauer et al., 2006; Smith et al., 1986). Budgerigars also showed
less apparent threshold elevation with increasing masker F0 than has been reported in humans.
Finally, budgerigar thresholds were largely unaffected by the roving-level paradigm, suggesting
that the animals used cues other than single-channel energy level to perform the masked-
detection task.

3.2. Neurophysiological Results

3.2.1. Neural frequency and amplitude-modulation tuning

Neurophysiological recordings were made from the budgerigar IC in awake animals (n=4; 142

multi-unit and 8 single-unit recording sites) to explore possible neural cues used by animals for

Schroeder-masked tone detection. Detailed analyses of basic frequency tuning and modulation

tuning in the budgerigar IC have been reported previously (Henry et al., 2017a; Henry et al.,

2016; Wang et al., 2021). Briefly, frequency response maps of recorded IC neurons showed V-

shaped excitatory tuning curves in response to tones (Fig. 5A), with thresholds at CF often

falling below 20 dB SPL. CFs ranging from 0.54-5.6 kHz with a median value of 2.59 kHz.

A. Frequency response maps

B. Modulation transfer functions

Figure 5. Basic tuning properties of recorded budgerigar IC neurons. Frequency response maps (A) show average rate as a function of tone frequency and level. SU: single unit; MU: multi unit; subsequent unit identification codes are arbitrary. Characteristic frequency (CF) increases from left to right. Modulation transfer functions (B) of the same recording sites in A, showing average response rate to sinusoidally amplitude-modulated tones across modulation frequencies. BMF: best modulation frequency. Dotted blue lines indicate the response rate to the unmodulated carrier signals. Carrier frequency is within ±1/6 octave of estimated CF.

An emergent response property at the IC processing level in birds and mammals is

modulation tuning of average discharge rate in response to stimulus envelope fluctuations,

typically quantified with SAM tones and a MTF approach (Fig. 5B) (Joris et al., 2004; Langner

and Schreiner, 1988; Nelson and Carney, 2007; Woolley and Casseday, 2005). Most recorded

budgerigar IC neurons exhibited some degree of band-enhanced modulation tuning (Kim et al.,

2020) (i.e., 117 out of 125 units for which modulation transfer functions were obtained). That is,

MTFs (Fig. 5B) showed greater response rate for a limited band of stimulus modulation

frequencies compared to the unmodulated stimulus. Best modulation frequency (BMF), which is

the modulation frequency associated with the peak rate of the MTF, ranged from 128-700 Hz

across recorded neurons with a median value of 406 Hz. Neurons not showing band-enhanced

modulation tuning had high-pass MTFs in all cases (n=8). The amplitude of modulation tuning,

defined as the percent difference between the MTF peak and the response rate for the

unmodulated stimulus (i.e., blue dotted lines in Fig. 5B), ranged from 22.5% to 199.8% with a

median value of 120.5%.

3.2.2. Effects of F0 and C on neural responses to Schroeder-phase HTCs without an added

tone

Neurophysiological recordings made in response to Schroeder HTCs without an added

tone showed robust fluctuations of discharge rate within F0 periods across the full range of F0

and C values studied (e.g., Figs 6A and 7A). Results from two representative IC units illustrate

some of the diversity observed in Schroeder responses across neurons. Results from one

neuron (Fig. 6) showed generally similar average rate and rate fluctuation (locked to F0

periodicity) between Schroeder HTC with opposite C values, but with moderate bias of rate

fluctuation toward the positive Schroeder for F0 of 200 Hz and C values greater than

approximately 0.5. In contrast, responses from a second neural recording (Fig. 7) showed

pronounced bias toward the negative Schroeder, for both average rate and rate fluctuation,

across most stimulus conditions tested.

A. Period histograms

SU 124-20.3 CF=1.90 kHz

— Positive Schroeder
— Negative Schroeder

F_0 = 50 Hz   200 Hz

C = 0

±0.25

±0.5

±0.75

±1

0   π   2π   0   π   2π

Phase (radians)

B.

Rate (spikes/s)

Rate fluctuation (spikes/s/100)

C magnitude

Fig. 6. Representative neural responses to Schroeder-phase HTCs of variable F0 and C value. Period histograms (A) illustrate variation in average discharge rate over two cycles of F0. F0 is indicated at the top of each column and C magnitude given to the left. (B) Single-trial average discharge rate (top) and F0 rate fluctuation plotted as a function of C value for two different F0s (left: 50 Hz; right: 200 Hz). Trend lines and error bars show means and across-trial standard deviation. Note bias of F0 rate fluctuation toward the positive Schroeder for 200 Hz F0 and absolute C values greater than 0.5. CF was 1.90 kHz.

A. Period histograms

MU 121-43.3 CF=0.85 kHz

– Positive Schroeder
– Negative Schroeder

F_0 = 50 Hz   200 Hz

C = 0

±0.25

±0.5

±0.75

±1

Phase (radians)

B.

Rate (spikes/s)

Rate fluctuation (spikes/s/100)

C magnitude

Fig. 7. Representative neural responses as in Figure 5, but for a different unit. Note widespread bias of average discharge rate and F0 rate toward the negative Schroeder, most prominently for moderate-to-high absolute C values. CF was 0.85 kHz.

To characterize patterns of Schroeder response selectivity across the neural population,

we calculated a Schroeder bias metric as the mean response difference between positive and

negative Schroeder polarities divided by the pooled standard deviation. Positive (negative) bias

values indicate greater response amplitude for the positive (negative) Schroeder polarity. Figure

8 shows Schroeder bias of rate fluctuation as a function of CF for each combination of stimulus

F0 and C magnitude tested. Sample size was 146 for C of ±0.25 and ±0.75, and 150 for C of

±0.5 and ±1. Schroeder bias varied considerably across recorded IC neurons, ranging from

negative to positive values for many conditions even among neurons of the same CF.

Furthermore, mean Schroeder bias of the neural population increased with increasing CF,

especially at high F0s and for higher absolute values of C (Fig. 8). The transition from negative

to positive bias with increasing CF occurred at CF of ~3 kHz. Schroeder bias of single units (Fig.

8, magenta circles) fell within the range observed for multi units of the same CF. Pearson

correlations (Fig. 8; top left corner of each plot) showed that the relationship between CF and

Schroeder bias was significantly positive for all stimulus conditions. Schroeder bias of average

response rate followed the same general patterns reported above for rate fluctuation (Fig. 9).

Fig. 8. Schroeder bias of response rate fluctuation, plotted as a function of CF for all stimulus conditions. F0 is indicated at the top of each column and absolute C values are given on the right. Thick blue lines are predicted values from a linear fit to the data. Pearson correlations and associated p values are reported in the top left corner of each panel. The number of recorded units is 146 for C of ±0.25 and ±0.75, and 150 for C of ±0.5 and ±1.

Fig. 9. As for Fig. 8, but with Schroeder bias calculated based on average response rate.

3.2.3. Neural thresholds for detection of Schroeder-masked tones

The changes in neural activity that could be used by behaving animals to detect tones masked by a Schroeder HTC were evaluated by recording IC neural responses to Schroeder-masked tone signals in a subset of units. Sample sizes were 92 for F0 of 100 Hz, 67 for F0 of 200 Hz, and 64 for F0 of 400 Hz. Masker level was 60 dB SPL and for each recording site, the signal frequency was set equal to that of the masker component nearest to CF. Thresholds were evaluated using ROC analyses, as the minimum signal level above which the area under the ROC curve (i.e., discrimination performance) consistently exceeded 70.7% correct. As illustrated in Fig. 10, many neural responses showed a pronounced reduction in activity as signal level increased. Neural threshold in these units was therefore based on a response decrement compared to the masker-alone condition (Fig. 10A, columns 1, 2, and 4; Fig. 10B).

While perhaps counterintuitive, given that increasing signal level elevates the overall energy

level of the stimulus, the finding is consistent with expectations for modulation-tuned IC neurons

because increasing the signal level flattens the envelope of the peripheral response, and these

neurons exhibit reduced response activity for sounds with weaker envelope fluctuations (Henry

et al., 2017a; Henry et al., 2016; Krishna and Semple, 2000; Nelson and Carney, 2007). In

contrast, detection thresholds of other neurons were based on response activity that increased

with signal level (Fig. 10A, column 3; Fig. 10B, column 2, red), or non-monotonic response

trajectories that elevated (Fig. 10A, column 4; Fig. 10B, column 2, blue) or precluded threshold

estimation altogether. Note that different response profiles were sometimes observed in the

same unit for opposite C values of the same masker F0 (e.g., Fig. 10A, columns 3 & 4; Fig. 10B,

column 2).

A. Period histograms

MU 121-10.1, CF=2.90 kHz   MU 121-75.1, CF=3.38 kHz

Signal level $C = +0.5$ -0.5 $+1$ -1

none

-30 dB

-24

-18

-12

-6

Phase (radians)

B.

$C = \pm0.5$ ±1 — Pos. C — Neg. C

Rate (spikes/s)

Rate fluctuation (spikes/s/100)

Signal level (dB re. masker component)

Fig. 10. Representative neural responses to near-CF tones masked by Schroeder HTCs. Two-cycle period histograms (A) for a range of tone levels (indicated left) in two neurons; F0 is 400 Hz and C is ±0.5 (columns 1 and 2; first neuron) or ±1 (columns 3 and 4; second neuron). Response functions (B) show average discharge rate (top) and rate fluctuation (bottom) as a function of tone level. Downward pointing arrows indicate neural thresholds above which detection performance consistently exceeds 70.7% correct. Trend lines indicate cross-trial means and standard deviations. *None:* masker alone with no tone.

Neural detection thresholds based on rate fluctuation are shown for the population of

neurons as a function CF (Fig. 11). Among neurons with a measurable tone-detection threshold

(29-82% of neurons dependent on condition), threshold was in most cases based on decreasing

discharge rate consistent with IC modulation tuning (Fig. 11, blue circles and text) rather than a

rate increase (Fig. 11; red triangles and text). Among neurons with CFs within ±¼ octave of the

2800-Hz signal frequency of behavioral experiments, thresholds increased for higher absolute C

values (see medians and interquartile ranges in Fig. 11) and were similar between opposite

polarities of the same C value, consistent with behavioral results (Fig. 11, large black circles).

The mean value of measurable neural thresholds in this CF range was similar between negative

and positive polarities of the same C value at F0s of 100 Hz (C ±1: 0.94 ±2.89 dB; t_{23}=0.32,

p=0.75; C ±0.5: 0.53 ±2.34 dB; t_{25}=0.23, p=0.82), 200 Hz (C ±1: -2.84 ±2.67 dB; t_{39}=-1.06,

p=0.30; C ±0.5: 1.79 ±2.85 dB; t_{50}=0.63, p=0.53), or 400 Hz (C ±1: -0.46 ±2.15 dB; t_{37}=-0.21,

p=0.83; C ±0.5: 2.10 ±2.17 dB; t_{37}=0.97, p=0.34; mean threshold differences between negative

and positive C value ±1 SE, and two-sample t-tests). On the other hand, whereas behavioral

thresholds increased for higher F0s, neural thresholds showed the opposite pattern of lower

values for higher F0s. Consequently, the most sensitive neural thresholds approximated

behavioral thresholds for F0 of 100 Hz but were considerably more sensitive than behavioral

performance for F0s of 100 and 200 Hz. Analyses of neural thresholds based on average rate

produced the same conclusions (Fig. 12).

Fig. 11. Neural thresholds for Schroder-masked tone detection based on rate fluctuation, plotted against CF. Tone frequency is the nearest harmonic frequency to CF and is within ±1/6 octave for all recordings. Masker level is 60 dB SPL. Threshold decreases for lower absolute C values, appears similar between opposite polarities of C, and increases for the lowest F0. Behavioral means are from Fig. 3. IQR: interquartile range. The total number of recorded units is 92 for F0 of 100 Hz, 67 for F0 of 200 Hz, and 64 for F0 of 400 Hz.

Fig. 12. As for Fig. 11, but with neural thresholds calculated based on average rate. The total number of recorded units is 92 for F0 of 100 Hz, 67 for F0 of 200 Hz, and 64 for F0 of 400 Hz.

3.2.4 Effects of Schroeder bias on neural masked-tone sensitivity

Finally, we evaluated the extent to which more extreme levels of Schroeder bias, as tended to

occur in neurons with low and high CFs (see Fig. 8), might influence Schroeder-masked

sensitivity to tones near CF. Separate analyses were conducted of signal thresholds assessed

in Schroeder maskers with positive and negative C values. For F0s of 200 and 400 Hz, neurons

with greater bias toward the positive Schroeder had lower tone-detection thresholds in the

positive Schroeder masker (Fig. 13). Separation of neural data into low-, mid-, and high-CF

ranges (Fig. 13, different symbols) further demonstrated that threshold variation was associated

with the bias metric rather than CF per se. These results are broadly consistent with the premise

from psychophysical studies that a peakier physiological response to the masker should

enhance sensitivity to an added tone (Smith et al., 1986). On the other hand, neural thresholds

for F0 of 100 Hz (both masker polarities; Fig. 13, top row), and for all maskers with negative C

values (p=0.08-0.58), showed no significant association with Schroeder bias. Analyses of

response metrics based on average rate produced the same conclusions (Fig. 14). Taken

together, these results suggest that pronounced bias toward the positive-C Schroeder HTC can

in fact enhance neural sensitivity for an added tone.

Fig. 13. Neural thresholds for masked tone detection in positive Schroeder HTCs as a function of Schroeder bias observed for the same absolute C value. Both response metrics are based on rate fluctuation. Trend lines are a linear fit to the data excluding units with no threshold. Pearson correlations are reported in the lower left of each panel. Sample sizes are 30 and 26 for row 1 (left to right), 39 and 34 for row 2, and 37 and 39 for row 3. Greater positive-Schroeder bias is associated with lower masked thresholds for C values of +0.5 and +1 at F0s of 200 and 400 Hz.

Fig. 14. As for Fig. 13, but with neural thresholds and Schroeder bias calculated based on average rate. Sample sizes are 25 and 35 for row 1 (left to right), 46 and 32 for row 2, and 42 and 38 for row 3.

4. Discussion

Budgerigar behavioral thresholds for detection of a 2.8-kHz tone signal masked by a Schroeder-

phase HTC were similar between C values of opposite polarity. Behavioral thresholds

decreased for lower F0s, decreased for lower absolute C values, and were relatively unaffected

by a roving-level paradigm that degrades the utility of single-channel energy cues for masked

detection. Reponses of IC neurons to Schroeder HTCs showed considerable asymmetry

between Schroeder HTCs with opposite C values in many cases, transitioning from average

response bias toward the negative Schroeder at CFs less than 2-3 kHz to average response

bias toward the positive Schroeder for higher CFs, but with substantial variability at any given

CF. Neural thresholds for detection of Schroeder-masked tones near CF varied widely across IC

units and were most often based on a response decrement upon addition of the tone signal,

consistent with band-enhanced modulation tuning in IC neurons. Neural thresholds were

generally similar between masker polarities, in agreement with behavioral results, though
somewhat different effects of F0 were observed between behavioral and neurophysiological
datasets. Finally, budgerigar IC neurons with pronounced bias toward the positive Schroeder
HTC, as observed at high CFs, showed enhanced sensitivity to tones masked by positive
Schroeder HTCs.

Behavioral results from the current study were largely consistent with prior studies of
Schroeder masking in budgerigars, showing lowest thresholds for C values near zero (Lauer et
al., 2006) and generally similar thresholds between Schroeder maskers of opposite polarity
(Dooling et al., 2001; Lauer et al., 2006; Leek et al., 2000). That is, budgerigars showed
symmetric V-shaped Schroeder masking as a function of C value. On the other hand, Dooling et
al. (2001) found a different effect of masker F0 in budgerigars than was observed here, using C
values of +1 and -1 and a fixed masker level of 80 dB SPL. Whereas thresholds in the current
study increased monotonically with increasing F0, the earlier study found a substantial threshold
reduction of 10-15 dB between F0s of 200 Hz and 400 Hz (Dooling et al., 2001). While the
reason for this discrepancy is unknown, one difference between studies was that the current
work used a roving-level paradigm to explore F0 effects, for which masker level varied randomly
from 70-90 dB SPL across trials. The roving-level paradigm degrades the utility of single-
channel energy cues for performing masked-detection tasks (Kidd et al., 1989; Richards, 1992).
If animals in the prior fixed-level behavioral study relied more on single-channel energy cues for
tone detection in maskers with F0 of 400 Hz,, disruption of the energy cue with the roving-level
paradigm here could plausibly explain divergent F0 effects between our studies.

Schroeder-masked thresholds of human subjects can be 15-20 dB lower for maskers
with positive C values compared to negative, depending on signal frequency, F0, and other
factors (Kohlrausch and Sander, 1995; Lauer et al., 2006; Smith et al., 1986). These findings in
humans are fundamentally different from the essentially symmetric V-shaped behavioral
masking functions observed here, in prior studies of budgerigars, and in prior studies of other
avian species including zebra finches and domestic canary (Dooling et al., 2001; Lauer et al.,
2006; Leek et al., 2000). Unfortunately, behavioral studies of Schroeder masking have not yet
been conducted in any nonhuman mammalian species, precluding comparison to our results.
Compared to human results obtained with similar stimulus parameters to the present study,
budgerigar thresholds at F0 of 100 Hz appear reasonably well matched to human data for C
values from -1 to zero, but increase substantially between C of zero and +1 whereas human
thresholds remain low across the same range (Kohlrausch and Sander, 1995; Lauer et al.,
2006; Smith et al., 1986). Intriguingly, human studies have in fact found budgerigar-like V-

shaped Schroeder-masking functions for signal frequencies of 250 Hz and below (Oxenham

and Dau, 2001) and in listeners with sensorineural hearing loss (Summers and Leek, 1998).

These results are perhaps attributable to reduced strength of fast-acting nonlinear cochlear gain

(compression) at apical cochlear locations and in individuals with hearing loss.

Comparing masker-F0 effects on tone detection between species, while both

budgerigars from the present study (but not Dooling et al., 2001) and humans show increasing

thresholds for higher masker F0s, the differences are considerably more pronounced in the

human data (Kohlrausch and Sander, 1995; Oxenham and Dau, 2001). For example, human

thresholds for C of zero increase by ~25 dB between F0s of 100 and 400 Hz (Kohlrausch and

Sander, 1995), whereas budgerigar thresholds increased by just 10 dB over the same F0 range.

Consequently, budgerigar behavioral thresholds were broadly similar to reported human data at

the masker F0 of 100 Hz, excepting differences in masking asymmetry between C polarities,

while being more sensitive than human results at 200 and especially 400 Hz. Budgerigars have

also been found to discriminate between positive and negative Schroeder stimuli with greater

accuracy than human subjects for stimulus F0s greater than or equal to 200 Hz (Dooling et al.,

2002).

Neurons in the budgerigar IC often showed considerable response differences between

Schroeder HTCs with opposite C values, in both average discharge rate and the amplitude of

instantaneous-rate fluctuations within Schroeder F0 periods (i.e., referred to as "rate fluctuation"

throughout). While variation was apparent within all CF ranges studied, both response metrics

transitioned from bias toward negative C values at CFs below 2-3 kHz to bias toward positive C

values at higher CFs. In other words, neural responses were stronger for HTCs with upward-

sloping instantaneous-frequency sweeps at CFs below 2-3 kHz, but downward-sloping sweeps

at higher CFs. These results could reflect a transition from downward-gliding to upward gliding

impulse responses of the cochlea with increasing CF, consistent with what has been reported in

several mammalian species (Carney et al., 1999; Recio-Spinoso et al., 2005; Recio and Rhode,

2000; Summers et al., 2003). On the other hand, it seems likely that "across-CF" combinations

of excitatory and inhibitory inputs to IC neurons, with different timing, could produce neural

sensitivity to sweep direction (Gittelman et al., 2009; Suga, 1965), or at least influence sweep

sensitivity, potentially explaining differences in Schroeder bias observed between IC neurons of

similar CF. Multiple excitatory inputs from auditory-nerve inputs with different CFs produces

direction selectivity for frequency sweeps in octopus cells of the mammalian cochlear nucleus

(Lu et al., 2022).

Differences in IC neural responses to Schroeder-phase HTCs with opposite C values
have also been recently reported in anesthetized gerbils (Steenken et al., 2022). As in the
present budgerigar study, Schroeder F0s were 50, 100, 200, or 400 Hz, and C values ranged
from -1 to +1 with a step size of 0.25. Gerbil neural response differences were quantified using
a discriminability index similar to our bias metric (but without polarity), based on average rate
and temporal responses calculated using several window lengths, including 1/F0. Neural
discriminability of Schroeder sweep direction was observed in most gerbil IC neurons based on
average rate and, to a lesser extent, based on F0-related spike timing. Large response
differences were frequently found between units, and these differences were not clearly related
to CF or other basic response properties such as modulation tuning (see Fig. 4 in Steenken et
al., 2022). Statistical analyses showed increasing Schroeder discriminability in gerbil IC neurons
with band-reject modulation tuning, a response property not observed in our budgerigar study,
and in neurons with higher BMFs (Steenken et al., 2022). Whereas average IC neural
discriminability in gerbils was higher for low stimulus F0s, consistent with behavioral
discriminability of Schroeder HTCs measured in the same species, individual IC neurons with
high discriminability were found for every stimulus condition included in the study (Steenken et
al., 2022). Taken together, these studies suggest that IC neural discriminability of Schroeder
stimuli based on C polarity (i.e., direction of instantaneous-frequency sweeps) could be a
broadly conserved aspect of complex-sound processing across diverse animal taxa.
Adding a tone signal to a Schroeder HTC increases the stimulus energy level,
particularly in the processing channel centered on the signal frequency. Consequently, single-
channel energy level is a potential cue by which human or animal subjects might detect the
signal. Several lines of evidence in budgerigars argue against use of single-channel energy
cues for Schroeder-masked tone detection. First, budgerigar Schroeder-masked thresholds,
using a masker F0 of 100 Hz, were relatively unaffected by the roving-level paradigm that
degrades single-channel energy cues. Similar results have been reported in prior behavioral
studies of tone-in-noise detection in this species that compared fixed- and roving-level test
paradigms (Henry and Abrams, 2021; Henry et al., 2020; Wang et al., 2021). Second, most IC
neurons in budgerigars responded to Schroeder-masked tones in a manner consistent with
modulation tuning and neural sensitivity to envelope fluctuations (Carney, 2018) rather than
rate-based encoding of stimulus energy level. Neurons with band-enhanced modulation tuning,
as commonly occur in the IC of many species including budgerigars, react to greater fluctuation
depth of their inputs though increased average and synchronized response rate (Henry et al.,
2016; Joris et al., 2004; Krishna and Semple, 2000; Langner and Schreiner, 1988; Nelson and

Carney, 2007). IC inputs are highly modulated in response to the Schroeder masker alone,

attributable to both the physical envelope of the HTC (for C values less than 1; Fig. 1) and the

pronounced impact of band-pass filtering of the wideband HTC by the cochlea. These strongly

fluctuating input signals become less modulated when the near-CF tone signal is added,

resulting in a response decrement compared to the HTC masker alone due to modulation

tuning.

While a response decrement could also feasibly result from inhibition by high-level

tones, a previous study of budgerigar IC tone-in-noise sensitivity (Wang et al., 2021) suggests

that this is not likely the case. Using tone signals added to third-octave narrowband noise, Wang

and colleagues (2021) controlled level variation of both the signal and masker to help separate

the roles of energy and envelope cues in determining IC response rates using a statistical

model. Neural tone-in-noise thresholds were most often based on a response decrement

compared to the masker alone, as in the present work on Schroeder masking. Multiple

regression analyses demonstrated that response rate in most budgerigar IC neurons was

positively correlated with the envelope cue, as expected based on IC modulation sensitivity, and

was positively correlated with stimulus energy in contrast to expectations based on inhibition

(Wang et al., 2021). Only a small percentage of units showed negative response correlations to

stimulus energy, indicative of inhibition by high-level stimuli, most of which had CFs above 4

kHz, near the budgerigar's upper frequency limit of hearing sensitivity. In summary, decrements

in neural response amplitude appear to be a major cue for masked detection of pure-tone

signals in the IC and likely result from the emergence of prominent modulation tuning at this

processing level.

Budgerigar IC neural thresholds for Schroeder-masked tone detection showed several

patterns broadly consistent with our behavioral results, including lower values for lower absolute

C values and relatively similar values for opposite polarities of the same C value (i.e., V-shaped

Schroeder masking functions). In contrast, whereas behavioral thresholds increased for higher

masker F0s, neural thresholds showed the opposite pattern of lower values for higher masker

F0s, regardless of whether they were calculated based on average rate or rate fluctuation.

While the reason for this difference is unknown, divergent results could feasibly reflect the fact

that neural recordings were conducted with a relatively low, fixed masker level of 60 dB SPL,

intended to minimize agitation of animals during awake, passive listening sessions. In contrast,

the behavioral experiment exploring F0 effects was conducted with roving-level maskers of 70-

90 dB SPL. If fixed- and roving-level thresholds increasingly diverge for higher masker F0s, this

could explain discrepant F0 effects noted not only here, between behavioral and neural results,

but also between behavioral results of the present study and those of Dooling et al. (2001) who

use a fixed-level test strategy, as discussed previously.

While neural thresholds were on average similar between opposite C values, we found

that units with strong response bias toward positive Schroeder HTCs were more sensitive to the

addition of a tone presented with the positive Schroeder. This finding is consistent with general

predictions in the Schroeder-masking literature (Smith et al., 1986; Summers and Leek, 1998).

Because strong positive-Schroeder bias was most often observed at neural CFs above 3 kHz,

for F0s of 200-400 Hz, and for absolute C value between 0.5 and 1, we would predict that

behavioral Schroeder masking difference might exist in the budgerigar for these same

conditions. Furthermore, we expect that thresholds should be lower for positive C values, as

occurs in humans (Kohlrausch and Sander, 1995; Lauer et al., 2006; Oxenham and Dau, 2001;

Smith et al., 1986). Unfortunately, behavioral testing in the present study was limited to 2.8 kHz,

a signal frequency for which near-zero Schroeder bias was observed in IC neural responses.

Furthermore, prior budgerigar studies that included a 4-kHz signal frequency were limited to a

masker F0 of 100 Hz, for which little neural Schroeder bias was found in the present study.

Future studies in budgerigars should test for asymmetry of Schroeder masking using 4-kHz tone

signals and masker F0s from 200-400 Hz.

In summary, behavioral results of the present study showed V-shaped Schroeder-

masking as function of C value in budgerigars, extending prior findings of this type in

budgerigars and other bird species to a wider range of masking parameters. Schroeder-masked

thresholds increased for higher masker F0s and were relatively unaffected by a roving-level

paradigm, arguing against single-channel energy level as a major detection cue (at least for the

100-Hz masker F0). Neural recordings from the budgerigar IC in awake animals showed that

tone detection in most neurons was based on a response decrement attributable to modulation

tuning. This result highlights the likely importance of envelope cues and changes in the

fluctuation strength of neural inputs (Carney, 2018) for masked detection. Neural thresholds

showed symmetric V-shaped Schroeder masking functions, similar to behavioral results, but

decreased somewhat for higher F0s in contrast to behavioral findings. Questions raised by the

work include whether the roving-level effect, which was negligible behaviorally for a masker F0

of 100 Hz, might be more pronounced for higher masker F0s. Furthermore, future studies

should determine whether asymmetric masking by Schroeder HTCs occurs behaviorally in this

species for high signal frequencies (~4 kHz) and when the masker F0 is 200-400 Hz.

Declaration of competing interest

The authors declare no competing interests.

Funding

This research was supported by grants R01-DC001641 and R01-DC017519.

Figure captions

Fig. 1. Waveforms of Schroeder-phase harmonic tone complexes (HTCs) produced with the
same fundamental frequency (F0; 100 Hz) and values of the phase-scaling parameter, C,
ranging from -1 to 1. Positive C values (right column) produce downward-sloping instantaneous
frequency sweeps within F0 periods whereas negative C values (left column) produce upward-
sloping frequency sweeps. Lower absolute C value decreases the duty cycle of the waveform,
with C of zero (bottom panel; all components in cosine phase) producing an impulse train.

Fig. 2. Representative results of two-down one-up tracking sessions in trained budgerigars.
Tracks show variation in signal level across trials.. Roving-level tracks (A) are obtained with
±10-dB random variation in stimulus level across trials that reduces the utility of single-channel
energy cues for performing the task. Extended tracks (B) transition from a fixed- (black) to the
roving-level (blue) test procedure within sessions. Crosses indicate final reversal points used to
calculate track thresholds, given above each track in dB. F0 is 100 Hz and C is +1.

Fig. 3. Behavioral thresholds of individual budgerigars for detection of a tone signal masked by
a Schroeder HTC (A). Trend lines and error bars are means and across-subject standard
deviations, respectively. Budgerigar Schroeder-masked tone thresholds increase for higher F0s,
increase for higher absolute C values, and are similar between opposite polarities of the same C
value. Mean thresholds from the current study compared to previously published results from
humans and other budgerigar studies (B). Budgerigars show less masking difference between
positive and negative C value than humans.

Fig. 4. Behavioral Schroeder-masking thresholds of budgerigars from the second experiment
comparing performance under fixed- and roving-level test conditions. Trend lines and error bars
indicate means and cross-subject standard deviations, respectively. Symbols refer to animal

identity as if Fig. 3. F0 is 100 Hz. Budgerigars showed little of no effect of roving stimulus level

on Schroeder masking thresholds.

Fig. 5. Basic tuning properties of recorded budgerigar IC neurons. Frequency response maps

(A) show average rate as a function of tone frequency and level. SU: single unit; MU: multi unit;

subsequent unit identification codes are arbitrary. Characteristic frequency (CF) increases from

left to right. Modulation transfer functions (B) of the same recording sites in A, showing average

response rate to sinusoidally amplitude-modulated tones across modulation frequencies. BMF:

best modulation frequency. Dotted blue lines indicate the response rate to the unmodulated

carrier signals. Carrier frequency is within ±1/6 octave of estimated CF.

Fig. 6. Representative neural responses to Schroeder-phase HTCs of variable F0 and C value.

Period histograms (A) illustrate variation in average discharge rate over two cycles of F0. F0 is

indicated at the top of each column and C magnitude given to the left. (B) Single-trial average

discharge rate (top) and F0 rate fluctuation plotted as a function of C value for two different F0s

(left: 50 Hz; right: 200 Hz). Trend lines and error bars show means and across-trial standard

deviation. Note bias of F0 rate fluctuation toward the positive Schroeder for 200 Hz F0 and

absolute C values greater than 0.5. CF was 1.90 kHz.

Fig. 7. Representative neural responses as in Figure 5, but for a different unit. Note widespread

bias of average discharge rate and F0 rate toward the negative Schroeder, most prominently for

moderate-to-high absolute C values. CF was 0.85 kHz.

Fig. 8. Schroeder bias of response rate fluctuation, plotted as a function of CF for all stimulus

conditions. F0 is indicated at the top of each column and absolute C values are given on the

right. Thick blue lines are predicted values from a linear fit to the data. Pearson correlations and

associated p values are reported in the top left corner of each panel. The number of recorded

units is 146 for C of ±0.25 and ±0.75, and 150 for C of ±0.5 and ±1.

Fig. 9. As for Fig. 8, but with Schroeder bias calculated based on average response rate.

Fig. 10. Representative neural responses to near-CF tones masked by Schroeder HTCs. Two-

cycle period histograms (A) for a range of tone levels (indicated left) in two neurons; F0 is 400

Hz and C is ±0.5 (columns 1 and 2; first neuron) or ±1 (columns 3 and 4; second neuron).

Response functions (B) show average discharge rate (top) and rate fluctuation (bottom) as a

function of tone level. Downward pointing arrows indicate neural thresholds above which

detection performance consistently exceeds 70.7% correct. Trend lines indicate cross-trial

means and standard deviations. *None:* masker alone with no tone.

Fig. 11. Neural thresholds for Schroder-masked tone detection based on rate fluctuation, plotted

against CF. Tone frequency is the nearest harmonic frequency to CF and is within ±1/6 octave

for all recordings. Masker level is 60 dB SPL. Threshold decreases for lower absolute C values,

appears similar between opposite polarities of C, and increases for the lowest F0. Behavioral

means are from Fig. 3. IQR: interquartile range. The total number of recorded units is 92 for F0

of 100 Hz, 67 for F0 of 200 Hz, and 64 for F0 of 400 Hz.

Fig. 12. As for Fig. 11, but with neural thresholds calculated based on average rate. The total

number of recorded units is 92 for F0 of 100 Hz, 67 for F0 of 200 Hz, and 64 for F0 of 400 Hz.

Fig. 13. Neural thresholds for masked tone detection in positive Schroeder HTCs as a function

of Schroeder bias observed for the same absolute C value. Both response metrics are based on

rate fluctuation. Trend lines are a linear fit to the data excluding units with no threshold. Pearson

correlations are reported in the lower left of each panel. Sample sizes are 30 and 26 for row 1

(left to right), 39 and 34 for row 2, and 37 and 39 for row 3. Greater positive-Schroeder bias is

associated with lower masked thresholds for C values of +0.5 and +1 at F0s of 200 and 400 Hz.

Fig. 14. As for Fig. 13, but with neural thresholds and Schroeder bias calculated based on

average rate. Sample sizes are 25 and 35 for row 1 (left to right), 46 and 32 for row 2, and 42

and 38 for row 3.

References

Bates, D., Mächler, M., Bolker, B., Walker, S., 2015. Fitting linear mixed-effects models using

lme4. Journal of Statistical Software 67(1), 1-48. https://doi.org/10.18637/jss.v067.i01.

Carney, L.H., 2018. Supra-threshold hearing and fluctuation profiles: implications for

sensorineural and hidden hearing loss. Journal of the Association for Research in

Otolaryngology 19(4), 331-352. https://doi.org/10.1007/s10162-018-0669-5.

Carney, L.H., McDuffy, M.J., Shekhter, I., 1999. Frequency glides in the impulse responses of
auditory-nerve fibers. The Journal of the Acoustical Society of America 105(4), 2384-
2391. https://doi.org/10.1121/1.426843.

Choi, J.H., Jung, H.K., Kim, T., 2006. A new action potential detector using the MTEO and its
effects on spike sorting systems at low signal-to-noise ratios. IEEE Transactions on
Biomedical Engineering 53(4), 738-746. https://doi.org/10.1109/TBME.2006.870239.

Dooling, R.J., Dent, M.L., Leek, M.R., Gleich, O., 2001. Masking by harmonic complexes in
birds: behavioral thresholds and cochlear responses. Hearing Research 152(1-2), 159-
172. https://doi.org/10.1016/S0378-5955(00)00249-5.

Dooling, R.J., Leek, M.R., Gleich, O., Dent, M.L., 2002. Auditory temporal resolution in birds:
discrimination of harmonic complexes. The Journal of the Acoustical Society of America
112(2), 748-759.

Dooling, R.J., Lohr, B., Dent, M.L., 2000. Hearing in Birds and Reptiles, in: Dooling, R.J., Fay,
R.R., Popper, A.N. (Eds.), Comparative Hearing: Birds and Reptiles. Springer, New
York, pp. 308-359.

Egan, J.P., 1975. Signal Detection Theory and ROC Analysis. Academic Press, New York.

Fletcher, H., 1940. Auditory Patterns. Reviews of Modern Physics 12, 47-65.

Fontaine, B., Köppl, C., Peña, J.L., 2015. Reverse correlation analysis of auditory-nerve fiber
responses to broadband noise in a bird, the barn owl. Journal of the Association for
Research in Otolaryngology 16(1), 101-119. https://doi.org/10.1007/s10162-014-0494-4.

Gittelman, J.X., Li, N., Pollak, G.D., 2009. Mechanisms underlying directional selectivity for
frequency-modulated sweeps in the inferior colliculus revealed by in vivo whole-cell
recordings. The Journal of Neuroscience 29(41).
https://doi.org/10.1523/JNEUROSCI.2477-09.2009.

Henry, K.S., Abrams, K.S., 2021. Normal tone-in-noise sensitivity in trained budgerigars despite
substantial auditory-nerve injury: No evidence of hidden hearing loss. The Journal of
Neuroscience 41(1), 118-129. https://doi.org/10.1523/JNEUROSCI.2104-20.2020.

Henry, K.S., Abrams, K.S., Forst, J., Mender, M.J., Neilans, E.G., Idrobo, F., Carney, L.H.,
2017a. Midbrain synchrony to envelope structure supports behavioral sensitivity to
single-formant vowel-like sounds in noise. Journal of the Association for Research in
Otolaryngology 18(1), 165-181. https://doi.org/10.1007/s10162-016-0594-4.

Henry, K.S., Amburgey, K.N., Abrams, K.S., Carney, L.H., 2020. Identifying cues for tone-in-
noise detection using decision variable correlation in the budgerigar (*Melopsittacus*

undulatus). The Journal of the Acoustical Society of America 147(2), 984-997.
https://doi.org/10.1121/10.0000621.

Henry, K.S., Amburgey, K.N., Abrams, K.S., Idrobo, F., Carney, L.H., 2017b. Formant-frequency
discrimination of synthesized vowels in budgerigars (*Melopsittacus undulatus*) and
humans. The Journal of the Acoustical Society of America 142(4), 2073-2083.
https://doi.org/10.1121/1.5006912.

Henry, K.S., Neilans, E.G., Abrams, K.S., Idrobo, F., Carney, L.H., 2016. Neural correlates of
behavioral amplitude modulation sensitivity in the budgerigar midbrain. Journal of
Neurophysiology 115(4), 1905-1916. https://doi.org/10.1152/jn.01003.2015.

Joris, P.X., Schreiner, C.E., Rees, A., 2004. Neural processing of amplitude-modulated sounds.
Physiological reviews 84(2), 541-577. https://doi.org/10.1152/physrev.00029.2003.

Kidd, G., Mason, C.R., Brantley, M.A., Owen, G.A., 1989. Roving-level tone-in-noise detection.
The Journal of the Acoustical Society of America 86(4), 1310-1317.

Kim, D.O., Carney, L.H., Kuwada, S., 2020. Amplitude modulation transfer functions reveal
opposing populations within both the inferior colliculus and medial geniculate body.
Journal of Neurophysiology. https://doi.org/10.1152/jn.00279.2020.

Kohlrausch, A., Sander, A., 1995. Phase effects in masking related to dispersion in the inner
ear. II. Masking period patterns of short targets. The Journal of the Acoustical Society of
America 97(3), 1817-1829. https://doi.org/10.1121/1.413097.

Krishna, B.S., Semple, M.N., 2000. Auditory temporal processing: responses to sinusoidally
amplitude-modulated tones in the inferior colliculus. Journal of Neurophysiology 84(1),
255-273.

Langner, G., Schreiner, C.E., 1988. Periodicity coding in the inferior colliculus of the cat. I.
Neuronal mechanisms. Journal of Neurophysiology 60(6), 1799-1822.

Lauer, A.M., Dooling, R.J., Leek, M.R., Lentz, J.J., 2006. Phase effects in masking by harmonic
complexes in birds. The Journal of the Acoustical Society of America 119(2), 1251-1251.
https://doi.org/10.1121/1.2151816.

Leek, M.R., Dent, M.L., Dooling, R.J., 2000. Masking by harmonic complexes in budgerigars
(*Melopsittacus undulatus*). The Journal of the Acoustical Society of America 107(3),
1737-1744. https://doi.org/10.1121/1.428455.

Levitt, H., 1971. Transformed up-down methods in psychoacoustics. The Journal of the
Acoustical Society of America 49, 467-477.

Lu, H.W., Smith, P.H., Joris, P.X., 2022. Mammalian octopus cells are direction selective to
frequency sweeps by excitatory synaptic sequence detection. Proceedings of the

National Academy of Sciences of the United States of America 119(44).

https://doi.org/10.1073/pnas.2203748119.

Macmillan, N.A., Creelman, C.D., 1991. Detection Theory: A User's Guide. CUP Archive.

Manley, G.A., Gleich, O., Leppelsack, H.J., Oeckinghaus, H., 1985. Activity patterns of cochlear

ganglion neurones in the starling. Journal of Comparative Physiology A: Sensory,

Neural, and Behavioral Physiology 157(2), 161-181.

https://doi.org/10.1007/BF01350025.

Nelson, P.C., Carney, L.H., 2007. Neural rate and timing cues for detection and discrimination

of amplitude-modulated tones in the awake rabbit inferior colliculus. Journal of

Neurophysiology 97(1), 522-539. https://doi.org/10.1152/jn.00776.2006.

Oxenham, A.J., Dau, T., 2001. Towards a measure of auditory-filter phase response. The

Journal of the Acoustical Society of America 110(6). https://doi.org/10.1121/1.1414706.

Recio-Spinoso, A., Temchin, A.N., van Dijk, P., Fan, Y.-H., Ruggero, M.A., 2005. Wiener-kernel

analysis of responses to noise of chinchilla auditory-nerve fibers. Journal of

Neurophysiology 93(6), 3615-3634. https://doi.org/10.1152/jn.00882.2004.

Recio, A., Rhode, W.S., 2000. Basilar membrane responses to broadband stimuli. The Journal

of the Acoustical Society of America 108(5), 2281-2298.

https://doi.org/10.1121/1.1318898.

Recio, A., Rich, N.C., Narayan, S.S., Ruggero, M.A., 1998. Basilar-membrane responses to

clicks at the base of the chinchilla cochlea. The Journal of the Acoustical Society of

America 103(4), 1972-1972. https://doi.org/10.1121/1.421377.

Richards, V.M., 1992. The detectability of a tone added to narrow bands of equal-energy noise.

The Journal of the Acoustical Society of America 91(6), 3424-3435.

https://doi.org/10.1121/1.402831.

Sachs, M.B., Young, E.D., Lewis, R.H., 1974. Discharge patterns of single fibers in the pigeon

auditory nerve. Brain Research 70, 431-447.

Schroeder, M., 1970. Synthesis of low-peak-factor signals and binary sequences with low

autocorrelation. IEEE Transactions on Information Theory 16(1), 85-89.

https://doi.org/10.1109/TIT.1970.1054411.

Smith, B.K., Sieben, U.K., Kohlrausch, A., Schroeder, M.R., 1986. Phase effects in masking

related to dispersion in the inner ear. The Journal of the Acoustical Society of America

80(6), 1631-1637. https://doi.org/10.1121/1.394327.

Steenken, F., Oetjen, H., Beutelmann, R., Carney, L.H., Koeppl, C., Klump, G.M., 2022. Neural

processing and perception of Schroeder-phase harmonic tone complexes in the gerbil:

Relating single-unit neurophysiology to behavior. European Journal of Neuroscience

56(3), 4060-4085. https://doi.org/10.1111/EJN.15744.

Strube, H.W., 1985. A computationally efficient basilar-membrane model. Acoustica 58(4), 207-

214.

Suga, N., 1965. Analysis of frequency-modulated sounds by auditory neurones of echo-locating

bats. The Journal of Physiology 179(1). https://doi.org/10.1113/jphysiol.1965.sp007648.

Summers, V., de Boer, E., Nuttall, A.L., 2003. Basilar-membrane responses to multicomponent

(Schroeder-phase) signals: Understanding intensity effects. The Journal of the

Acoustical Society of America 114(1), 294-306. https://doi.org/10.1121/1.1580813.

Summers, V., Leek, M.R., 1998. Masking of tones and speech by Schroeder-phase harmonic

complexes in normally hearing and hearing-impaired listeners. Hearing Research 118(1-

2). https://doi.org/10.1016/s0378-5955(98)00030-6.

Takasaka, T., Smith, C.A., 1971. The structure and innervation of the pigeon's basilar papilla.

Journal of Ultrastructure Research 35, 20-65.

Wang, Y., Abrams, K.S., Carney, L.H., Henry, K.S., 2021. Midbrain-level neural correlates of

behavioral tone-in-noise detection: dependence on energy and envelope cues. The

Journal of Neuroscience 41(34), JN-20. https://doi.org/10.1523/jneurosci.3103-20.2021.

Wong, S.J., Abrams, K.S., Amburgey, K.N., Wang, Y., Henry, K.S., 2019. Effects of selective

auditory-nerve damage on the behavioral audiogram and temporal integration in the

budgerigar. Hearing Research 374, 24-34. https://doi.org/10.1016/j.heares.2019.01.019.

Woolley, S.M.N., Casseday, J.H., 2005. Processing of modulated sounds in the zebra finch

auditory midbrain: responses to noise, frequency sweeps, and sinusoidal amplitude

modulations. Journal of Neurophysiology 94(2), 1143-1157.

https://doi.org/10.1152/jn.01064.2004.

1041