Supercomputers and Reverse Engineering of Motoneuron Firing Patterns

Matthieu K. Chardon[1,10], Y. Curtis Wang[2], Marta Garcia[3], Emre Besler[4], J. Andrew Beauchamp[5], Michael D'Mello[6], Randall K. Powers[7], and Charles J. Heckman[1,8,9]

[1]Department of Neuroscience, Northwestern University, Chicago, IL, USA

[2]Department of Electrical and Computer Engineering, California State University, Los Angeles, Los Angeles, CA, USA

[3]Argonne Leadership Computing Facility, Argonne National Laboratory, Lemont, IL, USA

[4]Department of Electrical Engineering, Northwestern University, Evanston, IL, USA

[5]Department of Biomedical Engineering, Northwestern University, Chicago, IL, USA

[6]Intel Corporation, Santa Clara, CA, USA

[7]Department of Physiology and Biophysics, University of Washington, Seattle, WA, USA

[8]Physical Medicine and Rehabilitation, Shirley Ryan Ability Lab, Chicago, IL, USA

[9]Physical Therapy and Human Movement Sciences, Northwestern University, Chicago, IL, USA

[10]Northwestern-Argonne Institute of Science and Engineering (NAISE), Evanston, IL, USA

December 2022

Abstract

In this study, we achieved a major step forward in the analysis of firing patterns of populations of motoneurons, through remarkably extensive parameter searches enabled by massively-parallel computation on supercomputers. The ability to implement these extensive parameter searches seem ideally matched to understanding the many parameters that define the inputs to neuron populations that generate these patterns. Therefore, we investigated the feasibility of using supercomputer-based models of spinal motoneurons as a basis for reverse engineering (RE) their firing patterns to identify the organization of their inputs, which we defined as the amplitudes and patterns of excitation, inhibition, and neuromodulation. This study combines two advances: 1) highly-realistic motoneuron models based on extensive in situ voltage and current clamp studies focused on neuromodulatory actions, and 2) implementation of these models using the Laboratory Computing Resource Center at Argonne National Laboratory to carry thousands (soon millions) of simulations simultaneously. The goal for computing and performing RE on over 300,000 combinations of excitatory, inhibitory, and neuromodulatory inputs was twofold: 1) to estimate the synaptic input to the motoneuron pool and 2) to generate training data for identifying the excitatory, inhibitory, and neuromodulatory inputs based on output firing patterns. As with other neural systems, any given motoneuron firing pattern could potentially be non-unique with respect to the excitatory, inhibitory, and neuromodulatory input combination (many input combinations produce

similar outputs). However, our initial results show that the neuromodulatory input makes the motoneuron input-output properties so nonlinear that the effective RE solution space is restricted. The RE approach we demonstrate in this work is successful in generating estimates of the actual simulated patterns of excitation, inhibition, and neuromodulation with variances accounted for ranging from 75% to 90%. It was striking that the nonlinearities induced in firing patterns by the neuromodulation inputs did not impede RE, but instead generated distinctive features in firing patterns that aided RE. These simulations demonstrate the potential of this form of RE analysis. It is likely that the ever-increasing power of supercomputers will allow increasingly accurate RE of neuron inputs from their firing patterns from many neural systems.

1   Introduction

Array electrodes that allow simultaneous recording of firing patterns of populations of neurons in mammals have transformed understanding of the computations implemented by neural networks during natural behaviors and the utilization of these computations for brain machine interfaces (Buonomano and Maass 2009; Chandrasekaran et al. 2021; Stevenson, London, et al. 2012; Stevenson and Kording 2011; Vyas et al. 2020). However, to understand how a given neural network generates the firing patterns that implement these computations, it is necessary to understand the transformation of inputs to outputs by the constituent neurons. The net effect of ionotropic excitatory inputs in activating a neural circuit is likely to be strongly impacted by the pattern of inhibitory inputs arising from local interneurons and the effects of neuromodulatory inputs acting on G-protein coupled receptors (Binder, Powers, and Heckman 2020; Goaillard and Marder 2021; McCormick and Nusbaum 2014). In-depth analyses of the resulting complex interactions require intracellular electrode techniques, but these are not yet feasible simultaneously in many neurons during a natural behavior. An alternative is reverse engineering (RE) the firing patterns recorded by arrays to identify the neurons' inputs and properties.

Thus far, RE has been used to achieve several different goals, including estimation of circuit structures within simulations with simple neuron models (Lim, Keniston, and Cios 2011; Pisokas 2021; Rostro-Gonzalez, Cessac, and Viéville 2012) and estimation local field potentials from measurements of spiking patterns (Telenczuk, Telenczuk, and Destexhe 2020; see also Yochum et al. 2019). In this study, our goal was to harness the computational power provided by implementation of realistic neuron models on a supercomputer to investigate the feasibility of reverse engineering (RE) these model firing patterns to identify the underlying organization of their simulated excitatory, inhibitory and neuromodulatory inputs. Successful RE of firing patterns into input organization would greatly advance the effectiveness of array recordings in identifying how neural circuits implement their computations.

RE of neural outputs into inputs faces a formidable barrier. Multiple neural systems have been shown to exhibit non-uniqueness, which is manifest as closely similar outputs being produced by many combinations of parameters specifying neuron properties and inputs (Edelman and Gally 2001; Marder 2012; Prinz, Bucher, and Marder 2004). This set of parameters forms the "solution space" for that neural system (Prinz 2010). Although likely advantageous for stability and resilience of neurons and circuits (Goaillard and Marder 2021), a large solution space that contain many combinations of excitation, inhibition and neuromodulation may limit the effectiveness of RE. In addition, the parameters within the solution space may interact in complex, nonlinear ways (Mukunda and Narayanan 2017). Neuromodulatory inputs, for example, may have highly nonlinear effects on how neurons process their ionotropic inputs (Binder, Powers, and Heckman 2020; Marder 2012; McCormick and Nusbaum 2014). On the other hand, when neuronal output behaviors are complex,

non-uniqueness may be reduced by the constraints of matching multiple outputs (Mukunda and Narayanan 2017; Yang et al. 2022).

To reduce the impact of non-uniqueness, we chose a well-understood neural system for evaluation of RE, the motoneurons that transform all motor commands into signals for control of muscles (Heckman and Enoka 2012). Motoneuron properties and inputs have been extensively studied using in situ voltage clamp methods in animal preparations, with a focus on neuromodulatory actions (Heckman and Enoka 2012; Henneman and Mendell 1981). This data set has enabled us to generate highly realistic motoneuron models (Powers, ElBasiouny, et al. 2012; Powers and Heckman 2017), which we have successfully implemented on a supercomputer for the present study. Furthermore, recent advances in flexible array electrode methods now allow measurement of firing patterns of populations of motoneurons in humans, due to the one-to-one relation between motoneuron action potentials and those of its innervated muscle fibers (Holobar et al. 2010; Hug et al. 2021; Negro et al. 2016). Consequently, RE of these population firing patterns may generate deep insights into the synaptic organization of motor commands in humans as well as other animals.

We used an ensemble modeling approach (Prinz 2010) to determine how non-uniqueness and nonlinearity affected RE identification of the pattern of excitatory, inhibitory and neuromodulatory inputs that produces motor output. The supercomputer implementation of motoneuron models allowed us to thoroughly explore this input solution space, via more than 300,000 simulations of the effects of many input combinations on firing patterns. Our previous intracellular studies of motoneuron input-output functions suggest that motoneuron firing patterns contain substantial information about their inputs (Hyngstrom, Johnson, and Heckman 2008; Kuo et al. 2003; Lee and Heckman 1999; Lee and Heckman 1998a; Lee and Heckman 1998b). We therefore hypothesized that RE of motoneuron firing patterns would effectively deal with the problems of non-uniqueness and would therefore identify a reasonably small solution space of input combinations. To assess the importance of information contained within neuron firing patterns for achieving a small solution space, we compared RE of motoneuron firing patterns to RE of an overall measure of motor output generated by summing all neuron firing patterns together. This cumulative spike train (CST) has been shown to closely replicate muscle electromyogram (EMG), which is directly related to muscle force. Our simulation results supported the hypothesis and demonstrated a much smaller solution space for RE of firing of neuron populations than for the CST.

2 Results

2.1 Performance of the motoneuron models for integration of inputs

All simulations are run using a set of 20 model motoneurons, which have been designed to closely recreate the behaviors documented in our extensive data base of current and voltage clamp studies in motoneurons in animal preparations (see Supplemental Figure 10). These models were first developed in NEURON (Hines and Carnevale 1997) for a previous study (Powers and Heckman 2017) and have been implemented on a supercomputer for the present work (see Methods). Our goal of investigating the feasibility of RE of motoneuron firing patterns depends on accuracy of these motoneuron models. Figure 1 illustrates the performance of our motoneuron models in realistically capturing the integration of excitatory (Figure 1A), neuromodulatory (Figure 1B) and inhibitory (Figure 1C) inputs. Each of these simulated behaviors are considered in the following subsections.

Figure 1: Summary plots showing the performance of the motoneuron pool model with respect to integration of inputs. *A1* - Shows a subset of 6 of the 20 MN in the pool given the same excitatory triangular input, the black trace above. The MN pool follows an orderly activation known as the Henneman's size principle, showing that this MN model can transform a "common drive" into different MN activities (see section 2.1.1). *A2* - Shows the models ability to favor S-type vs F-type motoneuron within the pool. The orange $[w_{start}, w_{end}] = [1, 2]$ Distribution favors the fast (F-type) motoneuron. The recruitment of theses F-type motoneurons (e.g. MN 11, MN 15 and MN 19) happens sooner and their maximum firing rates are higher with respect to their $[w_{start}, w_{end}] = [1, 1]$ counterparts. For the slow (S-type) motoneurons the recruitment is the same but their max firing rates decrease with respect to their $[w_{start}, w_{end}] = [1, 1]$ counterparts (see section 2.1.2). *B* - Shows our models ability to trigger PIC type behavior. For a neuromodulation level of 1.2 (max of range tested) and no inhibition, the motoneurons firing rates show a fast rise time, then attenuation, followed by sustained firing (see section 2.1.3). *C1 and C2* - Shows the model's ability to modulate the effects of neuromodulation with inhibition. C1 shows a inhibition in the "Push-Pull" or reciprocal configuration. C2 shows inhbition in the balanced configurations (see section 2.1.4).

2.1.1 Common input structure, differences in motoneuron properties

A fundamental point in achieving accurate modeling of the outputs of a pool of motoneurons innervating a muscle is that they are subject to "common drive" (De Luca and Erim 1994; Farina and Negro 2015; Heckman and Enoka 2012). As a result, motoneuron firing patterns for a specific task exhibit an overall similarity, which is likely essential for efficient force control (Farina and Negro 2015). This point is important for reverse engineering, as common drive precludes independent inputs to each motoneuron. Firing patterns, however, are not identical. As in any biological system, noise is present, though this is relatively low in motoneurons (coefficient of variation during steady firing at about 10-20% (Heckman and Enoka 2012)). We add noise to our excitatory synaptic conductances to match this level, as illustrated in Figure 1A1, which illustrates firing patterns of 5 of the 20 motoneuron models in response to a linearly rising and falling excitatory conductance. This figure also shows systematic differences in activation (i.e. recruitment) thresholds. These differences are due to systematic differences in intrinsic electrical thresholds for spiking of motoneurons, which generates an orderly activation (i.e. recruitment) sequence known as Henneman's size principle (Henneman and Mendell 1981). The size principle is essential for effective utilization of the slow (S) vs fast (F) muscle fibers, with motoneurons innervating slow fibers having the lowest thresholds. S units tend to reach higher firing rates than F units, which require more input to reach their higher thresholds so less is available for suprathreshold rate modulation (Beauchamp, Khurram, et al. 2022; De Luca and Contessa 2012; Hu, Rymer, and Suresh 2013).

2.1.2 Distribution of excitatory input to S vs F motoneurons

In addition to the pattern and amplitude of excitatory input, there is another important aspect of excitatory motor commands, which is that all excitatory inputs studied thus far project differentially to S vs. F motoneurons (Powers and Binder 2001) (in contrast, inhibition tends to be uniform ((Powers and Binder 2001; Lindsay and Binder 1991) as does neuromodulation (Lee and Heckman 1998a; Lee and Heckman 1999). Descending inputs tend to generate larger synaptic currents in the F's, especially the corticospinal input (Powers and Binder 2001) (see Discussion). As yet only one input favors S motoneurons, but it is an essential one, monosynaptic Ia excitation from muscles spindles (Heckman and Binder 1988). These differences, though, do not provide independent control of F motoneurons, much less of individual motoneurons, as common drive still dominates and recruitment still follows the size principle (Heckman and Binder 1993). Figure 1A2 however shows that greater relative excitatory synaptic current in high threshold F motoneurons does tend to compress the range of recruitment thresholds and increase the steepness of rate modulation as input levels rise. This compression/steepening may thus provide RE sufficient information to identify the distribution of excitatory input to S vs F motoneurons and provide information on the relative roles of descending versus sensory input.

2.1.3 Neuromodulation and excitatory input

We chose to focus on just one type of neuromodulation (see Methods), the monoaminergic input originating in the brainstem, because this system has proved to have particularly powerful effects on motoneuron excitability (Heckman, Gorassini, and Bennett 2005; Heckman and Enoka 2012). These monoaminergic axons form a dense and monosynaptic projection onto motoneurons throughout the spinal cord, with the synapses releasing either 5HT (axons originating in the caudal raphe nuclei) or NE (axons from the locus coeruleus) (Alvarez et al. 1998; Holstege and Kuypers 1987; Maratta et al. 2015). Both 5HT and NE have multiple effects on

motoneuron ion channels, but their strongest action is via facilitation of persistent inward currents (PICs) mediated by dendritic Ca channels (likely CaV 1.3) (Binder, Powers, and Heckman 2020). Our motoneuron models have been fine tuned to accurately replicate the highly nonlinear interactions between PICs and excitatory inputs (Powers and Heckman 2017). Figure 1B shows that, when brainstem neuromodulatory are moderately high and dendritic PICs become strong, three marked nonlinearities become apparent: an initial acceleration (due to PIC activation and consequent amplification of input), followed by attenuation (due to PIC depolarization of dendritic regions, which reduces excitatory driving force) and then hysteresis (offset at a lower level than onset, due to the prolongation of input). In this example, where a pure excitatory drive is applied with no background of inhibition, low threshold motoneurons continue firing long after the input returns to baseline (this is known as self-sustained firing). These nonlinearities are striking in comparison to the nearly linear behavior in the low neuromodulatory state (Figure 1A1).

2.1.4 Neuromodulation and inhibition

Our models also accurately capture the very strong interaction of the PIC with inhibition. Even a small background of inhibition reduces PIC amplitudes (Hyngstrom, Johnson, Miller, et al. 2007; Kuo et al. 2003). Figure 1C shows that modulation of inhibitory input that is either reciprocally or proportionally organized with respect to excitation also dramatically alters the pattern of rate modulation. Reciprocal inhibition (Figure 1C1) tends to allow strong PIC expression with acceleration, attenuation and hysteresis, whereas proportional inhibition (Figure 1C2) tends to flatten rate modulation and reduce hysteresis (in fact, of all the patterns shown in Figure 1, C1 is closest to that seen in many human muscles (Beauchamp, Khurram, et al. 2022; Heckman and Enoka 2012). Thus the nonlinearities in firing patterns are not a straightforward reflection of neuromodulatory input but instead result from a complex interaction between neuromodulation and inhibition.

Given the above effects of the organization of excitation, inhibition and neuromodulation on firing patterns, our RE effort targeted identification of the following aspects of excitation, inhibition and neuromodulation: amplitude and time course of excitation, distribution of excitation to S versus F motoneurons, amplitude and time course of inhibition (including the baseline level and then whether inhibition was proportional, constant or balanced) and level of neuromodulation from low to high.

2.2 Ensemble modeling for Reverse Engineering

The concept for the RE approach we used is illustrated in Figure 2. The left portion shows the flow of motor commands from the brain, brainstem and spinal cord to motoneurons, which then activates a muscle. The muscle produces an output force. This force is due to the summed actions of recruited motor units, whose spike trains sum to produce an overall electrical signal (EMG). Our focus is on the spike trains themselves, which can be measured in both animals and humans. The pattern of average firing rate is obtained by summing the rates of all active units (see Methods) and is thus referred to as the cumulative spike train (CST) (righthand side, bottom) When then apply RE methods to both the CST and to individual motor unit firing patterns (right, middle), which, if successful, will allow us to estimate the temporal patterns and amplitudes of the three components of motor commands. Two hypothetical outcomes are illustrated. In both, a triangular form of excitation is applied. The push-pull scheme is a reciprocal organization in which a tonic level of inhibition decreases as excitation increases. The balanced scheme has the opposite organization, inhibition increasing in proportion to excitation. Neuromodulation is assumed to be constant but can varied

Figure 2: Reverse Engineering Paradigm. The left side shows a schematic of the input pathway to the MN pool and its subsequent connection to a muscle. The right side shows a schematic of our goal. Can we predict the 3 inputs of the MN pool given the firing pattern of the MN pool used to generate the muscle output? In the push pull scheme at upper right, inhibition (red) decrease as excitation (green) increases. In contrast, inhibition increases with excitation in the balanced scheme. In this work we show that using the "MN Pool Firing Pattern" one is able to reverse engineer back to the MN pool inputs.

Figure 3: Schematic of the algorithm used to approximate the excitatory input needed to produce the triangular output from the motoneuron pool. The schematic resembles a classic controller schematic. The algorithm starts at the "Input to MN Pool" box where the light pink triangular input is used as the initial guess to the "Plant System" box. Using this initial input guess, the MN pool model calculates it first output, seen in the "System Output" box (light pink trace). This initial output is compared the "Reference" Box and the resulting error $e(t)$ is fed into the "Controller" box. Based on this error the controller calculates a new guess for an input and the cycle is repeated until a satisfactory error is achieved (MSE < 1 Hz^2). The iterations are shown within the "Input to MN Pool" and "System Output" boxes along a left to right diagonal scheme to show the evolution of the traces produced by the algorithm. From iteration 0 to iteration n the input to the MN pool morphs to a highly non linear form to produce a linear output. Finally, this algorithm is repeated over a range of neuromodulation, inhibitory bias, inhibitory gain and exciatatory synaptic weights as shown in the "MN parameters" box. Taking all the iterations and combinations, the model was run at total of 6,300,000 times. See subsection 4.2 for details.

widely in its level. Although the balanced scheme often is used to drive cortical neurons (Berg, Alaburda, and Hounsgaard 2007), it is unknown how these three components interact in motor commands to motoneurons.

The ensemble modeling approach we utilize for RE begins with estimation of the trajectory of the excitatory motor command. The procedure is illustrated in Figure 3. We required all simulations to achieve the same overall output, a triangular waveform for CST (upper left; Methods for the match criterion). For each simulation, we specified the following properties of the input organization:

1. Distribution of excitatory input on to S vs F motoneurons (range of 0.5 to 2.5; at 0.5 the highest threshold type F motoneuron received half the average input of lowest threshold type S; at 2.5 the F received 2.5 times the input of the S).,

2. Level of neuromodulation: range 0.8 to 1.2, specified in terms of the maximum conductance of the PIC.

3. Baseline level of inhibition: This was set to the lowest level that prevented the PIC from generating self-sustained firing (Figure 1B shows an example of motoneurons with strong self-sustained firing due to lack of sufficient inhibitory baseline)

4. Pattern of inhibition relative to excitation: This pattern was set to be linearly proportional to excitation via multipliers ranging from +0.7 to -0.7. Figure 1C1 and Figure 1C2 illustrate firing patterns resulting from maximum proportional inhibition (multiplier of +0.7) to maximal push pull (-0.7). At 0.0, the baseline of inhibition remained constant.

5. A physiological level of synaptic noise (see Methods). The RMS value for this noise was the same in all simulations, but was regenerated 30 times to allow estimates of variance for each combination of the above 4 input properties.

Then, for each simulation, we set the input and noise properties as above and then applied a triangular pattern of excitation to the motoneuron models, starting with a purely triangular form and modifying it in an iterative process until the CST of the motoneurons reproduced the linear target CST (Figure 3, flow diagram). We repeated these simulations with different sets of input parameters 315,000 times to form the ensemble model of the motor pool (see section 4.5.1 for parameter combination details). We used the resulting large data set for successful matches to the target CST to assess the feasibility of RE for both the CST and individual motoneuron firing patterns.

2.3 Solution space for overall output

We hypothesized that the CST, which contains information only about the overall output trajectory, would have a large solution space. It was nonetheless surprising that our process for modifying the shape of the excitatory input command generated good matches to the target CST for every motor command combination we tried (all 315,000 of them (see section 4.5.1)). However, as illustrated in by the progression of input forms in Figure 2 and further elaborated in Figure 4, the potent amplification and large nonlinearities in firing patterns induced by PICs usually resulted in highly nonlinear excitatory commands being required to generate the linear CST. The excitatory conductance input that leads to a good match to the target firing rate typically shows a rapid increase to get recruitment started, followed by a drop off during the acceleration phase due to wide-spread PIC activation across the active motor units, followed by a more rapid increase to keep the average firing rate rising in the face of PIC rate saturation. The falling phase of the command was roughly the mirror image of the rising phase. This general trend is evident in all the examples in Figure 4. As expected, as the level of neuromodulation increased, these nonlinear trends increased, but less excitation is required to achieve the same global output. The examples in upper half of Figure 4 assumed inhibition was constant. The lower left example in Figure 4 shows examples of the effects of different organizations of inhibition. Much higher levels of excitation are needed to counteract inhibition when it varies in proportion to the excitatory command (balanced inhibition, red traces), then when it varies inversely (push-pull inhibition, green traces). To quantify the effects of neuromodulation and inhibition on the overall amplitude of excitation, we calculated the area under the curve for the excitation patterns as neuromodulation and inhibition varied. Figure 5 shows that the amount of excitation required to generate the standard CST target decreased as neuromodulation increased or as inhibition progressively changed from proportional to push pull. Thus, although the solution space for reproducing the target CST is very wide, encompassing the full range of neuromodulation and inhibition investigated, achieving this wide range required large changes in the pattern and amplitude of the excitatory drive.

2.4 The solution space for firing patterns of motor units

If each of patterns of excitation, neuromodulation and inhibition that generated the the standard triangular CST generated highly similar motoneuron firing patterns, then the solution spaces for each set of firing patterns would each be large. This firing pattern similarity however did not occur. The heat map in Figure 6 provides a quantitative analysis of one the main differences in motor unit firing patterns, onset-offset hysteresis (this hysteresis was quantified by the ΔF method developed for studies of real motor unit firing patterns

Figure 4: *Top Row* – shows the average and std excitatory input to the MN pool to produce the reference command (Figure 3 – reference input). Each column has a different neuromodulation value from lowest (0.8) to highest (1.2). For this example, the inhibitory gain is set to zero and the excitatory weight distribution is equal across the pool (111 configuration - see section 4.2.3). In short, the lower the neuromodulation the more linear the input command becomes however, the higher the excitatory values becomes. *Bottom Row* - shows the average and std excitation (solid) and inhibition (dotted) for the two extremes of inhibitory schemes (Push-Pull in green and Balanced in orange). Neuromodulation is set to 1.0 (middle of range tried) and the excitatory weight distribution is equal across the pool (111 configuration - see section 4.2.3). The "Push-Pull" inhibitory scheme requires less overall drive to achieve the same output.

Figure 5: Area under the curve for the excitatory inputs calculated by the algorithm (Figure 3 and Methods). *Left* - Shows the area under the curve of the excitatory input with respect to neuromodulation and inhibitory levels (color scheme). There inhibitory levels are clearly segregated across the neurmodulation range. The most efficient inhibitory scheme is "Push-Pull" (-0.7) and the least is "Balanced" (0.7). *Right* - shows the area under the curve of the excitatory input with respect to inhibiton for three neuromodulation level. The curves for each neuromodulation level do not intersect across the range of inhibition. The overall trend resembles the results on the left where the most efficent scheme is for high neurmodulation (1.2) and a "Push-Pull" inhibition (-0.7). These curves were calculated using an equally weighted excitatory input.

in humans (Gorassini et al. 2002) (see Methods and Figure 7)). The differences in neuromodulation and inhibition produced a huge range of hysteretic firing behaviors, ranging from < 1.0 at low neuromodulation levels coupled to strong proportional inhibition (lower left in Figure 6) to > 7.0 for high neuromodulation and strong reciprocal inhibition. Fig. 6 also shows the simulated firing patterns generated by a subset of these combinations (arrows link these patterns to the hysteresis values). As neuromodulation increases, PIC effects (acceleration, attenuation, hysteresis) increase, with push-pull inhibition emphasizing these effects and balanced inhibition suppressing them. These differences for each combination of neuromodulation and inhibition shown in Figure 6 demonstrate that the solution space for matching a particular set of motor unit firing is much more restricted than for matching the overall CST (see Figure 4 and Figure 5).

Note however there is some degree of trade-off for effects of inhibition and neuromodulation on hysteresis along the diagonals in Figure 6. Fortunately, hysteresis is not the only index of motoneuron firing behaviors. Figure 7 illustrates additional features of motoneuron firing patterns that are easily measured and likely to reflect other effects of excitation, inhibition and neuromodulation. These features include firing rate acceleration and attenuation (which are also driven by actions of neuromodulation and inhibition on PICs – see Figure 1C1 and Figure 1C2) as well as recruitment and de-recruitment behaviors (sensitive to the distribution of excitation and S vs F motoneurons – see Figure 1A2). Each of these other characteristics had patterns of variation with respect to inhibition and neuromodulation that varied in comparison to each other and to hysteresis (see Supplemental Figure 10). Therefore, to quantify the effectiveness of RE of motor unit firing patterns to predict the organization of synaptic inputs, we next used multiple regression methods to determine how well combinations of these characteristics of simulated firing properties predicted the level of neuromodulation, the patterns of inhibition and the distribution of excitation to low verse high threshold motoneurons.

2.5 Regression of output variables to predict input organization

We utilized several different types of linear regression techniques (see Methods) and one nonlinear technique (Support Vector Regression using a radial basis function kernel (RBF)). In each case, the regression parameters were calculated from a subset of the data (∼70% of the total) and then used to predict the remaining subset (∼30%). For neuromodulation, all regression methods were similar in their effectiveness. Figure 8A shows the results for standard linear regression (the dashed red line has slope = 1.0 to indicate perfect predictive performance). For each level of neuromodulation (0.8 to 1.2), the vertical scatter is due to various combinations of the pattern of inhibition (which ranged from 0.7 to -0.7, as is in Figure 6) and of the distribution of excitation to low versus high threshold motoneurons (which ranged 0.5 to 2.5). The scatter is considerable, but there is also a tendency for points to cluster near the line. As a result, the regression relation accounts for 76% of the variance (i.e. $R^2 = 0.76$; Table 1 shows the R^2 values for all regression methods for prediction of neuromodulation, inhibition and the distribution of excitation). Thus prediction of the level of neuromodulation is good and indicates that this regression approach can identify the level of neuromodulation with a resolution of about 0.1 units of neuromodulation out of a range of 0.4 (from 0.8 to 1.2). For inhibition, the nonlinear regression was most effective, giving the results shown in Figure 8B. Variance accounted for is 0.85, implying a prediction resolution of about 0.23 units of a range of 1.4 units of inhibition. Finally, Figure 8C shows the regression results for prediction of the relative ing for RE, implying that characteristics of motor unit firing patterns can predict input structure with variances accounted for ranging from 76-91%.

As a final step, we analyzed which motor unit firing characteristics had the most predictive power in identifying each of the three input organizations. Figure 9 provides two perspectives on this question. The

Figure 6: This figure links the firing rate shapes of the MN pool model to the inhibitory and neuromodulatory search space. *Heat Map* - The central figure is a heat map of the mean ΔF values of the MN pool model calculated using the firing rate patterns of the motoneurons in the MN pool model (see section 4.4). These ΔF values are organized along the neuromodulation (x-axis) and inhibitory values (y-axis) used in the simulations. *Firing Rate Plots* - Emanating from the central figure are a subset of the firing rate plots of the MN pool model given a specific Inhibitory and Neuromodulation set (e.g. (0.2, 0.9)). These plots are linked to a ΔF value with an arrow. For clarity, only a subset of motoneuron firing rates are shown. From visual inspection, the shape of the firing rates differ given the Inhibition and Neuromodulation pair, from more non-linear (e.g. (-0.7, 1.2)) to more linear (e.g. (0.2, 0.9))

Figure 7: Features extracted from the firing rate patterns of each of the motoneurons in the pool. We extracted the following 7 features: Recruitment Time (t_{rec}), De-Recruitment Time (t_{drec}), Activation Duration (t_{dur}), Recruitment Range (t_{range}), Firing Rate Saturation (α_{sat}), Firing Rate Hysteresis (ΔF) and brace–height (*brace–height*). These features are then used to estimate the neuromodulation, inhibition and excitatory weights of the motor pool (see section 4.5 and 2.5). See subsection 4.4 for details on how to extract features.

Figure 8: Summary plots showing the goodness of fit of the different predicted values: (A) Inhibition, (B) Neuromodulation and (C) excitatory Weight Ratio. The summary plots are for the models showing highest R^2 results in Table 1. The predicted values are calculated using the features extracted from the firing rates (see Figure 7, section 4.5 and 2.5)

.

left column shows results of step-wise regression, starting with the characteristic with the strongest predictive power and then progressively adding the others. For neuromodulation, all regression methods behaved similarly, in that the first two characteristics (brace-height and ΔF see Figure 7) was highly effective in reducing error in the regression prediction, with little addition benefit from adding the others. For inhibition prediction via the linear regression models, ΔF was most effective, followed by α_{sat}, with all others being ineffective. This is shown in the mutual information ranking (right side) in Figure 9, which ranks the characteristics (features) by contribution of new information to the regression model. The left side of Figure 9 ranks the features by the F-statistic, which does not necessarily imply that new information is introduced into the regression model. This is shown by the very subtle improvements in the error (mean squared error) as features are cumulatively added to the regression model, until t_{drec} and α_{sat} are added to the model. However, the nonlinear regression method (RBF SVR) was more effective than any of the linear methods. For this method, each of the firing characteristics had a notable effect in reducing error. For linear regression for prediction of excitation, t_{drec} (the average time when units were de-recruited) was the most impactful and adding the other characteristics brought little improvement. The nonlinear regression, as for inhibition, continued to reduce error as additional firing characteristics were added. The right column in Figure 9 shows mutual information for each characteristic, which reflects how well each one predicts the input behaviors on its own. As expected, the order of effectiveness of prediction in these plots is identical to that for the step-wise regression. Overall, neuromodulation is best predicted by brace-height and ΔF. Inhibition is also predicted by ΔF while *brace–height* is ineffective. Excitation (excitatory weight ratio) is best predicted by parameters that assess recruitment and derecruitment timings and less informed in prediction by ΔF and *brace–height.* These different roles for RE prediction of input make sense in terms of the physiological effects of the three types of inputs on motoneuron firing patterns (see Discussion).

3 Discussion

Our simulation shows that the solution space for a motor output variable that reflects the net action of all active motoneurons is indeed very broad. The variable investigated here, the cumulative spike train (CST), has been shown to be closely proportional muscle EMG and muscle force (Thompson et al. 2018), which are widely assessed in experimental paradigms in both animals and humans. Our simulations however indicate that RE analyses of CSTs, EMGs and forces are likely to fail due to the problem of non-uniqueness. In contrast, motoneuron firing patterns provide a much greater level of information about motor output. Our simulations showed that the solution space for a set of motoneuron firing patterns is reasonably small, allowing predictions that account for 75-90% of the variance in the level of neuromodulation, the pattern of inhibition and the distribution of excitation to S vs F motoneurons.

Table 1: R^2 values. Rows are the predicted values. Columns are the models. The R^2 values in bold represents the best model fit: Inhibition is best predicted using the RBF SVM model, Neuromodulation is best predicted by the Ridge model, Excitation Weight Ratio is best predicted by the RBF SVM model.

Name	Linear Regression	Lasso	Ridge	Elastic Net	Linear SVM	RBF SVM
Inhibition	0.36	0.36	0.36	0.36	0.35	**0.85**
Neuromodulation	0.75	0.76	**0.76**	0.75	0.74	0.71
Excitation Weight Ratio	0.72	0.72	0.72	0.72	0.72	**0.91**
Average	0.61	0.61	0.61	0.61	0.60	**0.83**

Figure 9: Shows the impact of the features on the models at predicting Inhibition, Neuromodulation and the excitatory Weight Ratios. The plots are split along two columns showing two types of complementary analysis: F-Statistic (left) and Mutual Information (right). *Left* - The left column shows the impact of the features on the MSE as ranked by their *F* value. The effect of the features are cumulative along the x-axis such that the value of the MSE at a given position in the x-axis is calculated using the features up to that point. Each of the colored traces represent one of the models used to predict the 3 outcomes and follows the trends found in Table 1. *Right* - The right column shows the mutual information of each feature with respect to the outcome: Inhibition, Neuromodulation and exciatory Weight Ratio (Top to Bottom). The features are ranked from best to worst along the x-axis. The ranking matches the MSE ranking in the right column. See section 4.5.3 to see details on how these techniques were implemented.

3.1 Generalization

Array electrodes are extensively used in many parts of the CNS to record firing patterns of populations of neurons in awake behaving animals (see Introduction). Moreover, highly realistic models of neurons and their interconnections in many systems are already available and undergoing rapid development, including supercomputer implementation (Einevoll et al. 2019). Since models and firing patterns are the fundamental elements for success of RE in the simulations presented here, this same type of approach may be effective in many other neural systems. In each neural system, however, success of RE of firing patterns into input structures as simulated here is likely to depend on the particular interactions between neuromodulation, inhibition and excitation. For motoneurons the nonlinearities induced by PICs in motoneuron firing patterns have proven to be a major advantage for RE. These nonlinearities impart distinctive characteristics to firing patterns (acceleration, attenuation, hysteresis – see Figure 1C1, the firing pattern at the upper right in Figure 6), which are easy to quantify (see Figure 7). Moreover, because the PIC is highly sensitive to inhibition, these same firing characteristics provided effective indices of the temporal pattern of inhibition. Furthermore, because these relations between neuromodulation and inhibition were different for each firing characteristic (see Supplementary Figure 10), multiple regression using these characteristics was effective. It seems likely that if motoneurons were nearly linear input output processors, non-uniqueness would be a much greater problem for RE.

3.2 Muscle EMG versus single motor unit firing patterns

Muscle EMG is the electrical signal generated by the summed action potentials of the muscle fibers of all active motor units. EMG is easy to measure in many types of motor behaviors in humans and other animals and provides an effective measurement of the timing and overall pattern of the neural output from the spinal cord to muscle. However, the simulations here and in our previous work (Powers, ElBasiouny, et al. 2012; Powers and Heckman 2017) show that EMG does not provide information about the organization of motor commands that produce spinal motor output. On the other hand, because motoneurons action potentials are one-to-one with those of their muscle fibers in healthy humans and other animals, motor unit firing patterns are equivalent to motoneuron firing patterns. While motor unit firing patterns are more technically difficult to measure than whole muscle EMG, the accessibility of muscle makes these measurements highly feasible. In fact, motor unit firing patterns in humans were recorded at the very onset of single neuron studies, over 90 years ago (Adrian and Bronk 1929). The likelihood that this single neuron information provide deep insights into the structure of motor commands has thus long been appreciated (Duchateau and Enoka 2011). Many such studies were essential for establishing the prevalence of Henneman's size principle of recruitment (reviewed in Heckman and Enoka 2012). Many studies also focused on inferring the time course of EPSPs and IPSPS driving motoneuron responses transient ionotropic inputs during steady contractions (reviewed in Türker and Powers 2005). The distinctive effects of PICs on firing have also been a focus, with the ΔF method developed by Gorassini and colleagues for quantifying PIC-induced hysteresis having become a standard in the field Gorassini et al. 2002. However, intracellular current and voltage clamp studies have demonstrated that the PIC is highly sensitive both to neuromodulatory input (Hounsgaard et al. 1988; Lee and Heckman 2000; Lee and Heckman 1999) and inhibition (Hyngstrom, Johnson, and Heckman 2008; Kuo et al. 2003). Consistent with this, ΔF does not provide good discrimination of neuromodulation versus inhibition in our simulations (Figure 9). In contrast, and consistent with our previous study (Beauchamp, Pearcey, et al. 2022), the brace–height parameter was sensitive to neuromodulation but insensitive to inhibition, likely because it is

normalized for peak firing. In general, our simulations show that no one motor unit firing characteristic is sufficient for estimation of input structure and thus a form of RE is necessary.

3.3 Limitations

Ensemble model approaches for RE are obviously reliant on the biological accuracy of the constituent models. Our models have been carefully tuned to replicate experimental data from years of current and voltage clamp studies of the integration of neuromodulatory, inhibitory and excitatory inputs motoneurons in feline preparations. We made a few adjustments to these models to more closely replicate the slow firing rates in human motor units but will likely need to further adjustment parameters like the spike AHP and the PIC voltage threshold. Our RE was not applied for identification of the amplitude or time course of the excitation. The peak excitatory conductance for each simulation strongly depends on the level of neuromodulation and the pattern of inhibition (Figure 4). This correlation was built into our simulations to match the CST for each combination of neurmodulation/inhibition and so excitation was not an independent parameter. Further simulations in which we relax this constraint or allow inhibition and/or neuromodulation to vary for a given pattern of excitation may prove interesting. It will also be interesting to expand our range of neuromodulation. At the high end, this expansion will have to be limited, as controlling such large PICs is difficult. But exploring whether RE works as at lower neuromodulation levels where input-output processing is nearly linear would reveal whether this simpler behavior limits RE effectiveness.

3.4 Summary

Although our models likely need modification before we begin RE of human motor unit firing patterns, they were well situated to the goal of this study, which was to investigate the feasibility of RE of neuron firing patterns despite the strong tendency for neural systems to be non-unique.

4 Methods

4.1 Motoneuron pool model

The motoneuron pool consists of 20 model motoneurons with a range of intrinsic properties. This motonouron pool size was chosen to reflect the typical sample size of motor units discriminated based on surface EMG array recordings. Each model motoneuron consisted of a soma compartment and four dendritic compartments, each coupled to the soma. The size of the compartments, the values of capacitance and passive conductance of each compartment, and the values of coupling conductance between compartments were chosen to replicate a number of features of fully constructed dendritic trees, including local input resistance, asymmetric voltage attenuation between the soma and dendritic areas, membrane time constants, total surface area, and neuronal input resistance, as described by Kim and colleagues (Kim, Major, and Jones 2009; Kim and Jones 2012). Spike conductances (g_{Na} and g_K) and conductances mediating the medium AHP were inserted into the soma compartment and a calcium conductance mediating the slowly-activating persistent inward current (PIC) was inserted into each of the dendritic compartments. In addition, a hyperpolarization-activated mixed-cation (HCN) conductance was inserted into all compartments. Conductance densities, kinetics and steady-state activation curves were originally tuned to recreate the range of input-output behavior recorded in medial gastrocnemius (MG) motoneurons in decerebrate cats, as described in Powers and Heckman 2017. Specifically,

the models replicated the range of current-voltage (I − V) relations recorded during somatic voltage-clamp and the frequency-current (F − I) relations recorded during somatic current injection (Powers and Heckman 2017). The range of observed behaviors was achieved by systematically varying a number of parameters across the pool, including AHP duration, specific input resistance, surface area, and the density and half-activation voltage of the PIC conductance. We made four modifications to model parameters for the cat MG pool in order to produce the lower firing rates and less than full recruitment typically observed during moderate voluntary contractions in human subjects. First, the range of values governing excitability were restricted to the first 75% of the original recruitment range (i.e., the parameters of motoneuron 20 in the new model corresponded to motoneuron 15 in the original parameter set). Second, AHP durations and amplitudes were increased by increasing the values of the time constant of calcium removal for the calcium-activated potassium conductance (from 60 to 10 ms in the original model to 90 to 57 ms). The larger and longer AHPs acted to oppose early PIC activation during increasing excitatory synaptic drive, so we hyperpolarized the PIC half-activation threshold (from -40 to -37 mV in the original model to -42 to -40.4 mV). Finally, in the original model the slow decay of PICs observed in high threshold MG motoneurons (Lee and Heckman 1996) was replicated by including a voltage-dependent inactivation process. We found that this process limited the firing rate hysteresis to values below those typically seen in human motor unit recordings, so we eliminated PIC inactivation in the present model pool. All simulations were run using the Python interface to the NEURON simulator (Hines and Carnevale 1997). NEURON files specifying motoneuron pool parameters, conductance mechanisms and protocols for producing motoneuron pool output in response to synaptic conductance inputs can be found at http://modeldb.yale.edu/239582.

4.2 Simulation protocol

4.2.1 Inputs to the motoneuron pool

The target motoneuron pool output, representing the average firing rate across the entire pool of 20 motoneurons was 22 seconds in length and consisted of 1 sec delay followed by a linear rise to a peak value of 16 imp/s over then next 10 sec, and a linear decline back to zero in 10 sec (Figure 3, Reference Ref). A scaled version of this command, $I_{ex} = 0.6Ref$, (Figure 3, light salmon colored with the value 0 to its bottom left) was used as the first guess of the time course of the excitatory input needed to produce the target output. For each iteration an inhibitory conductance input (I_{in}) was also applied according to the following equation:

$$I_{in} = G_{in}I_{ex} + b_{in} \tag{1}$$

where the excitatory input I_{ex} is multiplied by a gain G_{in} and biased by b_{in} as defined by:

$$b_{in} = 6.25R_{mod}^2 - 1.25R_{mod} - 1 \tag{2}$$

where R_{mod} is the neuromodulation value, set in this work, from 0.8 to 1.2 at increments of 0.1 (i.e. [0.8:0.1:1.2]). The inhibition is therefore coupled to the neuromodulation through its bias, b_{in}, and was set to value just sufficient to ensure PIC deactivation at the end of the command. The inhibitory gain, G_{in}, is varied from -0.7 to 0.7 in increments of 0.1 thus traversing the possible control schemes push-pull inhibition to balanced inhibition. Example of both control schemes can be seen in Figure 2 (green for excitatory and red for inhibitory).

Changes in neuromodulation were simulated by changing the density of dendritic PIC channels: from 80%

to 120% of the standard density in 10% increments. Mathematically, the MN model was altered by changing the current I_{Ca_L} of the L-type calcium channel according to these equations:

$$I_{Ca_L} = g_{Ca_L} m_{Ca_L} h_{Ca_L} (V - E_{Ca_L}) \tag{3}$$

$$g_{Ca_L} = R_{mod} \bar{g}_{Ca_L} \tag{4}$$

where I_{Ca_L} is the current for L-type calcium channel, g_{Ca_L} is the conductance of the L-type calcium channel, m_{Ca_L} and h_{Ca_L} are the activation gates, V is the compartment voltage, and E_{Ca_L} is the reversal potential for the L-type calcium channel. R_{mod} is the gain factor that changes the maximum conductance – $\bar{g}_{Ca_L}$ – of the L-type Calcium channel with the following values $[0.8, 0.9, 1.0, 1.1, 1.2]$.

Finally, filtered Gaussian noise was added to both the excitatory and inhibitory commands with a standard deviation that varied in proportion to the square root of the mean level and a decay time constant of 20 ms to reflect the fact that most of the power in the synaptic input to motoneurons is thought to be in the low frequency (< 10 Hz) range (Farina, Rehbaum, et al. 2014).

4.2.2 Feedback and optimization

We used an iterative optimization procedure to find the motoneuron pool input needed to produce the "Reference" output as shown in Figure 3. We opted for a feedback type of optimization method to converge onto the solution.

For the feedback to work, an error term is calculated between the output of the MN pool and the "Reference" (see the "Controller" Figure 3). The output of the MN pool is the average of the 20 MN pool calculated by convolving each model spike train with a 2-s Hanning window with unit area, adding up the result across all 20 spike trains and dividing by 20:

$$I_{ex_n} = \frac{1}{20} \sum_{i}^{20} (F(t)_i * H(t)) + Ke(t) \tag{5}$$

where I_{ex_n} is the new excitatory input, n is the iteration in the feedback loop, $F(t)_i$ is the firing rate of a MN $i = [0:20]$ in the 20 MN pool, $H(t)$ is the 2-s Hanning window, $e(t)$ is the error and K is proportional gain (usually 20%). This average firing rate response produced plus the error – I_{ex_n} – is then used as the new excitatory command to the MN Pool. This is shown by the series of traces leaving the "Plant System - Motoneuron (MN) pool" in Figure 3. Using I_{ex_n}, a new inhibitory command is also calculated using equation 1 and is subsequently used in the new computational iteration n.

This process was repeated until the mean squared error between the output and the target was less than 1 Hz^2 (generally less than 0.5 Hz^2). In the case shown in Figure 3, good convergence was reached by the fifth iteration.

This iterative matching procedure was repeated for 225 different input combinations: five levels of neuromodulation, three different distributions of excitatory input, and fifteen different levels of inhibition.

4.2.3 Excitatory distribution or MN weights

The density of the excitatory synaptic conductance was either uniform across all cells, weighted toward low threshold units (synaptic weight onto lowest threshold unit 2 X that of highest threshold unit), or weighted

toward high threshold units (high weight 2X low). The parameters governing cell excitability were skewed to produce a greater proportion of low threshold units, so synaptic weighting showed a similar skew according to the following equation:

$$w_{MN\#} = w_{start} + \left(\frac{MN\#}{\#MN - 1} \right)^2 (w_{end} - w_{start}) \tag{6}$$

where $w_{MN\#}$ is the weight of the given motoneuron, $\#MN$ is the number of the MN in the pool (e.g. 20), w_{end} and w_{start} are the weight range. For weights favoring low threshold units, $w_{start} = 2.5$ and $w_{end} = 1.0$ and for the opposite $w_{start} = 1.0$ and $w_{end} = 2.5$. In total we used 7 different types of weight configurations: $[w_{start}, w_{end}] \iff [1, 1], [1.5, 1], [2, 1], [2.5, 1], [1, 1.5], [1, 2], [2.5, 1]$.

4.2.4 Noise Seed

We chose to calculate the model using 30 different noise seeds. We assumed that each seed would represent a "unique" individual and allow for the use of averages and variance in our interpretation of the results. *Note*: The noise seed was not reset for each of motoneurons in the pool. The synaptic noise is thus coupled for each of the motoneurons which fits with the "common drive" argument (see section 2.1.1).

4.3 Massively-parallel Data Generation Methods

Since the majority of the simulation is able to operate independently as the simulations for each of the parameter sets (noise seeds, inhibitory gains, and neuromodulation) did not need to feed into each other, we were able to run this simulation in a perfectly parallel way. Each unique parameter set was simulated using one node (computer) in a supercomputing cluster, which produced a dataset file of the simulation results (see Algorithm 1). Each node simulated one motor pool, with the computation of each motoneuron run on each processor on the compute node (see Algorithm 2). To implement this setup, we utilized the MPI interface in NEURON 7.7 (CITE) and Python 3.6.7 running on the Bebop supercomputer (Intel Broadwell nodes) at Argonne National Laboratory, (Figure 11). Each combination tuple tuple_comb contains a particular ginmult, nmmult, ginadd, and random_seed (if noise is used).

4.4 Feature Extraction

For each simulation input combination, we analyzed the individual motoneuron discharge patterns to extract 7 features: Recruitment Time (t_{rec}), De-Recruitment Time (t_{drec}), Activation Duration (t_{dur}), Recruitment Range (t_{range}), Firing Rate Saturation (α_{sat}), Firing Rate Hysteresis (ΔF) and brace–height (*brace–height*). The calculation of these quantitative measures is illustrated in Figure 7, which shows the instantaneous discharge rates (dots) of a higher (upper panel) and lower threshold (lower threshold) motoneuron, along with the smoothed firing rates calculated by convolving the spike times with a 2-s Hanning window (continuous lines).

Recruitment Time (t_{rec}): Recruitment time is the time of the first instantaneous discharge rate of a given motorneuron.

De-Recruitment Time (t_{drec}): De-Recruitment time is the time of the last instantaneous discharge of a given motoneuron.

Activation Duration (t_{dur}): Activation duration is the difference between de-recruitment time and recruitment time:

Algorithm 1 Python pseudocode for reverse engineering proportional controller on each compute node

```python
def mpi_run_proportional_controller(combinations_subset):
    gain = 0.2  # base gain
    for ginmult, ginadd in combinations_subset:
        stim_time, stim_target = load_targets()
        excitatory_input = load_base_excitatory_input()
        for fit_iteration in range(0, 20):
            # setup simulation
            inhibitory_input = excitatory_input * ginmult + ginadd
            inhibitory_input = max(inhibitory_input, 1e-7)
            sim_data = mpi_run_neuron_sims(
                ginmult, ginadd, excitatory_input, inhibitory_input, stim_time)

            # process simulation result
            average_rate = get_average_rate(sim_data)
            mse = mean_squared_error(stim_target, average_rate)
            if mse < 0.5 and mn_recruited == 20:
                return inhibitory_input, mse, fit_iteration
            elif mse < 3:
                gain = 0.5 * gain
            elif mse < 1.5:
                gain = 0.25 * gain
            error = (stim_target - average_rate) * gain
            excitatory_input += error
            excitatory_input = kludge_me_fam()  # TODO!!!!
            excitatory_input = max(excitatory_input, 1e-7)
```

Algorithm 2 Python pseudocode for simulating each motoneuron independently

```python
def mpi_run_motoneuron(tuple_motoneuron):
    motoneuron_h = load_neuron_data(tuple_motoneuron)
    while motoneuron_h.time_elapsed < 22000:
        motoneuron_h.step()
    return motoneuron_h.spike_times_soma

def mpi_run_neuron_sims(ginmult, ginadd, excitatory_input, inhibitory_input):
    params = [(ginmult, ginadd, excitatory_input, inhibitory_input, mn_id)
              for mn_id in range(0, 20)]
    sim_data = mpi_parallel_context.map(mpi_run_motoneuron, params)
    return sim_data
```

$$t_{dur} = t_{drec} - t_{rec} \tag{7}$$

509 *Recruitment Range* (t_{range}): The recruitment range is the difference between the recruitment time of the
510 last and the first motorneuron in the motorpool.

511 *Firing Rate Saturation* (α_{sat}): The motorneuron firing rate is characterized by an initial acceleration phase
512 that lasts about 1s followed by partial saturation of firing rate. The degree of this saturation is quantified by
513 calculating the rate of firing rate increase from 1 sec after recruitment to the target peak (11 s):

$$\alpha_{sat} = \frac{f_3 - f_2}{t_3 - t_2} \tag{8}$$

where f_3 is the firing rate at 11 s, f_2 is the firing rate 1 s post recruitment (t_{rec}), t_3 is time at target peak 11
s and t_2 is 1 s post recruitment.

Firing Rate Hysteresis (ΔF): A motorneuron rate hysteresis can be quantified using the ΔF measure
introduced by Gorassini and colleagues (Gorassini et al. 2002). ΔF is defined as the difference in the smoothed
firing rate of a lower threshold reporter motorneuron (Figure 7 - bottom) at the onset (t_{rec}, f_0) and offset
(t_{drec}, f_1) of the higher threshold motorneuron (Figure 7 - top):

$$\Delta F = f_0 - f_1 \tag{9}$$

brace–height ($brace - height$): Brace height is a measure of the non-linear portion of the rising phase of
the firing rate of the motoneuron (see Figure 7 - top trace). It is the maximum perpendicular distance from
the line linking the firing rates at recruitment time (t_{rec}) to t_3, the time at which the triangular "Reference"
reaches its maximum (11 s). This distance is calculate by solving the geometric problem of finding the
"Distance from a point to a line". This analysis is further detailed by Beauchamp, Pearcey, et al. 2022.

We restricted the calculation to motorneuron pairs for which the recruitment time difference between the
two was more than 1 s. This restriction was imposed to ensure that PIC activation in the reporter unit had
reached near steady state, so that further changes in reporter discharge rate primarily reflected changes in
synaptic drive (cf. Powers, Nardelli, and Cope 2008).

4.5 Reverse Engineering via machine learning

4.5.1 Data preparation and Heat map

We ran the model for a range of neuromodulation (5), inhibition (15), excitatory weights (7) and noise seeds
(30) for a total of 15,750 combinations. Given 20 motoneuron per pool and 20 optimization iterations (see
Figure 3 or section 4.2.2) we ran a grand total of 6,300,000 simulations.

Post simulations, we extracted the features from the firing rates of each motoneuron (see section 4.4 and
organized them according to the neuromodulation, inhibition, excitatory weight and noise seed. We then first
calculated the average of these features accordingly and then took an average of these averages with respect
to the noise seed. In final, the was an average of the features grouped by neurmodulation, inhibition and
excitatory weight. Figure 10 shows the average of each feature in a heat map configuration for the excitatory
weight distribution $[w_{start}, w_{end}] = [1, 1]$. This data was the used subsequently (see section 4.5.2 and 4.5.3).

4.5.2 Model fits

One of the goals of our reverse engineering approach is to infer the characteristics of the input to the motoneuron pool based on our measures of motor unit output. Since a data-based approach is preferred throughout this study, several machine learning (ML) models are used to implement the reverse engineering process by predictive analysis. The numeric features extracted from the discharge patterns are used to create a five-dimensional input data for the models. The dimensions were the mean ΔF value, times of recruitment (t_{rec}) and derecruitment (t_{drec}), the firing rate saturation degree (α_{sat}), the recruitment range (t_{range}) and brace–height ($brace-height$).

While converging on the ML models, both the size and the dimensionality of the data was taken into account. Since the dataset is relatively small (<1000 instances) and has only 5 dimensions, linear models and their kernelized versions are chosen for predictive analysis. More complex models such as tree-based methods and neural networks were omitted due to the high risk of underfitting to inadequate data.

The target values to predict were the simulation input values, namely level of neuromodulation, inhibition and excitatory weight. One thing not to be confused about is that the ML input values are the features extracted from the simulation output patterns, whereas the ML outputs are the simulation input values. This makes sense because the ML part implements a reverse-engineering process. Since all target values to be predicted in this study were continuous numeric values, the reverse engineering process was posed as a regression task. A regression model is created for each simulation input value to be predicted.

The first model we used was a linear regression model. It maps the instances in a dataset to their predicted values by taking a linear combination of the features of each instance. For a given instance, the predicted value is:

$$\hat{y} = w^T x \tag{10}$$

where $\hat{y}$ is the predicted value, x is the given instance as a vector and w is the parameter vector that consists of the linear combination coefficients. These coefficients are the parameters of the linear model and their optimal values are obtained by training the model with the training dataset. The training for a dataset with N instances in D dimensions is done by minimizing the cost function defined as:

$$J(\mathbf{w}) = \frac{1}{N} \sum_{i=1}^{N} (y^{(i)} - \mathbf{w}^T \mathbf{x}^{(i)})^2 + r\alpha \sum_{j=1}^{D} (|w_i|) + \frac{1-r}{2} \alpha \sum_{j=1}^{D} (w_i)^2 \tag{11}$$

where the first term is the mean squared error (MSE) cost and the rest is the regularization cost. The second term uses $L1$ penalty to the model by adding the absolute value of the parameters to the cost function and the third term uses $L2$ penalty by adding the parameter values squared. The hyperparameter α determines the scale of the penalty as the coefficients get bigger, which indicates model complexity. Another hyperparameter is r and it determines which penalty is used to what extent. If r is 0, only the $L2$ penalty will be used (Lasso Regression) and if it is 1, only the $L1$ penalty is used (Ridge Regression). For any value of r between 0 and 1, both penalties are used and this is called Elastic Net Regression.

Even though a closed form solution to minimize the cost can be calculated, it would be computationally inefficient. Hence, Mini-batch Gradient Descent (GD) method is used to optimize the model parameters. The hyperparameters are optimized by an extensive grid search, using 10-fold cross-validation.

A support vector machine (SVM) was the second linear ML model we used. For a regression task, it fits

the data to a narrow "street" with its margin as small as possible. The width of the "street" is controlled by a hyperparameter ϵ and another hyperparameter C controls the penalty for each instance that remains outside the margin. Even though the intuition behind SVM models is fairly simple, the math behind the optimization is complex and can be further read in the included references.

Lastly, a non-linear model was used on the data to see if there is more than a linear relation between the extracted features and the target values. Since most non-linear models would be useful because of the small data size, we introduced a non-linear kernel to the dual optimization step of the SVM. So, instead of a dot product between two instances, there is a Radial Basis Function (RBF) kernel, which is formulated as:

$$K(\mathbf{x}^{(i)}, \mathbf{x}^{(j)}) = exp(-\gamma||\mathbf{x}^{(i)}, \mathbf{x}^{(j)}||^2) \tag{12}$$

where γ is the kernel hyperparameter that adjusts the variance of the Gaussian function, that defines how far the influence of a single instance can go. A high γ value means the influence of each instance remains within their close vicinity. Introducing the kernel allows the SVM model to capture the non-linearities in a model without much computational cost which is very beneficial, especially for small datasets. The only downside is having another hyperparameter to tune.

4.5.3   Feature Selection: F-Test and Mutual Information

To measure the performance of linear regression against the firing features (see section 4.4), we use a greedy approach towards incorporating more and more features into the linear regression model. For this approach, the F-statistic (linear regression test) is used as the scoring function to order-rank the features for incorporation into a linear regression model. The results of this are shown in the left column of Figure 9, which shows decreasing mean square error (MSE) as more features are incorporated. This was implemented using the F_REGRESSION scorer in SKLEARN library in Python.

We used mutual information (MI) to rank the dependence of the firing rate features (see section 4.4) to the inhibition, neuromodulation and excitatory weight ratio levels of the motoneurons in the pool model. In information theory, MI measures the "amount of information" about one variable by observing another (Ross 2014; Kraskov, Stögbauer, and Grassberger 2004; Kozachenko and Leonenko 1987). An MI of 0 signifies that the two variables are independent. We used the SKLEARN library in Python to calculate the MI for each of the features Pedregosa et al. 2011. Using the MI allows for an alternate ranking if a nonlinear regression method is used, such as support vector regression.

Acknowledgement

1. This research used resources of the Argonne Leadership Computing Facility, which is a DOE Office of Science User Facility supported under Contract DE-AC02-06CH11357.

2. We gratefully acknowledge the computing resources provided on Bebop, a high-performance computing cluster operated by the Laboratory Computing Resource Center at Argonne National Laboratory.

References

Adrian, Edgar D and Detlev W Bronk (1929). "The discharge of impulses in motor nerve fibres: Part II. The frequency of discharge in reflex and voluntary contractions". In: *The Journal of physiology* 67.2, p. i3.

Alvarez, Francisco J et al. (1998). "Distribution of 5-hydroxytryptamine-immunoreactive boutons on α-motoneurons in the lumbar spinal cord of adult cats". In: *Journal of Comparative Neurology* 393.1, pp. 69–83.

Beauchamp, James A, Obaid U Khurram, et al. (2022). "A computational approach for generating continuous estimates of motor unit discharge rates and visualizing population discharge characteristics". In: *Journal of Neural Engineering* 19.1, p. 016007.

Beauchamp, James A, Gregory EP Pearcey, et al. (2022). "A geometric approach to quantifying the neuromodulatory effects of persistent inward currents on single motor unit discharge patterns". In: *bioRxiv.*

Berg, Rune W, Aidas Alaburda, and Jørn Hounsgaard (2007). "Balanced inhibition and excitation drive spike activity in spinal half-centers". In: *Science* 315.5810, pp. 390–393.

Binder, Marc D, Randall K Powers, and CJ Heckman (2020). "Nonlinear input-output functions of motoneurons". In: *Physiology* 35.1, pp. 31–39.

Buonomano, Dean V and Wolfgang Maass (2009). "State-dependent computations: spatiotemporal processing in cortical networks". In: *Nature Reviews Neuroscience* 10.2, pp. 113–125.

Chandrasekaran, Santosh et al. (2021). "Historical perspectives, challenges, and future directions of implantable brain-computer interfaces for sensorimotor applications". In: *Bioelectronic medicine* 7.1, pp. 1–11.

De Luca, Carlo J and Paola Contessa (2012). "Hierarchical control of motor units in voluntary contractions". In: *Journal of neurophysiology* 107.1, pp. 178–195.

De Luca, Carlo J and Zeynep Erim (1994). "Common drive of motor units in regulation of muscle force". In: *Trends in neurosciences* 17.7, pp. 299–305.

Duchateau, Jacques and Roger M Enoka (2011). "Human motor unit recordings: origins and insight into the integrated motor system". In: *Brain research* 1409, pp. 42–61.

Edelman, Gerald M and Joseph A Gally (2001). "Degeneracy and complexity in biological systems". In: *Proceedings of the National Academy of Sciences* 98.24, pp. 13763–13768.

Einevoll, Gaute T et al. (2019). "The scientific case for brain simulations". In: *Neuron* 102.4, pp. 735–744.

Farina, Dario and Francesco Negro (2015). "Common synaptic input to motor neurons, motor unit synchronization, and force control". In: *Exercise and sport sciences reviews* 43.1, pp. 23–33.

Farina, Dario, Hubertus Rehbaum, et al. (2014). "Noninvasive, accurate assessment of the behavior of representative populations of motor units in targeted reinnervated muscles". In: *IEEE Transactions on Neural Systems and Rehabilitation Engineering* 22.4, pp. 810–819.

Goaillard, Jean-Marc and Eve Marder (2021). "Ion channel degeneracy, variability, and covariation in neuron and circuit resilience". In: *Annual review of neuroscience* 44.1, pp. 335–357.

Gorassini, Monica et al. (2002). "Intrinsic activation of human motoneurons: reduction of motor unit recruitment thresholds by repeated contractions". In: *Journal of Neurophysiology* 87.4, pp. 1859–1866.

Heckman, CJ and Marc D Binder (1988). "Analysis of effective synaptic currents generated by homonymous Ia afferent fibers in motoneurons of the cat". In: *Journal of Neurophysiology* 60.6, pp. 1946–1966.

— (1993). "Computer simulations of the effects of different synaptic input systems on motor unit recruitment". In: *Journal of Neurophysiology* 70.5, pp. 1827–1840.

Heckman, CJ and Roger M Enoka (2012). "Motor unit". In: *Comprehensive physiology* 2.4, pp. 2629–2682.

Heckman, CJ, Monica A Gorassini, and David J Bennett (2005). "Persistent inward currents in motoneuron dendrites: implications for motor output". In: *Muscle & Nerve: Official Journal of the American Association of Electrodiagnostic Medicine* 31.2, pp. 135–156.

Henneman, E and LM Mendell (1981). "Handbook of Physiology. The Nervous System. Motor Control." In: *Bethesda, MD: American Physiological Society*, pp. 423–507.

Hines, Michael L and Nicholas T Carnevale (1997). "The NEURON simulation environment". In: *Neural computation* 9.6, pp. 1179–1209.

Holobar, Aleş et al. (2010). "Experimental analysis of accuracy in the identification of motor unit spike trains from high-density surface EMG". In: *IEEE Transactions on Neural Systems and Rehabilitation Engineering* 18.3, pp. 221–229.

Holstege, JC and HGJM Kuypers (1987). "Brainstem projections to spinal motoneurons: an update". In: *Neuroscience* 23.3, pp. 809–821.

Hounsgaard, JORN et al. (1988). "Bistability of alpha-motoneurones in the decerebrate cat and in the acute spinal cat after intravenous 5-hydroxytryptophan." In: *The Journal of physiology* 405.1, pp. 345–367.

Hu, Xiaogang, William Z Rymer, and Nina L Suresh (2013). "Motor unit pool organization examined via spike-triggered averaging of the surface electromyogram". In: *Journal of neurophysiology* 110.5, pp. 1205–1220.

Hug, François et al. (2021). "Analysis of motor unit spike trains estimated from high-density surface electromyography is highly reliable across operators". In: *Journal of Electromyography and Kinesiology* 58, p. 102548.

Hyngstrom, Allison S, Michael D Johnson, and Charles J Heckman (2008). "Summation of excitatory and inhibitory synaptic inputs by motoneurons with highly active dendrites". In: *Journal of neurophysiology* 99.4, pp. 1643–1652.

Hyngstrom, Allison S, Michael D Johnson, Jack F Miller, et al. (2007). "Intrinsic electrical properties of spinal motoneurons vary with joint angle". In: *Nature neuroscience* 10.3, pp. 363–369.

Kim, Hojeong and Kelvin E Jones (2012). "The retrograde frequency response of passive dendritic trees constrains the nonlinear firing behaviour of a reduced neuron model". In.

Kim, Hojeong, Lora A Major, and Kelvin E Jones (2009). "Derivation of cable parameters for a reduced model that retains asymmetric voltage attenuation of reconstructed spinal motor neuron dendrites". In: *Journal of computational neuroscience* 27.3, pp. 321–336.

Kozachenko, Lyudmyla F and Nikolai N Leonenko (1987). "Sample estimate of the entropy of a random vector". In: *Problemy Peredachi Informatsii* 23.2, pp. 9–16.

Kraskov, Alexander, Harald Stögbauer, and Peter Grassberger (2004). "Estimating mutual information". In: *Physical review E* 69.6, p. 066138.

Kuo, Jason J et al. (2003). "Active dendritic integration of inhibitory synaptic inputs in vivo". In: *Journal of neurophysiology* 90.6, pp. 3617–3624.

Lee, RH and CJ Heckman (1996). "Influence of voltage-sensitive dendritic conductances on bistable firing and effective synaptic current in cat spinal motoneurons in vivo". In: *Journal of neurophysiology* 76.3, pp. 2107–2110.

— (1998a). "Bistability in spinal motoneurons in vivo: systematic variations in persistent inward currents". In: *Journal of neurophysiology* 80.2, pp. 583–593.

— (1998b). "Bistability in spinal motoneurons in vivo: systematic variations in rhythmic firing patterns". In: *Journal of neurophysiology* 80.2, pp. 572–582.

Lee, RH and CJ Heckman (1999). "Enhancement of bistability in spinal motoneurons in vivo by the noradrenergic α1 agonist methoxamine". In: *Journal of neurophysiology* 81.5, pp. 2164–2174.

Lee, Robert H and Charles J Heckman (2000). "Adjustable amplification of synaptic input in the dendrites of spinal motoneurons in vivo". In: *Journal of Neuroscience* 20.17, pp. 6734–6740.

Lim, Hun Ki, Leslie P Keniston, and Krzysztof J Cios (2011). "Modeling of multisensory convergence with a network of spiking neurons: a reverse engineering approach". In: *IEEE transactions on biomedical engineering* 58.7, pp. 1940–1949.

Lindsay, AD and Marc D Binder (1991). "Distribution of effective synaptic currents underlying recurrent inhibition in cat triceps surae motoneurons". In: *Journal of neurophysiology* 65.2, pp. 168–177.

Maratta, Robert et al. (2015). "Distribution and density of contacts from noradrenergic and serotonergic boutons on the dendrites of neck flexor motoneurons in the adult cat". In: *Journal of Comparative Neurology* 523.11, pp. 1701–1716.

Marder, Eve (2012). "Neuromodulation of neuronal circuits: back to the future". In: *Neuron* 76.1, pp. 1–11.

McCormick, David A and Michael P Nusbaum (2014). "Editorial overview: neuromodulation: tuning the properties of neurons, networks and behavior". In: *Current opinion in neurobiology* 29, p. iv.

Mukunda, Chinmayee L and Rishikesh Narayanan (2017). "Degeneracy in the regulation of short-term plasticity and synaptic filtering by presynaptic mechanisms". In: *The Journal of Physiology* 595.8, pp. 2611–2637.

Negro, Francesco et al. (2016). "Multi-channel intramuscular and surface EMG decomposition by convolutive blind source separation". In: *Journal of neural engineering* 13.2, p. 026027.

Pedregosa, F. et al. (2011). "Scikit-learn: Machine Learning in Python". In: *Journal of Machine Learning Research* 12, pp. 2825–2830.

Pisokas, Ioannis (2021). "Reverse Engineering and Robotics as Tools for Analyzing Neural Circuits". In: *Frontiers in Neurorobotics* 14, p. 578803.

Powers, Randall K and Marc D Binder (2001). "Input-output functions of mammalian motoneurons". In: *Reviews of physiology, biochemistry and pharmacology*, pp. 137–263.

Powers, Randall K, Sherif M ElBasiouny, et al. (2012). "Contribution of intrinsic properties and synaptic inputs to motoneuron discharge patterns: a simulation study". In: *Journal of neurophysiology* 107.3, pp. 808–823.

Powers, Randall K and Charles J Heckman (2017). "Synaptic control of the shape of the motoneuron pool input-output function". In: *Journal of neurophysiology* 117.3, pp. 1171–1184.

Powers, Randall K, Paul Nardelli, and Timothy C Cope (2008). "Estimation of the contribution of intrinsic currents to motoneuron firing based on paired motoneuron discharge records in the decerebrate cat". In: *Journal of neurophysiology* 100.1, pp. 292–303.

Prinz, Astrid A (2010). "Computational approaches to neuronal network analysis". In: *Philosophical Transactions of the Royal Society B: Biological Sciences* 365.1551, pp. 2397–2405.

Prinz, Astrid A, Dirk Bucher, and Eve Marder (2004). "Similar network activity from disparate circuit parameters". In: *Nature neuroscience* 7.12, pp. 1345–1352.

Ross, Brian C (2014). "Mutual information between discrete and continuous data sets". In: *PloS one* 9.2, e87357.

Rostro-Gonzalez, Horacio, Bruno Cessac, and Thierry Viéville (2012). "Parameter estimation in spiking neural networks: a reverse-engineering approach". In: *Journal of Neural Engineering* 9.2, p. 026024.

Stevenson, Ian H and Konrad P Kording (2011). "How advances in neural recording affect data analysis". In: *Nature neuroscience* 14.2, pp. 139–142.

Stevenson, Ian H, Brian M London, et al. (2012). "Functional connectivity and tuning curves in populations of simultaneously recorded neurons". In: *PLoS computational biology* 8.11, e1002775.

Telenczuk, Bartosz, Maria Telenczuk, and Alain Destexhe (2020). "A kernel-based method to calculate local field potentials from networks of spiking neurons". In: *Journal of Neuroscience Methods* 344, p. 108871.

Thompson, Christopher K et al. (2018). "Robust and accurate decoding of motoneuron behaviour and prediction of the resulting force output". In: *The Journal of physiology* 596.14, pp. 2643–2659.

Türker, KS and RK Powers (2005). "Black box revisited: a technique for estimating postsynaptic potentials in neurons". In: *Trends in neurosciences* 28.7, pp. 379–386.

Vyas, Saurabh et al. (2020). "Computation through neural population dynamics". In: *Annual Review of Neuroscience* 43, p. 249.

Yang, Jane et al. (2022). "Minimal requirements for a neuron to coregulate many properties and the implications for ion channel correlations and robustness". In: *Elife* 11, e72875.

Yochum, Maxime et al. (2019). "Reconstruction of post-synaptic potentials by reverse modeling of local field potentials". In: *Journal of Neural Engineering* 16.2, p. 026023.

Figure 10: Heat maps for the different features extracted from the firing rates of the monotoneurons in the pool model. These heat maps are for the equally distributed excitatory weights $[w_{start}, w_{end}] = [1, 1]$ (see section 4.2.3). Each heat map is organized along the Neuromodulation and Inhibitory ranges tried in this work (see section 4.5.1 for details on how the values were calculated). The values within these heat maps show structure with respect to Neuromodulation and Inhibition and show that this structure can be used to reverse engineer the Neuromodulation and Inhibition themselves (see 2.5 and 4.5.2).

Figure 11: Schematic of the parallel architecture used to solve the MN pool model and to find the solution for the input to that pool (see Figure 3). Each neuromodulation, inhibition, excitatory input weight and noise seed combination was assigned a node on the computer via the slurm batch scheduler. These "hyper-parameters" were passed to each motoneuron which had a dedicated CPU core using the message passing interface (MPI). This work was done on the high performance computer BEBOP at Argonne National Laboratory, Lemont, IL. See section 4.3 for details.