1 **Different methods to estimate the phase of neural rhythms agree, but**
2 **only during times of low uncertainty**
3

Anirudh Wodeyar [1], François A. Marshall [1], Catherine J. Chu [2,3], Uri T.
Eden [1,4], Mark A. Kramer [1,4]

1. Department of Mathematics & Statistics, Boston University, Boston MA, USA
2. Department of Neurology, Massachusetts General Hospital, Boston, MA; USA
3. Harvard Medical School, Boston, MA, USA
4. Center for Systems Neuroscience, Boston University, Boston MA, USA

10
11

12
13
14

15 **Abstract**
16
Rhythms are a common feature of brain activity. Across different types of rhythms,
the phase has been proposed to have functional consequences, thus requiring its
accurate specification from noisy data. Phase is conventionally specified using
techniques that presume a frequency band-limited rhythm. However, in practice,
observed brain rhythms are typically non-sinusoidal and amplitude modulated. How these
features impact methods to estimate phase remains unclear. To address this, we consider
three phase estimation methods, each with different underlying assumptions about the
rhythm. We apply these methods to rhythms simulated with different generative
mechanisms and demonstrate inconsistency in phase estimates across the different
methods. We propose two improvements to the practice of phase estimation: (1)
estimating confidence in the phase estimate, and (2) examining the consistency of phase
estimates between two (or more) methods.

29
Significant Statement: Rhythms in the brain can coordinate the activity of individual
neurons and communication within brain networks, making these rhythms a target for
therapeutic interventions. Brain rhythms manifest in diverse ways, appearing with
sinusoidal and non-sinusoidal waveforms, multiple peak frequencies, and variable
durations. Across this diversity of rhythms, an important feature to characterize is the
rhythm's phase. In this manuscript, we demonstrate the ambiguity inherent in estimating
phase from neural data. We propose estimating uncertainty in the phase and comparing
multiple phase estimators improves phase estimation in practice.
38
39
40

41   **Introduction**

A rhythm in the local field potential (LFP), magneto/electroencephalogram
(M/EEG), or intracranial EEG (iEEG) is a waveform repeating without overlap. A cycle of
a rhythm is an expression of the waveform (Cole & Voytek, 2017). Once the waveform is
defined the phase can be used as a local time index of a cycle relative to the waveform.
The phase of rhythms may have a role to play in perception (Busch et al., 2009; Herbst
et al., 2022; Fiebelkorn et al., 2018; Helfrich et al., 2018; VanRullen, 2016),
communication across neural populations (Fries, 2015; Roberts et al., 2013; Wodeyar et
al., 2022), co-ordination within a neural population (Canolty & Knight, 2010) and co-
ordination between local field potentials and neural spikes (Ray et al., 2008; Zanos et al.,
2012; Jarvis & Mitra, 2001; Lepage et al., 2011; Pesaran et al., 2018). Phase has been
of critical importance for therapeutic interventions as well (Widge & Miller, 2019): e.g.,
acoustic stimulation during sleep can induce slow waves (Ngo et al., 2013) and deep-
brain stimulation can reduce Parkinsonian tremor (Cagnan et al., 2017).
55
In practice, phase is estimated with a Fourier analysis on tapered versions of the
time series (Lepage et al., 2013), such as by using a Hilbert transform. In this approach,
we assume that the time series consists of a stable rhythm accurately described as a
harmonic (single frequency) or a narrowband waveform. A truly narrowband signal has
spectral power concentrated in a tight frequency band. Any cycle will have an average
rate of change of phase equal to the center frequency of the frequency band of maximum
spectral power. This assumption determines the waveform and the phase. However,
specifying phase for a cycle is difficult when the rhythm is inseparable from noise, the
waveform has non-sinusoidal properties (Jones, 2016), or there is distortion of the
waveform (such as from filtering a time series (Yael et al., 2018)).
66
Recent evidence suggests that a narrowband model for neural rhythms may be
inaccurate. For example, visual cortex gamma band activity (30-90 Hz, c.f. Buzsaki 2006)
is amplitude modulated and lacks narrowband periodicity (Burns et al., 2010; Spyropoulos
et al., 2022; Xing et al., 2012). In this case, stochastically-driven damped harmonic
oscillators may better model the gamma activity. The discretized version of such a model
is an autoregressive process of order two (abbreviated as AR(2), see Appendix A of
Kramer, 2022). Spyropoulos et al. (2022) show that an AR model fits the broadband
power spectrum of the gamma rhythm well. AR models for both non-invasive (Fran & Bilo
1985) and invasive (Nozari 2020) electroencephalogram recordings support a broadband
representation for brain rhythms. In addition, several studies suggest that brain rhythms
can consist of non-sinusoidal waveforms (Bernardi et al., 2019, Cole & Voytek 2017, Cole
& Voytek 2018, Ouedraogo 2016), exhibit multiple nearby peak frequencies (Tort 2010),
and persist for short periods at a time (Jones 2016, van Ede 2018). These observations

suggest brain rhythms may be broadband, and in these cases narrowband models lead
to phase estimates which do not capture what is intuitively sought by the practitioner.
82
Phase is relatively defined, and how we estimate phase depends on the
interpretation sought by the practitioner. In this manuscript, we consider how different
methods define phase when applied to simulated signals generated in different ways.
Through this analysis, we identify moments when phase estimates agree and disagree
across methods and examine how one may decide which method is best in different
simulation scenarios. We consider three distinct phase estimators: (i) the Hilbert
transform of a narrowband filtered time series, (ii) a state space model of rhythms, and
(iii) the Poincaré section. We apply each of these methods to three simulated time series:
(i) a broadband rhythm in pink noise, (ii) an AR(2) process, and (iii) a Fitzhugh-Nagumo
oscillator. Comparing the cross-method consistency in phase, we show how uncertainty
metrics can be used to improve consistency; when any method shows confidence in the
phase estimate, the different methods tend to agree. Finally, we illustrate example
applications of these methods to estimate coherence and phase-amplitude coupling in *in*
vivo data. We show how estimating uncertainty in the phase helps clarify the link between
phase and other quantities of interest. Understanding the role of phase in neural dynamics
requires us to be aware that phase is not unique and phase estimates may vary
depending upon the method employed.
100
101   **Methods**
102
Overview of Phase Estimation Approaches
We apply three methods to estimate phase, each of which makes different
assumptions for the rhythm model. The first method we consider consists of bandpass
filtering the data and then estimating the phase via the Hilbert transform. While a common
method in neuroscience applications (e.g., Canolty & Knight, 2010; Navas-Olive et al.,
2020; Petersen & Buzsáki, 2020; Zhong et al., 2017), this approach is sensitive to noise
and susceptible to waveform distortion. The second method we consider is a state space
model with the state, representing the amplitude and phase, modeled by stochastically-
driven oscillators. The state space model makes stronger assumptions of the data but is
more resistant to model noise when the model class optimally explains the periodicity in
the data. The final method we consider is the application of the Poincaré section, which
is the most general method considered but is also the most sensitive to noise and user-
defined choices. A complication is that different models which fit a brain rhythm
equivalently well can still give phase estimates tracking distinct features of a rhythm. In
what follows, we use this ambiguity when specifying phase to explore approaches to
validate analyses involving phase.
119

Finite Impulse Response filter and Hilbert Transform (FIR-Hilbert) Method

Fourier-transform based analysis, a wavelet-transform, or a Hilbert transform
employ essentially the same procedure (Bruns, 2004) to estimate the phase but with
different tapering functions. Critically, all these approaches demarcate a set of
frequencies (bandwidth of the narrowband) as relevant to capture the neural signal of
interest and a set of frequencies as being irrelevant (for example, filtering to select the
alpha band, defined as 8 – 13 Hz). This demarcation is intended to separate the signal
and noise without relying on a parameter to explicitly model the noise contribution
(Donoghue et al. 2020). Given the essential equivalence of the windowed-Fourier,
wavelet, and Hilbert transforms (Bruns, 2004), we focus here on the Hilbert transform;
i.e., we apply a filter to the data time series to select a frequency band of interest, apply
the Hilbert transform, and derive the instantaneous phase (Chavez et al., 2006).
132
For an interpretable instantaneous phase - where the phase captures the
waveform periodicity as opposed to amplitude modulation - the Hilbert transform (or a
windowed-Fourier transform or a wavelet-transform) should only be applied when the
spectral support (i.e., band for which spectral mass is non-zero) of the amplitude time
series does not overlap with the spectral support of the phase time series (Boashash,
1991; Chavez et al., 2006). This is a consequence of the Bedrosian theorem (Bedrosian,
1963; see Boashash, 1991 for a discussion) which shows:
140

$$H(A \cos(\phi)) = A \, H(\cos(\phi)) \tag{1}$$

141
where H is the Hilbert transform operator, A is the amplitude time series, and ϕ is the
phase time series. The Bedrosian theorem holds when the effective spectral support of A,
i.e., the frequencies with maximal spectral mass, are distinct from the effective spectral
support of ϕ. Thus, any data time series with multiple rhythms or a rhythm with amplitude
modulations may lead to phase estimates under the Hilbert transform that are difficult to
interpret as the argument of a cosine function; see Chavez et al., 2006 for extended
discussions of these theorems.
149
Another factor affecting the interpretability of the phase under the Hilbert transform
is the parameter set used for the narrowband filter. A practitioner must decide the filter
type, filter order, and window duration (see Widmann et al. (2015) for a discussion and
Zrenner et al. (2020) for an analysis of different parameter choices). The practitioner must
also choose the filter's bandwidth; any waveform whose spectral support is wider than
the bandwidth of the filter will be altered in the filtered time series.
156
For all analyses here, we apply a least-squares linear-phase FIR filter of order 3
times the longest cycle length expected (as in, e.g., Cohen, 2008 and Nadalin et al.,

2019). After forward and backward filtering of the data (using the filtfilt function in
MATLAB), we apply the Hilbert transform to the data to estimate the quadrature
component of the signal. We compute the analytic signal using the hilbert function in
MATLAB, which computes the quadrature component (the imaginary term) and combines
it with the in-phase component (the real term). Finally, we estimate phase using the four-
quadrant arctan function implemented by the angle function in MATLAB.

We estimate the 99% confidence interval for the FIR-Hilbert phase estimator,
assuming stationary noise and complex-valued normality for the additive noise to the
analytic signal, using (Eq. 3.18 of Lepage et al., 2013):

$$\widehat{\phi_t} \sim N(\phi_t, \frac{B\sigma^2}{2|A_t|^2}) \qquad (2)$$

Where A_t is the time-t element of the amplitude time series, B is the bandwidth of the
filter divided by sampling frequency, and σ^2 is the additive noise variance, which is
estimated using the residual after removing the filtered data from the unfiltered data. This
confidence interval is derived by operationalizing the filter and Hilbert transform in terms
of linear operators applied to the signal, and assuming for the analytic signal a simple
signal plus additive noise model (see Eqs 3.2 - 3.11 of Lepage et al., 2013), where the
noise is complex-Gaussian. From the inferred confidence bounds, asymptotic
expressions for the maximum likelihood estimate of phase can be derived, assuming that
the amplitude of the signal is significantly higher than the standard deviation of the noise
(for further discussion, see Lepage et al., 2013).

State Space Model

A state space modeling approach to specify phase (Matsuda & Komaki, 2017;
Wodeyar et al., 2021; Soulat et al., 2022) expects the random time series to exhibit
periodicity similar to that of a vector-valued AR(2) process. We assume that the analytic
signal of a rhythm is a latent, unobservable process, that we can estimate from the
observed data. We build this assumption into a state space structure, with the state
equation (see Eq. 3 below) representing the latent analytic signal and the observation
equation (see Eq. 5 below) representing the observed data. On receipt of each new
sample of the observed data, we correct the estimate of the state using a Kalman filter -
an optimal strategy when the state update equation is linear and Gaussian (see Chapter
2 of Schiff, 2012).

To illustrate this approach, we consider the case of tracking a single rhythm whose
central baseband frequency is 6 Hz. The state equation of the analytic signal for this case
is:

$$x_t = aO(\omega_j)x_{t-1} + u_t, u_t \sim N(0, Q) \tag{3}$$

197 where x is complex-valued with real (Re(x)) and imaginary (Imag(x)) parts. At time instant
198 $t-1$, the modeled rhythm's analytic signal is represented by x_{t-1}. The state equation
199 yields a prediction for the next point along this trajectory (x_t) by rotating the current state
200 (x_{t-1}) in the complex plane and adding u_t, Gaussian independent and identically
201 distributed (IID) noise process. The rotation matrix $O(\omega)$ is given by:

$$O(\omega) = \begin{pmatrix} \cos{(\omega)} & -\sin{(\omega)} \\ \sin{(\omega)} & \cos{(\omega)} \end{pmatrix}, \ \omega = 2\pi\frac{6\,Hz}{Fs} \tag{4}$$

203 where Fs is the sampling frequency in Hertz. After rotation of x_{t-1}, the output is damped
204 by a factor $a \in [0,1)$, and then a realization of Gaussian noise ($u_t \sim N(0, Q)$) is added. We
205 estimate the observation at time t (y_t) as the real-part of the state time series at time t in
206 the presence of additive observation noise:

$$y_t = [1\ 0](x_t) + v_t \tag{5}$$

where v_t is Gaussian IID ($v_t \sim N(0, \sigma^2)$).

When applying this method to identify brain rhythms and track the associated
analytic signal, we need to estimate Q, a, σ^2, ω (assumed 6 Hz in illustration above).
Estimating these parameters can be done by applying the expectation-maximization
algorithm (Shumway & Stoffer, 1982), and depends on good initial estimates for the
parameters (see Matsuda & Komaki, 2017; Soulat et al., 2022 for potential initialization
strategies). We use the model described in Equations (3) - (5) under a Kalman filter
framework, after estimating parameters, to obtain the optimal state estimates for each
observed data sample. Further, we perform a backward smoothing operation (Shumway
& Stoffer, 1982; Soulat et al., 2022), i.e., sending a time-reversed version of the data
through the filter. Finally, after smoothing, for each data sample we derive the posterior
distribution for the state prediction that we use to define the credible interval over the
phase (Morey et al., 2016). We sample 10,000 times from the posterior distribution for the
state and use this to extract 99% credible intervals (see *Methods* in Wodeyar et al., 2021
for details).

Poincaré Section Method

For any K-dimensional dynamical system and associated particle trajectory, we
can define a Poincaré section as a K-1 dimensional plane which intersects the considered
trajectory. We specify phase relative to the moment of plane crossing. For example, in a

one-dimensional system (i.e., the activity varies along a single axis), negative to positive
zero-crossings define a Poincaré section, where the origin is the ordinate through which
we mark the particle trajectory. As described by Chavez et al., 2006 and others
(Kralemann et al., 2007; Rosenblum et al., 1997), phase specified using a Poincaré
section depends upon the selection of observables (for example, the signal alone versus
a time-delayed embedding (Takens, 1981)), and how the section is defined. In this
manuscript, we consider K=2 and select zero-crossings to define the phase. From one
zero-crossing (i.e., from the voltage traveling from negative to positive values) to the next,
2π radians are uniformly covered by the evolution of the phase. We denote t_n and t_{n+1}
as the times of the n^{th} and $n+1^{th}$ zero-crossings of the time-evolving particle. During
$[t_n, t_{n+1})$ the phase-space of the particle completes one full rotation. The phase ϕ is
specified by a linear ramp on $[t_n, t_{n+1})$ (Rosenblum et al., 1997):

$$\phi = 2\pi \frac{t-t_n}{t_{n+1}-t_n}, t_n \leq t < t_{n+1} \tag{6}$$

For a pair of consecutive zero-crossing times, the Poincaré section assigns a
phase of 0 at t_n and 2π at the sample immediately prior to t_{n+1}. We note that, in the other
two methods of phase specification, 0 and 2π are assigned to phase at the amplitude
maxima. To make the phase mapping isomorphic across methods, we unwrap the phase
(unwrap function in MATLAB) assigned by the Poincaré section, add π/2, and wrap
(wrapToPi in MATLAB) the phase to [-π,π]. This transformation shifts the phase by π/2
and remaps phase to [-π,π]. Unlike the other two methods considered here, the Poincaré
section does not explicitly model a source of noise and thus lacks a measure of
uncertainty in the phase estimate. Despite this and as we will see in the *Results*, for non-
sinusoidal rhythms, the Poincaré section serves as a useful comparison.
252
253 **Signal-to-Noise Ratio**
254
255   We define the signal-to-noise ratio (SNR) as the extent to which the power within
256 a limited band of frequencies around the central frequency is greater than power at other
257 frequencies. We control SNR in our simulations to exceed 2.5 for clear visual identifiability
258 of a rhythm. To infer the SNR for an oscillation in the data with center frequency in F, we
259 apply:
260

$$SNR = \frac{\text{Power}_{F \in [f_1, f_2]}}{\text{Power}_{F \notin [f_1, f_2]}} \tag{7}$$

261
262 where $\text{Power}_{F \in [f_1, f_2]}$ is the summed power across the frequency band F as derived from
263 a multitaper spectral estimator with 19 tapers using the mtspectrumc function from
264 Chronux (Bokil et al., 2010), and the summation occurs at frequencies around the central

265   frequency $[f_1, f_2]$ - where f_1 is less than the central frequency and f_2 is greater than the
266   central frequency - in the numerator, and outside this frequency band in the denominator.
267
268   **Estimating Phase Difference Variability**
269
To determine the consistency of phase across methods, we compute the circular
standard deviation (Zrenner et al., 2020). This method characterizes the width of the
distribution of phase differences between a pair of phase estimators around a mean
difference in the phase. To measure the circular standard deviation of the phase
differences between phases θ_M and θ_N for estimators M and N, we apply (Zrenner et al.,
2020),

$$CircSD = \sqrt{-2 \log \left| \left(\frac{1}{n} \sum_{l=1}^{n} \exp\left(i\theta_{M,l} - i\theta_{N,l}\right) \right) \right|} \tag{8}$$

We note that this method of assessing phase across methods presumes that any bias
(i.e., a phase difference centered at a value other than zero) is consistent across time
(Zrenner et al., 2020). We interpret the $CircSD$ as a measure in radians. We note that this
interpretation is valid only when the spread of phase-difference angles is non-uniform;
closer to a uniform distribution, this measure exceeds 2π. However, for the cases
considered here, this situation does not occur.
282
283   **Analysis of in vivo data**
284
To illustrate application of the phase estimation methods, we consider an open-
source dataset consisting of recordings from two invasive EEG electrodes (iEEG, 400 s
sampled at 1000 Hz) in a non-human primate anesthetized with propofol (available at
http://neurotycho.org/expdatalist/listview?task=75). Propofol anesthesia yields a brain
state with synchronized brain rhythms (Lewis et al., 2012), resulting in strong cross-
cortical coherence and phase-amplitude coupling relationships, phenomena proposed to
coordinate neural spiking within and between brain regions (Fries, 2015; Jarvis & Mitra,
2001; Lepage et al., 2011; Pesaran et al., 2018). Here we apply different phase estimation
methods to analyze the coherence in the slow delta band [0.25, 1.5 Hz] between the two
recordings, and phase-amplitude coupling between the slow delta and beta [13, 30] Hz
bands within each recording (Ma et al., 2019).
296
297   To estimate the phase of slow delta activity via the FIR-Hilbert method, we apply
298   an FIR filter to isolate the frequency band of interest (slow delta) and calculate the Hilbert
299   transform to estimate the slow delta phase. We apply the same FIR-Hilbert approach to
300   estimate the amplitude time series for the beta band (Cohen, 2008; Nadalin et al., 2019).
301   For the state space method, we first estimate model parameters as well as the central

frequencies for each band (slow delta and beta) using a subset of the data (10 s). We do
so for each recording separately, and then use these parameters for state estimation
across all 400 s of data (see Equations 6 - 10 in Wodeyar et al., 2021). For the Poincaré
method, we first broadband filter the iEEG between 0.1 Hz to 50 Hz using a 4th order
Butterworth filter. Filtering before applying the Poincaré method reduces the influence of
higher frequency noise and slow drifts on zero-crossings. The Poincaré method does not
yield an amplitude time series, so we assume the amplitude is constant and equal to 1.
We note that, in this case, coherence values using the Poincaré method are akin to
estimating a phase locking value (Lachaux et al., 1999).
310
We use phase estimates from each method to estimate the coherence of the slow
delta [0.25 - 1.5 Hz] rhythm between the two recordings. Coherence is an estimate of the
consistency in the phase and amplitude at one frequency (or in a single frequency band)
between two electrophysiological time series (for a discussion see Pesaran et al., 2018).
We compute coherence (C) for two complex-valued row vectors over time E_1 and E_2,
each representing the amplitude and phase in one frequency band using the function corr
in MATLAB.
318
Phase-amplitude coupling represents how the phase of a low frequency rhythm
(here, the slow delta band) coordinates the amplitude of a high frequency rhythm (here,
the beta band) (Hyafil et al., 2015). We note that we cannot apply the Poincaré method
for phase-amplitude coupling estimation as this method does not estimate an amplitude
time series. We therefore analyze the phase-amplitude coupling within each recording
using only the Hilbert and state space methods. To visualize the phase-amplitude
coupling, we divide the phase between 0 to 2π into 20 non-overlapping intervals and plot
the average amplitude for each interval of phase (Canolty & Knight, 2010; Tort et al.,
2010).
328
329 **Code Accessibility**
330
331 All code developed for and applied in this paper are available for reuse and further
332 development at: https://github.com/wodeyara/UncertaintyInPhase. All code was run on a
333 Dell XPS 15 7590 running Windows 10 and having 32 GB of RAM. A README file is
334 included with the code that has a legend for all files.
335
336   **Results**
337
A pure sinusoid is the only function that has an explicitly specified phase
parameter, but it is too restrictive a model for most brain rhythms (Cole & Voytek, 2017).
For the simulated time series considered below, an optimal specification of phase does
not exist. Instead, we must choose a method to specify the phase. This makes defining

what one might consider a "true phase"- i.e., an optimal model - impossible, and thus
eliminates any principled error estimate. Because in practice the true phase for observed
data does not exist, we instead consider different methods to estimate phase, each
imposing different assumptions about the data. We then compare the relative
performance of these different methods. In what follows, we show that when any method
indicates reduced uncertainty in the phase estimate, then all three methods tend to agree
allowing practitioners to limit the phase estimates required to be considered.
348
We analyze simulation data from three generative models. We simulate a non-
parametric model, a simple stochastic parametric model, and a dynamical systems
model. The first generative model can fit the broadest range of neural data, while the
second and third generative models are relevant for smaller subsets of data. Each
generative model serves as a potential exemplar of a range of empirical data. For all
generative models, we make three assumptions. First, we assume that a rhythm always
exists in the data with high signal-to-noise ratio (SNR, with SNR >= 2.5 to allow for an
identifiable rhythm, see *Methods*). Second, we assume that the data consists of a single
rhythm of interest. Third, we assume that any temporal variability in the data is derived
from the generative model.
359
360
361 **Broadband Rhythm in Pink Noise**
362
To match empirical observations in neuroscience (Miller et al., 2009a; Miller et al.,
2009b), we consider a phenomenological model of rhythms with increased power over a
broad range of frequencies, emerging above $1/f^\alpha$ background activity (i.e., the background
activity power decreases with frequency as $1/f^\alpha$, where $\alpha \in [1,3]$ (Donoghue et al., 2020).
We simulate this type of data in the frequency domain as a complex-valued vector. To do
so we add a Gaussian-function shaped broadband amplitude (center frequency 6 Hz,
standard deviation 1 Hz) with a zero phase to a background of pink noise (power
proportional to $1/f^{1.5}$; Figure 1a) with random phases at each frequency. The inverse
discrete Fourier transform applied to this complex-valued vector yields a time series of
10 s duration.
373
We estimate the phase of the simulated 6 Hz rhythm using the Poincaré method,
the FIR-Hilbert method, and the state space method (examples in Figure 1b). Visual
inspection suggests that the latter two methods produce similar phase estimates when
the rhythm is visible; at these times the credible intervals of the state space method tend
to overlap the confidence bounds of the FIR-Hilbert method (i.e., the two shaded curves
tend to overlap in Figure 1b, see t $\approx$ 1.5 s). During periods of low amplitude ($t \in [1.75,2]$ s),
the FIR-Hilbert method computes phase estimates whose trajectory completes full cycles

(continuous traversal from $-\pi$ to π) while phase estimates under the state space method
remain consistently near $\pm\pi$. Visual inspection of the phase estimated by the Poincaré
method reveals a different result than what is seen using the other methods; sudden zero
crossings, which arise because of appreciable spectral power at high frequencies, lead
to rapid phase-series cycles that may be undesirable if the goal is to track phase for
fluctuations at lower frequencies. The distributions of phase differences between all pairs
of methods support the similarity between the state space and FIR-Hilbert methods and
their contrast with the Poincaré method (Figure 1c); phase differences between the state
space and FIR-Hilbert methods concentrate near 0, while phase differences with the
Poincaré method appear at all angles. Repeating this analysis for 1000 realizations of the
generating model and considering the variability of phase differences using circular
standard deviation (see *Methods: Estimating Phase Difference Variability*), we find
consistent results (Figure 1d, left boxplots).
394
We infer moments of consistent phase using the confidence bounds determined
from the FIR-Hilbert method and the credible intervals from the state space method. We
designate time segments with both smaller confidence bounds and smaller credible
intervals as "high confidence" time segments. These are times when the values are jointly
in the bottom quartile (as empirically determined) for both uncertainty metrics. Across high
confidence time segments, the phase difference between the FIR-Hilbert and state space
methods shows a circular standard deviation of 14.22 ± 0.07 degrees (mean ± standard
error of the mean or SEM) reduced from 30.02 ± 0.13 degrees when considering all data
(i.e., times with and without high confidence in the phase estimates). Similarly, the circular
standard deviation between the FIR-Hilbert/Poincaré (44.8 ± 0.3 degrees) and state
space/Poincaré (45.8 ± 0.3 degrees) methods decreases in high confidence time
segments, compared to all data (FIR-Hilbert/Poincaré: 69.5 ± 0.2 degrees; state
space/Poincaré: 68.6 ± 0.2 degrees; Figure 1d, right boxplots). However, we note that
circular standard deviation remains high when comparing the Poincaré method for both
choices of time segments (Figure 1d, red and pink boxplots).
410
We conclude that, for a broadband rhythm in pink noise, the state space and FIR-
Hilbert methods produce comparable results. High frequency fluctuations in the time
series produce intervals of rapid zero-crossings in the Poincaré method. Intervals exist
with increased agreement between all three methods; these intervals occur when the
state space and FIR-Hilbert methods produce confident estimates (i.e., small confidence
bounds/credible intervals).
417

Figure 1: The FIR-Hilbert and state space methods produce consistent results for a broadband signal in pink noise. (a) *Analytic power spectrum of the background pink noise (red) and broadband spectral peak at 6 Hz (blue).* ***(b)*** *(Top) Example trace of broadband signal with added pink noise. (Bottom) Phase estimates from the Poincaré method (black), FIR-Hilbert method (mean estimate blue, confidence intervals shaded blue) and state space method (mean estimate red, credible intervals shaded red). All three methods show periods where they disagree (t ∈ 1.75 s, see orange rectangle) and agree (t ~ 1.5 s, green rectangle).* ***(c)*** *Distributions of differences in the estimated phase between each pair of methods using (upper) all example data or (lower) a subset of data with confident phase estimates. Estimates from all methods better align during segments of data with confident phase estimates.* ***(d)*** *Distributions of differences between methods across 1000 simulations. Using samples of data with high confidence in the phase improves consistency between methods. For broadband rhythms, the state space and FIR-Hilbert methods are more similar than the Poincaré method.*

Noise-driven Damped Harmonic Oscillator

Auto-regressive (AR) processes of order 2 are linear time-series models capable
of exhibiting periodicity (Shumway & Stoffer, 2017). AR(2) processes sustaining a rhythm
demonstrate spontaneous variability in the amplitude of the rhythm or amplitude

modulation (Spyropoulos et al., 2022) and a $1/f^\alpha$ proportional power spectrum. These
features are consistent with features that characterize gamma band rhythms, as inferred
from *in vivo* observations(Burns et al., 2010; Spyropoulos et al., 2022; Xing et al., 2012).
Unlike the previous simulation where the additive noise is characterized by a $1/f^\alpha$ power
spectrum, here the Gaussian noise is passed through an AR(2) filter to yield spectra that
has both a broadband peak centered at 6 Hz and a $1/f^\alpha$ power spectrum; see analytic
power spectrum in Figure 2a and an example trace in Figure 2b.
431
Visual inspection of the estimated AR(2) phase reveals intervals of agreement and
disagreement between the three methods (Figure 2b) as a result of amplitude modulation.
For example, when the rhythm has high amplitude ($t < 0.5$ s), the uncertainty reduces and
the three phase estimates are qualitatively similar in the features (e.g., peaks, troughs,
and zero-crossings) tracked by the phase. At other times the methods disagree about
what constitutes a full phase cycle. For example, at t near 1.5 s, the observed time series
exhibits two low amplitude troughs. Between these troughs, the state space model
suggests no phase cycle occurs (staying near $\pm\pi$), the Poincaré method indicates a long
phase cycle spanning beyond the two troughs, and the FIR-Hilbert method indicates a
complete phase cycle between the two troughs. We find similar phase estimates across
methods (Figure 2c, top row), with a circular standard deviation of 37.9 ± 0.1 degrees
(mean and SEM across comparisons of all three methods over 1000 realizations of the
simulation; see Figure 2d). Restricting analysis to high confidence time segments, we find
increased consistency in phase estimates across methods (Figure 2c, bottom row) and a
nearly 2-fold reduction in the circular standard deviations between methods (22.9 ± 0.1
degrees, 1000 realizations of the simulation; see Figure 2d).
448
We conclude that, for an AR(2) simulated time series, all three methods produce
comparable results. Compared to the simulation of a broadband rhythm in pink noise
(Figure 1), in the AR(2) simulated time series fewer high frequency fluctuations distort the
phase estimates under the Poincaré method. Consistent with the previous simulation,
when the state space method and FIR-Hilbert methods both produce confident estimates
(i.e., small confidence bounds/credible intervals), the agreement across methods
improves. Despite this general agreement between methods, an important difference
exists; when the rhythm amplitude is small, the state space method produces non-
evolving phase estimates (e.g., near $\pm\pi$ in Figure 2b), while phase estimates continue to
evolve for the other methods.
459
460

Figure 2: All three methods produce similar phase estimates for data generated by an AR(2) model. (a) *Analytic power spectrum of the AR(2) model. A broadband spectral peak occurs at 6 Hz.* ***(b)*** *(Top) Trace of example AR(2) signal. (Bottom) Phase estimates from the Poincaré method (black), FIR-Hilbert method (mean estimate blue, confidence intervals shaded blue) and state space method (mean estimate red, credible intervals shaded red). Intervals occur in which the methods agree (t < 0.5 s) and disagree (t near 1.5 s, orange rectangle)* ***(c)*** *Distributions of differences in the estimated phase between each pair of methods using (upper) all example data or (lower) a subset of data with confident phase estimates. Estimates from all methods better align during segments of data with confident phase estimates.* ***(d)*** *Distributions of differences between methods across 1000 simulations. Using samples of data with high confidence in the phase improves consistency between methods.*

Fitzhugh-Nagumo oscillator

As a third example of a generative model, we consider the Fitzhugh-Nagumo

oscillator, an approximation of Hodgkin-Huxley neuronal membrane potential dynamics

(Izhikevich and FitzHugh, 2006). The model is defined by the following equations where

(in normalized units) V denotes the voltage, and I denotes the input stimulation to the
neural population (Hong 2011):

$$\dot{V} = -10\,V^3 + 11\,V^2 - V - W + I + \epsilon$$
$$\dot{W} = V$$
$$I = \frac{0.1}{\omega}\cos(\omega t) \tag{9}$$
$$\omega = 0.8168; \ \epsilon \sim N(0,3)$$

We select parameter values that permit chaotic oscillations (as elicited at a 'strange
attractor') (Izhikevich, 2007), in which the voltage dynamics follow a trajectory consistently
around a point in the coordinate space to yield a non-uniform waveform shape (relative
to a sinusoid, Cole & Voytek, 2017, Figure 3a,b). This rhythm is phenomenologically
similar to a slow oscillation measured in the ferret visual cortex LFP (see Figure 2A of
Fröhlich & McCormick, 2010) and in hippocampal LFP in rats (see the Visual Abstract of
Ouedraogo et al., 2016). After simulating data using the ode45 function in MATLAB, we
rescale time such that the rhythm has an approximately 1 Hz periodicity to match a slow
oscillation timescale.
478
In this generative model, we have access to all the variables underlying the data,
i.e., the full system is known, yet we cannot define a singular phase - the definition of
phase depends on the voltage events of interest. Visual inspection of the dynamics
reveals waves (e.g., between 6-7 s in Figure 3b, green rectangle) for which determining
whether a full wave occurs remains unclear. Two potential ways to define a waveform for
this system are: (1) A repetition of the high amplitude wave ($V > 10$, see t near 3.5 s in
Figure 3b, orange rectangle), or (2) The dynamical system completes a full cycle in the
phase space at any amplitude (i.e., including the small amplitude rotations in Figure 3a,
and t near 6.5 s in Figure 3b); we note that waves included in (1) are a subset of waves
included in (2).
489
During times of smaller amplitude waves, all methods infer a complete phase
cycle, and the state space and FIR-Hilbert methods suggest increased uncertainty (wider
credible/confidence intervals). During higher amplitude waves, the phase cycle estimated
from the Poincaré method differs from that from the other two methods (e.g., see black
trace in Figure 3b in shaded orange rectangle). The Poincaré method produces a longer
phase cycle for high-amplitude waves but the same phase cycle for lower amplitude
waves. Additionally, we note that the state space method has wider credible intervals at
the start of each phase cycle (phase at $-\pi$) for high-amplitude events. Comparing
methods, we find more agreement between the FIR-Hilbert and state space methods
(mean and SEM of the circular standard deviance across 1000 realizations of the
simulation: 18.9 ± 0.1 degrees) compared to the Poincaré method (FIR-Hilbert: 39.6 ± 0.1
degrees; state space: 30.9 ± 0.05 degrees; Figure 3c,d). Differences between methods

decrease when examining times with high-confidence phase estimates (FIR-Hilbert and
state space: 3.04 ± 0.04; FIR-Hilbert and Poincaré: 23.9 ± 0.1; State space and Poincaré:
24.8 ± 0.1; Figure 3c,d).
505

We conclude that for non-sinusoidal signals with multiple waveforms, as
exemplified here by the Fitzhugh-Nagumo model, phase estimates from the different
methods tend to agree. As in the previous two simulation studies, considering only time-
indices where we have high confidence in the phase estimates improves similarity across
all methods, including to the Poincaré method. However, an important distinction between
methods becomes more apparent in this simulation; the state space and FIR-Hilbert
methods yield non-uniform phase cycles i.e., a non-linear ramp in the phase (see orange
rectangle, Figure 3b). By contrast, the Poincaré method necessarily produces linear
increases in the phase. Depending on the desired interpretation of phase – as beginning
to evolve only when the voltage begins to rise (state space and FIR-Hilbert methods) as
opposed to evolving purely as a function of time (Poincaré method) – different methods
are appropriate.

Figure 3: Phase estimates for a rhythm generated by the Fitzhugh-Nagumo oscillator. *(a) Example trace of the coordinate space for the two variables comprising*

*the Fitzhugh-Nagumo model. **(b)** (Top) Trace of example Fitzhugh-Nagumo oscillator signal. (Bottom) Phase estimates from the Poincaré method (black), FIR-Hilbert method (mean estimate blue, confidence intervals shaded blue) and state space method (mean estimate red, credible intervals shaded red). Intervals occur in which the methods agree (t ∈ [6,7]s, green rectangle) and disagree (t ∈ [3, 4] s, orange rectangle). **(c)** Differences in the estimated phase between each pair of methods. Upper row shows differences between methods across all data, and lower row shows differences only for time indices of high confidence. **(d)** Distributions of differences Distributions of differences in the estimated phase between each pair of methods across 1000 simulations using (upper) all example data or (lower) a subset of data with confident phase estimates.*

Example in vivo Applications

For example applications to *in vivo* data, we focus on two common analysis
approaches that require phase: coherence (Pesaran et al., 2018) and phase-amplitude
coupling (Hyafil et al., 2015; Tort et al., 2010) (see Methods). We analyze 400 seconds
of data from two frontal electrodes with visually identifiable rhythms from an anesthetized
macaque   monkey   (see   Figure   4a   and
http://wiki.neurotycho.org/Anesthesia_Task_Details for details). Extensive analyses of
these data have been conducted by Ma et al. (2019) where those authors demonstrated
long range (between frontal and parietal regions) coherence in the slow delta (0.25 - 1.5
Hz) and local phase-amplitude coupling between rhythms in the slow delta (0.25 - 1.5 Hz)
and beta bands (15-25 Hz).

Analysis of Coherence

We apply all three phase estimation methods to compute the coherence in the slow
delta band. We compare coherence results from two sets of data: all the data, and a
subset of the data with "high confidence" in the phase estimates. We define "high
confidence" intervals as times included when thresholding for the lower quantile of
confidence bounds for the FIR-Hilbert method or lower quantile of credible intervals for
the state space method. Using either the FIR-Hilbert or the state space method leads to
a sharp increase in the estimated coherence for the high-confidence phase data
(coherence 0.7) compared to all data (coherence 0.3). We note that we cannot compare
the coherence estimate using the Poincaré method to estimates from the other methods;
the Poincaré method does not estimate an amplitude time series (see *Methods: Poincaré*
section). However, we can compare the coherence estimated using the Poincaré method
(see *Methods: Analysis of in vivo data*) across the two subsets of data. In this case, we
define high confidence intervals as times at which FIR-Hilbert and state space phase
estimators are simultaneously associated with low statistical uncertainty. We again find
that the coherence increases from 0.15 for all data to 0.58 for the high confidence intervals
of data (Figure 4c, right column). We conclude that, for all three methods, the estimated

coherence increases during time indices of high confidence phase estimates. This
conclusion is not obvious; during time indices with high-confidence phase estimates, the
phases and amplitudes for the slow delta rhythm could remain randomly distributed
between recordings. In addition, we note that isolating the high confidence phase data
produced bimodal distributions for the phase differences between electrodes with the FIR-
Hilbert and state space methods, a result not clear when analyzing all data (Figure 4c). A
bimodal phase-difference distribution (as seen in Figure 4c) with one mode (peak) near
0 degrees could imply a common source acting on both areas (Nunez and Srinivasan,
2006), and another mode near 30 degrees could reflect a delayed signal propagating
between electrodes. We conclude that coherence estimates can be better interpreted by
using segments of data with confident phase estimates.
560
Phase-Amplitude Coupling
In a second example analysis of the *in vivo* data, we use only the FIR-Hilbert and
state space methods to estimate the phase-amplitude coupling between the slow delta
phase and beta amplitude (see *Methods: Analysis of in vivo data*). We note that the
Poincaré method is unusable for phase-amplitude coupling estimation due to the lack of
an estimated amplitude time series. We expect the low-frequency delta phase to influence
the high-frequency beta amplitude (Ma et al., 2019). We observe this effect when
analyzing all of the data (Figure 5), and find that considering only subsets of data with
high confidence in the phase estimate increases the effect size - there is greater
modulation of the amplitude of the beta band rhythm as a function of the slow delta phase
when considering only intervals with high confidence phase estimates. These results are
consistent across the FIR-Hilbert and state space methods, demonstrating the robustness
of this effect to model misspecification.

Figure 4: Coherence estimates increase when incorporating a measure of uncertainty in the phase. (a) *Power spectra from multitaper estimation for the two recordings analyzed. (Inset) Macaque brain showing location of recordings.* ***(b)*** *Example traces of data from the two recordings analyzed. Note the large amplitude, slow (~0.5 Hz) oscillation.* ***(c)*** *Estimates of coherence (numerical value) and the phase differences between recordings (histograms) under different methods and when considering all data (upper row) and only the high confidence segments of data (lower row). A bimodal distribution of phase differences appears for the FIR-Hilbert and state space methods for the high confidence segments.*

Figure 5: Cross-frequency coupling estimates are improved when incorporating a measure of uncertainty in the phase. (a) *Example traces of the slow delta and beta signals showing timing of beta rhythms with specific phases of slow delta at each electrode location (inset image with arrow). Delta trace is colored according to beta amplitude (see colorbar).* ***(b)*** *Estimates of phase-amplitude coupling when using the state space method (red, shaded confidence bands) and FIR-Hilbert (blue, shaded confidence bands) method for each recording. Both methods demonstrate significant phase-amplitude coupling between slow delta phase and beta amplitude. When only using segments of data with high confidence phase (dashed curves), the modulation increases.*

575
576

Discussion

577
578
In this manuscript, we demonstrated the ambiguity in specifying phase for
neuroscientific applications. We used simulations from three generative models of
rhythms and applied three methods to specify phase. Together, these three models and
three methods encompass a wide range of empirical data and methods applied (Bruns,
2004; Cole & Voytek, 2017; Donoghue et al., 2020; Kralemann et al., 2008; Ouedraogo
et al., 2016; Spyropoulos et al., 2022; Wodeyar et al., 2021). We showed that for each
model of rhythms, each method produced phase estimates that optimally tracked different
characteristics of the rhythms. These phase estimates converge when using only
segments of data when the methods suggested greater confidence in the phase estimate.
Using this insight, we applied two common analyses – coherence and phase-amplitude
coupling – to example *in vivo* recordings. Considering only the subset of data with high
confidence phase estimates, we found increases in both the coherence and phase-
amplitude coupling, and a bimodal phase-difference distribution for the coherence that
was not apparent in the original analysis. We conclude that phase is ambiguous (i.e.,
application specific) for neural data but using uncertainty metrics reduces the ambiguity.
594
Every method to specify phase imposes a model of the data time series. In
practice, phase estimation is performed without careful consideration of the model
(implicitly) selected. For the estimation methods considered here, we propose a decision
tree (Figure 6) to guide practitioners in choosing a phase estimator. In essence, the
method chosen depends on the goal of the analysis. In the ideal case of sufficiently
sampled sinusoidal data (Lainscsek et al., 2017) and no noise process, the FIR-Hilbert,
state space, and Poincaré methods are all viable to identify and track inferable rhythms.
If the data time series periodicity is nearly sinusoidal and noise contamination is low, then
both the FIR-Hilbert and state space methods generate similar phase estimates and are
not susceptible to high-frequency fluctuations like those seen using the Poincaré method.
Alternatively, if there is amplitude modulation, or if the data are non-sinusoidal and noise
contamination is high and the goal is to identify phase for periods with high SNR waves,
then the state space method is the best option. Finally, if the data are non-sinusoidal and
the noise contamination is low, then the Poincaré method performs better at maintaining
a linear ramp for the phase compared to the FIR-Hilbert and state space methods.
610
The features tracked by the phase are least dependent on the experimenter's
choice of estimation method when the similarity between methods is high. Across different
models of rhythms, we found uncertainty metrics help in identifying segments of time
when phase is similar across methods. However, the metrics of uncertainty are specific
to the model assumed by each method. The uncertainty metric under the FIR-Hilbert
method is a transformation of the amplitude time series for the filtered data. One can

identify instances when this measure of uncertainty does not capture what we may want.
For example, when the time series is contaminated with $1/f^\alpha$ noise (see *Results:*
Broadband Pink Noise), high amplitude activity may appear due to noise rather than the
rhythm of interest. In contrast, segments of time with low SNR rhythms can also fall below
a given amplitude-dependent uncertainty threshold (see *Methods:* Eq. 2). Alternatively,
the state space model assumes that the analytic signal representing the rhythm process
is complex-Gaussian distributed and applies the Kalman filter before determining the
uncertainty in the phase. When the signal is non-sinusoidal or the noise driving the rhythm
is non-Gaussian, this measure of uncertainty may fail to capture confidence in the phase
accurately – e.g., visible at the start of each phase cycle for high amplitude events in the
Fitzhugh-Nagumo simulation (see the orange rectangle in Figure 3). Modifications of the
state space model (such as the application of an extended Kalman Filter to independently
track amplitude and phase or the use of particle filters - Schiff 2012) can permit more
accurate modeling of non-sinusoidal rhythms and non-Gaussian noise.
631
While we focused on three methods to specify phase, other methods exist. We
highlight two alternatives. The generalized phase method (Davis et al., 2022) estimates
the smoothed Hilbert-transform derived phase of the largest fluctuation in the data at a
given time instant. This method prioritizes the rhythm with highest amplitude present in
the time series and assumes only a single rhythm is present at any instant in time. Given
the similarity of this method to the basic Hilbert transform and the intent to examine
distinct types of phase estimation methods, we chose not to apply this method here.
Another method – the masked empirical mode decomposition or masked EMD (Quinn et
al., 2021) – seeks to identify distinct waveforms in the time series. Such a method could
closely track an inferable rhythm while reducing the contamination of noise and create a
phase evolution that linearly tracks a non-sinusoidal rhythm. The masked EMF may
struggle with identifying a singular waveform if the underlying limit-cycle attractor of the
dynamical system measured is chaotic (as seen in the Fitzhugh-Nagumo simulation),
leading to wave morphology that is inconsistent across cycles.
646
A major difficulty in identifying the best phase estimation method is that the quantity
defined as phase depends on the goals of the practitioner. Thus, the idea of a "best"
phase estimator is not meaningful. Instead, we recommend alternative approaches of
comparing estimators, for example by comparing phase from different methods to identify
consistency or testing which method of phase estimation shows the highest effect size
for the feature of interest. For example, Davis and colleagues (Davis et al., 2022) compare
the phase from the FIR-Hilbert method and that under the generalized phase method to
the multi-unit neuronal spiking rate, demonstrating increased spike-field coherence under
the generalized phase method. However, choosing the phase across methods that
maximizes the relationship to neuronal activity or behavior may suffer from "voodoo

correlations" (Vul et al., 2009): increases in effect size due to random chance in the
method selected. The true efficacy of a method to define phase that tracks the desired
feature of population neural activity (such as the peaks or troughs) could be verified by
causal approaches, such as stimulation.
661
Closed-loop approaches to non-invasive (Klinzing et al., 2021; Ngo et al., 2013)
and invasive (Fröhlich & McCormick, 2010; Lustenberger et al., 2016; Zrenner et al.,
2018) stimulation based on a signal's phase require methods for real-time phase
estimation. For example, auditory stimulation triggered by the phase of a slow-wave
oscillation improves memory (Ngo et al., 2013) and thalamic stimulation triggered by a
patient's tremor rhythm suppresses tremor in patients with Parkinson's disease (Cagnan
et al., 2017). The Poincaré and FIR-Hilbert methods do not directly support causal phase
estimation, precluding their real-time application. However, several methods have been
developed to perform real-time phase estimation using the Hilbert transform by first
forecasting data under autoregressive models (Blackwood et al., 2018; Schatza et al.,
2022), and a similar approach may support real-time implementation of the Poincaré
method. The state space method is easily translated to a real-time framework (Wodeyar
et al., 2021). Finally, similar to what we showed in the *in vivo* analyses, measures of
uncertainty can help guide closed-loop stimulation to times of greater certainty in the
phase estimate (Schatza et al., 2022; McNamara et al., 2022).
677
Phase is an important characteristic of neural activity that may be used to index
cortical excitability (Freeman, 1961), availability of attentional resources (Busch et al.,
2009; Fiebelkorn et al., 2019), and the neural population capacity for communication
(Fries, 2015). As such, knowledge of how different phase estimators define phase is
critical to address mechanistic questions in neuroscience. In this manuscript, we
proposed guidelines to identify the appropriate phase estimator, namely applying
estimation methods whose reconstructed phase tracks the relevant characteristics of the
rhythm of interest and using metrics of statistical uncertainty. Improved approaches to
phase estimation will help us better understand the network implications of rhythms and
ascertain the potential for non-invasive interventions that alter cognitive ability (Ngo et al.,
2013) or reduce clinical symptoms (Cagnan et al., 2017).

Figure 6: A decision-making heuristic for estimating phase in observed data based on the aspects of rhythms that are of interest. *Whether the signal is nearly sinusoidal, amplitude-modulated, or has significant noise that affects visibility of the rhythm, impact the choice of method applied to specify phase.*

References

Bernardi, G., Betta, M., Ricciardi, E., Pietrini, P., Tononi, G., & Siclari, F. (2019). Regional Delta Waves In Human Rapid Eye Movement Sleep. *The Journal of Neuroscience*, *39*(14), 2686–2697.

He, B. J., Zempel, J. M., Snyder, A. Z., & Raichle, M. E. (2010). The temporal structures and functional significance of scale-free brain activity. *Neuron*, *66*(3), 353-369.

Blackwood, E., Lo, M., & Widge, A. S. (2018). Continuous Phase Estimation for Phase-Locked Neural Stimulation Using an Autoregressive Model for Signal Prediction*. *2018 40th Annual International Conference of the IEEE Engineering in Medicine and Biology Society (EMBC)*, 4736–4739.

Boashash, B. (1991). *Estimating and Interpreting The Instantaneous Frequency of a Signal-Part 1: Fundamentals*. 19.

Bokil, H., Andrews, P., Kulkarni, J. E., Mehta, S., & Mitra, P. P. (2010). Chronux: A platform for analyzing neural signals. *Journal of Neuroscience Methods*, *192*(1), 146–151.

Bruns, A. (2004). Fourier-, Hilbert- and wavelet-based signal analysis: Are they really different approaches? *Journal of Neuroscience Methods*, *137*(2), 321–332.

Burns, S. P., Xing, D., Shelley, M. J., & Shapley, R. M. (2010). Searching for Autocoherence in the Cortical Network with a Time-Frequency Analysis of the Local Field Potential. *Journal of Neuroscience*, *30*(11), 4033–4047.

Busch, N. A., Dubois, J., & VanRullen, R. (2009). The Phase of Ongoing EEG Oscillations Predicts Visual Perception. *Journal of Neuroscience*, *29*(24), 7869–7876.

Cagnan, H., Pedrosa, D., Little, S., Pogosyan, A., Cheeran, B., Aziz, T., Green, A.,

Fitzgerald, J., Foltynie, T., Limousin, P., Zrinzo, L., Hariz, M., Friston, K. J.,

Denison, T., & Brown, P. (2017). Stimulating at the right time: Phase-specific

deep brain stimulation. *Brain*, *140*(1), 132–145.

Canolty, R. T., & Knight, R. T. (2010). The functional role of cross-frequency coupling.

Trends in Cognitive Sciences, *14*(11), 506–515.

Chavez, M., Besserve, M., Adam, C., & Martinerie, J. (2006). Towards a proper

estimation of phase synchronization from time series. *Journal of Neuroscience*

Methods, *154*(1), 149–160.

Cohen, M. X. (2008). Assessing transient cross-frequency coupling in EEG data.

Journal of Neuroscience Methods, *168*(2), 494–499.

Cole, S. R., & Voytek, B. (2017). Brain Oscillations and the Importance of Waveform

Shape. *Trends in Cognitive Sciences*, *21*(2), 137–149.

Davis, Z. W., Muller, L., & Reynolds, J. H. (2022). Spontaneous Spiking Is Governed by

Broadband Fluctuations. *Journal of Neuroscience*, *42*(26), 5159–5172.

Donoghue, T., Haller, M., Peterson, E. J., Varma, P., Sebastian, P., Gao, R., Noto, T.,

Lara, A. H., Wallis, J. D., Knight, R. T., Shestyuk, A., & Voytek, B. (2020).

Parameterizing neural power spectra into periodic and aperiodic components.

Nature Neuroscience, *23*(12), 1655–1665.

Fiebelkorn, I. C., Pinsk, M. A., & Kastner, S. (2019). The mediodorsal pulvinar

coordinates the macaque fronto-parietal network during rhythmic spatial

attention. *Nature Communications*, *10*(1), 215.

Freeman, W. J. (1961). Harmonic Oscillation as Model for Cortical Excitability Changes

with Attention in Cats. *Science*, *133*(3470), 2058–2059.

Fries, P. (2015). Rhythms for Cognition: Communication through Coherence. *Neuron*,

88(1), 220–235.

Fröhlich, F., & McCormick, D. A. (2010). Endogenous Electric Fields May Guide

Neocortical Network Activity. *Neuron*, *67*(1), 129–143.

https://doi.org/10.1016/j.neuron.2010.06.005

Herbst, S. K., Stefanics, G., & Obleser, J. (2022). Endogenous modulation of delta

phase by expectation–A replication of Stefanics et al., 2010. *Cortex*, *149*, 226–

245.

Hong, K. S. (2011). Synchronization of coupled chaotic FitzHugh–Nagumo neurons via

Lyapunov functions. *Mathematics and Computers in Simulation*, *82*(4), 590-603.

Hyafil, A., Giraud, A.-L., Fontolan, L., & Gutkin, B. (2015). Neural Cross-Frequency

Coupling: Connecting Architectures, Mechanisms, and Functions. *Trends in*

Neurosciences, *38*(11), 725–740.

Izhikevich, E. M., & Fitzhugh, R. (n.d.). *FitzHugh-Nagumo model—Scholarpedia*.

Retrieved January 13, 2022, from http://www.scholarpedia.org/article/FitzHugh-

Nagumo_model

Jarvis, M. R., & Mitra, P. P. (2001). Sampling properties of the spectrum and coherency

of sequences of action potentials. *Neural Computation*, *13*(4), 717–749.

Jones, S. R. (2016). When brain rhythms aren't 'rhythmic': Implication for their

mechanisms and meaning. *Current Opinion in Neurobiology*, *40*, 72–80.

Klinzing, J. G., Tashiro, L., Ruf, S., Wolff, M., Born, J., & Ngo, H.-V. V. (2021). Auditory

stimulation during sleep suppresses spike activity in benign epilepsy with

centrotemporal spikes. *Cell Reports Medicine*, *2*(11), 100432.

Kralemann, B., Cimponeriu, L., Rosenblum, M., Pikovsky, A., & Mrowka, R. (2007).

Uncovering interaction of coupled oscillators from data. *Physical Review E*,

76(5), 055201.

Kramer, Mark A. "Golden Rhythms as a Theoretical Framework for Cross-Frequency

Organization." Neurons, Behavior, Data Analysis, and Theory 1 (October 20,

2022).

Kramer, M. A., & Eden, U. T. (2016). *Case Studies in Neural Data Analysis: A Guide for*

the Practicing Neuroscientist. MIT Press.

Lachaux, J.-P., Rodriguez, E., Martinerie, J., & Varela, F. J. (1999). Measuring phase

synchrony in brain signals. *Human Brain Mapping*, *8*(4), 194–208.

Lepage, K. Q., Kramer, M. A., & Eden, U. T. (2011). The Dependence of Spike Field

Coherence on Expected Intensity. *Neural Computation*, *23*(9), 2209–2241.

Lepage, K. Q., Kramer, M. A., & Eden, U. T. (2013). Some Sampling Properties of

Common Phase Estimators. *Neural Computation*, *25*(4), 901–921.

Lewis, L. D., Weiner, V. S., Mukamel, E. A., Donoghue, J. A., Eskandar, E. N., Madsen,

J. R., Anderson, W. S., Hochberg, L. R., Cash, S. S., Brown, E. N., & Purdon, P.

L. (2012). Rapid fragmentation of neuronal networks at the onset of propofol-

induced unconsciousness. *Proceedings of the National Academy of Sciences*,

109(49), E3377–E3386.

Lustenberger, C., Boyle, M. R., Alagapan, S., Mellin, J. M., Vaughn, B. V., & Fröhlich, F.

(2016). Feedback-Controlled Transcranial Alternating Current Stimulation

Reveals a Functional Role of Sleep Spindles in Motor Memory Consolidation.

Current Biology, *26*(16), 2127–2136.

Ma, L., Liu, W., & Hudson, A. E. (2019). Propofol Anesthesia Increases Long-range

Frontoparietal Corticocortical Interaction in the Oculomotor Circuit in Macaque

Monkeys. *Anesthesiology*, *130*(4), 560–571.

Matsuda, T., & Komaki, F. (2017). Time Series Decomposition into Oscillation

Components and Phase Estimation. *Neural Computation*, *29*(2), 332–367.

McNamara, C. G., Rothwell, M., & Sharott, A. (2022). Stable, interactive modulation of

neuronal oscillations produced through brain-machine equilibrium. *Cell Reports*,

41(6), 111616.

Miller, K. J., Zanos, S., Fetz, E. E., Den Nijs, M., & Ojemann, J. G. (2009a). Decoupling

the cortical power spectrum reveals real-time representation of individual finger

movements in humans. *Journal of Neuroscience*, *29*(10), 3132-3137.

Miller, K. J., Sorensen, L. B., Ojemann, J. G., & Den Nijs, M. (2009b). Power-law scaling

in the brain surface electric potential. *PLoS computational biology*, *5*(12),

e1000609.

Morey, R. D., Hoekstra, R., Rouder, J. N., Lee, M. D., & Wagenmakers, E.-J. (2016).

The fallacy of placing confidence in confidence intervals. *Psychonomic Bulletin &*

Review, *23*(1), 103–123.

Mormann, F., Lehnertz, K., David, P., & Elger, C. E. (2000). Mean phase coherence as

a measure for phase synchronization and its application to the EEG of epilepsy

patients. *Physica D: Nonlinear Phenomena*, *144*(3-4), 358-369.

Nadalin, J. K., Martinet, L. E., Blackwood, E. B., Lo, M. C., Widge, A., Cash S. S., Eden

U. T., & Kramer, M. A. (2019). A statistical framework to assess cross-frequency

coupling while accounting for confounding analysis effects. *Elife*, *8*, e44287.

Navas-Olive, A., Valero, M., Jurado-Parras, T., de Salas-Quiroga, A., Averkin, R. G.,

Gambino, G., Cid, E., & de la Prida, L. M. (2020). Multimodal determinants of

phase-locked dynamics across deep-superficial hippocampal sublayers during

theta oscillations. *Nature Communications*, *11*(1), Article 1.

Ngo, H.-V. V., Martinetz, T., Born, J., & Mölle, M. (2013). Auditory Closed-Loop

Stimulation of the Sleep Slow Oscillation Enhances Memory. *Neuron*, *78*(3),

545–553.

Nunez, P. L., & Srinivasan, R. (2006). *Electric fields of the brain: the neurophysics of*

EEG. Oxford University Press, USA.

Ouedraogo, D. W., Lenck-Santini, P.-P., Marti, G., Robbe, D., Crépel, V., & Epsztein, J.

(2016). Abnormal UP/DOWN Membrane Potential Dynamics Coupled with the

Neocortical Slow Oscillation in Dentate Granule Cells during the Latent Phase of

Temporal Lobe Epilepsy. *Eneuro*, *3*(3), ENEURO.0017-16.2016.

Pesaran, B., Vinck, M., Einevoll, G. T., Sirota, A., Fries, P., Siegel, M., Truccolo, W.,

Schroeder, C. E., & Srinivasan, R. (2018). Investigating large-scale brain

dynamics using field potential recordings: Analysis and interpretation. *Nature*

Neuroscience, *21*(7), Article 7.

Petersen, P. C., & Buzsáki, G. (2020). Cooling of Medial Septum Reveals Theta Phase

Lag Coordination of Hippocampal Cell Assemblies. *Neuron*, *107*(4), 731-744.e3.

Quinn, A. J., Lopes-dos-Santos, V., Huang, N., Liang, W.-K., Juan, C.-H., Yeh, J.-R.,

Nobre, A. C., Dupret, D., & Woolrich, M. W. (2021). Within-cycle instantaneous

frequency profiles report oscillatory waveform dynamics. *Journal of*

Neurophysiology, *126*(4), 1190–1208.

Ray, S., Crone, N. E., Niebur, E., Franaszczuk, P. J., & Hsiao, S. S. (2008). Neural

Correlates of High-Gamma Oscillations (60–200 Hz) in Macaque Local Field

Potentials and Their Potential Implications in Electrocorticography. *The Journal*

of Neuroscience, *28*(45), 11526–11536.

Roberts, M. J., Lowet, E., Brunet, N. M., Ter Wal, M., Tiesinga, P., Fries, P., & De

Weerd, P. (2013). Robust Gamma Coherence between Macaque V1 and V2 by

Dynamic Frequency Matching. *Neuron*, *78*(3), 523–536.

Rosenblum, M. G., Pikovsky, A. S., & Kurths, J. (1997). Phase synchronization in driven

and coupled chaotic oscillators. *IEEE Transactions on Circuits and Systems I:*

Fundamental Theory and Applications, *44*(10), 874–881.

Schatza, M. J., Blackwood, E. B., Nagrale, S. S., & Widge, A. S. (2022). Toolkit for

Oscillatory Real-time Tracking and Estimation (TORTE). *Journal of Neuroscience*

Methods, *366*, 109409.

Schiff, S. J. (2012). *Neural control engineering: The emerging intersection between*

control theory and neuroscience. MIT Press.

Shumway, R. H., & Stoffer, D. S. (1982). An Approach to Time Series Smoothing and

Forecasting Using the Em Algorithm. *Journal of Time Series Analysis*, *3*(4), 253–

264.

Shumway, R. H., & Stoffer, D. S. (2017). ARIMA Models. In R. H. Shumway & D. S.

Stoffer (Eds.), *Time Series Analysis and Its Applications: With R Examples* (pp.

75–163). Springer International Publishing.

Soulat, H., Stephen, E. P., Beck, A. M., & Purdon, P. L. (2022). State space methods for

phase amplitude coupling analysis. *Scientific Reports*, *12*(1), Article 1.

Spyropoulos, G., Saponati, M., Dowdall, J. R., Schölvinck, M. L., Bosman, C. A., Lima,

B., Peter, A., Onorato, I., Klon-Lipok, J., Roese, R., Neuenschwander, S., Fries,

P., & Vinck, M. (2022). Spontaneous variability in gamma dynamics described by

a damped harmonic oscillator driven by noise. *Nature Communications*, *13*(1),

Article 1.

Takens, F. (1981). Detecting strange attractors in turbulence. In D. Rand & L.-S. Young

(Eds.), *Dynamical Systems and Turbulence, Warwick 1980* (pp. 366–381).

Springer.

Tort, A. B. L., Komorowski, R., Eichenbaum, H., & Kopell, N. (2010). Measuring Phase-

Amplitude Coupling Between Neuronal Oscillations of Different Frequencies. *J*

Neurophysiol, *104*, 16.

VanRullen, R. (2016). Perceptual Cycles. *Trends in Cognitive Sciences*, *20*(10), 723–

735.

Vul, E., Harris, C., Winkielman, P., & Pashler, H. (2009). Puzzlingly High Correlations in

fMRI Studies of Emotion, Personality, and Social Cognition. *Perspectives on*

Psychological Science, *4*(3), 274–290.

Widge, A. S., & Miller, E. K. (2019). Targeting Cognition and Networks Through Neural

Oscillations: Next-Generation Clinical Brain Stimulation. JAMA Psychiatry, 76(7),

671–672.

Widmann, A., Schröger, E., & Maess, B. (2015). Digital filter design for

electrophysiological data—A practical approach. *Journal of Neuroscience*

Methods, *250*, 34–46.

Wodeyar, A., Schatza, M., Widge, A. S., Eden, U. T., & Kramer, M. A. (2021). A state

space modeling approach to real-time phase estimation. *ELife*, *10*, e68803.

Wodeyar, A., & Srinivasan, R. (2022). Structural connectome constrained graphical

lasso for MEG partial coherence. *Network Neuroscience*, *6*(4), 1219-1242.

Xing, D., Shen, Y., Burns, S., Yeh, C.-I., Shapley, R., & Li, W. (2012). Stochastic

Generation of Gamma-Band Activity in Primary Visual Cortex of Awake and

Anesthetized Monkeys. *Journal of Neuroscience*, *32*(40), 13873–13880a.

Yael, D., Vecht, J. J., & Bar-Gad, I. (2018). Filter-Based Phase Shifts Distort Neuronal

Timing Information. *ENeuro*, *5*(2).

Zanos, S., Zanos, T. P., Marmarelis, V. Z., Ojemann, G. A., & Fetz, E. E. (2012).

Relationships between spike-free local field potentials and spike timing in human

temporal cortex. *Journal of Neurophysiology*, *107*(7), 1808–1821.

Zhong, W., Ciatipis, M., Wolfenstetter, T., Jessberger, J., Müller, C., Ponsel, S.,

Yanovsky, Y., Brankačk, J., Tort, A. B. L., & Draguhn, A. (2017). Selective

entrainment of gamma subbands by different slow network oscillations.

Proceedings of the National Academy of Sciences, *114*(17), 4519–4524.

Zrenner, C., Desideri, D., Belardinelli, P., & Ziemann, U. (2018). Real-time EEG-defined

excitability states determine efficacy of TMS-induced plasticity in human motor

cortex. *Brain Stimulation*, *11*(2), 374–389.

Zrenner, C., Dragana Galevska, Jaakko O. Nieminen, David Baur, MariaIoanna

Stefanou, & Ulf Ziemann. (2020). *The shaky ground truth of real-time phase*

estimation. 21.