Title: Effective networks mediate right hemispheric dominance of human 40 Hz auditory steady-state response.

Authors: Neeraj Kumar*, Amit Jaiswal, Dipanjan Roy, Arpan Banerjee*

Cognitive Brain Dynamics Lab, National Brain Research Centre, NH 8, Manesar,

Gurgaon, 122052, India.

* Corresponding authors.

Email: arpan@nbrc.ac.in (A. Banerjee), neeraj.b15@nbrc.ac.in (N. Kumar)

Abbreviations:

ASSR: Auditory steady-state responses

STG: Superior temporal gyrus / rSTG: Right superior temporal gyrus

PAC: Primary auditory cortex

CC: Corpus callosum

MRI: Magnetic resonance imaging

SD: Standard deviation

EEG: Electroencephalography

MEG: Magnetoencephalography

ITPC: Inter-trial phase clustering

LI: Laterality index

CI: Confidence interval

eLORETA: Exact low-resolution brain electromagnetic tomography

BEM: Boundary element method

MNI: Montreal Neurological Institute

AAL: Automated anatomical labelling

GC: Granger causality

HG: Heschl's gyrus

IFG: Inferior frontal gyrus / rIFG: Right inferior frontal gyrus

BA: Brodmann area

PET: Positron emission tomography

fMRI: Functional magnetic response imaging

BOLD: Blood oxygenation level dependent

Abstract:

Auditory steady-state responses (ASSR) are induced from the brainstem to the neocortex when humans hear periodic amplitude-modulated tonal signals. ASSRs have been argued to be a key marker of auditory temporal processing and pathological reorganization of ASSR – a biomarker of neurodegenerative disorders. However, most of the earlier studies reporting the neural basis of ASSRs were focused on looking at individual brain regions. Here, we seek to characterize the large-scale directed information flow among cortical sources of ASSR entrained by 40 Hz external signals. Entrained brain rhythms with power peaking at 40 Hz were generated using both monaural and binaural tonal stimulation. First, we confirm the presence of ASSRs and their well-known right hemispheric dominance during binaural and both monaural conditions. Thereafter, reconstruction of source activity employing individual anatomy of the participant and subsequent network analysis revealed that while the sources are common among different stimulation conditions, differential levels of source activation and differential patterns of directed information flow using Granger causality among sources underlie processing of binaurally and monoaurally presented tones. Particularly, we could characterize bidirectional interactions involving the right superior temporal gyrus and inferior frontal gyrus and interhemispheric flow of information from left primary auditory areas to right superior temporal areas result in the right hemispheric dominance of tonal auditory processing in violation of contralateral processing symmetry observed for various examples of sensory processing.

Keywords: 40 Hz ASSRs, Hemispheric lateralization, Inter-hemispheric flow, Electroencephalography

1. Introduction

Auditory steady-state response (ASSR) is a phase-locked oscillatory response to periodic sound recorded from the scalp (Kuwada, Batra, and Maher 1986; Lithari et al. 2016; Zhang et al. 2013). ASSR can be identified by the frequency-based analysis, exhibiting a sharp rise in spectral power and phase-locking across trials at the frequency of periodicity. In the literature, ASSRs have been reported widely to be elicited maximally at a stimulation frequency of 40 Hz (Galambos, Makeig, and Talmachoff 1981; Hari et al. 1989; Linden et al. 1987). Moreover, it is reported that ASSRs can be detected readily at a single participant level and do not show gender-specific differences among right-handed participants (McFadden et al., 2014; Melynyte et al., 2017). Due to its robustness and reliability, 40 Hz ASSR is widely used for theoretical and clinical research, e.g., temporal auditory processing, screening hearing threshold, and measurement of consciousness during global anaesthesia (Farahani et al., 2020; Haghighi et al., 2018; Niepel et al., 2020), etc. Additionally, 40 Hz ASSR is also used as a biomarker in certain neuropsychological disorders like schizophrenia and autism (O'Donnell et al., 2013).

In general, the processing of sensory stimuli requires coordinated interactions among specialised brain regions that are distributed across the hierarchal cortical networks (Bressler & Menon, 2010; Fries, 2005). Therefore, studying the pattern of information flow among specialised brain regions that are involved would allow us to understand the causal basis of ASSRs. There is converging evidence that neural generators for 40 Hz ASSRs predominantly lie in the right superior temporal gyri (STG) (Gutschalk et al. 1999; Hari et al. 1989; Mäkelä and Hari 1987; Tiihonen et al. 1989) and bilateral primary auditory cortex (Pantev et al. 1996; Bohórquez and Özdamar 2008; Ross et al. 2005; Spencer et al. 2009) in addition to sub-cortical regions (Herdman et al. 2002; Poelmans et al. 2012). While there is an emerging consensus among regions activated during 40 Hz ASSRs, the pattern of interactions and information flow among relevant nodes of ASSRs remains poorly understood. This is an interesting question

since the patterns of information flow between relevant brain regions in the distributed auditory

hierarchy are indicative of directed functional connectivity, which offers a refined picture of

the communication channels and a critical role of the underlying drivers and followers involved

in the generation of ASSRs. For example, a unidirectional information flow from one sensory

node to another will reveal hierarchical processing, initiating at sub-cortical areas such as the

thalamus, directing the cortical primary sensory node, which eventually directs the information

to the other cortical node/s. On the other hand, a bidirectional connectivity between cortical

nodes would imply a parallel and simultaneously recurrent processing scheme and possibly a

common subcortical generator affecting directly the bilateral cortical regions underlying the

generation of ASSR. Thus, an overall characterization of the direction of information flow

pathways in auditory pathways within and between two hemispheres will reveal that the

functional organization between two hemispheres is governed by the symmetry/ asymmetry of

auditory stimulation during auditory tone processing tasks. Motivating our work from previous

studies that suggest lateralization enables more efficient information transfer among

specialized brain regions during language processing (Toga et al. 2003), we propose studying

ASSR lateralization at the cortical source space level and interactions between key cortical

sources. We hypothesize that causal interactions between cortical sources will provide critical

insights into underlying brain networks and their task-specific functional organization.

Following studies demonstrating right hemispheric dominance of non-linguistic / tonal/musical

auditory sounds (Albouy et al., 2020), we further hypothesize that the underlying effective

brain network interactions (Friston, 2011) should also reflect the presence of hemispheric

dominance. Furthermore, the directionality of effective connections will reflect the hierarchical

aspects of underlying information processing.

Earlier studies have reported right hemispheric dominance in source activation during 40 Hz ASSRs. Existing evidence from structural and functional studies suggests that ~70 % of ascending auditory inputs from either ear cross at the brainstem level and 30% remain on the same side (Hackett, 2015; Kaas & Hackett, 2000; Langers et al., 2005). Consequently, one would expect a contralateral dominance in primary auditory cortical (PAC) response during monaural stimulation conditions. Now, it's naturally intriguing how the information, particularly during the monaural right condition, that enters the left PAC is eventually redistributed to a specialised centre present in the right hemisphere. Transcortical communication through the corpus callosum (CC) has been suggested to compensate for this asymmetric input to achieve hemispheric specialization during the processing of distinct features of auditory stimuli (Zaidel & Marco, 2003; Cammoun et al., 2015). This can be very well experimentally validated by monaural stimulations. Hence, according to the principle of contralateral dominance, the monaural right would evoke a greater response in the left PAC than the monaural left condition (Andoh, Matsushita, and Zatorre 2015). In the present work, we record human electroencephalography (EEG) during 40 Hz ASSRs during binaural and both monaural left and right stimulation conditions. We reconstruct trial-wise source activity employing subject-wise anatomical structure by co-registering EEG with individual subject Magnetic resonance imaging (MRI) data and subsequently characterize effective network interactions using spectral Granger's causality among sources of ASSRs.

2. Materials and Methods

2.1. Participants

Twenty-one healthy, right-handed human volunteers (16 males, 5 females, age range 22–39 years old; mean $\pm$ SD = 28 $\pm$ 2.10) participated in this study[1]. The right-handedness of participants was verified by the Edinburgh Handedness Questionnaire based upon a cut-off of 60–100. All the volunteers reported no medical history of audiological, neurological or psychiatric disorders. All of them had normal or corrected to normal visual acuity. Informed consent was given by all the volunteers in a format approved by the Institutional Human Ethics Committee (IHEC) of National Brain Research Centre that confirms the guidelines set by the Declaration at Helsinki. All participants were fluent in at least two languages, Hindi and English, but some were familiar with another language of Indian origin.

2.2. Experimental design

Stimuli consisted of sinusoidal tones of 1 kHz frequency and 25 ms duration comprising 5% of rise and falling time, presented 40 times per second (Linden et al. 1987). Each trial comprised of 1s "On" block (auditory stimulation) period followed by 1s "Off" block (silent) period (Figure 1A). A total of 100 trials were presented for each kind of auditory stimulation, monaural and binaural. In total, four experimental conditions, each lasting 200 seconds, were performed in the following order— 1) a baseline condition in which the volunteers were not given any tonal stimuli; 2) Binaural (in both ears); 3) Monaural left (only through left ear); 4) Monaural right (only through right ear). The time interval between each condition was set to 100 s (silent). Auditory stimuli were created and presented in Stim2 software (Compumedics,

---

[1] A subset of this data (10 volunteers) were used in a Methods paper Halder, T; Talwar, S., Jaiswal, A.K., Banerjee, A.(2019): Quantitative evaluation in estimating sources underlying brain oscillations using current source density methods and beamformer approaches. eNeuro. 2019 Jul-Aug; 6(4): ENEURO.0170-19.2019.

Inc., USA) at 85 dB sound pressure level. The specific value of loudness was chosen to have

reliable ASSR responses in all participants based on a prior pilot study in our group.

Participants were instructed to stay still in a sitting position, fixate on a visual cross displayed

on a computer screen for the duration, and listen to the tones. Continuous scalp EEG was

recorded when the volunteers were performing the experiment.

2.3. Data acquisition

EEG data were recorded using 64 Ag/AgCl sintered electrodes mounted in an elastic head cap

according to the international 10-20 system. All recordings were done in a noise-proof isolated

room using NeuroScan (SynAmps2) system (Compumedics Inc, USA) with a 1 kHz sampling

rate. Abrasive electrolyte gel (EASYCAP) was used to make contact between EEG sensors and

scalp surface, and impedance was kept below 5 kΩ in each sensor. The default EEG system-

assigned reference electrode was placed at the vertex (Cz) and the ground electrode at the

forehead (AFz). The electrode locations were obtained relative to three fiducials at the nasion

and left and right preauricular points using a 3D digitizer (Polhemus Inc., Colchester, VT,

USA).

2.4. Pre-processing of EEG signals

EEG data analysis was performed with Chronux (http://chronux.org/), EEGLAB (Delorme &

Makeig, 2004), FieldTrip (http://fieldtriptoolbox.org) and custom MATLAB scripts

(www.mathworks.com). EEG data was imported in MATLAB using EEGLAB from

Neuroscan raw files. Continuous long-time EEG time series were bandpass filtered to retain

frequencies between 3–48 Hz. Thereafter, eyeblinks and heartbeat artefacts were removed from

EEG data using independent component analysis in-built in EEGLAB after careful visual

inspection. The temporal window of steady-state activity was identified from the grand mean

event-related potentials (ERPs) of both mastoid channels (Coffey et al., 2016) (Figure 1).

Hence, baseline corrected epochs of 750 ms from "On" blocks were extracted from each trial,

excluding the first 250 ms of the time series from the onset of auditory stimuli. Furthermore,

simple threshold-based artefact rejection was applied to exclude the remaining noisy epochs.

Hence, epochs having a voltage greater than ±85 µv were discarded. After artefact rejection,

none of the epochs from monaural conditions of one participant survived the thresholding.

Therefore, we removed the data of that participant from further analysis. The remaining

participants contained fewer than 3 noisy trials. Thereafter, we re-referenced the EEG signal to

common mode average reference, followed by combining trials from every participant into a

single pool for group analysis at the sensor-level. On average less than 5 trials were removed

per subject. In total we have recorded 2000 trials from all participants per condition (100 trials

X 20 participants). The surviving trials numbers were 1980 in binaural; 1975 for monaural left

and 1980 trials for monaural right.

2.5. Identification of ASSRs at sensor-level

2.5.1. **Inter-trial phase clustering**

Inter-trial phase clustering (ITPC) was employed to ensure the presence of the entrainment

effect at 40 Hz. ITPC quantify the degree of non-uniformity or clustering in the distribution of

oscillatory phase across trials at a particular frequency (Palva et al., 2005). The value of ITPC

range between zero and one, with one being perfect phase consistency across trials and zero

being complete uniformity. Mathematically, ITPC is defined as

$$ITPC_f = \left| \frac{1}{n} \sum_{r=1}^{n} e^{i\theta} \right| \qquad (1)$$

wherein, $\frac{1}{n} \sum_{r=1}^{n}$ represents an average of complex vector $e^{i\theta}$ across n trials; $e^{i\theta}$ is Euler's

formula wherein θ is phase angle at frequency f derived from complex Fourier coefficients.

We calculated the ITPC of all the channels during the binaural condition and selected a channel

with maximum ITPC at 40 Hz. To assess the significance of phase clustering, the observed

ITPC values were compared with a critical value $ITPC_\alpha$ at the significance level of p < 0.01

(Bonferroni corrected) obtained as (Zar, 1999, Cohen 2014)

$$ITPC_\alpha = \sqrt{-log(pval) * n^{-1}} \qquad (2)$$

where n is the total number of trials. ITPC values higher than critical ITPC were considered

statistically significant.

2.5.2. **Power spectrum**

The power spectrum was computed using Chronux function *mtspectrumc.m* scripts at each

sensor, trial, and condition. First, power spectra were calculated in the frequency range of 3–

48 Hz (~ 1 Hz smoothing), and grand averaged for all channels and trials. Subsequently, t-

statistic were calculated as test statistic between auditory stimulation and baseline conditions

at the frequency of interest i.e., 40 Hz, followed by a statistical evaluation of observed t-statistic

employing a permutation test described above. The procedure involves 1000 time shuffling of

the trials among both conditions and measuring t-statistic in each permuted data sets.

Thereafter, a histogram is plotted, comprising all 1000 t-statistic from permuted data creating

a null distribution (Maris & Oostenveld, 2007). Observed t-statistic were then thresholded to

the 99th quantile of the respective null distribution corresponding to p = 0.01 (Bonferroni

corrected). The p-values were considered significant if the observed difference was beyond the

aforesaid threshold.

2.5.3. **Laterality analysis**

Hemispheric asymmetry in brain responses was quantified using laterality index (*LI*), which is

the difference between right hemisphere (RH) and left hemispheric (LH) responses normalized

by the sum of responses in both hemispheres.

$$LI = \frac{RH - LH}{RH + LH} \tag{3}$$

The value of *LI* ranges between +1 and -1. Wherein +1 represents complete right hemispheric dominance, -1 for complete left hemispheric dominance and 0 for a bilaterally symmetric response. Trial-wise median of 40 Hz spectral power was calculated over right and left hemispheric sensors, excluding midline sagittal plane electrodes. Furthermore, to assess the statistical significance of LIs, the 95% confidence interval (*CI*) was calculated as

$$CI = \left(\mu + t_{d.f.} \times S.E., \ \mu - t_{d.f.} \times S.E. \right) \tag{4}$$

where μ is the mean of data, t is the inverse of Student's t cumulative distribution function at corresponding $d.f$ (degree of freedom), and $S.E.$ is the standard error of the mean. Moreover, to determine whether lateralization has a common source during different stimulation conditions, we performed one-way ANOVA on the distribution of LI values among different stimulation conditions, followed by controlling for multiple comparisons employing the Tuckey-Kramer test.

2.6. Source localization of ASSRs

Converging evidence suggests that utilising individual brain anatomy yields better source localization (Coffey et al., 2016). Hence, source-level analysis was performed by co-registering EEG sensor locations to MRI-guided fiducial points. Exact low-resolution brain electromagnetic tomography (eLORETA) (Pascual-Marqui, 2007) was used to calculate the three-dimensional spatial distribution of source activity underlying 40 Hz ASSRs. Earlier research demonstrated that eLORETA yields a favourable performance when false positives were considered (Halder et al., 2019). We performed exact low-resolution brain electromagnetic tomography (eLORETA) (Pascual-Marqui, 2007) to locate the stimulus-specific sources of 40 Hz ASSRs and then reconstructed the source-level spectral activity to characterize underlying functional networks. eLORETA employs distributed source modelling

and estimates the current source density across brain volume by minimizing the surface

Laplacian component during the construction of the spatial filter (Pascual-Marqui, 2007;

Pascual-Marqui et al., 2011). Additionally, eLORETA does not rely upon any assumption

regarding the number of underlying sources while having excellent control over the

suppression of false positives during the detection of sources (Halder et al., 2019). Hence,

source analysis employing eLORETA was performed using the FieldTrip toolbox (Oostenveld

et al., 2011) implemented in MATLAB and connectivity analysis was done by customized

MATLAB scripts.

The ingredients to construct a frequency domain eLORETA spatial filter are the forward model

and the cross-spectral matrix of sensor data. The forward model also called the volume

conduction model for the head define how an electrical current propagates across brain and

would be recorded at the sensor level. Therefore, geometrical properties of the head including

surface description of brain, skull and scalp were derived from subject-specific T1-weighted

anatomical MRI scan and used for forward modelling based on the boundary element method

(Fuchs et al., 2001). Subsequently, employing channel position leadfields for individual

subjects were computed. Construction of leadfield requires description of locations known as

grids on which the leadfields are calculated. Here, we first create 11,000 template grids that

were defined according to Automated anatomical labelling (AAL) atlas (Rolls et al., 2015).

Subsequently, these template grids were warped to individual MRI yielding 11,000 subject-

specific grids arranged in normalised space. The leadfield matrix was computed at each grid in

3 orthogonal directions.

Moreover, we computed sensor-level cross-spectral matrices for each condition from the SSR

time series (250:1000 ms), same as used for the sensor-level analysis. Thus, we computed a

spatial filter employing the subject-specific forward model and sensor-level cross-spectral

matrix for each condition. A common spatial filter was computed from combined data i.e.,

trials from all four conditions were grouped into a single pool. Since, common filter employs

cross-spectral matrices from all conditions hence, attenuating filter-specific variability during

inverse modelling, i.e., the observed difference between different conditions is attributed only

to the differences in conditions, not due to differences in the spatial filter. Subsequently, sensor-

level cross-spectra were projected to the spatial filter obtaining the source power across trials,

space and orientation. Since we do not have any prior assumption about the orientation of the

underlying source activity, the largest eigenvalue was selected as grid power from strongest

dipole orientation that explaining the maximum variance of data. Consequently, subject and

trial wise distribution of source power across brain volume was obtained for each condition.

Thereafter, pairwise t-statistic was computed as test statistic for each grid between auditory

stimulation and baseline condition. Since there was total 11,000 grids hence would have

required same number of statistical comparisons, therefore, to circumvent the multiple

comparison problem we down-sampled the source powers from grid space to parcel space by

taking median t-statistic of each parcel. Further, the prominent sources for each subject were

selected after thresholding at the 95^{th} quantile from distribution of t-statistic of parcels and

further tested for statistical significance by non-parametric statistic as described above for

sensor-level 40 Hz spectral power (see section 2.5.2). Finally, for visualization purpose, all

grids from significant parcels were visualized after rendering onto a cortical surface from the

Colin27 brain template provided in the FieldTrip toolbox (http://fieldtriptoolbox.org).

2.7. Source activity reconstruction and connectivity analysis

The source-level spectral activity was reconstrued by projecting the trial-wise sensor-level

cross-spectral matrix to the spatial filter of significant parcels to calculate the global coherence

and Granger's causality among significant sources.

2.7.1. **Global Coherence**

Global coherence analysis was employed to identify the presence of a brain-wide large-scale functional network (Cimenser et al., 2011, Fonseca et al., 2015). The global coherence can be calculated from the cross-spectral matrix using the leading eigenvalue method in two steps. First, cross-spectrum was computed as:

$$S_{ij}(f) = \frac{1}{n} \sum_{r=1}^{n} X_i^r(f) X_j^r(f)^* \tag{5}$$

where $X_i^r(f)$ and $X_j^r(f)$ are trial (r) and frequency (f) specific Fourier transforms from the sources i and j, respectively and asterisk represents matrix transposition and complex conjugate calculated over n trials.

Second, global coherence was computed as the ratio of the maximum eigenvalue and the sum of eigenvalues calculated from the cross-spectral matrices.

$$C_{Global}(f) = \frac{S_1(f)}{\sum_{r=1}^{k} S_r(f)} \tag{6}$$

where $C_{Global}(f)$ is the global coherence, $S_1(f)$ is the largest eigenvalue and the denominator $\sum_{r=1}^{k} S_r(f)$ represents the sum of eigenvalues of the cross-spectral matrix. The non-parametric statistical testing at $p < 0.01$ was performed to evaluate the significant differences in global coherences at 40 Hz during the auditory stimulation conditions. The differences in coherences between task and baseline condition were quantified using coherence Z-statistic (Maris et al., 2007).

$$Z = \frac{\left(tanh^{-1}(|C_1(f)|)\right) - (1/d.f._{\cdot 1} - 2) - \left(tanh^{-1}(|C_2(f)|)\right) - (1/d.f._{\cdot 2} - 2)}{\sqrt{(1/d.f._{\cdot 1} - 2) + (1/d.f._{\cdot 2} - 2\,))}} \tag{7}$$

where $d.f._{\cdot 1}$ and $d.f._{\cdot 2}$ denote the degrees of freedom, $C_1(f)$ and $C_2(f)$ are coherence values during the first and the second conditions, respectively, at the frequency of interest ($f = 40$ Hz). The resulting Z-statistic was considered an observed test statistic, which was tested for significance after comparison with the null distribution as described above (see section 2.5.2).

2.7.2. Directed sub-networks of ASSRs

After confirming the presence of a synchronised network, we calculated the multivariate

Granger causality (GC) to establish the direction and strength of causal influence (Granger

1969). Subject-level nonparametric GC in the spectral domain were calculated among sources

(Brovelli et al. 2004; Dhamala, Rangarajan, and Ding 2008). This involved Fourier

transformations of the sensor time series followed by nonparametric spectral matrix

factorization (using Wilson's algorithm) of the cross-spectral density to yield transfer function

H and the noise covariance matrix $\sum$. Pairwise GC from Y to X at the frequency(f) can then

be expressed as

$$I_{Y \to X} = \ln \frac{S_{xx}(f)}{S_{xx}(f) - \left(\sum_{yy} - \frac{\sum_{xy}^2}{\sum_{xx}} |H_{xy}(f)|^2 \right)} \qquad (8)$$

where $S_{xx}(f)$ is the total spectral power (auto-spectrum) and the denominator represents

intrinsic power (total power minus the causal contribution) of the "effect" signal

(Geweke 1982).

After measuring causality in both directions, one can locate the "source" and "effect"

regions of the brain by comparing significant GC values in both directions. Since GC values

follow unknown distribution, we adopt non-parametric statistical testing to assess significant

GC spectral peaks among GC pairs (Brovelli et al. 2004). First, 1000 permuted data sets were

generated by independently shuffling trials from each source pair. Shuffling trial order

abolished task-specific information while keeping the data pool same. Then, GC was

computed, and the maximum GC value was selected over the frequency range from each

permuted data set (Ding, Chen, and Bressler 2006). Subsequently, a null distribution consisting

of all GC values was constructed from the shuffled data set. GC peaks in unshuffled data were

considered statistically significant when the observed GC value reached beyond the 99th

quantile value ($p < 0.01$) of the null distribution. The multiple comparison problem was

handled by Bonferroni corrections. We have also quantified the relative contribution of each

source in the whole-brain causal network, as number of connections linked to each source.

Mathematically, node degree was calculated as the number of edges connecting the source

normalised by the maximum number causal connections each source could make i.e.,

$(N-1)\,X\,2$. In our case, we found 6 significant sources so any source could maximally

make10 causal connection. Additionally, since our objective included identifying the role of

trans-cortical communication in manifestation of right hemispheric dominance during different

stimulation conditions, we specifically focused on the inter-hemispheric flow. Here, to

maximize the number of measurements, Granger causality was calculated again from all voxels

in the left PAC to all voxels in right STG during different stimulation conditions. Subsequently,

we evaluated the effect on interhemispheric flow during different stimulation conditions by a

non-parametric Kruskal-Wallis test, followed by Tuckey-Kramer post-test.

3. Results

3.1. **Presence of ASSRs at sensor-level**

In the time domain, evoked potential of mastoid channels showed steady-state activity in the time range of 250 – 1000 ms from the onset of periodic auditory stimuli (Figure 1A). In the frequency domain, we evaluated the strength of inter-trial phase clustering (ITPC) during auditory stimulation and baseline conditions across the frequency range of 3-46 Hz. We found significant ITPC during all auditory stimulation conditions ($p < 0.01$) only at 40 Hz (Figure 1B). Increase in the ITPC was a result of phase clustering around one region of polar space while the distribution of phase angles is uniform during the baseline condition (Figure 1C). Grand mean power spectra averaged over all electrodes and trials showed significant enhancement of spectral power at 40 Hz in binaural [$t_{(1970)} = 4.19$, $p < 0.0001$], monaural left [$t_{(1970)} = 2.28$, $p < 0.0001$] and monaural right condition [$t_{(1970)} = 3.19$, $p < 0.0001$] (Figure 2A).

3.2. **Hemispheric asymmetry**

Laterality indices were calculated to quantify the degree of asymmetry during ASSRs across different stimulation conditions. Both upper and lower 95 % confidence intervals of LI values were greater than zero during every auditory stimulation condition suggesting right hemispheric dominance in sources of ASSRs during binaural and both monaural conditions. Particularly, during binaural condition the group-mean hemispheric laterality index was LI = 0.023 and with 95 % lower and upper confidence interval was 95% CI = [0.010, 0.035]. During the monaural left condition (LI = 0.019, 95% CI = [0.007,0.032]) and monaural right condition (LI = 0.032, 95% CI = [0.019, 0.045]). One-way ANOVA among LI values across different stimulation conditions showed no significant difference in mean LI values across conditions ($F(2, 5910) = 1.01, p = 0.36$).

3.3. Source-level functional organization of 40 Hz ASSRs

3.3.1. Sources of ASSRs

Exact low-resolution brain electromagnetic tomography (eLORETA) was used to reconstruct

whole-brain distribution of 40 Hz activity. The source activity has been parcellated according

to AAL atlas and tested for significance. The locations of significant sources during monaural

left, monaural right and binaural conditions are shown in Figure 3. Anatomical labels

corresponding to significant source and their respective t-statistic are summarised in Table 1.

Table 1: Anatomical labels (according to AAL parcellation) of 40 Hz ASSRs sources along with their corresponding power (t-statistic between auditory stimulation and baseline condition).

	Binaural	Monaural left	Monaural right
Right Heschl's gyrus	3.81	3.25	3.46
Left Heschl's gyrus	3.69	3.24	3.28
Right Superior temporal gyrus	3.52	3.12	3.31
Right Inferior frontal gyrus (triangular part)	3.39	2.70	3.17
Right Precentral gyrus	4.01	3.17	3.34
Left Precentral gyrus	3.35	3.01	3.34

In total, six sources were found significant at p < 0.001 during every stimulation condition.

Interestingly, locations of sources were same for binaural and both monaural conditions (see

Table 1), namely, bilateral Heschl's gyri, bilateral precentral gyri, right superior temporal gyrus

and right inferior frontal gyrus (triangular part). Hence, 4 sources were located in right

hemisphere and 2 sources in left hemisphere for every stimulation condition. Though, the

sources were same the source power of different regions differed across auditory stimulation

conditions (Table 1).

3.3.2. Functional brain networks underlying ASSR

Global coherence measures the extent of coordinated neuronal activity over the whole brain

(Cimenser et al., 2011; Kumar et al., 2016). The enhancement in global coherences among

ASSR sources was evaluated by nonparametric statistical testing (Maris et al., 2007),

employing Z-statistic as the test statistic. In line with our hypothesis, we observed a stimuli-

specific enhancement of global coherence at 40 Hz, revealing a highly selective large-scale

synchronization of neuronal assemblies at this frequency during binaural [$Z_{20} = 1.35$, $p <$

0.0001], monaural left [$Z_{20} = 1.14$, $p < 0.0001$], and monaural right [$Z_{20} = 1.17$, $p < 0.0001$]

conditions (Figure 4). The increase in whole-brain global coherence motivated for pairwise

connectivity analysis employing Granger causality.

Multivariate non-parametric spectral Granger's causality (GC) was computed in all possible

sources of ASSRs to measure source-level directed networks that may contribute to the whole-

brain global coherence contribution (Geweke 1982; Granger 1969). Heatmaps in Figure 5 (left

panel) show GC values among all possible source pairs. Significant Causal flow were depicted

in the glass brain (Figure 5; Right panel) and also tabulated in Table 2 with corresponding GC

values.

Table 2: Pairwise list of causally interacting sources pairs along with their respective causal strengths. Causal interactions among sources identified using Granger causality and significant causal interactions are illustrated in Figure 5.

Binaural		
From	To	GC value (10^{-2})
R STG	R HG	8.6
R HG	R STG	7.3
L HG	R STG	7.2
R STG	R IFGtriang	4.1
R IFGtriang	R STG	4.1

Monaural left		
L HG	R STG	6.0
R HG	R STG	5.1
L HG	L PreCG	3.7
R IFGtriang	R STG	3.7
R STG	R HG	3.4

Monaural right		
L HG	R STG	8.2
R HG	R STG	7.6
R IFGtriang	R STG	5.1
R STG	R IFGtriang	4.7

Connectivity plots reveal the organization of directed network interaction during different

auditory conditions (Figure 5; Right panel). Interestingly, at least three GC interactions were

common in all three conditions; namely, 1) Left HG to Right STG, 2) Right HG to Right STG

and, 3) Right STG to Right IFG. Specifically, outflows from bilateral HG reaching to the right

STG, consequently involving unidirectional interhemispheric flow from left HG to right STG.

Presence of interhemispheric flow was in line with our hypothesis of involvement of trans-

cortical flow during ASSR. During the monaural left and binaural conditions, there was

bidirectional causal flow between right HG and right STG. During the binaural and monaural

right condition, the right STG was bidirectionally connected to the right IFG. Node degree of

ASSR sources (see Table 3) showed right STG was the most connected source among all ASSR

sources having an average node degree of 0.43 followed by right HG (node degree = 0.17).

Table 3: Node degree of ASSRs sources in the whole-brain network of ASSRs during different auditory stimulation conditions. Fourth column show the average of node degree calculated as mean of node degree in all 3 conditions.

Source Name	Binaural	Monaural left	Monaural right	Average
Right Superior temporal gyrus	0.50	0.40	0.40	0.43
Right Heschl's gyrus	0.20	0.20	0.10	0.17
Right Inferior frontal gyrus	0.20	0.10	0.20	0.17
Left Heschl's gyrus	0.10	0.20	0.10	0.13
Left Precentral gyrus	0.00	0.10	0.00	0.03
Right Precentral gyrus	0.00	0.00	0.00	0.00

Specifically, right STG was causally connected with bilateral HG and right IFG during every

ASSR condition. Overall, three nodes from the right hemisphere (HG, STG and IFG) contribute

to whole-brain causal network of ASSR while left hemisphere had two nodes (HG, Precentral

Gyrus). For visualization purpose, we did not plot GC flow from left HG to left PCG during

the monaural left condition.

Additionally, we found that the strength of inter-hemispheric flow was significantly different

between at least two groups (χ (2,8097) =80.34, $p < 0.0001$). Particularly, both binaural and

monaural right were significantly different from monaural left conditions ($p < 0.0001$) however

there was no difference between binaural and monaural right conditions ($p = 0.9$). The

difference in distributions of inter-hemispheric flow was visualised by 'violin.m' (Hoffmann,

2015). The maximum interhemispheric flow was present during the binaural condition,

followed by monaural right and least during the monaural left condition (Figure 6).

4. Discussion

Our study attempted to reveal the directed interactions that unfold during the entrainment of periodic auditory stimuli of tonal nature in brain dynamics. The stimuli-driven sources of neuronal oscillations were present across the hierarchy of cortical auditory pathways — Heschl's gyrus (HG), superior temporal gyrus (STG), precentral gyri, inferior frontal areas corroborating with the previous fMRI, PET and EEG/MEG studies (Farahani et al., 2020; Poelmans et al., 2012; Reyes et al., 2004). Digging deeper, we explored the information flow organization in these structures using effective connectivity analysis. We found that the right STG serves as an integrative area, receiving inputs from both primary auditory cortices, wherein information from the left primary auditory cortex is received via trans-cortical pathways, the organizational symmetry of which was dependent on the ears being stimulated. Furthermore, our directional network analysis suggests bidirectional interactions between right STG and frontal regions may provide efficient information exchange required for a comprehensive mapping of the auditory environment that ultimately manifests as right hemispheric dominance. The present findings may provide not only a network-level basis for right hemispheric dominance during 40 Hz ASSRs but also a clue about idiosyncratic violation of contralateral dominance in functional hemispheric asymmetry during monaural stimulations, as observed in several past studies, revealing a hierarchical processing organization, not dependent on stimulus location in the environment, underlying the phenomena of rhythm entrainment.

4.1. Sources of ASSR

A significant oscillatory response was seen in bilateral HG during every condition. HG residing in the primary auditory cortex is known to be the first cortical structure that receives auditory inputs (Hackett, 2015). Additionally, monaural right condition generated a maximum response

in the left Heschl's gyri. Contralateral dominance of primary auditory areas during monaural

stimulations is a well-established phenomenon reported in several fMRI, PET and EEG/MEG

studies and attributed to the crossing of ascending anatomical fibres at the brainstem level

(Hackett, 2015; Kaas & Hackett, 2000; Langers et al., 2005). In addition to the classic auditory

pathway, we also report activation beyond the primary auditory cortex, for instance, bilateral

pre-central gyri, which is in line with earlier findings on reconstructed 40 Hz ASSRs sources

with equivalent dipole modelling (Farahani et al., 2020). Interestingly, significant activation in

the right inferior frontal gyrus (triangular part) (rIFG) was also found during every condition

of ASSR. Right IFG, an analogue of Broca's area in the right hemisphere has been suggested

to process sound length and attending to pitch/rhythms (Plakke & Romanski, 2014; Wang et

al. 2015). Though most sources of 40 Hz ASSR are well established, the enhancement of global

coherence among sources in the present study reveals inter-areal brain synchronization among

sources, a prerequisite of communication among neuronal assemblies (Bressler & Menon,

2010; Fries, 2005). Further analysis of directed information flow among sources provides a

much clearer understanding of the role of observed sources.

4.2. Interhemispheric transfer

During every stimulation condition, there were causal flows originating from both primary

auditory cortices reaching the right STG, consequently requiring an interhemispheric causal

flow from the left PAC. There are anatomical fibres that support this information flow. In

general, interhemispheric transfer of information is achieved via the corpus callosum (Andoh

et al., 2015). The corpus callosum provides a functionally relevant scaffold for mediating

proper communication across both hemispheres (Zaidel & Marco, 2003). Although the inter-

hemispheric flow was present during every auditory stimulation condition there was

differences in strength of interhemispheric flow during different conditions. The observed

differences in the strength of interhemispheric pathway during different task conditions suggest

its differential functional requirements. Due to existing afferent structural constraints,

irrespective of the ear being stimulated both PAC receives some amount of acoustic

information in tandem with the manifestation of contralateral dominance during monaural

conditions (Langers et al., 2005). The right hemispheric specialization to process rhythmic

features of acoustic input would require transfer of information from left PAC to specialised

centres present in the right hemispheres. Hence, the monaural right condition would naturally

require higher inter-hemispheric flow to compensate for the early asymmetric inputs.

Alternatively, during the monaural left condition, wherein the information is already dominant

in left hemisphere would show least involvement of inter-hemispheric flow. The strength of

inter-hemispheric flow was maximum during the binaural condition. In general, binaural

condition requires more trans-cortical communication to integrate incoming bilateral acoustic

inputs in addition to the transfer of primary information from PAC to the secondary auditory

cortex. The complexity in dissociation of these two kinds of information prevents a

straightforward explanation of inter-hemispheric flow during binaural conditions.

4.3. Integrative nature of STG

After initial processing in bilateral HG, information related to ASSR is feedforwarded to the

right superior temporal gyrus (rSTG). Several studies of ASSRs have reported prominent

activations in rSTG (Mäkelä and Hari 1987). We observed rSTG showing maximum inward

causal information flow in the whole network (See Figure 5 and Table 2). This type of causal

information flow from primary sensory areas to intermediate areas of the auditory pathway

suggests the integrative nature of rSTG mediating acoustic-pattern analysis. Ross and

colleagues proposed that the right auditory cortex process temporal regularities associated with

pitch processing of incoming sound (Ross et al. 2005). In the context of the earlier view, rSTG

can be considered as a specialised region for detecting regularities in acoustic input and subsequently sending information to "higher-order" frontal cortices. Also, our analyses revealed that rSTG is bidirectionally connected to the right inferior frontal gyrus (BA45). STG to frontal gyrus causal flow can be considered a bottom-up process, while causal influence from frontal to right STG can be seen as a top-down modulation or relevant for predicting incoming sensory inputs. Right IFG (rIFG) areas are known to be associated with identifying features like sound length and attending to pitch/rhythms plausibly utilising periodic cues received from STG (Plakke & Romanski, 2014). Activity in rIFG along with activation in bilateral primary auditory cortex was also reported by Reyes and colleagues using PET imaging in response to 40 Hz amplitude modulated (AM) tone (Reyes et al. 2005). Several studies have reported anatomical projections from STG to the frontal cortex (Hackett 2011; Kaas and Hackett 2000; Plakke and Romanski 2014). Wang and colleagues identified a functional network comprising the frontal cortex and superior temporal regions that are sensitive to tone repetition patterns, which is associated with human's unique ability for language processing (Wang et al. 2015). Here we show, this fronto-temporal network that is central to processing of periodic structure of auditory stimuli, is mediated by bidirectional interactions between rSTG and right frontal regions.

4.4. Right hemispheric dominance

The present findings could give us a possible basis for right hemispheric dominance during 40 Hz ASSRs, as observed in several past studies by exploring the directed information flow among cortical sources. We argue that the right hemispheric lateralization of 40 Hz can be attributed to the right STG and its bidirectional interaction with the right frontal region. Furthermore, the activation of the pattern was similar in every condition, suggesting it as a central network of processing of periodic auditory stimuli and facilitator of brain-wide

entrainment of cortical rhythms. This is in line with the previous finding that suggested tonal

or melodic stimuli are predominantly processed in the right hemisphere while speech and

language stimuli showed left hemisphere dominance (Zatorre and Belin, 2001; Ross et al.,

2005; Albouy et al., 2020). thus, following the same reverberating theme of right hemispheric

dominance.

5.   Methodological considerations

We have employed distributed source modelling based on individual-subject anatomy to

account for variability in the head-size of participants. Though, we did not restrict our source

analysis to only cortical regions, nevertheless we did not find any activation in the sub-cortical

areas of brain. However, it should not be assumed that any sub-cortical source dynamics does

not underlie in the whole-brain processing of ASSR. There are sufficient studies about the role

of thalamus in the whole-brain network processing (Lee, 2013; Das et al., 2021). However, in

our study, the detectability of thalamus and other sub-cortical regions were limited by several

methodological factors. In principle, sub-cortical regions of brain are predisposed to the signal

cancelation given their deep location and irregular cell architecture and thereby cortical activity

dominate over sub-cortical regions (Attal et al., 2007; Hnazaee et al., 2020). That result in very

poor signal to noise ratio for deeper sources (Halder et al., 2019), specifically to estimate 40

Hz ASSR as phase of higher frequency is more susceptible for distortion along the propagation

to the scalp. Emerging studies suggest possibility for the detection of sub-cortical sources by

restricting the source analysis to pre-defined areas and sometimes in addition to defining the

region of interest bigger than in its actual volume (Coffey et al., 2016; Farahani et al., 2021).

In the present study both of this methodology would be counter-intuitive as we didn't have a

priori assumptions about the locations of source-level network dynamics. Influence of sub-

cortical sources whole-brain network auditory processing could be potentially delineated by an

EEG-fMRI study in the future where source network locations over long-time scales can be

identified from BOLD activity and source-level EEG time series reconstructed from a filter,

receptive to thalamic signals.

6.　Conclusion

Comprehensive source-level network analysis provides a plausible explanation of hemispheric

asymmetry of 40 Hz ASSR during binaural and both monaural conditions. Right hemispheric

dominance emerges due to bidirectional flow between the right STG and right frontal area. In

contrast, idiosyncratic hemispheric asymmetry, departing from a contralateral dominance of

information processing, can be attributed to the strength of the interhemispheric causal flow of

information from left PAC to right STG. Overall, while the source location and direction of

information flow were the same across both monaural and binaural conditions, the differential

strength of activation underlies the entrainment of external environmental rhythms into

macroscopic neuroelectric signals.

Conflict of Interest Statement

The authors declare no conflicts of interest.

Acknowledgements

The study was supported by NBRC Core funds and by grants Ramalingaswami fellowship,

(BT/RLF/Re-entry/31/2011) and Innovative Young Bio-technologist Award (IYBA),

(BT/07/IYBA/2013) from the Department of Biotechnology (DBT), Ministry of Science and

Technology, Government of India to AB. AB also acknowledges the support of Centre of

Excellence in Epilepsy and MEG (BT/01/COE/09/08/2011) from DBT. DR was supported by

the Ramalingaswami fellowship (BT/RLF/Re-entry/07/2014) from DBT. We sincerely thank

late Dr. Jeffrey Michael Valla for his constructive comments on an earlier version of this

manuscript.

References

Albouy, P., Benjamin1, L., Morillon, B., & Zatorre, R. J. (2020). Distinct sensitivity to

spectrotemporal modulation supports brain asymmetry for speech and melody. Science,

367(6481), 1043–1047.

Attal, Y., Bhattacharjee, M., Yelnik, J., Cottereau, B., Lefèvre, J., Okada, Y., Bardinet, E.,

Chupin, M., & Baillet, S. (2007). Modeling and detecting deep brain activity with MEG

& EEG. Annual International Conference of the IEEE Engineering in Medicine and

Biology - Proceedings, 4937–4940.

Andoh, J., R. Matsushita, and R. J. Zatorre. 2015. "Asymmetric Interhemispheric Transfer in

the Auditory Network: Evidence from TMS, Resting-State FMRI, and Diffusion

Imaging." *Journal of Neuroscience* 35(43):14602–11.

Bohórquez, Jorge and Özcan Özdamar. 2008. "Generation of the 40-Hz Auditory Steady-State

Response (ASSR) Explained Using Convolution." *Clinical Neurophysiology*

119(11):2598–2607.

Bressler, S. L., & Menon, V. (2010). Large-scale brain networks in cognition: emerging

methods and principles. In Trends in Cognitive Sciences (Vol. 14, Issue 6, pp. 277–290)

Brovelli, A., M. Ding, A. Ledberg, Y. Chen, R. Nakamura, and S. L. Bressler. 2004. "Beta

Oscillations in a Large-Scale Sensorimotor Cortical Network: Directional Influences

Revealed by Granger Causality." *Proceedings of the National Academy of Sciences*

101(26):9849–54.

Cammoun, Leila, Jean Philippe Thiran, Alessandra Griffa, Reto Meuli, Patric Hagmann, and

Stephanie Clarke. 2015. "Intrahemispheric Cortico-Cortical Connections of the Human

Auditory Cortex." *Brain Structure and Function* 220(6):3537–53.

Cimenser, A., P. L. Purdon, E. T. Pierce, J. L. Walsh, A. F. Salazar-Gomez, P. G. Harrell, C.

Tavares-Stoeckel, K. Habeeb, and E. N. Brown. 2011. "Tracking Brain States under

General Anesthesia by Using Global Coherence Analysis." *Proceedings of the National Academy of Sciences* 108(21):8832–37.

Coffey, E. B. J., Herholz, S. C., Chepesiuk, A. M. P., Baillet, S., & Zatorre, R. J. (2016). Cortical contributions to the auditory frequency-following response revealed by MEG. Nature Communications, 7.

Das, M., Singh, V., Uddin, L. Q., Banerjee, A., & Roy, D. (2021). Reconfiguration of Directed Functional Connectivity Among Neurocognitive Networks with Aging: Considering the Role of Thalamo-Cortical Interactions. Cerebral Cortex, 31(4), 1970–1986.

Dhamala, M., G. Rangarajan, and M. Ding. 2008. "Analyzing Information Flow in Brain Networks with Nonparametric Granger Causality." *NeuroImage* 41(2):354–62.

Delorme, A., & Makeig, S. (2004). EEGLAB: An open source toolbox for analysis of single-trial EEG dynamics including independent component analysis. Journal of Neuroscience Methods, 134(1), 9–21.

Ding, M., Y. Chen, and S. L. Bressler. 2006. "Granger Causality: Basic Theory and Application to Neuroscience." *Handbook of Time Series Analysis: Recent Theoretical Developments and Applications* (February):437–60.

Fahimi Hnazaee, M., Wittevrongel, B., Khachatryan, E., Libert, A., Carrette, E., Dauwe, I., Meurs, A., Boon, P., Van Roost, D., & Van Hulle, M. M. (2020). Localization of deep brain activity with scalp and subdural EEG. NeuroImage, 223.

Farahani, E. D., Wouters, J., & van Wieringen, A. (2021). Brain mapping of auditory steady-state responses: A broad view of cortical and subcortical sources. Human Brain Mapping, 42(3), 780–796.

Farahani, E. D., Wouters, J., & van Wieringen, A. (2020). Neural Generators Underlying Temporal Envelope Processing Show Altered Responses and Hemispheric Asymmetry Across Age. Frontiers in Aging Neuroscience, 12, 431.

Fisher, N. I. (1995). Statistical analysis of circular data. Cambridge University Press.

Fonseca, L. C., Tedrus, G. M. a S., Rezende, A. L. R. a, & Giordano, H. F. (2015). Coherence

of brain electrical activity: a quality of life indicator in Alzheimer's disease? Arquivos de

Neuro-Psiquiatria, 73(5), 396–401.

Fries, P. (2005). A mechanism for cognitive dynamics: Neuronal communication through

neuronal coherence. Trends in Cognitive Sciences, 9(10), 474–480.

Friston, K. J. (2011). Functional and Effective Connectivity: A Review. Brain Connectivity,

1(1), 13–36.

Fuchs, M., Wagner, M., & Kastner, J. (2001). Boundary element method volume conductor

models for EEG source reconstruction. Clinical Neurophysiology, 112(8), 1400–1407.

Galambos, Robert, Scott Makeig, and Peter Talmachoff. 1981. "A 40-Hz Auditory Potential

Recorded from the Human Scalp." *Proceedings of the National Academy of Sciences of*

the United States of America 78(4):2643–47.

Geweke, John. 1982. "Measurement of Linear Dependence and Feedback between Multiple

Time Series." *Journal of the American Statistical Association* 77(378):304–13.

Granger, C. W. J. 1969. "Investigating Causal Relations by Econometric Models and Cross-

Spectral Methods." *Econometrica* 37(3):424.

Gutschalk, Alexander, Ryuzo Mase, Rainer Roth, Nicole Ille, André Rupp, Stefan Hähnel,

Terence W. Picton, and Michael Scherg. 1999. "Deconvolution of 40 Hz Steady-State

Fields Reveals Two Overlapping Source Activities of the Human Auditory Cortex."

Clinical Neurophysiology 110(5):856–68.

Hackett, Troy A. 2011. "Information Flow in the Auditory Cortical Network." *Hearing*

Research 271(1–2):133–46.

Hackett, T. A. (2015). Anatomic organization of the auditory cortex. In Handbook of Clinical

Neurology (Vol. 129, pp. 27–53)

Haghighi, S. J., Komeili, M., Hatzinakos, D., & Beheiry, H. El. (2018). 40-Hz ASSR for

Measuring Depth of Anaesthesia during Induction Phase. IEEE Journal of Biomedical and

Health Informatics, 22(6).

Halder, T., Talwar, S., Jaiswal, A. K., & Banerjee, A. (2019). Quantitative Evaluation in

Estimating Sources Underlying Brain Oscillations Using Current Source Density Methods

and Beamformer Approaches. *Eneuro*, *6*(4), ENEURO.0170-19.2019..

Hari, Riitta, Matti S. Hämäläinen, and S. L. Joutsiniemi. 1989. "Neuromagnetic Steady-State

Responses to Auditory Stimuli." *J Acoust Soc Am* 86(3):1033–39.

Herdman, A. T., O. Lins, P. Van Roon, D. R. Stapells, M. Scherg, and T. W. Picton. 2002.

"Intracerebral Sources of Human Auditory Steady-State Responses." *Brain Topography*

15(69–86).

Hoffmann, H. (2015). violin. m-Simple violin plot using matlab default kernel density

estimation. INRES (University of Bonn), Katzenburgweg, 5, 53115.

Kaas, J. H. and T. A. Hackett. 2000. "Subdivisions of Auditory Cortex and Processing Streams

in Primates." *Proceedings of the National Academy of Sciences* 97(22):11793–99.

Kaminski, M.J., Blinowska, K.J. A new method of the description of the information flow in

the brain structures. Biol. Cybern. 65, 203–210 (1991).

Kumar, G. Vinodh, Tamesh Halder, Amit K. Jaiswal, Abhishek Mukherjee, Dipanjan Roy, and

Arpan Banerjee. 2016. "Large Scale Functional Brain Networks Underlying Temporal

Integration of Audio-Visual Speech Perception: An EEG Study." *Frontiers in Psychology*

7(OCT):1558.

Kuwada, Shigeyuki, Ranjan Batra, and Virginia L. Maher. 1986. "Scalp Potentials of Normal

and Hearing-Impaired Subjects in Response to Sinusoidally Amplitude-Modulated

Tones." *Hearing Research* 21(2):179–92.

Langers, D. R. M., Van Dijk, P., & Backes, W. H. (2005). Lateralization, connectivity and

plasticity in the human central auditory system. NeuroImage, 28(2), 490–499

Lee, C. C. (2013). Thalamic and cortical pathways supporting auditory processing. Brain and

Language, 126(1), 22.

Linden, R. D., Terence W. Picton, G. Hamel, and K. B. Campbell. 1987. "Human Auditory

Steady-State Evoked Potentials during Selective Attention." *Electroencephalography and*

Clinical Neurophysiology 66(2):145–59.

Lithari, Chrysa, Carolina Sánchez-Garciá, Philipp Ruhnau, and Nathan Weisz. 2016. "Large-

Scale Network-Level Processes during Entrainment." *Brain Research* 1635:143–52.

Mäkelä, J. P. and R. Hari. 1987. "Evidence for Cortical Origin of the 40-Hz Auditory Evoked

Response in Man." *Electroencephalography and Clinical Neurophysiology* 66:539–46.

Maris, Eric, Jan Mathijs Schoffelen, and Pascal Fries. 2007. "Nonparametric Statistical Testing

of Coherence Differences." *Journal of Neuroscience Methods* 163(1):161–75.

Maris, E., & Oostenveld, R. (2007). Nonparametric statistical testing of EEG- and MEG-data.

Journal of Neuroscience Methods, 164(1), 177–190.

McFadden, K. L., Steinmetz, S. E., Carroll, A. M., Simon, S. T., Wallace, A., & Rojas, D. C.

(2014). Test-Retest Reliability of the 40 Hz EEG Auditory Steady-State Response. PLOS

ONE, 9(1), e85748

Melynyte, S., Pipinis, E., Genyte, V., Voicikas, A., Rihs, T., & Griskova-Bulanova, I. (2017).

40 Hz Auditory Steady-State Response: The Impact of Handedness and Gender. Brain

Topography, 31(3), 419–429.

Niepel, D., Krishna, B., Siegel, E. R., Draganova, R., Preissl, H., Govindan, R. B., & Eswaran,

H. (2020). A pilot study: Auditory steady-state responses (ASSR) can be measured in

human fetuses using fetal magnetoencephalography (fMEG). PLoS ONE, 15(7 July),

e0235310.

O'Donnell, Brian F., Jenifer L. Vohs, Giri P. Krishnan, Olga Rass, William P. Hetrick, and

Sandra L. Morzorati. 2013. "The Auditory Steady-State Response (ASSR): A Translational Biomarker for Schizophrenia." *Supplements to Clinical Neurophysiology* 62:101–12.

Oostenveld, Robert, Dick F. Stegeman, Peter Praamstra, and Adriaan van Oosterom. 2003. "Brain Symmetry and Topographic Analysis of Lateralized Event-Related Potentials." *Clinical Neurophysiology : Official Journal of the International Federation of Clinical Neurophysiology* 114(7):1194–1202.

Palva, J. M., Palva, S., & Kaila, K. (2005). Phase synchrony among neuronal oscillations in the human cortex. Journal of Neuroscience, 25(15), 3962–3972

Pantev, C., L. E. Roberts, T. Elbert, B. Ross, and C. Wienbruch. 1996. "Tonotopic Organization of the Sources of Human Auditory Steady-State Responses." *Hear Res* 101(1–2):62–74.

Pastor, Maria A., Julio Artieda, Javier Arbizu, Josep M. Marti-Climent, Ivan Peñuelas, and Jose C. Masdeu. 2002. "Activation of Human Cerebral and Cerebellar Cortex by Auditory Stimulation at 40 Hz." *The Journal of Neuroscience : The Official Journal of the Society for Neuroscience* 22(23):10501–6.

Plakke, Bethany and Lizabeth M. Romanski. 2014. "Auditory Connections and Functions of Prefrontal Cortex." *Frontiers in Neuroscience* (8 JUL).

Poelmans, Hanne, Heleen Luts, Maaike Vandermosten, Pol Ghesquière, and Jan Wouters. 2012. "Hemispheric Asymmetry of Auditory Steady-State Responses to Monaural and Diotic Stimulation." *JARO - Journal of the Association for Research in Otolaryngology* 13(6):867–76.

Reyes, Samuel A., Alan H. Lockwood, Richard J. Salvi, Mary Lou Coad, David S. Wack, and Robert F. Burkard. 2005. "Mapping the 40-Hz Auditory Steady-State Response Using Current Density Reconstructions." *Hearing Research* 204(1–2):1–15.

Reyes, Samuel A., Richard J. Salvi, Robert F. Burkard, Mary Lou Coad, David S. Wack, Paul

J. Galantowicz, and Alan H. Lockwood. 2004. "PET Imaging of the 40 Hz Auditory Steady State Response." *Hearing Research* 194(1–2):73–80.

Ross, B., A. T. Herdman, and C. Pantev. 2005. "Right Hemispheric Laterality of Human 40 Hz Auditory Steady-State Responses." *Cerebral Cortex* 15(12):2029–39.

Ross, Bernhard, Terence W. Picton, and Christo Pantev. 2002. "Temporal Integration in the Human Auditory Cortex as Represented by the Development of the Steady-State Magnetic Field." *Hearing Research* 165(1–2):68–84.

Rolls, E. T., Joliot, M., & Tzourio-Mazoyer, N. (2015). Implementation of a new parcellation of the orbitofrontal cortex in the automated anatomical labeling atlas. NeuroImage, 122, 1–5.

Toga, A. W., & Thompson, P. M. (2003). Mapping brain asymmetry. Nat Rev Neurosci, 4(1), 37–48. https://doi.org/10.1038/nrn1009Toga, A. W., & Thompson, P. M. (2003). Mapping brain asymmetry. Nat Rev Neurosci, 4(1), 37–48.

Wang, Liping, Lynn Uhrig, Bechir Jarraya, and Stanislas Dehaene. 2015. "Representation of Numerical and Sequential Patterns in Macaque and Human Brains." *Current Biology* 25(15):1966–74.

Ying J, Zhou D, Lin K, Gao X. Network Analysis of Functional Brain Connectivity Driven by Gamma-Band Auditory Steady-State Response in Auditory Hallucinations. J Med Biol Eng. 2015;35(1):45-51. doi: 10.1007/s40846-015-0004-0.

Zaidel, E., & Iacoboni, M. (Eds.). (2003). The parallel brain: The cognitive neuroscience of the corpus callosum. MIT Press.

Zatorre, R. J. and P. Belin. 2001. "Spectral and Temporal Processing in Human Auditory Cortex." *Cerebral Cortex (New York, N.Y. : 1991)* 11(10):946–53.

Zatorre, Robert J., Pascal Belin, and Virginia B. Penhune. 2002. "Structure and Function of Auditory Cortex: Music and Speech." *Trends in Cognitive Sciences* 6(1):37–46.

Zatorre, Robert J. and Jackson T. Gandour. 2008. "Neural Specializations for Speech and Pitch:

Moving beyond the Dichotomies." *Philosophical Transactions of the Royal Society B:*

Biological Sciences 363(1493):1087–1104.

Zhang, Li, Weiwei Peng, Zhiguo Zhang, and Li Hu. 2013. "Distinct Features of Auditory

Steady-State Responses as Compared to Transient Event-Related Potentials." *PLoS ONE*

8(7).

Figure Captions

Figure 1: Steady-state response: (A) Group-level ERPs of mastoid channels (M1 as red and M2 as sky-blue) having oscillatory response in the time window of 250 to 1000 ms relative to the onset of periodic auditory stimuli. **(B)** ITPC of single channel during auditory stimulation conditions showed maximum ITPC at 40 Hz compared with same channel during baseline (silent) condition as black line. **(C)** Phase-angle distribution at 40 Hz during auditory stimulation and baseline conditions. The arrow in the middle of each circle represents strength of ITPC.

Figure 2: Spectral power and hemispheric asymmetry: (A) Group-level power spectrum showing sharp enhancement of spectral power at 40 Hz during monaural left (magenta), monaural right (green), binaural stimuli (blue) relative to baseline (black) condition. **(B)** Group-level hemispheric laterality indices (LI) distribution for 40 Hz spectral power during different stimulus conditions. The central node in each line represents mean of data while lower and upper boundary of the line represents the lower and upper limit of 95% confidence interval, respectively.

Figure 3: Sources of 40 Hz ASSRs: source power rendered over cortical surface derived from Colin27 brain.

Figure 4: Presence of large-scale network among ASSRs: Enhancement in global coherence during auditory conditions was measured by z-statistic representing the normalized difference of coherence in task conditions relative the baseline condition.

Figure 5: Directionality among recruited sub-networks: Left panel: heatmaps depicting

pairwise GC values among ASSRs sources. 1^{st} and 4^{th} quadrant compose of GC pairs within

right and left hemisphere, respectively. 2^{nd} and 3^{rd} quadrant depict respective interhemispheric

GC flows. Significant GC values ($p > 0.01$) tested against surrogate data using a permutation-

based non-parametric statistical test, were bordered by blue boxes. Schematic representation

of frequency specific directed interactions that underlie 40 Hz ASSRs. Each black arrow

represents a causal flow among brain regions denoted by blue nodes.

Figure 6: Interhemispheric causal flow: Variability in the GC strengths from left primary

auditory cortex to the right STG during different auditory conditions.

Figure 1

A

B

C

| Binaural | Monaural left | Monaural right | Baseline |

Figure 2

Figure 3

A Binaural

B Monaural left

C Monaural right

A Binaural

B Monaural left

C Monaural right