Degeneracy in negative feedback (NFBL) and incoherent feedforward (IFFL) loops: Adaptation and resonance

Alejandra C. Ventura [1,2] *, Horacio G. Rotstein [3] †

[1] Departamento de Física
Facultad de Ciencias Exactas y Naturales
[2] Instituto de Fisiología, Biología Molecular Y Neurosciencias
Consejo Nacional de Investigaciones Científicas y Técnicas (CONICET)
Universidad de Buenos Aires
Ciudad Universitaria, 1428, Buenos Aires, Argentina
[3] Federated Department of Biological Sciences,
New Jersey Institute of Technology & Rutgers University,
Newark, NJ 07102, USA.

August 12, 2023

Abstract

Degeneracy in dynamic models refers to these situations where multiple combinations of parameter values produce identical patterns for the observable variable. In this paper we investigate the presence of degeneracy and the biological and dynamic mechanism that give rise to ti in adaptive and resonant/phasonant patterns generated by two qualitatively different circuit mechanisms: non-linear feedback loop (NFBL) and incoherent feedback loop (IFFL). We use minimal models of these circuit types together with analytical calculations, regular perturbation analysis, phase-plane analysis and numerical simulations. We identify the principles underlying the emergence of degeneracy in NFBLs and IFFLs and the the persistence of the degeneracy structure in the response of these adaptive systems to oscillatory inputs at arbitrary frequencies. Our results have implication for the understanding of adaptive systems and for the development of methods for circuit and dynamical systems reconstruction based on experimental or observational data.

1   Introduction

The study of adaptive responses to constant or step-constant inputs (Fig. 1-B, top) has been the focus of several studies in Systems Biology [1–6]. These patterns consists of an overshoot type of response, where the observable variable first increases and then decays towards a steady-state value (Fig. 1-C) [1]. We refer to these patterns as adaptive patterns and to the systems that produce them as adaptive systems.

---

*alejvent@fbmc.fcen.uba.ar
†horacio@njit.edu

Biologically, the generation of adaptive patterns is determined by the interplay of the input and the system's properties. From the dynamical systems point of view, the generation of adaptive patterns requires two-dimensional systems where the activity of an observable state variable is controlled or modulated by second, possibly hidden state variable. From the circuits point of view, the two variables can be embedded in a single node or in different nodes, depending on the biological context and conceptual framework. Two minimal two-node circuit architectures have been identified as being able to produce adaptive behavior (Fig. 1-A) [3]: the negative feedback loop (NFBL, $\xi = 0$) and the incoherent feedforward loop (IFFL, $k_3 = 0$). Adaptive patterns are the result of network regulation (processing) in NFBLs, while they are orchestrated by the input in IFFLs. Specifically, in the NFBL ($\xi = 0$), the activator variable (x) receives the input (amplitude A_c) and activates the inhibitor variable (y), which in turn inhibits x. In the IFFL ($k_3 = 0$), in contrast, both the activator (x) and inhibitor (y) receive the inputs with an amplitude ratio equal to ξ and y inhibits x, but y is not activated x. In all both cases, the observable variable is x. These circuits have been associated to the processing of temporal information and related regulatory functions in a number of systems [7–12] (IFFL) and [13–19] (NFBL).

Dynamically, the generation of adaptive patterns in NFBLs and IFFLs requires that the observable evolves faster than the inhibitor so that the former can grow before being forced by the latter to turn around and decrease. These time scales, and the resulting properties of the adaptation peak, are determined by the combined effect of the model parameters and may differ for comparable NFBLs and IFFLs, having identical parameter values except for these defining the type of circuit, ξ and k_3. On the other hand, because balances between the activation and inhibition processes are expected, the question arises of whether NFBLs and IFFLs can produce identical adaptive patterns for multiple combinations of model parameters, thus giving rise to degeneracy [20, 21] both within and across circuit types. This in turn raises the question of whether and how the circuit properties can be inferred from the observable data and, in particular, under what conditions it is possible to distinguish between NFBLs and IFFLs from experimental or observational available data. Despite the pervasive presence of adaptive patterns in biological and related systems, these mechanistic issues are not well understood.

In this paper we systematically address these questions in minimal models of NFBLs and IFFLs. The dynamics of the nodes are assumed to be relatively simple: they are unidimensional and exhibit linear decay representing self-regulation (rates k_1 and k_4 in Fig. 1-A). We use linear and nonlinear models. Linear models are mathematically tractable and therefore allow us to gain intuition. The nonlinearities arise from the properties of the connectivity. We consider two types of nonlinearities: multiplicative, based on the law of mass action [22–24], and divisive (of sigmoidal type), based on the Michaelis-Menten formulation [25]. They are representative of the two ways inhibition can affect the rate of change of the observable variable. In the context of the diagram in Fig. 1-A, increasing values of the inhibitory variable (y) causes an increase of the negative contribution (negative term) to the rate of change of x in the multiplicative case and a decrease of the positive contribution (positive term) to the rate of change of x in the second case. We analyze the nonlinear models by using dynamical systems tools (comparative phase-plane analysis). An important result of this analysis is that the mechanisms of generation of degeneracy in the linear and nonlinear models comparable models (e.g., linear and nonlinear models of the same circuit types such as two NFBLs, two IFFLs, or one NFBL and one IFFL) are qualitatively similar.

Previous work by other authors [26] has focused on the discrimination between NFBLs and IFFLs, for example, by analyzing and comparing the circuits response to time-dependent signals such as periodic signals [4,27] and ramps [28] or used stochastic models [29]. However, none of these approaches considered the presence of degeneracy in adaptive systems and the resulting adaptive patterns.

Common to these approaches is the use of time-dependent external signals, which can be captured by the circuits' impedance amplitude and phase profiles in response to oscillatory inputs. Previous work has shown that adaptive systems can produce resonance (band-pass filters) (Fig. 1-D1) and phasonance (Fig. 1-D2) in the observable variable in response to oscillatory inputs [30–33] (see also [34–36]). Resonance is defined as the ability of a system to exhibit a peak in the amplitude response to oscillatory inputs at a preferred (resonant) non-zero input frequency. Phasonance is defined as the ability of a system to exhibit a zero-phase (phase-shift) response to oscillatory inputs at a preferred (phasonant) input frequency. Mechanistically, while resonance and phasonance have been observed in adaptive systems, it is not clear what aspects of adaptation control the generation of resonance and phasonance in NFBLs and IFFLs, and whether the generation of these patterns depend on the same balances that give rise to the corresponding adaptive patterns. The question arises of whether the degeneracy present in adaptive systems in inherited to their responses to oscillatory inputs. Whether and how resonant and phasonant patterns in NFBLs and IFFLs exhibit degeneracy has consequences for the ability of time-dependent inputs both deterministic and stochastic (e.g., Gaussian white noise) to be appropriate input signals to resolve degeneracy within and across NFBLs and IFFLs.

By including the relevant ingredients of NFBLs and IFFLs, the minimal models we use achieve a healthy balance between tractability and complexity that allows to identify the different types of degeneracy in response to constant and oscillatory inputs, identify the basic principles that govern the generation of degeneracy and related phenomena in NFBLs and IFFLs in response to both constant and time-dependent inputs, and understand the similarities and differences between the degenerate patterns observed in the two circuit types. Our results shed light on the mechanisms of generation of degeneracy in more complex NFBLs and IFFLs and have implications for the identification and development of the appropriate tools to differentiate between circuit types in the presence of degeneracy based on experimental or observational data. Additionally, the tools we use in this paper can be extended to the analysis of more complex models of NFBLs and IFFLs. We illustrate this by extending our work to include neuronal rate models describing the evolution of the instantaneous firing rates of excitatory and inhibitory networks [37–41].

2 Methods

2.1 Models of NFBL and IFFL circuits

2.1.1 Linear NFBL and IFFL circuits

The linear NFBL and IFFL circuits (Fig. 1-A) are described by the following system

$$\frac{dx}{dt} = -k_1 x - k_2 y + A_c + A_s \sin(2\pi\omega t), \qquad x(0) = x_0, \tag{1}$$

$$\frac{dy}{dt} = k_3 x - k_4 y + \xi A_c + \xi A_s \sin(2\pi\omega t), \qquad y(0) = y_0, \tag{2}$$

where x represents the observable, y represents the inhibitor, k_1, k_2, k_3, k_4, A_c, A_s, ω, ξ, x_0 and y_0 are non-negative constants. For the NFBL, $\xi = 0$, while for the IFFL, $k_3 = 0$.

Figure 1: **Negative feedback loop (NFBL) and incoherent feedforward loop (IFFL) schematic diagram**. **A.** Combined NFBL and IFFL circuit. The circuit represents a NFBL for $\xi = 0$ and a IFFL for $k_3 = 0$. The input arrives into the nodes X (with strength given by I) and Y (with strength given by $\xi\,I$). The node X activates the node Y (rate constant k_3), which in turn inhibits the node X (rate constant k_2). Both nodes exhibit self-regulation decay (linear decay rate constants k_1 and k_4). The output is measured in the node X. **B.** Representative input functions. Top: step-constant input function with amplitude A_c. The jump occurs at $t = t_0$. Bottom: sinusoidal input function with amplitude A_s and frequency ω. **C.** Representative response patterns of the observable variable X to a step-constant input I (light gray). **C1.** Representative adaptive pattern. In response to the abrupt change in I from $I = 0$ to $I = A_c$, X first increases, reaches a peak x_{peak} at $t = t_{peak}$, and then decreases towards a steady-state value $\bar{X}$. The three attributes of the response pattern are $\bar{X}$ and the two time constants τ_1 and τ_2. **C2.** Representative damped oscillatory pattern. The three attributes of the response pattern are $\bar{X}$, the frequency ω and the envelope time constant τ. **D.** Representative resonant (D1) and phasonant (D1) response profiles to oscillatory inputs. **D1.** Normalized amplitude response Z defined as the quotient of the steady state output amplitude and the input amplitude A_s. The resonant frequency f_{res} is the input frequency at which Z peaks. **D2.** Phase (-shift) response Φ defined as difference between the peaks of the steady-state output amplitude and the input amplitude normalized by the period. The phasonant frequency f_{phas} is the (non-zero) input frequency at which $\Phi = 0$.

2.1.2 Nonlinear NFBL and IFFL circuits

We consider models with two types of nonlinearities in the inhibitory connectivity: multiplicative and divisive. The general formulation is given by

$$\frac{dx}{dt} = -k_1 x + \Gamma(x, k_2\, y, I) \qquad\qquad x(0) = x_0, \tag{3}$$

$$\frac{dy}{dt} = k_3 x - k_4 y + \xi I(t), \qquad\qquad y(0) = y_0, \tag{4}$$

where

$$I(t) = A_c + A_s \frac{\sin(2\pi f t) + 1}{2} \tag{5}$$

and all the parameters are as for the linear models in Section 2.1.1.

The multiplicative nonlinearity is based on the law of mass action [22–24]

$$\Gamma(x, k_2\, y, I) = -k_2\, y\, x + I(t). \tag{6}$$

It produces a multiplicative interaction between the observable and the inhibitor. Increasing levels of y increases the negative contribution of the nonlinear term to the rate of change of x.

The divisive nonlinearity is based on the Michaelis-Menten formulation [25] (see also [42] for covalent modification cycles). We consider two different forms, which differ on the location of the input signal

$$\Gamma(x, k_2\, y, I) = \frac{1}{1 + k_2\, y} + I(t) \tag{7}$$

and

$$\Gamma(x, k_2 y, I) = \frac{I(t)}{1 + k_2\, y}. \tag{8}$$

In both cases, increasing levels of levels of y decreases the positive contribution of the nonlinear term to the rate of change of x.

2.2 Model attributes and observable attributes: The linear case

Consider the following generic system

$$\frac{dx}{dt} = a\, x + b\, y + A + F(t), \qquad\qquad x(0) = x_0, \tag{9}$$

$$\frac{dy}{dt} = c\, x + d\, y + \xi A + G(t), \qquad\qquad y(0) = y_0. \tag{10}$$

The model parameters a, b, c, d, ξ and A are assumed to be constant. For this system to represent the NFBL or the IFFL, $a < 0$, $b < 0$, $c \geq 0$, $d < 0$ and $\xi \geq 0$. Additionally, for the NFBL, $\xi = 0$, while for the IFFL, $c = 0$.

2.2.1 Reduction to a second order linear ODE

System (9)-(10) can be rewritten as a linear second order ODE in terms of the variable x

$$\frac{d^2x}{dt} + B\frac{dx}{dt} + Cx = QA - dF(t) + bG(t) + F'(t), \tag{11}$$

and as a linear second order ODE in terms of the variable y

$$\frac{d^2y}{dt} + B\frac{dy}{dt} + Cy = PA + cF(t) - aG(t) + G'(t), \tag{12}$$

where the model attributes are given by

$$B = -(a+d), \qquad C = ad - bc, \qquad Q = -(d-b\xi) \quad \text{and} \quad P = (c-a\xi). \tag{13}$$

We refer to the reduced parameters in (13) as model attributes to differentiate them from the model parameters in System (9)-(10). In eq. (11), the initial conditions are $x(0) = x_0$ and $dx/dt(0) = ax_0 + by_0 + A + F(0)$. In eq. (12), the initial conditions are $y(0) = y_0$ and $dy/dt(0) = cx_0 + dy_0 + \xi A + G(0)$.

2.2.2 Observable attributes for a second order linear ordinary differential equation

Consider the following general form of a 2D linear system written as a second order linear ODE

$$\frac{d^2X}{dt} + B\frac{dX}{dt} + CX = QA, \qquad X(0) = X_0, \ \frac{dX}{dt}(0) = X_0' \tag{14}$$

where B, C, A, X_0 and X_0' are constants.

Solutions to two-dimensional ODEs are characterized by three obsevable attributes (in addition to the initial conditions) that can be extracted from the response patterns to the constant input A. One of them is the steady-state

$$\bar{X} = \frac{Q}{C}A, \tag{15}$$

which is assumed to be stable. If the solution is evolves monotonically or exhibits and overshoot [1], the other two attributes are the time constants

$$\tau_{1,2}^{-1} = -\lambda_{1,2} = r_{1,2} = \frac{-B \pm \sqrt{B^2 - 4C}}{2}. \tag{16}$$

In this case, the eigenvalues $r_{1,2}$ are real and negative. (Overshoots are often refer to as sags if the solution first decreases and then increases.). If, instead, the solution exhibits damped oscillations [2] ($r_{1,2}$ are complex with non-zero imaginary part), the two attributes are frequency

$$\omega = \frac{\sqrt{4C - B^2}}{2} \tag{17}$$

and the oscillations envelope time constant

---

[1] e.g.., see [43], Figs. A1-B1 and A1-B3, Appendix
[2] e.g., see [43], Fig. A1-B2, Appendix

$$\tau = -\frac{2}{B}. \tag{18}$$

We refer to them as observable attributes to differentiate them from the model attributes (B, C and Q).

We note that these are not the only possible set of attributes that can be extracted from the response patterns (e.g., the time constants $\tau_{1,2}$ can be substituted by the peak and peak time if the solution exhibits an overshoot), but the total number of attributes that completely determine the solution X is three. We also note that when the time constants are not different enough (the time scales are not well separated) two attributes are enough to approximately describe the solution.

2.2.3 Recovery of the model attributes from the observable attributes

In all cases, the three model attributes (B, C and Q) can be uniquely computed from the response pattern attributes ($\bar{X}$, $\tau_{1,2}$, or, alternatively, $\bar{X}$, τ and ω).

Specifically for adaptive patterns, if one has access to the eigenvalues λ_1 and λ_2 in addition to the steady state $\bar{X}$, then

$$B = -(r_1 + r_2) \qquad C = r_1 \, r_2 \qquad \text{and} \qquad Q = \frac{\bar{X} \, C}{A}. \tag{19}$$

From 13, for the NFBL,

$$a = Q - B, \qquad d = -Q \qquad \text{and} \qquad b \, c = Q \, (B - Q) - C. \tag{20}$$

For the IFFL,

$$a = \frac{-B \pm \sqrt{B^2 - 4\,C}}{2}, \qquad d = \frac{2\,C}{-B \pm \sqrt{B^2 - 4\,C}} \qquad \text{and} \qquad b\,\xi = Q + \frac{2\,C}{-B \pm \sqrt{B^2 - 4\,C}}. \tag{21}$$

Note that

$$a = r_{1,2}, \qquad d = \frac{C}{r_{1,2}} \qquad \text{and} \qquad b\,\xi = Q + \frac{C}{r_{1,2}} \tag{22}$$

2.3 Non-oscillatory solutions to second order linear ODEs

The non-oscillatory solutions to eq. (11) for $x(0) = 0$ and $x'(0) = \eta > 0$ is given by

$$x(t) = C_1 \, e^{-\lambda_1 \, t} - C_2 \, e^{-\lambda_2 \, t} + \bar{x} \tag{23}$$

where $\lambda_{1,2} = -r_{1,2}$ (16) and

$$C_1 = \frac{\eta - \lambda_2 \, \bar{x}}{\lambda_2 - \lambda_1} \qquad \text{and} \qquad C_2 = \frac{\eta - \lambda_1 \, \bar{x}}{\lambda_2 - \lambda_1}. \tag{24}$$

If the solution $x(t)$ has an overshoot, then the peak time and peak value are given by

$$t_{peak} = \frac{1}{\lambda_2 - \lambda_1} \, \ln \left(\frac{C_2 \, \lambda_2}{C_1 \, \lambda_1} \right) = \frac{1}{\lambda_2 - \lambda_1} \, \ln \left(\frac{(\eta_x - \lambda_1 \, \bar{x}) \, \lambda_2}{(\eta_x - \lambda_2 \, \bar{x}) \, \lambda_1} \right) \tag{25}$$

and $x_{peak} = x(t_{peak})$, respectively.

The corresponding solution to eq. (12) for $y(0) = 0$ and $y'(0) = \eta > 0$ is given by

$$y(t) = C_1 \, e^{-\lambda_1 t} - C_2 \, e^{-\lambda_2 t} + \bar{y} \tag{26}$$

where

$$\bar{y} = \frac{P}{C} \, A \tag{27}$$

and

$$C_1 = \frac{\eta - \lambda_2 \, \bar{y}}{\lambda_2 - \lambda_1} \qquad \text{and} \qquad C_2 = \frac{\eta - \lambda_1 \, \bar{y}}{\lambda_2 - \lambda_1}. \tag{28}$$

2.4   Response of two-dimensional linear systems to oscillatory inputs

The response of a two-dimensional system to oscillatory inputs can be characterized by the impedance amplitude (Z) and phase (Φ) profiles. These are curves of the impedance amplitude (illustrated in Fig. 1-D1) and phase-shift (illustrated in Fig. 1-D2) as a function of the input frequency. For linear systems, the input and output frequencies coincide. For the nonlinear models we consider in this paper, the number of input and output cycles coincide and the response amplitude is uniform across cycles for a given input frequency (assuming steady-state).

The quantities Z and Φ are the real and imaginary parts of the complex impedance $\mathbf{Z}$, defined as the quotient of the Fourier transforms of the output and input signals. For linear systems, Z and Φ can be computed analytically. For the nonlinear models we use in this paper, we use a generalization of the impedance for linear system [33].

The notion of impedance is borrowed from the field of electric circuits. While the interpretation of the responses of biological and electric systems to oscillatory signals is inherently different, we use the same terminology for convenience.

2.4.1   Linear systems: Impedance amplitude and phase profiles

We consider the two-dimensional linear system described by eqs. (9)-(10) in Section 2.2 with

$$F(t) = A_\omega \, e^{i\omega t} \qquad \text{and} \qquad G(t) = B_\omega \, e^{i\omega t}. \tag{29}$$

The stationary solution of system (9)-(10) is given by

$$x(t) = \mathbf{A_0}(\omega) \, e^{i\omega t} \qquad \text{and} \qquad y(t) = \mathbf{B_0}(\omega) \, e^{i\omega t}. \tag{30}$$

with

$$\mathbf{A_0}(\omega) = \frac{(-d + i \, \omega) \, A_\omega + b \, B_\omega}{a \, d - b \, c - \omega^2 - i \, (a + d) \, \omega} \qquad \text{and} \qquad \mathbf{B_0}(\omega) = \frac{c \, A_\omega - (a - i \, \omega) \, B_\omega}{a \, d - b \, c - \omega^2 - i \, (a + d) \, \omega}. \tag{31}$$

We express the input amplitudes in terms of a common parameter A_{in}

$$A_\omega = \xi_x \, A_{in} \qquad \text{and} \qquad B_\omega = \xi_y \, A_{in} \tag{32}$$

This allows us to consider inputs to only one node in the network ($\xi_x = 0$ or $\xi_y = 0$) or to both (for the NBFL-IFFL, $\xi_x = 1$ and $\xi_y = \xi$). By substituting into (31), after some algebra one obtains

$$\mathbf{A_0}(\omega) = \frac{-(d\,\xi_x - b\,\xi_y) + i\,\omega\,\xi_x}{a\,d - b\,c - \omega^2 - i\,(a+d)\,\omega}\,A_{in} \qquad \text{and} \qquad \mathbf{B_0}(\omega) = \frac{c\,\xi_x - a\,\xi_y + i\,\omega\,\xi_y}{a\,d - b\,c - \omega^2 - i\,(a+d)\,\omega}\,A_{in}. \tag{33}$$

By analogy with electric circuits, we define the impedances

$$\mathbf{Z_x}(\omega) = \frac{\mathbf{A_0}(\omega)}{A_{in}} \qquad \text{and} \qquad \mathbf{Z_y}(\omega) = \frac{\mathbf{B_0}(\omega)}{A_{in}}. \tag{34}$$

The impedance amplitudes are given by

$$Z_x^2(\omega) = \frac{(d\,\xi_x - b\,\xi_y)^2 + \omega^2\,\xi_x^2}{(a\,d - b\,c - \omega^2)^2 + (a+d)^2\,\omega^2} \tag{35}$$

and

$$Z_y^2(\omega) = \frac{(c\,\xi_x - a\,\xi_y)^2 + \omega^2\,\xi_y^2}{(a\,d - b\,c - \omega^2)^2 + (a+d)^2\,\omega^2}. \tag{36}$$

The impedance phases (phase-shift) are given by

$$\Phi_1(\omega) = \tan^{-1}\frac{\xi_x\,(a\,d - b\,c - \omega^2) - (d\,\xi_x - b\,\xi_y)\,(a+d)}{(d\,\xi_x - b\,\xi_y)\,(a\,d - b\,c - \omega^2) + \omega^2\,(a+d)\,\xi_x}\,\omega \tag{37}$$

$$\Phi_1(\omega) = \tan^{-1}\frac{(c\,\xi_x - a\,\xi_y)\,(a+d) + \xi_y\,(a\,d - b\,c - \omega^2)}{-(c\,\xi_x - a\,\xi_y)\,(a\,d - b\,c - \omega^2) + \omega^2\,(a+d)\,\xi_y}\,\omega \tag{38}$$

2.4.2 Response of two-dimensional nonlinear systems to oscillatory inputs: Impedance amplitude and phase profiles

We extend the notion of Z and Φ to characterize the response of the observable variable X in a nonlinear system receiving an oscillatory input of the form (5). Following [33], we define

$$Z(f) = \frac{X_{max}(f) - X_{min}(f)}{2\,A_{in}} \qquad \text{and} \qquad \Phi(f) = \frac{t_{peak,out}(f) - t_{peak,in}(f)}{T_{per}(f)}, \tag{39}$$

where $X_{max}(f)$ and $X_{min}(f)$ are the maximum and minimum of the (stationary) oscillatory response, respectively, $t_{peak,in}(f)$ and $t_{peak,out}(f)$ are the peak times of the input and output signals, respectively, and $T_{per}(f)$ is the oscillation period.

The two quantities in (39) generalize the notion of impedance for linear systems described above under the assumption that the number of input and output cycles per unit of time coincides and the output voltage waveforms for each each input frequency are identical across cycles (assuming steady state). This is the case for linear models and a number of nonlinear models [32, 33, 44, 45]. We note that the nonlinearities are expected to affect the response waveforms as compared to the analogous responses of linear systems and the waveforms may significantly differ across frequencies.

3 Results

3.1 Degeneracy within and across circuit types in linear NFBLs and IFFLs in response to constant inputs

System (1)-(2) with $A_s = 0$ can be rewritten as a linear second order ODE in terms of the variable x

$$\frac{d^2x}{dt} + B\frac{dx}{dt} + Cx = QA_c, \tag{40}$$

with initial conditions $x(0) = x_0$ and $dx/dt(0) = -k_1 x_0 - k_2 y_0 + A_c$, where

$$B = k_1 + k_4, \qquad C = k_1 k_4 + k_2 k_3 \qquad \text{and} \qquad Q = (k_4 - k_2 \xi). \tag{41}$$

For a given set of initial conditions, the response patterns to constant (or step-constant) inputs (A_c) for the observable variable x in linear systems of ODEs are completely determined by the steady-state

$$\bar{x} = \frac{Q}{C} A_c \tag{42}$$

and two other response attributes: the two time constants

$$\tau_{1,2} = \frac{2}{-B \pm \sqrt{B^2 - 4C}}, \tag{43}$$

if the response is adaptive (Fig. 1-C1), or the frequency and the oscillations envelope time constant

$$\omega = \frac{\sqrt{4C - B^2}}{2} \qquad \text{and} \qquad \tau = -\frac{2}{B}, \tag{44}$$

respectively, if the response is oscillatory (Fig. 1-C2). These three response attributes uniquely determine the parameters B, C and Q (see Section 2.2.2) , which we refer to as the model attributes here to differentiate them from the model parameters in the original system (1)-(2). Response patters having the same model or response attributes for the same value of A_c are identical. Therefore, if one only has access to the observable variable x the solutions are degenerate. We note that the IFFL circuit cannot produce intrinsic oscillations.

For the NFBL ($\xi = 0$),

$$B = k_1 + k_4, \qquad C = k_1 k_4 + k_2 k_3, \qquad \text{and} \qquad Q = k_4, \tag{45}$$

whereas for the IFFL ($k_3 = 0$),

$$B = K_1 + K_4, \qquad C = K_1 K_4, \qquad \text{and} \qquad Q = K_4 - K_2 \xi. \tag{46}$$

We use capital letters for the rate constants in the IFFL to indicate that the model parameters in the NFBL and IFFL models for which the model attributes (B, C and Q) are the same, have not necessarily the same values.

3.1.1 Degeneracy within circuit types

For the NFBL, from (45), k_1 and k_4 are uniquely determined by B and Q. The intra-circuit NFBL degeneracy is given by the multiple combinations of k_2 and k_3 that can produce

$$k_2\,k_3 = C - k_1\,k_4 = C - (B - Q)\,Q. \tag{47}$$

We illustrate this in Fig. 7-A.

For the IFFL, from (46), K_1 and K_4 are uniquely determined by B and C. The intra-circuit IFFL degeneracy is given by the multiple combinations of K_2 and ξ that can produce

$$K_2\,\xi = K_4 - Q = \frac{B \pm \sqrt{B^2 - 4C}}{2} - Q. \tag{48}$$

We illustrate this in Fig. 7-B.

Degeneracy in both circuit types reflects the multiple possible balances between the activation of y (k_3 or ξ) and the inhibition y exerts on x (k_2). There are other possible balances in both circuit types, but they will affect the shape of the response and therefore not result in degeneracy (Fig. 7-D). For example, one can find multiple combinations of parameter values, other than exclusively the degenerate ones mentioned above, that keep $\bar{x}$ constant. Since this will necessarily require different values of B, then it will also require different values of the other two attributes (43) or (44). Therefore, degeneracy is a special class of balance.

3.1.2 Degeneracy between circuit types

The cross-circuit degeneracy between the NFBLs and IFFLs follows from our discussion above. In practice, we first fix the parameters of the NFBL model and determine the values of B, C and Q from eqs. (45). Then, we find the values of the parameters of the IFFL model from eqs. (46). Alternatively, we fix the parameters of the IFFL model and the values of B, C and Q from eqs. (46). Then, we find the values of the parameters of the IFFL model from eqs. (45). We illustrate this in Fig. 7-C.

3.1.3 Linear IFFLs, but not NFBL can achieve perfect adaptation

Perfect adaptation refers to the scenarios where the response pattern to a step-constant input returns to its baseline value prior to the arrival of the signal. For system (1)-(2), this happens when $\bar{x} = x_0$. Without loss of generality, we take $x_0 = 0$.

In the absence of inhibition, the observable (x) for the isolated node (X) monotonically increases towards $\bar{x} = A_c/k_1 > 0$. Inhibition creates the overshoot and may cause $\bar{x}$ to decrease. From (41) and (42), for the IFFL perfect adaptation occurs when $k_4 = k_2\,\xi$. In other words, perfect adaptation is possible because of the orchestration of inhibition by the input signal in IFFLs. In contrast, for the NFBL, perfect adaptation is not possible. The steady-state $\bar{x}$ can at most approach to zero as the denominator increases, but it never reaches zero for finite parameter values. We note that for the linear IFFL $\bar{x}$ can become negative, posing a limitation to the validity of the model.

3.1.4 Degeneracy in the observable variable does not imply degeneracy in the hidden variable

System (1)-(2) with $A_s = 0$ can be rewritten as a linear second order ODE in terms of the variable y

Figure 2: **Degeneracy within and across circuit types: representative examples of adaptive responses (to a constant input).** We used System (1)-(2) with $A_c = 1$, $A_s = 0$, $x(0) = 0$ and $y(0) = 0$. **A.** Degeneracy within NFBLs. Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$ (blue), $k_1 = 1$, $k_2 = 1$, $k_3 = 0.1$, $k_4 = 0.05$ (dashed-red). **B.** Degeneracy within NFBLs. Parameter values: $K_1 = 1$, $K_2 = 2$, $\xi = 0.015$, $K_4 = 0.05$ (blue), $K_1 = 1$, $K_2 = 1$, $\xi = 0.03$, $K_4 = 0.05$ (dashed-red). **C.** Degeneracy across NFBL and IFFL. Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$ (C1, blue), $K_1 = 0.8794$, $K_2 = 1.2056$, $\xi = 0.1$, $K_4 = 0.1706$ (C1, dashed-red), $K_1 = 1$, $K_2 = 2$, $\xi = 0.015$, $K_4 = 0.05$ (C2, blue), $k_1 = 1.03$, $k_2 = 0.588$, $k_3 = 0.05$, $k_4 = 0.02$ (C2, dashed-red). **D.** Balance, but not degeneracy within circuit types. Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$ (D1, blue), $k_1 = 1.2$, $k_2 = 1.8$, $k_3 = 0.05$, $k_4 = 0.05$ (D1, dashed-red), $K_1 = 1$, $K_2 = 2$, $\xi = 0.015$, $K_4 = 0.05$ (D2, blue), $K_1 = 1.15$, $K_2 = 1.8$, $\xi = 0.015$, $K_4 = 0.05$ (D2, dashed-red).

$$\frac{d^2 y}{dt} + B \frac{dy}{dt} + C \, y = P \, A_c, \tag{49}$$

with initial conditions $y(0) = y_0$ and $dy/dt(0) = c \, x_0 + d \, y_0 + \xi \, A_c$, where B and C are given by (41) and

$$P = (k_3 + k_1 \, \xi). \tag{50}$$

An analysis similar to the one carried above identifies the degeneracy structure for the hidden variable y and shows that this structure is different from the degeneracy structure for the variable x. This is because the right hand side term in (49) involves the model attribute P instead of the model attribute Q.

3.1.5 The hidden variables corresponding to two degenerate observable variables within circuit types, but not across circuit types are multiples of each other

This follows from eqs. (40) and (49). Degeneracy in x implies that B and C are fixed, but P is different. For two values P_1 and P_2 of P, the corresponding variables y_1 and y_2 must satisfy

$$\frac{y_2(t)}{y_1(t)} = \frac{P_2}{P_1} \tag{51}$$

for all values of t provided $y_1'(0) = y_2'(0)$ or the ratio $y_2'(0)/y_1'(0)$ and the ratio of the steady values $\bar{y}_2/\bar{y}_1$ are equal (it is assumed that $y_1(0) = y_2(0) = y_0$). This is the case for two degenerate NFBL adaptive patterns for which $y_1'(0) = y_2'(0) = 0$ and for two degenerate IFFL adaptive patterns for which $y_2'(0)/y_1'(0) = \xi_2/\xi_1 = \bar{y}_2/\bar{y}_1$ (for a IFFL, $\bar{y} = -k_1 \, \xi \, A/(k_1 \, k_4)$). However, it is not the case across circuit types. For the NFBL, $y_1'(0) = 0$, while for the IFFL, $y_2'(0) = \xi, A$. In addition, for the NFBL, $\bar{y}_1 = k_3 \, A/(k_1 \, k_4 + k_2 \, k_3)$, and for the IFFL, $\bar{y}_2 = -k_1 \, \xi \, A/(k_1 \, k_4)$.

3.2 The intra- and cross-circuit-type degeneracy in linear NFBLs and IFFLs persists in response to oscillatory inputs

The presence of degeneracy in biological circuits presents an obstacle to identify the circuit architecture from observable data and to distinguish between NFBLs and IFFLs. Different types of time-dependent inputs have been used in the past to achieve the latter goal [4, 26–29]. In order to test whether time-dependent inputs are appropriate tools to resolve the degeneracy present in the linear adaptive systems within and across circuit types, we examine the response of these system (1)-(2) to oscillatory inputs.

The steady-state response for the observable variable is given by

$$x(t) = Z(\omega) A_s \, \sin(2\pi\omega t - \Phi(\omega)) \tag{52}$$

where the impedance amplitude and phase (see Section 2.4.1) are given, respectively, by

$$Z(\omega) = \sqrt{\frac{Q + \omega^2}{(C - \omega^2)^2 + B^2 \, \omega^2}} \tag{53}$$

and

$$\Phi(\omega) = \tan^{-1} \frac{(C - \omega^2) - B\,Q}{(C - \omega^2)\,Q + B\,\omega^2}\,\omega. \tag{54}$$

Both quantities involve only the model attributes B, C and Q. It follows that the degeneracy structure of the response to oscillatory signals is identical to the degeneracy structure discussed above for the response to constant inputs. Fig. 3 shows representative examples of the impedance amplitude and phase profiles (curves of the impedance amplitude and phase as a function of the input frequency) for the same parameter values as in Fig. 7-C. Therefore, oscillatory signals and, more generally, time-dependent signals are not useful tools to resolve the degeneracies for the linear adaptive systems discussed above.

Figure 3: **Degeneracy across circuit types: representative examples or resonant and phasonant profiles (in response to oscillatory inputs).** We used System (1)-(2) with $A_c = 0$, $A_s = 1$, $x(0) = 0$ and $y(0) = 0$. **Left column.** Impedance amplitude profile. **Right column.** Phase profile. We use the same parameter values as in Fig. 7-C. **A.** We fixed the parameter values in the NFBL and computed the degenerate parameter values in the IFFL. Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$ (blue), $K_1 = 0.8794$, $K_2 = 1.2056$, $\xi = 0.1$, $K_4 = 0.1706$ (dashed-red). **B.** We fixed the parameter values in the IFFL and computed the degenerate parameter values in the NBFL. Parameter values: $K_1 = 1$, $K_2 = 2$, $\xi = 0.015$, $K_4 = 0.05$ (blue), $k_1 = 1.03$, $k_2 = 0.588$, $k_3 = 0.05$, $k_4 = 0.02$ (dashed-red).

3.3 Degeneracy across circuit-types is lost in non-dimensionalized linear NFBLs and IFFLs

Non-dimensionalization is a widely used technique that helps identifying the number of free parameters that govern the dynamics of a system [46–49] and the properties of these dynamics. By defining dimensionless variables and parameters (in terms of the original ones) the complexity of models is reduced, the magnitude of the free parameters is revealed, and the structure (e.g., temporal) of the solutions is easier to uncover than in the original model. The solutions of the dimensional model can be obtained by reintroducing the (dimensional) model parameters and therefore this reduction process does not result in any loss of information about the dynamics of the original model. For these reason, modelers usually restrict their investigation to the simpler dimensionless models. While non-dimensionalization reveals important structural properties of NFBls and IFFLs and structural differences between NFBLs and IFFLs, it is not clear it captures the degeneracy present in the dimensional models both within and across circuit types.

We define the following dimensionless variables

$$t^* = k_1\,t, \qquad x^* = \frac{k_1\,x}{A_c} \qquad \text{and} \qquad y^* = \frac{k_2\,y}{\bar{A}_c}, \tag{55}$$

and parameters

$$\epsilon = \frac{k_4}{k_1}, \qquad \alpha = \frac{k_2\,k_3}{k_1\,k_4}, \qquad \xi = \frac{\xi\,k_2}{k_4}, \qquad \beta = \frac{A_s}{A_c}, \qquad \text{and} \qquad \nu = \frac{\omega}{k_1}. \tag{56}$$

We note that (55) and (56) is not the only choice for dimensionless variables and parameters. For example, the choice $t^* = k_4\,t$ leads to a different set of dimensionless variables and parameters and a dimensionless model with a different form.

Substitution into system (1)-(2) and dropping the "*" sign yields

$$\frac{dx}{dt} = -x - y + 1 + \beta\,\sin(2\pi\nu t), \tag{57}$$

$$\frac{dy}{dt} = \epsilon\,[\,\alpha\,x - y + \xi + \xi\,\beta\,\sin(2\pi\nu t)\,]. \tag{58}$$

As before, system (57)-(58) with $\beta = 0$ can be rewritten as a linear second order ODE of the form

$$\frac{d^2x}{dt^2} + B\,\frac{dx}{dt} + C\,x = Q \tag{59}$$

where

$$B = 1 + \epsilon, \qquad C = \epsilon\,(1 + \alpha) \qquad \text{and} \qquad Q = \epsilon\,(1 - \xi). \tag{60}$$

For the NFBL ($\xi = 0$),

$$B = 1 + \epsilon, \qquad C = \epsilon\,(1 + \alpha) \qquad \text{and} \qquad Q = \epsilon, \tag{61}$$

while for the IFFL ($\alpha = 0$),

$$B = 1 + \epsilon, \qquad C = \epsilon \qquad \text{and} \qquad Q = \epsilon\,(1 - \xi). \tag{62}$$

The steady-state solution is given by

$$\bar{x} = \frac{(1 - \xi)}{1 + \alpha}. \tag{63}$$

The eigenvalues are given by

$$r_{1,2} = \frac{-(1 + \epsilon) \pm \sqrt{(1 - \epsilon)^2 - 4\,\epsilon\,\alpha}}{2}. \tag{64}$$

If they are real, then the time constants are $\tau_{1,2} = r_{1,2}^{-1}$. Otherwise the damped oscillations envelope time constant is given by

$$\tau = -\frac{2}{1 + \epsilon} \tag{65}$$

and the oscillation frequency is given by

$$\omega = \frac{\sqrt{4\,\alpha - (1 - \epsilon)^2}}{2}. \tag{66}$$

Two of the main differences between the NFBL and IFFL are immediately apparent from these results: First, the IFFL ($\alpha = 0$) can produce perfect adaptation for $\xi = 1$, while the NFBL ($\xi = 0$) cannot. Second, the NFBL ($\xi = 0$) can produce damped oscillations, while the IFFL ($\alpha = 0$) cannot.

For each set of initial conditions, the solutions are controlled by two free parameters in each circuit type. This gives enough flexibility to the models to produce adaptation (and damped oscillations), but not full flexibility since the model attributes are constrained. For the NFBL, $B = 1 + Q$ and for the IFFL, $B = 1 + C$. These properties carry over to the dimensional model.

From (61) and (62), intra-circuit-type degeneracy is absent in both the NFBL and IFFL dimensionless models since the number of dimensionless parameters in each circuit type is smaller than the number of attributes. However, for fixed dimensionless parameters (ϵ, α and ξ), the dimensionless solutions for each circuit type capture the intra-circuit-type degeneracy present in the corresponding dimensional models. This requires k_1 to be fixed so the temporal shape of the solution is unaffected. This in turn requires $k_4 = k_1\,\epsilon$ to be fixed. For the NBFL, there are multiple combinations of k_2 and k_3 that produce the same value of α. Similarly, for the IFFL, there are multiple combinations of k_2 and ξ that produce the same value of ξ.

By comparing (61) and (62), the cross-circuit-type degeneracy is also absent in the dimensionless models. A fix value of the model attribute B forces the values of ϵ in both the NBLF and IFFL to be equal. Therefore, the equality of C and Q between the NFBL and IFFL cannot be met. Multiple combinations of α and ξ produce the same stationary value $\bar{x}$. However, the time constants $\tau_{1,2}$ are different in the two models for $\alpha > 0$ (Fig. 4)-A). These differences are translated to the impedance and phase profiles (Fig. 4-B and -C).

3.4 Degeneracy in weakly nonlinear NFBLs and IFFLs: a window into degeneracy in nonlinear models

In the previous sections we have discussed the presence of degeneracy within and across linear NFBLs and IFFLs and we showed that these types of degeneracy cannot be resolved by time-dependent inputs. The question arises of whether and under what conditions this persists for nonlinear NFBLs and IFFLs.

Figure 4: **Degeneracy across circuit types is lost in non-dimensionalized linear NFBLs and IFFLs.** We used System (57)-(58) with $x(0) = 0$ and $y(0) = 0$. **Top row.** Adaptive responses to constant inputs for representative parameter values for which the steady-states $\bar{x}$ for the NFBL and IFFL coincide. **Middle row.** Impedance amplitude profiles (in response to oscillatory inputs) for the same parameter values as in panel A. **Bottom row.** Phase profiles (in response to oscillatory inputs) for the same parameter values as in panel A. In all panels $\epsilon = 0.1$. In panels B and C we used eqs. (53) and (54). For the model attributes we used eqs. (60). We used the following additional parameter values. **A.** NFBL: $\alpha = 1$ and $\xi = 0$. IFFL: $\alpha = 0$ and $\xi = 0.5$. **B.** NFBL: $\alpha = 2$ and $\xi = 0$. IFFL: $\alpha = 0$ and $\xi = 0.6667$.

In principle, there is no reason to expect degeneracy to be communicated from linear to nonlinear systems. The types of nonlinearities we consider in this paper (see Section 2.1.2) involve the (hidden) variable y, which, as we showed in Section 3.1.4, has a different degeneracy structure than the (observable) variable x in linear NFBLs and IFFLs. This is particularly relevant, for example, for the model (3)-(4) with a nonlinearity of the form (6) that involves the product of x and y.

Here we begin to examine these ideas by using a weakly nonlinear model. Nonlinear systems cannot be solved analytically and therefore one typically relies on numerical simulations. Weakly nonlinear systems are an intermediate step that provides a window into the dynamics of nonlinear systems by using linear tools.

To this end, we will use system (3)-(4) with a multiplicative weakly nonlinear term $\Gamma(x, k_2\, y, I)$ of the form

$$\Gamma(x, k_2\, y, I) = -k_2\, y\, (1 + \epsilon\, x + \ldots) + I(t) \tag{67}$$

where $0 < \epsilon \ll 1$ and $I(t)$ is given by eq. (5). We define

$$x = X_0 + \epsilon\, X_1 + \mathcal{O}(\epsilon) \qquad \text{and} \qquad y = Y_0 + \epsilon\, Y_1 + \mathcal{O}(\epsilon). \tag{68}$$

By substituting (68) into system (3)-(4), rearranging terms and collecting the terms with the same power of ϵ, one obtains

$$\frac{dX_0}{dt} = -k_1 X_0 - k_2 Y_0 + A_c + A_s \sin(2\pi\omega t), \qquad X(0) = 0, \tag{69}$$

$$\frac{dY_0}{dt} = k_3 X_0 - k_4 Y_0 + \xi A_c + \xi A_s \sin(2\pi\omega t), \qquad Y(0) = 0, \tag{70}$$

and

$$\frac{dX_1}{dt} = -k_1 X_1 - k_2 Y_1 - k_2\, X_0\, Y_0, \qquad X_1(0) = 0, \tag{71}$$

$$\frac{dY_1}{dt} = k_3 X_1 - k_4 Y_1, \qquad Y_1(0) = 0. \tag{72}$$

The zeroth order approximation (69)-(70) is the linear system studied in the previous sections. Degeneracy (in the observable variable x_0) in response to constant inputs requires that $k_2\, k_3$ satisfies eq. (47) for the NFBL and $K_2\, \xi$ satisfies eq. (48) for the IFFL. In both cases, the other two parameters are uniquely determined by the model attributes (B an Q for the NFBL and B and C for the IFFL). Degeneracy within and across circuit types persists in response to oscillatory inputs ($A_s > 0$).

Now we turn our attention to the first order approximation (71)-(72) for $A_s = 0$. This is a forced linear system where the forcing term is the product of the solutions to the zeroth order approximation. We assume that the model parameters are constrained by fixed values of the model attributes B, C and Q so that x_0 exhibits degeneracy.

From eqs. (23)-(24), (26)-(28) and (15),

$$X_0(t) = \left[\frac{C/Q - \lambda_2}{\lambda_2 - \lambda_1} e^{-\lambda_1 t} - \frac{C/Q - \lambda_1}{\lambda_2 - \lambda_1} e^{-\lambda_2 t} + 1 \right] \frac{Q}{C} A_c = \Psi_x(t) \frac{Q}{C} A_c \tag{73}$$

and

$$Y_0(t) = \left[\frac{\xi\,C/P - \lambda_2}{\lambda_2 - \lambda_1}\,e^{-\lambda_1 t} - \frac{\xi\,C/P - \lambda_1}{\lambda_2 - \lambda_1}\,e^{-\lambda_2 t} + 1 \right] \frac{P}{C}\,A_c = \Psi_y(t)\,\frac{P}{C}\,A_c. \tag{74}$$

The functions $\Psi_x(t)$ and $\Psi_y(t)$ are elementary solutions to the linear system in the sense that they they transition from $\Psi_x = \Psi_y = 0$ at $t = 0$ to $\Psi_x = \Psi_y = 1$ as $t \to \infty$. All other solutions satisfying the linear system we are working with are multiples of these elementary functions.

For the NFBL ($\xi = 0$), $Y_0(t)$ simplifies to

$$Y_0(t) = \left[\frac{-\lambda_2}{\lambda_2 - \lambda_1}\,e^{-\lambda_1 t} + \frac{\lambda_1}{\lambda_2 - \lambda_1}\,e^{-\lambda_2 t} + 1 \right] \frac{P}{C}\,A_c =$$

$$= \Psi_y(t; \xi = 0)\,\frac{k_3}{k_1 k_4 + k_2 k_3}\,A_c. \tag{75}$$

For the IFFL ($k_3 = 0$, $C = k_1\,k_4$, $P = k_1\,\xi$), $Y_0(t)$ simplifies to

$$Y_0(t) = \left[\frac{K_4 - \lambda_2}{\lambda_2 - \lambda_1}\,e^{-\lambda_1 t} - \frac{K_4 - \lambda_1}{\lambda_2 - \lambda_1}\,e^{-\lambda_2 t} + 1 \right] \frac{P}{C}\,A_c =$$

$$= \Psi_y(t; k_3 = 0)\,\frac{\Xi}{K_4}\,A_c. \tag{76}$$

The functions $\Psi_y(t; \xi = 0)$ and $\Psi_y(t; k_3 = 0)$ have the same degeneracy structure as $X_0(t)$ since they do not involve only the model attributes B and C (through λ_1 and λ_2) and k_4, which is uniquely determined by the model attributes. Therefore, the differences between two solutions $Y_0(t)$ corresponding to two degenerate solutions $X_0(t)$ are given by factores multiplying these functions in (75) or (76).

Consequently, the differences between the forcing terms $-k_2\,X_0\,Y_0$ in (71) or (72) to two degenerate solutions $X_0(t)$, if they exist, are given by

$$\Gamma_{NFBL} = k_2\,\frac{k_3}{k_1 k_4 + k_2 k_3} \tag{77}$$

for the NFBL and

$$\Gamma_{IFFL} = K_2\,\frac{\Xi}{K_4} \tag{78}$$

for the IFFL. Because degeneracy in X_0 implies that $k_2\,k_3$ (NFBL) and $K_2\,\Xi$ (IFFL) are fixed, Γ_{NFBL} and Γ_{IFFL} are also fixed accordingly. Therefore, the first order approximation to the NFBL and IFFL inherits the degeneracy (within the circuit types) from the linear zeroth order approximation.

In contrast, degeneracy across circuit types is not directly inherited from the linear zeroth order approximation. For this to happen, eqs. (77) and (78) should be equal upon the transformations ($K_1 = B - K_4$, $2\,K_4 = B \pm \sqrt{B^2 - 4C}$, $K_2\,\Xi = K_4 - Q$ in the IFFL).

3.5 Degeneracy extends to nonlinear NFBLs and IFFLs with multiplicative and divisive nonlinearities

Here we examine whether the ideas discussed in the previous section persist for nonlinear NFBLs and IFFLs. To this end, we use nonlinear models of the form (3)-(4) with a multiplicative nonlinear term given by eq. (6) (M-) and divisive nonlinear terms given by eqs. (7) (Da) or (8) (Dp) (see Section 2.1.2). We

refer to these models as M-NFBL and -IFFL (multiplicative nonlinearities), Da-NFBL and -IFFL (divisive nonlinearities with an additive input), Dp-NFBL and -IFFL (divisive nonlinearities with an product input). These nonlinearities affect the mechanism of inhibition that y exerts on x. For the multiplicative model, increasing values of y cause an increase in the negative contribution of the nonlinear term to the rate of change of x, while for the divisive model, increasing values of y cause a decrease in the positive contribution of the nonlinear term to the rate of change of x. Our results are presented in Figs. 9 and 10 (M-NFBL and -IFFL), Figs. S1 and S2 (Da-NFBL and -IFFL), and Figs. S3 and S4 (Dp-NFBL and -IFFL).

3.5.1 Intra-circuit-type degeneracy is present in NFBLs and IFFLs in response to constant inputs

Figs. 9-A and -B illustrate the presence of (intra-circuit-type) degeneracy in the adaptive patterns produced by the M-NFBL (Figs. 9-A) and M-IFFL (Figs. 9-B) for two different combinations of k_2 and k_3 (NFBL) and K_2 and Ξ (IFFL). Degeneracy in both circuit types reflects the multiple balances between the activation of y, exerted either by x (k_3) or directly by the input signal (ξ) and the inhibition of x exerted by y (k_2) as for the linear and weakly nonlinear NFBLs and IFFLs discussed above. While it is not surprising that balances between two opposing processes lead to the same. steady-state response ($\bar{x}$), it is not a priori clear that they would necessarily lead to degeneracy in nonlinear models. The divisive models show similar results (Figs. S1-A and -B for the Da-NFBL and -IFFL and Figs. S3-A and -B the Dp-NFBL and -IFFL).

3.5.2 Intra-circuit-type degeneracy persists in NFBLs and IFFLs in response to oscillatory inputs

We measure the model's response to oscillatory inputs of the from (5) by using the definitions of Z and Φ given by eqs. (39) (see Section 2.4.2).

Figs. 9-C and -D illustrate that the degeneracy structure in response to oscillatory signals is identical to the degeneracy structure in response to constant inputs. Specifically, these Figs. show the impedance (Figs. 9-C1 and -D1) and phase (Figs. 9-C2 and -D2) profiles for the M-NFBL ((Fig. 9-C) and M-IFFL (Fig. 9-D) for the same set of parameter values as in Figs. 9-A1 and -B1. Similarly to linear models, the degeneracies within NFBLs and IFFLs cannot be resolved by oscillatory signals, and more generally time-dependent signals. The divisive models exhibit similar behavior (Figs. S1-C and -D for the Da-NFBL and -IFFL and Figs. S3-C and -D the Dp-NFBL and -IFFL).

3.5.3 Quasi-degeneracy across NFBLs and IFFLs in response to constant inputs

Uncovering degeneracy across linear NFBLs and IFFLs was mathematically facilitated by the formulas relating the model parameters with the model attributes (B, C and Q). In contrast to the intra-circuit-type degeneracy where degeneracy reflects different possible balances between the activation of y (k_3 or ξ) and the inhibition it exerts on x (k_2), degeneracy across circuit types reflected more complex relationships involving the remaining parameters.

Since we have no access to analytic formulas for nonlinear models, we searched for solutions to the M-IFFL model that approximate the previously computed solutions to the M-NFBL model (Figs. 9-A , blue). To this end, we used a gradient descent algorithm to compute the optimal parameter

values for K_1 and K_4 (within an error of 10^{-6}). The superimposed adaptive patterns are shown in Fig. 10-A. We refer to this phenomenon as quasi-degeneracy since the solutions are not identical. Additional quasi-degenerate adaptive patterns are provided by the multiple combinations of K_2 and Ξ that produce degeneracy within the M-IFFL (as discussed in the previous section). Quasi-degenerate adaptive patterns are also obtained for the Da- and Dp-NFBL and -IFFL models (Figs. S2-A and S4-A).

Because the adaptive patterns for the nonlinear M-NFBL and -IFFL resemble the adaptive patterns for the linear NFBL and IFFL, we asked whether there exists quasi-degeneracy both across circuit types and across linear and nonlinear models. To this end used a gradient descent algorithm to compute the optimal values of λ_1 and λ_2 in the analytical solution to linear models (see Section 2.3) that approximates the solution to the M-NFBL (within an error of 10^{-6}). (We used the same parameter values as in Figs. 9-A and 10-A, blue curves.) We then reconstructed the linear IFFL model (see Section 2.2.3) from this optimal solution by recovering the parameter values. The superimposed adaptive patterns are shown in Fig. 9-B. Additional quasi-degenerate adaptive patterns are provided by the (intra-circuit-type) degenerate adaptive patterns for linear IFFLs discussed above (not shown).

We repeated the process for the Da-NFBL model (for the same parameter values as in Figs. S1-A and S2-A, blue curves.) We computed the quasi-degenerate, optimal solution for linear models (within an error of 10^{-6}). Our result is shown in Fig. Fig. S1-B The parameters η in C_1 and C_2 is given by $\eta = -k_1x(0)+1/(1+k2y(0))+A = 1+A$ instead of $\eta = -k_1x(0)-k_2y(0)+A = A$ as for the M-IFFL. This has consequences for the reconstruction of the Da-IFFL model since the appropriate initial condition for the linear model is $y(0) = -(\eta - A)/K_2$, which is different from the initial condition for the Da-NFBL and -IFFL models, $y(0) = 0$. Additionally, for the linear model, the recovered parameter $\Xi < 0$. For the same recovered parameter values, but $y(0) = 0$, the solution not only show no adaptation, but it is monotonically increasing. In other words, the adaptive patterns in the reconstructed linear model are generated by the initial value of the variable y that causes x to increases and an inhibitory input signal that causes x to peak and subsequently decrease. This mechanism is different from the M- and Da-NFBL models the linear IFFL model is approximating. We also repeated the process for the Dp-NFBL model and obtained results similar to the M-NFBL model (Fig. S4-B).

3.5.4 Quasi-degeneracy across NFBLs and IFFLs is disrupted in response to oscillatory inputs

Fig. 10-C shows the impedance (Fig. 10-C1) and phase (Fig. 10-C2) profiles for the M-NFBL and -IFFL models discussed above (using the same parameter values as in Figs. Fig. 10-A and -B). The small difference between the adaptive patterns for the M-NFBL and M-IFFL are reflected in larger difference between the corresponding impedance and phase profiles (compare the blue and dashed-red curves). Similarly, the difference between the adaptive patterns for the nonlinear NFBL and the linear IFFL are reflected in larger differences between the corresponding impedance and phase profiles (compare the blue and dashed-green curves). Interestingly, the differences between the impedance and phase profiles between the linear IFFL and the nonlinear NFBL and IFFL are significantly larger than the differences between the corresponding adaptive patterns. In other worlds, oscillatory inputs and more generally time-dependent inputs are potentially useful tools to resolve the quasi-degeneracy present in the adaptive patterns by amplifying the small differences between them.

Fig. S2-C shows the impedance (Fig. S2-C1) and phase (Fig. S2-C2) profiles for the Da-NFBL and -IFFL models discussed above (using the same parameter values as in Figs. Fig. S2-A and -B). The results for the nonlinear models are analogous to the ones described above: a small difference between the adaptive patterns for the Da-NFBL and Da-IFFL are reflected in larger difference between the

corresponding impedance and phase profiles (compare the blue and dashed-red curves). In contrast, the impedance and phase profiles for the linear IFFL model is qualitatively different from the other two. Specifically, the IFFL exhibits a low-pass filter (no resonance) and a monotonically increasing phase (no phasonance). This is a direct consequence of the response to constant input being a monotonically increasing function for zero initial conditions as opposed to an adaptive pattern.

The results for the Dp-NFBL and -IFFL models are similar to the corresponding M- models (Figs. S4-C and -D).

In summary, quasi-degeneracy across circuit types for nonlinear NFBLs and IFFLs can be resolved by oscillatory inputs and, more generally, by time-dependent inputs.

3.6 A dynamical systems mechanistic interpretation of degeneracy in adaptive NFBLs and IFFLs

Here we use dynamical system tools to analyze the mechanisms of generation of adaptive patterns (in response to constant inputs) within and across circuit types. We use system (1)-(2) with $A_c = 1$, $A_s = 0$, $x(0) = 0$ and $y(0) = 0$. Our results for degeneracy within NFBLs are presented in Fig. 7.

3.6.1 Dynamic balances responsible for the generation of degeneracy within NFBLs

Fig. 7-A1 shows an example of degenerate adaptive patterns for $k_2 = 2$, $k_3 = 0.05$ (NFBL-1, blue), $k_2 = 1$, $k_3 = 0.1$ (NBFL-2, dashed-red) and the same values of k_1 and k_4. As discussed in Section 3.1.5, the quotient of the corresponding y-traces is constant (inset). Fig. 7-A2 shows the superimposed phase-plane diagrams for the two parameter sets in Fig. 7-A1 (solid curves for NFBL-1 and dashed curves for NFBL-2). The x- and y-nullclines are given, respectively, by

$$N_x(x) = -\frac{k_1}{k_2}\,x + \frac{A}{k_2} \qquad \text{and} \qquad N_y(x) = \frac{k_3}{k_4}\,x, \tag{79}$$

and the fixed-points (computed as the intersection of the two nullclines) s given by

$$\bar{x} = \frac{k_4}{k_1\,k_4 + k_2\,k_3}\,A \qquad \text{and} \qquad \bar{y} = \frac{k_3}{k_1\,k_4 + k_2\,k_3}\,A. \tag{80}$$

We first describe the geometry of the generation of adaptive patterns by focusing on NFBL-1 (blue curve in Fig. 7-A1 and solid curves in Fig. 7-A2). The adaptive trajectory transitions from $(0,0)$ to $(\bar{x}, \bar{y})$ (black dot). The overshoot is created because the structure of the vector field requires the trajectory to first move to the right (increasing values of x), then cross the x-nullcline (red), thus generating the peak of the adaptive pattern, and finally moves to the left (decreasing values of x) towards the fixed-point.

For the two degenerate adaptive patterns, $k_2\,k_3 = 0.1$. The transition from NFBL-1 to NFBL-2 consists of a decrease in k_2 (inhibition) and an increase in k_3 (activation). While $\bar{x}$ remains constant (necessary condition for degeneracy), $\bar{y}$ increases (Fig. 7-A2, black dots). The quotient between the two values of k_3 ($0.1/0.05 = 2$) determines the value of the constant quotient of the two y-traces (see Section 3.1.5) (Fig. 7-A1, inset).

The decrease in k_2 and the increase in k_3 cause the slopes of the x- and y-nullclines, respectively, to increase. This in turn causes the fixed-point to raise. These changes need to be balanced so the two trajectories cross the corresponding x-nullclines for the same value of x and evolve towards the fixed-point by maintaining a constant quotient of the variables y. In other words, if the x-nullcline's

Figure 5: **Degeneracy within circuit types in the presence of multiplicative nonlinearities: representative examples or adaptive responses (to a constant input).** We used System (3)-(4) with $x(0) = y(0) = 0$ and $\Gamma(x, k_2\, y, I)$ given by eq. (6). **A, B.** Adaptive responses for $A_c = 1$ ($A_s = 0$). **C, D.** Impedance amplitude and phase profiles for $A_s = 1$ ($A_c = 0$). **A.** Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$, $\xi = 0$ (blue), $k_1 = 1$, $k_2 = 1$, $k_3 = 0.1$, $k_4 = 0.05$, $\xi = 0$ (dashed-red). **B.** Parameter values: $K_1 = 1$, $K_2 = 2$, $K_3 = 0$, $K_4 = 0.015$, $\Xi = 0.05$ (blue), $K_1 = 1$, $K_2 = 0.4$, $K_3 = 0$, $K_4 = 0.015$, $\Xi = 0.25$ (dashed-red). **C.** Same parameter values and color-code as in A. **D.** Same parameter values and color-code as in B.

Figure 6: **Quasi-degeneracy across circuit types in the presence of multiplicative nonlinearities: representative examples of adaptive responses (to a constant input).** We used System (3)-(4) with $x(0) = y(0) = 0$ and $\Gamma(x, k_2\, y, I)$ given by (6). **A, B.** Adaptive responses for $A_c = 1$ ($A_s = 0$). **C.** Impedance amplitude and phase profiles for $A_s = 1$ ($A_c = 0$). Degeneracy is disrupted in response to oscillatory inputs. **A.** Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$, $\xi = 0$ (blue), $K_1 = 0.9525$, $K_2 = 2$, $K_3 = 0$, $K_4 = 0.086$, $\Xi = 0.045$ (dashed-red). **B.** Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$, $\xi = 0$ (blue). For the linear model we used System (1)-(2) with $K_1 = 1.0102$, $K_2 = 2$, $K_3 = 0$, $K_4 = 0.1216$, $\Xi = 0.0301$. For these parameter values, the eigenvalues are given by $r_1 = -0.1216$ and $r_2 = -1.0102$. **C.** Quasi-degeneracy breaks in response to oscillatory inputs. The parameter values and color-code are as in A and B.

slope increases (due to a decrease in k_2), then the y-nullcline's slope needs to increase (by increasing k_3) in such a way as to maintain the constancy of the quotient of the variables y. Conversely, if the y-nullcline's slope increases (due to an increase in k_3, then the x-nullcline's slope needs to increase (by decreasing k_2) in such a way as to maintain the constancy of the quotient of the variables y. In order for the trajectories to cross the x-nullclines for the same values of x, the two x-nullclines need to intersect for a values of x higher than the crossing value (peak of the adaptive pattern).

If the y-nullcline's slope does not increase enough (Fig. 7-B2, (k_2, k_3) transitions from $(2, 0.05)$ for NFBL-1 to $(1, 0.06)$ for NFBL-2), then the two fixed-points are not on a vertical line and degeneracy is broken (Fig. 7-B1).

Maintaining the two fixed-points on a vertical line does not require $k_2\,k_3$ to be fixed for both NFBL-1 and NFBL-2 (Fig. 7-C2, (k_2, k_3) transitions from $(2, 0.05)$ for NFBL-1 to $(1, 0.07)$ for NFBL-2). However, this requires k_1 to change as well ($k_1 = 1$ for NBFL-1 and $k_1 = 1.6$ for NFBL-2). This causes the x-nullcline's slope to increase, but the x-nullcline does not simply shifts upwards (by maintaining the same x-intercept), but it crosses the other x-nullcline at a non-zero values of x (the two x-nullclines have different x-intercepts). As a result, the trajectory for NFBL-2 crosses the corresponding x-nullcline at a lower values of x than the trajectory for NBFL-1, and therefore degeneracy is broken (Fig. 7-C1). Note the quotient of the y variables is not constant (inset).

3.6.2 Dynamic balances responsible for the generation of degeneracy within IFFLs

Fig. 8-A1 shows an example of degenerate adaptive patterns for $k_2 = 2$, $\xi = 0.015$ (IFFL-1, blue), $k_2 = 1$, $\xi = 0.03$ (IFFL-2, dashed red) and the same values of k_1 and k_4. As discussed above, the quotient of the corresponding y-traces is constant (inset). Fig. 8-A2 shows the superimposed phase-plane diagrams for the two parameter sets in Fig. 8-A1(solid curves for IFFL-1 and dashed curves for IFFL-2). The x-nullclines are given by eq. (79) (left) and the y-nullcline is given by

$$y = \frac{\xi}{k_4}\,A. \tag{81}$$

The fixed-points are given by

$$\bar{x} = \frac{k_4 - k_2\,\xi}{k_1\,k_4}\,A \qquad \text{and} \qquad \bar{y} = \frac{\xi}{k_4}\,A. \tag{82}$$

The mechanism of generation of adaptive patterns is similar to the mechanism described above. Briefly, for the two degenerate adaptive patterns, $k_2\,\Xi = 0.03$. The transition from IFFL-1 to IFFL-2 consists of a decrease in k_2 (inhibition) and an increase in ξ (direct activation). While $\bar{x}$ remains constant (necessary condition for degeneracy), $\bar{y}$ increases (Fig. 8-A2, black dots). The quotient between the two values of ξ ($0.1/0.05 = 2$) determines the value of the constant quotient of the two y-traces (see Section 3.1.5) (Fig. 8-A1, inset).

The decrease in k_2 and the increase in ξ cause the slope of the x-nullcline to increase and the y-nullcline to raise, respectively.This in turn causes the fixed-point to raise. These changes need to be balanced so the two trajectories cross the corresponding x-nullclines for the same value of x and evolve towards the fixed-point by maintaining a constant quotient of the variables y. In other words, if the x-nullcline's slope increases (due to a decrease in k_2), then the y-nullcline needs to raise (by increasing ξ) in such a way as to maintain the constancy of the quotient of the variables y. In order for the trajectories to cross the x-nullclines for the same values of x, the two x-nullclines need to intersect for a values of x higher than the crossing value (peak of the adaptive pattern).

Figure 7: **Degeneracy of adaptive patterns (responses to constant inputs) : Phase-plane analysis.** We used system (1)-(2) with $A_c = 1$, $A_s = 0$, $x(0) = 0$ and $y(0) = 0$. **Left column.** Superimposed x-traces for two NFBLs: NFBL-1 (blue) and NFBL-2 (dashed-red). Inset: quotient of corresponding y- traces. **Right column.** Superimposed phase-plane diagrams for the two cases in the corresponding left column. The x-nullclines (red), y-nullclines (green) and trajectories (blue) are presented with solid lines (NBFL-1) and dashed lines (NFBL-2). The two fixed-points are indicated with black dots. The dashed-black line connects between them. **A.** Degeneracy within NFBLs. Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$ (NFBL-1, blue), $k_1 = 1$, $k_2 = 1$, $k_3 = 0.1$, $k_4 = 0.05$ (NBFL-2, dashed-red). **B.** No degeneracy within NFBLs. The adaptive patterns have different steady-state values ($\bar{x}$). Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$ (NFBL-1, blue), $k_1 = 1$, $k_2 = 1$, $k_3 = 0.06$, $k_4 = 0.05$ (NBFL-2, dashed-red). **C.** No degeneracy within NFBLs. The adaptive patterns have the same steady-state value ($\bar{x}$). Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$ (NFBL-1, blue), $k_1 = 1.6$, $k_2 = 1$, $k_3 = 0.07$, $k_4 = 0.05$ (NBFL-2, dashed-red).

Figure 8: **Degeneracy of adaptive patterns (responses to constant inputs): Phase-plane analysis.** We used system (1)-(2) with $A_c = 1$, $A_s = 0$, $x(0) = 0$ and $y(0) = 0$. **Left column.** Superimposed x-traces for two NFBLs: NFBL-1 (blue) and NFBL-2 (dashed-red). Inset: quotient of corresponding y- traces. **Right column.** Superimposed phase-plane diagrams for the two cases in the corresponding left column. The x-nullclines (red), y-nullclines (green) and trajectories (blue) are presented with solid lines (NBFL-1) and dashed lines (NFBL-2). The two fixed-points are indicated with black dots. The dashed-black line connects between them. **A.** Degeneracy within IFFLs. Parameter values: $k_1 = 1$, $k_2 = 2$, $k_4 = 0.05$, $\xi = 0.015$ (IFFL-1, blue), $k_1 = 1$, $k_2 = 1$, $k_4 = 0.05$, $\Xi = 0.03$ (IFFL-2, dashed-red). **B.** Degeneracy across NFBL and IFFL. Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$ (NFBL-1, blue), $k_1 = 0.8794$, $k_2 = 1.2056$, $k_4 = 0.1706$ and $\xi = 0.1$.

3.6.3 Dynamic balances responsible for the generation of degeneracy across NFBLs and IFFLs

Fig. 8-B1 shows an example of degenerate adaptive patterns for $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$ (NFBL-1, blue), $k_1 = 0.8794$, $k_2 = 1.2056$, $k_4 = 0.1706$ and $\xi = 0.1$ (IFFL-2, dashed-red). Fig. 8-B2 shows the superimposed phase-plane diagrams for the two parameter sets in Fig. 8-B1 (solid curves for NFBL-1 and dashed curves for IFFL-2). Together, they show the mechanism of generation of degenerate adaptive patterns is a combination of the ideas discussed in the previous section.

3.6.4 The dynamic balances responsible for the generation of degeneracy within and across nonlinear NFBLs and IFFLs are inherited from the linear regimes

Here we extend our investigation of the mechanism of generation of degeneracy within and across NF-BLs and IFFLs to include nonlinear models (3)-(4) with multiplicative (6) and divisive (7) nonlinearities. Our results are presented in Fig. 9 (multiplicative) and Fig. 10 (divisive). In both cases, the nonlinear-ities affect the x-nullclines, but not the y-nullclines. The latter are given by eq. (79) (NFBL, right) and eq. (81) (IFFL). The x-nullclines for the multiplicative and divisive models are given, respectively, by

$$y = -\frac{k_1}{k_2} + \frac{A}{k_2 \, x} \qquad \text{and} \qquad y = \frac{1}{k_2} \left(\frac{A}{k_1 \, x} - 1 \right). \tag{83}$$

The fixed-points are computed as the intersection between the corresponding x- and y-nullclines. Note that these nullclines are identical for $k_1 = 1$.

The phase-plane diagramas in Figs. 9 and 10 are different from the corresponding ones for the lin-ear models (Figs. 7-A and 10). However, their structures are qualitatively similar. In fact, geometrically, the phase-plane diagrams for the nonlinear models can be thought of as deformation of the phase-plane diagrams for the corresponding linear models. Therefore, the mechanism responsible for the generation of degeneracy in the nonlinear multiplicative and divisive models can be explained following the same ideas as for the linear models discussed above. This explains why one can relatively easily find quasi-degenerate adaptive patterns between linear and nonlinear models. One consequence of this is that the mechanisms of generation of degeneracy are qualitatively similar between the multiplicative and divisive models. This is supported by the fact that although the two models are qualitatively different, the phase-plane diagrams are very similar (in some cases the x-nullclines are identical as mentioned above).

4 Discussion

Biological adaptation has received significant attention in recent years [1–6]. The identification of NFBLs and IFFLs as two elementary building block circuits able to produce these types of adaptive patterns [3] motivated the investigation of methods to discriminate between these two circuit types [4,26–29]. These efforts require an understanding of the biological and dynamic mechanisms that give rise to adaptive patterns (in response to step-constant inputs) and, more generally, how network processing (NFBL) and input orchestration (IFFL) control the responses of adaptive systems to biologically plausible, time-dependent inputs. In an ideal situation, there would exist a one-to-one and onto map between the model parameters and the attributes that characterize the adaptive patterns (e.g., steady-state, time constants, peak values and times) so that the latter can be uniquely identified from the former. However, the presence of degeneracy [20, 21, 43], where multiple combinations of parameter values produce

Figure 9: **Degeneracy of adaptive patterns (responses to constant inputs) in nonlinear NFBLs and IFFLs with multiplicative nonlinearities: Phase-plane analysis.** We used System (3)-(4) with $x(0) = y(0) = 0$ and $\Gamma(x, k_2 y, I)$ given by eq. (6). **Left column.** Superimposed x-traces for two NFBLs: NFBL-1 (blue) and NFBL-2 (dashed-red). Inset: quotient of corresponding y- traces. **Right column.** Superimposed phase-plane diagrams for the two cases in the corresponding left column. The x-nullclines (red), y-nullclines (green) and trajectories (blue) are presented with solid lines (NBFL-1) and dashed lines (NFBL-2). The two fixed-points are indicated with black dots. The dashed-black line connects between them. **A.** Degeneracy within NFBLs. Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$, $\xi = 0$ (blue), $k_1 = 1$, $k_2 = 1$, $k_3 = 0.1$, $k_4 = 0.05$, $\xi = 0$ (dashed-red). **B.** Degeneracy within IFFLs. Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0$, $k_4 = 0.05$, $\xi = 0.015$ (blue), $k_1 = 1$, $k_2 = 0.4$, $k_3 = 0$, $k_4 = 0.05$, $\xi = 0.075$ (dashed-red). **C.** Quasi-degeneracy across NFBLs and IFFLs. Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$, $\xi = 0$ (blue) $k_1 = 0.9525$, $k_2 = 2$, $k_3 = 0$, $k_4 = 0.086$, $\xi = 0.045$ (dashed-red).

Figure 10: **Degeneracy of adaptive patterns (responses to constant inputs) in NFBLs and IFFLs with divisive nonlinearities: Phase-plane analysis.** We used System (3)-(4) with $x(0) = y(0) = 0$ and $\Gamma(x, k_2\,y, I)$ given by eq. (7). **Left column.** Superimposed x-traces for two NFBLs: NFBL-1 (blue) and NFBL-2 (dashed-red). Inset: quotient of corresponding y- traces. **Right column.** Superimposed phase-plane diagrams for the two cases in the corresponding left column. The x-nullclines (red), y-nullclines (green) and trajectories (blue) are presented with solid lines (NBFL-1) and dashed lines (NFBL-2). The two fixed-points are indicated with black dots. The dashed-black line connects between them. **A.** Degeneracy within NFBLs. Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$, $\xi = 0$ (blue), $k_1 = 1$, $k_2 = 1$, $k_3 = 0.1$, $k_4 = 0.05$, $\xi = 0$ (dashed-red). **B.** Degeneracy within IFFLs. Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0$, $k_4 = 0.05$, $\xi = 0.015$ (blue), $k_1 = 1$, $k_2 = 0.4$, $k_3 = 0$, $k_4 = 0.05$, $\xi = 0.075$ (dashed-red). **C.** Quasi-degeneracy across NFBLs and IFFLs. Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$, $\xi = 0$ (blue) $k_1 = 0.9594$, $k_2 = 2$, $k_3 = 0$, $k_4 = 0.0855$, $\xi = 0.0464$ (dashed-red).

identical output patterns leads to the problem of unidentifiability in parameter estimation [50–54] from the available experimental or observable data.

We set out to systematically understand the structure of degeneracy in minimal models of NF-BLs and IFFLs and the conditions under which degeneracy in the adaptive patterns is inherited to the impedance amplitude and phase profiles, which characterize the response of these circuits to oscillatory inputs at all frequencies. We used analytical calculations, regular perturbation analysis, phase-plane analysis and numerical simulations. Our results for minimal models define scenarios and hypotheses for the systematic investigation of the mechanisms of generation of adaptive patterns, resonance/phasonance and degeneracy in more complex models involving negative feedback processing, input orchestration, and combinations of these in the presence of external fluctuations and confounding factors. Our results have also implications for the development of methods for circuit and dynamical systems reconstruction based on experimental or observational data. Finally, while our investigation was motivated by previous work originated in the field of systems biology, similar circuit structure is present in neuronal systems. Our findings for neuronal rate models describing the evolution of the instantaneous firing rates of excitatory and inhibitory networks [37–41] raise questions for more complex models of spiking neurons having the same circuit structure.

The investigation of the mathematically tractable linear systems allowed us to identify the principles underlying the generation of degeneracy in NFBLs and IFFLs and the persistence of the degeneracy structure in the response of these adaptive systems to oscillatory inputs. Key to these findings is the reduction of the two-dimensional system to a second order differential equation. While the two are equivalent formulations, the transformation process reduces the number of effective parameters, which we refer to as model attributes, to the minimal possible number that allow for a one-to-one and onto link between them and the attributes characterizing the adaptive patterns (time constants and steady-state). Degeneracy results from the definition of the model attributes in terms of the larger number of model parameters. The presence of degeneracy in the impedance amplitude and phase profiles and the fact that it has the same structure as in the adaptive patterns is a direct consequence of this reduction. Because of the success of this approach, one might be tempted to believe that further reductions will aid in process. One such approach is the widely used non-dimensionalization technique [46–49]. However, we found that dimensionless NFBLs and IFFLs fail to capture the degeneracy structure of NFBLs and IFFLs both within and across circuit types.

Because this approach is not applicable to nonlinear systems, it is not immediately clear whether and under what conditions degeneracy is present in nonlinear models of NFBLs and IFFLs. A regular perturbation analysis of weakly nonlinear systems showed that degeneracy within circuit types, but not across circuit types is inherited to the nonlinear NFBLs and IFFLs. Numerical simulations and phase-plane analysis established that the mechanisms underlying the generation of degeneracy in nonlinear systems are qualitatively similar among them and to the ones for the linear systems. The fact that these mechanisms are qualitatively similar for different types of nonlinear models suggest the universality of the phenomena.

The mechanisms of generation of degeneracy both within and across circuit types involve balances between the activation of the inhibitory process and the effect it exerts on the observable variable. More specifically, degeneracy within the linear NFBLs and IFFLs is created by multiple combinations of the parameter values that control the inhibition of the observable node X (k_2) by the hidden node Y and its activation by X (NFBL, k_3) or the input (IFFL, ξ). Degeneracy across circuit types is a direct consequences of these activation-inhibition balances. The persistence of degeneracy in the impedance and phase profiles for the same combination of parameter values is consistent with previous findings

linking adaptive patterns with the resonance and phasonance phenomena [30–33] and precludes the ability of time-dependent inputs to resolve the degeneracy in these adaptive patterns. While the type of balances between opposing process are expected to produce similar patterns, it is not obvious that these balances will produce the type of robust degeneracy we found. The robustness of degeneracy decreases for nonlinear systems as compared to linear ones. Specifically, while the nonlinear models show degeneracy within circuit types, they show quasi-degeneracy, a weaker form of degeneracy, across circuit types. Quasi-degenerate adaptive patterns are almost identical, but not identical. They are almost indistinguishable, but they respond differently to external perturbations, in contrast to the fully degenerate adaptive patterns. Specifically, quasi-degeneracy is not inherited by the impedance amplitude and phase profiles. This suggests that it is easier to discriminate between circuit types than to identify the precise structure of each circuit type. This is important when designing algorithms to systematically reconstruct the systems' structure from experimental/observable data.

In previous work [43] we have identified a canonical models for degeneracy in the so-called λ-ω models and related models. These are two-dimensional nonlinear models producing oscillations. This type of degeneracy is different from the one described here. First, in the λ-ω degeneracy is exhibited by both state variables. Second, for the λ-ω models, degeneracy is exhibited only in the steady-state regime in contrast to the NFBL and IFFL models where degeneracy is present in both the steady-state and the transient regimes. However, oscillatory models can be constituent building blocks of complex NFBL and IFFL models. Research is required to establish the dynamics of these complex networks, their degeneracy structure and the mechanisms by which the two types of degeneracy described above interact.

NFBL and IFFL have been proposed to play significant roles in the processing of temporal information and related regulatory functions in biological and neuronal systems [7–19, 37–41, 55] (and references therein). Research is needed to examine the ideas and results discussed in this paper in models describing more complex scenarios.

Acknowledgments

HGR acknowledges support from the National Science Foundation grants DMS-1608077 and IOS-2002863. ACV acknowledges support from a Grant from the Argentine Agency of Research and Technology (PICT2019-01681) . HGR is a Corresponding Investigator in CONICET, Argentina and a Graduate Faculty Member in the Behavioral Neurosciences Program at Rutgers University. HGR is also Visiting Researcher/Academic in the Neurosciences Institute and the Courant Institute of Mathematical Sciences at New York University.

References

[1] J. E. Ferrell. Commentary perfect and near-perfect adaptation in cell signaling. *Cell Systems*, 2:62–67, 2016.

[2] G. De Palo, G. Facchetti, M. Mazzolini, A. Menini, V. Torre, and C. Altafini. Common dynamical features of sensory adaptation in photoreceptors and olfactory sensory neurons. *Scientific Reports*, 3:1–8, 2013.

[3] W. Ma, A. Trusina, H. El-Samad, W. A. Lim, and C. Tang. Defining network topologies that can achieve biochemical adaptation. *Cell*, 138:760–773, 2009.

[4] S. J. Rahi, J. Larsch, K. Pecani, A. Y. Katsov, N. Mansouri, K. Tsaneva-Atanasova, E. D. Sontag, and F. R. Cross. Oscillatory stimuli differentiate adapting circuit topologies. *Nature Methods*, 14:1010–1016, 2017.

[5] O. S. Soyer, H. Kuwahara, and A. Csika. Regulating the total level of a signaling protein can vary its dynamics in a range from switch like ultrasensitivity to adaptive responses. *FEBS J*, 276:3290–3298, 2009.

[6] Y. Tu, T. S. Shimizu, and H. C. Berg. Modeling the chemotactic response of escherichia coli to time-varying stimuli. *Proc. Natl. Acad. Sci. USA*, 105:14855–14860, 2008.

[7] I. Joanito, J. Chu, S. Wu, and C. Hsu. An incoherent feed-forward loop switches the arabidopsis clock rapidly between two hysteretic states. *Scientific Reports*, 8:13944, 2018.

[8] S. Mangan, S. Itzkovitz, A. Zaslaver, and U. Alon. The incoherent feed-forward loop accelerates the response-time of the gal system of Escherichia coli. *J Mol Biol*, 356:1073–1081, 2006.

[9] N. N. Mank, B. A. Berghoff, and G. Klug. A mixed incoherent feed-forward loop contributes to the regulation of bacterial photosynthesis genes. *RNA Biology*, 10:347–352, 2013.

[10] M. Metzig, Y. Tang, S. Mitchell, B. Taylor, R. Foreman, R. Wollman, and A. Hoffman. An incoherent feedforward loop interprets NFkB/RelA dynamics to determine TNF-induced necroptosis decisions. *Molecular Systems Biology*, 16:e9677, 2020.

[11] S. Grigolon, F. Di Patti, A. De Martino, and E. Marinari. Noise processing by microRNA-mediated circuits: The incoherent feed-forward loop, revisited. *Heliyon*, 2:e00095, 2016.

[12] C. Zhang, R. Tsoi, F. Wu, and L. You. Processing oscillatory signals by incoherent feedforward loops. *PLoS Computational Biology*, 12:e1005101, 2016.

[13] S. S. Shen-Orr, R. Milo, and U. Mangan, S. abd Alon. Network motifs in the transcriptional regulation network of Escherichia coli. *Nature Genetics*, 31:64–68, 2002.

[14] J. B. Welsh, G. N. Gill, M. G. Rosenfeld, and A. Wells. A negative feedback loop attenuates egf-induced morphological changes. *J Cell Biol*, 114:533–543, 1991.

[15] J. Guo, P. Cheng, H. Yuan, and Y. Liu. The exosome regulates circadian gene expression in a postranscriptional negative feedback loop. *Cell*, 138:1236–1246, 2009.

[16] Q. He, J. Cha, Q. He, H. C. Lee, Y. Yang, and Y. Liu. CKI and CKII mediate the FREQUENCY-dependent phosphorylation of the WHITE COLLAR complex to close the Neurospora circadian negative feedback loop. *Genes Dev*, 20:2552–2565, 2006.

[17] C. Heintzen, M. Nater, K. Apel, and D. Staiger. AtGRP7, a nuclear RNA-binding protein as a component of a circadian-regulated negative feedback loop in Arabidopsis thaliana. *Proc. Natl. Acad. Sci. USA*, 94:8515–8520, 1997.

[18] H. Hirata, S. Yoshiura, T. Ohtsuka, Y. Bessho, T. Harada, K. Yoshikawa, and R. Kageyama. Oscillatory expression of the bhlh factor hes1 regulated by a negative feedback loop. *Science*, 298:840–843, 2002.

[19] W. Zhang and H. T. Liu. REVIEW MAPK signal pathways in the regulation of cell proliferation in mammalian cells. *Cell Research*, 12:9–18, 2002.

[20] G. M. Edelman and J. A. Gally. Degeneracy and complexity in biological systems. *Proc. Natl. Acad. Sci. USA*, 98:13763–13768, 2001.

[21] A. A. Prinz, D. Bucher, and E. Marder. Similar network activity from disparate circuit parameters. *Nature Neurosci.*, 7:1345–1352, 2004.

[22] J. Keener and J. Sneyd. *Mathematical Physiology*. Springer-Verlag, New York, 2001.

[23] B. P. Ingalls. *Mathematical models in systems biology*. MIT Press, 2013.

[24] U. Alon. *An introduction to systems biology: design principles of biological circuits*. Chapman & Hall/CRC, 2007.

[25] L. Michaelis and M. L. Menten. Kinetik der invertinwirkung. *Biochem. Zeitung*, 49:333–369, 1913.

[26] O. Hoeller, D. Gong, and O. D. Weiner. How to understand and outwit adaptation. *Developmental Cell*, 28:607–616, 2014.

[27] B. Mélykúti, E. August, A. Papachristodoulou, and H. El-Samad. Discriminating between rival biochemical network models: Three approaches to optimal experiment design. *BMC Systems Biology*, 4:38, 2010.

[28] H. Chang and A. Levchenko. Adaptive molecular networks controlling chemotactic migration: Dynamic inputs and selection of the network architecture. *Philos. Trans. R Soc Lond B Biol.*, 368:1629, 2013.

[29] P. A. Iglesias and C. Shi. Comparison of adaptation motifs: Temporal, stochastic and spatial responses. *IET Systems Biology*, 8:268–281, 2014.

[30] M. J. E. Richardson, N. Brunel, and V. Hakim. From subthreshold to firing-rate resonance. *J. Neurophysiol.*, 89:2538–2554, 2003.

[31] H. G. Rotstein and F. Nadim. Neurons and neural networks: Computational models. *In: Encyclopedia of Life Sciences. John Wiley & Sons, Ltd: Chichester http://www.els.net/ [DOI: 10.1002/9780470015902.a0000089.pub2]*, a0000089:1–9, 2007.

[32] H. G. Rotstein. Frequency preference response to oscillatory inputs in two-dimensional neural models: a geometric approach to subthreshold amplitude and phase resonance. *J. Math. Neurosci.*, 4:11, 2014.

[33] H. G. Rotstein. Subthreshold amplitude and phase resonance in models of quadratic type: nonlinear effects generated by the interplay of resonant and amplifying currents. *J. Comp. Neurosci.*, 38:325–354, 2015.

[34] A. Cournac and J.-A. Sepulchre. Simple molecular networks that respond optimally to time-periodic stimulation. *BMC Systems Biology*, 3:29, 2009.

[35] Y. Zhang, C. Cuba Samaniego, K. Carleton, Y. Qian, G. Giordano, and E. Franco. Building molecular band-pass filters via molecular sequestration. *2022 IEEE 61st Conference on Decision and Control (CDC)*, pages 3890–3895, 2022.

[36] J. Reves-Szemere. *Frequency selectivity in biochemical systems in response to oscillatory stimuli: mechanisms, functionality and modulation by targets*. PhD Thesis, Universidad de Buenos Aires, Buenos Aires, Argentina, 2022.

[37] H. R. Wilson and J. D. Cowan. Excitatory and inhibitory interactions in localized populations of model neurons. *Biophysical J.*, 12:1–24, 1972.

[38] M. V. Tsodyks, W. E. Skaggs, T. J. Sejnowski, and B. L. McNaughton. Paradoxical effects of external modulation of inhibitory interneurons. *J. Neurosci.*, 17:4382–4388, 1997.

[39] P. Dayan and L. F. Abbott. *Theoretical Neuroscience*. The MIT Press, Cambridge, Massachusetts, 2001.

[40] P. Miller. *An introductory course in computational neuroscience*. MIT Press, Cambridge, MA, 2018.

[41] G. B. Ermentrout. Phase-plane analysis of neural nets. *In The handbook of brain theory and neural networks (MIT Press, M. A. Arbib, Ed.)*, pages 881–885, 1998.

[42] A. Goldbeter and D. E Koshland. An amplified sensitivity arising from covalent modification in biological systems. *Proc. Natl. Acad. Sci. USA*, 78:6840–6844, 1981.

[43] D. Lederman, R. Patel, O. Itani, and H. G. Rotstein. Parameter estimation in the age of degeneracy and unidentifiability. *Mathematics*, 10:170 (1:35), 2022.

[44] H. G. Rotstein and F. Nadim. Frequency preference in two-dimensional neural models: a linear analysis of the interaction between resonant and amplifying currents. *J. Comp. Neurosci.*, 37:9–28, 2014.

[45] H. G. Rotstein. Spiking resonances in models with the same slow resonant and fast amplifying currents but different subthreshold dynamic properties. *J. Comp. Neurosci.*, 43:243–271, 2017.

[46] C. C. Lin and L. A. Segel. *Mathematics applied to deterministic problems in the natural sciences*. SIAM (Classics in Applied Mathematics), 1988.

[47] L. Segel and A. Goldbeter. Scaling in biochemical kinetics: dissection of a relaxation oscillator. *J. Math. Biol.*, 32:147–160, 1994.

[48] L. Segel and M. Slemrod. The quasi-steady state assumption: A case study in perturbation. *SIAM Review*, 31:446–477, 1989.

[49] L. Segel. Simplification and scaling. *SIAM Review*, 14:547–551, 1972.

[50] R. Bellman and K. M. Armstrong. On structural identifiability. *Math. Biosci.*, 7:329–339, 1970.

[51] Y.-H. Kao and M. C. Eisenberg. Practical unidentifiability of a simple vector-borne disease model: Implications for parameter estimation and intervention assessment. *Epidemics*, 25:89–100, 2018.

[52] C. Cobelli and J.J. DiStefano. Parameter and structural identifiability concepts and ambiguities: a critical review and analysis. *Am. J. Physiol.*, 239:R7–R24, 1980.

[53] F.-G. Wieland, A. L. Hauber, M. Rosenblatt, C. Tonsing, and J. Timmer. On strutural and practical identifiability. *Curr. Op. Neurobiol.*, 25:60–69, 2021.

[54] A. F. Villaverde, A. Barreiro, and A. Papachristodoulou. Structural identifiability of dynamic systems biology models. *PLoS Comp. Biol.*, 12:e1005153, 2016.

[55] W. Gerstner, W. M. Kistler, R. Naud, and L. Paninski. *Neuronal dynamics: From single neurons to networks and models of cognition*. Cambridge University Press, 2014.

A   Degeneracy in neuronal firing rate NFBL and IFFL circuits

A.1   Neuronal rate models

The rate models describing the evolution of the instantaneous firing rates of excitatory (E) and inhibitory (I) networks (Fig. 11-A) in their simplest form [37–41] are given by

$$\tau_E \frac{dr_E}{dt} = -r_E + F_E[\, J_{EE}\, r_E - J_{EI}\, r_I + I(t)\,], \tag{84}$$

$$\tau_I \frac{dr_I}{dt} = -r_I + F_I[\, J_{IE}\, r_E - J_{II}\, r_I + \xi\, I(t)\,], \tag{85}$$

where r_E and r_I are the rates of the E- and I-nodes, τ_E and τ_I (ms) are the time constants, $I(t)$ is the input to the E-node, $\xi\, I(t)$ is the input to the I-node, and J_{EE}, J_{EI}, J_{IE} and J_{II} are the connectivity weights (J_{XZ} represents the connectivity weight from the Z-node to the X-node). The input-output functions F_E and F_I are monotonically increasing. Typical examples are shown in Fig. 11-B. For the NFBL rate models, $\xi = 0$, and for the IFFL rate models, $J_{EI} = 0$.

From the topology point of view, this type of rate E-I network models are similar to the NFBL and IFFL circuits studied above. However, from the dynamics point of view, the time constants τ_E and τ_I add richness to temporal behavior of the circuits' patterns.

A.2   Degeneracy in the NFBL and IFFL circuits: linear neuronal rate models

From (84)-(85), the linear rate models for the excitatory-inhibitory (E-I) network (Fig. 11-A) is given by

$$\tau_E \frac{dr_E}{dt} = -(1 - J_{EE})\, r_E - J_{EI}\, r_I + A, \tag{86}$$

$$\tau_I \frac{dr_I}{dt} = J_{IE}\, r_E - (1 + J_{II})\, r_I + \xi\, A, \tag{87}$$

where A is a constant. These models can be thought of as linearization of rate models, or as describing the dynamics of threshold-linear models (Fig. 11-B2) in the region of positive values for the argument of the ReLux function.

From (11)-(13) in Section 2.2.1, system (87)-(87) can be rewritten as

$$\frac{d^2x}{dt} + B\frac{dx}{dt} + C\, x = Q\, A \tag{88}$$

where

$$B = \frac{(1 - J_{EE})\, \tau_I + (1 + J_{II})\, \tau_E}{\tau_E\, \tau_I}, \tag{89}$$

$$C = \frac{(1 - J_{EE})\, (1 + J_{II}) + J_{EI}\, J_{IE}}{\tau_E\, \tau_I}, \tag{90}$$

and

$$Q = \frac{1 + J_{II} - \xi\, J_{EI}}{\tau_E\, \tau_I}. \tag{91}$$

A.2.1 Determining the model parameters from the model attributes: NFBL

From (89)-(91) for $\xi = 0$,

$$J_{II} = Q\,\tau_E\,\tau_I - 1, \tag{92}$$

$$J_{EE} = 1 - (B - Q)\,\tau_E, \tag{93}$$

and

$$J_{EI}\,J_{IE} = C\,\tau_E\,\tau_I - (B - Q)\,Q\,\tau_E. \tag{94}$$

For fixed values of τ_E and τ_I, J_{II} is uniquely determined by Q and J_{EE} is uniquely determined by B and Q. However, there are multiple combinations of J_{EI} and J_{IE} that satisfy eq. (94). This type of degeneracy is the result of the multiple balances between network excitation and inhibition as for the NFBL circuits discussed in the main body of the paper.

The presence of degeneracy within and across circuit types and its dependence on the model parameters follow from the following observations.

A.2.2 Determining the model parameters from the model attributes: IFFL

From (89)-(91) for $J_{IE} = 0$,

$$J_{II} = \frac{\tau_I}{2}\,[\,B \pm \sqrt{B^2 - 4\,C}\,] - 1, \tag{95}$$

$$J_{EE} = 1 - \frac{2\,C\,\tau_E}{B \pm \sqrt{B^2 - 4\,C}}, \tag{96}$$

and

$$\xi\,J_{EI} = \frac{\tau_I}{2}\,[\,B \pm \sqrt{B^2 - 4\,C}\,] - Q\,\tau_E\,\tau_I. \tag{97}$$

For fixed values of τ_E and τ_I, J_{EE} and J_{II} are uniquely determined by B and C. However, there are multiple combinations of ξ and J_{EI} that satisfy eq. (97). This type of degeneracy is the result of the multiple balances between the activation of the inhibitory node and the inhibition this node exertes on the excitatory node, as for the IFFL circuits discussed in the main body of the paper.

Supplementary Material

Figure 11: **Negative feedback loop (NFBL) and incoherent feedforward loop (IFFL): schematic diagram for excitatory-inhibitory (E-I) firing rate models**. **A.** Combined NFBL and IFFL circuit of a neuronal excitatory - inhibitory (E-I) network. The circuit represents a NFBL for $\xi = 0$ and a IFFL for $J_{IE} = 0$. The input arrives into the nodes E (with strength given by I) and I (with strength given by $\xi\, I$). The node E activates the node I (synaptic weight J_{IE}), which in turn inhibits the node E (synaptic weight J_{EI}). The two nodes also exhibit self-excitation (synaptic weight J_{EE}) and self-inhibition (synaptic weight J_{II}, respectively. The output is the firing rate of the node E. **B.** Representative input-output functions F. **B1.** Sigmoid: $F(x) = (1 + e^{-x})^{-1}$. **B2.** Threshold-linear: $F(x) = [x]_+ = H(x)\, x$ where $H(x)$ is the Heaviside function. **B3.** Threshold-nonlinear: $F(x) = H(x)\, H(1-x)\, x^2 + H(x-1)\, 2\, \sqrt{x - 3/4}$.

Figure S1: **Degeneracy within circuit types in the presence of Divisive nonlinearities: representative examples or adaptive responses (to a constant input).** We used System (3)-(4) with $x(0) = y(0) = 0$ and $\Gamma(x, k_2\, y, I)$ given by eq. (7). **A, B.** Adaptive responses for $A_c = 1$ ($A_s = 0$). **C, D.** Impedance amplitude and phase profiles for $A_s = 1$ ($A_c = 0$). **A.** Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$, $\xi = 0$ (blue), $k_1 = 1$, $k_2 = 1$, $k_3 = 0.1$, $k_4 = 0.05$, $\xi = 0$ (dashed-red). **B.** Parameter values: $K_1 = 1$, $K_2 = 2$, $K_3 = 0$, $K_4 = 0.015$, $\Xi = 0.05$ (blue), $K_1 = 1$, $K_2 = 0.4$, $K_3 = 0$, $K_4 = 0.015$, $\Xi = 0.25$ (dashed-red). **C.** Same parameter values and color-code as in A. **D.** Same parameter values and color-code as in B.

Figure S2: **Quasi-degeneracy across circuit types in the presence of Divisive nonlinearities: representative examples of adaptive responses (to a constant input).** We used System (3)-(4) with $x(0) = y(0) = 0$ and $\Gamma(x, k_2 \, y, I)$ given by (7). **A, B.** Adaptive responses for $A_c = 1$ $(A_s = 0)$. **C.** Impedance amplitude and phase profiles for $A_s = 1$ $(A_c = 0)$. Degeneracy is disrupted in response to oscillatory inputs. **A.** Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$, $\xi = 0$ (blue), $K_1 = 0.915$, $K_2 = 2$, $K_3 = 0$, $K_4 = 0.0541$, $\Xi = 0.1303$ (dashed-red). **B.** Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$, $\xi = 0$ (blue). For the linear model we used System (1)-(2) with $K_1 = 1.0455$, $K_2 = 2$, $K_3 = 0$, $K_4 = 0.1161$, $\Xi = -0.0197$. For these parameter values, the eigenvalues are given by $r_1 = -0.1161$ and $r_2 = -1.0455$. **C.** Quasi-degeneracy breaks in response to oscillatory inputs. The parameter values and color-code are as in A and B.

Figure S3: **Degeneracy within circuit types in the presence of Divisive nonlinearities: representative examples or adaptive responses (to a constant input).** We used System (3)-(4) with $x(0) = y(0) = 0$ and $\Gamma(x, k_2\, y, I)$ given by eq. (8). **A, B.** Adaptive responses for $A_c = 1$ ($A_s = 0$). **C, D.** Impedance amplitude and phase profiles for $A_s = 1$ ($A_c = 0$). **A.** Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$, $\xi = 0$ (blue), $k_1 = 1$, $k_2 = 1$, $k_3 = 0.1$, $k_4 = 0.05$, $\xi = 0$ (dashed-red). **B.** Parameter values: $K_1 = 1$, $K_2 = 2$, $K_3 = 0$, $K_4 = 0.015$, $\Xi = 0.05$ (blue), $K_1 = 1$, $K_2 = 0.4$, $K_3 = 0$, $K_4 = 0.015$, $\Xi = 0.25$ (dashed-red). **C.** Same parameter values and color-code as in A. **D.** Same parameter values and color-code as in B.

Figure S4: **Quasi-degeneracy across circuit types in the presence of Divisive nonlinearities: representative examples of adaptive responses (to a constant input).** We used System (3)-(4) with $x(0) = y(0) = 0$ and $\Gamma(x, k_2\, y, I)$ given by (8). **A, B.** Adaptive responses for $A_c = 1$ ($A_s = 0$). **C.** Impedance amplitude and phase profiles for $A_s = 1$ ($A_c = 0$). Degeneracy is disrupted in response to oscillatory inputs. **A.** Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$, $\xi = 0$ (blue), $K_1 = 0.9594$, $K_2 = 2$, $K_3 = 0$, $K_4 = 0.0855$, $\Xi = 0.0464$ (dashed-red). **B.** Parameter values: $k_1 = 1$, $k_2 = 2$, $k_3 = 0.05$, $k_4 = 0.05$, $\xi = 0$ (blue). For the linear model we used System (1)-(2) with $K_1 = 1.0129$, $K_2 = 2$, $K_3 = 0$, $K_4 = 0.1178$, $\Xi = 0.0291$. For these parameter values, the eigenvalues are given by $r_1 = -0.1178$ and $r_2 = -1.0129$. **C.** Quasi-degeneracy breaks in response to oscillatory inputs. The parameter values and color-code are as in A and B.