AC-BioSD : A biomolecular signal differentiator module with enhanced performance

Emmanouil Alexis, José L. Avalos, Luca Cardelli, Antonis Papachristodoulou, *Fellow, IEEE*

Abstract— Temporal gradient estimation is a pervasive phenomenon in natural biological systems and holds great promise for synthetic counterparts with broad-reaching applications. Here, we advance the concept of BioSD signal differentiation by introducing a novel biomolecular topology, termed AC-BioSD. Its structure allows for insensitivity to input signal changes and high precision in terms of signal differentiation, even when operating far from nominal conditions. Concurrently, disruptive high-frequency signal components are effectively attenuated. In addition, the usefulness of our topology in biological regulation is highlighted via a PID bio-control scheme with set point weighting and filtered derivative action in both the deterministic and stochastic domains.

I. INTRODUCTION

Estimating time derivatives of biomolecular signals is an essential process of several natural biological systems. Bacterial chemotaxis [1] stands as a notable example. This navigation mechanism guides bacteria, such as *Escherichia coli*, towards beneficial chemicals (*attractants*) and away from harmful ones (*repellents*). It relies on a temporal sampling strategy enabling bacteria to calculate temporal gradients in order to infer spatial ones.

Designing reliable biomolecular topologies capable of (mathematically) differentiating signals, such as the concentration of biochemical substances or light, can be pivotal in addressing challenges in the realm of Synthetic Biology [2]–[4]. For instance, such topologies can be utilized as speed biosensors to monitor the rate of change with respect to biomolecular signals of interest. These biosensors are therefore able to assess cellular uptake and secretion rates of biomolecules, rendering them powerful tools for bioremediation purposes [5], [6] or for establishing efficient interactions within synthetic microbial communities for a variety of applications [7]–[10]. In parallel, derivative action allows the development of advanced regulation strategies. For example, Proportional-Integral-Derivative (PID) control constitutes one of the cornerstones of control engineering [11]. Recent *in-silico* studies have compellingly showcased the benefits of derivative control within PID bio-control schemes, such as enhanced dynamic performance and mitigated stochastic noise. These schemes include implementations based on nucleic acid strand displacement systems, single cells as well as microbial consortia [12]–[18].

A convenient and effective way of realizing derivative action in a biological setting is by leveraging the concept of *BioSD* (*Biomolecular Signal Differentiators*), initially introduced in [19]. *BioSD* motifs can serve as tunable,

general-purpose signal differentiator modules around their nominal operation. Under appropriate tuning, they are able to compute the first derivative of a biomolecular signal with high accuracy. At the same time, they offer protection against undesired amplification of high-frequency signal components through an embedded second-order low-pass filter. Additionally, they provide considerable experimental flexibility, and their output is encoded as a species concentration which simplifies measurement procedures. *BioSD* modules can also be employed for derivative control, potentially in conjunction with proportional and integral action (PID control) [17]. Note that different approaches to realizing derivative action (including derivative control) via biochemical interactions have been proposed in the recent literature [12]–[16], [18], [20]–[22]. For a concise comparative discussion, we refer the reader to [23].

In this work, we expand upon the concept of *BioSD* signal differentiation by introducing a novel BioSD topology with enhanced capabilities, termed *Autocatalytic-BioSD* (*AC-BioSD*), using the *BioSD-III* topology [19] as its structural foundation. The distinguishing feature of *AC-BioSD* lies in the fact that the input excitation is applied through an autocatalytic biochemical reaction. Notably, this modification does not add structural complexity in terms of the number of reactions and species. However, it endows *AC-BioSD* with significant advantages. Firstly, contrary to *BioSD-III*, the ability of the former to differentiate (or attenuate) input signals is independent of the input excitation reaction, allowing fine-tuning based exclusively on its intrinsic characteristics. At the same time, its behavior away from the nominal operation (non-local behavior) remains remarkably reliable, whereas that of *BioSD-III* can be greatly compromised. Furthermore, we demonstrate how *AC-BioSD* can be used for derivative control by adapting the PID scheme described in [17] and make comparisons with PI control as well as with the same PID scheme based on *BioSD-III*. Finally, it is important to emphasize that this study considers only realistic (bounded) physical signals of finite time duration which can be considered both differentiable and Fourier-transformable [19], [24].

The paper is structured as follows: Section II provides a brief background, encompassing modeling principles, computational approaches, and the concepts of BioSD signal differentiation as well as a special PID bio-control strategy. Section III presents the structure and the local behavior of the AC-BioSD module. Section IV examines its non-local ability to differentiate signals and Section V concentrates on derivative control. Lastly, Section VI summarizes our work and discusses future experimental and theoretical research avenues.

II. BACKGROUND

A. Modeling principles and computational analysis

We use three main types of biochemical reactions to structurally describe the biomolecular topologies herein, which

We would like to thank Prof. Ioannis G. Kevrekidis for his insightful comments on the manuscript. E.A. (corresponding author) and J.L.A. are with the Department of Chemical and Biological Engineering, Princeton University, Princeton, NJ, 08544 USA. E-mail:{ea2063, javalos}@princeton.edu. L.C. is with the Department of Computer Science, University of Oxford, Oxford, OX1 3QD, UK. E-mail: luca.cardelli@cs.ox.ac.uk. A.P. is with the Department of Engineering Science, University of Oxford, Oxford, OX1 3PJ, UK. E-mail:antonis@eng.ox.ac.uk. E.A. and J.L.A. were supported by the U.S. DOE-BER (DE-SC0022155) and U.S. NSF (MCB-2300239).

are aligned with the law of mass action [19], [25], [26]: general transformation of reactants into products, catalytic production and catalytic inhibition. Assuming A, B are two biochemical species, these reactions take the following general form $A \longrightarrow B$, $A \longrightarrow A+B$, $A+B \longrightarrow A$, respectively. The corresponding graphical representations are given in Fig. 1(a). Note that autocatalytic production can be regarded as a special case of catalytic production where a reactant enables its own formation, potentially in the presence of some other reactant with or without the latter being consumed - for example $A+B \longrightarrow A+2B$ or $A+B \longrightarrow 2B$, respectively.

To study the deterministic dynamics of the topologies (Sections III, IV, V), we use Ordinary Differential Equation (ODE) models and perform simulations in MATLAB (Mathworks). To investigate their stochastic behavior (Section V), we employ the Linear Noise Approximation (LNA) of the Chemical Master Equation (CME) [27] and perform simulations in Kaemika [28].

B. BioSD-III module

The architecture of *BioSD-III* [19] is illustrated in Fig. 1(b) and its dynamics can be modelled as:

$$\dot{X}_1 = k_{in}U + b - k_1X_1X_2 + k_1X_1X_3 - \delta X_1 \tag{1a}$$
$$\dot{X}_2 = k_2X_1 - \eta X_2X_3 \tag{1b}$$
$$\dot{X}_3 = k_3 - \eta X_2X_3 \tag{1c}$$

where k_{in}, b, k_1, k_2, $\eta \in \mathbb{R}_+$. Here U is the input excitation process, corresponding to one of the following reactions: $U \longrightarrow X_1$ or $U \longrightarrow U+X_1$ (at rate k_{in}); these can be summarized by the notation $\varnothing \xrightarrow{U} X_1$ as in Fig. 1(a).

We now discuss some important characteristics of *BioSD-III* which are proved in [19]. Given any non-negative constant input U^*, system (1) has a unique positive steady state (X_1^*, X_2^*, X_3^*) which is locally exponentially stable. Assuming sufficiently small deviations u, x_1, x_2, x_3 around $(U^*, X_1^*, X_2^*, X_3^*)$, its input/output relation can be described in the Laplace domain by the transfer function:

$$\tilde{H}(s) = \frac{\tilde{x}_1(s)}{\tilde{u}(s)} = \frac{k_{in}}{k_1k_3} \frac{s}{\varepsilon(s^2+s)+1} \tag{2}$$

where s is the Laplace variable (complex frequency) and $\tilde{x}_1(s)$, $\tilde{u}(s)$ are the Laplace transform of x_1, u, respectively. Moreover:

$$\varepsilon = \frac{k_2^2}{k_1k_3^3}(k_{in}U^*+b)^2 \tag{3}$$

Equation (2) represents an ideal signal differentiator (accompanied by a constant gain) in series with a second-order low pass filter. Moving now to the frequency response of *BioSD-III*, we obtain via Fourier Transform:

$$\tilde{H}(j\omega) = \frac{\tilde{x}_1(j\omega)}{\tilde{u}(j\omega)} = \frac{k_{in}}{k_1k_3} \frac{j\omega}{\varepsilon(-\omega^2+j\omega)+1}$$

where ω is the (real) frequency, $j = \sqrt{-1}$ is the imaginary unit and $\tilde{x}_1(s)$, $\tilde{u}(s)$ are the Fourier transform of x_1, u, respectively.

Finally, in the time domain, for a sufficiently slow input signal of sufficiently long time duration, the output of *BioSD-III* can be approximated by:

$$X_1 = \frac{k_{in}}{k_1k_3}\dot{U} + \frac{k_3}{k_2} \tag{4}$$

C. PID control and BioSD action

Fig. 1(c) depicts a biochemical reaction network implementation of a PID control scheme with *set point weighting* and filtered derivative action, as introduced in [17]. Here, derivative control is carried out by BioSD-III (see species X_1, X_2, X_3), which interacts with the output species, Y, via a production-inhibition loop. BioSD-III contributes to the proportional control involved, as well.

The corresponding closed-loop dynamics is given by the following set of ODEs:

$$\dot{Y} = F + \underbrace{\beta_1R - \alpha_1Z_0Y + \alpha_4Z_1 - \alpha_3Z_2Y - \alpha_7X_1Y}_{\text{control input signal}} \tag{5a}$$
$$\dot{Z}_1 = \beta_2R - \alpha_5Z_1Z_2 \tag{5b}$$
$$\dot{Z}_2 = \alpha_2Y - \alpha_5Z_1Z_2 \tag{5c}$$
$$\dot{X}_1 = \alpha_6Y + \alpha_8 - \alpha_{11}X_1X_2 + \alpha_{11}X_1X_3 \tag{5d}$$
$$\dot{X}_2 = \alpha_9X_1 - \alpha_{12}X_2X_3 \tag{5e}$$
$$\dot{X}_3 = \alpha_{10} - \alpha_{12}X_2X_3 \tag{5f}$$

where $\alpha_i \in \mathbb{R}_+$ with $i \in \mathbb{N}$ and $1 \leq i \leq 12$. R is a non-negative reference signal, β_1, β_2 are non-negative scaling parameters and Z_0 is an auxiliary species with constant concentration. F denotes potential interactions with respect to Y inside the cloud network.

Given some constant value of the reference signal, R^*, we assume the existence of a (locally) asymptotically stable and biologically meaningful steady state (indicated by $*$ next to the respective variables) of system (5). Focusing on the closed-loop behavior around this steady state, we further assume sufficiently small deviations of the (uppercase) variables which are represented by the corresponding lowercase letters. As shown in [17], the control input signal in Equation (5a) can take the following form of a PID control law with *set point weighting* and filtered derivative action:

$$k_p(\lambda y_{sp} - y) + k_i \int_0^t (y_{sp} - y)\, d\tau - k_dx_1 \tag{6}$$

where: $y_{sp} = \dfrac{\beta_2 r}{\alpha_2}$ (set point), $\lambda = \dfrac{\beta_1}{\delta}$, $k_p = \dfrac{\alpha_2\delta}{\beta_2}$, $k_i = \dfrac{\alpha_4}{\alpha_2}$, $k_d = \dfrac{\alpha_4\alpha_7}{\alpha_3}$, $\delta = \dfrac{\beta_2(\alpha_1Z_0 + \alpha_3Z_2^* + \alpha_7X_1^*)}{\alpha_2}$, $\beta_2R^* = \dfrac{\alpha_2\alpha_4}{\alpha_3}$

Furthermore:

$$\frac{\tilde{x}_1(s)}{\tilde{y}(s)} = \frac{\alpha_6}{\alpha_{10}\alpha_{11}} \frac{s}{\varepsilon(s^2+s)+1}, \quad \varepsilon = \frac{\alpha_9^2}{\alpha_{10}^3\alpha_{11}}(\alpha_6Y^*+\alpha_8)^2$$

III. AC-BioSD MODULE

Fig. 2(a) illustrates the biomolecular architecture of *AC-BioSD*. It consists of the same biochemical reactions as *BioSD-III* except for the part of the input excitation process. Here, the latter corresponds to one of the following autocatalytic reactions: $U+X_1 \xrightarrow{k_{in}} U+2X_1$ or $U+X_1 \xrightarrow{k_{in}} 2X_1$. Note that the function of *AC-BioSD* remains the same regardless of which of the above reactions is adopted.

The dynamics of *AC-BioSD* is captured by the ODE

model:

$$\dot{X}_1 = k_{in}UX_1 + b - k_1X_1X_2 + k_1X_1X_3 - \delta X_1 \quad (7a)$$

$$\dot{X}_2 = k_2X_1 - \eta X_2X_3 \quad (7b)$$

$$\dot{X}_3 = k_3 - \eta X_2X_3 \quad (7c)$$

where k_{in}, b, k_2, k_1, $\eta \in \mathbb{R}_+$.

Theorem 1 For any positive constant input U^*, system (7) has a unique positive steady state which is locally exponentially stable.

Proof: By setting the time derivatives of system (7) to zero and taking into account that X_1, X_2, X_3 are always nonnegative as physical quantities, we get the following unique steady state:

$$X_1^* = \frac{k_3}{k_2} \quad (8a)$$

$$X_2^* = \frac{1}{2}\xi + \frac{1}{2}\sqrt{\xi^2 + 4\frac{k_3}{n}} \quad (8b)$$

$$X_3^* = -\frac{1}{2}\xi + \frac{1}{2}\sqrt{\xi^2 + 4\frac{k_3}{n}} \quad (8c)$$

with

$$\xi = \frac{1}{k_1}\left(\frac{k_2b}{k_3} + k_{in}U^* - \delta\right)$$

Note that k_{in}, b, k_1, k_2, $\eta \in \mathbb{R}_+$ which also entails $\sqrt{\xi^2 + 4\frac{k_3}{n}} > \xi$. Clearly, the steady state (8) is positive.

Jacobian linearization of system (7) around the fixed point (8) yields:

$$\begin{bmatrix} \dot{X}_1 \\ \dot{X}_2 \\ \dot{X}_3 \end{bmatrix} = \underbrace{\begin{bmatrix} -\dfrac{k_2b}{k_3} & -\dfrac{k_1k_3}{k_2} & \dfrac{k_1k_3}{k_2} \\ k_2 & -\eta X_3^* & -\eta X_2^* \\ 0 & -\eta X_3^* & -\eta X_2^* \end{bmatrix}}_{M} \begin{bmatrix} X_1 \\ X_2 \\ X_3 \end{bmatrix}$$

We calculate the characteristic polynomial of M as:

$$P(s) = \det(sI - G_2) = s^3 + \zeta_2s^2 + \zeta_1s + \zeta_0$$

with $\zeta_2 = \eta(X_2^* + X_3^*) + \frac{k_2b}{k_3}$, $\zeta_1 = \eta\frac{k_2b}{k_3}(X_2^* + X_3^*) + k_1k_3$ and $\zeta_0 = \eta k_1k_3(X_2^* + X_3^*)$. According to Routh-Hurwitz criterion, $P(s)$ has all roots in the open-half plane if and only if $\zeta_2, \zeta_1, \zeta_0 > 0$ and $\zeta_2\zeta_1 > \zeta_0$. The first condition clearly holds. For the second one we have:

$$\left(\eta(X_2^* + X_3^*) + \frac{k_2b}{k_3}\right)\left(\eta\frac{k_2b}{k_3}(X_2^* + X_3^*) + k_1k_3\right) >$$
$$\eta k_1k_3(X_2^* + X_3^*)$$

or

$$\eta^2\frac{k_2b}{k_3}(X_2^* + X_3^*)^2 + \eta\frac{k_2^2b^2}{k_3^2}(X_2^* + X_3^*) + bk_2k_1 > 0$$

which is always true as a sum of positive quantities. Consequently, M is Hurwitz and steady state (8) is locally exponentially stable for system (7).

Theorem 2 In the neighbourhood of $(U^*, X_1^*, X_2^*, X_3^*)$, the input/output relation of system (7) in the Laplace domain is given by $\dfrac{\tilde{x}_1(s)}{\tilde{u}(s)} = \dfrac{k_{in}}{k_1k_2}\dfrac{s}{\varepsilon(s^2 + s) + 1}$ with $\varepsilon = \dfrac{b^2k_2^2}{k_1k_3^3}$.

Proof: We adopt the coordinate transformations: $u = U - U^*$, $x_1 = X_1 - X_1^*$, $x_2 = X_2 - X_2^*$, $x_3 = X_3 - X_3^*$ de-

noting sufficiently small deviations around $(U^*, X_1^*, X_2^*, X_3^*)$. Subsequently, through Jacobian linearization around the aforementioned fixed point, the local dynamics of system (7) is derived as:

$$\begin{bmatrix} \dot{x}_1 \\ \dot{x}_2 \\ \dot{x}_3 \end{bmatrix} = \underbrace{\begin{bmatrix} -\dfrac{k_2b}{k_3} & -\dfrac{k_1k_3}{k_2} & \dfrac{k_1k_3}{k_2} \\ k_2 & -\eta X_3^* & -\eta X_2^* \\ 0 & -\eta X_3^* & -\eta X_2^* \end{bmatrix}}_{M} \begin{bmatrix} x_1 \\ x_2 \\ x_3 \end{bmatrix} + \begin{bmatrix} \dfrac{k_{in}k_3}{k_2} \\ 0 \\ 0 \end{bmatrix} u \quad (9)$$

By adopting the linear transformation $\phi = x_2 - x_3$, system (9) becomes:

$$\begin{bmatrix} \dot{x}_1 \\ \dot{\phi} \\ \dot{x}_3 \end{bmatrix} \begin{bmatrix} -\dfrac{k_2b}{k_3} & -\dfrac{k_1k_3}{k_2} & \dfrac{k_1k_3}{k_2} \\ k_2 & 0 & 0 \\ 0 & -\eta X_3^* & -\eta(X_2^* + X_3^*) \end{bmatrix} \begin{bmatrix} x_1 \\ \phi \\ x_3 \end{bmatrix} + \begin{bmatrix} \dfrac{k_{in}k_3}{k_2} \\ 0 \\ 0 \end{bmatrix} u \quad (10)$$

We next introduce the nondimensional variables: $t_n = \frac{bk_2}{k_3}t$, $x_{1n} = \frac{1}{\gamma}x_1$, $\phi_n = \frac{b}{\gamma k_3}\phi$, $u_n = \frac{bk_{in}}{\gamma k_1k_3}u$, where γ is an arbitrary scaling parameter that carries the same units as x_1. We also consider the nondemensional parameter

$$\varepsilon = \frac{b^2k_2^2}{k_1k_3^3} \quad (11)$$

Hence, focusing on the dynamics of x_1 and ϕ in system (10), we obtain: $\varepsilon\dot{x}_{1n} = -\varepsilon x_{1n} - n + u_n$ and $\dot{\phi}_n = x_{1n}$ or, equivalently,:

$$\varepsilon\ddot{x}_{1n} + \varepsilon\dot{x}_{1n} + x_{1n} = \dot{u}_n \quad (12)$$

Applying Laplace Transform to Equation (12) results in the following transfer function

$$\tilde{\Lambda}(s) = \frac{\tilde{x}_{1n}(s)}{\tilde{u}_n(s)} = \frac{s}{\varepsilon(s^2 + s) + 1}$$

If we now take into account the aforementioned nondimensional variables, we get:

$$\tilde{\Lambda}(s) = \frac{\tilde{x}_1(s)}{\tilde{u}(s)} = \frac{k_{in}}{k_1k_2}\frac{s}{\varepsilon(s^2 + s) + 1} \quad (13)$$

To study the frequency response of the above system, we apply Fourier Transform. Due to the existence of asymptotic stability, we can do that by setting $s = j\omega$ in Equation (13) to obtain:

$$\tilde{\Lambda}(j\omega) = \frac{\tilde{x}_1(j\omega)}{\tilde{u}(j\omega)} = \frac{k_{in}}{k_1k_2}\frac{j\omega}{\varepsilon(-\omega^2 + j\omega) + 1} \quad (14)$$

or, equivalently, $\tilde{\Lambda}(j\omega) = |\tilde{\Lambda}(j\omega)|\angle\phi_\Lambda(\omega)$ with:

$$|\tilde{\Lambda}(j\omega)| = \frac{k_{in}}{k_1k_2}\frac{\omega}{\sqrt{\varepsilon^2\omega^2 + (1 - \varepsilon\omega^2)^2}} \quad (15)$$

and

$$\angle\phi_\Lambda(\omega) = \arctan\left(\frac{1}{\varepsilon\omega} - \omega\right) \quad (16)$$

Perfect signal differentiation entails $|\tilde{\Lambda}(j\omega)| = \frac{k_{in}}{k_1k_2}\omega$ and $\angle\phi_\Lambda(\omega) = 90°$ whereas perfect signal attenuation entails $|\tilde{\Lambda}(j\omega)| = 0$.

Taking also into account the initial coordinate transformations as well as Equation (8a), the output of *AC-BioSD* in

the time domain can be approximated as:

$$X_1 = \frac{k_{in}}{k_1 k_2} \dot{U} + \frac{k_3}{k_2} \tag{17}$$

assuming a sufficiently slow input signal of sufficiently long time duration. Note that X_1^* can be regarded as our "x-axis" or "zero-level concentration" around of which signal differentiation is carried out.

As can be seen in Fig. 2(b)-(c), for a given positive ε, there is a "low-frequency" and a "high-frequency" range over which signal differentiation and signal attenuation is effectively performed, respectively. As ε increases, the latter expand towards the former (and vice versa). Different performance standards can therefore be met by appropriately tuning this parameter.

It is apparent that both *BioSD-III* and *AC-BioSD* exhibit filtered derivative action and their behavior around their nominal operation can be described by equations of the same form but characterized by some distinct parametrization differences. That is, the reaction rates involved generally influence the behavior of these modules in different ways (Equation (4) vs (17)). As already pointed out, the nondimensional parameter ε, which is a function of several reaction rates, plays a pivotal role for the appropriate tuning and, by extension, the reliable operation of the BioSD modules. As Equations (3), (11) indicate, in the case of *BioSD-III*, ε highly depends on the input excitation process since it is a function of both k_{in} and U^*. On the other hand, in the case of *AC-BioSD* ε is completely independent of that process. This particular attribute can be a major benefit for a circuit designer implementation-wise. More specifically, the topology of *AC-BioSD* can be designed to achieve certain performance requirements based solely of its internal reactions, eliminating the need of a priori knowledge of the input signal and/or the input reaction rate. This stands in contrast to *BioSD-III*, where the presence of different input signals/reaction rates may necessitate the re-tuning of other internal reactions of the topology (potentially during operation) which can be challenging in many biological settings [2]–[4].

IV. Non-local signal differentiation

Under suitable tuning, *BioSD-III* can act as a signal differentiator of high accuracy in the vicinity of its equilibrium point [19]. Nevertheless, as the system is driven away from this point the accuracy might drop and, in sufficiently distant operating regimes, the ability of signal differentiation can be entirely compromised. This happens because, as the system moves further from its equilibrium point, its inherent nonlinearities gradually become significant, changing its (nonlocal) behavior in an unfavorable manner. Interestingly, this is not the case for *AC-BioSD* whose signal differentiation capacity far from its equilibrium point shows remarkable consistency. In Fig. 3 we computationally demonstrate the above by applying appropriate input signals which allow us to investigate such operating regimes.

V. *AC-BioSD* derivative control

Fig. 4(a) illustrates how derivative control can be realized via the AC-BioSD module within the PID control scheme presented in Section II. C. For demonstration purposes, we consider a simple biological process of two mutually activated species [17], [26] inside the cloud network (this does not affect the generality of the PID architecture outside

the cloud network). The corresponding closed-loop dynamics is given by the ODE model:

$$\dot{Y} = F + \underbrace{\beta_1 R - \alpha_1 Z_0 Y + \alpha_4 Z_1 - \alpha_3 Z_2 Y - \alpha_7 X_1 Y}_{\text{control input signal}} \tag{18a}$$

$$\dot{Z}_1 = \beta_2 R - \alpha_5 Z_1 Z_2 \tag{18b}$$

$$\dot{Z}_2 = \alpha_2 Y - \alpha_5 Z_1 Z_2 \tag{18c}$$

$$\dot{X}_1 = \alpha_6 Y X_1 + \alpha_8 - \alpha_{11} X_1 X_2 + \alpha_{11} X_1 X_3 \tag{18d}$$

$$\dot{X}_2 = \alpha_9 X_1 - \alpha_{12} X_2 X_3 \tag{18e}$$

$$\dot{X}_3 = \alpha_{10} - \alpha_{12} X_2 X_3 \tag{18f}$$

where $F = \gamma_1 - \gamma_3 Y + \gamma_6 W$ and $\dot{W} = \gamma_2 - \gamma_4 W + \gamma_5 Y$.

Although, as expected, the dynamics of the derivative part of system (18) is different compared to the one in system (5), the remaining part of the two systems is identical. Consequently, using the methodology of Section III in [17], it is straightforward to show that the control input signal in Equation (18a) can be (locally) described by Equation (6) with the following modification regarding the derivative part (see Section III):

$$\frac{\tilde{x}_1(s)}{\tilde{y}(s)} = \frac{\alpha_6}{\alpha_9 \alpha_{11}} \frac{s}{\varepsilon(s^2 + s) + 1}, \quad \varepsilon = \frac{\alpha_8^2 \alpha_9^2}{\alpha_{10}^3 \alpha_{11}}$$

As illustrated in Fig. 4(b), both the AC-BioSD- and the BioSD-III-based PID controller practically yield the same output response in the deterministic setting, characterized by smooth transient dynamics - the overshoot and the oscillations observed in the PI control case are eliminated by the anticipatory derivative action. Simultaneously, Fig. 4(c) shows that both PID controllers, when compared to the PI controller, significantly reduce the standard deviation of the output, denoted here as σ, at steady-state. However, in this specific example, the standard deviation in the AC-BioSD case is slightly elevated compared to the one in the BioSD-III case.

VI. Conclusion

In this study, we present the *AC-BioSD* module, a novel *BioSD* design for signal differentiation in biomolecular environments. We built upon the architecture of the previously proposed *BioSD-III* module and appropriately embedded an autocatalytic input excitation process. Unlike the latter module, this structural modification renders the characteristics of *AC-BioSD*'s function insensitive to changes of the input reaction and offers greater reliability away from nominal conditions. Moreover, *AC-BioSD* can be conveniently employed for derivative control contributing to improved dynamic performance and suppression of stochastic noise.

We anticipate that the design approach introduced here will facilitate the experimental implementation of robust and predictable synthetic circuits. Notably, *AC-BioSD* consists of a finite set of (unimolecular and bimolecular) reactions following mass-action kinetics and, therefore, is suitable for molecular programming applications. For example, detailed information on how such a topology can be realized *in vitro* using strand displacement DNA-based chemistry is available in [12], [26]. In terms of *in vivo* implementations, the core parts of *AC-BioSD* (which are similar to the original *BioSD* modules) can be realized through gene expression systems – see, for instance, [19] for potential implementations in *Escherichia coli*. As for the autocatalytic reaction, it could be realized through a gene expression system based on positive feedback [25]. A promising candidate might be a

(a)   (b)   (c)

Fig. 1: (a) Biochemical reactions considered in this work [26]. (b) *BioSD-III* module with U and X_1 being the input and the output signal/species, respectively [19]. (c) PID control architecture with *set point weighting* and filtered derivative action [17]. The cloud network represents an arbitrary biomolecular process including the target/output species Y. The controller species are shown outside the cloud network.

(a)   (b)   (c)

Fig. 2: (a) *AC-BioSD* module with U and X_1 being the input and the output signal/species, respectively. (b) Bode plot based on Equations (15), (16). For simplicity we assume $\frac{k_{in}}{k_1 k_2} = 1$. (c) Simulated output response of *AC-BioSD* (system (7)) with $k_{in} = 1$, $b = 220$, $k_1 = 1$, $k_2 = 1$, $\eta = 30$. Equation (11) therefore gives $\varepsilon = 0.0484$. Moreover, we apply the input signal $U + U_{hfn}$ for $0 \leq t \leq 100$, where $U = 1.2 + sin(\omega t)$ represents the useful information (signal to be differentiated) and $U_{hfn} = 0.2 sin(400 \omega t)$ represents unwanted high-frequency noise (signal to be attenuated). Note that the output response is practically the same to the one of the *BioSD* modules in [19] (see Fig. 5.A) where the same ε and input signal are considered.

(a)   (b)   (c)

Fig. 3: Simulated output response of *AC-BioSD* (system (7)) and *BioSD-III* (system (1)) to the following input signals: (a) $e^{0.08t} + 0.01(t^3 + t^2 + t + 1)$ (b) $60 + 30 sin(t) + 20 sin(1.5t)$ (c) the sum of (a), (b) for $0 \leq t \leq 100$. The paramater tuning corresponds to the performance standards adopted in Fig. 2(c) (for details regarding *BioSD-III* see Fig. S1.B and Fig. 5.A in [19]).

(a) (b) (c)

Fig. 4: (a) Biochemical reaction representation of system (18). For comparison reasons, the simulated output responses and standard deviations depicted in (b) and (c), respectively, refer to the scenario considered in [17] (Fig. 4) using the same parameter values. Note that for the case of the *AC-BioSD*-based PID control (system (18)) we select $\alpha_6 = 1$ instead of $\alpha_6 = 100$ (which is used for the case of the *BioSD-III*-based PID control). This facilitates comparison as the respective derivative gains become equal.

protein, such as a transcription factor, which activates its own expression in the presence of a second chaperone protein [29] or light [30].

Finally, an intriguing theoretical extension of this work would involve exploring further the *AC-BioSD* concept using other *BioSD* modules, namely *BioSD-I* or *BioSD-II* [19], as structural foundations. Subsequently, investigation and comparison of different ways for applying derivative control, for instance within PID regulation strategies, using various *(AC-) BioSD* modules would be of great interest. Performance characteristics of the output response that merit attention include deterministic features such as settling time, rising time, and overshoot as well as estimation of the variance or higher moments in the stochastic setting.

REFERENCES

[1] U. Alon, *An Introduction to Systems Biology: Design Principles of Biological Circuits*. CRC Press, 2019.

[2] D. Del Vecchio, Y. Qian, R. M. Murray, and E. D. Sontag, "Future systems and control research in synthetic biology," *Annual Reviews in Control*, vol. 45, pp. 5–17, 2018.

[3] H. Steel, G. Lillacci, M. Khammash, and A. Papachristodoulou, "Challenges at the interface of control engineering and synthetic biology," in *2017 IEEE 56th Annual Conference on Decision and Control (CDC)*. IEEE, 2017, pp. 1014–1023.

[4] M. H. Khammash, "Cybergenetics: Theory and applications of genetic control systems," *Proceedings of the IEEE*, vol. 110, no. 5, pp. 631–658, 2022.

[5] E. L. Rylott and N. C. Bruce, "How synthetic biology can help bioremediation," *Current Opinion in Chemical Biology*, vol. 58, pp. 86–95, 2020.

[6] D. H. Pieper and W. Reineke, "Engineering bacteria for bioremediation," *Current opinion in biotechnology*, vol. 11, no. 3, pp. 262–270, 2000.

[7] J. S. Yu, C. Correia-Melo, F. Zorrilla, L. Herrera-Dominguez, M. Y. Wu, J. Hartl, K. Campbell, S. Blasche, M. Kreidl, A.-S. Egger *et al.*, "Microbial communities form rich extracellular metabolomes that foster metabolic interactions and promote drug tolerance," *Nature microbiology*, vol. 7, no. 4, pp. 542–555, 2022.

[8] M. Gasparek, H. Steel, and A. Papachristodoulou, "Deciphering mechanisms of production of natural compounds using inducer-producer microbial consortia," *Biotechnology Advances*, p. 108117, 2023.

[9] S. van Vliet, C. Hauert, K. Fridberg, M. Ackermann, and A. Dal Co, "Global dynamics of microbial communities emerge from local interaction rules," *PLoS computational biology*, vol. 18, no. 3, p. e1009877, 2022.

[10] G. Micali, A. M. Hockenberry, A. Dal Co, and M. Ackermann, "Minorities drive growth resumption in cross-feeding microbial communities," *Proceedings of the National Academy of Sciences*, vol. 120, no. 45, p. e2301398120, 2023.

[11] K. J. Åström and R. M. Murray, *Feedback systems: an introduction for scientists and engineers*. Princeton University Press, 2021.

[12] M. Whitby, L. Cardelli, M. Kwiatkowska, L. Laurenti, M. Tribastone, and M. Tschaikowski, "PID control of biochemical reaction networks," *IEEE Transactions on Automatic Control*, 2021.

[13] N. M. Paulino, M. Foo, J. Kim, and D. G. Bates, "PID and state feedback controllers using dna strand displacement reactions," *IEEE Control Systems Letters*, vol. 3, no. 4, pp. 805–810, 2019.

[14] M. Chevalier, M. Gómez-Schiavon, A. H. Ng, and H. El-Samad, "Design and analysis of a proportional-integral-derivative controller with biological molecules," *Cell Systems*, vol. 9, no. 4, pp. 338–353, 2019.

[15] S. Modi, S. Dey, and A. Singh, "Noise suppression in stochastic genetic circuits using PID controllers," *PLoS Computational Biology*, vol. 17, no. 7, p. e1009249, 2021.

[16] M. Filo, S. Kumar, and M. Khammash, "A hierarchy of biomolecular proportional-integral-derivative feedback controllers for robust perfect adaptation and dynamic performance," *Nature Communications*, vol. 13, no. 1, pp. 1–19, 2022.

[17] E. Alexis, L. Cardelli, and A. Papachristodoulou, "On the design of a pid bio-controller with set point weighting and filtered derivative action," *IEEE Control Systems Letters*, vol. 6, pp. 3134–3139, 2022.

[18] V. Martinelli, D. Salzano, D. Fiore, and M. di Bernardo, "Multicellular pd control in microbial consortia," *IEEE Control Systems Letters*, 2023.

[19] E. Alexis, C. C. Schulte, L. Cardelli, and A. Papachristodoulou, "Biomolecular mechanisms for signal differentiation," *Iscience*, vol. 24, no. 12, 2021.

[20] W. Halter, R. M. Murray, and F. Allgöwer, "Analysis of primitive genetic interactions for the design of a genetic signal differentiator," *Synthetic Biology*, vol. 4.

[21] C. C. Samaniego, G. Giordano, and E. Franco, "Practical differentiation using ultrasensitive molecular circuits," in *2019 18th European Control Conference (ECC)*. IEEE, 2019, pp. 692–697.

[22] C. C. Samaniego, J. Kim, and E. Franco, "Sequestration and delays enable the synthesis of a molecular derivative operator," in *2020 59th IEEE Conference on Decision and Control (CDC)*. IEEE, 2020, pp. 5106–5112.

[23] E. Alexis, "Design and analysis of genetic feedback architectures for synthetic biology," Ph.D. dissertation, University of Oxford, 2023.

[24] K. B. Howell, *Principles of Fourier analysis*. CRC Press, 2016.

[25] D. Del Vecchio and R. M. Murray, *Biomolecular feedback systems*. Princeton University Press Princeton, NJ, 2015.

[26] E. Alexis, C. C. Schulte, L. Cardelli, and A. Papachristodoulou, "Regulation strategies for two-output biomolecular networks," *Journal of the Royal Society Interface*, vol. 20, no. 205, p. 20230174, 2023.

[27] L. Cardelli, M. Kwiatkowska, and L. Laurenti, "Stochastic analysis of chemical reaction networks using linear noise approximation," *Biosystems*, vol. 149, pp. 26–33, 2016.

[28] L. Cardelli, "Kaemika app: Integrating protocols and chemical simulation," in *International Conference on Computational Methods in Systems Biology*. Springer, 2020, pp. 373–379.

[29] T. S. Moon, C. Lou, A. Tamsir, B. C. Stanton, and C. A. Voigt, "Genetic programs constructed from layered logic gates in single cells," *Nature*, vol. 491, no. 7423, pp. 249–253, 2012.

[30] E. M. Zhao, Y. Zhang, J. Mehl, H. Park, M. A. Lalwani, J. E. Toettcher, and J. L. Avalos, "Optogenetic regulation of engineered cellular metabolism for microbial chemical production," *Nature*, vol. 555, no. 7698, pp. 683–687, 2018.