Inferring Neural Communication Dynamics from Field Potentials Using Graph Diffusion Autoregression

Felix Schwock[1,3*,] Julien Bloch[2,3], Karam Khateeb[2,3], Jasmine Zhou[2,3], Les Atlas[1], Azadeh Yazdan-Shahmorad[1,2,3*]

Estimating dynamic network communication is attracting increased attention, spurred by rapid advancements in multi-site neural recording technologies and efforts to better understand cognitive processes. Yet, traditional methods, which infer communication from statistical dependencies among distributed neural recordings, face core limitations: they do not model neural interactions in a biologically plausible way, neglect spatial information from the recording setup, and yield predominantly static estimates that cannot capture rapid changes in the brain. To address these issues, we introduce a graph diffusion autoregressive model. Designed for distributed field potential recordings, our model combines vector autoregression with a network communication process to produce a high-resolution communication signal. We successfully validated the model on simulated neural activity and recordings from subdural and intracortical micro-electrode arrays placed in macaque sensorimotor cortex demonstrating its ability to describe rapid communication dynamics induced by optogenetic stimulation, changes in resting state communication, and the trial-by-trial variability during a reach task.

Introduction

The coordinated interactions across different brain networks and subnetworks underlies cognitive processes[1–6], and disruptions of these interactions are linked to a range of neurological disorders[7–10]. Despite this demonstrated importance, we still do not fully understand how brain networks perform computations through the coordinated signaling of connected neurons and neural populations during natural behavior, following a disease or injury, or as the result of rehabilitative intervention. The development of new electrophysiological recording technologies such as large-scale micro-electrode arrays provides unique opportunities for measuring brain network activity simultaneously over multiple areas with high spatial and temporal resolution[11–16]. While this can in principle allow us to monitor network communication with better precision, a key challenge arises: Neural communication cannot be measured directly, but instead must be inferred from the recorded neural activity.

A common signal extracted from subdural and intracortical micro-electrode arrays is the local field potential (LFP), which describes voltage fluctuations in the extracellular space of neuronal tissue. For these signals, the most common approach for estimating neural communication is through functional connectivity (FC) analysis[17,18]. In general, FC measures define neural communication as the undirected (symmetric) or directed (asymmetric) statistical dependence between different measurements that can be inferred directly from data using either model-free approaches or very general model classes. A popular model class that underlies many FC measures,

[1]Department of Electrical and Computer Engineering, University of Washington, Seattle, WA, USA. [2]Department of Bioengineering, University of Washington, Seattle, WA, USA. Washington National [3]Primate Research Center, Seattle, WA, USA. *e-mail: fschwock@uw.edu; azadehy@uw.edu

such as Granger Causality or partial directed coherence, are multivariate vector autoregressive
(VAR) models[19–22]. Assuming two time series A and B, the key idea is that a directed
communication link from A to B exists when information from the past of A improves the
prediction of the future of B compared to only using past information of B itself. Some advantages
of VAR models include that they are easily interpretable, can capture a wide range of network
dynamics, are easy to fit to data, produce directed estimates of neural communication, and allow
for a frequency specific analysis of neural interactions. Hence, VAR based measures have been
successfully applied to various neurophysiological datasets to study changes due to stroke[23,24],
patterns of seizure propagation[25], or the rehabilitative effects of electrical or magnetic
stimulation[26–28].

Despite the many advantages, VAR models have a few key limitations: 1) They are general purpose
tools that describe statistical relations between time series rather than modeling neural
interactions in a biologically plausible way. 2) They do not incorporate information about the
spatial relation between the recording electrodes, and interactions between nearby sensors are
treated in the same way as interactions between distant ones. 3) Communication metrics based on
VAR models are typically derived from the model coefficients, which are assumed to be static
within a predefined time window. Therefore, these metrics are not well suited to capture fast
temporal changes and transient network effects, which have been shown to drive neural dynamics
and cognition[7,29–32] and underlie aberrant neurological processes such as the propagation of
epileptic seizures[33,34].

To address these shortcoming, we propose an alternative framework for estimating network level
neural communication dynamics from LFP recordings, by combining a biologically plausible
network diffusion process[35,36] with the autoregressive framework[37]. The resulting graph diffusion
autoregressive (GDAR) model naturally gives rise to a communication signal with millisecond
temporal resolution between nodes of a predefined graph, therefore incorporating the spatial
information of the recording array and describing highly transient communication events. To
demonstrate the utility of our framework, we tested the GDAR model on five, highly diverse
datasets. First, using synthetic data from various networks of Wilson-Cowan oscillators we
demonstrate that the high-resolution communication signal estimated by our model aligns with
the simulated interactions more accurately than standard VAR models. Next, using three micro-
electrocorticography (μECoG) and one Utah array dataset we demonstrate that the GDAR model
can be used to uncover transient communication dynamics evoked *during* cortical optogenetic
stimulation, highlight the trial-to-trial neural variability underlying a monkey's reach behavior,
and analyze changes in resting state neural communication *after* electrical stimulation. For all
datasets, we show that the GDAR model outperforms standard VAR models and other FC
measures and provides insights that cannot be obtained by other models. Finally, we show that
the GDAR model better generalizes to unseen data than VAR models.

Results
Graph diffusion autoregressive (GDAR) model. An overview of the GDAR model is shown
in Fig. 1 and a more detailed mathematical description can be found in Methods. First, the
electrode layout of the recording array is used to construct a sparse and locally connected graph,
with each electrode representing a node and with edges connecting nearby nodes Fig. 1a left). By
modeling the spatiotemporal evolution of neural activity observed at the nodes of the graph as a

parameterized diffusion process, the GDAR model transforms the neural activity into a directed
communication or information flow signal defined on the graph edges (Fig. 1a right). This
communication signal, which we will refer to as *GDAR flow*, describes the moment to moment
signaling between the nodes. Unlike classical functional connectivity analysis, which aggregates
information over multiple time points thereby estimating an average information flow, the GDAR
model transforms the neural activity at each time point into a flow signal without losing temporal
resolution. Therefore, it can be used to study transient communication events in the brain.

As with VAR models, the GDAR model can be formalized as a predictive model with order p,
which describes the number of lags used for predicting future neural activity. A model order of
$p = 1$ describes a classic graph diffusion process, where temporal changes in neural activity are
driven by the discrete approximation of the surface Laplacian, i.e., the second spatial derivative
(see Eq. (3) in Methods). Increasing the model order increases the capacity of the model and adds
"memory" to the diffusion process, thus offering the increased ability to model complex
spatiotemporal neural dynamics. An overview of the p^{th} order model is shown in Fig. 1b and c.
The neural activity at time t at each node $s_i[t]$ is modeled using a linear combination of its own
p past samples plus the time varying information flow from all neighboring nodes:

$$s_i[t] = \sum_{k=1}^{p} m_k^{\{i\}} s_i[t-k] + \sum_{j \in \mathcal{N}(i)} f^{\{i,j\}}[t]. \tag{1}$$

99 The GDAR flow $f^{\{i,j\}}$ between node i and j is given by a linear combination of the p past activity
100 gradients between the two nodes (Fig. 1c; see Methods for more details)

$$f^{\{i,j\}}[t] = \sum_{k=1}^{p} w_k^{\{i,j\}} \left(s_j[t-k] - s_i[t-k] \right) \tag{2}$$

and can be positive or negative, depending on whether information flows into or out of node i.
The node and edge parameters of the GDAR model $m_k^{\{i\}}$ and $w_k^{\{i,j\}}$ can be estimated from neural
recordings using linear regression (see Methods) and are assumed to be static within a predefined
time window.

Computing the second spatial derivative is equivalent to computing the current source densities
(CSDs), which is a popular technique for analyzing field potential recordings obtained from
technologies such as ECoG or electroencephalography (EEG)[38,39]. Therefore, the GDAR model
can also be considered a combination of CSD analysis and VAR model. For field potential
recordings the model parameters $w_1^{\{i,j\}}, \dots, w_p^{\{i,j\}}$ can be interpreted as conductivities such that
voltage gradients multiplied by conductivity yields current flow. Summing the current flows at
each node is analogous to computing the current sources and sinks in CSD analysis.

The high temporal resolution of the GDAR flow signal $f^{\{i,j\}}[t]$ is ideal to study transient signaling
events. For example, the propagation of neural activity due to cortical stimulation can be tracked
by concatenating consecutive time steps of $f^{\{i,j\}}[t]$ and analyzing its spatiotemporal evolution

Fig. 1: Overview of the graph diffusion autoregressive (GDAR) model. (a) The recording array is used to form a sparse, locally connected graph, where each electrode represents a node, and edges connect neighboring nodes. The GDAR model then transforms the neural activity observed at the nodes into a directed flow signal defined on the graph edges, representing the real-time signaling between nodes. (b) The model incorporates an order p autoregressive system, where at time t each node's neural activity is modeled using a combination of its past p samples and the flow from all adjacent nodes. (c) The directed GDAR flow at time t between node i and j, denoted as $f^{\{i,j\}}[t]$, is calculated as the weighted sum of the previous p activity gradients between these nodes. In analogy to current source density analysis, the edge parameters $w_1^{\{i,j\}}, ..., w_p^{\{i,j\}}$ can be interpreted as conductivities for local field potential measurements, such that conductivity times potential gradient yields a current flow. The model parameters are assumed to be static within a particular time window and can be estimated using linear regression (see Methods). (d) The GDAR flow can be used to study transient communication events, for example due to cortical stimulation. (e) For resting state recordings, power spectral density estimates of the GDAR flow signal can be used to study frequency band specific communication patterns.

(Fig. 1d). Alternatively, the model can be applied to resting state recording in which case it may
be reasonable to compute the power spectrum of $f^{\{i,j\}}[t]$. This results in a similar frequency
decomposition as is typical for VAR based FC measures (Fig. 1e) with the distinction that the
GDAR flow power spectrum is determined by magnitude and phase differences between
neighboring channels that are modulated by the Fourier transform of the model parameters (see

Methods) whereas VAR based FC measures only utilize the model parameters for the spectral
representation.

The GDAR model outperforms VAR models in inferring communication dynamics in
a network of coupled Wilson-Cowan oscillators: To assess the accuracy of the GDAR flow
signal, we fit the model to simulated data generated by various networks of coupled Wilson-Cowan
oscillators (Fig. 2). The networks are used to generate a ground truth neural flow signal, as well
as simulated neural activity, which is used to fit GDAR and VAR models of varying model orders
(see Methods for more details). In contrast to the GDAR model, VAR models assume no structural
connectivity and may find communication links between any pair of nodes in the network.
Therefore, we also compare the GDAR model to a VAR model with access to the ground truth
structural connectivity network, denoted as enhanced VAR (eVAR) model. All models are used to
transform the simulated neural activity into a neural flow signal, which is compared to the ground
truth neural flow using various metrics (Fig. 2a). Furthermore, we estimate the neural flow using
the CSD approach and compare it to the ground truth flow.

First, we compare the Pearson correlation coefficients (PCCs) between ground truth and estimated
flow from 10^{th} order GDAR, VAR, and eVAR models, as well as the CSD approach and found
that the GDAR model significantly outperforms all other models (Wilcoxon rank-sum test, $p <$
0.001), thus providing the most accurate estimate of the truth neural flow dynamics. (Fig. 2b).
Next, we tested the effect of the model order and found that the GDAR model consistently
outperforms the other models for $p \geq 7$ (Fig. 2c). Finally, we repeated the simulations for different
network structures (12-node locally connected graph, 16-node grid graph, 16-node randomly
connected graphs) and found that, for all graphs, the GDAR model significantly outperforms the
other two models (Fig. 2d; see Extended Fig. 1 for performance using different model orders).

In principle, low correlations between two time series can arise from mismatches in amplitude or
phase of their respective frequency components. To investigate the source of the low PCCs
observed in Fig. 2b and c, we computed the spectrum of the ground truth and estimated flow and
plotted the magnitude and phase differences between them in Fig. 2e (see Methods). We found
that the GDAR model exhibits consistently lower magnitude errors than VAR and eVAR models
above 30 Hz. Compared to the VAR model the GDAR model also shows consistently lower phase
errors, particularly in the gamma (30-70 Hz) and high-gamma (70-200 Hz) bands. Lower
magnitude and phase errors in high frequency bands between GDAR and ground truth flow also
result in higher PCCs between band-pass filtered flow signals (see Extended Fig. 2). Note that the
strong phase error oscillation above 40 Hz observed with all models can be explained by the filter
properties of the estimated model parameters (see Extended Fig. 2 and Methods). Finally, example
flow traces between high-gamma estimated and ground truth flow demonstrate that, the GDAR
flow tracks the peaks and troughs noticeably better than both VAR and eVAR flow (Fig. 2f).

Application of GDAR model to electrophysiological recordings: To show the versatility
157 of the GDAR model to analyze communication dynamics evoked by cortical stimulation, during
158 behavior, and at rest, we have applied the model to electrophysiological recordings from four
159 separate experiments that either use a μECoG array (3 datasets) or a Utah array (1 dataset) to

Fig. 2: Evaluation of the GDAR model's accuracy in capturing neural communication dynamics using a network of Wilson Cowan oscillators. (a) A toy network was used to simulate neural activity at each network node as well as compute a ground truth flow across each edge (see Methods). The estimated neural activity is transformed into the estimated neural flow signal using GDAR, VAR, and eVAR (VAR model with knowledge of the structural connectivity) models of different model orders, as well as the CSD approach. Ground truth and estimated neural flow are then compared using various metrics. (b) Distribution of the Pearson correlation coefficient (PCC) using data from 100 independent simulation trials pooled over all graph edges between ground truth and estimated neural flow from 10^{th} order GDAR, VAR, and eVAR models, as well as the CSD approach (shown are median, upper and lower quartile, whiskers at quartile $\pm 1.5 \times$ inter quartile range, and outliers). The GDAR 10 model significantly outperforms all other models, thus providing the most accurate overall estimate of the ground truth flow (Wilcoxon rank-sum test, $p \leq 0.001$; Exact p-values can be found in Supplementary Table 1.). (c) Performance for different model orders (median, upper and lower quartile). Significance markers compare GDAR and eVAR model. The GDAR model consistently outperforms the other two models for model orders $p \geq 7$. (d) Performance of the models for different network structures. The GDAR model outperforms the other two models for a 12-node locally connected graph (left), a 16-node grid graph (middle), and a set of 16-node randomly connected graphs (right). (e) Magnitude and phase difference between the spectrum of ground truth and estimated flow (median, upper and lower quartile) for the network shown in (a). The GDAR model shows consistently lower magnitude and phase errors over a wide frequency range than the other two models. (f) Example traces of estimated and ground truth flow band-pass filtered between 70-200 Hz, demonstrating that the GDAR model can accurately track the ground truth flow signal.

record LFPs from the sensorimotor cortex of macaques. For all datasets, the layout of the recording array was first used to construct a locally connected and sparse graph, where each node

corresponds to a recording channels (see Fig. 3 -Fig. 5). Next, GDAR models of different orders
were fit to the recorded LFPs. The resulting model coefficients were then used to transforms the
LFPs into GDAR flow signals, which were post-processed depending on the experimental setup.

<u>The GDAR model uncovers communication dynamics evoked by cortical optogenetic stimulation:</u>
First, we show that the GDAR model can uncover fast, stimulation induced communication
dynamics that match the experimental protocol. To do so we use three sessions from an
optogenetic stimulation experiment performed in macaques, where two lasers repeatedly
stimulated different locations of the primary motor (M1) and somatosensory (S1) cortex expressing
the opsin C1V1, and fit a 5^{th} order GDAR model to the LFPs recorded by a 96-channel μECoG
array during stimulation (see Fig. 3a-c and Methods)[11,40,41]. GDAR flow signals averaged over all
stimulation trials in the milliseconds before and after stimulation for Session 1 are shown in Fig.
3d and Supplementary Video 1. When the network is at rest, flow levels across the network are
small. Activation by the first laser located in M1 causes the GDAR flow to immediately increase
near the stimulation location before spreading further into the network and reaching S1. After the
second laser was activated, the flow increases near the second stimulation location and spreads
into most parts of the network within the next few milliseconds.

It is apparent from Fig. 3d that the GDAR flow exhibits complex spatiotemporal dynamics within
milliseconds after stimulation. To test how these dynamics depend on the stimulation pattern, we
project the high-dimensional flow signal from three sessions, which only differ in their stimulation
location (see Fig. 3b), onto their first two principal components (PCs) and compare the flow
dynamics in this lower dimensional subspace (see Methods). We found that these low dimensional
communication dynamics are very consistent within each session and strongly differ between
sessions (Fig. 3e). Furthermore, the communication dynamics show some remarkable similarities
with the stimulation patterns. For Sessions 1 and 2, where the flow trajectories largely align in
the PC space, the stimulation patterns are similar in that the second stimulation occurs to the
top right of the first stimulation. On the other hand, for Session 3, which results in flow trajectories
orthogonal to Session 1 and 2, the second stimulation occurs to the top left of the first stimulation.
Furthermore, the magnitude of the PC reduced GDAR flow dynamics is noticeably smaller for
Session 2 compared to Sessions 1 and 3. This might be a result of the spatial separation between
Laser 1 and 2, which is smallest for Session 2. Our findings extend previous work showing that
LFP power in monkeys and humans distinctly depend on stimulation parameters such as
amplitude and frequency[42,43].

We also tested whether the VAR or CSD flow, or node signal like raw LFPs or its second spatial
derivative, which resembles traditional current source density, can uncover dynamics that depend
on the stimulation pattern but found that this is not the case (Fig. 3f and g, and Extended Fig.
3). Perhaps it is not surprising that the raw LFPs or simple, model-free transformations thereof
(CSD flow, second spatial derivative of raw LFP) fail to describe stimulation dependent dynamics
using PC analysis as these signals may be dominated by noise and non-stimulation specific
variation. Autoregressive models on the other hand may effectively filter out some of these non-
stimulation noise sources. Our results suggest that the GDAR model is more effective at
uncovering such transient stimulation-dependent communication dynamics compared to standard
VAR models. We also note that the dependence on the stimulation location can be observed when

Fig. 3: *GDAR model applied to optogenetic stimulation experiment to study transient communication events. (a) LFPs from the primary motor (M1) and somatosensory (S1) cortex of a signal non-human primate were recorded using a 96-channel micro-ECoG array, while repeated paired stimulation was performed using two lasers (modified from Bloch et al.[34]). (b) The relative positions of the electrodes after rejecting bad channels and the locations of the two lasers are shown at the top for the three sessions that were analyzed in this work. The location of the sulcus between M1 and S1 is approximated by the thick gray line. The electrode array was not moved between the sessions. At the bottom, the stimulation protocol is shown. Each laser stimulates alternatingly for 5 ms, with a 10 ms delay between stimulation by Laser 1 and 2. This paired stimulation is repeated every 143 ms. Each stimulation block lasts approximately 7 min and is intermitted shorter long resting blogs during which no stimulation is performed. (c) The recording array is used to construct a sparsely connected graph and the recorded LFPs are then transformed into a flow signal using a 5th order GDAR model. (d) The GDAR flow for Session 1 averaged over all stimulation blocks and trials is shown for different time steps before (first plot) and after (remaining four plots) onset of stimulation from the first laser. The graphs suggest complex spatiotemporal signaling patterns evoked by cortical stimulation. (e) Flow snapshots from the first 25 ms after onset of the first laser stimulation for all trials, blocks, and sessions were stacked into a single matrix and the flow snapshots were projected onto its first two principal components (PCs). The PC reduced GDAR flow trajectories for different sessions are indicated by different colors. Average trajectories are shown as black solid lines with markers indicating different times point after the onset of stimulation by the first laser. Thin colored lines show trajectories by individual paired pulse trials. The plot highlights that GDAR flow trajectories are very consistent within and distinct between sessions, demonstrating that transient communication dynamics depend on the stimulation parameters. (f), (g) PC reduced flow trajectories similar to (e) but using a 5th order VAR model and the CSD approach. In contrast to the GDAR flow, VAR and CSD flow do not exhibit significant time and session dependent dynamics, thus, highlighting the utility of the GDAR model in stimulation induced transient communication dynamics.*

plotting a low-dimensional representation of the model parameters itself, where the GDAR model
shows a stronger separation between sessions than the VAR model (Extended Fig. 3). Finally, the
model can also be adapted to model longer signal propagation paths between specific nodes in the
network as it would be reasonable to assume for connections across the sulcus between M1 and
S1 (see Extended Fig. 3, Supplementary Video 2, and Supplementary Note).

<u>The GDAR model can track changes in resting state neural communication that are consistent</u>
<u>across experiments and recording modalities:</u> Like classical FC analysis, the GDAR model can be
utilized to study frequency specific changes in neural communication from resting state recordings.
We demonstrate this using two distinct electrical stimulation experiments that employ either
intracortical recordings via a 96-channel microelectrode array (Utah array) or subdural recordings
via two 32-channel ECoG arrays (Fig. 4 and Fig. 5). For both experiments, repeated electrical
stimulation of the macaque sensorimotor cortex is performed for 10-minute blocks at a time either
at a single site or alternatingly at two sites (paired-stim), and resting state neural activity is
recorded before, after, and between the stimulation blocks. Changes in gamma (30-70 Hz) flow
power due to stimulation are estimated via 10^{th} order GDAR models and tested for statistical
significance (significance level $p \leq 0.01$; two-sample Kolmogorov-Smirnov test) (see Methods).

For the Utah array data we analyzed recordings from three separate sessions that employ either
single site or paired stimulation. For single site stimulation, we observe an increase in GDAR flow
power proximal to the stimulation site (Fig. 4b, left). For paired stimulations, a localized increase
was only observed near the first stimulation site (Fig. 4b, middle and right), with no notable
changes near the second site. We quantified this increase by computing the average flow magnitude
over all edges connected to the stimulation site and adjusted it for changes in LFP power (Fig.
4c-e; also see Methods and Extended Fig. 6). Across all sessions, stimulation led to a sustained
increase in resting-state communication near the first stimulation site above baseline levels.
Notably, for paired stimulation sessions, this augmented communication persisted for at least 17
minutes following the final stimulation block.

For the ECoG data we analyzed changes in resting state neural communication due to single-site
electrical stimulation performed during the acute phase after focal ischemic lesioning of the
macaque sensorimotor cortex (Fig. 5a and b). In the ipsilesional hemisphere, gamma GDAR flow
power increases locally near the stimulation site and decreases across other parts of the network
(Fig. 5c). In the contralesional hemisphere, this effect is weakly mirrored, as we observe an increase
in GDAR flow power for some edges in the area corresponding to stimulation in the ipsilesional
hemisphere but not across the entire network. Similar patterns can be observed for changes in
CSD flow power. On the other hand, VAR flow power suggest increased communication within
both hemispheres, showing that the GDAR model can describe changes in resting state
communication that are not captured by the VAR model. The changes in GDAR flow power from
the ECoG dataset are also consistent with our finding from the Utah array dataset, underscoring
the GDAR model's ability to robustly capture neural interactions across different experimental
and recording modalities.

Fig. 4: Application of GDAR model to LFP data recorded from a macaque monkey using a Utah array during a paired electrical stimulation experiment. (a) The locations of the electrodes were used to construct a locally connected sparse graph as input to the GDAR model. Electrode A and B are used for single site and paired stimulation. For paired stimulation, electrode A stimulates before electrode B. (b) Changes in gamma (30-70 Hz) GDAR flow power due to stimulation are shown for three separate sessions. For the single-stim session, only electrode B stimulates. For the paired-stim sessions, electrode A and B stimulate repeatedly and alternatingly for a total of 50 minutes divided into five 10min blocks (see Methods for more details on the stimulation protocol). An increase in gamma GDAR flow power near the first stimulation location can be observed for all sessions. (c)-(e) Temporal evolution of the normalized gamma GDAR flow power averaged over all edges adjacent to the first stimulation site for all three sessions. The 2-minute blocks immediately after stimulation are highlighted in red. The gamma GDAR flow power has been corrected for linear changes in LFP power at the stimulation site (see Methods). For the paired stimulation sessions, the GDAR flow power remains elevated even after the stimulation period ends.

Finally, for the ECoG dataset we have compared our results with changes of three traditional FC
measures: gamma coherence, gamma partial directed coherence (PDC), and gamma directed
transfer function (DTF) (Fig. 5d). Note that in contrast to the GDAR model and CSD approach,
coherence and VAR based measures assumes fully connected graphs, which typically results in
much denser communication networks. In the ipsilesional hemisphere we found that PDC and
DTF most closely agree with the results from the GDAR model, with the main difference that

Fig. 5: Analyzing changes in resting state neural communication following electrical stimulation in the acute phase after ischemic lesioning using various flow and FC measures. (a) Two 32-channel ECoG arrays were placed over the left and right hemisphere of a macaque monkey and an ischemic stroke lesion was induced in the left hemisphere using the photothrombotic technique (see Methods). The estimated lesion size is indicated by the red patch in the center of the left hemisphere. One hour after lesioning, electrical stimulation was performed approximately 8 mm away from the lesion location. Neural activity was recorded before and after stimulation to assess the effects of stimulation on network connectivity in the acute phase after stroke. (b) The locations of the electrodes were used to construct two locally connected sparse graphs. (c) Similar to previous applications, 10^{th} order GDAR and VAR models, as well as the CSD approach were used to transform the recorded neural activity before and after stimulation into neural flow signals. Next, power spectra of the flow signals were estimated and changes in gamma (30 − 70 Hz) flow power due to stimulation were computed. The changes in gamma flow power (in percent) are shown as undirected edges. Only changes with a significance threshold of $p \leq 0.01$ (two-sample Kolmogorov-Smirnov test) are shown. The lesion location is indicated by the black patch and the stimulation location is shown by the yellow marker. The plots show a local increase in GDAR gamma flow power in the ipsilesional hemisphere near the stimulation location. (d) Same as (c) but instead using coherence, partial directed coherence (PDC), and directed transfer function (DTF) to assess changes in neural communication. Similar to the GDAR flow, PDC and DTF increase for connections with the stimulation location. However, in contrast to the GDAR flow, these changes are less localized and instead affect communication across the entire network.

changes in communication by these two measures affect larger parts of the network. In the
contralesional hemisphere, PDC and DTF changes are somewhat opposing the GDAR flow

changes. We note that the patterns observed in Fig. 5c and d are highly frequency dependent (see
Extended Fig. 4).

<u>The GDAR model finds trial-to-trial variability in neural communication during a center-out reach</u>
<u>task:</u> Previous studies have shown that the trial-to-trial variability in reaction time and task
performance during motor tasks is related to various biomarkers such as initial neural state[45],
magnitude of neural activity[46], and cortical transmission time[47]. Using μECoG recordings from
M1 of a macaque monkey performing a center-out reach task (Fig. 6), we show that the GDAR
model can be leveraged to study the trial-to-trial variability of cortical communication dynamics
during reach. To do so, we focus on the top-left reach direction, which shows relatively large
variability in reach time and trajectory between slow and fast reach trials (Fig. 6a and b). For this
direction, we then computed the change in high-gamma GDAR flow power during the reach period
compared to the preceding rest period. We found that faster reach times are associated with a
larger increase in GDAR flow power across most parts of the network suggesting a stronger
coordination between different areas of the cortex than for slower reach trials (Fig. 6c). To further
investigate this relation, we used data from all reach directions and computed the average change
in neural flow power across all network edges for each trial and plotted it against the log of the
corresponding reach time. Changes in GDAR, VAR, and CSD flow power show a significant
negative correlation with the log of the reach time (Fig. 6d). However, GDAR and CSD flow
exhibit the smallest p-values (Wald test with t-distribution of the test statistic) and largest $|R|$
suggesting that these models best emphasize the variability in reach time. High-gamma power of
the LFP signal shows correlation with reach time comparable to the VAR flow (Extended Fig.
5a). If the LFP signal is first preprocessed via the graph Laplacian (i.e., resembling classical current
source density analysis) the correlation is close to the ones observed for the CSD and GDAR flow
(Extended Fig. 5b).

Next, to study the trial-to-trial variability of the GDAR flow maps in more detail, we computed
the dominant flow component (first PC of the time varying flow signal; see Methods) for each
reach trial (Fig. 6e). Slow reach trials corresponds to a dominant source/sink pattern centered
around a single network node, but do not show significant flow activity outside that region. The
dominant flow pattern of fast reach trials shows a more coordinated flow pattern involving larger
parts of the network with information propagating towards/originating from the center right
boundary of the graph. To test whether these two flow patterns persist across all 25 trials within
the single reach direction, we projected them to a two-dimensional subspace using PCA (Fig. 6f).
It is apparent that the slow reach trials form a cluster that is distinct from the fast and medium
fast trials. We computed the centroids of the two clusters in the original flow space (Fig. 6g) and
found that they show approximately the same pattern that was observed for the individual fast
and slow trials in Fig. 6e. We repeated the analysis in Fig. 6e-g using the high-gamma CSD flow
instead of the GDAR flow. While differences between slow and fast trials can also be observed
from the CSD flow, they are less distinct and less consistent than differences observed in the
GDAR flow (see Extended Fig. 5c-e).

a

direction 4

b

0.23 - 0.32s

trial 5 trial 12 trial 13 trial 8 trial 23   trial 22 trial 17 trial 19 trial 15 trial 21 trial 9 trial 24

trial 2 trial 16 trial 7 trial 14 trial 11 trial 10   trial 18 trial 20   trial 4 trial 0 trial 3 trial 6 trial 1

1.43 - 8.19s

c

direction 4 - fastest reach time

trial 5   trial 12   trial 13   trial 8   trial 23

direction 4 - slowest reach time

trial 1   trial 6   trial 3   trial 0   trial 4

change in GDAR flow power (%)

d

GDAR flow

change in GDAR flow power (%)

$|R| = 0.47$
$p = 1.51 \cdot 10^{-12}$

$\log_{10}(\text{reach time (s)})$

VAR flow

change in VAR flow power (%)

$|R| = 0.21$
$p = 0.0031$

$\log_{10}(\text{reach time (s)})$

CSD flow

change in CSD flow power (%)

$|R| = 0.46$
$p = 6.66 \cdot 10^{-12}$

$\log_{10}(\text{reach time (s)})$

e

trial 5   trial 12   trial 13   trial 8   trial 23

trial 4   trial 0   trial 3   trial 6   trial 1

f

C1

C2

PC2

PC1

g

centroid C1   centroid C2

Fig. 6: Applying the GDAR model to ECoG recordings during a center-out reach tasks to study trial-by-trial variability of neural communication. (a) A rhesus macaque monkey performed an eight directional reach tasks during which reach trajectories and LFPs using a 96-channel micro-ECoG array placed over the primary motor cortex were recorded. For each reach direction, 25 successful trials were recorded. To analyze the trial-by-trial variability, we mainly focus on Direction 4 (upper left) as it showed a greater reach variability than other directions. (b) The 25 reach trajectories of Direction 4 were grouped into the five fastest, 15 normal, and five slowest trials. The reach times during the fastest (slowest) trials range from $0.23 - 0.31$ s $(1.43 - 8.19$ s$)$. The five slowest trajectories are very jagged either at the beginning or end of the reach. (c) Similar to the procedure described in Fig. 5, changes in GDAR flow power during reach compared to baseline were computed for the high-gamma band $(70 - 200$ Hz$)$ and are plotted for the five fastest, and slowest reach trials, respectively. Fast reach t rials show a significantly stronger increase in GDAR flow power than slow trials. (d) The average change in high-gamma GDAR, VAR and CSD flow power is plotted against the reach time for each of the 200 trials (all directions). While all metrics show a significant negative relation between the log of the reach time and the change in average flow power, the GDAR model shows the highest $|R|$, closely followed by the CSD flow. (e) Dominant GDAR flow patterns (obtained via principal component analysis) for the five fastest and slowest reach trials of Direction 4. (f) These GDAR flow patterns naturally form two clusters where C1 contains fast and average trials and C2 the five slowest trials. (g) Cluster centroids of C1 and C2. Fast reach trials correspond to a more coordinated GDAR flow pattern that involves larger parts of the network, whereas slow reach trials exhibit a flow pattern that is mainly centered around a single node.

The GDAR model generalizes to unseen data better than VAR models: To test the GDAR model's ability to generalize to unseen data, we evaluate the model's one-step ahead prediction performance on data that were not included for estimating its parameters. Using the simulated field potentials from the network of Wilson-Cowan oscillators shown in Fig. 2a (100 independent trials with 5s of simulated neural activity per trial), the GDAR model was trained on the initial N samples of each trial and then tested on the remaining samples (see Methods for more details). An advantage of the GDAR model, owing to its fewer parameters compared to both VAR and eVAR models, is its reduced need for extensive training samples to accurately estimate model parameters. This results in the flatter RMSE curves for both training and testing data (Fig. 7a left and middle) as well as the lowest generalization gap (difference between test and train RMSE) among all models (Fig. 7a, right). Notably, the generalization gap for the GDAR model is nearly an order of magnitude smaller than that for the eVAR model.

We found similar results across the electrophysiology datasets (Fig. 7b-d). Despite the VAR model possessing significantly more parameters – ranging from 8 to 20 times more, depending on the size of the electrode array – the GDAR model exhibited comparable predictive performance on the training set (Fig. 7b). Unlike the VAR model, the GDAR model also generalizes almost perfectly to unseen data, as evidenced by a median generalization gap very close to zero for all datasets (Fig. 7c). Finally, we tested how well the model generalizes to data separated by longer time periods from the training set (Fig. 7d). The GDAR model again maintains a lower generalization gap across all time gaps and datasets compared to the VAR model, with the generalization gap remaining relatively stable as gap lengths increased. An intriguing observation emerged from the optogenetic stimulation dataset, where both the GDAR and VAR models exhibited increasing generalization gaps for larger gap lengths. We believe that this trend stems from plasticity mechanisms within each stimulation block, as repeated paired stimulation induces sustained alterations in brain network activity, thereby challenging the models' ability to generalize over extended time periods.

Fig. 7: Generalization Performance of GDAR model on simulated data and electrophysiological recordings. (a) 10th order GDAR, VAR and eVAR models were fit to the first N samples (train length) of neural activity simulated by the network of Wilson-Cowan oscillators shown in Fig. 2a independently for each of the 100 simulation trials. The model coefficients are then used to perform a one-step ahead prediction on the training data as well as the remaining samples in the trial (test data). The left and middle panel show the mean, 10th, and 90th percentile of the root mean square prediction error (RMSEs). The generalization gap (right panel) is defined as the difference between mean test and train RMSE. The GDAR model generalizes significantly better to unseen data than the VAR and eVAR model. (b) Normalized train RMSE of GDAR and VAR models for all four electrophysiology datasets considered in this study. The RMSE generally decreases with increasing model order p and is comparable between GDAR and VAR model within each dataset. (c) Generalization gap (see Methods) of both models for the electrophysiology datasets. The GDAR model almost perfectly generalizes to unseen data. On the other hand, the VAR model always shows some degree of overfitting (Wilcoxon rank-sum test, p ≤ 0.001). (d) The generalization gap for the optogenetic stimulation and two resting state dataset as a function of the time gap between train and test set. Except for the optogenetic stimulation experiment, the generalization gap remains constant or decreases as the time gap between train and test set increases. For all time gaps, the GDAR model outperforms the VAR model.

Discussion

We have introduced a novel framework for estimating dynamic network level neural communication from field potential recordings by combining a network communication process (diffusion) with the modeling power of classical VAR models. Our GDAR model gives rise to a communication signal that matches the temporal resolution of the original recordings, which makes it well suited to study transient and long-term communication dynamics. Furthermore, spatial information provided by the layout of the recording array is naturally incorporated into the model, which significantly reduces the number of parameters compared to standard VAR models, thus rendering it effective for scenarios where data is limited. Using simulations and four electrophysiology

datasets from macaque sensory motor cortex, we have demonstrated that the GDAR model outperforms competing approaches (standard VAR models, CSD flow) in estimating fast communication dynamics and trial-by-trial variability and provides complementary insights into resting state communication that are consistent across different experiments and recording technologies.

Why does the GDAR model perform better than standard VAR models? VAR models and other approaches for estimating functional brain connectivity have successfully been used to study neural interactions for many years. Yet these techniques remain relatively generic and can – without substantial modifications – easily be applied to any multivariate time series dataset. Furthermore, VAR models have many parameters, potentially causing them to overfit to idiosyncrasies in the data that do not correspond to meaningful neural interactions. This is particularly evident in the poor generalization performance for the reach dataset where model fitting relies on a limited number of observations (see Fig. 7c). By assuming that information propagation resembles a diffusive process where signals mainly travel via local connections through the network (i.e., assuming a sparse communication network) the GDAR model significantly reduces the number of parameters and incorporates biologically plausible communication constraints. Indeed diffusion models have previously been proposed as a mechanism through which different neural populations communicate[35,48], and it has been shown that diffusion processes can explain functional connectivity estimates[49] and model the propagation of activity evoked by intracranial stimulation more accurately than alternative communication models[36]. Furthermore, it has been shown that adding spatial information in the form of structural priors to standard VAR models and other FC measures can improve the estimation of FC networks[50–53], which suggests that incorporating spatial information from the recording array into the GDAR model contributes to its improved performance.

The GDAR model also has an important practical advantage for processing field potential signals, which can suffer from spurious correlations due to volume conduction, signal artifacts that are shared across channels, and the common reference signal problem. Such spurious correlations are known to cause erroneous connectivity estimates using classical measures of neural communication such as coherence, phase locking value, or metrics based on standard VAR models[17]. These spurious correlations can be addressed by preprocessing field potentials using CSD (i.e., the second spatial derivative) or activity gradients (i.e., the first spatial derivative) instead of using the raw neural activity[17,54,55]. Since the GDAR model employs the second spatial derivative, the effects of spurious correlations are strongly mitigated and should not negatively impact the performance of the model.

A limitation of the GDAR model is that it requires the specification of a graph that supports the propagation of information. We assume that this graph is a sparse and locally connected nearest neighbor graph that is obtained in a non-data-driven manner from the locations of the electrodes in the recording array. While the diffusive nature of the model supports this choice, it neglects the potential existence of any direct longer-range propagation paths. For electrophysiological recordings, it is difficult to determine the best underlying network structure as structural information is often not available or, if the information is available (e.g., from diffusion tensor imaging), it is unclear how to map the recording array onto an imaged structural network. Therefore, we suggest that in the future, the process of determining the structural connectivity

graph could be augmented in a more data-driven way, for example, through the use of sparsity
and distance regularizers. Furthermore, we currently make no distinction between nodes
corresponding to electrodes in the interior versus the boundary of the array. Especially the
boundary nodes may exhibit a large exchange of information with regions outside the array, which
is not captured by the model, but could be incorporated by adding additional input terms.

Another promising avenue would be to explore how other proposed mechanisms of brain network
signaling, such as biased random walks or shortest path routing[35,48], could be incorporated as
biologically plausible constraints into data-driven models of network communication. Furthermore,
the GDAR model could be extended to model non-linear communication dynamics by introducing
activation functions into the divergence step of the model.

Acknowledgements

We thank Daniel Silversmith and Joseph O'Doherty for their help with data collection and Philip
Sabes for his laboratory in which some of the data was collected. We also thank Toni Haun, Sandi
Thelen, and Christopher English for their help with animal surgeries and experimentation for the
stroke experiment. This work was supported by the American Heart Association (FS, AY), the
National Institute of Health R01NS119593 (JB, AY) and R01MH125429 (FS, AY), the Washington
Research Foundation (AY), the Big Data for Genomics and Neuroscience Training Grant NIH
5T32LM012419 (JB), the Center for Neurotechnology NSFERC 1028725 (JB), the Washington
National Primate Research Center NIH P51OD010425, U42 OD011123 (AY), the Eunice Kennedy
Shriver National Institute of Child Health and Human Development NIH K12HD073945 (AY),
the National Institute of Neurological Disorders and Stroke of the National Institute of Health
R01NS116464 (AY, JZ), the University of Washington Royalty Research Fund (AY, KK), the
National Science Foundation Graduate Research Fellowship Program (KK), the Graduate
Education for Minorities Fellowship (JB), and the Weill Neurohub (JZ).

Methods

Graph Diffusion Autoregressive (GDAR) Model

Derivation and algebraic representation: The starting point for deriving the GDAR model
is to describe the spatiotemporal dynamics of the neural activity s as a heat diffusion process

$$\dot{s} = w\Delta s, \tag{3}$$

where temporal changes in activity ($\dot{s}$) are driven by spatial activity gradients (Δs, where Δ is the
surface Laplacian) multiplied by the diffusion rate w. The right-hand side of (3) is equivalent to
current source density (CSD) which is a common technique for analyzing neurophysiological
recordings. In practice, we have given a finite set of spatially distributed and discrete LFP
measurements recorded from an N-channel electrode array (see Fig. 1a left). Thus, we can denote
the LFPs recorded at time t as a vector $s[t] \in \mathbb{R}^N$. The surface Laplacian Δ is equivalent to the
second spatial derivative and thus describes local interactions within the brain network. In a
discrete measurement setup, this can be encoded by constructing a locally connected graph from
the locations of the electrodes within the recording array[56]. Thereby, each electrode corresponds

to a node in the graph and edges connect neighboring electrodes such as illustrated in Fig. 1a. The resulting unweighted graph consisting of N vertices and E edges can be represented algebraically using the node-to-edge incident matrix $\mathbf{B} \in \mathbb{R}^{N \times E}$, where the e^{th} column $b^{(e)}$ corresponds to the e^{th} edge in the graph. Each edge is defined by a tail node e_i and head node e_j such that $b_{e_i}^{(e)} = -b_{e_j}^{(e)} = -1$ and all other entries $b_{e_k}^{(e)} = 0$ for $k \neq i,j$. For each edge it is thereby arbitrary which incident node is defined as head and tail node. Using $\mathbf{B}$, the continuous surface Laplacian Δ can be approximated using the negative of the graph Laplacian operator $\mathbf{BB}^T$. Furthermore, the first temporal derivative $\dot{s}$ can be approximated by the first temporal difference $s[t] - s[t-1]$. Thus, (3) can be approximated by

$$s[t] = (\mathbf{I}_N - w\mathbf{BB}^T)s[t-1] + u[t] = \mathbf{I}_N s[t-1] - \mathbf{B}w\mathbf{B}^T s[t-1] + u[t], \qquad (4)$$

Where, $\mathbf{I}_N$ is the $N \times N$ identity matrix and $u[t]$ is a white noise term. Previously, it has been shown that the matrices $\mathbf{B}^T$ and $\mathbf{B}$ can be interpreted as discrete approximations of the gradient and divergence operators, respectively[57]. Thus, the term $\mathbf{B}w\mathbf{B}^T s[t-1]$ has a clear physical meaning in the context of LFP recordings as elaborated in the steps below:

1. $\mathbf{B}^T s[t-1] = \nabla s[t-1]$: computes the voltage gradient for each node in the graph.
2. $w\nabla s[t-1] = f[t]$: In analogy to resistive circuits and CSD analysis, w can be interpreted as a conductivity such that conductivity times voltage gradient yields a current flow $f[t]$.
3. $\mathbf{B}f[t]$: For each node, the net flow, i.e., the sum of all in flows minus the sum of all outflows, is computed. This is equivalent to computing the current sources and sinks in CSD analysis.

Equation (4) effectively expresses CSD analysis as a first order vector autoregressive (VAR) model. However, the model in Eq. (4) has limited expressivity as the only learnable parameter is the conductivity w. Thus, to improve its expressivity, we can 1) add parameterized node dynamics, 2) assume a spatially varying conductivity, and 3) extend the model order to a pth order VAR model. The resulting graph diffusion autoregressive (GDAR) model is given by

$$s[t] = \sum_{k=1}^{p} (\mathbf{M}_k - \mathbf{B}\mathbf{W}_k\mathbf{B}^T)s[t-k] + u[t], \qquad (5)$$

where $\mathbf{M}_k = \text{diag}(\boldsymbol{m}_k) \in \mathbb{R}^{N \times N}$ and $\mathbf{W}_k = \text{diag}(\boldsymbol{w}_k) \in \mathbb{R}^{E \times E}$ are diagonal matrices containing the node and edge parameters $\boldsymbol{m}_k \in \mathbb{R}^N$ and $\boldsymbol{w}_k \in \mathbb{R}^E$ of the k^{th} lag, respectively. The term $\mathbf{B}\mathbf{W}_k\mathbf{B}^T$ can also be regarded as a weighted graph Laplacian matrix. The GDAR flow is defined as

$$f[t] = \sum_{k=1}^{p} \mathbf{W}_k\mathbf{B}^T s[t-k] \qquad (6)$$

Representation as constrained VAR model: The GDAR model in (5) can be related to the standard notation of a VAR model

$$s[t] = \sum_{k=1}^{p} \mathbf{A}_k s[t-k] + u[t] \qquad (7)$$

where $\mathbf{A}_k \in \mathbb{R}^{N \times N}$ contains the VAR model parameters and is generally a dense matrix. It can be shown that if $\mathbf{A}_k$ has the same sparsity structure as the graph Laplacian $\mathbf{BB}^T$ and is symmetric,

Eq. (7) is equivalent to Eq. (5) with $(\mathbf{A}_k)_{i,j} = (\mathbf{A}_k)_{j,i} = (\mathbf{W}_k)_{l,l}$ if l corresponds to the edge between
node i and j and $(\mathbf{M}_k)_{i,i} = (\mathbf{A}_k)_{i,i} + \sum_{j \in \mathcal{N}(i)}(\mathbf{A}_k)_{i,j}$, where $\mathcal{N}(i)$ are the set of neighbors of node i.
The representation of the GDAR model as a constrained VAR model is useful for fitting the model
to neural data.

Model fitting: Using the VAR representation in Eq. (7), the model parameters $\mathbf{M}_k$ and $\mathbf{W}_k$ can
be estimated using least squares regression following the procedure described by Lütkepohl[58].
Given $T + p$ snapshots of neural activity by an N-channel recording array (T is the number of
samples used for model fitting), the predicted neural activity can be collected in the data matrix
$\mathbf{Y} = [s[p + 1], \dots, s[p + T]] \in \mathbb{R}^{N \times T}$ and its vectorized version $\gamma = \text{vec}(\mathbf{Y})$. The regressors can be
expressed as $\mathbf{S} = [S_1, \dots, S_T] \in \mathbb{R}^{Np \times T}$, where $S_t = [s[t + p - 1]^T, \dots, s[t]^T]^T \in \mathbb{R}^{Np \times 1}$. The
coefficients $\mathbf{A}_k$ can be expressed as $\mathbf{A} = [\mathbf{A}_1, \dots, \mathbf{A}_p] \in \mathbb{R}^{N \times Np}$ and $\alpha = \text{vec}(\mathbf{A})$. As shown in the
previous section, $\mathbf{A}_k$ is spare and symmetric. Therefore, there exist a matrix $\mathbf{R}$ such that $\alpha = \mathbf{R}\tilde{\alpha}$
and $\tilde{\alpha}$ only contains the non-zero entries of the upper triangle of $\mathbf{A}$. Now (7) can be written as

$$\gamma = (\mathbf{S}^T \otimes \mathbf{I}_N)\mathbf{R}\tilde{\alpha} + u, \tag{8}$$

450 where $\otimes$ is the Kronecker product. Furthermore, we assume that u is white noise with covariance
451 matrix $\mathbf{\Sigma}_u$. Eq. (8) can be solved in close form by minimizing $u^T(\mathbf{I}_T \otimes \mathbf{\Sigma}_u^{-1})u$, where $\mathbf{I}_T$ is the $T \times T$
452 identity matrix, to obtain the optimal parameters $\tilde{\alpha}^*$:

$$\tilde{\alpha}^* = [\mathbf{R}^T(\mathbf{SS}^T \otimes \mathbf{\Sigma}_u^{-1})\mathbf{R}]^{-1}\mathbf{R}^T(\mathbf{S} \otimes \mathbf{\Sigma}_u^{-1})\gamma. \tag{9}$$

453 Eq. (9) is the solution to the generalized least squares (GLS) estimator, which is generally different
454 from the ordinary least squares (OLS) estimator due to the sparsity and symmetry contraints[58].
455 However, it requires knowledge of the noise covariance matrix $\mathbf{\Sigma}_u^{-1}$, which is unknown in practice.
456 Therefore, we first estimate the $\mathbf{\Sigma}_u^{-1}$ by solving the OLS estimator $u^T u$ to compute $\hat{\tilde{\alpha}}$ as

$$\hat{\tilde{\alpha}} = [\mathbf{R}^T(\mathbf{SS}^T \otimes \mathbf{I}_N)\mathbf{R}]^{-1}\mathbf{R}^T(\mathbf{S} \otimes \mathbf{I}_N)\gamma \tag{10}$$

457 and denote $\hat{\alpha} = R\hat{\tilde{\alpha}}$. The corresponding coefficient matrix is $\hat{\mathbf{A}}$ with $vec(\hat{\mathbf{A}}) = \hat{\alpha}$. Then we estimate
458 $\mathbf{\Sigma}_u$ as

$$\mathbf{\Sigma}_u = \frac{1}{T}(\mathbf{Y} - \hat{\mathbf{A}}\mathbf{S})(\mathbf{Y} - \hat{\mathbf{A}}\mathbf{S})^T \tag{11}$$

It is also noted that (5) can be directly casted as a least squares minimization problem. However,
we found that it is more efficient to compute the optimal parameters according to (8).

Power spectrum of GDAR flow: If the model is applied to resting state neural activity, the
GDAR flow signal may exhibit a similar oscillatory behavior as the neural activity. Therefore, it
may be reasonable to compute its power spectrum to study frequency specific communication
patterns. Using Eq. (6) and recognizing that it expresses the GDAR flow as the convolution
between the model parameters $\mathbf{W}_k$ and the activity gradients $\mathbf{B}^T s[t]$, the GDAR flow power
spectrum between nodes i and j is given by

$$|F(\omega)|^2 = |W^{\{i,j\}}(\omega)|^2 \cdot |S_j(\omega) - S_i(\omega)|^2, \tag{12}$$

467 where $W^{\{i,j\}}(\omega)$, $S_i(\omega)$, and $S_j(\omega)$ are the Fourier transforms of the parameters, as well as the
468 neural activity of the two channels, and ω is the frequency variable. An interesting case occurs

469 when the spectra of both channels have the same magnitude for a given frequency. Assuming
470 $|S_i(\omega)| = |S_j(\omega)| = 1$, Eq. (12) can be simplified to

$$\frac{|F(\omega)|^2}{2} = |W^{\{i,j\}}(\omega)|^2 \cdot [1 - \cos(\phi_j - \phi_i)], \tag{13}$$

471 where ϕ_i and ϕ_j are the phase of the $S_i(\omega)$, and $S_j(\omega)$, respectively. That is, in this case the
472 communication dynamics are driven only by phase differences between connected nodes. In
473 general, however, communication dynamics will be determined by differences in magnitude and
474 phase modulated by $W^{\{i,j\}}(\omega)$, which was estimated with the objective of improving the prediction
475 of future neural activity.

Wilson-Cowan Simulations

477 **Simulating local field potentials (LFPs):** We simulated LFPs using various networks of
478 Wilson-Cowan oscillators[59,60] shown in Fig. 2 and Extended Fig. 1. Each node consists of an
479 excitatory and inhibitory subpopulation whose dynamics are governed by the following differential
480 equations:

$$\tau_e \frac{de_i(t)}{dt} = -e_i(t) + S\left(c_{ee}e_k(t) + c_{ie}i_k(t) + P + \xi(t) + \sum_{j \in \mathcal{N}(i)} w_{j \to i} e_j(t - \tau_{jk})\right) \tag{14}$$

$$\tau_i \frac{di_i(t)}{dt} = -i_i(t) + S(c_{ei}e_i(t) + \xi(t)) \tag{15}$$

481 where S is the sigmoid function:

$$S(x) = \frac{1}{1 + e^{\frac{x - \mu}{\sigma}}} \tag{16}$$

The description of the parameters and their values are listed in Table 1. The values are based on
previous work by Abeysuriya et al.[61] and Deco et al.[62] and result in a power spectrum with a
pronounced gamma oscillation around 35 Hz and a $1/\omega$ slope for higher frequencies. Coupling
between excitatory populations of neighboring nodes is determined by the parameter $w_{j \to i}$ where
each edge in the graph has two coupling parameters ($w_{j \to i}$ and $w_{i \to j}$) resulting in bidirectional
coupling. For the 7-node, 12-node, and 16-node grid graph, we simulated 100 independent trials,
where for each trial the values of the edge weights $w_{j \to i}$ are randomly sampled from a uniform
distribution (see Table 1 for range of $w_{j \to i}$). For the 16-node random graphs, we simulated 10
independent trials per graph, resulting in a total of 100 trials for 10 graphs. The ranges of $w_{j \to i}$
where chosen such that reasonably realistic LFPs were generated by the network. We integrated
the system with a time step of 1e-4 seconds using a 4th order Runge-Kutta scheme for 20 seconds
and discarded the first 15 seconds to eliminate transient effects of the simulation. The resultant 5
seconds of excitatory activity $e[t]$ was then downsampled to 1 kHz using an 8th order Chebyshev
type I anti-aliasing filter and denoted as the simulated field potentials. Average power spectral
density (PSD) estimates of the simulated field potentials and ground truth flow for the 7-node
graph are shown in Extended Fig. 1a and b. Furthermore, we have repeated the simulations for

the 7-node graph using an excitatory time constant of $t_e = 0.005$ resulting in an oscillation around
12 Hz. This change does not negatively impact the performance of the GDAR model (see Extended
Fig. 1f-h).

Table 1: Simulation parameters of Wilson-Cowan model adapted from Abeysuriya et al.[61] and Deco et al.[62]

Parameter	Description	Value
τ_e	Excitatory time constant	0.002
τ_i	Inhibitory time constant	0.004
c_{ee}	Local excitatory to excitatory coupling	3.5
c_{ie}	Local inhibitory to excitatory coupling	-2.5
c_{ei}	Local excitatory to inhibitory coupling	3.75
P	Constant excitatory input	0.31
μ	Firing response threshold	1
σ	Firing threshold variability	0.25
ξ	Random noise input	$\mathcal{N}(0, 0.05)$
$w_{i \to j}$	Excitatory to excitatory connectivity (7 node graph)	0.05, ..., 0.55
$w_{i \to j}$	Excitatory to excitatory connectivity (12 node graph)	0.1, ..., 0.35
$w_{i \to j}$	Excitatory to excitatory connectivity (16 node grid graph)	0.1, ... 0.5
$w_{i \to j}$	Excitatory to excitatory connectivity (16 node random graphs)	0.05, ... 0.3

Simulating ground truth neural flow: We simulated the ground truth flow by calculating the
moment-to-moment influence that each excitatory node exerts on its neighbors. To do so, we first
executed each integration step with the full set of parameters to obtain $e[t]$. Then, for each
excitatory coupling parameter $w_{j \to i}$, we repeated the integration step with $w_{j \to i} = 0$ to obtain
$e_i[t]|_{w_{j \to i}=0}$, which denotes the activity at node i in the absence of an influence from node j at
time t. The flow from node j to node i was then defined as $f_{j \to i}[t] = e_i[t] - e_i[t]|_{w_{j \to i}=0}$. This
second step is repeated for all excitatory coupling parameters. The full two-step procedure is
repeated for each integration step. The resulting bidirectional ground truth flow $f^{\text{gt,b}}[t]$ was
downsampled using the same anti-aliasing filter as used for the simulated LFPs. As our GDAR
model only produced a unidirectional flow at each point in time, we define the unidirectional
ground truth flow $f^{\text{gt}}[t]$ between node i and j as $f_{i,j}^{\text{gt}}[t] = f_{i \to j}^{gt,b}[t] - f_{j \to i}^{gt,b}[t]$. It is noted that while
$f^{\text{gt}}[t]$ is unidirectional at each time point, the flow direction across each edge can change over
time.

GDAR flow: For each trial, we used the last 5 seconds of simulated LFPs to estimate the
parameters of the GDAR model for varying model orders as described in (Graph Diffusion
Autoregressive (GDAR) Model). The graph used for fitting the model is equal to the graph used
for the simulations. The estimated model parameters were then used to transform the simulated
LFP into an estimated flow signal according to (6).

VAR flow: For comparison, we also estimated the neural flow using a classical VAR model (Eq.
(7)). To do so, we first estimated the VAR model parameters using the same data as for fitting
the GDAR model. The directional flow across edge $j \to i$ is then computed as $f_{j \to i}^{\text{VAR,b}}[t] =$

$\sum_{k=1}^{p}(A_k)_{i,j}s_i[t]$. Similar to the ground truth flow, the unidirectional flow is defined as $f_{i,j}^{\text{VAR}}[t] =$
$f_{i\to j}^{VAR,b}[t] - f_{j\to i}^{VAR,b}[t]$. The VAR model assumes a fully connected network resulting into non-zero
flow signals across connections that are not part of the network. To compare the VAR flow with
the ground truth flow, we therefore only extract the VAR flow for edges that exists in the ground
truth network.

eVAR flow: For a fair comparison with the GDAR model, we test a second autoregressive model
that has access to the ground truth graph when estimating the VAR model coefficients. That is,
we enforce $(A_k)_{i,j} = (A_k)_{j,i} = 0$ if node i and j are not connected. Using this eVAR models, we
also computed a bidirectional flow $f^{\text{VAR,b}}[t]$ and compare it to the ground truth bidirectional flow
$f^{\text{gt,b}}[t]$. However, we found that this does not result in higher correlation coefficients than the
unidirectional flow (see Extended Fig. 1e).

CSD flow: The last approach for estimating the neural flow is through CSD analysis. Since CSD
is the second spatial derivative, which, for a given graph, can be approximated as the graph
Laplacian operator $\mathbf{BB}^T$, the CSD flow is simply the voltage gradient between the LPFs at
connected nodes in the network: $f_{i,j}^{CSD}[t] = s_i[t] - s_j[t]$. This is equivalent to a first order GDAR
model with spatially constant conductivity.

Comparing ground truth and estimated neural flow: The ground truth and estimated flow
signals are first z-scored independently for each trial and model, and then compared using the
Pearson correlation coefficient (PCC) computed independently for each edge in the graph. The
PCC distributions obtained by pooling PCCs from all edges and 100 trials for each model are
compared using a Wilcoxon rank-sum test. Furthermore, for the 7-node graph, the error between
magnitude and phase spectrum of ground truth and estimated flow were computed for each graph
edge and trial. To do so, the power spectral density (PSD) of the flow across each edge (5s for
each trial) was estimated using Welch's method[63] with a Hann window of size 256 samples and
50% overlap. Then the absolute difference (in dB) between ground truth and estimated flow was
computed. To compare the phases, the 5s of neural flow obtained for each trial were first divided
into 19 non-overlapping segments of 256 samples and then the discrete Fourier transform for each
segment was computed. Afterwards, the phase difference between ground truth and estimated
phase was computed and mapped into the range from 0 to π for each segment before being
averaged over all 19 segments. Fig. 2e shows the median, first, and third quartile of the magnitude
and phase difference using data from all edges and trials.

Optogenetic Stimulation Experiment

One adult male rhesus macaque (monkey G: 8 years old, 17.5 kg) was used in this experiment. All
procedures were performed under the approval of the University of California, San Francisco
Institutional Animal Care and Use Committee and were compliant with the Guide for the Care
and Use of Laboratory Animals.

Neural stimulation and recording interface: In this study, we used a subset of neural data
recorded by a large-scale optogenetic neural interface[11] that has previously been utilized to study

changes in network functional connectivity due to cortical stimulation[40,41]. The interface was
composed of several key components: a semi-transparent micro-electrode array, a semi-transparent
artificial dura, a titanium implant, and a laser system for delivering optical stimulation. First,
neurons in the primary sensorimotor cortex were rendered light-sensitive through a viral-mediated
expression of the C1V1 opsin. To do so, $200\,\mu$L of the viral cocktail AAV5-CamKIIa-
C1V1(E122T/E162T)-TS-eYFP-WPRE-hGH (2.5×10^{12} virus molecules/mL; Penn Vector Core,
University of Pennsylvania, PA, USA, Addgene number: 35499) was administered across four sites
into the primary somatosensory (S1) and primary motor (M1) cortices of the left hemisphere using
convection-enhanced delivery[11,40,64]. Next, the chronic neural interface was surgically implanted
by performing a 25mm craniotomy over the primary sensorimotor cortex, replacing the dura mater
beneath the craniotomy with a chronic transparent artificial dura housed in a titanium chamber.
During each experimental session, the artificial dura was removed and a custom 96 channel micro-
electrocorticography array consisting of platinum-gold-platinum electrodes and traces encapsuled
in Parylene-C[12] was placed on the cortical surface. Optical stimulation was performed by two 488
nm lasers (PhoxX 488-60, Omicron-Laserage, Germany) connected to a fiber optic cable
(core/cladding diameter: 62.5/125 μm, Fiber Systems, TX, USA) and positioned above the array
such that the tip of the fiber-optic cable touched the array. Neural data in the form of local field
potentials was recorded by the micro-ECoG array at a sampling frequency of 24 kHz using a
Tucker-Davis Technologies system (FL, USA). It was verified that evoked neural responses were
due to optogenetic activation and not other effects such as photoelectric artifacts or heating[11,12,41].

Stimulation protocol: The data analyzed in this study stems from three experimental sessions
all performed on the same day. The only difference between the sessions was the location of
stimulation, which is depicted in Fig. 3b. As the micro-ECoG array was not removed between
sessions its location on the cortex remains unchanged. Each experimental session consists of 5
stimulation blocks during which two lasers alternatingly and repeatedly stimulate. Each
stimulation block lasts approximately 7 min and is intermittent by shorter resting state blocks
during which no stimulation is performed. The stimulation pulse width for both lasers was 5 ms
with a delay of 10 ms between stimulation by lasers 1 and 2. This paired stimulation is repeated
at a frequency of 7 Hz (143 ms) resulting in a total of approximately 2970 pulse pairs for each
stimulation block. All stimulation parameters (except for stimulation locations) are identical for
the three sessions analyzed in this study.

Signal preprocessing: First, bad channels were identified as 1) electrodes with high impedance
and 2) channels with a low signal-to-noise ratio, and excluded from the analysis[41]. The location of
the remaining 67 good channels was used to construct a sparse and locally connected graph, where
each electrode corresponds to a node in the graph and each node is connected approximately to it
8 nearest neighbors (see Fig. 3c top). The raw time series data was downsampled to 1017.25 Hz
using a low-pass Chebyshev anti-aliasing filter and the mean activity within each channel was
subtracted from the respective time series.

GDAR model fitting: The preprocessed LPFs during each stimulation block were divided into
segments of 10004 samples (approximately 10 s) with 4 samples overlap between segments and a
5^{th} order GDAR model was fitted to each segment as described in (Graph diffusion autoregressive
(GDAR) model). The estimated model parameters were used to transform the neural activity into

a neural flow signal according to equation (6). The overlap between segments was chosen such
that a continuous neural flow signal was obtained from the segmented LFPs without relying on
zero padding. A model order of 5 was chosen for this application due to the short (10 ms) delay
between stimulation by lasers 1 and 2. For larger model orders, the neural flow evoked by the
second laser would increasingly be influenced by the neural activity evoked by the first laser
resulting in a mixing of the neural responses to both stimulation pulses. Flow dynamics akin to
the plots in Fig. 3e for a model order $p = 10$ are shown in Extended Fig. 3c and d.

Visualizing flow dynamics: To visualize the flow dynamics evoked by paired cortical
stimulation, we have to project the high dimensional flow signals ($f[t] \in \mathbb{R}^E$, where E is the
number of edges in the graph) onto a lower dimensional subspace. To so so, we first pooled the
first 25 flow snapshots from the onset of stimulation by the first laser from all sessions, blocks,
and pulse pairs in a single data matrix $F \in \mathbb{R}^{E \times M}$, where $M \approx 3 \cdot 5 \cdot 2970 \cdot 25$ (3 sessions, 5 blocks
per session, approximately 2970 pulse pairs per block, 25 flow snapsots per pulse pair). Afterwards
we performed principle component analysis (PCA) and projected F onto its first two principal
components (PCs) to obtain $\tilde{F} \in \mathbb{R}^{2 \times M}$. Fig. 3e shows the PCA reduced GDAR flow dynamics
where each trace illustrates a 25 snapshot long flow trajectory from a single pulse pair. For better
visualization only 250 individual trajectories per stimulation block selected at random are plotted.
Fig. 3g shows the same dynamics but instead using the VAR and CSD flow, respectively. Since
the number of edges for the VAR model is very large, computing the PCs of the associated matrix
M was not feasible. Therefore we first averaged the flow snapshots over 20 consequitive trials
before computing the PCs. For comparison, we performed the same trial averaing for the GDAR
flow and recomputed the flow trajectories (Extended Fig. 3e). The averaging does not seem to
have a negative effect on the discriminability of the trajectories between different sessions.

Modeling increased delay across sulcus: The GDAR model can easily be augmented to model
variable delay across different edges. For example, it is reasonable to assume that signals that
travel across the sulcus between M1 and S1 experience larger delays than signals traveling within
each cortex. Larger delays in the GDAR model across an edge between node i and j can be
incorporated by constraining edge coefficients $w_k^{\{i,j\}} = 0$ for small delays (i.e., $k = 1, 2, \dots$), which
can be achieved by augmenting the matrix $\mathbf{R}$ in equation (8). We have used this approach to
model larger delays across the sulcus by setting $w_k^{\{i,j\}} = 0$ for edges that connect nodes in M1 to
nodes in S1 for $k = 1, 2, 3$. That is, the minimum delay across each sulcus edge is constrained to
be 4 (see Extended Fig. 3f and Supplementary Video 2 for corresponding GDAR flow dynamics).

Changes in resting-state communication due to electrical stimulation:

To demonstrate the GDAR model's ability to uncover changes in communication during resting
state, we analyze data from two distinct experiments that were conducted using a 96-channel
microelectrode array (Utah array) and two 32-channel ECoG arrays.

Utah array experimental procedure: One adult rhesus macaque (*Macaca mulatta*, 12 kg, 11
years, male) was used in this study. All procedures were performed under the approval of the
University of California, San Francisco Institutional Animal Care and Use Committee and were
compliant with the Guide for the Care and Use of Laboratory Animals. The experimental

procedure was previously described by Bloch et al.[70]. A 96-channel Utah array was implanted in
S1 and LFPs were recorded at a sampling frequency of 24 kHz before being downsampled to a
frequency of 1017 Hz (8[th] order Chebychev anti-aliasing filter). The dataset consists of resting
state recordings intermitted by five 10 minute stimulation blocks that contain repeated single site
or paired electrical stimulation. For the single site stimulation session, stimulation is performed in
in the form of five pulses (1 kHz burst frequency) that are repeated every 200 ms. The paired
stimulation sessions use the same stimulation patterns for each stimulation site. For session *paired-*
stim 1, electrode B stimulated 100 ms after electrode A. For session *paired-stim 2*, the delay
between stimulation sites A and B is chosen uniformly at random between -100 ms and 100 ms
for each paired stimulation trial.

ECoG array experimental procedure: One adult macaque (*Macaca nemestrina*, 14.6 kg, 7
years, male) was used in this study. All procedures were performed under the approval of the
University of Washington Institutional Animal Care and Use Committee and were compliant with
the Guide for the Care and Use of Laboratory Animals. The experimental procedure was
previously described elsewhere[13,65,66]. The animal was first anesthetized with isoflurane and a
craniotomy with 25mm diameter was performed in each hemisphere over the sensorimotor cortex.
A focal ischemic lesion in the left hemisphere was created by photo-activation of a previously
injected light-sensitive dye (Rose Bengal). Following illumination, the dye causes platelet
aggregation, thrombi formation, and interruption of local blood flow, leading to local neural cell
death near the illuminated area. The location and extent of the lesion were estimated through
post-mortem histological analysis of coronal slices and is illustrated as a black patch in Fig. 5.
Electrical activity was recorded before, during, and after lesion induction simultaneously in the
ipsi- and contralesional hemisphere using two 32-channel ECoG arrays (Fig. 5c)[66,67].
Approximately 60 min after the end of lesioning, repeated electrical stimulation was performed 8
mm away from the lesion center. 1 kHz stimulation charge-balanced pulses (60 µA, 450 µs pulse
width, 50 µs interphase interval) were given in 5 Hz bursts (5 pulses per burst) consecutively for
10 minutes, where each stimulation block was followed by 2 min of baseline recording. The
experiments included a total of six 10 min stimulation blocks. We used the 60 min of neural
recording after lesion induction but before stimulation (pre stim), as well as the 2 min blocks of
baseline recording in between the stimulation blocks (post stim). In total we used 4 blocks of post
stim recordings for each hemisphere as the recordings in the other blocks were corrupted.

Signal preprocessing: The preprocessing for both datasets was performed akin to the
optogenetic stimulation experiment. The location of the ECoG channels was used to construct a
sparse and locally connected graph (for the ECoG data, this was done separately for each
hemisphere), where each node (electrode) is connected approximately to its 8 nearest neighbors
(no bad channels were identified). The raw time series data was downsampled to 1 kHz using low-
pass Chebyshev anti-aliasing filter and the mean was removed from each channel. Additionally,
artifacts – defined as signal values that deviate by ten or more standard deviations from the mean
simultaneously for all channels – were removed by linearly interpolating between the sample
immediately before and after the artifact.

Model fitting and postprocessing: The preprocessed LFPs for both datasets during each block
were divided into segments of length 10009 samples (approximately 10 s) with 9 samples overlap

between segments and a 10^{th} order GDAR model was fitted to each segment as described in Graph
diffusion autoregressive (GDAR) model. The estimated model parameters were used to transform
the neural activity into a neural flow signal according to equation (6), where each segments
contains 10000 samples. To assess changes in neural communication due to stimulation in different
frequency bands, we then computed the GDAR flow power spectral density (PSD) using Welch's
method[63] (Hann window of size 1000 samples with 50% overlap) for each segment, and stored the
average flow PSD within the gamma band $(30 - 70$ Hz). Finally, we computed the change in
average flow PSD from before to after stimulation. Specifically, if we denote $F_k^{\text{pre stim}}$ and $F_k^{\text{post stim}}$
as the average gamma flow PSD before and after stimulation of the k^{th} segment, the relative
change in neural flow magnitude Δ_{stim} is given by

$$\Delta_{\text{stim}} = \frac{\langle F_k^{\text{post stim}} \rangle_k - \langle F_k^{\text{pre stim}} \rangle_k}{\langle F_k^{\text{pre stim}} \rangle_k}, \qquad (17)$$

where $\langle \cdot \rangle_k$ denotes the average over all segments. We assessed the statistical significance of Δ_{stim}
for each edge by forming sample distributions for pre- and post-stim communication from all pre-
and post-stim segments and compared the distributions using a two-sample Kolmogorov-Smirnov
test. If the distributions for a given edge differ with a significance level of $p \leq 0.01$, the edge is
plotted in the graph.

For the Utah array data, changes in gamma GDAR flow power due to stimulation (Fig. 4b) were
computed using all data before stimulation (pre stim) as well as the five 2-minute resting state
blocks following the stimulation blocks (post stim) for each session. To compute the temporal
evolution of the normalized and averaged gamma GDAR flow power (Fig. 4c-e), the GDAR flow
power in the gamma band was first averaged over all edges connected to the stimulation node.
Then GDAR flow and LFP power were z-scored using the mean and standard deviation from the
pre stim period for each session independently. We then computed the best linear fit between the
z-scored LFP and average GDAR flow power $\bar{F}_{\text{GDAR}}$ using all segments (pre and post stim)

$$\bar{F}_{\text{GDAR}} = s \cdot LFP + o. \qquad (18)$$

708 The goal is to test whether the GDAR flow power changes beyond what can be linearly explained
709 by changes in LFP power. Hence, we subtract the linear regression line from the average GDAR
710 flow power

$$\bar{F}_{\text{GDAR,corrected}} = \bar{F}_{\text{GDAR}} - s \cdot LFP. \qquad (19)$$

and plotted the result in Fig. 4c-e.

For the ECoG data, we additionally computed the change in flow power Δ_{stim} using the CSD
approach and a 10^{th} order VAR model (CSD and VAR flow were computed as described in Wilson-
Cowan Simulations). The 10^{th} order VAR model was also used to compute changes in coherence,
partial directed coherence (PDC)[22] and directed transfer function (DTF)[21]. PDC and DTF for
each directed edge pair $j \rightarrow i$ were calculated using the following equations:

$$PDC_{j \to i} = \frac{|A_{i,j}(\omega)|^2}{\sum_{l=1}^{N}|A_{l,j}(\omega)|^2},$$ (20)

$$DTF_{j \to i} = \frac{|H_{i,j}(\omega)|^2}{\sum_{l=1}^{N}|H_{i,l}(\omega)|^2},$$ (21)

where $A_{i,j}(\omega)$ is the Fourier transform of $(A_k)_{i,j}$ (note that here k is the time variable), and $H_{i,j}(\omega)$
is the (i,j) entry of the Fourier transform of the inverse of A_k. To obtain a unidirectional
communication signal (Fig. 5d), we calculated the average between $i \to j$ and $j \to i$ for each pair
of edges.

Center-out Reach Task

One adult male rhesus macaque (7 years old, 16.5 kg) was used in this study. All procedures were
performed under the approval of the University of California, San Francisco Institutional Animal
Care and Use Committee and were compliant with the Guide for the Care and Use of Laboratory
Animals. Surgical procedure, neural interface, and signal preprocessing are the same as described
in Optogenetic Stimulation Experiment. However, for the center-out reach task, the ECoG was
placed fully over the primary motor (M1) cortex. Channels with persistent distortions were
identified and excluded from the analysis resulting in 77 good channels used to construct a sparsely
connected nearest neighbor graph as described previously. The animal performed a total of 200
successful reach trial, 25 for each of the eight directions (see Fig. 6a). Except for Fig. 6d, which
considers all 200 trials, we limit our analysis to the top-left direction (Direction 4) as this direction
exhibits a larger trial-by-trial variability than other directions. Each individual reach trial is
divided into start, instructed delay, and reach phase. During the start phase, the monkey places
its hand on the center of the screen. After that the instructed delay phase begins where first the
target direction is presented before a randomly selected delay period terminated by a go-tone is
introduced. The reach phase starts once the go-tone appears and ends when the monkey touches
the target. The finger position of the monkey was tracked throughout the experiment using and
electromagnetic position sensor (Polhemus Liberty, Colchester, VT) at 240 Hz[68].

GDAR model fitting and post-processing: To ensure accurate model fitting, recorded LFPs
from all three phases were used to estimate the parameters of the GDAR and VAR models. For
both models, the order was set to $p = 5$ to ensure a sufficient number of independent samples for
each parameter. After the model parameters have been estimated, the GDAR (VAR) flow is
computed according to Eq. (6) and filtered into the high-gamma band using a 3rd order
Butterworth filter with edge frequencies 70 and 200 Hz. Since we are specifically interested in
studying neural communication dynamics during the reach phase, we attempted to remove noise
from the sensory processing of the go-tone. To do so, we used the recorded reach trajectories to
identify the first time point $T_{\text{movement onset}}$ where significant movement is detected (defined as a
deviation of 3 mm from average finger position during the first 208 ms after the go-tone). The
GDAR (VAR) flow during reach is then defined as the flow starting 120 ms before $T_{\text{movement onset}}$
to account for the time delay between motor commands and actual movement[69]. Changes in GDAR
(VAR) flow power during reach over the instructed delay period (Fig. 6c) are then computed as

$$\Delta_{\text{reach}} = \frac{\langle |f_t^{\{\text{reach},k\}}|^2 \rangle_t - \langle |f_t^{\{\text{delay},k\}}|^2 \rangle_t}{\langle |f_t^{\{\text{delay},k\}}|^2 \rangle_t}, \tag{22}$$

where $f_t^{\{\cdot,k\}}$ is a flow snapshot of the k^{th} trial at time t and $\langle \cdot \rangle_t$ denotes the average over all time points within the respective experimental period.

To study the trial-by-trial variability of the spatial flow maps (Fig. 6e-g), first all flow snapshots $f_t^{\{\text{reach},k\}}$ for $t = 1, \dots T_k$ are stacked into an $E \times T_k$ matrix where T_k is the number of samples during reach of the k^{th} trial. Then PCA is performed independently for each trial and the first component $PC_1^{\{k\}} \in \mathbb{R}^E$ is stored. That is, $PC_1^{\{k\}}$ represents the dominant high-gamma flow pattern during the k^{th} reach trial. To test whether the dominant principal components from the 25 trials, form distinct clusters, we performed a second PCA to the $E \times 25$ matrix whose columns are comprised by $PC_1^{\{k\}}$ to reduce the dimension of the PCs to two. It is noted that the signs of some of the $PC_1^{\{k\}}$ had to be flipped manually prior to performing the second PCA to obtain two maximally compact clusters for the five slow and 20 faster reach trials, respectively.

and plot the resulting corrected average GDAR flow power $\bar{F}_{\text{GDAR,corrected}}$ in Fig. 4c-e. The relation between average GDAR flow and LFP power, along with the linear regression lines can be found in Extended Fig. 6.

Generalization performance

According to Eq. (5), the GDAR model can predict the neural activity at the current time step using the past p samples. To assess the generalization performance of the model, we computed the normalized root mean square error (RMSE) between the observed neural activity $s[t]$ and predicted neural activity $\hat{s}[t]$ as follows:

$$RMSE = \frac{\sqrt{\sum_{t,n}(\hat{s}_n[t] - s_n[t])^2}}{\sqrt{\sum_{t,n}(s_n[t])^2}} \tag{23}$$

The summation is performed over all time points t within a segment, as well as over all channels n of the recording array. To compute the train RMSEs, the predictions $\hat{s}[t]$ are computed for the same time points that were used for model fitting. For the test RMSEs, the models are applied to data that were not used for fitting the model. To compute the test RMSEs for the optogenetic stimulation, stroke, and Utah array datasets, the prediction RMSEs are computed for the 10 s segment that immediately follows the segment used for model fitting. That is, if the models have been fitted using segment i, the test RMSEs are computed using segment $i + 1$. For Fig. 7d, where the generalization gap over larger time scales is assessed, the prediction RMSEs are computed for segments further away from the segment used for model fitting. For the reach dataset, the models are tested on the subsequent reach trial in the same direction. That is if the models have been fitted using trial i from direction d then the test RMSE is computed for trial $i + 1$ from direction d.

Data availability:

Data will be made available upon reasonable request from the authors.

Code Availability:

Source code for the GDAR model will be made available prior to publication.

References:

1. Zeki, S. & Shipp, S. The functional logic of cortical connections. *Nature* 335, 311–317 (1988).
2. Bressler, S. L. Large-scale cortical networks and cognition. *Brain Res. Rev.* 20, 288–304 (1995).
3. Friston, K. Beyond Phrenology: What Can Neuroimaging Tell Us About Distributed Circuitry? *Annu. Rev. Neurosci.* 25, 221–250 (2002).
4. McIntosh, A. R. Towards a network theory of cognition. *Neural Netw.* 13, 861–870 (2000).
5. Duncan, J., Humphreys, G. & Ward, R. Competitive brain activity in visual attention. *Curr. Opin. Neurobiol.* 7, 255–261 (1997).
6. Bressler, S. L. & Menon, V. Large-scale brain networks in cognition: emerging methods and principles. *Trends Cogn. Sci.* 14, 277–290 (2010).
7. Voytek, B. & Knight, R. T. Dynamic Network Communication as a Unifying Neural Basis for Cognition, Development, Aging, and Disease. *Biol. Psychiatry* 77, 1089–1097 (2015).
8. He, B. J., Shulman, G. L., Snyder, A. Z. & Corbetta, M. The role of impaired neuronal communication in neurological disorders. *Curr. Opin. Neurol.* 20, 655 (2007).
9. Seeley, W. W., Crawford, R. K., Zhou, J., Miller, B. L. & Greicius, M. D. Neurodegenerative Diseases Target Large-Scale Human Brain Networks. *Neuron* 62, 42–52 (2009).
10. Shing, N., Walker, M. C. & Chang, P. The role of aberrant neural oscillations in the hippocampal-medial prefrontal cortex circuit in neurodevelopmental and neurological disorders. *Neurobiol. Learn. Mem.* 195, 107683 (2022).
11. Yazdan-Shahmorad, A. *et al.* A Large-Scale Interface for Optogenetic Stimulation and Recording in Nonhuman Primates. *Neuron* 89, 927–939 (2016).
12. Ledochowitsch, P. *et al.* Strategies for optical control and simultaneous electrical readout of extended cortical circuits. *J. Neurosci. Methods* 256, 220–231 (2015).
13. Khateeb, K. *et al.* A versatile toolbox for studying cortical physiology in primates. *Cell Rep. Methods* 2, 100183 (2022).
14. Griggs, D. J. *et al.* Optimized large-scale optogenetic interface for non-human primates. in *Optogenetics and Optical Manipulation 2019* (eds. Mohanty, S. K. & Jansen, E. D.) 3 (SPIE, San Francisco, United States, 2019). doi:10.1117/12.2511317.
15. Vázquez-Guardado, A., Yang, Y., Bandodkar, A. J. & Rogers, J. A. Recent advances in neurotechnologies with broad potential for neuroscience research. *Nat. Neurosci.* 23, 1522–1536 (2020).
16. Chang, E. F. Towards Large-Scale, Human-Based, Mesoscopic Neurotechnologies. *Neuron* 86, 68–78 (2015).
17. Bastos, A. M. & Schoffelen, J.-M. A Tutorial Review of Functional Connectivity Analysis Methods and Their Interpretational Pitfalls. *Front. Syst. Neurosci.* 9, (2016).
18. He, B. *et al.* Electrophysiological Brain Connectivity: Theory and Implementation. *IEEE Trans. Biomed. Eng.* 66, 2115–2137 (2019).
19. Granger, C. W. J. Investigating Causal Relations by Econometric Models and Cross-spectral Methods. *Econometrica* 37, 424–438 (1969).

20. Geweke, J. F. Measures of Conditional Linear Dependence and Feedback between Time Series. *J. Am.*
Stat. Assoc. 79, 907–915 (1984).

21. Kaminski, M. J. & Blinowska, K. J. A new method of the description of the information flow in the
brain structures. *Biol. Cybern.* 65, 203–210 (1991).

22. Baccalá, L. A. & Sameshima, K. Partial directed coherence: a new concept in neural structure
determination. *Biol. Cybern.* 84, 463–474 (2001).

23. Liu, S. *et al.* Abnormal EEG Complexity and Functional Connectivity of Brain in Patients with
Acute Thalamic Ischemic Stroke. *Comput. Math. Methods Med.* 2016, e2582478 (2016).

24. Xu, F. *et al.* Time-Varying Effective Connectivity for Describing the Dynamic Brain Networks of
Post-stroke Rehabilitation. *Front. Aging Neurosci.* 14, (2022).

25. Franaszczuk, P. J., Bergey, G. K. & Kamiński, M. J. Analysis of mesial temporal seizure onset and
propagation using the directed transfer function method. *Electroencephalogr. Clin. Neurophysiol.* 91,
413–427 (1994).

26. Wang, H. *et al.* Effects of tDCS on Brain Functional Network of Patients After Stroke. *IEEE Access*
8, 205625–205634 (2020).

27. Song, P. *et al.* Repetitive transcranial magnetic stimulation (rTMS) modulates time-varying
electroencephalography (EEG) network in primary insomnia patients: a TMS-EEG study. *Sleep Med.*
56, 157–163 (2019).

28. Olejarczyk, E. *et al.* Statistical Analysis of Graph-Theoretic Indices to Study EEG-TMS Connectivity
in Patients With Depression. *Front. Neuroinformatics* 15, (2021).

29. Palmigiano, A., Geisel, T., Wolf, F. & Battaglia, D. Flexible information routing by transient
synchrony. *Nat. Neurosci.* 20, 1014–1022 (2017).

30. Ferezou, I. *et al.* Spatiotemporal Dynamics of Cortical Sensorimotor Integration in Behaving Mice.
Neuron 56, 907–923 (2007).

31. Matsui, T., Murakami, T. & Ohki, K. Transient neuronal coactivations embedded in globally
propagating waves underlie resting-state functional connectivity. *Proc. Natl. Acad. Sci.* 113, 6556–
6561 (2016).

32. O'Neill, G. C. *et al.* Dynamics of large-scale electrophysiological networks: A technical review.
NeuroImage 180, 559–576 (2018).

33. Ren, Y. *et al.* Transient seizure onset network for localization of epileptogenic zone: effective
connectivity and graph theory-based analyses of ECoG data in temporal lobe epilepsy. *J. Neurol.*
266, 844–859 (2019).

34. Scheid, B. H. *et al.* Time-evolving controllability of effective connectivity networks during seizure
progression. *Proc. Natl. Acad. Sci.* 118, e2006436118 (2021).

35. Seguin, C., Sporns, O. & Zalesky, A. Brain network communication: concepts, models and
applications. *Nat. Rev. Neurosci.* 24, 557–574 (2023).

36. Seguin, C. *et al.* Communication dynamics in the human connectome shape the cortex-wide
propagation of direct electrical stimulation. *Neuron* 111, 1391-1401.e5 (2023).

37. Schwock, F., Bloch, J., Atlas, L., Abadi, S. & Yazdan-Shahmorad, A. Estimating and Analyzing
Neural Information flow using Signal Processing on Graphs. in *ICASSP 2023-2023 IEEE*
International Conference on Acoustics, Speech and Signal Processing (ICASSP) 1–5 (IEEE, 2023).

38. Carvalhaes, C. & de Barros, J. A. The surface Laplacian technique in EEG: Theory and methods. *Int.*
J. Psychophysiol. 97, 174–188 (2015).

39. Mitzdorf, U. Current source-density method and application in cat cerebral cortex: investigation of
evoked potentials and EEG phenomena. *Physiol. Rev.* 65, 37–100 (1985).

40. Yazdan-Shahmorad, A., Silversmith, D. B., Kharazia, V. & Sabes, P. N. Targeted cortical
reorganization using optogenetics in non-human primates. *eLife* 7, e31034 (2018).

41. Bloch, J. *et al.* Network structure mediates functional reorganization induced by optogenetic
stimulation of non-human primate sensorimotor cortex. *iScience* 25, 104285 (2022).

42. Yang, Y. *et al.* Modelling and prediction of the dynamic responses of large-scale brain networks during direct electrical stimulation. *Nat. Biomed. Eng.* 5, 324–345 (2021).

43. Sun, S. *et al.* Human intracortical responses to varying electrical stimulation conditions are separable in low-dimensional subspaces. in *2022 IEEE International Conference on Systems, Man, and Cybernetics (SMC)* 2663–2668 (2022). doi:10.1109/SMC53654.2022.9945369.

44. Afshar, A. *et al.* Single-Trial Neural Correlates of Arm Movement Preparation. *Neuron* 71, 555–564 (2011).

45. He, B. J. & Zempel, J. M. Average Is Optimal: An Inverted-U Relationship between Trial-to-Trial Brain Activity and Behavioral Performance. *PLOS Comput. Biol.* 9, e1003348 (2013).

46. Paraskevopoulou, S. E., Coon, W. G., Brunner, P., Miller, K. J. & Schalk, G. Within-subject reaction time variability: Role of cortical networks and underlying neurophysiological mechanisms. *NeuroImage* 237, 118127 (2021).

47. Avena-Koenigsberger, A., Misic, B. & Sporns, O. Communication dynamics in complex brain networks. *Nat. Rev. Neurosci.* 19, 17–33 (2018).

48. Abdelnour, F., Voss, H. U. & Raj, A. Network diffusion accurately models the relationship between structural and functional brain connectivity networks. *NeuroImage* 90, 335–347 (2014).

49. Ng, B., Varoquaux, G., Poline, J.-B. & Thirion, B. A Novel Sparse Graphical Approach for Multimodal Brain Connectivity Inference. in *Medical Image Computing and Computer-Assisted Intervention – MICCAI 2012* (eds. Ayache, N., Delingette, H., Golland, P. & Mori, K.) 707–714 (Springer, Berlin, Heidelberg, 2012). doi:10.1007/978-3-642-33415-3_87.

50. Hinne, M., Ambrogioni, L., Janssen, R. J., Heskes, T. & van Gerven, M. A. J. Structurally-informed Bayesian functional connectivity analysis. *NeuroImage* 86, 294–305 (2014).

51. Pineda-Pardo, J. A. *et al.* Guiding functional connectivity estimation by structural connectivity in MEG: an application to discrimination of conditions of mild cognitive impairment. *NeuroImage* 101, 765–777 (2014).

52. Pascucci, D. *et al.* Structure supports function: Informing directed and dynamic functional connectivity with anatomical priors. *Netw. Neurosci.* 6, 401–419 (2022).

53. Trongnetrpunya, A. *et al.* Assessing Granger Causality in Electrophysiological Data: Removing the Adverse Effects of Common Signals via Bipolar Derivations. *Front. Syst. Neurosci.* 9, (2016).

54. Pesaran, B. *et al.* Investigating large-scale brain dynamics using field potential recordings: analysis and interpretation. *Nat. Neurosci.* 21, 903–919 (2018).

55. Burago, D., Ivanov, S. & Kurylev, Y. A graph discretization of the Laplace–Beltrami operator. *J. Spectr. Theory* 4, 675–714 (2015).

56. Schaub, M. T., Zhu, Y., Seby, J.-B., Roddenberry, T. M. & Segarra, S. Signal processing on higher-order networks: Livin' on the edge... and beyond. *Signal Process.* 187, 108149 (2021).

57. Lütkepohl, H. *New Introduction to Multiple Time Series Analysis.* (New York : Springer, Berlin, 2005).

58. Wilson, H. R. & Cowan, J. D. Excitatory and Inhibitory Interactions in Localized Populations of Model Neurons. *Biophys. J.* 12, 1–24 (1972).

59. Wilson, H. R. & Cowan, J. D. A mathematical theory of the functional dynamics of cortical and thalamic nervous tissue. *Kybernetik* 13, 55–80 (1973).

60. Abeysuriya, R. G. *et al.* A biophysical model of dynamic balancing of excitation and inhibition in fast oscillatory large-scale networks. *PLOS Comput. Biol.* 14, e1006007 (2018).

61. Deco, G., Jirsa, V., McIntosh, A. R., Sporns, O. & Kötter, R. Key role of coupling, delay, and noise in resting brain fluctuations. *Proc. Natl. Acad. Sci.* 106, 10302–10307 (2009).

62. Welch, P. The use of fast Fourier transform for the estimation of power spectra: A method based on time averaging over short, modified periodograms. *IEEE Trans. Audio Electroacoustics* 15, 70–73 (1967).

63. Khateeb, K., Griggs, D. J., Sabes, P. N. & Yazdan-Shahmorad, A. Convection Enhanced Delivery of
Optogenetic Adeno-associated Viral Vector to the Cortex of Rhesus Macaque Under Guidance of
Online MRI Images. *JoVE J. Vis. Exp.* e59232 (2019) doi:10.3791/59232.
64. Bloch, J. A. *et al.* Cortical Stimulation Induces Network-Wide Coherence Change In Non-Human
Primate Somatosensory Cortex. in *2019 41st Annual International Conference of the IEEE*
Engineering in Medicine and Biology Society (EMBC) 6446–6449 (2019).
doi:10.1109/EMBC.2019.8856633.
65. Khateeb, K. *et al.* A Practical Method for Creating Targeted Focal Ischemic Stroke in the Cortex of
Nonhuman Primates. in *2019 41st Annual International Conference of the IEEE Engineering in*
Medicine and Biology Society (EMBC) 3515–3518 (IEEE, Berlin, Germany, 2019).
doi:10.1109/EMBC.2019.8857741.
66. Zhou, J. *et al.* Neuroprotective Effects of Electrical Stimulation Following Ischemic Stroke in Non-
Human Primates. in *2022 44th Annual International Conference of the IEEE Engineering in Medicine*
& Biology Society (EMBC) 3085–3088 (2022). doi:10.1109/EMBC48229.2022.9871335.
67. Griggs, D. J. *et al.* Multi-modal artificial dura for simultaneous large-scale optical access and large-
scale electrophysiology in non-human primate cortex. *J. Neural Eng.* 18, 055006 (2021).
68. Griggs, D. J. *et al.* Demonstration of an Optimized Large-scale Optogenetic Cortical Interface for
Non-human Primates. in *2022 44th Annual International Conference of the IEEE Engineering in*
Medicine & Biology Society (EMBC) 3081–3084 (2022). doi:10.1109/EMBC48229.2022.9871332.
69. Dadarlat, M. C., O'Doherty, J. E. & Sabes, P. N. A learning-based approach to artificial sensory
feedback leads to optimal integration. *Nat. Neurosci.* 18, 138–144 (2015).
70. Van Acker, G. M., III, Luchies, C. W. & Cheney, P. D. Timing of Cortico-Muscle Transmission
During Active Movement. *Cereb. Cortex* 26, 3335–3344 (2016).
949
950

951   Extended data figures

Extended Fig. 1: PCC of GDAR, VAR, and eVAR model on (a) 12-node locally connected graph, (b) 16-node grid graph, and (c) 16-node random graphs for various mode orders. For (a) and (b) the PCC is pooled from 100 simulation trials with varying excitatory coupling parameters (see Methods). For (c) ten trials are run for each of the graphs resulting in a total of 100 trials. Markers indicate whether the GDAR model significantly outperforms the eVAR model. The GDAR model significantly outperforms the other two models for all tested graphs given a sufficiently high model order.

Extended Fig. 2: Additional figures for simulations. All results are based on the 7-node graph shown in Fig. 2a. (a), (b) Power spectral densities of simulated field potentials and ground truth flow, respectively. The black line shows the average across all edges and trials. The gray shaded area indicated one half of the standard deviation. The steep drop-off above 400 Hz can be attributed to the 8th order Chebyshev filter that was used for downsampling the data to a sampling frequency of 1 kHz. (c) Magnitude spectrum (top) and group delay (bottom) computed from GDAR model edge parameters (model order of $p = 10$). The edge parameters can be interpreted as coefficients of finite impulse response filters that filter the voltage gradients to produce the GDAR flow signal (see Methods). Each gray line represents a single edge during an individual trial. The red line shows the absolute value of the phase error of the estimated GDAR flow compared to the ground truth flow (axis on the right). The oscillations in phase error correspond to zeros in the magnitude spectrum of the GDAR model edge filters (top). These zeros also cause large deflections in group delay (bottom) that closely match the oscillatory patterns of the phase error. (d) Distribution of correlation coefficients after band-pass filtering the ground truth and estimated flow into theta (4-7 Hz), beta (12-30 Hz), gamma (30-70 Hz), and high-gamma (70-200 Hz) frequency bands. The black surrounding box indicates the best performing model within each band. The GDAR model significantly outperforms all other models in the gamma and high-gamma band. (e) PCC between unidirectional ground truth and eVAR flow, as well as bidirectional ground truth and eVAR flow for various model orders. There is no significant performance difference between unidirectional and bidirectional eVAR flow for any model order. For most model orders, the unidirectional eVAR flow yields slightly higher median PCCs than the bidirectional eVAR flow. (f)-(h) performance of the GDAR model when changing the excitatory time constant τ_e to 0.005. The subplots replicate Fig. 2b, Extended Fig. 2d, Fig. 2e, respectively. Setting $\tau_e = 0.005$ results in a pronounced oscillation around 12 Hz. The overall performance of the GDAR model is largely unaffected by this change. p-values for (d)-(g) can be found in Supplementary Table 2 and Supplementary Table 4.

Extended Fig. 3: (a)-(f) Stimulation evoked dynamics using different signals and modeling approaches similar to the plots in Fig. 3e. Neither LFP (a) nor classical CSD (b), i.e., the second spatial derivative computed via the graph Laplacian, show significant temporal dynamics that are distinct between the sessions. Using a 10^{th} order GDAR model (c) results in reduced separability between sessions when compared to a 5^{th} order model shown in Fig. 3e (similarly for a 10^{th} order VAR model (d)). This is likely a result of the time scale of the paired stimulation (the onset of the second laser pulse occurs 5 ms after the offset of the first pulse) causing a mixing of the effects of the two lasers when fitting the models. (e) Averaging the flow signal over 20 consecutive trials before computing the low dimensional embedding does not a have negative affect on the dynamics. (f) PC reduced GDAR flow dynamics when constraining edges crossing the sulcus between M1 and S1 to exhibit a minimum signal propagation delay of 4ms. The dynamics are almost identical to the dynamics from the unconstrained GDAR model (Fig. 3e), suggesting that the stimulation induced communication dynamics uncovered by our model are robust to such constraints. (g), (h) The parameters of the 5^{th} order GDAR and VAR model for all segments, blocks, and sessions were stacked into a single matrix and projected onto its first two PCs. Each dot represents the PC reduced parameters of a single 10 s segment used for model fitting. The parameters from the three different sessions are well separated in this low dimensional subspace for the GDAR model, but not for the VAR model where Session 2 and 3 are not separable.

1000

Extended Fig. 4: *Replication of Fig. 5c and d for different frequency bands. Changes in communication are strongly dependent on frequency, as well as the methods used for estimating it. However, some features such an increase in communication in areas near the stimulation location in the ipsilesional hemisphere can be observed across multiple frequency bands and methods.*

Extended Fig. 5: Extended plots for reach data shown in Fig. 6 (a), (b) dependence of high-gamma LFP and CSD power on reach time across all eight directions. The CSD is computed via the graph Laplacian as described in (Methods). (c) Dominant CSD flow patterns for fast (top) and slow (bottom) reach trials for Direction 4 akin to the GDAR flow patterns in Fig. 6e. Compared to the GDAR flow, dominant CSD flow patterns generally cover larger parts of the network. (d) Projection of dominant CSD flow patterns into low-dimensional subspace defined by the first two principal components. The five fastest and slowest reaches are marked in green and purple, respectively. Cluster C1 is defined as the five fastest and 15 medium fast reach trials. Cluster C2 contains the five slowest trials. (c) Cluster centroids of C1 and C2, respectively. Dominant CSD flow patterns from fast and slow reach trials are less well separated compared to the GDAR flow.

1016

1017 *Extended Fig. 6: Relation between average gamma GDAR flow and LFP power for the stimulation electrodes in the*
1018 *Utah array dataset. The best linear regression lines are also shown (Single-stim:* **slope** $= -0.0692$, $p = 0.827$; *Paired-*
1019 *stim 1:* **slope** $= 2.41$, $p = 1.05e - 19$; *Paired-stim 2:* **slope** $= 2.15$, $p = 2.1e - 43$*). The two paired stim sessions show*
1020 *a strong linear relation between LFP and average GDAR flow power. Nevertheless, the GDAR flow power increases*
1021 *due to stimulation beyond what can be explained by linear changes in LFP power.*

Supplementary Material:

1023 *Supplementary Table 1: p-values for differences in Pearson correlation coefficients shown in Fig. 2b and Extended Fig.*
1024 *2d. The top row indicates the frequency band and model with the highest median PCC in that respective band. p-values*
1025 *are only computed with respect to the best performing model in each frequency band using a one-sided Wilcoxon rank-*
1026 *sum test.*

Broadband (GDAR 10)		Theta (eVAR 10)		Beta (eVAR 10)		Gamma (GDAR 10)		High-gamma (GDAR 10)	
CSD	7.96 $\cdot 10^{-70}$	CSD	3.21 $\cdot 10^{-16}$	CSD	1.17 $\cdot 10^{-17}$	CSD	3.73 $\cdot 10^{-38}$	CSD	1.16 $\cdot 10^{-105}$
VAR 10	2.91 $\cdot 10^{-19}$	VAR 10	3.14 $\cdot 10^{-6}$	VAR 10	0.00119	VAR 10	8.41 $\cdot 10^{-14}$	VAR 10	7.81 $\cdot 10^{-24}$
eVAR 10	8.24 $\cdot 10^{-8}$	GDAR 10	5.13 $\cdot 10^{-10}$	GDAR 10	0.0234	eVAR 10	1.4 $\cdot 10^{-5}$	eVAR 10	4.89 $\cdot 10^{-10}$

1027

1028 *Supplementary Table 2: p-values for differences in Pearson correlation coefficients shown in Fig. 2c and Extended Fig.*
1029 *2e. For "GDAR vs. eVAR", the alternative hypothesis is that the GDAR model outperforms the eVAR model. For "eVAR*
1030 *bidirectional vs. eVAR unidirectional", the alternative hypothesis is that the bidirectional outperforms the unidirectional*
1031 *VAR flow. We used one-sided Wilcoxon rank-sum tests.*

Model order	GDAR vs. eVAR	eVAR bidirectional vs. eVAR unidirectional
1	0.118	0.985
2	0.9997	0.99904
3	0.176	0.8
4	0.719	0.987
5	0.121	0.954
6	0.457	0.961
7	0.00497	0.871
8	0.0161	0.834
9	$8.26 \cdot 10^{-8}$	0.793
10	$8.24 \cdot 10^{-8}$	0.619
11	$3.06 \cdot 10^{-10}$	0.662
12	$6.31 \cdot 10^{-9}$	0.577
13	$2.1 \cdot 10^{-10}$	0.602
14	$8.03 \cdot 10^{-10}$	0.508
15	$5.28 \cdot 10^{-9}$	0.491

1032

1033 *Supplementary Table 3: p-values comparing GDAR and eVAR model for differences in Pearson correlation coefficients*
1034 *for larger graphs shown in Fig. 2d and Extended Fig. 1. We used one-sided Wilcoxon rank-sum tests.*

Model order	12-node graph	16-node grid graph	16-node random graphs
2	0.00716	1.0	0.917
4	$3.56 \cdot 10^{-7}$	1.0	0.948
6	$6.12 \cdot 10^{-7}$	1.0	0.76
8	$1.57 \cdot 10^{-6}$	1.0	0.246
10	$5.84 \cdot 10^{-6}$	0.955	0.00495
12	$1.61 \cdot 10^{-5}$	0.19	$5 \cdot 10^{-8}$
14	$8.29 \cdot 10^{-6}$	$8.05 \cdot 10^{-8}$	$1.03 \cdot 10^{-24}$
16	$1.37 \cdot 10^{-6}$	$2.35 \cdot 10^{-23}$	$5.85 \cdot 10^{-35}$
18	$3.39 \cdot 10^{-8}$	$8.21 \cdot 10^{-40}$	$1.2 \cdot 10^{-40}$
20	$6.05 \cdot 10^{-10}$	$3 \cdot 10^{-44}$	$9.99 \cdot 10^{-41}$
22	$2.98 \cdot 10^{-11}$	$2.33 \cdot 10^{-42}$	$8.34 \cdot 10^{-47}$
24	$6.58 \cdot 10^{-13}$	$4.59 \cdot 10^{-43}$	$9.79 \cdot 10^{-46}$
26	$1.21 \cdot 10^{-14}$	$1.25 \cdot 10^{-46}$	$2.19 \cdot 10^{-52}$
28	$5.63 \cdot 10^{-13}$	$6.56 \cdot 10^{-50}$	$2.42 \cdot 10^{-49}$
30	$5.08 \cdot 10^{-10}$	$4.58 \cdot 10^{-49}$	$7.13 \cdot 10^{-43}$

1035

1036

1037

1038

1039

1040

Broadband (GDAR 10)		Theta (eVAR 10)		Beta (eVAR 10)		Gamma (GDAR 10)		High-gamma (GDAR 10)	
CSD	$1.98 \cdot 10^{-25}$	CSD	$3.21 \cdot 10^{-11}$	CSD	0.0383	CSD	$2.89 \cdot 10^{-122}$	CSD	$7.91 \cdot 10^{-162}$
VAR 10	$4.01 \cdot 10^{-7}$	VAR 10	0.00138	VAR 10	0.0643	VAR 10	$1.54 \cdot 10^{-18}$	VAR 10	$8.6 \cdot 10^{-12}$
eVAR 10	0.0144	GDAR 10	$1.62 \cdot 10^{-8}$	GDAR 10	0.0305	eVAR 10	$2.91 \cdot 10^{-7}$	eVAR 10	$2.19 \cdot 10^{-4}$

Opto	Reach	Rest Utah	Rest ECoG
$8.27 \cdot 10^{-16}$	$1.76 \cdot 10^{-60}$	$4.05 \cdot 10^{-40}$	$2.37 \cdot 10^{-5}$

Supplementary Notes:

<u>Modeling signal propagation delay across sulcus for optogenetic stimulation experiment:</u> The GDAR model can also be adapted to model longer signal propagation paths between specific nodes in the network. For example, this may be the case for connections across the sulcus that separates M1 and S1. To model this, we have constrained the GDAR model to enforce a minimum propagation delay of 4 ms for all edges that connect nodes in M1 with nodes in S1 (see Methods). The evolution of the GDAR flow for Session 1 averaged over all trials is shown in Supplementary Video 2 and is similar to the dynamics observed in Fig. 3d and Supplementary Video 1, but with noticeably less flow across the sulcus. The PC reduced flow dynamics across all sessions are shown in Extended Fig. 3f and are almost identical to the dynamics shown in Fig. 3e, suggesting that adding signal propagation constraints to the model does not negatively impact the sensitivity of the GDAR flow signal to the stimulation parameters.