RealtimeDecoder: A fast software module for online clusterless decoding

Joshua P. Chu[1]☯, Michael E. Coulter[2,4]☯, Eric L. Denovellis[2,3,4], Trevor T. K. Nguyen[2,4,7], Daniel F. Liu[2,3,4], Xinyi Deng[5], Uri T. Eden[6], Caleb T. Kemere[1*], Loren M. Frank[2,3,4*]

1 Department of Electrical and Computer Engineering, Rice University

2 Department of Physiology, University of California, San Francisco

3 Howard Hughes Medical Institute, University of California, San Francisco

4 Kavli Institute for Fundamental Neuroscience, University of California, San Francisco

5 Department of Statistics and Data Science, Beijing University of Technology

6 Department of Mathematics and Statistics, Boston University

7 SpikeGadgets, Inc.

☯Equal contribution

* Corresponding authors: caleb.kemere@rice.edu, loren.frank@ucsf.edu

Abstract

Decoding algorithms provide a powerful tool for understanding the firing patterns that underlie cognitive processes such as motor control, learning, and recall. When implemented in the context of a real-time system, decoders also make it possible to deliver feedback based on the representational content of ongoing neural activity. That in turn allows experimenters to test hypotheses about the role of that content in driving downstream activity patterns and behaviors. While multiple real-time systems have been developed, they are typically

implemented in C++ and are locked to a specific data acquisition system, making them difficult to adapt to new experiments.

Here we present a Python software system that implements online clusterless decoding using state space models in a manner independent of data acquisition systems. The parallelized system processes neural data with temporal resolution of 6 ms and median computational latency <50 ms for medium- to large-scale (32+ tetrodes) rodent hippocampus recordings without the need for spike sorting. It also executes auxiliary functions such as detecting sharp wave ripples from local field potential (LFP) data. Performance is similar to state-of-the-art solutions which use compiled programming languages. We demonstrate this system use in a rat behavior experiment in which the decoder allowed closed loop neurofeedback based on decoded hippocampal spatial representations . This system provides a powerful and easy-to-modify tool for real-time feedback experiments.

Introduction

The brain enables animals to keep track of information about internal states and the external world and to use that information to guide action selection. This tracking engages neural representations, and thus understanding how those representation relate to internal or external variables can help us understand mental processes.(Knierim 2014). Decoding analyses provide one approach to understanding neural representations: an initial encoding model is built that relates observed variables to spiking, and then this model is inverted to enable predictions of observed variables based on spiking data (Brown et al. 1998). This approach has been used to characterize representations of neural activity from brain regionssuch as the hippocampus (Davidson, Kloosterman, and Wilson 2009; Karlsson and Frank 2009; Pfeiffer and Foster 2013).

The classic application of decoding was to assess how well a given variable could be read

out from ongoing neural population activity when that variable (e.g. the position of a limb or of the animal in space) could be observed. When such a correspondence has been established, decoding can also provide insight into representations expressed in the absence of an observable variable. In the hippocampus, for example, the spiking of "place cells" can be decoded both during movement and during periods of immobility. Strikingly, there are times when this spiking corresponds not to current location but instead to other places in the animals environment or even other environments (Carr, Jadhav, and Frank 2011; Foster 2017; Ólafsdóttir, Bush, and Barry 2018; Pfeiffer 2020). Similarly, decoding has also enabled the development of neurofeedback systems, such as brain-machine interfaces, that can translate neural activity patterns into useful outputs (e.g. moving a cursor on a screen or generating speech in patients with paralysis) (Daly and Wolpaw 2008; Luo, Rabbani, and Crone 2023).

Historically decoding hippocampal spatial activity patterns used a decoder which relied on sorted spikes (spikes that can be "clustered" and thereby assigned with reasonable confidence to a single neuron)(Davidson, Kloosterman, and Wilson 2009; Davoudi and Foster 2019; Diba and Buzsáki 2007; Farooq et al. 2019; Grosmark and Buzsáki 2016; Gupta et al. 2010; Karlsson and Frank 2009; Pfeiffer and Foster 2013; Shin, Tang, and Jadhav 2019; Wu et al. 2017; Zheng et al. 2021). In this decoder a Poisson model was used to describe the neural dynamics of individual place cells, where the Poisson rate is directly related to the place field (Brown et al. 1998; Meer, Carey, and Tanaka 2017; K. Zhang et al. 1998).

One disadvantage of the sorted spikes decoder is that it excludes lower amplitude or otherwise non-clusterable spikes. These spikes nevertheless contain valuable information for decoding, and alternative models known as clusterless decoders have been developed. (Deng, Liu, Karlsson, et al. 2016; Deng, Liu, Kay, et al. 2015; Denovellis et al. 2021; Kloosterman et al. 2014; Williams et al. 2020). These decoders use many more of the recorded spikes (typically all that pass a specific amplitude threshold), and provide more accurate decoding compared to sorted spike decoders in cases that have been tested (Deng, Liu, Kay, et al.

2015; Kloosterman et al. 2014). Subsequent studies have applied these methods to derive ₃₉ scientific conclusions (Gillespie et al. 2021; Hu et al. 2018; Michon et al. 2019). ₄₀

Clusterless decoding thus offers a powerful tool for identifying the content of neural ₄₁ representations, and real-time implementations have the potential to enable the use of this ₄₂ tool in closed-loop experiments. Current implementations are tied to a specific data ₄₃ acquisition system and written in a compiled programming language, however, which ₄₄ increases the difficulty of customization for end users without more advanced programming ₄₅ experience (Ciliberti, Michon, and Kloosterman 2018). We therefore developed ₄₆ `RealtimeDecoder` our software program that implements the state space models in ₄₇ (Denovellis et al. 2021) for online, real-time clusterless decoding ₄₈ (https://github.com/LorenFrankLab/realtime_decoder). The system is parallelized and ₄₉ written entirely in Python for ease of use for both users and developers. Despite using an ₅₀ interpreted language, the software achieves computational latencies similar to state-of-the-art ₅₁ solutions. An added benefit is the implementation of a state space model, allowing the ₅₂ experimenter to use both likelihood and posterior for downstream analysis. ₅₃

In this work we describe the architecture and performance of `RealtimeDecoder`. We focus ₅₄ on the latencies of computations and feedback, which are especially relevant in a real-time ₅₅ context. We also demonstrate the system's use in a live closed-loop experiment for proof of ₅₆ concept, and we briefly discuss some results. Our hope is that this work will help advance ₅₇ scientific research by enabling other closed-loop experiments that can elucidate the role of ₅₈ hippocampal spatial representations. ₅₉

Materials and Methods

Model formulation

The clusterless decoder used in this work is based on (Deng, Liu, Kay, et al. 2015; Denovellis et al. 2021). Similar to the sorted spikes decoder, this decoder uses a Bayesian framework. The model is governed by the equation

$$p(x_k | \Delta N_k \,,\, \{\vec{m}_k\} \,,\, H_k) = \frac{p(x_k | H_k) \; p(\Delta N_k \,,\, \{\vec{m}_k\} \mid x_k \,,\, H_k)}{p(\Delta N_k \,,\, \{\vec{m}_k\} \mid H_k)} \tag{1}$$

where for a given time bin k, x_k is decoded position, ΔN_k is the number of spikes emitted, and $\{\vec{m}_k\}$ is the set of marks of length ΔN_k, that is, vectors associated with each spike observed in time bin k. In practice the marks used in the model are spike waveform features such as peak amplitudes. Lastly H_k represents the spiking history from time 1 to time k.

The distribution $p(x_k | H_k)$ in Eq. 1 is given by

$$p(x_k \mid H_k) = \int p(x_k \mid x_{k-1}) \; p(x_{k-1} \mid \Delta N_{k-1} \,,\, \vec{m}_{k-1} \,,\, H_{k-1}) \; dx_{k-1} \tag{2}$$

assuming that (1) transitions from x_{k-1} to x_k are Markovian, and (2) the distribution of the current decoded position is independent of past spiking history, given the previous decoded position (Deng, Liu, Kay, et al. 2015).

For the clusterless likelihood, the relation is

$$p(\Delta N_k \,,\, \vec{m}_k \mid x_k \,,\, H_k) = p(\Delta N_k^{(1:E)} \,,\, \{\vec{m}_{k,j}^i\}_{j=1:\Delta N_k^i}^{i=1:E} \mid x_k)$$
$$\propto \prod_{i=1}^{E} \prod_{j=1}^{\Delta N_k^i} [\lambda_i(t_k, \vec{m}_{k,j}^i \mid x_k)\Delta_k] \; exp[-\Lambda_i(t_k \mid x_k)\Delta_k] \tag{3}$$

where $\prod_{j=1}^{\Delta N_k^i}[\lambda_i(t_k, \vec{m}_{k,j}^i \mid x_k)\Delta_k] \; exp[-\Lambda_i(t_k \mid x_k)\Delta_k]$ is the likelihood for electrode group $i = 1, ..., E$. (Our model assumed $p(\Delta N_k \,,\, \vec{m}_k \mid x_k \,,\, H_k) = p(\Delta N_k \,,\, \vec{m}_k \mid x_k)$). For each

electrode group, the product $[\lambda_i(t_k, \vec{m}^i_{k,j} \mid x_k)\Delta_k] \ exp[-\Lambda_i(t_k \mid x_k)\Delta_k]$ is computed for every

spike j within time bin k. If there are no spikes observed for electrode group i in time bin k,

then that electrode group's likelihood becomes

$$exp[-\Lambda_i(t_k \mid x_k)\Delta_k], \quad \Delta N^i_k = 0 \tag{4}$$

The likelihood consists of intensity functions

$$\lambda_i(t_k, \vec{m}^i_{k,j} \mid x_k) = \mu_i \frac{p_i(x_k, \vec{m}^i_{k,j})}{\pi(x)} \tag{5}$$

$$\Lambda_i(t_k \mid x_k) = \mu_i \frac{p_i(x_k)}{\pi(x)} \tag{6}$$

where μ_i is the mean firing rate of electrode group i and $\pi(x)$ is the occupancy, a

distribution of positions the animal has visited. $p_i(x_k)$ is the probability of observing any

spike given for electrode i, given the position. Lastly $p_i(x_k, \vec{m}^i_{k,j})$ represents a joint

probability distribution over position and marks. During the model learning phase, no

computation is performed–each mark $\vec{m}$ is simply saved along with the position x at which

the mark was observed. Once the learning phase is complete, $p(x, \vec{m})$ is estimated on-the-fly

for each observed mark $\vec{m}_l$. First a weight is computed for each mark $\vec{m}_o$ that has been

saved in the model, using a Gaussian kernel:

$$a_o{}^2 = \sum_{d=1}^{D} (\vec{m}_{o,d} - \vec{m}_{l,d})^2 \tag{7}$$

$$w_o = \frac{1}{\sigma\sqrt{2\pi}} exp[-\frac{a_o{}^2}{2\sigma^2}] \tag{8}$$

where D is the number of mark dimensions and σ is a user-defined parameter. Then a

weighted histogram representing the estimate $p(x, \vec{m})$ is computed using the positions $\{x_o\}$

saved during the learning phase, and the corresponding weights $\{w_o\}$ described above. ₉₀

Finally the posterior distribution can be written as ₉₁

$$p(x_k \mid \Delta N_k, \{\vec{m}_k\}, H_k) \propto p(x_k|H_k) \ p(\Delta N_k, \{\vec{m}_k\} \mid x_k, H_k) \tag{9}$$

where $p(x_k|H_k)$ is given in Eq. 2 and $p(\Delta N_k, \{\vec{m}_k\} \mid x_k, H_k)$ is given in Eq. 3. ₉₂

Software architecture ₉₃

Figure 1. (a) Data flows through different Process nodes in the `RealtimeDecoder` system, which are responsible for different computations.

Since the clusterless likelihood in Eq 3 is a product over electrode groups, this formula ₉₄
presents a straightforward scheme for parallelization. Each factor in can be computed ₉₅
simultaneously before being combined into the overall likelihood. The likelihood is then used ₉₆
to estimate the posterior distribution in Eq. 9. ₉₇

To carry out these computations `RealtimeDecoder` uses three different input data ₉₈
streams: LFP, spike events (particularly the waveform data), and position. An overview of ₉₉
the computational approach is shown in Fig. 1. Input data (ellipses) flow to parallel ₁₀₀
processes (rounded rectangles) which compute intermediate quantities (rhomboids), resulting ₁₀₁

in a reward trigger output (parallelogram) if a specific, experimenter specified representation is detected. To send messages between different processes, we used the low-latency messaging protocol MPI (Walker and Dongarra 1996).

The primary objective of online real-time clusterless decoding is to estimate the posterior distribution in relation 9, which is a conditional probability distribution over a variable x. In this application x represents linearized (1D) position. Recall that the clusterless likelihood in Eq. 3 is a product over electrode groups, which presents an obvious target over which to parallelize. The overall software architecture reflects this feature, as the computation of Eq. 3 can be split among multiple processes to reduce total system latency. These sub-computations is then be aggregated to form the posterior probability distribution.

Additionally the system can process LFP data to extract time boundaries in which LFP events (specifically sharp wave ripples or SWRs) occur. Experimenters thus have multiple options when using the system; for example they may specify that only replay with a concomitant SWR will trigger neurofeedback.

`RealtimeDecoder` is implemented as different `*Process` objects, namely `MainProcess`, `RippleProcess`, `EncoderProcess`, and `DecoderProcess` which serve different computational functions (Fig 1). Each instance of these objects (with the exception of the event-driven `GuiProcess`) implements a polling `while` loop which typically consists of the following pseudocode:

MainProcess

The `MainProcess` coordinates all other Process instances by gathering information about the binary data they output to file and monitoring their status to check for runtime errors, among other functions. Inside the `MainProcess` runs a custom data handler that processes data computed by other `*Process` objects, such as position information, ripple onset times, a new posterior distribution estimate, etc. In our usage this object detects replay events;

```
while no errors or stop signal not triggered do

    check for messages from other processes

    if message ready
        process message
    endif

    if data ready
        process data
        sent results to other processes
        write results
    endif

endwhile
```

Listing 1. Pseudocode example for a `Process` object

upon detection it sends a signal to dispense reward. ₁₂₇

RippleProcess ₁₂₈

An instance of a `RippleProcess` processes LFP data and is primarily responsible for ₁₂₉
detecting sharp wave ripples. This occurs via the following procedure: (1) LFP from the ₁₃₀
data acquisition system is band-pass filtered to the SWR frequency band (150-250 Hz), (2) ₁₃₁
an estimate of SWR power is obtained by applying a low pass filter to the square of the ₁₃₂
band-pass filtered data, and finally (3) the baseline (mean) power is estimated. The start of ₁₃₃
a SWR is then marked when the z-score of this power estimate exceeds a user-defined ₁₃₄
threshold (typically at least 3). ₁₃₅

EncoderProcess ₁₃₆

An instance of an `EncoderProcess` manages the encoding model for one or more electrode ₁₃₇
groups (e.g. a single tetrode). Typically if the number of available threads permits, a single ₁₃₈

instance will handle just one electrode group for minimum computational delay. During the training period, an `EncoderProcess` adds spikes to the encoding model and also computes an estimate of the joint mark intensity function (Deng, Liu, Kay, et al. 2015). When the training period is over, spikes are no longer added to the encoding model, but the joint mark intensity function continues to be estimated.

DecoderProcess

The `DecoderProcess` gathers the joint mark intensity functions sent by instances of an `EncoderProcess`. At every user-defined time bin step, it computes the likelihood and posterior distribution of the clusterless decoding state space model. It sends these estimates to the `MainProcess` to be further processed by a custom data handler. This data handler is developed according to the needs of the particular experiment and may implement features such as remote spatial representation detection.

GuiProcess

The `GuiProcess` increases user-friendliness of the system. It consists of a visualization window that displays the likelihood, posterior, and state probabilities in real time. It also includes a dialog window that allows the user to change parameters during the course of the experiment, as well as some control options to start and stop the software as a whole.

System characterization

The utility of an online decoding system for real-time feedback depends in large part on its latency. For example, if one chooses too small of a time step to update the posterior distribution estimate, the system cannot compute the necessary quantities quickly enough to be suitable for real-time use. The overall latency stems from the latencies of four major components (Fig 2a): (1) Network latency, (2) spike incorporation latency, (3) posterior

computational latency, and (4) event detection latency, which are further expanded in panel

(b). Each of these latencies is expanded in further detail below.

Figure 2. (a) The four major components contributing to overall latency. (b) Network latency. (c)-(d) Four spikes are shown. The darker shade indicates when a spike occur, and the lighter shade indicates when it is in usable form for a `DecoderProcess`. Note that spike 4 is in usable form subsequent to t_{curr}. (c) Time bin for when $\Delta t_{delay} > 0$. (d) Time bin for when $\Delta t_{delay} = 0$. (e) Overall distribution of latencies due to estimation of $p(x, m)$ using an example tetrode. (f) $p(x, m)$ estimation latencies as a function of number of spikes in the encoding model. (g) Computational latency induced by update of the posterior distribution.

Network latency

The network latency (Fig 2b) is the time difference between when data (spikes, LFP, position) is sent out by the data acquisition system, and when that data is actually requested by `RealtimeDecoder`. This type of latency depends on different factors such as network speed, the type of machine running the decoder, etc. Spikes have a higher latency than LFP due to its size, as the entire spike waveform/snippet is transmitted over the network. Nevertheless the median network latency of the pooled data (spikes and LFP combined) is <1 ms when the data acquisition program executes on the same host machine as `RealtimeDecoder`.

Spike incorporation latency

The spike incorporation latency refers to the maximum length of time between when a spike occurs and when it is sent to the decoder in a usable form. To be usable the joint mark intensity must be estimated with the spike and be visible to a `DecoderProcess` instance. At that point in time, the spike is ready to be incorporated into the posterior distribution estimation via an update of the likelihood.

The spike incorporation latency is a user-defined parameter and therefore a constant value. It must be long enough to account for the latency incurred from estimating the joint mark intensity function, a step whose computation time typically increases with the number of spikes used to generate the encoding models utilized by the decoder.

In `RealtimeDecoder`, the estimation of the posterior distribution occurs one time bin at a time. The data incorporated into each estimation step are those contained within a certain time window. This window is directly impacted by Δt_{delay} and Δt, the time bin size.

t_{curr} refers to the time at which an update to the posterior occurs. Δt_{delay} (a non-negative value) refers to how far behind t_{curr} should define the upper edge of the window. A combination of Δt_{delay} and Δt defines the lower edge. In other words, the window is defined

by $[t_{curr} - \Delta t_{delay} - \Delta t, \ t_{curr} - \Delta t_{delay})$. The spike incorporation latency is the sum $\Delta t_{delay} + \Delta t$.

Fig 2b-c illustrates the effect of the spike incorporation latency on the boundaries of the time window when an update to the posterior is requested at time t_{curr}. In Fig 2c, Δt_{delay} is chosen to be a non-zero value so the upper edge of the window lies at a time prior to t_{curr}. Spikes s_1, s_2, and s_3 are incorporated into the update of the posterior.

If $\Delta t_{delay} = 0$ (Fig 2d), then the upper edge of the window is simply t_{curr}. However, spike s_4 is NOT incorporated into the posterior update because it has not been transformed into a usable form until a time past t_{curr}. For this reason, it is advised to set $\Delta t_{delay} > 0$.

Fig 2e-f illustrates some considerations for determining an appropriate value to set as the spike incorporation latency. The joint mark intensity (JMI) in Eq. 5 must be estimated, where estimation of $p(x, m)$ is the most computationally expensive component. Fig 2e shows the overall distribution of the $p(x, m)$ estimation latencies. However, this is not the complete picture: Fig. 2f shows that these latencies are a function of number of samples in the encoder model. It thus illustrates typical operation of `RealtimeDecoder`: at some point the encoding model is considered trained, so no more spikes are added to the model and the estimation latency no longer increases linearly. On our test machine the estimation latency increased at an approximate rate of 0.5 ms additional latency for every 10000 additional spikes in the encoding model.

In general, the more spikes are expected to be added to the encoding models, the higher the user must set the value of the spike incorporation latency. Too low of a value would mean some JMI's cannot be computed and incorporated into the posterior estimation step in time, which could adversely affect the quality and accuracy of the posterior.

Posterior computational latency

The posterior computational latency is the computation time required to estimate the posterior distribution for a single update step. Fig 2g shows the distribution of this latency (median value 1.722 ms on our test machine). The latency is affected by multiple factors, including how many electrodes `RealtimeDecoder` is configured to analyze and how many states are in the state space model. The distribution in Fig 2g is useful for informing the user what the time bin size Δt should be. We advise setting Δt to at least the 75th percentile of this distribution. If Δt is too small, then the decoder would not be able to estimate the posterior quickly enough and would fail to operate in real time.

Event detection latency

The event detection latency is a user-defined parameter relevant for replay detection. Similar to the spike incorporation latency, it is a constant value. At each time bin step, a window is drawn. If the current timestamp is t_{curr}, then the event detection window is defined by $[t_{curr} - \Delta t_{event}, t_{curr}]$ where Δt_{event} is the event detection latency, a positive value denoting the size of the window. For example if Δt_{event} is 20 ms, then a putative representation will have been expressed for at least 20 ms before it is detected by the software. A higher value of the event detection latency will theoretically reduce the number of spurious detections, at the cost of increasing the reaction time to a true event.

Summary

Overall our decoder performs comparably to state-of-the-art solutions (Table 1) despite being written entirely in Python.

Scalability

The estimation of the JMI depends on the mark dimensionality, where Fig. 3(a)

Decoder	Network latency	Spike incorporation latency	Posterior computation latency	Event detection latency
Ciliberti 2018 (32 tetrodes)	0 ms (median, localhost)	10 ms	~2.2 ms (median)	30 ms
This work (49 tetrodes)	0.102 ms (median, localhost)	12 ms	1.722 ms (median)	30 ms

Table 1. `RealtimeDecoder` latency performance relative to the decoder in (Ciliberti, Michon, and Kloosterman 2018).

```python
import numpy as np
def generate_mark_data(mark_dim, num_marks_in_model, max_position_bin):

    marks = np.ones((num_marks_in_model, mark_dim))

    positions = np.zeros(num_marks_in_model)
    for ii in range(num_marks_in_model):
        positions[ii] = ii % max_position_bin

    return marks, positions
```

Listing 2. Test input generation for characterizing effect of mark dimensionality on computational latency.

demonstrates this relation. Here test inputs were generated deterministically according to   235
Listing 2, where all spikes were identical in magnitude and the distribution of positions was   236
uniform. Note that different test inputs are not expected to change the relations   237
demonstrated by Fig 3(a) since the actual values of the marks and position do not matter   238
when only latency measurements are of concern.   239

Although the computational latencies increase with the number of mark dimensions, the   240
multiplier for this increase is less than the ratio of a given mark dimensionality to a reference   241
mark dimensionality. As an example, increasing the dimensionality from 1 to 16 does not   242

Figure 3. (a) Computational latency for estimation of the JMI depends on the mark dimensionality. (b) LFP computational latency. Median values are labeled above the distribution they were computed from.

result in a 16X increase in the computational latencies. This is a favorable characteristic   243
especially for experimenters using larger electrode groupings, such as for polymer or silicon   244
multielectrode arrays.   245

For the LFP processing path, users may want to process multiple channels on one given   246
`RippleProcess` instance. Real-time constraints dictate that every LFP sample must be   247
processed at $\Delta t_{LFP} < 1/fs_{LFP}$ where Δt_{LFP} is the LFP processing time and fs_{LFP} is the   248
LFP sampling rate.   249

A `RippleProcess` instance is responsible for processing LFP by filtering the data into the   250
ripple band, estimating the ripple power (or a proxy of it), and determining the start and   251
end times of a ripple. Fig 3(b) shows the computational latency caused by processing LFP   252
data, for a single `RippleProcess` instance. Here the LFP sampling rate was 1500 Hz, so the   253
maximum LFP processing latency is 667 microseconds. These results demonstrate that 10   254
(and likely more) LFP channels may be processed with comfortable margin to meet the 667   255
microsecond real-time deadline. Recall that each `*Process` instance, with the exception of   256
`GuiProcess`, implements a polling `while` loop so this deadline represents the upper bound   257
since other tasks must be executed for every loop iteration.   258

Overall Fig 3 demonstrates favorable scaling characteristics for higher dimensionality data. ₂₅₉

Results ₂₆₀

To demonstrate the utility of `RealtimeDecoder` we applied it to an experiment to study ₂₆₁ internally driven memory retrieval. Specifically, we used `RealtimeDecoder` to deliver reward ₂₆₂ based on decoded spatial representation to test whether rats can control the activation of ₂₆₃ specific remote spatial representations . This endeavor is a type of experiment that can ₂₆₄ decode neural activity while it is occurring and react on a timescale of 10s of milliseconds, ₂₆₅ bringing researchers to a closer understanding of memory-related neural firing patterns. ₂₆₆

In this experiment a Long-Evans rat was surgically implanted with a microdrive with 64 ₂₆₇ individually adjustable tetrodes (all animal surgery and care was performed in accordance ₂₆₈ with UCSF IACUC guidelines). Over the course of several weeks, tetrodes were lowered into ₂₆₉ the CA1 region of dorsal hippocampus. The rat was food-restricted and trained to run on a ₂₇₀ two-arm maze where it collected sweetened milk reward from lick ports in the maze. ₂₇₁

Once tetrodes were in place, the experiment began. Each day consisted of interleaved ₂₇₂ RUN and REST sessions in the following manner: REST 1, RUN 1, REST 2, RUN 2, REST ₂₇₃ 3, RUN 3, REST 4. During REST sessions, the animal was placed in an enclosed box away ₂₇₄ from the maze. ₂₇₅

The structure of a RUN session was sub-divided into two tasks (Fig 4a), but the decoder ₂₇₆ itself runs for the entire duration of a session. During task 1 ($\sim$ 10 min.), a light cue directed ₂₇₇ the rat to explore each arm (12 visits each). The data collected from this exploration period, ₂₇₈ and specifically spikes that occurred during periods of running, defined the encoding models ₂₇₉ contained in the decoder. ₂₈₀

In task 2, the animal no longer collected reward by running to the end of a maze arm. ₂₈₁ Instead, reward was only available at a reward port at the center of the maze, located away ₂₈₂ from each arm. When the decoder detected a remote representation of a target location ₂₈₃

Figure 4. (a) Overview of experiment to which the real-time decoder was applied. Each session consists of two tasks. In task 1 an animal explores the maze arms. This data is used to train the encoding models. In task 2 the animal receives reward for generating a remote representation event. Although place cells and remote sequences are expected to be present, they are not used directly by the clusterless decoder. (b) Example events captured by the decoder. The blue trace is the actual position of the animal. A 100 ms window is drawn around the time of event detection. (c) Number of rewards for each session of neurofeedback.

unknown to the rat (the end of one arm), a sound cue was played and the rat had 3 seconds
to nose-poke and collect the milk reward. Importantly, remote representations were only
rewarded if the rat was near the center port, away from the arms. Detected representations
were required to be high-fidelity events i.e. with little representation in the off-target arm.

To detect a remote representation, a sliding window is applied to the posterior or
likelihood, which are both normalized to be a probability distribution. The distribution used
for detection is a user-defined parameter. Whenever the distribution is updated (i.e. one
time bin step has advanced), a window $[t_{curr} - \Delta t_{window}, t_{curr}]$ is drawn around the current
timestamp. The average for each bin (more exactly, position bin) in the distribution is taken
across the window. If representation in the target region exceeds a threshold and
representation in the off-target region is below a (different) threshold, a remote
representation is considered to have occurred. Note that in this implementation we did not
use the continuity constraint that combines information from the previous timestep with the
spiking information from the current timestep. We also did not include a requirement for a
specific LFP signature, although there would likely be some overlap among the events
detected by this method and those that detect SWRs or population burst events (PBEs).
Some example events are shown in Fig. 4b.

One pilot animal performed this task and demonstrated that the closed-loop
neurofeedback worked as designed to detect and reward sustained remote representations
(Fig. 4b). After several days of preliminary neurofeedback, we introduced the requirement
that at least 2 tetrodes had spatially specific activity for event detection, so as to reward
population-level representations. With this requirement, we found that detected event count
increased across 9 feedback sessions targeting arm 1 and then after switching the target
region to arm 2, also increased across 9 more sessions (Fig. 4c). This provides a preliminary
suggestion that remote hippocampal content can be enriched via reward-based
neurofeedback. In subsequent experiments, we tested whether this finding was reproducible

across multiple animals and robust to additional controls (ref: mikes bioarxiv). ₃₁₀

Discussion ₃₁₁

Decoding neural activity allows experimenters to assess the structure of ongoing neural ₃₁₂
representations. Here we present a real-time system that implements a clusterless state space ₃₁₃
decoder. The specific implementation was designed to decode spatial representations from ₃₁₄
the spiking of hippocampal neurons, but the system would be relatively easy to modify to ₃₁₅
decode other variables. We improved upon previous real-time clusterless decoders by writing ₃₁₆
the software in pure Python to ease the experience of users intending to extend and ₃₁₇
customize the system for their needs. Despite the use of Python, our system achieved ₃₁₈
comparable performance to previous systems written with a compiled language, ₃₁₉
demonstrating the viability of using an interpreted language for this specific application. We ₃₂₀
also demonstrate the system in a pilot experiment, illustrating how it can be used to detect ₃₂₁
the expression of specific hippocampal representations of space and to trigger experimental ₃₂₂
stimuli based on that expression. ₃₂₃

One area for improvement is the scalability of our decoder. For best results, one hardware ₃₂₄
thread is needed for every electrode group. However, the channel counts of neural recording ₃₂₅
devices are continuing to increase, and even with systems that have many computing cores, ₃₂₆
the number of channels per device will exceed current CPU capabilities. One potential ₃₂₇
solution would be to leverage computing on GPUs so that a single hardware thread can ₃₂₈
support multiple electrode groups. In order to fully take advantage of the GPU, this strategy ₃₂₉
would likely require some non-trivial programming to convert the synchronous computing ₃₃₀
into asynchronous. Alternatively, it may be possible to develop dimensionality reduction ₃₃₁
approaches that make it possible to carry out real-time clusterless decoding from very high ₃₃₂
channel count probes, something that is currently only possible offline (Y. Zhang et al. 2024). ₃₃₃

While these improvements can be made, the current `RealtimeDecoder` has numerous ₃₃₄

applications within the neuroscience sub-field of hippocampal physiology by assisting researchers to run many kinds of closed-loop experiments. Applications to other neuroscience sub-fields are also possible. For example one may wish to design a brain-computer interface which can decode memories its human operator is attempting to retrieve, and to subsequently react in real-time based on that decoding. The computational approach illustrated by `RealtimeDecoder` has the potential to inform solutions to other decoding-based problems in general. Overall we believe our work serves as a valuable tool to accelerate neuroscience research.

Appendix

Customization

Although we have endeavored to write a generalized software system for real-time decoding, it is difficult to anticipate every use case. In some scenarios customization may be necessary to fulfill the particular needs of the experiment. Here we cover different layers of customization and explain the source code at a deeper level so that the user can better understand the modifications that must be made for their specific application.

Customizing the data acquisition interface

As explained previously our software can be likened to a client in a client-server architecture, where `RealtimeDecoder` is the client and the data acquisition system is the server which sends preprocessed data for decoding. The decoder will work out of the box with Trodes software; for other systems, the user will need to develop a `DataSourceReceiver` subclass to interface with their data acquisition. The data acquisition is not constrained to be one that streams live data, as in the case of Trodes. One may wish to feed pre-recorded data into `RealtimeDecoder`, by reading from file. The parent class is defined in Listing 3, and an

explanation of the intended uses of each method follows.

```python
class DataSourceReceiver(MPIClass, metaclass=ABCMeta)

    def __init__(self, comm, rank, config, datatype:datatypes.Datatypes):
        super().__init__(comm, rank, config)
        self.datatype = datatype

    @abstractmethod
    def register_datatype_channel(self, channel):
        pass

    @abstractmethod
    def activate(self):
        pass

    @abstractmethod
    def deactivate(self):
        pass

    @abstractmethod
    def stop_iterator(self):
        pass

    @abstractmethod
    def __next__(self):
        pass
```

Listing 3. Definition of DataSourceReceiver class

In the `__init__()` method `comm` is the MPI communicator, `rank` is the MPI rank, and `config` is the dictionary obtained from parsing the configuration file (explained in the previous chapter). Finally `datatype` is one of the datatypes enumerated in the `datatypes` module.

The `register_datatype_channel()` method is used to add an electrode group that the object should receive from. Each electrode group may consist of multiple electrodes; for example a tetrode consists of 4 electrodes.

The `activate()` method signifies that the `DataSourceReceiver` is ready to receive data; thus `__next__()` may return a non-`None` object.

The `deactivate()` method signifies that the object is no longer receiving data. In this state `__next__()` should always return `None`.

The `stop_iterator()` stops the object from running entirely. Since the object can be used as an iterator (hence the `__next__()` method), this method should at the minimum contain a `raise StopIteration` statement.

Lastly `__next__()` should be called whenever data is to be returned. If no data are currently available or the object is in a deactivated state, then this method should return `None`.

Upon a call to `__next__()`, any `DataSourceReceiver` object that returns a data point in the following formats are automatically compatible with `RealtimeDecoder`. These are further explained below.

Spike data points are implemented as Listing 4. `timestamp` is a value that marks the timestamp of the data point and can be represented as a 32-bit unsigned integer. `elec_grp_id` is an integer denoting the electrode group the data point is coming from. `data`

```python
class SpikePoint(messages.PrintableClass):
    """Object describing a single spike event"""

    def __init__(self, timestamp, elec_grp_id, data, t_send_data,
        t_recv_data):

        self.timestamp = timestamp
        self.elec_grp_id = elec_grp_id
        self.data = data
        self.t_send_data = t_send_data
        self.t_recv_data = t_recv_data
```

Listing 4. Definition of SpikePoint class

is the actual spike waveform data, a 2D array of shape (nch, nt) where nch is the number of
electrodes in the electrode group and nt is the number of time samples in the spike waveform.
t_send_data is a 64-bit integer marking the time in nanoseconds where the data was sent out
by the data acquisition system. Similarly t_recv_data is a 64-bit integer marking the time in
nanoseconds where the data was actually received by the DataSourceReceiver. Both
t_send_data and t_recv_data are primarily used for diagnostics purposes to characterize
network latency.

LFP data points are implemented as 5. For an LFPPoint timestamp, t_send_data, and
t_recv_data have identical meanings as for a SpikePoint. Differences include elec_grp_ids:
since a LFPPoint typically may contain data from *multiple* electrode groups elec_grp_ids is
a list of those groups. Finally data is a 1D array containing the actual LFP data.

Lastly position data points are implemented as 6. Both timestamp and t_recv_data have
identical meanings to those in SpikePoint and LFPPoint. In a real experiment the position
is often coming from a head-tracked animal, so we will refer to that when explaining the rest
of the data that this object represents. segment refers to a line segment (integer-valued) that
the animal is closest to. position is a value in [0, 1] that denotes the position along the line

```python
class LFPPoint(messages.PrintableClass):
    """Object describing a single LFP data sample"""

    def __init__(self, timestamp, elec_grp_ids, data, t_send_data,
        t_recv_data):

        self.timestamp = timestamp
        self.elec_grp_ids = elec_grp_ids
        self.data = data
        self.t_send_data = t_send_data
        self.t_recv_data = t_recv_data
```

Listing 5. Definition of LFPPoint class

```python
class CameraModulePoint(messages.PrintableClass):
    """Object describing a single data sample coming from a camera"""

    def __init__(
        self, timestamp, segment, position,
        x, y, x2, y2, t_recv_data
    ):

        self.timestamp = timestamp
        self.segment = segment
        self.position = position
        self.x = x
        self.y = y
        self.x2 = x2
        self.y2 = y2
        self.t_recv_data = t_recv_data
```

Listing 6. Definition of CameraModulePoint class

segment. 0 and 1 are the ends of the segment. x and y are the x and y position of the   398
animal, respectively, in pixels. x2 and y2 have the same interpretation as x and y, except   399
that this is another point on the animal that is being tracked. For example the coordinates   400
(x, y) and (x2, y2) may be the position of a red and green LED.   401

The fastest way to make RealtimeDecoder compatible with a custom data acquisition   402
system is to develop a DataSourceReceiver subclass that still returns a SpikePoint,   403
LFPPoint, or CameraModulePoint. If the experimenter desires to use a different data format,   404
additional development will be necessary so that the software can handle the custom data   405
objects. The most relevant modifications to make will be the next_iter() methods for the   406
RippleManager, EncoderManager, and DecoderManager objects in ripple_process.py,   407
encoder_process.py, and decoder_process.py, respectively.   408

When `RealtimeDecoder` is running, it records results to disk. These can simply be thought   410
of as log entries in binary form. For example a record is written when the posterior   411
distribution is updated one time step.   412

Occasionally a user may wish to add, remove, or otherwise change the type of records that   413
are written. At the minimum the appropriate `*Manager` object should be modified in its   414
constructor. Listing 7 shows an example for the `DecoderManager`.   415

`rec_ids` are a list of integer-valued numbers, each of which describes the type of record   416
that is being written. These are particularly useful when the outputs of `RealtimeDecoder`   417
are merged into a single file. Different processes can write the same type of records, so when 418
merging records, the ID is used to group them together.   419

`rec_labels` are used to label each element in a single record (i.e. a binary blob). This is   420
useful for converting the binary data into human-readable format, such as a `pandas`   421
dataframe.   422

Finally `rec_formats` describe the datatype (such integer, float, etc.) used to represent a   423
given record. These are all format strings from the `struct` module in the Python standard   424
library.   425

If a record is changed, the corresponding call to `write_record()` must likewise be   426
updated so that the correct arguments are supplied. Other modifications to the code may be   427
necessary. Since it is impossible to anticipate every possibility, such changes are not   428
described here. Nevertheless this section should point the user in the right direction on   429
where to begin their modifications.   430

```python
rec_ids=[
    binary_record.RecordIDs.DECODER_OUTPUT,
    binary_record.RecordIDs.LIKELIHOOD_OUTPUT,
    binary_record.RecordIDs.DECODER_MISSED_SPIKES,
    binary_record.RecordIDs.OCCUPANCY
],
rec_labels=[
    ['bin_timestamp_l', 'bin_timestamp_r', 'velocity', 'mapped_pos',
    'raw_x', 'raw_y', 'raw_x2', 'raw_y2', 'x', 'y',
    'spike_count', 'task_state', 'cred_int_post', 'cred_int_lk',
    'dec_rank', 'dropped_spikes', 'duplicated_spikes', 'vel_thresh',
    'frozen_model'] +
    pos_labels + state_labels,
    ['bin_timestamp_l', 'bin_timestamp_r', 'mapped_pos', 'spike_count',
        'dec_rank',
    'vel_thresh', 'frozen_model'] +
    likelihood_labels,
    ['timestamp', 'elec_grp_id', 'real_bin', 'late_bin'],
    ['timestamp', 'raw_x', 'raw_y', 'raw_x2', 'raw_y2', 'x', 'y',
    'segment', 'pos_on_seg', 'mapped_pos', 'velocity', 'dec_rank',
    'vel_thresh', 'frozen_model'] +
    occupancy_labels
],
rec_formats=[
    'qqdddddddddqqqqqqqqd?' + 'd'*len(pos_labels) + 'd'*len(state_labels),
    'qqdqqd?' + 'd'*len(likelihood_labels),
    'qiii',
    'qdddddddqdddqd?' + 'd'*len(occupancy_labels)
]
```

Listing 7. Defining record types

References

Brown, E. N., L. M. Frank, D. Tang, M. C. Quirk, and M. A. Wilson (1998). A statistical paradigm for neural spike train decoding applied to position prediction from ensemble firing patterns of rat hippocampal place cells. In: *Journal of Neuroscience* 18.18, pp. 7411–7425.

Carr, M. F., S. P. Jadhav, and L. M. Frank (2011). Hippocampal replay in the awake state: a potential substrate for memory consolidation and retrieval. In: *Nature neuroscience* 14.2, pp. 147–153.

Ciliberti, D., F. Michon, and F. Kloosterman (2018). Real-time classification of experience-related ensemble spiking patterns for closed-loop applications. In: *Elife* 7, e36275.

Daly, J. J. and J. R. Wolpaw (2008). Brain–computer interfaces in neurological rehabilitation. In: *The Lancet Neurology* 7.11, pp. 1032–1043.

Davidson, T. J., F. Kloosterman, and M. A. Wilson (2009). Hippocampal replay of extended experience. In: *Neuron* 63.4, pp. 497–507.

Davoudi, H. and D. J. Foster (2019). Acute silencing of hippocampal CA3 reveals a dominant role in place field responses. In: *Nature neuroscience* 22.3, pp. 337–342.

Deng, X., D. F. Liu, M. P. Karlsson, L. M. Frank, and U. T. Eden (2016). Rapid classification of hippocampal replay content for real-time applications. In: *Journal of neurophysiology* 116.5, pp. 2221–2235.

Deng, X., D. F. Liu, K. Kay, L. M. Frank, and U. T. Eden (2015). Clusterless decoding of position from multiunit activity using a marked point process filter. In: *Neural computation* 27.7, pp. 1438–1460.

Denovellis, E. L., A. K. Gillespie, M. E. Coulter, M. Sosa, J. E. Chung, U. T. Eden, and L. M. Frank (2021). Hippocampal replay of experience at real-world speeds. In: *Elife* 10, e64505.

Diba, K. and G. Buzsáki (2007). Forward and reverse hippocampal place-cell sequences during ripples. In: *Nature neuroscience* 10.10, pp. 1241–1242.

Farooq, U., J. Sibille, K. Liu, and G. Dragoi (2019). Strengthened temporal coordination within pre-existing sequential cell assemblies supports trajectory replay. In: *Neuron* 103.4, pp. 719–733.

Foster, D. J. (2017). Replay comes of age. In: *Annual review of neuroscience* 40, pp. 581–602.

Gillespie, A. K., D. A. A. Maya, E. L. Denovellis, D. F. Liu, D. B. Kastner, M. E. Coulter, D. K. Roumis, U. T. Eden, and L. M. Frank (2021). Hippocampal replay reflects specific past experiences rather than a plan for subsequent choice. In: *Neuron* 109.19, pp. 3149–3163.

Grosmark, A. D. and G. Buzsáki (2016). Diversity in neural firing dynamics supports both rigid and learned hippocampal sequences. In: *Science* 351.6280, pp. 1440–1443.

Gupta, A. S., M. A. Van Der Meer, D. S. Touretzky, and A. D. Redish (2010). Hippocampal replay is not a simple function of experience. In: *Neuron* 65.5, pp. 695–705.

Hu, S., D. Ciliberti, A. D. Grosmark, F. Michon, D. Ji, H. Penagos, G. Buzsáki, M. A. Wilson, F. Kloosterman, and Z. Chen (2018). Real-time readout of large-scale unsorted neural ensemble place codes. In: *Cell reports* 25.10, pp. 2635–2642.

Karlsson, M. P. and L. M. Frank (2009). Awake replay of remote experiences in the hippocampus. In: *Nature neuroscience* 12.7, pp. 913–918.

Kloosterman, F., S. P. Layton, Z. Chen, and M. A. Wilson (2014). Bayesian decoding using unsorted spikes in the rat hippocampus. In: *Journal of neurophysiology*.

Knierim, J. J. (2014). Chapter 19 - Information Processing in Neural Networks. In: *From Molecules to Networks (Third Edition)*. Ed. by J. H. Byrne, R. Heidelberger, and M. N. Waxham. Third Edition. Boston: Academic Press, pp. 563–589. ISBN: 978-0-12-397179-1. DOI: https://doi.org/10.1016/B978-0-12-397179-1.00019-1. URL: https://www.sciencedirect.com/science/article/pii/B9780123971791000191.

Luo, S., Q. Rabbani, and N. E. Crone (2023). Brain-computer interface: applications to speech decoding and synthesis to augment communication. In: *Neurotherapeutics* 19.1, pp. 263–273.

Meer, M. A. van der, A. A. Carey, and Y. Tanaka (2017). Optimizing for generalization in the decoding of internally generated activity in the hippocampus. In: *Hippocampus* 27.5, pp. 580–595.

Michon, F., J.-J. Sun, C. Y. Kim, D. Ciliberti, and F. Kloosterman (2019). Post-learning hippocampal replay selectively reinforces spatial memory for highly rewarded locations. In: *Current Biology* 29.9, pp. 1436–1444.

Ólafsdóttir, H. F., D. Bush, and C. Barry (2018). The role of hippocampal replay in memory and planning. In: *Current Biology* 28.1, R37–R50.

Pfeiffer, B. E. (2020). The content of hippocampal "replay". In: *Hippocampus* 30.1, pp. 6–18.

Pfeiffer, B. E. and D. J. Foster (2013). Hippocampal place-cell sequences depict future paths to remembered goals. In: *Nature* 497.7447, pp. 74–79.

Shin, J. D., W. Tang, and S. P. Jadhav (2019). Dynamics of awake hippocampal-prefrontal replay for spatial learning and memory-guided decision making. In: *Neuron* 104.6, pp. 1110–1125.

Walker, D. W. and J. J. Dongarra (1996). MPI: a standard message passing interface. In: *Supercomputer* 12, pp. 56–68.

Williams, A., A. Degleris, Y. Wang, and S. Linderman (2020). Point process models for sequence detection in high-dimensional neural spike trains. In: *Advances in neural information processing systems* 33, pp. 14350–14361.

Wu, C.-T., D. Haggerty, C. Kemere, and D. Ji (2017). Hippocampal awake replay in fear memory retrieval. In: *Nature neuroscience* 20.4, pp. 571–580.

Zhang, K., I. Ginzburg, B. L. McNaughton, and T. J. Sejnowski (1998). Interpreting neuronal population activity by reconstruction: unified framework with application to hippocampal place cells. In: *Journal of neurophysiology* 79.2, pp. 1017–1044.

Zhang, Y., T. He, J. Boussard, C. Windolf, O. Winter, E. Trautmann, N. Roth, H. Barrell, M. Churchland, N. A. Steinmetz, et al. (2024). Bypassing spike sorting: Density-based

decoding using spike localization from dense multielectrode probes. In: *Advances in* ₅₁₂
Neural Information Processing Systems 36. ₅₁₃

Zheng, C., E. Hwaun, C. A. Loza, and L. L. Colgin (2021). Hippocampal place cell sequences ₅₁₄
differ during correct and error trials in a spatial memory task. In: *Nature communications* ₅₁₅
12.1, pp. 1–14. ₅₁₆

a

a JMI computational latency

b LFP Computational Latency