Magnified interaural level differences enhance spatial release from masking in bilateral cochlear implant users

Benjamin N. Richardson,[1] Jana M. Kainerstorfer,[1,2] Barbara G. Shinn-Cunningham,[1] and

Christopher A. Brown[3]

[1] *Neuroscience Institute, Carnegie Mellon University, Pittsburgh, PA 15213, U.S.A.*

[2] *Biomedical Engineering, Carnegie Mellon University, Pittsburgh, PA 15213, U.S.A*

[3] *Communication Science and Disorders, University of Pittsburgh, Pittsburgh, PA 15213, U.S.A*

Bilateral cochlear implant (BiCI) usage makes binaural benefits a possibility. However, access to interaural time difference (ITD) cues is limited, leaving users reliant on interaural level difference (ILD) cues for binaural tasks. But even ILD cues may not be as salient for BiCI users as for normal-hearing (NH) listeners. Thus, the benefits that BiCI listeners obtain when target and masker are spatially separated are limited. Here, we explore whether magnifying ILD cues improves masked speech intelligibility for BiCI listeners in a "symmetrical-masker" configuration, which controls for improvements to target-to-masker ratio (TMR) at the ear nearer the target from naturally occurring ILD cues. We magnified ILDs by estimating moment-to-moment ITDs in 1-octave-wide frequency bands and applying corresponding ILDs to the target-masker mixtures at each ear in two experiments: with NH listeners using vocoded stimuli and with BiCI users. ILD magnification significantly improved intelligibility in both experiments. CI listeners showed no improvement with natural ILDs, even for the largest target-masker separation. Because ILD magnification is applied to the mixed signals at each ear, the strategy does not alter the TMR; therefore, the improvements to masked speech intelligibility observed are not due to improved TMR, but likely from improved perceptual separation of the competing sources.

I. INTRODUCTION

Bilateral cochlear implant (BiCI) use has become more common in recent years, in part because of the potential of providing CI users access to binaural cues. Because cochlear implant (CI) devices do not deliver a robust representation of temporal fine structure (TFS; Lorenzi et al., 2006; Moore, 2008), CI users are insensitive to cues important for good speech understanding in noise, including pitch (Brown and Bacon, 2010) and interaural time differences (ITDs; (Noel and Eddington, 2013). Indeed, BiCI users are less accurate than their normal-hearing peers on sound localization tasks (Grantham et al., 2008; Jones et al., 2014; Dorman et al., 2016) and on spatial release from masking (SRM) tasks (Loizou et al., 2009; D'Onofrio et al., 2020), even though they retain some sensitivity to interaural level differences (ILDs; (Grantham et al., 2008).

Alternative CI stimulation strategies have attempted to re-introduce or extend ITD information in BiCIs (Long et al., 2003; van Hoesel et al., 2009; Srinivasan et al., 2020; Thakkar et al., 2023). However, BiCI users show limited ITD sensitivity even using such strategies. These outcomes likely reflect limitations inherent to electrical stimulation, such as current spread, frequency limitations on phase locking, and interaural asymmetry in electrode position (Laback et al., 2015; Gray et al., 2021). ILD cues, on the other hand, are simple to introduce into existing BiCI strategies because they only require sensitivity to differences in stimulation intensity at each ear, which is better preserved than timing information in electric hearing.

In normal hearing (NH) listeners, naturally occurring ILDs can contribute to SRM in several ways. When two competing sound sources arrive at a listener's head from different directions, the target sound is closer to one ear than is the masker, resulting in a greater acoustic target-to-masker energy ratio (TMR) in that ear, termed the better-ear effect (Glyde et al., 2013a, 2013b). Even in situations where there is not a long-term average TMR benefit, ILDs can provide

dynamic short term better-ear advantages ("glimpses") at moments when one of the maskers has

a "dip" (Glyde et al., 2013a, 2013b). Beyond better-ear effects, ILD cues also contribute to the

perception of spatial differences in competing sources, which can contribute to SRM by

promoting sound segregation and supporting selective attention based on perceived source

laterality (Best et al., 2005; Ihlefeld and Shinn-Cunningham, 2008; Middlebrooks and Waters,

2020). This suggests that naturally occurring ILDs can support SRM in NH listeners when target

and masker sound sources are sufficiently spatially separated, through long-term and dynamic

better-ear effects and by promoting sound source segregation and enabling spatial selective

attention.

ILD cues are encoded in BiCI devices, and thus may provide a positive TMR at the ear

nearer the target (Litovsky et al., 2006, 2009; Loizou et al., 2009). However, they are reduced

after processing (Gray et al., 2021), likely due to a number of factors including dynamic range

compression associated with frontend automatic gain control that operates independently at the

two ears (Spencer et al., 2019), backend mapping (Khing et al., 2013), and independent peak

picking (Gray et al., 2021). In addition, CI vocoding reduces glimpsing (Hu et al., 2018; Gibbs et

al., 2022). Finally, the reduced representation of binaural cues in BiCI configurations reduces the

ability of these users to selectively attend to a target in the presence of a spatially separated

masker (Goupell et al., 2016; Akbarzadeh et al., 2020). As a result, ILD cues alone are not

sufficient to support SRM in BiCI users (Ihlefeld and Litovsky, 2012).

A previous study from our group demonstrated that magnification of low-frequency ILD

information (i.e., increasing ILD cue magnitudes to be larger than what occurs naturally)

significantly improves speech intelligibility in BiCI users compared to when they are presented

with naturally occurring ILDs alone (Brown, 2014). Briefly, the approach applies ILDs based on

the ITDs in the signal at a given time and frequency. Specifically, the target-masker mixtures at

each ear are first band-pass filtered. The moment-to-moment ITD in each band is estimated by

cross-correlating the left and right ear band-passed signals and taking the interaural delay

resulting in the strongest correlation. A lookup table assigns an ILD to each band at each

moment based on the computed ITD, mapping small ITDs to small ILDs and large ITDs to large

ILDs. ILDs are then applied via attenuation at the ear with the delayed signal.

In the previous study (Brown, 2014), the low-frequency region (< 2 kHz) was targeted for

ILD magnification because naturally occurring ILD cues are small at these frequencies.

However, the mid-frequencies (i.e., 1-5 kHz) are important for speech understanding (DePaolis

et al., 1996). One of the goals of the current study was to compare performance in two ILD

magnification conditions: one in which magnification was restricted to frequency bands below 2

kHz (as in Brown, 2014), and one in which ILDs were magnified across the entire frequency

spectrum available to most CI users.

A second goal of the current study was to examine the benefit of magnified ILD cues as a

function of spatial separation of target and masker. To control for better-ear benefits from target-

masker separation, we employed a symmetrical-masker spatial configuration. Specifically, we

positioned the target talker at 0° (midline) and presented two competing maskers, one from the

left and one from the right of the listener, and varied the masker location to be ±0, 15, 30, 45, 60,

75, and 90°. For the tested spatial configurations, naturally occurring ILDs cause the target-to-

masker ratio (TMR) to vary with the masker eccentricity; however, the ILD magnification

algorithm will not change the TMR at either ear in any meaningful way, because magnification is

applied to the target-masker mixture reaching each ear. For example, if the algorithm indicates a

left-leading ITD in a particular spectro-temporal bin, an ILD will be applied by attenuating the

target-masker mixture in the right ear, preserving the TMR in that ear.

We were also interested in the symmetrical-masker configuration because it is more

acoustically complex than the single-masker configuration used previously, and we wanted to

observe the effectiveness of the algorithm in this more acoustically complex scene. This spatial

configuration increases the difficulty of the task and reduces the impact of better-ear glimpsing

(Bronkhorst and Plomp, 1992; Gibbs et al., 2022).

We presented listeners with an SRM task in three ILD magnification conditions. The first

(No Magnification) used naturally occurring spatial cues via non-individualized head-related

transfer functions (Gardner and Martin, 1994). The second (Low-Frequency Magnification)

applied the same HRTF-based natural cues, then applied ILD magnification in frequency bands

below 2 kHz, as was done previously (Brown, 2014), where naturally occurring ILDs are

perceptually negligible. The third condition (Broadband Magnification) applied ILD

magnification in frequency bands spread across the entire usable frequency spectrum.

The current low-frequency implementation of ILD magnification differs from that in the

previous study in that ILD magnification was applied independently to four 1-octave-wide

frequency bands between 100 and 2000 Hz, rather than independently in 32 bands below 2 kHz.

We considered using one processing band per vocoder channel, but this would have made

across-participant comparisons difficult since BiCI users may have different numbers of

channels, and in any event it would have resulted in a number of processing bands that was

almost certainly higher than needed. If the strategy were implemented in actual CI devices,

computational load would be an issue. Load scales linearly with the number of processing bands,

since ITD estimation must be computed in each band, and that stage of processing represents the

vast majority of the total processing requirements. As a result, we decided to use only 4

processing bands, based on a previous study that showed that 1-octave wide processing

bandwidths are sufficient to achieve significant benefits to localization performance from

magnified ILD cues (Brown, 2018).

We were also interested in the extent to which applying ILD magnification across the entire

usable frequency spectrum would be beneficial. As noted above, frequencies above 2 kHz

convey significant speech information (DePaolis et al., 1996). We chose to fix the number of

processing bands, and let bandwidth vary. Thus, this condition applied ILD magnification in four

roughly equally spaced (on a logarithmic scale) contiguous frequency bands with cutoff

frequencies of 100, 300, 900, 3500, and 5500 Hz. In all conditions, stimuli were ultimately

bandpassed to between 100 and 5500 Hz, to approximate the bandwidth of typical CI processing,

and to maintain a relatively consistent bandwidth across participants, especially as the BiCI

group may have devices with different bandwidths.

In NH listeners, we predicted that naturally occurring ILDs alone would be insufficient for

SRM at small target-masker separations since ILDs are small for sources within 30 degrees of

midline but would be sufficient at large separations where ILDs are significant. We expected

magnification of ILDs to increase SRM by increasing the perceived spatial separation of target

and maskers, increasing the efficacy of spatial selective attention. Specifically, we expected

Low-frequency magnification to yield better performance than naturally occurring ILDs and that

Broadband magnification would produce the best performance (and the strongest SRM).

For BiCI listeners, we expected no SRM with naturally occurring ILDs (Ihlefeld and

Litovsky, 2012), even for large target-masker separations. We hypothesized that Low-frequency

ILD magnification would enhance spatial perception and support SRM, and that Broadband ILD

magnification would produce even better perceptual spatial separation and greater SRM.

II.   EXPERIMENT 1

A. Methods

1. Participants

Sixteen normal-hearing subjects participated. A hearing screening confirmed that all

participants had audiometric thresholds of 25 dB HL or better at octave frequencies up to 8 kHz.

All participants were compensated either monetarily or with course credit for their participation.

All procedures were approved by the Institutional Review Board of the University of Pittsburgh.

2. Equipment and Procedures

All digital signals (sampling frequency 44.1 kHz) were converted to analog signals with an

RME Fireface UFX+ soundcard and attenuated to an overall sound pressure level of 70 dB with

Atlas AT100-RM passive attenuators. Listeners wore Etymotic ER-3 insert phones. All

participants sat in an audiometric booth during testing while the experimenter sat in an

acoustically isolated, but physically adjoined booth with a window between and an intercom

allowing verbal communication.

Participants first heard ten target sentences presented in quiet to familiarize them with the

normal acoustic voice of the target talker, and then heard 10 vocoded target sentences. All

participants were instructed to verbally repeat back as many of the words as possible produced

by the centrally located "target" talker and to guess if they were not sure. Masker sentences were

spatialized to the left and the right at various simulated locations (see next section). Ten

sentences, each with an average of five keywords (nouns, verbs, adjectives) for a total of 50

keywords, were presented in each condition. No participant ever heard a sentence more than

once. For each condition, we quantified performance by calculating the total number of target

keywords out of 50 that were correctly identified.

3. Stimuli and Signal Processing

Target speech stimuli were drawn from the CUNY sentence corpus (Boothroyd et al., 1985)

produced by a female talker. Masker stimuli were drawn from the IEEE corpus (IEEE

Recommended Practice for Speech Quality Measurements, 1969), which were produced by a

different female talker. Masker sentences were concatenated if needed and then truncated to be

equal in length to the target.

Stimulus processing and presentation, as well as experiment control, were accomplished

using the Python programming language. All signal processing was performed offline. To

generate stimuli, each masker sentence was first adjusted in level relative to the target sentence

level to achieve a TMR of +2 dB. Then, naturally occurring binaural cues were applied

separately to the target and maskers by convolving each with appropriate non-individualized

HRTFs to simulate the target sentence at midline and the maskers symmetrically positioned

around midline at azimuths of +/- 0, 15, 30, 45, 60, 75, and 90 degrees, all at ear height (0

degrees elevation). The 0-degree conditions (where target and maskers were all co-located)

served as a reference for the spatial configurations using the same type of processing. Next,

spatialized target and masker tokens were summed into left and right channels. Finally, stimuli

were bandpass filtered between 125 and 5500 Hz to simulate the limited bandwidth of CI

processing and to set the effective bandwidth of the signals to be comparable to that available to

typically BiCI users (Exp 2).

In the No Magnification condition, no further spatial processing was performed. In the other

(ILD-magnified) conditions, target-masker mixtures were filtered into different frequency bands,

with the number depending on the processing condition. In the Low-Frequency Magnification

condition, the filter bank used 4th-order Butterworth filters, and consisted of five contiguous

bands with cutoff frequencies of 125, 250, 500, 1000, 2000, and 5500 Hz. ILD magnification

was applied to the lowest four bands. In the Broadband Magnification condition, four contiguous

bands were created using cutoff frequencies of 125, 300, 900, 3500, and 5500, and ILD

magnification was applied to all four bands. These parameters were chosen in order to fix the

number of frequency bands in which ILD magnification occurred to four. Note that we opted not

to implement one processing band per vocoder channel, as that would have made comparisons

across BiCI users difficult since individuals may have different numbers of channels available.

Moreover, ILD magnification with processing bandwidths of one octave significantly improves

sound localization performance (Brown, 2018). Given this, we expected ILD magnification using

the same processing bandwidths to enhance SRM.

To implement ILD magnification, non-overlapping 20-ms boxcar-shaped windows of data

were created within each frequency band. While applying level changes to each contiguous

window creates audible static, pilot testing indicates that this static is not audible after vocoding

by listeners with NH, or by CI users. In each window, an ITD was estimated by finding the

interaural delay corresponding to the peak in the cross-correlation of the left and right channels.

A lookup table was used to convert the ITDs to ILDs. Specifically, a zero-μs ITD corresponded

to a 0-dB ILD, a 750-μs ITD corresponded to a 32 dB ILD, and intermediate values were linearly

interpolated. The resulting ILD in each 20-ms segment was then achieved by attenuating the

signal for the ear contralateral to the direction of the ITD, leaving the ipsilateral ear segment

unchanged. Although this processing approach often causes intensity transitions from window to

window, pilot testing indicated that these are not audible after vocoding by either NH listeners or

BiCI users.

Finally, stimuli were processed with an 8-channel sinusoidal vocoder to make the available

information similar to what a CI user could access. The first stage of the vocoder was a filterbank

with cutoff frequencies logarithmically spaced between 125 and 5500 Hz. In each band, the

amplitude envelope was extracted via half-wave rectification and low-pass filtering at the lesser

of 400 Hz or half the bandwidth. These envelopes were then applied to sine tones with

frequencies at the logarithmic center of the bands, which were then summed.

B. Results

Figure 1 presents the across-subject average results for Experiment 1, showing the raw

percent correct speech intelligibility for each condition as a function of target-masker separation.

As expected, performance in the co-located control conditions is similar across all types of ILD

magnification, with about 50% of the keywords correctly identified. In the No Magnification

condition, performance does not improve from the co-located configuration for less lateral

maskers (±15, 30 & 45°), but is better for more lateral masker locations (±60, 75 & 90°). In

contrast, performance is better and similar for all spatially separated masker conditions in both of

the ILD magnification conditions. As a result, target speech intelligibility is consistently better

with ILD magnification than with naturally occurring ILDs when the maskers are spatially

separated from the target but relatively close to midline.

A 2-factor repeated-measures ANOVA was computed, with Masker location and ILD

Magnification as the two main factors and percent correct speech intelligibility as the dependent

factor. We excluded the co-located conditions from the analysis, because it was intended as a

control condition, and we were primarily interested in whether performance depended on the

degree of spatial separation between target and maskers.

Significant effects were observed for the main factors of ILD Magnification ($F_{(2,30)}$ = 5.4, p

= 0.01) and Masker Location ($F_{(5,75)}$ = 3.9, p = .003), as was the interaction between them

($F_{(10,150)}$ = 2.1, p = 0.027). Post hoc pairwise analyses with Bonferroni corrections revealed a

significant difference between Broadband and No magnification (p=.018). However, Low-

frequency magnification was not significantly different than either No Magnification or

Broadband Magnification (p > .05). To understand the significant interaction, we conducted

follow-up one-way ANOVAs separately for each magnification condition. We found no

significant effect of masker location for the Low-Frequency and Broadband Magnification

conditions. Importantly, however, there was a significant effect of spatial separation in the No

Magnification condition (p < 0.001). Pairwise t-tests showed that performance in the 15-, 30-,

and 45-degree masker locations was significantly lower than in the 60- and 75-degree masker

locations. This pattern of results clearly drives the interaction between target-masker separation

and magnification conditions.

FIG. 1. Experiment 1 Results. Average percent keywords correct as a function of masker location for sixteen NH participants in a BiCI (vocoded) simulation. Data are shown for the three ILD Magnification conditions: None (circles), Low-frequency (square), and Broadband (diamonds). The symbols show the across -subject average and the error bars show the across-subject standard error.

C. Discussion

We hypothesized that both Low-frequency and Broadband magnification would significantly improve performance compared to naturally occurring ILD cues (No magnification). Supporting these hypotheses, we observed a significant benefit from Broadband magnification, and a small, albeit non-significant benefit from Low-frequency ILD magnification. These results are in line with a previous study that showed a statistically significant increase in intelligibility even for low-frequency ILD magnification using different ILD magnification algorithm parameters and a different spatial configuration (Brown, 2014). The fact that the current study found no significant benefit with low-frequency amplification may be a question of statistical power; however, the

spatial configuration used here, with a masker to either side of the target, poses much greater

challenges, both for the algorithm and for the listener, than in the previous study. Thus, this more

challenging listening situation may require greater spatial separation in higher frequency regions

important for speech intelligibility (DePaolis et al., 1996; Hogan and Turner, 1998; Vickers et

al., 2001). Consistent with this hypothesis, the Broadband condition yielded significantly greater

benefit than Low-frequency magnification.

The only condition in which performance was not flat across azimuth in this experiment was

in the No Magnification case. In this case, listeners performed well at large target-masker

separations, but at smaller target-masker separations, performance was equivalent to the co-

located configuration. This suggests that naturally occurring ILD information at small masker

eccentricities does not support SRM. For these vocoded stimuli, only azimuths greater than 45

degrees provided enough perceptual separation for NH listeners to selectively attend to the

target. Performance improved with ILD magnification for these conditions, indicating that the

magnification provides a spatial perceptual benefit when natural cues are insufficient to support

SRM.

III.   EXPERIMENT 2

A. Methods

1. Participants

Seven BiCI patients participated, using their everyday program without modification, except

for a minor adjustment to ensure that sounds were at a comfortable overall level. All participants

were compensated monetarily. All procedures were approved by the Institutional Review Board

of the University of Pittsburgh.

2. *Equipment and Procedures*

All equipment and procedures were identical to those used in Exp. 1, except for a few minor differences. Specifically, instead of a 70-dB SPL presentation level, BiCI participants used the attenuators to adjust the presentation level to most comfortable. In addition, instead of Etymotic ER-3 insert phones, direct-connect accessory cables delivered sound to participants. Participants used their everyday programs with no adjustments, including for automatic gain control. Finally, practice consisted of 10 unprocessed target sentences in quiet, with no vocoder practice.

3. *Stimuli and Signal Processing*

Stimuli and signal processing were identical to that used in Exp. 1, except that no vocoding was performed on the stimuli.

B. Results

Figure 2 presents the across-subject average results for Exp. 2 in 7 BiCI users, showing the raw percent correct speech intelligibility for each condition as a function of target-masker separation. In this population, performance in the co-located condition (about 40 percentage points) was generally lower than in the spatially separated conditions.

A 2-factor repeated-measures ANOVA was conducted with dependent factors of masker location and ILD magnification, and percent-correct speech intelligibility as the dependent variable. As with Experiment 1, co-located conditions were excluded from the analysis. The ANOVA revealed a significant main effect of ILD Magnification ($F(2,12) = 11.4$, $p = 0.009$). However, neither Masker Location ($F(5,30) = 2.15$, $p = .116$) nor the interaction term ($F(10,60) = 1.18$, $p = 0.342$) were significant. Post hoc pairwise analyses with a Bonferonni correction revealed that the Broadband ILD magnification strategy produced performance that was significantly better than both No Magnification ($p = 0.041$), and Low-Frequency Magnification (p

= .011). However, there was no significant difference between No Magnification and Low-

Frequency Magnification (p = 0.629).

FIG. 2. Experiment 2 Results. Average percent keywords correct as a function of masker

location for seven BiCI patients. Data are shown for the three ILD Magnification conditions:

None , low-frequency, and Broadband. The symbols show the across -subject average and the

error bars show the across-subject standard error in each condition.

C. Discussion

In BiCI users, we hypothesized that both Low-frequency and Broadband magnification

would allow for greater benefit than naturally occurring ILD cues. We observed a significant

improvement in performance with Broadband magnification over No magnification; however,

Low-frequency magnification provided no statistically significant benefit.

The effect of ILD magnification was relatively consistent across azimuth in the BiCI group.

In all three conditions, percent correct in spatially separated conditions did not vary much with

increased spatial separation. This effect was confirmed by the ANOVA, which revealed no

significant effect of masker location.

Naturally occurring cues provided insufficient perceptual separation to observe a benefit,

even with maskers at ±90°. This result supports our hypothesis that BiCI users require greater

ILDs to perceive a separation between target and maskers. This is consistent with the literature

(Ihlefeld and Litovsky, 2012; Brown, 2014), and is likely due to the compressed perceptual space

they experience in the horizontal plane with naturally occurring cues (Grantham et al., 2007).

ILD Magnification can mitigate this limitation for BiCI users however, by expanding the

perceptual space (Brown, 2018). These BiCI users showed a consistent benefit of target-masker

separation with the Broadband ILD magnification across masker azimuth. Given that our ILD

magnification does not alter the TMR at either ear, these results suggest that Broadband ILD

magnification allows BiCI listeners to focus on the target speech and suppress the maskers by

deploying spatial selective attention. However, neither naturally occurring ILDs nor Low

frequency ILD magnification allowed the BiCI users to effectively deploy spatial attention.

IV.   GENERAL DISCUSSION

Both NH and BiCI listeners benefitted from magnifying ILD cues. For NH listeners,

Broadband magnification improved performance compared to naturally occurring ILDs when

symmetrically positioned maskers were close to midline and natural ILDs were too small to

support SRM. For BiCI users, Broadband magnification significantly improved performance

compared to both Low frequency Magnification and No Magnification conditions.

The overall benefit of ILD magnification observed in the current study is less than what was

observed previously with a single masker (Brown, 2014). That is, previous results showed a

masking release of about 30 percentage points from ILD magnification, while the amount of

benefit in the current study is around 20 percentage points with Broadband magnification. This

difference is almost certainly due to the perceptual difficulty associated with the symmetrical

masker configuration used in the current study. Nevertheless, 20 percentage points of masking

release represents a substantial benefit and indicates that ILD magnification can be effective in

relatively complex auditory scenes.

A. ILD Magnification Enhances Spatial Differences, Thereby Supporting Spatial

Attention

In natural listening conditions, the better-ear effect contributes to improved speech

intelligibility, and this effect grows as the eccentricity of the masker increases. However, our

algorithm does not alter the acoustic TMR at either ear, precluding better-ear benefit. This is due

to the fact that our algorithm achieves ILD magnification by attenuating the target-masker

mixture at each ear, as dictated by the ITD in that frequency band and time point: both target and

masker are attenuated by the same amount. This fact is not changed by the spatial configuration

(ie., it is true even in the case where the target and masker are in opposite hemifields, as in

Brown, 2014). As a result, the benefits observed from ILD magnification cannot be explained by

either increases in the TMR at the better ear or increased opportunities for dip listening. Even

when magnified, ILD cues are not likely to facilitate dip listening by BiCI listeners in any event,

as the perceptual ability has been shown to be reliant on TFS information, which is reduced in

vocoded stimuli (Hopkins and Moore, 2009; Brown and Bacon, 2010; Gibbs et al., 2022).

Consistent with this observation, our results do not show a significant effect of target-masker

separation in any magnified condition (Low-frequency or Broadband). If ILD magnification

improved performance by increasing TMR, percent correct should increase as a function of

target-masker separation. Instead, we found that performance improved over co-located

conditions when ILDs were "large enough," but did not increase monotonically with increasing

masker eccentricity. Given this, the observed benefits of ILD magnification must reflect other

mechanisms. Specifically, we propose that magnified ILDs enhance spatial perception of the

vocoded / BiCI stimuli, allowing listeners to filter out masker-dominated frequencies / time

instances that are perceived as off midline and focus attention on the target. When spatial cues do

not meaningfully change the TMR, as in experiments in which only ITDs are manipulated,

spatial selective auditory attention allows NH listeners to attend to a target amongst spatially

separated maskers (Shinn-Cunningham and Best, 2008; Shinn-Cunningham, 2017; Noyce et al.,

2021). Such spatial auditory selective attention occurs through coordinated activity in multiple

areas of the brain, including prefrontal cortex, parietal cortex, and auditory cortex (Alho et al.,

2014; Choi et al., 2014; Deng et al., 2019, 2020; Noyce et al., 2022). Attention modulates the

information represented in auditory cortex, enhancing the representation of a target and

suppressing the representation of maskers (Noyce et al., 2021; Auerbach and Gritton, 2022).

Spatial auditory attention is less effective in listeners with hearing loss; indeed, performance is

inversely correlated with spatial discrimination thresholds (Dai et al., 2018; Bonacci et al., 2019).

Similarly, limitations of electrical stimulation reduce CI users' ability to capitalize on naturally

occurring spatial cues to direct selective attention (Goupell et al., 2016; Akbarzadeh et al., 2020).

ILD magnification, which yields an SRM benefit without changing TMR, enhances the

perceived spatial separation of target and maskers, thereby supporting spatial attentional

processes. This underscores the need for processing algorithms that facilitate greater perceptual

segregation and easier deployment of attention.

B. Corrective ILD Magnification

ILD magnification has the potential to be corrective; that is, to improve spatial hearing

outcomes in BiCI users in a targeted, individualized way. Individualized corrective ILD

processing benefits users by magnifying cues according to baseline frequency- and azimuth-

specific localization abilities (Brown, 2018). While this corrective approach works well for

optimizing sound source localization and making spatial perception veridical, tasks with multiple

sound sources may require a different level of magnification. In a cocktail-party like

environment, increased perceptual separation between target and masker may improve speech

reception, even if sources are not perceived at their veridical locations. When a target and masker

are on either side of the head (as in Brown, 2014), magnifying ILD cues will likely support

SRM even though the perceived spatial locations of the target and masker are incorrect (i.e.,

large ILD cues will lead to hyper-lateralization, in which perceived locations will be at or near

± 90 degrees azimuth). Exaggerated ILD magnification also works well for speech understanding

in the spatial configuration used in the current study, in which the target is at midline and the

maskers are on either side of the head. Because the target is at 0 degrees azimuth, its perceived

location does not change after ILD magnification, so perceived spatial separation between it and

the maskers increases from ILD magnification, which accentuates the eccentricity of the

maskers. If a target and masker are both off midline and on the same side of the head, however,

ILD magnification may actually decrease the perceived spatial separation between them.

C. Future Work

Future experiments will explore the frequency-, azimuth-, and subject-specific benefits of

magnified ILD cues in an SRM paradigm. This will include an examination of the effects of

parameters such as the number of magnification bands, the cutoff frequencies of those

magnification bands, and the ITD to ILD mapping function (lookup table). Four magnification

bands were used in this study, as we wanted to explore if fewer, broader bands than used in

Brown (2014) could elicit SRM benefits. Fewer bands would be easier to implement in BiCI

configurations as it is computationally less expensive. We also used a bandwidth of about 2

octaves in the Broadband magnification, which yielded the largest benefit. Future work will be

needed to determine the optimal bandwidth for magnification. Both the number of bands and the

bandwidth may be frequency-, azimuth-, or subject specific.

Ongoing extensions of this work will also measure neural responses to sound in both normal

hearing listeners and BiCI users completing spatial selective attention tasks. This is motivated by

a need to understand the perceptual and neural mechanisms that underlie the benefit observed in

this experiment. If the magnified ILD cues used here do, in fact, allow for attentional modulation

of responses to target and masker sounds, this will provide strong motivation for the use of ILD

magnification in bilateral cochlear implant processing.

ACKNOWLEDGMENTS

This work was supported in part by NIH grants R21-DC018408 to CAB and R01-DC015988

to BGSC. We would like to thank Sydney Sepkovic and Cece Restauri for their help with data

collection.

AUTHOR DECLARATIONS

Conflict of Interest

The authors have no conflicts of interest to disclose.

Ethics Approval

All procedures were approved by the Institutional Review Board of the University of Pittsburgh.

All participants gave written informed consent and were compensated for their participation.

DATA AVAILABILITY

The data that support the findings of this study are available from the corresponding author

upon reasonable request.

REFERENCES

Akbarzadeh, S., Lee, S., and Tan, C.-T. (**2020**). The Implication of Sound Level on Spatial

Selective Auditory Attention for Cochlear Implant Users: Behavioral and

Electrophysiological Measurement., 2497–2501. doi: 10.21437/Interspeech.2020-2836

Alho, K., Rinne, T., Herron, T. J., and Woods, D. L. (**2014**). Stimulus-dependent activations and

attention-related modulations in the auditory cortex: A meta-analysis of fMRI studies.

Hear. Res. 307, 29–41. doi: 10.1016/j.heares.2013.08.001

Auerbach, B. D., and Gritton, H. J. (**2022**). Hearing in Complex Environments: Auditory Gain

Control, Attention, and Hearing Loss. Front. Neurosci. 16. doi:

10.3389/fnins.2022.799787

Best, V., Ozmeral, E., Gallun, F. J., Sen, K., and Shinn-Cunningham, B. G. (**2005**). Spatial

unmasking of birdsong in human listeners: Energetic and informational factorsa). J.

Acoust. Soc. Am. 118, 3766–3773. doi: 10.1121/1.2130949

Bonacci, L. M., Dai, L., and Shinn-Cunningham, B. G. (**2019**). Weak neural signatures of spatial

selective auditory attention in hearing-impaired listeners. J. Acoust. Soc. Am. 146, 2577.

doi: 10.1121/1.5129055

Boothroyd, A., Hanin, L., and Hnath, T. (**1985**). A sentence test of speech perception: reliability,

set equivalence, and short term learning. Publ. Res. Available at:

https://academicworks.cuny.edu/gc_pubs/399

Bronkhorst, A. W., and Plomp, R. (**1992**). Effect of multiple speechlike maskers on binaural

speech recognition in normal and impaired hearing. J. Acoust. Soc. Am. 92, 3132–3139.

doi: 10.1121/1.404209

Brown, C. A. (**2014**). Binaural Enhancement for Bilateral Cochlear Implant Users. Ear Hear. 35,

580–584. doi: 10.1097/AUD.0000000000000044

Brown, C. A. (**2018**). Corrective binaural processing for bilateral cochlear implant patients.

PLOS ONE 13, e0187965. doi: 10.1371/journal.pone.0187965

Brown, C. A., and Bacon, S. P. (**2010**). Fundamental frequency and speech intelligibility in

background noise. Hear. Res. 266, 52–59. doi: 10.1016/j.heares.2009.08.011

Choi, I., Wang, L., Bharadwaj, H., and Shinn-Cunningham, B. (**2014**). Individual differences in

attentional modulation of cortical responses correlate with selective attention

performance. Hear. Res. 314, 10–19. doi: 10.1016/j.heares.2014.04.008

Dai, L., Best, V., and Shinn-Cunningham, B. G. (**2018**). Sensorineural hearing loss degrades

behavioral and physiological measures of human spatial selective auditory attention.

Proc. Natl. Acad. Sci. 115, E3286–E3295. doi: 10.1073/pnas.1721226115

Deng, Y., Choi, I., and Shinn-Cunningham, B. (**2020**). Topographic specificity of alpha power

during auditory spatial attention. NeuroImage 207, 116360. doi:

10.1016/j.neuroimage.2019.116360

Deng, Y., Reinhart, R. M., Choi, I., and Shinn-Cunningham, B. G. (**2019**). Causal links between

parietal alpha activity and spatial auditory attention. eLife 8, e51184. doi:

10.7554/eLife.51184

DePaolis, R. A., Janota, C. P., and Frank, T. (**1996**). Frequency importance functions for words,

sentences, and continuous discourse. J. Speech Hear. Res. 39, 714–723. doi:

10.1044/jshr.3904.714

D'Onofrio, 'Onofrio Kristen, Richards, V., and Gifford, R. (**2020**). Spatial Release From

Informational and Energetic Masking in Bimodal and Bilateral Cochlear Implant Users.

J. Speech Lang. Hear. Res. 63, 3816–3833. doi: 10.1044/2020_JSLHR-20-00044

Dorman, M. F., Loiselle, L. H., Cook, S. J., Yost, W. A., and Gifford, R. H. (**2016**). Sound

Source Localization by Normal-Hearing Listeners, Hearing-Impaired Listeners and

Cochlear Implant Listeners. Audiol. Neurotol. 21, 127–131. doi: 10.1159/000444740

Gardner, B., and Martin, K. (**1994**). HRTF Measurements of a KEMAR Dummy-Head

Microphone. MIT Media Lab Perceptual Computing.

Gibbs, B. E., Bernstein, J. G. W., Brungart, D. S., and Goupell, M. J. (**2022**). Effects of better-ear

glimpsing, binaural unmasking, and spectral resolution on spatial release from masking in

cochlear-implant users. J. Acoust. Soc. Am. 152, 1230. doi: 10.1121/10.0013746

Glyde, H., Buchholz, J., Dillon, H., Best, V., Hickson, L., and Cameron, S. (**2013a**). The effect

of better-ear glimpsing on spatial release from masking. J. Acoust. Soc. Am. 134, 2937–

2945. doi: 10.1121/1.4817930

Glyde, H., Buchholz, J. M., Dillon, H., Cameron, S., and Hickson, L. (**2013b**). The importance

of interaural time differences and level differences in spatial release from masking. J.

Acoust. Soc. Am. 134, EL147–EL152. doi: 10.1121/1.4812441

Goupell, M. J., Kan, A., and Litovsky, R. Y. (**2016**). Spatial attention in bilateral cochlear-

implant users. J. Acoust. Soc. Am. 140, 1652–1662. doi: 10.1121/1.4962378

Grantham, D. W., Ashmead, D. H., Ricketts, T. A., Haynes, D. S., and Labadie, R. F. (**2008**).

Interaural time and level difference thresholds for acoustically presented signals in post-

lingually deafened adults fitted with bilateral cochlear implants using CIS+ processing.

Ear Hear. 29, 33–44. doi: 10.1097/AUD.0b013e31815d636f

Grantham, D. W., Ashmead, D. H., Ricketts, T. A., Labadie, R. F., and Haynes, D. S. (**2007**).

Horizontal-Plane Localization of Noise and Speech Signals by Postlingually Deafened

Adults Fitted With Bilateral Cochlear Implants*. Ear Hear. 28, 524. doi:

10.1097/AUD.0b013e31806dc21a

Gray, W. O., Mayo, P. G., Goupell, M. J., and Brown, A. D. (**2021**). Transmission of Binaural

Cues by Bilateral Cochlear Implants: Examining the Impacts of Bilaterally Independent

Spectral Peak-Picking, Pulse Timing, and Compression. Trends Hear. 25,

23312165211030411. doi: 10.1177/23312165211030411

Hogan, C. A., and Turner, C. W. (**1998**). High-frequency audibility: benefits for hearing-

impaired listeners. J. Acoust. Soc. Am. 104, 432–441. doi: 10.1121/1.423247

Hopkins, K., and Moore, B. C. J. (**2009**). The contribution of temporal fine structure to the

intelligibility of speech in steady and modulated noise. J. Acoust. Soc. Am. 125, 442–

446. doi: 10.1121/1.3037233

Hu, H., Dietz, M., Williges, B., and Ewert, S. D. (**2018**). Better-ear glimpsing with

symmetrically-placed interferers in bilateral cochlear implant users. J. Acoust. Soc. Am.

143, 2128–2141. doi: 10.1121/1.5030918

IEEE Recommended Practice for Speech Quality Measurements (**1969**). IEEE No 297-1969, 1–

24. doi: 10.1109/IEEESTD.1969.7405210

Ihlefeld, A., and Litovsky, R. Y. (**2012**). Interaural Level Differences Do Not Suffice for

Restoring Spatial Release from Masking in Simulated Cochlear Implant Listening. PLOS

ONE 7, e45296. doi: 10.1371/journal.pone.0045296

Ihlefeld, A., and Shinn-Cunningham, B. (**2008**). Spatial release from energetic and informational

masking in a selective speech identification taska). J. Acoust. Soc. Am. 123, 4369–4379.

doi: 10.1121/1.2904826

Jones, H., Kan, A., and Litovsky, R. Y. (**2014**). Comparing Sound Localization Deficits in

Bilateral Cochlear-Implant Users and Vocoder Simulations With Normal-Hearing

Listeners. Trends Hear. 18, 2331216514554574. doi: 10.1177/2331216514554574

Khing, P. P., Swanson, B. A., and Ambikairajah, E. (**2013**). The Effect of Automatic Gain

Control Structure and Release Time on Cochlear Implant Speech Intelligibility. PLoS

ONE 8, e82263. doi: 10.1371/journal.pone.0082263

Laback, B., Egger, K., and Majdak, P. (**2015**). Perception and coding of interaural time

differences with bilateral cochlear implants. Hear. Res. 322, 138–150. doi:

10.1016/j.heares.2014.10.004

Litovsky, R., Parkinson, A., Arcaroli, J., and Sammeth, C. (**2006**). Simultaneous Bilateral

Cochlear Implantation in Adults: A Multicenter Clinical Study. Ear Hear. 27, 714–731.

doi: 10.1097/01.aud.0000246816.50820.42

Litovsky, R. Y., Parkinson, A., and Arcaroli, J. (**2009**). Spatial hearing and speech intelligibility

in bilateral cochlear implant users. Ear Hear. 30, 419–431. doi:

10.1097/AUD.0b013e3181a165be

Loizou, P. C., Hu, Y., Litovsky, R., Yu, G., Peters, R., Lake, J., et al. (**2009**). Speech recognition

516   by bilateral cochlear implant users in a cocktail-party setting. J. Acoust. Soc. Am. 125,

517   372–383. doi: 10.1121/1.3036175

518   Long, C. J., Eddington, D. K., Colburn, H. S., and Rabinowitz, W. M. (**2003**). Binaural

519   sensitivity as a function of interaural electrode position with a bilateral cochlear implant

520   user. J. Acoust. Soc. Am. 114, 1565–1574. doi: 10.1121/1.1603765

521   Lorenzi, C., Gilbert, G., Carn, H., Garnier, S., and Moore, B. C. J. (**2006**). Speech perception

522   problems of the hearing impaired reflect inability to use temporal fine structure. Proc.

523   Natl. Acad. Sci. 103, 18866–18869. doi: 10.1073/pnas.0607364103

524   Middlebrooks, J. C., and Waters, M. F. (**2020**). Spatial Mechanisms for Segregation of

525   Competing Sounds, and a Breakdown in Spatial Hearing. Front. Neurosci. 14. doi:

526   10.3389/fnins.2020.571095

527   Moore, B. C. J. (**2008**). The Role of Temporal Fine Structure Processing in Pitch Perception,

528   Masking, and Speech Perception for Normal-Hearing and Hearing-Impaired People. J.

529   Assoc. Res. Otolaryngol. 9, 399–406. doi: 10.1007/s10162-008-0143-x

530   Noel, V. A., and Eddington, D. K. (**2013**). Sensitivity of bilateral cochlear implant users to fine-

531   structure and envelope interaural time differencesa). J. Acoust. Soc. Am. 133, 2314–

532   2328. doi: 10.1121/1.4794372

533   Noyce, A. L., Kwasa, J. A. C., and Shinn-Cunningham, B. G. (**2021**). Defining attention from an

534   auditory perspective. WIREs Cogn. Sci. n/a, e1610. doi: 10.1002/wcs.1610

535   Noyce, A. L., Lefco, R. W., Brissenden, J. A., Tobyne, S. M., Shinn-Cunningham, B. G., and

536   Somers, D. C. (**2022**). Extended Frontal Networks for Visual and Auditory Working

537   Memory. Cereb. Cortex 32, 855–869. doi: 10.1093/cercor/bhab249

Shinn-Cunningham, B. (**2017**). Cortical and Sensory Causes of Individual Differences in

Selective Attention Ability Among Listeners With Normal Hearing Thresholds. J. Speech

Lang. Hear. Res. JSLHR 60, 2976–2988. doi: 10.1044/2017_JSLHR-H-17-0080

Shinn-Cunningham, B. G., and Best, V. (**2008**). Selective attention in normal and impaired

hearing. Trends Amplif. 12, 283–299. doi: 10.1177/1084713808325306

Spencer, N. J., Tillery, K. H., and Brown, C. A. (**2019**). The Effects of Dynamic-range

Automatic Gain Control on Sentence Intelligibility With a Speech Masker in Simulated

Cochlear Implant Listening. Ear Hear. 40, 710–724. doi:

10.1097/AUD.0000000000000653

Srinivasan, S., Laback, B., Majdak, P., and Arnoldner, C. (**2020**). Improving Interaural Time

Difference Sensitivity Using Short Inter-pulse Intervals with Amplitude-Modulated Pulse

Trains in Bilateral Cochlear Implants. J. Assoc. Res. Otolaryngol. 21, 105–120. doi:

10.1007/s10162-020-00743-6

Thakkar, T., Kan, A., and Litovsky, R. Y. (**2023**). Lateralization of interaural time differences

with mixed rates of stimulation in bilateral cochlear implant listeners. J. Acoust. Soc.

Am. 153, 1912–1923. doi: 10.1121/10.0017603

van Hoesel, R. J. M., Jones, G. L., and Litovsky, R. Y. (**2009**). Interaural Time-Delay Sensitivity

in Bilateral Cochlear Implant Users: Effects of Pulse Rate, Modulation Rate, and Place of

Stimulation. J. Assoc. Res. Otolaryngol. 10, 557–567. doi: 10.1007/s10162-009-0175-x

Vickers, D. A., Moore, B. C., and Baer, T. (**2001**). Effects of low-pass filtering on the

intelligibility of speech in quiet for people with and without dead regions at high

frequencies. J. Acoust. Soc. Am. 110, 1164–1175. doi: 10.1121/1.1381534