FORCE trained spiking networks do not benefit from faster learning while parameter matched rate networks do

Thomas R. Newton [1,2], Wilten Nicola* [1,2,3],

1 Department of Mathematics and Statistics, University of Calgary, Calgary, Canada.
2 Hotchkiss Brain Institute, University of Calgary. Calgary, Canada.
3 Department of Cell Biology and Anatomy, University of Calgary, Calgary, Canada.

* wilten.nicola@ucalgary.ca

Abstract

There are considerable difficulties in training spiking recurrent neural networks versus the standard recurrent neural networks (RNNs) that are more closely associated with neural firing rates. Here, we investigate where these difficulties arise by training networks of spiking neurons and their parameter matched instantaneous rate RNNs in supervised learning tasks. We FORCE trained leaky-integrate-and-fire spiking and their parameter matched instantaneous rate-networks across different dynamical tasks with the FORCE hyperparameters also matched. We found that when the learning rate was slow, spiking and rate networks largely operated identically, with FORCE training discovering highly correlated solutions to the weight matrices, and similar hyperparameter areas of successful convergence. In fact, these weight matrix solutions were broadly interchangeable between networks, with learned spiking network weights able to lead to correct dynamical decoding in the rate network and vice-versa. However, when learning is too fast, the correlations between the learned solutions drop precipitously, and the solutions are no longer swappable between networks, with some supervisors having completely different optimal hyperparameter zones between rate and spiking networks. These networks also qualitatively behave in different ways across network sizes for different learning rates: faster learning leads to better performance in rate networks across network size, while leading to no tangible change across network size in spiking networks aside from network instability. Our results show that some of the difficulties that arise in training spiking neural networks are due to overly fast learning, which rate networks can tolerate, but matched spiking networks cannot.

Author summary

Training spiking neural networks is much harder compared to training standard recurrent neural networks that are more closely tied to neural firing rates. To understand why, we trained parameter matched spiking and rate-based networks on the same supervised learning tasks. We found that the learned spike weights were highly correlated and interchangeable across spiking and firing rate networks for slow learning rates. However, when both networks learn fast, the spiking networks show no tangible improvements in their performance in comparison to the rate networks, with instabilities caused faster learning in the spiking network. These networks also discover uncorrelated solutions to their weights when the learning is fast.

Introduction

One way that neurons communicate with one-another is through action potentials or spikes [1, 2]. However, one of the most prevailing questions in neuroscience is how neurons use these spikes to encode information

and perform computation. One perspective is that individual spikes do not perform specific tasks but instead the relevant quantity for computation is the firing rate or frequency of spikes transmitted between neurons [3, 4]. Conversely, it has been suggested that the precise or relative timing of spikes is important for neural computation [4]. Rather than debating these two perspectives, it is sensible to discuss which representation captures the necessary information for a given system and modelling task.

Learning low-dimensional dynamical systems is one such task where the difference between spikes and rates becomes readily apparent. There has tremendous success in training recurrent neural networks with a variety of techniques to learn low-dimensional dynamical systems [5, 6, 7, 8, 9, 10, 11, 12, 13, 14], however learning in spiking networks is considerably more difficult. One of the most important differences between spiking and rate based neurons is the techniques used to train their resulting networks. Spike based neurons are typically more difficult to train and require specialized techniques due to discontinuities in the differential equations used to phenomenologically describe spiking (integrate-and-fire neurons) and synaptic propagation, which complicates the computation of derivatives. As a result, gradient based optimization routines cannot be immediately applied to spiking networks. In contrast, rate based neurons are readily trained with gradient based techniques and have demonstrated remarkable flexibility and performance [15]. Recently, there has been developed a range of different approaches to training spiking neural networks. For example the neural engineering framework (NEF) [5], predictive coding [6, 7, 8, 9], surrogate gradient [10, 11], and FORCE [12, 13, 14].

All of these training techniques use a top-down approach that use a prescribed target task (supervisor) to determine the connectivity of the network required to perform the task. In the NEF, neuronal tuning curves are used to optimize for the weights while predictive coding uses fast, precise synaptic interactions between neurons to balance neural activity. The surrogate gradient methods are different from other techniques as they utilize a smoothed approximation of the neurons derivative, called a pseudo-derivative, to apply gradient descent based backpropagation algorithms to train the network [16]. However, all three of these approaches depend on the specific type of neuron model being used in the networks. In contrast, FORCE based techniques are agnostic to the underlying network model being used. This offers the advantage that it can be applied to train networks with both rate [12] and spike based neurons [13] without major modifications. Nonetheless, there are underlying differences in FORCE trained rate and spiking neural networks, which as of now have not be thoroughly investigated.

Here we compare FORCE trained leaky-integrate-and-fire (LIF) networks and their equivalent instantaneous firing rate networks. We first introduce the Leaky-integrate-and-fire (LIF) spiking model and an equivalent LIF instantaneous firing rate neuron model. Then, we connect these two types of neuron models into spiking networks and rate networks, which we demonstrate can both be trained using FORCE [12, 13], with exact matches for the initial weights, neuronal parameters, and FORCE hyperparameters in both networks. We found that when the learning rate is slow, the learned connectivity structure of the spiking and firing rate networks were highly correlated to the point that learned weight solutions could be interchanged, with learned spiking weights leading to successful task dynamics in the rate network, and vice-versa. However, substantial differences emerged when the learning rate was fast. First, the correlation in the learned weights dropped precipitously with the solutions no longer being interchangeable. Second, we found that the spiking network had inherently noisier neural outputs which resulted in the poorer error scaling than in the rate network, which prevented the learned connectivity from converging to a stationary structure. Third, rate networks benefit from faster learning rates, with reduced errors and larger areas of the hyperparameter space leading to successful training, with no discernible improvements displays by spiking networks. Our work shows that some of the difficulties in training spiking neural networks arise from having learning rates that are too fast, which rate networks are more tolerant of.

Results

Network Models

To investigate the differences in spiking and rate based neural networks, we leveraged the FORCE method to train both spiking neural networks and their firing rate equivalent networks on a range of tasks (Fig 1) [12, 13]. By using exactly parameter matched networks, we can compare the weight matrix solutions derived from spiking and rate networks to determine if these solutions are interchangeable and under what conditions. Further, if the weights are interchangeable, then the networks are operating in equivalent fashion.

We considered networks of N leaky integrate-and-fire neurons with double-exponential filter synapses:

$$\tau_m \dot{v}_i(t) = -v_i(t) + I_i(t) \tag{1}$$

$$\dot{r}_i(t) = -\frac{r_i(t)}{\tau_d} + h_i(t) \tag{2}$$

$$\dot{h}_i(t) = -\frac{h_i(t)}{\tau_r} + \frac{1}{\tau_r \tau_d} \sum_{t_{ik} < t} \delta(t - t_{ik}) \tag{3}$$

$$\hat{\boldsymbol{x}}(t) = \sum_{i=1}^{N} \boldsymbol{\phi}_i^S r_i(t). \tag{4}$$

The voltage of the ith neuron is given by $v_i(t)$. Neuron i fires its kth spike at time t_{ik} when $v_i(t) = v_{th}$. After each spike, the voltage $v_i(t)$ is reset to v_{th} and held there for a fixed refractory period (τ_r). Each neuron receives a current, given by:

$$I_i(t) = \sum_{j=1}^{N} \omega_{ij}^S r_j(t) + I_{bias} \tag{5}$$

where $r_j(t)$ is the postsynaptic current due to the filtered spikes and I_{bias} is a background bias current which was set at the rheobase ($I_{bias} = -40$ pA). The weight matrix ω_{ij}^S is trained by the FORCE algorithm so that the spiking network can approximate some M-dimensional dynamical system, $\boldsymbol{x}(t)$. The approximant for this system is given by $\hat{\boldsymbol{x}}(t)$ which is computed using an $N \times M$ linear decoder $\boldsymbol{\phi}^S$ applied to the filtered spikes, $\boldsymbol{r}(t)$. The neuronal parameters used across both network types are listed in Table 1.

Table 1: Leaky Integrate-and-fire neuron model parameters.

Parameter	τ_r	τ_d	τ_m	τ_{ref}	v_{reset}	v_{th}	I_{bias}
Value	2 ms	20 ms	10 ms	2 ms	-65 mV	-40 mV	-40 pA

In FORCE trained networks, the synaptic connectivity matrix $\boldsymbol{\omega}$ consists of the sum of random static weights and a learned, low rank perturbation to the weight matrix:

$$\boldsymbol{\omega}^S = G\boldsymbol{\omega}^0 + Q\boldsymbol{\eta}(\boldsymbol{\phi}^S)^T \tag{6}$$

where $\boldsymbol{\omega}^0 \in N \times N$, and $\boldsymbol{\eta}, \boldsymbol{\phi}^S \in N \times M$ where M is the dimension of the target dynamics $\boldsymbol{x}(t)$ (Fig 2). The static portion of the network weights $G\boldsymbol{\omega}^0$ consists of a scalar strength parameter G and a sparse random matrix $\boldsymbol{\omega}^0$. The static weights serve to initialize the network into a regime of high-dimensional chaotic dynamics, which we control with the parameter G. The other portion of the weight matrix consists of a learned decoder $\boldsymbol{\phi}^S$, a static random encoder $\boldsymbol{\eta}$, and a scalar strength parameter Q. The learned linear decoder $\boldsymbol{\phi}^S$ serves the primary task of decoding the neural dynamics to produce the network output $\hat{\boldsymbol{x}}(t)$, but also works in conjunction with the encoder to stabilize the network dynamics via the feedback

connections. The encoder $\boldsymbol{\eta}$ partially defines the tuning properties of the neurons to the learned output dynamics. The parameter Q is used to control the strength of the feedback to balance against the chaotic dynamics induced by static weight matrix $G\boldsymbol{\omega}^0$ controlled by the parameter G. By introducing the Q and G parameters the macro-scale dynamics of the network can be controlled; either making the system more (less) chaotic by increasing (decreasing) G or creating more (less) structured heterogeneity in the neural firing rates by increasing (decreasing) Q [17, 18].

The random matrix $\boldsymbol{\omega}^0$ was generated from a normal distribution with mean 0 and variance of $(Np^2)^{-1}$ where p is the sparsity of the matrix and N the number of neurons. This scales the weights to be in proportion to the inverse of the square-root of the number of connections [13, 18]. We additionally considered the case where the sample mean of each row in the matrix was explicitly set to be 0 [13]. The components of the encoder $\boldsymbol{\eta}$ are drawn from the uniform distribution over the M dimensional unit square $[-1, 1]^M$, where M is the dimension of the target dynamics.

The LIF network above has an equivalent system of instantaneous rate equations [1, 19]:

$$R_i(t) = \left[\tau_r - \tau_m \log\left(\frac{I_i(t) - v_{th}}{I_i(t) - v_{reset}}\right)\right]^{-1}$$

$$\dot{r}_i(t) = -\frac{r_i(t)}{\tau_d} + h_i(t)$$

$$\dot{h}_i(t) = -\frac{h_i(t)}{\tau_r} + \frac{1}{\tau_r \tau_d} R_i(t)$$

$$\hat{\boldsymbol{x}}(t) = \sum_{i=1}^{N} \boldsymbol{\phi}_i^R r_i(t)$$

where $R_i(t)$ acts as the firing rate for neuron i as a function of input current $I_i(t)$:

$$I_i(t) = \sum_{j=1}^{N} \omega_{ij}^R r_j(t) + I_{bias}$$

$$\boldsymbol{\omega}^R = G\boldsymbol{\omega}^0 + Q\boldsymbol{\eta}(\boldsymbol{\phi}^R)^T$$

To determine how both networks learn low dimensional dynamics, the parameters for both the instantaneous rate network and the LIF spiking network were exactly matched, down to the initial static weight matrix $G\boldsymbol{\omega}^0$ and randomly generated encoders $\boldsymbol{\eta}$. After training, each model will have an associated decoder $\boldsymbol{\phi}^S$ (S for Spikes) and $\boldsymbol{\phi}^R$ (R for Rates). Thus, to compare and contrast the differences and similarities between spiking and rate networks, we can compare the decoders $\boldsymbol{\phi}^R$ and $\boldsymbol{\phi}^S$ as all other parameters are matched (Fig 1).

The FORCE technique was previously used to train rate-based hyperbolic tangent networks [12] and a variety of spiking neural networks [13]. FORCE training applies online updates to the learned decoder $\boldsymbol{\phi}$ using the Recursive Least Squares (RLS) supervised learning method [20, 12]:

$$\boldsymbol{\phi}(t) = \boldsymbol{\phi}(t - \Delta t) - \boldsymbol{e}^T(t)\boldsymbol{P}(t)\boldsymbol{r}(t)$$

$$\boldsymbol{P}(t) = \boldsymbol{P}(t - \Delta t) - \frac{\boldsymbol{P}(t - \Delta t)\boldsymbol{r}(t)\boldsymbol{r}^T(t)\boldsymbol{P}(t - \Delta t)}{1 + \boldsymbol{r}^T(t)\boldsymbol{P}(t - \Delta t)\boldsymbol{r}(t)}$$

RLS minimizes the mean squared error between the target dynamics $\boldsymbol{x}(t)$ and the network's output dynamics $\hat{\boldsymbol{x}}(t)$. To prevent large weights (decoders), RLS incorporates Tikhonov regularization [21, 22, 23], controlled by the ridge parameter λ. The ridge parameter influences both the regularization and is the inverse of the learning rate α. Initially, the networks are run with the decoders set to zero, allowing the generation of rich neural dynamics before RLS is activated to update the decoder. Training is considered successful if the network can continue displaying the target dynamics without supervision (RLS Off).

FORCE Can Train LIF-Spiking and Parameter Matched LIF-Rate Networks

To demonstrate that LIF-spiking and LIF-rate networks are comparable when trained using the FORCE method, we trained several networks to learn various dynamical systems tasks and compared the resulting neural dynamics across spiking and rate networks (Fig 3A). During the initial spontaneous activity phase, both network types exhibit irregular asynchronous activity in their dynamics, reflecting the chaotic state. However, during learning, the neural dynamics rapidly converge and become highly correlated between the two network types (Fig 3A). This convergence coincides with rapid adjustments to the decoders, causing the decoded output to quickly match the target supervisor. The magnitude of these rapid updates to the decoders is also highly correlated between the spike and rate networks (Fig 3A). Once the decoders and dynamics have stabilized, the RLS learning algorithm can be turned off. If the learning process was successful and the target dynamics are not chaotic, the resulting learned network dynamics show a high degree of correlation between the rate and spiking networks (Fig 3A). This pattern holds true for various periodic supervisors, including more complex oscillators (Fig 3C) and higher-dimensional periodic signals, such as those in "Ode to Joy" (Fig 3D) [13].

The correlation between the LIF-rate and LIF-spiking network dynamics trained with FORCE is not limited to periodic functions. We also demonstrated that both types of networks can learn dynamical systems with inputs, such as the pitchfork system (Fig 3B) and chaotic systems like the Lorenz system (Figures 3F-G). For the pitchfork system, there was a high degree of correlation between the two network dynamics both during and after training. In contrast, with the Lorenz system, we observed a high degree of correlation during training, but the neural dynamics of the two networks diverged after RLS was turned off as seen by differences in the neural currents. This divergence is due to the chaotic nature of the Lorenz system. Despite this divergence, the networks continued to produce qualitatively similar neural dynamics. The output dynamics also qualitatively matched across networks and with the target supervisor, with both networks producing tent maps consistent with those expected from the target Lorenz system [24] (Figures 3F-G).

Learned Weights are Interchangable Between LIF-Spiking and LIF-Rate Networks for Slow Learning Rates

After demonstrating that both LIF-spiking and LIF-rate networks could learn similar tasks and exhibit similar neural dynamics, we investigated under what parameter regimes did the correlation across networks hold, and were the correlated dynamics reflected in the correlation between their decoders ϕ^S and ϕ^R? In particular, is it possible to use the same learned weights for both the LIF-spiking network and the equivalent firing rate network? We trained each network type on a range of tasks, sweeping the (Q, G, α) parameter space, and compared the correlation of the decoders across the network types.

We observed that the correlation between decoders relied on both networks having successfully learned the task and was contingent on the learning rate α. Specifically, for a slow learning rate (equivalently, high regularization) of approximately $\alpha \sim 10^{-5}$ or slower, we found a high correlation between the LIF-rate network's learned decoder ϕ^R and the spiking network's learned decoder ϕ^S (see Fig 4) This correlation was sufficiently strong that, in many cases, the decoders could be interchanged across network types and still have the networks retain the ability to reproduce the target dynamics without requiring further training.

The correlation was also robust to different supervisors (Fig 4A-C) such as the pitchfork, Ode to Joy, and sinusoidal signals with slow learning rates for both networks across a grid of (Q, G) values. Subsequently, we selected the (Q, G) point that yielded the highest Pearson correlation coefficient ρ_{ϕ^R, ϕ^S} between the learned decoders ϕ^R and ϕ^S (Fig 4D-F). We found a high degree of correlation across the learned neural dynamics, as well as a strong correlation across the decoders ($\rho = 0.61, 0.87$ and 0.74 for pitchfork, Ode to Joy, and 5 Hz sine supervisors, respectively). Further, we exchanged the decoders between the network types, running the spiking network with the firing rate decoder ϕ^R and the LIF-rate network with the spiking decoder ϕ^S (Fig 4G-I). The resulting output dynamics and neural dynamics for the networks with

swapped decoders were qualitatively similar to those of the original trained networks. Additionally, we observed a slight time dilation or contraction in the supervisor dynamics after swapping decoders, stemming from subtle differences in the time scales of the firing rate approximation.

When the learning rate was fast ($\alpha > 10^{-4}$), we observed a diminished correlation between ϕ^R and ϕ^S (Fig 5). Nevertheless, we noted that the area of convergence in the (Q, G) hyperparameter space tended to be larger and achieving lower testing errors for the rate network. Across a grid of (Q, G) values, we simulated the pitchfork, Ode to Joy, and sinusoidal signals for both networks and computed the Pearson correlation coefficient ρ_{ϕ^R, ϕ^S} across the learned decoders (Fig 5A-C). Subsequently, we plotted the learned network outputs and neural dynamics for the (Q, G) point with the highest cross-network decoder correlation ρ_{ϕ^R, ϕ^S}, along with the linear regression between ϕ^R and ϕ^S.

When the learning rate was fast, we observed that the networks typically performed worse at reproducing the output and neural dynamics of the trained networks (Fig 5G-I). However, in some instances, the swapped decoder networks managed to produce some of the target dynamics, particularly in the LIF-rate network with the LIF-spiking decoder (Fig 5E). This suggests that either the rate network inherently possesses more stable dynamics or that the decoder learned by the spiking network is more robust. It could be that in the rate network, the faster learning rate leads to a form of overfitting that is less prevalent in the spiking network due to the inherent noisiness of the spike times. Intuitively, the rate network generates a neural basis that is highly reproducible across trials of the target dynamics (Fig 7). Conversely, in the spiking network, there is a high degree of variability in the neural basis across trials (Fig 7), hindering the decoder from being finely tuned to the basis. This one-sided interoperability implies that the spiking network is effectively utilizing a firing rate encoding scheme [4, 6].

Faster Learning Improves Performance in LIF-Rate Networks but not LIF-Spiking Networks

In the fast learning regime, the divergence of the cross-network decoders suggests that the two networks may be learning different weight structures. To further investigate this, we examined the testing errors and decoder correlations across a grid of (Q, G) values and for different network sizes (Fig 6). We considered the Ode to Joy, Fourier, and Sinusoidal tasks across a (Q, G) grid with four distinct learning rates, ranging from slow ($\alpha = 5 \times 10^{-6}$) to fast ($\alpha = 5 \times 10^{0}$).

As the learning rate increased, we found that the area of convergence (Fig 6A) and minimal error achieved (Table 2) for the LIF-spiking networks were largely unaffected. In contrast, for the LIF-rate networks, increasing the learning rate tended to increase the area of convergence (Fig 6A) and decrease the minimal error (Table 3). In the Ode to Joy tasks, higher learning rates ($\alpha > 5 \times 10^{-2}$) resulted in points of high testing error and a decreased area of convergence, suggesting that the FORCE weight updates were unstable [12].

Table 2: Minimal error achieved over (Q, G) grid for LIF network on Fourier, Ode to Joy with HDTS, and 5 Hz sinusoidal oscillator.

Learning Rate	$\alpha = 5e0$	$\alpha = 5e\text{-}2$	$\alpha = 5e\text{-}4$	$\alpha = 5e\text{-}6$
Fourier	4.5e-06	4.9e-06	4.0e-06	2.9e-06
Ode to Joy with HDTS	2.4e-06	1.7e-06	2.1e-06	1.9e-06
Simple Oscillator	1.7e-06	1.9e-06	1.8e-06	2.0e-06

The differences in learning rate dependence between LIF-spiking and LIF-rate networks suggest that the decoders are optimized differently to leverage their respective neural dynamics. We investigated this further by considering the error scaling as a function of network size for the 5 Hz sinusoidal task at four

Table 3: Minimal error achieved over (Q, G) grid for LIF-rate network on Fourier, Ode to Joy with HDTS, and 5 Hz sinusoidal oscillator.

Learning Rate	$\alpha = $ 5e0	$\alpha = $ 5e-2	$\alpha = $ 5e-4	$\alpha = $ 5e-6
Fourier	8.5e-09	2.0e-08	1.5e-07	1.4e-06
Ode to Joy with HDTS	3.6e-08	3.5e-08	5.9e-08	4.2e-07
Simple Oscillator	1.2e-08	2.2e-08	6.5e-08	9.8e-07

different learning rates (Fig 6). For a network with N neurons, an efficient spiking network is expected to scale with N^{-1}, whereas a firing rate encoding scheme with imprecise spike times would scale with $N^{-1/2}$ [6, 25].

To investigate the error scaling further, we trained 21 networks with different random connections for each network type, size, and learning rate (Fig 6B). We then computed the linear line of best fit for the log-log plots to determine the scaling factor α such that the root mean squared error (RMSE) satisfies $RMSE \propto N^\zeta$. For the LIF-spiking networks (Fig 6B.I), we found that the learning rate did not significantly affect the scaling factor ζ or the intercept of the linear fit. Across all learning rates, the scaling factor was approximately -0.5, which, when paired with the spike time variability in the networks (Fig 7), indicates a noisy firing rate encoding scheme. In the firing rate network (Fig 6B.II), the scaling factor remained approximately constant across learning rates within the range of $[-0.83, -0.68]$, demonstrating greater coding efficiency than the LIF-spiking networks.

Additionally, increasing the learning rate decreased the y-intercept of the log-log linear fit, implying that higher learning rates enhance the reduction in testing error as network size increases. We also computed the decoder correlation across the LIF-spiking and LIF-rate networks (Fig 6C). As the network size increased, the cross-network decoder correlation converged to a value dependent on the learning rate, with slower learning resulting in higher decoder correlation.

The Bias–Variance Decomposition of the RMSE Reveals a Noisy Spiking Basis

The scaling factors found in Fig 6B.I suggest that LIF-spiking networks use a firing rate encoding scheme with noisy spike times. This would imply measurable variability in the spike times of the LIF network across multiple repetitions of the same target output signal. Conversely, since the LIF-rate model represents the theoretical firing rate, we would expect the neural basis of the firing rate networks to be unaffected by spike-time noise, and consequently, less varied across repeated trials.

To investigate this further, we simulated the networks trained on the 5 Hz sine wave over a (Q, G) grid with different learning rates (Fig 6A) for 100 repetitions (20s) of the supervisor. We then computed the time-averaged bias and variance across the trials. As there are slight differences in the frequency of the target and learned sinusoidal oscillator, there is an apparent phase shift between the network and target outputs, which becomes more pronounced over time (Fig 6A). To account for this, we time-aligned each repetition of the network's output so that the peaks of the sinusoidal oscillator across trials agreed. To compare the variance and bias within each network, we squared the bias, resulting in a decomposition of the mean squared error into the bias squared, the variance, and a cross-term dependent on the probability distribution of the noise [25].

We then computed the proportion of the variance relative to the sum of the variance and bias squared, to determine which dominated the network testing error. In the LIF-spiking network, we found that the learning rate had little effect on either bias or variance, neither decreasing the minimal values achieved (Table 4) nor affecting the hyper-parameter space where good values were achieved (Fig 7A). Additionally, in all cases where the networks successfully learned the target dynamics, the bias squared was dominated by the variance (Fig 7A), indicating the primary source of testing error to be variance across trials.

In contrast, the firing rate networks showed a dependence on the learning rate, and the bias squared dominated the variance in all cases where the networks successfully learned the target dynamics (Fig 7A). We found that in the LIF-rate networks, faster learning rates led to both the bias and variance achieving good values over a larger area of the (Q, G) hyperparameter space (Fig 7A) and achieving a lower best-case value (Table 5).

Table 4: Minimal bias squared and variance achieved over (Q, G) grid for LIF network on 5 Hz sinusoidal oscillator. The minimal variance was only computed over (Q, G) points that had a corresponding bias squared less than 1e-2.

Learning Rate	$\alpha = 5e0$	$\alpha = 5e-2$	$\alpha = 5e-4$	$\alpha = 5e-6$
Minimum Bias Squared	2.4e-05	2.8e-05	2.1e-05	2.8e-05
Minimum Variance	1.5e-03	1.5e-03	1.3e-03	9.8e-04

Table 5: Minimal bias squared and variance achieved over (Q, G) grid for LIF firng-rate network on 5 Hz sinusoidal oscillator. The minimal variance was only computed over (Q, G) points that had a corresponding bias squared less than 1e-2.

Learning Rate	$\alpha = 5e0$	$\alpha = 5e-2$	$\alpha = 5e-4$	$\alpha = 5e-6$
Minimum Bias Squared	1.4e-08	2.3e-08	1.5e-07	6.4e-06
Minimum Variance	5.3e-15	7.1e-11	2.9e-09	9.9e-09

To understand the difference in variance between the LIF-spiking and LIF-rate network outputs, we analyzed the neural basis generated by each network for an example network (Fig 7B-C) across repetitions of the target output, both at a fast learning rate ($\alpha = 5 \times 10^0$) and a slow learning rate ($\alpha = 5 \times 10^{-6}$). For the selected networks, we recorded the postsynaptic currents of the neurons in both network types, as well as the spike times for the LIF-spiking network. We then time-aligned the postsynaptic currents and spike times for each repetition of the output to create the raster plots in Fig 7B and filtered postsynaptic current plots in Fig 7C.

The spike rasters demonstrated that for both fast and slow learning rates, the inter-trial spike times for each neuron were highly varied but clustered around an average spike time. This variability in spike times resulted in a highly varied filtered postsynaptic current in the spiking networks (Fig 7C), which consequentially led to high variance in the network's output. In contrast, the firing rate networks exhibited highly reproducible postsynaptic currents for both slow and fast learning rates, allowing them to produce network outputs with low cross-trial variance. Averaging the postsynaptic current over trials, we found that LIF-spiking and LIF-rate networks had similar mean neural dynamics, although the mean LIF-spiking postsynaptic current showed some finer structure due to the clustering of spike times.

In some neurons, the variance around the mean spike times was low enough to prevent significant overlap in subsequent spike times within a repetition of the target signal. This resulted in peaks at the mean firing times and troughs in between. These dynamics are not captured in the instantaneous firing rate model since the theoretical firing rate depends only on the input current, whereas the peaks in firing result from a correlation in the neuron state across trials. This can be better understood by noting that the firing rate networks use a temporal firing rate while the average postsynaptic current over trials can be understood as the postsynaptic current due to a firing rate average over trials (see [4] or 1.5 of [26] for a discussion of types of firing rate).

Given the difference in variability between the spiking and rate bases, we investigated whether there was a difference in the dynamics of the spiking and rate decoders during the learning phases of FORCE.

The FORCE algorithm assumes that the output error is kept small so that the feedback signal is close to the target signal, stabilizing the learning network basis. However, we found that even if the feedback output current to the spiking neural networks is stable, the spiking neural basis need not be. This could lead to instability and convergence issues when using the FORCE algorithm for training a spiking neural network.

To investigate this, we recorded a time series for both a LIF-spiking and LIF-rate network decoders during learning for the 5 Hz sinusoidal signal at a successfully trained point in the (Q, G) grid (Fig 8). We observed that during training, the firing rate decoders quickly converged as the training error of the network decreased. Conversely, the spiking network decoders failed to stabilize during training and continued to drift randomly even after the network had learned the target dynamics (Fig 8). This decoder instability was accompanied by a more varied testing error which decreased to a point and then continued fluctuating, likely due to the variability of the spiking basis as mentioned. Furthermore, in the fast learning regimes, we often observed that the spiking decoders would completely destabilize and diverge, resulting in spikes in the training error of the network and better network output with less training (Fig 8).

We also observed that the correlation across the spiking and rate decoders during training initially peaked and then decreased over time (Fig 8). The peak correlation and subsequent decrease were both dependent on the learning rate; slower learning leading to increased peak correlation and a slower decrease. The decrease is likely due to the instability of the spiking decoders, which continue to drift during training.

Discussion

In this work, we sought to understand the differences between spiking and firing rate based neural networks trained with the FORCE technique. Identifying these differences can help improve spiking neural network learning techniques for engineering tasks (neuromorphic computing) and for modelling learning in biological spiking neural networks. Additionally, understanding what information is preserved or lost when using a rate-based versus a spiking-based model is crucial for developing neural computation theory. Importantly, we suggest that LIF-spiking networks trained with the FORCE technique learn to utilize an approximate rate encoding scheme due to the variability in spike times, a result we predict will extend to other least squares based optimization techniques for training spiking neural networks that do not stabilize spike times appropriately. Further, we find that LIF-rate networks show dramatic improvements when faster learning rates are used, while LIF-spiking networks show no improvement, or worse, destabilize.

Additionally, although the dynamics in the LIF-spiking and LIF-rate networks were always correlated when both networks successfully learned the target dynamics, the correlation between the learned decoder weights depended on the learning rate used in training. We found that when the decoders were correlated (slow learning), we could swap the learned decoders across networks and retain the learned output dynamics. When the decoders were less correlated (fast learning), the firing rate network could still function with the learned spiking decoder, but the converse was not always true. We also found that the firing rate network was able to achieve lower testing error than the corresponding LIF-spiking network. These findings suggest that although both networks performed correlated neural computations when learning was successful, the LIF-rate networks achieved more finely tuned solutions that could not work in the LIF-spiking networks. Furthermore, since we were able to convert trained LIF-spiking networks into equivalent LIF-rate networks without loss of performance, the information utilized by the LIF spiking network to perform each task was largely captured by the reduced LIF-rate model. This suggests that the spiking networks were using a firing rate based encoding scheme, where the information used for decoding a task was carried by the firing rates.

To further understand the difference in how the LIF-spiking and LIF-rate networks utilized the neural bases to encode information, we investigated the error scaling as a function of network size. The scaling relationship between error and network size provides insight into how efficiently neural basis elements are being utilized and can suggest the neural encoding scheme. For a perfectly efficient encoding scheme, we

would expect the error to scale like N^{-1} where N is the network size [6, 25]. Alternatively, in a random noisy spike basis utilizing a rate code, the error would be expected to scale like $N^{-1/2}$ [6, 25]. We found an error scaling of about $N^{-1/2}$ in the spiking networks and about $N^{-3/4}$ in the firing rate networks across learning rates. This suggests that the spiking networks are utilizing a noisy rate encoding and demonstrates that the firing rate network is using the neural basis more efficiently. We additionally found that as the learning rate increased, the performance of the spiking networks was largely unaffected, but the firing rate networks were able to achieve lower error at all network sizes.

Furthermore, we found that the time-averaged cross-trial variance dominated the time-averaged cross-trial bias squared in the spiking networks. This meant that most of the spiking output error came from the variability in the spiking neural basis. This was corroborated by the high cross-trial time-wise variability found in the spiking basis and spike times. Conversely, in the firing rate networks, the time-averaged cross-trial bias squared dominated the time-averaged cross-trial variance. This indicates that the limiting source of error in the firing rate networks was the expressiveness of the neural basis and decoder. The existence of spike time jitter explains the error scaling we previously found [6, 27]. This suggests that a scheme closer to a rate encoding is likely utilized by the spiking networks here.

One important implication of our findings is that to avoid learning an encoding scheme that approximates that of a cross-trial averaged firing rate in the LIF network, it is likely necessary to either stabilize spike times in someway relative to the desired learning task or use an error function different from the L^2 norm. In an unreliable spike basis, the variance will dominate the output error, meaning the L^2 or least squares error is forced to find a solution that minimizes the error due to the variance. This inherently leads to an encoding that is approximately that of a cross-trial firing rate. Thus, reducing the variance so that the bias dominates the error would allow for spike encoding strategies that are unique from the cross-trial averaged firing rate to emerges. We suspect that it is possible to analytically demonstrate that the expected decoder learned by a least-squares-based technique under certain assumptions about the spike noise will converge to the optimal decoder for the average cross-trial firing rate basis.

There are several possible extensions and notable limitations to this work. The techniques we applied to compare the spiking and equivalent firing rate networks were relatively simple; primarily looking at swapability and cross-network correlations. It would be beneficial to use more robust techniques for quantifying the differences in the network types. Due to the increased interest in understanding the largely "blackbox" function of ANNs, there have been several attempts to derive techniques to understand them, which could possibly be applied here. For example, work on creating low-dimensional representations of the error landscape for neural networks [28], or on computing the Lyapunov exponents for RNNs [29, 30]. Additionally, reservoir techniques have highly constrained network connectivity and weight structure due to only updating a small subset of the network weights. It would also be interesting to see if our results extend to other spiking neural network training techniques such as full-FORCE [14], E-prop [31], and surrogate gradient descent methods [10, 11].

We suspect that similar results will be found for full-FORCE due to its similarity to FORCE, despite full-FORCE being designed to create a more stable basis. For example, in full-FORCE based spiking training techniques [32], there was considerable variability within the spike times (raster plots Fig. 4.b). The issue of variability in the spike trains of FORCE trained spiking network has been discussed previously [33]. One way to address this is to utilize fast strong inter-neuron connections that stabilize the cross-trial firing rates of neural populations [7, 8, 9]. This approach in essence uses the interactions between neurons to couple and create correlation between the spike time jitters which effectively cancel out perturbations to the population level firing rates [33].

Materials and Methods

Leaky Integrate-and-Fire Networks

To analyze trained spiking networks with a firing rate match, we used the Leaky-Integrate and Fire (LIF) neuron model with a refractory period:

$$v_i(t) \to v_{reset}, \qquad \text{if } v_i(t) \geq v_{th}$$

$$\tau_m \dot{v}_i(t) = \begin{cases} 0, & \text{if in a refractory period} \\ -v_i(t) + I_i(t), & \text{else} \end{cases} \tag{7}$$

where the sub-index i denotes a specific neuron in the network. The sub-threshold dynamics of the membrane potentials v_i are governed by (7). Once the threshold v_{th} is crossed, the neuron is instantaneously set to a reset voltage v_{reset} and then held at this voltage for a refractory period τ_{ref}. The time that $v_i(t)$ reaches v_{th} corresponds to the firing of a spike in the i^{th} LIF neuron. The parameter τ_m is the membrane time constant, which dictates the memory of the LIF neuron for subthreshold events. Larger τ_m lead to longer "storage" and filtering of the sub-threshold dynamics in a neuron. The spiking events are then filtered using the double exponential synaptic filter:

$$\dot{r}_i = -\frac{r_i}{\tau_d} + h_i \tag{8}$$

$$\dot{h}_i = -\frac{h_i}{\tau_r} + \frac{1}{\tau_r \tau_d} \sum_{t_{ik} < t} \delta(t - t_{ik}) \tag{9}$$

where $\delta(\cdot)$ is the Dirac delta function. The parameter τ_r is the synaptic rise time and τ_d the synaptic decay time. The neuron parameters are listed in Table 1. The current of the i^{th} neuron, $I_i(t)$ is the sum of a background bias current I_{bias}, which we took to be the rheobase ($I_{bias} = -40$ pA), and the synaptic input currents $s_i(t)$, which are computed as:

$$s_i(t) = \sum_{j=1}^{N} \omega_{ij} r_j(t) \tag{10}$$

where $\boldsymbol{\omega}$ is the synaptic connectivity matrix. A unit resistance is absorbed into the input current. The synaptic connectivity matrix is composed of a static portion $G\boldsymbol{\omega}^0$ and a learned portion $Q\boldsymbol{\eta} \left(\phi^S\right)^T$ as:

$$\boldsymbol{\omega} = G\boldsymbol{\omega}^0 + Q\boldsymbol{\eta}\boldsymbol{\phi}^T. \tag{11}$$

The static portion of the matrix was scaled by a recurrent connectivity strength parameter G scaling a sparse random matrix $\boldsymbol{\omega}^0$. For our investigation we generated $\boldsymbol{\omega}^0$ from a normal distribution with mean 0 and variance of $(Np^2)^{-1}$ where p is the sparsity of the matrix and N the number of neurons in the network. This scales the weights to be in proportion to the inverse of the square-root of the number of connections [13]. To introduce sparsity into the reservoir connections, each weight ω_{ij}^0 was randomly set to be zero with probability $1 - p$. Further, the sample mean of each row in the matrix was explicitly set to be 0, which encourages homogeneity in the neural firing rates. This is done by first generating a random matrix $\tilde{\boldsymbol{\omega}}^0$ from the normal distribution $\mathcal{N}(0, p(N)^{-1/2})$ with the desired level of sparsity then defining:

$$\omega_{ij}^0 = \tilde{\omega}_{ij}^0 - \frac{1}{N} \sum_{j=1}^{N} \tilde{\omega}_{ij}^0. \tag{12}$$

The learned portion of the connectivity matrix consisted of a constant scalar strength parameter Q, a static encoder $\boldsymbol{\eta}$, and a learned decoder $\boldsymbol{\phi}$. By introducing the Q and G parameters we can control

the macro-scale dynamics of the network; either inducing more (less) chaos by increasing (decreasing) G or creating more (less) structured heterogeneity in the neural firing rates by increasing (decreasing) Q [17, 18]. The static encoder $\boldsymbol{\eta}$ is an $M \times N$ matrix where M is the dimension of the network output. The components of the encoder are drawn from the uniform distribution over the M dimensional unit square $[-1, 1]^M$. The learned linear decoder $\boldsymbol{\phi}$ serves the primary task of decoding the neural dynamics to produce the network output:

$$\hat{\boldsymbol{x}}(t) = \sum_{i=1}^{N} \phi_i r_i \tag{13}$$

but also works in conjunction with the encoder to stabilize the network dynamics via the feedback connections.

Firing Rate Networks

If the current I_i is constant or very slowly varying relative to $v_i(t)$, in (7), the solution to the differential equation for the LIF neuron is computed exactly as:

$$v_i(t) = (v_i(0) - I_i) \exp \left[\frac{t}{\tau_m} \right] - I_i \tag{14}$$

for some initial voltage $v(0)$. Then, the time to the first spike t_{spike}, can be computed as the time required to reach the threshold voltage v_{th} from the reset voltage v_{reset} given by:

$$t_{spike} = -\tau_m \ln \left[\frac{I_i - v_{th}}{I_i - v_{reset}} \right]. \tag{15}$$

This value plus the refractory period τ_{ref} is then the time between spikes given a constant current. As the spike rate is the inverse of the time between spikes, the firing rate for a LIF neuron with an input current I_i is given by:

$$R(I_i) = \left[\tau_{ref} - \tau_m \ln \left(\frac{I_i - v_{th}}{I_i - v_{reset}} \right) \right]^{-1} \tag{16}$$

where $R(I_i)$ is often called the transfer function (or $f - I$ curve) of neuron i. The firing rate, $R(I_i)$, is then used to approximate the filtered spike train as [1]:

$$\dot{r}_i = -\frac{r_i}{\tau_d} + h_i$$

$$\dot{h}_i = -\frac{h_i}{\tau_r} + \frac{1}{\tau_r \tau_d} R_i(I_i)$$

which will be valid under the assumption that the synapses are much slower than the spiking dynamics or that the specific spike-times are not important for the network dynamics [1].

Thus, for a leaky-integrate-and-fire network of N neurons, the firing rate system is determined by:

$$I_i(t) = \sum_{j=1}^{N} \omega_{ij} r_j(t) + I_{bias} \tag{17}$$

$$\dot{r}_i = -\frac{r_i}{\tau_d} + h_i \tag{18}$$

$$\dot{h}_i = -\frac{h_i}{\tau_r} + \frac{1}{\tau_r \tau_d} R\left(I_i\left(t \right) \right) \tag{19}$$

$$R(x) = \left[\tau_{ref} - \tau_m \ln \left(\frac{x - v_{th}}{x - v_{reset}} \right) \right]^{-1}. \tag{20}$$

When all the parameters in equations (17)-(20) are matched to their spiking network counterpart, the system (17)-(20) predicts the dynamics of the firing rates of the spiking network.

FORCE Training

The primary objective of FORCE training is to approximate some target dynamical system $\boldsymbol{x}(t)$ with the network output $\hat{\boldsymbol{x}}(t)$, using a sample of the dynamics of $\boldsymbol{x}(t)$ over an interval. To do this, FORCE uses the Recursive Least Squares (RLS) technique to minimize the squared error loss function:

$$L(\hat{\boldsymbol{x}}, x; t) = \sum_{j=1}^{M} \int_0^t (\hat{x}_j(s) - x_j(s))^2 \, ds + \lambda \boldsymbol{\phi}^T \boldsymbol{\phi} \tag{21}$$

where λ is a scalar regularization parameter that penalizes large values of the decoders. The RLS algorithm works by dynamically reducing the error in the network output and target dynamics, $\boldsymbol{e}(t) = \hat{\boldsymbol{x}}(t) - \boldsymbol{x}(t)$, at a series of time steps by performing discrete updates to the decoder $\boldsymbol{\phi}$. The update at time step t with step size Δt is computed according to:

$$\boldsymbol{\phi}(t) = \boldsymbol{\phi}(t - \Delta t) - \boldsymbol{e}^T(t) \boldsymbol{P}(t) \boldsymbol{r}(t)$$
$$\boldsymbol{P}(t) = \boldsymbol{P}(t - \Delta t) - \frac{\boldsymbol{P}(t - \Delta t) \boldsymbol{r}(t) \boldsymbol{r}^T(t) \boldsymbol{P}(t - \Delta t)}{1 + \boldsymbol{r}^T(t) \boldsymbol{P}(t - \Delta t) \boldsymbol{r}(t)}$$

where $\boldsymbol{P}(t)$ is the discrete approximation to the inverse cross-correlation plus regularization matrix:

$$\boldsymbol{P}(t)^{-1} \approx \int_0^t \boldsymbol{r}(s) \boldsymbol{r}(s)^T \, ds + \lambda \boldsymbol{I}_N. \tag{22}$$

The decoder is initialized as $\phi(0) = 0$ and the correlation matrix with:

$$\boldsymbol{P}(0) = \frac{\boldsymbol{I}_N}{\lambda} = \alpha \boldsymbol{I}_N. \tag{23}$$

where we can view the parameter α as the learning rate for the FORCE algorithm [12]. We note that the regularization parameter in the least squares formalization λ is the inverse of the learning rate α in the RLS FORCE framework. We make this distinction since, in the least squares framework, the optimization occurs over a fixed time interval so λ adjusts the magnitude of ϕ but in the RLS framework, α influences how large updates to $\boldsymbol{\phi}$ are at each time step. As we are dealing mainly with RLS, we will mainly refer to the learning rate α but will occasionally refer to the regularization λ as they serve a related function.

Fig 3 Methods

Networks of LIF-spiking neurons and their parameter-matched LIF-rate networks were separately trained using the FORCE technique to produce various dynamical systems. For all simulations, an integration time step of 0.05ms was used in a forward Euler integration scheme. The network size N, graph sparsity p, reservoir strength G, feedback strength Q, training time T_{train}, testing time T_{test}, and RLS update interval Δt are as listed in Table 6.

The sinusoidal supervisor depicted in Fig 3 is a 5 Hz sinusoidal oscillator with unit amplitude. To illustrate the spontaneous activity before training, the network ran for 0.6s before RLS training commenced. Then, RLS was activated for 1s, followed by deactivation for 0.6s to test the network. The complex oscillator (Fig 3.C) results from the product of 1 Hz and 2 Hz sinusoidal oscillators. For the Ode to Joy supervisor, a 5-dimensional signal representing the G, F, E, D, and C notes of the first bar of the song was used. Each pulse of the supervisor was generated by the positive portion of a 1 Hz or 2 Hz sinusoidal waveform, representing a half or quarter note in the song based on the pulse duration, respectively. During training, the signal was repeated 20 times, totaling 80 s of simulated training time, and then tested for an additional 2 repetitions of the signal (8 s), with the last repetition (4 s) utilized in Fig 3.D-E.

Table 6: Parameters for Fig 3.

Supervisor	N	p	G	Q	T_{train}	T_{test}	Δt	τ_d
Simple Oscillator	2000	0.4	0.19	25	1 s	0.6 s	0.25 ms	20 ms
pitchfork	2000	0.4	0.16	28	120 s	28 s	0.5 ms	20 ms
Complex Oscillator	2000	0.3	0.16	28	5 s	3 s	0.5 ms	20 ms
Ode to Joy	2000	0.4	0.16	28	80 s	4 s	0.5 ms	20 ms
Lorenz System	5000	0.3	0.1	20	200 s	200 s	0.25 ms	100 ms

The pitchfork supervisor was generated from the pitchfork normal form

$$\gamma \dot{x} = rx - x^3 + p(t)$$

for some perturbation function in time $p(t)$. The parameter γ is a time constant that adjusts how quickly the system responds to perturbations due to $p(t)$ and the positive parameter r controls the location of the stable fixed points in the unperturbed system $(p(t) \equiv 0)$, which occur at $\pm\sqrt{r}$. The parameters r and γ were fixed at $r = 1$ and $\gamma = 0.01$. To generate the perturbations, $p(t)$, a random sequence of square pulses was created where the time between pulses was uniformly sampled from $[0.1, 0.5]$ while the length of the pulse was uniformly sampled from $[0.005, 0.01]$, and the height of the pulses were sampled from a normal distribution with standard deviation 2 and zero mean.

The Lorenz system was generated from the following equations:

$$\dot{x} = \sigma(y - x) \tag{24}$$
$$\dot{y} = x(\rho - z) - y \tag{25}$$
$$\dot{z} = xy - \beta z \tag{26}$$

with parameters $\rho = 28$, $\sigma = 5$, and $\beta = \frac{7}{3}$. Along with the Lorenz-like trajectories shown in Fig 3.F, we computed the return maps for both the trained LIF-spiking and LIF-rate networks. The Lorenz maps were computed by first smoothing the raw network output $\hat{z}$ by convolution with a window filter of length 21 time steps, then computing the local maximums $\hat{z}_n$ of the resulting signal using the SciPy argrelextrema [34] function with order 10000. The maps are then formed by plotting $\hat{z}_{n+1}$ vs $\hat{z}_n$.

Fig 4 and 5 Methods

The pitchfork, Ode to Joy, and sinusoidal supervisors were produced in the same way as those in Fig 3, with the addition that the Ode to Joy supervisors also included a high-dimensional temporal signal (HDTS) [13]. The HDTS consists of a series of extra components added to the supervisor to increase its dimensionality. These components help stabilize the network by driving subsets of the network into assemblies of synchronized activity, which helps disambiguate repeating note sub-sequences in the Ode to Joy song [13].

To produce an m-dimensional HDTS, we divided the time interval $[0, T]$ into m subintervals $I_n = \left[T\left(\frac{n-1}{m}\right), T\left(\frac{n}{m}\right)\right]$ for $n = 1, 2, \ldots, m$. The nth component of the HDTS contained a pulse in the interval I_n. Here, we used the positive portion of a sine wave, yielding the additional components:

$$x_n(t) = \begin{cases} \left|\sin\left(\frac{m\pi t}{T}\right)\right| & t \in I_n \\ 0 & \text{otherwise.} \end{cases} \tag{27}$$

For the Ode to Joy examples, an HDTS with 16 components was used.

The testing error of a decoded output $\hat{\boldsymbol{x}}(t)$ for each point in the (Q, G) grid for an M dimensional supervisor $x(t)$ on the interval $[0, T]$ was computed by the L^2 norm:

$$E\left(\hat{\boldsymbol{x}}(t), \boldsymbol{x}(t)\right) = \frac{1}{M} \sum_{i=1}^{M} \sqrt{\int_0^T \left(\hat{x}_i(t) - x_i(t)\right)^2 \, dt} \tag{28}$$

The Pearson correlation coefficient between the M dimensional spiking decoder ϕ^S and the firing rate decoder ϕ^R for a network of size N at each point in the (Q, G) grid was computed as:

$$\rho_{\phi^R, \phi^S} = \frac{\sum_{i=1}^{M} \sum_{j=1}^{N} \left(\phi_{ij}^R - \overline{\phi^R}\right)\left(\phi_{ij}^S - \overline{\phi^S}\right)}{\sqrt{\sum_{i=1}^{M} \sum_{j=1}^{N} \left(\phi_{ij}^R - \overline{\phi^R}\right)^2} \sqrt{\sum_{i=1}^{M} \sum_{j=1}^{N} \left(\phi_{ij}^S - \overline{\phi^S}\right)^2}} \tag{29}$$

where $\overline{\phi}$ is the mean of ϕ over all components and dimensions. For each supervisors, we then chose the (Q, G) point with the highest ρ_{ϕ^R, ϕ^S} where the testing errors $E(\hat{x})$ for both the spiking and rate networks was less than 5×10^{-5}. For the resulting point (Q^*, G^*), the spiking network was simulated with the firing rate decoder ϕ^R and the firing rate network was simulated with the spiking decoder ϕ^S. The network size N, sparsity p, training time T_{train}, testing time T_{test}, and RLS update interval Δt for each supervisor are as listed in Table 7.

Table 7: Training parameters for Fig 4 and 5.

Supervisor	N	p	T_{train} (s)	T_{test} (s)	Δt (ms)
pitchfork	2000	0.4	120	120	0.5
Ode to Joy with HDTS	2000	0.4	80	8	0.5
Simple Oscillator	2000	0.4	0.6	0.6	0.5

Fig 6 Methods

The Ode to Joy with HDTS and sinusoidal supervisors were constructed as previously described. The Fourier supervisors consisted of 9 sinusoidal waves, with frequencies evenly distributed from 0.5 to 4.5, each serving as its own component of the supervisors. The overall Fourier supervisor is described by:

$$x_n(t) = \sin\left(n\pi t\right) \tag{30}$$

where x_n is the n^{th} component of the supervisor and $n = 1, 2, \ldots, 9$.

To compute the error scaling and cross network decoder correlations, 21 different LIF-spiking and LIF-rate networks were trained on the 5 Hz sinusoidal supervisors for network sizes ranging from $N = 100$ to $N = 25600$. Each network was row balanced with reservoir and feedback paramters $(Q, G) = (20, 0.125)$, trained with $T_{train} = 5$ s and tested with $T_{test} = 0.4$ s. The testing error and cross networks decoder correlation was calculated as previously described.

Fig 7 Methods

For each point on the (Q, G) grid, a LIF-spiking and LIF-rate network with 2000 neurons was trained on a 5 Hz sinusoidal supervisor for 10 (2s) repetitions and then tested for 100 (20s) repetitions. The 20s interval was segmented into 100 evenly spaced 0.2s intervals, each containing a single repetition of the sinusoidal

supervisor. Each repetition was time-aligned by computing the maximal value in the sub-interval and rolling the output signal so that the maximal value occurred at the expected time of $t = 0.05$s. For the spiking network, the signal was first smoothed by convolving it with a square window function of width 0.0250s before computing the maximal value and then time-aligning the original unsmoothed signal. Let $\hat{x}_i(t)$ be the i^{th} time aligned repetition and n_{rep} the number of repetitions, the bias squared was then computed by:

$$\text{Bias}\,(\hat{x})^2 = \frac{1}{T} \int_0^T \left(\frac{1}{n_{rep}} \sum_{i=1}^{n_{rep}} \hat{x}_i(t) - x(t) \right)^2 dt \tag{31}$$

the variance is computed as:

$$\text{Var}\,(\hat{x}) = \frac{1}{T} \sum_{j=1}^{n_{rep}} \int_0^T \left(\hat{x}_j(t) - \frac{1}{n_{rep}} \sum_{i=1}^{n_{rep}} \hat{x}_i(t) \right)^2 dt \tag{32}$$

and the proportion of variance as:

$$\frac{\text{Var}\,(\hat{x})}{\text{Bias}\,(\hat{x})^2 + \text{Var}\,(\hat{x})}. \tag{33}$$

Code availability

All code is available at https://github.com/Trnewton/RateVsSpike [35].

Figures

Fig. 1: **Leaky Integrate-and-Fire Spiking and Equivalent LIF-Rate Networks.** In standard LIF-spiking networks, each neuron has a membrane voltage governed by linear dynamics. Once this voltage crosses a threshold, a spike is fired by the neuron which is then filtered by a set of double exponential filter equations. The resulting filtered spike current or post-synaptic current is then used as the output from the neuron. In the firing rate network model, compute the instantaneous theoretical firing rate given the input current for each neuron. This firing rate is then again filtered by the double exponential filter equations to produce the post-synaptic current as the neurons output.

Fig. 2: **FORCE Training LIF-Spiking and LIF-Rate Networks** The single layer recurrent neural network used in the FORCE method consists of: a set of fixed reservoir weights, a set of fixed encoder weights and a set of learned decoder weights. The reservoir network creates a chaotic pool of rich mixed dynamics which are used to linearly decode the target supervisor $\boldsymbol{x}(t)$ with $\hat{\boldsymbol{x}}(t)$. This decoder $\boldsymbol{\phi}_S/\boldsymbol{\phi}_R$ (S for spikes, R for rates) is learned online using the Recursive Least Squares (RLS) algorithm. The encoder weights η then feedback the decoded output $\hat{x}(t)$ into the reservoir to stabilize the dynamics.

Fig. 3: **FORCE can Train Both LIF-spiking and matched LIF-rate Networks.** LIF-spiking and parameter matched LIF-rate networks are trained on different tasks. The network outputs (black or red) and sample neuron firing rates (blue) are overlaid. LIF-spiking values are plotted with a solid line, LIF-rate values are plotted with a dotted line, and supervisors with a thick grey line. **A** FORCE training can be broken down into three phases: pre-learning, learning, and post-learning. Before learning, the network dynamics are spontaneously chaotic. During learning, the network output is forced to match the target output, and the network dynamics are stabilized accordingly. After learning, if the training is successful, the network output and dynamics will continue to reproduce those stabilized during learning without any further weight updates. The green line indicates the change in the Euclidean norm of the decoder. Across all three stages of learning, the neural dynamics and network outputs of the LIF-spiking and LIF-rate networks are highly correlated. **B** Networks of 2000 neurons were trained to reproduce the pitchfork normal form using 120s of training, with 27s of testing displayed. **C** Networks of 2000 neurons were chaotically initialized, then trained to reproduce the product of a 1Hz and 2Hz sine wave using 5s of training, with 5s of testing displayed. **D-E** Networks of 2000 neurons were chaotically initialized, then trained to reproduce the first bar of the song "Ode to Joy" by Beethoven. Each of the 5 notes in the first bar was converted to a component of a 5-dimensional target signal. Quarter notes were represented by the positive portion of a 2Hz sine wave, and half notes by the positive portion of a 1Hz sine wave. Training consisted of 80s or 20 bar repetitions, while the testing displayed consists of 4s or 1 repetition. **F-G** Networks of 5000 neurons were chaotically initialized, then trained to reproduce the global dynamics of the Lorenz system with parameters $\rho = 28, \sigma = 10, \beta = \frac{8}{3}$. To train the networks, 200s of Lorenz target trajectory was used, and then 200s of testing output is displayed. Each of the 3 components of the Lorenz system was used to train a component of the 3-dimensional network output.

Pitchfork

A — Test Error Spike, Test Error Rate, Decoder Correlation

D — LIF Network, Rate Network, Supervisor; Output; Neuron Currents; 2.5 s

G — Spike Network with Rate Decoder; Output; Neuron Currents; 2.5 s; Rate Network with Spike Decoder; Output; Neuron Currents; 2.5 s

J — $\phi_S = 0.43\phi_R + 1.6 \times 10^{-6}, \rho = 0.61$; ϕ_S; ϕ_R

Ode to Joy with HDTS

B — Test Error Spike, Test Error Rate, Decoder Correlation

E — LIF Network, Rate Network; Neuron Currents; 500 ms

H — Spike Network with Rate Decoder; Neuron Currents; 500 ms; Rate Network with Spike Decoder; Neuron Currents; 500 ms

K — $\phi_S = 0.88\phi_R + 1.9 \times 10^{-7}, \rho = 0.87$; ϕ_S; ϕ_R

Sinusoid (5 Hz)

C — Test Error Spike, Test Error Rate, Decoder Correlation

F — LIF Network, Rate Network, Supervisor; Output; 10 ms

I — Spike Network with Rate Decoder; Output; Neuron Currents; 10 ms; Rate Network with Spike Decoder; Output; Neuron Currents; 10 ms

L — $\phi_S = 0.75\phi_R - 6.6 \times 10^{-7}, \rho = 0.74$; ϕ_S; ϕ_R

Fig. 4: **FORCE Training with Slow Learning Rates Leads to Strongly Correlated and Swapable Decoders Across LIF-spiking and LIF-rate networks. A-C** Networks of 2000 neurons were trained on different supervisors (Table 7) over a 40×40 grid of points in the (Q, G) parameter space for both LIF-spiking and LIF-rate networks. The learning rates used were: $\alpha = 5 \times 10^{-6}$, $\alpha = 5 \times 10^{-8}$, and $\alpha = 5 \times 10^{-6}$ for the pitchfork, Ode to Joy, and oscillator respectively. Each set of heatmaps from top to bottom are: the L_2 testing error for the LIF-spiking networks, the L_2 testing error for the firing rate networks, and the Pearson correlation between the learned decoders of the LIF-spiking and LIF-rate networks. The stars indicate the most correlated pair of networks with both networks L_2 error below a threshold of 5×10^{-6}, which were used in remaining panels. **D-F** Sample overlaid network outputs (black), sample neuron firing rates (blue), and target supervisor (grey) for both the LIF-spiking (solid) and LIF-rate (dotted) networks. **G-I** Sample output and neuron dynamics for swapped decoders. The top plots are the output and neuron dynamics for the LIF network with the trained firing rate deocder. The bottom plots are the output and neuron dynamics for the firing rate network with the trained LIF deocder. **J-L** Scatter plot of LIF decoder ϕ_s versus firing rate decoder ϕ_R with a linear fit.

Pitchfork

D — LIF Network ⋯ Rate Network — Supervisor

Output

Neuron Currents

2.5 s

J $\phi_S = 0.10\phi_R + 2.5 \times 10^{-6}$, $\rho = 0.34$

ϕ_S
ϕ_R

G Spike Network with Rate Decoder

Output

Neuron Currents

2.5 s

Rate Network with Spike Decoder

Output

Neuron Currents

2.5 s

Ode to Joy with HDTS

E — LIF Network ⋯ Rate Network

Neuron Currents

500 ms

K $\phi_S = 0.15\phi_R + 1.1 \times 10^{-6}$, $\rho = 0.32$

ϕ_S
ϕ_R

H Spike Network with Rate Decoder

Neuron Currents

500 ms

Rate Network with Spike Decoder

Neuron Currents

500 ms

Sinusoid (5 Hz)

F — LIF Network ⋯ Rate Network — Supervisor

Output

Neuron Currents

10 ms

L $\phi_S = 0.22\phi_R - 2.4 \times 10^{-8}$, $\rho = 0.31$

ϕ_S
ϕ_R

I Spike Network with Rate Decoder

Output

Neuron Currents

10 ms

Rate Network with Spike Decoder

Output

Neuron Currents

10 ms

A
Test Error Spike — log Error
Test Error Rate — log Error
Decoder Correlation — Pearson Correlation

B
Test Error Spike — log Error
Test Error Rate — log Error
Decoder Correlation — Pearson Correlation

C
Test Error Spike — log Error
Test Error Rate — log Error
Decoder Correlation — Pearson Correlation

Fig. 5: **FORCE Training with Fast Learning Rates Reduces Decoder Correlation and Swappability. A-C** Row balanced networks of 2000 neurons were train on a supervisors (Table 7) over a 40×40 grid of points in the (Q, G) parameter space for both LIF-spiking and LIF-rate networks. The learning rates used were: $\alpha = 5 \times 10^{-4}$, $\alpha = 5 \times 10^{-3}$, and $\alpha = 5$ for the pitchfork, Ode to Joy, and oscillator respectively. Each set of heatmaps from top to bottom are: the L_2 testing error for the LIF-spiking networks, the L_2 testing error for the LIF-rate networks, and the Pearson correlation between the learned decoders of the LIF-spiking and LIF-rate networks. The stars indicate the most correlated pair of networks with both networks L_2 error below a threshold of 5×10^{-6}, which were used in remaining panels. **D-F** Sample overlaid network outputs (black), sample neuron firing rates (blue), and target supervisor (grey) for both the LIF-spiking (solid) and LIF-rate (dotted) networks. **G-I** Sample output and neuron dynamics for swapped decoders. The top plots are the output and neuron dynamics for the LIF network with the trained firing rate deocder. The bottom plots are the output and neuron dynamics for the firing rate network with the trained LIF deocder. **J-L** Scatter plot of LIF decoder ϕ_s versus firing rate decoder ϕ_R with a linear fit.

Fig. 6: **Fast Learning Improves Performance of LIF-Rate but not LIF-Spiking Networks. A**
Networks of 2000 neurons were train on the Ode to Joy, Fourier basis, and sinusoidal tasks over a 40×40 grid
of points in the (Q, G) hyperparameter space with 4 different learning rates for both LIF-spiking and LIF-rate
networks. Within each sub-panel, in order from left to right, we plotted the testing error for the LIF-spiking
network, the LIF-rate network, and the cross network decoder correlation ρ_{ϕ^R,ϕ^S}. **B** For the 5 Hz sinusoidal
oscillator task and (Q, G) hyperparameter point $(20, 0.125)$, we trained 21 repetitions of randomly initialized
networks with sizes in the range $[100, 100 \times 2^6]$ for 4 different learning rates for both the LIF-spiking (**B.I**)
and LIF-rate model (**B.II**). Each blue point represents a repetition and each black point the mean. The
blue lines indicate the linear regression fit with slope and intercepts indicated. **C** Mean Pearson correlation
coefficient of decoders across networks (ρ_{ϕ^R,ϕ^S}) for simulations in **B**. The shaded area indicates the corrected
sampled standard deviation.

Fig. 7: **Comparing the Bias and Variance in LIF-spiking and LIF-rate Networks. A** For the 5 Hz sinusoidal oscillator task, we trained networks over a 40×40 grid of points in the (Q, G) hyperparameter space with 4 different learning rates for both LIF-spiking and LIF-rate networks. For each point in the (Q, G) space, we simulated the trained network for 100 (20s) repetitions of the sinusoidal output, then computed the cross trail bias and variance of the networks output. Columns of heatmaps within each sub-panel from left to right are: the time averaged bias squared, time averaged variance, and the proportion of the variance to bias squared. The left panel and left panels contain the plotted values for the LIF-spiking network simulations and LIF-rate networks, respectively. **B-C** For a selected point (indicated by star in **A**) in the (Q, G), the corresponding trained networks was simulated with both LIF-spiking and LIF-rate neuron models for slow and fast learning rates for 100 (20s) repetitions of the 5 Hz sinusoidal task. For 5 randomly chosen neurons, the spike times (**B**) for the LIF-spiking networks and filtered postsynaptic currents (**C**) for both networks were recorded. To counteract output time-drift, each repetition of the network output was time-aligned to the first peak of the supervisor. **B** Each spike time was represented by a dot where the colour indicates order of the spike time in its respective repetition of the supervisor. **C** The postsynaptic filters for both the LIF-spiking and LIF-rate networks, where the shaded areas indicate the corrected sample standard deviation for both. Note that the deviation for the rate network is also displayed.

Fig. 8: **FORCE Trained Spiking Decoders do not Stabilize for Fast Learning.** Time series data for LIF-spiking and LIF-rate networks trained on a 5 Hz sinusoidal for 10 s with $(Q, G) = (25, 0.15)$. **A** Sampled decoder elements, **B** Euclidean norm of decoders $\left(\left\|\boldsymbol{\phi}_{R/S}\right\|_2\right)$, **C** Pearson correlation across network decoders $\left(\rho_{\phi^R, \phi^S}\right)$, and **D** log instantaneous error $\left(\log |x(t) - \hat{x}(t)|\right)$.

Bibliography

[1] Dayan P, Abbott LF. Theoretical Neuroscience: Computational and Mathematical Modeling of Neural Systems. The MIT Press; 2005.

[2] Kandel ER, Schwartz JH, Jessell TM, Siegelbaum SA, Hudspeth AJ. Principles of Neural Science. 5th ed. McGraw Hill; 2013.

[3] Adrian ED, Zotterman Y. The impulses produced by sensory nerve-endings. J Physiol. 1926;61(2):151–171.

[4] Brette R. Philosophy of the Spike: Rate-Based vs. Spike-Based Theories of the Brain. Frontiers in Systems Neuroscience. 2015;9:151. doi:10.3389/fnsys.2015.00151.

[5] Eliasmith C, Anderson CH. Neural engineering: Computation, representation, and dynamics in neurobiological systems. MIT press; 2003.

[6] Denève S, Machens CK. Efficient codes and balanced networks. Nature Neuroscience. 2016;19(3):375.

[7] Boerlin M, Machens CK, Denève S. Predictive coding of dynamical variables in balanced spiking networks. PLoS computational biology. 2013;9(11):e1003258.

[8] Schwemmer MA, Fairhall AL, Denéve S, Shea-Brown ET. Constructing precisely computing networks with biophysical spiking neurons. Journal of Neuroscience. 2015;35(28):10112–10134.

[9] Boerlin M, Denève S. Spike-Based Population Coding and Working Memory. PLOS Computational Biology. 2011;7(2):1–18. doi:10.1371/journal.pcbi.1001080.

[10] Neftci EO, Mostafa H, Zenke F. Surrogate Gradient Learning in Spiking Neural Networks: Bringing the Power of Gradient-Based Optimization to Spiking Neural Networks. IEEE Signal Processing Magazine. 2019;36(6):51–63. doi:10.1109/MSP.2019.2931595.

[11] Perez-Nieves N, Goodman DFM. Sparse Spiking Gradient Descent. In: Beygelzimer A, Dauphin Y, Liang P, Vaughan JW, editors. Advances in Neural Information Processing Systems; 2021.

[12] Sussillo D, Abbott LF. Generating Coherent PFtrazrs of Activity from Chaotic Neural Networks. Neuron. 2009;63:544–557.

[13] Nicola W, Clopath C. Supervised learning in spiking neural networks with FORCE training. Nature communications. 2017;8(1):1–15.

[14] DePasquale B, Cueva CJ, Rajan K, Escola GS, Abbott L. full-FORCE: A target-based method for training recurrent networks. PloS one. 2018;13(2):e0191527.

[15] Goodfellow IJ, Bengio Y, Courville A. Deep Learning. Cambridge, MA, USA: MIT Press; 2016.

[16] Rumelhart DE, Hinton GE, Williams RJ. Learning representations by back-propagating errors. Nature. 1986;323(6088):533–536. doi:10.1038/323533a0.

[17] Sompolinsky H, Crisanti A, Sommers HJ. Chaos in Random Neural Networks. Physical Review Letters. 1988;61(3):259–262.

[18] Mastrogiuseppe F, Ostojic S. Linking Connectivity, Dynamics, and Computations in Low-Rank Recurrent Neural Networks. Neuron. 2018;99:609–623.

[19] Harish O, Hansel D. Asynchronous Rate Chaos in Spiking Neuronal Circuits. PLOS Computational Biology. 2015;11(7):1–38. doi:10.1371/journal.pcbi.1004266.

[20] Haykin SS. Neural networks and learning machines. 3rd ed. Pearson Education; 2009.

[21] Willoughby RA. Solutions of Ill-Posed Problems (A. N. Tikhonov and V. Y. Arsenin). SIAM Review. 1979;21(2):266–267.

[22] Phillips DL. A Technique for the Numerical Solution of Certain Integral Equations of the First Kind. J ACM. 1962;9(1):84–97. doi:10.1145/321105.321114.

[23] Hoerl AE, Kennard RW. Ridge Regression: Biased Estimation for Nonorthogonal Problems. Technometrics. 2000;42:80 – 86.

[24] Strogatz SH. Nonlinear Dynamics and Chaos: With Applications to Physics, Biology, Chemistry, and Engineering. 2nd ed. Westview Press; 2015.

[25] Nicola W, Newton TR, Clopath C. The impact of spike timing precision and spike emission reliability on decoding accuracy. Scientific Reports. 2024;14(10546).

[26] Gerstner W, Kistler WM. Spiking Neuron Models. Cmabridge University Press; 2002.

[27] Hahnloser RH, Kozhevnikov AA, Fee MS. An ultra-sparse code underliesthe generation of neural sequences in a songbird. Nature. 2002;419(6902):65.

[28] Li H, Xu Z, Taylor G, Studer C, Goldstein T. Visualizing the Loss Landscape of Neural Nets. In: Bengio S, Wallach H, Larochelle H, Grauman K, Cesa-Bianchi N, Garnett R, editors. Advances in Neural Information Processing Systems. vol. 31. Curran Associates, Inc.; 2018.

[29] Vogt R, Puelma Touzel M, Shlizerman E, Lajoie G. On Lyapunov Exponents for RNNs: Understanding Information Propagation Using Dynamical Systems Tools. Frontiers in Applied Mathematics and Statistics. 2022;8.

[30] Engelken R, Wolf F, Abbott LF. Lyapunov spectra of chaotic recurrent neural networks. Phys Rev Res. 2023;5:043044. doi:10.1103/PhysRevResearch.5.043044.

[31] Bellec G, Scherr F, Subramoney A, Hajek E, Salaj D, Salaj D, et al. A solution to the learning dilemma for recurrent networks of spiking neurons. Nature Communications. 2020;11(3625).

[32] DePasquale B, Churchland MM, Abbott LF. Using firing-rate dynamics to train recurrent networks of spiking model neurons; 2016. Available from: https://arxiv.org/abs/1601.07620.

[33] Abbott LF, DePasquale B, Memmesheimer RM. Building functional networks of spiking model neurons. Nature neuroscience. 2016;19(3):350–355.

[34] Virtanen P, Gommers R, Oliphant TE, Haberland M, Reddy T, Cournapeau D, et al. SciPy 1.0: Fundamental Algorithms for Scientific Computing in Python. Nature Methods. 2020;17:261–272. doi:10.1038/s41592-019-0686-2.

[35] Newton T. RateVsSpikeV1; 2024. Available from: `https://doi.org/10.5281/zenodo.13333935`.