Dual-timescale motor circuit dynamics underlies fast head exploratory behavior and efficient locomotion

Pinjie Li[1,2,*], **Heng Zhang**[3,*,✉], **Yifan Su**[4,*], **Jiaqi Wang**[1,2], **Louis Tao**[3,4,✉], and **Quan Wen**[1,2,✉]

[1] Division of Life Sciences and Medicine, University of Science and Technology of China, Hefei, China

[2] Hefei National Laboratory for Physical Sciences at the Microscale, Center for Integrative Imaging, University of Science and Technology of China, Hefei, China

[3] Center for Quantitative Biology, Academy for Advanced Interdisciplinary Studies, Peking University, Beijing, 100871, China

[4] Center for Bioinformatics, National Laboratory of Protein Engineering and Plant Genetic Engineering, School of Life Sciences, Peking University, Beijing, 100871, China

***Caenorhabditis elegans* exhibits complex head exploratory behavior in natural environments. We quantified these movements and examined the motor circuits responsible for their intricate dynamics. Using variational mode decomposition, we distinguished between fast casts and slow bends. Slow bends backpropagate along the body, whereas fast casts show phase-specific timing and influence directional bias during forward movement. Combinatorial ablations of three types of cholinergic motor neurons, coupled with dynamical systems analysis of subsequent behaviors, revealed their distinct and overlapping roles. RMD contribute to head casts; SMD maintain bending states; SMB and SMD enable slow rhythmic bending and head-body coupling; RMD, SMD, and SMB together constitute the head central pattern generator (CPG) that drives forward locomotion. We propose a computational model with dual-timescale proprioceptive feedback to reproduce fast casts and slow bends and demonstrate how phase-specific head casts enhance roaming efficiency by optimizing movement speed. These findings highlight how different excitatory motor neurons control distinct and complementary aspects of head bending dynamics while working synergistically to maximize locomotion efficiency.**

[*] Equal contribution

Correspondence: *heng.zhang@stu.pku.edu.cn; taolt@mail.cbi.pku.edu.cn; qwen@ustc.edu.cn*

Introduction

Animals are internally motivated to engage with and learn about their surroundings. From seasonal migrations of birds to instinctual reactions of cats to novel objects, exploratory behaviors are characterized by complex and diverse sequences of actions that span a broad temporal spectrum ([1]). On a short timescale, rodents employ rapid whisker movements to gather tactile information ([2]), elephants manipulate their trunks to investigate and interact with their environment ([3]), and humans use quick eye movements to visually scan their surroundings ([4]). These behavior patterns are driven by highly adaptable sensorimotor systems that enable organisms to navigate efficiently in complex environments.

The one-millimeter long nematode *Caenorhabditis elegans* exemplifies the importance of exploration in a microscopic world. *C. elegans* navigates complex environments using biased random walks ([5]) and weathervane strategies. Moving away from attractants, it often interrupts forward movement with a 'pirouette', which involves a reversal and a large angle Ω-turn. The 'weathervane' strategy involves gradual, shallow turns in a forward run ([6]–[8]). On food, *C. elegans* also exhibits two distinct behavioral states: dwelling, characterized by local search, and roaming, where the worm covers larger areas with sustained forward movements ([9]). These strategies are believed to maximize the efficiency of finding food and resources by balancing exploration with exploitation ([10], [11]).

Much less has been characterized about the finer, short-timescale head swings that occur during these navigational processes. Most sensory neurons in *C. elegans* expose their cilia ends at the tip of the head, acting as tiny antennae. As the worm moves, each head swing translates spatial cues into a dynamic temporal code, allowing

it to make informed decisions about food, mates, and potential dangers. In particular, head swings are shaped by intricate dynamics, including fast and slow oscillations. Fast head movements, or "casts," may facilitate rapid sampling of the surroundings and inform the worm to make directional changes, while slower, rhythmic bends support sustained forward movement and body coordination over long distances. However, the mechanism and function of this duality remain elusive.

Here, by dissecting the neural circuit that controls spontaneous head movements, we show that these head swings are not only exploratory but are tightly linked to movement efficiency. The ventral-dorsal head movement in *C. elegans* is predominantly driven by three classes of cholinergic motor neurons RMD, SMD, and SMB. Specifically, the RMD class includes six neurons, while SMD and SMB each comprise four neurons (Fig. 1B). The ventral head muscles are innervated by RMDV, RMDR, SMDV, and SMBV, while the dorsal head muscles are innervated by RMDD, RMDL, SMDD, and SMBD (12–15). In particular, both RMDV and SMDV have putative inhibitory connections with their contralateral counterparts and vice versa. Although SMBV and SMBD do not connect directly, they are bridged by SAA interneurons (14, 16).

These canonical connectivity patterns, which involve reciprocal inhibition between pairs of neurons, find parallels in B-type or A-type cholinergic motor neurons that reside in the *C. elegans* ventral nerve cord and, more broadly, in many other motor systems as part of a central pattern generator (CPG) (17–20). Previous studies have shown that rhythmic motion near the head is required to entrain and establish the appropriate frequency and amplitude of body undulation during a forward run in *C. elegans* (17, 19). Consistent with this view, several works have demonstrated that SMD and SMB play important roles in klinotaxis behavior, namely, steering worm movement towards or away from food sources (21, 22). The reciprocal interactions between SMD and the major interneuron RIA can modulate head bending direction during animal navigation (23, 24). Inhibition of SMD suppresses head bending and promotes reversals (25, 26). Laser ablation of SMB and the GABAergic inhibitory motor neurons RME has revealed their roles in modulating the head bending amplitude (21, 25).

These findings raise interesting questions. If the sole goal of the head motor circuit is to generate rhythmic activity, why does the animal dedicate *three* different types of motor neurons instead of merely one? Do they each have unique roles, or do their functions overlap? Prior works have shown that these motor neurons all exhibit head-bending correlated Ca^{2+} activity (26–28). The common circuit motif suggested by the worm connectome (15) does not readily address these questions. Here, by combining experimental and computational analyses, we demonstrate that each of these three types of cholinergic motor neurons controls a distinctive aspect of head movements, and they work synergistically to generate intricate and variable dynamics that span different timescales. Our findings support a computational model with delayed mechanosensory feedback operating on two timescales. These coordinated activities optimize forward movement speed. Thus, our work sheds new light on how motor circuit complexity optimizes navigation efficiency, providing valuable insights into the dynamic interplay of neural control and movement optimization.

Results

Temporal decomposition of head movements

We recorded *C. elegans* spontaneous crawling behavior at a frame rate of ~ 90 Hz using dark-field microscopy and computed the head curvature $\kappa(t)$ during forward locomotion by averaging over the first 15% of the worm body centerline (Fig. 1A and Methods). To characterize the dynamics of complex head movements (Fig. 1C top), we applied variational mode decomposition (VMD) (29) to decompose the time-varying signal into different modes with decreasing central frequencies (Fig. 1D, E, Fig. S1A). A slower mode exhibits a higher magnitude in the power spectrum (Fig. 1E). The first mode, which entails the highest frequency (Fig. S1B), is noise. The sum of the remaining four modes (mode 2-5) is sufficient for an accurate reconstruction of head bending dynamics (Fig. 1D).

As illustrated in the spatiotemporal curvature kymograph (Fig. 1C bottom), only the slow rhythmic bending activity of the head back-propagated along the body during *C. elegans* forward locomotion (Fig. 1F). We therefore used VMD to identify the *slow dynamic mode* $\kappa_s(t)$ (e.g., mode 5) that has the highest cross-correlation with body bending activity (Fig. 1G and Methods). The sum of the remaining modes (e.g. mode 2-4) was considered a *fast dynamic mode* $\kappa_f(t)$ intrinsic to the motor activity of the head (Fig. 1D bottom).

Figure 1. Slow and fast components of head movements. A. Centerline extraction of angle measurement. **B.** Schematic of the putative head CPG circuit, consisting of SMD, RMD and SMB motor neurons. Dashed lines indicate indirect connections bridged by SAA interneurons (not shown). **C.** Representative head curvature and the corresponding kymograph of wild type N2. **D.** Variational Mode Decomposition (VMD) of the representative head curvature. The reconstructed signal is obtained by subtracting the noise mode from the original signal. Slow mode and fast mode correspond to the 5th mode and the summation of mode 2-4, respectively. **E.** Power spectral density (PSD) of each decomposed mode. **F.** Example time series of slow mode and middle body curvature (mean curvature of 45% - 60% portion of the body). **F.** Cross-correlation of slow dynamic model and middle body bending signal.

Phase-dependent head casts promote shallow turns

Head curvature is sinusoidal, with distinct dips and peaks contributing to the fast dynamic mode. These rapid and intricate movements, reminiscent of the previously studied "head casts"(26), involve head bends that propagate and terminate before the middle body. We pinpoint the location of head casts, characterized by small and rapid bidirectional changes in head curvatures (Fig. 2A shaded) (14, 26). These unique events were identified in the time derivative of head curvature, since $\dot{\kappa}(t)$ rapidly crosses zero twice, leading to a pronounced peak in the time series (Fig. 2A bottom and Methods). The larger amplitude head casts tended to propagate further along the body (Fig. S2A, B), while most had a limited propagating distance (Fig. S2C). We found that the occurrence of head casts exhibited a phase-dependent distribution (Fig. 2C and Methods) when aligned with the slow dynamic mode. Without loss of generality, we define $\phi = 0$ when the slow-mode curvature κ_s is at its maximum and $\phi = -\pi$ when κ_s is at its minimum. Consistent with Kaplan's work (26), head casts occurred with a higher probability when ϕ was in the first or third quadrant (Fig. 2C).

We sought to understand how phase-dependent head casts could influence exploratory behaviors on an extended timescale. We analyzed all head casts within three undulation cycles, using a linear regression model to predict changes in worm orientation during that period of movement (Methods). Linear regression revealed that a large amplitude head cast made a significant contribution to a change in movement direction (Fig. 2D). Importantly, these phase-dependent head casts extended the head bending duration towards one side (Fig. 2A), resulting in a ventral/dorsal bias of head bending. This led us to hypothesize that this bias might translate into changes in running direction (see example trajectory in Fig. 2B). To empirically assess this idea, we introduced a head bias index, calculated as the area under the curve $\kappa(t)$ over three undulation cycles. Our subsequent analysis confirmed that this bias index is significantly positively correlated with the change in movement orientation (Fig. 2E) as this bias can propagate along the body (Fig. S2 F). Together, our findings underscore the importance of fine head movements in guiding exploratory behavior.

Different cholinergic motor neuron classes contribute to distinct aspects of head bending dynamics

We sought to discern the roles of each type of cholinergic motor neuron in head movement using combinatorial optogenetics. With cell-specific promoters, we generated transgenic animals that allow optogenetic ablation of RMD, SMD, and SMB motor neurons either individually or in combination. We then quantified the changes in head bending dynamics $\kappa(t)$ (Fig. 3A, Fig. S3A) by calculating the power of the slow dynamic mode P_s and the fast dynamic mode P_f (Fig. 1D and Methods). Interestingly, RMD-ablated animals saw a decrease in the contribution of the fast dynamic mode to head movements, calculated by the power ratio $P_f/(P_s + P_f)$, whereas the contribution of the slow mode grew (Fig. 3B). However, SMD or SMB ablation reversed this trend, diminishing the slow-mode contribution.

In examining the factors causing the power shift, we found that RMD-ablated animals displayed a higher head bending amplitude (Fig. 3C, Methods) but a lower head-cast rate (Fig. 3D) and a lower average head-cast amplitude (Fig. 3E left). On the contrary, SMD or SMB-ablated animals had a decreased head bending amplitude (Fig. 3C) and an elevated head cast rate (Fig. 3D, Fig. S3B). The changes in these parameters aligned with the observed shifts in power dynamics. Notably, while RMD ablation left the head cast's phase dependence unaltered (Fig. 3E left), SMD or SMB ablation disrupted it, resulting in head casts distributed randomly across all phases of the slow dynamic mode (Fig. 3E middle and right).

Furthermore, in SMD- or SMB-ablated animals, the head-body coupling was disrupted. This is evident as the maximum cross-correlation between the slow dynamic mode and the body-bending activity was significantly reduced (Fig. S3C). Intriguingly, when RMD, SMD and SMB were co-ablated, the animals could not move forward, but backward movements remained unaffected (Fig. 3F). Our results suggest that continuous *C. elegans* forward locomotion requires sustained rhythmic bending activity initiated from the head motor circuit.

Phase space analysis of head bending dynamics

Next, we applied time-delay embedding to reconstruct the multidimensional phase space from the one-dimensional time series $\kappa(t)$ (Methods). According to Takens' theorem, the structure of the reconstructed phase space would be topologically equivalent to the original system. This invariance offers a geometric perspective to deepen our understanding of the intricacies of head motor circuit dynamics.

We found that the phase trajectories of head movements could be largely embedded in 3 dimensions. The phase space coordinates are a linear transformation of the time-delayed $\kappa(t)$, and thus are correlated with the head

Figure 2. Illustration of head casts and their association with gradual directional changes. A. (Top) Time series of the head bending curvature and the corresponding slow dynamic mode (depicted by blue and green dashed lines, respectively). The light red and light blue shaded regions correspond to the dorsal and ventral head casts, respectively. (Below) Time derivatives of the denoised head curvature and slow dynamic mode. **B.** Sequential snapshots of the nematode's posture at the beginning of every period of undulations revealed gradual directional changes resulting from persistent dorsal head casting (here over 3 undulation periods). **C.** The joint distribution of head casts over their stroking amplitude and the occurring phase. The phase is defined by the slow dynamic mode: 0 phase at maximum dorsal bending and π at maximum ventral bending. The color map represents the logarithm of the head cast rate. **D.** Correlation between head cast amplitudes and the directional changes in forward runs. Head casts were categorized into six coarse levels (<-6, $-6 - -3$, $-3 - 0$, $0 - 3$, $3 - 6$, >6), where negative levels represent head casts during negative curvature and vice versa. The impact of head casts at various levels was evaluated through a linear model. For each period of three undulation cycles, the resulting orientation change was recorded, and the contributions from different levels of head casts were linearly combined. Linear coefficients were calculated using least squares. To estimate the uncertainty in the coefficients, the datasets were bootstrapped 10,000 times and obtained 10,000 set of coefficients, the SD is depicted in black bars. **E.** Correlation between dorsal-ventral bending bias and the directional change in forward runs. We recorded the total orientation change and dorsoventral bending bias of the head (area under the curve) over intervals of three head bending cycles (black dots). The red line is a linear regression to measure their correlation. Pearson correlation coefficient $r = 0.49, \text{p} = 3.5 \times 10^{-7}$.

Figure 3. Ablation of different motor neuron types. A. Representative time series of head bending curvatures in head motor neuron ablated animals. **B.** Power ratio of fast dynamic mode and slow dynamic mode in N2 (n=108, 18 worms), RMD-ablated animals (n=138, 19 worms), SMD-ablated animals (n=101, 15 worms), and SMB-ablated animals (n=85, 21 worms). n represents a single episode of forward movements. **C.** Head bending amplitude in N2 and motor neuron ablated animals. **D.** Head cast frequency during each episode of forward locomotion. The frequency is defined as the number of head casts with a large relative amplitude (Methods) divided by the duration of a forward run. **E.** The joint distributions of head casts over their stroking amplitude and the occurring phase in RMD, SMD, and SMB ablated animals. **F.** Example head curvature time series (top), and whole body curvature kymogram (bottom) from a RMD, SMD, and SMB triple-ablated worm. **G.** Reversal rate increases for RMD, SMD, and SMB ablated worms in their roaming state. *p < 0.05, **p < 0.01, ***p < 0.001, ****p < 0.0001, Mann-Whitney U test.

curvature and its time derivative (Methods). We used a contour density map and its maximum intensity projection to indicate how often local regions in the phase space were visited (Fig. 4). For wild-type animals, these phase-space trajectories appear circular, indicating periodic motion (Fig. 4A1). However, the irregularity in head movements causes localized scattering, making the overall phase space resemble a doughnut when visualized using a density plot.

We explored the influence of different motor neuron types on the topological features of head dynamics by conducting single- and combinatorial ablation experiments on three types of motor neurons. This approach allowed us to observe changes in topology when head movements were governed by one or two types of motor neurons (Fig. 4). When governed predominantly by SMD (with and without RMD in Fig. 4B1 and B2, respectively), the phase space density displayed two nearly symmetrical clusters, suggesting bistable dynamics with the head in either a dorsal or ventral bending state. In head movements predominantly governed by SMB (with and without RMD in Fig. 4C1 and C2, respectively), the ring structure (in Fig. 4A1) collapsed and the phase trajectories spread almost uniformly within a disc. Here, the phase space's center, corresponding to minimal head bending velocity and amplitude, was visited more frequently than in wild-type animals. Interestingly, RMD ablation expanded the circular density distribution *without* changing its topology (Fig. 4A2), whereas SMD or SMB ablation significantly altered the topology. Together, SMD and SMB enable rhythmic head bending together, while RMD neurons aid in fast head casts during the main oscillation.

Figure 4. Exploratory head dynamics in an embedding phase space. Each animal's head curvature time series during forward locomotion was embedded into a high-dimensional space with automatically estimated dimensions and delays. The trajectories were then projected onto three principal components, forming a 3D embedding space. Different motor neuron dominance led to varied phase space density features. Gray ellipses represent ablated motor neuron types. The second row shows figures with RMD ablated, and the second and third columns with SMB and SMD ablated. Topological features vary significantly across columns but show similarities between rows, reflecting dynamic characteristics: **A1-A2.** SMD-SMB dominated control show a doughnut-like density, similar to limit cycle dynamics. **B1-B2.** Worms with SMB ablated and SMD-dominated bending exhibit two symmetric density clusters, indicating bistable dynamics. **C1-C2.** SMB-dominant control display a uniform disk-like density, indicating chaotic head bending.

Head casts enhance kinematic efficiency

For long-distance exploration, *C. elegans* must maintain an efficient crawling posture. Previous studies (30, 31) suggested that the angle of attack of crawling worms is close to an optimal value for maximum locomotion speed. Here, we provide a theoretical derivation considering the wavelength correction under large amplitude. Our derivation is based on linear resistive force theory, which effectively and accurately links the body posture kinematics to locomotion (32–35). The theory shows that the locomotion velocity is given by (Methods)

$$V = \frac{\frac{C_N}{C_L} - 1}{\frac{C_N}{C_L} + \frac{2}{\tan^2(A_a)}} f \lambda_x(b, k), \tag{1}$$

where C_N is the frictional drag coefficient normal to the body centerline, C_L is the one parallel to it, and f is the undulation frequency. λ_x is the effective wavelength along the movement direction: it decreases as the wave number k, the wave amplitude b, and the angle of attack A_a increase. Eq. (1) shows a small angle of attack increases the slip rate, the ratio between the wave velocity $f\lambda_x$ and the locomotion velocity V, while a large angle reduces the effective wavelength. Both extremes negatively impact speed. Consequently, for a given wave number, there is an optimal angle of attack that maximizes the *kinematic efficiency*, defined as V/f. This efficiency measures the distance traveled per undulation cycle and is independent of the undulation frequency (Fig. 5B). Our analysis showed that RMD-ablated animals displayed an increase in head and body curvature (Fig. 5A bottom, C) and the angle of attack (Fig. 5D top), along with a decrease in locomotion velocity and kinematic efficiency (Fig. 5D middle and bottom).

Given the worm's ability to bend into large curvatures, how does the neural circuit control the amplitude for efficient crawling? What is the optimal head muscle control signal? To this end, we assume that the head neural circuit produces a binary input signal, alternating between dorsal and ventral head muscle activation. We simulated head bending in response to control signals based on a realistic mechanic model and propagated this bending along the body (Methods, (33, 36)). We integrated fast switches in a slow periodic input signal and optimized the pattern to maximize crawling speed. The optimal head curvature resembles the observed phase-specific head casts nested in a slow oscillation (Fig. 5E). These simulated head casts reduced both head bending amplitude and overall body curvature (Fig. 5F) as the bends propagated backward. This optimized movement pattern increased locomotion velocity by 14%, consistent with our theoretical predictions. Reversing the phase of the fast switches (Fig. S5D) led to larger head bending, similar body bending curvatures (Fig. S5E) and a slight decrease in velocity. Thus, our optimization method clarifies how head casts improve locomotion efficiency and partially explain their timing. The head motor circuit is likely to impose additional constraints that affect the phase dependency of head casts.

The head cast strategy boosts speed by lowering the average angle of attack at frequencies below 0.5 Hz and aligns with the baseline square-wave input above 0.5 Hz (Fig. 5G,H). Our model thus predicts that when the head oscillation becomes sufficiently fast, head cast will vanish, which agrees with a previous finding (26). Furthermore, our model predicts that the use of the head-cast reduces muscle energy expenditure due to a decrease in overall curvature (Fig. S5F). Together, our results suggest that by optimizing head muscle input in our neuromechanical model, phase-specific head casts effectively control crawling posture, maximizing locomotion velocity and minimizing energy use during exploration.

A bend-sensitive feedback model captures slow and fast dynamics

We asked whether the observed fast and slow head-bending activity could be reproduced by a minimal model that is consistent with known anatomical and functional data. Our ablation experiments demonstrated the synergistic role of SMD and SMB as a core oscillator and the role of RMD in the generation of head casts. Direct or indirect cross-inhibition between contralateral SMD/SMB neurons, as well as our ablation studies, suggest bistable switches in the slow oscillator. We modeled SMDD and SMBD as one dorsal unit and SMDV and SMBV as one ventral unit (Fig. 6A left), activating dorsal and ventral muscles, respectively. Both units exhibit bistable dynamics, modeled as the hysteresis curve (Fig. 6A right). SMD and SMB, with posterior sublateral processes, are hypothesized to sense posterior curvature. Thus, our model includes proprioceptive feedback from neck bending to the core oscillator, acting as a slow integration of head curvature, captured by K^{slow} (Fig. 6A left, Methods).

On the fast timescale, RMDD/L and RMDV/R motor neurons activate dorsal and ventral muscles respectively, operating in a bistable state according to electrophysiological measurements (40). As upstream mechanosensitive neurons (e.g., URY, IL1, OLQ, and CEP) may sense head pressure (14, 41, 42), we hypothesize that RMD receive rapid feedback from head curvature, captured by K^{fast}, toggling neural activity on and off (Fig. 6A bottom). Our

Figure 5. Locomotion Efficiency. A. Angle of attack refers to the average angle between the body and the moving direction (top). N2 (middle) and RMD ablated worms (bottom) have different postures during forward locomotion. **B**. The non-monotonic relationship between kinematic efficiency and angle of attack indicates an optimal angle of attack exists for maximum locomotion efficiency. $C_N/C_L = 10$ following recent estimations on agar surface (37–39). **C**. Optogenetic ablation of RMD neurons increased overall body curvature. **D**. RMD-ablated worms (n=138, 19 worms) showed an increased angle of attack in radian (top, p $= 7.5 \times 10^{-4}$), a decreased crawling speed (middle, p $= 7.1 \times 10^{-4}$), and a decreased kinematic efficiency (bottom, p $= 8.9 \times 10^{-3}$) compared to N2 (n=108, 18 worms), Mann-Whitney U test. **E**. Comparison of baseline and optimized head muscle input (inset, dashed box) and resulting head curvature. The head input period is fixed at 2.4 s. **F**. Body curvature along the worm's length showed an overall decrease, following the optimized head input from **D**. **G-H**. Locomotion efficiency and angle of attack under baseline and optimized head input across various undulation frequency.

model thus includes two parallel neuronal groups and a dual feedback system that integrates head curvature over two distinct timescales.

When the head bends dorsally (positive curvature, Fig. 6B, t_1), fast feedback follows the head curvature and activates the RMDV/R neurons at the threshold θ_1 (at t_2 in Fig. 6B), producing opposite muscle torque and reducing head curvature. The fast feedback signal then drops below θ_1, turning off the RMDV/R neurons (at t_3 in Fig. 6B). However, the input to the dorsal muscles from the core oscillator persists, increasing the dorsal bending. Therefore, fast negative feedback could generate phase-specific head casts. The activity of the core oscillator is regulated by a low-pass filter of the head curvature K^{slow} that mimics the neck movement. Indeed, the observed phase lag between head and neck curvature in real animals closely matches the lag between head curvature and surrogate posterior curvature in our model (Fig. 6C,D, Methods). Sustained bending enhances this negative feedback, changing the neuronal state from dorsal to ventral activation (at t_4 in Fig. 6B) and producing the slow dynamic mode. Ablating RMD neurons in simulations by removing fast negative feedback showed a similar increase in bending amplitude as seen in experiments (Fig. 6B, Fig. 3A).

A key prediction of the model is that the feedback originating from neck bending plays a key role in defining the slow dynamic mode. To test this, we reduced the neck curvature by optogenetically inhibiting the neck muscles. Upon inhibition, the head bent to one side for a long time, significantly increasing the duration on both sides (Fig. 6E,F). This observation can be captured by our model: reducing the amplitude of the slow feedback signal led to a longer accumulation, and thus extended the period of the slow oscillator (Fig. 6G), consistent with the persistent head bending state observed in the experiments.

Discussion

Bilaterians have thrived evolutionarily because their bilaterally symmetrical body plan enables advanced directed movement. This movement involves efficient forward propulsion and controlled turning, with head movement being a key to both maintaining forward speed and steering in animals such as fish (43) and snake (44). Here, we quantitatively analyzed head movements in *C. elegans* during spontaneous roaming behavior using high-speed imaging. We detailed intricate head dynamics by decomposing head curvature into slow and fast modes. A global metric, the power ratio between the fast mode and the slow mode, was introduced to measure the irregularity of head movement. Within the fast mode, we identified stereotypical head-cast events, first reported by Kaplan (26). These rapid head movements propagate posteriorly along the body for a limited distance, and this observation remains consistent despite the difference in the parameters used to define the spatial extent of head curvature between the previous work (26) and ours (Fig. S2E and C).

A significant correlation between head casts and worm reorientation, along with a causal relationship between dorsal-ventral bending biases in the head and the middle body where head bends propagate, links intricate head movements with the worm's overall turning behavior. Prior research has shown that the curved paths during weathervane behavior stem from asymmetric dorso-ventral modulation of head bending (45). Theoretical and empirical studies suggest that this occurs through differential gain modulation of contralateral head motor neurons in response to a chemical gradient (22, 46, 47). We propose head casting as an additional navigation mechanism, achieved by a dorso-ventrally asymmetric number of head casts. Adjusting head cast timing and amplitude could lead to new navigation strategies. Future research should confirm the role of head casting in reorientation amid sensory signal gradients.

The head is crucial for leading forward movement, with its undulation necessary for coordinating body waves and propulsion. Head and body movements are closely coupled, largely through directional proprioceptive coupling (36), resulting in a strong correlation of amplitude and entrainment of the undulation frequency (17, 19). Here we demonstrated that RMD, SMD and SMB constitute the major component of the head CPG. When all three motor neuron types were ablated, *C. elegans* could not propel itself to move forward. Furthermore, using a computational model, we discovered that control signals for head casts emerged from optimizing movement velocity by tuning the overall bending amplitude close to an optimal value. This explains the ubiquity of head casts in the locomotion of *C. elegans*: they rely on this strategy to dynamically adjust their posture, keeping it optimized for efficient long-distance exploration.

We sought to understand the neural basis of flexible head movements. Single and combinatorial motor neuron ablations allowed us to define the functional roles of three types of cholinergic motor neurons, RMD, SMB, and SMD. Ablation of RMD led to more regular head oscillations, whereas ablation of SMD or SMB destabilized head

Figure 6. A circuit model captures the fast and slow dynamic modes. A. Schematic of the model circuit and the bistable dynamics of its elements. SMD and SMB motor neurons on the same side operate as one functional unit and receive a slow integration of the head curvature K^{slow} as feedback. The mutually inhibiting dorsal-ventral units were posited to operate in a bistable regime and have a hysteresis curve in the input-voltage relation (upper right). RMDD/L and RMDV/R activate the dorsal and ventral muscles, respectively. Their activation levels are switched by a fast integation of head curvature (bottom right). **B.** Representative trajectories of head curvature, fast feedback, and slow feedback. Dashed lines indicate the four different circuit states: t_1: Dorsal SMD-SMB unitactivated. t_2: The fast curvature feedback activated RMDV/R, generating an opposite muscle torque. t_3: decreased fast feedback shut RMDV/R down. t_4: slow curvature feedback switches the core oscillator to ventral outputting. Shaded area simulated RMD inhibition which showed increased head bending amplitude due to lack of fast feedback. **C.** Representative head (0-15% body length) and neck (15%-30% body length) curvature from wild-type animals. **D.** Histogram of time lag between head and neck curvature in N2 worms (n=108, 18 worms); The mean time lag was 0.16 undulation period. The time lag between head curvature and surrogate posterior curvature in the model is 0.15 period. **E.** Representative head curvature during optogenetic neck inhibition. Illumination (shaded area) induces extended bending toward both sides. **F.** Significant increase in time spent bending toward both sides during neck inhibition. $p = 1.1 \times 10^{-5}$, Mann-Whitney U test. **G.** Simulated neck inhibition (shaded area).

oscillations. Time-delay embedding analysis further confirmed that SMD and SMB neurons collectively contribute to robust, limit-cycle-like, slow head movement dynamics, while RMD influences head casts without altering the topology of the dynamics. Previous work (26) emphasized the role of SMD neurons in orchestrating phase-nested head casting. In our experiment, SMD inhibition suppressed the overall head/neck bending (Fig. S6A,B) and increased the contribution of the fast mode to the head bending power (Fig. S6C). This discrepancy likely arises from the different levels of SMD inhibition: acute optogenetic inhibition of SMD through exogenous expression of the light-gated chloride channel (GtACR2) could severely disrupt the SMD-SMB oscillation, while continuous inhibition with a histamine chloride channel (26) may only slightly reduce muscle output.

In conclusion, here we proposed a model for *C. elegans* exploratory head movements, where slow and fast dynamic modes emerge from the interplay between dual-timescale negative proprioceptive feedback and the bistable dynamics of the circuit components. Fast feedback to the RMD neurons likely comes from putative mechanosensitive neurons, such as URY, IL1, OLQ, and CEP (14, 41, 42). Individual RMD neurons have a bistable membrane potential (40), a mode that allows nonlinear responses to mechanosensitive inputs. The neck and body act as low-pass filters, delaying and smoothing head movement. The posterior sublateral extensions of SMD and SMB neurons could act as stretch receptors, detecting the posterior curvature and providing slow feedback. This circuit modulates the bistable state transitions of the core oscillator to generate a slow dynamic mode. Together, rapid local feedback, delayed slow feedback, and neural input-output nonlinearity shape the dual oscillatory head movements and work collectively to optimize locomotion efficiency.

ACKNOWLEDGEMENTS
The authors appreciate helpful discussions with Dmitri Chklovskii, Shangbang Gao, Yuichi Iino, Manuel Zimmer, and Mei Zhen. PL, HZ, YS, JW, LT and QW were partially supported by the Natural Science Foundation China through Major International (Regional) Joint Research Project (32020103007).

Reference

1. Tinbergen, N. *The Study of Instinct*. The Study of Instinct. Clarendon Press/Oxford University Press, New York, NY, US, 1951.
2. Xu, N. L., Harnett, M. T., Williams, S. R., Huber, D., O'Connor, D. H., Svoboda, K., and Magee, J. C. Nonlinear dendritic integration of sensory and motor input during an active sensing task. *Nature*, 492(7428):247–51, 2012. doi: 10.1038/nature11601. Xu, Ning-long Harnett, Mark T Williams, Stephen R Huber, Daniel O'Connor, Daniel H Svoboda, Karel Magee, Jeffrey C eng Howard Hughes Medical Institute/ Research Support, Non-U.S. Gov't England 2012/11/13 Nature. 2012 Dec 13;492(7428):247-51. doi: 10.1038/nature11601. Epub 2012 Nov 11.
3. Dagenais, P., Hensman, S., Haechler, V., and Milinkovitch, M. C. Elephants evolved strategies reducing the biomechanical complexity of their trunk. *Curr Biol*, 31(21):4727–4737 e4, 2021. doi: 10.1016/j.cub.2021.08.029. Dagenais, Paule Hensman, Sean Haechler, Valerie Milinkovitch, Michel C eng Research Support, Non-U.S. Gov't Video-Audio Media England 2021/08/25 Curr Biol. 2021 Nov 8;31(21):4727-4737.e4. doi: 10.1016/j.cub.2021.08.029. Epub 2021 Aug 23.
4. Zhu, S., Lakshminarasimhan, K. J., Arfaei, N., and Angelaki, D. E. Eye movements reveal spatiotemporal dynamics of visually-informed planning in navigation. *eLife*, 11:e73097, may 2022. doi: 10.7554/eLife.73097.
5. Berg, H. C. *Random walks in biology*. Princeton University Press, Princeton, N.J., expanded edition, 1993. ISBN 0691000646 (pbk.).
6. Pierce-Shimomura, J. T., Morse, T. M., and Lockery, S. R. The Fundamental Role of Pirouettes in *Caenorhabditis elegans* Chemotaxis. *The Journal of Neuroscience*, 19(21):9557–9569, Nov. 1999. doi: 10.1523/JNEUROSCI.19-21-09557.1999.
7. Iino, Y. and Yoshida, K. Parallel Use of Two Behavioral Mechanisms for Chemotaxis in *Caenorhabditis elegans*. *The Journal of Neuroscience*, 29(17):5370–5380, Apr. 2009. doi: 10.1523/JNEUROSCI.3633-08.2009.
8. Stephens, G. J., Johnson-Kerner, B., Bialek, W., and Ryu, W. S. From Modes to Movement in the Behavior of Caenorhabditis elegans. *PLoS ONE*, 5(11):e13914, Nov. 2010. doi: 10.1371/journal.pone.0013914.
9. Flavell, S. W., Pokala, N., Macosko, E. Z., Albrecht, D. R., Larsch, J., and Bargmann, C. I. Serotonin and the neuropeptide PDF initiate and extend opposing behavioral states in C. elegans. *Cell*, 154(5):1023–1035, Aug. 2013. doi: 10.1016/j.cell.2013.08.001.
10. Vergassola, M., Villermaux, E., and Shraiman, B. I. 'Infotaxis' as a strategy for searching without gradients. *Nature*, 445(7126):406–409, Jan. 2007. doi: 10.1038/nature05464.
11. Calhoun, A. J., Chalasani, S. H., and Sharpee, T. O. Maximally informative foraging by Caenorhabditis elegans. *eLife*, 3: e04220, Dec. 2014. doi: 10.7554/eLife.04220.
12. White, J., Southgate, E., Thomson, J. N., and Brenner, S. The structure of the nervous system of the nematode *Caenorhabditis elegans*. *Philosophical Transactions of the Royal Society of London. B, Biological Sciences*, 314(1165): 1–340, Nov. 1986. doi: 10.1098/rstb.1986.0056.
13. Cook, S. J., Jarrell, T. A., Brittin, C. A., Wang, Y., Bloniarz, A. E., Yakovlev, M. A., Nguyen, K. C. Q., Tang, L. T. H., Bayer, E. A., Duerr, J. S., Bülow, H. E., Hobert, O., Hall, D. H., and Emmons, S. W. Whole-animal connectomes of both caenorhabditis elegans sexes. *Nature*, 571(7763):63–71, 2019. doi: 10.1038/s41586-019-1352-7.
14. White, J. Clues to basis of exploratory behaviour of the *C. elegans* snout from head somatotropy. *Philosophical Transactions of the Royal Society B: Biological Sciences*, 373(1758):20170367, Oct. 2018. doi: 10.1098/rstb.2017.0367.

15. Witvliet, D., Mulcahy, B., Mitchell, J. K., Meirovitch, Y., Berger, D. R., Wu, Y., Liu, Y., Koh, W. X., Parvathala, R., Holmyard, D., Schalek, R. L., Shavit, N., Chisholm, A. D., Lichtman, J. W., Samuel, A. D. T., and Zhen, M. Connectomes across development reveal principles of brain maturation. *Nature*, 596(7871):257–261, Aug. 2021. doi: 10.1038/s41586-021-03778-8.

16. Huo, J., Xu, T., Liu, Q., Polat, M., Kumar, S., Zhang, X., Leifer, A. M., and Wen, Q. Hierarchical behavior control by a single class of interneurons. *Proc Natl Acad Sci U S A*, 121(47):e2410789121, 2024. doi: 10.1073/pnas.2410789121.

17. Xu, T., Huo, J., Shao, S., Po, M., Kawano, T., Lu, Y., Wu, M., Zhen, M., and Wen, Q. Descending pathway facilitates undulatory wave propagation in *Caenorhabditis elegans* through gap junctions. *Proceedings of the National Academy of Sciences*, 115(19):E4493–E4502, May 2018. doi: 10.1073/pnas.1717022115.

18. Gao, S., Guan, S. A., Fouad, A. D., Meng, J., Kawano, T., Huang, Y.-C., Li, Y., Alcaire, S., Hung, W., Lu, Y., Qi, Y. B., Jin, Y., Alkema, M., Fang-Yen, C., and Zhen, M. Excitatory motor neurons are local oscillators for backward locomotion. *eLife*, 7: e29915, Jan. 2018. doi: 10.7554/eLife.29915. Publisher: eLife Sciences Publications, Ltd.

19. Fouad, A. D., Teng, S., Mark, J. R., Liu, A., Alvarez-Illera, P., Ji, H., Du, A., Bhirgoo, P. D., Cornblath, E., Guan, S. A., and Fang-Yen, C. Distributed rhythm generators underlie Caenorhabditis elegans forward locomotion. *eLife*, 7:e29913, Jan. 2018. doi: 10.7554/eLife.29913.

20. Marder, E., Bucher, D., Schulz, D. J., and Taylor, A. L. Invertebrate Central Pattern Generation Moves along. *Current Biology*, 15(17):R685–R699, Sept. 2005. doi: 10.1016/j.cub.2005.08.022.

21. Gray, J. M., Hill, J. J., and Bargmann, C. I. A circuit for navigation in *Caenorhabditis elegans*. *Proceedings of the National Academy of Sciences*, 102(9):3184–3191, Mar. 2005. doi: 10.1073/pnas.0409009101.

22. Kocabas, A., Shen, C.-H., Guo, Z. V., and Ramanathan, S. Controlling interneuron activity in Caenorhabditis elegans to evoke chemotactic behaviour. *Nature*, 490(7419):273–277, Oct. 2012. doi: 10.1038/nature11431.

23. Hendricks, M., Ha, H., Maffey, N., and Zhang, Y. Compartmentalized calcium dynamics in a C. elegans interneuron encode head movement. *Nature*, 487(7405):99–103, July 2012. doi: 10.1038/nature11081.

24. Ouellette, M.-H., Desrochers, M. J., Gheta, I., Ramos, R., and Hendricks, M. A Gate-and-Switch Model for Head Orientation Behaviors in *Caenorhabditis elegans*. *eneuro*, 5(6):ENEURO.0121–18.2018, Nov. 2018. doi: 10.1523/ENEURO.0121-18.2018.

25. Shen, Y., Wen, Q., Liu, H., Zhong, C., Qin, Y., Harris, G., Kawano, T., Wu, M., Xu, T., Samuel, A. D., and Zhang, Y. An extrasynaptic GABAergic signal modulates a pattern of forward movement in Caenorhabditis elegans. *eLife*, 5:e14197, May 2016. doi: 10.7554/eLife.14197. Publisher: eLife Sciences Publications, Ltd.

26. Kaplan, H. S., Salazar Thula, O., Khoss, N., and Zimmer, M. Nested Neuronal Dynamics Orchestrate a Behavioral Hierarchy across Timescales. *Neuron*, 105(3):562–576.e9, Feb. 2020. doi: 10.1016/j.neuron.2019.10.037.

27. Matsumoto, A., Toyoshima, Y., Zhang, C., Isozaki, A., Goda, K., and Iino, Y. Neuronal sensorimotor integration guiding salt concentration navigation in caenorhabditis elegans. *Proc Natl Acad Sci U S A*, 121(5):e2310735121, 2024. doi: 10.1073/pnas.2310735121.

28. Kramer, T. S., Wan, F. K., Pugliese, S. M., Atanas, A. A., Hiser, A. W., Luo, J., Bueno, E., and Flavell, S. W. Neural sequences underlying directed turning in c. elegans. *bioRxiv*, 2024. doi: 10.1101/2024.08.11.607076.

29. Dragomiretskiy, K. and Zosso, D. Variational Mode Decomposition. *IEEE Transactions on Signal Processing*, 62(3):531–544, Feb. 2014. doi: 10.1109/TSP.2013.2288675.

30. Gray, J. and HANCOCKf, G. J. THE PROPULSION OF SEA-URCHIN SPERMATOZOA. page 13.

31. Fang-Yen, C., Wyart, M., Xie, J., Kawai, R., Kodger, T., Chen, S., Wen, Q., and Samuel, A. D. T. Biomechanical analysis of gait adaptation in the nematode Caenorhabditis elegans. *Proceedings of the National Academy of Sciences*, 107(47): 20323–20328, Nov. 2010. doi: 10.1073/pnas.1003016107.

32. Johnson, R. and Brokaw, C. Flagellar hydrodynamics. A comparison between resistive-force theory and slender-body theory. *Biophysical Journal*, 25(1):113–127, Jan. 1979. doi: 10.1016/S0006-3495(79)85281-9.

33. Boyle, J. H., Berri, S., and Cohen, N. Gait Modulation in C. elegans: An Integrated Neuromechanical Model. *Frontiers in Computational Neuroscience*, 6, 2012. doi: 10.3389/fncom.2012.00010.

34. Keaveny, E. E. and Brown, A. E. X. Predicting path from undulations for *C. elegans* using linear and nonlinear resistive force theory. 14(2):025001. doi: 10.1088/1478-3975/aa5ce6.

35. Costa, A. C., Ahamed, T., Jordan, D., and Stephens, G. J. A markovian dynamics for *Caenorhabditis elegans* behavior across scales. 121(32):e2318805121. doi: 10.1073/pnas.2318805121.

36. Wen, Q., Po, M. D., Hulme, E., Chen, S., Liu, X., Kwok, S. W., Gershow, M., Leifer, A., Butler, V., Fang-Yen, C., Kawano, T., Schafer, W., Whitesides, G., Wyart, M., Chklovskii, D., Zhen, M., and Samuel, A. Proprioceptive Coupling within Motor Neurons Drives C. elegans Forward Locomotion. *Neuron*, 76(4):750–761, Nov. 2012. doi: 10.1016/j.neuron.2012.08.039.

37. Karbowski, J., Schindelman, G., Cronin, C. J., Seah, A., and Sternberg, P. W. Systems level circuit model of C. elegans undulatory locomotion: mathematical modeling and molecular genetics. *Journal of Computational Neuroscience*, 24(3): 253–276, June 2008. doi: 10.1007/s10827-007-0054-6.

38. Shen, X., Sznitman, J., Krajacic, P., Lamitina, T., and Arratia, P. Undulatory Locomotion of Caenorhabditis elegans on Wet Surfaces. *Biophysical Journal*, 102(12):2772–2781, June 2012. doi: 10.1016/j.bpj.2012.05.012.

39. Rabets, Y., Backholm, M., Dalnoki-Veress, K., and Ryu, W. S. Direct Measurements of Drag Forces in C. elegans Crawling Locomotion. *Biophysical Journal*, 107(8):1980–1987, Oct. 2014. doi: 10.1016/j.bpj.2014.09.006.

40. Mellem, J. E., Brockie, P. J., Madsen, D. M., and Maricq, A. V. Action potentials contribute to neuronal signaling in C. elegans. *Nature Neuroscience*, 11(8):865–867, Aug. 2008. doi: 10.1038/nn.2131.

41. Hart, A. C., Sims, S., and Kaplan, J. M. Synaptic code for sensory modalities revealed by C. elegans GLR-1 glutamate receptor. *Nature*, 378(6552):82–85, Nov. 1995. doi: 10.1038/378082a0.

42. Kindt, K. S., Viswanath, V., Macpherson, L., Quast, K., Hu, H., Patapoutian, A., and Schafer, W. R. Caenorhabditis elegans TRPA-1 functions in mechanosensation. *Nature Neuroscience*, 10(5):568–577, May 2007. doi: 10.1038/nn1886.

43. Akanyeti, O., Thornycroft, P., Lauder, G., Yanagitsuru, Y., Peterson, A., and Liao, J. Fish optimize sensing and respiration during undulatory swimming. *Nature Communications*, 7:11044, 03 2016. doi: 10.1038/ncomms11044.

44. Tingle, J. L., Garner, K. L., and Astley, H. C. Functional diversity of snake locomotor behaviors: A review of the biological literature for bioinspiration. *Annals of the New York Academy of Sciences*, 1533(1):16–37, 2024. doi: https://doi.org/10.

413 1111/nyas.15109.

45. Kim, D., Park, S., Mahadevan, L., and Shin, J. H. The shallow turn of a worm. *Journal of Experimental Biology*, 214(9): 1554–1559, May 2011. doi: 10.1242/jeb.052092.

46. Soh, Z., Sakamoto, K., Suzuki, M., Iino, Y., and Tsuji, T. A computational model of internal representations of chemical gradients in environments for chemotaxis of Caenorhabditis elegans. *Scientific Reports*, 8(1):17190, Nov. 2018. doi: 10.1038/s41598-018-35157-1.

47. Lockery, S. R. The computational worm: spatial orientation and its neuronal basis in C. elegans. *Current Opinion in Neurobiology*, 21(5):782–790, Oct. 2011. doi: 10.1016/j.conb.2011.06.009.

48. Brenner, S. The genetics of caenorhabditis elegans. *Genetics*, 77(1):71–94, 1974.

49. Qi, Y. B., Garren, E. J., Shu, X., Tsien, R. Y., and Jin, Y. Photo-inducible cell ablation in caenorhabditis elegans using the genetically encoded singlet oxygen generating protein minisog. *Proceedings of the National Academy of Sciences*, 109(19): 7499–7504, 2012.

50. Xu, S. and Chisholm, A. D. Highly efficient optogenetic cell ablation in c. elegans using membrane-targeted minisog. *Scientific reports*, 6(1):21271, 2016.

51. Leifer, A. M., Fang-Yen, C., Gershow, M., Alkema, M. J., and Samuel, A. D. Optogenetic manipulation of neural activity in freely moving caenorhabditis elegans. *Nature methods*, 8(2):147–152, 2011.

52. Takens, F. Detecting strange attractors in turbulence. In Rand, D. and Young, L.-S., editors, *Dynamical Systems and Turbulence, Warwick 1980*, pages 366–381, Berlin, Heidelberg, 1981. Springer Berlin Heidelberg. ISBN 978-3-540-38945-3.

53. Fraser, A. M. and Swinney, H. L. Independent coordinates for strange attractors from mutual information. *Phys. Rev. A*, 33: 1134–1140, Feb 1986. doi: 10.1103/PhysRevA.33.1134.

54. Rhodes, C. and Morari, M. False-nearest-neighbors algorithm and noise-corrupted time series. *Phys. Rev. E*, 55:6162–6170, May 1997. doi: 10.1103/PhysRevE.55.6162.

55. Ji, H., Fouad, A. D., Teng, S., Liu, A., Alvarez-Illera, P., Yao, B., Li, Z., and Fang-Yen, C. Phase response analyses support a relaxation oscillator model of locomotor rhythm generation in Caenorhabditis elegans. *eLife*, 10:e69905, Sept. 2021. doi: 10.7554/eLife.69905.

Methods

C. elegans strains

C. elegans strains were cultivated by standard procedures (48). Transgenic worms in optogenetic experiments were cultivated in the dark on NGM plates with OP50 bacteria and all-trans-retinal (ATR) for over 8 hr. We used young adult hermaphrodites to carry out all the experiments.

Molecular biology

We used standard molecular biology methods. Promoters P*rig-5a* (2.2 kb), P*flp-22p-Δ4* (1.5 kb), and P*odr-2* were amplified by PCR from the N2 genome.

Behaviour recording

We recorded *C. elegans* behaviours on 0.8% (wt/vol) M9 agar plate. Before recording, the worms were first transferred to a sterile NGM plate to eliminate the OP50 bacteria, then transferred to another sterile NGM plate for 25-35 min to make more frequent forward movements. The worms also acclimatized to the M9 agar for 2-3 min. Then we recorded freely moving worms for 5-15 min. Under dark field infrared illumination, the worms were automatically tracked and retained within the field of view of a 10 × objective on a Nikon inverted microscope (Ti-U, Japan). Behaviors were recorded by a Basler CMOS camera (aca2000-340kmNIR, Germany). We used MATLAB custom software (MathWorks, Inc Natick, MA, USA) to process the behavioral data afterwards.

Optogenetic ablation

We used a mitochondrial-targeted miniSOG (TOMM20-miniSOG) (49) or a membrane-targeted miniSOG (PH-miniSOG) (50) to ablate specific neurons in *C. elegans*. Late L4/early young adult transgenic worms were transferred to an unseeded NGM plate, on which the worms were restricted by a 1 cm diameter filter paper ring soaked with 100 μM $CuCl_2$. The worms were then illuminated for 5 min using pulse blue LED (M470L3-C5; Thorlabs) light (0.5 s on and 0.5 s off) at an intensity of 2.0 mW/mm^2. After illumination, worms were transplanted to an OP50-seeded NGM plate and recovered over 4hrs before behaviour recording.

Optogenetics

Lasers and a digital micromirror device (DLI4130 0.7 XGA, Digital Light Innovations, TX, USA) were used to generate spatiotemporal optogenetic manipulations (51) at a specific wavelength (473 nm, 561 nm or 635 nm). We manipulated the activities of neurons through light-activated channels (GtACR2, Arch, or Chrimson). Each worm was stimulated 5–8 times with at least a 40-second inter-stimulus interval.

Behavioural analysis

We exclusively analyzed the forward movement. Forward-moving frames were manually labeled and further processed in MATLAB to quantify parameters. Forward movement was identified when the trajectory of a worm remained straight or turned no less than 90 degrees.

The worm orientation is the average angle between the x-axis of the camera frame and the 100 centerline segments. To quantify orientation changes during forward movement, the following steps were executed: 1. The curvature vectors of the centerlines were projected onto the first two principal components, producing two-dimensional postural representations denoted as $a_1(t)$ and $a_2(t)$. 2. The phase of forward movement (Φ) was computed with $\Phi = \text{angle}(a_1 + i \cdot a_2)$, with zero phase instances occurring when a_1 is at its maximum and a_2 is zero. 3. Orientation changes were measured between zero-phase moments separated by three cycles.

Statistical test

Statistical tests were indicated in the figure legends, including methods, error bars, numbers of trials and animals, and p-values. Using MATLAB, we applied the Mann-Whitney U test to determine the significance of the difference between the groups, and all multiple comparisons were adjusted using the Bonferroni correction.

Kinematic analysis of head movements

We used custom-written MATLAB scripts to extract the timestamp, stage position and the centerline of a worm. The centerline of the worm was first divided into $N = 100$ segments and the orientation of each segment, $\theta(s)$, $s = 1, 2, \cdots, N$, was calculated. The curvature $K(s) = \Delta\theta(s)/\Delta s$ was calculated and then normalized into a dimensionless unit $K \cdot L$, where L is the body length. And the dimensionless head curvature κ was calculated as

$$\kappa = \frac{1}{50} \sum_{j=0}^{4} \sum_{i=1}^{10} K(i+j) \cdot L \qquad (2)$$

The head bending amplitude of each forward run episode was calculated using the following procedure: 1. A reference amplitude was introduced as $A_{\text{ref}} = (\kappa(t)^{\text{Max}} - \kappa(t)^{\text{Min}})/2$. 2. Using the scipy.signal package, we detected peaks in the curvature time series that exceeded the reference amplitude A_{ref} in prominence. These peaks correspond to maximum head-bending positions. The final amplitude was computed as the median of the absolute values of these identified peaks. The neck curvature is defined as the average curvature of the anterior 15%-30% region of the body and is calculated in the same way as the head curvature.

Head-cast analysis

The rapid oscillation superimposed on the slow dynamic mode can sometimes move backward along the anterior body, a phenomenon known as the "head cast" (26). We extend this term to include smaller and rapid wiggles restricted to the very front part of the head.

Head-casts notably move opposite to the slow dynamic mode, identified in this study via a two-step process:

1. We identified zero-crossing points in the time derivative of a denoised head curvature time series $\dot{\kappa}(t)$, where $\kappa(t) = \kappa^s(t) + \kappa^f(t)$.

2. We distinguished these time points: zero crossings where the time derivatives of the denoised signal and the slow dynamic mode have opposite signs ($\text{sign}(\dot{\kappa}) = -\text{sign}(\dot{\kappa^s})$) mark the start of a head cast. The next zero-crossing point is designated as the end of a head cast, after which $\text{sign}(\dot{\kappa}) = \text{sign}(\dot{\kappa^s})$.

The head-cast amplitude was measured as the absolute difference in head curvature between the start and end points. The relative amplitude, the ratio of absolute amplitude to head bending magnitude of the forward run, was used to identify significant head casts with relative amplitudes greater than 0.3, thus reducing the noise of curvature measurement. The occurrence rate was calculated as the number of significant head casts per episode divided by its duration.

We defined the phase of head bending using the slow dynamic mode, given its sinusoidal nature. Specifically, we used the instantaneous phase resulting from its Hilbert transform.

Variational mode decomposition

We use the variational mode decomposition, abbreviated as VMD(29), to distinguish the fast and slow components of head bending dynamics. The head curvature signal was decomposed into five different intrinsic mode functions $(\kappa_i, \ i=1,2,3,4,5)$ with decreasing central frequencies. The first mode κ_1, which has the highest frequency, corresponds to the noise. The remaining four modes can reconstruct the fast and slow dynamics of head bending: a fast dynamic mode $\kappa_f(t)$ is reconstructed by a linear combination of the modes 2-4, and a slow dynamic mode $\kappa_s(t)$ is identified by the mode 5.

The power of each mode P_i was calculated as $P_i = \int_0^\infty p_i \mathrm{d}f$, $i = 1, 2, 3, 4, 5$, where p_i is the power spectrum density of mode i. Then the power of the fast dynamic mode was calculated as $P_f = P_2 + P_3 + P_4$ while the power of the slow dynamic mode was calculated as $P_s = P_5$. Subsequently, the power ratio was calculated as $\frac{P_f}{P_f+P_s}$ for the fast dynamic mode and $\frac{P_s}{P_f+P_s}$ for the slow dynamic mode.

Linear regression to relate head cast and turning angle

We use a linear model to capture the relationship between the head casts and the gradual turning angle that the animal perform. The head casts were classified into six coarse levels (<-6, $-6-3$, $-3-0$, $0-3$, $3-6$, >6), where negative levels indicate head casts during negative curvature and vice versa. For each period of three undulation cycles, the resulting orientation change was quantified and the contributions from different levels of head casts were linearly aggregated. For example, if a '<-6' head-cast and two '3-6' level head-casts occur and the orientation of the worm changes by 0.2 rad during one period, the head-casts impact vector is [1,0,0,0,2,0] and the reorientation change will be collected. In the end, we run a linear regression to obtain the linear coefficients using least squares. To estimate the uncertainty in the coefficients, the data set was bootstrapped 10,000 times and 10,000 sets of coefficients were obtained.

Phase space reconstruction

To analyze the dynamics of head movement, we employed phase space reconstruction using time-delay embedding, a technique based on Takens' theorem (52). This method allows us to reconstruct the multidimensional phase space from our one-dimensional time series of head curvature $\kappa(t)$.

To estimate the optimal time delay τ and embedding dimension m, we used MATLAB *phaseSpaceReconstruction* toolbox, which uses Average Mutual Information (AMI) (53) and False Nearest Neighbor (FNN) algorithm (54) to determine the delay time and embedding dimension respectively.

With τ and m determined, we constructed the phase space vector $y(t)$ from the time series $\kappa(t)$ as follows: $y(t) = [\kappa(t), \kappa(t+\tau), \kappa(t+2\tau), ..., \kappa(t+(m-1)\tau)]$ This process transforms our one-dimensional time series into a set of m-dimensional vectors.

To visualize the topological feature of the reconstructed phase space, we projected the m-dimensional vectors into the space spanned by three principal components. For better visualization, we then fitted the density plots using kernel density estimation with a Gaussian kernel, whose optimal bandwidth was determined by the MATLAB *ksdensity* function.

This reconstructed phase space provides a geometric representation of the system's dynamics, allowing us to identify features such as attractors, periodic orbits, or chaos, which are not apparent in the original time series.

Circuit Model

The head circuit model consists of two parallel neuronal groups that innervate the head muscle: the RMD group and the SMD-SMB group. These groups utilize proprioceptive feedback from different time scales to modulate their states and output. The RMD group integrates rapid feedback from upstream mechanosensitive neurons, which are likely to detect head movements. Specifically, this fast feedback signal (K^{fast}) is a low-pass filtered version of head curvature.

$$\tau_f \frac{dK^{\mathrm{fast}}}{dt} = -K^{\mathrm{fast}} + \kappa$$

On the other hand, the SMD-SMB group receives slow feedback K^{slow} from posterior curvature, presumably detected by their posterior sublateral processes. This slow feedback signal K^{slow} is a low-pass filtered version of the surrogate posterior curvature $-\kappa'$, which is a slow integration of head curvature:

$$\tau_s \frac{d\kappa'}{dt} = -\kappa' + a^s \kappa$$

$$\tau_f \frac{dK^{\text{slow}}}{dt} = -K^{\text{slow}} + \kappa'$$

where the time constants are $\tau_f = 0.3s$ and $\tau_s = 0.8s$. a^s determines the scale of surrogate posterior curvature $-\kappa'$. We represent the bistable dynamics of the SMD-SMB group using a hysteresis curve (Fig. 6 A):

$$U_t^{\text{SMD\&SMB}}(x) = \begin{cases} 1 & x > \theta_s \\ -1 & x < -\theta_s \\ U_{t-1}^{\text{SMD\&SMB}} & \text{else} \end{cases}$$

When the slow feedback exceeds θ_s or falls below $-\theta_s$, the neuronal output switches to the dorsal muscle activation (upper branch) or ventral activation (lower branch), respectively.

The output voltage of the RMDV/R neuron is a Heaviside step function of fast feedback.

$$U^{\text{RMD}}(x) = \begin{cases} 1 & x > \theta_f \\ 0 & x < \theta_f \end{cases}$$

The combined neuronal outputs activate the muscle and drive the head bending:

$$\tau_M \frac{dM}{dt} = -M + U_t^{\text{SMD\&SMB}}\left(-K^{\text{slow}}\right) + cU_t^{\text{RMDD/L}}\left(-K^{\text{fast}}\right) - cU_t^{\text{RMDV/R}}\left(K^{\text{fast}}\right)$$

$$\tau_\kappa \frac{d\kappa}{dt} = -\kappa + M$$

Positive M and κ represent dorsal muscle activation and dorsal bending, respectively. The RMDD/L senses ventral bending and drives dorsal bending, contributing $U_t^{\text{RMDD/L}}\left(-K^{\text{fast}}\right)$ Conversely, RMDV/R neurons contribute $-U_t^{\text{RMDV/R}}\left(K^{\text{fast}}\right)$. The coefficient c scales the contribution of the RMD group.

We determined the head's mechanical time constant τ_κ through relaxation experiments. Following optogenetic activation of unilateral head muscles, we analyzed the decrease in the head curvature after the termination of head muscle activation. By fitting exponential functions to these relaxation curves, we found that the head returns to its resting position with a characteristic time scale of 0.4 seconds. This rapid relaxation is notably faster than the body's mechanical time constant (31), likely due to the head's lower mechanical load. The head's quick response dynamics prove essential for generating the rapid head casts captured in our model. The time constant for muscle activation τ_M is 0.1 seconds following previous works(33, 55).

We examined how well our model's surrogate posterior curvature aligned with actual worm posterior curvature. To do this, we compared two time lags: (1) the lag between head and neck curvature in N2 worms, and (2) the lag between head and surrogate posterior curvature in our model. We determined these lags by identifying the time point at which the cross-correlation between the head curvature's slow mode and posterior curvature signal reached its maximum.
Simulated RMD ablation was implemented by removing the contributions from $U_t^{\text{RMDD/L}}$ and $U_t^{\text{RMDV/R}}$ by setting $c = 0$. The simulated neck inhibition was implemented by scaling the slow feedback K_{slow} by setting $a_s = 0.6a_s$.

Neuro-mechanical Model

To investigate the impact of the temporal pattern of head bending on the curvature amplitude of the rest of the body, we employed a bio-realistic mechanical model from (33) to simulate forward locomotion. We proposed a ventral nerve cord (VNC) circuit featuring bistable motor neuron pairs and anterior proprioceptive coupling to drive this mechanical model.

The mechanical model (33) comprises 48 connected mechanical units, with the body wall muscles modeled as elastic rods capable of active contraction. The model is controlled by 12 pairs of dorsal and ventral motor neurons, with each pair governing 4 mechanical units.

The dynamics of each pair of body motor neurons is governed by two main mechanisms:

1. Dorsal contraction in the anterior units activates the dorsal motor neuron, and ventral contraction activates the ventral motor neuron.

2. Reciprocal inhibition exists between the dorsal and ventral motor neuron partners.

We use directional proprioceptive coupling (36) to induce an activation of motor neurons through anterior bending curvature changes(Fig. S5A). The mutually inhibiting neuron pairs operate within a bistable regime, modulated by the curvature in the anterior section of the body (Fig. S5B).

Let $S_t = 1$ represent the dorsal domination, and $S_t = -1$ represent the ventral domination. The proprioceptive signal P, which is equal to the mean curvature of anterior 8 units (48 units in total), switches the motor neurons pair between dorsal domination and ventral domination:

$$S_t = \begin{cases} -S_{t-1} & \text{if } P > P_{th} \text{ or } P < -P_{th} \\ S_{t-1} & \text{else} \end{cases} \tag{3}$$

Here, P is positive for anterior dorsal bending and negative for ventral bending. When $S = 1$, the dorsal motor neuron dominates (Fig. S5B upper and lower branches for Vd and Vv, respectively):

$$U_D = g(P - P_{th}) + U_b \tag{4}$$
$$U_V = 0 \tag{5}$$

Conversely, when $S = -1$, the ventral motor neuron is activated (Fig. S5B lower and upper branches for Vd and Vv, respectively):

$$U_D = 0 \tag{6}$$
$$U_V = -g(P + P_{th}) + U_b \tag{7}$$

Here U_D and U_V denote the activation levels of the dorsal and ventral motor neurons, respectively. U_b is the baseline activation and g modulates how the activation level changes with proprioception. We set $g > 0$ so that deeper anterior bending leads to higher motor neuron activity and thus deeper posterior bending. This activation function helps to propagate the change in the head bending amplitude along the body.

Finally, the activation of the foremost motor neuron pair, which drives head bending, is controlled by an external input u_t, which alternates between 1 and -1 i.e. between dorsal activation and ventral activation:

$$U_D^0, U_V^0 = \begin{cases} U_{\text{head}}, 0 & u_t = 1 \\ 0, U_{\text{head}} & u_t = -1 \end{cases} \tag{8}$$

The head input is simplified to a binary signal to capture rapid head casts, which are more likely due to abrupt changes in head motor neuron output rather than gradual gain modulation (22, 24).

Using our neuro-mechanical model, we can simulate forward locomotion by applying periodic input to the head motor neurons. Our goal is to identify the input pattern that maximizes kinematic efficiency, defined as the ratio of the average locomotion speed to the undulation frequency. This efficiency measure represents the distance the worm covers in one undulation period.

To explore possible input patterns, we discretized one period of the head input signal into 20 intervals, resulting in a binary sequence of length 20. To further constrain the search space, we imposed dorsal-ventral symmetry around the midpoint and limited the number of transitions between dorsal and ventral activation to no more than two in half a period. These constraints reduced the number of possible input signal profiles to 72. Among these profiles, we identified the one that yielded the highest kinematic efficiency.

Optimal angle of attack for maximum locomotion speed

We describe the traveling body wave along the moving direction with $y = b\sin\frac{2\pi}{\lambda_x}(x - V_W t) = b\sin\frac{2\pi}{\lambda_x}(x - f\lambda_x t)$, where b is the body wave amplitude, λ_x is the effective wavelength along the moving direction, $V_W = f\lambda_x$ is the wave speed, and f is the undulation frequency. For simplicity, the wave number is 1 in this derivation.

It's crucial to distinguish between the effective wavelength and the wavelength in the body length coordinate used in previous works (30, 31). While these wavelengths are similar for small amplitudes, they diverge as the amplitude increases. This divergence occurs because the effective wavelength decreases due to the shrinkage along the anterior-posterior axis in a more curled posture. The sine wave amplitude b and effective wavelength λ_x are related by a constant worm length:

$$L = \int_0^{\lambda_x} \left(1 + \left(\frac{dy}{dx}\right)^2\right)^{\frac{1}{2}} dx = \lambda_x \int_0^1 \left(1 + (\frac{2\pi b}{\lambda_x})^2 \cos^2(2\pi x')\right)^{\frac{1}{2}} dx' \tag{9}$$

Follow Gray and Hankcock (30), the resistive force on an element ds along the moving axis is given by:

$$dF = \left\{ \frac{(C_N - C_L)\frac{dy}{dt}\frac{dy}{dx} - V_x\left[C_L + C_N\left(\frac{dy}{dx}\right)^2\right]}{1 + \left(\frac{dy}{dx}\right)^2} \right\} ds, \tag{10}$$

For large amplitude, we have $ds = \sqrt{1 + (dy/dx)^2}dx$ thus:

$$dF = \left\{ \frac{(C_N - C_L)\frac{dy}{dt}\frac{dy}{dx} - V_x\left[C_L + C_N\left(\frac{dy}{dx}\right)^2\right]}{\left(1 + \left(\frac{dy}{dx}\right)^2\right)^{\frac{1}{2}}} \right\} dx, \tag{11}$$

Total force over a complete wave is:

$$F = \int_0^{\lambda_x} dF \tag{12}$$

We introduce integrals:

$$I = I(b, \lambda_x) = \int_0^{\lambda_x} \frac{1}{\left(1 + \left(\frac{dy}{dx}\right)^2\right)^{\frac{1}{2}}} dx = \int_0^1 \frac{1}{\left(1 + (\frac{2\pi b}{\lambda_x})^2 \cos^2(2\pi x')\right)^{\frac{1}{2}}} dx' \tag{13}$$

$$J = J(b, \lambda_x) = \int_0^{\lambda_x} \frac{\left(\frac{dy}{dx}\right)^2}{\left(1 + \left(\frac{dy}{dx}\right)^2\right)^{\frac{1}{2}}} dx = \int_0^1 \frac{(\frac{2\pi b}{\lambda_x})^2 \cos^2(2\pi x')}{\left(1 + (\frac{2\pi b}{\lambda_x})^2 \cos^2(2\pi x')\right)^{\frac{1}{2}}} dx' \tag{14}$$

Using the zero net force condition:

$$F = \int_0^{\lambda_x} dF = J(C_N - C_L)V_W - V_x(C_L I + C_N J) = 0 \tag{15}$$

The locomotion speed is derived as:

$$\frac{V_x}{V_W} = \frac{\frac{C_N}{C_L} - 1}{\frac{C_N}{C_L} + \frac{I}{J}} \tag{16}$$

We then can numerically calculate the moving speed of the worm at an arbitrarily varying amplitude b, with a fixed frequency and with the wave number equal to 1:

$$V_x = \frac{\frac{C_N}{C_L} - 1}{\frac{C_N}{C_L} + \frac{I(b)}{J(b)}} f\lambda_x(b) \tag{17}$$

To further simplify the equation, we apply a small amplitude approximation to the integrals:

$$\frac{I(b)}{J(b)} \approx \frac{\lambda_x^2}{2\pi^2 b^2} \tag{18}$$

The body angle α along the moving direction follows $\tan(\alpha) = \frac{dy}{dx} = \frac{2\pi b}{\lambda_x} \sin \frac{2\pi}{\lambda_x}(x - V_W t)$. The angle of attack A_a is defined as the maximum angle, which follows

$$\tan A_a = \frac{2\pi b}{\lambda_x} \tag{19}$$

Combining these, we arrive at:

$$V_x \approx \frac{\frac{C_N}{C_L} - 1}{\frac{C_N}{C_L} + \frac{\lambda_x^2}{2\pi^2 b^2}} f \lambda_x(b) = \frac{\frac{C_N}{C_L} - 1}{\frac{C_N}{C_L} + \frac{2}{\tan^2(A_a)}} f \lambda_x(b) \tag{20}$$

Our numerical analysis suggested that Eq. (20), which incorporates the small amplitude approximation in the integrals and wavelength compensation (accounting for finite amplitude), closely approximates Eq. (17). We defined the kinematic efficiency as:

$$V_x/f = \frac{\frac{C_N}{C_L} - 1}{\frac{C_N}{C_L} + \frac{2}{\tan^2(A_a)}} \lambda_x(b) \tag{21}$$

that equals the distance covered by the worm in one period of undulation.

Supplementary figures (S1)

Figure S1. Fast and slow head movement dynamics. A. Representative time series of 5 modes from Variational Mode Decomposition (VMD) of a head curvature signal. **B.** Contribution of each decomposed mode to head motion signal, higher dissimilarity represents higher contribution. **C, D.** Cumulative probability distribution of bending frequency and amplitude of head and body movements, as well as slow and fast dynamic mode of head curvature. K-S test. n.s. p > 0.05, ****p < 0.0001,

Figure S2. Head cast propagation A. Kymograph demonstrating the propagation of head casts to the middle body (highlighted by yellow dashed box). **B.** Correlation between head cast amplitude and propagation distance. Larger head casts exhibit greater propagation distances. **C.** Distribution of head cast propagation distances. **D-E** Similar to **B** and **C**, the head casts were identified using curvature from the anterior 4% - 8% body length instead of 0% - 15%. **F.** Analysis of dorsal-ventral (D-V) bias correlation between head and middle-body curvatureLeft: Strong correlation between D-V bias in head curvature and middle-body curvature when head undulation propagates to the middle body (r=0.73). Right: No correlation was observed when comparing head D-V bias to middle-body curvature from preceding propagation (control, r=-0.01).

Figure S3. Head motor neuron ablation. A. Ablation schemes (top), illustrative head curvature time series (middle), and whole body curvature kymogram (bottom) for RMD, SMD, and SMB ablated animals. **B**. Occurring rate of head casts at different relative amplitude for RMD, SMD, and SMB ablated worms. **C**. Cumulative probability distribution of cross correlation coefficient between middle body curvature and the slow mode of head curvature. KS test. **D**. Head undulation frequency changes for RMD, SMD, and SMB ablated animals. **E**. Body power changes for RMD, SMD, and SMB ablated animals. Mann-Whitney U test. *p < 0.05**p < 0.01, ****p < 0.0001,

Figure S4. Head motor neuron co-ablation. A. Ablation schemes (top), example curvature time series (middle), and whole body curvature kymogram (bottom) for SMD&SMB, RMD&SMD, and RMD&SMB co-ablated animals. **B**. Power ratio of fast mode and slow mode to total signal power for co-ablated animals. **C-D**. head-casts frequency changes for RMD&SMD, and RMD&SMB co-ablated animals. n.s. p > 0.05, **p < 0.01, ****p < 0.0001, Mann-Whitney U test.

Figure S5. Kinematic efficiency. A. Head muscle input pattern drives head bending. Body motor neuron pairs nonlinearly transform anterior curvature to local muscle activation, propagating the bending. The mechanical model (33) receives muscle activation from the motor circuit to generate forward locomotion. We measure locomotion speed and muscle output power. **B**. Two hysteresis curves model the mutually inhibiting motor neuron pairs. Proprioceptive signals switch their state between two branches (S=1 and S=-1). **C**. Crawling trajectories from simulation with baseline and optimized head input in Fig. 5E. **D-E**. Reversing the optimized head input pattern (gray line) increases anterior curvature, resulting in sub-optimal kinematic efficiency. **F**. Estimated Muscle Energy Expenditure: Comparison of baseline and optimized head input across various undulation frequencies. **G**. Theoretical calculation of kinematic efficiency. Two theoretical approximations of kinematic efficiency using small amplitude assumptions. Approximation 1 includes wavelength correction, while Approximation 2 does not.

Figure S6. SMD inhibition. A. Representative head curvature time series (top) and whole body curvature kymogram (bottom) during SMD inhibition. **B**. SMD inhibition resulted in a significant decrease in head and neck curvature, quantified by curvature signal power. **C**. SMD inhibition resulted in an increased power ratio in fast mode and a decreased ratio in slow mode. *p < 0.05, ****p < 0.0001, Wilcoxon signed-rank test.

Supplementary tables (S2) Information of plasmids and strains

Table S1. Plasmids used in this work.

Identifier	Plasmid
quan0180	P*rig-5a::PH-miniSOG::wCherry*
quan0765	P*rig-5a::GtACR2::wCherry*
quan0770g	P*rig-5a::Chrimson::GFP*
quan0771	P*flp-22δ4::PH-miniSOG::wCherry*
quan0772	P*flp-22δ4::GtACR2::GFP*
quan0773	P*flp-22δ4::Chrimson::GFP*
quan0200	P*odr-2::TOMM-20-miniSOG::wcherry*

Table S2. Primers used in this work.

Promoter	Primer
rig-5a	ATTACTTGTACATTTCCA TGATGGTTGTTGAATTG
flp-22δ4	TGCAGGAAACACCACCTAGT TTGCAAGCTTAGAGTACAAC

Table S3. Strains used in this work.

Identifier	Strain
WEN1036	wenEx1036[P*myo-3::arch::wCherry*(30 ng/µL)];
WEN1037	wenEx1037[P*flp22δ4::ph-miniSOG::wCherry*(30 ng/µL)];
WEN1101	wenEx1101[P*rig5a::ph-minisog::wCherry*(30 ng/µL); P*lin-44::mCherry*(10 ng/µL)]
WEN1108	wenEx1108[P*rig-5a::gtacr2::wCherry*(30 ng/µL); P*lin-44::mCherry*(10 ng/µL)]
WEN1111	wenEx1111[P*rig-5a::ph-minisog::wCherry*(30 ng/µL);P*flp-22δ4::ph-minisog::wCherry*(30 ng/µL); P*unc-122::RFP*(10 ng/µL)];
WEN1112	wenEx1112[P*flp-22δ4::gtacr2::gfp*(55 ng/µL); P*lin-44::mCherry*10 ng/µL)]
WEN1113	wenEx1113[P*flp-22δ4::chrimson::gfp*(50 ng/µL); P*lin-44::GFP*(10 ng/µL)]
WEN1116	wenEx1116[P*rig-5a::ph-minisog::wCherry*(30 ng/µL);P*flp-22δ4::ph-minisog::wCherry*(30 ng/µL); P*osm-6::gtacr2::wCherry*(30 ng/µL);P*lin-44::mCherry*10 ng/µL)]
WEN1119	wenEx1119[P*odr-2(18)::tomm-20-minisog::wCherry*(30 ng/µL);P*lin-44::mCherry*10 ng/µL)]
WEN1120	wenEx1120[P*odr-2(18)::tomm-20-minisog::wCherry*(30 ng/µL);P*rig-5a::ph-minisog::wCherry*(30 ng/µL);P*flp-22δ4::ph-minisog::wCherry*(30 ng/µL); P*lin-44::mCherry*10 ng/µL)]
WEN1112	wenEx1122[P*rig5a::chrimson::GFP*(30 ng/µL); P*lin-44::GFP*(10 ng/µL)]
WEN1123	wenEx1123[P*flp-22δ4::ph-minisog::wCherry*(30 ng/µL); P*odr-2(18)::tomm-20-minisog::wCherry*(30 ng/µL); P*lin-44::GFP*(10 ng/µL)]
WEN1124	wenEx1124[P*rig-5a::ph-minisog::wCherry*(30 ng/µL); P*odr-2(18)::tomm-20-minisog::wCherry*(30 ng/µL); P*lin-44::mCherry*(15 ng/µL)]