Title: Slow-varying normalization explains diverse temporal frequency

masking interactions in the macaque primary visual cortex

Authors: Divya Gulati[1] and Supratim Ray[1,2]*

Affiliations: [1] Centre for Neuroscience, Indian Institute of Science, Bangalore, India, 560012

Telephone +918022933437

[2] Corresponding Author: sray@iisc.ac.in

Keywords: SSVEP, plaids, low-pass filter, V1

No. of Pages: 59

No.of Figures: 8

No. of Tables: 2

No. of Supplementary Figures: 5

No. of Supplementary Tables: 2

No. of words in Abstract: 148

No. of words in Introduction: 741

No: of words in Discussion: 1923

Author Contributions: Conceptualization, D.G., S.R.; methodology, D.G., S.R.;
investigation, D.G.; formal analysis, D.G., S.R.; writing – review and editing, D.G., S.R.;
funding acquisition S.R.; supervision S.R.

Declaration of interests: The authors declare no competing interests.

Funding Disclosure and Acknowledgements: This work was supported by Wellcome
Trust/DBT India Alliance (Senior Fellowship IA/S/18/2/504003) and DBT-IISc Partnership
Programme to S.R. and Senior Research Fellowship from Council of Scientific and Industrial
Research to D.G.

Data and Code Availability: Data and codes are available on https://osf.io/jzb5u/ and
https://github.com/Divya-Gulati/Temporal-Frequency-Masking-, respectively.

ABSTRACT

Neurons in the primary visual cortex (V1) respond non-linearly with increasing stimulus contrast or with presentation of multiple stimuli, which has been explained by a normalization model where the excitatory drive is divided by the summed activity of a larger neuronal population. However, while recent studies have suggested that normalization could be time and frequency-dependent, neural mechanisms underlying this dependence remain unknown. We presented two overlapping counterphasing grating stimuli (plaids), either parallelly or orthogonally, at multiple contrasts and temporal frequencies and recorded spikes, local field potential and electrocorticogram activity from V1 of bonnet macaques while they passively fixated. The resulting steady-state visually evoked potentials (SSVEPs) exhibited complicated dynamics – with "low-pass" and "band-pass" suppression profiles for orthogonal and parallel plaids, respectively. Surprisingly, adding a simple low-pass filter in the normalization signal sufficiently explained these diverse effects. Our results present a simple mechanism to explain the spectro-temporal dynamics of normalization.

INTRODUCTION

For efficient encoding of sensory information, neurons dynamically adjust their responsiveness based on the context[1,2]. In addition, visual cortical neurons often exhibit non-linear response properties when multiple stimuli are presented, such as cross-orientation suppression[3,4], surround suppression[5], and pattern masking[3,6–10]. Many of these response properties can be explained using a canonical computation known as the divisive normalization model, which asserts that the pooled activity of the neighbouring neuronal population scales a given neuron's excitatory drive[11]. The model can also be generalized to various sensory modalities, cognitive functions and species[12–14]. However, the basic normalization model does not consider the dynamic temporal facets of the neural responses. Though a growing body of literature[6,15–18] suggests that addition of a slowly accumulating inhibitory drive can explain changes in the temporal domain, the factors influencing the summation of signals within the inhibitory pool are not yet fully teased apart, especially for temporally modulated inputs.

These underlying rules can be probed using masking paradigms, which involve simultaneously presenting multiple stimuli in spatial proximity[19]. Temporal frequency-based masking interactions can be studied by presenting a plaid stimulus generated by overlapping two counterphase or contrast reversal gratings. A counterphase stimulus evokes a stimulus-locked periodic oscillatory response at the temporal frequency of the stimulus[20], known as steady-state visual evoked potential (SSVEP). SSVEPs are very sensitive to changes in stimulus characteristics, which make them suitable for quantifying the suppression in the response of a stimulus (referred to as 'target') when a second stimulus ('mask') is presented. Two stimuli tagged at different temporal frequencies generate SSVEPs at the respective stimulus frequencies, their harmonics, as well as low-order sums and differences of the input

frequencies[21]. Normalization-based models have been used to understand the SSVEP and its

harmonic responses[6,8,9].

Figure 1A shows a normalization model along with the equation[8,22]. Generally, the target

grating is kept at a fixed temporal frequency while the temporal frequency of the mask is

varied. The response is considered only at the target frequency. The excitatory drive only

depends on the contrast of the target frequency and has no contribution from the mask

stimulus since the mask has a different temporal frequency. Nevertheless, non-linear

interactions allow the mask to contribute to the normalization pool (the term S in the

denominator of the equation in Figure 1A denotes this contribution). This suppressive

contribution (S) could further depend on the difference between the orientations of the target

and mask ($\delta\theta$) or the difference in the target and mask frequency (δf).

There could be several hypotheses as to how the response of target grating could vary as a

function of the temporal frequency of the mask (Figure 1, panel C-F; suppression profile (S)

is shown in magenta while the response profile is shown in dotted blue). Suppression could

be non-specific (Figure 1C) or could be proportional to the magnitude of the SSVEP response

at different frequencies (Figure 1D; typical SSVEP response profile in primate primary visual

cortex (V1) is shown in Figure 1B). Other possibilities include having stronger suppression

from low-frequency masks (Figure 1E) or target-frequency dependent suppression that is

maximally suppressive at mask frequencies closest to the target frequency (Figure 1F). These

hypotheses can be tested by presenting masks and targets at multiple frequencies. While we

initially found evidence for low-frequency suppression for parallel plaids in the local field

potential (LFP) recorded from V1 of monkeys[9], the profile was found to be target-frequency

dependent (Figure 1F) when a larger range of target and mask frequencies were used, in both

LFP and human EEG recordings[10]. For orthogonal plaids, the profile was non-specific

(Figure 1C).

However, three questions remain unanswered. First, these studies used full-field stimuli that

did not elicit robust spiking activity, so it is unclear if spikes also show similar response

characteristics as LFP. Second, previous studies used a single mask contrast, so the

suppression profile was not explicitly estimated (only the response profiles were compared).

Most importantly, there was no explanation for the hypothesized suppression profiles. To

address these questions, we presented small plaid stimuli at multiple target and mask

contrasts while recording chronically from macaque V1 and directly estimated the

suppression profiles for both LFP and spiking responses for both parallel and orthogonal

plaids. Extending previous results, we found target-specific (Figure 1F) and low-frequency

(Figure 1E) suppression profiles for parallel and orthogonal plaids. Surprisingly, simply

adding a low-pass filter in the inhibitory drive (in the box marked with "?" in Figure 1A) was

sufficient to explain these varied effects.

RESULTS

We trained three monkeys to passively fixate at a fixation point within a 2° window while we presented either full-field or a small (1° or 1.5°) counterphase grating or plaid stimulus centred on the receptive fields (eccentricity of ~2.5°-4.5°; Figure S1) of the microelectrode grid. We recorded spiking and LFP activity using a chronic array from two monkeys (M1 and M2) and ECoG activity using a custom hybrid array from a third monkey (M3) while they performed the fixation task. SSVEPs generated in response to counterphase gratings or plaids were characterized using their amplitude spectrum computed using Fourier analysis. In cases of plaid stimuli, target grating had a fixed temporal frequency of 15 Hz across all experiments, and the mask grating had a varying temporal frequency between 1-29 Hz across trials.

Response profiles remain similar across stimulus sizes and recording scales

First, we tested whether the response profiles reported earlier for full-field stimuli[9,10] could be observed with small stimuli. The mask grating was fixed at 25% contrast, whereas the target grating could be either 0 or 25%. This allowed us to have both plaid and grating conditions in the same experiment. The relative orientation difference between the two gratings was either kept at 0° or 90°, giving parallel and orthogonal plaids, respectively. Figure 2, panels A and B show the amplitude spectrum of electrode-averaged LFP responses for target grating only (grey trace; same for all conditions) and parallel and orthogonal plaid conditions (colour traces) for full-field and small stimuli, respectively. These counterphasing stimuli produce the strongest SSVEP response at twice the stimulus frequency[9,10], so we analyzed the change in amplitude for target grating at 30Hz. The response at 30Hz for plaid conditions was reduced compared to the grating condition when the mask temporal frequency differed from that of

the target grating (shown by red bars). Facilitation only happened when the target and mask

had the same temporal frequency. The suppression in response to a plaid stimulus was

quantified as the change in amplitude between grating only and plaid conditions. We found

that the response profiles for full-field (Figure 2C) and small (Figure 2D) were similar, with

both showing a target frequency-dependent profile (Figure 1F) for parallel and non-specific

(Figure 1C) profile for orthogonal plaids, as shown previously for full-field stimulus[9,10].

Suppression was stronger for parallel plaids than orthogonal, as observed previously in

macaques and humans[8–10,22]. In addition to self-harmonics peaks in the amplitude spectra, we

observed peaks at intermodulation (IM) terms (f_1+f_2, f_1-f_2, $2f_1+2f_2$, $2f_1-2f_2$) primarily for

parallel plaid conditions.

While these stimuli allow us to obtain the response profiles (Figure 2C-D), the suppression

profile $S(\delta\theta,\delta f)$ in Figure 1A cannot be determined from this data. This is because $S(\delta\theta,\delta f)$

has a different value for each mask temporal frequency (14 free parameters each for parallel

and orthogonal conditions in our case). Therefore, to estimate $S(\delta\theta,\delta f)$ for a particular mask

frequency and orientation, multiple mask and target contrasts are needed, which was not done

in our previous studies. To address this, we presented both target and mask gratings

independently at 4 contrasts (0%,6.25%,12.5% and 25%), generating 16 response profiles

(one for each combination of target and mask contrasts; Figure 3).

We first tested whether the SSVEP interactions at the LFP or ECoG scale differ from spiking

activity. We presented stimuli big enough to cover the aggregate receptive fields of the

microelectrode grids for LFP and MUA recordings, while full-field stimuli were presented for

ECoG recordings as the receptive field centres were far apart (Figure S1). Figure 3A-3B

shows the response profiles for varying mask and target contrasts for LFP (top row), ECoG

(middle) and spikes (bottom row). Note that these effects were difficult to quantify for many

spike electrodes, since the firing rate had to be sufficiently high to get a robust response at 30

Hz using Fourier analysis. We, therefore, generated a single response profile after first

averaging all the spiking data across electrodes and then computing the amplitude at 30 Hz.

Importantly, we found that the characteristic dip in the response profile near the target

frequency, characteristic of the target-frequency profile (Figure 1F), was present even for

spiking data for mask and target contrasts of 25% (blue trace in the rightmost column of

Figure 3A). Similarly, for orthogonal plaids (Figure 3B), spiking responses showed a non-

specific response similar to what was observed for LFP and ECoG. These results show that

the core shape of the response profile is visible even for individual neurons, even though it

has been previously observed that spikes and LFP have different tuning for preferred

temporal frequencies[9].

In either of the recording scales, with increasing target contrast and mask contrast,

suppression became stronger. The suppression profile appeared contrast invariant for parallel

plaids, such that increasing contrast only scaled the responses but did not change the target-

frequency dependent profile. Interestingly, for orthogonal plaids with lower contrasts of mask

or target, a low-frequency tuned suppression was observed instead of a non-specific

suppression observed when both target and mask were at maximum contrast (25% each). We

also recorded responses for plaids with component gratings separated by 45° (Figure S2,

panel A) in orientation for M2 and M3. We observed a similar low-frequency tuned

suppression in LFP and ECoG activity.

The suppression profile shape is based on the relative orientations of the

component gratings.

In masking literature, normalization models have been extensively used to characterize

responses to temporally modulated plaid stimuli[3,6–9] as they capture non-linear operations

well. So, we examined if our observations could also be fitted using a 'tuned' normalization

model[9] (Figure 1 panel A, equation 4 in methods). This equation has 16 free parameters –

L_{amp}, which denotes response within the receptive field to a stimulus at unit contrast, σ (semi-

saturation constant) and 14 'S' parameters to describe the suppression profile due to 14

different temporal frequencies of mask grating. We fitted this model to data from individual

LFP and ECoG electrodes. Figure 4 shows these data individually for each monkey. For each

electrode, the entire dataset consisting of 14 mask temporal frequencies (the data point at the

target frequency was not considered) and 16 different contrast combinations (224 data points

as shown in individual rows of Figure 4) was fitted using this equation. The predictions

(Figure 4) explained more than 80% of the variance for almost all conditions (except for the

orthogonal condition in M1, as the recording quality for that session was noisy). We obtained

two kinds of suppression profiles depending on the relative orientation difference between the

component counterphase gratings. We obtained a band-pass like suppression profile for

parallel plaids (Figure 4 panel A, last column, deep magenta trace), and a low-frequency

tuned profile for orthogonal and 45 separated plaids (Figure 4 panel B, last column, gold

trace; Figure S2 panel B-C, top rows, last column, orange trace). However, the suppression

profile for parallel case had two distinct features – suppression values tended to be higher at

very low frequencies (especially pronounced for M1), and there was asymmetry around the

target frequency as well, with mask frequencies lower than the target, producing stronger

suppression than ones higher. This asymmetry is also readily observed in the response

profiles for the target contrast of 25% (Figure 4A).

To limit the number of free parameters, we fixed the exponent value to 2. However, we also

fitted the data by keeping the exponent as a free parameter and found that these exponent

values converged near 2 (data not shown). The median values obtained for semi-saturation

constant (σ) and L_{amp} are shown in Table 1 (for parallel and orthogonal plaids) and Table S1

(for 45° separated plaids). The original-tuned normalization model used here does not assume

any functional form for the suppressive drive. So, our next goal was to understand how the

shape of the suppression profile can be obtained.

Low-pass filtering of the normalization signal produces the desired suppression

profiles

Previous reports[8,22,23] suggest that the inhibitory drive is a combination of the physical form

of the input stimuli. So, we first assumed the 'S' as a summation of two sinusoids

corresponding to target and mask gratings, and to account for the stronger response at the

second harmonics in the response (owing to the squared output of complex cells[24,25]), these

signals can be raised to a squaring exponent. For parallel plaids, summation happens before

squaring since the signals pass through the same channel (see Figure 1A), while for

orthogonal plaids, the sinusoids are squared and then summed. The first column in Figure 5

shows these signals for the fixed target frequency and three different mask frequencies, while

the second column shows the normalization signals, with 5A and 5B representing the

computation for parallel and orthogonal conditions. The overall normalization strength

obtained by averaging this signal is comparable whether the mask frequency is low (magenta

trace), near the target (blue) or fast (cyan), and therefore the suppression profile is essentially

flat (third column; at the mask frequency of 5 Hz there is an overlap between an IM term

leading to a different value in Figure 5A). Thus, the basic normalization model yields a non-

specific suppression and response profile.

Some studies[6,15–18] have suggested that the normalization signal is not instantaneous with

respect to the incoming excitatory drive leading to response onset. The delay in the signal can

be achieved by low-pass filtering the normalization signal. We found that simply adding a

low-pass filter (LPF) to the normalization signal shown in the second column is sufficient to

get the desired suppression profiles. For parallel plaids, this happens because when two

sinusoids are summed and squared, the output contains terms at harmonics, sum and

difference intermodulation frequencies:

$$(sin\omega_T t + sin\omega_M t)^2 = \ sin^2\omega_T t + sin^2\omega_M t + [cos(\omega_T - \omega_M)t - \ cos(\omega_T + \omega_M)t]$$

$$= 1 - \frac{(cos2\omega_T t + cos2\omega_M t\ )}{2} + cos(\omega_T - \omega_M)t - \ cos(\omega_T + \omega_M)t$$

When this signal is passed through a low-pass filter, the output is high when (i) lower mask

frequencies (ω_M) are presented or when (ii) ω_M is close to ω_T such that the sinusoid with

frequency of $|\omega_T - \omega_M|$ can pass through the filter. Therefore, maximum suppression (Figure

5C, third column) is observed for frequencies closest to the target frequency, followed by

slower mask frequencies (Figure 5C, third column). Indeed, the low-pass-filtered

normalization signal shown in the second column of Figure 5C is largest when the mask is

close to the target frequency (blue trace), followed by the slow mask frequency (magenta

trace), and is weakest for fast mask frequencies (cyan trace). Similarly, the low-frequency

dependent suppression profile can be obtained when sinusoids, which are first squared and

then summed, are passed through a low-pass filter (Figure 5D). In this case there are no

intermodulation terms, so lower mask frequencies are most suppressive since they can pass

through the low-pass-filter while higher mask frequencies cannot (Figure 5D).

In this formulation, there is no explicit suppression profile (S) anymore that is contributed by

the mask, since both target and mask frequencies interact non-linearly to produce the overall

normalization signal. However, to maintain uniformity with the previous model, we

continued with a suppression profile (as in equation 4) which was explicitly calculated by the

action of a low-pass filter on the summed and squared (or squared and summed) sinusoids. To

account for the effect of orientation, we assumed that the suppression profile was a weighted

sum of the two summation mechanisms described in Figure 5C and 5D (equation 5), with the

weights as free parameters dependent on the relative orientations of the gratings.

Next, we fitted our data with this 'optimal-tuned normalization model', where the number of

free parameters to represent S reduced from 14 to 6 (equation 5). Despite that, we could

explain >80% of the variance for more than ninety per cent of the electrodes (Figure 6) and

could qualitatively capture the overall response and suppression profiles. We obtained a target

frequency-dependent profile for the parallel plaids with $\alpha_1 > \alpha_2$ (Table 2) as well as a low-

frequency tuned profile for orthogonal plaids with $\alpha_2 > \alpha_1$. For plaids with delta 45° also (for

M2 and M3; Figure S2 panel B and C bottom rows), a low-frequency tuned suppression

profile was obtained with more than 80% explained variance for all the electrodes and $\alpha_2 > \alpha_1$

(see Table S2). Our empirical data suggested that distinct channels give rise to orientation-

selective masking profiles.

The fit quality obtained from the original-tuned model was slightly better than that of the

optimal-tuned normalization model across electrodes and monkeys for both parallel and

orthogonal plaids. (Figure 7A Wilcoxon signed rank test, parallel: p = 1.631e-09; orthogonal:

p = 2.3968e-09). When differences in model parameters were compared, the corrected Akaike

Information Criteria values (AIC$_C$) were significantly higher for the optimal-tuned

normalization model for the parallel case but were almost the same across the two models

orthogonal plaids (Wilcoxon signed rank test, parallel: p = 0.1.8514e-09; orthogonal: p =

0.14131; Figure 7B).

While the optimal-tuned normalization model achieved the desired suppression profiles with

very few parameters, we could not explain the asymmetry in the profile near the target

frequency (compare the magenta traces in Figure 4A versus 6A), which could also have

explained the slightly poorer performance of the optimal-tuned normalization model

compared to the original model. However, we found that such asymmetry in the suppression

could be achieved by passing the inhibitory drive from non-linearity of different order other

than squaring (Figure S3), as elaborated in the Discussion section.

Difference-Intermodulation terms are also low-passed

We also studied the sum and difference intermodulation (IM) terms as a function of the

contrast and temporal frequency of the mask grating (Figure S4 and S5). IM terms were

predominantly present for parallel plaids and became stronger as the mask and target contrast

were increased. The terms were barely perceptible for orthogonal and 45° separated plaids

except when the temporal frequency of the mask was a harmonic of the temporal frequency

of the target. Again, this indicates that the temporal frequencies pass through the non-linear

stage together when the orientation of the two gratings matches. The difference-

intermodulation terms (f_1-f_2) had the minimum amplitude response when the temporal

frequencies of the target and mask grating were closest, and the response increased as the two

moved away (Figure S4, panel B). As before, this could be attributed to the low-passed

normalization drive, which becomes strongest when $|\omega_T - \omega_M|$ is small, thereby leading to a

small amplitude change. The results for sum-intermodulation components are discussed in the

supplementary.

Additional evidence for low-pass filtering

The preferred temporal frequency of a grating depends on stimulus size

If the normalization signal has more energy from lower frequencies, we hypothesized that

temporal frequency tuning of counterphase gratings should be a function of stimulus size.

When a larger stimulus is presented, the feedforward input remains the same as when a small

stimulus is presented, but since more surround is activated, it leads to a more extensive

interneuronal network activation[26]. A recent study has also shown reduced synaptic excitatory

input for a larger stimulus compared to a smaller stimulus[27]. Thus, the normalization signal

would be more robust for larger stimuli, and therefore, the lower temporal frequencies would

be suppressed more for larger stimuli compared to small stimuli. This, in turn, will lead to a

higher preferred temporal frequency for larger stimuli. To test this, we presented

counterphase gratings of two sizes (full-field and 1.5°) at various temporal frequencies

(Figure 8). We observed that for a maximum contrast small-sized stimulus, a clear peak in the

tuning curve was indiscernible, with 4Hz-16Hz having approximately a similar amplitude

change. However, a distinguishable peak at 16Hz was evident for the large stimulus.

Consistent with the hypothesis, the preferred TF shifted towards higher frequencies when

stimulus size was increased across all stimulus contrasts (Figure 8D; right-tailed Wilcoxon

signed rank test, p = 1.8199e-14).

DISCUSSION

By using counterphasing plaid stimuli, we demonstrated that the masking interactions in V1 neurons are a function of both temporal frequency and relative orientations of component gratings, which holds irrespective of the stimulus size and recording scale. The band-pass suppression profile obtained for parallel plaids and the low-pass suppression profile obtained for the orthogonal plaids can be explained simply by adding a low-pass filter to the normalization pool, which receives input from orientation-selective channels. We also show that the rightward shift of the preferred temporal frequency of a counterphase grating when stimulus size increases and the amplitude of difference-intermodulation terms as a function of the temporal frequency of the mask can also be attributed to low-pass filtering of the inhibitory drive.

Comparison with previous studies

Divisive normalization has significantly explained pattern masking in the temporal domain. While some studies[7–9] have assumed the model to be memoryless, many previous studies have used low-pass filters to explain the dynamics of normalization[6,15–17]. However, most studies have used the filter to explain the temporal dynamics of the response. We have used the low-pass filter to instead explain the shape of the suppression function, not the temporal dynamics of the response. Specifically, the response and suppression profiles in equation 4 and 5 are not functions of time. Although the computation of S is done by low-pass filtering signals that are functions of time, we averaged the energy over time (which can be thought of as another 'hidden' low-pass filter with a large time-constant in our formulation). Since the characteristics of the low-pass filter were not used to explain the temporal variation of the response, this is an independent approach to study the characteristics of the filtering action.

Reassuringly, this alternate approach also yielded compatible results. We obtained cutoff of

the low-pass filter between ~7-11 Hz for parallel plaids and ~24-30Hz for non-parallel plaids

(except for M3, where the cutoff was ~6 Hz). These correspond to an integration time ($1/(2\Pi$

f)) of the normalization signal to be about ~14-23ms and ~5-7ms for parallel and orthogonal

plaids, respectively. Note that for the orthogonal condition, the filtering action produces a

"low-pass" effect, with shallower slopes corresponding to high filter cutoffs. However, the

same can be achieved by having a large value of the semi-saturation constant, leading to a

shallower overall slope. The parallel condition puts stronger constraints on the low-pass filter,

for which the time constants (14-23 ms) were in agreement with previous reports that have

reported time constants of ~25-30ms in humans[6] and monkey V1[18] and between ~5-25ms in

cat's retinal ganglion cells[28], albeit the mechanisms that give rise to these time constants are

very different (as discussed below).

However, it is unlikely that a single low-pass filter with a cutoff of ~10 Hz is sufficient to

explain the temporal dynamics of normalization. Note that a counterphase grating, even at

low frequencies, produces a response only at the counterphasing frequency and its harmonics.

If the normalization signal which comes in the denominator of equation 4 is allowed to

oscillate, the resulting response function will have many other frequencies since division by a

sinusoid generates a non-sinusoidal signal. Since this is not observed in real data, the

normalization signal must be low-pass filtered with a sufficiently long time constant (in our

formulation, the averaging operation in equation 5 was this 'hidden' filter). For example,

Zhou and colleagues[16] found a time constant of ~100 ms when they fitted the temporal

dynamics of the response. It is likely that multiple filters are operating at different levels, as

suggested previously[28], which could explain stimulus interactions as well as the temporal

evolution of the response.

Our results are more comparable with those of Tsai and colleagues[6], who also used a low-

pass filter to explain the changes in responses at target, mask and intermodulation frequencies

with varying contrasts. However, contrast response functions were only obtained for a single

target and mask frequency, as in other studies as well[6,8,23], whereas we obtained contrast

responses for the target against multiple temporal frequencies and orientations of mask

grating. Our time constants match those reported by Tsai et al., even though the stimulus used

was a random noise pattern, unlike the counterphase plaids we used.

For orthogonal plaids, we found a low-frequency tuned suppression at lower contrasts that

changed to non-specific suppression at high contrast. This can happen because the relative

contribution of the suppression term in the normalization signal reduces when the target

contrast is high (see equation 5). Note that we kept the semi-saturation constant fixed; in a

previous report, it was varied as the function of mask contrast[6]. So, the change in the

response profile at different contrast levels could also be explained by varying semi-

saturation value with contrast. For example, if the semi-saturation constant increases with

target contrast, it could also make the suppression profile non-specific at high target contrasts.

According to the winner-take-all computation, the stimulus with higher contrast should be

favoured for combinations where the target or mask stimuli have dissimilar contrasts[4]. This

would also mean that IM components should be negligible for such cases, as shown by Tsai

and colleagues[6]. However, in our results, we did not observe any enhancement in IM

components when target and mask contrasts were matched (Figure S4; matched target and

contrast conditions correspond to light green in the first column of S4B (both at 0%), dark

green in second (both at 6.25%) and so on, which did not seem out of place compared to the

remaining non-matched conditions). These observations were in contrast to those observed by

Tsai et al., as they observed sum-IM components decreasing with increasing mask contrast

beyond the maximum target contrast, and they did not obtain strong difference-IM

components[6]. However, they used modulation frequencies for the two stimuli very close to

each other, with a difference of ~2Hz ($|\omega_T - \omega_M|$), comparable to the data points at mask

frequencies of 13 or 17 Hz in Figure S4B-S4C. We also found the difference IM responses to

be small for that case, since the IM components were able to pass through the low-pass filter

and contribute in the suppressive drive. By using a much wider range of mask frequencies

compared to previous studies, a more complete IM interaction profile could be observed.

We observed that IM terms were absent from the responses for orthogonal and 45° separated

plaids and were found only for parallel plaids, hinting that the orientation bandwidth for the

filters is less than 45 degrees. Results from the previous EEG study[8] also align with this

observation, where the presence of IM terms falls to negligible at 45° separation. This is not

surprising since the orientation channel bandwidth in V1 is reported to be around ~20-30° in

neural[29] and psychophysical responses[30]. Therefore, 45° separated plaids are likely to be

processed by separate filters and, hence, are supposed to be more similar to the orthogonal

case than the parallel one, as observed in our data.

Underlying architecture of dynamic normalization

The stimulus sizes we used (1-1.5° and full-field) activate two kinds of suppression – overlay

and surround suppression[31]. Suppression is generally delayed by ~10-25ms with respect to

the onset of excitatory response[32–34], although the delay is dependent on the strength of

suppression[33]. Overlay suppression is relatively faster by ~10ms than surround suppression[34]

but is also broadly tuned[31]. Contrarily, near and far surround suppression are orientation-

tuned and arise by lateral and feedback connections, although near surround suppression is

much more sharply tuned[33,35]. This suppression of responses because of masking is mediated

by $GABA_A$ irrespective of the relative orientation difference between the plaid components[36].

GABAergic neurons, which include somatostatin-expressing (SST) and parvalbumin-

expressing fast-spiking (PV) interneurons, are thought to play distinct roles in

normalization[37], input summation and output normalization. SST neurons have slower

dynamics but are selective, while PV neurons provide faster-untuned feedforward

suppression[38,39]. Since orthogonal suppression becomes non-specific at higher contrasts and

has relatively faster time constants, it may have a higher contribution from PV interneurons.

On the other hand, SST neurons might play a more prominent role in the suppression caused

by parallel plaid stimuli. The onset latency of SST neurons is about ~20-25ms delayed

compared to that of pyramidal and PV cells[38]; this is equivalent to the time constants we

obtained from the model for parallel plaids.

A recent study[40] showed that the frequency fall-off in gamma oscillations arising from such

excitation-inhibition interactions could also be attributed to delayed surround input. The

study used an inhibitory stabilized network (ISN) model, where delayed inhibition was

modelled as Ornstein-Uhlenbeck (OU) noise, which can be thought of Gaussian white noise

passed through a low-pass filter. Similar ISN models have also been used to explain masking

dynamics[41,42]. Thus, there are multiple ways to incorporate slow-dynamics in the inhibitory

circuit, and more work is warranted to explain the mechanisms that lead to temporal

frequency masking interactions described here.

Model peculiarities and limitations

The optimal-tuned normalization model successfully explained the overall profile of the

suppression but failed to capture the asymmetry observed in the suppression profile for the

parallel plaids. One way to achieve asymmetry using the current form of the model would be

to change the exponent when the inhibitory drive passes through the orientation filter. With

even exponents (Figure S3 B and D), the band-pass profile obtained is symmetric as $|\omega_T -$

$\omega_M|$ is the same for both sides of the target frequency. However, with odd exponents, an

asymmetric low-pass profile emerges where the temporal frequencies lower than that of the

target suppress more. This happens because the Fourier domain components are no longer

symmetric, and energy found for lower mask frequencies comes closer to the cutoff of the

low-pass and can, therefore, pass through it (Figure S3, panels A and C, third column,

lavender peaks). Hence, contributions from the discrete populations of V1 neurons that

follow odd and even-order non-linearities can give rise to such asymmetry in the response.

Interestingly, the low-pass suppression profile that we observed for orthogonal plaids can also

be obtained by using odd exponents in the model (Figure S3A and C). However, this would

suggest that, like parallel plaids, these stimuli also pass through the same filters before any

non-linearity. Some studies[43,44] have favoured this hypothesis for target and mask stimuli at

different orientations. However, unlike our study, they used stationary stimuli at different

spatial frequencies, but we matched the spatial frequencies of the component gratings of the

counterphasing plaid. Studies[8,23] in the past, which have used orthogonally oriented

temporally modulated stimuli, favoured passing signals through non-linearity and then

summing them up in a way similar to that obtained by our model. For orthogonal plaids, the

suppression profile for M3, which was computed using ECoG, was different from the other

two monkeys (Figure 6). It reflected contributions from both hypotheses but had a higher

contribution from the addition of non-linear signals ($\alpha_2 > \alpha_1$, Table 2). The difference could

simply be due to the larger spatial summation of ECoG signals compared to LFP[45]. In

summary, we note that adding more filters, making the semi-saturation constant a function of

contrast, or changing the exponent can all lead to improvements in the model to capture

additional features (e.g., temporal dynamics of the response or asymmetry in suppression

profile).

In light of the ubiquity of normalization, it would be interesting to test if similar dynamics are

seen in higher visual areas and for other senses and whether they are better explained by

manipulating different parameters in the model. Our results are useful for designing different

attention and brain-computer interfacing studies, which use multiple stimuli that are often

spatially overlapping.

METHODS

All the animal surgeries and experiments were reviewed and approved by the Institutional Animal Ethics Committee of the Indian Institute of Science and were conducted following the guidelines approved by the Committee for the Purpose of Control and Supervision of Experiments on Animals (CPCSEA). Three adult female bonnet macaques (*Macaca radiata*) participated in the experiments (M1 – 3.2 kg, 13 years; M2 – 5.8 kg, 15 years; M3 – 3 kg, 17 years) conducted for this study.

Animal Preparation and Training

Before training, each monkey was surgically implanted with a titanium headpost over the frontal region of the skull under general anaesthesia. Following a two-week recovery period, monkeys were trained on passive fixation tasks. After the monkeys learned the task, a second surgery was performed to implant a microelectrode grid (Utah Array, Blackrock Neurotech). Grids consisted of platinum microelectrodes of 1mm in length, with a tip diameter of 3-5µm and an interelectrode distance of 400µm; the grids were centred ~10-15mm rostral from the occipital ridge and ~10-15mm lateral from the midline, with slightly varying locations across the monkeys. M1 was implanted with a 10×10 microelectrode array grid with 96 active electrodes, and M2 was implanted with a 6×8 microelectrode grid with 48 active electrodes in the right primary visual cortex. In M2, a second grid of similar specifications was implanted in the V4 region, but this study did not analyze those signals. M3 was implanted with a custom hybrid array that consisted of a 9×9 microelectrode grid with 81 active microelectrodes and a 3×3 Electrocorticogram (ECoG) grid (Ad-Tech Medical Instrument Corporation). ECoG contacts were 2.3 mm wide platinum discs with a 10mm centre-to-centre interelectrode distance. The current study analyzed only ECoG electrodes, as the microelectrode grid had stopped working before recording the experiments described in this

study. M1 and M3 were also used in our previous findings on SSVEP local interactions, as

their monkey two and monkey one, respectively[10]. Reference wires were inserted under the

dura at the edge of the craniotomy or secured to titanium screws or metal straps, which were

used to secure the bone of the craniotomy. Referencing was performed using 96 Channel

Cereplex E headstage. The receptive field of the recorded neurons was located in the lower

left quadrant for M1 and M2 and the lower right quadrant for M3 about the fixation point (at

the eccentricity of ~2.7°-4.4° in M1, ~2.6°-3.3° in M2 and ~1.9°-7.2° in M3, Figure S1).

Neural data was collected once monkeys recovered from the grid implantation surgery and

performed the task.

Experimental Setup and Data Acquisition

Monkeys sat ~50cm away from the monitor in a primate chair, their heads restrained by a

headpost. The monitor (BenQ XL2411, LCD, 1280×720 resolution with a refresh rate of

100Hz) was gamma-corrected using Colorchecker Display Plus (Calibrite; formerly known as

i1 Display Pro), with the gamma value set to unity and mean luminance set at 60 cd/m2.

Monkey's eye position data (horizontal and vertical coordinates/positions and pupil

diameters) was tracked and recorded using the ETL-200 Primate tracking system (ISCAN,

sampled at 200Hz). The display setup, eye tracker and the animal were housed in a dark

Faraday enclosure lined with a copper sheet to minimize external electrical interference.

Stimulus generation, pseudorandom stimulus presentation, and eye signal monitoring were

done using custom software (Lablib) running on MacOS. Neural signals, local field potentials

(LFP) and multiunit activity (MUA), were recorded using a 128-channel Cerebus neural

signal processor (Blackrock Neurotech). Raw data was band-pass filtered between 0.3Hz

(analog Butterworth filter, first order) and 500Hz (digital Butterworth filter, fourth order) and

was sampled at 2000Hz, digitized at a resolution of 16 bits to collect LFP data. To obtain

multiunit activity, neural signals were sampled at 30KHz and filtered between 250Hz (digital

Butterworth filter, fourth order) and 7500Hz (analog Butterworth filter, third order), followed

by amplitude thresholding the signal at ~5 standard deviations below the mean (except for

one session for M2 where it was kept at 4). The MUA was not sorted further, and no further

offline filtering was done on the data.

Experimental Design and Visual Stimuli

Each experiment started by presenting a fixation dot (radius 0.1°) at the centre of the display

monitor. Monkeys were trained to fixate on this dot while holding their gaze within a fixation

window (1.5° for M1 and M2 and 2° for M3) for the entire trial duration to get a juice reward

at the end. Monkeys were given ~1000-2000ms to start fixating; if they failed to fixate within

this stipulated time or broke fixation during the trial duration, the trial was aborted. While

monkeys fixated, a series of achromatic counterphasing grating or plaid stimuli (generated by

overlapping two counterphasing gratings) were presented. We ran three experiments with

different stimulus presentations.

In Experiment 1 (Figure 2), performed by M1 and M2, full-field counterphasing plaid stimuli

were pseudorandomly presented. The trial began with a fixation period (1000ms for M1 and

1500ms for M2) followed by two stimulus presentations of 1500ms each, with an inter-

stimulus interval of 1500ms. The inter-trial interval was kept at 1500ms (for M1) or 1000ms

(for M2). The first grating (the target grating) had an orientation of either 0° or 90° in a

session with a fixed temporal frequency of 15Hz. The second grating (the mask grating) was

presented at two different orientations (0° and 90°) at varying temporal frequencies (1-29Hz

in the step of 1Hz). The contrast of the target grating was either kept at 0 or 25%, and the

mask grating had a fixed contrast of 25%, allowing us to record responses to grating and

plaid stimuli in the same session. The spatial frequency of both the gratings was fixed at four

cycles/degree (cpd). Each session had 116 stimulus conditions (2 target contrasts × 2 mask

orientations × 29 mask temporal frequency), with at least 15 repeats for each stimulus. We

collected data from one session for M1 and two sessions for M2.

Since full-field stimuli highly suppress MUA response; in Experiment 2 (Figure 2-7), a

smaller stimulus (radii - 1° for M1 and 1.5° for M2) spanning the aggregate receptive field of

the microelectrodes was presented. Target and mask gratings were presented at four contrasts

(0 to 25% on a log scale) at a spatial frequency of 4 cpd. Superimposing the two gratings

doubled the contrast of the resulting plaid stimulus. Multiple contrasts allowed us to estimate

the parameters for the normalization model (explained below) as the complete profile of

masking responses could be obtained. The temporal frequency of target grating was fixed at

15Hz, while the mask grating in a trial could take any value between 1-29Hz (in steps of

2Hz). Orientation of target or mask grating could either be at 0° (parallel plaids) or

90°(orthogonal plaids) for M1 or could take any value between 0° to 135° (in steps of 45°)

for M2 such that the difference between the orientation of the two gratings is either 0° or 90°

for a single session. A total of 240 unique stimulus conditions (4 target contrasts × 4 mask

contrasts × 15 mask temporal frequency) were repeated 15 times in one session. Since we had

almost doubled the stimulus conditions compared to the first experiment, we reduced the

stimulus duration to keep the time taken to finish a session the same, as it was already

between ~2.5-3 hours. Three stimuli of 800ms each were presented in a trial after an initial

fixation period of 1000ms with an inter-stimulus interval of 700ms, followed by an inter-trial

interval of 1000ms. We collected data from 2 sessions from M1 (one session each for parallel

and orthogonal plaid) and across 8 sessions (4 sessions each for parallel and orthogonal

plaids) for M2. We ran the same experiment on M3 but with a full-field stimulus instead, as

we were collecting data from the ECoG grid only, with a target and mask orientation of 0° or

90°. We collected data from 3 sessions for orthogonal plaids and 2 sessions for parallel plaids.

In M2 and M3, we also ran additional sessions, where the orientation difference between the

target and mask gratings was fixed at 45° (4 sessions for M2 and 2 sessions for M3, Figure

S2).

Experiment 3 (Figure 8) involved presentations of counterphase gratings of full-field and 1.5°

in size across five contrast levels (0 to 100% on a log scale) and 8 temporal frequencies (0, 1,

2, 4, 8, 16, 32 and 50Hz). The orientation and spatial frequency of gratings were fixed at 90°

and 4cpd. Each trial started with a fixation period of 1000 or 1500ms, followed by two or

three stimulus presentations. Stimulus was presented for 800ms for M1 and 1500ms for M2

with an interstimulus interval of 700 and 1500ms, respectively. Eighty stimuli (2 sizes × 5

contrasts × 8 temporal frequency) were each repeated at least 12 times. Recordings were done

from one session for M1 and two sessions for M2.

Receptive Field Mapping and Electrode Selection

A receptive field mapping protocol, which involves the flashing small grating stimuli (0.3°-

0.4°) on equally spaced locations within a rectangular grid (11×11 for M1, 14×17 for M2 and

19×25 for M3), was run across multiple days to estimate receptive field locations of the

electrodes. While the monkey fixated on the central fixation spot, a series of stimuli, each for

200ms (with an interstimulus period of 0ms), was presented at full contrast. The stimulus had

a spatial frequency of 4cpd (for M1 and M3) or 2cpd (M2) and could take any of the four

orientations (0°, 45°, 90° or 135°). The evoked LFP responses were used to estimate

receptive field centres and sizes by fitting a 2D Gaussian. Any electrode with a stable

receptive field centre across 50% of the sessions and a receptive field size within 0.1° to 0.5°

was selected for LFP analysis. Impedances for all the electrodes across all sessions were

under 2500kΩ. This yielded 21 and 32 microelectrodes for M1 and M2 and 5 ECoG

electrodes for M3. In M1, for Experiment 2, the recording quality was relatively poor, so only

electrodes with strong evoked responses on that session (N = 10-11 electrodes) were used.

For MUA analysis, electrodes that accumulated more than a certain number of spikes in one

session (2000 for M1,4000 spikes for M2) and had a signal-to-noise ratio (SNR) and change

in firing rate more than a predetermined cutoff (SNR >= M1 – 1.9, M2 – 1.2, Δ Firing rate >=

M1 – 1 spikes/second and M2 – 2 spikes/second (stimulus period – 250-750ms; baseline

period – -500-0ms) and had a sharp transient increase of activity during first 150ms of

stimulus presentation were used. We obtained 80 electrodes for the parallel plaids session and

51 for the orthogonal plaids session, pooled across both monkeys (M1 and M2) across all the

sessions.

Data Analysis

All the data were analyzed using custom-written codes in MATLAB (MathWorks, RRID:

SCR_001622). For the analysis window, the stimulus period was defined as 250 to 750ms or

250 to 1250ms post-stimulus onset, depending on the stimulus presentation duration. The

baseline was defined as the corresponding period before the stimulus onset (-500 to 0ms or -

1000 to 0ms). Consequently, this results in a frequency resolution of 2Hz or 1Hz. Trials with

excessive noise (due to any movement or electrical artefact) during these periods were

discarded if the amplitude of the waveform exceeded a threshold of six times the standard

deviation from the mean waveform. Thereby rejecting <2% of trials for each monkey for all

experiments. The remaining waveforms were then used for further analysis. The

counterphasing stimulus evokes a more vigorous SSVEP response at the second harmonic,

and the amplitude difference was calculated at twice the temporal frequency (f) of the grating

(for experiments 1 and 2 – at 2f of target grating, i.e. 30Hz, experiment 3 – at 4, 8, 16, 32, 64

and 100Hz) between stimulus and baseline period (equation 1). For experiment 2, the change

in amplitude was also calculated at intermodulation terms (f_1-f_2 and f_1+f_2). For LFP analysis,

the baseline across all stimuli repeats was averaged, and a common baseline was used.

Amplitude spectra were calculated for stimulus and baseline period using discrete Fourier

transform for individual trials. To obtain firing rate spectra, we generated peristimulus time

histograms by binning spikes across each trial in 10ms bins and averaged across trials for

each condition and multiunits, followed by their Fourier transform.

$$Change\ in\ Amplitude = Amp_{ST}(2 \times f) - Amp_{BL}(2 \times f)$$ equation 1

SSVEP tuning functions (Figure 8) were fitted using the difference of exponential

function[46,47] (equation 2) using an ordinary least squares fit. The peak of the fitted function

was considered as the preferred temporal frequency. Electrodes were classified as low-pass if

the preferred temporal frequency of an electrode was <=1 Hz and otherwise called band-pass.

The statistics of preferred temporal frequency are calculated further only on band-pass with a

fit quality of >=0.6.

$$r(f) = \alpha_1 e^{-\beta_1 f} - \alpha_2 e^{-\beta_2 f}$$ equation 2

$r(f)$ is the change in amplitude at twice the temporal frequency of the grating. Coefficients

α1, β1, α2, and β2 were constrained to be non-negative. The fit quality (*qval*) was calculated

as the fraction of the total variance in the data explained by the fits:

$$qval = 1 - \frac{\sum_f [r(f) - \tilde{r}(f)]^2}{\sum_f [r(f) - \bar{r}]^2}$$ equation 3

where $\tilde{r}(f)$ is the fitted value corresponding to $r(f)$ and $\bar{r}$ is the mean change in amplitude

across all temporal frequencies. A qval close to 1 corresponds to decent fits, whereas negative

qval values close to 0 indicate poor fits.

Normalization model

A tuned divisive normalization model, which has been previously used to explain SSVEP

interactions[9], was adapted to explain the suppression profile obtained for the amplitude of

target grating as a function of the temporal frequency of the mask grating (equation 4, Figure

1 panel A) for experiment 2. The following equation describes the model:

627
$$R(f_{Target}) = \left[\frac{L_{amp} c_{Target}}{\sqrt{\sigma^2 + c_{Target}^2 + S(\delta\theta, \delta f) c_{Mask}^2}} \right]^n \qquad \text{equation 4,}$$

where $R(f_{Target})$ is the resultant mean amplitude response at twice the temporal frequency of

target (30Hz). L_{amp} corresponds to the response of an individual grating at the unit contrast, σ

and n represent the semi-saturation constant and non-linearity in the gain of the response.

$S(\delta\theta, \delta f)$ captures the suppression driven by the mask grating with a particular orientation and

temporal frequency. First, we kept the following sixteen as non-negative free parameters:

L_{amp}, constrained <15; σ, constrained <4; and S (14 mask temporal frequencies), constrained

<35. Exponent 'n' was fixed at a value of 2. This version of the model is referred to as the

original-tuned normalization model in the rest of the text.

A second, optimal-tuned normalization model was also fitted, which accounts for a functional

form for 'S'. In this approach, we assumed that the neural responses towards target and mask

grating are sinusoidal. Similar to the Foley-style model[22] (equation 8 - Model 3), we

presumed that depending upon the orientation difference between the target and the mask

grating, the component sinusoid contribution would be summed before or after the

exponentiation. We also argue that the normalization signal coming as the inhibitory drive

will vary slowly over time, thereby integrating responses from the pool within a temporal

window. This can be achieved by low-pass filtering (LPF) of the signal, similar to the

previous studies[6,16]. In this model, 'S' was assumed to be the mean energy of the inhibitory

gain pool and was denoted as:

$$S = \overline{\left[\alpha_1 \times \left(LPF\left(\sin\omega_T t + ScF \times (\sin\omega_M t) \right)^2 \right) + \alpha_2 \times \left(LPF\left(\sin\omega_T t^2 + ScF \times (\sin\omega_M t^2) \right) \right) \right]^2}$$

646                       equation 5

647 where $\square_T$ and ω_M represent the angular frequency of the target and mask grating. α_1 and α_2

648 represent the weights of the low-pass drive of the two orientation-selective filters. The bar

649 denotes average over time (so S is not a function of time). The scaling factor (ScF) factors in

650 the contribution from the mask grating as the signals from the target and mask might be

651 weighted to allow an optimal combination. It primarily controls the contribution from lower

652 mask frequencies. We used a fourth-order Butterworth low-pass filter and left the filter cutoff

653 as a free parameter. But before passing the signal through the low-pass filter, we corrected the

654 signal to remove the DC component. We plugged the value of S obtained from this equation

655 back into equation 4 to estimate the final response. In this model, we had fixed the exponent

656 at 2 and had six non-negative free parameters, L_{amp}, constrained <15; σ, constrained <4;

657 cutoff frequency of the filter, constrained <40; α_1 and α_2, constrained >0; and ScF, constrained

658 between 0 and 1.

659 The curve fitting was done using fmincon function in MATLAB to minimize the sum of the

660 squared estimate of the errors:

661       $$SSE_D \;=\; \sum([r(f) \;-\; \tilde{r}(f)]^2)$$      equation 6

662 where $r(f)$ is the observed response and $\tilde{r}(f)$ is the fitted value. The quality of the fits

663 provided by the model was assessed by computing the explained variance (equation 3).

664 We used corrected Akaike information Criteria[48,49] (AIC_C) to compare the model performance

665 as the two models varied in their complexity owing to different numbers of free parameters.

666     $$AIC_C = N \times log_e \frac{SSE_D}{N} + 2K + \frac{2K(K+1)}{N-K-1}$$    equation 7

667 where N refers to the number of observations, SSE_D is the sum of the squared estimate of

668 errors (equation 6), and K represents the number of free parameters in the model. We also

added SSE_D as an additional free parameter[49] for the calculation, increasing the tally of free

parameters to 17 and 7, respectively, for the two models. The AIC_C values are comparative in

nature and do not have any interpretation on their own.

Quantification and statistical analysis

We performed a two-tailed Wilcoxon signed rank test to compare the model performance

across two versions of the normalization model with the null hypothesis that samples come

from distributions with equal medians. We used the right-tailed Wilcoxon signed rank test to

compare if the preferred temporal frequency changes with stimulus size, with the null

hypothesis that larger stimuli prefer faster temporal frequencies than small ones.

REFERENCES

1. Schwartz, O., and Simoncelli, E.P. (2001). Natural signal statistics and sensory gain control. Nat Neurosci *4*, 819–825. https://doi.org/10.1038/90526.

2. Ferguson, K.A., and Cardin, J.A. (2020). Mechanisms underlying gain modulation in the cortex. Nat Rev Neurosci *21*, 80–92. https://doi.org/10.1038/s41583-019-0253-y.

3. Carandini, M., Heeger, D.J., and Movshon, J.A. (1997). Linearity and Normalization in Simple Cells of the Macaque Primary Visual Cortex. J Neurosci *17*, 8621–8644. https://doi.org/10.1523/JNEUROSCI.17-21-08621.1997.

4. Busse, L., Wade, A.R., and Carandini, M. (2009). Representation of concurrent stimuli by population activity in visual cortex. Neuron *64*, 931–942. https://doi.org/10.1016/j.neuron.2009.11.004.

5. Cavanaugh, J.R., Bair, W., and Movshon, J.A. (2002). Nature and interaction of signals from the receptive field center and surround in macaque V1 neurons. J Neurophysiol *88*, 2530–2546. https://doi.org/10.1152/jn.00692.2001.

6. Tsai, J.J., Wade, A.R., and Norcia, A.M. (2012). Dynamics of normalization underlying masking in human visual cortex. J Neurosci *32*, 2783–2789. https://doi.org/10.1523/JNEUROSCI.4485-11.2012.

7. Boynton, G.M., and Foley, J.M. (1999). Temporal sensitivity of human luminance pattern mechanisms determined by masking with temporally modulated stimuli. Vision Research *39*, 1641–1656. https://doi.org/10.1016/S0042-6989(98)00199-0.

8. Candy, T.R., Skoczenski, A.M., and Norcia, A.M. (2001). Normalization models applied to orientation masking in the human infant. J Neurosci *21*, 4530–4541. https://doi.org/10.1523/JNEUROSCI.21-12-04530.2001.

9. Salelkar, S., and Ray, S. (2020). Interaction between steady-state visually evoked potentials at nearby flicker frequencies. Sci Rep *10*, 5344. https://doi.org/10.1038/s41598-020-62180-y.

10. Liza, K., and Ray, S. (2022). Local Interactions between Steady-State Visually Evoked Potentials at Nearby Flickering Frequencies. J Neurosci *42*, 3965–3974. https://doi.org/10.1523/JNEUROSCI.0180-22.2022.

11. Heeger, D.J. (1992). Normalization of cell responses in cat striate cortex. Vis Neurosci *9*, 181–197. https://doi.org/10.1017/s0952523800009640.

12. Carandini, M., and Heeger, D.J. (2012). Normalization as a canonical neural computation. Nat Rev Neurosci *13*, 51–62. https://doi.org/10.1038/nrn3136.

13. Reynolds, J.H., and Heeger, D.J. (2009). The normalization model of attention. Neuron *61*, 168–185. https://doi.org/10.1016/j.neuron.2009.01.002.

14. Rangel, A., and Clithero, J.A. (2012). Value normalization in decision making: theory and evidence. Curr Opin Neurobiol *22*, 970–981. https://doi.org/10.1016/j.conb.2012.07.011.

15. Chen, S.C.-Y., Chen, Y., Geisler, W.S., and Seidemann, E. (2024). Neural correlates of
perceptual similarity masking in primate V1. eLife *12*, RP89570.
https://doi.org/10.7554/eLife.89570.

16. Zhou, J., Benson, N.C., Kay, K., and Winawer, J. (2019). Predicting neuronal dynamics
with a delayed gain control model. PLoS Comput Biol *15*, e1007484.
https://doi.org/10.1371/journal.pcbi.1007484.

17. Mikaelian, S., and P. Simoncelli, E. (2001). Modeling temporal response characteristics
of V1 neurons with a dynamic normalization model. Neurocomputing *38–40*, 1461–1467.
https://doi.org/10.1016/S0925-2312(01)00529-X.

18. Reynaud, A., Masson, G.S., and Chavane, F. (2012). Dynamics of local input
normalization result from balanced short- and long-range intracortical interactions in area
V1. J Neurosci *32*, 12558–12569. https://doi.org/10.1523/JNEUROSCI.1618-12.2012.

19. Fox, R. (1978). Visual Masking. In Perception, S. M. Anstis, J. Atkinson, C. Blakemore,
O. Braddick, T. Brandt, F. W. Campbell, S. Coren, J. Dichgans, P. C. Dodwell, P. D.
Eimas, et al., eds. (Springer), pp. 629–653. https://doi.org/10.1007/978-3-642-46354-
9_20.

20. Regan, D. (1966). Some characteristics of average steady-state and transient responses
evoked by modulated light. Electroencephalogr Clin Neurophysiol *20*, 238–248.
https://doi.org/10.1016/0013-4694(66)90088-5.

21. Zemon, V., and Ratliff, F. (1982). Visual evoked potentials: evidence for lateral
interactions. Proceedings of the National Academy of Sciences *79*, 5723–5726.
https://doi.org/10.1073/pnas.79.18.5723.

22. Foley, J.M. (1994). Human luminance pattern-vision mechanisms: masking experiments
require a new model. J. Opt. Soc. Am. A, JOSAA *11*, 1710–1719.
https://doi.org/10.1364/JOSAA.11.001710.

23. Baker, D.H., and Wade, A.R. (2017). Evidence for an Optimal Algorithm Underlying
Signal Combination in Human Visual Cortex. Cereb Cortex *27*, 254–264.
https://doi.org/10.1093/cercor/bhw395.

24. Movshon, J.A., Thompson, I.D., and Tolhurst, D.J. (1978). Receptive field organization
of complex cells in the cat's striate cortex. J Physiol *283*, 79–99.
https://doi.org/10.1113/jphysiol.1978.sp012489.

25. Adelson, E.H., and Bergen, J.R. (1985). Spatiotemporal energy models for the perception
of motion. J Opt Soc Am A *2*, 284–299. https://doi.org/10.1364/josaa.2.000284.

26. Adesnik, H., Bruns, W., Taniguchi, H., Huang, Z.J., and Scanziani, M. (2012). A Neural
Circuit for Spatial Summation in Visual Cortex. Nature *490*, 226–231.
https://doi.org/10.1038/nature11526.

27. Li, B., Routh, B.N., Johnston, D., Seidemann, E., and Priebe, N.J. (2020). Voltage-Gated
Intrinsic Conductances Shape the Input-Output Relationship of Cortical Neurons in
Behaving Primate V1. Neuron *107*, 185-196.e4.
https://doi.org/10.1016/j.neuron.2020.04.001.

28. Victor, J.D. (1987). The dynamics of the cat retinal X cell centre. J Physiol *386*, 219–246.
https://doi.org/10.1113/jphysiol.1987.sp016531.

29. Ringach, D.L., Shapley, R.M., and Hawken, M.J. (2002). Orientation Selectivity in
Macaque V1: Diversity and Laminar Dependence. J Neurosci *22*, 5639–5651.
https://doi.org/10.1523/JNEUROSCI.22-13-05639.2002.

30. Meese, T.S., and Holmes, D.J. (2010). Orientation masking and cross-orientation
suppression (XOS): Implications for estimates of filter bandwidth. Journal of Vision *10*,
9. https://doi.org/10.1167/10.12.9.

31. Petrov, Y., Carandini, M., and McKee, S. (2005). Two Distinct Mechanisms of
Suppression in Human Vision. J. Neurosci. *25*, 8704–8707.
https://doi.org/10.1523/JNEUROSCI.2871-05.2005.

32. Albrecht, D.G., Geisler, W.S., Frazor, R.A., and Crane, A.M. (2002). Visual Cortex
Neurons of Monkeys and Cats: Temporal Dynamics of the Contrast Response Function.
Journal of Neurophysiology *88*, 888–913. https://doi.org/10.1152/jn.2002.88.2.888.

33. Bair, W., Cavanaugh, J.R., and Movshon, J.A. (2003). Time Course and Time-Distance
Relationships for Surround Suppression in Macaque V1 Neurons. J. Neurosci. *23*, 7690–
7701. https://doi.org/10.1523/JNEUROSCI.23-20-07690.2003.

34. Smith, M.A., Bair, W., and Movshon, J.A. (2006). Dynamics of Suppression in Macaque
Primary Visual Cortex. J. Neurosci. *26*, 4826–4834.
https://doi.org/10.1523/JNEUROSCI.5542-06.2006.

35. Bijanzadeh, M., Nurminen, L., Merlin, S., Clark, A.M., and Angelucci, A. (2018).
Distinct Laminar Processing of Local and Global Context in Primate Primary Visual
Cortex. Neuron *100*, 259-274.e4. https://doi.org/10.1016/j.neuron.2018.08.020.

36. Morrone, M.C., Burr, D.C., and Speed, H.D. (1987). Cross-orientation inhibition in cat is
GABA mediated. Exp Brain Res *67*, 635–644. https://doi.org/10.1007/BF00247294.

37. Northoff, G., and Mushiake, H. (2020). Why context matters? Divisive normalization and
canonical microcircuits in psychiatric disorders. Neuroscience Research *156*, 130–140.
https://doi.org/10.1016/j.neures.2019.10.002.

38. Ma, W., Liu, B., Li, Y., Josh Huang, Z., Zhang, L.I., and Tao, H.W. (2010). Visual
Representations by Cortical Somatostatin Inhibitory Neurons—Selective But with Weak
and Delayed Responses. J Neurosci *30*, 14371–14379.
https://doi.org/10.1523/JNEUROSCI.3248-10.2010.

39. Atallah, B.V., Bruns, W., Carandini, M., and Scanziani, M. (2012). Parvalbumin-
Expressing Interneurons Linearly Transform Cortical Responses to Visual Stimuli.
Neuron *73*, 159–170. https://doi.org/10.1016/j.neuron.2011.12.013.

40. Krishnakumaran, R., Pavuluri, A., and Ray, S. (2025). Delayed Accumulation of
Inhibitory Input Explains Gamma Frequency Variation with Changing Contrast in an
Inhibition Stabilized Network. J. Neurosci. *45*.
https://doi.org/10.1523/JNEUROSCI.1279-24.2024.

41. Bertalmío, M., Cyriac, P., Batard, T., Martinez-Garcia, M., and Malo, J. (2017). The
Wilson-Cowan model describes Contrast Response and Subjective Distortion. Journal of
Vision *17*, 657. https://doi.org/10.1167/17.10.657.

42. Malo, J., Esteve-Taboada, J.J., and Bertalmío, M. (2024). Cortical Divisive
Normalization from Wilson–Cowan Neural Dynamics. J Nonlinear Sci *34*, 35.
https://doi.org/10.1007/s00332-023-10009-z.

43. Meese, T.S., and Holmes, D.J. (2002). Adaptation and gain pool summation: alternative
models and masking data. Vision Research *42*, 1113–1125.
https://doi.org/10.1016/S0042-6989(01)00291-7.

44. Holmes, D.J., and Meese, T.S. (2004). Grating and plaid masks indicate linear summation
in a contrast gain pool. Journal of Vision *4*, 7. https://doi.org/10.1167/4.12.7.

45. Dubey, A., and Ray, S. (2019). Cortical Electrocorticogram (ECoG) Is a Local Signal. J
Neurosci *39*, 4299–4311. https://doi.org/10.1523/JNEUROSCI.2917-18.2019.

46. Levitt, J.B., Kiper, D.C., and Movshon, J.A. (1994). Receptive fields and functional
architecture of macaque V2. Journal of Neurophysiology *71*, 2517–2542.
https://doi.org/10.1152/jn.1994.71.6.2517.

47. Hawken, M.J., Shapley, R.M., and Grosof, D.H. (1996). Temporal-frequency selectivity
in monkey visual cortex. Visual Neuroscience *13*, 477–492.
https://doi.org/10.1017/S0952523800008154.

48. Hurvich, C.M., and Tsai, C.-L. (1989). Regression and time series model selection in
small samples. Biometrika *76*, 297–307. https://doi.org/10.1093/biomet/76.2.297.

49. Motulsky, H., and Christopoulos, A. (2004). Fitting Models to Biological Data Using
Linear and Nonlinear Regression: A Practical Guide to Curve Fitting (Oxford University
Press).

 FIGURE LEGENDS

Figure 1. Hypothesis for interaction between target and mask temporal frequency.

(A) Schematic and equation for the tuned normalization model. The masking model is

adapted from Foley's Model 3[8,22]. The excitation drive only consists of input from the

target grating. The inhibitory drive consists of input both from the target and mask

grating. The filters tile the entire orientation space (from 0° to 180°). For the parallel

mask, the two gratings match in their orientation and, thus, pass through the same

filter. They are, therefore, first summed and then passed through expansive non-

linearity. For an orthogonal mask, the two pass through different filters and are passed

through expansive non-linearity separately and then summed. This drive is then

pooled, and it divisively scales the excitatory drive. However, the temporal dynamics

of pooling are not well characterized (denoted by the question mark).

(B) SSVEP tuning profile of counterphase grating presented at 25% contrast. The blue dot

represents the target frequency used in the main study.

(C-F) Hypothetical suppression profile (solid deep magenta trace) as a function of temporal

frequency of mask grating, and the corresponding response profile (dotted blue trace) at the

temporal frequency of the target grating.

(C) Non-specific suppression: Suppression strength is independent of the temporal

frequency of the mask.

(D) SSVEP gain-specific suppression: Suppression strength is dependent on SSVEP

tuning preference as shown in B.

(E) Low-frequency tuned suppression: Suppression strength is progressively stronger for

lower frequencies.

(F) Target frequency dependent suppression: Suppression strength is maximum when the

temporal frequency of the mask grating is closer to the frequency of the target grating

and decreases as the difference between the temporal frequencies of the two gratings

increases.

Figure 2. LFP amplitude response suppression for different stimuli sizes.

(A) Mean amplitude spectra averaged across M1 and M2 microelectrodes for a full-field

stimuli.

(B) Same as (A) but for a small stimuli presented over the aggregate receptive field of the

microelectrode grid.

The two columns in (A) and (B) indicate the two different plaid stimuli (deep magenta

– parallel; gold – orthogonal), indicating the relative orientation difference between

the target and mask grating and each row corresponds to a different temporal

frequency of mask grating superimposed on the target grating of 15Hz. The grey

coloured trace denotes the grating 'only' condition at 25% contrast (same across all

the plots for (A) and across each column for (B) as a single type of plaid stimuli was

presented in one session for small sized stimulus). The coloured trace represents the

plaid condition with target and mask grating at 25% contrast each. The dotted vertical

lines indicate the second harmonic of the target (black) and mask grating (magenta).

The numbers indicate the difference in amplitude between the grating 'only' condition

and the relative plaid condition at 30Hz.

(C) Amplitude response difference between full-field grating 'only' condition and plaid

condition as a function of temporal frequency of mask grating averaged across

electrodes for two monkeys (N = 51). Error bars indicate ±SEM.

(D) Same as (C) but for small stimuli (averaged across electrodes for all sessions for

parallel (N = 43) and orthogonal plaids (N = 42)).

Figure 3. Amplitude response suppression as a function of different contrasts and orientations

across recording scales.

(A) Change in amplitude at 30Hz from the baseline condition averaged across sessions

and electrodes for parallel plaid stimuli, with target and mask grating presented at

various contrast combinations plotted as a function of temporal frequency of mask

grating. Each grating can take one of the four contrast values between 0% and 25%

(on a log scale). Within each panel, four traces represent the contrast of mask grating

(green to blue, indicating increasing contrast level) and each column represents the

contrast of the target grating. Different row corresponds to different recording scales.

The first row represents the average change in amplitude response from the baseline

condition for M1 and M2 for a small stimulus. The second row corresponds to the

change in amplitude from the baseline for ECoG response in M3 against a full-field

stimulus. The third row indicates the change in amplitude calculated from the Fourier

transform of the electrode-averaged peri-stimulus time histogram (PSTH) for M1 and

M2 in response to the presentation of a small stimulus. Error bars indicate ±SEM.

(B) Same as (A) but for orthogonal plaids.

Figure 4. The suppression profile obtained from the tuned normalization model depends on

the relative orientation difference between the target and mask grating.

(A) Model fits for averaged amplitude response at 30Hz and obtained suppression profiles
from the tuned normalization model (equation 4) for parallel plaids; plotted for
electrodes with explained variance >= 0.8. Rows correspond to LFP response for M1,
M2 and ECoG response for M3. The first four columns show the model fits (dotted
traces with the shaded region indicating mean±sem) for the empirical averaged
amplitude response (circles, error bars not shown) for different target contrasts. Each
subplot further has four coloured traces corresponding to different mask contrasts.
Same as Figure 3. The percentage of electrodes with explained variance >= 0.8 are
represented as 'GoodFitsElecs' in the inset of each row. The last column of each row
represents the mean suppression values obtained from the model, with error bars
indicating ±SEM.
(B) Same as (A) but for orthogonal plaids.

Figure 5. Simulations of the drive coming from the normalization pool and their expected
suppression profiles.

The four columns correspond to the input signal, inhibitory normalization drive based
on different equations, expected suppression profiles and response profiles. Three
different mask gratings (same across A-D) of varying temporal frequencies are
highlighted in different colours. The input signal represents the form of the sinusoids.
The normalization term depicts the input signal after going through the operation
described. The suppression profile is obtained by calculating the energy of the
inhibitory drive by squaring the amplitude of the response across the entire spectrum
(equation 5). The response profile is the inverse of the magnitude of the suppression
profile.

(A) The inhibitory normalization signal is obtained by first adding the signal from the target and mask sinusoids, followed by rectification.

(B) The normalization signal is obtained by rectifying the target and mask sinusoids and then summing up the input.

(C) Same as (A), but the inhibitory drive is passed through a low-pass filter, analogous to integrating responses from the neighbouring population over some temporal integration window.

(D) Same as (B), but the inhibitory drive passes through a low-pass filter.

Figure 6. An optimal-tuned normalization model with a low-pass filtered normalization signal can explain SSVEP suppression responses.

(A) and (B) same as Figure 4, but the model is fitted using Equation 4 and Equation 5. The suppression profiles as a function of temporal frequency of mask grating (in the last column; shown in magenta and gold) were calculated from the free parameter values obtained from the optimal-tuned normalization model using Equation 5 and were normalized for each electrode before averaging.

Figure 7. Comparison of performance for original-tuned and optimal-tuned normalization model.

Scatter plots with histograms for (A) explained variance and (B) Akaike information criteria calculated for original-tuned and optimal-tuned normalization model. The subplots at the top and right represent the histograms of counts for each model. Each data point in the scatter plot represents one electrode. Colors denote parallel (deep magenta) and orthogonal (gold) plaid conditions. Three different markers are used to

indicate the three monkeys. P-values obtained from the two-tailed Wilcoxon signed rank test are denoted in the bottom left.

Figure 8. SSVEP tuning profiles of counterphase gratings in LFP signal as a function of stimulus size.

(A) Evoked responses of a representative electrode in response to a full-field and a small (1.5°) counterphasing grating stimulus presented at varying temporal frequencies (0,1,2,4,8,16,32 and 50Hz) and 100% contrast.

(B) SSVEP tuning plots show the change in amplitude at twice the temporal frequency of the stimulus as a function of contrast (light to dark shaded markers) plotted for the representative electrode for the two stimulus sizes. The responses for each contrast were fitted using the difference of exponentials function (equation 2). Triangles represent the preferred TF.

(C) Same as (B) but for LFP responses averaged across sessions and electrodes for M1 and M2 (N = 51).

(D) Scatter plots of preferred TFs estimated for full-field and small stimulus for each electrode of M1 and M2. Each data point represents an electrode with fit quality >= 0.6 and a preferred TF > 1Hz for a particular contrast condition (grey colour levels).

 TABLES

956 *Table 1*: Showing median ± bootstrapped SEM values for parameters obtained from the

957 original-tuned normalization model

	Parallel Plaid			Orthogonal Plaid		
Parameters	M1	M2	M3	M1	M2	M3
σ	0.23±0.08	0.23±0.01	0.31±0.01	0.21±0.06	0.23±0.02	0.35±0.03
L_{amp}	3.41±0.53	2.58±0.10	6.22±0.34	2.88±0.68	2.45±0.43	6.21±0.34

960 *Table 2*: Showing median ± bootstrapped SEM values for parameters obtained from the

961 optimal-tuned normalization model

	Parallel Plaid			Orthogonal Plaid		
Parameters	M1	M2	M3	M1	M2	M3
σ	0.28±0.06	0.22±0.01	0.30±0.02	0.21±0.06	0.23±0.04	0.35±0.02
L_{amp}	3.47±0.30	2.55±0.16	6.18±0.55	2.87±0.38	2.49±0.90	6.41±0.57
Cutoff	11.03±1.48	7.52±0.01	8.86±0.45	23.99±3.36	24.78±4.11	6.92±0.87
α_1	11.98±3.51	7.49±0.27	6.64±1.23	0±0.36	0±0.34	1.30±0.12
α_2	0±0	0±0	0±0	5.87±1.87	4.89±2.47	3.20±0.46
ScF	0.59±0.08	0.46±0.02	0.38±0.09	0.70±0.25	0.70±0.22	1±0

SUPPLEMENTAL INFORMATION

Figure Legends:

Figure S1. Location of receptive fields and stimulus.

Locations of receptive field centres with their respective sizes of the microelectrodes

implanted in V1 of (A) M1, (B) M2. Only electrodes with stable receptive fields

across days are plotted. Refer to receptive field mapping and electrode selection in the

methods section for more details. The blue circle marks the size and location of the

stimulus presented in experiment 2. (C) Locations of receptive field centres with their

sizes for ECoG grid implanted in M3.

Figure S2. Amplitude response suppression for plaids with 45° orientation difference.

(A) Amplitude response at 30Hz averaged across sessions and electrodes for plaid stimuli

with 45° separation, with target and mask grating presented at various contrast

combinations plotted as a function of temporal frequency of mask grating. Same

format as Figure 3. The first row represents the average change in amplitude response

from the baseline condition for M2 for a small stimulus. The second row corresponds

to the change in amplitude from the baseline for ECoG response in M3 against a full-

field stimulus. LFP activity was not collected from M1 for these conditions.

(B) Empirical and fitted averaged change in amplitude data for electrodes of M2 using

original-tuned (upper row) and optimal-tuned normalization model (bottom row)

shown in first four columns. The last column shows the suppression profile obtained

from the respective model. The percentage of electrodes having explained variance >=

0.8 are represented as 'GoodFitsElecs' in the inset of each row.

(C) Same as (B) but for the ECoG grid implanted in M3.

Figure S3. Simulations of low-pass normalization signals with different orders of non-

linearity and their respective expected suppression profiles.

The five columns correspond to the input signal, inhibitory normalization drive based

on summing the sinusoids and then raised to different exponents (exp $=1\Box$ 4 for

panels A-D), its Fourier transform, the expected suppression and response profiles.

Similar to Figure 5.

Figure S4. Amplitude response profiles at intermodulation terms for parallel and orthogonal

plaids

(A) Mean amplitude spectra averaged across electrodes for parallel plaid sessions (deep

magenta trace) with target and mask grating at 25% contrast each for LFP (M1 and

M2) and ECoG (M3) activity. Each row corresponds to a mask grating at a different

temporal frequency. The grey-coloured trace denotes the grating 'only' condition at

25% contrast. The dotted vertical lines indicate intermodulation terms: f_1-f_2 (dark

brown trace) and f_1+f_2 (light brown trace).

(B) Change in amplitude at plots f_1-f_2 as a function of temporal frequency and contrast of

mask grating (green to blue, indicating increasing contrast level) for different

contrasts of target grating (different columns). The first row represents the average

change in amplitude response from the baseline condition for M1 and M2 for a small

stimulus (N = 43). The second row corresponds to the change in amplitude from the

baseline for ECoG response in M3 against a full-field stimulus (N=5).

(C) Same as (B) but showing change in amplitude at f_1+f_2 instead. The sum-

intermodulation components (f_1+f_2) observed for parallel plaids followed a low-

passed profile, with lower mask temporal frequencies evoking a stronger IM

component. These results do not align with the suggested model, but they can be

obtained when the response itself passes through a low-pass filter. As shown in Figure

8, the SSVEP response in V1 peaks at around 11.51±0.62Hz for small gratings at

maximum contrast, so cells are unlikely to respond vigorously to summed IM

components with values high as 29+15 = 44 Hz.

(D-F) Same as (A-C) but for orthogonal plaid stimuli.

1018

1019   Figure S5: Same *Figure S4*, panels (A-C) but for 45° separated plaid stimuli presented to M2

1020   and M3. LFP activity was not collected from M1 for these conditions.

1021

1022   Tables:

1023   *Table S1*: Showing median ± bootstrapped SEM values for parameters obtained from the

1024   original-tuned normalization model for 45° separated plaids.

45° separation Plaid

Parameters	M2	M3
σ	0.17±0.01	0.41±0.04
L_{amp}	2.93±0.27	7.27±0.36

1025

1026

1027   *Table S2*: Showing median ± bootstrapped SEM values for parameters obtained from the

1028   optimal-tuned normalization model for 45° separated plaids.

45° separation Plaid

Parameters	M2	M3
σ	0.17±0.01	0.42±0.03
L_{amp}	2.93±0.22	7.53±0.66
Cutoff	31.18±0.76	23.48±5.48
α_1	0.16±0.06	0.73±0.58
α_2	4.74±0.42	3.89±0.64
ScF	1±0	1±0

1029

1030

$$R_{(f_{Target})} = [\frac{L_{amp}c_{Target}}{\sqrt{\sigma^2 + c_{Target}^2 + S(\delta\theta, \delta f)c_{Mask}^2}}]^n$$

1031
1032   Figure 1

1033

1034
1035   Figure 2

1036

1037   Figure 3

1038

1039

1040   Figure 4

1041

1042

1043   Figure 5

1044
1045   Figure 6

1046

1047　　Figure 7

1048

1049

1050   Figure 8

1051

1052

1053   Figure S1

1054

1055   Figure S2

1056

1057

1058   Figure S3

1059

1060

1061   Figure S4

1062

1063   Figure S5