Maximizing the fidelity of a photovoltaic subretinal prosthesis for human patients

Nathan Jensen[1]*, Anna Kochnev Goldstein[1], Keith Ly[2,3], Quentin Devaud[4], and Daniel Palanker[2,3]

Abstract—Objective. **PRIMA subretinal implants provide prosthetic vision in patients blinded by age-related macular degeneration, with acuity closely matching the sampling limit of the pixel pitch: a single 100 μm pixel per line of a letter corresponds to 20/420 acuity. Decreasing the pixel size in the same flat geometry is difficult due to the constrained electric field, especially considering a 40 μm thick debris layer separating the implant from the target neurons. Here we optimize the electrode design to help overcome such limitations.** *Approach.* **An end-to-end modeling pipeline combines the subretinal photovoltaic implant simulator (RPSim) based on the Xyce circuit simulator with an interface to COMSOL Multiphysics for electric field modelling. It was used to generate and characterize implants in an open-loop sampling-based optimization. Implant performance was evaluated with respect to voltage drop across bipolar cells (representing the stimulation strength), pattern contrast, and neural selectivity.** *Main Results.* **The highest selectivity in stimulation of bipolar cells was achieved with arrays having active electrodes on pillars and return electrodes connected in a mesh surrounding the photovoltaic pixels in the array. Such a design with pixel size down to 20 μm provides stimulation strength exceeding, and contrast similar to that of flat 100 μm PRIMA pixels.** *Significance.* **Using a novel 3-D electrode design, the pitch of the photovoltaic array can be decreased to 20 μm, while providing performance that exceeds the flat 100 μm PRIMA pixels. In humans, 20 μm resolution on the retina corresponds to a visual acuity of 20/80 – a five times improvement compared to the current clinical device.**

Index Terms—**Optimization, Micro-Electrode arrays, Neural prostheses, Retinal prosthesis, Brain-Computer Interface**

I. INTRODUCTION

The retinal prothesis system PRIMA provides central vision in patients impaired by atrophic age-related macular degeneration [1]. The system includes a wireless subretinal implant and a pair of augmented reality (AR) glasses equipped with a video camera. Images captured by the camera are processed and projected onto the implant using pulsed light. The implant itself is a 2x2 mm hexagonal multielectrode array (MEA) with photovoltaic pixels (Fig. 1(a)) that convert this light into electric current to stimulate the nearby retinal neurons in the inner nuclear layer (INL), primarily the bipolar cells (BCs). To avoid stimulation of the healthy peripheral retina, the glasses use an invisible near-infrared (NIR, 880 nm) wavelength..

Submitted for review. Studies were supported by the National Institutes of Health (R01-EY-035227 and P30-EY-026877) and the Department of Defense (W81XWH-22-1-0933).

1. Department of Electrical Engineering, Stanford University, Stanford, CA 94305 USA

2. Department of Ophthalmology, Stanford University

3. Hansen Experimental Physics Laboratory, Stanford University

4. School of Life Sciences, EPFL, Lausanne, Switzerland

* Corresponding author (e-mail: njensen@stanford.edu)

Each pixel in the PRIMA MEA is 100 μm wide and contains two photodiodes connected in series, a shunt resistor, and a pair of electrodes - a central active electrode and a peripheral return electrode (Fig. 1(b,c)), a configuration that will be referred to as bipolar. The sampling limit of such an array is set by the pixel pitch, and for human retina, a 100 μm spacing corresponds to a visual acuity of 20/420 [2]. Clinical results of PRIMA patients demonstrated that their prosthetic visual acuity reached up to 20/460, closely matching this theoretical limit [3].

Despite being the highest reported prosthetic acuity to date, further improvements are needed to exceed the legal blindness limit of 20/200. Rodent models have shown that with a photovoltaic subretinal array having 40 μm pixels, the grating acuity matched the pixel pitch, while with 20 μm pixels, it reached the limit of their natural resolution – 28 μm [4]. The 20 μm pixels geometrically correspond to a visual acuity of 20/80 in a human eye.

Translation of these promising results to human patients requires careful consideration of a few additional factors: 1) Unlike rodent models of retinal degeneration, human degenerate retina has a debris layer of a few tens of μm in thickness, which separates the INL from the subretinal implant [2], [5]. This layer is likely to increase the stimulation threshold and decrease resolution, compared to rodents. 2) PRIMA's success in eliciting form vision, as opposed to just light perception with many other implants, is attributed in part to the network-mediated retinal response, which preserves many features of the natural retinal signal processing [6]–[9]. Therefore, it is important to ensure that while the second-order neurons (bipolar cells) are stimulated at maximum strength and contrast, the third-order neurons (ganglion cells) are not activated directly.

Here, we present a multi-objective optimization of the structure and electrical parameters (e.g. pixel size, electrode configuration) of future implants that could provide higher visual acuity while maintaining selective activation of bipolar cells in human degenerate retina, and demonstrate the range of expected perceptual brightness, resolution and contrast in patients with various thicknesses of the subretinal debris layer.

II. METHODS

A pattern of NIR light projected from the AR glasses onto the photovoltaic subretinal MEA leads to the generation of electric field in tissue, which in turn drives the retinal neural response. To characterize this field, a Retinal Prosthesis Simulator (RPSim) was previously created. It combines the

(a)

2 mm

2 mm

(b)

W_r

Photosensitive area

W_a

(c)

I_p

C_a

R_s

R_e

C_r

(d)

Active
Return

Fig. 1: (a) PRIMA implant with $100\,\mu$m wide hexagonally tiled bipolar pixels (b) Drawing of a single bipolar pixel. W_r and W_a indicate the widths of the return and active electrodes, respectively (c) The circuit model of a single pixel labelled with design parameters: R_s, R_e - the shunt and electrolyte resistance; C_a, C_r - capacitance of the active and return electrodes; and I_p - the photocurrent (d) Drawing of a bipolar pixel with a pillar electrode.

finite element modelling of electric fields (COMSOL) with a SPICE-based circuit solver (Xyce) to simulate non-linear circuitry of multiple pixels coupled via a common electrolyte [10], [11].

This in-house simulator is expanded in this paper as part of a multi-objective optimization pipeline with the goal of finding the optimal next-generation implant design while considering several key parameters: 1) Electrical stimulation strength, which is assessed as the voltage drop across BCs [12] and is assumed to be manifested as perceptual brightness. 2) Contrast of the electrical pattern across BCs, which should be sufficient for resolving the image. 3) Electric field in the ganglion cell layer, which should be below the threshold of direct activation of retinal ganglion cells (RGCs) and their axons. 4) The design

should be robust enough to ensure proper implant performance within the expected variation in the thickness of the subretinal debris that separates the implant from the inner nuclear layer, where BCs reside. Such multi-objective optimization requires a trade-off between the various factors, and so each parameter is benchmarked to the PRIMA implant.

A. An End-to-End Implant Evaluation Platform

Each pixel on the implant can be modeled as an electrical circuit that includes active and return electrodes, a photodiode, a shunt resistor R_s and a conductive medium (Fig. 1(c)). At the operation frequency used in the PRIMA system (pulses of 1-10 ms at 30 Hz frame rate) and within the voltage range

of a Si photodiode ($< 0.6\,\mathrm{V}$), the dynamics of an electrode-tissue interface are closely approximated by a capacitor and resistor in series, where the capacitance of both the active electrode C_a and the return electrode C_r is determined by the SIROF coating of the electrodes [13]. The resistor R_e models the ohmic drop in the medium - traditionally referred to as the access resistance of the electrodes. In this diagram, the access resistances of the active and return electrodes have been combined.

Referring to the circuit model shown in Fig. 1(c), R_s, R_e, C_r, C_a, and I_p are all adjustable. C_r and C_a depend on the physical dimensions of their respective SIROF coatings. R_e depends on the geometry of the active and return electrodes. The photocurrent I_p depends on the photosensitive area of a pixel and the light intensity, and the resistor R_s is adjustable in the fabrication process. The way each of these components is adjusted affects the overall performance of the implant and finding the optimal values for these variables is the essence of this paper.

The electrode geometries that will be addressed are 1) flat, where the active and return electrodes are located on the same plane, and 2) pillars with elevated active electrodes. It will be shown that R_s has a very shallow optimum, which does not change significantly between pillar and flat geometries. This allows treating R_s independently and then fixing it for examination of the other variables since its shallow optimum limits the probability that such an optimization sequence will result in a local minimum. While not ideal, this separate treatment is necessary to keep the multidimensional search space computationally tractable. To find the optimal value for R_s, the electric field generated by Landolt C optotypes (Fig. 2(a)) was simulated using RPSim, and the stimulation strength and contrast were quantified through methods explained in section II-B below. This process was performed for arrays with 20, 40 and 55 µm pixels, and optimum values for other pixel sizes were found by interpolation.

The elementary electric fields, used as inputs to RPSim, are calculated with the finite element method platform COMSOL Multiphysics [14], and these are unique for every electrode geometry. Therefore, a COMSOL simulation must be run for every implant design under consideration. To do this, we wrote a Matlab program to automatically run a simulation with the needed configuration and generate the necessary files for RPSim using COMSOL Livelink with Matlab.

B. Evaluating Performance of the Microelectrode Array

Since PRIMA implants successfully provide form vision in human patients with an average resolution of 1.2 of the pixel pitch [3], we evaluate the next-generation arrays with smaller pixels using a pattern of tiled Landolt Cs (Fig. 2(a)) – the optotypes used in visual acuity tests. The sizes of these optotypes were selected such that their gap width corresponds to 1.2 times the pixel width tested. They are therefore 24, 36, 48, 60, 90 and 120 µm wide for pixels of 20, 30, 40, 50, 75 and 100 µm, respectively. These patterns were projected at a frequency of 30 Hz, with an on time of 9.8 ms, at an irradiance of 3 mW/mm^2, as in clinical testing [3]. The resulting electric

potential in the retina (Fig. 2(c)) was then analyzed and compared with that generated with the PRIMA implant (Fig. 2(d)).

The first objective for optimization is stimulation strength, defined as the electric potential drop from bottom to top of the bipolar cells. Neuronal stimulation can be complex to model and very nuanced, however it has been shown that for retinal bipolar cells, the voltage drop between its two ends (Fig. 2(b)) serves as a good approximation for assessment of their response [15] and acts as a surrogate of perceptual brightness.

Despite the pixelated stimulation, patients report perceiving smooth patterns, such as lines and letters. Therefore, perceptual brightness and contrast of a pattern are likely represented by some form of average over a pattern. Due to the nonlinear nature of the cellular response to polarization, it is likely a weighted summation (e.g. the classical linear-nonlinear model) rather than just a simple integral of the potential drop between two planes over the pattern. As can be seen in Fig. 2(c), the electric potential generated by the optimized arrays with smaller pixels is much more uniform than that produced by the PRIMA implant (Fig. 2(d)). Since potential within the outlined pattern in Fig. 2(d) is above the stimulation threshold, and the maximum-to-average ratio is significantly higher with the PRIMA implant, the assessment of the maximum rather than average over the pattern serves as a worst-case estimate for new implants, when compared to PRIMA. To avoid complex assumptions regarding the nonlinearity of cellular response and to provide a conservative comparison of the new implants to PRIMA, we assess the pattern brightness by the maximum potential drop across bipolar cells within it, which are above the active electrodes.

The second metric is the contrast of the resulting electric field pattern, as 'seen' by the BCs. To resolve the gap between the projected lines of a Landolt C letter, the electric field must rapidly decline near the edges of the letter. The contrast is defined as the relative difference between the average stimulation strength of the Landolt C pattern I_p and its gap I_g (Fig. 2(d)). Contrast $C = (Ip - Ig)/(Ip + Ig)$.

The third metric is neural selectivity. We aim to selectively stimulate BCs while avoiding the direct activation of RGCs, and especially of their axons, which would distort the retinotopic map of the percepts [16], [17]. It has been shown that a good predictor of axonal stimulation is the maximum drop in electric potential along the RGC axons [18]. Since PRIMA patients did not report distortions in prosthetic vision, we assume that they do not experience axonal stimulation. With new implants, we first optimized towards high neural selectivity, and then scaled the irradiance such that the drop in electric potential in the nerve fiber layer (NFL) never exceeds 20 mV, roughly matching that from PRIMA.

Fourth, OCT imaging demonstrated that, unlike rodents, in human patients the INL is separated from the implant by a layer of debris [2]. Its thickness varies between patients and within individual retinas in the range of about $25 - 55$ µm [5]. To assess the effect of the debris layer on stimulation strength and attainable resolution, we shift the location of the retinal cell by the debris thickness. For flat implants, we used a range of 20 to 57 µm. For pillar implants, their height was designed

Fig. 2: (a) The illumination pattern of tiled Landolt Cs overlaid with an implant containing 40 μm pixels (b) Visualization of the electric potential and current density resulting from the activation of a single bipolar pixel, overlaid on histology of the retina and a diagram of a bipolar cell and a ganglion cell. GCL - ganglion cell layer , IPL - inner plexiform layer, INL - inner nuclear layer. Colored arrows next to the diagrammed cells indicate the planes along which the electric potential drops (ΔV_{BC} and ΔV_{RGC}). (c) ΔV_{BC} calculated from the tiled Landolt C pattern for an optimized device with 40 μm bipolar pixels having pillar electrodes matching the debris layer thickness (d) ΔV_{BC} for a Landolt C with a 120 μm gap, generated by the PRIMA implant with 100 μm flat pixels. The solid and dotted outlines indicate the area where the electric potential is averaged for the 'on' and 'off' portions of the pattern, used to calculate contrast.

Fig. 3: Monopolar arrays of 1.5 mm in diameter, composed of 55 (a) and 20 µm (b) pixels. In the central area of the arrays, return electrodes are hidden under the insulation layer. The green ring along the edge of the implant is the exposed common return electrode. Insert in the middle of each image shows a higher magnification view of the pixels.

to match the average debris thickness of 35 µm and we varied the debris thickness above the pillars from an additional 2 to 22 µm (corresponding to the total of 57 µm). The BCs are modelled as 52 µm tall cells, starting above the debris, and the NFL is located 31 µm above the top of the BCs.

Finally, it is important to note that since electric potential is affected by crosstalk of neighboring pixels, these metrics depend on the size of the projected image. A Landolt C is considered resolvable if the stimulation strength exceeds the voltage corresponding to the highest clinical thresholds (16.4 mV [10]), and the contrast exceeds that with the PRIMA implant, calculated for the average debris.

C. Monopolar Pixels

One method for reducing the pixel size is to employ a monopolar (MP) electrode design. This involves replacing the local return mesh in each pixel with one global electrode at the periphery of an implant (Fig. 3) [10]. With this approach, the uniform activation of a disk pattern results in an electric field similar to that of a correspondingly sized disc electrode. Summation, or crosstalk, of electric fields from neighboring monopolar pixels allows generating stronger electric fields than bipolar pixels, where local electric fields are much more confined. However, much stronger crosstalk between neighboring pixels also leads to significantly lower contrast and higher electric field in the NFL.

Lowering the capacitance of the global return electrode forces the electric current to return through the shunt resistors of the non-illuminated pixels and through the diodes of the pixels charged during the previous pulse. This results in a more constrained electric field, as current does not flow as far on a return path, leading to better contrast and selectivity.

Assuming a fixed capacitance of SIROF coating on active electrodes, we can perform a one-dimensional sweep of the return electrode capacitance to examine the effects of forcing more of the current to return through nearby dark pixels. It was shown earlier that arrays of 20 µm pixels provide higher contrast, but lower stimulation strength compared to larger pixels [10]. Since the main drawback to the monopolar design is contrast, in this optimization, we sampled the return-to-active capacitance ratio from 0.01 to 5 for implants with 20 µm pixels.

D. Bipolar pixels

For bipolar pixels, R_a, C_r, C_a, and I_d can be optimized with a two-dimensional parameterized sweep, where parameters are the relative areas of the active and return electrodes in the pixel. This fully defines a pixel's geometry based on the radius of the active electrode, W_a, and the width of the return, W_r (Fig. 1(b)). Since the minimal width of the return electrode W_r is limited to 2 µm by design rules in the fabrication processes, smaller return capacitances are simulated using a thinner SIROF layer. Inability to reduce the return electrode width below 2 µm harms performance of small pixels as it decreases the photosensitive area and thereby the photocurrent. If the resolution of the fabrication process will improve, photoresponsivity of small pixels should increase.

In search of the optimum, we varied the active and return electrode sizes from 5 to 40% of the pixel area on 20, 30, 40, 50, and 75 µm pixels. These sizes were chosen to correspond to devices that have already been fabricated, and they provide a dense enough sampling for assessing the best possible resolution. From the results of this grid search, a Pareto

frontier was formed and an optimal implant was selected for each geometry with respect to the four key design parameters.

III. RESULTS AND DISCUSSION

A. Shunt resistance

The first optimized parameter was the value of the shunt resistor, R_s. Since it provides a path of return for current via neighboring dark pixels, it helps constrain the electric field and improve the image contrast. Shunt resistors also help discharge the electrode capacitance between the pulses and thereby increase the injected current during the next pulse, which increases the stimulation strength [15]. On the other hand, excessive drainage of the photocurrent through the shunt of the same pixel limits the current flowing into the tissue. These opposing effects result in an optimal shunt value when considering the stimulation strength (Fig. 4(a)).

We determined optimal R_s values for implants with monopolar and bipolar electrode configurations, of flat and pillar geometries. For 40 µm pixels, the optimal shunt value for maximizing the stimulation strength varies at most by 11% from the average of all 3 scenarios, which was around 1 MΩ (Fig. 4(a)). Due to the extremely shallow shape of this optimum, using this average value results in less than 0.4% drop of the stimulation strength compared to the exact optima for each scenario. We also found no significant changes in this value nor performance loss due to variation in retinal resistivity from 200 to 1000 Ω ∗ cm, nor for different projection patterns. The contrast for a Landolt C with a 48 µm gap is shown in Fig. 4(b). Lower shunt resistance provides higher contrast (due to better field confinement), but weaker stimulation. For example, lowering the shunt resistance to 0.5 MΩ improves the contrast of MP pillar devices from 60 to 67%, but results in a 20% decrease in stimulation strength. For the other electrode geometries, the tradeoff is even worse.

A similar process was performed for 20 and 55 µm pixels, resulting in the optima around 4 and 0.75 MΩ, respectively. Shunt resistances for 30 and 50 µm pixels were then found by interpolation (Fig. 4(c)).

B. Monopolar arrays

In the monopolar array, the local returns in each pixel are hidden under the insulator and a common return electrode covers the circumference of the implant (Fig. 3). Summation of electric fields from multiple illuminated pixels increases the penetration depth of the electric field into the tissue and reduces the contrast of the pattern, which can lead to poor neural selectivity and strong variation of the stimulation strength with the size of the projected image. As was discussed in section II-C, the stimulation selectivity and contrast can be improved by minimizing the return capacitance. This forces the current to return through local shunt resistors of inactive (dark) pixels, at the cost of lower stimulation strength. Since contrast is the limiting factor for this design, we maximized it by using the smallest modeled ratio of the return/active capacitance: 0.01. This effect largely plateaus at a ratio below 0.04, at which point any additional decrease in the ratio results

Fig. 4: (a) ΔV_{BC} and (b) contrast as a function of the shunt resistance, calculated for bipolar (BP) pillar electrodes and monopolar (MP) pillar and flat electrodes, all with 40 µm pixels (c) Optimal shunt resistance that provides the highest stimulation strength for various pixel sizes.

in a very marginal change of electric field. However, practically removing the global return in this manner comes with additional challenges as it limits the maximum illuminated area on the device (see details in supplementary information).

The expected performance for the 20 µm monopolar array with both flat and pillar electrodes is shown in Fig. 5. Stimulation strength and pattern contrast for BCs, as well as the potential drop in the RGC layer, are plotted as a function

Fig. 5: (a) BC stimulation strength, contrast and potential drop in the RGC layer as a function of the letter size (gap width in Landolt C) projected onto monopolar array with 20 μm pixels having pillar electrodes of 35 μm in height. Red, magenta and blue lines correspond to debris thickness of 37, 47 and 57 μm, respectively. Green and grey shaded zones show the stimulation thresholds of bipolar cells at 10 ms for the best and worst patients (b) Similar plots for flat arrays. The additional green line corresponds to 20 μm debris thickness.

of the Landolt C size, calculated for 3 debris thicknesses. Irradiance was scaled such that the electric potential drop in RGC layer never exceeds 20 mV (see Tables I and II). The performance of the PRIMA device in the best case (20 μm debris) and worst case (35 μm debris) is shown by horizontal dash lines for comparison, although it applies only to the largest font size (120 μm gap). Finally, the corresponding stimulation thresholds of bipolar cells (best and worst, based on clinical data [10]) are shown by colored strips. Because the irradiance must be scaled down significantly with pillar electrodes to avoid RGC stimulation, they do not offer a significant improvement in BC stimulation compared to their flat counterparts. They do, however, provide higher contrast. The stimulation of RGCs is nearly 4 times weaker with the smallest pattern than the largest. This implies that if large patterns could be avoided, the implant irradiance could be increased, thus providing significantly stronger stimulation of bipolar cells. This could be achieved by creating sparse visualizations of objects.

While the stimulation strength remains above the threshold with smaller Landolt Cs, the contrast falls below the PRIMA benchmark, which limits the utility of these devices. In the flat configuration, a 100 μm Landolt C can be resolved for patients with a thin (20 μm) debris. By employing pillar electrodes, the minimum size of a resolvable Landolt C with debris matching the pillar height is 73 μm – a 1.62 times improvement in resolution from the PRIMA implant. Even optimized, monopolar implants are still unable to provide sufficient contrast and neural selectivity to offer dramatic improvements in resolution (see details in Tables I and II).

C. Bipolar Arrays

Bipolar arrays have similar shape and size to monopolar devices, but as with the PRIMA implant shown in Fig. 1(a), a mesh of local returns in each pixel is exposed to electrolyte and there is no ring of a common return along the edge of the implant. For bipolar implants, we first found the optimum sizes of the active and return electrodes in flat arrays and those with pillar electrodes. This was accomplished with a uniform grid search. Suboptimal designs were eliminated using Pareto optimality with the objectives of maximizing the stimulation strength and the neural selectivity. This process is described in detail in the supplementary information. For most flat implants, the best performance occurs when allocating 25% and 15% of the pixel area to the active and return electrodes, respectively. The only exception was for 20 μm pixels, which

Fig. 6: (a) BC stimulation strength for bipolar arrays with 35 μm tall pillars as a function of pixel size when Landolt C gap width corresponds to 1.2 times pixel width. (b) BC stimulation strength as a function of pixel size when Landolt C size is fixed to 120 μm (c) Contrast of the pattern in BC layer corresponding to conditions in (a). Red, magenta and blue lines correspond to debris thickness of 37, 47 and 57 μm, respectively. Green and grey shaded zones show the stimulation thresholds of bipolar cells at 10 ms for the best and worst patients. Horizontal green dash line labeled "PRIMA best" indicates the performance of the PRIMA device with 20 μm debris (d, e, f) Same as in (a, b, c), but for flat bipolar pixels, with the green line showing debris thickness of 20 μm.

performed better with 30% and 10% respective allocations. Pillar implants all performed optimally with a 25% active and 20% return area allocation. For each design, the irradiance was scaled such that electric potential in the NFL remained below the axonal stimulation threshold.

Fig. 6(a,c,d,f) depicts the stimulation strength and contrast calculated for the Landolt Cs corresponding to 1.2 times the pixel width. In Fig. 6(b,e) the stimulation strength is plotted for a Landolt C of a 120 μm gap – the size resolvable with the PRIMA implant. The rightmost point on each plot shows the performance of the PRIMA implant, indicated by an empty symbol as it is not a newly optimized device. The debris thicknesses and thresholds are indicated in the same manner as in Fig. 5. On the plots for pillar devices, a horizontal green dash line indicates the PRIMA best case (20 μm debris) performance. With both flat and pillar implants, the stimulation strength diminishes quickly with decreasing pattern size. However, pillar implants maintain stimulation above the threshold for much smaller patterns than their flat counterparts. Additionally, performance with a 120 μm Landolt

C shows that percepts provided by pillar implants with small pixels will not be any dimmer than with the PRIMA device for any patterns the PRIMA implant can resolve at any debris thickness. Contrast with both flat and pillar devices also exceeds that of PRIMA for all patterns which stimulate above the threshold. This means that stimulation strength rather than contrast limits the resolution of flat bipolar implants.

Resolution limits depend on the implant geometry as well as the thickness of the debris layer and are summarized in Tables I and II. For flat implants and 37 μm thick debris, the smallest resolvable Landolt C is 62 μm - achieved by a device with 50 μm pixels. Since the stimulation strength grows dramatically with proximity to the target neurons, pillar electrodes allow better performance in nearly all respects. With a pillar height matching the debris thickness, the achievable resolution matches the sampling limit of the pixel pitch down to 20 μm. Smaller pixels therefore have the advantage when it comes to the best-case anatomies. However, as the debris thickness exceeds the pillar height, resolution declines faster with smaller pixels. For a 57 μm debris layer, 40 μm pixels

Pixel size (µm)	Monopolar flat		Bipolar flat				
	20	**40**	**20**	**30**	**40**	**50**	**75**
Irradiance (mW/mm^2)	2.5	2.0	3.0	2.6	2.2	2.2	2.3
20 µm debris	101	113	41	38	48	60	90
37 µm debris	116	120+	73	67	66	62	90
47 µm debris	120+	120+	91	77	83	89	90
57 µm debris	120+	120+	112	95	103	106	112
Average	109	113	79	69	75	79	96

TABLE I: The predicted minimal resolvable Landolt C gap sizes, in µm, for each evaluated implant design with flat electrodes and the laser irradiance used for each device to maintain the RGC voltage drop below 20 mV. The red shading represents values resolution worse than 120 µm, and excluded from the average value. Green shading highlights the best possible performance for a given debris thickness.

Pixel size (µm)	Monopolar Pillar		Bipolar Pillar				
	20	**40**	**20**	**30**	**40**	**50**	**75**
Irradiance (mW/mm^2)	1.5	1.3	2.2	2.2	2.1	2.0	2.0
37 µm debris	73	96	24	36	48	60	90
47 µm debris	89	106	48	36	48	60	90
57 µm debris	103	115	56	55	54	60	90
Average	88	106	43	42	50	60	90

TABLE II: The predicted minimal resolvable gap sizes, in µm, for each implant design with pillar electrodes of 35 µm in height and the laser irradiance used for each device to maintain the RGC voltage drop below 20 mV. Green shading highlights the best possible performance for a given debris thickness.

provide the best possible resolution of a 54 µm Landolt C gap. When considering all three debris thicknesses, 30 µm pixels provide the smallest resolvable Landolt C with an average gap width of 42 µm. If the debris layer thickness varies across the implant, patients may have slightly better or worse visual acuity in different parts of their visual field.

IV. CONCLUSIONS AND IMPACT

The geometry of active and return electrodes plays a crucial role in the efficacy and selectivity of neural stimulation. Suboptimal electrode design can result in weak stimulation, low contrast of the patterns, or the undesired stimulation of non-target cells. Conversely, an optimal design of subretinal photovoltaic arrays, as shown in this study, has the potential to improve visual acuity 2 to 5 times of what has been achieved in clinical trials. Similar considerations and models can be used for optimizing other electro-neural interfaces.

ACKNOWLEDGMENT

Daniel Palanker reports a relationship with Science Corporation that includes consulting or advisory. Daniel Palanker's patents in the field of retinal prosthesis are owned by Stanford University and licensed to Science Corporation. Other authors declare no competing financial interests that could have appeared to influence the work reported in this paper.

REFERENCES

[1] M. M. K. Muqit, Y. Le Mer, L. Olmos de Koo, F. G. Holz, J. A. Sahel, and D. Palanker, "Prosthetic visual acuity with the prima subretinal microchip in patients with atrophic age-related macular degeneration at 4 years follow-up," *Ophthalmology Science*, vol. 4, no. 5, p. 100 510, 2024, ISSN: 2666-9145. DOI: https://doi.org/10.1016/j.xops.2024.100510. [Online]. Available: https://www.sciencedirect.com/science/article/pii/S2666914524000460.

[2] D. Palanker, Y. L. Mer, S. Mohand-Said, M. Muqit, and J. Sahel, "Photovoltaic restoration of central vision in atrophic age-related macular degeneration," *Ophthalmology*, vol. 127, no. 8, pp. 1097–1104, Aug. 2020.

[3] D. Palanker, Y. L. Mer, S. Mohand-Said, and J. Sahel, "Simultaneous perception of prosthetic and natural vision in amd patients," *Nature Communications*, vol. 13, no. 513, Jan. 2022. DOI: 10.1038/s41467-022-28125-x.

[4] B. Wang, Z. Chen, M. Bhuckory, *et al.*, "Electronic photoreceptors enable prosthetic vision with acuity matching the natural resolution in rats," *Nature Communications*, vol. 13, no. 6627, Nov. 2022.

[5] M. M. K. Muqit, Y. L. Mer, F. G. Holz, and J. A. Sahel, "Long-term observations of macular thickness after subretinal implantation of a photovoltaic prosthesis in patients with atrophic age-related macular degeneration," *Journal of Neural Engineering*, vol. 19, no. 5, p. 055 011, Oct. 2022. DOI: 10.1088/1741-2552/ac9645.

[Online]. Available: https://dx.doi.org/10.1088/1741-2552/ac9645.

[6] H. Lorach, G. Goetz, R. Smith, *et al.*, "Photovoltaic restoration of sight with high visual acuity," *Nature Medicine*, vol. 21, pp. 476–482, Apr. 2015. DOI: 10.1038/nm.3851.

[7] E. Ho, R. Smith, G. Goetz, *et al.*, "Spatiotemporal characteristics of retinal response to network-mediated photovoltaic stimulation," *Journal of Neurophysiology*, vol. 119, no. 2, pp. 389–400, 2018, PMID: 29046428. DOI: 10.1152/jn.00872.2016. eprint: https://doi.org/10.1152/jn.00872.2016. [Online]. Available: https://doi.org/10.1152/jn.00872.2016.

[8] E. Ho, X. Lei, T. Flores, *et al.*, "Characteristics of prosthetic vision in rats with subretinal flat and pillar electrode arrays," *Journal of Neural Engineering*, vol. 16, no. 6, Oct. 2019. DOI: 10.1088/1741-2552/ab34b3.

[9] K. Ly, M. L. Italiano, M. N. Shivdasani, *et al.*, "Virtual human retina: Simulating neural signalling, degeneration, and responses to electrical stimulation," *Brain Stimulation*, vol. 18, no. 1, pp. 144–163, 2025, ISSN: 1935-861X. DOI: https://doi.org/10.1016/j.brs.2025.01.013. [Online]. Available: https://www.sciencedirect.com/science/article/pii/S1935861X25000154.

[10] Z. Chen, B. Wang, A. Goldstein, E. Butt, K. Mathieson, and D. Palanker, "Photovoltaic implant simulator reveals resolution limits in subretinal prosthesis," *Journal of Neural Engineering*, vol. 19, no. 5, Sep. 27, 2022. DOI: 10.1088/1741-2552/ac8ed8.

[11] N. Jensen, Z. C. Chen, A. K. Goldstein, and D. Palanker, "Accelerated simulation of multi-electrode arrays using sparse and low-rank matrix techniques," *IEEE Transactions on Biomedical Engineering*, pp. 1–10, 2025. DOI: 10.1109/TBME.2025.3541489.

[12] P. Werginz, B.-Y. Wang, Z. C. Chen, and D. Palanker, "On optimal coupling of the 'electronic photoreceptors' into the degenerate retina," *Journal of Neural Engineering*, vol. 17, no. 4, p. 045 008, Jul. 2020. DOI: 10.1088/1741-2552/aba0d2. [Online]. Available: https://dx.doi.org/10.1088/1741-2552/aba0d2.

[13] Z. C. Chen, B.-Y. Wang, and D. Palanker, "Harmonic-balance circuit analysis for electro-neural interfaces," *Journal of Neural Engineering*, vol. 17, no. 3, p. 035 001, May 2020. DOI: 10.1088/1741-2552/ab89fd. [Online]. Available: https://dx.doi.org/10.1088/1741-2552/ab89fd.

[14] *Comsol multiphysics® v. 6.2*, https://www.comsol.com, COMSOL AB, Stockholm, Sweden, 2022.

[15] D. Boinagrov, X. Lei, G. Goetz, *et al.*, "Photovoltaic pixels for neural stimulation: Circuit models and performance," *IEEE Transactions on Biomedical Circuits and Systems*, vol. 10, no. 1, pp. 85–97, 2016. DOI: 10.1109/TBCAS.2014.2376528.

[16] J. D. Weiland and M. S. Humayun, "Retinal prosthesis," *IEEE Transactions on Biomedical Engineering*, vol. 61, no. 5, pp. 1412–1424, 2014. DOI: 10.1109/TBME.2014.2314733.

[17] M. Beyeler, D. Nanduri, J. D. Weiland, A. Rokem, G. M. Boynton, and I. Fine, "A model of ganglion axon pathways accounts for percepts elicited by retinal implants," en, *Scientific Reports*, vol. 9, no. 1, p. 9199, Jun. 2019. DOI: 10.1038/s41598-019-45416-4.

[18] S. Joucla and B. Yvert, "The "mirror" estimate: An intuitive predictor of membrane polarization during extracellular stimulation," *Biophysical Journal*, vol. 96, no. 9, pp. 3495–3508, 2009, ISSN: 0006-3495. DOI: https://doi.org/10.1016/j.bpj.2008.12.3961. [Online]. Available: https://www.sciencedirect.com/science/article/pii/S0006349509005621.