Closed-form expressions for the directions of maximum modulation depth in temporal interference electrical brain stimulation.

Mariano Fernández-Corazza[1*], Sergei Turovets[2], Carlos H. Muravchik[1]

[1]LEICI Instituto de Investigaciones en Electrónica, Control y Procesamiento de Señales, Universidad Nacional de La Plata - CONICET, Argentina.

[2]NeuroInformatics Center, University of Oregon, Eugene, OR, USA.

* Correspondence: Mariano Fernández-Corazza, LEICI Instituto de Investigaciones en Electrónica, Control y Procesamiento de Señales, Facultad de Ingeniería, Universidad Nacional de La Plata, CC91 (1900), La Plata, Buenos Aires, Argentina.

E-mail: marianof.corazza@ing.unlp.edu.ar.

Abstract

In temporal interference (TI) electrical brain stimulation (EBS), an emerging neuromodulation technique, the interference of two high-frequency currents with a small frequency difference is used to target specific brain regions with better focality than in standard EBS. While the magnitude of the modulation depth has been previously investigated, an explicit formula for the directions in which this modulation is maximized has been lacking. This work provides a novel closed-form analytical expression for the orientation of maximum modulation depth in TI EBS. We also found a secondary orientation where the modulation depth has a local maximum and provide closed-form analytical formulas for this orientation as well as for the modulation depth along this orientation. To our knowledge, this is the first published closed-form expressions for these specific orientations in the context of TI stimulation. We mathematically derive these compact formulas and validate them through comprehensive computational simulations using a realistic human head model. Our simulations demonstrate that the modulation depth predicted with our new analytic direction formula of maximum modulation depth is indeed the maximum compared to other directions. The derived closed-form expression offers a faster and more precise alternative to numerical iterative optimization methods used in previous studies to estimate this direction. We also provide a complete analytical derivation of the widely used (Grossman et al., 2017) formula for the maximum modulation depth magnitude. Furthermore, we found that due to interference in 3D, the modulation depth along the secondary maximum orientation can be of similar strength than the maximum modulation depth intensity when interfering electric field vectors are significantly misaligned. Finally, we show that by modifying the ratio of the injected current

strengths, it is possible to steer these directions to fine tune the stimulation along a desired
direction of interest. Overall, this work represents a detailed treatment of TI electrical fields in
3D. The presented closed-form expressions for the directions of maximum and secondary
maximum modulation depths are relevant for the better interpretation of both simulated and
experimental results in TI studies by allowing comparison with neuronal orientations in the
brain.

Keywords: transcranial electrical stimulation, brain stimulation, temporal interference,
optimization.

1 Introduction
Electrical brain stimulation (EBS) is an emerging therapy for the treatment of neuropsychiatric
conditions such as clinical depression (Kalu et al., 2012), Parkinson's disease (Boggio et al.,
2006), anxiety and chronic pain (Mori et al., 2010). Research has also shown that EBS can be a
valuable therapeutic tool in epilepsy (Holmes et al., 2019; Yook et al., 2011), stroke
rehabilitation (Schlaug et al., 2008), and other neurological and psychiatric disorders (Brunoni
et al., 2013). It has also been extensively studied in the context of enhancing cognition
including memory and learning (Berryhill and Jones, 2012; Nitsche et al., 2003) and
psychomotor skills in military and sports contexts (Perrey, 2023; van der Groen et al., 2025).
This technique may eventually become an alternative to psychoactive drugs, as it can be more
selective than drugs by targeting specific regions of interest in the brain with minimal adverse
side effects. If applied with electrodes placed in the scalp, EBS is termed Transcranial Electrical
Stimulation (TES) or Transcranial Brain Stimulation (TBS). Even without producing direct
neuronal firing, the application of TES is capable of modifying cortical excitability (Nitsche
and Paulus, 2000; Priori et al., 1998) as well as brain rhythms and networks (Lang et al., 2005;
Priori, 2003), which is why the method is also termed Transcranial Electrical
Neuromodulation (TEN). If direct or alternating currents are used, TES is termed transcranial
direct current stimulation (tDCS) or transcranial alternating current stimulation (tACS),
respectively. Despite recent advances, ongoing debates address the clinical effectiveness of TES
(Antal et al., 2015; Horvath et al., 2015, 2014), with many issues still to be resolved, in
particular, substantial inter-subject response variability (Batsikadze et al., 2013; Wiethoff et al.,
2014). The general idea is that optimal targeting protocols and the use of subject-specific
accurate head models may enhance rigor and reproducibility in TES (Bikson et al., 2018).

Following the work by (Grossman et al., 2017), there has been a renewed interest in temporal
interference (TI) TES introduced clinically in the 1960s in the context of electrosleep (Sachkov
et al., 1967). In TI, two current injection patterns are simultaneously active, each of them
injecting a relatively high frequency (in a few KHz range) but with a low frequency difference
between them (for instance 10Hz). Each of these current injection pairs produces a different
electric field E_1 and E_2 with the idea that neither peripheral nerves nor the brain are responsive
to each of the signals separately due to its high frequency. However, the neurons of the brain
mix input signals nonlinearly and rectify the low frequency differential beating signal. The
modulation depth of the interfering fields, which is the amplitude of the low-frequency
envelope and thus also called the beating amplitude, is thought to be responsible for the

neuromodulation effects (Grossman et al., 2017). Although the field is still in the early stage of systematic experimental research, the recent TI simulations in realistic human head models have shown that neuromodulation with TI is feasible despite being attenuated by the skull like TES. In contrast to ordinary TES, it was demonstrated that TI TES can achieve increased focality and local "hot" spots in deep regions of the brain which is usually impossible in TES (even in optimal TES) where intensity of stimulation diffusively decays away from electrodes (Fernandez-Corazza et al., 2019). Focality gets even better if TI stimulation montages are optimized (Esmaeilpour et al., 2021; Howell and McIntyre, 2020; Huang et al., 2020; Lee et al., 2020). Thus, TI (and optimized TI) offers a very promising approach for specific manipulation of brain networks.

Recent studies have explored the efficacy of TI stimulation in humans (Zhu and Yin, 2023). One study investigated the effects of 20 Hz TI stimulation targeting the primary motor cortex (M1) in 40 healthy individuals (Zhu et al., 2022). Their findings indicated an enhancement in functional connectivity between M1 and secondary motor cortices during stimulation. Similarly, another work examined the impact of TI stimulation on motor cortex excitability and motor learning (Ma et al., 2022). They reported that 70 Hz TI stimulation improved reaction times in a random reaction time task and increased motor cortex excitability, while 20 Hz TI stimulation significantly enhanced motor learning in a serial reaction time task. A recent study provided further evidence of TI's potential by demonstrating non-invasive stimulation of the human hippocampus, revealing changes in memory-related functional connectivity and behavioral improvements in spatial memory tasks (Violante et al., 2023). Their study supports the feasibility of TI for targeting deep brain regions involved in cognition. Another study combined transcranial TI with virtual reality (VR) and functional magnetic resonance imaging (fMRI) to enhance spatial memory in healthy participants (Beanato et al., 2024). Participants received TI targeting the hippocampus and adjacent structures while navigating VR environments designed to test spatial memory. The study demonstrated that TI, combined with VR training, led to significant improvements in participants' ability to recall locations and navigate effectively, suggesting a potential non-invasive intervention for age-related memory decline and early-stage dementia. Despite these promising outcomes, challenges persist in the application of TI stimulation in human studies. One significant concern is the limited amplitudes of stimulation currents permissible in humans compared with animal models, which may affect the efficacy of the intervention. Additionally, inconsistencies in neurophysiological responses across studies highlight the need for further research to understand the underlying spatiotemporal distribution of the electric fields, optimize stimulation parameters, and fully understand the underlying mechanisms of TI stimulation in humans.

The spatiotemporal patterns of TI are complex and understanding them is key to developing advanced TI tools and to better interpret the experimental results. At each point in space, TI of two sinusoidal currents with frequencies f_1 and f_2 produces a vector that rotates in time with a carrier frequency $(f_1 + f_2)/2$ and an amplitude varying with frequency $(f_1 - f_2)/2$ within a plane defined by the two interfering electric field vectors, as it is pointed in our previous work (Fernández-Corazza et al., 2019) and later in (Huang, 2023). If this rotating vector is projected onto a specific predefined direction of interest, such as the predominant axonal orientation, the

formula to obtain the modulation depth is straightforward (Grossman et al., 2017). The
problem with rotation is that a dosage delivered in one predefined direction, say, parallel or
perpendicular to the cortex, might be very low even with a significant total magnitude of the
electric field. However, at each point in the brain, there exists a specific direction among all
possible orientations in which beating signal depth is maximized, resulting in the highest
dosage. This is why an analytical expression for finding this direction is important. The work
by (Grossman et al., 2017) provides a conditional formula for the expression of the maximum
intermodulation depth intensity, but it does not provide an expression for the specific direction
where this maximum intermodulation depth occurs, nor the derivation of the formula. Several
other articles simply replicate this formula without any demonstration of its origin (Rampersad
et al., 2019; von Conta et al., 2021). (Wang et al., 2022) simulated the electric fields at a
macroscopic and neuronal level, and they provide a different expression for the maximum
amplitude depth, which looks similar to that of (Grossman et al., 2017), but we show here that
they do not exactly match. (Huang and Parra, 2019) opted not to use (Grossman et al., 2017)
formulation, reverting to a numerical solution of the maximization-minimization problem by
performing a 1D brute-force search on the angle of the direction of maximum modulation
depth. (Lee et al., 2020) cite this study of (Huang and Parra, 2019) and use the same
maximization-minimization formulation, which is less efficient than (Grossman et al., 2017)
formulation. (Meng et al., 2025a) study the direction of maximum modulation, highlighting its
relevance to interpret TI results, but they also use the inefficient maximization-minimization
iterative optimization process to compute it.

In this work, we mathematically derive a compact closed-form expression for the direction of
maximum modulation depth, $\widehat{d_M}(\vec{x})$, and validate it through simulations. As the discovery of
this formula is the major novelty of this work, we show it here in advance:

25
$$\widehat{d_M}(\vec{x}) = \begin{cases} \pm\vec{E}_2(\vec{x})/|\vec{E}_2(\vec{x})| & if\ |\vec{E}_2(\vec{x})| < |\vec{E}_1(\vec{x})|\cos(\alpha) \\ \dfrac{\pm\left(\vec{E}_1(\vec{x}) - \vec{E}_2(\vec{x})\right) \times \left(\vec{E}_2(\vec{x}) \times \vec{E}_1(\vec{x})\right)}{\left|\left(\vec{E}_1(\vec{x}) - E_2(\vec{x})\right) \times \left(\vec{E}_2(\vec{x}) \times \vec{E}_1(\vec{x})\right)\right|} & otherwise \end{cases} \tag{1}$$

Where $\vec{E}_1(\vec{x})$ and $\vec{E}_2(\vec{x})$ are the amplitudes of the two interfering electric fields and α is the
angle between them, considering the same assumptions made by (Grossman et al., 2017) for
their closed-form expression of the maximum modulation depth intensity. To our knowledge,
there is no analytical expression for this direction published so far, except in one of our
conference works (Fernández-Corazza et al., 2019). With a few more steps, we provide a
complete mathematical derivation of the expression given by (Grossman et al., 2017) for the
modulation depth intensity, given its relevance in the context of TI EBS and the lack of a
derivation of it in previous TI EBS works. Finally, we also found that there is another
orientation where the modulation depth reaches a local maximum that, in some brain regions,
has a similar strength of the maximum modulation depth. As another novelty of this work, we
derive closed-form expressions of this secondary maximum modulation depth and of its
directions. To our knowledge, this was unnoticed before.

2 Modulation depth formulas

In TI, the magnitude of interest is the modulation depth, which indicates how strongly the neurons are being modulated or affected by the stimulation. In TI, a higher modulation depth means stronger potential for neuronal activation. Suppose that $\overrightarrow{EF}_{f_1}(\vec{x}, t) = \vec{E}_{f_1}(\vec{x}) \cdot \cos(2\pi f_1 t)$ and $\overrightarrow{EF}_{f_2}(\vec{x}, t) = \vec{E}_{f_2}(\vec{x}) \cdot \cos(2\pi f_2 t)$ are the two interfering electric fields that oscillate at frequencies f_1 and $f_2 = f_1 + \Delta f$, and with amplitudes $\vec{E}_{f_1}(\vec{x})$ and $\vec{E}_{f_2}(\vec{x})$, respectively. Note that the amplitudes only depend on the spatial location $\vec{x}$ and not on the time t. To simplify the formulations, we use the same assumptions made by (Grossman et al., 2017). Without loss of generality, we assume that the two interfering fields are $\overrightarrow{EF}_1(\vec{x}, t)$ and $\overrightarrow{EF}_2(\vec{x}, t)$ (instead of $\overrightarrow{EF}_{f_1}(\vec{x}, t)$ and $\overrightarrow{EF}_{f_2}(\vec{x}, t)$) with amplitudes $\vec{E}_1(\vec{x})$ and $\vec{E}_2(\vec{x})$ respectively, where $|\vec{E}_1(\vec{x})| > |\vec{E}_2(\vec{x})|$, and where the angle α between $\vec{E}_1(\vec{x})$ and $\vec{E}_2(\vec{x})$ is lower than $\frac{\pi}{2}$. Note that $\vec{E}_1(\vec{x})$ is not everywhere $\vec{E}_{f_1}(\vec{x})$ and similarly for $\vec{E}_2(\vec{x})$ and $\vec{E}_{f_2}(\vec{x})$ because at a specific position $\vec{x}$, $\vec{E}_1(\vec{x})$ is always the strongest electric field generated by one of the two frequencies f_1 or f_2, and $\vec{E}_2(\vec{x})$ is the weakest electric field generated by the other frequency. Moreover, one of the amplitudes of the two fields $\vec{E}_{f_1}(\vec{x})$ and $\vec{E}_{f_2}(\vec{x})$ might change its sign when converted to $\vec{E}_1(\vec{x})$ and $\vec{E}_2(\vec{x})$ to comply with the assumption made for α.

The modulation depth at a specific unitary direction $\hat{d}(\vec{x})$ at each point of the space $\vec{x}$, $MD_{\hat{d}}(\vec{x})$, can be calculated as a difference between constructive and destructive interference (Grossman et al., 2017):

$$|MD_{\hat{d}}(\vec{x})| = \left| \left| \left(\vec{E}_1(\vec{x}) + \vec{E}_2(\vec{x}) \right) \cdot \hat{d}(\vec{x}) \right| - \left| \left(\vec{E}_1(\vec{x}) - \vec{E}_2(\vec{x}) \right) \cdot \hat{d}(\vec{x}) \right| \right| \qquad (2)$$

Note that the expression in Eq. (2), as well as all the analysis that follows, does not depend on the time varying electric fields but only on their amplitudes. The formula of Eq. (2) is equivalent to that in (Huang et al., 2020):

$$|MD_{\hat{d}}(\vec{x})| = 2 \min\left(|\vec{E}_1(\vec{x}) \cdot \hat{d}(\vec{x})|, |\vec{E}_2(\vec{x}) \cdot \hat{d}(\vec{x})| \right) \qquad (3)$$

Now, without assuming any specific direction, the formulation for the maximum modulation depth is (Grossman et al., 2017):

$$|MD(\vec{x})| = \begin{cases} 2|\vec{E}_2(\vec{x})| & if \ |\vec{E}_2(\vec{x})| < |\vec{E}_1(\vec{x})| \cos(\alpha) \\ 2 \cdot \left| \vec{E}_2(x) \times \left(\vec{E}_1(\vec{x}) - \vec{E}_2(\vec{x}) \right) \right| / |\vec{E}_1(\vec{x}) - \vec{E}_2(\vec{x})| & otherwise \end{cases} \qquad (4)$$

However, along which direction Eq. (4) holds, which we found to be Eq. (1), was not presented before. From now on, we skip the explicit dependency on $\vec{x}$ and the upper arrow to indicate vectors to simplify the notation.

3 Deduction of maximum modulation depth direction

In Eq. (4) there are two cases: **Case I** occurs in regions of the space where the projection of E_1 onto the direction of E_2 is larger than $|E_2|$ (i.e. $|E_1|\cos{(\alpha)} > |E_2|$), depicted in Fig. 1(A); and **Case II** holds where the projection of E_1 onto the direction of E_2 is smaller than $|E_2|$ (i.e., $|E_1|\cos{(\alpha)} \leq |E_2|$), which is depicted in Fig. 1(B).

Figure 1. Schematic of Cases I (A) and II (B), where $Proj_{E_2}E_1$ denotes the projection of E_1 onto the direction of E_2, and α is the angle between the two vectors. (C) Schematic showing the directions of maximum modulation depth $\pm\widehat{d_M}$ for Case II, which are perpendicular to the $E_1 - E_2$ vector. (D) Schematic showing the directions of second maximum modulation depth $\pm\widehat{d_{M2}}$, valid for both Cases, which are perpendicular to the $E_1 + E_2$ vector. The directions perpendicular to E_1 and E_2, namely $E_1^\perp$ and $E_2^\perp$, are shown in (C) and (D) as reference because in these directions the modulation depth is zero. Note that in this figure we show the amplitudes of the electric fields as static vectors, without considering the time instance.

For two interfering sinusoidal signals in 3D, the amplitude of the interference at a given unitary direction $\hat{d}$ is given by Eq (2). The goal is to find the unitary vector $\widehat{d_M}$ where the maximum of the interference amplitude occurs by analyzing the signs of $(E_1 + E_2) \cdot \hat{d}$ and $(E_1 - E_2) \cdot \hat{d}$ for each Case. Without loss of generality, we also assume that E_2 is located on the x axis and that E_1 lies in the first quadrant, as depicted in Fig. 1. We also assume that $\widehat{d_M}$ lies in between E_1 and E_2 and that $\widehat{d_M}$ belongs to the plane defined by E_1 and E_2, as demonstrated in (Huang and Parra, 2019).

3.1 Case I

In this case, the projection of E_1 onto E_2 is larger than $|E_2|$ (Fig. 1, left). Due to $\widehat{d_M}$ lying between E_1 and E_2, $(E_1 + E_2) \cdot \widehat{d_M} > 0$. Also, because the projection of E_1 onto E_2 is larger than $|E_2|$, the projection of E_1 onto any d in between E_1 and E_2 is always larger than the projection of E_2 onto $\hat{d}$ (see Fig. 1). Thus, $(E_1 - E_2) \cdot \hat{d} = E_1 \cdot \hat{d} - E_2 \cdot \hat{d} > 0$.

Then, from Eq. (2):

$$|MD_{\hat{d}}| = |E_1 \cdot \hat{d} + E_2 \cdot \hat{d} - E_1 \cdot \hat{d} + E_2 \cdot \hat{d}| = |2E_2 \cdot \hat{d}| = 2E_2 \cdot \hat{d}, \qquad (5)$$

since $\hat{d}$ lies between E_1 and E_2 and thus the dot product $2E_2 \cdot \hat{d}$ is positive.

If we want to find the unitary direction $\widehat{d_M}$ such that $2E_2 \cdot \widehat{d_M}$ is maximum, the answer is obvious:

$$\widehat{d_M} = \frac{E_2}{|E_2|} \qquad (6)$$

Finally, replacing Eq. (6) in Eq. (5), the maximum modulation depth for Case I is:

$$|MD| = 2E_2 \cdot \frac{E_2}{|E_2|} = 2\frac{|E_2|^2}{|E_2|} = 2|E_2| \qquad (7)$$

As in (Grossman et al., 2017) formula of Eq. (4), first condition.

3.2 Case II

In this case, the projection of E_1 onto the direction of E_2 is smaller than the module of E_2 . But still, the module of E_1 is larger than the module of E_2 (Fig. 1, right). In this case, $(E_1 - E_2) \cdot \hat{d} = E_1 \cdot \hat{d} - E_2 \cdot \hat{d}$ can be either positive, negative or zero. So, we consider three subcases, II-A, II-B, and II-C respectively. We start from the case where $(E_1 - E_2) \cdot \hat{d} = 0$, which derives to $\widehat{d_M}$. Then, we show that the other two cases can be discarded.

3.2.1 Case II-A:

In this case, $(E_1 - E_2) \cdot \hat{d} = 0$, or equivalently $E_1 \cdot \hat{d} = E_2 \cdot \hat{d}$, meaning that $\hat{d}$ will be the direction in which the projections of both vectors are equal, as shown schematically in Fig. 1(C). It can be observed that $\hat{d}$ is oriented along the 'height' of the triangle with base $\overline{E_1 E_2}$. Then, to find $\widehat{d_M}$ in $\mathbb{R}^3$ we have a set of conditions:

$$\begin{cases} (E_1 - E_2) \cdot \widehat{d_M} = 0 & (a) \\ (E_2 \times E_1) \cdot \widehat{d_M} = 0 & (b) \\ |\widehat{d_M}| = 1 & (c) \end{cases} \qquad (8)$$

Condition (a) is the one of this subcase II-A, condition (b) means that $\widehat{d_M}$ belongs to the plane defined by E_1 and E_2 and condition (c) forces $\widehat{d_M}$ to be unitary. Based on the properties of the cross product: (i) $a \cdot (b \times c) = b \cdot (c \times a) = c \cdot (a \times b)$ and (ii) $a \times a = \vec{0}$, we deducted that $d_M = (E_1 - E_2) \times (E_1 \times E_2)$ satisfies conditions (a) and (b).

To verify (a), we can write $(E_1 - E_2) \cdot d_M = (E_1 - E_2) \cdot ((E_1 - E_2) \times (E_2 \times E_1))$, and using identities (i) and (ii), $(E_1 - E_2) \cdot ((E_1 - E_2) \times (E_2 \times E_1)) = (E_2 \times E_1) \cdot ((E_1 - E_2) \times (E_1 - E_2)) = (E_2 \times E_1) \cdot \vec{0} = 0$.

To verify (b), we can write $(E_2 \times E_1) \cdot d_M = (E_2 \times E_1) \cdot ((E_1 - E_2) \times (E_2 \times E_1))$, and using identities (i) and (ii), $(E_2 \times E_1) \cdot ((E_1 - E_2) \times (E_2 \times E_1)) = (E_1 - E_2) \cdot ((E_2 \times E_1) \times (E_2 \times E_1)) = (E_1 - E_2) \cdot \vec{0} = 0$.

To satisfy (c), we just normalize d_M obtaining the $\widehat{d_M}$ expression of Eq. (1), repeated here for clarity:

$$\widehat{d_M} = \frac{\pm(E_1 - E_2) \times (E_2 \times E_1)}{|(E_1 - E_2) \times (E_2 \times E_1)|} \qquad (9)$$

Eq. (9) shows the explicit formula of the direction where the maximum modulation depth of the interfering signals occurs, and it constitutes the major novelty of this work. The $\pm$ sign is because as everything is alternate current (AC), there are in fact two opposite directions where the intermodulation depth is maximum. Strictly speaking, one can refer to only one orientation of maximum modulation depth. Note that formula of Eq. (9) is not given in (Grossman et al., 2017).

We show next that Cases II-B and II-C lead lower modulation depths and thus, there is a maximum at $\widehat{d_M}$.

3.2.2 Case II-B:

In this subcase, $\hat{d}$ is in between $\widehat{d_M}$ and E_1, thus $(E_1 - E_2) \cdot \hat{d} > 0$ (see Fig. 1c). From Eq. (2),

$$|MD_{\hat{d}}| = |E_1 \cdot \hat{d} + E_2 \cdot \hat{d} - E_1 \cdot \hat{d} + E_2 \cdot \hat{d}| = |2E_2 \cdot \hat{d}| = 2E_2 \cdot \hat{d} \quad (10)$$

The last equality holds because from Fig. 2, $E_2 \cdot \hat{d}$ is always positive. But as $\widehat{d_M}$ is closer to E_2 than $\hat{d}$, then $|MD_{\hat{d}}| < |MD_{\widehat{d_M}}|$.

3.2.3 Case II-C:

In this subcase, $\hat{d}$ is in between $\widehat{d_M}$ and E_2, thus $(E_1 - E_2) \cdot \hat{d} < 0$ (see Fig. 1c). From Eq. (2),

$$|MD_{\hat{d}}| = |E_1 \cdot \hat{d} + E_2 \cdot \hat{d} + E_1 \cdot \hat{d} - E_2 \cdot \hat{d}| = |2E_1 \cdot \hat{d}| = 2E_1 \cdot \hat{d} \quad (11)$$

The last equality holds because from Fig. 2, $E_1 \cdot \hat{d}$ is always positive. But as $\widehat{d_M}$ is closer to E_1 than $\hat{d}$, then $|MD_{\hat{d}}| < |MD_{\widehat{d_M}}|$.

In summary, there is a maximum at $\widehat{d_M}$ (and at $-\widehat{d_M}$ because everything is AC). However, there are secondary maximums in the second and fourth quadrants, as shown in Section 4.

3.2.4 Derivation of Grossman et. al. formula for Case II.

Here we derive Grossman et al (2017) closed form expression for the maximum modulation depth of Case II, i.e., the bottom row of Eq. (4). Using the condition that we found $(E_1 - E_2) \cdot \widehat{d_M} = 0$ and consequently $E_1 \cdot \widehat{d_M} = E_2 \cdot \widehat{d_M}$, the maximum modulation depth from Eq. (2) can be written as:

$$|MD| = \left| |(E_1 + E_2) \cdot \widehat{d_M}| - |(E_1 - E_2) \cdot \widehat{d_M}| \right| = (E_1 + E_2) \cdot \widehat{d_M} = 2E_2 \cdot \widehat{d_M} \quad (12)$$

Using the dot product property, $|MD| = 2E_2 \cdot \widehat{d_M} = 2 \cdot |E_2| \cdot |\widehat{d_M}| \cdot \cos(\theta) = 2 \cdot |E_2| \cdot \cos(\theta)$, where θ is the angle between E_2 and $\widehat{d_M}$ (see Fig. 1c), and $|\widehat{d_M}| = 1$ because it is unitary by definition. But $\cos(\theta) = \sin\left(\frac{\pi}{2} + \theta\right)$ (a trigonometric property), and $\frac{\pi}{2} + \theta$ is the angle between $E_1 - E_2$ and E_2 (see Fig. 2). Remember that in this subcase II-A $(E_1 - E_2) \cdot \widehat{d_M} = 0$, meaning that $E_1 - E_2$ is perpendicular to $\widehat{d_M}$ (see Fig. 2). Then:

$$|MD| = 2 \cdot |E_2| \cdot \cos(\theta) = 2 \cdot |E_2| \cdot \sin\left(\frac{\pi}{2} + \theta\right) \quad (13)$$

Now, using the cross-product property $|a \times b| = |a||b||\sin(\alpha)|$, and because $\frac{\pi}{2} + \theta$ is the angle between $(E_1 - E_2)$ and E_2:

$$\sin\left(\frac{\pi}{2} + \theta\right) = \frac{|E_2 \times (E_1 - E_2)|}{|E_2||E_1 - E_2|} \quad (14)$$

Remember that $\theta < \frac{\pi}{2}$, thus $\sin\left(\frac{\pi}{2} + \theta\right)$ is always positive.

Finally, replacing Eq. (14) in Eq. (13), we get

$$|MD| = 2 \cdot |E_2| \cdot \frac{|E_2 \times (E_1 - E_2)|}{|E_2||E_1 - E_2|} = 2 \cdot \frac{|E_2 \times (E_1 - E_2)|}{|E_1 - E_2|} \quad (15)$$

Which is (Grossman et al., 2017) formula for Case II.

4   Direction of secondary modulation depth maximum

It is obvious that there are four nulls in the directions perpendicular to E_1 and to E_2, namely $E_1^\perp$ and $E_2^\perp$ respectively. These directions are shown in Fig. 1c and Fig. 1d. And because the modulation depth is always positive, there should be another two maximums between these two orientations. We found that these secondary maximums are located at the orientation perpendicular to $(E_1 + E_2)$, i.e. $d \cdot (E_1 + E_2) = 0$. We also found the closed-form expression of these directions, valid for both Cases I and II (see Fig. 1d):

$$\widehat{d_{M2}} = \frac{\pm(E_1 + E_2) \times (E_1 \times E_2)}{|(E_1 + E_2) \times (E_1 \times E_2)|} \quad (16)$$

Note that Eq. (16) is analogous to Eq. (9). Following similar steps of sections 3.2.2 and 3.2.3, considering first a direction d in between $\widehat{d_{M2}}$ and $E_2^\perp$ (i.e. $d \cdot (E_1 + E_2) > 0$), and then a direction $\hat{d}$ in between $\widehat{d_{M2}}$ and $E_1^\perp$ (i.e. $d \cdot (E_1 + E_2) < 0$) it is possible to demonstrate that there is a local maximum of the modulation depth at $\widehat{d_{M2}}$. In fact, these proofs demonstrate that there are only four maximums located at $\pm\widehat{d_M}$ and at $\pm\widehat{d_{M2}}$ in standard TI stimulation with two sinusoidal frequencies, if the two electric fields are not exactly aligned. Thus, there are no more maximums besides the ones we found. If E_1 and E_2 are exactly aligned, unlikely to occur in a real case scenario, there will be only two maximums at $\pm\widehat{d_M}$.

Moreover, following similar steps of section 3.2.4 to get Eq. (15) from Eq. (12), it is possible to obtain the modulation depth at this secondary orientation, which turns out to be:

$$\left|MD_{\widehat{d_{M2}}}\right| = 2 \cdot \frac{|(E_1 + E_2) \times E_1|}{|E_1 + E_2|} \quad (17)$$

In this case, the trigonometrical identity $\cos(\theta) = \sin\left(\frac{\pi}{2} - \beta\right)$ is used instead of $\cos(\theta) = \sin\left(\frac{\pi}{2} + \theta\right)$, where β is the angle between $\widehat{d_{M2}}$ and E_1 (see Fig. 1d). Note that Eq. (17) is

analogous to Eq. (4) – Case II, same as Eq. (15), but for the secondary maximum it is valid in both Cases I and II.

5   Validation using simulations

We validated the theoretical findings by means of computational simulations of TI TES on a finite element realistic head model with seven tissues (scalp, compact skull, marrow bone, cerebrospinal fluid, eyeballs, gray matter and white matter), ~6.5 million tetrahedra (~800 k belonging to the brain) and ~1.1 million nodes. We assigned literature conductivity values for each tissue as follows: 0.2S/m for the WM (Koessler et al., 2017), 0.006 S/m for the skull (Fernandez Corazza et al., 2018), 0.3 S/m for the scalp (Fernandez Corazza et al., 2018), 1.6S/m for the CSF (Chauhan et al., 2018), 0.45 for the GM (McCann et al., 2019) and 1.55 S/m for the eyeballs (Lindenblatt and Silny, 2001). We reused a realistic head model for electrical fields in the quasistatic approximation from a previous work, where the construction process is highly detailed (Fernandez Corazza et al., 2018).The four electrode positions for applying the two interfering patterns of 1mA each were selected to mimic the current injection pattern used in (Violante et al., 2023) for real experiments (Figs. 3a and 3b). Computations were done separately for each frequency f_1 and f_2. As a result, two independent static vector field amplitudes E_{f_1} and E_{f_2} were obtained in each tetrahedral element of the 3D head model and sorted out to form E_1 and E_2 following the assumptions described in section 2. Those static vector amplitudes due to the linearity of the Poisson equation and constant tissue conductivities represent the amplitudes of the interfering fields. Fig. 3c shows a sagittal slice at approximately the same height as the electrode locations with the regions of Case I (blue) and the regions of Case II (green).

Figure 3. (a) Left view with electrodes positions e1 and e3. (b) Right view with electrodes positions e2 and e4. The current injection pairs are e1-e2 for one frequency and e3-e4 for the other. (c) Sagittal slice of the brain (white matter and gray matter) at the approximate height of the electrode positions showing the regions where Cases I (blue) and II (green) hold.

For each tetrahedral element of the brain, we computed the modulation depth intensity in three different ways. First, we computed the maximum modulation depth direction of Eq. (1) and used it as $\hat{d}$ in Eq. (2) to compute the maximum modulation depth (Fig. 4A). Second, we

computed the modulation depth directly using (Grossman et al., 2017) formula of Eq. (4) (Fig.
4B). Third, we generated two sinusoidal waveforms at 1000Hz and at 1010Hz (sampling rate
of 40KHz and 1 second of duration), multiplied each of them by the two field amplitudes
$E_{f_1}(x)$ and $E_{f_2}(x)$ respectively obtaining the dynamic fields $EF_{f_1}(x, t)$ and $EF_{f_2}(x, t)$, computed
the sum of the electric fields at each tetrahedral element of the brain and at each time point,
projected the fields onto the optimal direction of Eq. (1) and used MATLAB's "envelope"
function to obtain the modulation depth of the envelope of the time varying signals (Fig. 4C).
It can be observed that the three ways of computing the maximum modulation depth give
identical results, thus verifying that the direction of maximum modulation depth of Eq. (1) is
correct. Note that for the first two methods (Figs. 4A and 4B), the computation does not
require simulations of the raw signals evolving with time. We also computed the modulation
depth along the secondary direction of Eq. (16) following the same three procedures, where in
the second procedure we used Eq. (17) which is the analogue to (Grossman et al., 2017)
formula of Eq. (4). In Fig. 4D we show only one image because again all three procedures for
computing this map are equal. At the regions near points "b" and "c", the intensities of the
main (Fig 4C) and the secondary (Fig 4D) maximums are almost the same, while in the region
near point "a" at the left hemisphere, the main maximum dominates over the secondary one.

Figure 4. Sagittal slices of the brain (white matter and gray matter) showing the maximum modulation depth (in
[V/m]) computed (A) using the novel closed-form expression of the maximum modulation depth direction $\widehat{d_M}$ of Eq.
(1) inserted into the general formula of Eq. (2), (B) using Grossman et al formula of Eq. (4), and (C) generating the
two raw interfering electric field waveforms projected onto the direction of Eq. (1) and computing the depth using
MATLAB's "envelope" function. Subplot (D) shows the secondary maximum modulation depth at the same scale
computed using the closed form expression of Eq. (16) inserted into Eq. (2), likewise (A). We also computed the
secondary modulation depth using Eq. (17), likewise (B), and using the waveforms, likewise (C), yielding in both
cases the exact same results as (D) (not shown). In subplots (C) and (D) we highlight three positions "a", "b" and "c"
used as representative examples.

In Fig. 5 we show, for the same slice of the brain, the orientations of the two electric field
amplitudes E_1 and E_2, plus the orientations of the main and secondary maximum modulation
depths. It can be observed that in the Case I regions, the maximum modulation depth
orientation matches one of the electric field directions (for instance, position "a" in Fig 5). In
the Case II regions, the maximum modulation depth orientation is different than the two
interfering electric fields. One interesting phenomenon can be observed in the zoomed region
of Fig. 5, where the maximum modulation depth orientation changes abruptly, as it occurs

between positions "b" and "c". It can be observed that in those cases, the main and secondary maximum modulation depth orientations are like 90 degrees apart (but not exactly) and switch positions. When the two electric fields are almost perpendicular and of similar strength, the orientation of maximum modulation depth is approximately at 45 degrees of both fields, but the direction of secondary maximum depth has also a large modulation depth. Thus, when a slight change in the angle of the fields occurs, the previous secondary direction $\widehat{d_{M2}}$ now takes the lead replacing $\widehat{d_M}$ as the one with maximum modulation depth. Overall, the switching phenomenon is smooth, but the maximum modulation depth orientation can have abrupt jumps. To illustrate this phenomenon, we plot in Fig. 6 the waveforms projected onto the orientations of maximum modulation depth $\widehat{d_M}$ and $\widehat{d_{M2}}$, for the three representative positions "a", "b" and "c" of Fig. 5.

Figure 5: Electric field orientations (E_1 in cyan and E_2 in magenta), orientation of maximum modulation depth $\widehat{d_M}$ (in black) and of secondary maximum $\widehat{d_{M2}}$ (white) for the same sagittal brain slice of Fig. 4, distinguishing where Cases I (dark gray) and II (light gray) hold (left). A zoomed version of the red rectangle region is shown in the middle and regions near the points of interest are shown on the right with an even larger zoom. In the Case I regions (dark gray), $\widehat{d_M}$ matches one of the electric fields. Note how $\widehat{d_M}$ switches to $\widehat{d_{M2}}$ when moving from "b" to "c" and vice versa. The time waveforms of representative positions "a", "b" and "c" are shown in Fig. 6. In all cases the 3D vectors are normalized and only the x and y components are depicted. $\widehat{d_M}$ and $\widehat{d_{M2}}$ lines were shortened a little bit more to improve clarity when they overlap with one electric field (such as in position "a").

Figure 6: Waveforms (blue) and envelopes (black) for three representative examples at the three locations "a" (first
column), "b" (second column) and "c" (third column) of Fig. 5 for one period of the beating amplitude variation in
time (200ms = 1/5Hz) or two periods of the envelope frequency (100ms = 1/10Hz). The top row shows the
waveforms projected onto the orientation of maximum modulation depth $\widehat{d_M}$ and the bottom row shows the
waveforms projected onto $\widehat{d_{M2}}$. The numerical value of the modulation depth is shown in the title of each subplot. In
the first column, example "a", Case I holds, and the two electric fields are almost aligned. Thus, $\widehat{d_M}$ matches one of
the electric fields and $\widehat{d_{M2}}$ is much smaller. In the second and third examples, both electric fields are almost
perpendicular and thus, the modulation depths are high for both $\widehat{d_M}$ and $\widehat{d_{M2}}$.

In Fig. 6 it is possible to observe that in all cases the envelopes at $\widehat{d_M}$ and $\widehat{d_{M2}}$ are in anti-phase
(90 degrees difference in time). This means that, at one timepoint, the peak of the beating low-
frequency signal can be at maximum along the primary direction and minimum along the
secondary direction but swap values in half of the envelope frequency (50ms in Fig. 6). Note
that the result of summing two signals at two different frequencies results in a carrier wave
with average frequency $(f_1 + f_2)/2$ (1005Hz in our simulations) that has an amplitude
modulated with a frequency $|f_1 - f_2|/2$ (5Hz). However, taking the envelope involves a
rectification process where the intensity is the square of the amplitude, resulting in an envelope
of twice the frequency, i.e. $\frac{2|f_1 - f_2|}{2} = |f_1 - f_2|$ (10Hz).

We also performed a brute force analysis where we computed for all elements of the brain the
modulation depths of the envelope of the sum of the two interfering electric fields, projected
onto ~2500 fixed directions uniformly covering the entire 4π solid angles. We compared the
modulation depths with the modulation depth of the signals projected onto $\widehat{d_M}$. In all cases, as
expected, the $\widehat{d_M}$ resulted in the largest modulation depth among all tested directions. This
serves as an empirical validation of the direction of maximum modulation depth of Eq. (1) and
of the assumptions described at the end of section 2.

In Fig. 7 we show the modulation depth for all the angles of the plane defined by E_1 and E_2
(top row) and for all the 3D directions (bottom row), at the three positions "a", "b" and "c" of

Fig. 5. The directions $\widehat{d_M}$ and $\widehat{d_{M2}}$ are also plotted and once again, we validate that they correspond to the peaks of the modulation depth. It can be observed that besides $\pm\widehat{d_M}$ and $\pm\widehat{d_{M2}}$ there are no other maximums. It is interesting to observe how the modulation depth is broader in case "a" and more focal in terms of direction in cases "b" and "c", where $\widehat{d_{M2}}$ is almost as strong as $\widehat{d_M}$. Note also how the modulation depth smoothly diminishes outside the plane defined by E_1 and E_2.

Figure 7: Examples of the brute force modulation depth calculations for positions "a" (first column), "b" (second column), and "c" (third column) of Fig. 5. The top row shows the modulation depth in the plane defined by E_1 and E_2 as a function of the angle, where directions $\pm\widehat{d_M}$ and $\pm\widehat{d_{M2}}$ are indicated with black and gray vertical lines respectively. The bottom row shows the modulation depths along all directions of a 3D sphere encoded in color. The directions of the E_1 and E_2 fields are shown as cyan and magenta arrows as well as $\widehat{d_M}$ and $\widehat{d_{M2}}$ as black and gray arrows respectively. The plane defined by E_1 and E_2 is also shown.

In previous studies it was shown that by changing the current intensity ratio between the two electrode pairs, it was possible to spatially steer the spot of maximum modulation depth slightly to one side or to another (Fernández-Corazza et al., 2019; Grossman et al., 2017). Here we show that the directions of the main and secondary maxima can also be slightly steered to one side or to the other using the same technique, as in the two examples depicted Fig. 8. In one example, we applied 1.2mA in the e1-e2 pair and 0.8mA in e3-e4 pair, and in the other we applied 0.8mA and 1.2mA in the e1-e2 and e3-e4 pairs respectively. Note that in Case I the steering might not be strong enough to modify the direction of maximum modulation depth because in this case it matches one of the electric fields. However, the secondary maximum field does steer (see zoomed region in Fig. 8, top row first column). In Case II, the steering occurs in the directions of both the main and secondary maximum modulation depth because these directions do not match any of the interfering field directions. Overall, the current injection ratio steering can be useful to easily perform a fine adjustment of either the primary or secondary maximum modulation depth directions to better align any of them to some desired direction, such as the direction of the neuronal columns.

Figure 8: Examples of the directional steering when changing the ratio of the applied current to each frequency pair, for positions "a" (first column), "b" (second column), and "c" (third column) of Fig. 5. The top row shows the modulation depths in the plane defined by E_1 and E_2 as a function of the angle for: 1.2mA in the e1-e2 pair and 0.8mA in e3-e4 pair (orange line); 0.8mA in the e1-e2 pair and 1.2mA in e3-e4 pair (purple line); and equal current injection for reference (dashed-blue line, same as Fig. 7 top row). Directions $\pm\widehat{d_M}$ and $\pm\widehat{d_{M2}}$ are indicated with black and gray vertical lines respectively. The middle row shows the modulation depths along all directions of a 3D sphere when 1.2mA and 0.8mA are applied to the e1-e2 and e3-e4 pairs respectively and the bottom row shows the modulation depth when the applied currents are 0.8mA and 1.2mA respectively. The directions of the $\pm E_1$ and $\pm E_2$ fields are shown as cyan and magenta arrows as well as $\pm\widehat{d_M}$ and $\pm\widehat{d_{M2}}$ as black and gray arrows respectively. The plane defined by E_1 and E_2 is also shown. Note that the scales are different than the scales of Fig. 7, bottom row (equal current injection).

6 Comparison with other studies

Other studies state the maximum modulation depth as a maximization-minimization problem that can be solved numerically with iterative solvers (Huang and Parra, 2019; Meng et al., 2025b), based on Eq. (3).

$$1 \qquad |MD| = \max_{\hat{d}}\{2\min\{|E_1 \cdot \hat{d}|, |E_2 \cdot \hat{d}|\}\} \qquad (18)$$

2 We showed in Section 3 that Eq. (4) is the closed-form solution to Eq. (18). Eq. (4) is preferred
3 over Eq. (18) to avoid time consuming and error prone iterative solvers.

4 Regarding closed-form expressions, (Wang et al., 2022) propose a formulation that looks
5 similar to Eq. (4) although it does not exactly match:

$$6 \qquad |MD| = \begin{cases} 2\min\{|E_1|, |E_2|\} & if\ \ |E_1||sec(\alpha)| < |E_2| < |E_1||cos(\alpha)| \\ |(E_1 + E_2) \times (n_1 - n_2)| & otherwise \end{cases} \qquad (19)$$

In Eq. (19), $n_i = \frac{E_i}{|E_i|}$ and it is not assumed that $|E_1| > |E_2|$. First, the condition $|E_1||sec(\alpha)| <$
$|E_2| < |E_1||cos(\alpha)|$ is at least misleading because it impossible to satisfy both conditions
simultaneously, since $|E_1||sec(\alpha)| < |E_1||cos(\alpha)|$ or equivalently $|E_1| < |E_1||cos(\alpha)|^2$ will
never occur ($|cos(\alpha)| < 1$ always). To match Eq. (4), if $\min\{|E_1|, |E_2|\} = |E_2|$, only the second
inequality $|E_2| < |E_1||cos(\alpha)|$ should hold (same condition of Eq. (4)), and if $\min\{|E_1|, |E_2|\} =$
$|E_2|$, only the first inequality $|E_1||sec(\alpha)| < |E_2|$ should hold. Further, the bottom-line
expression in Eq. (19) should be

$$14 \qquad |(E_1 + E_2) \times (E_1 - E_2)/|E_1 - E_2|| \qquad (20)$$

instead of $|(E_1 + E_2) \times (n_1 - n_2)|$ to match the expression of Eq. (4). Adding and subtracting
$\vec{E}_2$ to the first term of Eq. (20) we get $|(E_1 + E_2 + E_2 - E_2) \times (E_1 - E_2)/|E_1 - E_2|| =$
$|(2E_2 + (E_1 - E_2)) \times (E_1 - E_2)/|E_1 - E_2|| = |2E_2 \times (E_1 - E_2)/|E_1 - E_2||$ because $\vec{a} \times \vec{a} = \vec{0}$.
We also checked numerically that in fact both expressions from Eq. (4) and (19) are different.
Thus, we consider valid only the expression of Eq. (4) (Grossman et al., 2017).

Regarding the direction of maximum modulation depth $\widehat{d_M}$, only (Meng et al., 2025b) claim
they find it, but they do it by solving the numerical formulation of Eq. (18) and not finding a
closed-form expression as we show in this work. They claim they use these additional
equations to find $\widehat{d_M}$:

$$24 \qquad \begin{cases} \widehat{d_M} \cdot (E_1 \times E_2) \\ \widehat{d_M} \cdot E_1 = |E_1|cos\ (\alpha - \theta) \\ \widehat{d_M} \cdot E_2 = |E_2|cos\ (\theta) \end{cases} \qquad (21)$$

Where θ is the angle between $\widehat{d_M}$ and E_2. However, the expressions in Eq. (21) hold for any $\hat{d}$
within the plane defined by E_1 and E_2. Thus, expressions of Eq. (21) do not provide additional
information to define a unique $\widehat{d_M}$ in contrast to the conditions presented in in this work in Eq.
(8) that do define a unique $\widehat{d_M}$.

Moreover, no other study explicitly noted neither existence nor orientation of the secondary
maximum modulation depth $\widehat{d_{M2}}$, which we provide its closed-form expression in Eq. (17) and
a closed-form expression of its modulation depth in Eq. (18).

7 Conclusion

In this work we present closed-form expressions for the main and secondary directions of the maximum modulation depth in temporal interference brain stimulation. The direction of maximum modulation depth was not discussed in previous studies that present closed-form expressions for the maximum modulation depth (Grossman et al., 2017; Wang et al., 2022), whereas the existence and direction of the secondary maximum modulation depth was completely overlooked due to the vectorial 3D nature of temporal interference. A use of the closed form expressions presented in this work results in much faster and precise computations than using numerical iterative optimizations as done in recent studies (Huang and Parra, 2019; Meng et al., 2025b). The closed-form expressions found for two possible maxima of comparable strength and anti-phase in time provide new insights and are highly relevant for better understanding and interpretation of both synthetic and real experimental results of TI stimulation by comparing these directions with the neuronal alignment at different locations of the brain (Meng et al., 2025b). We also show that by changing the ratio of the applied currents, it is possible to steer these directions for better alignment. As secondary results, we provide a full derivation of (Grossman et al., 2017) formulation which was missing in the literature and a corrected version of (Wang et al., 2022) formulation. Finally, our analytic 3D results can be generalized beyond neuromodulation to other fields of research in physics, like radar and sensing, signal processing, radiofrequency and optical communications, acoustics and sound engineering where the notion of TI is used.

Acknowledgements

This work was supported by the ANPCyT PICT 2019- 0701, UNLP 11/EI-003, CONICET PIP 11220200101515CO. MFC wants to thank PhD. S. Collavini, PhD. D. Dellavale and PhD. E. Urdapilleta for their helpful input on specific aspects of this paper.

Conflicts of interest

Authors declare that they have no conflicts of interest.

References

Antal, A., Keeser, D., Priori, A., Padberg, F., Nitsche, M.A., 2015. Conceptual and Procedural Shortcomings of the Systematic Review "Evidence That Transcranial Direct Current Stimulation (tDCS) Generates Little-to-no Reliable Neurophysiologic Effect Beyond MEP Amplitude Modulation in Healthy Human Subjects: A Systematic R. Brain Stimul. 8, 846–849. https://doi.org/10.1016/j.brs.2015.05.010

Batsikadze, G., Moliadze, V., Paulus, W., Kuo, M.-F., Nitsche, M.A., 2013. Partially non-linear stimulation intensity-dependent effects of direct current stimulation on motor cortex excitability in humans. J. Physiol. 591, 1987–2000. https://doi.org/10.1113/jphysiol.2012.249730

Beanato, E., Moon, H.-J., Windel, F., Vassiliadis, P., Wessel, M.J., Popa, T., Pauline, M., Neufeld, E., De Falco, E., Gauthier, B., Steiner, M., Blanke, O., Hummel, F.C., 2024. Noninvasive modulation of the hippocampal-entorhinal complex during spatial navigation in humans. Sci. Adv. 10. https://doi.org/10.1126/sciadv.ado4103

Berryhill, M.E., Jones, K.T., 2012. tDCS selectively improves working memory in older adults with
more education. Neurosci Lett 521, 148–151. https://doi.org/10.1016/j.neulet.2012.05.074

Bikson, M., Brunoni, A.R., Charvet, L.E., Clark, V.P., Cohen, L.G., Deng, Z.-D., Dmochowski, J.,
Edwards, D.J., Frohlich, F., Kappenman, E.S., Lim, K.O., Loo, C., Mantovani, A., McMullen,
D.P., Parra, L.C., Pearson, M., Richardson, J.D., Rumsey, J.M., Sehatpour, P., Sommers, D.,
Unal, G., Wassermann, E.M., Woods, A.J., Lisanby, S.H., 2018. Rigor and reproducibility in
research with transcranial electrical stimulation: An NIMH-sponsored workshop. Brain Stimul. 11,
465–480. https://doi.org/10.1016/j.brs.2017.12.008

Boggio, P.S., Ferrucci, R., Rigonatti, S.P., Covre, P., Nitsche, M., Pascual-Leone, A., Fregni, F., 2006.
Effects of transcranial direct current stimulation on working memory in patients with Parkinson's
disease. J Neurol Sci 249, 31–38.

Brunoni, A.R., Fregni, F., Priori, A., Ferrucci, R., Boggio, P.S., 2013. Transcranial direct current
stimulation: challenges, opportunities and impact on psychiatry and neurorehabilitation. Front.
Psychiatry 4. https://doi.org/10.3389/fpsyt.2013.00019

Chauhan, M., Indahlastari, A., Kasinadhuni, A.K., Schar, M., Mareci, T.H., Sadleir, R.J., 2018. Low-
Frequency Conductivity Tensor Imaging of the Human Head In Vivo Using DT-MREIT: First
Study. IEEE Trans. Med. Imaging 37, 966–976. https://doi.org/10.1109/TMI.2017.2783348

Esmaeilpour, Z., Kronberg, G., Reato, D., Parra, L.C., Bikson, M., 2021. Temporal interference
stimulation targets deep brain regions by modulating neural oscillations. Brain Stimul. 14, 55–65.
https://doi.org/10.1016/j.brs.2020.11.007

Fernández-Corazza, M., Turovets, S., Luu, P., Tucker, D., 2019. Abstract #102: Temporal Interference
Transcranial Electrical Stimulation in Humans: Actual Doses and Steerability. Brain Stimul. 12,
e35. https://doi.org/10.1016/j.brs.2018.12.109

Fernandez-Corazza, M., Turovets, S., Muravchik, C., 2019. Spatial sensitivity of the optimal dose in
transcranial electrical stimulation to the skull and scalp conductivity specifications. Brain Stimul.
12, 581. https://doi.org/10.1016/j.brs.2018.12.927

Fernandez Corazza, M., Turovets, S., Luu, P., Price, N., Muravchik, C.C.H., Tucker, D., 2018. Skull
Modeling Effects in Conductivity Estimates Using Parametric Electrical Impedance Tomography.
IEEE Trans. Biomed. Eng. 65, 1785–1797. https://doi.org/10.1109/TBME.2017.2777143

Grossman, N., Bono, D., Dedic, N., Kodandaramaiah, S.B., Rudenko, A., Suk, H.J., Cassara, A.M.,
Neufeld, E., Kuster, N., Tsai, L.H., Pascual-Leone, A., Boyden, E.S., 2017. Noninvasive Deep
Brain Stimulation via Temporally Interfering Electric Fields. Cell 169, 1029-1041.e16.
https://doi.org/10.1016/j.cell.2017.05.024

Holmes, M.D., Feng, R., Wise, M. V., Ma, C., Ramon, C., Wu, J., Luu, P., Hou, J., Pan, L., Tucker,
D.M., 2019. Safety of slow-pulsed transcranial electrical stimulation in acute spike suppression.
Ann. Clin. Transl. Neurol. 6, 2579–2585. https://doi.org/10.1002/acn3.50934

Horvath, J.C., Carter, O., Forte, J.D., 2014. Transcranial direct current stimulation: five important
issues we aren't discussing (but probably should be). Front. Syst. Neurosci. 8.
https://doi.org/10.3389/fnsys.2014.00002

Horvath, J.C., Forte, J.D., Carter, O., 2015. Evidence that transcranial direct current stimulation (tDCS)
generates little-to-no reliable neurophysiologic effect beyond MEP amplitude modulation in
healthy human subjects: A systematic review. Neuropsychologia 66, 213–236.
https://doi.org/10.1016/j.neuropsychologia.2014.11.021

Howell, B., McIntyre, C.C., 2020. Feasibility of Interferential and Pulsed Transcranial Electrical
Stimulation for Neuromodulation at the Human Scale. Neuromodulation 2020.

https://doi.org/10.1111/ner.13137

Huang, Y., 2023. Visualizing interferential stimulation of human brains. Front. Hum. Neurosci. 17. https://doi.org/10.3389/fnhum.2023.1239114

Huang, Y., Datta, A., Parra, L.C., 2020. Optimization of interferential stimulation of the human brain with electrode arrays. J. Neural Eng. https://doi.org/10.1088/1741-2552/ab92b3

Huang, Y., Parra, L.C., 2019. Can transcranial electric stimulation with multiple electrodes reach deep targets? Brain Stimul. 12, 30–40. https://doi.org/10.1016/j.brs.2018.09.010

Kalu, U.G., Sexton, C.E., Loo, C.K., Ebmeier, K.P., 2012. Transcranial direct current stimulation in the treatment of major depression: a meta-analysis. Psychol. Med. 42, 1791–1800. https://doi.org/10.1017/S0033291711003059

Koessler, L., Colnat-Coulbois, S., Cecchin, T., Hofmanis, J., Dmochowski, J.P., Norcia, A.M., Maillard, L.G., 2017. In-vivo measurements of human brain tissue conductivity using focal electrical current injection through intracerebral multicontact electrodes. Hum. Brain Mapp. 38, 974–986. https://doi.org/10.1002/hbm.23431

Lang, N., Siebner, H.R., Ward, N.S., Lee, L., Nitsche, M.A., Paulus, W., Rothwell, J.C., Lemon, R.N., Frackowiak, R.S., 2005. How does transcranial DC stimulation of the primary motor cortex alter regional neuronal activity in the human brain? Eur J Neurosci 22, 495–504.

Lee, S., Lee, C., Park, J., Im, C.H., 2020. Individually customized transcranial temporal interference stimulation for focused modulation of deep brain structures: a simulation study with different head models. Sci. Rep. 10, 1–11. https://doi.org/10.1038/s41598-020-68660-5

Lindenblatt, G., Silny, J., 2001. A model of the electrical volume conductor in the region of the eye in the ELF range. Phys. Med. Biol. 46, 3051–9.

Ma, R., Xia, X., Zhang, W., Lu, Z., Wu, Q., Cui, J., Song, H., Fan, C., Chen, X., Zha, R., Wei, J., Ji, G.-J., Wang, X., Qiu, B., Zhang, X., 2022. High Gamma and Beta Temporal Interference Stimulation in the Human Motor Cortex Improves Motor Functions. Front. Neurosci. 15. https://doi.org/10.3389/fnins.2021.800436

McCann, H., Pisano, G., Beltrachini, L., 2019. Variation in Reported Human Head Tissue Electrical Conductivity Values. Brain Topogr. https://doi.org/10.1007/s10548-019-00710-2

Meng, W., Zhang, C., Wu, C., Huo, X., Zhang, G., 2025a. Direction of TIS envelope electric field: Perpendicular to the longitudinal axis of the hippocampus. J. Neurosci. Methods 418, 110416. https://doi.org/10.1016/j.jneumeth.2025.110416

Meng, W., Zhang, C., Wu, C., Huo, X., Zhang, G., 2025b. Direction of TIS envelope electric field: Perpendicular to the longitudinal axis of the hippocampus. J. Neurosci. Methods 418, 110416. https://doi.org/10.1016/j.jneumeth.2025.110416

Mori, F., Codecà, C., Kusayanagi, H., Monteleone, F., Buttari, F., Fiore, S., Bernardi, G., Koch, G., Centonze, D., 2010. Effects of Anodal Transcranial Direct Current Stimulation on Chronic Neuropathic Pain in Patients With Multiple Sclerosis. J. Pain 11, 436–442. https://doi.org/10.1016/j.jpain.2009.08.011

Nitsche, M.A., Paulus, W., 2000. Excitability changes induced in the human motor cortex by weak transcranial direct current stimulation. J. Physiol. 527, 633–639. https://doi.org/10.1111/j.1469-7793.2000.t01-1-00633.x

Nitsche, M.A., Schauenburg, A., Lang, N., Liebetanz, D., Exner, C., Paulus, W., Tergau, F., 2003. Facilitation of implicit motor learning by weak transcranial direct current stimulation of the

primary motor cortex in the human. J. Cogn. Neurosci. 15, 619–626.
https://doi.org/10.1162/089892903321662994

Perrey, S., 2023. Probing the Promises of Noninvasive Transcranial Electrical Stimulation for Boosting Mental Performance in Sports. Brain Sci. 13, 282. https://doi.org/10.3390/brainsci13020282

Priori, A., 2003. Brain polarization in humans: A reappraisal of an old tool for prolonged non-invasive modulation of brain excitability. Clin Neurophysiol 114, 589–595.

Priori, A., Berardelli, A., Rona, S., Accornero, N., Manfredi, M., 1998. Polarization of the human motor cortex through the scalp. Neuroreport 9, 2257–2260. https://doi.org/10.1097/00001756-199807130-00020

Rampersad, S., Roig-Solvas, B., Yarossi, M., Kulkarni, P.P., Santarnecchi, E., Dorval, A.D., Brooks, D.H., 2019. Prospects for transcranial temporal interference stimulation in humans: A computational study. Neuroimage 202, 116124. https://doi.org/10.1016/j.neuroimage.2019.116124

Sachkov, V.I., Liventsev, N.M., Kuzin, M.I., Zhukovskii, V.D., 1967. Experiences with combined electronarcosis with interference currents in clinical surgery, in: Wagender, F.M., Schuy, S. (Eds.), Electrotherapeutic Sleep and Electroanesthesia. Medica Foundation, pp. 321–326.

Schlaug, G., Renga, V., Nair, D., 2008. Transcranial direct current stimulation in stroke recovery. Arch Neurol 65, 1571–1576. https://doi.org/10.1001/archneur.65.12.1571

van der Groen, O., Rafique, S.A., Willmot, N., Murphy, M.G., Tisnovsky, E., Brunyé, T.T., 2025. Transcutaneous and transcranial electrical stimulation for enhancing military performance: an update and systematic review. Front. Hum. Neurosci. 19. https://doi.org/10.3389/fnhum.2025.1501209

Violante, I.R., Alania, K., Cassarà, A.M., Neufeld, E., Acerbo, E., Carron, R., Williamson, A., Kurtin, D.L., Rhodes, E., Hampshire, A., Kuster, N., Boyden, E.S., Pascual-Leone, A., Grossman, N., 2023. Non-invasive temporal interference electrical stimulation of the human hippocampus. Nat. Neurosci. 26, 1994–2004. https://doi.org/10.1038/s41593-023-01456-8

von Conta, J., Kasten, F.H., Ćurčić-Blake, B., Aleman, A., Thielscher, A., Herrmann, C.S., 2021. Interindividual variability of electric fields during transcranial temporal interference stimulation (tTIS). Sci. Rep. 11, 20357. https://doi.org/10.1038/s41598-021-99749-0

Wang, B., Aberra, A.S., Grill, W.M., Peterchev, A. V, 2022. Responses of model cortical neurons to temporal interference stimulation and related transcranial alternating current stimulation modalities. J. Neural Eng. 19, 066047. https://doi.org/10.1088/1741-2552/acab30

Wiethoff, S., Hamada, M., Rothwell, J.C., 2014. Variability in Response to Transcranial Direct Current Stimulation of the Motor Cortex. Brain Stimul. 7, 468–475. https://doi.org/10.1016/j.brs.2014.02.003

Yook, S.-W., Park, S.-H., Seo, J.-H., Kim, S.-J., Ko, M.-H., 2011. Suppression of Seizure by Cathodal Transcranial Direct Current Stimulation in an Epileptic Patient - A Case Report -. Ann Rehabil Med 35, 579–582. https://doi.org/10.5535/arm.2011.35.4.579

Zhu, Z., Xiong, Y., Chen, Y., Jiang, Y., Qian, Z., Lu, J., Liu, Y., Zhuang, J., 2022. Temporal Interference (TI) Stimulation Boosts Functional Connectivity in Human Motor Cortex: A Comparison Study with Transcranial Direct Current Stimulation (tDCS). Neural Plast. 2022, 1–7. https://doi.org/10.1155/2022/7605046

Zhu, Z., Yin, L., 2023. A mini-review: recent advancements in temporal interference stimulation in modulating brain function and behavior. Front. Hum. Neurosci. 17.

1   https://doi.org/10.3389/fnhum.2023.1266753