Distinct cortical encoding of acoustic and electrical cochlear stimulation

Ariel Edward Hight[1-3], Michele N. Insanally[2-5], Julia K. Scarpa[2,3], Yuko Tamaoki[1-3], Rohit Makol[1-3,6], Yew-Song Cheng[2], Michael Trumpis[7], Jonathan Viventi[7-10], Mario A. Svirsky[1-3,*], and Robert C. Froemke[1-3,*]

[1] Translational Neuroscience Institute, New York University Grossman School of Medicine, New York, NY 10016;

[2] Department of Otolaryngology-Head and Neck Surgery, New York University Grossman School of Medicine, New York, NY 10016;

[3] Department of Neuroscience, New York University Grossman School of Medicine, New York, NY 10016;

[4] Department of Otolaryngology, University of Pittsburgh School of Medicine, PA 15213;

[5] Department of Neurobiology, University of Pittsburgh School of Medicine, PA 15213

[6] University of Connecticut School of Medicine, CT 06030

[7] Department of Biomedical Engineering, Duke University, Durham, NC, USA

[8] Department of Neurobiology, Duke University School of Medicine, Durham, North Carolina, USA

[9] Department of Neurosurgery, Duke University School of Medicine, Durham, North Carolina, USA

[10] Department of Neurology, Duke University School of Medicine, Durham, North Carolina, USA

*, co-corresponding authors: robert.froemke@med.nyu.edu, mario.svirksy@med.nyu.edu

Abstract

Cochlear implants are neuroprosthetic devices that restore hearing and speech comprehension to profoundly deaf humans, and represent an exemplar application of biomedical engineering and research to clinical conditions. However, the utility of these devices in many subjects is limited, largely due to lack of information about how neural circuits respond to implant stimulation. Recently we showed that deafened rats can use cochlear implants to recognize sounds, and that this training refined the responses of single neurons in the primary auditory cortex. Here we asked how local populations of cortical neurons represent acute implant stimuli, using electrode arrays we developed for cortical surface recordings for micro-electrocorticography (μECoG), a form of intracranial electroencephalography (iEEG). We found that there was a limited tonotopic organization across recording sites, relative to a clearer tonotopic spatial representation in normal-hearing rats. Single-trial iEEG responses to acoustic inputs were more reliable than responses to cochlear implant stimulation, although stimulus identity could be successfully decoded in both cases. However, the spatio-temporal response profiles to acoustic vs cochlear implant stimulation were substantially different. Decoders trained on acoustic responses showed essentially zero information transfer when tested on electrical stimulation responses in the same animals after deafening and cochlear implant stimulation. Thus while acute cochlear implant stimulation might activate the auditory cortex in a cochleotopic manner, the dynamics of network activity are quite distinct, suggesting that pitch percepts from acoustic and electrical stimulation are fundamentally different.

Introduction

Cochlear implants are neuroprosthetic devices that restore hearing and provides users with an ability to attain open-set speech perception without other aids such as lip-reading (Djourno and Eyries, 1957; Simmons et al., 1965; Michelson, 1971; House and Urban, 1973; Eddington et al., 1978; Hochmair and Hochmair-Desoyer, 1981; Wilson et al., 1991; Clark, 2006; Svirsky, 2017). Cochlear implants function by inserting a single and flexible shank of electrodes along the cochlear spiral (generally 12-22 channels in human subjects), to stimulate primary afferent neurons of the auditory system and bypass pathologies of deafness. Individual electrodes deliver trains of electrical pulses, providing spectral cues as a function of location along the topographical axis of the cochlear spiral, mimicking the encoding of sound in a functional and healthy cochlea. Over 1 million users have been implanted world-wide, making it the most widely adopted type of brain-computer interface, surpassing vagus nerve stimulators, deep-brain stimulation electrodes, and artificial retinas (Hays et al., 2013; Dawson et al., 2016; Ayton et al., 2020; Zeng, 2022; Johnson et al., 2024). Cochlear implants are thus the gold-standard for neuroprosthetic device use in terms of performance, safety, and ability to fine-tune or personalize the programming of each device to individual users.

Despite their wide adoption in human subjects over the last several decades, there is limited understanding of how these devices restore functionality and the sense of hearing to users. One long-standing question has been how the central auditory system responds to and interprets signals resulting from electrical stimulation of auditory nerve fibers. It is unknown to what degree emulating the patterns evoked by acoustic stimulation in normal hearing users is important for the auditory system to interpret patterns of evoked neural activity and inform downstream auditory

perception. Many structures of the central auditory system are organized tonotopically, following

the frequency alignment of the cochlear basilar membrane (Walzl and Woolsey, 1946; Merzenich

et al., 1973; Polley et al., 2007). This topographic mapping might facilitate the encoding of

auditory stimuli. While previous studies have demonstrated cochleotopic organization in auditory

cortex of cochlear implant animals (Bierer and Middlebrooks, 2002; Johnson et al., 2016), a

fundamental question remains unanswered: does electrical stimulation of specific cochlear

locations elicit the same cortical representations and perceptual qualities as acoustic stimulation of

corresponding frequencies? The spatiotemporal dynamics of these representations and how they

relate to acoustic processing in normal hearing individuals remain unclear. Previous

psychophysical studies in human implant users have provided indirect evidence for perceptual

differences (McDermott, 2004) and similarities (Vermeire et al., 2013), but direct neural evidence

comparing representations in the same subjects has been lacking. This question has profound

implications for how we design and program cochlear implants, or more generally other brain-

computer interface devices.

Studies in non-human animals are required to understand the neural basis of cochlear implant use

and the relation to spatiotemporal representations in the auditory system. Responses to cochlear

implant stimulation have been studied in a number of species generally in non-behaving animals

under anesthesia (Klinke et al., 1999; Bierer and Middlebrooks, 2002; Middlebrooks and Bierer,

2002; Fallon et al., 2014; Johnson et al., 2016, Adenis et al. 2024), but occasionally in awake or

behaving animals (Vollmer and Beitel, 2011; Keating et al., 2013; Johnson et al., 2016). Over the

last decade we have examined cochlear implant responses in deafened rats (King et al., 2016;

Glennon et al., 2019), where we showed that animals can be trained to report the activation of

specific implant channels. Behavioral training with the cochlear implant led to substantial

plasticity within the deafened rat auditory cortex, modifying synaptic receptive fields and adjusting

excitatory-inhibitory balance at the level of single neurons. Prior to training, the responses of single

cells to implant stimulation were erratic and inhibition was mismatched relative to excitation. After

training, inhibition became aligned with excitation across the array of implant electrode channels

(Glennon et al., 2023). However, intracellular recording in vivo is infeasible in human subjects.

Thus other approaches more amenable to clinical use are required, to measure neural coding of

cochlear implant signals and enable translation of results from non-human studies to improve

implant performance by human subjects.

Here we aimed to determine the spatiotemporal representations of implant channels beyond the

responses of single neurons, but instead across a broader extent of rat auditory cortex. We take

advantage of improvements in micro-electrocorticography (μECoG), a sub-type of intracranial

electroencephalography (iEEG) that generally uses grid electrodes placed epi- or sub-durally over

the cortical surface to measure local electrical activity (Insanally et al., 2016; Woods et al. 2018).

iEEG recordings have high temporal precision, greatly improved signal-noise ratios, and better

spatial resolution than conventional scalp EEG recordings (Abdi-Sargezeh et al., 2023; Janiukstyte

et al., 2023). Signals reflect local electrical fields generated by aggregate neural activity in the

regions adjacent to recording sites (Jasper and Penfield, 1949; Chang, 2015; Fukushima et al.,

2015). iEEG has been used for studies of human brain organization particularly of speech and

language centers, but these recordings are necessarily done in epileptic subjects to help locate

seizure foci before surgical resection (Nourski et al., 2013; Mesgarani et al., 2014; Tang et al.,

2017; Beynon et al., 2021; Norman-Haignere et al., 2022). Non-human animal studies remain

essential for determining how sensory inputs are represented and processed in subjects without

overt neurological conditions. To this end, we have designed and manufactured a novel and

flexible 60-channel cortical surface iEEG array for adult rats, and validated that we can measure

auditory responses and cortical map topography in normal hearing animals with these arrays

(Insanally et al., 2016; Trumpis et al., 2017; Woods et al. 2018). Using these custom-fabricated

iEEG grid electrodes, we now ask how auditory cortex responds to implant stimulation in untrained

or trained deafened adult rats, and how different evoked signals and/or mesoscale tonotopic

organization is in cochlear implant users vs normal-hearing animals.

Materials and Methods

Surgical procedure for iEEG recordings. All animal procedures were performed in accordance

with National Institutes of Health standards and were conducted under a protocol approved by the

NYU Grossman School of Medicine Institutional Animal Care and Use Committee. We used a

custom array consisting of 61 passive electrodes spaced 406 μm apart in an 8 x 8 grid, with three

corner electrodes omitted and the fourth corner electrode intentionally unexposed to test

encapsulation, reducing the number of active recorded sites to 60 (Insanally et al., 2016). iEEG

grids were fabricated using a standard flex-PCB processing technique by Microconnex Flex

Circuits (Snoqualmie, WA). All procedures and experiments were carried out in a sound-

attenuation chamber and under anesthesia.

A specific surgical protocol was developed for implantation of cortical surface iEEG in

rats. Sprague-Dawley rats 4–6 months old were anesthetized with ketamine (40 mg kg−1,

intramuscular injection) and dexmedetomidine (0.125 mg kg−1, intramuscular injection), or

pentobarbital (50 mg kg−1, intraperitoneal injection). The head was secured in a custom head-

holder that left the ears unobstructed. A longitudinal incision was made along the midline to expose

the skull. Five bone screws were inserted into the skull around the point of entry of the electrode

array to help anchor the dental cement (C & B Metabond Quick! Luting Cement). After reflecting

the right temporalis muscle, a 5 mm × 5 mm craniotomy was made on the right temporal skull to

expose the brain, and a sterilized iEEG array was epidurally placed over the left hemisphere core

auditory cortex, located using vasculature landmarks. A thin silver wire was soldered between the

headstage and the skull screws to be used as ground and reference.

Surgical procedure unilateral cochlear implantation of the right ear. Cochlear implantation

procedures are similar to our past studies (King et al., 2016; Glennon et al., 2023). 8-channel

animal cochlear implant arrays (HL08) were provided by Cochlear Americas. The array contained

platinum-iridium band electrodes coated in silastic and connected to a nine-pin Nanonics

connector (TE Connectivity, Berwyn, PA) with a single, additional extracochlear ball ground. The

ipsilateral pinna was pulled forward and secured with a hemostat, the head rotated laterally, and

the post-auricular junction between the ear canal and the sternocleidomastoid muscle (SCM) is

identified as the initial incision site. An incision was made and the superficial fascia of the neck

was dissected to identify the facial nerve i.e., cranial nerve (CN) VII. Minor bleeding was

controlled using hemostatic epinephrine-soaked cotton pellets (Epidri pellets; Pascal International,

Bellevue, WA), applied with light pressure. The SCM and posterior belly of the digastric muscle

(PBD) were dissected from the tympanic bulla (TB) ventral and rostral to the trunk of CN VII. The

TB was cleared of muscle and periosteum; the periosteum of the bulla was kept in normal saline

and used later to seal the cochleostomy site. The drilling of the TB was begun ventrorostral to the

trunk of CN VII with a 0.5 mm diamond burr and continued dorsally with care taken to avoid

injuring CN VII, until the SA overlying the RW was fully visualized. Any remaining tissue or

debris was removed with microforceps before the cochleostomy was performed.

Prior to performing the cochleostomy and inserting the array, the array lead and connector

were secured. The post-auricular incision was expanded dorsally toward the skull. An area 4-5 mm

in diameter was cleared and cleaned to expose the occipital skull, and the connector was attached

perpendicular to the skull using C&B-Metabond (Parkell, Edgewood, NY) and bone screws. The

lead to the electrode array was then sutured to the trapezius muscle, allowing enough lead to remain

free to facilitate motion required for array insertion. The lead to the separate ground electrode was

similarly secured into small muscle pockets in the trapezius. The cochleostomy site was identified

~0.5 mm directly below the lip of the RW in the basal turn of the cochlea, identified by both the

stapedial artery and the cochlear promontory in the tympanic space. The site was gently drilled

with a 0.1 mm diamond burr, and the array was inserted into the scala tympani without resistance

using AOS forceps (Cochlear, Sydney, Australia) until all of the platinum-iridium contacts were

within the scala tympani. We required that all eight electrodes pass through the cochleostomy,

confirming that the array was inserted in the direction of the apex. The array occludes most, if not

all, of the drill site, but to minimize postsurgical perilymphatic leak strips of periosteum taken

from the bulla were placed around the implant to seal the site, followed by application of high-

grade cyanoacrylate (Surgi-lock 2oc; Meridian Animal Health, Omaha, NE). The remaining lead

was cemented into the bulla with C&B-Metabond (Parkell). Before closure, a small square of

gelfoam with dexamethasone was left on the root of the facial nerve to prevent inflammation and

heal any minor damage that may have occurred.

Bilateral sensorineural hearing loss. The deafening procedure (mechanical only, as described

and validated in Glennon et al. 2023) was identical to the cochlear implantation procedure, with

the exception of the array being removed before closure. Following both array and gelfoam

removal, the cochleostomy site was closed with a trapezius muscle or periosteum graft, followed

by 2-octyl cyanoacrylate (i.e., the array is removed from the cochlea). Both ears were deafened in

this manner, but a functional array remained in the right ear for acute electrical stimulation.

Behavioral training for tone and implant channel detection. Four animals with iEEG recording

electrodes were behaviorally trained to detect target tones. Rats were food restricted and trained

on a self-initiated, auditory go/no-go task (Froemke et al., 2013; Martins and Froemke, 2015; King

et al., 2016). Animals nosepoked in a designated port to initiate trials and are trained to nosepoke

in a different port if the target tone was presented (22.6 kHz, any intensity) or withhold from

nosepoking if a nontarget (foil) tone was presented (0.5-32 kHz excluding 4 kHz if 4 kHz was the

target, or 8-45.3 kHz excluding 22.6 kHz if 22.6 kHz was the target, at 0.5-1 octave intervals and

at any intensity). A sugar pellet reward was given for correct nosepokes within 2.5 s of target-tone

presentation, whereas a 7 s timeout was given if the animal incorrectly nosepoked for foil tones.

The four rats that achieved >70% target-tone hit rate and d' ≥1.7 were included for further testing

and implantation. A second subset of three animals was behaviorally trained to detect cochlear

implant channel 3 (n=2) or channel 4 (n=1); procedures were the same for tones except that a

programmable clinical cochlear implant processor was used. These animals were trained for 3, 9,

and 13 days.

Stimulus presentation for cortical sensory mapping in normal hearing rats. Tone presentation

was similar to our previous study of iEEG responses in normal-hearing rats (Insanally et al., 2016).

Pure tones 50 ms in duration with 2 ms cosine-squared ramps ranging from 0.5-32 kHz (0.5 octave

spacing) were generated using an auditory processor (TDT System III RZ6) and presented at a

pseudorandom sequence at a rate of 1.25 Hz to the contralateral (right) ear using a calibrated free-

field speaker (MF1 Multi-Field Magnetic Speaker, Tucker-Davis Technologies). Each tone was

repeated 30 times at 70 dB SPL. The calibrated speaker exhibited <1% harmonic distortion and a

flat output in the frequency range used.

Stimulus presentation for cortical sensory mapping in cochlear implanted rats. Electrical

stimulation was delivered by an off-the-shelf Nucleus Freedom system speech processor

(Cochlear) in which its transmitter coil drove a CI24RE implant emulator, where its output was

connected to the implanted electrodes. The implant emulator is a standard clinical cochlear implant

that is mounted in a plastic box with a DB-25 connector (Cochlear). We created a pigtail wire with

a DB-25 connector and an Omnetics/Nanonics connector (Omnetics/TE Connectivity) to couple

the emulator to the skull-anchored connector. The skull-anchored connector is also an

Omnetics/Nanonics connector that is directly attached to the implanted array. All stimuli were

based off standard parameters for cochlear devices including charge-balanced biphasic pulses with

8 µs interphase gaps and 25 µs/phase (total pulse width = 58 µs), presented at 900 pulses per

second and configured in monopolar configuration where currents were driven between a single

intracochlear electrode and the external ground electrode. For about half of tested animals (N=3),

auditory stimulation activated the implant through the microphone of the speech processor via

tones presented to each individual electrode's frequency allocation. The remaining cochlear

implanted animals (N=4) were stimulated directly; the CI24RE implant emulator was driven by a

Freedom system speech processor connected through the Freedom Programming Pod to a personal

computer running the Custom Sound EP software (Cochlear). The Custom Sound EABR function

was used (5 stimulation pulses presented at 900 pulses per second) to program and deliver stimuli

to the implant.

Cochlear implant programming. Impedance and threshold measurements were obtained

intraoperatively using Custom Sound EP (Cochlear) and were used for the initial programming of

the sound processor. Electrically-evoked compound action potential (ECAP) thresholds were

obtained and used to set the maximum stimulation level and the minimum stimulation level was
set to 30 'clinical units' below the maximum level, equivalent to 4.7 dB in the CI24RE implant
emulator (Azadpour and McKay, 2012). All additional settings typically deployed in a clinical
setting, such as ADRO, were turned off (Custom Sound, clinical programming software for
Nucleus Freedom).

ECAP measurements. Rats acutely implanted with an 8-channel cochlear implant were measured
for ECAPs by stimulating and recording from the array of implanted electrodes, with an additional
reference electrode implanted subdermally in the neck, using a cochlear implant emulator and a
custom software program written in MATLAB and Python and using the Nucleus Implant
Communicator (NIC, Cochlear Ltd.). All ECAP measures used the "ABCD" artifact removal
technique (Brown et al. 1990) with a probe-masker interval of 0.5 ms, and a similar artifact
removal for forward masking measures that was modified from the ABCD technique to
compensate for different masker electrode configurations (Azadpour et al. 2021). The
sense/recording electrode was selected as two channels apical to the probe; if that channel was not
available, then the sense was selected as two channels basalward. In cases where the masking
electrode was the same as the sense electrode, the sense was switched to the electrode closer to the
probe, and the corresponding masked ECAP was scaled relative amplitudes of the probe-evoked
masker-free ECAP measured at the two different sense electrodes. After impedance measurements
were made to confirm the device was correctly implanted, configured, and within safe/compliant
limits, ECAP thresholds were estimated for each electrode by manually stepping up and down
stimulation levels specific to the manufacturer's programming units by steps of 5, until evoked
ECAP amplitudes were of ~100 µV. Next, a forward masking paradigm was implemented to

measure channel interaction and temporal recovery. For channel interaction, probe electrodes were

preceded by a masker electrode by 0.5 ms, and masker electrode was roved from channel 1-8 to

extract spatial tuning functions for each probe electrode. For temporal recovery, a masker stimulus

was delivered on the electrode as the probe and the masker-probe interval was roved to capture

temporal tuning functions for each probe electrode.

Processing of cortical iEEG recordings. All signal processing and analyses were performed

using custom MATLAB scripts (MathWorks, MA). To determine whether trials were functional or

contained artifacts, raw measurements were first filtered (2-150 Hz, 6th order bandpass IIR filter)

and then root mean squared power (rms) was computed for each channel. All trials with rms 20-

300 µV were considered functional; power less than 20 µV corresponded with pre-amplifier

saturation, while power greater than 300 µV consistently indicated intermittent corruption from

non-neural sources. To then process functional recordings, we first used a notch filter to remove

60 Hz noise and 90, 120, 180 Hz harmonics. Recorded signals were then downsampled from 20 to

2 kHz using the decimate function (MATLAB), performing also the function of low-pass (anti-

alias) filter and thereby rejecting any artifacts resulting from electrical stimulation delivered by

cochlear implant electrodes.

Event-related potentials (ERPs) were extracted from raw downsampled recordings by

further bandpass filtering (2-100 Hz) using a digital zero-order 6th order Butterworth filter.

Magnitudes of evoked ERP transients were measured by first rectifying measurements using the

MATLAB abs() function and then subtracting the maximum of the baseline amplitude in the 50

ms pre-stimulus period (averaged over ±1 timestep) from the maximum of evoked amplitude in

the 50 ms post-stimulus period (also averaged across three trials).

High gamma responses were extracted from raw downsampled recordings by further

bandpass filtering (70-140 Hz) using a digital zero-order 6rd order Butterworth filter. Next, signals

were rectified and smoothed with a 20 ms sliding window. Resulting signals that exceeded 5 times

the 90th percentile were interpolated. Evoked high gamma magnitudes were extracted as for ERPs.

Estimation of best frequency. All analyses of tone-evoked responses were restricted to the range

of 1.4-32 kHz tones. Best frequency was estimated by computing the center of mass of tone-evoked

responses at 70 dB SPL. The response mass function was defined by the mean vector after

projecting all responses on a circular domain where vector angles are represented by tone

frequencies, to prevent biasing the center of mass towards the interior of the 1.4-32 kHz stimulus

range.

Principal component analysis (PCA). Evoked responses were analyzed by including both

temporal (i.e., R post-stimulus responses) and spatial (i.e., S responsive sites) variables. These

measurements were concatenated across individual trials, T, to create a 2-dimensional T (rows) x

R-S (columns) matrices. PCA was then performed and R-S vectors were compressed using singular

value decomposition to obtain a reduced-rank approximation of the original matrix. PCA was also

performed on variations of our data including only spatial P values (i.e., including only evoked

magnitudes) or only temporal R values (i.e., averaging responses across all recording sites). The

top 15 ranked projections were preserved for further analysis, reducing the datasets into a T (rows)

x 15 (column) matrix.

Tensor component analysis (TCA). We applied a canonical polyadic (CP) decomposition to a 3-dimensional model, enabling us to treating spatial and temporal aspects of iEEG recordings across multiple trials as linear independent (orthogonal) dimensions (Kolda and Bader, 2009; Williams et al., 2018). Naive feature vectors were constructed by arranging all data into a three-dimensional matrix composed of length-R post-stimulus responses, S responsive sites, and T stimulus trials resulting in a R x S x T matrix. CP decomposition was performed (Bader et al., 2023) for 15 latent factors, the number 15 chosen to exceed the number of tone or implant stimuli and to parallel the data reduction performed by PCA. Then the resulting estimate of the T factors for each of the 15 components reduced our datasets into T (rows) x 15 (column) matrices.

Linear discriminant analysis (LDA). We trained a decoder for predicting stimulus identity from single trial recordings by developing a supervised linear classifier. Each decoder was retrained and retested 1,000 times to average decoder performance across randomizations for combinations of trials used for training and test sets. Specifically, each bootstrap replicate was randomly partitioned to include 13 trials per stimulus for each training set and the remaining trials being used to test the decoder. LDA was applied to estimate the stimulus-likelihood map of the PCA- or TCA-compressed feature space. Naive feature vectors from the training set were normalized and compressed according to the learned transformations, and the maximum likelihood stimulus (i.e., the identity of the tone frequency or active cochlear implant electrode) was estimated for each response. Absolute accuracy of the decoder was computed as the average accuracy over all stimuli was estimated by the total proportion of correct predictions. In addition to absolute accuracy, we also computed the mean of the error distances between the predicted and actual stimulus, i.e., octaves or number of electrodes.

Linear mixed effects modeling. Group comparisons between normal-hearing and cochlear

implant conditions were assessed using linear mixed-effects (LME) models implemented in

MATLAB (fitglme, MathWorks). For each analysis, the dependent variable was modeled with at

least fixed effects of condition (normal-hearing vs cochlear implant) and a random intercept for

animal to account for repeated measurements within subjects. Model significance for fixed effects

was evaluated using F-tests obtained from an ANOVA on the fitted LME model.

Results

iEEG recordings in normal hearing and cochlear implanted rats.

We had two main goals: 1) to determine which features of auditory cortex iEEG signals were most informative about stimulus identities; and 2) to use iEEG recordings to assess cortical coding of acoustic vs electrical stimuli in normal-hearing (NH) vs bilaterally deafened + unilaterally cochlear implanted (CI) rats. Animals were first anesthetized and then a craniotomy was performed to expose the primary auditory cortex. We implanted a custom 60-channel iEEG recording array (Insanally et al., 2016; Trumpis et al., 2017) over primary auditory cortex. Seven rats were normal-hearing and presented with acoustic pure-tone stimuli (**Fig 1A**, 'NH'). Seven rats were bilaterally deafened via cochleostomy before receiving a unilateral cochlear implant (**Fig. 1B**, 'CI'). Peripheral sensitivity and tuning were assessed using electrically evoked compound action potentials (ECAPs), recorded via implanted channels. Using a forward masking paradigm (Azadpour et al. 2022) we found cochlear implant stimuli were consistently tuned, cochleotopically and temporally (**Supplemental Fig. 1**).

A subset of these animals from each of the two groups (N=4 normal-hearing rats, N=3 cochlear implant rats) were trained on an auditory detection and recognition go/no-go task we have used previously, both for normal hearing (Froemke et al., 2013; Carcea et al., 2017; Insanally et al., 2024) and with cochlear implants (King et al., 2016; Glennon et al., 2023). Normal-hearing rats each achieved high levels of performance, whereas the cochlear implant rats had more variable performance (**Fig. 1C**; normal-hearing behavioral performance d': 2.9±0.1, cochlear implant performance: 0.9±0.2, one normal-hearing animal lost the implant prior to that stage of training).

Figure 1. Auditory cortex iEEG responses to pure tone stimuli in normal-hearing and
355
deafened cochlear implant rats.
356
A, Schematic of 60-channel cortical surface electrode arrays, covering 3.25 x 3.25 mm on the
357
surface of auditory cortex to record tone-evoked responses in normal hearing (NH) trained rats.
358
B, Some animals were bilaterally deafened and fitted with a unilateral cochlear implant (CI).
359
C, Behavioral training of subset of animals on auditory go/no-go frequency recognition task.
360
Animals were first trained when normal-hearing (NH, N=4, d': 2.9±0.1) and then re-trained to
361
respond to cochlear implant stimulation (CI, N=3, d': 0.9±0.2).
362
D, Examples of trial-averaged single-site iEEG responses (top, ERPs; middle, ERP
363
spectrograms; bottom, HG). Clear transients were evoked by tones in normal-hearing animals
364
(NH, left column) and in cochlear implant rats (CI, right column).
365
E, iEEG response magnitude was similar between normal-hearing (NH, ERP amplitude: 1.9±0.1
366
µV; HG amplitude: 0.6±0.1 a.u.) and cochlear-implant rats (CI, ERP amplitude: 2.0±0.2 µV,
367
p=0.53 compared to normal-hearing ERPs, linear mixed effects model; HG amplitude: 0.6±0.1
368
a.u., p=0.39 compared to normal-hearing HG).
369

The combinations of animals that underwent behavioral training and acute iEEG measurements

are shown in **Supplemental Figure 2**. We acquired and then compared acute iEEG recordings of

acoustic tone-evoked and electrical cochlear-implant-evoked responses in normal-hearing and

cochlear implant rats. Raw responses were down-sampled and lowpass filtered to eliminate

electrical artifacts from cochlear implant stimuli, and bandpass filtered again either to reveal

slowly varying event-related potentials (ERPs, bandpass range: 2-100 Hz) or to reveal higher

frequency high gamma oscillations (HG, bandpass range: 70-140 Hz) (**Fig. 1D**). Trial-averaged

evoked responses were time-locked to the stimulus onset. Evoked response magnitudes were not

measurably different between normal-hearing and cochlear implant rats (**Fig. 1E**). We found that

the behavioral training (denoted purple in all figures) had no measured effect on our analyses of

sensory encoding compared to responses measured in untrained rats (linear mixed effects model,

$p > 0.3$ comparing normal hearing and cochlear implant signals in untrained vs trained rats).

A1 encoding of tones and cochlear implant electrodes are spatially organized.

iEEG recordings of tone-evoked responses are spatially restricted to areas across the recording

array that appeared to shift as a function of tone frequency in normal-hearing animals (**Fig. 2**).

Determining the best frequency at each recording site (i.e., the stimulus evoking the maximum

response overall at that location) confirmed the general tonotopic organization of auditory cortex

(**Fig. 2A-E**, ERPs; **Fig. 2F-J**, HG). Tone-evoked responses were similar in expected directions and

gradients (Polley et al., 2007) indicating that iEEG measurements have the spatial resolution for

testing whether evoked responses are cochleotopically organized.

Figure 2. Tone-evoked and cochlear implant-evoked iEEG measurements are spatially organized.

A, F, Trial-averaged tone-evoked event-related potentials (ERPs, panel **A**) and high gamma (HG, panel **F**) were spatially restricted to regions along the iEEG recording array; these active regions shifted as a function of stimulus.

B, G, Spatial correlations of evoked response areas decreased monotonically as a function of increasing stimulus separation, truncated at large separations due to low sample sizes. Evoked iEEG responses as assessed by ERPs and HG were nonrandom for normal-hearing and implanted

rats ($p<10^{-8}$ compared to all shuffled responses), but were locally tonotopic in normal-hearing

rats ($p<10^{-4}$) but not implanted rats (ERPs: p=0.64, HG: p=0.55).

C, H, Determining the preferred stimulus of spatially-evoked activity revealed smooth gradients

shifting from high-to-low to high tone frequencies or cochlear implant channels (ERPs, panel **C**;

HG, panel **H**).

D, I, Local tonotopic gradients for each recording site plotted on a unit circle (blue) as a function

of magnitude (strength of gradient) and angle (direction of gradient). The vectors across each

recording site were averaged to produce an overall tonotopic vector (black) whose magnitude

represents a metric of overall topography (ERPs, panel **D**; HG, panel **I**). The mean vector was

plotted against the mean vector computed from n=1,000 shuffled maps (ERPs, panel **D**: normal-

hearing z-score: 6.6, $p<10^{-10}$; implanted z-score: 7.9, $p<10^{-14}$; HG, panel **I**: normal-hearing z-

score: 2.1, p=0.02; implanted z-score: 1.5, p=0.07).

E, J, Z-scored magnitudes of mean tonotopic vectors across animals (ERPs, panel **E**: normal-

hearing mean z-score: 4.7±1.0, implanted mean z-score: 2.6±1.0, p=0.048, linear mixed-effects

model; HG, panel **J**: normal-hearing mean z-score: 3.0±0.9, implanted mean z-score: 2.1±0.9,

p=0.48).

We then asked whether central auditory pathways would effectively preserve cochleotopic

encoding provided by acute cochlear implants. We found that iEEG recordings of responses

evoked by individual electrodes were spatially restricted to areas across the recording array (**Fig.**

2A,F) that appear to shift as a function of cochlear electrode location. To determine the degree of

local and longer-range topography, we computed the spatial correlations as a function of stimulus

separation, and compared the actual correlation coefficients to the distribution of responses when

spatial locations were randomly shuffled. This analysis revealed a spatially structured but

relatively coarse topographic organization that was non-random (**Fig. 2B,G**; $p<10^{-8}$ compared to

all shuffled responses for ERPs and HG both for normal-hearing and implanted rats), but less

sharply tonotopic relative to the tonotopic organization in normal-hearing animals assessed with

pure tones (**Fig. 2B**, $p<10^{-4}$ for ERPs and HG for normal-hearing rats; **Fig. 2G**, ERPs: p=0.64, HG:

p=0.55 for implanted rats). At the extremes, the spatial correlations were always higher for small

vs. large tone separations (NH 0.5 vs $\geq$3.5 octaves, ERP: $p<10^{-4}$, HG: $p<10^{-4}$ Student's one-tailed

t-test) and electrode separations (CI 1 vs $\geq$5 electrodes, ERP: p=0.01, HG: p=0.04).

We then reduced stimulus-evoked responses into representative stimulus maps (**Fig. 2C,H**) whose

areas and orientations of these maps qualitatively match those published from similar iEEG

recordings (Insanally et al. 2015), and single unit recordings (Polley et al, 2006) albeit at coarser

gradients likely due to aggregate recordings of excitatory and inhibitory activity and spatial low-

pass filtering due to potentials originating far from recording sites. Direct within-animal

comparisons of normal-hearing vs implant maps (N=4) indicated that cochleotopic gradients were

positioned in similar orientations and directions (**Fig. 2C,H, Supplementary Fig. 3**). To quantify

the degree and direction of potential spatial tonotopic or cochleotopic organization in the iEEG

recordings, we computed the local gradients for each recording site (one example animal shown

in **Fig. 2D**, ERPs; **Fig. 2I**, HG). Each gradient is a vector consisting of a magnitude and direction,

and thus we then averaged these gradients from each recording site to get the overall cochleotopic

vector, the magnitude of which is an index of spatial organization for a given animal (Romero and

Hight et al. 2020). We shuffled the recording site location labels to generate putatively randomly

organized maps (n=1000 random shuffles per animal), and compared the actual mean vector

strength to the shuffled distributions. For this example animal, the ERP maps were significantly

different from chance in terms of spatial organization (**Fig. 2D**, NH p=0.00003, CI p=0.0033),

while this was more modest for the HG maps in this animal (**Fig. 2I**, NH p=0.02, CI p=0.07). This

analysis revealed a similar kind of organization between ERP and HG maps of normal-hearing vs

cochlear implant rats (**Fig. 2E**, NH mean z-score: 4.7±1.0, CI mean z-score: 2.6±1.0, p=0.05 linear

mixed effects; **Fig. 2J**, NH mean z-score: 3.0±0.9, CI mean z-score: 2.1±0.9, p=0.49). Combined

with results from **Figure 2B,G**, these analyses indicate that overall there was similar spatial

organization to cortical iEEG responses in normal-hearing and cochlear implant animals, although

the organization was substantially coarser and less sharply resolved in cochlear implant animals..

Increased variability of trial-by-trial responses evoked by cochlear implant stimulation.

The results described above for **Figures 1** and **2** used trial-averaged responses to examine the

spatio-temporal organization of iEEG responses. We noticed that the iEEG recordings provided

satisfactory signal-to-noise ratios to measure evoked ERPs (**Fig. 3A,B**) and HG transients (**Fig.**

3C,D) on a single trial basis. Therefore, we next asked if there were differences in single-trial

encoding for cochlear implant vs normal-hearing rats. We first averaged evoked responses across

all recording sites to reduce measurement noise. We then computed variability of responses in the

50 ms period immediately following stimulus onset, and found that in this temporal domain, the

within-animal trial-by-trial variability in evoked responses was similar for cochlear implant rats

compared to normal-hearing rats irrespective of recording site ('Temporal'; **Fig. 3B**, ERPs, linear

mixed effects, p=0.054; **Fig. 3D**, HG, p=0.17).

Figure 3. Trial-by-trial cochleotopic encoding is more variable in cochlear implant vs normal-hearing rats.

A, C, Trial-by-trial iEEG measurements of both tone-evoked (NH) and cochlear implant-evoked (CI) neural activity revealed peaks across time (left) and space (right) (ERP, **A**; HG, **C**)

B, D, Variability of iEEG measurements across trials (root mean square, rms) was consistently higher for spatial distributions of cochlear implant-evoked compared to tone-evoked activity, for ERPs in panel **B** (bottom, ERP spatial NH mean rms: 0.32±0.01, CI mean rms: 0.33±0.02,

p=0.011, linear mixed effects) but not for temporal distributions (top, ERP temporal NH mean

rms: 1.6±0.3 over all animals, CI mean rms: 1.9±0.5, for animals monitored before and after

deafening, p=0.054) and HG in panel **D** (top, HG temporal NH mean rms: 2.4±0.3 over all

animals, CI mean rms: 3.3±0.9, p=0.17; bottom, HG spatial NH mean rms: 1.2±0.2, CI mean

rms: 1.3±0.3, p=0.35).

Then, we returned to the evoked responses for each recording site and measured the trial-by-trial

evoked response peak. Next, we computed the variability of spatial distributions of evoked

responses and found modestly larger within-animal trial-by-trial variability in the spatial domain

of ERP responses for CI compared to normal-hearing rats ('Spatial'; **Fig. 3B**, ERPs, linear mixed

effects model, p=0.01; **Fig. 3D**, HG, p=0.35). Differences were subtle but consistent across animals

(**Fig. 3B**). We conclude that similar to the trial-averaged responses in **Figure 2**, analysis of ERPs

more so than HG signals could identify the increased spatial variability of evoked responses across

the auditory cortex in cochlear implant animals relative to normal-hearing rats.

Single trials encode stimulus identity in normal-hearing and cochlear implant rats.

Given that trial-by-trial variability was higher for implant-evoked responses vs responses in

normal-hearing rats, we wondered if this compromised decoding of cochlear implant signals in

some way. We next trained a classifier to ask if we could successfully decode stimulus identity

from individual trials, and examine differences of decoding accuracy for normal-hearing vs

cochlear implant rats. We reduced evoked responses into the top 15 principal components via PCA

(**Fig. 4A,B**). The number of components (15) was chosen based on PCA scree plots (**Supplemental**

Fig. 4A), which showed that explained variance entered a near-linear, low-slope regime beyond

this point demonstrating a similar plateau in reconstruction error (**Supplemental Fig. 4B**),

indicating diminishing returns for additional components. We then trained an LDA decoder on 13

randomized trials of stimulus presentation to enable comparisons across animals that had different

numbers of stimuli (Insanally et al., 2016). Computed prediction probabilities were estimated by

testing the decoder on the remaining trials. Selections of the 13 training and remaining test trials

were randomized (N=1,000 trials), and final prediction probabilities averaged across repeats.

Hight et al., Fig. 4

Figure 4. Trial-by-trial iEEG measurements encode stimulus identity.

A, Trial-by-trial ERPs evoked by 1.4 kHz (left), 8 kHz (middle), and 32 kHz tones (right) are plotted for three recording sites (blue) reveal discernable evoked transients and spatially restricted patterns of evoked magnitudes (stimulus onsets depicted by dotted line).

B, Trial-by-trial iEEG measurements concatenated such that columns represent recording sites (spatial) and post-stimulus sampling (temporal), rows by stimulus trials. Data then reorganized by PCA and reduced to the 15 components according to magnitude of explained variance.

C, Classification matrices are plotted means across bootstrapped repeated (N=1,000) versions of LDA classifiers trained using 13 randomly selected trials for each stimulus, and classification predictions of single and remaining trials reveal significant prediction of stimulus identity (dashed line: chance-level error distance; solid lines: actual mean error distances).

D, Stimulus prediction probabilities plotted across animals (black: mean, grey: s.e.m.) and as function of either octaves (normal-hearing) or channels (cochlear implant) from actual stimulus, reflecting a gradient in which adjacent stimuli share more encoded features than other stimuli.

E, Decoder performance (mean error distance) across individual animals was somewhat worse

for cochlear implant ERPs compared to tone-evoked ERPs (ERP mean error rate relative to

chance for normal-hearing: 0.74±0.05, cochlear implant: 0.78±0.06; for animals assessed both

first when normal-hearing and then after cochlear implantation $p<10^{-4}$, linear mixed effects), but

not for HG (HG mean error rate relative to chance for normal-hearing: 0.90±0.03, cochlear

implant: 0.91±0.04; for animals assessed both first when normal-hearing and then after cochlear

implantation p=0.15).

This approach successfully decoded tones and implant electrodes (**Fig. 4C**). Across rats, there were

above-chance predictions of correct stimuli from single trials, with higher errors when closer to

the actual stimulus (**Fig. 4D**). Computing error distance mean across trials allowed us to compare

decoding performance of normal-hearing vs implanted rats, as this combines absolute prediction

probability and distribution of errors while normalizing to chance-level error distances, determined

by number of trained and tested stimuli. Decoders trained on responses from normal-hearing rats

performed better compared to responses after implantation (**Fig. 4E**; ERP mean error distance for

normal-hearing rats: 0.74±0.05, cochlear implant rats: 0.78±0.06, $p<10^{-4}$, linear mixed effects; HG

mean error distance for normal-hearing: 0.90±0.03, cochlear implant: 0.91±0.04, p=0.15).

Single trial encoding is independently provided by both spatial and temporal cues.

Which aspects of iEEG signals (spatial topography and/or temporal dynamics) contribute to

stimulus decoding performance? We re-trained PCA-LDA decoders, but instead of using both

spatial and temporal aspects of the full set of iEEG measurements (**Fig. 5A**), decoders were trained

on the spatial-only (**Fig. 5B**) or temporal domain-only aspects (**Fig. 5C**) of evoked iEEG

measurements. Decoders trained on the spatial or temporal domains only were essentially as good

as predicting the stimulus as decoders trained on both aspects (**Fig. 5D,E**; mean error distance for

spatial-only ERPs, normal-hearing: 0.77±0.04, implant: 0.77±0.08; for spatial-only HG, normal-

hearing: 0.89±0.04, implant: 0.87±0.05; for temporal-only ERPs, normal-hearing: 0.82±0.05,

implant: 0.81±0.07; for temporal-only HG, normal-hearing: 0.87±0.04, implant: 0.93±0.05; for

spatial+temporal ERPs, normal-hearing: 0.74±0.04, implant: 0.86±0.06; for spatial+temporal HG,

normal-hearing: 0.90±0.03, implant: 0.97±0.04). We conclude that both spatial and temporal

aspects of iEEG measurements contribute to single-trial encoding of stimulus identity.

Figure 5. Trial-by-trial decoding from either spatial or temporal aspects of iEEG signals.

A, Raw trial-by-trial ERPs for a single animal are plotted for 3 channels.

B-C, Trial-by-trial iEEG measurements are reduced into either spatial only (**B**) or temporal only

(**C**) by extracting either the magnitude of evoked activity or averaging across all recording sites.

D, Re-training PCA-LDA decoders on spatial-only (middle) or temporal-only (right) does not

abolish the encoding of stimulus identity.

E, Decoder errors (mean error distance re. chance) across animals are plotted for decoders

trained on spatial+temporal, spatial-only, and temporal-only iEEG measurements. Mean error

distance for spatial+temporal ERPs, normal-hearing: 0.74±0.04, implant: 0.86±0.06; for

spatial+temporal HG, normal-hearing: 0.90±0.03, implant: 0.97±0.04. Mean error distance for

spatial-only ERPs, normal-hearing: 0.77±0.04, implant: 0.77±0.08; for HG, normal-hearing:

0.89±0.04, implant: 0.87±0.05. Mean error distance for temporal-only ERPs, normal-hearing:

0.82±0.05, implant: 0.81±0.07; for HG, normal-hearing: 0.87±0.04, implant: 0.93±0.05.

In some cases, we found that the performance of either spatial-only or temporal-only could be

somewhat better than decoders trained on both spatial and temporal aspects of iEEG

measurements. This is likely due to the noise inherent in iEEG signals, such that constraining PCA

reductions to one aspect of the data (either spatial or temporal) helps to eliminate variance in

individual recordings.

Reducing evoked responses using TCA preserves encoding of stimulus identity.

One challenge with using PCA is that the ordinations of dimensionality reduction are

unconstrained, because they are arbitrary linear combination of the original variables. A newer

approach for dimensionality reduction called tensor component analysis (TCA) explicitly enables

identification of which spatial, temporal, and single-trial factors best account for signal variability,

and thus drive single-trial stimulus decoding (Williams et al., 2018). Here, we used TCA instead

of PCA for LDA-based decoding, constraining data reduction dimensions on the full data set to

the spatial, temporal, and to the trials of iEEG measurements (**Fig. 6A**). The resulting TCA-

optimizations across 15 components reveal discernable patterns of spatial and temporal factors

(**Fig. 6B**). We trained and tested a LDA decoder using only the trial factors, and found that single

trial predictions accurately identified the stimulus (**Fig. 6C-D**). Decoders trained on responses

from normal-hearing rats had better prediction performance compared to the responses from these

same animals after cochlear implantation (**Fig. 6E**; ERP mean error distance for normal-hearing

rats: 0.78 ± 0.04, for cochlear implant rats: 0.80 ± 0.06, $p < 10^{-5}$, linear mixed-effects model; HG mean

error distance for normal-hearing: 0.90 ± 0.03, for cochlear implant: 0.88 ± 0.05, $p = 0.03$).

Hight et al., Fig. 6

Figure 6. TCA-based decoding of single-trial iEEG measurements.

A, Schematic of TCA with 3-dimensional tensors with orthogonal dimensions of spatial,

temporal and trial factors.

B, TCA-reduced iEEG measurements of stimulus-evoked ERPs in normal-hearing rats are

plotted across 15 components of spatial (top row), temporal (middle row) and trial factors

(bottom row).

C, Classification matrices of mean decoder predictions across bootstrapped repeated (N=1,000)

versions LDA classifiers trained using 13 randomly selected trials for each stimulus indicated

that iEEG measurements encode stimulus identity from single stimulus presentations (dashed

line: chance-level error distance; solid lines: actual mean error distances).

D, Stimulus prediction probabilities are plotted across animals (black: mean, grey: std. error) and

as a function of either octaves or channels in away from actual stimulus, normal-hearing and

implanted rats. Correct prediction probabilities are high across all conditions and prediction

errors coalescing of predictions toward actual stimuli (orange: mean and std. error of decoder

performance on shuffled trials; grey: mean error distance, dashed line: chance level error

distance).

E, Decoder errors (mean error distance) across individual animals were slightly smaller for

evoked iEEG measurements in normal-hearing compared to implanted rats (ERP mean error rate

re. chance normal-hearing: 0.78±0.04, implanted: 0.80±0.06; HG mean error rate re. chance

normal-hearing: 0.90±0.03, implanted: 0.88±0.05). Comparisons between normal-hearing and

implanted iEEG measurements showed significant decrease in estimated error distances for ERP

(top, linear mixed-effects model: $p<10^{-5}$) and HG (bottom, p=0.03).

Latent factors from unsupervised TCA revealed spatially-organized maps.

These analyses revealed that single-trial iEEG responses can be successfully decoded, and the TCA-based approach suggests that individual factors driving decoding might relate to specific spatiotemporal features inherent in the data. Specifically, we asked whether the TCA-reduced data contained organized spatial features, e.g., patterns of tonotopy. We next optimized TCA models of the original data (**Fig. 7A**) and then weighed the spatial factors by the strength of trial factors associated with each stimulus, resulting in spatial maps for each stimulus frequency for both normal-hearing and electrode for implants rats (**Fig. 7B**). The resulting reorganized spatial factors were further reduced to a preferred stimulus. Resulting TCA-maps exhibited tonotopic features (**Fig. 7C**), similar to tonotopic maps extracted from ERP or HG components of the iEEG responses. TCA-recreated spatial maps also exhibited coarse topographic organization that was non-random compared to shuffled distributions (**Fig. 7D**, $p<10^{-8}$ compared to all shuffled responses for ERPs and HG both for normal-hearing and implanted rats). TCA models from normal-hearing HG iEEG measurements exhibited clear tonotopic organization whereas tonotopy in models from other measurements was less clear (**Fig. 7D**, normal-hearing rats ERPs: $p=0.18$, normal-hearing rats HG: $p<10^{-4}$, cochlear implant rats ERPs: $p=0.43$, cochlear implant rats HG: $p=0.40$). As with analyses of **Figure 2E,J**, the magnitude of tonotopy computed from mean vector strengths was similar for ERP and HG measurements in normal-hearing vs cochlear implant rats (**Fig 7E**).

Figure 7. TCA data reductions reveal latent spatial factors are topographically organized.

A, TCA-based analysis of evoked neural activity, divided into 15 unique components where each component is separated into orthogonal dimensions of spatial factors (top row), temporal factors (middle row) and trial factors (bottom row).

B, Spatial maps for tone-evoked or electrode-evoked responses recreated from TCA reduced data.

C, Reducing re-organized spatial factors revealed a TCA map (left) with topographical gradients in same location and direction as the tonotopic map reduced from raw measurements (right).

D, Spatial correlations of evoked response areas decreased monotonically as a function of

increasing stimulus separation. TCA-reduced models of evoked iEEG responses as assessed by

ERPs and HG were nonrandom for normal-hearing and implanted rats ($p < 10^{-8}$ compared to all

shuffled responses). TCA-reduced models were locally tonotopic only for HG in normal-hearing

rats (normal-hearing ERPs: p=0.18, normal-hearing HG: $p < 10^{-4}$, cochlear implant ERPs: p=0.43,

cochlear implant HG: p=0.40).

E, Z-scored magnitudes of mean tonotopic vectors across animals were similar (ERPs, normal-

hearing mean z-score: 6.2±3.6, cochlear implant mean z-score: 3.9±2.1, p=0.16, linear mixed

effects; HG, normal-hearing mean z-score: 2.9±1.1, implanted mean z-score: 2.5±0.7, p=0.75).

642 iEEG measurements from implanted rats could not be decoded from models trained on

643 normal-hearing data.

We asked what features might be shared vs distinct in the nature of cortical encoding of tones (in

normal-hearing rats) and electrode channels (in cochlear implant rats). We hypothesized that this

overlap would be incomplete, with substantial variability across individuals. This was based on a

considerable number of previous studies finding that adaptation periods are needed before

maximizing cochlear implant outcomes in both animals (Glennon et al., 2023) and humans

(Holden et al., 2013; Cusumano et al., 2017; Glennon et al., 2020; Caswell-Midwinter et al., 2022),

as well as our results described above showing that iEEG measurements were less sharply

topographic and more variable in implanted rats compared to normal-hearing animals. Thus, here

we asked whether a decoder trained on tone-evoked iEEG measurements from normal-hearing rats

could interpret implant-evoked iEEG measurements on single trials.

Our measurements of iEEG activity in the same animals before and after deafening and implant

fitting provide an opportunity to examine this directly, and determine how individually distinct the

neural coding of sound is for the auditory cortex in both normal-hearing and cochlear implant

conditions. TCA-generated models provide a reasonable approach to quantify the degree of

information transfer from the normal-hearing to the implanted condition, because the dimensions

of data reductions are predetermined (i.e., spatial and temporal), rather than unconstrained as with

PCA models. We generated TCA models of tone-evoked iEEG measurements from normal-hearing

rats (**Fig. 8A**). Next, we extracted only the spatial and temporal components of these normal-

hearing TCA models to constrain models for implanted rats, leaving only the trial factors to be

optimized (**Fig. 8E**).

Figure 8. Lack of information transfer between acoustic and electrical stimulation

representations in the same animals.

A, Evoked iEEG measurements from a subset of data from normal-hearing rat reduced using

TCA.

B, Evoked iEEG measurements from previously withheld trials from normal-hearing rat reduced

using TCA, constraining the model with the spatial and temporal factors from the original TCA

model, leaving only the trials as the optimizable variables.

C, Linear discriminant analysis classifiers are trained on the trial factors extracted from the

original TCA-reduced models of evoked data and then used to predict stimulus identity from the

trial factors from the re-optimized TCA-reduced models of withheld normal-hearing

measurements.

D, Classification matrices are plotted means of decoder

F, Evoked iEEG measurements in cochlear implant rat reduced using TCA, constraining the

model with the spatial and temporal factors from the original TCA model optimized on normal-

hearing data, leaving only the trials as the optimizable variables. Linear discriminant analysis

classifiers are trained on the trial factors extracted from the original TCA-reduced models of

evoked data in normal-hearing conditions and then used to predict stimulus identity from the trial

factors from the TCA-reduced models of implant-evoked measurements.

G, Classification matrices are plotted means of decoder predictions across bootstrapped repeated

(N=1,000) versions of linear-discriminant analysis (LDA) classifiers.

H, Information transfer of normal-hearing trained and implant tested decoders reveal little-to-no

information transfer (IT mean across animals, ERP: 1.2±0.6, HG: 0.2±0.1%) compared to both

normal-hearing (IT mean across animals, ERP: 2.8±1.2%, p=0.044 Student's one-tailed t-test,

HG: 0.4±0.2%, p=0.187) and cochlear implant where rows were shuffled within columns (IT

mean across animals, ERP: 2.4±1.0%, p=0.042, HG: 0.3±0.2% p=0.209). Information transfer of

normal hearing re-optimized decoders was significantly higher compared to cochlear implant

decoders where rows were shuffled within columns (ERP: p=0.050, HG: p=0.107, Student's one-

tailed t-test)

Next, we compared these models across each animal by training an LDA decoder on the trial

factors from tone-evoked TCA models and then testing the decoder on trial factors of the implant-

evoked TCA models (**Fig. 8F**). From these resulting confusion matrices of prediction probabilities,

we computed the mutual information between predictions of tone identity and actual implant

channels to quantify how much tone predictions can be used to determine the actual identity of

single channels, without imposing any hypotheses about how predicted tones map onto implant

electrodes (e.g., tonotopy). We computed the pointwise mutual information for each combination

of predicted tones and actual implant channels, which was then normalized by the joint probability.

These resulting bits were combined across the entire confusion matrix to compute mutual

information, and finally we converted this to a percentage of information transfer by dividing the

experimentally measured mutual information by the total possible number of bits the matrix could

provide.

We found the resulting information transfer to be low across all four animals where we measured

both tone- and implant-evoked iEEG measurements (**Fig. 8G**; mean information transfer, ERPs:

1.2±0.6%; HG: 0.2±0.1%). The near-zero information transfer indicates that decoders trained on

tone-evoked iEEG measurements do not make meaningful interpretations of implant-evoked iEEG

measurements. We repeated this analysis but with first optimizing TCA models on a subset of tone-

evoked data and then constraining the spatial and temporal factors while optimizing a new TCA

model of withheld tone-evoked iEEG measurements (**Fig. 8B**). Training a classifier on the original

and testing the re-optimized trial factors, we found above-chance decoding accuracy and stimulus

tuning (**Fig. 8C,D**) indicating this analysis approach is effective. We conclude that although iEEG

responses can be meaningfully decoded from single-trial cortical responses (to either acoustic

tones in normal-hearing animals or cochlear implant stimulation in deafened animals), the

decoding algorithms and computations required are specific to the type of stimulus and do not

immediately generalize between acoustic and electrical stimulation. This has implications for

understanding the perceptual experiences of cochlear implant users at acute implant stimulation.

If the cortical representations were simply degraded or noisy versions of acoustic responses, we

would expect partial information transfer. This was not observed. Instead, the mutual information

analysis reveals that the acoustic response pattern does not inform the electrical stimulation

response pattern. In turn, this suggests that the perceptual qualities (e.g., pitch) evoked by acoustic

and electrical stimulation may be qualitatively different rather than simply degraded versions of

each other.

Discussion

Cochlear implants are the gold standard for success of brain-computer interfaces and neuroprosthetic devices to safely activate the human nervous system and effectively restore functional sensation (Hochmair et al., 2006; Wilson and Dorman, 2008; Clark, 2015; Svirsky, 2017; Glennon et al., 2020). While high levels of hearing and speech processing can be achieved by some users, outcomes remain highly variable in terms of learning rates and peak performance, especially in real-world conditions and even after controlling for age and durations of deafness (Blamey et al., 2013). Invariably, all users require an adaptation period; speech perception outcomes are initially poorer than later timepoints (Holden et al., 2013; Cusumano et al., 2017; Caswell-Midwinter et al., 2022; Stronks et al. 2025), indicating both that acute encoding of cochlear implant stimulation by the central auditory system is not optimal and that neuroplastic processes are needed for maximizing outcomes. Current and future advances in engineering and implant programming algorithms might help improve outcomes further, but there is a general belief in the field that what is now required is an understanding of how the central nervous system responds to peripheral electrical stimulation (Kral et al., 2002; Kral and Eggermont, 2007; Wilson and Dorman, 2008; Moore and Shannon, 2009).

Our findings provide the first direct neural evidence that acoustic and electrical cochlear stimulation create substantially distinct cortical representations, with near-zero information transfer between modalities. This addresses a longstanding question in cochlear implant research: whether electrical stimulation of the cochlea can evoke the same percepts as acoustic stimulation, such as pitch and timing. The lack of transferable representations suggests that cochlear implant users may experience qualitatively different percepts that cannot be predicted from normal acoustic

hearing. If so, this would challenge a foundational assumption of current cochlear implant

design—that electrical stimulation should mimic the tonotopic patterns of acoustic hearing. Our

data suggest that this biomimetic approach may be fundamentally limited because the cortical

representations are non-overlapping.

Previous studies in non-human animals have established that stimulus identity can be encoded in

A1 (Bierer and Middlebrooks, 2002; Middlebrooks and Bierer, 2002; Bierer and Middlebrooks,

2004). However, many of these studies have used invasive recording methods to examine single-

neuron responses to implant activation. Invasive recordings are not feasible for human cochlear

implant recipients, and thus decoding methods based on purely-invasive measures may be difficult

to translate into human subjects for optimizing implant programming and/or training for use of the

device. While our iEEG recordings are also invasive and under anesthesia, the principles of iEEG

analysis for cochlear implant responses developed here might be more applicable to non-invasive

EEG recordings or similar approaches more easily performed in humans. Grid electrodes allowed

us to take simultaneous advantage both of temporal and spatial features in the data, some of which

were more obvious in ERPs, others were more latent in HG signals or PCA/TCA factors.

Our results show that these features could provide accurate stimulus decoding even on single trials,

indicating that: 1) use of these methods in translational or clinical settings could aid personalization

and optimization of brain-computer interfaces, and 2) single-trial implant responses can be

adequately processed by auditory cortex and presumably downstream regions related to perception

and behavior. It has been unclear to what degree the patterns of tone-evoked and implant-evoked

responses in normal-hearing vs deaf subjects are similar. We found that the encoding of cochlear

implant electrodes was less reliable and identifiable than tone-evoked responses in normal-hearing

animals. One caveat is that direct comparisons of evoked iEEG measurements between normal-

hearing and implanted rats are challenging due to fundamental differences in the stimuli (e.g., the

cochleotopic separation between stimuli such as the spacing between half-octaves vs spacing

between successive CI electrodes), as well as the higher degree of inter-trial variability for implant

responses (which is presumably not influenced by stimulus separation).

We also observed interesting differences in the information provided by ERPs vs HG signals. In

terms of field potentials, the HG band is thought to most directly related to neuronal spike activity

(Ray and Maunsell, 2011), which may account for why HG-evoked activity was more time-locked

to stimuli and more spatially tuned compared to ERPs. Some single-channel HG measurements

also had higher signal-to-noise levels than ERPs. A priori, it would seem that a decoder with access

to both higher signal-to-noise measurements in the temporal and spatial domains should perform

better at predicting stimulus identity. Instead, we found that decoding was more accurate with

ERPs than HG. One possible explanation for poorer decoding performance with HG is that HG

signals are more spatially tuned, leading to a smaller number of discernable channels with clear

HG activity; accordingly, we found that across iEEG grid sites, there were more significant

recording sites with ERPs than HG. HG responses also have higher trial-by-trial variability and

are more temporally-constrained than ERPs, and thus the ERP might be more informative in terms

of decoding performance.

Finally, we found that single-trial temporal factors could suffice to provide accurate decoding of

implant channels. This suggests that preservation of clear cochleotopy in deaf subjects may not be

a pre-requisite for successful implant use. Rather, it is likely that reductions in trial-by-trial and

inter-neuronal variability might be more important as a mechanism for improving outcomes. This

means that the neural responses to neuroprosthetic stimulation and use of brain-computer

interfaces need not fully recapitulate responses to other modalities (e.g., acoustic stimulation) in

space and time. These findings are consistent with the possibility that cochlear implant stimulation

engages an alternative representation in auditory cortex, rather than a simple degraded version of

acoustic encoding. Previously we showed that deafened rats could learn to use a cochlear implant

to perform an auditory task, and that changes in cortical excitatory and inhibitory synapses related

to implant use outcomes. In the current study, we did not track responses to implant use over time

in relation to changes in perception and behavioral performance. Our results suggest that

refinement particularly of inhibitory cortical responses might help increase inter-neuronal variance

at the population level to increase spatial organization, while decreasing intra-trial variability at

the single neuron level to enhance temporal organization and improve auditory perception.

Acknowledgements:

We thank Badr Albanna, Elad Sagi, and Sam Zheng for comments, discussions, and technical assistance. This work was funded by the National Institute on Deafness and Other Communication Disorders (K99DC021727 to A.E.H., DC015543 to M.N.I., F30DC015170 to J.K.S., and R01DC012557 to R.C.F. and M.A.S.), the National Center for Advancing Translational Sciences (TL1TR001447 to A.E.H.), and the Charles H. Revson Foundation (to A.E.H.); the statements made and views expressed, however, are solely the responsibility of its authors. The current affiliation for Julia K. Scarpa is Weill Cornell Medicine, New York, NY 10065; for Yew-Song Cheng is Massachusetts Eye and Ear Infirmary, Harvard Medical School, Boston MA, 02114; for Michael Trumpis is Paradromics Inc., Austin TX 78759.

Conflict of interest:

The authors declare no competing financial interests

References

Abdi-Sargezeh B, Oswal A, Sanei S (2023) Mapping scalp to intracranial EEG using generative adversarial networks for automatically detecting interictal epileptiform discharges. In: 2023 IEEE Statistical Signal Processing Workshop (SSP), 710-714.

Adenis, V, et al. "Asymmetric Pulses Delivered by a Cochlear Implant Allow a Reduction in Evoked Firing Rate and in Spatial Activation in the Guinea Pig Auditory Cortex." *Hearing Research* [Netherlands], vol. 447, no. 109027, June 2024, https://doi.org/10.1016/j.heares.2024.109027.

Ayton LN, Barnes N, Dagnelie G, Fujikado T, Goetz G, Hornig R, Jones BW, Muqit MMK, Rathbun DL, Stingl K, Weiland JD, Petoe MA (2020) An update on retinal prostheses. Clin Neurophysiol 131:1383-1398.

Azadpour M, McKay CM (2012) A psychophysical method for measuring spatial resolution in cochlear implants. J Assoc Res Otolaryngol 13:145-157.

Bader BW, Kolda TG, Others a (2023) Tensor Toolbox for MATLAB. In, 3.6 Edition.

Beynon AJ, Luijten BM, Mylanus EAM (2021) Intracorporeal cortical telemetry as a step to automatic closed-loop EEG-based CI fitting: A proof of concept. Audiol Res 11:691-705.

Bierer JA, Middlebrooks JC (2002) Auditory cortical images of cochlear-implant stimuli: dependence on electrode configuration. J Neurophysiol 87:478-492.

Bierer JA, Middlebrooks JC (2004) Cortical responses to cochlear implant stimulation: channel interactions. J Assoc Res Otolaryngol 5:32-48.

Blamey P et al. (2013) Factors affecting auditory performance of postlinguistically deaf adults using cochlear implants: an update with 2251 patients. Audiol Neurootol 18:36-47.

Carcea I, Insanally MN, Froemke RC (2017) Dynamics of auditory cortical activity during

behavioural engagement and auditory perception. Nat Commun 8:14412.

Caswell-Midwinter B, Doney EM, Arjmandi MK, Jahn KN, Herrmann BS, Arenberg JG (2022)

The relationship between impedance, programming and word recognition in a large clinical

dataset of cochlear implant recipients. Trends Hear 26:23312165211060983.

Chang EF (2015) Towards large-scale, human-based, mesoscopic neurotechnologies. Neuron

86:68-78.

Clark GM (2006) The multiple-channel cochlear implant: the interface between sound and the

central nervous system for hearing, speech, and language in deaf people-a personal

perspective. Philos Trans R Soc Lond B Biol Sci 361:791-810.

Clark GM (2015) The multi-channel cochlear implant: Multi-disciplinary development of

electrical stimulation of the cochlea and the resulting clinical benefit. Hear Res 322: 4-13.

Cusumano C, Friedmann DR, Fang Y, Wang B, Roland JT, Jr., Waltzman SB (2017) Performance

plateau in prelingually and postlingually deafened adult cochlear implant recipients. Otol

Neurotol 38:334-338.

Dawson J, Pierce D, Dixit A, Kimberley TJ, Robertson M, Tarver B, Hilmi O, McLean J, Forbes

K, Kilgard MP, Rennaker RL, Cramer SC, Walters M, Engineer N (2016) Safety, feasibility,

and efficacy of vagus nerve stimulation paired with upper-limb rehabilitation after

ischemic stroke. Stroke 47:143-150.

Djourno A, Eyries C (1957) [Auditory prosthesis by means of a distant electrical stimulation of

the sensory nerve with the use of an indwelt coiling]. Presse Med (1893) 65:1417.

Eddington DK, Dobelle WH, Brackmann DE, Mladejovsky MG, Parkin JL (1978) Auditory

prostheses research with multiple channel intracochlear stimulation in man. Ann Otol

Rhinol Laryngol 87:1-39.

Fallon JB, Shepherd RK, Irvine DRF (2014) Effects of chronic cochlear electrical stimulation after

an extended period of profound deafness on primary auditory cortex organization in cats.

Eur J Neurosci 39:811-820.

Froemke RC, Carcea I, Barker AJ, Yuan K, Seybold BA, Martins ARO, Zaika N, Bernstein H,

Wachs M, Levis PA, Polley DB, Merzenich MM, Schreiner CE (2013) Long-term

modification of cortical synapses improves sensory perception. Nat Neurosci 16:79-88.

Fukushima M, Chao ZC, Fujii N (2015) Studying brain functions with mesoscopic measurements:

Advances in electrocorticography for non-human primates. Curr Opin Neurobiol 32:124-

131.

Glennon E, Svirsky MA, Froemke RC (2020) Auditory cortical plasticity in cochlear implant users.

Curr Opin Neurobiol 60:108-114.

Glennon E, Valtcheva S, Zhu A, Wadghiri YZ, Svirsky MA, Froemke RC (2023) Locus coeruleus

activity improves cochlear implant performance. Nature 613:317-323.

Glennon E, Carcea I, Martins ARO, Multani J, Shehu I, Svirsky MA, Froemke RC (2019) Locus

coeruleus activation accelerates perceptual learning. Brain Res 1709:39-49.

Hays SA, Rennaker RL, Kilgard MP (2013) Targeting plasticity with vagus nerve stimulation to

treat neurological disease. Prog Brain Res 207:275-299.

Hochmair ES, Hochmair-Desoyer IJ (1981) An implanted auditory eight channel stimulator for the

deaf. Med Biol Eng Comput 19:141-148.

Hochmair I, et al. (2006) MED-EL cochlear implants: State of the art and a glimpse into the future.

Trends Amplif 10:201-219.

Holden LK, Finley CC, Firszt JB, Holden TA, Brenner C, Potts LG, Gotter BD, Vanderhoof SS,

Mispagel K, Heydebrand G, Skinner MW (2013) Factors affecting open-set word

recognition in adults with cochlear implants. Ear Hear 34:342-360.

House WF, Urban J (1973) Long term results of electrode implantation and electronic stimulation

of the cochlea in man. Ann Otol Rhinol Laryngol 82:504-517.

Insanally M, Trumpis M, Wang C, Chiang C-H, Woods V, Palopoli-Trojani K, Bossi S, Froemke

RC, Viventi J (2016) A low-cost, multiplexedµECoG system for high-density recordings

in freely moving rodents. J Neural Eng 13:026030-26030.

Insanally MN, Albanna BF, Toth J, DePasquale B, Fadaei SS, Gupta T, Lombardi O, Kuchibhotla

K, Rajan K, Froemke RC (2024) Contributions of cortical neuron firing patterns, synaptic

connectivity, and plasticity to task performance. Nat Commun 15:6023.

Janiukstyte V, Owen TW, Chaudhary UJ, Diehl B, Lemieux L, Duncan JS, de Tisi J, Wang Y,

Taylor PN (2023) Normative brain mapping using scalp EEG and potential clinical

application. Sci Rep 13:13442.

Jasper H, Penfield W (1949) Electrocorticograms in man: Effect of voluntary movement upon the

electrical activity of the precentral gyrus. Archiv für Psychiatrie und Nervenkrankheiten

183:163-174.

Johnson KA et al. (2024) Proceedings of the 11th Annual Deep Brain Stimulation Think Tank:

pushing the forefront of neuromodulation with functional network mapping, biomarkers

for adaptive DBS, bioethical dilemmas, AI-guided neuromodulation, and translational

advancements. Front Hum Neurosci 18:1320806.

Johnson LA, Della Santina CC, Wang X (2016) Selective neuronal activation by cochlear implant

stimulation in auditory cortex of awake primate. J Neurosci 36:12468-12484.

Keating P, Nodal FR, Gananandan K, Schulz AL, King AJ (2013) Behavioral sensitivity to

broadband binaural localization cues in the ferret. J Assoc Res Otolaryngol 14:561-572.

King J, Shehu I, Roland JT, Jr., Svirsky MA, Froemke RC (2016) A physiological and behavioral

system for hearing restoration with cochlear implants. J Neurophysiol 116:844-858.

Klinke R, Kral A, Heid S, Tillein J, Hartmann R (1999) Recruitment of the auditory cortex in

congenitally deaf cats by long-term cochlear electrostimulation. Science 285:1729-1733.

Kolda TG, Bader BW (2009) Tensor Decompositions and Applications. SIAM Review 51:455-

500.

Kral A, et al. (2002) Hearing after congenital deafness: Central auditory plasticity and sensory

deprivation. Cereb Cortex 12:797-807.

Kral A, Eggermont JJ (2007) What's to lose and what's to learn: Development under auditory

deprivation, cochlear implants and limits of cortical plasticity. Brain Res Rev 56:259-269.

Martins ARO, Froemke RC (2015) Coordinated forms of noradrenergic plasticity in the locus

coeruleus and primary auditory cortex. Nat Neurosci 18:1483-1492.

McDermott HJ (2004) Music perception with cochlear implants: a review. Trends Amplif 8:49-82.

Merzenich MM, Knight PL, Roth GL (1973) Cochleotopic organization of primary auditory cortex

in the cat. Brain Res 63:343-346.

Mesgarani N, Cheung C, Johnson K, Chang EF (2014) Phonetic feature encoding in human

superior temporal gyrus. Science 343:1006-1010.

Michelson RP (1971) The results of electrical stimulation of the cochlea in human sensory

deafness. Ann Otol Rhinol Laryngol 80:914-919.

Middlebrooks JC, Bierer JA (2002) Auditory cortical images of cochlear-implant stimuli: coding

of stimulus channel and current level. J Neurophysiol 87:493-507.

Moore DR, RV Shannon (2009) Beyond cochlear implants: awakening the deafened brain. Nat

Neurosci 12:686-691.

Norman-Haignere SV, Long LK, Mesgarani N, Devinsky O, Flinker A, Doyle W, Irobunda I,

Merricks EM, Schevon CA, Feldstein NA, McKhann GM (2022) Multiscale temporal

integration organizes hierarchical computation in human auditory cortex. Nat Hum Behav

6:455-469-469.

Nourski KV, Etler CP, Brugge JF, Oya H, Kawasaki H, Reale RA, Abbas PJ, Brown CJ, Howard

MA (2013) Direct recordings from the auditory cortex in a cochlear implant user. J Assoc

Res Otolaryngol 14:435-450.

Polley DB, Read HL, Storace DA, Merzenich MM (2007) Multiparametric auditory receptive field

organization across five cortical fields in the albino rat. J Neurophysiol 97:3621-3638.

Ray S, Maunsell JH (2011) Different origins of gamma rhythm and high-gamma activity in

macaque visual cortex. PLoS Biol 9:e1000610.

Simmons FB, Epley JM, Lummis RC, Guttman N, Frishkopf LS, Harmon LD, Zwicker E (1965)

Auditory Nerve: Electrical Stimulation in Man. Science 148:104-106.

Stronks, HC, Arendsen TS, Veenstra M, Boermans P-PBM, Briaire JJ, Frijns JHM (2025) Effects

of preoperative factors on the learning curves of postlingual cochlear implant recipients.

Ear Hear (in press).

Svirsky M (2017) Cochlear implants and electronic hearing. Physics Today 70:52-58.

Tang C, Hamilton LS, Chang EF (2017) Intonational speech prosody encoding in the human

auditory cortex. Science 357:797-801.

Trumpis M, Insanally M, Zou J, Elsharif A, Ghomashchi A, Sertac Artan N, Froemke RC, Viventi

J (2017) A low-cost, scalable, current-sensing digital headstage for high channel count

muECoG. J Neural Eng 14:026009.

Vermeire K, Landsberger DM, Schleich P, Van de Heyning PH (2013) Multidimensional scaling

between acoustic and electric stimuli in cochlear implant users with contralateral hearing.

Hear Res 306:29-36.

Vollmer M, Beitel RE (2011) Behavioral training restores temporal processing in auditory cortex

of long-deaf cats. J Neurophysiol 106:2423-2436.

Walzl EM, Woolsey CN (1946) Effects of cochlear lesions on click responses in the auditory cortex

of the cat. Bull Johns Hopkins Hosp 79:309-319.

Williams AH, Kim TH, Wang F, Vyas S, Ryu SI, Shenoy KV, Schnitzer M, Kolda TG, Ganguli S

(2018) Unsupervised Discovery of Demixed, Low-Dimensional Neural Dynamics across

Multiple Timescales through Tensor Component Analysis. Neuron 98:1099-1115.

Wilson BS, Finley CC, Lawson DT, Wolford RD, Eddington DK, Rabinowitz WM (1991) Better

speech recognition with cochlear implants. Nature 352:236-238.

Wilson BS, MF Dorman (2008) Cochlear implants: A remarkable past and a brilliant future. Hear

Res 242:3-21.

Woods V, Trumpis M, Bent B, Palopoli-Trojani K, Chiang C-H, Wang C, Yu C, Insanally MN,

Froemke RC, Viventi J (2018) Long-term recording reliability of liquid crystal polymer

μECoG arrays. J Neural Eng 15:066024.

Zeng FG (2022) Celebrating the one millionth cochlear implant. JASA Express Lett 2:077201.

     Figures

Hight et al., Fig. 1

Figure 1. Auditory cortex iEEG responses to pure tone stimuli in normal-hearing and

deafened cochlear implant rats.

A, Schematic of 60-channel cortical surface electrode arrays, covering 3.25 x 3.25 mm on the

surface of auditory cortex to record tone-evoked responses in normal-hearing (NH) trained rats.

B, Some animals were bilaterally deafened and fitted with a unilateral cochlear implant (CI).

C, Behavioral training of subset of animals on auditory go/no-go frequency recognition task.

Animals were first trained when normal-hearing (NH, N=4, d': 2.9±0.1) and then re-trained to

respond to cochlear implant stimulation (CI, N=3, d': 0.9±0.2).

D, Examples of trial-averaged single-site iEEG responses (top, ERPs; middle, ERP spectrograms;

bottom, HG). Clear transients were evoked by tones in normal-hearing animals (NH, left column)

and in cochlear implant rats (CI, right column).

E, iEEG response magnitude was similar between normal-hearing (NH, ERP amplitude: 1.9±0.1

µV; HG amplitude: 0.6±0.1 a.u.) and cochlear-implant rats (CI, ERP amplitude: 2.0±0.2 µV,

p=0.53 compared to normal-hearing ERPs, linear mixed effects; HG amplitude: 0.6±0.1 a.u.,

p=0.39 compared to normal-hearing HG).

Figure 2. Tone-evoked and cochlear implant-evoked iEEG measurements are spatially

organized.

A, F, Trial-averaged tone-evoked event-related potentials (ERPs, panel **A**) and high gamma (HG,

panel **F**) were spatially restricted to regions along the iEEG recording array; these active regions

shifted as a function of stimulus.

B, G, Spatial correlations of evoked response areas decreased monotonically as a function of

increasing stimulus separation, truncated at large separations due to low sample sizes. Evoked

iEEG responses as assessed by ERPs and HG were nonrandom for normal-hearing and implanted

rats ($p < 10^{-8}$ compared to all shuffled responses), but were locally tonotopic in normal-hearing rats

($p < 10^{-4}$) but not implanted rats (ERPs: $p = 0.5$, HG: $p = 0.7$).

C, H, Determining the preferred stimulus of spatially-evoked activity revealed smooth gradients

shifting from high-to-low to high tone frequencies or cochlear implant channels (ERPs, panel **C**;

HG, panel **H**).

D, I, Local tonotopic gradients for each recording site plotted on a unit circle (blue) as a function

of magnitude (strength of gradient) and angle (direction of gradient). The vectors across each

recording site were averaged to produce an overall tonotopic vector (black) whose magnitude

represents a metric of overall topography (ERPs, panel **D**; HG, panel **I**). The mean vector was

plotted against the mean vector computed from n=1,000 shuffled maps (ERPs, panel **D**: normal-

hearing z-score: 6.6, $p < 10^{-10}$; implanted z-score: 7.9, $p < 10^{-14}$; HG, panel **I**: normal-hearing z-score:

2.1, $p = 0.02$; implanted z-score: 1.5, $p = 0.07$).

E, J, Z-scored magnitudes of mean tonotopic vectors across animals (ERPs, panel **E**: normal-

hearing mean z-score: 4.7 ± 1.0, implanted mean z-score: 2.6 ± 1.0, $p = 0.05$, linear mixed effects;

HG, panel **J**: normal-hearing mean z-score: 3.0 ± 0.9, implanted mean z-score: 2.1 ± 0.9, $p = 0.48$).

Hight et al., Fig. 3

1019

Figure 3. Trial-by-trial cochleotopic encoding is more variable in cochlear implant vs

normal-hearing rats.

A, C, Trial-by-trial evoked iEEG measurements in both normal-hearing and implanted rats

revealed peaks across time (left) and space (right) (ERP, panel **A**; HG, panel **C**)

B, D, Variability of iEEG measurements across trials (root mean square, rms) was consistently

higher for spatial distributions of cochlear implant-evoked compared to tone-evoked activity, for

ERPs in panel **B** (bottom, ERP spatial NH mean rms: 0.32±0.01, CI mean rms: 0.33±0.02, p=0.011,

linear mixed effects) but not for temporal distributions (top, ERP temporal NH mean rms: 1.6±0.3

over all animals, CI mean rms: 1.9±0.5, for animals monitored before and after deafening,

p=0.054) and HG in panel **D** (top, HG temporal NH mean rms: 2.4±0.3 over all animals, CI mean

rms: 3.3±0.9, p=0.17; bottom, HG spatial NH mean rms: 1.2±0.2, CI mean rms: 1.3±0.3, p=0.35).

Hight et al., Fig. 4

Figure 4. Trial-by-trial iEEG measurements encode stimulus identity.

A, Trial-by-trial ERPs evoked by 1.4 kHz (left), 8 kHz (middle), and 32 kHz tones (right) are

plotted for three recording sites (blue) reveal discernable evoked transients and spatially restricted

patterns of evoked magnitudes (stimulus onsets depicted by dotted line).

B, Trial-by-trial iEEG measurements concatenated such that columns represent recording sites

(spatial) and post-stimulus sampling (temporal), rows by stimulus trials. Data then reorganized by

PCA and reduced to the 15 components according to magnitude of explained variance.

C, Classification matrices are plotted means across bootstrapped repeated (N=1,000) versions of

LDA classifiers trained using 13 randomly selected trials for each stimulus, and classification

predictions of single and remaining trials reveal significant prediction of stimulus identity (dashed

line: chance-level error distance; solid lines: actual mean error distances).

D, Stimulus prediction probabilities plotted across animals (black: mean, grey: s.e.m.) and as

function of either octaves (normal-hearing) or channels (cochlear implant) from actual stimulus,

reflecting a gradient in which adjacent stimuli share more encoded features than other stimuli.

E, Decoder performance (mean error distance) across individual animals was somewhat worse for

cochlear implant ERPs compared to tone-evoked ERPs (ERP mean error rate relative to chance

for normal-hearing: 0.74±0.05, cochlear implant: 0.78±0.06; for animals assessed both first when

normal-hearing and then after cochlear implantation $p<10^{-4}$, linear mixed effects), but not for HG

(HG mean error rate relative to chance for normal-hearing: 0.90±0.03, cochlear implant:

0.91±0.04; for animals assessed both first when normal-hearing and then after cochlear

implantation p=0.15).

1054

Figure 5. Trial-by-trial decoding from either spatial or temporal aspects of iEEG signals.

A, Raw trial-by-trial ERPs for a single animal are plotted for 3 channels.

B-C, Trial-by-trial iEEG measurements are reduced into either spatial only (**B**) or temporal only

(**C**) by extracting either the magnitude of evoked activity or averaging across all recording sites.

D, Re-training PCA-LDA decoders on spatial-only (middle) or temporal-only (right) does not

abolish the encoding of stimulus identity.

E, Decoder errors (mean error distance re. chance) across animals are plotted for decoders trained

on spatial+temporal, spatial-only, and temporal-only iEEG measurements. Mean error distance for

spatial+temporal ERPs, normal-hearing: 0.74 ± 0.04, implant: 0.86 ± 0.06; for spatial+temporal HG,

normal-hearing: 0.90 ± 0.03, implant: 0.97 ± 0.04. Mean error distance for spatial-only ERPs,

normal-hearing: 0.77 ± 0.04, implant: 0.77 ± 0.08; for HG, normal-hearing: 0.89 ± 0.04, implant:

0.87 ± 0.05. Mean error distance for temporal-only ERPs, normal-hearing: 0.82 ± 0.05, implant:

0.81 ± 0.07; for HG, normal-hearing: 0.87 ± 0.04, implant: 0.93 ± 0.05.

1068

Figure 6. TCA-based decoding of single-trial iEEG measurements.

A, Schematic of TCA with 3-dimensional tensors with orthogonal dimensions of spatial, temporal

and trial factors.

B, TCA-reduced iEEG measurements of stimulus-evoked ERPs in normal-hearing rats are plotted

across 15 components of spatial (top row), temporal (middle row) and trial factors (bottom row).

C, Classification matrices of mean decoder predictions across bootstrapped repeated (N=1,000)

versions LDA classifiers trained using 13 randomly selected trials for each stimulus indicated that

iEEG measurements encode stimulus identity from single stimulus presentations (dashed line:

chance-level error distance; solid lines: actual mean error distances).

D, Stimulus prediction probabilities are plotted across animals (black: mean, grey: std. error) and

as a function of either octaves or channels in away from actual stimulus, normal-hearing and

implanted rats. Correct prediction probabilities are high across all conditions and prediction errors

coalescing of predictions toward actual stimuli (orange: mean and std. error of decoder

performance on shuffled trials; grey: mean error distance, dashed line: chance level error distance).

E, Decoder errors (mean error distance) across individual animals were slightly smaller for evoked

iEEG measurements in normal-hearing compared to implanted rats (ERP mean error rate re.

chance normal-hearing: 0.77±0.04, implanted: 0.80±0.06; HG mean error rate re. chance normal-

hearing: 0.90±0.03, implanted: 0.88±0.05). Comparisons between normal-hearing and implanted

iEEG measurements showed significant decrease in estimated error distances for ERP (top, linear

mixed-effects model: $p < 10^{-5}$) and HG (bottom, p=0.03).

1090

Figure 7. TCA data reductions reveal latent spatial factors are topographically organized.

A, TCA-based analysis of evoked neural activity, divided into 15 unique components where each

component is separated into orthogonal dimensions of spatial factors (top row), temporal factors

(middle row) and trial factors (bottom row).

B, Spatial maps for tone-evoked or electrode-evoked responses recreated from TCA reduced data.

C, Reducing re-organized spatial factors revealed a TCA map (left) with topographical gradients

in same location and direction as the tonotopic map reduced from raw measurements (right).

D, Spatial correlations of evoked response areas decreased monotonically as a function of

increasing stimulus separation. TCA-reduced models of evoked iEEG responses as assessed by

ERPs and HG were nonrandom for normal-hearing and implanted rats ($p<10^{-8}$ compared to all

shuffled responses). TCA-reduced models were locally tonotopic only for HG in normal-hearing

rats (normal-hearing ERPs: p=0.18, normal-hearing HG: $p<10^{-4}$, cochlear implant ERPs: p=0.43,

cochlear implant HG: p=0.40).

E, Z-scored magnitudes of mean tonotopic vectors across animals were similar (ERPs, normal-

hearing mean z-score: 6.2±3.6, cochlear implant mean z-score: 3.9±2.1, p=0.16, linear mixed

effects; HG, normal-hearing mean z-score: 2.9±1.1, implanted mean z-score: 2.5±0.7, p=0.75).

Hight et al., Fig. 8

Figure 8. Lack of information transfer between acoustic and electrical stimulation representations in the same animals.

A, Evoked iEEG measurements from a subset of data from normal-hearing rat reduced using TCA.

B, Evoked iEEG measurements from previously withheld trails from normal-hearing rat reduced using TCA, constraining the model with the spatial and temporal factors from the original TCA model, leaving only the trials as the optimizable variables.

C, Linear discriminant analysis classifiers are trained on the trial factors extracted from the original TCA-reduced models of evoked data and then used to predict stimulus identity from the trial factors from the re-optimized TCA-reduced models of withheld normal-hearing measurements.

D, Classification matrices are plotted means of decoder predictions across bootstrapped repeated (N=1,000) versions of linear-discriminant analysis (LDA) classifiers. Mutual information (IT) are indicated above these mean classification matrices.

E, Stimulus prediction probabilities plotted across animals (black: mean, grey: s.e.m.) and as function of either octaves (normal-hearing) or channels (cochlear implant) from actual stimulus, reflecting a gradient in which adjacent stimuli share more encoded features than other stimuli (for ERP, but not HG).

F, Evoked iEEG measurements in cochlear implant rat reduced using TCA, constraining the model with the spatial and temporal factors from the original TCA model optimized on normal-hearing data, leaving only the trials as the optimizable variables. Linear discriminant analysis classifiers are trained on the trial factors extracted from the original TCA-reduced models of evoked data in normal-hearing conditions and then used to predict stimulus identity from the trial factors from the TCA-reduced models of implant-evoked measurements.

G, Classification matrices are plotted means of decoder predictions across bootstrapped repeated

(N=1,000) versions of linear-discriminant analysis (LDA) classifiers.

H, Information transfer of normal-hearing trained and implant tested decoders reveal little-to-no

information transfer (IT mean across animals, ERP: 1.2±0.6, HG: 0.3±0.1%) compared to both

normal-hearing (IT mean across animals, ERP: 2.8±1.2%, p=0.044, HG: 0.4±0.4%, p=0.187 one-

tailed t-test) and cochlear implant where rows were shuffled within columns (IT mean across

animals, ERP: 2.4±1.0%, p=0.042, HG: 0.3±0.2%, p=0.209, one-tailed t-test). Information transfer

of normal hearing re-optimized decoders was significantly higher compared to cochlear implant

decoders where rows were shuffled within columns (ERP: p=0.050, HG: p=0.107, Student's one-

tailed t-test).

Hight et al., Supplemental Fig. 1

Supplemental Figure 1. ECAP measurements of spatio-temporal cochlear implant tuning.

A, Forward masking was performed to assess the spatial tuning of cochlear stimuli in the cochlea

via ECAPs measured by adjacent cochlear implant electrodes.

B, Forward masking was performed to assess temporal tuning of cochlear implant stimuli in the

cochlea via ECAPs measured by adjacent cochlear implant electrodes. The masker stimulus was

delivered by the same electrode as the probe.

C, Spatial tuning functions were averaged across all probe electrodes in N=3 animals (black, mean;

gray: s.e.m.; orange, average of individual subjects).

D, Temporal tuning functions were averaged across all probe electrodes and N=3 animals (black,

mean; gray, s.e.m.; orange, average of individual subjects).

Hight et al., Supplemental Fig. 2

1151

Supplemental Figure 2. Experimental timeline and animal tracker.

A, Rats underwent a combination of behavioral training (when typically-hearing), iEEG recordings, and then behavioral testing (after deafening) in a specific sequence, but not all animals included here participated in every phase.

B, iEEG measurements were obtained in a total of N=10 animals. In a subset of these animals (N=4), we also obtained iEEG measurements in response to both acoustic tones before deafening and cochlear implant stimulation after deafening. In addition to iEEG recordings, we also behaviorally trained either prior (tones) or after iEEG recordings with cochlear implant stimuli.

1160

Supplemental Figure 3. Maps of stimulus preferences for tone- or cochlear implant-evoked iEEG measurements.

A, Maps of preferred stimuli are derived from event-related potentials (ERP) for 10 animals, including tone evoked iEEG measurements (left column) and cochlear implant-evoked iEEG measurements (right column). For the cochlear implant, single channel stimuli were either delivered via tones presented to the cochlear implant processor (top 3 maps) and or single channel stimuli were triggered by a direct connection between computer and the cochlear implant processor (bottom 3 maps).

Hight et al., Supplemental Fig. 4

1169

Supplemental Figure 4: Numbers of components for PCA and TCA models

A. The means (±s.e.m.) of explained variance per component for PCA models across all ERP data

(top row) decreases rapidly from 30 percent to near zero within 30 components. The means

(±s.e.m.) of explained variance per component for PCA models for HG data (bottom row) and

decreases from 12 percent rapidly to a steady decline within 30 components. Orange dashed line:

linear regression of components 16-30 are plotted.

B. The means (±s.e.m.) of model error for TCA models of ERP (top row) and HG (bottom row)

decrease as a function of number of components.