Non-linear transfer characteristics of stimulation and recording hardware account for spurious low-frequency artifacts during amplitude modulated transcranial alternating current stimulation (AM-tACS)

Florian H. Kasten[1,2], Ehsan Negahbani[3], Flavio Fröhlich[3,4,5,6,7,8], Christoph S. Herrmann[1,2,9,*]

[1]Experimental Psychology Lab, Department of Psychology, European Medical School, Cluster for Excellence "Hearing for All", Carl von Ossietzky University, Oldenburg, Germany

[2]Neuroimaging Unit, European Medical School, Carl von Ossietzky University, Oldenburg, Germany

[3]Department of Psychiatry, University of North Carolina, Chapel Hill, NC, USA

[4]Department of Cell Biology and Physiology, University of North Carolina, Chapel Hill, NC, USA

[5]Department of Biomedical Engineering, University of North Carolina, Chapel Hill, NC, USA

[6]Neuroscience Center, University of North Carolina, Chapel Hill, NC, USA

[7]Department of Neurology, University of North Carolina, Chapel Hill, NC, USA

[8]Carolina Center for Neurostimulation, University of North Carolina, Chapel Hill, NC, USA

[9]Research Center Neurosensory Science, Carl von Ossietzky University, Oldenburg, Germany

*Corresponding author: Christoph S. Herrmann, Experimental Psychology Lab, Carl von Ossietzky University, Ammerländer Heerstr. 114 – 118, 26129, Oldenburg, Germany. christoph.herrmann@uni-oldenburg.de, phone: +49 441 798 4936

Abstract

Amplitude modulated transcranial alternating current stimulation (AM-tACS) has been recently proposed as a possible solution to overcome the pronounced stimulation artifact encountered when recording brain activity during tACS. In theory, AM-tACS does not entail power at its modulating frequency, thus avoiding the problem of spectral overlap between brain signal of interest and stimulation artifact. However, the current study demonstrates how weak non-linear transfer characteristics inherent in stimulation and recording hardware can reintroduce spurious artifacts at the modulation frequency. The input-output transfer functions (TFs) of different stimulation setups were measured. The setups included basic recordings of signal-generator and stimulator outputs as well as M/EEG phantom measurements. 6th-degree polynomial regression models were fitted to model the input-output TFs of each setup. The resulting TF models were applied to digitally generated AM-tACS signals to predict the location of spurious

artifacts in the spectrum. All four setups measured for the study exhibited low-frequency arti-

facts at the modulation frequency and its harmonics when recording AM-tACS. Fitted TF mod-

els showed non-linear contributions significantly different from zero (all p < .05) and success-

fully predicted the frequency of artifacts observed in AM-signal recordings. Results suggest

that even weak non-linearities of stimulation and recording hardware can lead to spurious ar-

tifacts at the modulation frequency and its harmonics. Thus, findings emphasize the need for

more linear stimulation devices for AM-tACS and careful analysis procedures, which take into

account these low-frequency artifacts to avoid confusion with effects of AM-tACS on the brain.

Abstract: 241 words, Manuscript: 3999 words (including figure captions)

Keywords: amplitude modulated transcranial alternating current stimulation (AM-tACS), MEG,

EEG, artifact, tACS, stimulation hardware.

1   Introduction

Transcranial alternating current stimulation (tACS) is receiving growing popularity as a tool to

interfere with endogenous brain oscillations in a frequency specific manner (Fröhlich and

McCormick, 2010; Helfrich et al., 2014; Herrmann et al., 2013; Ozen et al., 2010; Zaehle et al.,

2010), allowing to study causal relationships between these oscillations and cognitive functions

(Fröhlich, 2015; Herrmann et al., 2016). Further, its use might offer promising new pathways

for therapeutic applications to treat neurological or psychiatric disorders associated with dys-

functional neuronal oscillations (Brittain et al., 2013; Herrmann and Demiralp, 2005; Uhlhaas

and Singer, 2012, 2006).

While mechanisms of tACS have been studied in animals (Fröhlich and McCormick, 2010; Kar

et al., 2017; Ozen et al., 2010; Reato et al., 2010) and using computational modelling (Ali et

al., 2013; Reato et al., 2010; Zaehle et al., 2010), the investigation of tACS effects in human

subjects has so far mostly been studied behaviorally (Kar and Krekelberg, 2014; Lustenberger

et al., 2015; Neuling et al., 2012), by measuring BOLD response (Cabral-Calderin et al., 2016;

Violante et al., 2017; Vosskuhl et al., 2016), or by tracking outlasting effects in M/EEG signals

(Kasten et al., 2016; Kasten and Herrmann, 2017; Neuling et al., 2013; Veniero et al., 2015;

Vossen et al., 2015; Zaehle et al., 2010). Due to a strong electro-magnetic artifact, which spec-

trally overlaps with the brain oscillation under investigation, online measurements of tACS ef-

fects in M/EEG is challenging. However, uncovering these online effects is crucial as the afore-

mentioned approaches can only provide limited, indirect insights to the mechanisms of action

during tACS in humans. In addition, online monitoring of physiological signals during stimula-

tion may enable closed-loop applications that can provide potentially more powerful, individu-

ally tailored, adaptive stimulation protocols (Bergmann et al., 2016). Some authors applied

artifact suppression techniques such as template subtraction (Dowsett and Herrmann, 2016;

Helfrich et al., 2014; Voss et al., 2014) or spatial filtering (Neuling et al., 2015; Ruhnau et al.,

2016) to recover brain signals obtained during concurrent tACS-M/EEG. However, these ap-

proaches are computationally costly, and therefore i.e. difficult to implement in closed-loop

protocols. Further, their application is limited as they fail to completely suppress the artifact

and analysis approaches must be limited to robust procedures to avoid false conclusions about

stimulation effects (Neuling et al., 2017; Noury et al., 2016; Noury and Siegel, 2017).

As a solution to these issues, amplitude modulated tACS (AM-tACS), using a high frequency

carrier signal which is modulated in amplitude by a lower frequency modulation signal, chosen

to match the targeted brain oscillation has been proposed (Witkowski et al., 2016). Amplitude

modulated signals contain spectral power at the frequency of the carrier signal (f_c; and two

sidebands at $f_c \pm f_m$; modulation frequency), but no power at f_m itself (see **Figure 1** for an

illustration). Consequently, the tACS artifact would be shifted into higher frequencies, elegantly

avoiding spectral overlap with the targeted brain oscillation. However, more recently low-fre-

quency artifacts at f_m have been reported in sensor-level MEG recordings during AM-tACS

(Minami and Amano, 2017). These artifacts required the application of advanced artifact sup-

pression algorithms (Minami and Amano, 2017). Although the authors of that study explained

these artifacts by non-linear characteristics of the digital-analog conversion, a detailed inves-

tigation into these low-frequency artifacts arising during AM-tACS and how these emerge has

not yet been provided. In fact, the process of stimulation on the one side and signal recording

on the other side involves at least one step of digital-analog (generating a stimulation signal)

and one step of analog-digital conversion (sampling brain signal plus stimulation artifact). The

linearity of these conversions, however, is naturally limited by properties of the hardware in

use (Vargha et al., 2001). To further complicate the situation, the amplification involved in the

recording process using M/EEG can be another potential source of nonlinearity. The ampli-

tudes usually applied in tACS can potentially cause signals/artifacts, beyond the dynamic

range where the measurement devices exhibit linear transfer characteristics (Cooper, R.,

Osselton, J. W., & Shaw, 1974). In general all electronic components, including those that are

usually idealized as being linear (i.e. resistors), exhibit some degree of non-linearity in reality,

especially when operating under extreme conditions (Maas, Stephen, 2003).

To shed more light on the effects of non-linearity of stimulation and recording hardware on AM-

tACS signals, input-output transfer functions (TFs) of different AM-tACS setups were estimated

and evaluated with respect to their performance in predicting low-frequency artifacts of AM-

tACS[1].

2   Materials & Methods

In order to characterize non-linearities inherent in different tACS setups, the transfer functions

(TFs) relating input-output amplitudes of four different tACS setups, with increasing complexity,

were recorded and modeled by polynomial regression models. Additionally, AM-tACS signals

were recorded to demonstrate the presence of low-frequency artifacts. TF models were applied

to digital AM-signals to predict output spectra of the physical recordings. The following four

setups were evaluated. No human or animal subjects were involved in the experiment.

2.1   Test Setups

2.1.1   Basic DAC recording

112   For the first, basic setup, a digital/analog-analog/digital converter (DAC; NiUSB-6251, National

113   Instruments, Austin, TX, USA) recorded its own output signal. The signal was digitally gener-

114   ated using Matlab 2016a (The MathWorks Inc., Natick, MA, USA) and streamed to the DAC

115   via the Data Acquisition Toolbox. The signal was generated and recorded at a rate of 10 kHz

116   (**Figure 1A**).

2.1.2   DAC & tACS stimulator

118   In the second setup the DAC was connected to the remote input of a battery-driven constant

119   current stimulator (DC Stimulator Plus, Neuroconn, Illmenau, Germany). Stimulation was ad-

120   ministered to a 5.6 kΩ resistor. The signal was recorded from both ends of the resistor using

121   the DAC (**Figure 1B**).

2.1.3   DAC & tACS recorded from phantom using EEG

123   In the third setup the DC Stimulator was connected to two surface conductive rubber electrodes

124   attached to a melon serving as a phantom head. Electrodes were attached using an electrically

---

[1] In contrast to the frequency-domain definition of TFs commonly used in linear-system analysis, here TF refers to the input-output amplitude relation of a probe signal.

Figure 1: Experimental setups and signals. (A-D) Schematic representations of the evaluated setups. For details refer to the "**Test setups**" section in the manuscript. DAC: Digital-Analog converter. MSR: Magnetically shielded-room. Arrows indicate the direction of signal flow **(E,F)** Time domain representations of a low-frequency sine-wave classically used for tACS (**E**) and an amplitude modulated sine wave with a carrier frequency of 220 Hz modulated at 10 Hz (**F**). Red curve depicts the 10 Hz envelope of the signal. **(G,H)** Frequency-domain representations of the tACS signals. While the 10 Hz sine wave exhibits its power at 10 Hz (**G**), the amplitude modulated signal only exhibits power at the carrier frequency and two side-bands, but no power at the modulation frequency (**F**). (**I**) Probe stimulus for measuring the setups transfer curves was a 220 Hz single-cycle sine wave. Probe stimuli of different amplitude were concatenated to a sweep (**J**). Red asterisks mark points that were extracted as V_{out} measure. To enhance visibility of the general concept, a sweep consisting of 51 probes is displayed here. For the actual measurements of the TFs 10 sweeps with 10001 probes were used.

conductive, adhesive paste (ten20, Weaver & Co., Aurora, CO, USA). The signal was recorded from an active Ag/AgCl EEG electrode (ActiCap, Brain Products, Gilching, Germany), placed between the tACS electrodes. Two additional electrodes were attached to the phantom to serve as reference and ground for the recording (positions were chosen to mimic a nose-reference and a ground placed on the forehead). The signal was generated by the DAC at a rate of 10 kHz and recorded at 10 kHz using a 24-bit ActiChamp amplifier (Brain Products, Gilching, Germany). EEG and stimulation electrode impedances were kept below 10 kΩ (**Figure 1C**).

2.1.4   DAC & tACS recorded from phantom using MEG

Finally, the phantom was recorded using a 306-channel whole-head MEG system (Elekta Neu-

romag Triux, Elekta Oy, Helsinki, Finland) located inside a magnetically shielded room (MSR;

Vacuumschmelze, Hanau, Germany). Signals were recorded without internal active shielding

at a rate of 1 kHz and online filtered between 0.3 and 330 Hz. The stimulation signal was gated

into the MSR via the MRI-extension kit of the DC stimulator (Neuroconn, Illmenau, Germany;

Figure 1D).

2.2   Transfer function and AM-tACS measurements

A probe stimulus consisting of a one cycle sine wave at 220 Hz was used to obtain measure-

ments of each setups transfer function (TF). 10001 probes of linearly spaced amplitudes (V_{in}),

ranging from -10 V to 10 V for the first setup, from -0.75 V to 0.75 V for the second and third

setup, and from -0.5 V to 0.5 V for the MEG setup, were concatenated to a sweep stimulus

with a total duration of approximately 45 sec. (see **Figure 1I-J** for a schematic visualization).

Amplitudes had to be adjusted for setups involving the DC stimulator to account for higher

output voltages due to the 2 mA per V voltage-to-current conversion of the remote input. The

chosen input voltages correspond to a maximum output of 3 mA peak-to-peak amplitude of the

DC stimulator (a maximum current of 2 mA was chosen for the MEG setup to avoid saturation

and flux trapping of MEG sensors). Ten consecutive sweeps were applied and recorded for

each setup. In order to evaluate how well the obtained TF can predict artifacts in the spectrum

of AM-tACS, AM-signals with f_c = 220 Hz and f_m = 10 Hz, 11 Hz, and 23 Hz at different ampli-

tudes (100%, 66.7%, 33.4% and 16.16% of the maximum range applied during the TF record-

ing) were generated. Amplitudes were chosen to produce output currents of 3 mA, 2 mA, 1

mA, and 0.5 mA when using the DC-Stimulator (2 mA, 1.3 mA, 0.66 mA, 0.33 mA for the MEG

setup). AM-signals were computed based on the following equation:

168
$$AM_{Signal}(t) = a_{stim}\left(\left(\frac{\sin(2\pi * f_m * t)}{2} + \frac{1}{2}\right) * \sin(2\pi * f_c * t)\right), \tag{1}$$

169   where a_{stim} is the stimulation amplitude, f_m is the modulation frequency and f_c is the carrier

170   frequency. Each signal was generated and recorded with 60 repetitions to increase signal-to-

171   noise ratios.

2.3   Data Analysis

173   Data analysis was performed using Matlab 2016a (The MathWorks Inc., Natick, MA, USA).

174   The fieldtrip toolbox (Oostenveld et al., 2011) was used to import and segment M/EEG record-

175   ings. All scripts and underling datasets are available online (https://osf.io/czb3d/).

2.3.1   Data processing and transfer function estimation

The recorded sweeps were epoched into segments containing single cycles of the sine-waves

used as probes. All Segments were baseline corrected and the peak-amplitude (V_{out}) of each

epoch was extracted by identifying the minimum (for $V_{in} < 0$) or maximum values (for $V_{in} \geq 0$)

within each segment. A 6th-degree polynomial regression model was fitted to each repetition

of the sweep to predict V_{out} (recorded peak amplitudes) as a function of V_{in} (generated peak

amplitudes) using a least-square approach:

$$\widehat{V_{out}} = f(V_{in}), \tag{2}$$

184   with:

$$f(V_{in}) = \beta_6 * V_{in}^6 + \beta_5 * V_{in}^5 + \beta_4 * V_{in}^4 + \beta_3 * V_{in}^3 + \beta_2 * V_{in}^2 + \beta_1 * V_{in} + \beta_0 \tag{3}$$

The fitting procedure was performed separately for each sweep to obtain measures of variance

for each of the coefficients. Coefficients were averaged subsequently and the resulting function

was used to model each systems TF. R^2-values were calculated as measures for goodness of

fit.

In order to evaluate the performance of the TF models in predicting low-frequency AM-tACS

artifacts of the setups, the digitally generated AM-tACS signals were fed through the TF mod-

els. Subsequently, the predicted output signals were compared to the AM-tACS recordings

acquired for each setup. To this end, power spectra of the original digital, the predicted and

the recorded AM-signals were computed. The resulting power spectra of the AM-signals were

averaged over the 60 repetitions. For the MEG recording, results are presented for an exem-

plary parieto-occipital gradiometer sensor (MEG2113).

2.3.2   Identification of low-frequency artifacts

To identify systematic artifacts in the spectrum of the AM-signal in the noisy recordings, the

averaged power spectra were scanned for artifacts within a range from 2 Hz to 301 Hz. Artifacts

were defined as the power at a given frequency being altered by at least 5% as compared to

the mean power of the two neighboring frequencies. The identified artifacts were statistically

compared to the power in the two neighboring frequencies using student's t-tests. Bonferroni-

correction was applied to strictly account for multiple comparisons.

2.3.3   Simulation

To evaluate the effect of each non-linear term in the TF models on the output signal, a simu-

lation was carried out. To this end an amplitude modulated signal with $f_c = 220\ Hz$ and $f_m =$

$10\ Hz$ was evaluated by simplified TFs where all coefficients were set to zero except for the

linear and one additional non-linear term which were set to one in each run. This procedure

leads to exaggerated output spectra that do not realistically resemble the recorded TFs. How-

ever, they are well suited to illustrate the spectral artifacts arising from each of the non-linear

terms.

In addition to the AM-signal, we generated a temporal interference (TI) signal that was recently

proposed as a tool to non-invasively stimulate deep structures of the brain (Grossman et al.,

2017). TI stimulation consists of two externally applied, high frequency sine waves of slightly

differing frequencies that result in an AM-signal where their electric fields overlap. Since the

generation of this AM-signal is mathematically slightly different as compared to the other AM-

tACS approach, this signal was separately modelled for two stimulation signals based on the

following equation:

219
$$TI_{Signal}(t) = a_{Stim} * \frac{(\sin(2\pi*f_1*t)+\sin(2\pi*f_2*t))}{2}, \tag{4}$$

with $f_1 = 200\ Hz$ and $f_2 = 210\ Hz$. The overlap of these two frequencies results in an amplitude

modulation at 10 Hz.

3   Results

3.1   Systematic artifacts at modulation frequency of AM-tACS and harmonics

Analysis of the AM-tACS recordings identified systematic artifacts at the modulation frequency

and its harmonics that statistically differed from power at neighboring frequencies in all setups

(all p < .05; **Figure 2** and **3**). Notably, these artifacts were comparatively small, albeit still sig-

nificant at larger amplitudes, when the DAC measured its own output without any further de-

vices in the setup (**Figure 2 left**). When the complexity of the setup was increased, more and

stronger artifacts were observed (**Figure 2 right, Figure 3**). The number and size of artifacts

also tended to increase with stronger stimulation amplitudes. **Figures 2** and **3** depict lower

frequency spectra (1 Hz – 50 Hz) for all setups and frequency-amplitude combinations tested.

3.2   Setups exhibit non-linear transfer characteristics

To obtain a model of each setups TF, 6[th]-degree polynomial regression models were fitted to

the input-output amplitudes of the probe stimuli. All setups tested in this study exhibited coef-

ficients of the non-linear terms of the fitted TFs significantly differing from zero.

In setups 1, 2, and 4 all model coefficients significantly differed from zero (all $p < .004$; bonfer-

roni corrected). For the EEG setup, coefficients β_2 ($p < .02$), β_5 ($p < .004$) and β_6 ($p < .007$)

significantly differed from zero. Results are summarized in **Table 1**. High goodness of fit values

were achieved for all setups under investigation ($R^2 > .99$), indicating that the polynomial func-

tions provide powerful models to describe the input-output characteristics of the setups. Im-

portantly, the non-linearities found during this analysis are subtle compared to the contribution

of the linear terms in each TF. This leads to the impression of linearity when visually inspecting

each setups TF (**Figure 2,3 top panel**). However, as it will be shown in the following, these

small deviations from linearity are sufficient to cause the low frequency artifacts observed dur-

ing the AM-tACS recordings.

Figure 2: Transfer functions (top row) and spectra (lower rows) of setups of the DAC and Stimulator setup.

TFs (**top**) show recorded probe stimulus amplitudes in relation to their input amplitudes (V_{out}/V_{in}; black dots), as well as the course of the TF model (red line). The corresponding function is displayed in the title. Spectra show average power at each frequency in the different AM-recordings (black line). Thin colored lines show power spectra for each of the 60 repetitions. Red line shows the spectrum predicted by evaluating the digital AM-signal by the estimated TF of the setup. Grey areas indicate frequencies significantly differing in power compared to the two neighboring frequencies (*p* < .05, bonferroni corrected). Please note the different scaling of the power spectra. To enhance visibility, spectra are limited to the frequency range between 1 Hz and 50 Hz. Please refer to the **Supplementary Materials** for an alternative version of the figure, covering the full frequency range between 1 and 300 Hz.

3.3 Transfer functions predict frequency of spurious artifacts

When applying the TF models to the digital AM-signals, the resulting spectra provide accurate predictions of the systematic low-frequency artifacts at f_m of the AM-signal and its lower harmonics in the recordings. For the first two setups, where the TF models' goodness of fit is equal to 1, the predicted spectra also capture the amplitudes low-frequency artifacts with relatively high accuracy (**Figure 2**). For the two later setups, however, the predicted spectrum apparently underestimates amplitudes of the artifacts (**Figure 3**). In summary, results suggest that the polynomial functions fitted to the data successfully captured the non-linear process leading to the low-frequency artifacts at f_m, although for the later setups, that exhibited more

Figure 3: Transfer functions (top row) and spectra (lower rows) of the EEG and MEG setup. TFs (**top**) show recorded probe stimulus amplitudes in relation to their input amplitudes (V_{out}/V_{in}; black dots), as well as the course of the TF model (red line). The corresponding function is displayed in the title. Output values (V_{out}) for the MEG setup are expressed in nT. Spectra show average power at each frequency in the different AM-recordings (black line). Thin, colored lines show power spectra for each of the 60 repetitions. Red line shows the spectrum predicted by evaluating the digital AM-signal by the estimated TF of the setup. Grey areas indicate frequencies significantly differing in power compared to the two neighboring frequencies (*p* < .05, bonferroni-corrected). Please note the different scaling and units of the power spectra. To enhance visibility, spectra are limited to the frequency range between 1 Hz and 50 Hz. Please refer to the **Supplementary Materials** for an alternative version of the figure, covering the full frequency range between 1 and 300 Hz.

noise during the measurements, accuracy of the fits seems not sufficient to accurately predict the artifacts amplitudes. In addition, it should be noted that the application of a TF to a pure digital AM-signal can never completely capture the effects of the recording process that involves measurement of noise and external interferences (i.e. line-noise).

3.4 Simulating the isolated effect of non-linear TF-terms

Based on the results presented so far, it was possible to characterize each the non-linearity of each setup and to demonstrate that the estimated TF can be used to predict artifacts in the recorded AM-signals. However, since the obtained TFs are rather complex, a simulation was carried out to investigate the artifacts caused by each of the non-linear terms in isolation. The

Figure 4: Simulation results. (Left column) Spectra resulting from evaluating the digital AM-signal using a sim-

plified TF. A solely linear TF (**top left**) perfectly resembles the input spectrum. Setting the coefficient of an additional

polynomial term with an odd-valued exponent to 1 resulted in additional side bands around f_c (**middle** and **bottom**

left). In contrast, setting the coefficient of an additional polynomial term with an even-valued exponent to 1 resulted

in artifacts at f_m and its harmonics **(right column)**. The higher the exponent of the polynomial terms, the more side-

bands/harmonic artifacts they introduced. The polynomial function applied to generate each spectrum is printed on

top of each plot.

spectra obtained from this simulation are depicted in **Figure 4**. While a solely linear TF does

not change the spectral content of the AM-signal at all (**Figure 4 top left**), polynomial terms

with odd exponents > 1 result in additional side bands around f_c of the AM-signal (**Figure 4**

middle, bottom left). In contrast, terms with even exponents induced artifacts at f_m and its

harmonics (**Figure 4 right column**). The higher the exponent of the polynomial terms the more

sidebands and higher harmonics are introduced to the spectrum, respectively. A separate

simulation for an AM-signal resulting from temporal inteference (Grossman et al., 2017) yielded

a similar result (**Supplementary Figure S3**).

4   Discussion

Amplitude modulated transcranial alternating current stimulation (AM-tACS) offers a promising

new approach to investigate online effects of tACS using physiological recordings. While in

theory AM-tACS should not exhibit artifacts within the frequency range of brain signals, the

current study demonstrates that non-linear transfer characteristics of stimulation and recording

hardware reintroduces such artifacts at the modulation frequency and its lower harmonics.

These artifacts are likely too small to modulate brain activity themselves, they can potentially

be misinterpreted as stimulation effects on the brain if not considered during concurrent re-

cordings of brain activity during AM-tACS. Especially, in cases where spatial information is

missing (i.e. recording from only few EEG sensors), the artifacts in the spectrum might be hard,

if not impossible, to be disentangled from stimulation effects. Consequently, these recordings

must not be considered artifact-free in the range of the modulation frequency. Rather, the ex-

tent of low-frequency artifacts has to be evaluated carefully and taken into account.

The setups evaluated for the current study have been build based on a limited set of hardware.

Thus, the extent of non-linearity might differ for hardware combinations using other stimulator

or recording systems. However, since all electronic components exhibit some degree of non-

linearity (Maas, Stephen, 2003), the general process underlying the generation of low-fre-

quency AM-tACS artifacts is potentially applicable to all setups. Only the size of these artifacts

can differ depending on the (non-)linearity of the system. The current study provides a frame-

work to measure and estimate a setups transfer characteristics and evaluate the strength of

these low-frequency artifacts arising from its non-linearities. Interestingly, the DAC itself

exhibited comparatively weak artifacts, while the more complex setups showed stronger

artifacts at the modulation frequency and several harmonics. This might indicate that the effect

is driven by non-linearities of the stimulator or recording hardware rather than the DAC as

suggested by previous authors (Minami and Amano, 2017).

To obtain a model of each setups transfer characteristics, polynomial regression models were

fitted to the probe-signal recordings. The degree of the models is a best guess to tradeoff

sufficient complexity to capture each setups nonlinearity, and simplicity to retain a straightfor-

ward, interpretable model. Unfortunately, traditional approaches for model selection, i.e. based

on adjusted R^2 or Akaike Information Criterion, that start from a simple intercept or a saturated

model, are not applicable to the data at hand, as the non-linearities observed in the setups are

very subtle. A simple linear model would already account for a huge proportion of the input-

output recordings variance. Adding additional higher degree terms to the model does not suf-

ficiently increase the explained variance to counteract the penalty implemented in most model

evaluation metrics. However, as seen in the simulated data only these terms account for the

low-frequency artifacts observed in the AM-tACS recordings.

Given that the low-frequency AM-tACS artifacts are several orders of magnitude smaller than

the artifact arising during classical tACS (or at the carrier frequency), they are potentially easier

to correct/suppress i.e. by applying beamforming (Chander et al., 2016; Witkowski et al., 2016)

or temporal signal space separation (Minami and Amano, 2017; Taulu et al., 2005) in the MEG

and independent or principal component analysis (ICA/PCA) in the EEG (Helfrich et al., 2014).

However, the efficiency of these methods in the context of AM-tACS needs to be systematically

investigated in future studies. The optimal solution to overcome the artifacts observed here

would be the optimization of stimulation and recording hardware with respect to their linearity.

Neither have tES devices currently available been purposefully designed to apply AM-tACS,

nor are recording systems for brain activity intended to record AM-signals at intensities as

observed during AM-tACS. Devices exhibiting more linear transfer characteristics as i.e. ob-

served for the DAC output in setup 1 would decrease the size of the artifacts compared to the

signal of interest such that its influence eventually becomes negligible. Until such devices are

available, careful analysis procedures have to be carried out, to ensure trustworthy results from

concurrent AM-tACS-M/EEG studies. With the current study an analysis framework is provided

that enables researchers to check their AM-tACS setups for non-linearities and spurious low-

frequency artifacts and may help to disentangle actual effects of the stimulation on the brain

from artifacts introduced by the stimulation.

5   Conflict of interest

CH has filed a patent application on brain stimulation and received honoraria as editor from

Elsevier Publishers, Amsterdam. FF is the founder, chief scientific officer, and majority owner

of Pulvinar Neuro LLC. FK and EN declare no competing interests.

6   Author contributions

FK, EN, FF and CSH, conceived the study. FK collected and analyzed the data. All authors wrote the manuscript.

7   Acknowledgements

This research was supported by the Neuroimaging Unit of the Carl von Ossietzky University Oldenburg funded by grants from the German Research Foundation (3T MRI INST 184/152-1 FUGG and MEG INST 184/148-1 FUGG). Christoph S. Herrmann was supported by a grant of the German Research Foundation (DFG, SPP, 1665 3353/8-2). This work was supported in part by the National Institute of Mental Health of the National Institutes of Health under award numbers R01MH111889 and R01MH101547 (PI: Flavio Frohlich). The content is solely the responsibility of the authors and does not necessarily represent the official views of the National Institutes of Health.

8   References

Ali, M.M., Sellers, K.K., Frohlich, F., 2013. Transcranial Alternating Current Stimulation Modulates Large-Scale Cortical Network Activity by Network Resonance. J. Neurosci. 33, 11262–11275. doi:10.1523/JNEUROSCI.5867-12.2013

Bergmann, T.O., Karabanov, A., Hartwigsen, G., Thielscher, A., Siebner, H.R., 2016. Combining non-invasive transcranial brain stimulation with neuroimaging and electrophysiology: Current approaches and future perspectives. Neuroimage 140, 4–19. doi:10.1016/j.neuroimage.2016.02.012

Brittain, J.-S., Probert-Smith, P., Aziz, T.Z., Brown, P., 2013. Tremor Suppression by Rhythmic Transcranial Current Stimulation. Curr. Biol. 23, 436–440. doi:10.1016/j.cub.2013.01.068

Cabral-Calderin, Y., Williams, K.A., Opitz, A., Dechent, P., Wilke, M., 2016. Transcranial alternating current stimulation modulates spontaneous low frequency fluctuations as measured with fMRI. Neuroimage 141, 88–107. doi:10.1016/j.neuroimage.2016.07.005

Chander, B.S., Witkowski, M., Braun, C., Robinson, S.E., Born, J., Cohen, L.G., Birbaumer,

N., Soekadar, S.R., 2016. tACS Phase Locking of Frontal Midline Theta Oscillations

Disrupts Working Memory Performance. Front. Cell. Neurosci. 10, 1–10.

doi:10.3389/fncel.2016.00120

Cooper, R., Osselton, J. W., & Shaw, J.C., 1974. Recording Systems, in: EEG Technology.

Butterworths & Co. LTD, London, pp. 47–79. doi:10.1016/B978-0-407-16001-9.50001-8

Dowsett, J., Herrmann, C.S., 2016. Transcranial Alternating Current Stimulation with Sawtooth

Waves: Simultaneous Stimulation and EEG Recording. Front. Hum. Neurosci. 10, 1–10.

doi:10.3389/fnhum.2016.00135

Fröhlich, F., 2015. Experiments and models of cortical oscillations as a target for noninvasive

brain   stimulation,   in: Progress   in   Brain   Research.   pp.   41–73.

doi:10.1016/bs.pbr.2015.07.025

Fröhlich, F., McCormick, D.A., 2010. Endogenous Electric Fields May Guide Neocortical

Network Activity. Neuron 67, 129–143. doi:10.1016/j.neuron.2010.06.005

Grossman, N., Bono, D., Dedic, N., Kodandaramaiah, S.B., Rudenko, A., Suk, H.-J., Cassara,

A.M., Neufeld, E., Kuster, N., Tsai, L.-H., Pascual-Leone, A., Boyden, E.S., 2017.

Noninvasive Deep Brain Stimulation via Temporally Interfering Electric Fields. Cell 169,

1029–1041.e16. doi:10.1016/j.cell.2017.05.024

Helfrich, R.F., Schneider, T.R., Rach, S., Trautmann-Lengsfeld, S.A., Engel, A.K., Herrmann,

C.S., 2014. Entrainment of Brain Oscillations by Transcranial Alternating Current

Stimulation. Curr. Biol. 24, 333–339. doi:10.1016/j.cub.2013.12.041

Herrmann, C.S., Demiralp, T., 2005. Human EEG gamma oscillations in neuropsychiatric

disorders. Clin. Neurophysiol. 116, 2719–33. doi:10.1016/j.clinph.2005.07.007

Herrmann, C.S., Rach, S., Neuling, T., Strüber, D., 2013. Transcranial alternating current

stimulation: a review of the underlying mechanisms and modulation of cognitive

processes. Front. Hum. Neurosci. 7, 1–13. doi:10.3389/fnhum.2013.00279

Herrmann, C.S., Strüber, D., Helfrich, R.F., Engel, A.K., 2016. EEG oscillations: From
correlation   to   causality.   Int.   J.   Psychophysiol.   103,   12–21.
doi:10.1016/j.ijpsycho.2015.02.003

Kar, K., Duijnhouwer, J., Krekelberg, B., 2017. Transcranial Alternating Current Stimulation
Attenuates   Neuronal   Adaptation.   J.   Neurosci.   37,   2325–2335.
doi:10.1523/JNEUROSCI.2266-16.2016

Kar, K., Krekelberg, B., 2014. Transcranial Alternating Current Stimulation Attenuates Visual
Motion Adaptation. J. Neurosci. 34, 7334–7340. doi:10.1523/JNEUROSCI.5248-13.2014

Kasten, F.H., Dowsett, J., Herrmann, C.S., 2016. Sustained Aftereffect of α-tACS Lasts Up to
70 min after Stimulation. Front. Hum. Neurosci. 10, 1–9. doi:10.3389/fnhum.2016.00245

Kasten, F.H., Herrmann, C.S., 2017. Transcranial Alternating Current Stimulation (tACS)
Enhances Mental Rotation Performance during and after Stimulation. Front. Hum.
Neurosci. 11, 1–16. doi:10.3389/fnhum.2017.00002

Lustenberger, C., Boyle, M.R., Foulser, A.A., Mellin, J.M., Fröhlich, F., 2015. Functional role
of   frontal   alpha   oscillations   in   creativity.   Cortex   67,   74–82.
doi:10.1016/j.cortex.2015.03.012

Maas, Stephen, A., 2003. Nonlinear Microwave and RF Circuits, 2nd ed. Artec House, Boston.

Minami, S., Amano, K., 2017. Illusory Jitter Perceived at the Frequency of Alpha Oscillations.
Curr. Biol. 27, 2344–2351.e4. doi:10.1016/j.cub.2017.06.033

Neuling, T., Rach, S., Herrmann, C.S., 2013. Orchestrating neuronal networks: sustained after-
effects of transcranial alternating current stimulation depend upon brain states. Front.
Hum. Neurosci. 7, 161. doi:10.3389/fnhum.2013.00161

Neuling, T., Rach, S., Wagner, S., Wolters, C.H., Herrmann, C.S., 2012. Good vibrations:
Oscillatory   phase   shapes   perception.   Neuroimage   63,   771–778.
doi:10.1016/j.neuroimage.2012.07.024

Neuling, T., Ruhnau, P., Fuscà, M., Demarchi, G., Herrmann, C.S., Weisz, N., 2015. Friends,

not foes: Magnetoencephalography as a tool to uncover brain dynamics during

transcranial alternating current stimulation. Neuroimage 118, 406–413.

doi:10.1016/j.neuroimage.2015.06.026

Neuling, T., Ruhnau, P., Weisz, N., Herrmann, C.S., Demarchi, G., 2017. Faith and oscillations

recovered: On analyzing EEG/MEG signals during tACS. Neuroimage 147, 960–963.

doi:10.1016/j.neuroimage.2016.11.022

Noury, N., Hipp, J.F., Siegel, M., 2016. Physiological processes non-linearly affect

electrophysiological recordings during transcranial electric stimulation. Neuroimage 140,

99–109. doi:10.1016/j.neuroimage.2016.03.065

Noury, N., Siegel, M., 2017. Phase properties of transcranial electrical stimulation artifacts in

electrophysiological   recordings.   Neuroimage   158,   406–416.

doi:10.1016/j.neuroimage.2017.07.010

Oostenveld, R., Fries, P., Maris, E., Schoffelen, J.M., 2011. FieldTrip: Open source software

for advanced analysis of MEG, EEG, and invasive electrophysiological data. Comput.

Intell. Neurosci. 2011, 1–9. doi:10.1155/2011/156869

Ozen, S., Sirota, A., Belluscio, M.A., Anastassiou, C.A., Stark, E., Koch, C., Buzsaki, G., 2010.

Transcranial Electric Stimulation Entrains Cortical Neuronal Populations in Rats. J.

Neurosci. 30, 11476–11485. doi:10.1523/JNEUROSCI.5252-09.2010

Reato, D., Rahman, A., Bikson, M., Parra, L.C., 2010. Low-Intensity Electrical Stimulation

Affects Network Dynamics by Modulating Population Rate and Spike Timing. J. Neurosci.

30, 15067–15079. doi:10.1523/JNEUROSCI.2059-10.2010

Ruhnau, P., Neuling, T., Fuscá, M., Herrmann, C.S., Demarchi, G., Weisz, N., 2016. Eyes wide

shut: Transcranial alternating current stimulation drives alpha rhythm in a state dependent

manner. Sci. Rep. 6, 27138. doi:10.1038/srep27138

Taulu, S., Simola, J., Kajola, M., 2005. Applications of the signal space separation method.

IEEE Trans. Signal Process. 53, 3359–3372. doi:10.1109/TSP.2005.853302

Uhlhaas, P.J., Singer, W., 2012. Neuronal Dynamics and Neuropsychiatric Disorders: Toward

a Translational Paradigm for Dysfunctional Large-Scale Networks. Neuron 75, 963–980.

doi:10.1016/j.neuron.2012.09.004

Uhlhaas, P.J., Singer, W., 2006. Neural Synchrony in Brain Disorders: Relevance for Cognitive

Dysfunctions   and   Pathophysiology.   Neuron   52,   155–168.

doi:10.1016/j.neuron.2006.09.020

Vargha, B., Schoukens, J., Rolain, Y., 2001. Static nonlinearity testing of digital-to-analog

converters. IEEE Trans. Instrum. Meas. 50, 1283–1288. doi:10.1109/19.963198

Veniero, D., Vossen, A., Gross, J., Thut, G., 2015. Lasting EEG/MEG Aftereffects of Rhythmic

Transcranial Brain Stimulation: Level of Control Over Oscillatory Network Activity. Front.

Cell. Neurosci. 9, 477. doi:10.3389/fncel.2015.00477

Violante, I.R., Li, L.M., Carmichael, D.W., Lorenz, R., Leech, R., Hampshire, A., Rothwell, J.C.,

Sharp, D.J., 2017. Externally induced frontoparietal synchronization modulates network

dynamics and enhances working memory performance. Elife 6. doi:10.7554/eLife.22001

Voss, U., Holzmann, R., Hobson, A., Paulus, W., Koppehele-Gossel, J., Klimke, A., Nitsche,

M. a, 2014. Induction of self awareness in dreams through frontal low current stimulation

of gamma activity. Nat. Neurosci. 17, 810–812. doi:10.1038/nn.3719

Vossen, A., Gross, J., Thut, G., 2015. Alpha Power Increase After Transcranial Alternating

Current Stimulation at Alpha Frequency (α-tACS) Reflects Plastic Changes Rather Than

Entrainment. Brain Stimul. 8, 499–508. doi:10.1016/j.brs.2014.12.004

Vosskuhl, J., Huster, R.J., Herrmann, C.S., 2016. BOLD signal effects of transcranial

alternating current stimulation (tACS) in the alpha range: A concurrent tACS–fMRI study.

Neuroimage 140, 118–125. doi:10.1016/j.neuroimage.2015.10.003

Witkowski, M., Garcia-Cossio, E., Chander, B.S., Braun, C., Birbaumer, N., Robinson, S.E.,

Soekadar, S.R., 2016. Mapping entrained brain oscillations during transcranial alternating

current   stimulation   (tACS).   Neuroimage   140,   89–98.

doi:10.1016/j.neuroimage.2015.10.024

Zaehle, T., Rach, S., Herrmann, C.S., 2010. Transcranial Alternating Current Stimulation

Enhances Individual Alpha Activity in Human EEG. PLoS One 5, 13766.

doi:10.1371/journal.pone.0013766

9   Tables

Table 1: Transfer function coefficients tested for deviation from zero. Coefficients of the 10

polynomial functions fitted for each setups TF recordings were tested against zero using stu-

dent's t-test (two-sided, bonferroni corrected). Mean and standard deviation are shown for

each coefficient.

	Mean	Std.	df	T	p
DAC					
β_0	-1.05e-05	4.80e-06	9	-6.92	< .001*
β_1	0.9988	1.86e-05	9	> 100	< .001*
β_2	-3.28e-06	7.02e-07	9	-14.79	< .001*
β_3	-3.75e-07	7.16e-08	9	-16.56	< .001*
β_4	9.99e-08	2.31e-08	9	13.69	< .001*
β_5	3.73e-09	5.77e-10	9	20.41	< .001*
β_6	-6.32e-10	1.72e-10	9	-11.63	< .001*
DAC + Stimulator					
β_0	0.0042	0.0009	9	15.37	< .001*
β_1	10.8640	0.0123	9	> 100	< .001*
β_2	-0.0686	0.0153	9	-14.14	< .001*
β_3	-0.0904	0.0324	9	-8.83	< .001*
β_4	0.1838	0.0606	9	9.54	< .001*
β_5	0.0809	0.0484	9	5.28	< .001*
β_6	-0.1702	0.0712	9	-7.56	< .001*
EEG					
β_0	-0.0001	0.0001	9	-5.27	< .001*
β_1	0.1736	0.0007	9	> 100	< .001*
β_2	0.0024	0.0017	9	4.44	.002*
β_3	-0.0006	0.0024	9	-0.81	.44
β_4	0.0035	0.0069	9	1.64	.14

β_5	-0.0058	0.0035	9	-5.30	< .001*
β_6	-0.0118	0.0078	9	-4.80	.001*
MEG					
β_0	-0.0009	0.0002	9	-16.35	< .001*
β_1	11.3235	0.0576	9	> 100	< .001*
β_2	0.0267	0.0121	9	6.97	< .001*
β_3	0.3033	0.0393	9	24.41	< .001*
β_4	-0.5931	0.1532	9	-12.24	< .001*
β_5	-1.1228	0.2065	9	-17.19	< .001*
β_6	2.1034	0.5192	9	12.81	< .001*

Highlights

499 • Amplitude modulated tACS generates spurious artifacts at its modulation frequency

500 • The input-output transfer functions of different AM-tACS setups was estimated

501 • Hardwares non-linear transfer characteristics account for these spurious artifacts

502 • An analysis approach to characterize non-linearities of tACS setups is provided.

Supplementary Materials: Non-linear transfer characteristics of stimulation and recording hardware account for spurious low-frequency artifacts during amplitude modulated transcranial alternating current stimulation (AM-tACS)

Supplementary Figure S1: Full range version of Figure 2. TFs (**top**) show recorded probe stimulus amplitudes in relation to their input amplitudes (V_{out}/V_{in}; black dots), as well as the course of the TF model (red line). The corresponding function is displayed in the title. Spectra show average power at each frequency in the different AM-recordings (black line). Thin colored lines show power spectra for each of the 60 repetitions. Red line shows the spectrum predicted by evaluating the digital AM-signal by the estimated TF of the setup. Grey areas indicate frequencies significantly differing in power compared to the two neighboring frequencies ($p < .05$, bonferroni corrected). Please note the different scaling of the power spectra.

Supplementary Figure S2: Full range version of Figure 3. TFs (**top**) show recorded probe

stimulus amplitudes in relation to their input amplitudes (V_{out}/V_{in}; black dots), as well as the

course of the TF model (red line). The corresponding function is displayed in the title. Spectra

show average power at each frequency in the different AM-recordings (black line). Thin colored

lines show power spectra for each of the 60 repetitions. Red line shows the spectrum predicted

by evaluating the digital AM-signal by the estimated TF of the setup. Grey areas indicate fre-

quencies significantly differing in power compared to the two neighboring frequencies ($p < .05$,

bonferroni corrected). Please note the different scaling of the power spectra.

Supplementary Figure S3: Simulation of artifacts resulting from temporal interference (TI). Frequency spectra showing the effect of non-linear TF terms on amplitude modulated signals created by TI. Similar to the am-signals, the TI signals contain no low-frequency artifact when a solely linear TF is applied (**top left**). Adding non-linear terms to the TF model results in additional side-bands around the frequencies of the two applied sine wave signals for odd-valued exponents (**left column**) and in low-frequency artifacts at $\varDelta f$ (corresponding to the modulation frequency of the am-signal generated by the TI signals) and its harmonics for even valued exponents of the TF model (**right column**).