Explicit Neural Models for Flip-Flops and Oscillators Generate Phenomena of Short-Term Memory and Electroencephalography

Lane Yoder

Department of Science and Mathematics, retired

University of Hawaii, Kapiolani

Honolulu, Hawaii

LYoder@hawaii.edu

Abstract

For certain brain functions, the networks presented here almost certainly show how

neurons are actually connected. Stripped of details such as redundancies and other error-

correcting mechanisms, the basic organization of synaptic connections within the brain's building

blocks is likely to be less complex than it appears. For some brain functions, the network

architectures can even be quite simple.

Flip-flops are the basic building blocks of sequential logic systems. Certain flip-flops can

be configured to function as oscillators. The novel flip-flops and oscillators proposed here are

composed of two to six neurons, and their operation depends only on the minimal neuron

capabilities of excitation and inhibition. These networks generate neural correlates of so many

major phenomena of short-term memory and electroencephalography in such detail that the

possibility of the brain producing the phenomena with fundamentally different network

architectures is remote.

For example, cascaded oscillators can produce the periodic activity commonly known as

brainwaves by enabling the state changes of many networks simultaneously. (The function of

such oscillator-induced synchronization in information processing systems is timing error

avoidance.) Then the boundary separating the alpha and beta frequency bands is

$125/\{\mu_d + \sqrt{[(\mu_d)^2 + (\sigma_d)^2 \ln(4)]}\}$ hertz,

where μ_d and σ_d are the mean and standard deviation (in milliseconds) of delay times of neurons

that make up the initial ring oscillators in the cascades. With 4 and 1.5 ms being the best estimates

for μ_d and σ_d respectively, this predicted boundary value is 14.9 Hz, which is within the range of

commonly cited estimates of the boundary obtained empirically from electroencephalograms. The

delay parameters μ_d and σ_d also make predictions of the peaks and other boundaries of the five

major frequency bands that agree well with empirically estimated values.

The networks also make testable predictions of several unknown phenomena.

1. Introduction

The novel networks presented here are explicit and dynamic. They generate neural correlates of brain phenomena, and they demonstrate selective advantages for those phenomena. The last property includes phenomena whose functions are uncertain, such as the matched periods of neural activity found in electroencephalograms (EEGs). These four properties are necessary for a model to show how neurons might actually be connected to process information in the "real time" of most brain functions (a few milliseconds). The dual purpose of this article is to demonstrate that it is possible to design models with the properties and to call attention to the dearth of such models in the literature. Such models are needed to make progress in discovering how synaptic connections are organized.

This article is the fourth in a series of articles that show how neurons can be connected to process information. The networks generate neural correlates of brain phenomena that had been known but unexplained for decades. The first three articles [1-3] explored the analog properties of neuron signals in combinational logic operations, whose outputs depend only on the current state of the inputs. A fuzzy logic decoder was shown to generate neural correlates of the major phenomena of both color vision and olfaction, including the brain's shortcomings. The decoder's design is based on logic gates but the connectivity of components is radically different from a standard electronic digital (Boolean logic) decoder [2, 4, 5]. If implemented with electronic components and given digital inputs, the decoder performs the same function as the standard digital design more efficiently.

The present article considers the Boolean logic properties of neuron signals in sequential logic operations, whose outputs are functions of both the current inputs and the past sequence of inputs. Flip-flops are the basic building blocks of sequential logic systems. A few simple models for neural flip-flops (NFFs) and oscillators are presented here. They are similar in design to well-known electronic logic circuits that perform the same functions. These networks produce detailed

phenomena of short-term memory and EEGs, and they imply an exact relationship between the

distributions of neuron delay times and EEG frequencies.

Recognizing a neuron's logic capability can make a useful connection between

neuroscience and the field of logic circuit design in electronic computational systems. As shown

here and in the previous articles, the two disciplines can inform each other on how certain simple

functions can be performed. For higher level functions, such as pattern recognition and playing

chess, the methods of the brain and artificial intelligence are currently vastly different. However,

complex systems can consist of simple building blocks. With the recognition that the two systems

are likely to have similar logical design and essentially the same building blocks, neuroscience and

computer science may inform each other from the ground up.

2. Unexplained phenomena and previous models

There is no consensus on a single neuron's basic logic capabilities or on the brain's

organization of synaptic connections. Consequently, many brain phenomena lack explicit

explanations.

2.1. Single neuron logic capability

McCulloch and Pitts' seminal paper [6] proposed that the brain is made up of logic gates.

"The computational framework of McCulloch and Pitts had a tremendous impact on the

development of artificial neural networks … and machine learning theory … . Nevertheless, it is

fair to conclude that the concept of simplified Boolean neurons had a limited impact on

neuroscience … ." [7]. More than 70 years later, the brain's computational capabilities are still

unclear [8]. In that time span, many theoretical models have been proposed for neuron responses

as mathematical or logic functions, but the modern view of these models follows "the adage that

all models are wrong, but some are useful" [9].

The neuron response models that are useful in artificial intelligence are assumed to have

sophisticated mathematical capabilities. This makes it possible to simulate the models on a

computer with impressive results. However, there is little or no evidence that actual neurons can

carry out the particular mathematical functions assumed for the models.

A prominent example of a neuron response model assumes a neuron has modifiable

weights that are applied to signals at its synapses. The neuron then adds these weighted inputs in a

nonlinear way to produce a useful output. Apparently there is virtually no evidence that neurons

function in this way. Moreover, models that assume synaptic strengths or weights are modified

over time with repeated inputs are not dynamic and therefore cannot model fast functions such as

short-term memory.

Perhaps more importantly, sophisticated neuron capabilities are unnecessary for the

requirements of information processing. The model used here shows that neurons with one

inhibitory input that can suppress one excitatory input are sufficient for all information processing.

Apparently there is no other claim in the literature that a single neuron can function as a specific

logic primitive based on minimal neuron capabilities.

2.2. Short-term memory

Memory tests have shown that certain neurons fire continuously while information is held

in short-term memory. This activity was found in neurons in the visual, auditory, and

sensorimotor cortexes of monkeys while corresponding sensory information is held in memory

[10, 11]. Similar activity has been found more recently in humans [12].

In the experiments, seven characteristics of neural activity were associated with memory

formation, retention, retrieval, termination, and errors: 1) Before the stimulus was presented, the

sampled neuron discharged at a low, baseline level. 2) When the stimulus was presented, or

shortly after, the neuron began to fire at a high frequency. 3) The high frequency firing continued

after the stimulus was removed. 4) The response was still high when the memory was

demonstrated to be correct. 5) The response returned to the background level shortly after the test.

6) In the trials where the subject failed the memory test, the high level firing had stopped or 7) had

never begun.

Several models have been proposed for memory mechanisms composed of neurons, but

apparently none is explicit and dynamic, and none produces the seven phenomena described

above. The memory bank presented here produces all of the phenomena.

2.3. Electroencephalograms

Electroencephalograms show widespread rhythms that consist of many neurons firing with

matched periods. The spectrum of frequencies has been partitioned into bands according to the

behavioral and mental state associated with the frequencies in each band. Five EEG frequency

bands are considered here: gamma, beta, alpha, theta, and delta. Some researchers have found

more bands or divided the bands into sub-bands depending on the focus of their research, but these

five are discussed most often in the literature. Within each of these bands the distribution of

frequencies is unimodal [13-16]. The ratios of consecutive band boundaries [17] and the ratios of

consecutive band peak frequencies [13-16] are approximately 2, with the gamma band peaking at

about 40 Hz [13-16]. Several estimated frequencies have been found for each boundary between

bands.

The EEG phenomena raise several questions. What causes a neuron to fire with a regular

period for many seconds? What is the function of such long-term, periodic firing? What produces

and what is the function of the synchronization of widespread periodic firing? What produces and

what is the function of the wide distribution of EEG frequencies in bands? What produces the

unimodal distribution in each band and the octave relationships between the bands' peaks and

boundaries? What determines the specific frequencies of the peaks and boundaries? Why do

gamma oscillations peak at only 40 Hz, while neurons are capable of producing action potentials

considerably faster? Why is there little agreement on the boundaries separating the bands?

Answers to a few of these questions have been proposed, but there has been no explicit

model that can explain more than one or two phenomena. Most models are based on "black box"

networks or broad assumptions of neuron capabilities. Below are two prominent examples of

proposed oscillator models.

Pacemaker cells are natural oscillators that cause involuntary muscles and other tissues to

contract or dilate. They are spontaneously active neurons with a specialized cell membrane that

allows sodium and potassium to cross and generate regular, slow action potentials (around 100

spikes per minute) [18, 19]. Modulating input controls the spike frequency. Except for generating

periodic signals, pacemaker cells do not offer answers to any of the questions above. It is not

clear, for example, how pacemaker cells could generate the wide distribution of EEG frequencies,

their unimodal distribution in bands, or the octave relationships of the bands.

The Kuramoto model [20, 21] provides a widely accepted explanation of synchronized

firing found in EEGs. The model assumes, without supporting evidence and without an

explanation of a mechanism or function for any of these behaviors, that the neurons' signals

oscillate naturally, that these oscillations are nearly identical, and that each neuron is linked to all

the others. The model does not appear to answer any of the above questions besides how

synchronization occurs. The Kuramoto model is a macro explanation of a macro phenomenon.

The EEG data are quite distant from the micro explanation given here based on neuron delay

times.

The cascaded oscillators model proposed here can produce the synchronized firing found

in EEGs by enabling neural structures' state changes simultaneously. It will be shown that the

model provides answers to all of the questions above. In addition, the distribution of EEG

frequencies in each band is entirely determined by just two parameters: the mean and variance of

the initial oscillators' neuron delay times. This distribution includes the specific frequencies that

separate the EEG bands and the peak frequency within each band.

3. Methods and testable predictions

3.1. Neuron logic

Previously it was shown that a single neuron with one excitatory input and one inhibitory

input, with signal strengths X and Y respectively, can function as a logic primitive, X AND NOT

Y [2]. In simplest terms, this is because the neuron is active when it has excitatory input *and* does

not have inhibitory input. It was also shown that an AND-NOT gate can be configured to function

as an inverter (i.e., a NOT X logic primitive). The AND-NOT gate together with a NOT gate

make up a functionally complete set, meaning any logic function can be performed by a network

of such logic gates. In other words, sufficiently many neurons operating as AND-NOT gates can

perform all of the brain's processing of information. The neuron AND-NOT capability will be

reviewed here.

3.2. Networks

The networks presented here do not build on previous neural models, including those in [1-

3]. The networks are modifications of standard electronic logic circuits. The AND-NOT gate is

virtually never used as a building block in electronic computational systems, but it will be shown

here how a few AND-NOT gates can be connected to perform the same functions as two standard

electronic flip-flops, the Set-Reset (SR) and JK. A flip-flop is a mechanism that can be set

repeatedly to either one of two stable states, commonly labeled 0 and 1. A flip-flop can be used as

a memory mechanism to store one bit of information.

The rest of this article's network designs are straightforward engineering: A flip-flop can

function as a switch that enables other flip-flops. Certain flip-flops can be configured to function

as toggles. (A toggle is a flip-flop with one input that inverts the memory state.) An odd number

of inverters connected in a circular sequence forms a ring oscillator. An oscillator connected in

sequence with several toggles forms a cascade of oscillators with different frequencies. An

oscillator can synchronize state changes in other networks by enabling them simultaneously.

Two network designs presented here may be new to engineering: a flip-flop functioning as

a switch for a memory bank, and cascaded oscillators composed of JK toggles rather than the less

efficient master-slave toggles.

3.3. Testable predictions

This article ends with several testable predictions that are implied by the models, briefly

outlined here.

As noted above, one of an NFF's two outputs produces all seven characteristics of neuron

activity while information is held in short-term memory. NFFs predict eight additional

phenomena for the pair of outputs. These predictions can be tested by the same methods that led

to the discovery of the first seven phenomena. The two NFF output neurons are predicted to have

1) close proximity, 2) reciprocal, 3) inhibitory inputs, 4) complementary outputs, and 5) noise-

reducing responses to the inputs. When the memory state is changed, 6) the neuron with high

output changes first with 7) the other changing a few milliseconds later. 8) After the memory test,

the outputs of both neurons are low.

The hypothesis that cascaded oscillators produce EEG frequencies can be rigorously tested

by its implication that the oscillators and EEG frequency bands have exactly the same

distributions of frequencies. The oscillators' frequencies means and variances are given as

explicit, exact functions of the mean and variance of neuron delay times. The means and

variances of neuron delay times and EEG band frequencies can be estimated from random

samples. Using standard tests for equal means and variances, the EEG sample statistics can be

compared to the EEG parameters predicted by the delay time statistics.

Any of the proposed networks can be constructed with actual neurons and tested for

specific predicted behaviors.

4. Analysis

4.1. Figure symbols

For several reasons, the neural networks in the figures are illustrated with standard

(ANSI/IEEE) logic symbols rather than symbols commonly used in neuroscience schematic

diagrams. A comparison is shown in Fig 1.

Fig 1. Network symbols. A. A logic circuit illustrated with standard logic symbols. Each of the

six components represents a logic function that can be implemented with electronic hardware or

with a single neuron. **B.** The same logic circuit illustrated with symbols commonly used in

neuroscience schematic diagrams.

The symbols in Fig 1A can be interpreted in two ways. As a logic symbol, the rectangle

with one rounded side represents the AND logic function, and a circle represents negation. So the

networks in the figures can be constructed with ordinary electronic components or simulated with

electronic circuit software. Second, it will be shown that the logic gate represented by an AND

symbol and a circle can be implemented by a single neuron, with a circle representing inhibitory

input and no circle representing excitatory input. As illustrated in Fig 1B, inhibition is often

represented by a small closed circle and excitation by a closed triangle, but there does not seem to

be an accepted standard of symbols for networks of neurons.

The circles in Fig 1A are a small exception to standard symbols. A circle representing

negation normally comes after a logic gate. Standard notation would include a triangle before the

circles in the figures to represent a buffer gate, whose output equals the single input. The triangle

is omitted here to emphasize that the AND gate with a circle is considered a single logic gate or a

single neuron.

The standard logic symbols normally represent Boolean logic, which for most electronic

computational systems means digital signal processing. Neurons can convey analog signals, either

with signals of graded strength or with the strength of signals consisting of spikes measured by

spike frequency. It will be shown that the neural networks in the figures can generate robust

digital signals, i.e., signals with only high and low strengths (except during transition from one

state to the other).

The similarities and differences between the novel diagrams of networks that can be

implemented with neurons, and diagrams of standard logic circuits for the same functions

implemented electronically, are easier to see if they are both illustrated with the same symbols.

The single, branching output channels in Fig 1A are more realistic depictions of most

axons than the multiple output channels of Fig 1B.

Finally, diagrams in standard engineering form clarify the connectivity, the logic function

of each component, the distinction between feedback (right to left) and feed-forward (left to right)

signals, and the overall direction of a network's signal processing from input to output (left to

right).

4.2. Neuron signals

All results for the networks presented here follow from the neuron response to binary (high and low) input signals, given in the next section, and the algebra of Boolean logic applied to the networks' connections. Although binary signals are common in modeling neuron response, it has apparently not been demonstrated that neural networks are capable of maintaining such outputs, after brief inputs that change the outputs, in the presence of additive noise. Analog signals (intermediate strengths between high and low) are considered here only to show how the networks in the figures can generate robust binary signals in the presence of moderate levels of additive noise.

4.2.1. Binary neuron signals

Neuron signal strength, or intensity, is normalized here by dividing it by the maximum possible intensity for the given level of adaptation. This puts intensities in the interval from 0 to 1, with 0 meaning no signal and 1 meaning the maximum intensity. The normalized number is called the *response intensity* or simply the *response* of the neuron. Normalization is only for convenience. Non-normalized signal strengths, with the highest and lowest values labeled Max & Min rather than 1 and 0, would do as well.

If 1 and 0 stand for the truth values TRUE and FALSE, respectively, neurons can process information contained in neural signals by functioning as logic operators. The responses 1 and 0 are also referred to collectively as binary signals and separately as high and low signals.

As noted above, the strength of a signal consisting of action potentials, or spikes, can be measured by spike frequency. A high signal consists of a burst of spikes at the maximum spiking rate. For a signal that oscillates between high and low, the frequency of the oscillation is the frequency of bursts, not the frequency of spikes.

271   For binary signals, the response of a neuron with one excitatory and one inhibitory input is

272 assumed to be as shown in Table 1. Of the 16 possible binary functions of two variables, this table

273 represents the only one that is consistent with the customary meanings of "excitation" and

274 "inhibition." Table 1 is also a logic truth table, with the last column representing the truth values

275 of the statement X AND NOT Y.

Excitatory X	Inhibitory Y	Response
0	0	0
0	1	0
1	0	1
1	1	0

Table 1. Neuron response to binary inputs.

The networks presented here require a continuously high input. In the figures, this input is

represented by the logic value "TRUE." If the figure represents an electronic logic circuit, the

high input is normally provided by the power supply. If the figure represents a neural network, the

high input can be achieved by neurons in at least four ways. 1) A continuously high signal could

be provided by a neuron that has excitatory inputs from many neurons that fire independently [22].

2) Neurons that are active spontaneously and continuously without excitatory input are known to

exist [23, 24]. A network neuron that requires a high excitatory input could receive it from a

spontaneously active neuron, or 3) the neuron itself could be spontaneously active. 4) It will be

seen that the high input could be provided by one of a flip-flop's outputs that is continuously high.

4.2.2. Additive noise in binary neuron signals

This section covers a potential problem for neural processing of digital (Boolean)

information: Additive noise in binary inputs may affect the intended binary outputs of Table 1.

Evidence indicates that some neurons have noise-reducing capabilities. Noise can be sufficiently

reduced by neurons that have two simple properties that generalize the noise-reducing properties

of sigmoid functions. These properties do not indicate capabilities of sophisticated mathematics.

4.2.2.1. Noise reduction

Two lines of evidence indicate that some neurons have at least a minimal capability of

reducing moderate levels of additive noise in binary inputs. Perhaps the best evidence of neuron

noise-reducing capability is the high rate of firing known to be associated with short-term memory

[10-12]. Without some noise-reducing capability, no network would be able to maintain an output

that can be either high or low. The cumulative effect of additive noise would quickly attenuate the

output.

Second, some neurons are known to have sigmoid responses to single inputs, including

inhibitory inputs [25-27]. A sigmoid response reduces moderate levels of additive noise in a

binary input signal by producing an output that decreases an input near 0 and increases an input

near 1. The next section demonstrates that a sigmoid response to both excitatory and inhibitory

inputs is sufficient for the noise-reducing requirements of the NFFs presented here, but such a

response is not necessary. A simpler property is sufficient.

Noise reduction in a response to both noisy excitatory and inhibitory inputs can be

achieved by a function of two variables that generalizes a sigmoid function's features. The noise

reduction need only be slight for the proposed NFFs because they have feedback loops that

continuously reduce the effect of noise.

Let F(X, Y) represent a neuron's response to an excitatory input X and an inhibitory input

Y. The function must be bounded by 0 and 1, the minimum and maximum possible neuron

responses, and satisfy the values in Table 1 for binary inputs. For other points (X, Y) in the unit

square, suppose F satisfies:

1. F(X, Y) > X - Y for inputs (X, Y) near (1, 0) and

2. F(X, Y) < X - Y or F(X, Y) = 0 for inputs (X, Y) near the other three vertices of the unit

square.

The neuron responses of Table 1 are max{0, X-Y} (the greater of 0 and X-Y). For binary

inputs with moderate levels of additive noise that makes them non-binary, conditions 1 and 2

make the output either equal to, or closer to, the intended output of Table 1 than max{0, X-Y}.

Neurons that make up the networks proposed here are assumed to have these minimal noise-

reducing properties.

Conditions 1 and 2 are sufficient to suppress moderate levels of additive noise in binary

inputs and produce the results found here. The level of noise that can be tolerated by the NFFs

depends on the minimum distance from a vertex of the unit square to a point outside the region in

the unit square where condition 1 or 2 holds. Simulations demonstrate that the networks produce

certain phenomena, but these results can also be proven directly, although quite tediously, from

the explicit network connections and conditions 1 and 2.

4.2.2.2. Example of a neuron response that satisfies conditions 1 and 2

For any sigmoid function f from f(0) = 0 to f(1) = 1, the following function has the noise-

reducing properties 1 and 2 and also satisfies Table 1:

F(X, Y) = f(X) - f(Y), bounded below by 0.

This function is plausible as an approximation of a neuron response because it is sigmoid

in each variable and some neurons are known to have sigmoid responses to single inputs, as

mentioned above. The same sigmoid function applied to X and Y is not necessary to satisfy

conditions 1 and 2. The function F could be the difference of two different sigmoid functions.

The function is illustrated in Fig 2 for a specific sigmoid function. The sine function of

Fig 2A was chosen rather than any of the more common examples of sigmoid functions to

demonstrate that a highly nonlinear function is not necessary for robust maintenance of binary

signals. On half of the unit square, where $Y \geq X$, Fig 2B shows that F has the value 0. This

reflects the property that a large inhibitory input generally suppresses a smaller excitatory input.

Fig 2. Noise-reducing AND-NOT function. The graph shows an example of a neuron response

to analog inputs that reduces moderate levels of additive noise in binary inputs. **A.** A sigmoid

function $f(x) = (1/2)\sin(\pi(x - 1/2)) + 1/2$. **B.** Graph of a function that has the noise-reducing

properties 1 and 2. The function is $F(X, Y) = f(X) - f(Y)$, bounded by 0. Wireframe: Graph of the

response function $Z = F(X, Y)$. Green and red: A triangle in the plane $Z = X - Y$. Red:

Approximate intersection of the plane and the graph of F. Purple: Approximate region in the unit

square where $Z > X - Y$. Blue: Region in the unit square where $Z < X - Y$ or $Z = 0$.

The response function $F(X, Y)$ in Fig 2 is used for the network simulations as follows. The

whole number i represents i neuron delay times. The variables are initialized at time $i = 0$. At

time $i > 0$, the output Z_i of each neuron that has excitatory and inhibitory inputs X_{i-1} and Y_{i-1} at

time i-1 is:

3. $Z_i = F(X_{i-1}, Y_{i-1})$

$= \max\{0, [(1/2)\sin(\pi(X_{i-1} - 1/2)) + 1/2] - [(1/2)\sin(\pi(Y_{i-1} - 1/2)) + 1/2]\}.$

4.2.2.3. A primitive noise-reducing AND-NOT gate

Properties 1 and 2 do not indicate capabilities of sophisticated mathematics. An AND-NOT response with properties 1 and 2 can be produced by mechanisms that are quite simple. Fig 3 shows that a single transistor and three resistors can be configured to accomplish this. The network output was simulated in engineering software. The inputs X and Y vary from 0V to 5V in steps of 0.05V. A 5V signal commonly stands for logic value 1, and ground stands for logic value 0.

Fig 3. Single transistor AND-NOT gate that reduces noise. This minimal logic circuit satisfies the noise-reducing conditions 1 and 2. **A.** A logic circuit consisting of one transistor and three resistors. **B.** Engineering software simulation. Wireframe: Graph of the response Z as a function of the inputs X and Y. Green and red: A triangle in the plane Z = X - Y. Red: Intersection of the plane and the graph of the response function. Purple: Region in the unit square where Z > X - Y. Blue: Region in the unit square where Z < X - Y or Z = 0.

4.3. Neural logic gates and flip-flops

Fig 4 shows two logic primitives and several flip-flops. All are composed of the first type of logic primitive in Fig 4A, which can be implemented with a single neuron.

Fig 4. Neural logic gates and flip-flops. A. A symbol for an AND-NOT logic gate, with output X AND NOT Y. The symbol can also represent a neuron with one excitatory input and one inhibitory input. **B.** An AND-NOT gate configured as a NOT gate, or inverter. **C.** Active low Set-Reset (SR) flip-flop. **D.** Active high SR flip-flop. **E.** Flip-flop enabled by input from an oscillator. **F.** JK flip-flop or toggle. If S and R are high simultaneously, the flip-flop is inverted.

4.3.1. Neural logic gates

If X and Y are statements with truth values TRUE or FALSE, the statement "X AND NOT

Y" is TRUE if and only if X is TRUE and Y is FALSE. This logic primitive is illustrated in Fig

4A. The figure can also represent a neuron with one excitatory input and one inhibitory input,

whose response to binary inputs is X AND NOT Y by Table 1. The logic primitive NOT X is

TRUE if and only if X is FALSE. Fig 4B shows that an AND-NOT gate with a continuously high

input functions as a NOT gate.

The AND-NOT logic primitive has simplicity, efficiency, and power that have been

underappreciated. It is in the minority of logic primitives that are functionally complete.

Analogously to the single-neuron AND-NOT gate, the function can be implemented electronically

with a single transistor and one resistor [4]. Any mechanism that can activate and inhibit like

mechanisms and has access to a high activating input is a functionally complete AND-NOT gate.

It may not be coincidence that the components of disparate natural signaling systems have these

capabilities, e.g., immune system cells [28-31] and regulatory DNA [32, 33] in addition to

transistors and neurons. As noted earlier, AND-NOT gates with analog signals can make up a

powerful fuzzy logic decoder whose architecture is radically different from, and more efficient

than, standard electronic decoder architectures [2, 4, 5]. Implemented with neural AND-NOT

gates, these fuzzy decoders generate detailed neural correlates of the major phenomena of color

vision and olfaction [1, 2].

4.3.2. Neural flip-flops

The most common type of memory element used to store one bit of information in

electronic computational systems is a latch or flip-flop. The more formal name is bistable

multivibrator, meaning it has two stable states that can alternate repeatedly. A distinction is

sometimes made between a "flip-flop" and a "latch," with the latter term reserved for

asynchronous memory mechanisms that are not controlled by an oscillator. The more familiar

"flip-flop" will be used here for all cases.

A flip-flop stores a discrete bit of information in an output usually encoded as 0 or 1. This

output is labeled M in Fig 4. The value of M is the flip-flop *state* or *memory bit*. The information

is stored by means of a brief input signal that activates or inactivates the memory bit. Input S *sets*

the state to M = 1, and R *resets* it to M = 0. Continuous feedback maintains a stable state. A

change in the state *inverts* the state.

Two basic types of flip-flops are the Set-Reset and JK. Fig 4C shows an active low SR

flip-flop. The S and R inputs are normally high. A brief low input S sets the memory bit M to 1,

and a brief low input R resets it to 0. Adding inverters to the inputs produces the active high SR

flip-flop of Fig 4D. The S and R inputs are normally low. A brief high input S sets the memory

bit M to 1, and a brief high input R resets it to 0.

Fig 4E shows a flip-flop with an enabling input. The S and R inputs in Fig 4D have been

replaced by AND-NOT gates that allow the S or R input to be transmitted only when the enabling

input is low. In synchronized signaling systems, various logic circuits are enabled simultaneously

by an oscillator to avoid timing errors.

For the so-called JK flip-flop in Fig 4F, the enabling input in Fig 4E has been replaced by

input from the flip-flop outputs. A disadvantage of the SR flip-flop (active high Fig 4D) is that if

S and R are high simultaneously, the outputs are unpredictable. The advantage of the JK flip-flop

is that if S and R are both high simultaneously, the flip-flop state is inverted because the most

recent inverting input is inhibited by one of the outputs. This means the JK flip-flop can be

configured as a toggle by linking the Set and Reset inputs, as illustrated by the single input T in

the figure.

A problem with the JK toggle is that it functions correctly only for a short duration of high

input. If the duration is too long, the outputs will oscillate. This problem is handled in the

Oscillators section below.

4.3.3. Neural flip-flop simulation

The simulation in Fig 5 shows that the operation of the NFF in Fig 4D is robust in the presence of additive noise in the inputs. The simulation was done in a spreadsheet with the outputs of each neuron computed by equation 3. At time $i = 0$, the outputs are initialized at $M_0 = 0$ and $\overline{M}_0 = 1$. (If both are initialized at 0, they will oscillate until either S or R is high.) Low level additive noise and baseline activity in the inputs are simulated by a computer-generated random number between 0.01 and 0.1. The noise is offset by 0.01 so it does not obscure the high and low outputs in the graphs. The high Enabling input TRUE is simulated by 1 minus noise. Each of the two larger noise bursts in Set and Reset is simulated by the sum of two sine functions and the computer-generated noise. The higher Set and Reset signals that successfully invert the memory state are simulated by a sine function plus noise. The slow rise time of these inputs, over several neuron delay times, is exaggerated to make the robust operation of the network clear.

Fig 5. Simulation of an NFF operation with noise in the inputs. The simulation of the NFF in Fig 4D shows that the effect of baseline noise on the memory bit is negligible, and temporary bursts of larger noise have no lasting effect.

4.4. Neural memory bank

If information stored in short-term memory is no longer needed, active neurons consume

energy without serving any useful purpose. An energy-saving function can be achieved with

NFFs. Fig 6 shows a memory bank of three NFFs of Fig 4D, with a fourth serving as a switch to

turn the memory bank on and off. The memory elements are enabled by excitatory input from the

switch. A large memory bank could be organized as a tree, with switches at the branch points and

memory elements at the leaves, so that at any time only the necessary memory elements are

enabled.

Fig 6. Neural memory bank. Three NFFs (Fig 4D) enabled by a fourth NFF serving as an on-
off switch.

454   The enabling inputs of Fig 4E and Fig 6 have different functions. The enabling input in

455   Fig 4E enables only the inputs. By itself, it does not affect the outputs. It is normally used to

456   synchronize state changes in several networks with input from an oscillator. The enabling input

457   from the switch in Fig 6 enables the NFFs themselves. When the switch is off, energy is saved

458   and the information stored in the the flip-flops' output states is lost.

4.5. Neural oscillators

An oscillator produces periodic bursts of a high signal followed a quiescent period of a low

signal. It is the basic element of a timing mechanism. An odd number of three or more inverters

connected sequentially in a ring produces periodic bursts as each gate inverts the next one. All

inverters in the ring produce oscillations with the same frequency. Their phases are approximately

uniformly distributed over one cycle, and the high and low signal durations are approximately

equal. Their common period is twice the sum of the inverters' delay times. (The sum is doubled

because each component inverts twice per cycle.) A ring oscillator is the simplest type of

oscillator implemented with logic gates, and the simplest ring oscillator consists of three inverters.

As described in the introduction, an oscillator can be connected in sequence with toggles to

form a cascade of oscillators. Because two high inputs are required for each cycle of a toggle-as-

oscillator (one to set the memory state, another to reset it), a toggle produces a signal whose period

is exactly double that of the toggle's input.

The master-slave toggle is the customary choice for cascaded oscillators because of its

ability to invert no more than once regardless of the high input duration. The master-slave toggle

can be implemented with neurons by connecting two JK toggles in the standard way. However,

the problem of JK toggles inverting more than once with a long high input can be resolved by

using an early output in the JK toggle's signal pathway as the input to the next toggle. The JK

toggle's two initial neurons have the same pulse duration as the toggle's input. This means an

entire cascade can be composed of a ring oscillator and JK toggles, which require half as many

components as master-slave toggles. This configuration is illustrated in Fig 7. The use of JK

toggles as cascaded oscillators may be new.

Fig 7. Three cascaded neural oscillators. The cascade consists of a ring oscillator followed by

two JK toggles connected in sequence. The ring oscillator is composed of three inverters of Fig

4B, with an enabling first input. The toggles are as in Fig 4F. The input to the second toggle

comes from one of the first gates in the first toggle so that the duration of the high signal remains

the same throughout the cascade.

4.6. Cascaded neural oscillators simulation

The simulation in Fig 8 illustrates the main properties of the cascaded oscillators in Fig 7.

Like the simulation in Fig 5, this was done in a spreadsheet with the outputs of each neuron

computed by equation 3. At time $i = 0$, the outputs are initialized in a stable state. Additive noise

is simulated as a random number between 0 and 0.1. The Enabling input begins as baseline noise

and transitions between 0 and 1 as a sine function plus noise. During the interval when the

enabling input is high, it is 1 minus noise.

Fig 8. Simulation of three cascaded oscillators. The simulation illustrates the main properties

of the cascaded oscillators in Fig 7. The period of the ring oscillator's signal is twice the sum of

the three neurons' delay times. In each toggle, the period of every neuron's output is twice the

period of the toggle's input. The pulse duration of each toggle's two initial neurons is the same as

the pulse duration of the toggle's input. Using one of these signals as input to next JK toggle in the

cascade prevents it from inverting more than once during the input's cycle.

4.7. Frequency distribution of cascaded neural oscillators

502   Cascaded neural oscillators' frequencies are determined by the neuron delay times of the

503   cascades' initial ring oscillators.

4.7.1. Exact relationship between inverter delay times and cascaded oscillator frequencies

The interest here is in single-neuron inverters, but the argument applies to any

implementation of an inverter, including electronic.

As noted earlier, each cycle time of a ring oscillator is the sum of the times it takes for each

inverter to invert twice. If X_1, …, X_n are independent and identically distributed random variables

representing the delay times of n inverters in a ring oscillator, the oscillator's period is:

4. $Y = 2(X_1 + …+ X_n)$

If toggles are connected in sequence with the oscillator, each cycle time of each toggle's output is

the sum of two of the input's cycle times. Cascaded toggle number k has period:

5. $p^k = 2^k Y$

The mean and standard deviation of the delay times of inverters in ring oscillators are

denoted by μ_d and σ_d. By equations 4 and 5 and the elementary properties of random variables, for

i = 1, 2, 3, etc. (with i = 1 representing the initial ring oscillator), the period of cascaded oscillator

number i has mean and standard deviation:

6. $\mu_i = 2^i n \mu_d$, $\sigma_i = 2^i \sqrt{n} \sigma_d$

The factor 2^i shows the octave relationship between the periods' distributions. If the distributions

are normal, the first equation shows the octave relationship between the periods' peaks.

4.7.2. Normal distributions

Since neuron delay times are determined by several factors, the delay times are

approximately normally distributed (by the central limit theorem). By equations 4 and 5 and the

elementary properties of normal distributions, the periods of neural ring oscillators and cascaded

neural toggles are also approximately normally distributed.

The normal probability density function (PDF) with mean μ and standard deviation σ,

whose graph is commonly known as the bell curve, is:

7. $f(x) = \exp[-(x-\mu)^2/(2\sigma^2)]/\sqrt{(2\pi\sigma^2)}$

Substituting the cascaded oscillators' period parameters in equation 6 into equation 7, the

intersections of each pair of consecutive PDFs can be found by elementary algebra. For i = 1, 2, 3,

etc, (i = 1 representing the ring oscillator), the intersection of PDF_i and PDF_{i+1} occurs at:

8. $\text{Intersection}(i) = 2^i(2/3)\{n\mu_d + \sqrt{[(n\mu_d)^2 + 6n\sigma_d^2\ln(2)]}\}$ ms

The factor 2^i shows the intersections also have the octave relationship.

4.7.3. Neuron delay times

For small networks with chemical synapses, nearly all of the delay occurs at the synapses.

Several studies have measured synapse delay times [e.g., 34, 35], but the literature apparently does

not have empirical estimates of the parameters of the delay times' distribution. However, a

description of the range is "at least 0.3 ms, usually 1 to 5 ms or longer" [23]. Although the

description is far from precise, delay time parameters can be estimated.

The description of the range has two parts. The first part "at least 0.3 ms" seems to refer to

all observations. The second part "usually 1 to 5 ms or longer" seems to describe the ranges of

typical samples, with "5 ms or longer" representing the ranges' right endpoints. In that case, the

interval [1 ms, 7 ms] is at least a reasonable, rough estimate of the range of a moderately sized

sample.

If only the range of a sample (minimum value, m, and maximum, M) is known, the

midpoint can be used as an estimate of the mean of a distribution. Simulations have shown that

(M - m)/4 is the best estimator of the standard deviation for moderately sized samples [36]. Based

on this and the estimated range [1 ms, 7 ms], neuron delay times are estimated to have distribution

parameters:

9. $\mu_d = 4$ ms, $\sigma_d = 1.5$ ms

For a normal distribution with these parameters, about 99.3% of the distribution is greater than 0.3

ms. This agrees well with the description "at least 0.3 ms." About 73% lies between 1 and 5 ms,

and 95% is between 1 and 7 ms. This agrees reasonably well with the description "usually 1 to 5

ms or longer."

4.7.4. Graphs of neural oscillator frequency distributions

To produce oscillations for five EEG frequency bands, four toggles are needed in addition

to the initial ring oscillator. The hypothesis that cascaded oscillators produce EEG frequencies

implies the initial ring oscillator must have the minimum of three inverters, because an oscillator

with more inverters would be too slow to generate EEG oscillations in the gamma band. (This in

turn implies, unsurprisingly, that the brain evolved to enable some information to be processed as

fast as possible.) By substituting n = 3, the delay parameters of equations 9, and i = 1, …,5 into

equation 6, and substituting these period parameters into equation 7, the period PDFs of five

cascaded oscillators are obtained. Their graphs are shown in Fig 9. The PDF intersections shown

in the graphs are found by substituting the delay parameters in equations 9 and i = 1, ...,4 into

equation 8.

Fig 9. Frequency distribution of cascaded neural oscillators. The graphs are the estimated PDFs of the periods of a three-neuron ring oscillator and four cascaded toggles. The PDFs are derived from the estimated distribution of neuron delay times. The intersections and means (in Hz) are labeled in blue and yellow, respectively. Also shown in red and green are frequencies that are commonly cited as partition points separating the EEG frequency bands and peak frequencies

of three of the bands. The five intervals defined by the intersections of consecutive PDFs are

labeled with Greek letters to distinguish them from EEG frequency bands, which are commonly

written in the Roman alphabet.

4.8. Synchronization

The EEG frequency bands and associated behavioral and mental states are consistent with

the advantages of synchronous logic systems.

4.8.1. Synchronous logic systems

Logic systems have a timing problem in ensuring the various subcircuits change states in

the correct chronological sequence. Synchronous logic systems generally have simpler circuit

architecture and fewer errors than asynchronous systems. This is the reason nearly all electronic

logic systems are synchronized by an enabling pulse to each component circuit, so that whenever

any components change states, they change simultaneously. The enabling pulse in such systems is

usually produced by an oscillator. The enabling input in Fig 4E and the oscillators in Fig 7

illustrate how such synchronization is possible with neural networks.

Timing problems are greater in sequential logic than in combinational logic, and greater in

parallel processing than in serial processing. Much of the information processing in the brain

involves sequential logic and nearly all of it is parallel. The selective pressure for synchronization

in the brain would have been high, and the neural implementation demonstrated here is quite

simple.

The processing speed in a synchronous system depends largely on the enabling oscillator's

speed. Electronic processors generally operate at a single speed. A large system like the brain

that performs many diverse functions may have several different processing speed requirements.

The tradeoff for greater processing speed is a higher error rate. Functions that can tolerate a few

errors, and that need fast results with many simultaneous small computations, require high

processing speeds. Functions that are less dependent on speed or massive computation, or that

require few errors, or whose component networks are large and complex and therefore slow to

change state, call for slower processing.

4.8.2. Synchronization and EEG frequency bands

The EEG frequency bands and associated behavioral and mental states are consistent with

the function of multiple frequencies that was suggested in the preceding paragraph. Gamma

waves (high frequencies) are associated with vision and hearing, which make sense out of massive

data input in a few milliseconds. Beta waves are associated with purposeful mental effort, which

may involve less data input while requiring few errors and complex operations. Alpha waves are

associated with relaxed wakefulness, theta waves with working memory and drowsiness, and delta

waves with drowsiness and sleep. These categories require successively slower information

processing, and they have corresponding EEG bands of lower frequencies.

Cascaded oscillators can produce this neural activity. A neural oscillator can synchronize

state changes in neural structures by enabling them simultaneously. The enabling oscillator pulse

by itself does not produce any state changes. It only forces states to change simultaneously when

they do change. So the initial ring oscillator's high frequency signal could simply be connected

directly and permanently to the enabling gates (as illustrated in Fig 4E) of networks in the visual

and auditory cortexes, the first toggle's signal to networks in the prefrontal cortex for purposeful

mental effort, etc. A large number of neural structures synchronized in this way by cascaded

oscillators would exhibit the bands of matched periods found in EEGs.

4.9. Cascaded oscillators hypothesis

The *cascaded oscillators hypothesis* is that the brain structures' matched periods that are

found in EEGs are the result of the structures' synchronization by cascaded neural oscillators. The

main implication of the hypothesis is that the distribution of EEG frequencies in each band is the

same as the distribution of the corresponding oscillator's frequencies (Fig 9).

Two implications of the cascaded oscillators hypothesis are considered here. 1) The EEG

frequency band boundaries are the intersections of the oscillators' PDFs. 2) The EEG band peaks

occur at the means of the oscillators' PDFs. These implications are independent; i.e., neither

follows from the other. It follows from implications 1) and 2) that the ratios of consecutive EEG

band boundaries and the ratios of consecutive EEG band peak frequencies are 2.

The graphs in Fig 10 compare the means and intersections of the oscillator PDFs in Fig 9

with estimates of EEG band peaks and boundaries. The graphs strongly suggest that the

oscillators hypothesis is consistent with the available data. Following the EEG convention,

oscillations are measured in frequencies rather than periods. For convenient comparison, the data

in Fig 10 are shown together in Table 2. The linear regression results are in Table 3.

Fig 10. Cascaded neural oscillator PDF means and intersections compared with EEG band peaks and boundaries. Frequencies are given in hertz. **A.** The octave relationship of the means and intersections of cascaded oscillator PDFs in Fig 9 illustrated by an exponential function in log form. **B.** The oscillator graph in A compared to a log linear regression line for commonly cited EEG band peak frequencies and boundaries between bands. Numbers in parentheses show how many times each frequency was cited. **C.** The effect of different neuron delay time distributions. If the mean neuron delay time differs from 4 ms by as little as 1 ms, the cascaded oscillator means

639   and intersections lie outside the entire range of cited estimates of EEG peak locations & band

640   boundaries. **D.** The possible effect of rounding errors. The EEG regression line is shown with the

641   Theta-Delta boundary estimates of 4 Hz replaced by 3.7 Hz.

EEG band	Oscillators prediction Fig 10A	EEG regression Fig 10B	EEG regression Fig 10D
Gamma	41.7	38.8	39.9
	29.9	28.5	28.9
Beta	20.8	20.2	20.2
	14.9	14.8	14.7
Alpha	10.4	10.5	10.3
	7.46	7.69	7.50
Theta	5.21	5.45	5.25
	3.73	4.00	3.82
Delta	2.60	2.83	2.68
Distance of 10B regression from 10A		0.221	
Distance of 10D regression from 10A		0.133	

643   **Table 2. Fig 10 data.** Frequencies are given in hertz. Distances in the last two rows are the

644   square root of the sum of the squared differences of the column values in $\log_2$ linear form.

Fig 10A: Y = X + 1.38	Fig 10B	Fig 10D
Equation of linear regression:	Y = 0.944X + 1.50	Y = 0.973X + 1.42
Number of data pairs:	57	57
Sum of the squared deviations:	0.929	0.969
Standard error of the estimate:	0.130	0.133
Standard error of the slope:	0.016	0.016
Standard error of the intercept:	0.036	0.037
Correlation coefficient:	0.992	0.993

Table 3. Linear regression results for Fig 10.

4.9.1. Estimated oscillator PDF means and intersections compared with commonly cited

estimates of EEG band peaks and boundaries.

The following analysis for Fig 10 uses three properties of exponential functions:

10. In log form, the exponential function $y = A2^x$ is $\log_2(y) = x + \log_2(A)$.

11. The inverse function is $x = \log_2(y/A)$.

12. If $x_2 - x_1$ is a whole number n, then $y_2/y_1 = 2^n$. If y_1 and and y_2 represent frequencies
of periodic functions, the frequencies are n "octaves" apart.

The means and intersections of the PDFs in Fig 9 lie on an exponential function with base
two:

$y = 2.60(2^x)$.

The value 2.60 Hz was chosen as the constant for convenience because it is the smallest frequency

in Fig 9. By equation 10, the function in log form is $\log_2(y) = x + \log_2(2.60)$. The graph of this

function is shown in Fig 10A. The x coordinates of the points are computed from equation 11.

The whole number differences between the x coordinates for the means and intersections reflect

the frequencies' octave relationships, according to equation 12.

Fig 10B compares the graph of Fig 10A with a regression line for several frequencies that

are commonly cited as peak frequencies of three of the bands and partition points separating the

EEG frequency bands. The regression is based on 57 data points [13-16, 37-54]. (Estimates of

peak frequencies apparently have not been found for the lower frequency delta and theta bands

[48].) Since the oscillators hypothesis implies the EEG frequency distributions are the same as the

cascaded oscillators, the same x coordinates are assumed for the EEG data.

As predicted by the oscillators hypothesis, the graphs show a close match between EEG

frequency band boundaries and the intersections of the oscillators' PDFs, and between the EEG

band peaks and the means of the oscillators' PDFs. The slope 0.944 of the regression line is close

to the predicted value of 1. Although the apparent octave relationship between EEG frequency

bands "has been widely reported but rarely commented upon" [17], the regression in Fig 10B is

apparently the first test of the octave relationship.

4.9.2. The sensitivity of the distribution of oscillator frequencies to mean neuron delay time

Fig 10C shows how sensitive the distribution of oscillator frequencies is to the mean

neuron delay time. If μ_d differs from 4 ms by as little as 1 ms, the cascaded oscillator means and

intersections lie outside the entire range of cited estimates of EEG peak locations & band

boundaries.

As in Fig 10A, the constant terms in the exponential functions that contain the means and

intersections of the oscillator PDFs are chosen to be the smallest peak frequency, and the log of

this value is the constant term in the log representation of the function. Equation 6 shows that the

peak frequencies, and therefore the y-intercepts of the lines in Fig 10C as well, are determined by

μ_d. The delay time standard deviation σ_d affects only the placement of the PDF intersections on

the linear graphs, as indicated in the figure.

4.9.3. Sources and effects of errors in estimates of EEG band peaks and boundaries

The diverse values cited as band boundaries compared to the single values for band peaks

(Fig 10B) illustrate the greater difficulty in obtaining accurate boundary estimates. There are

several possible causes, some of which are suggested by the oscillators hypothesis.

4.9.3.1. Accuracy of estimates of EEG band peaks

The frequencies cited for the peaks of three EEG bands (10, 20, and 40 Hz) are likely to be

considerably more accurate than the frequencies cited for the band boundaries. First, any sample

of a unimodal distribution is likely to cluster near the peak. More data generally increases the

accuracy of an estimate. Second, the single value found for each peak is an indication of accurate

estimates. Third, the oscillators hypothesis implies the EEG band peaks have an exact octave

relation. The exact octave relation of the estimates is an indication of accurate estimates. Fourth,

the oscillators hypothesis and the close fit of the frequencies cited for the peaks to the predicted

values shown in Fig 10B indicates accurate estimates. Fifth, by equation 6 and the oscillators

hypothesis' implication that the EEG band peaks occur at the oscillator means, each of the three

peak estimates separately implies that the mean neuron delay time μ_d is 25/6 ms. This value,

approximately 4.167 ms, is close to the estimate of 4 ms obtained from a rough description of the

range of neuron delay times.

4.9.3.2. Accuracy of estimates of EEG band boundaries

4.9.3.2.1. Rounding errors

Rounding errors that result from the common practice of stating EEG band boundaries as

whole number frequencies could have a large effect on the regression line (Fig 10B). Unlike data

obtained in a noisy environment and other unbiased errors whose effects can be minimized with

large samples, rounding errors are biased in the direction of the integer nearest the value being

estimated. Fig 10D illustrates the possible effect of rounding errors in the estimates of just one

EEG band boundary.

The cascaded oscillators hypothesis' estimate of the delta-theta boundary is near 3.7 Hz

(Figs 9 and 10A), but nearly all of the cited boundary estimates in Fig 10B were 4 Hz. (It may be

significant that one of the cited estimates for the boundary was 3.5 Hz, the only non-integer in the

whole data set.) If the 12 cited values of 4 Hz in Fig 10B were obtained by rounding actual

experimental findings near 3.7 Hz, correcting this error alone would increase the slope of the

regression line from 0.944 to 0.973, substantially closer to the predicted value of 1. This

regression line is illustrated in Fig 10D. In addition, the regression line's y-intercept is changed

from $\log_2(2.83)$ in Fig 10B to $\log_2(2.68)$ in Fig 10D, substantially closer to the predicted value of

$\log_2(2.60)$ (Figs 9 and 10A). These values are displayed side by side in Table 3. The new slope

and intercept together move the regression's estimated EEG band peaks and boundaries

substantially closer to the oscillator PDF means and intersections.

The closeness of the two regression lines in Figs 10B and 10D to the oscillators' prediction

in Fig 10A can be measured by the square root of the sum of the squared differences of the nine

values (in $\log_2$ linear form) on each line, i.e., the Euclidean distance between two points with nine

coordinates. By this measure, the correction of a possible rounding error shown in Fig 10D cuts

the distance nearly in half. The distance between the two lines in Fig 10B is 0.221. The distance

between the lines in Fig 10D is 0.133. These values are shown in Table 2.

4.9.3.2.2. "Boundaries" of overlapping distributions

The oscillators hypothesis and the property that neuron delay times are approximately

normally distributed imply that the distributions of frequencies associated with the different

behavioral and mental states are overlapping ranges rather than discrete bands (Fig 9).

Researchers who estimated the band boundaries would have noticed the overlap because the

estimates of 4 ms and 1.5 ms for the delay time mean and standard deviation imply that only about

88% of the frequency distribution for each state lies between each PDF's intersections with two

adjacent PDFs (except for the first and last PDFs which have only one adjacent PDF).

The simplest and most obvious way of assigning a frequency to a band is by how often the

frequency is observed along with a particular behavioral and mental state, i.e., the ratio of the

number of observations of a frequency with a state to the total number of observations of the state.

(The ratio is necessary rather than the absolute number of observations of a frequency with a state

because one state may be observed more often than another.) For example, a frequency that is

observed more often with vision or hearing than with any other state is determined to be in the

gamma band. A frequency that is observed most often with purposeful mental effort is assigned to

the beta band. The endpoints of these bands would then be estimates of the oscillator PDF

intersections.

For a frequency near the intersection of two oscillator PDFs, the number of observations is

small compared to other frequencies because the probability of a particular frequency occurring is

minimized near the intersections. In addition, because the PDFs are nearly equal near the

intersection, how often the frequency is associated with one oscillator's behavioral and mental

state is likely to be nearly equal to how often the same frequency is associated with the other

oscillator's behavioral and mental state. Unless the number of observations of that frequency is

large, the larger of the two numbers could even be reversed from what the PDFs indicate is more

likely. This makes assigning frequencies to discrete bands difficult, which makes obtaining

accurate estimates of band boundaries difficult.

5. Results and explanations of known phenomena

5.1. Short-term memory

NFFs are a plausible mechanism for the brain's short-term memory. Flip-flops are the

main elements for random access (working) memory in electronic systems. The simulation shown

in Fig 5 demonstrated that with minimal neuron noise-reducing capabilities, NFFs can be robust in

storing information. Because NFFs function dynamically, information can be stored quickly. The

time required to set or reset an NFF is the time a signal takes to pass through two to four neurons,

roughly 10-20 ms. NFFs are inexpensive in material requirements because they require only a few

neurons and because storing information requires no physical change except neurons' activation

level. NFFs consume energy continuously while they are holding information, but this is

consistent with the brain's high energy consumption and it may be one of the selective pressures

that resulted in static mechanisms for long-term memory.

Direct electrophysiological evidence has shown that NFF memory banks (Fig 6) can

generate neural correlates of neuron firing associated with memory. Memory tests in monkeys

lasting up to 30 seconds found that certain neurons respond in the visual, auditory, or sensorimotor

cortexes of monkeys while corresponding sensory information is held in memory [10, 11].

Similar neuron responses have recently been found in humans [12]. For all of the seven memory

characteristics, one of the two outputs of an NFF in a memory bank is identical to the neuron's

response.

1) Before the stimulus was presented, the sampled neuron discharged at a low, baseline

level. This describes one of the two NFF output neurons before the NFF state is inverted. For

convenience, label the output M before the NFF is set. 2) When the stimulus was presented, or

shortly after, the neuron began to fire at a high frequency. This is the output M after the NFF is

set by the input S. 3) The high frequency firing continued after the stimulus was removed. This is

the stored memory bit M after the NFF input S returns to its normal low value. 4) The response

was still high when the memory was demonstrated to be correct. This is the high value of M

holding information in memory. 5) The response returned to the background level shortly after

the test. The memory bank is turned off when the stored information is no longer needed,

disabling all of the outputs. 6) In the trials where the subject failed the memory test, the high level

firing had stopped or 7) had never begun. In instances where the high level firing had stopped, the

memory bank may have been turned off before the memory was tested, or a distraction may have

caused the NFF to be overwritten with new information, or noise or other errors may have inverted

the NFF. In instances where the high level firing had never begun, the NFF was not set to record

the information or the NFF recorded it incorrectly (for one of many possible reasons, e.g., the

subject was not paying attention or was not motivated to remember). For each of these

possibilities, the NFF would correctly predict both the failed memory test and the corresponding

observed neuron behavior.

5.2. Electroencephalograms

The cascaded oscillators hypothesis answers the EEG questions raised in the introduction.

The hypothesis is that cascaded neural oscillators synchronize neural structures' state changes by

enabling them simultaneously. Here are the answers that follow from the hypothesis.

What causes a neuron to fire with a regular period for many seconds? Neurons fire with a

regular period because they are enabled by an oscillator. What is the function of such long-term,

periodic firing? The periodic firing continues for a time because the neurons are processing

information each time they are enabled.

What produces and what is the function of the synchronization of widespread periodic

firing? Many neural structures enabled simultaneously by the same oscillator produce the

synchronization. The function of synchronization is timing error avoidance in processing

information.

What produces and what is the function of the wide distribution of EEG frequencies in

bands? The frequencies in each EEG band are produced by a different oscillator. The function of

multiple oscillators is meeting the needs of different brain functions in the tradeoff between speed

and accuracy.

What produces the unimodal distribution in each band and the octave relationships

between the peaks and boundaries? The unimodal distributions are due to the normal distribution

of neuron delay times in the initial ring oscillators in cascades of oscillators. This makes the

distribution of frequencies of each oscillator normal. The ratio of consecutive boundaries and

peak locations is 2 because consecutive cascaded oscillators increase the oscillation period by a

factor of 2.

What determines the specific frequencies of the peaks and boundaries? The number of

neurons in the ring oscillators must be the minimum of 3 to produce the high frequencies in the

gamma band. Equations 6 and 8 show the EEG peaks and boundaries are determined by the mean

and variance of the delay times of the ring oscillators' neurons. The specific peak EEG

frequencies are given by the mean periods of the oscillators (first equation in 6), and the EEG

bands' boundaries are given by the intersections of the oscillator periods' PDFs (equation 8).

Why do gamma oscillations peak at only 40 Hz, while neurons are capable of producing

action potentials considerably faster? Three is the smallest possible number of inverters in a ring

oscillator, which produces bursts of spikes at an average estimated to be 41.7 Hz by the first

equations in equations 6 and 9 with $i = 1$. Although a neuron can produce spikes faster than 40

spikes per second, a single spike would not be a good enabler of state changes because the

duration of an enabling input needs to be long enough to overlap the input that is being enabled.

Why is there little agreement on the boundaries separating the EEG bands? The oscillators

hypothesis shows that assigning frequencies to bands by how often they are observed with a

certain behavioral and mental state makes the band boundaries coincide with oscillator PDF

intersections. Estimating boundaries empirically is difficult because there are relatively few

occurrences of frequencies near PDF intersections, and because different occurrences of the same

frequency near an intersection can be observed with the behavioral and mental state that defines

the band on either side of an intersection.

Two implications of the cascaded oscillators hypothesis were considered here: The EEG

frequency band boundaries are the intersections of the cascaded oscillators' PDFs, and the peaks

within the bands occur at the means of the PDFs. These results imply that EEG peaks and bands

have an octave relationship. Fig 10 and the accompanying analysis showed these implications

appear to be consistent with empirical measurements.

6. Testable predictions

6.1. Short-term memory

As stated earlier, one of the outputs of an NFF in a memory bank produces all seven

characteristics of neural activity associated with short-term memory [10-12]. An NFF's two

outputs M and $\overline{\text{M}}$ together predict eight more properties that could further test whether NFFs are

used for short-term memory. These predictions can be tested by the same methods that were used

in discovering the first seven phenomena since either M or $\overline{\text{M}}$ is predicted to be the neuron already

found in short-term memory, and the other is predicted to be nearby.

1) The outputs M and $\overline{\text{M}}$ are complements of each other; i.e., when one is high the other is

low. So not only is one neuron firing continuously while information is held in memory, as

already found experimentally, there should also be another neuron with complementary output.

Whenever one inverts, the other also inverts. 2) The two neurons have reciprocal input. This is

predicted by every NFF in Fig 4. 3) Because the two neurons have reciprocal input and are part of

a small network, they should be in close proximity. 4) The reciprocal inputs are predicted to be

inhibitory by every NFF in Fig 4. 5) The two neurons have responses that satisfy the noise-

reducing inequalities 1 and 2. 6) When the neurons change states, the high state changes first.

This is because the change in the neuron with the high output causes the change in the neuron with

the low output. This can be seen in every NFF in Fig 4. The change order is difficult to see in the

Fig 5 simulation because of the time scale and the slow rise time of the Set and Reset inputs, but

the simulation does have one neuron delay time between the completions of the two outputs' state

changes. 7) The other neuron's output then changes from low to high within a few milliseconds.

This happens quickly because reciprocal input from the first change causes the second within

approximately one neuron delay time, regardless of how long information is held in memory. 8)

After the memory test, the outputs of both neurons are low because the memory bank is turned off

to save energy when the information is no longer needed.

6.2. Constructed neural networks

Any of the networks in the figures could be constructed with actual neurons and tested for

the predicted behavior. The neurons only need to have the property that high inhibitory input

suppresses excitatory input. A neuron response that satisfies the inequality conditions 1 and 2 is

sufficient for robust operation of the networks in the presence of noise, but the conditions may not

be necessary.

The two-neuron NFF of Fig 4C and the three-neuron ring oscillator of Fig 7 may be the

simplest to construct and test because they are composed of a small number of neurons. The NFFs

are predicted to have outputs that are inverted by a brief input from S or R. (Recall Fig 4C is

active low.) The outputs should also exhibit the seven known properties of neural firing

associated with short-term memory and the eight properties predicted for NFFs in the preceding

section. The predicted behavior for the ring oscillator is oscillating outputs for all three neurons

with a period that is twice the sum of the neurons' delay times, and phases uniformly distributed

over one cycle.

6.3. Cascaded oscillators hypothesis

Fig 10 and the accompanying analysis offered enough evidence for the oscillators

hypothesis to warrant further research. More carefully documented examination of EEG

frequencies and neuron delay times are needed for a simple, rigorous test of the oscillators

hypothesis.

The number of neurons n in the ring oscillators almost certainly has to be 3 to produce the

fast frequencies in the gamma band. Equations 6 give an exact relationship between the

distribution parameters of neuron delay times and cascaded oscillators. The oscillators hypothesis

implies the distribution parameters of cascaded oscillators and EEG oscillations are the same.

The distribution parameters (mean and variance) of neuron delay times can be estimated

from a random sample of neuron delay times. The distribution parameters for one or more EEG

bands can be estimated from a random sample of EEG frequencies that are observed along with

the behavioral and mental state that defines the band. Such sampling data, or even estimates of

means and variances, may already be available in some database. The equality of the frequency

distributions of an EEG band and an oscillator as predicted by equations 6 can then be tested by

the standard tests for equal means and variances. To use equations 6 for this test, the EEG

frequencies must be converted to periods before computing the sample mean and variance. (The

period of the sample mean of frequencies is not the same as the sample mean of periods.)

Although it is possible that EEG frequencies are produced by cascades with initial ring

oscillators made up of specialized neurons whose delay times are different from the general

population of neurons, this appears to be unlikely. Fig 10B shows the EEG frequency bands are at

least close to the values predicted by the description of the range of all neuron delay times that was

used here to estimate oscillator neuron delay time parameters. In addition, neurons in general and

oscillator neurons in particular would have both evolved under selective pressure to function as

fast as possible.

7. Summary of results

The dynamic, explicit neural networks presented in Figs 4, 6, and 7 generate 13 EEG

phenomena and the seven phenomena of neural firing associated with short-term memory. The

networks also suggest selective advantages for both the synchronization of neural firing and

synchronization in different frequency bands that are found in EEGs (*Results and explanations of*

known phenomena section). Apparently no explanation of any of these phenomena has been

offered before. The networks predict eight testable phenomena of neural firing associated with

short-term memory, an exact relation between the distribution of neuron delay times and the

distributions of the five main bands of EEG frequencies, and numerous behavioral phenomena of

simple neural networks that can be constructed with neurons and tested (*Testable predictions*

section).

8. Acknowledgements

This manuscript has been released as a Pre-Print at BioRxiv [55]. Simulations were done

with Excel and CircuitLab. Network diagrams were created with CircuitLab and MS Paint.

Regressions were created with Converge 10.0. Graphs were created with Excel, Converge 10.0,

and MS Paint. The author would like to thank Ernest Greene, Arturo Tozzi, David Garmire, Paul

Higashi, Anna Yoder Higashi, Sheila Yoder, and especially David Burress for their support and

many helpful comments.

9. References

918 1. Yoder L. Relative absorption model of color vision. Color Research & Application.

919   2005 Aug 1;30(4):252-64.

2. Yoder L. Explicit Logic Circuits Discriminate Neural States. PloS one. 2009 Jan 7;4(1):e4154.

3. Yoder L. Explicit logic circuits predict local properties of the neocortex's physiology and anatomy. PloS one. 2010 Feb 16;5(2):e9227.

4. Yoder L, inventor. Logic circuits with and-not gate for fast fuzzy decoders. United States patent US 9,684,873. 2017 Jun 20.

5. Yoder L, inventor. Systems and methods for brain-like information processing. United States patent US 8,655,797. 2014 Feb 18.

6. McCulloch WS, Pitts W. A logical calculus of the ideas immanent in nervous activity. The bulletin of mathematical biophysics. 1943 Dec 1;5(4):115-33.

7. Goldental A, Guberman S, Vardi R, Kanter I. A computational paradigm for dynamic logic-gates in neuronal activity. Frontiers in computational neuroscience. 2014 Apr 29;8:52.

8. Hodges A. Beyond Turing's machines. Science. 2012 Apr 13;336(6078):163-4.

9. Paninski L, Brown EN, Iyengar S, Kass RE. Statistical models of spike trains. Stochastic methods in neuroscience. 2009 Sep 24:278-303.

10. Fuster JM, Alexander GE. Neuron activity related to short-term memory. Science. 1971 Aug 13;173(3997):652-4.

11. Funahashi S, Bruce CJ, Goldman-Rakic PS. Mnemonic coding of visual space in the monkey's dorsolateral prefrontal cortex. Journal of neurophysiology. 1989 Feb 1;61(2):331-49.

12. Kamiński J, Sullivan S, Chung JM, Ross IB, Mamelak AN, Rutishauser U. Persistently active neurons in human medial frontal and medial temporal lobe support working memory. Nature Neuroscience. 2017 Apr 1;20(4):590-601.

13. Posthuma D, Neale MC, Boomsma DI, De Geus EJ. Are smarter brains running faster? Heritability of alpha peak frequency, IQ, and their interrelation. Behavior genetics. 2001 Nov 1;31(6):567-79.

14. Johnson L, Lubin A, Naitoh P, Nute C, Austin M. Spectral analysis of the EEG of dominant and non-dominant alpha subjects during waking and sleeping. Electroencephalography and Clinical Neurophysiology. 1969 Apr 30;26(4):361-70.

15. Baumgarten TJ, Oeltzschner G, Hoogenboom N, Wittsack HJ, Schnitzler A, Lange J. Beta Peak Frequencies at Rest Correlate with Endogenous GABA+/Cr Concentrations in Sensorimotor Cortex Areas. PloS one. 2016 Jun 3;11(6):e0156829.

16. Voss U, Holzmann R, Tuin I, Hobson JA. Lucid dreaming: a state of consciousness with features of both waking and non-lucid dreaming. Sleep. 2009 Sep 1;32(9):1191-200.

17. Glassman RB. Hypothesized neural dynamics of working memory: Several chunks might be marked simultaneously by harmonic frequencies within an octave band of brain waves. Brain Research Bulletin. 1999 Sep 15;50(2):77-93.

18. Campbell N, Reece J, Taylor M, Simon E. Biology: concepts & connections. Pearson/Benjamin Cummings. San Francisco. 2006.

19. Weisbrod D, Khun SH, Bueno H, Peretz A, Attali B. Mechanisms underlying the cardiac pacemaker: the role of SK4 calcium-activated potassium channels. Acta Pharmacologica Sinica. 2016 Jan;37(1):82.

20. Kuramoto Y, Araki H. Lecture Notes in Physics, International Symposium on
Mathematical Problems in Theoretical Physics. Springer-Verlag. New York, NY.
1975:420.

21. Kuramoto Y. Chemical oscillations, waves, and turbulence. Springer Science &
Business Media; 2012 Dec 6.

22. Okun M, Lampl I. Balance of excitation and inhibition. Scholarpedia. 2009 Aug
16;4(8):7467.

23. Kandel E, Schwartz J, Jessell T, Siegelbaum SA, Hudspeth AJ. Principles of neural
science. McGraw-Hill Professional. New York, NY. 2013:160, 178.

24. Eggermann E, Bayer L, Serafin M, Saint-Mleux B, Bernheim L, Machard D, Jones BE,
Mühlethaler M. The wake-promoting hypocretin–orexin neurons are in an intrinsic
state of membrane depolarization. Journal of Neuroscience. 2003 Mar 1;23(5):1557-62.

25. Hopfield JJ. Neurons with graded response have collective computational properties
like those of two-state neurons. Proceedings of the national academy of sciences. 1984
May 1;81(10):3088-92.

26. Mysore SP, Knudsen EI. Reciprocal inhibition of inhibition: a circuit motif for flexible
categorization in stimulus selection. Neuron. 2012 Jan 12;73(1):193-205.

27. Carvalho TP, Buonomano DV. Differential effects of excitatory and inhibitory
plasticity on synaptically driven neuronal input-output functions. Neuron. 2009 Mar
12;61(5):774-85.

28. Jerne NK. The immune system. Scientific American. 1973 Jul 1;229(1):52-63.

29. Rajalingam R. Overview of the killer cell immunoglobulin-like receptor system.
Immunogenetics: Methods and Applications in Clinical Practice. 2012:391-414.

30. Vilches C, Parham P. KIR: diverse, rapidly evolving receptors of innate and adaptive
immunity. Annual review of immunology. 2002 Apr;20(1):217-51.

31. Uhrberg M. The KIR gene family: life in the fast lane of evolution. European journal of
immunology. 2005 Jan 1;35(1):10-5.

32. Robinson R. Mutations change the boolean logic of gene regulation. PLoS biology.
2006 Mar 28;4(4):e64.

33. Stepanova M, Tiazhelova T, Skoblov M, Baranova A. A comparative analysis of
relative occurrence of transcription factor binding sites in vertebrate genomes and gene
promoter areas. Bioinformatics. 2005 Feb 4;21(9):1789-96.

34. Adhikari BM, Prasad A, Dhamala M. Time-delay-induced phase-transition to
synchrony in coupled bursting neurons. Chaos: An Interdisciplinary Journal of
Nonlinear Science. 2011 Jun;21(2):023116.

35. Katz B, Miledi R. The measurement of synaptic delay, and the time course of
acetylcholine release at the neuromuscular junction. Proceedings of the Royal Society
of London B: Biological Sciences. 1965 Feb 16;161(985):483-95.

36. Hozo SP, Djulbegovic B, Hozo I. Estimating the mean and variance from the median,
range, and the size of a sample. BMC Medical Research Methodology. 2005;5:13.

37. "System and method of measuring and correlating human physiological characteristics
such as brainwave frequency." U.S. Patent 3,875,930, issued April 8, 1975.

38. Nunez PL. A study of origins of the time dependencies of scalp EEG: I-theoretical basis. IEEE Transactions on Biomedical Engineering. 1981 Mar(3):271-80.

39. Nunez PL. A study of origins of the time dependencies of scalp EEG: II-experimental support of theory. IEEE Transactions on Biomedical Engineering. 1981 Mar(3):281-8.

40. Teplan M. Fundamentals of EEG measurement. Measurement science review. 2002;2(2):1-1.

41. David O, Friston KJ. A neural mass model for MEG/EEG:: coupling and neuronal dynamics. NeuroImage. 2003 Nov 30;20(3):1743-55.

42. Ergenoglu T, Demiralp T, Bayraktaroglu Z, Ergen M, Beydagi H, Uresin Y. Alpha rhythm of the EEG modulates visual detection performance in humans. Cognitive Brain Research. 2004 Aug 31;20(3):376-83.

43. Mormann F, Fell J, Axmacher N, Weber B, Lehnertz K, Elger CE, Fernández G. Phase/amplitude reset and theta–gamma interaction in the human medial temporal lobe during a continuous word recognition memory task. Hippocampus. 2005 Jan 1;15(7):890-900.

44. König T, Prichep L, Dierks T, Hubl D, Wahlund LO, John ER, Jelic V. Decreased EEG synchronization in Alzheimer's disease and mild cognitive impairment. Neurobiology of aging. 2005 Feb 28;26(2):165-71.

45. Flagg RH, Barham WB, Stokes DA, Kotapish GE, inventors; Flagg Rodger H, Barham W Bruce, assignee. Method and apparatus for magnetic brain wave stimulation. United States patent US 6,978,179. 2005 Dec 20.

46. Herrmann CS, Demiralp T. Human EEG gamma oscillations in neuropsychiatric disorders. Clinical neurophysiology. 2005 Dec 31;116(12):2719-33.

47. Palva S, Palva JM. New vistas for α-frequency band oscillations. Trends in
neurosciences. 2007 Apr 30;30(4):150-8.

48. Jensen O, Colgin LL. Cross-frequency coupling between neuronal oscillations. Trends
in cognitive sciences. 2007 Jul 31;11(7):267-9.

49. Gireesh ED, Plenz D. Neuronal avalanches organize as nested theta-and beta/gamma-
oscillations during development of cortical layer 2/3. Proceedings of the National
Academy of Sciences. 2008 May 27;105(21):7576-81.

50. Lagopoulos J, Xu J, Rasmussen I, Vik A, Malhi GS, Eliassen CF, Arntsen IE, Sæther
JG, Hollup S, Holen A, Davanger S. Increased theta and alpha EEG activity during
nondirective meditation. The Journal of Alternative and Complementary Medicine.
2009 Nov 1;15(11):1187-92.

51. Poil SS, Hardstone R, Mansvelder HD, Linkenkaer-Hansen K. Critical-state dynamics
of avalanches and oscillations jointly emerge from balanced excitation/inhibition in
neuronal networks. Journal of Neuroscience. 2012 Jul 18;32(29):9817-23.

52. Thut G, Miniussi C, Gross J. The functional importance of rhythmic activity in the
brain. Current Biology. 2012 Aug 21;22(16):R658-63.

53. McConnell GC, So RQ, Hilliard JD, Lopomo P, Grill WM. Effective deep brain
stimulation suppresses low-frequency network oscillations in the basal ganglia by
regularizing neural firing patterns. Journal of Neuroscience. 2012 Nov 7;32(45):15657-
68.

54. Basar E, Basar-Eroglu C, Guntekin B, Yener GG. Brain's alpha, beta, gamma, delta,
and theta oscillations in neuropsychiatric diseases: proposal for biomarker strategies.
Suppl Clin Neurophysiol. 2013;62(1).

55. Yoder L. Explicit neural models for flip-flops and oscillators generate phenomena of

short-term memory and electroencephalograms. bioRxiv. 2018 Jan 1:403196.