High-order theta harmonics account for the detection slow gamma

Abbreviated Title: *Harmonics Account For Slow Gamma*

Y. Zhou[1], A. Sheremet[1,2], Y. Qin[1], J.P. Kennedy[2], N.M. DiCola[2], A. P. Maurer[1,2,3]

[1]Engineering School of Sustainable Infrastructure and Environment, University of
Florida, Gainesville, FL. 32611.
[2]McKnight Brain Institute, Department of Neuroscience, University of Florida,
Gainesville, FL. 32610.
[3]Department of Biomedical Engineering, University of Florida, Gainesville, FL. 32611.

Correspondence: Drew Maurer
18   McKnight Brain Institute,
19   1149 Newell Dr., RM L1-100E
20   University of Florida
21   Gainesville, Florida 32610
22   Tel: (352) 273-5092
23   Email: drewmaurer@ufl.edu

Number of pages: 49
Number of figures: 13
Number of tables: 0
Abstract words: 149
Introduction words: 980
Discussion words: 1785

The authors declare no conflict of interest.

Key words: Slow gamma, low gamma, nonlinearity, theta

Acknowledgements: This work was supported by the McKnight Brain Research
Foundation, and NIH grants- Grant Sponsor: National Institute on Aging; Grant number:
AG055544 and Grant Sponsor: National Institute on Mental Health; Grant Number:
MH109548 and a Diversity Supplement to NIH grant R01MH109548 (JPK). Special
thanks to S.D. Lovett for technical support.

ABSTRACT.

Local field potential (LFP) oscillations are the superposition of excitatory/inhibitory postsynaptic potentials. In the hippocampus, the 20-55 Hz range ('slow gamma') is proposed to support cognition independent of other frequencies. However, this band overlaps with theta harmonics. We aimed to dissociate the generators of slow gamma versus theta harmonics with current source density and different LFP decompositions. Hippocampal theta harmonic and low gamma generators were not dissociable. Moreover, comparison of wavelet, ensemble empirical-mode (EEMD), and Fourier decompositions produced distinct outcomes with wavelet and EEMD failing to resolve high-order theta harmonics well defined by Fourier analysis. The varying sizes of the time-frequency atoms used by wavelet distributed the higher-order harmonics over a broader range giving the impression of a wide band, low frequency burst. The absence of detectable slow gamma refutes a multiplexed model of cognition in favor of the energy cascade hypothesis in which dependency across oscillatory frequencies exists.

Introduction

In vivo neurophysiology has been a major tool in attempting to understand how the brain organizes behavior, with local-field potential (LFP) oscillations taking center stage. The large rhythmic oscillation in the hippocampus, theta (4-12Hz), was among the first to be characterized in the freely behaving animal (Jung and Kornmüller, 1938; Green and Arduini, 1954; Green and Machne, 1955; Vanderwolf and Heron, 1964; Vanderwolf, 1969; for review, see Buzsáki, 2005). The faster gamma oscillation (Stumpf, 1965; Leung, 1992; Bragin et al., 1995; Chrobak and Buzsáki, 1998; Penttonen et al., 1998), initially defined as a single, broad frequency range (e.g., 40-100 Hz, Bragin et al., 1995), has recently been subdivided into two, sometimes three independent ranges referred to as slow-, medium- and fast gamma (Colgin et al., 2009; Belluscio et al., 2012; Carr et al., 2012; Colgin, 2012; Schomburg et al., 2014; Colgin, 2015; Fernández-Ruiz et al., 2017; Lopes-Dos-Santos et al., 2018; Michaels et al., 2018). While the exact definition of these sub-bands varies across publications, they have been generally identified as 20-50Hz (slow), 50-90Hz (medium), and fast (90-120Hz). The identification of more than one gamma band has led to the multiple-gammas hypothesis of cognition, which proposes that different gamma frequencies reflect different synaptic inputs to the hippocampus and possibly distinct cognitive processing states (for review, see Colgin, 2015). Notably, the data have been equivocal on what those states might be, with both slow and fast gamma being linked to retrieval processes (Shirvalkar et al., 2010; Kemere et al., 2013; Newman et al., 2013; Bieri et al., 2014; Igarashi et al., 2014; Schomburg et al., 2014; Takahashi et al., 2014; Trimper et al., 2014; Yamamoto et al., 2014). Moreover, the theta and gamma oscillation are not strictly memory-dependent. Rather a substantial literature base demonstrates that these oscillations are velocity modulated (Chen et al., 2011; Ahmed and Mehta, 2012; Kemere et al., 2013; Zheng et al., 2015; Sheremet et al., 2018b).

Therefore, the exact relationship between the different gamma ranges and behavior is

not straight forward. The problem is further complicated by the existence of theta harmonics

(Harper, 1971; Coenen, 1975; Leung et al., 1982; Buzsaki et al., 1983; Leung and Buzsáki,

1983; Buzsáki et al., 1985; Ning and Bronzino, 1993; Czurkó et al., 1999; Terrazas et al., 2005),

which are frequency integer, phase coupled oscillations that precipitate in spectral

decomposition as a consequence of the fundamental 8Hz rhythm becoming both skewed and

asymmetric. As the harmonics of theta have been observed to go as high as 48 Hz (Sheremet

et al., 2016; Sheremet et al., 2018b), caution has been emphasized when examining the slow

gamma band to avoid harmonic contamination (Schomburg et al., 2014; Scheffer-Teixeira and

Tort, 2016). Specifically, theta harmonics (8, 16, 24, 32, 40, and 48 Hz) spill into the slow

gamma range (25-55Hz), potentially obfuscating spectral analyses.

In order to address the overlap between low gamma and high-order theta harmonics in

the power spectra, we sought to disambiguate the theta harmonics from slow gamma using

current source density analysis across hippocampal lamina and spectral decomposition.

Contemporary theories of slow gamma suggest that the oscillation is generated via CA3 to CA1

projections whereas the fast gamma is generated by entorhinal to CA1 projections (Colgin et al.,

2009; Belluscio et al., 2012; Schomburg et al., 2014; Colgin, 2015; Hsiao et al., 2016; Zheng et

al., 2016; Fernández-Ruiz et al., 2017). As these projections terminate in different layers of the

hippocampus, str. radiatum and str. lacunosum-moleculare respectively, we hypothesized that a

dissociation in the current source density pattern between these two oscillatory frequencies

could be identified. Remarkably, in neither our own data nor data provided from another

laboratory (Pastalkova et al., 2015; gift from the Buzsaki laboratory), were we able to find this

dissociation. This concern was increased in our failure to detect slow gamma-theta phase

coupling via bicoherence analysis which does not require any data preprocessing (Sheremet et

al., 2016; Sheremet et al., 2018b). Furthermore, using the methods of Masimore and colleagues

of determining the correlation coefficients between Fourier decompositions in order to identify

fundamental frequencies and cross-frequency interactions (2004; 2005), only coupling between

theta harmonics and a single 50-120 Hz gamma band was evident; there was a notable

absence of slow gamma (Sheremet et al., 2018b). Finally, the absence of low gamma was

further supported by recapitulating the phase-amplitude analyses of Colgin et al. (2009) as a

function of velocity (Sheremet et al., 2018b), which only revealed theta, theta harmonics and a

broad 50-120Hz band coupling.

In light of these incongruencies, we revisited many of the major tenets that have led to

the subdivision of the gamma band. Primary support for identifying the presence of an

oscillation that is distinct from noise is an increase in power over background activity (i.e., the

noise spectrum). Although initial approaches using Fourier based decompositions did not

observe a deviation that is supportive of slow gamma (e.g., Buzsáki et al., 2003), wavelet

decomposition (Colgin et al., 2009) and more recently, ensemble empirical mode decomposition

(Lopes-Dos-Santos et al., 2018), indicate a power deviation in the slow gamma range. In

investigating this, the methodological comparison suggest that slow gamma is an algorithmic

artifact of convolving the harmonics of theta. As secondary analyses, such as spike modulation,

coherence analyses, cross-regional interactions, and velocity modulation – *insufficient to*

determine the presence of an oscillation- have been provided as support for slow gamma, we

also revisit these results.

The major consequence of our research is that, as the subdivision of gamma has

provided a major foundation to the ideas of neural multiplexing and spectral fingerprinting

(Lisman, 2005; Siegel et al., 2012; Watrous and Ekstrom, 2014; Gu et al., 2015), the

multiplexed model of information routing becomes significantly weaker. Rather, these data

support an energy cascade model of hippocampal LFP in which low frequencies provide the

power, and thus entrainment, of higher frequencies (Sheremet et al., 2018b; Sheremet et al.,

2018a).

Methods

0.1 **Subjects and behavioral training**

All behavioral procedures were performed in accordance with the National Institutes of Health

guidelines for rodents and with protocols approved by the University of Florida Institutional

Animal Care and Use Committee. A total of seven 4-10 months old Fisher344-Brown Norway

Rats (Taconic) were used in the present study. This was a mixed sex cohort comprised of r530,

r538, r539, r544, r695, r779, r782 in order to integrate sex a biological variable and begin to

alleviate the disparity in research focused exclusively on males. Upon arrival, rats were allowed

to acclimate to the colony room for one week. The rats were housed and maintained on a 12:12

light/dark cycle. All training sessions and electrophysiological recordings took place during the

dark phase of the rats' light/dark cycle. Training consisted of shaping the rats to traverse a

circular track for food reward (45mg, unflavored dustless precision pellets; BioServ, New Jersey;

Product #F0021). During this time, their body weight was slowly reduced to 85% to their arrival

baseline. Once the rat reliably performed more than one lap per minute, they were implanted

with a custom single shank silicon probe from NeuroNexus (Ann Arbor, MI). This probe was

designed such that thirty-two recording sites, each with a recording area of 177 μm, were

spaced 60 μm apart allowing incremental recording across the hippocampal lamina. In

preparation for surgery, the probe was cleaned in a 4% dilution of Contrad detergent (Decon

Contrad 70 Liquid Detergent, Fisher Scientific) and then rinsed in distilled water.

0.2 **Surgical procedures**

Surgery and all other animal care and procedures were conducted in accordance with the NIH

Guide for the Care and Use of Laboratory Animals and approved by the Institutional Animal

Care and Use Committee at the University of Florida. Rats were initially sedated in an induction

chamber. Once anesthetized, the rat was transferred to a nose cone. The head was shaved

with care taken to avoid the whiskers. The rat was then transferred to the stereotax, gently

securing the ear bars and placing the front teeth over the incisor bar. The stereotaxic nose cone

was secured, ensuring that the rat was appropriately inhaling the anesthesia. During surgical

implantation, the rats were maintained under anesthesia with isoflurane administered at doses

ranging from 0.5 to 2.5%. Next, ophthalmic ointment was applied and tanning shades,

fabricated out of foil, were placed over but not touching the eyes to minimize direct light

exposure. Multiple cycle of skin cleaning, using betadine followed by alcohol was applied prior

to the first incision from approximately the forehead to just behind the ears. The remaining

fascia was blunt dissected away and bone bleeding was mitigated through application of bone

wax or cautery. Once the location of bregma was determined, the site of the craniotomy was

located and a 3x3mm contour was drilled out, but not completed. This was followed by the

placement of 7 anchor screws in the bone as well as a reference over the cerebellum and

ground screw placed over the cortex. Once the screws were secured, a thin layer of adhesive

cement (C&B-metabond, Parkell) followed by dental acrylic (Grip Cement Industrial Grade,

675571 (powder) 675572 (solvent); Dentsply Caulk, Milford, DE) were applied taking care to not

obscure the craniotomy location. Finally, the craniotomy location was completed, irrigating and

managing bleeding as necessary once the bone fragment was removed. Next a portion of the

dura was removed, taking care to avoid damaging the vessels and the surface of the neocortex.

Small bleeding was managed with saline irrigation and gel foam (sterile absorbable gelatin

sponges manufactured by Pharmacia & Upjohn Co, Kalamazoo, MI; a division of Pfizer, NY,

NY). The probe implant coordinates targeted the dorsal hippocampus (AP: -3.2 mm, ML: 1.5

relative to bregma, DV: -3.7 to brain surface). Some of these rats also received an identical 32-

site probe targeting the medial entorhinal cortex (0.5mm anterior to the transverse sinus, ML: -

4.6mm, DV: -5.78mm from brain surface, angled 15° posterior). Once the probe was in place,

the craniotomy was covered with silastic (Kwik-Sil, World Precision Instruments, Sarasota, FL)

and then secured to the anchor screws with dental acrylic. Four copper mesh flaps were placed

around the probe providing protection as well as acting as a potential Faraday cage. The wires

from the reference and ground screws were soldered to the appropriate pins of the connector.

Adjacent regions of the copper-mesh flaps were soldered together to ensure their electrical

continuity and the ground wire soldered to the copper mesh taking care to isolate the reference

from contact with the ground. Once the probe was secured, the rat received 10cc of sterile

saline as well as metacam (1.0 mg/kg) subcutaneously (the non-steroidal anti-inflammatory is

also known as meloxicam; Boehringer Ingelheim Vetmedica, Inc., St. Joseph, MO). The rat was

placed in a cage and monitored constantly until fully recovered. Over the next 7 days, the rat

was monitored to ensure recovery and no behavioral anomalies. Metacam was administered the

day following surgery as well. Antibiotics (Sulfamethoxazole/Trimethoprim Oral Suspension at

200mg/40mg per 5 mls; Aurobindo Pharma USA, Inc., Dayton, NJ) were administered in the rat

mash for an additional 5 days.

0.3 **Neurophysiology**

Following recovery from surgery, rats were retrained to run unidirectionally on a circle track

(outer diameter: 115 cm, inner diameter: 88 cm), receiving food reward at a single location. For

rats 530, 544 and 695, data is only analyzed from the circle track conditions. In order to deal

with low velocities from the circle track datasets, additional datasets for rats 538 and 539 from

running on figure-8 track (112 cm wide x 91 cm length) were used. In this task, rats were

rewarded on successful spatial alternations. Only datasets in which the rats performed more

than 85% of trials correctly were used. The local-field potential was recorded on a Tucker-Davis

Neurophysiology System (Alachua, FL) at 24 kHz (PZ2 and RZ2, Tucker-Davis Technologies).

The animal's position was recorded at 30 frames/s (Tucker-Davis). Spatial resolution was less

than 0.5 cm/pixel. Speed was calculated as the derivative of the smoothed position. The local-

field potential data was analyzed in Matlab® (MathWorks, Natick, MA, USA) using custom

written code as well as code imported from the HOSAtoolbox. Raw LFP records sampled at 24

kHz (Tucker-Davis system) were low-pass filtered down to 2 kHz and divided into fragments of

2048 time samples (approximately 1 second). To eliminate the effects of anatomic variations

between individuals and because the position and orientation of the hippocampal LFP probes

cannot be controlled precisely, the position of the hippocampal layers with respect to the

recording channels was determined by estimating the distribution of current-source density

(Rappelsberger et al., 1981; Mitzdorf, 1985; Buzsaki et al., 1986; Bragin et al., 1995). Current-

source density exhibits a unique distribution that is largely independent of anatomic details and

that may be used to accurately identify hippocampal layers.

Spike autocorrelation and cross-correlation spectrogram analyses.

Often the presence or absence of an oscillation is buttressed by whether or not single units are

modulated at a specific frequency, accomplished for examining if the spike times of the

individual cells prefer a specific phase of an oscillation. However, nonlinear issues can become

a factor in these analyses (Belluscio et al., 2012), necessitating a different approach. Therefore,

to determine the frequency in which neuronal spiking occurred, we implemented spectral

analyses on spike trains (Leung and Buzsáki, 1983; Sheremet et al., 2016). Single unit data was

generously provided by the Buzsaki laboratory and curated by the Collaborative Research in

Computational Neuroscience (Mizuseki et al., 2014; Pastalkova et al., 2015; datasets:

i01_maze06.005, i01_maze08.001, and i01_maze08.004). For these dataset, the rat performed

a delayed alternation task on a figure-8 maze, running in a wheel during the delay. Only

bilaterally recorded CA1 neurons were used for the analysis. Action potentials for pyramidal

cells and interneurons were initially sorted in to velocity bins, analyzing the 5-15 or 35+ cm/sec

conditions separately. These spike times were converted into a binary time series with a

sampling frequency of the 1250 Hz. As this binsize is slightly smaller than the traditional window

of 1 msec used for waveforms, a box car convolution was performed such that a single spike

registers as 1 across 3 adjacent bins. Each spike train was then passed through Matlab®'s

xcorr.m function which finds the correlation at specified lag times. Lags we only calculated up to

3 seconds. Each output was then passed through the pmtmPH

(https://www.mathworks.com/matlabcentral/fileexchange/2927-pmtmph-m) function to calculate

the power spectral density (PSD) based on multitaper analysis. Each unit's power was

normalized by the total power and then sorted by peak theta frequencies to align the harmonics

between units. The average and standard error power spectra is presented.

Fourier and Wavelet Transforms

I.   **Transforms**

The Fourier and wavelet transforms can be introduced formally as decomposition

on an orthogonal basis. Let S be some class of real functions and let ψ_f $(f \in R)$ be a basis in S;

then any $g \in S$ can be written uniquely as

243
$$G(f) = \int g(t)\psi_f^*(t)dt, \; g(t) = \int G(f)\psi_f(t)df.$$

244 The "coefficients" $G(f)$ of the decomposition (also referred to as the transform of g) are obtained

245 by taking the inner product of the function g with the basis elements (i.e., projecting $g(t)$ onto

246 the basis), The pair of equations are best known as direct and inverse transforms, sometimes

247 also called analysis and synthesis.

248 The Fourier transform pair is obtained letting $\psi_f(t) = e^{2\pi i f t}$

250
$$G(f) = \int_{-\infty}^{\infty} g(t)e^{-2\pi i f t}\, dt, \; g(t) = \frac{1}{2\pi}\int_{-\infty}^{\infty} G(f)e^{2\pi i f t}\, df$$

252 Unless the set of functions is carefully defined, these equations are only formal, and in most

253 cases they do not have any elementary mathematical meaning; when they do, their usefulness

254   is limited. For example, if $g(t) = 1$, the Riemann integral in the equation does not exist;

255   however, a rather restrictive elementary theory can be built for T-periodic functions.

256   The wavelet transform and its inverse are given by

257
$$G(s,\tau) = \int_{-\infty}^{\infty} g(t)\psi_{s\tau}(t)dt, \; g(t) = \iint_{-\infty}^{\infty} G(s,\tau)\psi_{s\tau}(t)dsd\tau$$

258
$$G(s,\tau) = \int_{-\infty}^{\infty} g(t)\psi_{s\tau}(t)dt, \; g(t) = C_\psi^{-1} \iint_{-\infty}^{\infty} G(s,\tau)\psi_{s\tau}(t)dsd\tau$$

259   Where the constant C_ψ depends only **on** ψ

260
$$C_\psi = 2\pi \int_{-\infty}^{\infty} |\hat{\psi}(\xi)|^2 |\xi|^{-1} d\xi$$

The functions $\psi_{s,\tau}(t) = \alpha\varphi\left(\frac{t-\tau}{s}\right)$ are "copies" of the "mother wavelet" $\varphi(t)$, shifted in time by τ

and scaled by s, with α a normalization constant. And $\hat{\psi}(\xi)$ is the frequency space

representation of the mother wavelet. The full set of wavelets $\{\psi_{s,\tau}(t)\}_{s,\tau \in R}$ is in general

complete but not independent (i.e., larger than a basis).

II.   **Discrete Transforms**

Evolving the generic Fourier and Wavelet equations into useful analysis tools has complexities

that required the development of full theories (e.g., the theory of distributions, or generalized

functions, e.g., Schwartz, 1950; Lighthill, 1958). For example, in Fourier equations $\psi_f(t) =$

$e^{2\pi i f t}$ are orthogonal in the sense that $\int_{-\infty}^{\infty} e^{2\pi i f t} dt = \delta(f)$, where δ is the Dirac delta function

(Vladimirov, 2002; Strichartz, 2003). A complete discussion of these is far beyond the scope of

this study, and is also unnecessary, because time series measured in practical applications are

always of finite length T, sampled at time intervals Δt ($T = n\Delta t$), i.e., are finite sequences of real

numbers $g(t) = \{g_1, g_2, \cdots, g_N\}$, with $g_j = g(t_j)$. Such sequences naturally form N-dimensional

spaces, in which integral Transforms, such as the Fourier or Wavelet equations, are

represented by finite-dimensional linear operators, i.e., $N \times N$ matrices. These discretized

versions of the Fourier and wavelet representations are called the *discrete* transforms (Briggs,

1995; Mallat, 1999; Strang, 2006).

The discrete Fourier transform pair is (in Matlab® convention)

281
$$G_m = \frac{1}{N} \sum_{n=0}^{N-1} g_n \psi_{mn}, \; g_n = \sum_{m=0}^{N-1} G_m \psi_{mn}^*, \; \psi_{mn} = e^{-2\pi i \frac{mn}{N}},$$

where $\psi_{mn} = \psi_m(t_n) = e^{-2\pi i f_m t_n}$ are the basis vectors. This pair of equations

are sometimes called the analysis and synthesis of the signal $g(t)$.

Here, $f_m = m\Delta f$ and $t_n = n\Delta t$ represent the discretized frequency and time grids, with $\Delta f = \frac{1}{T}$,

and $\Delta t = \frac{T}{N}$. Basis functions are orthogonal in the sense that, for any integer

m, with $m \neq 0$ and $m \neq N$, $\sum_{n=0}^{N-1} e^{-2\pi i \frac{mn}{N}} = 0$.

A discrete version of wavelet transform is

$G_{mn} = \sum_{k=0}^{N-1} g_k \, \varphi_{mnk}$, with $\varphi_{mnk} = s^{-\frac{m}{2}} \varphi[s^{-m}(k - n\Delta\tau s^m)]$,

where $\Delta\tau$ is a time-shift increment. The wavelets φ_{mnk} form orthogonal only for compact-support

wavelet shapes φ (e.g., Haar, and Daubechies wavelets; Daubechies, 1988, 1992; Mallat,

1999).

The Parseval relation insures that the discrete Fourier equations conserve the variance of the

time sequence and its transform (e.g., Briggs, 1995), i.e., $\sigma^g = \sigma^G$, where $\sigma^g = \sum_n |g_n|^2$ is the

variance of g. The discrete wavelet transform does conserve variance ($\sigma^g \neq \sigma^G$) and in general,

the variance ratio depends on g, which means that a universal correction factor does not exist.

299 Windowed Fourier Transform and the Detection of Fundamental Power

300 Interactions

301 To investigate the evolution of spectra over time, windowed Fourier transform (WFT) is

302 introduced where the original signal is multiplied by a window function which is nonzero

303 for only a short period of time

$$304 \qquad G^{\text{win}}(\tau, f) = \int_{-\infty}^{\infty} g(t)w(t - \tau)e^{-2\pi i ft}\, dt$$

305 where w is the window function (Priestley, 1981; Roads, 2004). The window function

306 slides along time axis, which gives rise to a time-frequency representation of the original

307 time series. This time-frequency representation can be plotted as the spectrogram.

308 Typically, window functions are smooth, "bell shaped", time-localized curves, the Fourier

309 transform of the window function is

$$310 \qquad W(f) = \int_{-\infty}^{\infty} w(t)e^{-2\pi i ft}\, dt.$$

311 In frequency space, the window function W is usually composed of a "bell shaped" main

312 lobe and symmetric side lobes. The window bandwidth of a window function is defined

313 as

$$314 \qquad B = \frac{\int_{-\infty}^{\infty} |W(f)|^2 df}{|W(f)|^2_{\max}}.$$

315   The spectrum estimation depends critically on the window bandwidth as it will smooth

316   the spectrum and influence the frequency resolution (**Fig. 1**). The time-frequency

317   resolution of transforms will be further discussed in the following section.

Figure 1. Windowed Fourier transform atoms. For windowed Fourier transform, window function is applied to all the frequency components. Adopting a Hanning window with wide time support to fast and slow oscillations (A) gives rise to fast and slow oscillations which decay slowly in time domain (B). In frequency domain, the power (amplitude square) of these slowly decay oscillations have relatively narrow frequency band and the bandwidth is the same for fast and slow oscillations (C). This results in transform with coarse time resolution but fine frequency resolution (D). As a result, windowed Fourier transform with wide time supported window functions has fine frequency resolution but coarse time resolution. On the contrary, applying Hanning window with narrow time support leads to fast decay oscillations in time domain (F). However, these fast decay oscillations have wide frequency band (G) and result in transform with fine time resolution but coarse frequency resolution (H).

In order to approach LFP interactions across regions, we implemented the method of

calculating the correlation coefficients of the spectrogram as outlined by Masimore and

colleagues (2004; 2005). The power cross-correlograms were obtained by estimating

the correlation coefficients between all the frequency pairs in the output of the discrete

Fourier Transform. Importantly, as discussed by Masimore et al. (2004; 2005), when

implemented as an autocorrelation, this method allows the fundamental frequencies of the

LFP to be identified without filtering as well as determine any potential interactions

across different oscillatory bands. When implemented as a cross-correlation, it provides

a measure of the degree in which the variance in power within one region affects the

variance in power within another region.

Ensemble empirical mode decomposition

The ensemble empirical mode decomposition (EEMD) analysis follows the procedure of Lopes-

Dos-Santos et al.(2018). The EEMD was applied to decompose the original LFP into Intrinsic

Mode Functions (IMFs). White noise was added to the original signal before decomposition to

alleviate mode mixing, and was canceled out after the decomposition by averaging over

ensemble (Wu and Huang, 2009). In this study, the ratio between the variance of added white

noise and the original LFP was 0.5, and the ensemble number was 200. After applying the

EEMD, the power spectrum for each IMF was used to identify the peak frequency. The supra-

theta signal is defined as the sum of all the IMFs with peak frequency above 12 Hz. The time-

scale power distribution of supra-theta signal was obtained by Morlet wavelet transform with

constant ratio for the wavelet family set as 7 (Colgin and Moser, 2009).

III.   Time-frequency atoms

340 For the Fourier transform, the duration T of the time sequence and the frequency resolution Δf

341 of the transformed sequence are related through the reciprocity relation

342
$$T\Delta f = 1,$$

which implies that increasing the frequency resolution Δf is equivalent to increasing the time

duration T of the analyzed signal. The $T\Delta f = 1$ equation highlights an important limitation of the

Fourier transform: if $g(t)$ is highly localized, its transform $G(f)$ has a wide frequency support.

This means that very high sampling rates to cover the wide frequency domain, and the

interpretation of the high-frequency content can become difficult. Restricting the Fourier analysis

equation to a specified duration T is equivalent to multiplying the time series $g(t)$

by finite support rectangular window $w(t - \tau) = 1$ if $|t - \tau| \leq {}^{T}\!/_{2}$ and zero otherwise,

$$350 \qquad \int_{\tau-T/2}^{\tau+T/2} dt e^{-2\pi i f t} = \int_{\tau-T/2}^{\tau+T/2} dt \, w(t-\tau)e^{-2\pi i f t} = \int_{-\infty}^{\infty} dt \varphi_{f\tau}^*(t),$$

or, alternatively by projecting g onto functions $\varphi(t) = w(t)\psi(t)$. The function φ could be

described as a localized oscillation. If one constructs in the time-frequency plane a rectangle of

sides T and Δf centered, say, at $t_0 = \frac{T}{2}$ and $f_0 = \frac{T\Delta f}{2\Delta t}$, the $T\Delta f = 1$ equation states that the area

of this rectangle is constant, regardless of the value of T. This rectangle is sometimes called

Heisenberg box (Mallat, 1999). This is in fact an example of the application of the general

Heisenberg uncertainty principle, which states that the area of a Heisenberg box cannot be

made arbitrarily small. For an arbitrarily-shaped localized oscillation $\varphi(t)$ with Fourier transform

$\phi(f)$ and unit variance $\left(\int_{-\infty}^{\infty}|\varphi|^2 \, dt = \int_{-\infty}^{\infty}|\phi|^2 \, dt = 1\right)$, defining the time and frequency widths as

$$359 \qquad \sigma_t = \int_{-\infty}^{\infty}(t - t_0)^2|\varphi|^2 \, dt, \quad \sigma_f = \int_{-\infty}^{\infty}(f - f_0)^2|\phi|^2 \, dt,$$

one can show (Gabor, 1946; Percival and Walden, 1993; Mallat, 1999) that $\sigma_t\sigma_f \geq \frac{1}{4\pi}$.

In other words, it is impossible to achieve simultaneous arbitrary resolutions both in time and

frequency. While the time-frequency resolution (area of Heisenberg boxes) cannot be made

arbitrarily small, it can be minimized. Gabor (1946) showed that the minimal area for a

Heisenberg box is achieved by localized oscillation $\varphi(t) = w(t)e^{2\pi i f t}$ where w is a Gaussian-

shaped window. Following his work, Goupillaud (1984) used this shape, later called the Morlet

wavelet, to introduce the continuous wavelet transform (Grossmann and Morlet, 1984; Mallat,

1999). The limitations imposed by the Heisenberg uncertainty principle are illustrated in **figure**

2. A Morlet wavelet results as a product of a sine function with a Gaussian window. The

resulting function is the "mother wavelet". The wavelet transform then uses scaled versions of

the mother wavelet as "elementary" functions.

It is important to note that the wavelets shown in figure **2**, panel d, are not harmonic,

therefore they are *not uniquely characterized by a single frequency value*; instead, they are

Figure 2: A schematic of the Heisenberg boxes of the wavelet transform. The mother wavelet is obtained by the multiplication of a sine function with a window (panels a-c). d) Wavelets at three scales resulting by the scaling of the mother wavelet. e) Frequency distribution of the power of wavelets shown in e). f) Heisenberg boxes of the wavelet transform.

characterized by a frequency interval, say, corresponding to the width of the frequency spread

of their power (as given by the Fourier transform). The frequency distribution of power is, as

expected, narrower for the larger-scale wavelets, and wider for smaller-scale wavelets.

Therefore, the wavelet Heisenberg boxes coverage of the frequency axis is not uniform, and

consequently, using wavelets as a "frequency" representation results in a non-uniform

frequency resolution, with resolution degrading at higher frequencies.

IV.   Numerical implementation

Fourier and wavelet analysis procedures were implemented in the Matlab® environment

using available Matlab® toolboxes. The Fourier cross-spectrum was estimated by dividing the

LFP time series into 2048-point (1 second) segments sorted by rat speed and windowed using a

hamming window; cross-spectra were estimated by averaging over all segments in each speed

bin; the coherence and phase lag are defined as the modulus and the argument of cross-

spectrum, respectively. The wavelet transform used the Morlet wavelet, with the central

frequency of Morlet wavelet used as nominal frequency. The Morlet wavelet family is

characterized by the constant ratio between the central frequency of wavelet and standard

deviation of the applied Gaussian window, set to 7 in our analysis in order to match the methods

of Colgin et al. (2009).

The wavelet scalogram is defined as the logarithm of the squared modulus $|G_{mn}|^2$ of the

wavelet coefficients. The power spectral density for the wavelet transform were computed as

the time marginal of the wavelet transform (Abry et al., 1993). The Fourier spectra were

estimated using the Welch method (Welch, 1967).

Methodological Limitation

At this point, it needs to be stressed that the wavelet and EEMD assignment of variance

to a specific frequency (e.g., in the construction of a power spectral density) is ultimately

arbitrary and potentially meaningless, since the elementary functions used for the

decompositions are not harmonics functions (sine/cosine). The data presented here are

for illustrative and replication purposes. We believe this methodological treatment is

flawed and should be treated with circumspection

RESULTS

The anatomical connectivity of the hippocampus is well conserved such that CA3 input into CA1

terminates into the str. radiatum layer of CA1 while entorhinal input terminates in both the oriens

and str. lacunosum-moleculare (Sheremet et al., 2018b). As the entorhinal cortex is has been

reported to convey fast gamma into the hippocampus whereas the radiatum supports low

gamma (Colgin et al., 2009), we first calculated the current source density LFP frequencies

across rats during behavior. Figure 3 shows the current-source density plots for the theta

frequency band as well as the first harmonic (15-17 Hz) and slow gamma (25-55Hz). With the

evidence that prospective coding increases with running velocity (Maurer et al., 2012) and that

prospective coding occurs during slow gamma epochs (Bieri et al., 2014; Zheng et al., 2016),

we optimized for the detection of low gamma by selecting epochs of rat speed greater than 35

cm/s. First, the current-source density of theta shows typical phase shift of theta rhythm from

oriens to the dentate gyrus across rats, demonstrating a reliable reconstruction of electrode

position (**Fig. 3**; also see Sheremet et al., 2018b). As the multiple gamma hypothesis contends

that there are two if not more gamma generators in the hippocampus that support the high and

low frequency oscillations (Colgin, 2015), we anticipated different source and sink patterns

between the harmonic of theta and the gamma oscillations.

Unsurprisingly, the distribution of sources and sink for the theta and the first harmonic are nearly

identical with both frequencies exhibiting maximum current deflection in the hippocampal fissure

(compare with figure 2 of Bragin et al., 1995). However, of concern is the similarity of fissure

sources and sinks between the traditional gamma range (25-55Hz) and both the fundamental

and first theta harmonic. One sure way to cleanly differentiate oscillations would be through the

demonstration of minimal synaptic overlap. These results, however, reveal that the synapses

that terminate around the fissure support both theta, the harmonic and the 25-55Hz oscillation

band (cf. figure 4C of Belluscio et al., 2012). Therefore, the current source density analysis is –

at the least – inconclusive regarding the disambiguation of low gamma from theta harmonics. At

the worst, it suggests that precisely the same synapses contribute to the spectral frequencies

between 8-55 Hz (suggesting that oscillations will inevitably be interdependent and coupled;

evidence against the multiplexing hypothesis).

Figure 3: Current source density (CSD) analysis of seven rats during high speed movement. LFP recordings were split into 1 second segments and only segments with mean velocity larger than 35 cm/s were kept. LFP segments were aligned based on maximum theta peak in stratum LM and then were averaged. CSD analysis were carried out for three frequency bands: 1) theta, 7-9 Hz (top row); 2) theta harmonic, 15-17 Hz (middle row); 3) slow-gamma, 25-55 Hz (bottom row). For each panel, CSD values were normalized by maximum source/sink strength. In contour plots, warm color represents current source and cold color represents current sink. Considering the differences of probe positions and hippocampus sizes among rats, the CSD data were rescaled and shifted based on hippocampus lamina. In individual rat maps the vertical axis is channel number (not shown). Phase changes across channels (vertical) of the current-source density allow for the identification of oriens (Or), pyramidal layer (Pyr), stratum radiatum (Rad), lacunosum-moleculare (LM), molecular layer (M) and upper granule layer, or dentate gyrus (DG). It may be interpreted that the dentate is capable supporting a 25-55Hz frequency oscillation such as low gamma (Colgin et al., 2009) or Beta (15-30 Hz; Rangel et al., 2015). We offer caution here as there are multiple theta diploes in the hippocampus with theta in the dentate potentially decoupled from theta in the str. radiatum (Montgomery et al., 2009). Furthermore, the theta oscillation in the dentate, cast a high number of harmonics relative to the other layers with the consequence of higher sources and sinks in the 25-55Hz band (see Fig. 5 below).

Comparison of these CSD results to the data of Belluscio et al. (2012; slow gamma

defined as 30-50 Hz) and Lasztóczi and Klausberger (2016; slow gamma defined as 32-41 Hz)

are partially at odds. Specifically, these studies identified a slow gamma rhythm in the radiatum.

In particular, Belluscio and colleagues observed a significant current source density in the

radiatum when the LFP was filtered in the low gamma range (see Figure 4C of Belluscio et al.,

2012). Therefore, we considered the possibility that due to unaccounted confounds, our results

in Figure 3 were incorrect. In light of this, we analyzed a single shank of a 256-site silicon probe

generously provided by the laboratory of Gyuri Buzsaki (Fernández-Ruiz et al., 2017). Current

source density was calculated during ripples as well as the LFP during behavior filtered for

theta, the first harmonic of theta, slow gamma (25-55 Hz) and a broad gamma (defined as 50-

120 Hz based on power spectral density cross-correlation and bicoherence analyses presented

in Sheremet et al., 2018b). Similar to figure 3, we found nearly identical profiles between theta,

the first harmonic, low gamma and the broad gamma frequency (**Fig. 4**). Therefore, in yet

another preparation, the radiatum has no more or less "slow gamma" than would be anticipated

from comparing the power spectral density profile across hippocampal layers (Sheremet et al.,

2018b). Furthermore, these results strongly parallel the original findings of Bragin et al. (1995).

It should be noted that Lasztóczi and Klausberger (2016) implimented a wavelet analysis to

identify different gamma bands with their slow gamma definition close to where the 32 and 40

Hz harmonics of theta would reside (Sheremet et al., 2016; Sheremet et al., 2018b). As the

CSD failed to disambiguate oscillatory frequencies across hippocampal lamina, but prior reports

using wavelet identified gamma, a new analytical course was determined.

Specifically, the overlap between the current sources of all oscilaltions works against the

idea that there are distinct generators that decouples theta from gamma. Moreover, there

seems to be limited rationale with respect to the sub-divion of the gamma band other than

analytical methods of spectral decomposition. Earlier methods utilizing Fourier based

decomposition only reported a unitary broad band gamma (Bragin et al., 1995; Buzsáki et al.,

2003) whereas the initial identification of slow gamma implemented a wavelet decomposition

Figure 4: Current source density (CSD) from data generously provided by the Buzsaki laboratory (Fernández-Ruiz et al., 2017). The ripple triggered CSD clearly resolves sources and sinks associated with the pyramidal layer, radiatum, lacunosum moleulcare and dentate gyrus. The source sink profile is distinct between ripple events and theta. Note well, however, that CSD plots for theta, the 16 Hz harmonic, slow gamma, and traditional gamma, the source sink profiles are highly similar. Simply, current is generated where there are synaptic contacts. As there does not appear to be separate layers that support specific frequencies, a parsimonious conclusion is that the synapses themselves are agnostic to the LFP frequency that they support. (Pyr, pyramidal layer; Rad, radiatum; LM, lacunosum-moleculare; g, granule cell layer). Color axis scales: Ripple: -0.75 to 0.75 mV; Theta: -0.15 to 0.15 mV; 1[st] Harmonic: -0.030 to 0.030 mV; Low Gamma: -0.015 to 0.015 mV; traditional gamma: -0.01 to 0.01 mV.

(Colgin et al., 2009). As the Heisenberg boxes differ between the two methods of analysis

(**Figs. 1 and 2**), the wavelet "convolves" over the higher order harmonics (potentially accounting

for why studies using wavelet decomposition rarely identify a harmonic above 16Hz).

Therefore, as an initial benchmark comparison of Fourier decomposition versus a Wavelet

decomposition, we generated a synthetic time series of pink noise embedded with an oscillation

at 8 Hz and harmonics at 16, 24 and 32 Hz (**Fig. 5**). Notably the power estimate of the Fourier

decomposition closely matched the theoretical distribution. However, as a consequence of the

multi-resolution analysis of the wavelet decomposition, the power estimate significantly expands

the frequency representation of the harmonics to cover a wide band, roughly overlapping with

reports of beta (15-30 Hz; Rangel et al., 2015; Rangel et al., 2016) and slow gamma.

Figure 5: Example of Fourier and wavelet analysis of a synthetic time series emulating an LFP recording dominated by an asymmetric theta signal. The signal is constructed from an asymmetric sine function (an 8-Hz fundamental oscillation with phase-coupled harmonics), and pink ($f^{-1.5}$) noise. a) A time-series segment. b) Estimates of power spectral density.

In addition to wavelet analysis, ensemble empirical mode decomposition (EEMD) has

been put forward as a method theoretically capable of breaking the LFP into theta and supra-

theta bands (Lopes-Dos-Santos et al., 2018). Specifically, Lopes-Dos-Santos and colleagues

claim that, following EEMD, the remaining supra-theta signal is "harmonic free". Therefore, we

conducted a direct comparison of fast Fourier transform, Wavelet decomposition and EEMD

from the lacunosum-moleculare of an awake-behaving rat as a function of velocity (**Fig. 6**). This

comparison clearly shows that, as anticipated from figure 6, that both the wavelet and EEMD

analytical approaches severely deviates from the Fourier representation at movement speeds

greater than 15 cm/s. Notably, this results in an apparent "convolution" of the third and fourth

harmonics of theta raising a significant cause for concern. In particular, wavelet and EEMD

yielded results congruent with the idea of "low gamma" while under representing the harmonics

of theta (which exist in the raw trace as a sawtooth shape; Buzsáki et al., 1985; Sheremet et al.,

2016). This phenomenon occurs to an extreme in the dentate gyrus, which exhibits up to the 5th

harmonic of theta, spilling into the range that has been defined recently as beta (Rangel et al.,

2015; Rangel et al., 2016) or potentially low gamma (Hsiao et al., 2016).

Figure 6: Comparison of three different spectral decomposition methods across layers and as a function of velocity. As previously describe by ourselves an others (Czurkó et al., 1999; Terrazas et al., 2005; Sheremet et al., 2016), Fourier decomposition clearly reveals the evolution of theta harmonics with velocity. This effect is consistent across layers, although the Fourier decomposition at high velocities in the str. radiatum and str. lacunosum-moleculare exhibits peak 32-36Hz range resembling a harmonic. However, wavelet decomposition based on the methods of Colgin et al., (2009) or the EEMD decomposition based on Lopes-Dos-Santos et al. (2018), due to the Heisenberg uncertainty boxes inherent in the analyses (Fig. 1) convolve over the 24Hz and higher order harmonics of theta. The peak of these broad bands roughly resembles what is described as "low gamma". Also, please note that in the decomposition of the str. pyramidale, str. radiatum and dentate gyrus, wavelet analyses potentially underestimates the true power of the traditional 60-100Hz gamma (Fourier decomposition power exceeds the wavelet). This most-likely is a consequence of broad range averaging as the Heisenberg box becomes larger with higher frequencies. (Fig. 1). Finally, it Is worth noting that the removal of a fundamental oscillation, as in EEMD, reduces power in the theta rhythm, but fails to demonstrate the capability of addressing higher order harmonics. Rather, it parallels the outcome of the wavelet analysis. Once again, we remind the reader that, for wavelet and EEMD, *the assignment of variance to any specific frequency is ultimately arbitrary and meaningless.*

With this concern in hand, we proceeded to revisit the wavelet scalogram analysis used

by Colgin et al. (2009) to investigate the interaction between gamma frequency and the theta

oscillation. This was first conducted for synthetically generated data (a sawtooth wave and an

oscillation with integer locked harmonics) as well as data collected from the dentate gyrus and

str. lacunosum-moleculare (**Fig. 7**). For the wavelet scalogram decomposition of the sawtooth

wave, an infinite series of harmonics capture the instantaneous change in amplitude. The

wavelet decomposition achieves this through a considerable peak in high frequency mid-trace.

However, this is accompanied by multiple low-level harmonics within the low gamma range.

While this is a simulation to an extreme derivative, the time-frequency representation the

synthetic harmonic series (8, 16, 24, and 32 Hz) is nearly identical to the slow gamma bumps

that can be seen in the decomposition of either the dentate granule layer or the lacunosum-

moleculare (compare Fig. 7 to figure 1Eb of Colgin et al., 2009). This "slow gamma" effect,

however, can be accounted for the smoothing of harmonics observed in figure 6.

As the results of wavelet and EEMD are rarely portrayed as frequency versus power, but

rather in terms of a time frequency representation, we furthered the comparison using two

different windows of analysis (**Fig. 8**). Both in the long, three-minute fast Fourier transform and

short, 6 second fast Fourier transform there is the clear presence of a 3[rd] order theta harmonic

(~24-27 Hz) and a trace of a 4[th] harmonic (~32-36 Hz; **Fig.8, top panels**). However, as

anticipated from the Heisenberg boxes (**Fig. 2**), examination of the wavelet on both the long and

short time series result in a "smearing" and apparent intermittency of the ~24-27 Hz frequency

band. Stated differently, the 24-27 Hz component is a direct consequence of theta being

skewed and asymmetric (for example, more "saw tooth" shape than a sinusoid; Buzsaki et al.,

1983; Buzsáki et al., 1985; Terrazas et al., 2005; Sheremet et al., 2016). This frequency is

inherently coupled to the fundamental 8 Hz frequency, but the wavelet decomposition artificially

detaches the 3[rd] harmonic from the fundamental by using a different decimation of time and

frequency (**Fig. 2**). This "bleed" and intermittency offers a strong resemblance to experiments

Figure 7: Wavelet scalograms for synthetic time series and LFP recordings in strata LM and DG. The averaged time series for one theta period (8 Hz) and wavelet scalograms were obtain for four time series: 1) Synthetic sawtooth waves (left to right, the 1st column); 2) Time series with fundamental 8 Hz oscillation and its harmonics (16, 24 and 32 Hz) (the 2nd column); 3) LFP recorded in DG (the 3rd column); 4) LFP recorded in LM (the 4th column). Synthetic time series have the total length of 10 seconds and were added with a background pink noise. LFP recordings were selected during high speed running with the total length of 5 seconds. The averaged time series were obtained by averaging over theta (8 Hz) periods (top row). The wavelet scalograms for averaged time series were computed with wavelet transform (middle row). Averaged time series were filtered within theta band (7.5-8.5 Hz) which represent the theta phase (bottom row). LFP data were collected from r530.

that report different theta cycles exhibiting unique gamma signatures (e.g., Colgin et al., 2009;

Bieri et al., 2014). To an extreme, using EEMD, it has been argued that theta can mix and

match different gamma frequencies (Bagur and Benchenane, 2018) in support of different

memory processes (Lopes-Dos-Santos et al., 2018). Therefore, we also replicated the methods

of Lopes-Dos-Santos et al. (2018). Notably, comparing both the long- and short- temporal

epochs of wavelet decomposition of the "supra-theta" reveals the distorted remnants of the

Figure 8: Spectrograms and power spectra during run epoch with different methods. Spectrogram and power spectrum were computed for a long run epoch (left column, 5 minutes) and a short epoch (right column, 6 seconds). For each epoch, the spectrograms were estimated with three methods: 1) Fourier transform (1st row) with window length of 1 second and window increment of 0.1 second. 2) Wavelet transform (2nd row) with Morlet wavelet. 3) Wavelet spectrogram of supra-theta signal (3rd row). The supra-theta signal was obtained from ensemble empirical mode decomposition (EEMD) with noise level equaling to 0.5 total variance and ensemble number equaling to 200. The supra-theta was defined as the sum of decomposed modes whose central frequencies were large than 12 Hz. The wavelet spectrogram of supra-theta was computed with the method described above. Power spectra were computed by averaging the spectrogram over time (bottom row). For both epochs, the Fourier transform identifies theta and high order harmonics while wavelet analysis tends to resolve a theta rhythm and a wide-band frequency component (16-30 Hz). By considering this band as independent from theta in this manner gives the unintentional representation that there are "bursts" of gamma. Stated differently, the 24Hz oscillation is inherently dependent on the nonlinearity of theta ("saw tooth" shape of theta) and thus is incorrectly decomposed by the wavelet. Data were collected from r782.

second harmonic of theta as well as the third harmonic (**Fig. 8**). Finally, the summary power

spectra for each method is presented demonstrating the inability of either wavelet or EEMD to

clearly resolve the theta harmonics.

Up to this point, the current manuscript has focused on the primary methods of spectral

decomposition that have led to the impression of a slow gamma oscillation in the hippocampus.

However, this does not encompass the entirety of support for slow gamma. For example,

analyses of hippocampal neuron spike times have revealed modulation to low gamma (e.g.,

Colgin et al., 2009), with the logic being that as the cells exhibit a phase preference, one can

sketch a theoretical mechanism by which they support the oscillation. The concern, however,

has been raised that modulation in the 20-30Hz band may not actually be related to the low

gamma, but rather coupled to the asymmetry of theta (Schomburg et al., 2014). That is, the

spike depth of modulation plots are not pure sinusoids, but exhibit skew and asymmetry

(Skaggs et al., 1996; Quilichini et al., 2010). Furthermore, spectral decomposition of spike trains

has revealed the presence an ~16 Hz harmonic modulation (Sheremet et al., 2016). Therefore,

we considered the possibility that prior publications reporting phase coupling of neurons to slow

gamma find significance for the reason that higher order harmonics in the LFP have a direct

relationship to higher order harmonics in the frequency of spikes. Therefore, the point process

spike trains (readily available on the CRCNS.org website; see Methods) were sorted into either

a low or high velocity bin, converted into a binary timeseries, and either correlated against itself

(autocorrelogram) or other neurons (cross-correlogram). These correlograms were then

spectrally decomposed to examine the burst frequency modulation (see Geisler et al., 2007 for

similar methods). Notably, in accordance with prior publications, the "power" (number of spikes)

increases from low to high velocity and the burst frequency of the population increases with

velocity (**Fig. 9**; Maurer et al., 2005; Geisler et al., 2007). Under the assumption that slow

gamma modulation is highest when prospective coding is the greatest (Bieri et al., 2014; Zheng

et al., 2016), which also describes the farther look-ahead at higher running speed

Fig. 9: Power spectral density of neuron autocorrelograms (top two rows) or cross-correlograms (bottom three rows). The left column are the individual power spectra for auto- and cross-correlograms taken at slow velocity (5-15 cm/s) while the middle column are the same neurons or neuron pairs at high velocity (35+ cm/s). The power spectral densities are normalized by the overall power of the high velocity spectrogram. The rows are sorted by the maximum frequency between 6-10Hz. The right column is the average power spectral density of the spike auto- and cross-correlograms at low (blue) and high velocities (red); errorbars are the standard error of the mean. The red dashed vertical lines are plotted at integers of 9 Hz up to 36 Hz. Note that neither the auto- or cross-correlogram power spectral show a single, slow gamma peak. Rather, should there be a notable deflection, it coincides with harmonics of the fundamental frequency. Also note that the dispersion in frequencies of the auto- and cross-correlations that include pyramidal neurons decreases as velocity increases. Energy/input stabilizes coherent oscillatory patterns.

(Maurer et al., 2012), it may be anticipated that there would be a single peak in the gamma

range of the spike correlation spectrograms. Investigations of the spectrograms, however, do

not support this perspective. Rather, the small observable peaks tend to coincide with harmonic

lines (7.5, 15, 22.5, and 30 Hz). Therefore, the most reasonable conclusion is that phase

coupling observed between a 25-55Hz band and spikes is carried by the harmonics evident in

the LFP and the spike trains rather than being a consequence of a slow gamma oscillation that

is distinct from theta. Note well that, when the power spectra are sorted by the frequency of the

maximum power, pyramidal neurons (and their pairs) exhibit a greater frequency dispersion in

the autocorrelograms and cross-correlograms relative to high velocity – *simply, oscillatory*

dynamics are stabilized by energy/input (Churchland et al., 2010).

Significant emphasis has been placed on coherence and cross-frequency analysis as a

justification for low gamma. Caution, however, has been emphasized with respect to low values

of coherence (Buzsáki and Schomburg, 2015), alluding to the idea that low values have

contracted meaning. Furthermore, under the hypothesis that hippocampal LFP patterns are

organized by a cascade of energy from low frequencies to high frequencies (Buzsaki, 2006;

Sheremet et al., 2018b), coherence should be significantly driven by activity into the

hippocampus (which is approximately correlated with running speed). Therefore, we

investigated coherence between the dentate gyrus and other lamina of the hippocampus as a

function of velocity (**Fig. 10**). For comparison, we have also included the power spectral density

measure and phase offset as a function of depth. At low velocities, coherence is fairly low

without any notable deflections above theta. At high velocities, however, there is both an

increase in the power of theta harmonics along with large coherence in theta harmonics across

hippocampal lamina. Given the substantial increase in coherence across the theta harmonics

with velocity, a traditional approach of considering coherence that does not account for velocity

may unintentionally smear the range between 16-48 Hz, giving the impression of a single peak.

Figure 10: Distribution of cross-spectrum over hippocampal layers during active behavior, at low speed (top three rows) or high speed (bottom three rows). Cross-spectra shown are estimated with reference to the DG layer. For each rat, the observed regions of the hippocampus Top: spectral density of LFP variance. Middle: coherence (cross-spectrum modulus). Bottom: phase lag (cross-spectrum argument). On each sub-panel, the vertical axis is channel number (not shown); the panels are aligned according to the layer identification procedure. Distribution of cross-spectrum over hippocampal layers during active behavior), at high speed. Note that at high velocities, the power spectra, coherence and phase measures support the observation of multiple theta harmonics.

Coherence analysis, however, to a large extent is unaffected by changes in power (of

course, an amplitude must be present to define a phase). Therefore, we considered the

argument that slow gamma is not entrained through the hippocampus in terms of phase-phase

coupling. Rather, power is the important driver of coupling. Therefore, using the methods of

Masimore et al. (2004; 2005), we investigated how changes in power within either the medial

entorhinal cortex or dentate gyrus correlated with power changes across the lamina of CA1. In

accordance with our recent publication (Sheremet et al., 2018b), we only found evidence of

cross-regional power interactions between theta, theta harmonics and a unitary gamma (**Fig.**

11). From these power-power analyses, there is no reason to believe a slow gamma oscillation

exists.

Finally, if the observation of slow gamma were a consequence of theta harmonics, then

there should be a strong dependence on velocity. Investigation of the primary literature,

Figure 11: Average cross correlation coefficients of Fourier transform across three rats with electrodes in the medial entorhinal cortex in order to identify fundamental frequencies of interaction. As previously described, regions of non-zero correlation potentially indicate that two oscillatory bands showed high power at similar times suggestive of an interaction (see Masimore et al., 2004; 2005). In both cross-correlations between the DG and hippocampal lamina as well as the MEC and hippocampal lamina, there are notable "dots" of correlations below at ~40Hz and below, indicative of theta and its harmonics (Sheremet et al., 2016; 2018). Further off-axis, there is a correlation between ~80-120 Hz and theta as well as its harmonic. Notably, there is no reason to expect the need to subdivide gamma into multiple bands. Rather, the interactions are constrained to theta, its harmonics and the broad gamma band as originally described by Bragin et al. (1995; 50-120 Hz). For all plots, values below 0.03 are set to white. Or, oriens; Pyr, CA1 pyramidal layer; Rad, Radiatum; and LM, lacunosum-moleculare.

however, is not so clear cut. For example, Chen and colleagues observed a linear change in

slow gamma with velocity (2011), supporting the harmonic hypothesis. Ahmed and Mehta, on

the other hand, found a reduction in slow gamma power with running speed (2012). Analytically,

these results are not incorrect, but more nuanced. Specifically, as animal running velocity

increases, there is an associated increase in theta power and the harmonics. These increases

in power can be viewed as the energy into the hippocampus increasing resonance or bringing

otherwise incoherent neural activity into coherent, dynamic patterns. The consequence is that

the incoherent activity surrounding the theta and harmonic bands: 1-6, 10-14, 19-23, and 25-40

Hz will effectively lose power (**Fig. 12**). Note well, this idea is against the idea of spectral

multiplexing, in which each frequency has an independent meaning. Thus, the parsimonious

explanation is that neurons can "drift" (exhibit a range of oscillations) when provided a low level

of input, but become strongly entrained with energy and velocity (Sheremet et al., 2018b). This

accretion of power in one or multiple bands comes at the expense of losing power in others.

Nevertheless, this effect of spectral reorganization – eroding background with energy- likely

accounts for the results also observed in Kemere et al. (2013) and Zheng et al. (2015). If

anything, as oscillations are often discussed through the lens of entrainment, the disappearance

of slow gamma power with energy/velocity supports the idea that it most-likely was never an

oscillation at all, but rather a component of the noise spectrum.

Figure 12: Spectral changes with velocity. It is often reported that there is a either no change or a decrease in slow gamma with increasing running velocity. While this is analytically, it is most-likely a result of the same reduction in power from 1-6, 10-14, 19-23, and 25-40Hz. That is, when a network of neurons receives a low level of input, the activity is unorganized, resulting in a smooth decrease in power from 1- 100Hz. However, as velocity is associated with increasing firing rates, the network organizes as a function of increasing energy (synaptic activity). Input stabilizes oscillatory dynamics (see Fig. 9; for similar data, see Churchland et al., 2010). By acting on one another, neurons will self-organize into a pattern of activity that supports theta, its harmonics and gamma. Thus, the reduction of the 25-40 Hz band is most likely a consequence of neurons becoming entrained. This effectively challenges the argument for slow gamma (it may be considered inappropriate to suggest an oscillatory band disappears when neural entrainment occurs). Compare to Ahmed and Mehta (2012; Fig 2).

Discussion

The identification of slow gamma was initially predicated on wavelet decomposition

(Colgin et al., 2009). More recently, empirical mode decomposition (EEMD) has been reported

to find multiple low-frequency oscillatory bursts (22 Hz beta, 35 Hz slow gamma, and a 54 Hz

mid-gamma; Lopes-Dos-Santos et al., 2018). Using the methods of Colgin et al. (2009) and

Lopes-Dos-Santos et al. (2018), we successfully replicate these findings, but the results are

contradicted by Fourier analysis. Specifically, the Fourier decomposition exhibits significant

peaks in the high-order theta harmonics (24, 32, and 40 Hz). Critically, these contradictory

outcomes are incompatible, necessitating a reevaluation of multiple concepts.

The fundamental issue is what defines an oscillation or rhythm? The identification of a

hippocampal oscillation is often based on visual examination, followed by analytical methods.

This has been true for theta which corresponds to a significant local maximum above the

background activity (Vanderwolf and Heron, 1964; Vanderwolf, 1969). Note, that in this

definition, the power distribution defines the frequency band. If the 6-8 Hz band deviates from

the noise slope, it is interpreted as the presence of an oscillation. This distinction is peculiar,

since in fact any frequency band with non-zero power is in the Fourier representation an

oscillation.

Moreover, the "peak above noise" definition of a rhythm does not work in general for the

gamma rhythm, because (in all cases but high running speed) there is no "significant local

maximum" in the power spectral density. Rather, gamma is an accumulation of energy that is

often made evident by compensating (e.g., whitening) the spectrum (n.b., finding peaks after

standard whitening procedures are problematic if the spectra does not follow a unitary slope

which appears to be true for hippocampal LFP; Sheremet et al., 2018b; Sheremet et al., 2018a).

This raises the question "what is so special about spectral deviations that single out those

frequency bands from 'noise bands' that have comparable energy?". The answer seems to be

the idea that there is a "background spectrum" that has a different meaning and does not really

matter enough to be called a rhythm. Only accumulations of energy past this background level

are significant. The significance of these accumulations of energy, however, is unclear in the

absence of a physical model of the phenomenon. Such a model should explain both the

processes underlying the "non-rhythm" background spectrum, and the "rhythm" spectral

deviations (e.g.,Sheremet et al., 2018a). In failing to do so, the multiplexing model of cognition

seems improvised to account for the wavelet decomposition results. One must conclude that

the definition of a "rhythm" based on the power distribution is an arbitrary decision, because it is

based on the "aspect" of subjective representations and not on a fundamental, analysis-

invariant description of the physics underlying the LFP process.

In contrast to the multiplexed "spectral finger print" perspective (e.g., Canolty et al.,

2010; Siegel et al., 2012; Knight and Eichenbaum, 2013; Watrous et al., 2013; Akam and

Kullmann, 2014; McLelland and VanRullen, 2016), the perspective that the hippocampal LFP is

generated by the superposition of electrical fields generated by microscopic elements of a large,

macroscopic system (Buzsáki et al., 2012) suggests statistical mechanics as a general

framework for understanding LFP characteristics. While transient behavior in large nonlinear

systems is possible (e.g. the sharp-wave/ripple complex), the behavior we expect for a "stable"

system is the weakly nonlinear type, characterized by stationarity. In such systems the Fourier

representation remains valid and the power spectral representation is defined. An alternative

description of LFP processes, based on statistical mechanics and seeking to account for all

processes expressed in the LFP spectral distribution ("rhythm" or not) is proposed in Sheremet

et al. (2018a).

Therefore, when discussing the meaning of the "slow gamma rhythm", it is important to

examine carefully the assumptions about the underlying physical process embedded in the

methods of power-frequency decomposition. Specifically, the observation of novel oscillatory

bands have been supported through wavelet analyses (e.g., Colgin et al., 2009), and ensemble

empirical mode decomposition (EEMD; Lopes-Dos-Santos et al., 2018). The issue of analytical

applicability of each method to the hippocampal LFP necessitates a discussion on whether or

not the experimenter considers the trace to be stationary or not (See Appendix). Nevertheless,

as emphasized in the methods, wavelet and the EEMD approach of assigning power to a

frequency is ultimately arbitrary and potentially meaningless, since the elementary functions

used for the decompositions are not harmonic (sine/cosine). In other words, the power to

frequency assignment becomes obscured.

Other empirical support for the existence of slow gamma included the correlation of units

to the LFP (Colgin et al., 2009; Schomburg et al., 2014; Fernández-Ruiz et al., 2017), within and

across region cross-frequency coherence (e.g., Colgin et al., 2009; Kemere et al., 2013; Hsiao

et al., 2016), and cross-frequency coupling (e.g., Colgin et al., 2009; Belluscio et al., 2012).

While these are supporting pieces of data, they neither confirm or deny the presence of an

oscillation. Nevertheless, we have addressed each of these in the current manuscript. Notably,

rather than perform a second-order analysis of investigating either phase locking to LFP or

spike-LFP coherence, we simply sought to determine what frequencies are evident in the action

potentials, using Thomson multitaper decomposition on auto- and cross-correlograms (Leung

and Buzsáki, 1983). We did not observe any slow gamma modulation, but did observe multiple

harmonics of theta (**Fig. 9;** Sheremet et al., 2016). Therefore, a wide band filter of 25-55Hz will

most-likely result in a significant phase modulation of spike firing (e.g., Colgin et al., 2009;

Schomburg et al., 2014) because- as noted by Schomburg and colleagues (2014)- this region

covers the harmonic range. As pyramidal cells spike at theta frequency (and the first harmonic)

and the harmonics can extend as high as 48 Hz (Sheremet et al., 2016), then the broad filter of

25-55Hz will be harmonic dominated. Furthermore, we have replicated cross-regional

coherence, this time using velocity as a parameter, to investigate whether it is tenable to believe

a broad slow gamma band exists. Although prior research would suggest that the dentate

entrains other regions through slow gamma (Hsiao et al., 2016), our analyses here (**Fig. 10**) and

elsewhere (Sheremet et al., 2018b) reveal coherence up to the 40Hz harmonic of theta.

Furthermore, cross-correlation of power between the medial entorhinal cortex or dentate gyrus

and layers of CA1 fail to show any interactions between frequencies other than theta, its

harmonics, and a single 50-120 Hz gamma band (**Fig. 11**). Finally, we have addressed all forms

of cross-frequency coupling – phase-phase, phase-amplitude, and amplitude-amplitude –in

another manuscript (Sheremet et al., 2018b). Therefore, when considering both the primary and

secondary evidence supporting the existence of slow gamma, there appear to be fundamental,

critical shortcomings.

Of course, our observations do not cover the compendium of manuscripts that have

supported the existence of slow gamma. An attempt to refute them all may prove to be a

Sisyphean task. It is, however, worth noting that independent component analysis has been

suggested as another method that reveals slow gamma (see Supplemental methods of

Schomburg et al., 2014). Independent component analysis takes advantage of the conserved

anatomy in order to identify source specific, non-volume conducted components localized to the

layer. Notably, the range of slow gamma in Schomburg et al. (2014), 30-80 Hz (also used in

Fernández-Ruiz et al., 2017), significantly differed relative to the prior publications of Colgin et

al. (2009), 25-55Hz, and Belluscio et al. (2012), 30-50 Hz. The extended range of slow gamma

in these papers were based off of a gamma amplitude-theta frequency (GA-TF) comodulogram

and buttressed by the wavelet based Gamma amplitude – theta phase (GA-TP) modulation

plots (see figures 2 and 3 of Fernández-Ruiz et al., 2017). Although the correlation coefficients

of the spectrogram presented in the current manuscript (also see Sheremet et al., 2018b) stand

in contrast to the comodulogram of Schomburg et al. (2014), we cannot speak directly to these

results as we did not present data implementing their analytical approach. We can only suggest

caution in running a preprocessing algorithm that involves applying principle component

analysis and whitening prior to independent component analysis (see Supplemental methods of

Schomburg et al., 2014) as it moves further away from the collected data.

To our knowledge, all of the aforementioned spectral decompositions and secondary

analyses that report slow gamma fail to account for harmonics as suggested by Aru and

colleagues (Aru et al., 2014). Using bicoherence to control for harmonics reveals that the low

end of the spectrum is dominated by integers of theta, phase locked to the fundamental up to 48

Hz (Sheremet et al., 2016; Sheremet et al., 2018b; Sheremet et al., 2018a). From this analysis,

there is no reason to believe that an independent slow gamma oscillation exists in the normal

rat. However, our failure to observe this oscillation does not mean that the brain cannot venture

into a parameter space in which slow gamma is prominently detectable from noise. It is

therefore worth discussing what empirical data would be needed to support the assertion of

slow gamma. Control for theta harmonics using bicoherence analysis should be required. As the

argument has been made that slow gamma is coupled to theta, a strong interaction in the

bicoherence between slow gamma and theta would further enhance this claim. Notably, the

bicoherence analysis detects a strong coupling of the 50-120 Hz gamma to both theta and its

first harmonic (Sheremet et al., 2018b). It should be mentioned that "wavelet bicoherence"

analysis (Van Milligen et al., 1995) would suffer similar pitfalls to wavelet time-frequency

representation. Moreover, considering asymmetry alone (e.g., Amemiya and Redish, 2018) is

an insufficient control as oscillatory skew can also contribute to harmonics (Sheremet et al.,

2016). Furthermore, as discussed above, oscillatory identification is partially determined by a

deflection that significantly deviates from the "background" activity. Therefore, a simple,

unwhitened, log-log power spectral density with a peak in the 25-55 Hz band using the Fourier

transform would be indicative that there is a uniform signal that exceeds noise. Finally,

controlling for animal velocity when conducting these analyses should become common

practice. The secondary analyses should only be implemented once due diligence has been

employed to ensure that a signal exists.

Through this presentation, we believe that fundamental, critical analytical inconsistencies

are responsible for "slow gamma" detection that are instead a consequence of the theta

harmonics. Moving forward, vigilance is necessary to ensure that the analytical treatment is

"true to the essence of the biological process studied" or otherwise risk generating mistakes as

a consequence of inappropriate methods (Marder, 2015). While quantitative data analysis

reflecting what can be observed qualitatively is the first step toward a model, caution should be

taken prior to applying analytical techniques that incorporate specific assumptions about the

system without a physical model.

Appendix

Fourier and wavelet representation of deterministic time series

As mathematical, abstract transforms of functions defined on the real axis, both the Fourier and wavelet representations work fine, in the sense that they reconstruct the signal exactly (have inverses). In terms of applications to observational data, however, the two transforms were designed to meet different efficiency criteria.

The Fourier and wavelet analysis function on similar principles, decomposing the signal into "elementary" functions. However, the similarity ends here. In the Fourier transform case, the "elementary" are harmonic functions uniquely defined by their frequency; they form an orthogonal basis; hence the representation is unique and has a number of other convenient properties (e.g., conserves variance). In the wavelet transform case the "elementary" functions (wavelets)are a two-parameter (scale and position on the time axis) family of copies of a fixed shape, the mother wavelet. In contrast to the harmonic Fourier modes 1) wavelets are only required to have near-zero mean and be integrable in some way (fast enough decay at infinity) but are otherwise arbitrary; 2) wavelets do not form (in general) a basis (the representation is in general not unique); and 3) the result is a time-scale representation.

While the Fourier transform exists for a wide class of reasonably behaved functions and may be extended generalized functions. Its usefulness is illustrated by the Heisenberg uncertainty principle (see **Figs, 1 and 2**) which implies that a highly localized signal has a wide Fourier spectrum. For example, if the time signal is a narrow pulse, the Fourier representation will require many high-frequency components to construct the sharp time variation – hence the wide spectrum. This also implies that the interpretation of the spectrum in this case is difficult, because the frequency components are phase locked to create the time pulse, hence they are not independent oscillations. Therefore, the Fourier representation is best applied to wide-support time functions, i.e., functions having some sort of translational near-invariance in time will have (we'll call this provisionally "stationarity").

The wavelet transform analyzes signals by shifting in time bits of oscillations with

different scales (**see fig. 2**). This approach is clearly efficient for signals with intermittent bursts

of energy. For stationary (in the sense used above) signals, wavelets are inefficient because

they use a two-parameter space when only one is really needed (see the Fourier

decomposition). The decomposition also loses its intended meaning of identifying intermittent

bursts.

Other than paying attention to these elementary efficiencies, the choice of representation

(Fourier vs wavelet) for a given time series is arbitrary. There is, however, an elementary fallacy

of reasoning that is often encountered: while they are both equally applicable, the results are not

interchangeable. We stress that the wavelet ordering parameter is scale (the value of the

dilation parameter) and not frequency. While scales are often translated to frequencies for ease

of interpretation, one should not be confused: Wavelet "frequencies" are, strictly speaking, just

labels. Wavelet have a non-trivial frequency distribution of power, i.e., "comprise" an entire

range of (true) Fourier frequencies. Referring to them as if they had the Fourier meaning is

incorrect and may lead to erroneous conclusions.

Fourier and wavelet representations of stochastic processes

The concept of a stochastic process assumes that such time series are in fact random

"realizations" of a "virtual" process, and the goal of analyzing the realizations is to characterize

this virtual process, and not its individual realizations. For example, averaging a quantity

characterizing the stochastic process is a procedure that takes all possible realizations and

computes a representative value that characterizes the stochastic process and not individual

realizations. Such averaged quantities are called in practice "estimators", exactly because they

are assumed to converge to a well-defined value if the averaging is done over the entire

realization space. In practical applications, the stochastic process whose realizations (time

series) are observed is not entirely accessible, therefore the existence of a particular average

quantity for an arbitrary process. This implies that one does not have a rigorous characterization

of the properties of the stochastic process. This is, however, essential for interpreting the

observations and insuring that one does not elaborate on meaningless, at worst non-existent,

quantities. It is important to understand that just because a finite number of realizations always

yields an average does not necessarily imply that the stochastic average (over all realizations)

exists. Therefore, in practice, one is forced to assume a model for the stochastic process, which

should guide the effort to estimate its characteristics.

The dissimilarity of the two transforms becomes particularly acute when considering

observations as realizations of a stochastic process. For Fourier analysis, a stochastic process

model exists: it is the generalized harmonic process (Priestley, 1981; Percival and Walden,

1993), a zero-mean, variance-stationary process (variance per unit of time is conserved).

Without going into the details (e.g., Priestley, 1981; Percival and Walden, 1993; Papoulis and

Pillai, 2002) we state that if the process $x(t)$ is stochastically continuous and stationary, there

exists a zero-mean process $X(f)$ with orthogonal increments such that

802
$$x(t) = \int_{-\infty}^{\infty} e^{2\pi i f t} \, dX(f).$$

The existence of the spectral density of the process is guaranteed by the celebrated

Wiener-Khinchin theorem (Priestley, 1981), which states that the power spectral density of

process x is the Fourier transform of its auto-covariance function. It is important to note the

condition of orthogonality of increments: it means that the Fourier components of different

frequencies are uncorrelated. Therefore, the Fourier stochastic mode cannot have (does not

include) non-stationary realizations such as sharp waves.

As far as we are aware, there no widely-accepted stochastic-process model for transient

signals. therefore, it appears that it makes little sense to look for a stochastic scope of the

wavelet transform, as it is hard to imagine an overarching stochastic model for non-stationary

processes (although recent attempts, e.g., Antoniou and Gustafson, 1999, might prove this

argument wrong). While one is free to average whatever feature seems relevant, we do not in

fact know under what conditions a particular average exists.

This discussion should show that the Fourier and wavelet representations are not

interchangeable. For example, remapping a wavelet scalogram to frequencies and averaging

over time to estimate the distribution of the power over frequencies has at least two fundamental

problem: the frequency mapping is basically arbitrary, and the time average is not defined, if the

process is non-stationary. Alternatively, if the process is stationary, the Fourier transform is the

correct tool, because the wavelet distorts the distribution due to its peculiar shape of time-

frequency atoms.

A simple stationarity test

Remarkably, the simple idea that a variance-stationary generalized harmonic process should

have at most weakly-correlated frequency components suggests a simple test for stationarity.

The bicoherence of a stationary stochastic process should be weak (Elgar, 1987; Sheremet et

al., 2016; Kovach et al., 2018). The examples shown in figure 13 illustrates this property. The

stationary series, although weakly asymmetric (not entirely free of cross-spectrum correlation)

exhibits a bicoherence that is essentially statistically zero, with the exception of the harmonic

phase coupling. One could classify this series as matching the generalized harmonic stochastic

process. In contrast, the non-stationary example in figure 13 shows large areas of strong

coupling, suggesting that this should indeed be classified as non-stationary.

Figure 13: Examples of bicoherence estimates (c, d) for two LFP recordings (sample time series shown in panels a,b). Left: LM layer, active exploration at high speed motion; arrows mark the areas in the bicoherence map corresponding to theta/harmonics, and theta/gamma phase-coupling. Right: Rad layer, non-REM sleep; arrows mark the areas in the bicoherence map corresponding to the phase-coupling between Fourier components that assemble together into the solitary wave, and those that correspond to sharp wave and sharp-wave/ripples phase coupling.

References

Abry P, Gonçalves P, Flandrin P (1993) Wavelet-based spectral analysis of 1/f processes. In: Acoustics, Speech, and Signal Processing, 1993. ICASSP-93., 1993 IEEE International Conference on, pp 237-240: IEEE.

Ahmed OJ, Mehta MR (2012) Running speed alters the frequency of hippocampal gamma oscillations. J Neurosci 32:7373-7383.

Akam T, Kullmann DM (2014) Oscillatory multiplexing of population codes for selective communication in the mammalian brain. Nat Rev Neurosci 15:111-122.

Amemiya S, Redish AD (2018) Hippocampal Theta-Gamma Coupling Reflects State-Dependent Information Processing in Decision Making. Cell Rep 22:3328-3338.

Antoniou I, Gustafson K (1999) Wavelets and stochastic processes. Mathematics and Computers in Simulation 49:81-104.

Aru J, Priesemann V, Wibral M, Lana L, Pipa G, Singer W, Vicente R (2014) Untangling cross-frequency coupling in neuroscience. Curr Opin Neurobiol 31C:51-61.

Bagur S, Benchenane K (2018) The Theta Rhythm Mixes and Matches Gamma Oscillations Cycle by Cycle. Neuron 100:768-771.

Belluscio MA, Mizuseki K, Schmidt R, Kempter R, Buzsáki G (2012) Cross-frequency phase-phase coupling between θ and γ oscillations in the hippocampus. J Neurosci 32:423-435.

Bieri KW, Bobbitt KN, Colgin LL (2014) Slow and fast γ rhythms coordinate different spatial coding modes in hippocampal place cells. Neuron 82:670-681.

Bragin A, Jandó G, Nádasdy Z, Hetke J, Wise K, Buzsáki G (1995) Gamma (40-100 Hz) oscillation in the hippocampus of the behaving rat. J Neurosci 15:47-60.

Briggs WL (1995) The DFT: an owners' manual for the discrete Fourier transform: Siam.

Buzsaki G (2006) Rhythms of the Brain: Oxford University Press.

Buzsaki G, Leung LW, Vanderwolf CH (1983) Cellular bases of hippocampal EEG in the behaving rat. Brain Res 287:139-171.

Buzsaki G, Czopf J, Kondakor I, Kellenyi L (1986) Laminar distribution of hippocampal rhythmic slow activity (RSA) in the behaving rat: current-source density analysis, effects of urethane and atropine. Brain Res 365:125-137.

Buzsáki G (2005) Theta rhythm of navigation: link between path integration and landmark navigation, episodic and semantic memory. Hippocampus 15:827-840.

Buzsáki G, Schomburg EW (2015) What does gamma coherence tell us about inter-regional neural communication? Nat Neurosci 18:484-489.

Buzsáki G, Rappelsberger P, Kellényi L (1985) Depth profiles of hippocampal rhythmic slow activity ('theta rhythm') depend on behaviour. Electroencephalogr Clin Neurophysiol 61:77-88.

Buzsáki G, Anastassiou CA, Koch C (2012) The origin of extracellular fields and currents--EEG, ECoG, LFP and spikes. Nat Rev Neurosci 13:407-420.

Buzsáki G, Buhl DL, Harris KD, Csicsvari J, Czéh B, Morozov A (2003) Hippocampal network patterns of activity in the mouse. Neuroscience 116:201-211.

Canolty RT, Ganguly K, Kennerley SW, Cadieu CF, Koepsell K, Wallis JD, Carmena JM (2010) Oscillatory phase coupling coordinates anatomically dispersed functional cell assemblies. Proc Natl Acad Sci U S A 107:17356-17361.

Carr MF, Karlsson MP, Frank LM (2012) Transient slow gamma synchrony underlies hippocampal memory replay. Neuron 75:700-713.

Chen Z, Resnik E, McFarland JM, Sakmann B, Mehta MR (2011) Speed controls the amplitude and timing of the hippocampal gamma rhythm. PLoS One 6:e21408.

Chrobak JJ, Buzsáki G (1998) Gamma oscillations in the entorhinal cortex of the freely behaving rat. J
Neurosci 18:388-398.
Churchland MM et al. (2010) Stimulus onset quenches neural variability: a widespread cortical
phenomenon. Nat Neurosci 13:369-378.
Coenen AM (1975) Frequency analysis of rat hippocampal electrical activity. Physiol Behav 14:391-394.
Colgin LL (2012) Slow gamma takes the reins in replay. Neuron 75:549-550.
Colgin LL (2015) Do slow and fast gamma rhythms correspond to distinct functional states in the
hippocampal network? Brain Res 1621:309-315.
Colgin LL, Moser EI (2009) Hippocampal theta rhythms follow the beat of their own drum. Nat Neurosci
12:1483-1484.
Colgin LL, Denninger T, Fyhn M, Hafting T, Bonnevie T, Jensen O, Moser MB, Moser EI (2009) Frequency
of gamma oscillations routes flow of information in the hippocampus. Nature 462:353-357.
Czurkó A, Hirase H, Csicsvari J, Buzsáki G (1999) Sustained activation of hippocampal pyramidal cells by
'space clamping' in a running wheel. Eur J Neurosci 11:344-352.
Daubechies I (1988) Orthonormal bases of compactly supported wavelets. Communications on pure and
applied mathematics 41:909-996.
Daubechies I (1992) Ten lectures on wavelets: Siam.
Elgar S (1987) Relationships involving third moments and bispectra of a harmonic process. Acoustics,
Speech and Signal Processing, IEEE Transactions on 35:1725-1726.
Fernández-Ruiz A, Oliva A, Nagy GA, Maurer AP, Berényi A, Buzsáki G (2017) Entorhinal-CA3 Dual-Input
Control of Spike Timing in the Hippocampus by Theta-Gamma Coupling. Neuron 93:1213-
1226.e1215.
Gabor D (1946) Theory of communication. Part 1: The analysis of information. Journal of the Institution
of Electrical Engineers-Part III: Radio and Communication Engineering 93:429-441.
Geisler C, Robbe D, Zugaro M, Sirota A, Buzsáki G (2007) Hippocampal place cell assemblies are speed-
controlled oscillators. Proc Natl Acad Sci U S A 104:8149-8154.
Goupillaud P, Grossmann A, Morlet J (1984) Cycle-octave and related transforms in seismic signal
analysis. Geoexploration 23:85-102.
Green JD, Arduini AA (1954) Hippocampal electrical activity in arousal. J Neurophysiol 17:533-557.
Green JD, Machne X (1955) Unit activity of rabbit hippocampus. Am J Physiol 181:219-224.
Grossmann A, Morlet J (1984) Decomposition of Hardy functions into square integrable wavelets of
constant shape. SIAM journal on mathematical analysis 15:723-736.
Gu BM, van Rijn H, Meck WH (2015) Oscillatory multiplexing of neural population codes for interval
timing and working memory. Neurosci Biobehav Rev 48:160-185.
Harper RM (1971) Frequency changes in hippocampal electrical activity during movement and tonic
immobility. Physiol Behav 7:55-58.
Hsiao YT, Zheng C, Colgin LL (2016) Slow gamma rhythms in CA3 are entrained by slow gamma activity in
the dentate gyrus. J Neurophysiol 116:2594-2603.
Igarashi KM, Lu L, Colgin LL, Moser MB, Moser EI (2014) Coordination of entorhinal-hippocampal
ensemble activity during associative learning. Nature 510:143-147.
Jung R, Kornmüller A (1938) Eine Methodik der Ableitung lokalisierter Potentialschwankungen aus
subcorticalen Hirngebieten. European Archives of Psychiatry and Clinical Neuroscience 109:1-30.
Kemere C, Carr MF, Karlsson MP, Frank LM (2013) Rapid and continuous modulation of hippocampal
network state during exploration of new places. PLoS One 8:e73114.
Knight RT, Eichenbaum H (2013) Multiplexed memories: a view from human cortex. Nat Neurosci
16:257-258.
Kovach CK, Oya H, Kawasaki H (2018) The bispectrum and its relationship to phase-amplitude coupling.
Neuroimage 173:518-539.

Lasztóczi B, Klausberger T (2016) Hippocampal Place Cells Couple to Three Different Gamma Oscillations
during Place Field Traversal. Neuron 91:34-40.
Leung LS (1992) Fast (beta) rhythms in the hippocampus: a review. Hippocampus 2:93-98.
Leung LW, Buzsáki G (1983) Spectral analysis of hippocampal unit train in relation to hippocampal EEG.
Electroencephalogr Clin Neurophysiol 56:668-671.
Leung LW, Lopes da Silva FH, Wadman WJ (1982) Spectral characteristics of the hippocampal EEG in the
freely moving rat. Electroencephalogr Clin Neurophysiol 54:203-219.
Lighthill MJ (1958) An introduction to Fourier analysis and generalised functions: Cambridge University
Press.
Lisman J (2005) The theta/gamma discrete phase code occuring during the hippocampal phase
precession may be a more general brain coding scheme. Hippocampus 15:913-922.
Lopes-Dos-Santos V, van de Ven GM, Morley A, Trouche S, Campo-Urriza N, Dupret D (2018) Parsing
Hippocampal Theta Oscillations by Nested Spectral Components during Spatial Exploration and
Memory-Guided Behavior. Neuron 100:940-952.e947.
Mallat S (1999) A wavelet tour of signal processing: Elsevier.
Marder E (2015) Understanding brains: details, intuition, and big data. PLoS Biol 13:e1002147.
Masimore B, Kakalios J, Redish AD (2004) Measuring fundamental frequencies in local field potentials. J
Neurosci Methods 138:97-105.
Masimore B, Schmitzer-Torbert NC, Kakalios J, Redish AD (2005) Transient striatal gamma local field
potentials signal movement initiation in rats. Neuroreport 16:2021-2024.
Maurer AP, Vanrhoads SR, Sutherland GR, Lipa P, McNaughton BL (2005) Self-motion and the origin of
differential spatial scaling along the septo-temporal axis of the hippocampus. Hippocampus
15:841-852.
Maurer AP, Burke SN, Lipa P, Skaggs WE, Barnes CA (2012) Greater running speeds result in altered
hippocampal phase sequence dynamics. Hippocampus 22:737-747.
McLelland D, VanRullen R (2016) Theta-Gamma Coding Meets Communication-through-Coherence:
Neuronal Oscillatory Multiplexing Theories Reconciled. PLoS Comput Biol 12:e1005162.
Michaels TI, Long LL, Stevenson IH, Chrobak JJ, Chen CA (2018) Effects of chronic ketamine on
hippocampal cross-frequency coupling: implications for schizophrenia pathophysiology. Eur J
Neurosci.
Mitzdorf U (1985) Current source-density method and application in cat cerebral cortex: investigation of
evoked potentials and EEG phenomena. Physiol Rev 65:37-100.
Mizuseki K, Diba K, Pastalkova E, Teeters J, Sirota A, Buzsáki G (2014) Neurosharing: large-scale data sets
(spike, LFP) recorded from the hippocampal-entorhinal system in behaving rats. F1000Res 3:98.
Montgomery SM, Betancur MI, Buzsáki G (2009) Behavior-dependent coordination of multiple theta
dipoles in the hippocampus. J Neurosci 29:1381-1394.
Newman EL, Gillet SN, Climer JR, Hasselmo ME (2013) Cholinergic blockade reduces theta-gamma phase
amplitude coupling and speed modulation of theta frequency consistent with behavioral effects
on encoding. J Neurosci 33:19635-19646.
Ning T, Bronzino JD (1993) Nonlinear analysis of the hippocampal subfields of CA1 and the dentate
gyrus. IEEE Trans Biomed Eng 40:870-876.
Papoulis A, Pillai SU (2002) Probability, random variables, and stochastic processes: Tata McGraw-Hill
Education.
Pastalkova E, Wang Y, Mizuseki K, Buzsáki G (2015) Simultaneous extracellular recordings from left and
right hippocampal areas CA1 and right entorhinal cortex from a rat performing a left / right
alternation task and other behaviors. . In: http://dx.doi.org/10.6080/K0KS6PHF: CRCNS.org.
Penttonen M, Kamondi A, Acsády L, Buzsáki G (1998) Gamma frequency oscillation in the hippocampus
of the rat: intracellular analysis in vivo. Eur J Neurosci 10:718-728.

Percival DB, Walden AT (1993) Spectral analysis for physical applications: cambridge university press.
Priestley MB (1981) Spectral analysis and time series.
Quilichini P, Sirota A, Buzsáki G (2010) Intrinsic circuit organization and theta-gamma oscillation
dynamics in the entorhinal cortex of the rat. J Neurosci 30:11128-11142.
Rangel LM, Chiba AA, Quinn LK (2015) Theta and beta oscillatory dynamics in the dentate gyrus reveal a
shift in network processing state during cue encounters. Front Syst Neurosci 9:96.
Rangel LM, Rueckemann JW, Riviere PD, Keefe KR, Porter BS, Heimbuch IS, Budlong CH, Eichenbaum H
(2016) Rhythmic coordination of hippocampal neurons during associative memory processing.
Elife 5:e09849.
Rappelsberger P, Pockberger H, Petsche H (1981) Current source density analysis: methods and
application to simultaneously recorded field potentials of the rabbit's visual cortex. Pflugers
Arch 389:159-170.
Roads C (2004) Microsound: MIT press.
Scheffer-Teixeira R, Tort AB (2016) On cross-frequency phase-phase coupling between theta and gamma
oscillations in the hippocampus. Elife 5.
Schomburg EW, Fernández-Ruiz A, Mizuseki K, Berényi A, Anastassiou CA, Koch C, Buzsáki G (2014)
Theta Phase Segregation of Input-Specific Gamma Patterns in Entorhinal-Hippocampal
Networks. Neuron.
Schwartz L (1950) Theorie desDistributions. Tomes I, II, Hermann Paris 1951.
Sheremet A, Burke SN, Maurer AP (2016) Movement Enhances the Nonlinearity of Hippocampal Theta. J
Neurosci 36:4218-4230.
Sheremet A, Qin Y, Kennedy JP, Zhou Y, Maurer AP (2018a) Wave turbulence and energy cascade in the
hippocampus. Frontiers in Systems Neuroscience 12:62.
Sheremet A, Kennedy JP, Qin Y, Zhou Y, Lovett SD, Burke SN, Maurer AP (2018b) Theta-Gamma Cascades
and Running Speed. J Neurophysiol.
Shirvalkar PR, Rapp PR, Shapiro ML (2010) Bidirectional changes to hippocampal theta-gamma
comodulation predict memory for recent spatial episodes. Proc Natl Acad Sci U S A 107:7054-
7059.
Siegel M, Donner TH, Engel AK (2012) Spectral fingerprints of large-scale neuronal interactions. Nat Rev
Neurosci 13:121-134.
Skaggs WE, McNaughton BL, Wilson MA, Barnes CA (1996) Theta phase precession in hippocampal
neuronal populations and the compression of temporal sequences. Hippocampus 6:149-172.
Strang G (2006) Linear algebra and its applications: Cengage learning.
Strichartz RS (2003) A guide to distribution theory and Fourier transforms: World Scientific Publishing
Company.
Stumpf C (1965) Drug action on the electrical activity of the hippocampus. Int Rev Neurobiol 8:77-138.
Takahashi M, Nishida H, Redish AD, Lauwereyns J (2014) Theta phase shift in spike timing and
modulation of gamma oscillation: a dynamic code for spatial alternation during fixation in rat
hippocampal area CA1. J Neurophysiol 111:1601-1614.
Terrazas A, Krause M, Lipa P, Gothard KM, Barnes CA, McNaughton BL (2005) Self-motion and the
hippocampal spatial metric. J Neurosci 25:8085-8096.
Trimper JB, Stefanescu RA, Manns JR (2014) Recognition memory and theta-gamma interactions in the
hippocampus. Hippocampus 24:341-353.
Van Milligen BP, Sanchez E, Estrada T, Hidalgo C, Brañas B, Carreras B, Garcia L (1995) Wavelet
bicoherence: a new turbulence analysis tool. Physics of Plasmas 2:3017-3032.
Vanderwolf CH (1969) Hippocampal electrical activity and voluntary movement in the rat.
Electroencephalogr Clin Neurophysiol 26:407-418.

Vanderwolf CH, Heron W (1964) ELECTROENCEPHALOGRAPHIC WAVES WITH VOLUNTARY MOVEMENT.
1030   STUDY IN THE RAT. Arch Neurol 11:379-384.
1031   Vladimirov VS (2002) Methods of the theory of generalized functions: CRC Press.
1032   Watrous AJ, Ekstrom AD (2014) The spectro-contextual encoding and retrieval theory of episodic
1033   memory. Front Hum Neurosci 8:75.
1034   Watrous AJ, Tandon N, Conner CR, Pieters T, Ekstrom AD (2013) Frequency-specific network connectivity
1035   increases underlie accurate spatiotemporal memory retrieval. Nat Neurosci 16:349-356.
1036   Welch P (1967) The use of fast Fourier transform for the estimation of power spectra: a method based
1037   on time averaging over short, modified periodograms. IEEE Transactions on audio and
1038   electroacoustics 15:70-73.
1039   Wu Z, Huang NE (2009) Ensemble empirical mode decomposition: a noise-assisted data analysis method.
1040   Advances in adaptive data analysis 1:1-41.
1041   Yamamoto J, Suh J, Takeuchi D, Tonegawa S (2014) Successful execution of working memory linked to
1042   synchronized high-frequency gamma oscillations. Cell 157:845-857.
1043   Zheng C, Bieri KW, Trettel SG, Colgin LL (2015) The relationship between gamma frequency and running
1044   speed differs for slow and fast gamma rhythms in freely behaving rats. Hippocampus 25:924-
1045   938.
1046   Zheng C, Bieri KW, Hsiao YT, Colgin LL (2016) Spatial Sequence Coding Differs during Slow and Fast
1047   Gamma Rhythms in the Hippocampus. Neuron 89:398-408.

1048