Microsecond Interaural Time Difference Discrimination Restored by Cochlear Implants After Neonatal Deafness

Nicole Rosskothen-Kuhl[1,2*#], Alexa N Buck[1#], Kongyan Li[1], Jan W H Schnupp[1*]

1) Department of Biomedical Sciences, City University of Hong Kong, Hong Kong (SAR China);

2) Neurobiological Research Laboratory, Section for Clinical and Experimental Otology, University Medical Center Freiburg, Freiburg, Germany

*Correspondence: nicole.rosskothen@uniklinik-freiburg.de; wschnupp@cityu.edu.hk

#: divided first author ship

Contact Info

Corresponding authors:

Dr. Nicole Rosskothen-Kuhl

Neurobiological Research Laboratory,

Section for Clinical and Experimental Otology,

University Medical Center Freiburg,

Killianst. 5, 79106 Freiburg i. Br., Germany

Phone: +49 761 27042650

nicole.rosskothen@uniklinik-freiburg.de

Prof. Dr. Jan W H Schnupp

Department of Biomedical Sciences

City University of Hong Kong

31 To Yuen Street

Kowloon, Hong Kong

wschnupp@cityu.edu.hk

29 Keywords

30 Deafness; prosthetics; cochlear implant; binaural hearing; interaural time difference;

31 psychoacoustics; hearing experience; inferior colliculus

Abstract

Cochlear implants (CIs) can restore a high degree of functional hearing in deaf patients however spatial hearing remains poor, with many early deaf CI users reported to have no measurable sensitivity to interaural time differences (ITDs) at all. Deprivation of binaural experience during an early critical period is often blamed for this shortcoming. However, we show that neonatally deafened rats provided with precisely synchronized CI stimulation in adulthood can be trained to localize ITDs with essentially normal behavioral thresholds near 50 μs. Furthermore, neonatally deaf rats show high physiological sensitivity to ITDs immediately after binaural implantation in adulthood. The fact that our neonatally deaf CI rats achieved very good behavioral ITD thresholds while prelingually deaf human CI patients usually fail to develop a useful sensitivity to ITD raises urgent questions about whether shortcomings in technology or treatment may be behind the usually poor binaural outcomes for current binaural CI patients.

For people with severe to profound sensorineural hearing loss, cochlear implants (CIs) can be enormously beneficial routinely allowing near normal spoken language acquisition particularly when CI implantation takes place early in life [1]. Nevertheless the performance of CI users remains variable, and falls short of natural hearing.

Good speech understanding with competing sound sources requires the ability to separate speech from background. This is aided by "spatial release from masking", which relies on the brain's ability to process binaural spatial cues, including interaural level and time differences (ILDs & ITDs) [2]. Bilateral cochlear implantation is becoming commonplace to provide benefits of binaural hearing to the deaf [3-5], but binaural CI recipients perform poorly in sound localization and auditory scene analysis tasks, particularly when multiple sound sources are present [6,7]. The parameters that would allow CI patients to derive maximum benefits from binaural spatial cues are only partially understood. A number of technical problems (see [8], chapter 8) limit the fidelity with which CIs can encode ITDs in particular. Contemporary CI speech processors were originally designed for monaural, not binaural, hearing, and this likely contributes to the observed deficits in bilateral CI users [3]. Standard CI processors provide pulsatile stimulation which is not locked to the temporal fine structure of incoming sounds, and the timing of electrical pulses is not synchronized between both ears, making these devices incapable of encoding the temporal fine structure and ITDs with the required resolution of a few tens of μs. While normal hearing human listeners may be able to detect ITDs as small as 10 μs [9], ITD sensitivity of CI patients is poor or completely missing [3,5-7,10-12].

Whether CI patients can detect ITDs at all depends largely on their history: Prelingually deaf CI users invariably exhibit poor or no ITD sensitivity at all (rare star performers at best achieving thresholds of a few hundred μs), but many postlingually deaf CI users show at least some degree of ITD sensitivity [4,5,11-15]. This led to the suggestion that early auditory deprivation during a sensitive period may prevent the development of ITD

sensitivity irrecoverably [1,15,16]. If this hypothesis is correct, then developing CI

processors with better ITD coding might not benefit patients with hearing loss early in life

because, by the time of implantation these patients would already have missed out on the

formative sensory input needed to develop the brain circuitry required for binaural

processing with microsecond precision. Various lines of evidence make this critical period

hypothesis plausible, including immunohistochemical studies which have shown degraded

tonotopic organization [17,18] and changes in stimulation-induced molecular,

morphological, and electrophysiological properties of the auditory pathway of neonatally

deafened (ND) CI-rats [17-21]. Additional studies demonstrate that abnormal sensory input

during early development can alter ITD tuning curves in key brainstem nuclei of gerbils

[22,23].

However, the "critical period hypothesis" of poor ITD sensitivity in CI patients has not been

rigorously tested, and it is possible that the ND auditory pathway could retain an innate

ability to encode ITD, which may then only be lost as a result of maladaptive plasticity after

a period of binaural CI stimulation which conveys no useful ITD information. These

possibilities cannot be distinguished based on clinical data, as there are no binaural CI

processors in clinical use capable of encoding microsecond ITDs effectively. Thus, animal

experimentation is needed, in a first instance, to examine how much functional ITD

sensitivity can be achieved through bilaterally synchronized CI stimulation in a mature ND

animal. Previous animal studies investigating binaural sensitivity after early deafness have

been limited to acute electrophysiological experiments on cats and rabbits. These studies

have reported reduced ITD sensitivity in the inferior colliculus (IC) [24-27] and auditory

cortex (AC) [28,29] compared to hearing experienced animals. There have been no

previous attempts to train ND animals to discriminate sub-millisecond ITDs across the

physiological range delivered with CIs fitted in adulthood. Here, we show that cohorts of

ND rats which received synchronized bilateral CI stimulation in young adulthood not only

exhibit a great deal of physiological ITD sensitivity in their IC straight after implantation but they can also be trained easily and quickly to lateralize ITDs behaviorally, achieving thresholds as low as ~50 μs, comparable to their normal hearing (NH) litter mates.

Results

Early deaf CI rats discriminate ITD as accurately as their normally hearing litter mates.

To test whether ND rats can learn to discriminate ITDs of CI stimuli, we trained five ND rats who received chronic bilateral CIs in young adulthood (postnatal weeks 10-14) in a simple two-alternative forced choice (2AFC) ITD lateralization task, and we compared their performance against behavioral data from five age-matched NH rats trained to discriminate the ITDs of acoustic pulse trains [30]. Animals initiated trials by licking a center "start spout", and responded to 200 ms long 50 Hz binaural pulse trains by licking either a left or a right "response spout" to receive drinking water as positive reinforcement (Figs. S2a, S3b). Which response spout would give water was indicated by the ITD of the stimulus. We used pulses of identical amplitude in each ear, so that systematic ITD differences were the only reliable cue available (Figs. S2c-d; S3f). ND rats were stimulated with biphasic electrical pulse trains delivered through chronic CIs, NH rats received acoustic pulse trains through near-field sound tubes positioned next to each ear when the animal was at the start spout (Fig. S3a). During testing, stimulus ITDs varied randomly. The behavioural data (Fig. 1) were collected over a testing period of around 14 days. For CI rats, the initial lateralization training started usually one day after CI implantation. On average, rats were trained for maximum eight days before we started to test them on ITD sensitivity. The behavioral performance of each rat is shown in Figure 1, using light blue for NH (a-e) and dark blue for ND (f-j) animals. Figure 1 clearly demonstrates that all rats, whether NH or ND with CIs, were capable of lateralizing ITDs. As might be expected, the

behavioral sensitivity varied from animal to animal. To quantify the behavioral ITD

sensitivity of each rat we fitted psychometric curves (see Methods, red lines in Fig. 1) to

the raw data and calculated the slope of that curve at ITD=0. Figure 1k summarizes these

slopes for NH (light blue) and ND CI (dark blue) animals. The slopes for both groups fell

within the same range. Remarkably, the observed mean sensitivity for the ND animals

(0.487 %/μs) is only about 20% worse than that of the NH (0.657 %/μs). Furthermore, the

differences in means between experimental groups (0.17 %/μs) were so much smaller

than the animal-to-animal variance (~0.73 %^{2}/μs^2) that prohibitively large cohorts of

animals would be required to have any reasonable prospect of finding a significant

difference. Similarly, both cohorts showed similar 75% correct lateralization thresholds

(median NH: 41.5 μs; ND: 54.8 μs; mean NH: 79.9 μs; ND: 63.5 μs). Remarkably, the ITD

thresholds of our ND CI rats are thus orders of magnitude better than those reported for

prelingually deaf human CI patients, who usually have ITD thresholds too large to

measure, often in excess of 3000 μs [5,31]. Indeed, their thresholds are not dissimilar from

the approx. 10-60 μs range of 75% correct ITD discrimination thresholds reported for

normal human subjects tested with noise bursts [32], and pure tones [9], or the ≈ 40 μs

thresholds reported for normally hearing ferrets tested with noise bursts [33].

Figure 1: Early deaf CI rats discriminate ITD as accurately as their normally hearing litter mates. **a-j** ITD psychometric curves of normal hearing (**a-e**) and neonatally deafened CI rats (**f-j**). Panel titles show corresponding animal IDs. Y-axis: proportion of responses to the right-hand side. X-axis: Stimulus ITD in ms, with negative values indicating left ear leading. Blue dots: observed proportions of "right" responses for the stimulus ITD given by the x-coordinate. Number fractions shown above or below each dot indicate the absolute number of trials and "right" responses for corresponding ITDs. Blue error bars show Wilson score 95% confidence intervals for the underlying proportion "right" judgments. Red lines show sigmoid psychometric curves fitted to the blue data using maximum likelihood. Green dashed lines show slopes of psychometric curves at x=0. Slopes serve to quantify the behavioral sensitivity of the animal to ITD. Panel **k** summarizes the ITD sensitivities (psychometric slopes) across the individual animal data shown in **a-j** in units of % change in animal's' "right" judgments per μs change in ITD.

Varying degrees and types of ITD tuning are pervasive in the neural responses in the IC of ND rats immediately after adult cochlear implantation.

To investigate the amount of physiological ITD sensitivity present in the hearing inexperienced rat brain, we recorded responses of n=1140 multi-units in the IC of four young adult ND rats (Fig. 2, left) to isolated, bilateral CI pulse stimuli with ITDs varying randomly over a ±160 μs range (ca 123% of the rat's physiological range [34]). For comparison, we also recorded responses of n=1312 IC multi-units in four age-matched NH rats (Fig. 2, right), using identical stimulation. For both cohorts, the stimuli were again biphasic current pulses of identical amplitude in each ear, so that systematic differences in responses can only be attributed to ITD sensitivity (see Fig. S2c-d). Responses of IC

neurons were detected for currents as low as 100 µA. Figure 2 shows a selection of

responses as raster plots and corresponding ITD tuning curves for both cohorts (Fig. 2,

#1-8).

Both for the ND and the NH animals, the manner in which varying ITD changed neural

discharge patterns varied from one recording site to the next. But the extent to which

discharge patterns depend on stimulus ITD is not obviously very different in the ND and

the NH examples shown. While many multi-units showed typical short-latency onset

responses to the stimulus with varying response amplitudes (Fig. 2, #1, #3, #6, #7), some

showed sustained, but still clearly tuned, responses extending for up to 80 ms or longer

post-stimulus (Fig. 2, #4). The shapes of ITD tuning curves we observed in rat IC (Fig. 2)

resembled mostly the "peak", "monotonic sigmoid", "trough", and "multi-peak" shapes

previously described in the IC of cats [35].

Figure 2: IC neurons of ND rats were ITD sensitive immediately following adult cochlear

implantation. Examples of ITD tuning curves of neonatally deafened (ND) rats (red, left)

and normal hearing (NH) rats (blue, right) with varying degrees and types of ITD

sensitivity. Dot raster plots are shown next to corresponding ITD tuning curves. The multi-

units shown were selected to illustrate some of the variety of ITD tuning curve depths and

types observed. In the raster plots, each blue dot shows one spike. Alternating white and

green bands show responses to n=30 repeats at each ITD shown. Tuning curve response

amplitudes are baseline corrected and normalized relative to the maximum of the mean

response across all trials, during a period of 3-80 ms post stimulus onset. Error bars show

SEM. Above each sub-panel we show signal-to-noise (SNR) values to quantify ITD tuning.

Panels are arranged top to bottom by increasing SNR. ITD>0: ipsilateral ear leading;

ITD<0: contralateral ear leading.

To quantify how strongly the neural responses recorded at any one site depended on

stimulus ITD, a "signal-to-noise ratio" (SNR) value was calculated as described in [24]. It

quantifies the proportion of response variance that can be accounted for by stimulus ITD

(see Methods). Each sub-panel of Figure 2 indicates SNR values obtained for the

corresponding multi-unit, while Figure 3 shows the distributions of SNR values for both ND

(dark red) and NH cohorts (light red). Figure 3 also shows the SNR values reported by

Hancock et al. [24] for the IC of congenitally deaf (dark blue) and hearing experienced

(light blue) cats. When comparing the distributions shown, it is important to be aware that

there are significant methodological, as well as species, differences between our study

and the study that produced the cat data shown in [24], so the cross-species comparison

in particular must be done with care. Nevertheless, the distributions clearly show that ITD

SNRs in our ND and NH rats are broadly similar, and also broadly in line with the values

reported by others using similar methodologies. It is noticeable, and perhaps surprising,

that the proportion of multi-units with relatively large SNRs values (substantial ITD tuning)

is if anything slightly higher among the ND rats compared to the NH rats, and the median

SNR value for ND rat IC multi-units (0.37) was in fact larger than that observed in NH rats

(0.25). The proportion of rat multi-units which showed statistically significant ITD tuning

($p \leq 0.01$), as determined by ANOVA (see Methods), was also similarly very large in both

ND (1041/1140 ≈ 91%) and NH CI-stimulated rats (1154/1312 ≈ 88%). Thus, for our rats

which were kanamycin deafened before the onset of hearing, a lack of early auditory

experience did not produce a measurable decline in overall sensitivity of IC neurons to the

ITD of CI stimulus pulses. This is perhaps unexpected given that previous studies

comparing ITD tuning in the IC of congenitally deaf white cats and with that in wild type

cats did report noticeably worse ITD tuning in the congenitally deaf cats [26].

Nevertheless, the results in Figures 2 and 3 clearly show that many IC neurons in the

inexperienced, adult midbrain of ND rats are quite sensitive to changes in ITD of CI pulse

stimuli by just a few tens of μs, and our behavioral experiments showed that ND rats (Fig.

1, f-j) can readily learn to use this neural sensitivity to perform behavioral ITD

discrimination with an accuracy similar to that seen in their NH litter mates (Fig. 1, a-e).

Figure 3: IC multi-units with good ITD tuning, as measured by high signal-to-noise ratio
(SNR) values, are not less common in ND than in NH rats. Bar chart shows distributions of
ITD SNR values for ICs multi-units of ND (red) and NH (light red) rats. SNR value
distributions for IC single unit data recorded by Hancock et al. [24] for congenitally deaf
(dark blue) and hearing experienced cats (light blue) are also shown for comparison.

Discussion

This study is the first demonstration that, at least in rats, severely degraded auditory

experience in early development does not inevitably lead to impaired binaural time

processing in adulthood. In fact, the ITD thresholds of our ND rats (≈ 50 μs) were as good

as the ITD thresholds of NH rats [30], and many times better than those typically reported

for early deaf human CI patients with thresholds often too large to measure [5,14,30,31].

The surprisingly good performance exhibited by our ND animals raises the important

question of whether early deaf human CI patients might perhaps also be able to achieve

near normal ITD sensitivity if supplied with better binaural CI stimulation from the

beginning of implantation. But before we consider translational questions that might be raised by our results, we should address two aspects of this study which colleagues may find surprising:

Firstly, some studies deemed rats to be generally poor at processing ITDs [36,37]. However, the only previous rat behavioral study outside of our lab tested interaural phase sensitivity only of relatively low frequency tones. We focused on broad-band acoustic or electrical pulse stimuli which provide plenty of "onset" and "envelope" ITDs, and which are processed well even at high carrier frequencies [38,39]. That may also explain why our CI rats showed good ITD sensitivity even though our CIs targeted the cochleas' mid-frequency region, and not the apical region associated with low frequency hearing. Recent studies in CI patients with late deafness have shown that ITDs delivered to mid and high-frequency cochlear regions can be detected behaviorally [5,40].

Secondly, electrophysiological studies on congenitally deaf CI cats reported a substantially reduced ITD sensitivity relative to wild type, hearing experienced cats [24,28,29]. These studies recorded neural tuning high up in the auditory pathway (AC and IC), so one cannot be certain whether the reduced sensitivity reflects a fundamental degradation of ITD processing in the olivary nuclei, or merely poor maturation of connections to higher order areas, which may be reversed with experience and training. In the IC of our ND rats we found significant ITD sensitivity in 91% of recordings sites, compared to only 48% reported for congenitally deaf cats [24] or 62% for early deaf rabbits [27]. The proportion of ITD sensitive sites in ND rats is thus more similar to proportions in adult deafened CI-stimulated cats (84%-86%; [24,35], rabbits (~75%; [27,41]) or gerbils (~74%; [42]) and is comparable with our own NH rats (88%). Figure 3 suggests that the ITD SNR seen in our ND and NH CI-rats fall in a similar range of the ITD SNRs previously reported for congenitally deaf and hearing experienced CI-cats [24]. While for cats, the proportion of IC multi-units with large ITD SNR values appears to be reduced in animals lacking early

auditory experience, the same does not appear to be the case in our rats. Whether these

quantitative differences in physiological ITD sensitivity are due to methodological and/or

species differences is not determinable, but we believe that these apparent differences are

ultimately unlikely to be important, because even the congenitally deaf cats still have a

decent number of IC units showing fairly large amounts of ITD sensitivity. In fact, more

than 20% of the congenitally deaf cat IC units have SNR values of 0.5 or higher, which

indicates really rather good ITD sensitivity. It is important to remember that it is essentially

unknown how much ITD tuning in the IC or AC is necessary, or whether this is species

specific, to make behavioral ITD discrimination thresholds of ≈ 50 μs possible, but multi-

units such as #3 and #4 shown in Figure 2 change their firing rates substantially when

ITDs change by only a few tens of microseconds, and these multi-units have SNRs that

are not outside the range reported for congenital cats. This level of physiological sensitivity

probably ought to be sufficient to enable quite good behavioral ITD discrimination

performance if only these animals could be trained and tested on an appropriate task.

Thus, in our opinion, any previously reported reductions in physiological ITD sensitivity

seen in the IC [27,41] or AC [28,29] of early deaf animals simply does not seem nearly

large enough to fully explain the extremely poor behavioral ITD thresholds seen in most

early deaf humans and the observation that the physiological ITD sensitivity in our ND rats

is comparable to that in NH animals [30] emphasizes the existence of other causes.

Consequently, why in congenitally deaf cats there appears to be a relatively modest

reduction in neural ITD sensitivity while in ND rats that appears not to be the case is not a

pressing question, given that the available evidence suggests that both have quite a lot of

innate or residual ITD sensitivity in their midbrains, and consequently ought to be able to

learn to make use of that binaural cue. Thus, our finding of apparently normal behavioral

ITD sensitivity in ND CI-rats may appear surprising, but it does not contradict previous

studies [24,26-29].

27   14

The most striking difference between our results and other previously published work

remains the vastly better behavioral ITD discrimination in ND CI rats compared to that of

early deaf CI patients [5,14,15]. Previous authors have proposed that the very poor

performance seen in these patients may be due to "factors such as auditory deprivation, in

particular, lack of early exposure to consistent timing differences between the ears" [5].

However, a lack of early exposure did not prevent our ND rats from achieving very good

ITD discrimination performance. Furthermore, our rats were neonatally deafened and

implanted with CI in early adulthood thus not only lacking auditory experience during a so

called 'critical period' but also having prolonged deprivation. This is comparable with

prelingually deafened CI users who receive CIs as adults. However, Litovsky et al. [11]

demonstrated that this cohort too had worse ITD performance as compared with adult-

onset deafened CI users. Admittedly, there may be species differences at play here. Our

ND rats were implanted as young adults, and were severely deprived of auditory input

throughout their childhood, but humans mature much more slowly, so even patients

implanted at a very young age will have suffered auditory deprivation for a substantially

longer absolute time period than our rats. Nevertheless, our results raise the possibility

that the poor ITD sensitivity of early deaf patients may perhaps not be caused by the "lack

of exposure to consistent timing differences" and other factors might be to blame, such as

the prolonged exposure to entirely inconsistent ITDs delivered by current clinical CI

processors, which do not synchronize pulses between ears. This argument is supported by

Zheng et al. [43] who found that CI implanted children with bilateral experience (>4 years)

still show a higher percentage of errors than age-matched NH peers and Litovsky and

Gordon [15] describe that "even the bilateral CI users who have had >6 years of

experience listening with their CIs did not perform as well as the children with NH".

Additionally, most binaural patients receive their CIs sequentially, and their initial,

potentially formative, auditory experience is monaural. In contrast, our rats received highly

precise and informative ITDs right from the start.

29   15

Developmental studies in ferrets have shown that the formation of afferent synapses to

medial superior olive, one of the main brainstem nuclei for ITD processing, is essentially

complete before the onset of hearing [44]. In mice, the highly specialized calyx of held

synapses which are thought to play key roles in relaying precisely timed information in the

binaural circuitry have been shown to mature before the onset of hearing [45]. In gerbils,

key parts of the binaural ITD processing circuitry in the auditory brainstem will fail to

mature when driven with strong, uninformative omnidirectional white noise stimulation

during a critical period [22,33,46-48], but no studies have demonstrated that critical

periods in the ITD pathways will irrevocably close if sensory input is simply absent. In fact

Tirko and Ryugo [49] show that inhibitory pathways in the medial superior olive, which are

thought to be essential for ITD encoding [50], are significantly reduced in congenitally deaf

cats at postnatal day 90, compared to normal hearing peers, and can be fully restored with

the advent of CI stimulation after only 3 months. These data are therefore not incompatible

with our hypothesis that inappropriate input, rather than its absence, may cause the loss of

ITD sensitivity in early deaf CI users.

It is well known that the normal auditory system not only combines ITD information with

ILD and monaural spectral cues to localize sounds in space, it also adapts strongly to

changes in these cues, and can re-weight them depending on their reliability [29,51-53].

Current CI processors produce pulsatile stimulation based on fixed rate interleaved

sampling, which is neither synced to stimulus fine structure nor synchronized between

ears. Consequently, they only ever provide uninformative ITDs to the children using them.

Perhaps brainstem circuits of children fitted with conventional binaural CIs simply "learn" to

ignore unhelpful inputs which would be adaptive to them given that no useful information

comes from the ITDs received. In contrast, precise ITD cues were essentially the only form

of useful auditory input that our ND CI rats experienced, and they quickly learned to use

them. Thus, our data raise the possibility that the mammalian auditory system may

develop ITD sensitivity in the absence of early sensory input, and that this sensitivity is

then either refined or lost depending on how informative binaural input turns out to be. The

inability of early deaf CI patients to use ITDs may thus be somewhat similar to conditions

such as amblyopia or failures of stereoscopic depth vision development, pathologies which

are caused more by unbalanced or inappropriate inputs than by a lack of sensory

experience [54]. For the visual system, it has been shown that orientation selective

neuronal responses exist at eye-opening and thus are established without visual input [55].

If this hypothesis is correct, then it may be possible to "protect" ITD sensitivity in young

binaural CI users by exposing them to regular periods of precise ITD information from the

beginning of binaural stimulation. Whether CI patients are able to recover normal ITD

sensitivity much later if rehabilitated with useful ITDs for prolonged periods, or whether

their ability to process microsecond ITDs atrophies irreversibly, is unknown.

While the interpretations of our findings would lead us to argue that binaural CI processing

strategies may need to change to make microsecond ITD information available to CI

patients, one must nevertheless acknowledge the difficulty in changing established CI

processing strategies. The continuous interleaved sampling (CIS) paradigm [56] from

which most processor algorithms are derived, times the stimulus pulses so that only one

electrode channel delivers a pulse at any one time. This is thought to minimize cross-

channel interactions due to "current spread" which might compromise the already quite

limited tonotopic place coding of CIs. Additionally, CI processors run at high pulse rates

(≥ 900 Hz), which seems necessary to encode sufficient amplitude modulations (AM) for

speech recognition [57]. However, ITD discrimination deteriorates when pulse rates

exceeded a few hundred Hz in humans [58,59] and animals [41]. This is likely related to

the observation that the ability of superior olivary neurons to encode envelope ITDs

declines at envelope rates exceeding several hundred hertz [60]. Our own behavioral

experiments described here were conducted with low pulse rates (50 Hz), and future work

33   17

will need to determine whether ITD discrimination performance would be as good at pulse

rates close to 1 kHz. Thus, designers of novel binaural CI speech processors may face

conflicting demands: They must invent devices which fire each of 20 or more electrode

channels in turn, at rates that are both fast, so as to encode speech AM in fine detail, but

also slow, so as not to overtax the brainstem's ITD extraction mechanisms, and they must

make the timing of at least some of these pulses encode stimulus fine structure and ITDs.

While difficult, this may not be impossible, and promising research is underway which

either uses a mixture of different pulse rates for different electrode channels [61], or aims

to "reset" the brain's ITD extraction mechanisms by introducing occasional "double pulses"

into the stimulus [62]. A detailed discussion is beyond the scope of this paper. Our results

underscore the need to pursue this work with urgency, as it might just save many

thousands of deaf patients from a loss of ITD sensitivity that could be caused by sub-

optimal binaural CI-stimulation.

Material and Methods

All procedures involving experimental animals reported here were approved by the

Department of Health of Hong Kong (#16-52 DH/HA&P/8/2/5) or Regierungspräsidium

Freiburg (#35-9185.81/G-17/124), as well as by the appropriate local ethical review

committee.

Deafening

Rats were neonatally deafened by daily intraperitoneal (i.p.) injections of 400 mg/kg

kanamycin from postnatal day 9 to 20 inclusively [17,63]. This is known to cause

widespread death of inner and outer hair cells [63-65] while keeping the number of spiral

ganglion cells comparable to that in untreated control rats [63,65]. Osako et al. [63] have

shown that rat pups treated with this method achieve hearing thresholds around 70 dB for

only a short period (~p14-16) and are severely to profoundly hearing impaired thereafter,

resulting in widespread disturbances in the histological development of their central

auditory pathways, including a nearly complete loss of tonotopic organisation [17,18,21].

We verified that this procedure provoked profound hearing loss (> 90 dB) by the loss of

Preyer's reflex [66], and the absence of auditory brainstem responses (ABRs) to

broadband click stimuli (Fig. S1b). ABRs were measured as described in [21]: under

ketamine (80mg/kg) and xylazine (12 mg/kg) anesthesia each ear was stimulated

separately through hollow ear bars with 0.5 ms broadband clicks with peak amplitudes up

to 130 dB SPL delivered at a rate of 43 Hz. ABRs were recorded by averaging scalp

potentials measured with subcutaneous needle electrodes between mastoids and the

vertex of the rat's head over 400 click presentations. While normal rats typically exhibited

click ABR thresholds near 30 dB SPL (Fig. S1a), deafened rats had very high click

thresholds of ≥130 dB SPL; Fig. S1b).

CI implantation, stimulation and testing

All surgical procedures, including CI implantation and craniotomy, were performed under anesthesia induced with i.p. injection of ketamine (80mg/kg) and xylazine (12 mg/kg). For maintenance of anesthesia during electrophysiological recordings, a pump delivered an i.p. infusion of 0.9% saline solution of ketamine (17.8 mg/kg/h) and xylazine (2.7 mg/kg/h) at a rate of 3.1 ml/h. During surgical and experimental procedures the body temperature was maintained at 38°C using a feedback-controlled heating pad (RWD Life Sciences, Shenzhen, China). Further detailed descriptions of our cochlear implantation methods can be found in previous studies [17,67-70]. In short, two to four rings of an eight channel electrode carrier (ST08.45, Peira, Beerse, Belgium) were fully inserted through a cochleostomy in medio-dorsal direction into the middle turn of both cochleae. Electrically evoked ABRs (EABRs) were measured for each ear individually to verify that both CIs were successfully implanted and operated at acceptably low electrical stimulation thresholds, usually around 100 µA (Fig. S1c). EABR recording used isolated biphasic pulses (see below) with a 23 ms inter-pulse interval. EABR mean amplitudes were determined by averaging scalp potentials over 400 pulses for each stimulus amplitude. For electrophysiology experiments, EABRs were also measured immediately before and after IC recordings, and for the chronically implanted rats, EABRs were measured once a week under anesthesia to verify that the CIs functioned properly and stimulation thresholds were stable.

Electric and acoustic stimuli

The electrical stimuli used to examine the animals' EABRs, the physiological, and the behavioral ITD sensitivity were generated using a Tucker Davis Technology (TDT, Alachua, Florida, US) IZ2MH programmable constant current stimulator at a sample rate of 48,828.125 Hz. The most apical ring of the CI electrode served as stimulating electrode, the next ring as ground electrode. All electrical intracochlear stimulation used biphasic

current pulses similar to those used in clinical devices (duty cycle: 61.44 µs positive, 40.96 µs at zero, 61.44 µs negative), with peak amplitudes of up to 300 µA, depending on physiological thresholds or informally assessed behavioral comfort levels (rats will scratch their ears frequently, startle or show other signs of discomfort if stimuli are too intense). For behavioral training we stimulated all CI rats 6 dB above these thresholds. For details on the calibration which confirmed that our CI setup delivered the desired ITDs and no useable intensity cues, see supplementary Figure S2. Acoustic stimuli used to measure behavioral ITD sensitivity in NH rats were single sample pulse clicks generated at a sample rate of 48,000 Hz via a Raspberry Pi 3 computer connected to a USB sound card (StarTech.com, Ontario Canada, part # ICUSBAUDIOMH), amplifier (Adafruit stereo 3.7W class D audio amplifier, New York City, US, part # 987) and miniature high fidelity headphone drivers (GQ-30783-000, Knowles, Itasca, Illinois, US) which were mounted on hollow tubes. Stimuli were delivered at sound intensities of ≈ 80 dB SPL. For details on the calibration of the acoustic setup delivered the desired ITDs and no useable intensity cues, see supplementary Figure S3 and [30].

To produce electric or acoustic stimuli of varying ITDs spanning the rat's physiological range of ± 130 µs [34], stimulus pulses of identical shape and amplitude were presented to each ear, with the pulses in one ear delayed by an integer number of samples. Given the sample rates of the devices used, ITDs could thus be varied in steps of 20.48 µs for the electrical, and 20.83 µs for the acoustic stimuli. The physiological experiments described here used single pulse stimuli presented in isolation, while the behavior experiments used 200 ms long 50 Hz pulse trains.

Animal psychoacoustic testing

We trained our rats on 2AFC sound lateralization tasks using methods similar to those described in [30,33,47,48]. The behavioral animals were put on a schedule with six days of testing, during which the rats obtained their drinking water as a positive reinforcer, followed

by one day off, with *ad-lib* water. The evening before the next behavioral testing period,

drinking water bottles were removed. During testing periods, the rats were given two

sessions per day. Each session lasted 25-30 min, which typically took 150-200 trials

during which ≈ 10 ml of water were consumed.

One of the walls of each behavior cage was fitted with three brass water spouts, mounted

≈ 6-7 cm from the floor and separated by ≈ 7.5 cm (Figs. S2a-b; S3a-c). We used one

center "start spout" for initiating trials and one left and one right "response spout" for

indicating whether the stimulus presented during the trial was perceived as lateralized to

that side. Contact with the spouts was detected by capacitive touch detectors (Adafruit

industries, New York City, US, part # 1362). Initiating a trial at the center spout triggered

the release of a single drop of water through a solenoid valve. Correct lateralization

triggered three drops of water as positive reinforcement. Incorrect responses triggered no

water delivery but caused a 5-15 s timeout during which no new trial could be initiated.

Timeouts were also marked by a negative feedback sound for the NH rats. Given that CI

stimulation can be experienced as strenuous and tiring by human patients [71], the ND CI

rats received a flashing LED as an alternative negative feedback stimulus. After each

correct trial a new ITD was chosen randomly from a set spanning ±160 µs in 25 µs steps,

but after each incorrect trial the last stimulus was repeated in a "correction trial". Correction

trials prevent animals from developing idiosyncratic biases favoring one side [47,72], but

since they could be answered correctly without attention to the stimuli by a simple "if you

just made a mistake, change side" strategy, they are excluded from the final psychometric

performance analysis.

The NH rats received their acoustic stimuli through stainless steel hollow ear tubes placed

such that, when the animal was engaging the start spout, the tips of the tubes were

located right next to each ear of the animal to allow near-field stimulation (Fig. S3a). The

pulses resonated in the tubes, producing pulse-resonant sounds, resembling single-

formant artificial vowels with a fundamental frequency corresponding to the click rate. Note

that this mode of sound delivery is thus very much like that produced by "open"

headphones, such as those commonly used in previous studies on binaural hearing in

humans and animals, e.g. [33,73]. We used a 3D printed "rat acoustical manikin" with

miniature microphones in the ear canals (Fig. S3c). It produced a channel separation

between ears of ≥ 20dB at the lowest, fundamental frequency and around 40 dB overall.

Further details on the acoustic setup and procedure are described in [30]. The ND CI rats

received their auditory stimulation via bilateral CIs described above, connected to the TDT

IZ2MH stimulator via a custom-made, head mounted connector and commutator, as

described in [74].

Multi-unit recording from IC

Anesthetized rats were head fixed in a stereotactic frame (RWD Life Sciences),

craniotomies were performed bilaterally just anterior to lambda. The animal and

stereotactic frame were positioned in a sound attenuating chamber, and a single-shaft, 32-

channel silicon electrode array (ATLAS Neuroengineering, E32-50-S1-L6) was inserted

stereotactically into the left or right IC through the overlying occipital cortex using a

micromanipulator (RWD Life Sciences). Extracellular signals were sampled at a rate of

24.414 kHz with a TDT RZ2 with a NeuroDigitizer headstage and BrainWare software. Our

recordings typically exhibited short response latencies (≈ 3-5 ms), which suggests that

they may come predominantly from the central region of IC. Responses from non-

lemniscal sub-nuclei of IC have been reported to have longer response latencies (≈ 20ms;

[75]).

At each electrode site, we first measured neural rate/level functions, varying stimulation

currents in each ear to verify that the recording sites contained neurons responsive to

cochlear stimulation, and to estimate threshold stimulus amplitudes. Thresholds rarely

varied substantially from one recording site to another in any one animal. We then

measured ITD tuning curves by presenting single pulse binaural stimuli with equal

amplitude in each ear, ≈ 10 dB above the contralateral ear threshold, in pseudo-random

order. ITDs varied from 163.84 µs (8 samples) contralateral ear leading to 163.84 µs

ipsilateral ear leading in 20.48 µs (one sample) steps. Each ITD value was presented 30

times at each recording site. The inter-stimulus interval was 500 ms. At the end of the

recording session the animals were overdosed with pentobarbitone.

Data analysis

To quantify the extracellular multi-unit responses we calculated the average activity for

each stimulus over a response period (3-80 ms post stimulus onset) as well as baseline

activity (300-500 ms after stimulus onset) at each electrode position. The first 2.5 ms post

stimulus onset were dominated by electrical stimulus artifacts and were discarded. For

display purposes of the raster plots in Figure 2 we extracted multi-unit spikes by simple

threshold crossings of the bandpassed (300 Hz - 6 kHz) electrode signal with a threshold

set at four standard deviation of the signal amplitude. To quantify responses for tuning

curves, instead of counting spikes by threshold crossings we instead computed an analog

measure of multi-unit activity (AMUA) amplitudes as described in [76]. The mean AMUA

amplitude during the response and baseline periods was computed by bandpassing (300

Hz - 6 kHz), rectifying (taking the absolute value) and lowpassing (6 kHz) the electrode

signal. This AMUA value thus measures the mean signal amplitude in the frequency range

in which spikes have energy. As illustrated in Figure 1 of [76], this gives a less noisy

measure of multi-unit neural activity than counting spikes by conventional threshold

crossing measures because the later are subject to errors due to spike collisions, noise

events, or small spikes sometimes reach threshold and sometimes not. The tuning curves

shown in the panels of Figure 2 were measured using this AMUA measure. It is readily

apparent that changes in the AMUA amplitudes track changes in spike density.

Signal-to-noise ratio (SNR) calculation

SNR values are a measure of the strength of tuning of neural responses to ITD which we adopted from [24] to facilitate quantitative comparisons. The SNR is defined in [24] as the proportion of trial-to-trial variance in response amplitude explained by changes in ITD. The SNR is calculated by computing a one-way ANOVA of responses grouped by ITD value and dividing the total sum of squares by the group sum of squares. This yields values between 0 (no effect of ITD) and 1 (response amplitudes completely determined by ITD). P-values were also computed from the one-way ANOVA and $p < 0.01$ served as a criterion to determine whether the ITD tuning of a given multi-unit was deemed statistically significant. The number of responses for each ITD value was 30, yielding with a degree of freedom (df) for the ANOVA of 29.

Psychometric curve fitting

In order to derive summary statistics that could serve as measures of ITD sensitivity from the thousands of trials performed by each animal we fitted psychometric models to the observed data. It is common practice in human psychophysics to fit performance data with cumulative Gaussian functions [77,78]. This practice is well motivated in signal detection theory, which assumes that the perceptual decisions made by the experimental subject are informed by sensory signals which are subject to multiple, additive, and hence approximately normally distributed sources of noise. When the sensory signals are very large relative to the inherent noise then the task is easy and the subject will make the appropriate choice with near certainty. For binaural cues closer to threshold, the probability of choosing "right" (p_R) can be modeled by the function

$$p_R = \Phi\left(ITD \cdot \alpha\right) \qquad (2)$$

where, Φ is the cumulative normal distribution, *ITD* denotes the interaural time difference (arrival time at left ear minus arrival time at right ear, in ms), and α is a sensitivity scale

parameter which captures how big a change in the proportion of "right" choices a given

change in ITD can provoke, with units of 1/ms.

Functions of the type in equation (2) tend to fit psychometric data for 2AFC tests with

human participants well, where subjects can be easily briefed and lack of clarity about the

task, lapses of attention or strong biases in the perceptual choices are small enough to be

explored. However, animals have to work out the task for themselves through trial and

error, and may spend some proportion of trials on "exploratory guesses" rather than direct

perceptual decisions. If we denote the proportion of trials during which the animal makes

such guesses (the "lapse rate") by γ, then the proportion of trials during which the animal's

responses are governed by processes which are well modeled by equation (2) is reduced

to (1-γ). Furthermore, animals may exhibit two types of bias: an "ear bias" and a "spout

bias". An "ear-bias" exists if the animal hears the midline (50% right point) at ITD values

which differ from zero by some small value β. A "spout bias" exists if the animal has an

idiosyncratic preference for one of the two response spouts or the other, which may

increase its probability of choosing the right spout by δ (where δ can be negative if the

animal prefers the left spout). Assuming the effect of lapses, spout and ear bias to be

additive, we therefore extended eqn (2) to the following psychometric model:

$$p_R = \Phi(ITD \cdot \alpha + \beta) \cdot (1 - \gamma) + \frac{\gamma}{2} + \delta \qquad (3)$$

We fitted the model in equation (3) to the observed proportions of "right" responses as a

function of stimulus ITD using the scipy.optimize.minimize() function of Python 3.4, using

gradient descent methods to find maximum likelihood estimates for the parameters α, β, γ

and δ given the data. This cumulative Gaussian model fitted the data very well, as is

readily apparent in Figure 1a-j. We then used the slope of the psychometric function

around zero ITD as our maximum likelihood estimate of the animal's ITD sensitivity, as

plotted in Figure 1k. That slope is easily calculated using the equation (4)

slope = $\varphi(0) \cdot \alpha \cdot (1-\gamma)$ (4)

which is obtained by differentiating equation (3) and setting ITD=0. $\varphi(0)$ is the Gaussian

normal probability density at zero (≈0.3989).

Seventy-five % correct thresholds were computed as the mean absolute ITD at which the

psychometric dips below 25% or rises above 75% "right" responses respectively.

Acknowledgements

We thank A. Hyun Jung for assisting behavioral training of CI rats, P. Ruther and the *Cluster of Excellence BrainLinks-BrainTools* (German Research Foundation, grant number EXC1086) for the support by recording electrodes. Work leading to this publication was supported by a grant from the Vice President of Research and Technology (VPRT) of the City University of Hong Kong, the German Academic Exchange Service (DAAD) with funds from the German Federal Ministry of Education and Research (BMBF) and the People Programme (Marie Curie Actions) of the European Union's Seventh Framework Programme (FP7/2007-2013) under REA grant agreement n° 605728 (P.R.I.M.E. – Postdoctoral Researchers International Mobility Experience), and friends' association "Taube Kinder lernen hören e. V.".

Author Contributions

N.R.K. and J.W.H.S. designed the study and wrote the article. N.R.K., A.N.B., K.L., and J.W.H.S. performed the experiments. J.W.H.S., N.R.K., and A.N.B. evaluated the data. All authors approved the final manuscript.

Declaration of Interests

The authors declare no competing interests.

Supplementary Figures

Figure S1: Brainstem recordings to verify normal hearing or loss of hearing function as

well as the symmetrical placement of CIs. **a** Auditory brainstem responses of an

acoustically stimulated normal hearing (NH) rat. ABRs are symmetrical for both ears and

show clear differentiation. **b** ABRs of a neonatally deafened (ND) rat. No hearing

thresholds were detectable up to 130 dB SPL. **c** Electrically evoked ABRs under CI

stimulation of a deafened rat. Each sub-panel includes measurements for the left and the

right ear, respectively, under acoustic (**a-b**) or electric stimulation (**c**). In (c) the first

millisecond (electrical stimulus artifact) is blanked out.

Figure S2: Binaural electrical intracochlear stimulation of CI rats. **a** Close-up of the training

setup for CI rats. The central "start" and lateral "response" spouts deliver the water reward

and are indicated by arrows. **b** CI rat during a testing session, making a response to the

left by making contact with the left reward spout. **c** Calibration measurements were

performed by connecting the stimulator cable to 10 kOhm resistors instead of the in-vivo

electrodes and recording voltages using a Tektronix MSO 4034B oscilloscope with 350

MHz and 2.5 GS/s. Recordings of stimulus pulses are shown with 100 µs ITD leading in

the right ear (top) or the left ear (bottom) respectively. Pulses delivered to the right ear are

shown in red, those delivered in the left ear in blue. The stimulator was programmed to

produce biphasic rectangular stimulus pulses with a 20 µA amplitude (y-axis) and a 20.5

µs interval between the positive and the negative phase. **d** Measured calibration pulses

such as those shown in (**c**) were used to verify that electric ILDs were negligible and did

not vary systematically with ITD. ILDs were computed as the difference in root mean

square (RMS) power of the signals in (**d**). Data from five presentations of ITDs of + or –

100 µs are shown by the green dots. These residual ILDs produced by device tolerances

in our system are not only an order of magnitude smaller than the ILD thresholds for

human CI subjects reported in the literature (~0.1 dB [79]), they also do not covary with

ITD. We can therefore be certain that sensitivity to ILDs can not account for our behavior

data.

Figure S3: Binaural psychoacoustics near-field setup for NH rats. Note that the setup is

identical to that described in Li et al. [30] and this supplementary figure is similar to Figure

1 of that paper. **a** NH rat during a testing session, initiating a trial by making contact with

the central "start" spout. Steel tube phones are positioned close to each ear. **b** Close-up of

the assembly. The central "start" and lateral "response" spouts deliver the water reward

and are indicated by arrows. Also visible are the custom ball joints for adjusting the tube

phone positions. **c** 3D printed "rat acoustical manikin" with miniature microphones in each

ear canal, used for validating the setup. **d** Validation data for acoustic click stimuli as

recorded from the microphones inside each ear canal of the 3D printed "rat acoustical

manikin" (L: left ear, R: right ear) in response to the +/- 100 µs ITD conditions (top and

bottom pair of traces, respectively). **e** Frequency spectra of the sound waveforms recorded

by the microphones in each ear for the +100 µs (top) and -100 µs (bottom) conditions. **f**

Acoustic ILDs (y-axes) measured through the "rat acoustical manikin" microphones for the

+/- 100 µs ITD conditions. ILDs were computed as the difference in root mean square

(RMS) power of the signals in panel (**d**). Data were recorded from 10 presentations of

each ITD stimulus, and each dot represents one trial (a random amount of scatter along

the x-axis was added for ease of visualization). Note that the residual ILDs are much

smaller than the reported behavioral thresholds for ferrets (~ 1.3 dB, dotted line, [33]) or

rats (~3 dB [37]). We can therefore be certain that sensitivity to ILDs cannot account for

our behavior data.

References

1. Kral, A. & Sharma, A. Developmental neuroplasticity after cochlear implantation. *Trends Neurosci.* **35**, 111-122 (2012)

2. Ellinger, R. L., Jakien, K. M. & Gallun, F. J. The role of interaural differences on speech intelligibility in complex multi-talker environments. *J. Acoust. Soc. Am.* **141**, EL170 (2017)

3. Litovsky, R. Bilateral Cochlear Implants. *ASHA Leader* **15**, 14 (2010)

4. Conti-Ramsden, G., St Clair, M. C., Pickles, A. & Durkin, K. Developmental trajectories of verbal and nonverbal skills in individuals with a history of specific language impairment: from childhood to adolescence.. *J. Speech. Lang. Hear. Rees* **55**, 1716-1735 (2012)

5. Ehlers, E., Goupell, M. J., Zheng, Y., Godar, S. P. & Litovsky, R. Y. Binaural sensitivity in children who use bilateral cochlear implants. *J. Acoust. Soc. Am.* **141**, 4264-4277 (2017)

6. van Hoesel, R. J. M. Exploring the Benefits of Bilateral Cochlear Implants. *Audiol. Neurootol.* **9**, 234-246 (2004)

7. van Hoesel, R. J. M. Contrasting benefits from contralateral implants and hearing aids in cochlear implant users. *Hear. Res.* **288**, 100-113 (2012)

8. Schnupp, J., Nelken, I. & King, A. *Auditory neuroscience : making sense of sound*. (MIT Press, Cambridge, Mass. ; London, 2011)

9. Zwislocki, J. & Feldman, R. S. Just Noticeable Dichotic Phase Difference. *J. Acoust. Soc. Am.* **28**, 152-153 (1956)

10. Kerber, S. & Seeber, B. U. Sound Localization in Noise by Normal-Hearing Listeners and Cochlear Implant Users. *Ear Hear.* **33**, 445-457 (2012)

11. Litovsky, R. Y., Goupell, M. J., Godar, S., Grieco-Calub, T., Jones, G. L., et al Studies on bilateral cochlear implants at the University of Wisconsin's Binaural Hearing and Speech Laboratory. *J. Am. Acad. Audiol.* **23**, 476-494 (2012)

12. Laback, B., Egger, K. & Majdak, P. Perception and coding of interaural time differences with bilateral cochlear implants. *Hear. Res.* **322**, 138-150 (2015)

13. Poon, B. B., Eddington, D. K., Noel, V. & Colburn, H. S. Sensitivity to interaural time difference with bilateral cochlear implants: Development over time and effect of interaural electrode spacing. *J. Acoust. Soc. Am.* **126**, 806-815 (2009)

14. Gordon, K. A., Deighton, M. R., Abbasalipour, P. & Papsin, B. C. Perception of binaural cues develops in children who are deaf through bilateral cochlear implantation. *PLoS One* **9**, e114841 (2014)

15. Litovsky, R. Y. & Gordon, K. Bilateral cochlear implants in children: Effects of auditory experience and deprivation on auditory perception. *Hear. Res.* **338**, 76-87 (2016)

16. Yusuf, P. A., Hubka, P., Tillein, J. & Kral, A. Induced cortical responses require developmental sensory experience. *Brain* **140**, 3153-3165 (2017)

17. Rosskothen-Kuhl, N. & Illing, R.-B. The impact of hearing experience on signal integration in the auditory brainstem: A c-Fos study of the rat. *Brain Res.* **1435**, 40-55 (2012)

18. Rauch, A.-K., Rosskothen-Kuhl, N. & Illing, R.-B. Counter-regulation of the AP-1 monomers
pATF2 and Fos: Molecular readjustment of brainstem neurons in hearing and deaf adult rats after
electrical intracochlear stimulation. *Neuroscience* **313**, 184-198 (2016)

19. Illing, R.-B. & Rosskothen-Kuhl, N. *The cochlear implant in action: molecular changes*
induced in the rat central auditory system. (INTECH Open Access Publisher, Freiburg, 2012)

20. Jakob, T. F., D{\"{o}}ring, U. & Illing, R.-B. The pattern of Fos expression in the rat auditory
brainstem changes with the temporal structure of binaural electrical intracochlear stimulation. *Exp.*
Neurol. **266**, 55-67 (2015)

21. Rosskothen-Kuhl, N., Hildebrandt, H., Birkenhäger, R. & Illing, R.-B. Astrocyte Hypertrophy
and Microglia Activation in the Rat Auditory Midbrain Is Induced by Electrical Intracochlear
Stimulation. *Front. Cell. Neurosci.* **12**, (2018)

22. Seidl, A. H. & Grothe, B. Development of sound localization mechanisms in the mongolian
gerbil is shaped by early acoustic experience. *J. Neurophysiol.* **94**, 1028-1036 (2005)

23. Beiderbeck, B., Myoga, M. H., Müller, N. I. C., Callan, A. R., Friauf, E., et al Precisely timed
inhibition facilitates action potential firing for spatial coding in the auditory brainstem. *Nat.*
Commun. **9**, (2018)

24. Hancock, K. E., Noel, V., Ryugo, D. K. & Delgutte, B. Neural coding of interaural time
differences with bilateral cochlear implants: effects of congenital deafness. *J. Neurosci.* **30**, 14068-
14079 (2010)

25. Hancock, K. E., Chung, Y. & Delgutte, B. Neural ITD coding with bilateral cochlear implants:
effect of binaurally coherent jitter. *J. Neurophysiol.* **108**, 714-728 (2012)

26. Hancock, K. E., Chung, Y. & Delgutte, B. Congenital and prolonged adult-onset deafness cause
distinct degradations in neural ITD coding with bilateral cochlear implants. *JARO* **14**, 393-411
(2013)

27. Chung, Y., Buechel, B. D., Sunwoo, W., Wagner, J. D. & Delgutte, B. Neural ITD Sensitivity
and Temporal Coding with Cochlear Implants in an Animal Model of Early-Onset Deafness..
Journal of the Association for Research in Otolaryngology : JARO **20**, 37-56 (2019)

28. Tillein, J., Hubka, P., Syed, E., Hartmann, R., Engel, A., et al Cortical representation of
interaural time difference in congenital deafness. *Cereb. Cortex* **20**, 492-506 (2009)

29. Tillein, J., Hubka, P. & Kral, A. Monaural Congenital Deafness Affects Aural Dominance and
Degrades Binaural Processing.. *Cereb. Cortex* **26**, 1762-1777 (2016)

30. Li, K., Chan, C. H. K., Rajendran, V. G., Meng, Q., Rosskothen-Kuhl, N., et al Microsecond
sensitivity to envelope interaural time differences in rats.. *The Journal of the Acoustical Society of*
America **145**, EL341 (2019)

31. Litovsky, R. Y., Jones, G. L., Agrawal, S. & van Hoesel, R. Effect of age at onset of deafness
on binaural sensitivity in electric hearing in humans. *J. Acoust. Soc. Am.* **127**, 400-414 (2010)

32. Klumpp, R. & Eady, H. Some measurements of interaural time difference thresholds. *J. Acoust.*
Soc. Am. **28**, 859-860 (1956)

33. Keating, P., Nodal, F. R., Gananandan, K., Schulz, A. L. & King, A. J. Behavioral sensitivity to

broadband binaural localization cues in the ferret. *JARO* **14**, 561-572 (2013)

34. Koka, K., Read, H. L. & Tollin, D. J. The acoustical cues to sound location in the rat:
measurements of directional transfer functions. *J. Acoust. Soc. Am.* **123**, 4297-4309 (2008)

35. Smith, Z. M. & Delgutte, B. Sensitivity to interaural time differences in the inferior colliculus
with bilateral cochlear implants. *J. Neurosci.* **27**, 6740-6750 (2007)

36. Grothe, B. & Klump, G. M. Temporal processing in sensory systems. *Curr. Opin. Neurobiol.*
10, 467-473 (2000)

37. Wesolek, C. M., Koay, G., Heffner, R. S. & Heffner, H. E. Laboratory rats (Rattus norvegicus)
do not use binaural phase differences to localize sound. *Hear. Res.* **265**, 54-62 (2010)

38. Joris, P. X. & Yin, T. C. Envelope coding in the lateral superior olive. I. Sensitivity to interaural
time differences. *J. Neurophysiol.* **73**, 1043-1062 (1995)

39. Bernstein, L. R. Auditory processing of interaural timing information: new insights. *J.*
Neurosci. Res. **66**, 1035-1046 (2001)

40. Kan, A., Jones, H. G. & Litovsky, R. Y. Lateralization of interaural timing differences with
multi-electrode stimulation in bilateral cochlear-implant users. *J. Acoust. Soc. Am.* **140**, EL392
(2016)

41. Chung, Y., Hancock, K. E. & Delgutte, B. Neural Coding of Interaural Time Differences with
Bilateral Cochlear Implants in Unanesthetized Rabbits. *J. Neurosci.* **36**, 5520-5531 (2016)

42. Vollmer, M. Neural processing of acoustic and electric interaural time differences in normal-
hearing gerbils. *J. Neurosci.* **38**, 6949-6966 (2018)

43. Zheng, Y., Godar, S. P. & Litovsky, R. Y. Development of Sound Localization Strategies in
Children with Bilateral Cochlear Implants.. *PLoS One* **10**, e0135790 (2015)

44. Brunso-Bechtold, J. K., Henkel, C. K. & Linville, C. Ultrastructural development of the medial
superior olive (MSO) in the ferret. *J. Comp. Neurol.* **324**, 539-556 (1992)

45. Hoffpauir, B. K., Grimes, J. L., Mathers, P. H. & Spirou, G. A. Synaptogenesis of the calyx of
Held: rapid onset of function and one-to-one morphological innervation. *J. Neurosci.* **26**, 5511-5523
(2006)

46. Kapfer, C., Seidl, A. H., Schweizer, H. & Grothe, B. Experience-dependent refinement of
inhibitory inputs to auditory coincidence-detector neurons.. *Nat. Neurosci.* **5**, 247-253 (2002)

47. Walker, K. M., Schnupp, J. W., Hart-Schnupp, S. M., King, A. J. & Bizley, J. K. Pitch
discrimination by ferrets for simple and complex sounds. *J. Acoust. Soc. Am.* **126**, 1321-1335
(2009)

48. Bizley, J. K., Walker, K. M. M., Nodal, F. R., King, A. J. & Schnupp, J. W. H. Auditory cortex
represents both pitch judgments and the corresponding acoustic cues. *Curr. Biol.* **23**, 620-625
(2013)

49. Tirko, N. N. & Ryugo, D. K. Synaptic plasticity in the medial superior olive of hearing, deaf,
and cochlear-implanted cats.. *The Journal of comparative neurology* **520**, 2202-2217 (2012)

50. Pecka, M., Brand, A., Behrend, O. & Grothe, B. Interaural time difference processing in the
mammalian medial superior olive: the role of glycinergic inhibition.. *The Journal of neuroscience :*

the official journal of the Society for Neuroscience **28**, 6914-6925 (2008)

51. Keating, P., Dahmen, J. C. & King, A. J. Context-specific reweighting of auditory spatial cues following altered experience during development. *Current biology : CB* **23**, 1291-1299 (2013)

52. Keating, P., Dahmen, J. C. & King, A. J. Complementary adaptive processes contribute to the developmental plasticity of spatial hearing. *Nat. Neurosci.* **18**, 185-187 (2015)

53. Kumpik, D. P., Campbell, C., Schnupp, J. W. H. & King, A. J. Re-weighting of Sound Localization Cues by Audiovisual Training.. *Front. Neurosci.* **13**, 1164 (2019)

54. Levi, D. M., Knill, D. C. & Bavelier, D. Stereopsis and amblyopia: a mini-review. *Vision Res.* **114**, 17-30 (2015)

55. Ko, H., Cossell, L., Baragli, C., Antolik, J., Clopath, C., et al The emergence of functional microcircuits in visual cortex. *Nature* **496**, 96-100 (2013)

56. Wilson, B. S., Finley, C. C., Lawson, D. T., Wolford, R. D., Eddington, D. K., et al Better speech recognition with cochlear implants. *Nature* **352**, 236-238 (1991)

57. Loizou, P. C., Poroy, O. & Dorman, M. The effect of parametric variations of cochlear implant processors on speech understanding. *J. Acoust. Soc. Am.* **108**, 790-802 (2000)

58. van Hoesel, R. J. M. Sensitivity to binaural timing in bilateral cochlear implant users. *J. Acoust. Soc. Am.* **121**, 2192-2206 (2007)

59. Laback, B., Majdak, P. & Baumgartner, W.-D. Lateralization discrimination of interaural time delays in four-pulse sequences in electric and acoustic hearing. *J. Acoust. Soc. Am.* **121**, 2182-2191 (2007)

60. Joris, P. X. & Yin, T. C. Envelope coding in the lateral superior olive. III. Comparison with afferent pathways. *J. Neurophysiol.* **79**, 253-269 (1998)

61. Thakkar, T., Kan, A., Jones, H. G. & Litovsky, R. Y. Mixed stimulation rates to improve sensitivity of interaural timing differences in bilateral cochlear implant listeners. *J. Acoust. Soc. Am.* **143**, 1428 (2018)

62. Srinivasan, S., Laback, B., Majdak, P. & Delgutte, B. Introducing Short Interpulse Intervals in High-Rate Pulse Trains Enhances Binaural Timing Sensitivity in Electric Hearing. *JARO* **19**, 301-315 (2018)

63. Osako, S., Tokimoto, T. & Matsuura, S. Effects of kanamycin on the auditory evoked responses during postnatal development of the hearing of the rat. *Acta Otolaryngol. (Stockh.)* **88**, 359-368 (1979)

64. Matsuda, K., Ueda, Y., Doi, T., Tono, T., Haruta, A., et al Increase in glutamate-aspartate transporter (GLAST) mRNA during kanamycin-induced cochlear insult in rats. *Hear. Res.* **133**, 10-16 (1999)

65. Argence, M., Vassias, I., Kerhuel, L., Vidal, P.-P. & de Waele, C. Stimulation by cochlear implant in unilaterally deaf rats reverses the decrease of inhibitory transmission in the inferior colliculus. *Eur. J. Neurosci.* **28**, 1589-1602 (2008)

66. Jero, J., Coling, D. E. & Lal, A. K. The Use of Preyer's Reflex in Evaluation of Hearing in Mice. *Acta Otolaryngol. (Stockh.)* **121**, 585-589 (2001)

67. Rosskothen, N., Hirschm{\"u}ller-Ohmes, I. & Illing, R.-B. AP-1 activity rises by stimulation-
dependent c-Fos expression in auditory neurons. *Neuroreport* **19**, 1091-1093 (2008)

68. Rosskothen-Kuhl, N. & Illing, R.-B. Nonlinear development of the populations of neurons
expressing c-Fos under sustained electrical intracochlear stimulation in the rat auditory brainstem.
Brain Res. **1347**, 33-41 (2010)

69Rosskothen-Kuhl, N.; Hildebrandt, H.; Birkenhaeger, R. and Illing, R.-B. Hearing Experience
Changes Neuron-Glia Interaction in the Midbrain of Adult Rats,   (2014).

70. Rosskothen-Kuhl, N. & Illing, R. The utilization of brain plasticity by cochlear implants:
Molecular and cellular changes due to electrical intracochlear stimulation. *HNO* **63**, 94-103 (2015)

71. Perreau, A. E., Wu, Y.-H., Tatge, B., Irwin, D. & Corts, D. Listening Effort Measured in Adults
with Normal Hearing and Cochlear Implants.. *J. Am. Acad. Audiol.* **28**, 685-697 (2017)

72. Keating, P., Nodal, F. R. & King, A. J. Behavioural sensitivity to binaural spatial cues in ferrets:
evidence for plasticity in the duplex theory of sound localization. *Eur. J. Neurosci.* **39**, 197-206
(2014)

73. Wightman, F. L. & Kistler, D. J. The dominant role of low-frequency interaural time differences
in sound localization.. *J. Acoust. Soc. Am.* **91**, 1648-1661 (1992)

74. Rosskothen-Kuhl, N. & Illing, R.-B. Gap43 transcription modulation in the adult brain depends
on sensory activity and synaptic cooperation. *PLoS One* **9**, e92624 (2014)

75. Syka, J., Popelár, J., Kvasnák, E. & Astl, J. Response properties of neurons in the central
nucleus and external and dorsal cortices of the inferior colliculus in guinea pig. *Exp. Brain Res.* **133**,
254-266 (2000)

76. Schnupp, J. W. H., Garcia-Lazaro, J. A. & Lesica, N. A. Periodotopy in the gerbil inferior
colliculus: local clustering rather than a gradient map. *Front. Neural Circuits* **9**, 37 (2015)

77. Wickens, T. D. *Elementary signal detection theory*. (Oxford University Press, USA, , 2002)

78. Schnupp, J. W., Dawe, K. L. & Pollack, G. L. The detection of multisensory stimuli in an
orthogonal sensory space. *Exp. Brain Res.* **162**, 181-190 (2005)

79. van Hoesel, R. J. & Tyler, R. S. Speech perception, localization, and lateralization with bilateral
cochlear implants. *The Journal of the Acoustical Society of America* **113**, 1617-1630 (2003)