1 ***Improved Statistical Efficiency of Simultaneous Multi-Slice fMRI by***
2 ***Reconstruction with Spatially Adaptive Temporal Smoothing***

3 Mark Chiew[1], Karla L. Miller[1]

4
5 [1]Wellcome Centre for Integrative Neuroimaging, FMRIB, Nuffield Department of Clinical Neurosciences,
6 University of Oxford

7
Corresponding Author:
Mark Chiew
FMRIB Centre
John Radcliffe Hospital
Oxford
OX3 9DU
Email: mark.chiew@ndcn.ox.ac.uk

15
16
17
18

Abstract

We introduce an approach to reconstruction of simultaneous multi-slice (SMS)-fMRI data
that improves statistical efficiency. The method incorporates regularization to adjust
temporal smoothness in a spatially varying, encoding-dependent manner, reducing the g-
factor noise amplification per temporal degree of freedom. This results in a net
improvement in tSNR and GLM efficiency, where the efficiency gain can be derived
analytically as a function of the encoding and reconstruction parameters. Residual slice
leakage and aliasing is limited when fMRI signal energy is dominated by low frequencies.
Analytical predictions, simulated and experimental results demonstrate a marked
improvement in statistical efficiency in the temporally regularized reconstructions
compared to conventional slice-GRAPPA reconstructions, particularly in central brain
regions. Furthermore, experimental results confirm that residual slice leakage and aliasing
errors are not noticeably increased compared to slice-GRAPPA reconstruction. This
approach to temporally regularized image reconstruction in SMS-fMRI improves statistical
power, and allows for explicit choice of reconstruction parameters by directly assessing
their impact on noise variance per degree of freedom.

1. Introduction

Simultaneous multi-slice (SMS) imaging (Barth et al., 2016; Larkman et al., 2001; Moeller et al., 2010) has become widely used for functional MRI (fMRI) data acquisition, particularly since the introduction of the controlled aliasing in parallel imaging (CAIPI) (Breuer et al., 2005) blipped EPI acquisition (Setsompop et al., 2012). The blipped CAIPI scheme significantly reduced noise amplification g-factor penalties associated with the SMS unaliasing by introducing a 3D k-space sampling pattern (Zahneisen et al., 2014; Zhu et al., 2012) that manipulates aliasing locations to improve conditioning of the encoding matrix.

All SMS reconstruction methods rely on knowledge of the coil sensitivities (Pruessmann et al., 1999) or equivalently, the GRAPPA kernels (Griswold et al., 2002) for reconstruction. Broadly speaking, SMS reconstructions have employed either SENSE/GRAPPA (Blaimer et al., 2013, 2006; Koopmans, 2017; Moeller et al., 2014), Slice-GRAPPA (Cauley et al., 2014; Hoge et al., 2018; Setsompop et al., 2012), or conventional SENSE (Zahneisen et al., 2014) formulations. In addition to coil sensitivity information, SMS reconstruction using additional phase (Blaimer et al., 2013) or low-rank (coil x space) (Kim and Haldar, 2015; Park and Park, 2017) constraints have also been proposed. Some of these methods have been specifically designed to minimize reconstruction spatial bias (Cauley et al., 2014; Park and Park, 2017) that arises from inter-slice leakage artifacts.

All of the above methods operate in a time-independent manner, reconstructing images individually. In the context of functional MRI (fMRI), methods additionally exploiting temporal structure in the data have been demonstrated in compressed sensing approaches, (Chavarrías et al., 2015; Jung et al., 2007; Zong et al., 2014), or by minimizing image differences (Li et al., 2018). Alternatively, low-rank (space x time) methods have been proposed for use in fMRI based on the use of low-dimensionality representations in fMRI analysis methods (Chiew et al., 2016, 2015). While low-rank approaches do not impose any specific constraint on the representation of spatial or temporal information, more recent low-rank plus sparse methods have also been used to additionally exploit sparsity in the temporal Fourier domain (Aggarwal et al., 2017; Petrov et al., 2017; Singh et al., 2015; Weizman et al., 2017) which requires smoothness or periodicity in voxel time-courses.

Here, we introduce an improvement to SMS-EPI for fMRI by introducing time-varying sampling with a spatially adaptive temporally regularized reconstruction. Analytical expressions for reconstruction bias and variance are presented, as well as assessment of the relative statistical efficiencies of a general linear model (GLM) analysis, and temporal SNR efficiency as a function of the image reconstruction parameters. We exploit the low-frequency distribution of BOLD signals to ensure that the proposed reconstruction results in comparable or lower mean squared error than is produced by conventional SENSE or slice-GRAPPA unaliasing, while improving statistical power. This paper demonstrates the utility of

76 this proposed reconstruction in simulations and experiments, and provides a framework for
77 principled analysis of temporal regularization factors in fMRI by directly calculating the
78 impact of unaliasing reconstruction parameters on GLM analysis.
79

2. Theory

2.1 Linear Reconstruction

By considering SMS unaliasing to be a special case of a 3D under-sampling problem, a
general SENSE-based framework can be used for reconstruction. The linear reconstruction
problem we propose to solve is:

$$\min_x \|Ax - k\|_2^2 + \lambda \cdot R(x) \qquad [1]$$

where A is the linear encoding operator, which incorporates point-wise multiplication of coil
sensitivities (assumed to be whitened) and the k-space sampling transform (which can be
Cartesian or non-uniformly sampled). If the spatio-temporal image vector x is formed by
vertically concatenating the time-series images across time-points (into a $N_x N_y N_z N_t \times 1$
vector, with $N_{x,y,z}$ corresponding to spatial dimensions x, y and z, and N_t corresponding to
the number of time-points), then A is a block-diagonal matrix where the block
corresponding to time-point t is $\left[F_u^{(t)} S_1, \quad \cdots, \quad F_u^{(t)} S_c\right]^T$, with $F_u^{(t)}$ denoting the under-
sampled Fourier transform at time t, and S_i is the sensitivity for the i^{th} coil, for $1 \le i \le c$,
where c is the number of coils. In Eq. 1, k is the vectorized noisy k-space data, R is the L2
penalty that enforces temporal smoothing, and λ is the parameter that controls the amount
of smoothing and effective temporal resolution.

We choose R to be:

$$R(x) = \|\nabla x\|_2^2 = x\nabla'\nabla x \qquad [2]$$

where ∇ is the finite difference operator acting on the time domain (voxel-by-voxel), and ∇'
denotes the adjoint of ∇. The L2 penalty allows the consequence of R to be interpreted like
a linear smoothing operation, with the solution to Eq. 1 well known to be:

$$\hat{x} = (A'A + \lambda\nabla'\nabla)^{-1}A'k \qquad [3]$$

2.2 Reconstruction Bias and Variance

To characterize the estimator in Eq. 3, we consider the total mean squared reconstruction
error as $MSE = bias^2 + variance$, where the bias term represents signal misallocation
error (e.g. leakage or residual aliasing) and the variance term related to noise amplification
(e.g. g-factor). We first reformulate Eq. 3 in terms of an equivalent, encoding dependent

smoothing operator, S_λ, that is applied following a conventional pseudoinverse
reconstruction:

$$S_\lambda = (A'A + \lambda \nabla'\nabla)^{-1}(A'A) \qquad [4]$$
$$\hat{x} = S_\lambda (A'A)^{-1}A'k = S_\lambda A^\dagger k \qquad [5]$$

where $A^\dagger$ denotes the Moore-Penrose pseudoinverse of A. Using this formulation, it is
apparent that S_λ is spatially adaptive in that it depends on $A'A$ (Fessler and Rogers, 1996),
unlike conventional shift-invariant post-hoc kernel smoothing.

With a conventional unbiased pseudoinverse reconstruction, $E(A^\dagger k) = E(x) = x$, and so
the bias expected from this reconstruction can be described by:

$$E(\hat{x} - x) = S_\lambda E(A^\dagger k) - x = [S_\lambda - I]x \qquad [6]$$

The g-factor at each time-point can be derived from the square root of the voxel-wise ratio
of the variance of the estimator $\hat{x}$ and the variance of a fully sampled, unsmoothed
reconstruction (see Eq. A9, Appendix A):

$$g_\lambda(m, t) = \sqrt{(S_\lambda (A'A)^{-1}S_\lambda{}')_{m,t}(A'A)_{m,t}} \qquad [7]$$

where here $M_{m,t}$ denotes the diagonal element of any matrix M corresponding to the m^{th}
voxel and t^{th} time-point, resulting in a g-factor for every voxel and time-point. The average
g-factor for any voxel m is then given by the root-mean-square across time (Ramb et al.,
2015):

$$\bar{g}_\lambda(m) = \sqrt{\frac{1}{N_t}\sum_t (g_\lambda(m, t))^2} \qquad [8]$$

2.3 GLM Efficiency

The benefit of regularization, in the context of general linear model regression analysis, can
be quantified by the efficiency of the estimator produced from the proposed
reconstruction. Efficiency is inversely related to the variance of the estimated GLM
regression coefficient, and an increase in efficiency results in increased statistical power.

A complete derivation of the relative efficiency between a regularized and un-regularized
reconstruction can be found in Appendix B, following closely from Worsley and Friston
(Worsley and Friston, 1995). Efficiency is a voxel-wise measure depending on g-factor, S_λ,
and the task design matrix:

154
$$e_\lambda = \left(\frac{g_0}{g_\lambda}\right)^2 \left(\frac{DOF_\lambda}{DOF_0}\right)\left(\frac{(D'D)^{-1}}{(\widetilde{D}'\widetilde{D})^{-1}\widetilde{D}'S_\lambda S_\lambda'\widetilde{D}(\widetilde{D}'\widetilde{D})^{-1}}\right)$$
[9]

156   where

157
$$DOF_\lambda = tr_m\left(\left(I - \widetilde{D}\left(\widetilde{D}'\widetilde{D}\right)^{-1}\widetilde{D}'\right)S_\lambda S_\lambda'\right)$$
[10]

159   can be interpreted as an effective degrees of freedom (DOF) measure, where $\widetilde{D} = S_\lambda D$ is

160   the smoothed task design matrix D, and $tr_m(\cdot)$ indicates that values across time for a given

161   voxel m are summed.

163   Asymptotically, when N_t is sufficiently large, λ is small, and the task waveform is sufficiently

164   slowly varying, Eq. 9 simplifies to an expression independent of D:

166
$$e_\lambda \approx \left(\frac{g_0}{g_\lambda}\right)^2 \left(\frac{tr_m(S_\lambda S_\lambda')}{N_t}\right) = \left(\frac{g_0{}^2}{N_t}\right) / \left(\frac{g_\lambda{}^2}{tr_m(S_\lambda S_\lambda')}\right)$$
[11]

168   With $\lambda = 0$ (no smoothing), $tr_m(S_\lambda S_\lambda') = N_t$ for all voxels, which naturally leads to defining

169   an approximate DOF expression as:

171
$$DOF_\lambda \approx tr_m(S_\lambda S_\lambda').$$
[12]

173   Then Eq. 11 can be interpreted intuitively as the ratio of the squared g-factors (g^2)

174   normalized by their respective DOF. When regularization reduces g-factor faster than the

175   loss of effective DOF, efficiency and statistical power are increased compared to the un-

176   regularized case.

2.4 tSNR Efficiency

179   Empirical temporal SNR (tSNR) efficiency can also be computed from resting condition data

180   by adjusting the voxel-wise temporal standard deviation with the normalized DOF using the

181   approximate form in Eq. 12:

183
$$tSNR_{eff} = \frac{mean(|x|)}{std(x)/\sqrt{DOF_\lambda/N_t}} = \frac{mean(|x|)}{std(x)}\sqrt{\frac{DOF_\lambda}{N_t}}$$
[13]

185   with the mean and standard deviation (std) taken across time. When $DOF_\lambda/N_t = 1$, this is

186   equivalent to conventional tSNR definitions, but when $DOF_\lambda/N_t < 1$, tSNR efficiency

187   decreases to reflect the reduced degrees of freedom per unit time.

3. Methods

To characterize the proposed method, numerical simulations and experiments were performed to assess the performance of the proposed reconstruction method.

First, two sets of numerical simulations were used to separately characterize noise and signal properties, exploiting the linearity of the reconstruction approach:

Sim1. A "noise only" Monte Carlo simulation to estimate the spectral response to regularization and validate the analytical g-factor, DOF and efficiency expressions

Sim2. A "signal only" numerical simulation to assess signal bias or leakage in the absence of any noise amplification effects

Next, three experiments were performed on healthy volunteers to assess the reconstruction performance *in vivo*, using different acquisition protocols:

Exp1. Resting fMRI with single-slice excitation and full SMS reconstruction, which allows for the evaluation of total mean squared error in the unexcited slices

Exp2. Resting fMRI with SMS-excitation and reconstruction, to evaluate tSNR efficiency

Exp3. Task fMRI with SMS-excitation and reconstruction, to evaluate GLM statistical efficiency

3.1 CAIPI Sampling

The k-space sampling schemes explored in this work can be characterized by 3 parameters:

$\Delta kz/\Delta ky$: defines the conventional *within-shot* CAIPI sampling pattern, corresponding to the z-gradient blips that control the FOV shift between simultaneously acquired slices

$\Delta kz/\Delta t$: defines the *between-shot* shift of the sampling pattern in the kz direction, which corresponds to a changing phase relationship between simultaneously acquired slices

$\Delta ky/\Delta t$: defines the *between-shot* shift of the sampling pattern in the ky direction, which is only non-zero if in-plane acceleration is used

Figure 1 illustrates the effects of $\Delta kz/\Delta ky = 3/2$, $\Delta kz/\Delta t = 3$, and $\Delta ky/\Delta t = 0$ sampling pattern. For SMS acquisitions with conventional CAIPI sampling, $\Delta kz/\Delta t = 0$, which means the sampling pattern is identical from shot-to-shot. Here, by introducing sampling patterns where $\Delta kz/\Delta t$ and $\Delta ky/\Delta t$ are non-zero, the sampling pattern (defined by $\Delta kz/\Delta ky$) is shifted in k-space from shot-to-shot. Although these parameters can also vary with time, in this work, we focus mainly on acquisitions with constant sampling parameters, so that the relative shift from any shot to the next does not change.

One advantage of designing the sampling scheme with constant shift parameters (i.e.
regular shifts across time) is that this results in g-factors that are also constant across time,
simplifying analysis and ensuring a stationary noise model for the entire time-series
reconstruction. Intuitively, this results from the property that any width sampling window
centered on any given time-point will have sampling patterns that are identical, to within a
shift, and that g-factors are invariant to shifts in k-space.
235

236
237   Figure 1 - (a) Example CAIPI sampling pattern for a MB8R2 acquisition. In this example, the $\Delta k_z = 3$, and $\Delta k_y = 2$,
238   leading to a slice-wise CAIPI shift of FOV*3/16. (b) The sampling pattern can be shifted over time, as shown
239   here by a $\Delta k_z/\Delta t = 3$. The time-shifting parameter $\Delta k_z/\Delta t$ does not need to be constant, and can be
240   pseudorandom.
241

3.2 Numerical Simulations

To form a basis for both sets of numerical simulations, a single-band reference dataset was
acquired on a cylindrical phantom using a 64-channel head and neck coil. This reference
data was used to provide realistic coil sensitivities and noise covariance, and to define the
geometry of the image for the signal modelled in *Sim2*. Both *Sim1* and *Sim2* simulated the
same MB=8 acquisition with no in-plane acceleration, and 256 timepoints using 16
compressed virtual coils using the geometric coil compression scheme (Zhang et al., 2013).
249

3.2.1 Simulation 1 (*Sim1*)

In *Sim1*, the Monte Carlo simulations were performed using Gaussian white additive noise
across 1000 different complex noise realizations. To compare the proposed reconstructions
against post-hoc smoothing, linear smoothing operators $S_\kappa = (I + \kappa \nabla' \nabla)^{-1}$ were
constructed, with κ chosen empirically to match effective DOF with S_λ using Eq. 10, across a
range of λ spanning 10^{-5} to 10^2, and ($\Delta kz/\Delta ky = 3$, $\Delta kz/\Delta t = 2$) sampling. Three
different GLM design regressors were initially used to evaluate DOF and efficiency: (i) 5-
period block design, (ii) fast event-related design, (iii) white noise regressor (see Supporting
Figure S1).

3.2.1 Simulation 2 (*Sim2*)

260
In *Sim2*, inter-slice leakage was examined by simulating reconstruction of a noise-free
dataset with a voxel-wise random signal, repeated 10 times. A 1/f characteristic of BOLD
fMRI data (Zarahn et al., 1997) was used to provide a low-frequency signal model for
assessing leakage bias, because residual bias is signal-dependent (Eq. 6) in the proposed
reconstruction. To characterize leakage, in this simulation only slice 5 contained signal, such
that any reconstructed signal in the other 7 slices would have to come from signal leakage.
A range of different λ (from 0 to 10^{-2}) and sampling patterns ($\Delta kz/\Delta ky = 3$, $\Delta kz/\Delta t =$
$0, 1, 2, 3$) were explored, with efficiencies calculated using the event-related regressor only.

3.3 In Vivo Experiments

270
Three total subjects were scanned on a 3 T system (Prisma, Siemens Healthineers) using a
64-channel head and neck coil with informed consent in accordance with local ethics.
Acquisition parameters common to all experiments are: 2 mm isotropic resolution, 64 slices,
flip angle = 40º, phase encoding direction = AP, bandwidth = 2368 Hz/px. For the "MB8R1"
protocols ($\Delta kz/\Delta ky = 5$ and $\Delta kz/\Delta t = 2$), sets of 8 slices were acquired simultaneously,
with no in-plane acceleration, with TE = 38 ms and TR_{vol} = 680 ms. For the "MB8R2"
protocols ($\Delta kz/\Delta ky = 5/2$, $\Delta kz/\Delta t = 3$, $\Delta ky/\Delta t = 1$), sets of 8 slices were acquired
simultaneously, with R=2 in-plane , with TE = 30 ms and TR_{vol} = 520 ms. MB excitation pulses
were designed to minimize peak power using optimized phase schedules (Wong, 2012).
Sensitivity maps were estimated using the ESPIRiT method (Uecker et al., 2014), from a
separate single-band reference acquisition, and the same reference data was used to train
slice GRAPPA kernels. All data were compressed down to 24 virtual channels after whitening
with the coil noise covariance.

3.3.1 Experiment 1 (*Exp1*)

285
In *Exp1*, one subject was scanned using the MB8R1 and MB8R2 protocols in a resting
condition, except the MB excitations were replaced by single slice excitations, of slice 5 only.
This data was reconstructed using the full SMS reconstruction to recover 8 imaging slices
(without using any knowledge that the other 7 slices are unexcited). This allowed for an
assessment of total mean squared error ($bias^2$ + noise variance) in the unexcited slices.
Voxel-wise assessment of efficiency gains in the excited slice were also calculated, using a
reference reconstruction generated with the knowledge that only a single slice has actually
been excited, and performing a standard, non-SMS reconstruction of the same data
(without any noise amplification due to the SMS unaliasing). One minute of data for each
(96 and 128 time-points for MB8R1 and MB8R2 respectively) were acquired.

3.3.2 Experiment 2 (*Exp2*)

297
298 In *Exp2*, one subject was scanned using the same MB8R1 and MB8R2 protocols as in *Exp1*,
299 but with full MB=8 excitations. One minute of data for each (96 and 128 time-points for

300   MB8R1 and MB8R2 respectively) were acquired, which was used to estimate voxel-wise

301   maps of resting tSNR efficiency.

303   3.3.3 Experiment 3 (*Exp3*)

304   In *Exp3*, two subjects were scanned in a 5 minute, 30 s off/on block design visual task

305   experiment. One subject using the MB8R1 protocol (440 time-points), and a second subject

306   using the MB8R2 protocol (576 time-points). The functional data were analyzed using FSL

307   FEAT, with pre-whitening for noise auto-correlations (Woolrich et al., 2001).

309   3.4 SMS-Reconstruction

Eq. 4 was solved iteratively using a conjugate gradient algorithm implemented in MATLAB,

using a tolerance of 10^{-4} and a maximum number of iterations of 200. Reconstruction times

depend on the data and λ, but typically ranged between 30 minutes - 2 hours for a

96x96x8x256 slice group on a 32-core AMD Opteron computer. The g-factor and efficiency

expressions were evaluated directly, by partitioning the matrix inversions into smaller

independent subproblems by exploiting the independence of each x-location (along the

fully-sampled readout direction) and the coherent aliasing patterns when possible.

Reconstruction code for the proposed method can be found at

https://users.fmrib.ox.ac.uk/~mchiew/research. The *in vivo* data were compared with

conventional slice-GRAPPA reconstructions using a MATLAB implementation of the CMRR-

SMS (Center for Magnetic Resonance Research, University of Minnesota) reconstruction

with the LeakBlock option set. All data were magnitude transformed following image

reconstruction, which constitutes a non-linear operation on the data and alters the noise

distribution, but this effect should be negligible when tSNR > 2 (Gudbjartsson and Patz,

1995).

325   4. Results

Figure 2 - (a) Average spectra from a representative voxel (voxel 1) showing unregularized (thin blue), $\lambda = 1 \times 10^{-3}$ (dotted blue), and $\lambda = 1 \times 10^{-2}$ (thick blue) reconstructions. DOF-matching post-hoc kernel smoothing reconstructions are shown in black dotted and thick lines respectively. (b-f) Analytical plots for 3 voxels showing different behavior (blue, orange, yellow lines) are shown alongside corresponding Monte Carlo estimates (blue, orange, yellow dots), versus λ (b) Approximate DOF/N_t plots. (c) g-factor. (d-f) Exact GLM efficiency combining information from DOF and g-factors, calculated using regressors (shown in the bottom left) corresponding to (d) block design, (e) event-related design and (f) white noise respectively. DOF-matched post-hoc smoothing efficiency is plotted in dashed black, overlapping with voxel 3.

The results of *Sim1* are plotted in Figure 2. In Fig. 2a, noise spectra are plotted, normalized to the unregularized spectrum, for $\lambda = 0$, 1×10^{-3} and 1×10^{-2} reconstructions, and DOF-matching post-hoc smoothing $\kappa = (2.89 \times 10^{-2}, 1.66 \times 10^{-1})$. As total noise is the sum of squares in either the temporal or frequency domain, it is apparent that the regularized reconstructions result in less noise compared to post-hoc smoothing with the same effective DOF (blue and black lines having similar spectral profiles, but with the blue lines having lower amplitude than the corresponding black lines). As λ or κ increases, the effective DOF decreases and the coloring of the noise spectrum is more pronounced as higher frequency content is suppressed. Additional plots of reconstruction noise spectra as a function of λ can be found in Supporting Figure S2. Figs. 2b and 2c plot the variation in approximate DOF (Eq. 12) and g-factor (Eq. 8) respectively against λ, showing the expected decrease with increasing regularization across the three voxels (selected to reflect a range of behavior). Voxels 1 and 2 show high and moderate g-factor voxels respectively, while voxel 3 does not alias onto any other voxel, with a g-factor of 1.

The relative efficiency metrics (Eq. 9) in Figs. 2d-f, which reflect the ratio of the squared g-factors to the DOF, show that while a net benefit ($e_\lambda > 1$) is observed in the linear

smoothing reconstructions for any voxel that has a $g_0 > 1$, there is no gain in efficiency for
any voxel that does not alias onto another voxel, where $g_0 = 1$. Post-hoc smoothing (black
dashed line) shows the same efficiency curve as voxel 3, indicating that no efficiency gain is
realized. In all cases with an efficiency benefit, e_λ increases with λ, to a maximum in this
case near $\lambda = 10^{-1}$. As λ gets too large, the loss of DOF in the regression begins to
outweigh the reduced g-factors, and statistical power decreases. The efficiency curves for
each regressor are unique due to the dependence of DOF on the design matrix. However,
they all show very similar characteristics for low values of λ. They exhibit fairly broad peaks
in a logarithmic scale, indicating that near-optimal gains are easily achieved within an order
of magnitude of the maxima.
364

365
366 Figure 3 - (a) Single slice phantom signal simulation (*Sim2*)÷in. (b) Normalized root-mean-square error across
367 time, quantifying spatial leakage bias, with (c) g-factor (d) normalized degrees of freedom (DOF/N_t) (e) GLM
368 relative efficiency. (f) Example voxel time-courses for the voxel outlined in green in (a).
369
The single-slice digital phantom (*Sim2*) is shown in Fig. 3a. To assess residual leakage and
aliasing, the normalized root mean square error (NRMSE) across time was computed across
varying λ in Fig. 3b, by comparing the reconstructed output to the input signal. While an
unbiased reconstruction ($\lambda = 0$) is zero everywhere, with increasing λ, increased intra-slice
error and slice leakage is observed. The 95[th] percentiles for the NRMSE values in each case
were: ($\lambda = 0, NRMSE = 0$), ($1 \times 10^{-3}, 0.006$), ($5 \times 10^{-3}, 0.020$), and ($1 \times 10^{-2}, 0.029$)

respectively. In Figs. 3c-e, g-factors, DOF/N_t, and efficiency are shown. The voxel-wise
maps show that the greatest efficiency increases are in regions with the highest
unregularized g-factors, which can be seen when comparing row 1 of Fig. 3c with row 4 of
Fig. 3e. Fig. 3f plots a representative voxel time-series from the digital phantom showing
increasing smoothness in the time-courses as λ increases.
381

382
383 Figure 4 - Digital phantom characteristics with different temporal sampling patterns. (a) bias or residual
384 aliasing and slice leakage (b) g-factor, (c) DOF/N_t, (d) GLM relative efficiency.
385

In Fig. 4, the effect of different sampling patterns (at $\lambda = 5 \times 10^{-3}$) is shown against fixed,
time-independent sampling $\Delta k_z/\Delta t = 0$, and sampling with shifts of 1, 2, or 3 in the k_z
direction. Fig. 4a shows that while residual bias and slice leakage is strongly dependent on λ,
it is not noticeably different across different $\Delta k_z/\Delta t$ sampling shifts. This is related to the
fact that the aliasing pattern (FOV shift) does not change when the entire sampling pattern
is shifted across time ($\Delta k_z/\Delta t > 0$). A reduction in g-factors (Fig. 4b) with time-varying
sampling is shown, without much difference in DOF/N_t (Fig. 4c). The net effect on
efficiency (Fig. 4d), however, particularly in the ($\Delta k_z/\Delta t = 1, 2$) cases, is a result of lower g-
factors while retaining the same degrees of freedom. Despite the clear benefit of time-
varying sampling, the top row of Fig. 4d shows that there is still a small efficiency gain with
time-independent sampling.

Figure 5 - Results from *Exp1* showing the normalized RMSE computed from an SMS reconstruction of single-band excitations of slice 5, using the (a) MB8R1 and (b) MB8R2 acquisition schemes. The RMSE values are normalized to the average RMS signal in the excited slice.

Single-band excitation *in vivo* data from *Exp1* were reconstructed using the full SMS pipeline for a single subject using the MB8R1 protocol is shown in Fig. 5. Ideally, these data should only signal in the excited slice, although in practice both noise (amplified by g-factors) and slice leakage bias will contribute to the RMSE in the un-excited slices. This data was also reconstructed using conventional single-slice methods (without the slice unaliasing step), to use as a reference for the RMSE calculation, and to normalize the RMSE values. Note that the masking of the coil-sensitivities here produces a brain-like outline in the non-excited slices. The errors are notably smoother in the slice GRAPPA reconstruction outside the target slice, with the regularized reconstructions showing lower overall RMSE, outside of some high RMSE edge or boundary features in the $\lambda = 1 \times 10^{-3}$ reconstruction. The errors are visibly noise (g-factor) dominated in the slice GRAPPA (row 1) and $\lambda = 1 \times 10^{-3}$ (row 2) reconstructions, and even in the highest regularization reconstruction at $\lambda = 1 \times 10^{-2}$ (row 3), little visible aliasing of the excited slice 5 is apparent in any of the other slice locations.

Figure 6 - Representative single time-point reconstructed images (a) and tSNR efficiencies (b) for the MB8R1 protocol. The top row shows the slice GRAPPA reconstruction, followed by the ($\lambda = 0$) unregularized SENSE reconstruction, and the ($\kappa = 1.66 \times 10^{-1}$) post-hoc smoothed data. The tSNR efficiencies in the bottom 2 rows are shown as ΔtSNR efficiencies relative to slice GRAPPA. The arrows denote regions where unaliasing errors are apparent, and the corresponding regions in the tSNR efficiency maps.

The results of the tSNR efficiency experiments (*Exp2*) are shown in Figures 6 and 7. Fig. 6a shows representative images from the fully excited MB8R1 protocol, across the slice GRAPPA and regularized reconstructions. The tSNR efficiency (Fig. 6b) is slightly improved in central brain areas for the regularized ($\lambda = 1 \times 10^{-2}$) reconstruction, which is highlighted by the positive values in the ΔtSNR efficiency maps relative to slice GRAPPA. However, some regions do show reduced tSNR efficiency, particularly noticeable in regions with unaliasing errors, highlighted by the arrows in the example images and tSNR efficiency maps. The arrows denote a region with residual aliasing to incorrect sensitivity estimation of the left eye, corresponding to the most significant region of tSNR efficiency loss.

Similar results for the MB8R2 protocol are plotted in Figs. 7a and b, illustrating that the slice GRAPPA reconstruction struggles to robustly unalias the SMS data at this acceleration. However, the temporally regularized reconstructions ($\lambda = 1 \times 10^{-3}, 1 \times 10^{-1},$) result in better images and higher tSNR efficiencies. In both the MB8R1 and MB8R2 regularized reconstructions, sharp boundaries and narrow regions of tSNR efficiency loss can be

observed in the tSNR efficiency maps , further highlighting the dependence of the
reconstruction on high fidelity sensitivity estimates. To characterize the specific tSNR
efficiency benefit in the central brain areas that often suffer most from g-factor penalties,
masks were drawn over the deep gray nuclei including the basal ganglia and thalamus (see
mask in Supporting Figure S3) for the MB8R2 data. The mean ± standard deviation of the
tSNR efficiency for the various reconstructions were, slice GRAPPA: 2.74 ± 0.31, $\lambda =$
1×10^{-3}: 4.56 ± 1.03, and $\lambda = 1 \times 10^{-2}$: 9.02 ± 2.42.

445
Figure 7 - Representative single time-point reconstructed images (a) and tSNR efficiency (b) for the resting
MB8R2 protocol. The top row shows the slice GRAPPA reconstruction, followed by the $\lambda = 1 \times 10^{-3}$ and
1×10^{-2} reconstructions. (c) shows histograms of the tSNR efficiency for each dataset.

A comparison of the impact of slower acquisition schemes on tSNR efficiency is shown in
Fig. 8, computed analytically using the MB8R2 protocol and the coil sensitivities measured
from the subject in Fig. 7. Two "slow" acquisitions were simulated to determine whether the
reduction in expected noise variance due to the slower acquisition will compensate for the

corresponding reduction in temporal degrees of freedom: (i) an effective MB8R1 acquisition
by binning multiple consecutive shots together, and (ii) reducing the number of
simultaneous slices down to 4 for a MB4R2 acquisition. Both of these methods halve the
effective number of time points (and temporal DOF) in the acquisition, and are compared to
the MB8R2 protocol with $\lambda = 1 \times 10^{-2}$ regularization. To ensure a fair comparison, the
MB8R1 efficiency map was multiplied by a factor of 2 to account for the increased sampling,
and the MB4R1 efficiency map was increased by a factor of 1.96 to account for higher
steady-state signal magnitude with the longer TR (assuming TR = 480 and 960 ms for the
MB8R2 and MB4R2 respectively, and T1 = 1600 ms). The results indicate that at comparable
effective DOF of approximately 50% relative to the unregularized MB8R2 acquisition in all
cases, the $\lambda = 1 \times 10^{-2}$ MB8R2 reconstruction produces considerably higher efficiency in
the central part of the FOV, while performing similarly in the periphery.
466

467
Figure 8 - Comparison of g-factors (a-c), normalized DOF (d-f), and relative efficiency (g-i) of 3 different
acquisition schemes compared to an unregularized MB8R2 acquisition in a single representative slice. The left
column (a,d,g) shows an effective MB8R1 acquisition formed by combining consecutive time-points of the
MB8R2 acquisition. The middle column (b,e,h) shows a MB4R2 acquisition that reduces the number of
simultaneous slices acquired by half. In both the MB8R1 and MB4R2 cases, the efficiencies have been adjusted
to account for the increased sampling or T1 recovery due to the longer volume TR. These are compared to a
MB8R2 reconstruction with regularization parameter $\lambda = 1 \times 10^{-2}$ in the right column (c,f,i).
475
476

478
Figure 9 - Visual task fMRI dataset using MB8R1 protocol. (a,b) Axial and sagittal z-statistic maps ($|z| \geq 5$)
overlaid on an example image reconstructed using slice GRAPPA. (c,d) Corresponding slices to (a,b) from
$\lambda = 1 \times 10^{-2}$ regularized SENSE reconstruction. (e) z-statistic scatterplot of all voxels in the $\lambda = 1 \times 10^{-2}$
reconstruction against the slice GRAPPA, with the line of identity in orange. Points above the line indicate
higher z-statistics in the $\lambda = 1 \times 10^{-2}$ reconstruction compared to slice GRAPPA.

The output of GLM analyses on the visual task block-design experiments (*Exp3*) are shown in
Figures 9 and 10. In Fig. 9, a MB8R1 dataset is shown for slice GRAPPA and a $\lambda = 1 \times 10^{-2}$
regularized reconstructions. At this under-sampling factors, the slice GRAPPA reconstruction
is quite robust, and there is little difference in the z-stat maps between the two
reconstructions. A scatterplot of the z-statistics in Fig. 9e, however, do reveal a small
improvement in z-statistics for the proposed reconstruction over slice GRAPPA, reflecting
the increased statistical efficiency.

In Fig. 10, a MB8R2 dataset is shown for slice GRAPPA, $\lambda = 1 \times 10^{-3}$, $\lambda = 1 \times 10^{-2}$, and
post-hoc smoothing reconstructions. Here, the underlying images highlight the apparent
tSNR difference expected between the slice GRAPPA and regularized reconstructions, and
no residual aliasing is apparent in the images or in the z-statistic maps in any of the
reconstructions. While apparent false positives are similar across reconstructions, the
regularized reconstructions show much higher sensitivity in the expected primary visual
areas. The post-hoc smoothing used a kernel width parameter ($\kappa = 2.5 \times 10^{-1}$) chosen to
match the average DOF from the $\lambda = 1 \times 10^{-2}$ reconstruction. Although the underlying
image does appear less noisy, as predicted, no apparent statistical benefit is observed with
post-hoc smoothing because the variance per DOF is unchanged. Fig. 10c shows example
time-courses from a high z-stat voxel across reconstructions, showing the effect of the
reconstruction parameters on temporal fidelity. In Fig. 10d, the power spectra
corresponding to these time-courses are shown, with the relatively flat slice GRAPPA
spectrum highlighting the fact that these data are dominated by g-factor noise
amplification. Furthermore, we see the effect of smoothing as a coloring of the spectra,
along with some temporal artefacts (red circles) resulting from the time-varying sampling.

509
Figure 10 - Visual task fMRI dataset using the MB8R2 protocol. (a,b) Sagittal and axial z-statistic maps
($|z| \geq 3$) overlaid on example image reconstructed images. From left to right, each column represents slice
GRAPPA, $\lambda = 1 \times 10^{-3}$ and $\lambda = 1 \times 10^{-2}$ regularized reconstructions, and $\kappa = 2.5 \times 10^{-1}$ post-hoc
smoothed reconstructions. (c) Example time-courses from a single high z-stat voxel, across all reconstructions.
(d) Example log power spectra from the same voxel, highlighting the noise colouring resulting from the
regularization and post-hoc smoothing. Red circles denote spikes related to the residual bias and the spatio-
temporal point spread function.
517

518 ## 5. Discussion
519

Reconstruction of SMS fMRI data has predominantly been performed using time

independent, volume-by-volume reconstructions based on SENSE or GRAPPA-based

equivalents. Here, we propose the use of regularization that modulates temporal

smoothness in a spatially adaptive manner, to reduce variance (g-factor) by sacrificing

temporal degrees of freedom in a way that has a net statistical benefit. Unregularized SENSE

reconstructions are unbiased (no leakage) and contrast independent, contingent on the

fidelity of the sensitivity estimates. Slice GRAPPA approaches, with limited kernel sizes and

dependence on signal contrast changes, trade robustness for residual intra- and inter-slice

artefact, effectively allowing for small amounts of bias in the reconstructions to produce

better overall images with potentially lower mean squared error. The proposed

reconstruction makes a similar trade-off, relying on the low-frequency nature of BOLD
signals to ensure that temporal regularization results in comparable or less mean squared
error than is produced by conventional slice-GRAPPA unaliasing, while improving statistical
efficiency.
534
A natural question is whether there is any advantage to acquiring data at higher
acceleration factors and temporally smoothing in reconstruction compared to acquisition at
intrinsically lower temporal resolution. As we have shown, choosing to reduce DOF by the
adaptive smoothing reconstruction does result in higher efficiency than slower acquisition
strategies, which reduce DOF uniformly across the volume by taking more time to sample
each volume. Although the proposed method results in images with spatially varying DOF,
voxel-wise variation in efficiency is already commonplace using conventional parallel
imaging due to spatially varying g-factors. Other advantages of acquiring data at higher
acceleration factors include reduced intra-volume motion, potentially better contrast, and
reduced physiological noise aliasing when slower acquisitions do not sufficiently sample
cardiac frequencies.
546
Spatially varying smoothing is also possible using voxel-wise post-hoc kernel smoothing of
varying kernel widths. However, we have shown that post-hoc smoothing with an encoding
independent kernel can only reduce the efficiency (Liu and Frank, 2004; Smith et al., 2007).
The proposed smoothing regularized reconstruction, in contrast, depends on the encoding
(i.e. the k-space sampling pattern and coil sensitivities), and reduces noise variance beyond
what would be expected from the spectral filtering effect alone. By shifting the noise
spectra down, there is a net reduction in variance per degree of freedom, and therefore a
benefit to statistical inference. The efficiency measure presented here generalizes the tSNR
efficiency commonly used to assess fMRI time-series fidelity, by accounting for the effective
degrees of freedom, rather than acquisition time.
557
The method described in this paper is not specific to SMS-EPI, although we chose to focus
on it in the scope of this work due to its popularity for fMRI data acquisition, and the
simplicity of the sampling modifications required. The proposed reconstruction framework
does not depend on any specific features of SMS acquisition, and will benefit any 2D or 3D
acquisition strategy that can support time-varying sampling schemes. Although time-varying
sampling is not a requirement of the method, efficiency gains are significantly greater when
time-varying sampling is employed. This is analogous to FOV shifting in conventional CAIPI,
by optimizing the sampling scheme to with respect to the reconstruction constraints. In this
case, time-varying k-space samples provide more information when the smoothness
constraint effectively shares sampling information across time. As we have also shown, the
sampling pattern does not need to have a fixed shift across time, although regular sampling
does result in the highest efficiency gains. With a fixed shift across time, where $\Delta kz/\Delta t$ is
constant, the g-factors are time-independent. In the case of more general sampling

571 patterns, as with the pseudorandom sampling, the conditioning of the inverse problem
572 associated with any given time-point is dependent on the sampling of its neighbors,
573 resulting in time-dependent g-factors that can be used to assess the impact of noise
574 amplification on individual time-points.

576 The smoothing parameter λ can be selected using a number of different criteria: an upper
577 limit on the amount of spatial leakage given some signal model, minimizing mean-squared
578 error, maximum efficiency, or a lower limit on the retained DOF. The benefit of the latter
579 two choices is that they are signal independent, although the trade-off between bias and
580 variance in the reconstruction does require a signal model to fully characterize. Simulations
581 showed that while the peak efficiency points can occur at relatively high regularization
582 factors (e.g. $\lambda = 1 \times 10^{-1}$), smaller regularization factors (e.g. $\lambda = 1 \times 10^{-2}$) can still
583 provide considerable efficiency gains without noticeable bias. The spatio-temporal
584 characteristics of the residual bias depend in part on the k-space sampling scheme, and can
585 be modulated by changing the temporal sampling shifts to produce less temporally coherent
586 residual aliasing, although this can cause issues with data analysis due to non-stationary
587 noise resulting from the time-varying g-factors.

589 While the assumption of low-frequency signal content was used to justify the use of the
590 temporal regularization by reducing the impact of signal leakage, the efficiency gain only
591 describes the effects on the residual white Gaussian thermal noise, and does not account
592 for noise autocorrelations or physiological noise. While consideration of a more
593 comprehensive fMRI noise model would provide more accurate statistical efficiency
594 modelling, e.g. by including spatio-temporal noise characteristics of sub-second TR
595 acquisitions (Bollmann et al., 2018), they would substantially increase noise model
596 complexity. The presence of other noise sources diminishes the impact of the efficiency
597 gains calculated here, although in g-factor limited regimes where the noise is thermally
598 dominated, the assumed thermal noise model is asymptotically correct. However,
599 incorporating more sophisticated noise modelling and better informed constraints for the
600 regularized time-series image reconstruction, as well as interactions between regularization
601 factors and acquisition parameters such as volume TR would be a natural extension of this
602 work.

604 In this work, we focus on statistical efficiency (reducing noise variance per degree of
605 freedom) as the primary metric of reconstruction quality, rather than optimizing directly for
606 minimizing noise or maximizing SNR. We explicitly construct the efficiency metric expression
607 by an end-to-end consideration of the fMRI dataset, from noisy multi-coil k-space to the
608 variance of the GLM estimator and the tSNR efficiency, which is possible due to the linear
609 reconstruction and analysis framework. While we do not directly optimize for other fMRI
610 analysis methods, such as independent component or seed-correlation analysis for resting

611 state fMRI, reduced noise variance per DOF should also be beneficial, although this has not
612 yet been evaluated.
613

614 ## 6. Conclusion
615 A linear reconstruction method for SMS-EPI fMRI data has been developed based on
616 temporal smoothing regularization in a spatially adaptive, encoding-dependent way. This
617 reduces noise for improved statistical power and efficiency compared to conventional slice-
618 GRAPPA reconstructions.

Appendix A

The reconstruction is a linear transform of the measured k-space and a noise term:

$$\hat{x} = (A'A + \lambda\nabla'\nabla)^{-1}A'(k+n) \qquad \text{[A1]}$$

The noise model we assume is zero-mean, Gaussian white noise, with $n = N(0,\sigma)$, and we further assume that the noise has been whitened using the coil noise covariance, so that:

$$E[nn'] = \sigma^2 I \qquad \text{[A2]}$$

The mean or expectation of the estimate (because the noise is zero mean):

$$\bar{x} = E[\hat{x}] = (A'A + \lambda\nabla'\nabla)^{-1}A'k \qquad \text{[A3]}$$

and the mean-subtracted estimate is a function of the noise:

$$(\hat{x} - \bar{x}) = (A'A + \lambda\nabla'\nabla)^{-1}A'n \qquad \text{[A4]}$$

We calculate the g-factor from the voxel-wise variance of the linear estimator:

$$Var(\hat{x}) = E[(\hat{x} - \bar{x})(\hat{x} - \bar{x})'] = E[(A'A + \lambda\nabla'\nabla)^{-1}A'nn'A(A'A + \lambda\nabla'\nabla)^{-1}] \qquad \text{[A5]}$$

Since the noise term is the only stochastic part of this expression:

$$Var(\hat{x}) = (A'A + \lambda\nabla'\nabla)^{-1}A'(\sigma^2 I)A(A'A + \lambda\nabla'\nabla)^{-1} \qquad \text{[A6]}$$

The square root of the entries along the diagonal of $Var(\hat{x})$ reflect the standard deviation of the noise expected in each voxel. The g-factor is calculated as the ratio of this standard deviation with the standard deviation expected from a fully-sampled acquisition. Since the fully-sampled, un-regularized variance in each voxel m is $\sigma^2/(A'A)_{m,t}$, the ratio then becomes:

$$g_\lambda(m,t) = \sqrt{\frac{\sigma^2((A'A + \lambda\nabla'\nabla)^{-1}A'A(A'A + \lambda\nabla'\nabla)^{-1})_{m,t}}{\frac{\sigma^2}{(A'A)_{m,t}}}} \qquad \text{[A7]}$$

$$= \sqrt{((A'A + \lambda\nabla'\nabla)^{-1}A'A(A'A + \lambda\nabla'\nabla)^{-1})_{m,t}(A'A)_{m,t}} \qquad \text{[A8]}$$

$$= \sqrt{(S_\lambda(A'A)^{-1}S_\lambda')_{m,t}(A'A)_{m,t}} \qquad \text{[A9]}$$

where $S_\lambda = (A'A + \lambda\nabla'\nabla)^{-1}A'A$, and $X_{m,t}$ denotes the diagonal element of X corresponding to the m^{th} voxel and t^{th} time-point.

For the operator $\nabla'\nabla$: if the data matrix X were vectorized with each voxel's time-course vertically concatenated, $\nabla'\nabla$ would be a block diagonal matrix where each block is a matrix with mostly 2 on the diagonals, and -1 on the neighboring off-diagonals. An example $\nabla'\nabla$ diagonal block for a 5-time point input is given as:

$$\nabla'\nabla = \begin{pmatrix} 1 & -1 & 0 & 0 & 0 \\ -1 & 2 & -1 & 0 & 0 \\ 0 & -1 & 2 & -1 & 0 \\ 0 & 0 & -1 & 2 & -1 \\ 0 & 0 & 0 & -1 & 1 \end{pmatrix} \qquad [\text{A10}]$$

We define ∇ using non-circular boundary conditions (i.e. only finite differences between
neighboring points were taken, not including the difference between the first and last time-
points). In practice, this matrix was not constructed, but the action of $\nabla'\nabla$ on X was
implemented by subtracting temporally shifted versions of X to a scaled version of itself,
using MATLAB's `circshift` function (and taking care of the boundary conditions
appropriately).

Appendix B

675 In the context of a univariate GLM analysis, a regression coefficient $\hat{\beta}$ can be expressed as a
676 function of S_λ as:

678
$$\hat{\beta} = \left(\widetilde{D}'\widetilde{D}\right)^{-1}\widetilde{D}'S_\lambda \tilde{x} \qquad [\text{B1}]$$

680 where $\widetilde{D} = S_\lambda D$ is the smoothed design matrix, assumed to be a single column. More
681 complex contrasts can be accommodated without any loss of generality by a simple
682 transformation (Smith et al., 2007).

684 From Worsley and Friston (Worsley and Friston, 1995), the variance of the regression
685 coefficient $\hat{\beta}$ is:

687
$$var(\hat{\beta}) = \epsilon^2 \left(\widetilde{D}'\widetilde{D}\right)^{-1}\widetilde{D}'S_\lambda S_\lambda'\widetilde{D}\left(\widetilde{D}'\widetilde{D}\right)^{-1} \qquad [\text{B2}]$$

689 with

691
$$\epsilon^2 = \frac{g^2\sigma^2}{DOF} \qquad [\text{B3}]$$

693 and

695
$$DOF = tr_m\left(\left(I - \widetilde{D}\left(\widetilde{D}'\widetilde{D}\right)^{-1}\widetilde{D}'\right)S_\lambda S_\lambda'\right) \qquad [\text{B4}]$$

with $tr_m(\cdot)$ used to indicate that values across time for a given voxel m are summed. In Eq.
[B3], we make use of the fact that following reconstruction, the noise variance is amplified
by the square of the g-factor. Note that in Worsley et al., the design matrix and smoothing
operators are denoted by G and K respectively.

Then benefit of regularization, in the context of the GLM, can be quantified by the relative
efficiency of the estimator, where a more efficient estimator has increased sensitivity and
statistical power. It is defined by the ratio of the variances of the estimators in the
unregularized ($\lambda = 0$) and regularized cases:

707
$$e_\lambda = \frac{var(\hat{\beta}_0)}{var(\hat{\beta}_\lambda)} = \left(\frac{g_0}{g_\lambda}\right)^2 \frac{tr_m\left(\left(I - \tilde{D}\left(\tilde{D}'\tilde{D}\right)^{-1}\tilde{D}'\right)S_\lambda S_{\lambda'}\right)}{tr_m\left(\left(I - D\left(D'D\right)^{-1}D'\right)\right)} \frac{\left(D'D\right)^{-1}}{\left(\tilde{D}'\tilde{D}\right)^{-1}\tilde{D}'S_\lambda S_{\lambda'}\tilde{D}\left(\tilde{D}'\tilde{D}\right)^{-1}} \qquad \text{[B5]}$$

709 which dictates whether the decrease in noise amplification outpaces the loss in effective
710 DOF. When $e_\lambda > 1$, a net benefit in GLM efficiency is observed.
711

Acknowledgements

713 The authors would like to thank Steen Moeller for providing the slice GRAPPA
714 reconstruction code. This research was funded by the Royal Academy of Engineering (MC,
715 RF201617\16\23) and the Wellcome Trust (KLM, 202788/Z/16/Z). The Wellcome Centre for
716 Integrative Neuroimaging is supported by core funding from the Wellcome Trust
717 (203139/Z/16/Z).

References

Aggarwal, P., Shrivastava, P., Kabra, T., Gupta, A., 2017. Optshrink LR + S: accelerated fMRI
reconstruction using non-convex optimal singular value shrinkage. Brain Inform 4,
65–83. https://doi.org/10.1007/s40708-016-0059-x
Barth, M., Breuer, F., Koopmans, P.J., Norris, D.G., Poser, B.A., 2016. Simultaneous multislice
(SMS) imaging techniques. Magn Reson Med 75, 63–81.
https://doi.org/10.1002/mrm.25897
Blaimer, M., Breuer, F.A., Seiberlich, N., Mueller, M.F., Heidemann, R.M., Jellus, V., Wiggins,
G., Wald, L.L., Griswold, M.A., Jakob, P.M., 2006. Accelerated volumetric MRI with a
SENSE/GRAPPA combination. J Magn Reson Imaging 24, 444–450.
https://doi.org/10.1002/jmri.20632
Blaimer, M., Choli, M., Jakob, P.M., Griswold, M.A., Breuer, F.A., 2013. Multiband phase-
constrained parallel MRI. Magn Reson Med 69, 974–980.
https://doi.org/10.1002/mrm.24685
Bollmann, S., Puckett, A.M., Cunnington, R., Barth, M., 2018. Serial correlations in single-
subject fMRI with sub-second TR. NeuroImage 166, 152–166.
https://doi.org/10.1016/j.neuroimage.2017.10.043
Breuer, F.A., Blaimer, M., Heidemann, R.M., Mueller, M.F., Griswold, M.A., Jakob, P.M.,
2005. Controlled aliasing in parallel imaging results in higher acceleration
(CAIPIRINHA) for multi-slice imaging. Magn Reson Med 53, 684–691.
https://doi.org/10.1002/mrm.20401
Cauley, S.F., Polimeni, J.R., Bhat, H., Wald, L.L., Setsompop, K., 2014. Interslice leakage
artifact reduction technique for simultaneous multislice acquisitions. Magn Reson
Med 72, 93–102. https://doi.org/10.1002/mrm.24898

Chavarrías, C., Abascal, J.F.P.J., Montesinos, P., Desco, M., 2015. Exploitation of temporal
redundancy in compressed sensing reconstruction of fMRI studies with a prior-based
algorithm (PICCS). Medical physics 42, 3814–3821.
https://doi.org/10.1118/1.4921365
Chiew, M., Graedel, N.N., Mcnab, J.A., Smith, S.M., Miller, K.L., 2016. Accelerating functional
MRI using fixed-rank approximations and radial-cartesian sampling. Magn Reson
Med 76, 1825–1836. https://doi.org/10.1002/mrm.26079
Chiew, M., Smith, S.M., Koopmans, P.J., Graedel, N.N., Blumensath, T., Miller, K.L., 2015. k-t
FASTER: Acceleration of functional MRI data acquisition using low rank constraints.
Magn Reson Med 74, 353–364. https://doi.org/10.1002/mrm.25395
Fessler, J.A., Rogers, W.L., 1996. Spatial resolution properties of penalized-likelihood image
reconstruction: space-invariant tomographs. Image Processing, IEEE Transactions on
5, 1346–1358. https://doi.org/10.1109/83.535846
Griswold, M.A., Jakob, P.M., Heidemann, R.M., Nittka, M., Jellus, V., Wang, J., Kiefer, B.,
Haase, A., 2002. Generalized autocalibrating partially parallel acquisitions (GRAPPA).
Magn Reson Med 47, 1202–1210. https://doi.org/10.1002/mrm.10171
Gudbjartsson, H., Patz, S., 1995. The rician distribution of noisy mri data. Magnetic
Resonance in Medicine 34, 910–914. https://doi.org/10.1002/mrm.1910340618
Hoge, W.S., Setsompop, K., Polimeni, J.R., 2018. Dual-polarity slice-GRAPPA for concurrent
ghost correction and slice separation in simultaneous multi-slice EPI. Magnetic
Resonance in Medicine 80, 1364–1375. https://doi.org/10.1002/mrm.27113
Jung, H., Ye, J.C., Kim, E.Y., 2007. Improved k-t BLAST and k-t SENSE using FOCUSS. Phys.
Med. Biol 52, 3201–3226. https://doi.org/10.1088/0031-9155/52/11/018
Kim, T.H., Haldar, J.P., 2015. SMS-LORAKS: Calibrationless simultaneous multislice MRI using
low-rank matrix modeling. Presented at the Proceedings - International Symposium
on Biomedical Imaging, pp. 323–326. https://doi.org/10.1109/ISBI.2015.7163878
Koopmans, P.J., 2017. Two-dimensional-NGC-SENSE-GRAPPA for fast, ghosting-robust
reconstruction of in-plane and slice-accelerated blipped-CAIPI echo planar imaging.
Magnetic Resonance in Medicine 77, 998–1009. https://doi.org/10.1002/mrm.26179
Larkman, D.J., Hajnal, J.V., Herlihy, A.H., Coutts, G.A., Young, I.R., Ehnholm, G., 2001. Use of
multicoil arrays for separation of signal from multiple slices simultaneously excited. J
Magn Reson Imaging 13, 313–317.
Li, X., Ma, X., Li, L., Zhang, Z., Zhang, X., Tong, Y., Wang, L., Sen Song, Guo, H., 2018. Dual-
TRACER: High resolution fMRI with constrained evolution reconstruction.
Neuroimage 164, 172–182. https://doi.org/10.1016/j.neuroimage.2017.02.087
Liu, T.T., Frank, L.R., 2004. Efficiency, power, and entropy in event-related FMRI with
multiple trial types: Part I: theory. NeuroImage 21, 387–400.
https://doi.org/10.1016/j.neuroimage.2003.09.030
Moeller, S., Vu, A.T., Auerbach, E., Ugurbil, K., Yacoub, E., 2014. RO extended FOV
SENSE/GRAPPA for multiband imaging with FOV shift, in: Proceedings of the 22nd
Annual Meeting of ISMRM, 4396. Presented at the Proceedings of the 22nd Annual
Meeting of ISMRM, p. 1.
Moeller, S., Yacoub, E., Olman, C.A., Auerbach, E., Strupp, J., Harel, N., Ugurbil, K., 2010.
Multiband multislice GE-EPI at 7 tesla, with 16-fold acceleration using partial parallel
imaging with application to high spatial and temporal whole-brain fMRI. Magn Reson
Med 63, 1144–1153. https://doi.org/10.1002/mrm.22361

Park, S., Park, J., 2017. SMS-HSL: Simultaneous multislice aliasing separation exploiting
hankel subspace learning. Magn Reson Med 78, 1392–1404.
https://doi.org/10.1002/mrm.26527
Petrov, A.Y., Herbst, M., Andrew Stenger, V., 2017. Improving temporal resolution in fMRI
using a 3D spiral acquisition and low rank plus sparse (L+S) reconstruction.
Neuroimage 157, 660–674. https://doi.org/10.1016/j.neuroimage.2017.06.004
Pruessmann, K.P., Weiger, M., Scheidegger, M.B., Boesiger, P., 1999. SENSE: sensitivity
encoding for fast MRI. Magn Reson Med 42, 952–962.
Ramb, R., Binter, C., Schultz, G., Assländer, J., Breuer, F., Zaitsev, M., Kozerke, S., Jung, B.,
2015. A g-factor metric for k-t-GRAPPA- and PEAK-GRAPPA-based parallel imaging.
Magn Reson Med 74, 125–135. https://doi.org/10.1002/mrm.25386
Setsompop, K., Gagoski, B.A., Polimeni, J.R., Witzel, T., Wedeen, V.J., Wald, L.L., 2012.
Blipped-controlled aliasing in parallel imaging for simultaneous multislice echo
planar imaging with reduced g-factor penalty. Magn Reson Med 67, 1210–1224.
https://doi.org/10.1002/mrm.23097
Singh, V., Tewfik, A.H., Ress, D.B., 2015. Under-sampled functional MRI using low-rank plus
sparse matrix decomposition, in: ICASSP 2015 - 2015 IEEE International Conference
on Acoustics, Speech and Signal Processing (ICASSP). Presented at the ICASSP 2015 -
2015 IEEE International Conference on Acoustics, Speech and Signal Processing
(ICASSP), IEEE, pp. 897–901. https://doi.org/10.1109/ICASSP.2015.7178099
Smith, S., Jenkinson, M., Beckmann, C., Miller, K.L., Woolrich, M.W., 2007. Meaningful
design and contrast estimability in FMRI. Neuroimage 34, 127–136.
https://doi.org/10.1016/j.neuroimage.2006.09.019
Uecker, M., Lai, P., Murphy, M.J., Virtue, P., Elad, M., Pauly, J.M., Vasanawala, S.S., Lustig,
M., 2014. ESPIRiT - An eigenvalue approach to autocalibrating parallel MRI: Where
SENSE meets GRAPPA. Magn Reson Med 71, 990–1001.
Weizman, L., Miller, K.L., Eldar, Y.C., Chiew, M., 2017. PEAR: PEriodic And fixed Rank
separation for fast fMRI. Medical physics 44, 6166–6182.
https://doi.org/10.1002/mp.12599
Wong, E.C., 2012. Optimized phase schedules for minimizing peak RF power in simultaneous
multi-slice RF excitation pulses, in: Proceedings of the 20th Annual Meeting of
ISMRM. Presented at the Proceedings of the 20th Annual Meeting of ISMRM.
Woolrich, M.W., Ripley, B.D., Brady, M., Smith, S.M., 2001. Temporal autocorrelation in
univariate linear modeling of FMRI data. Neuroimage 14, 1370–1386.
https://doi.org/10.1006/nimg.2001.0931
Worsley, K.J., Friston, K.J., 1995. Analysis of fMRI time-series revisited--again. Neuroimage 2,
173–181. https://doi.org/10.1006/nimg.1995.1023
Zahneisen, B., Ernst, T., Poser, B.A., 2014. SENSE and simultaneous multislice imaging. Magn
Reson Med 74, 1356–1362. https://doi.org/10.1002/mrm.25519
Zarahn, E., Aguirre, G.K., D'Esposito, M., 1997. Empirical analyses of BOLD fMRI statistics. I.
Spatially unsmoothed data collected under null-hypothesis conditions. Neuroimage
5, 179–197.
Zhang, T., Pauly, J.M., Vasanawala, S.S., Lustig, M., 2013. Coil compression for accelerated
imaging with Cartesian sampling. Magn Reson Med 69, 571–582.
https://doi.org/10.1002/mrm.24267

Zhu, K., Kerr, A., Pauly, J.M., 2012. Autocalibrating CAIPIRINHA: Reformulat- ing CAIPIRINHA
as a 3d problem, in: Proceedings of the 20th Annual Meeting of ISMRM. Presented at
the Proceedings of the 20th Annual Meeting of ISMRM.
Zong, X., Lee, J., John Poplawsky, A., Kim, S.-G., Ye, J.C., 2014. Compressed sensing fMRI
using gradient-recalled echo and EPI sequences. Neuroimage 92C, 312–321.
https://doi.org/10.1016/j.neuroimage.2014.01.045
840