Title

Precision phase targeting of event-related oscillations using real-time closed-loop TMS-EEG

Authors

Malte R. Güth[1,2]**,** Drew B. Headley[1] & Travis E. Baker[1]

Affiliations

[1]Center for Molecular and Behavioral Neuroscience, Rutgers University, Newark, USA

[2]Graduate Program in Neuroscience, Rutgers University, Newark, USA

Correspondence: Malte R. Güth, mgueth@umn.edu, 312 Church St SE, Minneapolis, MN 55455

Acknowledgements: We thank G. Karpov, N. Lalta, M.-H. Lin, and J. Stringfellow for assistance

with the data collection.

Funding: Rutgers Busch Biomedical Grant Program and Rutgers Research Council Grant. MRG

was supported by the Graduate Program in Neuroscience at Rutgers University.

Conflict of Interest: The authors declare no conflict of interest.

ABSTRACT

Current closed-loop TMS-EEG systems rely on phase prediction algorithms that require highly periodic signals, limiting their ability to target brief, event-related activity. We developed a real-time closed-loop (RT-CL) TMS-EEG system that directly detects oscillatory phase without prediction, enabling phase-locked stimulation within microseconds. We validated the system against a prediction-based approach using simulated sine waves and human EEG data (N=18), without active TMS delivery. Across frequency-modulated sweeps and spontaneous occipital alpha oscillations (eyes-open vs. closed), the RT-CL system achieved higher triggering probability (16-24%) and reduced the phase error variability (2-10°). Importantly, when targeting event-related theta oscillations during two spatial navigation tasks, RT-CL produced ~18% higher triggering probabilities and ~19° lower phase error variability than phase prediction. These findings validate the RT-CL system for probing phase-dependent mechanisms during active cognition and the development of precision TMS interventions targeting pathological brain states.

INTRODUCTION

Transcranial magnetic stimulation (TMS) offers a unique combination of millimeter spatial resolution and millisecond temporal precision for non-invasively modulating neural activity in humans. This capability positions TMS as a tool for both probing causal relationships between neural oscillations and cognitive functions, and developing therapeutic interventions for neurological and psychiatric disorders (Gaynes et al., 2014; Lam et al., 2008). However, conventional open-loop TMS protocols deliver stimulation without regard to ongoing brain states, potentially missing optimal windows for neuromodulation. Closed-loop stimulation approaches address this limitation by triggering stimulation based on real-time EEG features, such as oscillatory phase, frequency, and power (Wischnewski et al., 2024; C. Zrenner et al., 2016; C. Zrenner & Ziemann, 2024). Accumulating evidence demonstrates that the responsiveness to TMS applied over the motor and visual cortex critically depends on when it is delivered relative to ongoing neural dynamics (Bergmann et al., 2012; Dugué et al., 2011; Fakche et al., 2022), thereby motivating the application of closed-loop approaches that synchronize stimulation with the phase of spontaneous EEG oscillations (Schaworonkow et al., 2019; Stefanou et al., 2018; Wischnewski et al., 2022; C. Zrenner et al., 2018).

To achieve phase-targeted stimulation with sufficient speed, current closed-loop approaches predict oscillatory phase from the preceding hundreds of milliseconds of EEG data, in some cases after calibrating parameters on prior baseline recordings (Mansouri et al., 2017; Rodriguez Rivero & Ditterich, 2021; Shirinpour et al., 2020, 2025; Wodeyar et al., 2021; C. Zrenner et al., 2018). However, because prediction requires stable oscillatory properties, these methods are optimized for spontaneous oscillations with high periodicity but not for transient oscillations that emerge for only a few cycles following sensory and cognitive events (e.g., event-related potentials, phase-locked oscillatory activity). Moreover, EEG processing delays on PCs (e.g., data streaming, algorithm execution) and phase distortions (e.g., causal filtering) prevent real-time detection of oscillatory phase, forcing current closed-loop methods to rely on forward prediction of the phase (Chang et al., 2023; Iwama et al., 2024; C. Zrenner et al., 2016). This restricts both mechanistic investigation of phase-dependent neural processes and development of interventions targeting pathological brain states during active cognition.

To overcome these limitations, we developed a novel real-time closed-loop (RT-CL) EEG-TMS system using field programmable gate arrays (FPGAs), which enable microsecond-

scale processing of multiple EEG channels in parallel and precise temporal control for phase-

locked stimulation. This system was initially developed for animal studies in which optogenetic

stimulation was triggered by amygdala gamma cycles during memory consolidation (Kanta et

al., 2019). Importantly, this approach successfully modulated amygdala-dependent

consolidation of spatial memory processes. Building on this, we adapted the system for non-

invasive human application, enabling real-time detection and phase-locked TMS targeting of

transient event-related oscillations (EROs) during cognitive tasks. To validate the RT-CL

system, we compared its triggering probability and phase error with a phase prediction

algorithm (PPA-CL) on simulated sine waves, spontaneous occipital alpha oscillations (eyes-

open, eyes-closed), and EROs in the theta band during two spatial navigation reward tasks. To

note, all validation was performed without TMS delivery to isolate system performance from

stimulation artifacts. This validation study established RT-CL's capacity to reliably detect and

trigger TMS pulses to transient oscillatory signals during active cognition in real-time.

METHODS

Experiment 1: Validation using Frequency-modulated chirps.

To demonstrate the real-time FPGA system's and prediction algorithm's capabilities on

a signal with a known ground truth, a function generator (AFG1062, Tektronix) was used to

create a sinusoidal signal fed into the RT-CL and PPA-CL systems. Given the typical range of

the EEG frequency spectrum and the frequencies of interest, a chirp signal descending in

frequency from 50 Hz to 1 Hz lasting approximately 240 seconds was produced. The complete

slow chirp was run once for peak, trough, ascending, and descending phase targeting. While

running real-time triggering with the RT-CL system, these signals were saved to disk, so trigger

timings could be analyzed and the chirp could be used for offline triggering with the PPA-CL

system.

Experiment 2: Validation using spontaneous alpha and event-related theta oscillations.

Participants. For the human experiment, 25 undergraduate students ($M_{Age} = 25 \pm 2.76$

years; 5 female) were recruited from Rutgers University Newark and the New Jersey Institute

of Technology. Written informed consent was obtained from all participants. They were

compensated with course credit as well as a monetary bonus equivalent to their memory

performance in the T-maze and the Linear Track Memory (LTM) task. All subjects were
screened with self-report questionnaires regarding demographic information, handedness
(Oldfield, 1971), spatial navigation abilities (Hegarty et al., 2002), neurological and psychiatric
history, their vision, and TMS permissibility (i.e., pregnancy, metal or medical implants, etc.).
Only subjects who were right-handed, between 18 and 55 years of age, had normal-to-corrected
vision, and had no history of neurological or psychiatric disorders or medication were allowed
to participate. Seven subjects were excluded due to poor online EEG data quality or incomplete
data in one of the three EEG recordings, bringing the final sample to 18 subjects (M_{Age} = 24.2
± 2.51 years; 5 female). The study was approved by the Rutgers University Ethics Committee
Board and was conducted in accordance with the ethical standards described in the 1964
Declaration of Helsinki.

Protocol. To induce spontaneous occipital alpha oscillations, participants were seated in
a relaxed position in front of a black computer screen (Figure 1A). Over the course of ten
minutes, they underwent a series of alternating one-minute blocks of resting with their eyes
open or closed. Each pair of conditions (eyes-open and eyes-closed) formed a two-minute cycle.
A brief auditory cue was presented at the start of each 2.5-second transition interval to instruct
participants to switch between the two states. This protocol was designed to elicit robust and
alternating modulation of alpha-band activity over occipital regions (Barry et al., 2007). The
first block (one minute eyes-open, one minute eyes-closed) was used as a calibration period for
the closed-loop targeting parameters (i.e., amplitude threshold). For the remaining four blocks,
triggering alternated between ascending, peak, descending, and trough targeting. The order of
phase targets was randomized and counterbalanced across subjects. Closed-loop triggering was
focused on occipital alpha power (9-12 Hz) at the central occipital electrode Oz (Figure 1A).

Subjects then performed two spatial navigation tasks used to elicit a burst of theta
oscillations (4-10 Hz) over posterior electrodes, with larger amplitudes over right hemisphere
channel PO8 (Baker & Holroyd, 2009, 2013; Güth et al., 2025). This right posterior theta (RPT)
response is characterized by spectral power peaking in the theta band around 200 ms following
task-related feedback onset, and consistent with a partial phase reset of the oscillation (Güth et
al., 2025). First, participants performed 250 trials of a virtual T-maze task across four blocks
(50 practice trials, 50 trials per block). In this task, participants navigated a virtual T-maze by
choosing to go left or right in order to maximize monetary rewards (5 cents). Each trial began

with a view down the stem of the maze toward a junction. After 1000 ms, a green double arrow
appeared, prompting a choice: left (button 1, left index finger) or right (button 2, right index
finger). Upon response, participants advanced to the chosen alley and, after 1000 ms, received
visual feedback - an apple for reward or an orange for no reward - displayed for another 1000
ms. Feedback was randomly assigned with a 50% probability, unknown to participants (Figure
1B, left). The practice trials were used as another calibration period to ensure that closed-loop
triggering for RPT was set at an appropriate level for each subject. The four subsequent blocks
were used to target the same four phase targets as before in a different counterbalanced order.

Following the T-maze task, subjects performed 120 trials of the LTM task (Figure 1B,
right, Güth & Baker, 2026). Subjects were placed at the beginning of a straight track lined with
uniquely colored and textured pillar pairs. On every trial, subjects started moving down the
track after a green go sign appeared and they pressed a button to begin (400 ms ISI between
pillars). At each pillar, subjects paused for 150 ms and a reward (apple) or no reward cues
(orange) appeared for 350 ms in the middle of the track, each also eliciting RPT. At the end of
the path, subjects stopped at a wall and were presented with a list of previously seen and
distractor pillars. They were asked to indicate which cues they saw at a given pillar and could
earn 5 cents per correctly identified reward cue location. For more details see Güth & Baker
(2026). As before, closed-loop targeting was conducted in a counterbalanced order with one out
of four phase targets being chosen for each block of 30 trials. In both the LTM and T-maze task
triggering was enabled for from 50 ms before to 450 ms after the onset of feedback and reward
cues respectively (Figure 1C).

Figure 1. Tasks and triggering signals. A: Schematic of the paradigm for triggering on spontaneous alpha oscillations. Subjects alternated between closing and opening their eyes for one minute at a time. A tone indicated when to switch and triggering started 2.5 s after the onset of the tone. Triggering was performed on alpha oscillations recorded at Oz highlighted in teal on the 2D montage plot and the example traces separated by eyes-open (top) and eyes-closed (bottom). **B**: Overview of a single trial in the T-maze task (left) and LTM task (right). Teal rectangles highlight critical events for TMS triggering. On each trial subjects were placed in a T-shaped maze and chose to go left or right to search for rewards, which elicited RPT upon discovering feedback stimuli. On each trial of the LTM task subjects ran down a linear track towards a wall, passing five pairs of pillars where a reward (apple) or no reward cue (orange) appeared in the center of the track. **C**: Event-locked triggering time windows for the T-maze and LTM task. Triggering was performed on RPT recorded at channel PO8. The teal time window (-50 ms to 450 ms) on single-trial examples for trials from the respective tasks shows when triggering was enabled.

Real-time closed-loop triggering

Real-time TMS-EEG synchronization is constrained by hardware- and software-related latencies (Iwama et al., 2024; Wang et al., 2019), necessitating systems to apply forward prediction and to estimate an expected delay from signal detection to TMS pulse delivery. These delays are highly dependent on the experimental setup and arise from multiple sources. Intrinsic delays due to the EEG data transfer to PCs (<1-2 ms, Usakli & Gencer, 2007; C. Zrenner et al., 2018, 2026) or the output of a transistor-to-transistor logic pulse to trigger the TMS machine

(1-2 ms, Shirinpour et al., 2020; C. Zrenner et al., 2018) can be accounted for. More variable

software-related delays such as data streaming with Lab Streaming Layer (~6-12 ms, Kothe et

al., 2025), TCP/IP (e.g., 50-100 ms, Bártolo, 2015), or integrated acquisition and processing

platforms like Open Ephys (total system delay ~35 ms, Sousa et al., 2022) introduce latency

jitters that differ across implementations . Further, event-related, non-stationary signals like

phase resetting can extend common prediction algorithms' convergence period . These variable

delays can prevent accurate estimation of the total delay which has a substantial influence on

the accuracy of the algorithm (Chang et al., 2023). The RT-CL system addresses this limitation

by processing analog signals directly on the FPGA, which enables parallel signal processing

with microsecond-scale latency (Kanta et al., 2019). Unlike typical phase prediction

implementations that process data through sequential stages, FPGAs perform all signal

processing operations in dedicated hardware circuits. This eliminates the serial processing

bottlenecks inherent to prediction-based approaches.

The closed-loop algorithm compiled on the FPGA was designed to track the amplitude

and phase of EEG oscillations in real-time, acquire data, stream it to a PC for monitoring, and

trigger TMS pulses. All programming was done in LabVIEW (National Instruments, Austin,

TX, USA) and then compiled on a National Instruments USB-7845R reconfigurable data

acquisition system based on a Xilinx Kintex-7 K70T FPGA. EEG data analysis, streaming, and

acquisition was sampled at 1 kHz. While running, a fast direct memory access buffer between

the PC and the FPGA was used to stream EEG signals for monitoring. Triggering was focused

on channel Oz for alpha and PO8 for RPT, since in previous studies PO8 yielded the highest

RPT power (Baker & Holroyd, 2009, 2013; Güth et al., 2025).

The triggering algorithm compiled on the FPGA consisted of four modules (Figure 2,

top): First, the analogue EEG signal was passed through a bank of Butterworth filters with 2^{nd}

(for low pass) and 4^{th} (for high pass) orders (Figure 2, module 1a). Each pair of filters acted as

a band pass filter centered around a targeted frequency with a bandwidth of 2 Hz (alpha: 10 and

12 Hz; RPT: 4, 6, 8, and 10 Hz). Whichever filter band for amplitude detection had the highest

power was selected at that moment. Applying multiple filters, and selecting between them in

real-time, circumvented the problem of signal distortion as one moved away from the center

frequency, as would be the case for a single bandpass filter encompassing these frequencies. In

addition, the oscillation's phase was analyzed using a second set of 1^{st} order Butterworth filters

for the same bands, allowing for a more precise phase estimation (Figure 2, module 1b). The

lower order minimized phase distortion in the passband.

Second, peaks, troughs, descending, and ascending phases were identified based on sign

changes of the signal waveform and its first derivative (Figure 2, module 2). For each frequency

band, the third module searched the first 5 ms after the occurrence of a peak or a trough for the

maximum absolute value of the amplitude filter bank to assess the signal amplitude (Figure 2,

module 3). Third, the amplitude and phase of the strongest band were selected and sent to the

last module for triggering. Picking the amplitude and phase of the strongest band ensured that

the filter with the smallest phase error and the most pronounced signal was selected. The filter

banks could be weighted to bias them towards detection in the theta or alpha bands. Fourth, the

final module controlled whether a trigger was sent out after the targeted phase and frequency

had been detected and the amplitude had exceeded the set threshold (Figure 2, module 4). An

event gating mechanism based on digital trigger inputs from the computer displaying the T-

maze and LTM task ensured that a TMS pulse could only be triggered when a relevant task

event was detected (i.e., feedback in the T-maze and reward cue in LTM task).

215
216 **Figure 2. Closed-loop algorithms**. The top row contains the RT-CL and the bottom row the
217 PPA-CL. The middle row depicts the event gating logic, which was implemented in both
218 algorithms. RT-CL phase analysis modules (from left to right): Bandpass filter bank centered

around four theta frequencies for amplitude and phase estimation, phase detection, amplitude thresholding, and triggering logic. Triggering can be conditioned on the presence of event codes. The event gating mechanism used for the T-maze and LTM task added event code criteria and time constraint from a task like the feedback presentation. **C**: Single bandpass filter (9-12 Hz and 4-10 Hz) followed by fitting sinusoid waveform (blue) on Hilbert transform of EEG signal. Overlaid in red is the raw EEG signal. Triggering is enabled in crunch time window (blue vertical lines) on extrapolated sinusoid, reaching target criteria.

EEG acquisition

The RT-CL system consists of FPGAs performing the signal processing and triggering, which require analogue EEG input signals. Contemporary EEG systems typically digitize signals and use USB protocols to transfer the data to a PC. Thus, an EEG8 amplifier (Contact Precision Instruments, Glastonbury, UK) was used to preserve the signal in its analogue form and to forward the data to the FPGA. EEG data were recorded from a custom montage of five channels including Afz as ground. Oz (for alpha) and PO8 (for RPT) served as trigger channels and were referenced online to the average of M1 and M2. PO7 was included as a backup channel. Data were acquired using Ag/AgCl ring electrodes mounted in a nylon cap with abrasive conductive gel (Falk Minow Services, Herrsching), sampled at 1 kHz, and sent directly to the FPGA. To reduce electrical noise, the amplifier was housed in a shielded container with the FPGA hardware. An online bandpass filter (0.1-100 Hz) and 60 Hz notch filter (50 dB/octave) were applied.

Prediction-based triggering

To compare our approach to a conventional method for EEG phase-locked triggering, we used a phase prediction algorithm implemented in the EventIDE software environment (v. Feb 21, 2021, Okazo Lab, Achterom, Netherlands) to detect different phases of alpha and theta activity offline after data were recorded. A Fast Fourier Transform was continuously applied to the signal to estimate frequency spectra. This algorithm performed phase-locked triggering by fitting a sine wave onto the Hilbert transform of a buffered bandpass filtered EEG signal (alpha: high-pass: 9 Hz, low-pass: 12 Hz; RPT: high-pass: 4 Hz, low-pass: 10 Hz) and by extrapolating the signal into the future (Figure 2, bottom). The forecast window was set to 200 ms and triggers for the same phase targets as for the RT-CL were sent within a crunch time window of 26 ms after the current sample.

The same calibration periods were used to set the amplitude threshold, the maximum
model prediction error, and other triggering parameters. When adjusting parameters in either
closed-loop system, this adjustment can be made in favor of sensitivity (i.e., more but less
accurate triggering) or selectivity (i.e., less but more accurate triggering). To ensure
comparability between the two closed-loop runs, we attempted to match the level of sensitivity
by adjusting parameters for the offline PPA-CL runs until the number of pulses was similar to
the number of pulses in the RT-CL run. These included the power threshold and the minimum
model fit between the sine wave and the analytic signal.

Analysis of closed-loop triggering performance
For preprocessing of the human EEG data, time windows were trimmed to the respective
triggering time windows. The signal was bandpass filtered with a causal second-order
Butterworth filter in the targeted frequency range (9-12 Hz, 4-10 Hz) for the instantaneous
frequency estimation and with a first-order Butterworth filter in a wider range (1-20 Hz) for the
instantaneous phase estimation. All stimulated phase angles and all true alpha and theta cycles
exceeding the amplitude threshold used during the respective sessions were then extracted. Two
parameters were analyzed to evaluate triggering performance for each system and subject: the
triggering probability (i.e., sensitivity; Figure 3A) and the standard deviation of the phase errors
(SDPE, i.e., precision; Figure 3B). Triggering probability was calculated by dividing the
number of correctly detected phase targets of a given frequency by all true cycles of that
frequency and phase target, yielding the probability of detecting and triggering on a single cycle.
Phase error statistics were calculated as the circular mean and standard deviation of the
difference between the targeted phase angle and the stimulated phase angles across trials.
For the simulated chirp (Experiment 1), precision was assessed as the standard deviation
across frequencies of the theta band, since each specific frequency between 1-50 Hz only
occurred once. For the human EEG data (Experiment 2), the circular mean and standard
deviation of the phase error while targeting theta and alpha were computed across trials for each
subject. Performance differences between systems in triggering probability were assessed using
two-tailed Wilcoxon signed-rank tests for Experiment 1 (treating individual theta frequencies
as observations) and two-tailed paired t-tests for Experiment 2 (using individual subject
averages as observations).

Data and code availability

Analysis scripts, documentations, and the LabVIEW programming for the RT-CL

system can be found in the github repository for this study:

https://github.com/BakerlabRutgers/rt_cl. All further code and data are available upon

reasonable request.

RESULTS

Experiment 1: Frequency-modulated chirp

For RT-CL, triggering probability remained consistently high across the targeted theta

band, with ~100% triggering probability from 3.5-4 Hz until 10 Hz for every phase target (Figure

3C, left). On average, a single theta cycle was triggered with a probability of 90.6% for peak

targets, 91.7% for troughs, 91.3% for the descending phase, and 92.7% for the ascending phase.

The slight deviations from 100% triggering probability occurred only outside the targeted range at

the lower bound of the 4 Hz filter. When disregarding bins below 4 Hz, average triggering

probabilities reached 98.6% (peak: 95.1%, trough: 99.6%, descending: 100%, ascending: 100%).

In contrast, the PPA-CL system reached 100% triggering probability only around 5 Hz (92% at 4

Hz), with consistent performance in the 5-7 Hz range (91-94% triggering probability). However,

at the lower and upper edges of the desired range (4 Hz and 10 Hz), the probability of stimulating

a given cycle dropped substantially, falling below 10% at the upper edge of 10 Hz. Averaged

across the theta frequency range, the PPA-CL system achieved triggering probabilities of 73.2%

for peaks, 75.6% for troughs, 74.5% for the descending phase, and 77.2% for the ascending phase.

A Wilcoxon signed-rank test comparing the average triggering sensitivity across phase targets

between RT-CL and PPA-CL revealed significantly higher sensitivity for RT-CL ($W = 0$, $z = -2.934$, $p = .003$, $r_{rb} = 1$).

For phase precision, the SDPE of the RT-CL and PPA-CL systems was calculated (Figure

3C, right). The RT-CL system demonstrated low variability in phase error, with SDPEs of 7° for

peaks, 7.5° for troughs, 9.7° for the descending phase, and 9.7° for the ascending phase. This

variability remained relatively unaffected by frequency, staying consistent across the theta range.

Triggering with PPA-CL yielded slightly higher variability: 9.4° for peaks, 10.1° for troughs, 11.6°

for the descending phase, and 10.7° for the ascending phase. This larger phase error stemmed from

a frequency-dependent increase in stimulated phase, resulting in higher phase variability for the
PPA-CL system with a variability ratio of 1.59 (PPA-CL divided by RT-CL). Comparing average
SDPEs across phase targets, the RT-CL system achieved 19% higher precision than the PPA-CL
system. Notably, both systems showed relatively consistent performance across phase targets
(triggering probability: RT-CL 90.6-92.7%, PPA-CL 73.2-77.2%; SDPE: RT-CL 7-9.7°, PPA-CL
9.4-11.6°). Therefore, statistics for the Experiment 2 are presented for the average across phase
targets. A complete table of performance measures by task, system, and phase target can be found
in Supplementary Table 1.

321
Figure 3. Triggering performance on simulated slow chirps. **A**: Schematic of theta detection
and triggering, showing six simulated theta cycles (orange), their instantaneous phase angle
(black), and the timing of the TMS triggers targeting troughs. Triggering probability was
calculated as the ratio of real phase targets followed by a TMS trigger to the total number of
real targeted phases. **B**: Phase timings of triggers sent with the RT-CL (blue) and PPA-CL (red)
system targeting troughs and peaks overlaid on a theta sine wave. Phase angles are expressed
as deviations from the targeted phase in degrees. The phase error was calculated as the standard
deviation of phase timings across triggers. **C**: Right plot depicts triggering probability on a
single cycle for RT-CL (blue) and PPA-CL (red) systems on the slow chirp (1-50 Hz) for each
frequency target. Left plot shows the phase error across log-scaled frequency bins in degrees
for RT-CL (blue) and PPA-CL (red) systems and for each phase target. Targets are plotted in
the same row as on the left.

Experiment 2: Human EEG data

Alpha oscillations. Figure 4A depicts an example trial targeting peaks of occipital alpha

oscillations using RT-CL. Triggering occurred consistently within a few milliseconds of the

occurrence of the phase target, demonstrating the system's ability to detect and respond to

spontaneous oscillatory activity in real-time. The two systems also differed in their timing relative

to the targeted phase (Figure 4B). The PPA-CL system delivered triggers before the targeted phase

occurred, with an average phase error of -13.4° (negative values indicating early triggering), while

the RT-CL system delivered triggers with an average phase error of 15.8°, occurring after the

targeted phase as designed, $t(17) = 4.46$, $p = 0.0003$, $d = 1.08$. This timing difference is evident in

the example trace (Figure 4A) and in the circular histograms of phase errors across all subjects and

phase targets (Figure 4B). Visual inspection of these histograms confirmed narrower distributions

for the RT-CL system across all phase targets, indicating more consistent triggering performance.

For phase precision, measured as the SDPE, the RT-CL system demonstrated significantly lower

variability than the PPA-CL system, $t(17) = 8.45$, $p = 1.72 \times 10^{-7}$, $d = 2.05$ (Figure 4C, right). The

RT-CL system showed an average SDPE of 29.7° (SD = 4.35°), compared to 40.1° (SD = 2.7°)

for the PPA-CL system, representing approximately 10° higher precision. In terms on sensitivity,

triggering probability was significantly higher for RT-CL than for PPA-CL, $t(17) = 3.6$, $p = .002$,

$d = 0.86$ (Figure 4C, left). Specifically, the RT-CL system detected approximately 70% of alpha

cycles in the EEG signal (SD = 10.8%), compared to 59.3% (SD = 5.7%) detected by the PPA-CL

system.

Figure 4. Triggering performance for spontaneous alpha oscillations. **A**: The top trace shows an example of human alpha EEG signal (9-12 Hz) at Oz while targeting peaks using the RT-CL. Blue vertical lines mark the triggering timings. Below is the same time window convolved with a 5-cycle Morlet wavelet showing raw power values, highlighting alpha power increases. **B**: Circular histograms show the distributions of the phase error (deviation of triggered phase from targeted phase) for all subjects and for each closed-loop system (RT-CL: blue, PPA-CL: red) separated by phase target (left to right). Positive values indicate triggering after the target phase occurred, negative values before. Black, vertical lines mark the point of 0° deviation from the targeted phase angle. **C**: Triggering sensitivity (left) and the standard

deviation of the phase error (SDPE in degrees, right) for the RT-CL (blue) and PPA-CL (red)
systems. Raincloud plots are composed of a density distribution and boxplot for the individual
subject values marked by the dots in each scatterplot. Green circles inside the boxplot show the
mean value of the distribution and gray diamonds highlight outlier values. Higher triggering
probability and lower SDPE indicate better performance. **: *p < 0.01*, ****: *p < 0.0001*

T-maze RPT oscillations. Figure 5A depicts a single-trial triggering example and

average time-frequency transformation from one subject with RT-CL trigger timings.

Consistent with our previous reports (Baker et al., 2015; Güth et al., 2025), robust increases in

RPT at right posterior channels (maximal at P8) were detected following feedback presentation.

Similar to alpha oscillations, the two systems differed in timing relative to the targeted phase.

The RT-CL system delivered triggers shortly after the targeted phase ($M_{phase\ error}$: 26.2°), while

the PPA-CL delivered triggers before the targeted phase ($M_{phase\ error}$: -24.7°, Figure 5B). This

temporal difference reflects the RT-CL system's direct phase detection versus the PPA-CL's

system's predictive approach. For triggering precision, RT-CL achieved significantly lower

phase variability than PPA-CL, $t(17) = 6.96$, $p = 4.59 \times 10^{-6}$, $d = 1.8$ (Figure 5B and 5C). The

RT-CL system had an average SDPE of 42.6° (SD = 4.5°), compared to 55.6° (SD = 4.6°) for

the PPA-CL, representing approximately 13° higher precision. Phase error histograms (Figure

5B) showed narrower distributions for the RT-CL system, revealing more consistent triggering.

Regarding triggering sensitivity, the RT-CL system demonstrated significantly higher

triggering probability than the PPA-CL system, $t(17) = 2.8$, $p = .014$, $d = 0.72$ (Figure 5C, left).

RT-CL detected an average of 83% of RPT cycles (SD = 13.7%), compared to 72.1% (SD =

9.8%) for PPA-CL, representing an 11% advantage.

Figure 5. Triggering performance for RPT in the T-maze task. **A**: A single example trial from a subject performing the virtual T-maze task, time-locked to the feedback presentation. Blue bars highlight trigger timings on that trial while targeting 4-10 Hz peaks using RT-CL. Topography (4-10 Hz, 150-200 ms) and spectrogram (channel P8) show the total power results after convolving all trials of the same subject as above with a 7-cycle complex Morlet wavelet and calculating the power change as a ratio of the baseline from -300 ms to -200 ms pre-stimulus. **B**: Circular histograms of the phase error (deviation of triggered phase from targeted phase) for targeting RPT in the T-maze task structured the same as in Figure 4B (RT-CL: blue, PPA-CL: red). **C**: Analogous raincloud plots to Figure 4C showing the triggering probability

(left) and the standard deviation of the phase error (SDPE, right). As before, higher triggering
probability and lower SDPE indicate better performance. *: p < 0.05, ****: p < 0.0001

LTM RPT oscillations. Similar to the T-maze task, feedback-related cues in the LTM

task elicited robust RPT increases at right posterior channels. A single-trial triggering example

with RT-CL and RPT power averaged across trials are shown in Figure 6A. As in previous

analyses, the two systems differed in timing relative to the targeted phase. The RT-CL system

delivered triggers shortly after the targeted phase ($M_{phase error}$: 26.2°), while the PPA-CL system

delivered triggers before the targeted phase ($M_{phase error}$: -24.7°; Figure 6B). For phase precision,

triggering with RT-CL achieved significantly lower phase variability than with PPA-CL, $t(17)$

= 13.19, p = 2.33 × 10^{-10}, d = 3.2 (Figure 6B and 6C, right). RT-CL showed an average SDPE

of 41.6° (SD = 2.8°), compared to 60.3° (SD = 4.5°) for PPA-CL, representing approximately

19° higher precision. Phase error histograms (Figure 6B) revealed substantially narrower

distributions for RT-CL, with the performance advantage most pronounced in this task featuring

continuous movement and greater temporal variability of RPT across events. In terms of

sensitivity, the RT-CL system demonstrated significantly higher triggering probability than the

PPA-CL system, $t(17)$ = 6.38, p = 6.84 × 10^{-6}, d = 1.55 (Figure 6C, left). The RT-CL system

detected an average of 85.1% of RPT cycles (SD = 10.5%), compared to 67% (SD = 3%) for

the PPA-CL system, representing a 18% advantage – the largest sensitivity difference observed

across all tasks and frequency bands.

Figure 6. Triggering performance for RPT in the LTM task. **A**: A single example trial from a subject performing the LTM task, time-locked to the feedback presentation. Blue bars highlight trigger timings while targeting 4-10 Hz peaks using RT-CL. The topography (4-10 Hz, 200-250 ms) and spectrogram (channel P8) are the average of all trials after convolving them with the same wavelet as described for Figure 6A. **B**: Circular histograms of the phase error (deviation of triggered phase from targeted phase) for targeting RPT in the LTM task structured the same as in Figure 4B and 5B (RT-CL: blue, PPA-CL: red). **C**: Analogous raincloud plots to Figure 4C and 5C showing the triggering probability and the standard

deviation of the phase error (SDPE), with higher sensitivity and lower SPDE indicating better
performance. ***: $p < 0.001$, ****: $p < 0.0001$

DISCUSSION

Closed-loop TMS-EEG represents a critical advance for investigating phase-dependent
mechanisms during motor, sensory and cognitive processes, and for developing precision
neuromodulation interventions. This approach targets the periodic windows of excitability defined
by specific phases of ongoing oscillations. Motor-evoked potentials from single-pulse TMS are
largest at the trough or rising phase of mu oscillations, with roughly one Hedges' g separating peak
and trough excitability (Wischnewski et al., 2024). However, these foundational studies based on
phase prediction methods have targeted spontaneous oscillations during rest, and targeting the
phase of transient oscillations in real-time during cognitive tasks has yet to be achieved with high
precision. The RT-CL system validated here achieves direct phase detection through microsecond-
scale hardware processing, enabling reliable targeting of transient event-related oscillations that
emerge for only a few cycles during task-relevant processing.

We show that across simulated signals, spontaneous alpha oscillations, and event-related
theta activity during spatial navigation, RT-CL demonstrated consistently higher sensitivity (70-
86%) and precision (29-42° SDPE) than PPA-CL. When targeting theta cycles in the simulated
chirp (i.e., continuously frequency-modulated signal), both systems achieved high performance
levels, but only the RT-CL system had consistent triggering performance across the whole theta
band. Using PPA-CL on spontaneous alpha oscillations, we detected roughly 59% of alpha
cycles with a precision level of 40°, confirming that our results match benchmarks established
across multiple laboratories using diverse prediction algorithms for the theta and alpha bands
(40-70°, Gordon et al., 2021; Shirinpour et al., 2020, 2025; Wodeyar et al., 2021; C. Zrenner et
al., 2018). When using RT-CL, triggering probability was approximately 10% higher and the
SDPE was 10° lower, showcasing more consistent triggering on spontaneous oscillations.
Finally, we found the most substantial difference between systems when targeting the phases of
RPT related to memory encoding. The RT-CL system was 11-18% more sensitive and 13°-19°
more precise relative to the PPA-CL system, establishing the RT-CL system's higher precision
for testing causal hypotheses about oscillatory phase during active cognitive.

These capabilities of RT-CL versus PPA-CL reflect a fundamental distinction that
determines optimal applications for each method. Whereas the RT-CL system depends on fast

online detection, phase prediction relies on the assumption that ongoing neuronal oscillations are sufficiently stable to allow accurate phase extrapolation. Other phase prediction systems report lower average phase errors than we achieved, but with larger variability (Shirinpour et al., 2020, 2025), suggesting that on spontaneous oscillations predictions may get closer to the desired phase at the cost of consistency. To date, prediction-based algorithms have demonstrated excellent performance for targeting spontaneous oscillations with high periodicity and signal-to-noise ratio, such as sensorimotor mu rhythms during rest (Schaworonkow et al., 2019; Stefanou et al., 2018; Wischnewski et al., 2022; Wodeyar et al., 2021; C. Zrenner et al., 2018). However, prediction-based approaches face fundamental challenges when targeting EROs that exhibit abrupt phase shifts (e.g., phase resetting) and amplitude fluctuations, precisely the signals implicated in memory encoding, decision-making, and cognitive control.

EROs such as RPT and frontal midline theta, as well as event-related potentials (e.g., N100, N200, P300), have been proposed to arise from partial phase resetting, a stimulus-induced phase shift of ongoing oscillations accompanied by an increase in power (Baker & Holroyd, 2013; Güth et al., 2025; Luu et al., 2004; Yeung et al., 2004, 2007). The abrupt phase shift disrupts the temporal continuity phase extrapolation depends on, reducing prediction reliability at precisely the moment when the signal becomes behaviorally relevant. Although novel systems have started addressing this issue by using state space modeling for predictions (Wodeyar et al., 2021), a more common autoregressive approach avoids theta phase resetting to prevent inaccurate triggering (Gordon et al., 2021). Beyond phase resetting, the inherent trial-to-trial variability in onset latency and amplitude of event-related potentials and EROs (Arazi et al., 2017; Bagshaw & Warbrick, 2007; Michalewski et al., 1986) introduces signal variance, complicating prediction accuracy. This variability is reflected in the lower performance of PPA-CL when targeting RPT in the LTM task instead of the T-maze: Due to a single trial in the LTM task involving movement between five locations along a track, RPT may become less stereotyped across events. Thus, only RT-CL maintained strong performance for EROs characterized by trial-to-trial variability. By contrast, PPA-CL performance degraded as predictability decreased.

The mechanistic insights enabled by RT-CL have direct translational implications for precision neuromodulation. Beyond investigating basic neuroscience questions, RT-CL enables a unique approach to clinical intervention: targeting pathological brain states as they emerge during

clinically-relevant cognitive or emotional processing. Current FDA-approved repetitive TMS
(rTMS) protocols for depression, obsessive-compulsive disorder, and smoking cessation apply
rTMS at fixed frequencies independent of ongoing brain activity, yielding response rates of 50-
78% (Wischnewski et al., 2024). Closed-loop approaches synchronizing stimulation with
individual brain states promise to enhance these outcomes by delivering neuromodulation when
circuits are maximally responsive. Early clinical trials demonstrate feasibility of phase-specific
rTMS synchronized to individualized alpha rhythms, producing EEG alpha band entrainment in
depression (Faller et al., 2022; George et al., 2023; B. Zrenner et al., 2020). Matching the rTMS
pulse frequency or inter-burst intervals to EEG oscillations requires continuous oscillations for 2-
5 s trains, which is more likely to occur during rest than during cognitive and sensory tasks. Hence,
phase prediction approaches may be well-suited for this goal. Conversely, RT-CL specifically
enables targeting transient activity during active symptom provocation or cognition – for example,
synchronizing TMS with RPT oscillations evoked by stimulus encoding during the LTM task
(Güth, 2024). This "state-and-context-dependent" precision represents a shift from previous
closed-loop rTMS trials, with stimulation parameters optimized not only to oscillatory brain state
but to the context evoking symptoms.

With novel methods come several considerations that should inform future applications of
this approach. RPT during spatial navigation represents a challenging target characterized by a low
signal-to-noise ratio and substantial trial-to-trial variability compared to occipital alpha
oscillations. While this validates the capabilities of RT-CL under demanding conditions, future
work should assess whether the observed performance generalizes to other established event-
related EEG signals, such as frontal midline theta during cognitive control tasks (Cavanagh et al.,
2010). These signals exhibit varying degrees of periodicity and phase consistency, potentially
affecting optimal triggering approaches. Additionally, the present validation examined triggering
performance without TMS pulse delivery to avoid confounding TMS-induced EEG artifacts.
Further research is needed to test whether precise event-related and phase-dependent stimulation
with RT-CL produces predicted behavioral and neural effects.

Building on this validation, several applications of RT-CL technology merit investigation.
First, targeting higher-frequency oscillations (30-60 Hz gamma) would enable testing phase-
amplitude coupling mechanisms proposed to coordinate large-scale networks (Colgin, 2015;
Ursino & Pirazzini, 2024). While existing phase prediction systems have been successfully used

to trigger on faster frequency bands such as human beta rhythms (Guo et al., 2025; Shirinpour et

al., 2020, 2025; Wischnewski et al., 2022), gamma oscillations exhibit pronounced transient burst

characteristics potentially unsuitable for prediction-based methods. Therefore, the direct detection

of the RT-CL approach may prove particularly valuable for gamma oscillations. Second,

implementing complex therapeutic protocols, such as EEG-synchronized rTMS protocols, would

advance translational applications. Finally, integrating RT-CL with multi-modal brain state

assessment through individualized MRI-based targeting or peripheral physiological markers could

enable even more precise identification of optimal neuromodulation windows (Soleimani et al.,

2023). As closed-loop technologies transition from research tools to clinical interventions, the

demonstrated robustness for transient, variable neural signals positions the RT-CL system as a key

technology for the next generation of precision psychiatry and neurology treatments.

529 Conclusions

The RT-CL compared to the PPA-CL system demonstrated superior and consistent

performance for targeting transient EROs through direct phase detection enabled by FPGA-based

RT-CL processing EEG data within microseconds. By overcoming fundamental limitations of

phase prediction for brief, variable neural signals during active cognition, RT-CL establishes both

a methodological foundation for investigating causal phase-dependent mechanisms and a potential

platform for developing precision neuromodulation interventions that target pathological brain

states during symptom-relevant processing. The capability to reliably synchronize brain

stimulation with the fleeting neural dynamics of active human cognition and emotion could open

new horizons for understanding brain function and for treating neuropsychiatric disease.

540 REFERENCES

Arazi, A., Gonen-Yaacovi, G., & Dinstein, I. (2017). The Magnitude of Trial-By-Trial Neural

Variability Is Reproducible over Time and across Tasks in Humans. *Eneuro*, *4*(6),

ENEURO.0292-17.2017. https://doi.org/10.1523/ENEURO.0292-17.2017

Bagshaw, A. P., & Warbrick, T. (2007). Single trial variability of EEG and fMRI responses to

visual stimuli. *NeuroImage*, *38*(2), 280–292.

https://doi.org/10.1016/j.neuroimage.2007.07.042

Baker, T. E., & Holroyd, C. B. (2009). Which Way Do I Go? Neural Activation in Response to

Feedback and Spatial Processing in a Virtual T-Maze. *Cerebral Cortex*, *19*(8), Article 8.

https://doi.org/10.1093/cercor/bhn223

Baker, T. E., & Holroyd, C. B. (2013). The topographical N170: Electrophysiological evidence

of a neural mechanism for human spatial navigation. *Biological Psychology*, *94*(1),

Article 1. https://doi.org/10.1016/J.BIOPSYCHO.2013.05.004

Baker, T. E., Umemoto, A., Krawitz, A., & Holroyd, C. B. (2015). Rightward-biased

hemodynamic response of the parahippocampal system during virtual navigation.

Scientific Reports, *5*(1), Article 1. https://doi.org/10.1038/srep09063

Barry, R. J., Clarke, A. R., Johnstone, S. J., Magee, C. A., & Rushby, J. A. (2007). EEG

differences between eyes-closed and eyes-open resting conditions. *Clinical*

Neurophysiology, *118*(12), Article 12.

Bártolo, M. (2015, December 17). Getting EEG data in real-time for BCI, Neurofeedback and

more [Brainproducts.com]. *Brain Products Press Release*.

https://pressrelease.brainproducts.com/real-time-eeg/

Bergmann, T. O., Mölle, M., Schmidt, M. A., Lindner, C., Marshall, L., Born, J., & Siebner, H.

R. (2012). EEG-Guided Transcranial Magnetic Stimulation Reveals Rapid Shifts in

Motor Cortical Excitability during the Human Sleep Slow Oscillation. *The Journal of*

Neuroscience, *32*(1), Article 1. https://doi.org/10.1523/JNEUROSCI.4792-11.2012

Cavanagh, J. F., Frank, M. J., Klein, T. J., & Allen, J. J. B. (2010). Frontal theta links prediction

errors to behavioral adaptation in reinforcement learning. *NeuroImage*, *49*(4), Article 4.

https://doi.org/10.1016/J.NEUROIMAGE.2009.11.080

Chang, Y.-C., Chao, P.-H., Kuan, Y.-M., Huang, C.-J., Chen, L.-F., Mao, W.-C., Su, T.-P.,

Chen, S.-H., & Wei, C.-S. (2023). Delay Analysis in Closed-Loop EEG Phase-Triggered

Transcranial Magnetic Stimulation. *2023 45th Annual International Conference of the*

IEEE Engineering in Medicine & Biology Society (EMBC), 1–4.

https://doi.org/10.1109/EMBC40787.2023.10340744

Colgin, L. L. (2015). Theta–gamma coupling in the entorhinal–hippocampal system. *Current*

Opinion in Neurobiology, *31*, 45–50. https://doi.org/10.1016/j.conb.2014.08.001

Dugué, L., Marque, P., & VanRullen, R. (2011). The Phase of Ongoing Oscillations Mediates

the Causal Relation between Brain Excitation and Visual Perception. *The Journal of*

Neuroscience, *31*(33), Article 33. https://doi.org/10.1523/JNEUROSCI.1161-11.2011

Fakche, C., VanRullen, R., Marque, P., & Dugué, L. (2022). α Phase-Amplitude Tradeoffs

Predict Visual Perception. *eNeuro*, *9*(1), Article 1.

https://doi.org/10.1523/ENEURO.0244-21.2022

Faller, J., Doose, J., Sun, X., Mclntosh, J. R., Saber, G. T., Lin, Y., Teves, J. B., Blankenship, A.,

Huffman, S., Goldman, R. I., George, M. S., Brown, T. R., & Sajda, P. (2022). Daily

prefrontal closed-loop repetitive transcranial magnetic stimulation (rTMS) produces

progressive EEG quasi-alpha phase entrainment in depressed adults. *Brain Stimulation*,

15(2), 458–471. https://doi.org/10.1016/j.brs.2022.02.008

Gaynes, B. N., Lloyd, S. W., Lux, L., Gartlehner, G., Hansen, R. A., Brode, S., Jonas, D. E.,

Evans, T. S., Viswanathan, M., & Lohr, K. N. (2014). Repetitive Transcranial Magnetic

Stimulation for Treatment-Resistant Depression: A Systematic Review and Meta-

Analysis. *The Journal of Clinical Psychiatry*, *75*(5), 29758.

https://doi.org/10.4088/JCP.13r08815

George, M. S., Huffman, S., Doose, J., Sun, X., Dancy, M., Faller, J., Li, X., Yuan, H., Goldman,

R. I., Sajda, P., & Brown, T. R. (2023). EEG synchronized left prefrontal transcranial

magnetic stimulation (TMS) for treatment resistant depression is feasible and produces an

entrainment dependent clinical response: A randomized controlled double blind clinical

trial. *Brain Stimulation*, *16*(6), 1753–1763. https://doi.org/10.1016/j.brs.2023.11.010

Gordon, P. C., Dörre, S., Belardinelli, P., Stenroos, M., Zrenner, B., Ziemann, U., & Zrenner, C.

(2021). Prefrontal Theta-Phase Synchronized Brain Stimulation With Real-Time EEG-

Triggered TMS. *Frontiers in Human Neuroscience*, *15*.

https://doi.org/10.3389/fnhum.2021.691821

Guo, X., Pogosyan, A., Debarros, J., He, S., Wehmeyer, L., Rodriguez Plazas, F., Wendt, K.,

Yin, Z., Raslan, A., Hart, T., Morgante, F., Denison, T., Pereira, E. A., Ashkan, K.,

Wang, S., & Tan, H. (2025). Flexible and stable cycle-by-cycle phase-locked deep brain

stimulation system targeting brain oscillations in the management of movement

disorders. *Brain Stimulation*, *18*(5), 1705–1717. https://doi.org/10.1016/j.brs.2025.09.002

Güth, M. R. (2024). *Multimodal Imaging and Closed-Loop Brain Stimulation of Human Theta Oscillations During Spatial Navigation* [Ph.D.]. https://www.proquest.com/docview/3132656067/abstract/95E5663545C848D1PQ/1

Güth, M. R., & Baker, T. E. (2026). *Right posterior theta facilitates memory encoding and recall during virtual navigation* (p. 2026.02.24.707786). bioRxiv. https://doi.org/10.64898/2026.02.24.707786

Güth, M. R., Reid, A., Zhang, Y., Huntgeburth, S. C., Mill, R. D., Dagher, A., Kerns, K., Holroyd, C. B., Petrides, M., Cole, M. W., & Baker, T. E. (2025). Right posterior theta reflects human parahippocampal phase resetting by salient cues during goal-directed navigation. *Imaging Neuroscience*. https://doi.org/10.1162/IMAG.a.105

Hegarty, M., Richardson, A. E., Montello, D. R., Lovelace, K., & Subbiah, I. (2002). Development of a self-report measure of environmental spatial ability. *Intelligence*, *30*(5), Article 5. https://doi.org/10.1016/S0160-2896(02)00116-2

Iwama, S., Takemi, M., Eguchi, R., Hirose, R., Morishige, M., & Ushiba, J. (2024). Two common issues in synchronized multimodal recordings with EEG: Jitter and latency. *Neuroscience Research*, *203*, 1–7. https://doi.org/10.1016/j.neures.2023.12.003

Kanta, V., Pare, D., & Headley, D. B. (2019). Closed-loop control of gamma oscillations in the amygdala demonstrates their role in spatial memory consolidation. *Nature Communications*, *10*(1), Article 1.

Kothe, C., Shirazi, S. Y., Stenner, T., Medine, D., Boulay, C., Grivich, M. I., Artoni, F., Mullen, T., Delorme, A., & Makeig, S. (2025). The lab streaming layer for synchronized multimodal recording. *Imaging Neuroscience*, *3*, IMAG.a.136. https://doi.org/10.1162/IMAG.a.136

Lam, R. W., Chan, P., Wilkins-Ho, M., & Yatham, L. N. (2008). Repetitive Transcranial Magnetic Stimulation for Treatment-Resistant Depression: A Systematic Review and Metaanalysis. *The Canadian Journal of Psychiatry*, *53*(9), 621–631. https://doi.org/10.1177/070674370805300909

Luu, P., Tucker, D. M., & Makeig, S. (2004). Frontal midline theta and the error-related negativity: Neurophysiological mechanisms of action regulation. *Clinical Neurophysiology*, *115*(8), 1821–1835. https://doi.org/10.1016/j.clinph.2004.03.031

Mansouri, F., Dunlop, K., Giacobbe, P., Downar, J., & Zariffa, J. (2017). A Fast EEG

Forecasting Algorithm for Phase-Locked Transcranial Electrical Stimulation of the

Human Brain. *Frontiers in Neuroscience*, *11*. https://doi.org/10.3389/fnins.2017.00401

Michalewski, H. J., Prasher, D. K., & Starr, A. (1986). Latency variability and temporal

interrelationships of the auditory event-related potentials (N1, P2, N2, and P3) in normal

subjects. *Electroencephalography and Clinical Neurophysiology/Evoked Potentials*

Section, *65*(1), 59–71. https://doi.org/10.1016/0168-5597(86)90037-7

Oldfield, R. C. (1971). The assessment and analysis of handedness: The Edinburgh inventory.

Neuropsychologia, *9*(1), Article 1. https://doi.org/10.1016/0028-3932(71)90067-4

Rodriguez Rivero, C., & Ditterich, J. (2021). A user-friendly algorithm for adaptive closed-loop

phase-locked stimulation. *Journal of Neuroscience Methods*, *347*, 108965.

https://doi.org/10.1016/j.jneumeth.2020.108965

Schaworonkow, N., Triesch, J., Ziemann, U., & Zrenner, C. (2019). EEG-triggered TMS reveals

stronger brain state-dependent modulation of motor evoked potentials at weaker

stimulation intensities. *Brain Stimulation*, *12*(1), Article 1.

https://doi.org/10.1016/j.brs.2018.09.009

Shirinpour, S., Alekseichuk, I., Güth, M. R., Haigh, Z., Wischnewski, M., & Opitz, A. (2025).

Bayesian Temporal Prediction: A Robust Algorithm for Real-time EEG Phase-dependent

Brain Stimulation. *IEEE Transactions on Bio-Medical Engineering*, *PP*,

10.1109/TBME.2025.3589970. https://doi.org/10.1109/TBME.2025.3589970

Shirinpour, S., Alekseichuk, I., Mantell, K., & Opitz, A. (2020). Experimental evaluation of

methods for real-time EEG phase-specific transcranial magnetic stimulation. *Journal of*

Neural Engineering, *17*(4), 046002. https://doi.org/10.1088/1741-2552/ab9dba

Soleimani, G., Nitsche, M. A., Bergmann, T. O., Towhidkhah, F., Violante, I. R., Lorenz, R.,

Kuplicki, R., Tsuchiyagaito, A., Mulyana, B., Mayeli, A., Ghobadi-Azbari, P., Mosayebi-

Samani, M., Zilverstand, A., Paulus, M. P., Bikson, M., & Ekhtiari, H. (2023). Closing

the loop between brain and electrical stimulation: Towards precision neuromodulation

treatments. *Translational Psychiatry*, *13*(1), Article 1. https://doi.org/10.1038/s41398-

023-02565-5

Sousa, B. M. D., De Oliveira, E. F., Beraldo, I. J. D. S., Polanczyk, R. S., Leite, J. P., & Lopes

Aguiar, C. (2022). An open-source, ready-to-use and validated ripple detector plugin for

the Open Ephys GUI. *Journal of Neural Engineering*, *19*(4), 046040.

https://doi.org/10.1088/1741-2552/ac857b

Stefanou, M.-I., Desideri, D., Belardinelli, P., Zrenner, C., & Ziemann, U. (2018). Phase

Synchronicity of μ-Rhythm Determines Efficacy of Interhemispheric Communication

Between Human Motor Cortices. *The Journal of Neuroscience*, *38*(49), Article 49.

https://doi.org/10.1523/JNEUROSCI.1470-18.2018

Ursino, M., & Pirazzini, G. (2024). Theta–gamma coupling as a ubiquitous brain mechanism:

Implications for memory, attention, dreaming, imagination, and consciousness. *Current*

Opinion in Behavioral Sciences, *59*, 101433.

https://doi.org/10.1016/j.cobeha.2024.101433

Usakli, A. B., & Gencer, N. G. (2007). USB-Based 256-Channel Electroencephalographic Data

Acquisition System for Electrical Source Imaging of the Human Brain. *Instrumentation*

Science & Technology, *35*(3), 255–273. https://doi.org/10.1080/10739140701255581

Wang, Y., Markham, C., & Deegan, C. (2019). Assessing the time synchronisation of EEG

systems. *2019 30th Irish Signals and Systems Conference (ISSC)*, 1–6.

https://doi.org/10.1109/ISSC.2019.8904947

Wischnewski, M., Haigh, Z. J., Shirinpour, S., Alekseichuk, I., & Opitz, A. (2022). The phase of

sensorimotor mu and beta oscillations has the opposite effect on corticospinal

excitability. *Brain Stimulation*, *15*(5), Article 5. https://doi.org/10.1016/j.brs.2022.08.005

Wischnewski, M., Shirinpour, S., Alekseichuk, I., Lapid, M. I., Nahas, Z., Lim, K. O., Croarkin,

P. E., & Opitz, A. (2024). Real-time TMS-EEG for brain state-controlled research and

precision treatment: A narrative review and guide. *Journal of Neural Engineering*, *21*(6),

061001. https://doi.org/10.1088/1741-2552/ad8a8e

Wodeyar, A., Schatza, M., Widge, A. S., Eden, U. T., & Kramer, M. A. (2021). A state space

modeling approach to real-time phase estimation. *eLife*, *10*, e68803.

https://doi.org/10.7554/eLife.68803

Yeung, N., Bogacz, R., Holroyd, C. B., & Cohen, J. D. (2004). Detection of synchronized

oscillations in the electroencephalogram: An evaluation of methods. *Psychophysiology*,

41(6), Article 6. https://doi.org/10.1111/j.1469-8986.2004.00239.x

Yeung, N., Bogacz, R., Holroyd, C. B., Nieuwenhuis, S., & Cohen, J. D. (2007). Theta phase
697   resetting and the error-related negativity. *Psychophysiology*, *44*(1), Article 1.
698   https://doi.org/10.1111/j.1469-8986.2006.00482.x
699   Zrenner, B., Zrenner, C., Gordon, P. C., Belardinelli, P., McDermott, E. J., Soekadar, S. R.,
700   Fallgatter, A. J., Ziemann, U., & Müller-Dahlhaus, F. (2020). Brain oscillation-
701   synchronized stimulation of the left dorsolateral prefrontal cortex in depression using
702   real-time EEG-triggered TMS. *Brain Stimulation*, *13*(1), Article 1.
703   https://doi.org/10.1016/j.brs.2019.10.007
704   Zrenner, C., Belardinelli, P., Müller-Dahlhaus, F., & Ziemann, U. (2016). Closed-Loop
705   Neuroscience and Non-Invasive Brain Stimulation: A Tale of Two Loops. *Frontiers in*
706   *Cellular Neuroscience*, *10*. https://doi.org/10.3389/fncel.2016.00092
707   Zrenner, C., Belardinelli, P., & Ziemann, U. (2026). Oscillatory brain state-dependent
708   stimulation with transcranial magnetic stimulation combined with
709   electroencephalography. *Nature Protocols*. https://doi.org/10.1038/s41596-025-01309-7
710   Zrenner, C., Desideri, D., Belardinelli, P., & Ziemann, U. (2018). Real-time EEG-defined
711   excitability states determine efficacy of TMS-induced plasticity in human motor cortex.
712   *Brain Stimulation*, *11*(2), Article 2. https://doi.org/10.1016/j.brs.2017.11.016
713   Zrenner, C., & Ziemann, U. (2024). Closed-Loop Brain Stimulation. *Biological Psychiatry,*
714   *Transcranial Magnetic Stimulation*, *95*(6), Article 6.
715   https://doi.org/10.1016/j.biopsych.2023.09.014