Title: Emergence of an adaptive command for orienting behavior in premotor

brainstem neurons of barn owls

Authors: Fanny Cazettes[1,2], Brian J. Fischer[3], Michael V. Beckert[1], Jose L. Pena[1*]

Affiliations: [1]Department of Neuroscience, Albert Einstein College of Medicine, Bronx, New

York, USA

[2]Champalimaud Neuroscience Programme, Champalimaud Center for the Unknown, Lisbon,

Portugal

[3]Department of Mathematics, Seattle University, Seattle, Washington, USA

Summary: The brain can be viewed as a probabilistic estimator, where sensory statistics bias

judgments. Owls underestimate the direction of peripheral sound sources. This bias for central

locations was proposed to reflect the increased uncertainty about eccentric direction.

Understanding the neural pathway supporting this behavior provides a means to address how

adaptive motor commands are implemented by neurons. Here we find that the sensory evidence

about sound direction is weighted by its reliability in premotor neurons of the owl's midbrain

tegmentum such that the mean firing rate approximates the head-orienting bias. We demonstrate

that this coding emerges through convergence of upstream projections from a map of space. We

further show that manipulating the sensory input yields changes predicted by statistical inference

in both premotor responses and behavioral bias. This work demonstrates how a topographic

sensory representation can be linearly read out to adjust behavioral responses by statistics of the

sensory input.

INTRODUCTION

The role of internal representations of prior information and uncertainty in the synthesis of motor commands is critical for understanding how behavior adapts to sensory statistics. To address this question, we investigated the neural basis of the centrality bias of barn owls, which is a systematic underestimation of sound sources towards the center of gaze [1,2]. This centrality bias may be optimal for the owl's prey capture and can be explained by a Bayesian estimator with a prior distribution that emphasizes frontal directions [3,4]. Theoretical studies have proposed coding schemes linking behavioral biases to optimal behavior, where the amount of bias reflects the relative weights given to priors and sensory evidence depending on the reliability of the sensory input [3,5,6]. Yet, a neural circuit decoding a behavioral command that integrates the reliability of sensory evidence and prior information has not been demonstrated. This study describes how such a command may emerge in a premotor neural population that controls orienting behaviors in the sound localization system of the owl.

Most animals use interaural time difference (ITD) for inferring the horizontal direction of sound location [7,8]. In the barn owl, a map of auditory space emerges in the external nucleus of the inferior colliculus (ICx) [9], where selectivity for ITD determines the spatial tuning of auditory neurons (Figure 1). The ICx map is a distorted representation of space where the front is overrepresented [10]. It has also been shown that the frequency and spatial selectivity of ICx neurons co-vary [11], where neurons preferring frontal directions are tuned to higher frequencies than peripheral neurons (Figure 1). This direction-dependent frequency selectivity corresponds to how reliability of ITD changes across frequency and direction, estimated from the owl's head-related transfer function [11]. Previous studies have proposed that the non-uniform spatial and

frequency selectivity across the ICx allows for the representation of prior information and ITD

reliability [3,4,11].

ICx projects point-to-point to the optic tectum (OT) [12], leading to both structures having

neurons with similar spatial and frequency tunings [13-14]. As a result, both ICx and OT display

similar maps of auditory space, here referred to as the space-map (Figure 1). OT projects to the

midbrain tegmentum (mTeg), which drives spinal-cord motoneurons that generate the head-

orienting response to sound [15,16] (Figure 1). In vertebrates, the tectotegmental pathway

contributes prominently to the generation of orienting movements of the eyes, head, and body

[17,18]. Anatomical studies of the tectotegmental projections in the barn owl suggest that the

topographic representation of space in the OT is translated into a representation of orthogonal

movement coordinates in mTeg [15,16,19].

This study examined whether responses of premotor neurons in mTeg predict the owl's centrality

bias, how these responses emerge, and whether they reflect the statistics of the sensory input. We

found that neural responses in mTeg match the owl's behavioral bias, emerge from an effective

convergence from OT to mTeg and approximate a Bayesian estimate of sound location.

Furthermore, both the mTeg responses and orienting bias of behaving owls changed with

manipulations of the cue reliability and sound frequency, in a manner consistent with a Bayesian

estimate. Thus, we provided a mechanism for a neural system to encode a behavioral bias that

approximates a combination of sensory uncertainty and prior information.

RESULTS

Three male and three female adult barn owls (from 3 to 5 years old) were included in the electrophysiological study. We did not observe any significant difference between sexes in the neural responses, therefore the data from the two groups were pooled. Behavioral experiments used three different owls, two females and one male.

Emergence of mTeg tuning

To assess the spatial tuning of premotor neurons downstream of the midbrain space-map, we conducted single-unit recording of auditory responses in mTeg using metal electrodes. Previous studies have shown that microstimulation of mTeg produces head-orienting responses and eye-movements [16], and that this method could be used to reliably identify this region. Although these studies were successful in establishing mTeg as a region that commands orienting behaviors, sound-evoked responses of these neurons were never explored. To target mTeg we used the same stereotaxic [15,16] and microstimulation [16, 19, 20] guidelines reported previously. For each recording site, it was verified that: 1) microstimulation at the recording site elicited micro-saccades (Figure 2A,B) and 2) that microstimulation with the same current intensity no longer elicited saccades after the electrode was moved a few hundred microns away from the recording site.

Like ICx and OT neurons, mTeg neurons were tuned to ITD. For tonal stimulation, ITD curves across regions displayed a similar periodic shape (Figure 3A,B). However, when broadband noise was used, a notable difference was observed. Unlike neurons in ICx and OT, which display ITD curves for broadband noise with a narrow larger peak flanked by smaller side peaks [21] (Figure 3C), all mTeg neurons stimulated with broadband noise (n = 36; supplementary Figure

S1) displayed quasi-sigmodal tuning to ITD, favoring the contralateral hemifield (Figure 3D).

The maxima of these broadband-noise tuning curves were away from the midline on the

contralateral side. Although in some neurons there was a slight response decrease at eccentric

directions (ITD > 100 μs), this decrease was not statistically significant from the maximum

response across the sample (ANOVA, p (F>0.4) = 0.92). Therefore, ITD-tuning curves in

response to broadband-noise in mTeg can be considered largely monotonic, with responses

increasing across the midline, and reaching a plateau at eccentric locations in contralateral space.

We tested whether the transformation from a peaked ITD tuning to monotonic curves was

consistent with a convergent projection from OT to mTeg, as proposed for the midbrain network

guiding eye saccades [22]. If mTeg neurons received convergent input from OT, their responses

should reflect the varying ITD and frequency selectivity of OT neurons across the space-map

[11,14] (Figure 1). To verify this hypothesis, we tested two specific predictions for the

convergence from OT to mTeg on auditory responses: 1) because frequency tuning varies across

the space-map [11,14], a downstream neuron receiving convergent input from OT should have

broader frequency tuning; and 2) because ITD tuning covaries with preferred frequency in ICx

and OT [11,14], stimulation with tones will drive activity in only a subset of the cells exciting

each mTeg neuron. Thus varying frequencies should alter the mTeg ITD tuning curve shape in a

manner consistent with how frequency and ITD tuning change in ICx and OT.

To test the first prediction, we measured the half-width of frequency tuning curves in ICx, OT,

and mTeg neurons. Frequency tuning curves of mTeg neurons were significantly broader than

ICx and OT (Figure 3E,F, mean ± s.d difference in frequency bandwidth: 2.4 kHz ± 0.3 kHz, p <

10^{-11}, Wilcoxon rank-sum test). This result is consistent with a convergence from OT into mTeg.

To test the second prediction, we measured ITD tuning in mTeg for tonal stimulation, within the

range of frequencies that elicited significant responses. As reported above, the ITD tuning curves

of mTeg neurons measured with tonal stimulation were sinusoidal functions with the period

determined by the stimulating frequency (Figure 3B,G). Remarkably, unlike in ICx and OT,

where neurons prefer the same ITD at all frequencies they respond to, i.e., they display a

characteristic delay [21], mTeg neurons' preferred ITD varied with frequency (Figure 3G,H).

For each cell, the peak ITD shifted towards 0 µs when the stimulus frequency increased (Figure

3H, right, $r^2 = 0.85$, intercept=250 µs, slope= -0.042 µs/Hz, p<0.001). Moreover, the change in

preferred ITD with frequency of mTeg neurons was strongly correlated with the change in

frequency and ITD tuning in the space-map [11] ($r^2 = 0.75$, intercept=284 µs, slope= -0.045

µs/Hz, $p<10^{-55}$), where frontal neurons, tuned to ITDs near zero, prefer higher frequencies than

peripheral neurons tuned to large ITDs [11,14]. These results provide physiological evidence of a

convergence from OT into mTeg.

Weighted convergence from space-map to mTeg

It was shown above that mTeg tuning to ITD and frequency are consistent with a convergence

that takes place between the space-map in OT and mTeg. We next asked whether the mTeg

responses can be explained by a weighted linear convergence from space-map neurons, a

processing scheme that has been proposed for the emergence of motor commands [22,23]. For

this, a bank of ITD tuning curves of a population of OT neurons was modeled following criteria

from published tuning properties of space-map neurons. Specifically, cells tuned to frontal ITDs

are overrepresented, prefer higher frequencies, and therefore display narrower ITD tuning [11,

14] (Figure 4A). This modeled OT population was the same used previously for Bayesian

decoding analyses [3,10,24], as well as in the next section of the present study. Modeled OT

tuning curves were then weighted, i.e., rescaled (Figure 4B,C), and summed (Figure 4D) to

simulate the weighted convergence. To estimate the weights at each frequency/ITD channel

converging onto mTeg cells, we used linear decomposition by Fourier analysis of ITD tuning

curves for broadband noise of mTeg neurons. It has been shown that this method can be used to

efficiently assess the neurons' frequency responsiveness [25] (Figure 4B; see supplementary

Figure S2 for similar analysis using random weights). Here, a higher power at a specific

frequency in the Fourier decomposition of the broadband-noise ITD response of an mTeg neuron

corresponds to a higher weight applied to the projecting OT neurons corresponding to that

frequency (Figure 4A-C). The weighted OT ITD-tuning curves were then summed and the output

was compared to the actual ITD tuning of mTeg neurons on a cell-by-cell basis (Figure 4D). We

observed good correlations between modeled and measured mTeg ITD-tuning curves (Figure 4E,

pairwise linear correlation, p<0.05 for 34 out of 36 neurons, median variance explained = 70%),

indicating that ITD tuning of mTeg neurons to broadband sound could be predicted from the

weighted convergence of the space-map population. These results indicate that mTeg responses

are consistent with a weighted linear convergence from the midbrain space map, a plausible

mechanism in neural processing [22,23].

Emergence of an adaptive orientation estimate in mTeg

We next examined whether mTeg responses approached an optimal motor command by

integrating ITD information and the reliability of this cue in the sensory input. In neural theory

of probabilistic inference, a Bayesian estimate of a specific sensory feature results from the

integration of sensory input and prior information about this feature. This integration is done

while weighting the sensory input by its reliability. As a result, if sensory information is

degraded (i.e., unreliable), a Bayesian estimate will increasingly be biased toward the prior

information. To manipulate the reliability of the ITD cue in a quantitative manner, the similarity

of the sound at the left and right ears was varied by adding uncorrelated noise (referred to as

binaural correlation; BC). Lowering BC increases the sensory noise. In space-map neurons this

decreases the amplitude and broadens the ITD-tuning curves [26,27].

We investigated: 1) if mTeg responses can be explained by a Bayesian estimator, and 2) if these

responses predicted behavior when the reliability of the ITD cue changed. To answer the first

question, we read out sound source direction from the modeled population of OT neurons

described above as BC changed, using a Bayesian decoder (maximum a posteriori (MAP); see

supplementary Figure S3 for similar estimates using the mean of the posterior). Then, we

examined whether mTeg responses were consistent with the output of the MAP decoder when

BC changed. To answer the second question, we examined if mTeg responses predicted behavior

as BC levels changed.

The barn owl's sound localization accuracy can be predicted by Bayesian inference with a prior

for frontal space, i.e. frontal sound locations are considered more likely [3, 4]. Consistent with

the general properties of Bayesian inference explained above, the MAP estimate of sound source

direction applied to the modeled OT population showed an increasing bias toward the center of

gaze as BC decreased [27] (Figure 5A).

Interestingly, mTeg responses also varied with BC in a manner consistent with the MAP estimate

of sound direction (Figure 5A-D). Specifically, the mean normalized firing rate of mTeg neurons

in the sample was highly correlated with the Bayesian estimate at each BC (Figure 5A,B, mean

$r^2=0.75$, $p<10^{-22}$). Additionally, the change in the standard deviation of the mean mTeg

population response also correlated well with the standard deviation of the MAP estimate (Fig.

5C,D, $r^2=0.84$, $p=0.01$). Previous work has also demonstrated that the bias of the MAP estimate

across BCs does not change significantly until BC decreases below 0.5 [3,26,27]. To further

confirm the correspondence between mTeg responses and the MAP estimate, we examined

whether this feature was also present in mTeg population responses. Towards this end, we

examined how much mTeg responses for a given ITD changed as BC was decreased. As

observed in the MAP estimate, mTeg responses for a given ITD did not change significantly

when BC remained above 0.5 (Figure 5B,D blue, ANOVA, $p(F=0.03)=0.97$), whereas responses

when BC was below 0.5 were significantly different from when BC was equal to 1 (Figure 5B,D

green Tukey post-hoc test, $p<0.05$). Altogether, these results show that the mTeg response

changes consistently with the MAP estimate.

In addition to investigating the correspondence between mTeg responses and MAP estimate, we

examined whether mTeg responses and the sound localizing behavior were matched across BC.

For this, we relied on data previously reported, showing that the changes in the owl's behavioral

bias with varying BC (Figure 5E reported in [26]) were highly correlated with the MAP estimate

(mean r^2 for the four stimulus directions=0.95, $p<10^{-3}$; see Figure 6C in [27]). Here, to compare

the mTeg responses with the owl's localization data, we plotted mTeg responses as a function of

BC for the same four ITDs used in the published behavioral experiments. These mTeg responses

were well correlated with behavior (Figure 5F, mean r^2 for the four stimulus directions = 0.84,

$p=0.017$).

Finally, we examined whether the bias predicted by the MAP estimate, the bias in mTeg

responses, and the owl's behavioral bias matched as BC changed. To compare the bias in MAP

estimate, mTeg responses, and behavior, we computed the mean difference between responses at

BC= 1 and at lower BCs (Figure 5G,H,I). The MAP estimate predicted an increased bias at lower

BCs (Figure 5G). The same trend was observed in both the mTeg population response (Figure

5H) and in the orienting behavior of the owl (Figure 5I).

Overall, the correlations between mTeg neural responses, Bayesian (MAP) decoder predictions,

and behavior across BCs support the hypothesis that mean mTeg responses approximate an

estimate of sound direction that changes adaptively when the sensory input is degraded.

Testing the network architecture by manipulating the owl's behavioral bias

In light of the physiological and theoretical evidence of an adaptive behavioral command

emerging in mTeg, we set out to test if the weighted convergence across the space-map by mTeg

neurons was predicted by the MAP estimate and subsequently consistent with the owl's orienting

behavior. To this end, we aimed to selectively manipulate the activity in different parts of the

space-map and verify whether these manipulations yielded consistent changes in the MAP

estimate and the owl's behavior. To achieve this goal, we relied on previously published

evidence showing that frontal and peripheral space-map neurons are tuned to high and low

frequencies, respectively [11,14]. Therefore, stimulation with a sound containing only high

frequencies should enhance the response of frontal neurons relative to peripheral neurons, with

the converse occuring for stimulation with low frequency (Figure 6A). Hence, when the

frequency band of the stimulus is changed, the differential activation of neurons across the

space-map should be reflected in the predictions of the MAP estimate, the mTeg responses, and

ultimately the owl's behavior. To test this hypothesis, we first examined predictions of the MAP

estimate when the modeled population of space-map neurons was stimulated with high and low

band-pass noises and tested these predictions on mTeg neurons. Then, we asked if the owl's

sound localizing behavior was consistent with predictions of the weighted convergence.

The MAP estimate predicted that at peripheral locations, mTeg responses to high-frequency

sounds should be lower than mTeg responses to low-frequency sounds (Figure 6B, p=0.021,

Wilcoxon rank-sum test). Thus, if mTeg responses approximate a MAP estimate, the firing rate

of mTeg neurons should be more strongly driven by low frequencies within peripheral ITDs than

by high frequencies. Remarkably, mTeg responses were consistent with the MAP estimate

predictions, displaying significantly different responses for the two types of stimulation, where

mTeg neurons displayed lower firing rate at peripheral ITDs for high than low frequencies

(Figure 6D, ANCOVA, $p(F=9.93) <10^{-3}$). Similar to the MAP estimate, mTeg responses to high

frequency stimuli were less monotonic than at low frequencies, displaying shallow peaks and

troughs (Figure 6B,D, peaks of the MAP estimates at -190 μs and +160 μs; peaks of the mTeg at

-190 μs and +150 μs). These peaks and troughs for high frequency stimulation are expected from

the phase-ambiguous ITD information of high frequency stimuli within the ITD range tested (see

example in Figure 3G, purple curves). However, this is not inconsistent with the prediction of the

weighted-convergence network architecture that at larger ITDs the firing of mTeg neurons is

higher. Thus, the ITD tuning of mTeg neurons stimulated with high and low band-pass noises

was consistent with the predictions of the MAP estimate.

We next tested whether the changes observed at different frequencies predicted a change in

behavioral performance. Interestingly, the MAP estimate predicted different behavioral biases at

high and low frequency (Figure 6C, low frequency average bias of 13.2 deg; high frequency

average bias of 27.6 deg). This prediction was matched by mTeg responses (Figure 6E, low

frequency average bias of 14.3 deg; high frequency average bias of 31.4 deg).

We then tested whether the owl's behavioral bias was indeed consistent with the MAP estimate

and the responses of mTeg neurons. For this we measured non-reinforced head-turns triggered by

high and low-frequency band-pass as well as broadband sounds in behaving barn owls. Training

was limited to standing on a perch at the center of a speaker array; in this way we avoided

potential influences of over-training [28] (Figure 6F). The owl's natural tendency to orient the

head toward sounds was tracked with high-speed infrared cameras (Figure 6G). Head-saccades

were measured from any initial head angle to avoid positional biases. To control for the

confound between centrality bias and unwillingness of the barn owls to turn the head for sounds

close to the center of gaze, sound sources within 10 degrees or less from the center of gaze at the

time of sound presentation were not included in the analysis. We then estimated the average bias

as the mean difference from the actual sound source direction. Using this paradigm, owls

underestimated peripheral directions for broadband noise (the average bias over all eccentric

directions was 21 deg), as reported in previous studies using owls trained to fixate at the front

and motivated to respond through reward [1,2]. Remarkably, owls showed significantly stronger

underestimation when localizing high frequency sounds than low frequency sounds (Figure 6H

left, $p<10^{-4}$, permutation test; average bias at high frequency: 27 deg; average bias at low

frequency: 13 deg, see supplementary Figure S4 for the performance of each owl). Thus, the

amount of behavioral bias could be adjusted upward and downward by targeted manipulations of

the sensory input that elicited corresponding changes in mTeg activity.

In summary, the correlation between the MAP predictions, mTeg neural responses, and

behavioral bias observed during frequency manipulations of the auditory signal indicates,

independently from the BC manipulations, that mTeg responses could account for the behavioral

bias by integrating across the space-map population, approximating an adaptive command for the

owl's orienting behavior.

DISCUSSION

This work explained how the midbrain map of auditory space is read out by downstream neurons

to synthesize a command of orienting behavior that captures sensory uncertainty. It has

previously been shown that the selectivity of space-map neurons reflects cue reliability [11] and

proposed that this property may be a crucial parameter for guiding an adaptive behavioral bias

[27]. However, how precisely changes in space-map neurons' selectivity are translated into an

adaptive behavior was left unanswered. The present study shows how the space-map population

may be read-out by downstream neurons to guide behavior in situations of uncertainty. Here, we

demonstrated that this processing is consistent with a weighted convergence from the OT to

mTeg, generating a conversion from a map representation to a rate-code, driving orienting

behavior weighted by sensory reliability. Based on these mechanistic findings, predictions were

made about how the adaptive behavioral bias would change by controlling stimulus frequency.

These predictions were confirmed with behavioral experiments, allowing further demonstration

of the network architecture by manipulations at the encoding level. Therefore, we show here how

sensory statistics can be biologically decoded into a signal controlling head saccade. This is a

major conceptual advance over previous work.

Sensory-motor integration

Critical findings of this study are the evidence of convergence from OT onto mTeg and the effect

this convergence has on the ITD tuning in mTeg. Convergence from the space-map is supported

by the broader frequency tuning of mTeg neurons and their frequency-dependent ITD tuning,

which matches the ITD-dependent frequency tuning in ICx and OT previously reported [11,14].

The remarkable consistency of how best ITD changes with frequency in mTeg with how best

frequency changes with ITD in ICx [11] and OT [14] indicates that convergent projections of

neurons from the space-map explains the tuning in mTeg. Thus, mTeg neurons lacked the classic

characteristic-delay described for neurons of the inferior colliculus [21]. This is also consistent

with the dramatically different response to ITD with broadband stimulation in mTeg, compared

to ICx and OT, where mTeg responses appear quasi-sigmoidal while ICx and OT responses

display peaked and largely symmetric rate-ITD curves around a prominent preferred ITD.

A fundamental question in sensorimotor integration is the neural code controlling movement

[23,29-31]. Previous studies have reported correlations between the firing rate of sensorimotor

neurons and the kinematics of movements [29]. Here we propose that the premotor neurons in

mTeg encode direction in the population average firing rate, which, through weighted

convergence, captures the statistics represented in the upstream space-map. This is consistent

with the idea that mTeg neurons control muscle synergy rather than single muscles

independently [19,30,31], which has been proposed for explaining why correlations between

neuronal responses and movement properties are commonly observed [29].

The dorsal and medial tegmental areas are composed of multiple nuclei that receive direct

projections from the OT. Microstimulating these areas yields head-saccades in different

directions [16]. Therefore, populations of mTeg neurons in distinct nuclei are likely to have

different tuning properties. Here, we focused on the horizontal coordinate of sound direction,

which in barn owls is specifically linked to the coding of ITD [32]. Hence, we targeted mTeg

neurons with clear tuning to ITD throughout mTeg. While the purpose of this study was to

develop a normative model of the emergence of an adaptive motor command for head

lateralization and elucidate the underlying functional network, we did not attempt to completely

explain the anatomical pathway supporting head-orienting responses. Further experiments are

needed to explore the heterogeneous and likely complex properties of mTeg neurons that

participate in guiding eye and head movements in different directions.

Implementation of an adaptive behavior

In general, behavioral errors are composed of systematic errors (biases) and precision errors

(variance). A minority of studies have focused on behavioral biases to understand the underlying

neural code [6,33-36]. Yet, focusing on the bias itself can provide information about the strategy

the brain uses to produce adaptive behavior. Although both bias and variance contribute to the

magnitude of errors, they provide different insights into how errors may occur in judgments.

While the variance may reflect the level of confidence in either the evidence or the estimate, the

systematic nature of the bias and its direction can be interpreted as the manifestation of a prior

[3,5,27,34] or a cost function [37] that constrains the judgment. Understanding the neural

response properties that emerge from the underlying circuitry in the owl's sound localization

pathway made it possible to manipulate the behavioral bias using specific sensory stimuli. These

findings may also be testable in other species where auditory biases have been observed,

including humans [3,38-40].

The goal of this study was going beyond presenting the Bayesian model as a normative approach

of how evidence about sound direction can be weighted by cue reliability, but to demonstrate the

network implementing the neural command guiding a behavioral response weighted by the

uncertainty in sensory information. The normative model does not recapitulate exactly the neural

and behavioral variability. However, it helps in interpreting the experimental results from the

Bayesian approach perspective, i.e. that the adaptive behavioral bias reflects the statistics of the

sensory input. The MAP estimate and mTeg responses were highly correlated in shape and

changed consistently across independent conditions (sound frequency and BC). However, the

MAP estimate did not perfectly match the mTeg responses. Despite a correspondence in shape

and pattern of change across BCs, we observed that at negative (ipsilateral) ITDs, the mTeg

responses appeared more monotonic than the MAP estimate for higher BCs. For both

hemispheres neural responses were maximal for sound directions within the contralateral

hemifields. Yet, mTeg receives inputs from the left and right OTs [15]. Thus, although the

orienting behavior is presumably controlled by activity from both sides of the midbrain

tegmentum [16,19], it is likely that the stronger firing rate elicited by sounds on the contralateral

side, which matches better to the MAP estimate, have a stronger influence on guiding orienting

responses [16,19]. In addition, although variability of the MAP estimate and mTeg responses

changed in the same direction with BC, the absolute numbers are different, with the change in

variability from BC = 1 to BC = 0.1 being an order of magnitude larger for the MAP estimate.

Variations of the MAP estimate from one trial to another reflect the population response, where

neural variability is correlated, while mTeg standard deviation reflects changes in the response of

single neurons. Thus, the across-trial variability of the MAP is influenced by correlated noise in

the modeled space-map population, while this correlated noise is not captured in the variability

observed when averaging across individual mTeg responses, possibly leading to the difference in

absolute levels predicted by the model and observed in averages of mTeg responses recorded

separately.

Explaining biased behavior with Bayesian theory has implications for understanding sensory

perception [3,5,41]. Bayesian inference shows how combining prior and sensory information

predicts optimal perception of ambiguous sensory inputs [41-46]. However, theoretically optimal

methods are but metaphors for how the brain actually decodes information, and the fact that

mTeg responses approximate the Bayesian estimate is not trivial. Although both the specific

Bayesian estimate tested in this study and the weighted convergence act as linear decoders, they

could not be explained by any arbitrary linear convergence network. For example, a point-to-

point projection from OT to mTeg would produce a similar population code for direction to those

seen in ICx and OT, rather than a rate code reflecting movement direction. Additionally, a

random linear convergence from OT to mTeg did not necessarily predict the mTeg response and

approximate a Bayesian decoder (see supplementary Figure S2). Rather, a specific integration

across frequency and ITD was required for the convergence from OT to mTeg to approximate

the Bayesian direction estimate. Thus a precise, yet simple and biologically plausible mechanism

of weighted convergence explains how the neural code for sound localization can be translated

into an adaptive behavioral command.

MATERIALS AND METHODS

Electrophysiology

Surgical procedure: Surgery was performed as described previously [47]. Briefly, adult barn

owls (3 females and 3 male) were anesthetized with intramuscular injections of ketamine

hydrochloride (20 mg/kg; Ketaset, intramuscular) and xylazine (4 mg/kg; Anased,

intramuscular). Prophylactic antibiotics (ampicillin; 20 mg/kg, intramuscular) and lactated

Ringer's solution (10 ml, subcutaneous) were injected at the beginning of each session. An

analgesic (Carprofen; 3mg/kg, Rimadyl, intramuscular) was administered at the end of each

session to prevent inflammation and pain. These procedures complied with National Institutes of

Health and guidelines of the Albert Einstein College of Medicine's Institute of Animal Studies.

Recording from awake animals was impractical in these experiments as electrophysiology

required serial electrode penetrations, head restraint, and long recording sessions (up to 10

hours). To control for varying levels of anesthesia, records of the time of each recording relative

to anesthetic administration were rigorously maintained. Experiments were interrupted when

latencies or response thresholds changed. Regardless, the effect of anesthesia in the midbrain has

been shown to be less pronounced than in the forebrain [48,49] and therefore lessens concerns

about changes in neural response under anesthesia.

Extracellular recordings of ICx, OT and mTeg neurons: Single-unit responses were recorded

using 1MΩ tungsten electrodes (A-M Systems). Tucker Davis Technologies (TDT) System 3 and

custom written Matlab software (Mathworks) were used to record neural data. ICx and OT were

located stereotaxically and confirmed by the characteristic responses to ITD and interaural level

difference and firing properties [47]. The mTeg was also located stereotaxically [15,16] but

recording from this structure was further verified with microstimulation (see below).

Microstimulation: Recordings in mTeg were confirmed with microstimulation. At the end of

each recording, microstimulation at the recording site was conducted to verify that eye

movements were elicited and that the same electrical stimulus was no longer able to elicit eye

movements when the electrode was moved a few hundred micrometers away from the recording

site. A programmable digital stimulator (WPI, DS8000) was used to deliver trains of current

pulses (5ms pulse width, 200Hz, 80ms duration) through the recording electrode, varying the

current amplitude from 50 to 150 μA with inter-stimulus intervals larger than 15 seconds (as

described in [20]). In most experiments, 130 μA or less was enough to induce unequivocal eye

movements (see Figure 2 for example).

Sound stimulation

All experiments were performed inside a double-walled sound-attenuating chamber. Custom-

made earphones consisting of a calibrated speaker (Knowles model 1914) and a microphone

(Knowles model EK-23024) were inserted in the owl's ear canal [47]. Auditory stimuli delivered

through the earphones consisted of 100 to 150 ms signals with a 5 ms rise-fall time at 10-20 dB

above threshold. For each ICx, OT, and mTeg neuron, we first measured the ITD and rate-level

response with broadband noise (0.5 – 10 kHz). ITD was initially varied from ±300 μs with 30 μs

steps over 5-10 trials for ICx and OT and 20 trials for mTeg. Sound level varied from 0 dB SPL

to 70 dB SPL in 5-dB steps. Frequency tuning was measured with tones ranging from 500 Hz to

8000 Hz varied in 200 to 500 Hz steps over 20 trials. Neural responses to ITD in mTeg were also

recorded at various frequencies (from 1 to 6 kHz, 1 kHz steps, same ITD protocol as broadband).

Stimuli within all tested ranges were randomized during data collection.

To manipulate the binaural correlation, three random noise signals (N1, N2, and N3) were

generated. N1 was delivered to one ear and its copy with a time shift, to produce an ITD, was

delivered to the other ear. N2 and N3 were added to the N1 in the left and right ear respectively.

These additional noise signals reduced the correlation between the signals in the two ears,

depending on the relative amplitudes of the uncorrelated and correlated noises. Binaural

correlation was calculated from BC = $1/(1 + k^2)$, where k is the ratio between the root-mean-

square amplitudes of the uncorrelated and correlated noises [26]. On a subset of ICx neurons

(n=46) and on all recorded mTeg neurons, we obtained ITD curves (+/- 300 µs; 30 µs steps; 20

repetitions) using noise bursts at different BCs (from 0 to 1, in 0.2 steps).

Finally, for all mTeg neurons we measured ITD curves (+/- 300 µs; 30 µs steps; 20 repetitions)

with low (500-3500 Hz) and high (4500-7500 Hz) frequency band-pass sounds as well as

broadband noise (500-9000 Hz).

Behavior

Remote eye tracking: Eye movements triggered by microstimulation in mTeg were measured

with high-speed video imaging using a commercially available eye tracking system (EyeLink

1000) that detected the pupil and the position of the corneal reflection. Eyelids were opened

momentarily to conduct the test after each recording using a custom made retractor. This

procedure and the anesthesia did not prevent blinking of the nictitating membrane allowing for

natural protection of the eyes from drying.

Head-orienting behavior: Head-orienting behavior to sound was measured for three hand-raised

barn owls trained only to stand on a perch at the center of a speaker array. The speaker array

consisted of an azimuthal linear array of 21 speakers, a subset of a hemispherical array of

speakers constructed inside a sound-attenuating chamber [47,11]. The linear array spanned 100

degrees to the left and right of the midline, with 10 degrees separation between speakers. Each

speaker was calibrated in place using a microphone mounted on a pan-tilt robot located at the

array center. Head saccades were recorded with a pair of high-speed infrared cameras (Fastec

Imaging, 100 frames per sec) mounted in the corners of the room. Head saccades were then

tracked using custom designed image-analysis code (Xcitec, Proanalyst) from images calibrated

in 3-D using a grid located at the same position of the owl's head. Owls were presented with the

same noise bursts used to measure neural responses (100 ms long, 5 ms rise-fall time, high and

low frequency band-pass sounds, and broadband-noise) but through this free-field array. The

setup allowed us to measure head saccades from any starting head position, which made it

possible to rule out positional biases. To account for the position of the animal in the field of

view of the cameras, the owl's perch was designed such that it only allowed the bird a single

stance. However, owls did not always look straight ahead when the stimulus was presented;

therefore, the measured angles of head turn were transformed into a head-centered coordinate

system. Owls were unrewarded in this task to avoid biases introduced by training. As a

consequence, they only performed a few orienting-responses per experimental session [28],

requiring long periods of rest and repeated sessions over more than two years to collect the data.

For each sound presentation, the frequency band (0.5-3.5 kHz, 4.5-7.5 kHz or 0.5-9 kHz) and

location (±100 deg, 10 deg separation) of the source were randomized by the software. The

experimenter initiated a trial when the owl was standing upright and its beak (the tracking

reference, see Figure 6G) was in the field of view of both cameras. The experimenter remained

blind to the properties of the sound.

Data analysis

Electrophysiological data: For each stimulus parameter, a rate curve was computed by averaging

the firing rate during sound stimulation over trials. The spontaneous firing rate, obtained when

no sound stimulation was presented, was subtracted from the response to the stimulus. Best ITDs

were defined as the center of the range that elicited 50% of the maximum response of each

tuning-curve. To assess the relative broadness of the frequency tuning we calculated the areas

under the normalized frequency tuning curves. To find the peak of ITD-tuning curves of mTeg

neurons to tonal stimulation we first fitted the curves with a cosine function. We then defined the

ITD corresponding to the closest maximum from 0 μs as the peak [11]. The changes of ITD

tuning with BC were consistent in both hemispheres (maximal changes for sound directions

within the contralateral hemifields). Thus, analyses of the mean mTeg response were performed

on the combined data, normalized to contralateral and ipsilateral side leading.

ITD increases with eccentricity [32]: small values of ITD (~0 μs) are associated with frontal

directions and larger values of ITD (~200 μs) are associated with the periphery. Thus, we

converted ITD to azimuth [32] to measure the bias predicted by the mTeg response to ITD.

Behavioral data: Head orientation and angular velocity were computed offline using image-

analysis software (Xcitec, Proanalyst). Individuals analyzing the data remained blind to the

location of the sound source until the end. Subsets of the data were analyzed independently by

different persons to confirm the analysis was consistent across individuals. Trials where owls

moved during the presentation of the stimulus or where the beak disappeared from the field of

view of the cameras were discarded. We measured saccade latencies as the time from the onset

of each presentation of a stimulus to the first video frame where the owl's head started rotating.

Median latency varied across animals (owl L=240 ms; owl F=520 ms; owl P=210 ms). These

values are higher than previous reports [1,18,50]. However, most previous studies were

conducted with trained owls that were rewarded if the saccade was correct. For each owl, there

was no significant difference between the latencies across stimulus conditions. Saccades whose

latency was greater than 1 sec were discarded. Based on angular velocity, head movements

during a saccade were classified as rotation, translation, or fixation [51]. Consistent with the

literature, we only included head rotations with an angular velocity greater than 50 deg.sec^{-1}

[18,50,51]. When translational movements were included in the analysis the results remained

consistent, albeit more variable. The criteria for classifying movements as saccades became

unreliable when the sound source was close to the front [1,50], therefore only head-turns evoked

by sources located 10 degrees away from the initial head angle were included in the analysis.

Modeling

Heterogeneous population of neurons in the space-maps: We modeled a space-map population

of 500 neurons. To incorporate the overrepresentation of frontal space into the modeled

population, the density of preferred direction X was drawn from a Laplace prior:

494
$$p(X) \propto \exp\left(-\frac{|X|}{b}\right),$$

where the scale parameter is b=25 [3,10]. First, broadband noise signals between 0.2 and 12 kHz

were passed through a gammatone filter-bank with center frequencies ranging from 0.25 kHz to

8 kHz in 0.25 kHz steps. The time constants of the filters were specific to the owl and estimated

from Koppl [52] to model cochlear filters, as described in [24]. The outputs were cross-

correlated and transformed by an exponential input-output function to produce a set of

frequency-dependent ITD curves (from 0.5 to 8 kHz). The input to ICx was modeled as a

weighted sum of the frequency-dependent ITD curves. The weights were direction-dependent to

model the direction-dependent frequency tuning in ICx [11]. The weights for each neuron have a

Gaussian shape with a center and width selected to match the observed frequency tuning at the

preferred direction of the neuron. The weighted sum of the frequency-dependent ITD curves was

passed through an exponential nonlinearity to produce the firing rates of Poisson neurons that

modeled ICx responses. The responses in OT, which receive point-to-point projections from ICx

[12], are influenced by feedback inhibition that serves to select the dominant stimulus when

multiple peaks of activity are present in the map [53,54]. To model OT neurons, we used a

simplified version of the model of Mysore and Knudsen (2012, 2014) by multiplying the ICx

activity pattern by a rectangular window function to select the dominant peak. The window takes

a value of one on an interval that is 28 degrees wide centered at the location of the peak in a

smoothed version of the ICx activity pattern. The decoding analyses were applied to the

windowed response pattern representing the population activity of the OT.

Assuming a linear transformation between OT and mTeg, the mTeg response to ITD can be

explained entirely as a linear combination ITD-tuning curves form OT. Therefore, we modeled

the responses in mTeg with a weighted sum of the OT population. To estimate the weights of the

convergence, we used discrete Fourier transforms (FFT) of the experimental mTeg ITD tuning

curves calculated after offsetting the curves to zero mean, as described previously [25]. The

weights given by the normalized FFT phase spectra of mTeg neurons were applied to OT

neurons with equivalent preferred frequency (Figure 4A,B). The modeled mTeg response was

therefore given by: $Y_i(ITD) = \sum_{n=1}^{N} f_{i,n} X_n(ITD)$, where $X_n(ITD)$ is the modeled ITD curve of the

n^{th} neuron in OT and $f_{i,n}$ the weights given by the FFT phase spectra of the i^{th} mTeg neurons at

the preferred frequency of the n^{th} OT neuron.

Bayesian estimates: A general approach to decoding the neural population activity is to compute

a MAP estimate of the environmental property θ using a statistical model of the neural responses

[46,55,56]. The MAP estimate of stimulus direction at binaural correlation level *BC* (or stimulus

frequency F) is the value of θ that maximizes the posterior probability, or equivalently the log

posterior probability, of θ given the neural activities:

529
$$\hat{\theta}_{map} = \frac{argmax}{\theta} \ln p(\theta \mid \mathbf{r}, BC)$$
.

530 We computed the MAP estimate of stimulus direction at different BC (or stimulus frequency)

531 values from the model population response assuming Gaussian variability with mean population

532 response $\mathbf{f}(\theta, BC)$ and covariance matrix $\Sigma(\theta, BC)$ and that the determinant of the covariance

533 matrix is constant across stimulus direction. The MAP estimate is computed as:

534
$$\hat{\theta}_{map} = \frac{argmax}{\theta} \ln p(\theta \mid \mathbf{r}, BC)$$
$$= \frac{argmax}{\theta} \quad -\frac{1}{2}(\mathbf{r} - \mathbf{f}(\theta, BC))^T \Sigma^{-1}(\theta, BC)(\mathbf{r} - \mathbf{f}(\theta, BC)) - \frac{|\theta|}{25}$$
.

The covariance matrix $\Sigma(\theta, BC)$ is estimated from the responses of the modeled space-map

neurons and takes into account the correlations induced by shared noise at the input. Because we

are using a model of the space-map neurons, we can reliably estimate all of the correlations

between neurons in the population.

The variability of the MAP estimate for a given stimulus ITD is the standard deviation of the

MAP estimate over 50 trials of a stimulus presentation. The overall variability of the MAP

estimate as a function of BC was computed as the average standard deviation over all the 21

stimulus ITDs.

ACKNOWLEDGMENTS

This work was funded by NIH grants DC012949 and DC007690. We thank Kourosh Saberi for

providing the data used in Fig. 5E and Adam Kohn for comments on the manuscript. Clifford

Keller helped hand-raising the owlets and Daniel Munch participated in the blind analysis of

behavior.

COMPETING INTERESTS

The authors declare no competing financial interests.

REFERENCES

1   Hausmann, L., von Campenhausen, M., Endler, F., Singheiser, M. & Wagner, H. (2009).
     Improvements of sound localization abilities by the facial ruff of the barn owl (Tyto alba)
     as demonstrated by virtual ruff removal. *PloS one* **4**, e7721,
     doi:10.1371/journal.pone.0007721.

2   Knudsen, E. I., Blasdel, G. G. & Konishi, M. (1979). Mechanisms of sound localization
     in the barn owl (Tyto alba). *Journal of comparative physiology. A, Sensory, neural, and
     behavioral physiology* **133**, 13–21.

3   Fischer, B. J. & Pena, J. L. (2011). Owl's behavior and neural representation predicted by
     Bayesian inference. *Nature neuroscience* **14**, 1061-1066, doi:10.1038/nn.2872.

4   Rich, D., Cazettes, F., Wang, Y., Pena, J. L. & Fischer, B. J. (2015). Neural
     representation of probabilities for Bayesian inference. *Journal of computational
     neuroscience* **38**, 315-323, doi:10.1007/s10827-014-0545-1.

5   Girshick, A. R., Landy, M. S. & Simoncelli, E. P. (2011). Cardinal rules: visual
     orientation perception reflects knowledge of environmental statistics. *Nature
     neuroscience* **14**, 926-932, doi:10.1038/nn.2831.

6   Schwartz, O., Hsu, A. & Dayan, P. (2007). Space and time in visual context. *Nature
     reviews. Neuroscience* **8**, 522-535, doi:10.1038/nrn2155.

7   Strutt, J. W. (1907). On our perception of sound direction. *Philos Mag* **13**, 214-232.

8   Blauert, J. *Spatial hearing : the psychophysics of human sound localization*. Rev. edn,
     (MIT Press, 1997).

9   Knudsen, E. I. & Konishi, M. (1978). A neural map of auditory space in the owl.
     Science, New Series **200**, 795-797.

10   Knudsen, E. I. (1982). Auditory and visual maps of space in the optic tectum of the owl.
     The Journal of neuroscience : the official journal of the Society for Neuroscience **2**,
     1177-1194.

11   Cazettes, F., Fischer, B. J. & Pena, J. L. (2014). Spatial cue reliability drives frequency
     tuning in the Barn Owl's midbrain. *eLife* **3**, doi:10.7554/eLife.04854.

12   Knudsen, E. I. & Knudsen, P. F. (1983). Space-mapped auditory projections from the
     inferior colliculus to the optic tectum in the barn owl (Tyto alba). *The Journal of
     comparative neurology* **218**, 187-196, doi:10.1002/cne.902180206.

13   Olsen, J. F., Knudsen, E. I. & Esterly, S. D. (1989). Neural maps of interaural time and
     intensity differences in the optic tectum of the barn owl. *The Journal of neuroscience :
     the official journal of the Society for Neuroscience* **9**, 2591-2605.

14   Knudsen, E. I. (1984). Auditory properties of space-tuned units in owl's optic tectum.
     Journal of neurophysiology **52**, 709-723.

15   Masino, T. & Knudsen, E. I. (1992). Anatomical pathways from the optic tectum to the
     spinal cord subserving orienting movements in the barn owl. *Experimental brain
     research* **92**, 194-208.

16   Masino, T. & Knudsen, E. I. (1993). Orienting head movements resulting from electrical
     microstimulation of the brainstem tegmentum in the barn owl. *The Journal of
     neuroscience : the official journal of the Society for Neuroscience* **13**, 351-370.

17   Masino, T. (1992). Brainstem control of orienting movements: intrinsic coordinate
     systems and underlying circuitry. *Brain, behavior and evolution* **40**, 98-111.

18 du Lac, S. & Knudsen, E. I. (1990). Neural maps of head movement vector and speed in
the optic tectum of the barn owl. *Journal of neurophysiology* **63**, 131-146.
19 Masino, T. & Knudsen, E. I. (1990). Horizontal and vertical components of head
movement are controlled by distinct neural circuits in the barn owl. *Nature* **345**, 434-437,
doi:10.1038/345434a0.
20 Netser, S., Ohayon, S. & Gutfreund, Y. (2010). Multiple manifestations of
microstimulation in the optic tectum: eye movements, pupil dilations, and sensory
priming. *Journal of neurophysiology* **104**, 108-118, doi:10.1152/jn.01142.2009.
21 Takahashi, T. & Konishi, M. (1986). Selectivity for interaural time difference in the owl's
midbrain. *The Journal of neuroscience : the official journal of the Society for*
Neuroscience **6**, 3413–3422.
22 Groh, J. M. (2001). Converting neural signals from place codes to rate codes. *Biological*
cybernetics **85**, 159-165.
23 Salinas, E. (2006). How behavioral constraints may determine optimal sensory
representations. *PLoS biology* **4**, e387, doi:10.1371/journal.pbio.0040387.
24 Fischer, B. J., Anderson, C. H. & Pena, J. L. (2009). Multiplicative auditory spatial
receptive fields created by a hierarchy of population codes. *PLoS one* **4**, e8015,
doi:10.1371/journal.pone.0008015.
25 Vonderschen, K. & Wagner, H. (2012). Transformation from a pure time delay to a
mixed time and phase delay representation in the auditory forebrain pathway. *The*
Journal of neuroscience : the official journal of the Society for Neuroscience **32**, 5911-
5923, doi:10.1523/JNEUROSCI.5429-11.2012.
26 Saberi, K., Takahashi, Y., Konishi, M., Albeck, Y., Arthur, B.J., Farahbod, H. (1998).
Effects of interaural decorrelation on neural and behavioral detection of spatial cues.
Neuron **21**, 789-798.
27 Cazettes, F., Fischer, B. J. & Pena, J. L. (2016). Cue Reliability Represented in the Shape
of Tuning Curves in the Owl's Sound Localization System. *The Journal of neuroscience :*
the official journal of the Society for Neuroscience **36**, 2101-2110,
doi:10.1523/JNEUROSCI.3753-15.2016.
28 Hazan, Y., Kra, Y., Yarin, I., Wagner, H. & Gutfreund, Y. (2015). Visual-auditory
integration for visual search: a behavioral study in barn owls. *Frontiers in integrative*
neuroscience **9**, 11, doi:10.3389/fnint.2015.00011.
29 Todorov, E. (2000). Direct cortical control of muscle activation in voluntary arm
movements: a model. *Nature neuroscience* **3**, 391-398, doi:10.1038/73964.
30 Overduin, S. A., d'Avella, A., Carmena, J. M. & Bizzi, E. (2012). Microstimulation
activates a handful of muscle synergies. *Neuron* **76**, 1071-1077,
doi:10.1016/j.neuron.2012.10.018.
31 Joshua, M. & Lisberger, S. G. (2014). A framework for using signal, noise, and variation
to determine whether the brain controls movement synergies or single muscles. *Journal*
of neurophysiology **111**, 733-745, doi:10.1152/jn.00510.2013.
32 Moiseff, A. (1989). Bi-coordinate sound localization by the barn owl. Journal of
comparative physiology A, Sensory, neural, and behavioral physiology 164:637-644
33 Summerfield, C. & de Lange, F. P. (2014). Expectation in perceptual decision making:
neural and computational mechanisms. *Nature reviews. Neuroscience* **15**, 745-756,
doi:10.1038/nrn3838.

34   Wei, X. X. & Stocker, A. A. (2015). A Bayesian observer model constrained by efficient
coding can explain 'anti-Bayesian' percepts. *Nature neuroscience* **18**, 1509-1517,
doi:10.1038/nn.4105.
35   Wei, X. & Stocker, A. A. (2012a). Bayesian inference with efficient neural population
codes. In Proceedings of the Int'l Conf on Artificial Neural Networks
.NewYork:Springer..
36   Jazayeri, M. & Shadlen, M. N. (2010). Temporal context calibrates interval timing.
Nature neuroscience **13**, 1020-1026, doi:10.1038/nn.2590.
37   Kording, K. P. & Wolpert, D. M. (2004). Bayesian integration in sensorimotor learning.
Nature **427**, 244-247.
38   Populin, L. C. & Yin, T. C. (1998). Behavioral studies of sound localization in the cat.
The Journal of neuroscience : the official journal of the Society for Neuroscience **18**,
2147-2160.
39   Nodal, F. R., Bajo, V. M., Parsons, C. H., Schnupp, J. W. & King, A. J. (2008). Sound
localization behavior in ferrets: comparison of acoustic orientation and approach-to-target
responses. *Neuroscience* **154**, 397-408, doi:10.1016/j.neuroscience.2007.12.022.
40   Zahn, J. R., Abel, L. A. & Dell'Osso, L. F. (1978). Audio-ocular response characteristics.
Sensory processes **2**, 32-37.
41   Stocker, A. A. & Simoncelli, E. P. (2006). Noise characteristics and prior expectations in
human visual speed perception. *Nature neuroscience* **9**, 578-585, doi:10.1038/nn1669.
42   Weiss, Y., Simoncelli, E. P. & Adelson, E. H. (2002). Motion illusions as optimal
percepts. *Nature neuroscience* **5**, 598-604, doi:10.1038/nn858.
43   Pouget, A., Dayan, P. & Zemel, R. S. (2003). Inference and computation with population
codes. *Annual review of neuroscience* **26**, 381-410,
doi:10.1146/annurev.neuro.26.041002.131112.
44   Beck, J. M., Ma, W.J., Kiani, R., Hanks, T., Churchland, A.K., Roitman, J., Shadlen,
M.N., Latham, P.E., Pouget, A. (2008). Probabilistic population codes for Bayesian
decision making. *Neuron* **60**, 1142-1152, doi:10.1016/j.neuron.2008.09.021.
45   Lochmann, T. & Deneve, S. (2011). Neural processing as causal inference. *Current
opinion in neurobiology* **21**, 774-781, doi:10.1016/j.conb.2011.05.018.
46   Ma, W. J., Beck, J. M., Latham, P. E. & Pouget, A. (2006). Bayesian inference with
probabilistic population codes. *Nature neuroscience* **9**, 1432-1438, doi:10.1038/nn1790.
47   Wang, Y., Shanbhag, S. J., Fischer, B. J. & Pena, J. L. (2012). Population-wide bias of
surround suppression in auditory spatial receptive fields of the owl's midbrain. The
Journal of neuroscience : the official journal of the Society for Neuroscience **32**, 10470-
10478, doi:10.1523/JNEUROSCI.0047-12.2012.
48   Ter-Mikaelian, M., Sanes, D. H. & Semple, M. N. (2007). Transformation of temporal
properties between auditory midbrain and cortex in the awake Mongolian gerbil. The
Journal of neuroscience : the official journal of the Society for Neuroscience **27**, 6091-
6102, doi:10.1523/JNEUROSCI.4848-06.2007.
49   Schumacher, J. W., Schneider, D. M. & Woolley, S. M. (2011). Anesthetic state
modulates excitability but not spectral tuning or neural discrimination in single auditory
midbrain neurons. Journal of neurophysiology **106**, 500-514, doi:10.1152
50   Knudsen, E. I., konishi, M. & Blasdel, G. G. (1979). Sound Localization by the Barn
Owl (Tyto alba) Measured with the Search Coil Technique. J. Comp. Physiol. **133**, 1-11.

Ohayon, S., van der Willigen, R. F., Wagner, H., Katsman, I. & Rivlin, E. (2006). On the barn owl's visual pre-attack behavior: I. Structure of head movements and motion patterns. Journal of comparative physiology. A, Neuroethology, sensory, neural, and behavioral physiology **192**, 927-940, doi:10.1007/s00359-006-0130-9.

Koppl, C. (1997). Frequency tuning and spontaneous activity in the auditory nerve and cochlear nucleus magnocellularis of the barn owl Tyto alba. Journal of neurophysiology **77**, 364-377.

Mysore, S. P. & Knudsen, E. I. (2012). Reciprocal inhibition of inhibition: a circuit motif for flexible categorization in stimulus selection. Neuron **73**, 193-205, doi:10.1016/j.neuron.2011.10.037.

Mysore, S. P. & Knudsen, E. I. (2014). Descending control of neural bias and selectivity in a spatial attention network: rules and mechanisms. Neuron **84**, 214-226, doi:10.1016/j.neuron.2014.08.019.

Salinas, E. & Abbott, L. F. (1995). Transfer of coded information from sensory to motor networks. The Journal of neuroscience : the official journal of the Society for Neuroscience **15**, 6461-6474.

Seung, H. S. & Sompolinsky, H. (1993). Simple models for reading neuronal population codes. Proceedings of the National Academy of Sciences of the United States of America **90**, 10749-10753.

    FIGURES & FIGURE LEGENDS

    Figure 1. Sound localization pathway. ICx and OT display maps of frequency and space. Frontal

    space (small ITD in µs in purple) is associated with high frequency. Conversely, peripheral space

    (large ITD in µs in green) is associated with low frequency. Although OT directly projects to

    mTeg, the nature of the projection between OT and mTeg is unknown.

A Gaze position

B Normalized gaze position Time (s)

716   **Figure 2.** Microstimulation in mTeg elicits eye movements. (A) An eye tracking system detected

717   the pupil (blue ellipse) and the position of the corneal reflection (blue cross) over time. (B)

718   Microstimulation (red line) through the recording electrode elicited eye movements detected by

719   the eye tracker.

Figure 3. Tuning properties in the space-map and mTeg. (A,B) Example ITD tuning curves

(mean and standard deviation across trials) of ICx (A) and mTeg (B) neurons for tonal

stimulation. (C,D) Example ITD tuning curves (mean and standard deviation across trials) of ICx

(C) and mTeg (D) neurons for broadband noise. (E) Example frequency tuning curve of an mTeg

neuron (black) superimposed with frequency tuning curves of ICx (green) and OT (blue) cells

showing the broader frequency tuning in mTeg. (F) Across the samples, mTeg neurons (n=36

from Owls #1, 2 & 3) were significantly more broadly tuned than ICx (n=184 from Owls #1, 2 &

3) and OT (n=39 from Owls #4, 5 & 6) cells (***p<0.001). (G) Example ITD tuning curves of

an mTeg neuron for different frequencies, showing that ITD tuning varied with frequency. (H)

The mean and standard deviation of peak ITDs for tonal stimulation across the mTeg sample.

The mean peak ITD varied with stimulus frequency.

Figure 4. Convergence from the space-map into mTeg. (A) Model of frequency-dependent ITD

tuning curves in the space map. Neurons tuned to small ITDs preferred high frequencies (purple),

neurons tuned to intermediate ITDs preferred intermediate frequencies (blue) and neurons tuned

to larger ITDs preferred low frequencies (green). (B) The weights for each frequency

(normalized from 0 to 1) were estimated from the Fourier decomposition of responses of mTeg

neurons to broadband sound, on a neuron-by-neuron basis. (C) Space-map ITD tuning curves (A)

scaled by the weights estimated in (B) and summed to simulate the convergence. (D) Example

experimental ITD-tuning curve in mTeg (gray dotted line) and the output of the convergence

model with the respective weights. (E) The boxplot shows the median and quartiles of the

coefficient of determination (r^2) between modeled and measured mTeg ITD curves across the

sample.

Figure 5. The owl's behavioral bias under varying levels of noise is predicted by the MAP

estimate and mTeg responses. (A) MAP estimate with varying BC (high to low BC indicated by

changing from blue to green). (B) Mean ITD-response in mTeg for varying BC. To calculate the

mean ITD-response in mTeg, the ITD-response of each neuron was first normalized to its mean

activity at BC=1 before taking the average of the ITD-response across all the recorded neurons.

(C) Mean standard deviation over 15 ITDs and 50 iterations of the MAP estimate. (D) Mean over

21 ITDs of the standard deviation of the mean mTeg response. (E) Mean and standard deviation

of the owl's head orienting response as a function of BC (modified from [26]). Behavioral

responses to four different ITDs are shown (actual values indicated on the right). The centrality

bias increases as BC decreases. (F) Mean mTeg response across BC for similar ITDs as in (E).

(G,H,I) Reduction in response from the BC = 1 condition, which quantify the bias toward the

center, computed as the mean difference between responses at BC=1 and other BCs at the same

four directions shown in (E) and (F). Error bars in (F) and (G,H,I) represent s.e.m.

Figure 6. Changes in the owl's behavioral bias induced by manipulating stimulus frequency. (A)

Schematic population of space-map neurons whose relative response rate varies with the

frequency of the stimulating sound. Stimulation with high frequencies (middle) excites more

strongly the frontal neurons, which prefer higher frequencies. Conversely, stimulation with low

frequencies (bottom) excites more strongly the peripheral neurons. (B) MAP estimate for sound

stimulation of varying frequency as described in (A) (shaded areas are s.e.m). (C) Mean and

standard deviation over sound directions (ITD > 50 μs and ITD < -50 μs) of the bias predicted by

MAP estimate (in B). (D) Mean ITD tuning across mTeg neurons for varying frequency. (E)

Mean and standard deviation of the difference in bias between stimulating conditions predicted

from the mTeg responses across ITD. To compute the relative change in bias predicted by the

mTeg responses at high and low frequency, we measured the amplitude difference between the

two curves. To compare the biases predicted by the mTeg responses and MAP estimate, we used

the MAP estimate at low frequency as common scale for both datasets. Therefore, the mTeg

responses were normalized so that the maximum value of the mTeg response at low frequency

matches the maximum of the MAP estimate at low frequency. (F) Owls were trained to stand on

a perch at the center of a speaker array. (G) Images captured by two high-speed infrared video

cameras at different angles. The owl's head was tracked as it moved in space. Red dotted lines

indicate the trajectory preceding the shown images. (H) Median and quartiles of the bias of

head-orienting responses from three barn owls presented with high-frequency (n=47) and low-

frequency (n=36) bandpass noise. (c,e,h) $*p<0.05$, $**p<0.01$, $***p<0.001$, high frequency in

purple and low frequency in green.

 SUPPLEMENTARY FIGURES

Supplementary Figure S1. ITD tuning from broadband noise stimulation of 36 mTeg neurons recorded in 3 barn owls (1 male and 2 females). (a) Neurons in the left hemisphere display a peak or a plateau of activity at positive ITDs. (b) Neurons in the right hemisphere display a peak or a plateau of activity at negative ITDs. Overall, neurons respond maximally to the contralateral side.

Supplementary Figure S2. Mean modeled response of a random linear convergence from the space-map onto mTeg at different values of binaural correlation (BC). The convergence was modeled using the method described in the manuscript, except that weights were random (sampled uniformly from 0 to 1) rather than estimated from the Fourier transform of mTeg ITD curves. The random linear convergence does not predict the mTeg response, nor approximate a Bayesian decoder.

 Supplementary Figure S3. Posterior mean estimate at different values of binaural correlation
 (BC) (a) Posterior mean estimate with varying BC (high to low BC indicated by changing from
 blue to green). (b) Mean over 15 ITDs of the standard deviation over 50 trials of the posterior
 mean estimate.

 Supplementary Figure S4. Mean and s.e.m of the bias of head-orienting responses from three
 barn owls (F, L and P) presented with high-frequency and low-frequency bandpass noise.