Cortical control of virtual self-motion using task-specific subspaces

Karen E Schroeder* [1,2], Sean M Perkins* [2,3], Qi Wang[3], & Mark M Churchland[1,2,4,5, †]

* Equal contribution

[1] Department of Neuroscience, Columbia University Medical Center, New York, NY
[2] Zuckerman Institute, Columbia University, New York, NY
[3] Department of Biomedical Engineering, Columbia University, New York, NY
[4] Kavli Institute for Brain Science, Columbia University Medical Center, New York, NY
[5] Grossman Center for the Statistics of Mind, Columbia University, New York, NY

[†] Correspondence to: mc3502@columbia.edu

Abstract

Brain-machine interfaces (BMIs) for reaching have enjoyed continued performance improvements, yet there remains significant need for BMIs that control other movement classes. The question of how to decode neural activity is inexorably linked with the intrinsic covariance structure of that activity, which may depend strongly upon movement class. Here, we develop a self-motion BMI based on cortical activity as monkeys cycle a hand-held pedal to progress along a virtual track. Unlike during reaching, there were no high-variance dimensions that directly correlated with to-be-decoded variables. Yet this challenge yielded an opportunity: we could decode a single variable – self-motion – by non-linearly leveraging structure that spanned many high-variance neural dimensions. Online BMI-control success rates approached those during manual control. Our results argue that decoding can and should be task-specific, and suggest a broad principle: even when the decoded output is low-dimensional, it can be beneficial to leverage a multi-dimensional high-variance subspace.

Introduction

Intracortical brain-machine interfaces (BMIs) that support reach-like tasks have proved successful in primates and human clinical trials (Ajiboye et al., 2017; Collinger et al., 2013; Ethier et al., 2012; Gilja et al., 2015, 2012; Shanechi et al., 2017; Shenoy and Carmena, 2014; Wodlinger et al., 2015). Yet it is unclear whether current decode algorithms will generalize well to non-reaching applications. Early reach-based BMIs (Carmena et al., 2003; Chapin et al., 1999; Serruya et al., 2002; Taylor et al., 2002; Velliste et al., 2008; Wessberg et al., 2000) employed a strategy of inverting the ostensible neural encoding of kinematic variables, primarily hand velocity and direction. Despite evidence against literal kinematic encoding (Churchland et al., 2012; Michaels et al., 2016; Russo et al., 2018; Scott et al., 2001; Sergio et al., 2005; Sussillo et al., 2015), studies continue to exploit the robust correlation between neural activity and movement direction to achieve excellent BMI performance. Improvements have derived from honing this core strategy and/or better estimating the neural state (Aghagolzadeh and Truccolo, 2016; Gilja et al., 2012; Kao et al., 2015; Makin et al., 2018). Viewed this way, current decode strategies successfully leverage a statistical regularity (aspects of neural activity correlate with velocity) that is sizeable during reach-like movements. Should non-reach-like movements leverage the same or different statistical regularities?

This question is intertwined with our evolving understanding of motor cortex covariance structure. During a given task, neural covariance is typically low-dimensional, in the sense that a handful of neural dimensions captures considerable variance (Churchland et al., 2007; Gallego et al., 2017; Sadtler et al., 2014). Nevertheless, dimensions with non-negligible variance greatly outnumber to-be-decoded variables (Churchland and Shenoy, 2007; Shenoy et al., 2013). The traditional solution is to identify a subspace where population activity is both reasonably high-variance and correlates strongly with variables one wishes to infer. For example, regressing two-dimensional cursor velocity against neural activity identifies a two-dimensional neural subspace where activity resembles velocity. A few studies have successfully leveraged additional dimensions (Degenhart et al., 2020; Gallego et al., 2020; Kao et al., 2017b; Sussillo et al., 2016, 2012), but the typical scenario is that decoding N variables leverages an N-dimensional subspace chosen to maximize correlations.

Within a given task, neural covariance structure remains surprisingly fixed even when the decoder is altered (Golub et al., 2018; Sadtler et al., 2014) and can remain similar across

related tasks (Gallego et al., 2018). Yet covariance is often not stable. Covariance changes

dramatically when cycling forward versus backward (Russo et al., 2018), when using one arm

versus another (Ames and Churchland, 2019), when preparing versus moving (Elsayed et al.,

2016; Kaufman et al., 2014), and when reaching versus walking (Miri et al., 2017). Thus, there

may be no high-variance task-independent subspace that consistently exhibits correlations

with to-be-decoded variables. This would agree with the view that the highest-variance signals

in motor cortex ensure noise-robust task-specific dynamics and do not reliably encode any

external quantity (Russo et al., 2018). This possibility creates challenges, but also

opportunities. Task-specific subspaces may be of high utility even when there is no linear

correlation between activity and a decoded variable. For example, one could decode forward

self-motion from the angular momentum of neural activity in a two-dimensional subspace. To

guide backward self-motion, a completely different neural subspace could be employed. Thus,

a one-dimensional output could potentially leverage activity spanning many dimensions.

To explore such strategies, we employed a simple task in which monkeys cycle a hand-held

pedal to move along a virtual track. The class of neural activity evoked by this task could

potentially be leveraged by future BMI devices that guide self-motion. Even more critically,

cycling is overtly different from reach- or joystick-based tasks. Prior explorations of self-

motion-decoding borrowed from the strategies employed by reach-based BMIs, and decoded

a whole-body directional vector (Rajangam et al., 2016) or classified the direction of a joystick

intermediary (Libedinsky et al., 2016). This is a promising approach, but we wished to explore

whether a task-specific approach might also be promising.

During cycling, neural activity that correlated with kinematics and/or muscle activity was

relegated to low-variance subspaces. In contrast, there existed high-variance subspaces

where neural activity had reliable non-linear relationships with intended self-motion. A decoder

leveraging those multi-dimensional subspaces provided excellent online control of a one-

dimensional command for virtual self-motion. Almost no training was needed; decoder latency

and accuracy were such that monkeys appeared to barely notice transitions from manual

control to BMI control. Success rates and acquisition times were close to those achieved

under manual control. Our results establish that BMIs can be accurately guided by strategies

that leverage task-specific subspaces containing structure that, while not directly correlating

with kinematic variables, bears a reliable relationship with desired movement.

Results

Behavior

We trained two monkeys (G and E) to rotate a hand-held pedal to move through a virtual environment (**Fig. 1**). All motion was along a linear track – no steering was necessary. Consistent with this, a single pedal was cycled with the right arm only. Our goal when decoding was to reconstruct the virtual self-motion produced by that single pedal. On each trial, a target appeared in the distance. To acquire that target, monkeys produced virtual velocity in proportion to the rotational velocity of the pedal. The color of the environment (lush and green versus desert-like and tan) instructed cycling direction. When the environment was green (**Fig. 1a**, *left*) forward virtual motion was produced by cycling 'forward' (i.e., with the hand moving away from the body at the top of the cycle). When the environment was tan (**Fig. 1a**, *right*) forward virtual motion was produced by cycling 'backward' (the hand moving toward the body at the top of the cycle). Cycling in the wrong direction produced motion away from the target. Trials were presented in blocks of forward or backward trials. Within each block, targets were separated by a randomized distance of 2, 4 or 7 cycles. Acquisition of a target was achieved by stopping and remaining stationary 'on top' of the virtual target for a specified time. Reward was then given and the next target appeared.

Monkeys performed the task well, moving swiftly between targets, stopping accurately on each target, and remaining stationary until the next target was shown. Monkeys cycled at a pace that yielded nearly linear progress through the virtual environment (**Fig. 1b**). Although not instructed to cycle at any particular angular velocity, monkeys adopted a brisk ~2 Hz rhythm (**Fig. 1c**). Small ripples in angular velocity were present during steady-state cycling; when cycling with one hand it is natural for velocity to increase on the downstroke and decrease on the upstroke. Success rates were high, exceeding 95% in every session (failures typically involved over- or under-shooting the target location). This excellent performance under manual control provides a stringent bar by which to judge performance under BMI control.

BMI control was introduced after monkeys were adept at performing the task under manual control. Task structure and the parameters for success were unchanged under BMI control, and no cue was given regarding the change from manual to BMI control. The switch to BMI control was made after completion of a block of manual-control trials (25 forward and 25 backward 7-cycle trials). These manual-control trials were used to train the decoder, at which

Figure 1. A cycling task that elicits rhythmic movements. (a) Monkeys rotated a hand-held pedal forward (*left*, cued by a green background) or backward (*right*, cued by a tan background) to progress through a virtual environment. Traces at bottom plot pedal kinematics (vertical position) and the resulting virtual world position for two example manual-control trials. On both of these trials (one forward and one backward) the monkey progressed from one target to another by cycling seven cycles. **(b)** Trial-averaged virtual position from a typical manual-control session. Each trace plots the change in virtual position (from a starting position of zero) for one of six conditions: forward or backward for 2, 4, or 7 cycles. Black circle indicates the time of movement onset. Trials were averaged after being aligned to movement onset, and then scaled such that the duration of each trial matched the average duration for that condition. **(c)** Trial-averaged pedal rotational velocity from the same session, for the same six conditions. **(d)** Firing rates of two example units. Trial-averaged firing rates (computed after temporally aligning trials) are shown for two conditions: forward (*green*) and backward (*red*) for seven cycles. Black circles indicate the timing of movement onset and offset.

point the switch was made to BMI control for the remainder of the session. For monkey G, we

occasionally included blocks of manual-control trials later in the session to allow comparison

between BMI and manual performance. For Monkey E we used separate (interleaved) sessions

to assess manual-control performance.

During both BMI control and manual control, the monkey's ipsilateral (non-cycling) arm was

restrained. The contralateral (cycling) arm was never restrained. We intentionally did not

dissuade the monkey from continuing to physically cycle during BMI control. Indeed, our goal

was that the transition to BMI control would be sufficiently seamless to be unnoticed by the

monkey, such that he would still believe that he was in manual control. An advantage of this

strategy is that we are decoding neural activity when the subject attempts to actually move, as

a patient presumably would. Had we insisted the arm remain stationary, monkeys would have

needed to actively avoid patterns of neural activity that drive movement – something a patient

would not have to do. Allowing the monkey to continue to move normally also allowed us to

quantify decoder performance via direct comparisons with intended (i.e., actual) movement.

This is often not possible when using other designs. For example, in Rajangam et. al.

(Rajangam et al., 2016), performance could only be assessed via indirect measures (e.g., time

to target) because what the monkey was actually intending to do at each moment was unclear.

We considered these advantages to outweigh a potential concern: a decoder could potentially

'cheat' by primarily leveraging activity driven by proprioceptive feedback (which would not be

present in a paralyzed patient). This is unlikely to be a large concern. Recordings were made

from motor cortex, where robust neural responses precede movement onset. Furthermore, we

have documented that motor cortex population activity during cycling is quite different from

that within the proprioceptive region of primary somatosensory cortex (Russo et al., 2018).

Thus, while proprioceptive activity is certainly present in motor cortex (Fetz et al., 1980; Lemon

et al., 1976; Schroeder et al., 2017; Suminski et al., 2009) especially during perturbations

(Pruszynski et al., 2011), the dominant features of M1 activity that we leverage are unlikely to

be primarily proprioceptive.

Given our use of healthy animals, we stress that the goal of the present study is to determine

strategies for leveraging the dominant structure of neural activity. This follows the successful

strategy of BMI studies that leveraged the well-characterized structure of activity during

reaching. Of course, the nature of the training data used to specify decode parameters (e.g.,

the weights that define the neural dimensions to be used) will necessarily be different for a

healthy animal that cannot understand verbal instructions and an impaired human that can. We
thus stress that our goal is to determine a robust and successful decode strategy that works in
real time during closed-loop performance. We do not attempt to determine the best approach
to parameter specification, which in a patient would necessarily involve intended or imagined
movement.

Neural activity and decoding strategy

We recorded motor cortical activity using 96-channel Utah arrays. For monkey G, one array
was implanted in primary motor cortex (M1) and a second in dorsal premotor cortex (PMd). For
monkey E, a single array was implanted in M1. For each channel we recorded times when the
voltage crossed a threshold. Threshold crossings typically reflected individual spikes from a
small handful of neurons (a neural 'unit'). Spikes from individual neurons could be clearly seen
on many channels, but no attempt was made to spike-sort. The benefit of sorting is typically
modest when controlling a prosthetic device (Christie et al., 2014), and reduced-dimension
projections of motor cortex population activity are similar whether based on single or multi-
units (Trautmann et al., 2019). Unit activity was strongly modulated during cycling (**Fig. 1d**). The
phase, magnitude, and temporal pattern of activity depended on whether cycling was stopped,
moving forward (*green* traces) or moving backward (*red* traces). A key question is how these
unit-level features translate into population-level features that might be leveraged to estimate
intended motion through the virtual environment.

In traditional decoding approaches (**Fig. 2a**) neural activity is hypothesized (usefully if not
literally) to encode kinematic signals, which can be decoded by inverting the encoding scheme.
Although nonlinear methods (including variations of Kalman filtering) are often used to estimate
the neural state, the final conversion to a kinematic command is typically linear or roughly so.
To explore kinematic encoding in the present task, we used linear regression to identify neural
dimensions where activity correlated well with kinematics (including hand velocity and
position). Regression was performed using single trials. Use of single trials provides a large
quantity of training data and is implicitly regularizing: regression must find signals that are
robust in the face of single-trial spiking variability. The regression weights for a given kinematic
parameter define a neural dimension where activity correlates strongly with that parameter. We
computed the neural variance captured by each such dimension. Variance captured was
computed using trial-averaged data, to ensure that values were not diluted by noise. Despite

Figure 2. Different decode strategies leverage neural signals with different magnitudes.
(a) In the traditional decoding strategy, neural firing rates are assumed to predominantly encode the key variables. The encoding model is usually assumed to be roughly linear when variables are expressed appropriately. For example, cosine tuning for reach velocity is equivalent to a linear dependence on horizontal and vertical velocity. The goal of decoding is to invert encoding. Thus, decoding dimensions should capture the dominant signals in the neural data (because those are what is encoded). **(b)** Variance of the neural population response captured by dimensions used to decode kinematic parameters (*teal bars*) and muscle activity (*light teal bar*). Data are from three manual-control sessions where units (192 channels per day) and muscles (5-7 channels per day) were recorded simultaneously. Each bar plots the average and standard error across sessions (unless otherwise specified). *Left subpanel*: variance captured for kinematic variables (individual variables shown separately) and muscles (average across 19 recordings, standard error computed across recordings). *Right subpanel*: total variance captured by subspaces spanned by kinematic-decoding dimensions, muscle-decoding dimensions, or both. (These are not the sum of the individual variances as dimensions were not always orthogonal). We had different numbers of EMG recordings per day and thus always selected a subset of five. Variance captured by the top five principal components is shown for comparison. **(c)** Example cross-validated regression performance for offline decoding of angular velocity. R^2 is the coefficient of determination for the segment of data shown. **(d)** Example cross-validated regression performance for offline decoding of horizontal and vertical pedal position. R^2 is the coefficient of determination for the segment of data shown, same time period as (c). **(e)** A new strategy that can be applied even if the dominant signals do not have the goal of encoding. This strategy seeks to find neural response features that have a robust relationship with the variable one wishes to decode. That relationship may be complex or even incidental, but is useful if it involves high-variance response features. **(f)** Similar plot to (b) but for the dimensions upon which our decoder was built. *Left subpanel*: variance captured for each of these eight dimensions. *Right subpanel*: variance captured by the eight-dimensional subspace spanned by those dimensions. Variance captured by the top eight principal components is shown for comparison.

this, the neural dimensions that best captured kinematic signals captured little population

response variance (**Fig. 2b**, *teal* bars). This was also true of neural dimensions that captured

muscle activity (**Fig. 2b**, *light teal* bar). This was initially surprising: single-neuron responses

were robustly sinusoidally modulated, as were many kinematic variables. Yet sinusoidal

response features were often superimposed upon other response features (e.g., overall shifts in

rate when moving versus not moving). Sinusoidal features also did not display phase

relationships, across forward and backward cycling, consistent with kinematic encoding

(Russo et al., 2018). As a result, the dimensions where activity correlated strongly with

kinematics captured relatively little response variance.

The fact that kinematic-encoding neural dimensions are low-variance makes them a potentially

challenging basis for decoding. For example, we identified a dimension where the projection of

trial-averaged neural activity correlated with angular velocity, which is conveniently proportional

to the quantity we wish to decode (velocity of virtual self-motion). However, because that

dimension captured relatively little variance (1.0% ± 0.2% of the overall population variance;

standard deviation across three sessions) the relevant signal was variable on single trials (**Fig.**

2c) and the correlation with angular velocity was poor ($R^2 = 0.52 \pm 0.14$). Any decode based on

this signal would result in many false starts and false stops. The observed single-trial variability

is expected for any low-variance signal estimated from a limited number of neurons.

We considered an alternative kinematic decoding strategy that more closely mimics prior

successful reach-based approaches: decoding horizontal and vertical hand position. These

were captured in slightly higher-variance dimensions, and could be decoded somewhat better

on single trials ($R^2 = [0.81 \pm 0.03, 0.85 \pm .04]$, averaged across three sessions). A reasonable

strategy would be to convert this two-dimensional neural signal (**Fig. 2d**) into a one-dimensional

self-motion command. Possible approaches for doing so include deciphering where on the circle

the hand is most likely to be at each moment, computing the angular velocity of the neural state,

or computing its angular momentum. However, consideration of such approaches raises a

deeper question. If we are willing to non-linearly decode a one-dimensional quantity (self-

motion) from a two-dimensional subspace, why stop at two dimensions? Furthermore, why not

leverage dimensions that capture most of the variance in the population response, rather than

dimensions that capture a small minority? Projections onto high-variance dimensions have

proportionally less contribution from spiking variability. They are also less likely to be impacted

by electrical interference or recording instabilities. While of little concern in a controlled

laboratory environment, this is relevant to the clinical goals of prosthetic devices. One should

thus wish to leverage multiple dimensions that jointly capture as much variance as possible, so

long as the signals captured by those dimensions can be successfully leveraged.

We term this approach (**Fig. 2e**) task-specific subspace decoding, because it seeks one or more

subspaces that capture robust response features as the subject attempts to move within the

context of a particular task (in the present case, while generating a rhythmic movement to

produce self-motion). Both the population-level response features, and the subspaces

themselves, may be specific to that task. To pursue this strategy, we identified three high-

variance subspaces. The first was spanned by four 'rotational dimensions' (two each for

forward and backward cycling) which captured elliptical trajectories present during steady-

state cycling (Russo et al., 2018). The second was a single 'moving-sensitive' dimension, in

which the neural state distinguished whether the monkey was stopped or moving regardless of

movement direction (Kaufman et al., 2016). The third was a triplet of 'initial-direction'

dimensions, in which cycling direction could be transiently distinguished in the moments after

cycling began.

In subsequent sections we document the specific features present in these high-variance

subspaces. Here we concentrate on the finding that the eight-dimensional space spanned by

these eight dimensions captured 70.9% ± 2.3% of the firing-rate variance (**Fig. 2f**). Note that

because dimensions are not orthogonal, the total captured variance is not the sum of that for

each dimension. The 'initial direction' dimensions, for example, overlap considerably with the

'rotational dimensions.' Nevertheless, the total captured variance was only modestly less than

that captured by the top eight PCs (which capture the most variance possible), and much

greater than that captured by spaces spanned by dimensions where activity correlated with

kinematics and/or muscle activity (**Fig. 2b**). We thus based our BMI decode on activity in these

eight high-variance dimensions.

Direction of steady-state movement inferred from rotational structure

The dominant feature of the population neural response during steady-state cycling was a

repeating elliptical trajectory (Russo et al., 2018). Thus, the core of our decoder was built upon

this feature, leveraging the fact that forward-cycling and backward-cycling trajectories

occurred in non-identical subspaces (**Fig. 3a,b**). We employed an optimization procedure to

find a two-dimensional 'forward plane' that maximized the size of the forward trajectory relative

Figure 3. Leveraging rotational trajectories to decode velocity. (a) Trial-averaged population activity, during a manual-control block, projected onto the forward (*top*) and backward (*bottom*) rotational planes. Data are from seven-cycle forward (*green*) and backward (*red*) conditions. By design, the forward plane primarily captures rotational trajectories during forward cycling, and vice versa. Boldly colored portions of each trace highlight rotations during the middle cycles (a period that excludes the first and last half cycle of each movement). Colored arrows indicate rotation direction. Light portion of each trace corresponds to the rest of the trial. In addition to smoothing with a causal filter, neural data have been high-pass filtered to match what was used during BMI control. Data are from monkey G. **(b)** As in panel (a), but for three example single trials, one for each of the three distances. **(c)** Example angular momentum (L) in the backward plane (*dark blue*) and forward plane (*bright blue*) during six trials of BMI control. Velocity of the pedal is shown in black. Although the pedal was disconnected, this provides a useful indication of how the monkey was intending to move. Data are from the same day shown in panels **a** and **b**. **(d)** Probability densities of angular momentums found from the training dataset collected on the same day. **(e)** Histograms of BMI-control velocity (*bottom*) and (disconnected) pedal velocity (*top*) for all times the decoder was in the STEADY state (see Methods), across all BMI-control sessions.

to the backward trajectory. We similarly found an analogous 'backward plane'. These planes
were identified based on trial-averaged responses from the 50 trials of training data collected
under manual control (**Fig. 3a**). With the aid of filtering (*Methods*), these planes continued to
capture rotational features on individual trials (**Fig. 3b**). Although forward and backward
trajectories were not orthogonal to one another, the above procedure was still able to find
planes where strongly elliptical trajectories were present for only one cycling direction. To
convert the four-dimensional neural state to a one-dimensional decode of self-motion, we
compared angular momentum (the cross product of the state vector with its derivative)
between the two planes. When moving backward (first three cycling bouts in **Fig. 3c**) angular
momentum was sizeable in the backward plane (*dark blue*) but not the forward plane (*bright*
blue). The opposite was true when moving forward (subsequent three bouts).

Based on training data, we considered the joint distribution of forward-plane and backward-
plane angular momentum. We computed distributions when stopped (**Fig. 3d**, *orange*), when
cycling forward (*green*) and when cycling backward (*red*). These distributions overlapped little,
and we fit a Gaussian to each. During BMI control, we computed the likelihood of the observed
angular momentums under each of the three distributions. If likelihood under the stopped
distribution was high, decoded velocity was zero. Otherwise, decoded velocity was determined
by the relative likelihoods under the forward and backward distributions. These likelihoods
were converted into a virtual velocity that was maximal when one likelihood was much higher
and slower when likelihoods were more similar. The maximum decoded virtual velocity was set
to approximate the typical virtual velocity under manual control, when cycling at ~2 Hz.

Distributions of decoded velocity when moving under BMI control (**Fig. 3e**, *bottom*) were
similar to the distributions of velocity that would have resulted were the pedal still operative
(**Fig. 3e**, *top*). Importantly, distributions overlapped very little; the direction of decoded motion
was almost always correct. Decoded velocity was near maximal at most times, especially for
monkey G. The decoded velocity obtained from these four dimensions (out of the eight total we
used) constituted the core of our decoder. We document the performance of that decoder in
the next section. Later sections describe how aspects of the decoder were fine-tuned by
leveraging the remaining four dimensions.

Performance

Monkeys performed the task very well under closed-loop BMI control (**Fig. 4** and **Supp. Movie**

1). Monkeys continued to cycle as normal, presumably not realizing that the pedal had been

disconnected from the control system. The illusion that the pedal still controlled the task was

supported by a high similarity between decoded virtual velocity and intended virtual velocity

(i.e., what would have been produced by the pedal were it still controlling the task). The cross-

correlation between these peaked at $0.93 \pm .02$ and $0.81 \pm .03$ (monkey G and E, mean $\pm$ SD

across sessions) at a short lag: 76 ± 4 ms and 102 ± 7 ms (**Fig. 4a**). That illusion was also

aided by a low rate of false starts; it was exceedingly rare for decoded motion to be non-zero

when the monkey was attempting to remain stationary on top of a target. False starts occurred

on 0.29% and 0.09% of trials (monkeys G and E), yielding an average of 1.9 and 0.12

occurrences per day. This is notable because combatting unintended movement is a key

challenge for BMI decoding. The above features – high correlation with intended movement,

low latency, and few false starts – led to near-normal performance under BMI control (**Fig.**

4b,c). Success rates under BMI control (**Fig. 4d**, *magenta symbols*) were almost as high as

under manual control (*open symbols*), and the time to move from target to target was only

slightly greater under BMI control (**Fig. 4e**).

The only respect in which BMI control suffered noticeably was accuracy in stopping on the

middle of the target. Under manual control, monkeys stopped very close to the target center

(**Fig. 4f,** *gray histogram*), which always corresponded to the 'pedal-straight-down' position.

Stopping was less accurate under BMI control (*magenta histogram*). This was partly due to the

fact that because virtual self-motion was swift, small errors in decoded stopping time became

relevant. E.g., a 100 ms error corresponded to ~0.2 cycles of physical motion. The average

standard deviation of decoded stopping time (relative to actual stopping time) was 133

(monkey G) and 99 ms (monkey E). The relatively larger error in BMI-control trials was also due

to an incidental advantage of manual control: the target center was aligned with the pedal-

straight-down position, a fact which monkeys leveraged to stop very accurately in that

position. This strategy was not available during BMI control because the correct moment to

stop rarely aligned perfectly with the pedal-straight-down position (this occurred only if

decoded and intended virtual velocity matched perfectly when averaged across the cycling

bout).

Figure 4. Decoder performance. (a) Summary of the cross-correlation between decoded virtual velocity under BMI control, and the virtual velocity that would have been produced by the pedal (which monkeys continued to manipulate normally). Each symbol corresponds to one BMI-control session, and plots the peak of the cross-correlation versus the lag where that peak occurred. Colors indicate success rate during that session. **(b)** Example manual-control performance for six consecutive trials, 3 forward and 3 backward. World position is expressed in terms of the number of cycles of the pedal needed to move that distance. For plotting purposes, the position at the beginning of this stretch of behavior was set to zero. Bars indicate the time that targets turned on and off (horizontal span) and the size of the acceptance window (vertical span). **(c)** Similar plot during BMI control. For ease of comparison, world position is still expressed in terms of the number of physical cycles that would be needed to travel that far, although physical cycling no longer had any impact on virtual velocity. **(d)** Success rate for both monkeys. Each symbol plots, for one session, the proportion of trials where the monkey successfully moved from the initial target to the final target, stopped within it, and remained stationary until reward delivery. Dashed line at 1 for reference. **(e)** Target acquisition times for successful trials. Center lines indicate median, the box edges indicate the first and third quartiles, and the whiskers include all non-outlier points (points less than 1.5 times the interquartile range from the box edges). Data are shown separately for the three target distances. **(f)** Histograms of stopping location from both monkeys. Analysis considers both successful and failed trials. The bar at far right indicates the proportion of trials where the monkey failed for reasons other than stopping accuracy per se. This included trials where monkeys disrespected the reaction time limits, abandoned the trial before approaching the target, or passed through the target without stopping.

Performance was modestly better for monkey G versus E. This was likely due to the

implantation of two arrays rather than one. Work ethic may also have been a factor; monkey E

performed fewer trials under both BMI and manual control. Still, both monkeys could use the

BMI successfully starting on the first day, with success rates of 0.87 and 0.74 (monkey G and

E). Monkey G's performance rapidly approached his manual-control success rate within a few

sessions. Monkey E's performance also improved quickly, although his manual-control and

BMI-control success rates were mostly lower than Monkey G's. The last five sessions involved

BMI success rates of 0.97 and 0.96 for the two monkeys. This compares favorably with the

overall averages of 0.98 and 0.95 under manual control. Although this performance

improvement with time may relate to adaptation, the more likely explanation is simply that

monkeys learned to not be annoyed or discouraged by the small differences in decoded and

intended velocity.

State machine

The performance documented above was achieved using a state-dependent decode (**Fig. 5**).

The angular-momentum-based strategy determined virtual self-motion (as described above)

when in the "STEADY" state. Thus, self-motion could be forward, backward, or stopped while

in STEADY. The use of other states was not strictly necessary but helped fine-tune

performance. State transitions were governed by activity in the moving-sensitive dimension,

which was translated into a probability of moving, p_{move} as described in the next section. If

p_{move} was low, the STOP state was active and decoded virtual velocity was enforced to be

zero. For those time-points when the STOP state was active, the angular-momentum-based

strategy would have typically estimated zero velocity even if it were not enforced.

Nevertheless, the use of an explicit STOP state was useful in nearly eliminating false starts. It

was also useful in detecting transitions from stopping to moving, allowing us to leverage the

initial-direction dimensions.

When p_{move} became high, the INIT state was entered but decoded velocity remained zero.

After 175 ms, the EARLY state was entered and velocity was decoded using the initial-direction

dimensions (see below). After an additional 200 ms, the STEADY state was entered. The

decode then depended only on the four rotational dimensions. Values of $p_{move} < 0.1$ always

produced a transition back to STOP. This typically occurred from STEADY to STOP, as the

movement was successfully ending. However, it could also occur from the other two states.

Figure 5. State machine diagram. BMI motion was determined by a state machine with four states: STOP, INIT, EARLY, and STEADY, corresponding to the different stages of a typical trial. The output of the state machine at every millisecond was an estimate of decoded velocity through the virtual environment, v_{dec}, which was then smoothed and integrated to compute virtual position. Black arrows indicate the typical path of a successful BMI trial and gray arrows indicate all other possible transitions. State transitions were governed by activity in the moving-sensitive dimension, which was translated into a probability of moving, p_{move}. While p_{move} was low, the STOP state was active and decoded velocity was set to zero. When p_{move} became high, the INIT state was entered but decoded velocity remained zero. If p_{move} remained high for 175 ms, the EARLY state was entered and velocity was decoded using the initial-direction dimensions. After another 200 ms, the STEADY state was entered and decoded velocity depended on the neural state in the rotational dimensions. If p_{move} dropped below 0.1 at any point, STOP was reentered. States in which progress is made through the virtual environment are highlighted in blue and states in which BMI motion is held at zero are highlighted in orange.

325   This was especially helpful if p_{move} became high very briefly (and presumably erroneously). In

326   such cases the state could transition from INIT back to STOP with the decoded velocity never

327   departing from zero.

Inferring the probability of moving

Decoders that directly translate neural state to cursor velocity have historically had difficulty

remaining stationary when there is no intended movement. The ability to successfully decode

stationarity is of even greater importance for self-motion. This was central to our motivation for

using a state machine with distinct stopped and moving states (Ethier et al., 2011; Kao et al.,

2017a; Kemere et al., 2008). To govern state transitions, we identified the moving-sensitive

dimension by applying linear discriminant analysis to the 50 training-data trials, and finding the

direction that best discriminated whether the monkey was moving versus stopped. Projecting

trial-averaged data onto that dimension (**Fig. 6a**) revealed that activity transitioned suddenly

from low to high just before movement onset, and back to low around the time movement

ended. This pattern was remarkably similar regardless of cycling direction (*red* and *green*

traces largely overlap). Activity in this dimension behaved similarly for single trials (**Fig. 6b**).

We used a Hidden Markov Model (HMM) (Kao et al., 2017a; Kemere et al., 2008) to estimate

p_{move}, which allows the current estimate to depend on all prior observations. Because those

observations must be independent, we did not use filtered rates (which were used for all other

aspects of the decode) but instead considered spike counts in non-overlapping bins, projected

onto the moving-sensitive dimension. Figure 6c plots the resulting distributions when stopped

(*orange*) and moving (*blue*). These overlapped modestly, a result of the narrow (10 ms) bin. The

estimate of p_{move} is robust to this overlap because the HMM leverages the full history of spike

counts; it can ignore brief weak evidence for moving while still transitioning swiftly given strong

evidence. During BMI control, p_{move} (**Fig. 6d**, *blue*) was typically near unity during intended

movement (i.e., when the monkey was actually cycling, *black*) and near zero otherwise.

Transitions both out of STOP and into STOP were determined by p_{move} (**Fig. 5**). We employed

a conservative design; entering a state that produced virtual movement required that p_{move}

exceed 0.9 and remain consistently above 0.1 for 175 ms. This led to a very low rate of false

starts (~2 per day for monkey G and ~1 every ten days for monkey E). The transition to EARLY

(**Fig. 6d**, left edge of *gray regions*) occurred on average 117 and 194 ms after physical

movement onset (monkeys G and E). Trial-to-trial variability around these mean values was

Figure 6. Leveraging the moving-sensitive dimension to infer probability of moving. (a) Trial-averaged population activity, during a manual-control block, projected onto the moving-sensitive dimension (same session and trials as Figure 3a). **(b)** As in panel (a), but for three example single trials (same trials as in Figure 3b). **(c)** Histogram of the neural state projected onto the moving-sensitive dimension for training data. The neural state was measured every ten milliseconds, at times when the monkey was stopped within a target (*orange*) or actively cycling (*blue*). Traces show Gaussian fits used to compute p_{move}. **(d)** Example time-course, during BMI control, of p_{move} (*blue*) and the active state (*magenta*). Gray regions show times when the decoder produced virtual movement (i.e., when in EARLY or STEADY). These times corresponded well to times when the monkey was intending to move, as indicated by the angular velocity of the disconnected pedal (*black*). Note also that transient inappropriate spikes in p_{move} (as seen here around 18 s) do not lead to false starts because either they don't exceed 0.9, as was the case here, or they are too brief and the EARLY state is never reached. Same example data as in Figure 3c.

modest: standard deviations were 93 and 138 ms (computed within session and averaged

across sessions). As discussed above, estimated stopping time (when p_{move} dropped below

0.1) was also decoded with only modest trial-to-trial variability.

Inferring initial movement direction

Angular momentum of the neural state in the forward and backward planes became substantial

a few hundred milliseconds after p_{move} became high. Thus, the EARLY state became active

before the direction of movement could be inferred from the elliptical trajectories. To overcome

this problem, we leveraged the three-dimensional initial-direction subspace. The initial-

direction subspace comprised the top three PCs found from portions of the training data

surrounding movement onsets (a 200 ms segment from each trial, beginning at the time the

decoder would enter the INIT state, see *Methods*). The difference between the trajectory on

forward and backward trials began to grow just prior to physical movement onset, both on

average (**Fig. 7a**) and on individual trials (**Fig. 7b**; *solid* trajectory segment shows -200 to +175

ms relative to movement onset). For each of the 50 training trials, we considered the neural

state in these dimensions, measured 175 ms after decoded movement onset (**Fig. 7c**). We fit

Gaussian distributions separately for forward and backward trials.

During BMI control, upon transition from INIT to EARLY, we computed the likelihood of the

neural state under each distribution. A simple winner-take-all computation determined the

direction of virtual velocity during the EARLY state. The inference of movement direction during

EARLY was correct on 94% and 82% of trials (monkeys G and E). After 200 ms, the STEADY

state was entered and virtual velocity was controlled thereafter by activity in the rotational

dimensions. **Figure 7d** illustrates moments (*colored regions*) where the EARLY state was active

and the above strategy was used to decode virtual motion (physical pedal velocity is shown for

reference). These moments were brief, and had a very modest effect on the overall time to

reach the target. However, we still employed this strategy because our goal was to build a BMI

decode that closely tracked intended movement and felt responsive to the subject.

Speed control

The excellent performance of the decoder was aided by the relative simplicity of behavior:

when monkeys moved, they did so at a stereotyped speed. This allowed us to concentrate on

building a decode algorithm that decoded intended direction with accurate timing, and

Figure 7. Leveraging initial-direction dimensions to allow low-latency decoding. (a)
Trial-averaged population activity, during a manual-control block, projected onto two (of three)
initial-direction dimensions (same session and trials as Figure 3a and 6a). Boldly colored
portions of traces highlight -200 ms to +175 ms relative to physical move onset. Arrows indicate
direction of trajectories. **(b)** As in panel (a), but for three example single trials (same trials as in
Figure 3b and 6b). **(c)** The location of the neural state, for training data, at the time the
state-machine (applied post-hoc to that training data) entered the EARLY state. This data (50
total trials) was used to fit two Gaussian distributions. During BMI control, when the EARLY
state was entered, virtual direction was determined by which distribution maximized the data
likelihood. **(d)** Example of initial-direction decoding during BMI control. Colored windows show
the times in the EARLY state, with red and green indicating decoded direction. Same example
data as in Figure 3c and 6d.

remained stationary if movement was not intended. However, that decode provided only

limited control of movement speed. An obvious extension is to allow finer-grained speed

control. This would presumably be desired by users of a self-motion prosthetic. Furthermore,

speed control provides one possible way of steering: e.g., by decoding the relative intensity of

intended movement on the two sides of the body. While we do not attempt that here, we still

considered it important to determine whether the neural features we identified could support

speed control.

That assessment required a task where speed control is necessary for success. We thus

trained one monkey to track various speed profiles as he progressed through the virtual

environment. Two floating targets were rendered in the foreground as the monkey cycled. The

distance between them reflected the difference between actual and instructed speed.

Obtaining juice required aligning the two floating targets while progressing towards a final

target, on which he stopped to obtain additional reward. The task was divided into trials, each

of which required moving a distance equivalent to twenty cycles under manual control. We

used eight trial-types, four each for forward and backward cycling. Two of these employed a

constant target speed (equivalent to 1 or 2 Hz cycling) and two involved a ramping speed (from

1 Hz to 2 Hz or vice versa). As above, the decoder was trained based on a small number of

manual-control trials performed at the beginning of each session. Blocks of manual-control

trials were also included for comparisons between manual and BMI-based performance.

Our decode strategy was largely preserved from that described above. However, we used a

modified state machine (**Supp. Fig. 1**) and a slightly different algorithm for transforming

rotations of the neural state into decoded virtual velocity. Direction was determined based on

which distribution (forward or backward) produced the higher likelihood of observing the

measured angular momentums (as in **Fig. 3d**). Once that choice was made, speed was

determined by the angular velocity of the neural state in that plane. Thus, faster rotational

trajectories led to faster decoded virtual velocity. We chose a scaling factor so that a given

neural angular velocity produced the speed that would have been produced by physical

cycling at that angular velocity. Neural angular velocity was exponentially filtered with a time

constant of 500 ms. The filter memory was erased on entry into a movement state (EARLY or

STEADY) from a stopped state (INIT or EXIT) to allow brisk movement onset (see *Methods)*.

Figure 8. Performance in the modified task requiring speed tracking. (a) Instructed velocity and BMI-decoded virtual velocity during 12 contiguous trials of BMI control. **(b)** Expanded view of one example trial (the last trial from panel a). The virtual velocity that would have been produced by the pedal is shown in gray for comparison. **(c)** Percentage of time spent in rewarded velocity window for trials in manual-control (2 sessions, 333 trials) and BMI-control (3 sessions, 349 trials). Center lines indicate median, the box edges indicate the first and third quartiles, and the whiskers include all non-outlier points (points less than 1.5 times the interquartile range from the box edges). **(d)** Mean absolute error (MAE) between instructed velocity and virtual velocity for both manual control and BMI control sessions. One mean error was computed per trial. Same format as (c).

The above strategy allowed smooth BMI control of movement speed. In fact, it tended to give

BMI control an intrinsic advantage over manual control. In manual control, the angular velocity

of the pedal was naturally modulated within each cycle (being higher on the downstroke),

resulting in a fluctuating virtual velocity. Such fluctuations mildly impaired the ability to match

target speed under manual control. To allow a fair comparison, we thus also applied an

exponential filter to virtual velocity under manual control. Filters were chosen separately for

BMI ($\tau = 500$ ms) and manual control ($\tau = 1000$ ms) to maximize performance. This was done

informally, in the earliest session, by lengthening the filter until success rate roughly plateaued.

The filter then remained fixed for all further sessions.

Under BMI control, decoded virtual speed closely tracked instructed speed. This was true

across trials with different constant speeds, and within trials where speed modulated with time

(**Fig. 8a,b**). To compare BMI with manual control (which were performed on separate days) we

considered all trials where the monkey completed the portion of the trial that required matching

speed (87% of trials in arm control, and 79% in BMI control). The monkey was able to match

instructed speed nearly as accurately under BMI control as under manual control. This was

true judged both by time within the rewarded speed window (**Fig. 8c**) and by the error between

virtual and instructed velocity (**Fig. 8d**).

Discussion

Task-specific subspace decoding

We have previously argued that the largest signals in motor cortex are not 'representational' –

they do not encode variables but are instead essential for noise-robust dynamics. Those

dynamics produce outgoing commands that *are* representational (they covary with the

variables they control) but are low-variance. Because the dominant neural signals must be

produced by noise-robust dynamics, they obey the property of low trajectory tangling: similar

neural states avoid being associated with dissimilar derivatives (Russo et al., 2018). There is

little guarantee that the way in which low tangling is achieved will be the same across tasks –

on the contrary, the task often determines the most natural ways to keep tangling low. Thus,

the identity and number of high-variance dimensions will likely vary across tasks, as will the

basic response features captured by those dimensions. Put differently, both the intrinsic

covariance structure of the neural activity, and the nature of its correlations with kinematics,

will likely be task specific.

In this study we demonstrated that overtly task-specific decoding can be successful. This was

true even though we identified subspaces very differently from most reach-based BMI

approaches, and converted neural activity to movement using different (and often more non-

linear) approaches. These differences were critical. Unlike reaching we found no high-variance

dimensions where neural activity correlated with kinematics. Yet by using noncoding features

in high-variance dimensions, we achieved BMI control that was sufficiently natural that

monkeys appeared not to notice that the task was no longer under manual control. By most

measures (success rate, time to target) performance under BMI control was remarkably close

to that under manual control. The main limitation of BMI control was stopping accuracy.

Although our algorithm detected stopping with ~ 0.1 second precision, even small

discrepancies could lead to the target being over or undershot by a noticeable amount. A

beneficial feature of our BMI decode is that it almost never produced movement when it was

not intended. With rare exceptions, truly zero velocity was decoded when the monkey was

intending to remain stopped on the target. We consider this a particularly important attribute of

any self-motion decoding algorithm, due to the potentially large consequences of unintended

movement of the whole body.

Population dynamics in decoding

The present approach relates to recent studies that modeled neural dynamics to improve

online (Kao et al., 2015) or offline (Aghagolzadeh and Truccolo, 2016; Gallego et al., 2020; Kao

et al., 2017b) decoding of movement kinematics. A key insight of those studies is that signals

that do not correlate directly with kinematics can be used to infer those that do. For linear

decoding, the value of a given variable depends upon the neural state in one dimension: the

dimension defined by the regression weights. Nevertheless, inferring the neural state in that

dimension may benefit from a dynamical model that spans multiple dimensions. Much like the

present approach, this allows the decode to leverage features that are robust, even if they do

not directly correlate with the kinematic parameters of interest. The present approach extends

this idea to situations where there may be no high-variance dimensions that can be linearly

decoded, and/or where the most prominent features are not well-described by linear dynamics.

Another way of leveraging additional dimensions – or even the full neural state – would be to

use a trained recurrent neural network (RNN) to decode parameters of interest (Sussillo et al.,

2012; Willett et al., 2020). This is a promising approach, but also has known drawbacks. For

safety in clinical implementation, it may be crucial to know which features the decoder is

actually exploiting, and to understand how it uses them. We therefore decided to work with

hand-selected features. While these features will not generalize to different tasks, that is in

some sense the point: the presence of task-specific covariance structure essentially ensures

that any decoding approach will need to be task-specific.

Self-motion BMIs

In choosing an alternative to traditional reach-based BMI tasks, we had three reasons for

focusing on a BMI for virtual self-motion. First, our recently developed cycling task naturally

lends itself to this application. Second, BMI-controlled self-motion is likely to be desired by a

large patient population (potentially much larger than the population that desires BMI-

controlled cursors or robot arms). Third, prior work has demonstrated that BMI control of self-

motion is viable (Libedinsky et al., 2016; Rajangam et al., 2016). In particular, Rajangam et al.

(Rajangam et al., 2016) demonstrated BMI control of a physical wheelchair based on neural

activity recorded from monkey motor and somatosensory cortex. Our work supports their

conclusion that BMI-controlled self-motion is possible, and demonstrates the feasibility of an

alternative decode strategy. Rajangam et al. employed a traditional decode strategy: linear

filters transformed neural activity into the key variables: translational and angular velocity. That

strategy allowed monkeys to navigate ~2 meters to a target (which had to be approached with

an accuracy of +/- ~0.2 meters, or 10% of the distance traveled) in an average of 27-49

seconds (depending on the monkey and degree of practice). In our task, monkeys had to stop

with similar relative accuracy: +/- 0.5 cycles, or 7% of the distance traveled for a seven-cycle

movement. They traversed those seven cycles in ~4 seconds under BMI control (averages of

4.3 and 3.7 seconds for monkey G and E). While this is roughly tenfold faster, we stress that

movement durations are not directly comparable between our task and theirs. Success

requirements differed in multiple ways. For example, Rajangam et al. required that monkeys

turn *en route* (which adds considerable challenge) but did not require them to stop on the

target location. Yet while direct comparison is not possible, a tenfold improvement in time-to-

target argues that task-specific subspace decode strategies can be effective and should be

explored further.

An obvious limitation of the current study is that we did not explore strategies for steering,

which would be essential to a real-world self-motion prosthetic. There exist multiple candidate

strategies for enabling steering. Rajangam et al. used a Wiener filter to decode angular velocity

of the body. While straightforward, this strategy appears to have had limited success: even

during training, the R^2 of their angular velocity decode was 0.16 and 0.12 for the two monkeys.

One alternative strategy would be to apply our decode strategy bilaterally, and employ a

comparison (e.g., between left and right cycling speed) to control angular velocity. This

strategy should be viable even with a unilateral implant; recent work has shown that

information about both forelimbs can be decoded equally well from either hemisphere (Ames

and Churchland, 2019; Heming et al., 2019). Another strategy would be to control translational

velocity using the strategies developed here, but use a reach-like decode for steering (rather

like pedaling a bicycle while also steering). Which (if any) of these three strategies is preferable

remains a question for future experiments.

Methods

Subjects and primary task

All procedures were approved by the Columbia University Institutional Animal Care and Use
Committee. Subjects G and E were two adult male macaque monkeys (*Macaca mulatta*).
Monkeys sat in a primate chair facing an LCD monitor (144 Hz refresh rate) that displayed a
virtual environment generated by the Unity engine (Unity Technologies, San Francisco, CA).
The head was restrained via a titanium surgical implant. While the monkey's left arm was
comfortably restrained, the right arm grasped a hand pedal. Cloth tape was used to ensure
consistent placement of the hand on the pedal. The pedal connected via a shaft to a motor
(Applied Motion Products, Watsonville, CA), which contained a rotary encoder that measured
the position of the pedal with a precision of 1/10,000 of the cycle. The motor was also used to
apply forces to the pedal, endowing it with virtual mass and viscosity.

Manual-control sessions for the primary cycling task required that the monkey cycle the pedal
in the instructed direction to move through the virtual environment, and stop on top of a lighted
target to collect juice reward. The color of the landscape indicated whether cycling must be
'forward' (green landscape, the hand moved away from the body at the top of the cycle) or
'backward' (tan landscape, the hand moved toward the body at the top of the cycle). There
were 6 total conditions, defined by cycling direction (forward or backward) and target distance
(2, 4, or 7 cycles). Distance conditions were randomized within same-direction blocks (3 trials
of each distance per block), and directional blocks were randomized over the course of each
experiment. Trials began with the monkey stationary on a target. A second target appeared in
the future. To obtain reward, the monkey had to cycle to that target, come to a halt 'on top' of
it (in the first-person perspective of the task) and remain stationary for a hold period of 1000-
1500 ms (randomized). A trial was aborted without reward if the monkey began moving before
target onset (or in the 170 ms after, which would indicate attempted anticipation), if the
monkey moved past the target without stopping, or if the monkey moved while awaiting
reward. The next trial began 100 ms after the variable hold period. Monkeys performed until
they received enough liquid reward that they chose to desist. As their motivation waned, they
would at times take short breaks. For both manual-control and BMI-control sessions, we
discarded any trials in which monkeys made no attempt to initiate the trial, and did not count
them as 'failed'. These trials occurred 2 ± 2 times per session (mean and standard deviation,
Monkey G, maximum 10) and 3 ± 3 times per session (Monkey E, maximum 11).

In BMI control, trial parameters and failure conditions were the same as in manual control, for
purposes of comparison. The only difference between manual and BMI control was that, in the
latter, position in the virtual environment was controlled by the output of a decoder rather than
the pedal. We did not prevent or discourage the monkey from cycling during BMI-control
blocks, and he continued to do so as normal. In BMI control, monkey G performed an average

of 654 trials/session over 20 sessions and monkey E performed an average of 137

trials/session over 17 sessions. Manual-control data for monkey G (average of 229

trials/session over 8 sessions) were collected during sessions in which BMI-control data sets

were also collected. Manual-control sessions for monkey E (average of 231 trials/session over

5 sessions) were interleaved with BMI-control sessions on different days. For monkey G, an

additional three manual-control sessions (189, 407, and 394 trials) were employed to record

EMG, which was used for the variance captured analysis (**Fig. 2**). We recorded from 5-7

muscles per session, yielding a total of 19 recordings. We made one or more recordings from

the three heads of the *deltoid*, the lateral and long heads of *triceps brachii*, the *biceps brachii*,

trapezius, and *latissimus dorsi*. These muscles were selected due to their clear activations

during the cycling task.

Surgery and neural/muscle recordings

Neural activity was recorded using chronic 96-channel Utah arrays (Blackrock Microsystems,

Salt Lake City, UT), implanted in the left hemisphere using standard surgical techniques. In

each monkey, an array was placed in the region of primary motor cortex (M1) corresponding to

the upper arm. In monkey G, a second array was placed in dorsal premotor cortex (PMd), just

anterior to the first array. Array locations were selected based on MRI scans and anatomical

landmarks observed during surgery. Experiments were performed 1-8 months (monkey G) and

3-4 months (monkey E) after surgical implantation. Neural responses both during the task and

during palpation confirmed that arrays were in the proximal-arm region of cortex.

Electrode voltages were filtered (band-pass 0.3 Hz – 7.5 kHz) and digitized at 30 kHz using

Digital Headstages, Digital Hubs, and Cerebus Neural Signal Processors from Blackrock

Microsystems. Digitized voltages were high-pass filtered (250 Hz) and spike events were

detected based on threshold crossings. Thresholds were set to between -4.5 and -3 times the

RMS voltage on each channel, depending on the array quality on a given day. On most

channels, threshold crossings included clear action-potential waveforms from one or more

neurons, but no attempt was made to sort action potentials.

Intra-muscular EMG recordings were made using pairs of hook-wire electrodes inserted with

30 mm x 27 gauge needles (Natus Neurology, Middleton, WI). Raw voltages were amplified and

filtered (band-pass 10 Hz – 10 kHz) with ISO-DAM 8A modules (World Precision Instruments,

Sarasota, FL), and digitized at 30 kHz with the Cerebus Neural Signal Processors. EMG was

then digitally band-pass filtered (50 Hz – 5 kHz) prior to saving for offline analysis. Offline, EMG

recordings were rectified, low-pass filtered by convolving with a Gaussian (standard deviation:

25 ms), downsampled to 1 kHz, and then fully normalized such that the maximum value

achieved on each EMG channel was 1.

A real-time target computer (Speedgoat, Bern, CH) running Simulink Real-Time environment

(MathWorks, Natick, MA) processed behavioral and neural data and controlled the decoder

output in online experiments. It also streamed variables of interest to another computer that
saved these variables for offline analysis. Stateflow charts were implemented in the Simulink
model to control task state flow as well as the decoder state machine. Real-time control had
millisecond precision.

Spike trains were causally converted to firing rates by convolving each spike with a beta kernel.
The beta kernel was defined by temporally scaling a beta distribution (shape parameters: $\alpha = 3$
and $\beta = 5$) to be defined over the interval [0, 275] ms and normalizing the kernel such that the
firing rates would be in units of spikes/second. The same filtering was applied for online
decoding and offline analyses. Firing rates were also mean centered (subtracting the mean rate
across all times and conditions) and normalized. During online decoding, the mean and
normalization factor were values that had been computed from the training data. We used soft
normalization (Russo et al., 2018): the normalization factor was the firing rate range plus a
constant (5 spikes/s).

Computing trial-averaged firing rates

Analyses of BMI performance are based on real-time decoding during online performance, with
no need to consider trial-averaged firing rates. However, we still wished to compute trial-
averaged traces of neural activity and kinematics for two purposes. First, some aspects of
decoder training benefited from analyzing trial-averaged firing rates. Second, we employ
analyses that document basic features of single-neuron responses and of the population
response (e.g., **Fig. 1d**, **Fig. 3a**, **Fig. 6a, Fig. 7a**). These analyses benefit from the denoising
that comes from computing a time-varying firing rate across many trials. Due to the nature of
the task, trials could be quite long (up to 20 cycles in the speed-tracking task), rendering the
traditional approach of aligning all trials to movement onset insufficient for preserving
alignment across all subsequent cycles. It was thus necessary to modestly adjust the time-
base of each individual trial (e.g., stretching time slightly for a trial where cycling was faster
than typical). We employed two alignment methods. Method A is a simplified procedure that
was used prior to parameter fitting when training the decoder before online BMI control. This
method aligns only times during the movement. Method B is a more sophisticated alignment
procedure that was utilized for all offline analyses. This method aligns the entire trial, including
pre- and post-movement data. For visualization, conditions with the same target distance (e.g.,
7 cycles), but different directions, were also aligned to the same time base. Critically, any data
processing that relied on temporal structure was completed in the original, unstretched time
base prior to alignment.

Method A*:* The world position for each trial resembles a ramp between movement onset and
offset (**Fig. 1a**). First, we identify the portion of each trial starting ¼ cycle into the movement
and ending ¼ cycle before the end of the movement. We fit a line to the world position in this
period and then extend that line until it intercepts the starting and ending positions. The data

between these two intercepts is considered the movement data for each trial and is extracted.
This movement data is then uniformly stretched in time to match the average trial length for
each trial's associated condition. This approach compresses slower than average movements
and stretches faster than average movements within a condition, such that they can be
averaged while still preserving many of the cycle-specific features of the data.

Method B: This method consists of a mild, non-uniform stretching of time in order to match
each trial to a condition-specific template. For complete details, see Russo et al. 2018. (Russo
et al., 2018)

Variance captured analysis

Analysis of neural variance captured (**Fig. 2**) was based on successful manual-control trials
from the three sessions with simultaneous neural and muscle recordings. We considered data
from the full duration of each trial, including times before movement onset and after movement
offset. We analyzed the variance captured by neural dimensions of three types. First, neural
dimensions where activity correlated strongly with kinematic features. Second, neural
dimensions where activity correlated strongly with muscle activity. Third, neural dimensions
that captured robust 'features' leveraged by our decoder.

Dimensions of the third type (were found as detailed below in a dedicated section below.
Dimensions of the first two types were found using the model $z(r,t) = c + \boldsymbol{w}^\top \boldsymbol{y}(r,t)$, where
$z(r,t)$ is the kinematic or muscle variable at time t during trial r, and $\boldsymbol{y}(r,t)$ is the
corresponding *N*-dimensional vector of neural firing rates. The constant c and the column
vector $\boldsymbol{w}$ were found via regression. The vector $\boldsymbol{w}$ defines a direction in neural space where
activity correlates strongly with the variable z. We found multiple such vectors; e.g. $\boldsymbol{w}_{x-vel}$ is a
dimension where neural activity correlates with horizontal velocity and $\boldsymbol{w}_{biceps}$ is a dimension
where neural activity correlates with biceps activity. All such vectors were scaled to have unity
norm before computing the neural variance captured by that dimension. Regression was based
on single-trial responses because this was intrinsically regularizing. We wished to encourage
regression to find high-variance dimensions if possible, and the use of single-trial data
encouraged it to do so. Because filtering of neural activity introduces a net lag, this analysis
naturally assumes a ~100 ms lag between neural activity and the variables of interest. Results
were extremely similar if we considered longer or shorter lags.

We wished to compute, for each dimension, the percentage of neural variance explained – i.e.,
whether that dimension captured large or small signals. We were not interested in whether
dimensions captured stochastic spiking variability, but in whether they captured large features
that were reliable across trials. Thus, variance captured was always computed based on trial-
averaged neural responses. We considered the matrix $\overline{Y} \in \mathbb{R}^{N \times T}$ where T is the total number of
time points across all conditions. Each row of $\overline{Y}$ contains the trial-averaged firing rate of one

neuron. We computed an $N \times N$ covariance matrix $\Sigma = \mathrm{cov}(\overline{Y})$ by treating rows of $\overline{Y}$ as random
variables and columns as observations. The proportion of total neural variance captured by a
given dimension, $\boldsymbol{w}$, is therefore:

$$\frac{\boldsymbol{w}^\top \Sigma \boldsymbol{w}}{\mathrm{tr}(\Sigma)}$$

Some analyses considered the variance captured by a subspace spanned by a set of
dimensions. To do so we took the sum of the variance captured by orthonormal dimensions
spanning that space.

Decoding from kinematic dimensions

Offline decodes **(Fig. 2c,d)** were performed using the same arm-control datasets described in
the previous section, but in this analysis the data were split into training and testing sets. The
training set for a session comprised the first 25 forward and 25 backward trials of that day (the
same training set size used in our online decodes). Regression dimensions were found for
these training sets as described above, and coefficients of determination were calculated on
the test sets.

Identifying neural dimensions

Although the response features leveraged by the decode algorithm are clearly visible in the top
principal components of the data (when PCA is performed on the full trial-averaged time-series
of firing rates across conditions), we sought to choose neural dimensions that would cleanly
isolate particular features. To this end, each feature was isolated using dedicated
preprocessing and dimensionality reduction approaches.

We sought a moving-sensitive dimension, the projection onto which would allow an HMM to
estimate the probability of moving, p_{move}, at each moment. To do so, we first computed binned
spike-counts (10 ms for monkey G, 20 ms for monkey E) and applied a square-root transform
to these counts as this has been shown to improve the Gaussian fit for Poisson data with small
counts (Thacker and Bromiley, 2001). We then aggregated all of these square-rooted binned
counts from the training set (25 forward trials, 25 backward trials) and separated them into two
classes based on pedaling speed: 'moving' (speed > 1 Hz) and 'stopped' (speed < .05 Hz).
Samples that didn't fall into either of these two classes were discarded. We applied linear
discriminant analysis to these two labeled sets, which yielded a discriminating hyperplane that
best separated the two classes. We defined the moving-sensitive dimension, $\boldsymbol{w}_{move}$, as the
vector normal to this hyperplane.

In order to decode direction, we sought to isolate four neural dimensions that captured
rotational trajectories during steady-state cycling. Spike time-series were filtered to yield firing
rates (as described above), and then further high-pass filtered (2nd order Butterworth, cutoff

frequency: 1 Hz). This removed drift or other low-frequency signals. Single-trial movement-
period responses were then aligned (Method A) and averaged within conditions to generate
$N \times T_c$ matrices $\overline{Y}_f$ and $\overline{Y}_b$. We sought a 4-dimensional projection of these trial-averaged
responses that would maximally capture rotational trajectories while segregating forward and
backward data into different planes. Whereas the standard PCA cost function finds dimensions
that maximize variance captured, we opted instead for a cost function that would maximize the
difference in variance captured between the two conditions:

708
$$J(W) = \mathrm{tr}(W^\top \Sigma_f W) - \mathrm{tr}(W^\top \Sigma_b W)$$

where $\Sigma_f = \mathrm{cov}(\overline{Y}_f)$, $\Sigma_b = \mathrm{cov}(\overline{Y}_b)$, W is constrained to be orthonormal. Note that this cost
function will be maximized when the projection of the data captures a great deal of variance for
forward trials and very little variance for backward trials. Conversely, this cost function will be
minimized when the projection favors large variances for backward trials and small variances
for forward trials. We thus chose to define our forward rotational plane by the 2D matrix $W_f =$
$\left[\boldsymbol{w}_f^{(1)} \quad \boldsymbol{w}_f^{(2)} \right]$ that maximizes $J(W)$ and our backward rotational plane by the 2D matrix $W_b =$
$\left[\boldsymbol{w}_b^{(1)} \quad \boldsymbol{w}_b^{(2)} \right]$ that minimizes $J(W)$. An iterative optimization procedure was used to find W_f and
W_b with the Manopt toolbox (Boumal et al., 2014); full details of this in (Cunningham and
Ghahramani, 2015).

To decode direction during the EARLY state, we found a set of initial-direction dimensions. We
used activity in the moving-sensitive dimension to determine the time, t_{init}, at which the state
machine would have entered the INIT state during online control. We then considered trial-
averaged neural activity, for each condition. from t_{init} through $t_{init} + 200$ ms. We applied PCA
and retained the top three dimensions: $\boldsymbol{w}_{dir}^{(1)}$, $\boldsymbol{w}_{dir}^{(2)}$, and $\boldsymbol{w}_{dir}^{(3)}$. Such dimensions capture how
activity evolves both across that timespan, and how it differs across forwards and backwards
cycling conditions.

Computing probability of moving (p_{move})

To compute p_{move} based on neural activity in the moving-sensitive dimension, an HMM was
used to track two states: 'moving' or 'stopped' (Kao et al., 2017a). Square-rooted spike counts
in the training data were already separated into 'moving' and 'stopped' sets for the purposes of
identifying $\boldsymbol{w}_{move}$. We projected those counts onto $\boldsymbol{w}_{move}$ and a fit Gaussian distribution for
each state. The probability, p_{move}, of being in the 'moving' state, given the entire sequence of
current and previously observed square-rooted spike counts, was computed efficiently with a
recursive algorithm that uses the state transition matrix

733
$$\Phi = \begin{bmatrix} p_{move|move} & p_{move|stop} \\ p_{stop|move} & p_{stop|stop} \end{bmatrix}$$

and knowledge of the Gaussian distributions. Φ encodes prior assumptions about the

probability of transitioning from one state to the next at any given bin. We used a benchmark

set of manual-control training data from each monkey to determine reasonable values for Φ,

which were then used in all experiments. For monkey G, we set $p_{move|stop} = .0001$ and

$p_{stop|move} = .002$; for monkey E, we set $p_{move|stop} = .0002$ and $p_{stop|move} = .004$. The value

p_{move} was used throughout the decoder state machine to control transitions between various

states, effectively dictating the movement onset and offset behavior of the decoder (**Fig. 6d**).

Computing steady-state direction and speed

Projecting single-trial, high-pass filtered firing rates onto the rotational planes spanned by W_f

and W_b yielded trajectories that differed considerably between forward and backward

conditions. To further denoise these state trajectories we applied a Kalman filter of the form

$$x_t = Ax_{t-1} + q_t$$
$$y_t = Cx_t + r_t$$

where $q_t \in \mathcal{N}(0, Q)$, and $r_t \in \mathcal{N}(0, R)$. In these equations, x_t represents the true underlying

neural state in the rotational dimensions and y_t are the high-pass filtered firing rates, which we

treat as noisy measurements of that underlying state. We chose to let our measurements be

smooth firing rates, rather than use non-overlapping bins of spikes, for purely opportunistic

reasons: it consistently yielded better performance by our decoder. The parameters of the

Kalman filter were fit to the training data as follows:

$$A = \overline{X}_2 \overline{X}_1^\top \left(\overline{X}_1 X_1^\top \right)^{-1}$$

$$C = \begin{bmatrix} W_f^\top \\ W_b^\top \end{bmatrix}^{\dagger}$$

$$Q = \mathrm{cov}(\overline{X}_2 - A\overline{X}_1)$$

$$R = \mathrm{cov}(Y - C\overline{X})$$

757 where

$$\overline{X}_1 = \begin{bmatrix} W_f^\top \\ W_b^\top \end{bmatrix} [\overline{Y}_f(:,1:T_f - 1), \overline{Y}_b(:,1:T_b - 1)]$$

$$\overline{X}_2 = \begin{bmatrix} W_f^\top \\ W_b^\top \end{bmatrix} [\overline{Y}_f(:,2:T_f), \overline{Y}_b(:,2:T_b)]$$

$$\overline{X} = \begin{bmatrix} W_f^\top \\ W_b^\top \end{bmatrix} [\overline{Y}_1, \overline{Y}_2, \dots, \overline{Y}_{50}]$$

$$Y = [Y_1, Y_2, \dots, Y_{50}]$$

with Y_i denoting the neural activity (high-pass filtered firing rates) for the i-th trial in the training

set, $\overline{Y}_i$ denoting the trial-averaged activity for the condition that the i-th trial is an instantiation

of, † denoting the Moore-Penrose pseudoinverse, and the colon symbol designating how to

index matrices (e.g., $M(:, a{:}b)$ refers to the submatrix of M including all rows of M, but only the

columns a through b). Lastly, the initial state parameter x_0 was computed by taking the

average value of the trial-averaged projections over all times and conditions. Online inference

of the underlying neural state, which yields an estimate $\hat{x}_t$ at each millisecond t, was computed

recursively using the steady-state form of the Kalman filter (Malik et al., 2011).

After denoising the neural state in the rotational dimensions via the Kalman filter, angular

momentum was computed in each plane as the cross product between the estimated neural

state and its derivative, which (up to a constant scaling) can be written

773
$$L(t) = \begin{bmatrix} L_f(t) \\ L_b(t) \end{bmatrix} = \begin{bmatrix} \hat{x}_{t-1}^{(1)}\hat{x}_t^{(2)} - \hat{x}_t^{(1)}\hat{x}_{t-1}^{(2)} \\ \hat{x}_{t-1}^{(3)}\hat{x}_t^{(4)} - \hat{x}_t^{(3)}\hat{x}_{t-1}^{(4)} \end{bmatrix}$$

where the superscript indexes the elements of $\hat{x}_t$. We fit 2D Gaussian distributions to these

angular momentums for each of three behaviors in the training data: 'stopped' (speed < .05

Hz), 'pedaling forward' (velocity > 1 Hz), and 'pedaling backward' (velocity < -1 Hz) (**Fig. 3d**).

Online, the likelihood of the observed angular momentums with respect to each of these three

distributions dictated the steady-state estimates of direction and speed. We'll denote these

three likelihoods f_{stop}, $f_{forward}$, and $f_{backward}$.

In general, one can compute which of these three distributions is most likely by choosing the

maximizing likelihood and assess confidence in that choice by comparing the relative values of

the three likelihoods. However, we wanted the decoder to err on the side of withholding

movement. We therefore set a conservative threshold on f_{stop} corresponding to the point at

which L would have a Mahalanobis distance of 3 to the stopped distribution of angular

momentums. If f_{stop} ever exceeded this threshold, we set $speed_{steady}$ to zero. If this condition

was not met, we decoded direction and speed as follows:

787
$$direction_{steady}(t) = \text{sgn}\left(f_{forward}(t) - f_{backward}(t)\right)$$

788
$$speed_{steady}(t) = \left| 2 \cdot \frac{f_{forward}(t)}{f_{forward}(t) + f_{backward}(t)} - 1 \right| \beta$$

789   where $\left| 2 \cdot \frac{f_{forward}(t)}{f_{forward}(t)+f_{backward}(t)} - 1 \right|$ varies between 0 and 1 depending on the relative sizes of

790   the likelihoods (yielding a slower velocity if the direction decode is uncertain) and β is a

791   direction-specific constant learned from the training data whose purpose is simply to scale up

792   the result to match steady-state cycling speed. In practice, $speed_{steady}$ was frequently very

793   close to the monkeys' steady-state cycling speeds (**Fig. 3e**).

Computing initial direction and speed

Initial direction and speed were always computed at the moment the EARLY state was entered, t_{early}. These values then persisted throughout the remainder of the EARLY state. Given that the decoder state machine doesn't make use of the initial-direction dimensions prior to entering the EARLY state, t_{early} can be computed for the training trials. Single-trial firing rates from the training set were then projected onto the initial-direction dimensions at t_{early} and 3D Gaussian distributions were fit to the resulting sets of forward and backward neural states. Online, firing rates were projected onto the initial-direction dimensions at t_{early} and likelihoods $g_{forward}$ and $g_{backward}$ were computed with respect to each the learned distributions. If the observed neural state in the initial-direction subspace was not an outlier (>10 Mahalanobis distance units) with respect to both distributions, then the initial direction and speed were computed as follows:

$$direction_{initial}(t_{early}) = \text{sgn}\left(g_{forward}(t_{early}) - g_{backward}(t_{early})\right)$$

$$speed_{initial}(t_{early}) = \left|2 \cdot \frac{g_{forward}(t_{early})}{g_{forward}(t_{early}) + g_{backward}(t_{early})} - 1\right|\beta$$

If the observed neural state was an outlier, initial direction and speed were computed in the same manner as is done in the STEADY state.

Smoothing of decoded velocity

In the primary experiment, the decoder state machine produced an estimate of velocity, v_{dec}, at every millisecond. During the STOP and INIT states, this estimate was zero and the monkey's position in the virtual environment was held constant. During the EARLY and STEADY states, this estimate was smoothed with a trailing average:

$$v'_{dec}(t) = \frac{1}{T_{smooth} + 1} \sum_{i=0}^{T_{smooth}} v_{dec}(t - i)$$

where $T_{smooth} = \min(500, t - t_{early})$, i.e., the trailing average extended in history up to 500 ms or to the moment the EARLY state was entered, whichever was shorter. v'_{dec} was integrated every millisecond to yield decoded position in the virtual environment. In the speed-tracking experiment (described below) there was no need to smooth of v_{dec} prior to integration because the speed estimate had already been smoothed.

Speed-tracking task

In addition to the primary task (where the monkey traveled 2-7 cycles between stationary targets) we employed a speed-tracking task, in which the monkey was required to match his virtual speed to an instructed speed. Speed was instructed implicitly, via the relative position of

two moving targets. The primary target was located a fixed distance in front of the monkey's
location in virtual space: the secondary target fell 'behind' the first target when cycling was too
slow, and pulled 'ahead' if cycling was too fast. This separation saturated for large errors, but
for small errors was proportional to the difference between the actual and instructed speed.
This provided sufficient feedback to allow the monkey to track the instructed speed even when
it was changing. Because there was no explicit cue regarding the absolute instructed speed,
monkeys began cycling on each trial unaware of the true instructed speed profile and 'honed
in' on that speed over the first ~2 cycles.

We quantify instructed speed not in terms of the speed of translation through the virtual
environment (which has arbitrary units) but in terms of the physical cycling velocity necessary
to achieve the desired virtual speed. E.g., an instructed speed of 2 Hz necessitated cycling at
an angular velocity of 2 Hz to ensure maximal reward. Under BMI control, the output of the
decoder had corresponding units. For example, a 2 Hz angular velocity of the neural trajectory
produced movement at the same speed as 2 Hz physical cycling (see *'Neural features for*
speed-tracking' for details of decoder). Reward was given throughout the trial so long as the
monkey's speed was within 0.2 Hz of the instructed speed. We employed both constant and
ramping instructed-speed profiles.

Constant profiles were at either 1 Hz or 2 Hz. Trials lasted 20 cycles. After 18 cycles, the
primary and secondary targets (described above) disappeared and were replaced by a final
stationary target two cycles in front of the current position. Speed was not instructed during
these last two cycles; the monkey simply had to continue cycling and stop on the final target to
receive a large reward. Analyses of performance (e.g., **Fig. 8c,d**) were based on the ~16 cycle
period starting when the monkey first honed in on the correct speed (within 0.2 Hz of the
instructed speed) and ending when the speed-instructing cues disappeared 2 cycles before
the trial's end.

Ramping profiles began with three seconds of constant instructed speed to allow the monkey
to hone in on the correct initial speed. Instructed speed then ramped, over 8 seconds, to a new
value, and remained constant thereafter. As for constant profiles, speed-instructing cues
disappeared after 18 cycles and the monkey cycled two further cycles before stopping on a
final target. Again, analyses of performance were based on the period from when the monkey
first honed in on the correct speed, to when the speed-instructing cues disappeared. There
were two ramping profiles: one ramping up from 1 to 2 Hz, and one ramping down from 2 to 1
Hz. There were thus four total speed profiles (two constant and two ramping). These were
performed for both cycling directions (presented in blocks and instructed by color as in the
primary task) yielding eight total conditions. This task was only performed by monkey G, who
completed an average of 166 trials/session over 2 sessions in manual control and an average
of 116 trials/session over 3 sessions in BMI control.

As will be described below, the speed decoded during BMI control was low-pass filtered to
remove fluctuations due to noise. This had the potential to actually make the task easier under
BMI control, given that changes in instructed speed were slow within a trial (excepting the
onset and offset of movement). We did not wish to provide BMI control with an 'unfair'
advantage in comparisons with manual control. We therefore also low-pass filtered virtual
speed while under manual control. Filtering (exponential, $\tau = 1$ second) was applied only when
speed was above 0.2 Hz, so that movement onset and offset could remain brisk. This aided the
monkey's efforts to track slowly changing speeds under manual control.

During training and while under manual control, trials were failed if there was ever a large
discrepancy between actual and instructed speed. This ensured that monkeys tried their best
to consistently match speed at all times. We relaxed this failure mode under BMI control
because we did not wish to mask large failures in decoded speed. Over the course of single
sessions, this did not discourage monkeys from trying their best, but simply allowed us to
observe and quantify decode failures that would otherwise have resulted in aborted trials. This
potentially puts BMI performance – quantified as in **Figure 8c,d** – at a disadvantage relative to
manual control, where large errors could not persist. In practice this was not an issue as large
errors were rare.

Neural features for speed-tracking

Although the speed-tracking experiment leveraged the same dominant neural responses that
were used in the primary experiment, the specific features calculated for the decoder state
machines differed. Details on how the relevant features were calculated in the speed-tracking
experiment are presented in this section.

The probability of moving, p_{move}, was calculated using a different set of parameters for speed-
tracking, largely due to changes in recording quality in the intervening time between data
collection from the primary experiment and data collection for the speed-tracking experiment.
The bin size was increased to 100 ms and the following state transition values were used:
$p_{move|stop} = .0005$ and $p_{stop|move} = .0005$. In addition, we observed that the square-root
transform seemed to be having a negligible impact on the quality of the decoder at this bin
size, so we removed it for this task.

Several features used in the speed-tracking state machine rely on neural activity in the
rotational dimensions. In the primary experiment, this activity was high-pass filtered (cutoff
frequency: 1 Hz) prior to projection into these dimensions, which helped isolate the rotational
neural trajectories during ~2 Hz cycling. For speed-tracking, we wanted to accommodate a
broader range of cycling speeds (which corresponded to a broader range of periodicities in the
rotational neural trajectories). Thus, we dropped the cutoff frequency from 1 Hz to 0.75 Hz for
this experiment.

In computing $direction_{steady}$, the same computations were performed as for the primary-
experiment, with one exception: a new direction was not necessarily decoded every
millisecond. In order to decode a new direction, the follow conditions needed to be met: 1) the
observed angular momentums had a Mahalanobis distance of less than 4 to the distribution
corresponding to the decoded direction, 2) the observed angular momentums had a
Mahalanobis distance of greater than 6 to the distribution corresponding to the opposite
direction. These criteria ensured that a new steady-state direction was only decoded when the
angular momentums were highly consistent with a particular direction. When these criteria
were not met, the decoder continued to decode the same direction from the previous time
step.

Speed was computed identically in the EARLY and STEADY states by decoding directly from
the rotational plane corresponding to the decoded direction. A coarse estimate of speed was
calculated as the derivative of the phase of rotation follows:

911
$$\theta'(t) = \begin{cases} \dfrac{d\theta_f}{dt}, & direction(t) = +1 \\ \dfrac{d\theta_b}{dt}, & direction(t) = -1 \end{cases}$$

where $\theta_f(t)$ and $\theta_b(t)$ are the phases of the two planes in the neural state estimate $\hat{x}_t$,
$direction$ corresponds to $direction_{early}$ while in the EARLY state and $direction_{steady}$ while in
the STEADY state, and the derivative θ' is computed in units of Hz. The coarse speed estimate,
θ', was then smoothed with an exponential moving average ($\tau = 500$ ms) to generate $speed$, the
variable that gets used in the decoder state machine. Additional saturation limits were set such
that $speed$ never dropped below 0.5 Hz or exceeded 3.5 Hz, so as to remain in the range
typically seen during pedaling. On entry into EARLY or STEADY from either INIT or EXIT, when
$speed$ gets initialized, the output of this exponential moving average was reset to an initial
value of 1.5 Hz, which was the average starting speed across conditions.

Lastly, there were two new conditions for decoder state transitions in the speed-tracking
experiment (**Supp. Fig. 1**). First, transitions from INIT to EARLY required that a condition
termed "confident initial direction decode" was obtained. This condition was met when the
Mahalanobis distance from the neural state in the initial-direction subspace to either the
forward or backward distributions dropped below 4. Second, transitions into the EXIT state
required (in addition to a drop in p_{move}) that the observed angular momentums, L, belong to a
set termed 'Stationary'. This set was defined as all L with a Mahalanobis distance of less than
4 to the 'stopped' distribution of angular momentums, which was learned from the training set.

Supplementary Figure 1. State machine diagram for speed-control experiments. BMI motion for the speed-tracking experiment was determined by a state machine with five states: STOP, INIT, EARLY, STEADY, and EXIT. Each of these states describes how to compute virtual velocity, v_{dec}, which gets integrated every millisecond into virtual position. Following the conventions from Figure 4, black arrows indicate the typical path of a successful BMI trial (gray arrows indicate all other transitions) and colors differentiate states in which there is progress through the virtual environment (blue) from states in which BMI motion is zero (orange). In the STOP, INIT, and EXIT states, virtual velocity is simply set to zero. During the EARLY and STEADY states, virtual velocity is computed as the product of decoded direction and decoded speed, which are computed based on activity in the rotational dimensions. Transitions between the states were determined by p_{move} (computed from the moving-sensitive dimension), angular momentum vector L (computed from the rotational planes), and the neural state in the initial-direction dimensions. Details on computing each of the neural features used in this state machine are provided in the section *'Neural features for speed-tracking'*. While in the STOP state, virtual velocity remains zero. If p_{move} goes high, the INIT state is entered (time of entry is denoted t_{init}), but virtual velocity remains zero. From the INIT state, one of three things can happen: 1) p_{move} goes low and the movement aborts with a transition back to the STOP state, 2) the neural state in the initial-direction dimensions becomes sufficiently close to the learned distributions of neural states for forward or backward conditions, triggering a transition to the EARLY state, or 3) no transition occurs within 500 ms of t_{init}, triggering a transition to the STEADY state. The INIT state serves to withhold BMI motion in situations where there is a transient spike in p_{move} and to delay movement when the early estimate of decoded direction is only weakly confident. The EARLY state dictates how virtual velocity is computed in the early portion of movement (when less than 500 ms have elapsed since t_{init}). The STEADY state determines virtual velocity for the remainder of decoded movement. While in the EARLY or STEADY states, if p_{move} goes low and the angular momentums in the rotational planes are consistent with a stationary pedal, a transition will occur to the EXIT state and virtual velocity will again go to zero. After 350 consecutive ms in the EXIT state, the state machine transitions back to the STOP state. However, if p_{move} goes high while in the EXIT state, a transition back to either EARLY or STEADY will occur. The transitions from EXIT back to EARLY and STEADY

exist to allow a rapid return to decoded movement if neural activity briefly, erroneously reflects that the monkey is ceasing movement, but then returns to exhibiting robust activity consistent with an ongoing movement.

Supplementary Movie 1. MI and manual control of primary task (monkey G, 10/4/2018). Both manual (left) and BMI control (right) sessions were performed on the same day, which was the fourth day of BMI control. Manual and BMI control success rates were very similar on this day (see Figure 3d). The task required that the monkey turn the hand pedal in the instructed direction to move through the virtual environment, stop on top of a lighted target, and remain still while collecting juice reward. The color of the landscape indicated whether cycling must be 'forward' (green landscape) or 'backward' (tan landscape). There were 6 total conditions, defined by cycling direction and target distance (2, 4, or 7 cycles).

Supplementary Movie 2. BMI and manual control of speed-tracking task (monkey G, 4/18/2019 and 3/27/2019, respectively). These examples were selected as representative of performance in this task. In this version of the task, the monkey was required to track various instructed speed profiles (constant, ramping up, and ramping down) as he progressed through the environment. A red target was rendered a short distance in front of the monkey, and remained at that distance ahead throughout the trial. A second, white target drifted ahead or behind the red target to indicate the error between the avatar's speed and the instructed speed. Thus, successful speed tracking required aligning these targets on top of one another. Whenever the error was within the rewarded tolerance window, the white target would light up and juice reward would be dispensed. This speed-tracking epoch lasted until the monkey was within two cycles of the final turquoise stopping target (total of 20 cycles from starting position).

Acknowledgements

We thank Y. Pavlova for expert animal care, A. Russo for sharing code and data for preliminary analysis, and E. Oby for surgical expertise and assistance. This work was supported by NINDS 1DP2NS083037, NIH CRCNS R01NS100066, NINDS 1U19NS104649, the Simons Foundation (SCGB#325233 and SCGB#542957), the Grossman Center for the Statistics of Mind, the McKnight Foundation, P30 EY019007, a Klingenstein-Simons Fellowship, and the Searle Scholars Program.

Author Contributions

M.M.C. conceived the study. K.E.S., S.M.P., and M.M.C. designed experiments. S.M.P., K.E.S., M.M.C., and Q.W. created the decoding algorithms. K.E.S. and S.M.P. collected and analyzed datasets. K.E.S., S.M.P., and M.M.C. wrote the paper. All authors contributed to editing.

References

Aghagolzadeh M, Truccolo W. 2016. Inference and Decoding of Motor Cortex Low-Dimensional Dynamics via Latent State-Space Models. *IEEE Trans Neural Syst Rehabil Eng* **24**:272–282. doi:10.1109/TNSRE.2015.2470527

Ajiboye AB, Willett FR, Young DR, Memberg WD, Murphy BA, Miller JP, Walter BL, Sweet JA, Hoyen HA, Keith MW, Peckham PH, Simeral JD, Donoghue JP, Hochberg LR, Kirsch RF. 2017. Restoration of reaching and grasping movements through brain-controlled muscle stimulation in a person with tetraplegia: a proof-of-concept demonstration. *The Lancet* **0**. doi:10.1016/S0140-6736(17)30601-3

Ames KC, Churchland MM. 2019. Motor cortex signals for each arm are mixed across hemispheres and neurons yet partitioned within the population response. *eLife* **8**. doi:10.7554/eLife.46159

Boumal N, Mishra B, Absil P-A, Sepulchre R. 2014. Manopt, a Matlab Toolbox for Optimization on Manifolds. *J Mach Learn Res* **15**:1455–1459.

Carmena JM, Lebedev MA, Crist RE, O'Doherty JE, Santucci DM, Dimitrov DF, Patil PG, Henriquez CS, Nicolelis MAL. 2003. Learning to Control a Brain–Machine Interface for Reaching and Grasping by Primates. *PLoS Biol* **1**:e42. doi:10.1371/journal.pbio.0000042

Chapin JK, Moxon KA, Markowitz RS, Nicolelis MAL. 1999. Real-time control of a robot arm using simultaneously recorded neurons in the motor cortex. *Nat Neurosci* **2**:664–670. doi:10.1038/10223

Christie BP, Tat DM, Irwin ZT, Gilja V, Nuyujukian P, Foster JD, Ryu SI, Shenoy KV, Thompson DE, Chestek CA. 2014. Comparison of spike sorting and thresholding of voltage waveforms for intracortical brain–machine interface performance. *J Neural Eng* **12**:016009. doi:10.1088/1741-2560/12/1/016009

Churchland MM, Cunningham JP, Kaufman MT, Foster JD, Nuyujukian P, Ryu SI, Shenoy KV. 2012. Neural population dynamics during reaching. *Nature* **487**:51–56. doi:10.1038/nature11129

Churchland MM, Shenoy KV. 2007. Temporal complexity and heterogeneity of single-neuron activity in premotor and motor cortex. *J Neurophysiol* **97**:4235–4257. doi:10.1152/jn.00095.2007

Churchland MM, Yu BM, Sahani M, Shenoy KV. 2007. Techniques for extracting single-trial
activity patterns from large-scale neural recordings. *Curr Opin Neurobiol*, Neuronal and
glial cell biology / New technologies **17**:609–618. doi:10.1016/j.conb.2007.11.001

Collinger JL, Wodlinger B, Downey JE, Wang W, Tyler-Kabara EC, Weber DJ, McMorland AJ,
Velliste M, Boninger ML, Schwartz AB. 2013. 7 degree-of-freedom neuroprosthetic
control by an individual with tetraplegia. *Lancet* **381**:557–564. doi:10.1016/S0140-
6736(12)61816-9

Cunningham JP, Ghahramani Z. 2015. Linear Dimensionality Reduction: Survey, Insights, and
Generalizations. *J Mach Learn Res* **16**:2859–2900.

Degenhart AD, Bishop WE, Oby ER, Tyler-Kabara EC, Chase SM, Batista AP, Yu BM. 2020.
Stabilization of a brain–computer interface via the alignment of low-dimensional spaces
of neural activity. *Nat Biomed Eng* **4**:672–685. doi:10.1038/s41551-020-0542-9

Elsayed GF, Lara AH, Kaufman MT, Churchland MM, Cunningham JP. 2016. Reorganization
between preparatory and movement population responses in motor cortex. *Nat Commun*
7. doi:10.1038/ncomms13239

Ethier C, Oby ER, Bauman MJ, Miller LE. 2012. Restoration of grasp following paralysis through
brain-controlled stimulation of muscles. *Nature* **485**:368–371. doi:10.1038/nature10987

Ethier C, Sachs NA, Miller LE. 2011. Continuous state-dependent decoders for brain machine
interfaces2011 5th International IEEE/EMBS Conference on Neural Engineering.
Presented at the 2011 5th International IEEE/EMBS Conference on Neural Engineering.
pp. 473–477. doi:10.1109/NER.2011.5910589

Fernández-Rodríguez Á, Velasco-Álvarez F, Ron-Angevin R. 2016. Review of real brain-
controlled wheelchairs. *J Neural Eng* **13**:061001. doi:10.1088/1741-2560/13/6/061001

Fetz EE, Finocchio DV, Baker MA, Soso MJ. 1980. Sensory and motor responses of precentral
cortex cells during comparable passive and active joint movements. *J Neurophysiol*
43:1070–1089.

Gallego JA, Perich MG, Chowdhury RH, Solla SA, Miller LE. 2020. Long-term stability of cortical
population dynamics underlying consistent behavior. *Nat Neurosci* **23**:260–270.
doi:10.1038/s41593-019-0555-4

Gallego JA, Perich MG, Miller LE, Solla SA. 2017. Neural Manifolds for the Control of
Movement. *Neuron* **94**:978–984. doi:10.1016/j.neuron.2017.05.025

Gallego JA, Perich MG, Naufel SN, Ethier C, Solla SA, Miller LE. 2018. Cortical population
activity within a preserved neural manifold underlies multiple motor behaviors. *Nat*
Commun **9**:4233. doi:10.1038/s41467-018-06560-z

Gilja V, Nuyujukian P, Chestek CA, Cunningham JP, Yu BM, Fan JM, Churchland MM,
Kaufman MT, Kao JC, Ryu SI, Shenoy KV. 2012. A high-performance neural prosthesis
enabled by control algorithm design. *Nat Neurosci* **15**:1752–1757. doi:10.1038/nn.3265

Gilja V, Pandarinath C, Blabe CH, Nuyujukian P, Simeral JD, Sarma AA, Sorice BL, Perge JA,
Jarosiewicz B, Hochberg LR, Shenoy KV, Henderson JM. 2015. Clinical translation of a
high-performance neural prosthesis. *Nat Med* **21**:1142–1145. doi:10.1038/nm.3953

Golub MD, Sadtler PT, Oby ER, Quick KM, Ryu SI, Tyler-Kabara EC, Batista AP, Chase SM, Yu
BM. 2018. Learning by neural reassociation. *Nat Neurosci* 1. doi:10.1038/s41593-018-
0095-3

Heming EA, Cross KP, Takei T, Cook DJ, Scott SH. 2019. Independent representations of
ipsilateral and contralateral limbs in primary motor cortex. *eLife* **8**:e48190.
doi:10.7554/eLife.48190

Kao JC, Nuyujukian P, Ryu SI, Churchland MM, Cunningham JP, Shenoy KV. 2015. Single-trial
dynamics of motor cortex and their applications to brain-machine interfaces. *Nat*
Commun **6**:1–12. doi:10.1038/ncomms8759

Kao JC, Nuyujukian P, Ryu SI, Shenoy KV. 2017a. A High-Performance Neural Prosthesis
Incorporating Discrete State Selection With Hidden Markov Models. *IEEE Trans Biomed*
Eng **64**:935–945. doi:10.1109/TBME.2016.2582691
Kao JC, Ryu SI, Shenoy KV. 2017b. Leveraging neural dynamics to extend functional lifetime of
brain-machine interfaces. *Sci Rep* **7**. doi:10.1038/s41598-017-06029-x
Kaufman MT, Churchland MM, Ryu SI, Shenoy KV. 2014. Cortical activity in the null space:
permitting preparation without movement. *Nat Neurosci* **17**:440–448.
doi:10.1038/nn.3643
Kaufman MT, Seely JS, Sussillo D, Ryu SI, Shenoy KV, Churchland MM. 2016. The Largest
Response Component in the Motor Cortex Reflects Movement Timing but Not
Movement Type. *eNeuro* **3**. doi:10.1523/ENEURO.0085-16.2016
Kemere C, Santhanam G, Yu BM, Afshar A, Ryu SI, Meng TH, Shenoy KV. 2008. Detecting
Neural-State Transitions Using Hidden Markov Models for Motor Cortical Prostheses. *J*
Neurophysiol **100**:2441–2452. doi:10.1152/jn.00924.2007
Lemon RN, Hanby JA, Porter R. 1976. Relationship between the activity of precentral neurones
during active and passive movements in conscious monkeys. *Proc R Soc Lond B Biol*
Sci **194**:341–373. doi:10.1098/rspb.1976.0083
Libedinsky C, So R, Xu Z, Kyar TK, Ho D, Lim C, Chan L, Chua Y, Yao L, Cheong JH, Lee JH,
Vishal KV, Guo Y, Chen ZN, Lim LK, Li P, Liu L, Zou X, Ang KK, Gao Y, Ng WH, Han
BS, Chng K, Guan C, Je M, Yen S-C. 2016. Independent Mobility Achieved through a
Wireless Brain-Machine Interface. *PLOS ONE* **11**:e0165773.
doi:10.1371/journal.pone.0165773
Makin JG, O'Doherty JE, Cardoso MMB, Sabes PN. 2018. Superior arm-movement decoding
from cortex with a new, unsupervised-learning algorithm. *J Neural Eng* **15**:026010.
doi:10.1088/1741-2552/aa9e95
Malik WQ, Truccolo W, Brown EN, Hochberg LR. 2011. Efficient Decoding With Steady-State
Kalman Filter in Neural Interface Systems. *IEEE Trans Neural Syst Rehabil Eng* **19**:25–
34. doi:10.1109/TNSRE.2010.2092443
Michaels JA, Dann B, Scherberger H. 2016. Neural Population Dynamics during Reaching Are
Better Explained by a Dynamical System than Representational Tuning. *PLOS Comput*
Biol **12**:e1005175. doi:10.1371/journal.pcbi.1005175
Miri A, Warriner CL, Seely JS, Elsayed GF, Cunningham JP, Churchland MM, Jessell TM. 2017.
Behaviorally Selective Engagement of Short-Latency Effector Pathways by Motor
Cortex. *Neuron* **95**. doi:10.1016/j.neuron.2017.06.042
Pruszynski JA, Kurtzer I, Nashed JY, Omrani M, Brouwer B, Scott SH. 2011. Primary motor
cortex underlies multi-joint integration for fast feedback control. *Nature* **478**:387–390.
doi:10.1038/nature10436
Rajangam S, Tseng P-H, Yin A, Lehew G, Schwarz D, Lebedev MA, Nicolelis MAL. 2016.
Wireless Cortical Brain-Machine Interface for Whole-Body Navigation in Primates. *Sci*
Rep **6**. doi:10.1038/srep22170
Russo AA, Bittner SR, Perkins SM, Seely JS, London BM, Lara AH, Miri A, Marshall NJ, Kohn
A, Jessell TM, Abbott LF, Cunningham JP, Churchland MM. 2018. Motor Cortex Embeds
Muscle-like Commands in an Untangled Population Response. *Neuron* **97**:953-966.e8.
doi:10.1016/j.neuron.2018.01.004
Sadtler PT, Quick KM, Golub MD, Chase SM, Ryu SI, Tyler-Kabara EC, Yu BM, Batista AP.
2014. Neural constraints on learning. *Nature* **512**:423–426. doi:10.1038/nature13665
Schroeder KE, Irwin ZT, Bullard AJ, Thompson DE, Bentley JN, Stacey WC, Patil PG, Chestek
CA. 2017. Robust tactile sensory responses in finger area of primate motor cortex
relevant to prosthetic control. *J Neural Eng* **14**:046016. doi:10.1088/1741-2552/aa7329

Scott SH, Gribble PL, Graham KM, Cabel DW. 2001. Dissociation between hand motion and population vectors from neural activity in motor cortex. *Nature* **413**:161–165. doi:10.1038/35093102

Sergio LE, Hamel-Pâquet C, Kalaska JF. 2005. Motor Cortex Neural Correlates of Output Kinematics and Kinetics During Isometric-Force and Arm-Reaching Tasks. *J Neurophysiol* **94**:2353–2378. doi:10.1152/jn.00989.2004

Serruya MD, Hatsopoulos NG, Paninski L, Fellows MR, Donoghue JP. 2002. Brain-machine interface: Instant neural control of a movement signal. *Nature* **416**:141–142. doi:10.1038/416141a

Shanechi MM, Orsborn AL, Moorman HG, Gowda S, Dangi S, Carmena JM. 2017. Rapid control and feedback rates enhance neuroprosthetic control. *Nat Commun* **8**:13825. doi:10.1038/ncomms13825

Shenoy KV, Carmena JM. 2014. Combining Decoder Design and Neural Adaptation in Brain-Machine Interfaces. *Neuron* **84**:665–680. doi:10.1016/j.neuron.2014.08.038

Shenoy KV, Sahani M, Churchland MM. 2013. Cortical control of arm movements: A dynamical systems perspective. *Annu Rev Neurosci* **36**:337–359. doi:10.1146/annurev-neuro-062111-150509

Suminski AJ, Tkach DC, Hatsopoulos NG. 2009. Exploiting multiple sensory modalities in brain-machine interfaces. *Neural Netw* **22**:1224–1234. doi:10.1016/j.neunet.2009.05.006

Sussillo D, Churchland MM, Kaufman MT, Shenoy KV. 2015. A neural network that finds a naturalistic solution for the production of muscle activity. *Nat Neurosci* **18**:1025–1033. doi:10.1038/nn.4042

Sussillo D, Nuyujukian P, Fan JM, Kao JC, Stavisky SD, Ryu S, Shenoy K. 2012. A recurrent neural network for closed-loop intracortical brain–machine interface decoders. *J Neural Eng* **9**:026027. doi:10.1088/1741-2560/9/2/026027

Sussillo D, Stavisky SD, Kao JC, Ryu SI, Shenoy KV. 2016. Making brain–machine interfaces robust to future neural variability. *Nat Commun* **7**:13749. doi:10.1038/ncomms13749

Taylor DM, Tillery SIH, Schwartz AB. 2002. Direct Cortical Control of 3D Neuroprosthetic Devices. *Science* **296**:1829–1832. doi:10.1126/science.1070291

Thacker NA, Bromiley PA. 2001. The Effects of a Square Root Transform on a Poisson Distributed Quantity. (Technical Report). Manchester, UK: Univ. of Manchester.

Trautmann EM, Stavisky SD, Lahiri S, Ames KC, Kaufman MT, O'Shea DJ, Vyas S, Sun X, Ryu SI, Ganguli S, Shenoy KV. 2019. Accurate Estimation of Neural Population Dynamics without Spike Sorting. *Neuron* **0**. doi:10.1016/j.neuron.2019.05.003

Velliste M, Perel S, Spalding MC, Whitford AS, Schwartz AB. 2008. Cortical control of a prosthetic arm for self-feeding. *Nature* **453**:1098–1101. doi:10.1038/nature06996

Wessberg J, Stambaugh CR, Kralik JD, Beck PD, Laubach M, Chapin JK, Kim J, Biggs SJ, Srinivasan MA, Nicolelis MAL. 2000. Real-time prediction of hand trajectory by ensembles of cortical neurons in primates. *Nature* **408**:361–365. doi:10.1038/35042582

Willett FR, Avansino DT, Hochberg LR, Henderson JM, Shenoy KV. 2020. High-performance brain-to-text communication via imagined handwriting. *bioRxiv* 2020.07.01.183384. doi:10.1101/2020.07.01.183384

Wodlinger B, Downey JE, Tyler-Kabara EC, Schwartz AB, Boninger ML, Collinger JL. 2015. Ten-dimensional anthropomorphic arm control in a human brain−machine interface: difficulties, solutions, and limitations. *J Neural Eng* **12**:016011. doi:10.1088/1741-2560/12/1/016011