Title: Fronto-temporal coupling dynamics during spontaneous activity and auditory

processing

Authors: Francisco García-Rosales[1**], Luciana Lopez-Jury[1], Eugenia Gonzalez-Palomares[1],

Yuranny Cabral-Calderín[2], Julio C. Hechavarría[1*].

Affiliations: [1] Institut für Zellbiologie und Neurowissenschaft, Goethe-Universität, 60438

Frankfurt/M., Germany. [2] Research Group Neural and Environmental Rhythms, MPI for

Empirical Aesthetics, Frankfurt, Germany.

[*] *Corresponding authors.*

[**] *Lead contact.*

Mailing address:

** Francisco García, Institut für Zellbiologie und Neurowissenschaft, Max-von-Laue-Str. 13,

60438 Frankfurt/Main, Germany, Tel.: (+49) 69 / 798 42066. Email: garciarosales@bio.uni-

frankfurt.de

* Julio C. Hechavarria, Institut für Zellbiologie und Neurowissenschaft, Max-von-Laue-Str.

13, 60438 Frankfurt/Main, Germany, Tel.: (+49) 69 / 798 42062. Email:

hechavarria@bio.uni-frankfurt.de

Abstract

Most mammals rely on the extraction of acoustic information from the environment in order to survive. However, the mechanisms that support sound representation in auditory neural networks involving sensory and association areas in the brain remain underexplored. In this study, we address the functional connectivity between an auditory region in the frontal cortex (the frontal auditory field, FAF) and the auditory cortex (AC) in the bat *Carollia perspicillata*. The AC is a classic sensory area central for the processing of acoustic information. The FAF, on the other hand, belongs to the frontal lobe, a brain region involved in the integration of sensory inputs, the modulation of cognitive states, and the coordination of behavioural outputs. The FAF-AC network was examined in terms of oscillatory coherence (local-field potentials, LFPs), and within an information theoretical framework linking FAF and AC spiking activities. We show that in the absence of acoustic stimulation, simultaneously recorded LFPs from FAF and AC are coherent in low frequencies (1-12 Hz). This "default" coupling was strongest in deep AC layers and was unaltered by acoustic stimulation. However, presenting auditory stimuli did trigger the emergence of coherent auditory-evoked gamma-band activity (25-45 Hz) between the FAF and AC. In terms of spiking, our results suggest that FAF and AC engage in distinct coding strategies for representing artificial and natural sounds. Taken together, our findings shed light onto the functional coupling dynamics that could underlie acoustic processing in fronto-temporal networks of the brain.

Introduction

Most mammals rely on the processing of acoustic information for survival. Nevertheless, the mechanisms by which sounds are represented in neural networks involving distant areas in the brain remain obscure. In the mammalian cortex, sensory and integration areas have been described as part of putative neural networks tasked with sound processing. The auditory cortex (AC), for example, plays an important role in sound analysis and even in coordinating acoustically guided behaviours (Song et al., 2010; Li et al., 2017). Neuronal activity within the AC represents a large range of acoustic properties including spectrotemporal structure (Gaese and Ostwald, 1995; Lu et al., 2001; Yin et al., 2011; Gaucher et al., 2013; Kanold et al., 2014; Gao et al., 2016; Lu et al., 2016; Martin et al., 2017; Sheikh et al., 2019), sound source location (Hechavarria et al., 2013; Hechavarria and Kossl, 2014; Salminen et al., 2015; Beetz et al., 2016; Moshitch and Nelken, 2016), and even abstract properties such as sound "emotional valence" (Concina et al., 2019) and future behavioural outcomes based on auditory stimuli (Francis et al., 2018).

Regions within the frontal lobe of the mammalian brain also participate in auditory processing and could in principle synchronize their activity with that of canonical auditory areas, such as the AC (see (Winkowski et al., 2018)). Frontal and AC regions are strongly connected through feedforward and feedback anatomical pathways (Kobler et al., 1987b; Winkowski et al., 2013; Medalla and Barbas, 2014; Plakke and Romanski, 2014; Winkowski et al., 2018). Neurons within the prefrontal cortex (PFC, a region in the frontal lobe) respond to sounds when the latter possess rich spectrotemporal dynamics (Eiermann and Esser, 2000; Kanwal et al., 2000; Romanski and Goldman-Rakic, 2002). Additionally, PFC is thought to engage in cognitive processes ranging from attention, learning, and memory formation/retrieval, to decision making (Miller, 2000; Floresco and Ghods-Sharifi, 2007; St Onge et al., 2011; Gourley et al., 2013; Gilmartin et al., 2014; Pezze et al., 2014; Helfrich and Knight, 2016; Kim et al., 2016; Werchan et al., 2016; Helfrich et al., 2017). This area could thus be a fundamental node for sound evaluation in auditory networks, and even for the implementation of acoustically guided behaviours.

Though there is increasing evidence supporting the idea of frontal-AC functional networks for auditory processing, specifics regarding activity coupling within this network remain unknown. For example, it remains unclear if different types of neural signals (i.e. spikes and local field potentials, LFPs) measured simultaneously in frontal and AC areas synchronize during spontaneous activity and during listening. Moreover, it is unknown whether frontal

activity displays preferential coupling patterns with certain layers of the AC. Assessing the latter can only be achieved by conducting simultaneous measurements from frontal and AC regions using layer-specific intracranial recordings to study spikes and LFPs.

In the current study, we address the functional connectivity in a fronto-auditory cortical circuit in bats (species *Carollia perspicillata*). The bat AC has been studied extensively, and it has been shown that oscillatory and spiking activities in the bat AC are in accordance with those observed during the processing of artificial and naturalistic sounds in other animal models, including speech in humans. This comprises phenomena such as multiscale temporal processing of acoustic streams (Giraud and Poeppel, 2012; Hyafil et al., 2015; Hechavarria et al., 2016b; Teng et al., 2017; García-Rosales et al., 2018a), and interactions between spikes and LFPs for audition (Lakatos et al., 2005; Kayser et al., 2009; Arnal and Giraud, 2012; Kayser et al., 2012; García-Rosales et al., 2018b; Garcia-Rosales et al., 2019b)).

In bats, there exists a region within the frontal lobe that is responsive to sounds: the frontal auditory field (FAF, (Kobler et al., 1987b; Eiermann and Esser, 2000; Kanwal et al., 2000)). This region is reciprocally connected with the AC (Kobler et al., 1987a), but it also receives auditory afferents via a non-lemniscal pathway through the suprageniculate nucleus of the thalamus, bypassing main auditory centres in the midbrain (Kobler et al., 1987a). Neurons in the FAF encode preferentially complex, naturalistic sounds with variable latencies and response properties (Eiermann and Esser, 2000; Kanwal et al., 2000), although they also respond to pure tones (Eiermann and Esser, 2000; Lopez-Jury et al., 2019). Our goal was to examine specifics of fronto-AC activity in awake bats during the processing of acoustic streams. We tackled this question by quantifying neural synchronization in the FAF-AC network in terms of oscillatory coherence (a mechanism underlying interareal communication; (Fries, 2015)), during both spontaneous activity and the processing of natural and artificial acoustic sequences. We found that the FAF-AC network is synchronized by default (i.e. without sensory stimulation) in low-frequencies (up to 12 Hz), and that coherence with the FAF is strongest in deep laminae of the AC. In addition, low-frequency coherence between the two structures remains unchanged during acoustic processing, and auditory-evoked gamma-band synchronization emerges at stimulus onset without clear layer specificity. Finally, based on an information theoretical framework, our data suggest that neuronal coding of acoustic streams in FAF and AC may occur with non-overlapping neural codes. Taken together, the data presented in this manuscript offer insights into the strategies for sound representation in fronto-AC neural networks.

Results

Stimulus-related LFPs in AC lag relative to those in FAF

We recorded electrophysiological data from the primary AC, paired with penetrations from the FAF, in 5 awake *Carollia perspicillata* bats (all males; n = 50 penetrations). Recordings in the AC were performed with laminar electrodes inserted perpendicularly into the brain, spanning depths of 0-750 μm as measured from the cortical surface. Each penetration in AC was paired with a simultaneous recording from the FAF using a single carbon electrode at an average depth of 313 ± 56 μm (mean ± std). Auditory stimuli consisted of artificially constructed syllabic trains with repetition rates of 5.28 and 97 Hz in order to test for slow and fast periodicities in acoustic streams, plus another syllabic train that had no clear rhythmicity as syllables were presented in a Poisson-like sequence with 70 Hz average rate (see Methods). The stimulus conforming the trains was a short duration, broadband distress syllable from *C. perspicillata*, recorded in previous work (Hechavarria et al., 2016a), whose spectrotemporal design is typical of distress syllables emitted by this species. In addition, we presented a natural distress vocalization (*"nat"* throughout the text) that has been used in previous research (Hechavarria et al., 2016b; García-Rosales et al., 2018a; Garcia-Rosales et al., 2019b), and which comprises temporal modulations in low (ca. 4 Hz) and high-frequency ranges (> 50 Hz), corresponding to the bout and syllabic periodicities, respectively, typical of this animal's distress vocalizations (Hechavarria et al., 2016a).

Grand average traces of simultaneously recorded LFPs from FAF and AC (the latter at a depth of 450 μm, corresponding to input layers in AC) during acoustic stimulation are shown in **Fig. 1A**. LFP responses from frontal and auditory cortical regions showed clear modulation by the acoustic streams that were well-correlated across structures for each stimulus tested, particularly at depths > 200 μm (**Fig. S1**). Remarkably, population averaged LFPs appeared "faster" in the FAF than in the AC (see **Fig 1A**, right column; blue: FAF; orange: AC at 450 μm) relative to stimulus onset. In fact, cross-correlation analysis of the traces depicted in **Fig. 1A** showed that LFPs recorded in frontal regions preceded those recorded from the AC by at least 4 ms (**Fig. 1B**), effectively indicating that primary auditory cortical stimulus-related LFPs in input layers "lag" relative to those in the FAF. We confirmed this trend by systematically determining the temporal lag between LFPs in the AC at various depths, and LFPs from the FAF. **Figure 1C** summarizes the results by illustrating, for each stimulus, the distribution of lags between FAF and AC across depths (note that negative lags indicate FAF

"leading"). Indeed, we observed a significant effect of LFPs in the FAF being "faster" than those in the AC, robust across depths in the latter structure, and also across stimuli (**Fig 1C**; FDR-corrected tailed Wilcoxon signed rank tests, testing that the medians of the lag distributions were significantly less than 0 across electrodes; $p_{corr} < 0.05$; precise p_{corr} values are indicated next to each heatmap). These results were corroborated by testing FAF-AC lags in LFPs but considering only LFP pairs that were well correlated across structures (correlation coefficients higher than 0.5, shown in **Fig. S1**).

That LFPs in the frontal auditory field "lead" relative to those in the auditory cortex suggests the presence of fast inputs into frontal auditory areas, agreeing with a non-lemniscal auditory pathway converging into the FAF and consisting of as few as four synapses in bats (Kobler et al., 1987a). We sought for evidence of fast neuronal responses in FAF that would support these observations by measuring response latencies of the neuronal spiking recorded simultaneously in both structures (see Methods). We observed that spiking responses from the FAF could in fact be as fast as spiking responses from the AC, although this effect was found only in a subpopulation of neurons (see **Fig. 2A, B**, which depicts example responses from one FAF and one AC unit at 450 μm recorded simultaneously). Measured neuronal response latencies from both structures yielded that AC spiking was on average faster than the FAF spiking (**Fig. 2C**; for illustrative purposes AC responses are those recorded at 450 μm). Still, some FAF units exhibited response latencies below 10 ms, indicative of fast acoustic inputs into this structure. By subtracting latencies from simultaneously recorded units in the FAF and the AC (across depths; latencies were pooled from all tested stimuli, but paring was only done within a particular stimulus), it became evident that auditory cortical spiking was typically faster than its FAF counterpart, although some latencies from frontal regions were shorter than those in the AC. **Figure 2D** shows the distribution of latency differences (across cortical depths in the AC), depicting the abovementioned observations. Latencies differences were significantly higher than 0 for all recording depths in the AC, except in the case of the most superficial channel (FDR-corrected Wilcoxon signed rank tests, significance when $p_{corr} < 0.05$; corrected p values across channels are given to the right of the latency distribution heatmap in **Fig. 2D**).

Altogether, these results provide evidence supporting that the FAF receives fast auditory inputs. Notwithstanding, such inputs do not necessarily elicit equally fast spiking, suggesting that the neuronal dynamics in frontal areas are "sluggish" in comparison to primary AC.

Sluggish dynamics can arise from multiple factors, and may be essential for sensory

integration in the frontal cortex (see Discussion).

FAF and AC synchronize in low frequency LFP bands during spontaneous activity

Local-field potentials recorded in the FAF and the AC typically showed visible phase

synchronization, even in the absence of acoustic stimulation (see **Fig. 3A,** where LFP traces

from both structures during a single 3 s epoch of spontaneous activity are depicted). We

quantified phase coherence between the two structures by means of the imaginary part of the

coherency ("iCoh" in this manuscript; see Methods and (Nolte et al., 2004)), for data recorded

both during spontaneous and sound-driven activities. The iCoh metric allows to minimize

spurious phase-synchrony attributable, for example, to common referencing and passive

spreading of field potentials, by effectively removing non-lagged phase correlations (Bastos

and Schoffelen, 2015).

Coherence analyses revealed that, as shown in **Fig. 3A**, FAF and AC were synchronized in

low frequencies. **Figure 3B** depicts population averaged z-normalized (to a surrogate

distribution where phase relationships were abolished; see Methods) iCoh values (z-iCoh)

across electrode depths in the AC. Elevated low-frequency coherence is evident in deep layers

of the AC, suggesting as well that FAF-AC synchrony was depth-dependent. A time-resolved

analysis of iCoh (**Fig. 3C**) over the same LFP traces used to calculate values in **Fig. 3B** also

showed that low-frequency phase synchrony was strongest in deeper channels, and

furthermore limited to the low-frequency region of the coherence spectrum. The data depicted

in **Fig. 3C** are shown here for illustrative purposes and serve as a comparison with the time-

resolved coherence estimations performed on LFPs recorded during acoustic processing (see

below).

To statistically corroborate our observations, we divided the coherence spectrum into

canonical frequency bands encompassing delta (1-4 Hz), theta (4-8 Hz), alpha (8-12 Hz), beta

(12-25 Hz) and low-gamma (25-45 Hz). We then tested if z-normalized iCoh values in each

band were significantly different than 0 across the population. Because of the nature of the

surrogate analyses (see Methods), non-consistent phase synchronization in the data would

yield a distribution of z-iCoh statistically undistinguishable from 0. In order words, z-iCoh

values significantly higher than 0 suggest consistent, population-wise phase-locking between

LFPs in FAF and AC during spontaneous activity. **Figure 3D** (top) depicts the z-iCoh

calculated between FAF and AC oscillations for each frequency band at various AC depths.

For frequency bands between 1-12 Hz (i.e. delta to alpha), we observed significantly higher

than 0 z-iCoh estimates (FDR-corrected Wilcoxon signed rank tests, $p_{corr} < 0.05$ for

significance; log-converted p values are shown in **Fig. 3D**, bottom), which became gradually

lower towards higher frequencies (note also the decay in **Fig. 3B**). Beta or gamma z-iCoh

distributions were not significantly different than 0 at any cortical depth.

It was also apparent that coherence values were depth dependent in the AC, particularly in the

delta band (where z-iCoh was strongest, see **Fig. 3B, D**). We tested the depth dependence of

coherence by comparing the distributions of z-iCoh for all pairs of channels, across all

penetrations and frequency bands. Results are summarized in significance matrices depicted

in **Fig. 3E**. Each cell (*i, j*) in a matrix represents the log-converted, corrected p value (FDR

Wilcoxon signed rank tests), obtained after statistically comparing FAF-AC coherence using

an AC channel at depth *i,* and another at depth *j*. In the matrices, cells within red contour lines

correspond to statistically significant p_{corr} values ($p_{corr} < 0.05$). As shown in **Fig. 3E**, deep

electrodes in the AC were significantly better synchronized with the FAF, an effect only

visible in the delta band.

FAF-AC synchronization during acoustic processing

To quantify synchronization during acoustic processing in the FAF-AC circuit, we calculated

time-resolved iCoh values in response to four acoustic stimuli (a natural call, syllabic trains of

5.28 and 97 Hz, and a syllabic train with Poisson temporal structure; see above). Population

average coherograms (i.e. time-frequency representations of iCoh values) are shown in **Fig.**

4A-D for all stimuli tested, and at representative depths in the AC (50, 450 and 700 μm). The

most conspicuous pattern across stimuli was the appearance of low-gamma coherence

(typically in the range of 25-45 Hz), which was associated with stimulus onset (at time 0) and

apparently independent of auditory cortical depth. Gamma synchrony was auditory-evoked, a

notion strengthened when considering responses to the 5.28 Hz syllabic train (**Fig. 4B**), where

the evoked coherence tracked individual syllable presentations. Remarkably, we observed

little evidence for an increase of low-frequency synchrony when compared to spontaneous

activity (compare heatmaps in **Fig. 4** with **Fig. 3C**). That is, even though low-frequency

coherence was present before sound presentation (in line with our results using spontaneous

LFPs), it did not change visibly after stimulus onset. To illustrate the occurrence of low and

high frequency coherence, **Figure 4E-H** depict trial-averaged LFPs from a representative pair

of simultaneous penetrations in the AC (450 μm depth) and FAF. LFPs are shown in their

broadband form (1-300 Hz), and filtered in frequency ranges of 4-12 Hz and 25-45 Hz (i.e.

low and high frequencies oscillations). The range 4-12 Hz was chosen for low-frequency

activity because spectral parameters at lower frequencies could not be reliably estimated with

the window size chosen for time-resolved coherence analyses (200 ms; see Methods). Note

the occurrence of synchronized waves in the AC and FAF is clear after stimulus onset (0-ms

mark).

The defined low- and high-frequency ranges were then used to quantify changes from

spontaneous to stimulus-driven coherence in the FAF-AC network. A systematic, time-

resolved analysis of low-frequency synchrony revealed that, across stimuli and auditory

cortical depths, there was little change (calculated as percentage increase from spontaneous to

sound-driven activity: $[iCoh_{stim} - iCoh_{spont}]/iCoh_{spont} * 100$) in coherence between both

structures (**Fig. 5A, D, G, J**, top heatmaps). The data showed that low frequency synchrony

preceded stimulus presentation in deep layers, seldom reached 50% increase from

spontaneous across stimuli (black contour lines in **Fig. 5A, D, G, J**), and when it did, it

typically happened at middle AC depths. We did not observe statistical evidence showing

significant increase of low frequency coherence at stimulus onset (i.e. first 100 ms after sound

presentation; **Fig. 5B, E, H, K**, black traces; FDR-corrected Wilcoxon signed rank tests,

significance when $p_{corr} < 0.05$).

Figure 5C, F, I, L (top heatmaps) illustrate effect size calculations (r; see Methods) for the

low-frequency coherence increase in a time resolved manner across channels. In the

heatmaps, only time points where the increase was significantly different from 0 (uncorrected

Wilcoxon singed-rank test, $p < 0.05$) are shown. From this analysis the following was evident:

(i) the pattern of significance was inconsistent across stimuli for low frequency coherence;

and (ii) effect sizes were typically small, with areas of medium effect size (those within grey

contour lines) appearing also with an inconsistent pattern across sounds. Large effect sizes

(within red contour lines) were overall only observed in small clusters, lacking any

consistency throughout the stimulus set. The boundaries between small, medium and large

effect sizes were defined as follows: $r < 0.3$, small; $0.3 \leq r < 0.5$, medium; $r \geq 0.5$, large (Fritz

et al., 2012). Altogether, these results corroborate a lack of reliable increase in low-frequency

coherence between FAF and AC during passive listening, compared to spontaneous activity.

High frequency FAF-AC coherence was considerably more sensitive to acoustic stimulation.

As expected from the data depicted in **Fig. 4**, we observed a strong increase of low-gramma

interareal synchronization associated to the stimulus onset (**Fig. 5A, D, G, J**, bottom

heatmaps). Stimulus-evoked gamma synchrony was typically higher than 50% (reaching

values as high as 80%) and tracked the syllable presentations of the 5.28 Hz syllabic train

(**Fig. 5D**, bottom). Indeed, the increase of low-gamma synchrony at stimulus onset was

significantly above 0 for all stimuli (**Fig. 5B, E, H, K**, grey traces; same statistical analysis as

for low-frequencies; $p_{corr} < 0.05$), and more reliably so for channels located in input layers of

the AC (depths of 250-350 μm). For the 5.28 Hz and the Poisson syllabic trains, the onset-

related increase in low-gamma coherence occurred essentially along all AC depths studied. In

terms of effect size (**Fig. 5C, F, I, L**; bottom heatmaps), we observed large effects of

increased low-gamma coherence at stimulation onset across stimuli (less clearly in the case of

the natural vocalization), with sustained, seemingly periodic increases along the time-course

of the 5.28 Hz syllabic sequence. Taken together, coherence analysis results indicate that

acoustic stimulation elicits auditory-evoked low-gamma synchronization between the frontal

auditory field and the auditory cortex.

Mutual information in FAF and AC spiking

We investigated spike-spike interactions in the FAF-AC network within an information

theoretical framework (Shannon, 2001). Mutual information (MI or "information" throughout

the text) between the stimuli and neuronal responses allows to quantify the theoretical ability

of a neuron (or a set of thereof) to represent the acoustic input on a single trial basis (see

Methods). MI captures all non-linear dependencies of any statistical order in the data, and its

quantification depends on the neural code being considered (Kayser et al., 2009). Here, we

aimed to determine the coding abilities in AC, FAF, and a joint response from both structures

based on a spike rate code (I_{rate} for single units, I_{joint} considering responses from AC and FAF

together; (Kayser et al., 2009; García-Rosales et al., 2018a)). A rate code was considered so

that our results could be comparable with previous data obtained from *C. perspicillata*'s AC

(García-Rosales et al., 2018a).

Overall, we relied on an information theoretic approach because we observed that

representations in AC and FAF were quite different and on occasions, at least in appearance,

complementary. For example, **Fig. 6A** depicts spiking from two simultaneously recorded FAF

and AC units in response to the natural stimulus. Note how the firing rate of the FAF unit

increases as the stimulus progresses, whereas the AC unit is time-locked to slow temporal

modulations in the stimulus and does not respond like its FAF counterpart. Information theory

would allow to measure possible interactions between these responses in a quantitative

manner.

Figure 6B shows a schematic of the rate code used to quantify MI for single units and joint responses. For subsequent analysis and in order to guarantee that all units considered were auditory-responsive (both in FAF and AC), we used only responses that provided at least 0.1 bit/s of information (with a window size of 4 ms this corresponds to 4×10^{-3} bits; see Methods). The number of units used to quantify I_{rate}, per channel (including the FAF electrode, and across the AC linear probe) is depicted in **Fig. 6C,** left. Note that the number of penetrations is equivalent to the number of units per channel in this case: $n \geq 13$ in FAF, and $n \geq 29$ in AC. For paired responses (FAF-AC) the number of units considered was less because the inclusion criterion ($I_{rate} \geq 0.1$ bit/s) had to be fulfilled by units in AC and FAF simultaneously ($n \geq 8$ pairs; **Fig. 6C, right**).

Population values of I_{rate} for the FAF and the AC at different depths are depicted in **Fig. 6D**, for each stimulus. Two main conclusions can be drafted from this figure. (i) In the AC, the highest information about the stimuli was found at depths between 200-650 μm. (ii) Neurons in the FAF were on average less informative than AC ones, but were well above the limit set in the inclusion criterion across stimuli (*nat*: 0.56 ± 0.09 bits/s, 5.28 Hz train: 0.45 ± 0.06 bits/s, 97 Hz train: 0.48 ± 0.04 bits/s, Poisson train: 0.42 ± 0.05 bits/s; given as mean ± s.e.m). We also quantified the information provided by paired neuronal responses from both regions (I_{joint}), which is illustrated as black traces in **Fig. 6E**. This figure also shows a direct comparison between I_{joint} and the I_{rate} of FAF and AC neurons that conform each pair ($I_{rate\_pair\_FAF}$ and $I_{rate\_pair\_AC}$, respectively). The contribution of I_{rate} from the FAF was significantly smaller than the contribution of I_{rate} from the AC (FDR-corrected Wilcoxon signed rank tests, $p_{corr} < 0.05$; corrected p values of all comparisons are given in **Fig. S2**). Although I_{rate} in the FAF was nevertheless always > 0.1 bit/s, we did not observe I_{joint} to be significantly higher than the I_{rate} from the AC (I_{rate_AC}; orange traces in the **Fig. 6E**), across electrodes and stimuli tested (**Fig. S7**). We did observe I_{joint} to be well correlated with the sum of I_{rate} calculated using the information of FAF and AC spiking ($I_{sum} = I_{rate\_pair\_FAF} + I_{rate\_pair\_AC}$; **Figs. S3-S7**).

When considering the interactions of spiking across structures in terms of the codes defined in this study, the linear relationsip between I_{sum} and I_{joint}, evident in **Figs. S3-S7**, would support "independence" in the information provided by the spiking in each structure. Independence arises theoretically when $I_{joint} = I_{sum}$, and implies that each structure represents different aspects of the sensory stimulus. However, the results illustrated in **Fig. 6E** suggest that independence cannot be inferred from the data with certainty. Mathematically, independence

would require I_{joint} to be higher than both I_{rate} in AC and FAF simultaneously, which was not fulfilled at a population level: I_{joint} was not significantly different than I_{rate} obtained from AC units (see **Fig. S2**). Calculating information estimates using time windows of up to 12 ms yielded comparable results, indicating that the temporal resolution of the codes had little effect in the described outcomes (data not shown). Overall, our quantification of stimulus-related spiking information, occurring simultaneously in the AC and FAF, suggests different sound coding strategies in these two structures. These observations are further addressed in the Discussion section.

Discussion

In this study we investigated the functional connectivity between frontal and auditory cortical regions of the bat *Carollia perspicillata*. Specifically, we examined the coupling dynamics of the FAF, a frontal area which receives auditory afferents from cortical and subcortical structures, and the primary AC. Functional connectivity was assessed during spontaneous activity and during the processing of natural and artificially generated acoustic sequences. Our main results are: i) LFPs recorded simultaneously in both regions suggest that the FAF receives faster auditory inputs relative to the AC, yet these inputs do not necessarily elicit faster spiking in the FAF; ii) during spontaneous activity, the FAF-AC network is coupled in low frequencies (up to 12 Hz), with stronger coherence values at deep layers of the AC; iii) while acoustic stimulation does not considerably alter the default low-frequency coupling, auditory-evoked gamma-band synchronization in the FAF-AC circuit emerges upon sound presentation; iv) considering a spiking rate code, the FAF is less informative than the AC about the acoustic stimuli, while a joint code using simultaneous spiking from both regions suggests that FAF and AC engage in distinct coding dynamics. Altogether, our results shed light into how distant brain areas in the mammalian brain engage in sound representation.

Auditory afferents into the FAF

Stimulus-related LFPs recorded simultaneously from FAF and primary AC, at various depths in the latter structure, indicate the presence of fast synaptic inputs into the frontal region that precede those arriving into the AC even at input layers. The work of Kobler, Casseday, and colleagues in the late 1980s (Kobler et al., 1987a; Casseday et al., 1989), showed that the FAF receives auditory afferents via a non-canonical pathway that bypasses major auditory centres in the midbrain, including the inferior colliculus (IC). In this pathway, acoustic information from neurons in the cochlear nucleus is sequentially relayed to the anterolateral olivary

complex, the suprageniculate nucleus of the thalamus (SGN), and from there into the FAF. Thus, although auditory inputs reach the frontal region also through the AC, acoustic information may reach the frontal field, directly from the cochlea, in as few as four synapses (Kobler et al., 1987a). Synaptic currents related to inputs from the SGN into the FAF could lead to changes in LFPs (Buzsaki et al., 2012) faster than their counterparts at input layers of the AC, which are predominantly driven by thalamocortical synapses originating in the ventral region of the medial geniculate body. Therefore, a rapid, non-canonical pathway into FAF accounts for our observations regarding the temporal relation between LFPs in both regions studied.

The results described in this manuscript indicate that, although sound-related LFPs from the FAF lead those from the AC, the neuronal spiking latencies are shorter in AC. In other words, our data indicate that faster inputs in FAF are not sufficient to elicit faster spiking in most cases. Electrophysiological studies in frontal auditory areas have shown that neuronal responses are usually of relatively large latencies (although short latencies are also to be found), sparse and of high variability (Newman and Lindsley, 1976; Eiermann and Esser, 2000; Kanwal et al., 2000; Plakke and Romanski, 2014). Recent data from *C. perspicillata*'s FAF highlighted the possibility that the sparseness in the response properties of frontal neurons could be explained by slow, low-threshold, and long-lasting synaptic dynamics, at least considering projections from the AC (Lopez-Jury et al., 2019). These slow, long-lasting synaptic dynamics could in principle support sensory integration, by conditioning FAF neurons to spike after accumulating synaptic inputs over time, and/or to integrate multiple synaptic inputs originating from different sensory modalities. Certainly, cross-modal sensory integration occurs in the frontal cortex (Fuster et al., 2000; Romanski, 2007; Hwang and Romanski, 2015), whereas integration over relatively long timescales appears to be a feature of higher-order cortical areas in general (Runyan et al., 2017).

Fast acoustic afferents, even without eliciting reliable stimulus-evoked spiking, imply nonetheless that auditory information is already present in the FAF before it receives inputs from the AC. Within the predictive coding framework (Arnal and Giraud, 2012; Friston, 2018), it is then possible to hypothesize that the frontal field may be a region where prediction errors could also be generated. That is, the rapid non-lemniscal pathway could relay faithful information into FAF about the auditory stimuli, which can in turn be compared with information received from primary AC and the thalamus. Alternatively, a further proposition would be that prediction errors, relayed "upwards" along the auditory hierarchy (Carbajal and

Malmierca, 2018), and generated in the SGN and the AC, are integrated in the FAF. The

result of such integration could in turn be used to update the "expectations" of the system. In

rodents, prediction error signals appear all along the auditory pathway, but occur more

strongly in higher-order structures (Parras et al., 2017), while prediction error signals related

to sounds have also been described in the frontal cortex of rats (Imada et al., 2012) and

humans (Durschmid et al., 2016; Durschmid et al., 2018). The involvement of the FAF in

predictive coding could be thoroughly tested in future experimental work.

A number of FAF neurons project directly to the superior colliculus (SC), a structure related

to motor control of head and pinna movement in bats (Kobler et al., 1987a). The presence of

early acoustic information in FAF, the fact that frontal neurons show preference for

naturalistic echolocation acoustic stimuli (high-frequency pulses used to navigate by bats;

(Eiermann and Esser, 2000)), and the presence of projections from FAF into motor-related

structures such as the SC, suggest that the FAF plays an important role in coordinating

auditory-guided behaviour. This would be in line with proposed roles of prefrontal cortex in

motor control (Risterucci et al., 2003), including volitional motor (vocal) production after

acoustic stimulation (Hage and Nieder, 2015). However, whether neuronal activity in the FAF

mediates motor outputs is still to be tested in depth.

FAF-AC synchronization during spontaneous activity

We examined the default (i.e. in the absence of external stimulation) functional connectivity

in the FAF-AC network in terms of oscillatory coherence (**Fig. 3**). The data presented in this

manuscript show that simultaneously recorded LFPs from both structures are phase-

synchronized in low-frequencies of the spectrum (1-12 Hz), although more strongly so in the

delta band (1-4 Hz). Empirical evidence points towards a role of oscillatory coherence in the

coupling of distant brain regions, a view that is summarized in proposed theoretical

mechanisms such as the communication-through-coherence framework (Fries, 2015). Several

studies have pinpointed an involvement of low-frequency synchronization in the functional

coupling between the frontal cortex and a variety of brain structures. Coherent oscillations

between distant cortical areas (including the frontal cortex) in the low-frequency range

correlate with working memory (Daume et al., 2017), fear memory consolidation (Popa et al.,

2010), and attentional selection (Womelsdorf and Everling, 2015). In the auditory domain,

top-down control exerted from frontal cortical areas, through low-frequency oscillatory

activity, increases coupling to speech signals in the human AC (Park et al., 2015). Our results

indicate that, in the bat brain, frontal areas that participate in audition are functionally

interconnected by means of low-frequency LFPs with primary auditory cortex. Critically,

such coupling does not require external input, which hints towards the presence of a default

synchrony in the fronto-auditory cortical circuitry. The latter could constitute a functional

basis for high-order, interareal auditory processing in the mammalian brain.

Because recordings in the AC were performed with a laminar probe, we were able to study the

laminar dependence of FAF-AC synchrony in AC. During spontaneous activity, low-

frequency coherence was strongest in deep layers (depth > 700 μm), but the strength of

coherence was only affected by depth in the delta band. Interestingly, a recent study revealed

that, also during spontaneous activity, spike-LFP synchronization was strongest in deep layers

of the AC (Garcia-Rosales et al., 2019a). Such spike-LFP coupling was associated to the

presence of discrete spontaneous states of increased spiking rate (UP-states) in laminae V and

VI. The origins of deep layer UP-states are unclear, but it has been hypothesized that they

could be driven by higher-order structures (Sakata and Harris, 2009). In the current study, we

observed a putative higher-order auditory structure (the FAF in the frontal lobe) synchronized

via a low-frequency oscillatory channel with deep layers of a primary sensory area (the AC).

From the phase correlation of delta-band LFPs in the FAF-AC network, it is possible to

speculate that delta oscillations in FAF could modulate UP-states in AC. However, we note

that causality cannot be inferred from our current dataset and needs to be addressed

thoroughly with further experimental approaches.

In all, the "default" coupling in the FAF-AC circuit is supported by the presence of

bidirectional anatomical connections between frontal and auditory cortices (Kobler et al.,

1987a)). Although it has to be properly addressed, we propose that homologous frontal

regions tasked with audition in other species may be functionally interconnected with AC in a

similar manner. This possibility is still unexplored, yet addressing this question might be

crucial for unravelling the mechanisms of high-order auditory processing, cognition, and

behaviour based on audition.

Functional coupling in the FAF-AC network during acoustic processing

Functional coupling between FAF and AC was also addressed in the context of acoustic

processing (**Figs. 4, 5**). Animals were exposed to four distinct acoustic streams, including a

conspecific distress vocalization, and three "trains" constructed by repeating a distress

syllable at distinct rates. Independently of the stimulus used, we observed little change in the

low-frequency phase synchrony of the FAF-AC network, as compared to spontaneous

activity. This is a puzzling result which, assuming that low-frequency oscillatory coupling in the network is useful for auditory perception, could in principle be explained largely by our experimental design. Although the animals were awake during the experiments, they listened to the sequences passively: i.e. they were not expected to behave in response to the stimulus, and other variables (e.g. attentional processes) were not modulated according to a controlled experimental approach. Thus, statistically negligible and unreliable changes in the low-frequency dynamics of FAF-AC connectivity could be explained by the fact that the passive listening of acoustic streams is not sufficient to alter the default functional coupling in the network. Whether attention (a top-down process) or behavioural planning could modify the neuronal connectivity in the circuit by either enhancing it or decreasing it, as compared to spontaneous activity, needs to be tested in further research.

On the other hand, we show that low-gamma (25-45 Hz) coherence in the FAF-AC circuit significantly increased with sound presentation, independently of the stimulus considered. Experimental evidence suggests that oscillatory activity in the gamma range is crucial for neuronal computations, including sensory processing and cognitive mechanisms (Fries, 2009). Data from awake rats have shown the presence of auditory-evoked gamma-band activity (aeGBA) in the primary auditory cortex during passive listening (Vianney-Rodrigues et al., 2011). In humans, sources of aeGBA can be found both in primary auditory and frontal (anterior cingulate cortex, ACC) cortices (Mulert et al., 2007; Polomac et al., 2015). Frontal aeGBA is modulated by attention and correlates with performance in auditory detection tasks (Debener et al., 2003; Gurtubay et al., 2004). Moreover, aeGBA in the frontal lobe and gamma-band synchronization between frontal and auditory cortical regions correlate too with task difficulty (Mulert et al., 2007; Polomac et al., 2015), suggesting a role of gamma-band coherence in a fronto-auditory cortical circuit for cognitive control in audition. In fact, disorders of the central nervous system such as schizophrenia are marked by a dysregulation of aeGBA in frontal regions (Cho et al., 2006; Leicht et al., 2010; Curic et al., 2019), further supporting the importance of gamma-band activity for cognition.

With our data, we are unable to probe how aeGBA correlates to cognitive dynamics like the ones described above. However, the presence of sound-related coherent gamma activity in the fronto-auditory cortical circuit addressed in this study, supports previous findings and highlights the importance of gamma activity for the functional connectivity of distant cortical regions. The observed FAF-AC low-gamma synchronization cannot be immediately explained by the temporal structure of the acoustic streams, because the frequency range in

which it manifested was independent of the sound the animal listened. That is, a natural

sequence with syllabic repetition rates of ~70 Hz (see (Hechavarria et al., 2016a; García-

Rosales et al., 2018a)), together with syllabic trains of 5.28 Hz, 97 Hz, and a "Poisson"-like

train with an average rate of 70 Hz, elicited evoked gamma-synchronization between FAF and

AC in the range of 25-45 Hz (**Fig. 4**). In sum, we speculate that the reported synchronous

aeGBA in the FAF-AC circuit could have an important role for auditory processing.

Mutual information in the FAF-AC circuit

Quantifying the amount of information provided by FAF and AC about the acoustic stimuli

revealed that the former structure was, in comparison, significantly less informative than the

latter. In addition, when considering responses from frontal or auditory cortices in a joint rate

code, it was not possible to determine a clear population trend towards independence,

redundancy or synergy between the spiking activities of both structures, from an information

theoretic perspective. We propose two candidate explanations for our results, which need not

be mutually exclusive. First, it is possible that the way in which FAF encodes incoming

auditory stimuli is not sufficiently well-captured by means of a code based on spiking rate,

and therefore the true encoding capabilities could be underestimated by assuming such

scheme (see (Masquelier, 2013; Insanally et al., 2019)). Second, we note that the fact that the

FAF conveys, in comparison, significantly less information than the AC, is an expected result

as the AC is a structure specialized for auditory computations. As part of the frontal cortex, it

is plausible that the FAF encodes for other variables that go beyond acoustic features (e.g.

ethological relevance of the sound, multimodal sensory information, etc.). In that case, FAF

units would yield low I_{rate} values when attempting to quantify their abilities to encode a sound

based on relatively simple methodological approaches, which rely solely on acoustic

processing. The former allows to hypothesize that FAF and AC might engage in distinct, non-

overlapping coding strategies.

Methods

Animal preparation and surgical procedures

All experimental procedures were performed in compliance with current German and

European regulations on animal experimentation. Experiments were approved by the

Regierungspräsidium Darmstadt (experimental permit #FU-1126). The study was performed

on 5 adult bats of the species *Carollia perspicillata* (all males). Animals were obtained from a

colony in the Institute for Cell Biology and Neuroscience, Goethe University, Frankfurt am

Main. Bats used for experiments were kept separately from the main colony.

Before undergoing surgical procedures, bats were anaesthetized with a mixture of ketamine

(10 mg*kg^{-1}, Ketavet, Pfizer) and xylazine (38 mg*kg^{-1}, Rompun, Bayer). For surgery and

any subsequent handling of the wounds, local anaesthesia (ropivacaine hydrochloride, 2

mg/ml, Fresenius Kabi, Germany) was applied subcutaneously in the scalp area. A rostro-

caudal midline incision was made in the scalp, after which skin and muscle tissues were

removed carefully in order to expose the skull. A sufficiently large area of the bone was also

exposed to make possible the attachment of a custom-made metal rode (1 cm length, 0.1 cm

diameter), used during recordings to fixate the animal's head. The rod was attached with

dental cement (Paladur, Heraeus Kulzer GmbH, Germany). Animals were given at least one

full day of recovery after surgery, and before experiments were performed upon them. The

AC and the FAF were located based on well-establish landmarks such as blood vessel

patterns, and the sulcus anterior (see (Esser and Eiermann, 1999; Eiermann and Esser, 2000)).

On the first day of recordings each cortical region was exposed by cutting a small hole (~ 1

mm^2) in the skull with a scalpel blade.

Recordings, which lasted no more than 4 hours a day, were performed chronically on awake

bats. Water was given to the animals at a period of approximately 1-1.5 hours. Between

recording sessions, a bat was allowed to recover for at least a full day. Experiments for the

day were halted if the bat showed any sign of discomfort.

Electrophysiological recordings

Recordings were made inside an electrically isolated and sound-proofed chamber. Inside the

chamber, bats were placed upon a custom-made holder which was kept at a constant

temperature of 30 °C with a heating blanket (Harvard, Homeothermic blanket control unit). A

speaker (NeoCD 1.0 Ribbon Tweeter; Fountek Electronics, China), located inside of the

chamber 12 cm away from the animal's right ear (contralateral to the hemisphere were

recordings were performed), was used for free-field stimulation. The speaker was calibrated

using a ¼-inch microphone (Brüel & Kjær, model 4135, Denmark), which was connected to a

custom-made amplifier.

Data were acquired from the bat's left AC as described in a previous study (Garcia-Rosales et

al., 2019a). Neurophysiological data were recorded from the AC using 16-channel laminar

electrodes (Model A1x16, NeuroNexus, MI; impedance: 0.5–3 MΩ), with a channel

separation of 50 μm. The probe was carefully inserted into the brain perpendicular to the

cortical surface using a piezo manipulator (PM-101, Science 455 products GmbH, Hofheim,

Germany) until the top-channel was barely visible on the surface of the tissue. Thus, we were

able to record from depths ranging 0-750 μm, reaching all layers in AC. Histological

confirmation of the extent of the electrodes inside the cortex are detailed elsewhere (Garcia-

Rosales et al., 2019a). Recordings were made in primary AC, although we cannot discard the

presence of columns from high frequency fields (Esser and Eiermann, 1999). The laminar

probes were connected to a micro-amplifier (MPA 16, Multichannel Systems MCS GmbH,

Reutlingen, Germany), and acquisition was done via a portable multichannel system with

integrated analogue-to-digital converter (Multi Channel Systems MCS GmbH, model ME32

System, Germany) with a sampling frequency 20 kHz and a precision of 16 bits. Data

acquisition was on-line monitored and stored in a computer using MC_Rack_Software (Multi

Channel Systems MCS GmbH, Reutlingen, Germany; version 4.6.2).

For recordings in the FAF, a single carbon electrode (Carbostar-1, Kation scientific;

Impedance at 1 kHz: 0.4–1.2 MΩ) was inserted into the frontal region of the left hemisphere

and lowered to depths of ~300-450 μm with the aid of a second piezo manipulator (same

characteristics as the previous one). The electrode was connected to a micro-amplifier which

was also connected to the integrated multichannel recording system as described above. It was

possible to use the same hardware because the integrated system accommodates up to 32

simultaneous channel recordings. Ground and reference electrodes (silver wires) were inserted

as to only touch the dura mater of non-auditory regions of the bat's brain, preferentially

located in occipital areas of the contralateral hemisphere.

Acoustic stimulation

Acoustic stimulation was controlled from the recording computer using a custom-written

Matlab (version 7.9.0.529 (R2009b), MathWorks, Natick, MA) software. Frequency-level

receptive fields were calculated from responses to pure tone stimuli with a duration of 10 ms

(0.5 ms rise/fall time), with frequencies in the range of 5-90 kHz, at a level of 75 dB SPL (in

steps of 15 dB SPL). Tones of different frequencies were each pseudorandomly presented a

total of 8 times, with an inter-stimulus interval of 250 ms.

As acoustic stimulus we used a natural distress call from *C. perspicillata* and three synthetic

trains constructed from a single distress syllable, repeated at different rates. Procedures for

recording the natural sequence are described in a previous study (Hechavarria et al., 2016a).

The call is representative of *C. perspicillata*'s vocal repertoire, and has been used by us in

previous studies addressing auditory processing at the level of the AC (Hechavarria et al.,

2016b; García-Rosales et al., 2018a; Garcia-Rosales et al., 2019a). Distress calls of *C.*

perspicillata exhibit two prominent, coexistent temporal modulations: the syllabic- and bout

rhythmicities. Syllabic rates in *C. perspicillata'*s distress utterances are in the range of > 30

Hz (on average 71.4 Hz), whereas bouts (groups of syllables emitted in close sequence) are

repeated with rates typically < 12 Hz (Hechavarria et al., 2016a). In the natural call used here,

syllables are repeated on average with a rate of 63.7 Hz, whereas bouts are uttered with a rate

of 4 Hz (i.e. 8 bouts in 1.96 s).

To emulate the temporal dynamics of the communication sequences, a stereotypical distress

syllable was used to construct artificial acoustic sequences. A first syllabic train had a

repetition rate of 5.28 Hz, matching the slow temporal dynamics of *C. perspicillata*'s distress

utterances. A second one, with a repetition rate of 97 Hz, was used to simulate fast temporal

dynamics in communication streams. Finally, we constructed a syllabic train where syllables

were repeated in a Poisson-like manner, with an average rate of 70 Hz. This simulated fast-

repetition rates without any periodicity and without a slow temporal structure. The 5.28 and

97 Hz trains had a duration of 2 s, while the Poisson train was 4 s long. The syllables had an

intensity of 70 dB SPL, close to the intensity of the natural call (see (García-Rosales et al.,

2018a)).

Sounds were digital-to-analogue converted by means of a sound card ((M2Tech Hi-face DAC,

384 kHz, 32 bit) and amplified (Rotel power amplifier, model RB-1050) in order to be

presented through the speaker inside of the chamber. Prior to presentation the call and syllabic

trains were down-sampled to 192 kHz, and low-pass filtered (80 kHz cut-off). All sounds

were pseudorandomly presented 50 times each, with and inter-stimulus interval of 1 s. A

period of 300 ms, and another of 500 ms, was appended at the beginning and the end of each

sequence, respectively.

Prior to any acoustic stimulation, per penetration, electrophysiological data were acquired for

a period of 180 s. These data were used for coherence analyses during spontaneous activity.

Separation of spiking activity and local-field potentials

All analyses were performed offline with custom-written Matlab (version 8.6.0.267246

(R2015b)) scripts. Initially, the raw electrophysiological signal from each channel (all

electrodes in AC and FAF) was bandpass filtered (fourth-order Butterworth filter) in order to

extract traces pertaining spiking activity (300-3000 Hz cut-off frequencies) and LFPs (0.1-300

Hz cut-off frequencies). For computational reasons, LFP data were down-sampled to 1 kHz

and stored for subsequent analyses.

Spike detection and sorting from FAF and AC electrodes were performed using the SpyKING

CIRCUS toolbox (Yger et al., 2018). Spike detection threshold was set at 5 median absolute

deviations from the noise baseline, and spike sorting was done automatically by the SpyKING

CIRCUS algorithm based on the probe's geometry to avoid detecting the same templates in

two adjacent electrodes. Each template was assigned to the electrode where its amplitude was

the strongest. Per electrode (either in AC or FAF), we chose as representative spiking the

template with the highest spike count. Spiking responses relative to a single electrode are

referred to as a "unit" in the manuscript.

Spike latency estimation

Spike latency was defined as the time point in which a unit's spiking rate was statistically

different from the expected rate during spontaneous activity, based on a previous study

(Chase and Young, 2007). In brief, the algorithm proposed by Chase and Young compares a

unit's response to a stimulus across several time windows, with the expected spiking rate

under the assumption that the unit fires spontaneously with Poisson statistics, given a certain

rate. A unit's firing rate in the 250 ms silence period before stimulus onset, across the 50

repetitions from all stimuli tested (a total 200 trials), was considered its spontaneous spiking

rate for the abovementioned assumption. The response of a unit to a certain stimulus (i.e.

spiking after stimulus onset) was pooled across trials. Taking this pooled response, the

probability of observing at least n spikes in a given window t_n (after stimulus onset), assuming

Poisson firing in the absence of acoustic inputs, can be defined as follows (Chase and Young,

2007):

$$P_{t_n}(\geq n) = 1 - \sum_{m=0}^{n-1} \frac{(N\lambda t_n)^m e^{-N\lambda t_n}}{m!}, \qquad [1]$$

where N is the number of repetitions of the given stimulus, and λ is the spontaneous firing

rate. Starting from stimulation onset, the probability that each elicited spike indicates a

stronger than chance deviation in rate from the firing rate estimated in the absence of

stimulation (the 250 ms window), is taken as the probability that the spontaneous firing rate

would have produced that particular spike as the last of n spikes in a window t_n. In this

context, t_n is the width of the window containing the n spikes observed so far. Hence, the time

of the first spike for which the aforementioned probability is sufficiently low (here, $P_{t_n}(\geq n)$

$< 10^{-5}$) is considered as the unit's latency. This method circumvents caveats regarding

classical peak latency estimations using peri-stimulus time histograms or spike-density

functions over time (Levakova et al., 2015).

Interareal coherence analyses

All coherence analyses were done using the Chronux toolbox (Bokil et al., 2010). As a metric

of interareal phase synchronization we used the imaginary part of the coherency ("iCoh" in

the manuscript; (Nolte et al., 2004)), both during spontaneous activity and acoustic

processing. Coherency is complex value that measures phase consistency between two time

series, across several trials. The coherency between two signals *x* and *y*, at a certain frequency

ω, can be defined as follows (Bastos and Schoffelen, 2015):

665
$$coh_{xy}(\omega) = \frac{\frac{1}{n}\sum_{k=1}^{n} A_x(\omega,k)A_y(\omega,k)e^{i(\phi_x(\omega,k)-\phi_y(\omega,k))}}{\sqrt{(\frac{1}{n}\sum_{k=1}^{n} A_x^2(\omega,k))(\frac{1}{n}\sum_{k=1}^{n} A_y^2(\omega,k))}}, \quad [2]$$

where $A_x(\omega, k)$ and $A_y(\omega, k)$ are the amplitudes of signals *x* and *y* at frequency ω and trial *k*,

while coh_{xy} represents the coherency between both signals, and *n* is the number of trials per

stimulus (n = 50). Coherency is a complex quantity, but its absolute value ranges from 0 to 1,

indicating the relative, normalized strength of phase synchronization between time series.

Taking the imaginary part of coh_{xy} is a straightforward manner to remove non phase-lagged

interactions that could be attributable to, for example, passive field spread or common

referencing (Bastos and Schoffelen, 2015). In order to minimize further common influences

related to the temporal structure of the stimuli, we subtracted from each trial the mean (across

all trials of a given stimulus) LFP of each channel (Kikuchi et al., 2017), and calculated

coherence using the de-meaned traces. Note that this could affect low frequencies more than

high frequencies, because the latter are more sensitive to temporal jitter. Additionally, while

the approach alleviates obtaining simply stimulus-evoked coherence, it could also mask

phase-locking that is time-locked to the stimulus but not entirely attributable to acoustic

temporal features.

From the 180 s trace of spontaneous activity recorded simultaneously from FAF and AC

penetrations, 50 chunks of 3 s length each were taken. The precise time at which chunks

started was chosen randomly in a way that the resulting sub-segments would still be non-

overlapping. Each of these paired chunks from FAF and AC were treated as a trial, and iCoh

was estimated from all 50 of them for the corresponding penetration (data shown in **Fig. 3B**).

A surrogate calculation was performed whereby the precise phase relationship between FAF

and AC "trials" in spontaneous activity was abolished. This was accomplished by pairing

FAF chunks with AC chunks randomly. The former affects the timing of the phase-

relationships but maintains the overall power across selected chunks. The pairing was

performed randomly a sufficiently large number of times (250), and iCoh was calculated at

each repetition of the surrogate analysis. Thus, it was possible to obtain a distribution of iCoh

values that represented coherence estimates in the absence of consistent phase relationships

between AC and FAF during spontaneous activity. The iCoh calculated from the original data

was then related to the surrogate iCoh values by means of z-normalization (z-iCoh). At a

population level, lack of consistent phase coherence between FAF and AC at a certain

frequency would yield z-iCoh values close to 0.

Time-frequency resolved iCoh values were obtained by means of coherogram calculations

(*cohgram* function in Chronux; data depicted in **Figs. 3C**, **4** and **5**). A time-resolved approach

allowed us to examine changes of coherence over time while animals listened to acoustic

streams. Each coherogram was constructed by calculating coherence in a sliding window of

200 ms length, which was advanced in steps of 2 ms. Because of the spectral resolution due to

window length, the coherence spectrum for frequencies below 4 Hz could not be estimated

with precision. As with any time-frequency resolved approach, there is a compromise

between temporal and spectral resolutions, which we empirically found to be best balanced

with a 200 ms window. All power spectra in the time-resolved analysis were obtained with

the multitaper method (Percival and Walden, 1993), available in the Chronux toolbox, using 3

tapers and a time-bandwidth (TW) product 2.

The frequency range of 4-12 Hz was used as a representative of low-frequencies in the

spectrum, and the 25-45 Hz band was considered as low-gamma. For comparing iCoh values

during sound presentation vs. iCoh values during spontaneous activity, we calculated time-

resolved iCoh during spontaneous activity using the same segments with which non-time

resolved coherency was calculated (shown in **Fig. 3C**). Because the length of the spontaneous

segments (3 s) was not precisely equal to the length of the stimuli (the Poisson process, for

example, was 4 s long), we collapsed the time-resolved spontaneous iCoh values in the

temporal dimension (median across timepoints per frequency). Thus, it was possible estimate

the percentage increase during sound processing in a time-resolved manner as follows:

$$iCoh_{increase}(\omega,t) = \frac{iCoh_{stim}(\omega,t) - iCoh_{spont}(\omega)}{iCoh_{spont}(\omega)} * 100, \qquad [3]$$

where $iCoh_{stim}(\omega, t)$ is the iCoh value during stimulus presentation at frequency ω ant time t,

while $iCoh_{spont}(\omega)$ is the collapsed time-resolved iCoh during spontaneous activity at the same

frequency. The percentage increases were narrowed to the frequency bands of interest (i.e. 4-

12 and 25-45 Hz) by calculating the median iCoh increase in the corresponding frequency

range over time (data depicted in **Fig. 5A, D, G, J**). For evaluating iCoh increase at stimulus

onset, the median was calculated not only for the frequency range, but also across time in the

first 100 ms after the sequence onset.

Information theoretic analyses

Information in the neuronal response regarding the acoustic stimuli was quantified by means

of Shannon's mutual information (MI; (Shannon, 2001)). The MI between a stimulus set S

and a response set R is mathematically expressed as follows:

$$I(R; S) = H(R) - H(R|S), \quad [4]$$

where $H(R)$ is the response entropy (i.e. the overall variability of the response set), which is

expressed as:

$$H(R) = -\sum_{r \in R} P(r) \log_2[P(r)], \quad [5]$$

while

$$H(R|S) = -\sum_{s \in S} P(s) \sum_{r \in R} P(r|s) \log_2[P(r|s)], \quad [6]$$

is referred to as the "noise entropy", representing the irreproducibility of the response given a

stimulus. The probabilities $P(r)$, $P(s)$ and $P(r|s)$ indicate the probability of observing response

r taken from the set R, the probability of observing stimulus s from the set S, and the

probability of observing response r given stimulus s, respectively. If the logarithm in **Eqs. 5**

and **6** is of base 2, the MI has units of bits. Each bit of information means that an external

observer is able to reduce, by observing the response, the uncertainty about the stimulus by a

factor of 2 on a single trial basis. These quantities were estimated by means of the Information

Breakdown Toolbox (ibTB; (Magri et al., 2009)).

Stimuli for MI computations

With aims of quantifying the amount of information provided by FAF and AC spiking

regarding a specific acoustic stream, we calculated each unit's ability to discriminate

consecutive chunks of the stimulus from each other (de Ruyter van Steveninck et al., 1997;

Kayser et al., 2009; Kayser et al., 2010; García-Rosales et al., 2018a). A particular sequence *S*

(be it, for example, the natural the distress call) was subdivided into non-overlapping,

consecutive segments s_k (k = 1, 2, 3, …, M), all of length T = 4 ms. We chose this segment

length so that results from this paper would be comparable with previous data from the AC of

C. perspicillata (García-Rosales et al., 2018a). Using lengths in the range of 2-12 ms did not

alter the results qualitatively. Each segment *s* was treated as an independent substimulus from

the set *S*. Note that, in this framework, all substimuli are equiprobable.

Rate and joint neuronal codes

The manner in which *P(r)* is quantified depends directly on the assumptions made to

characterize the neuronal response (i.e. the neural code considered). Here we used a rate code

(I_{rate}), which determines how well a unit discriminates between each substimulus *s*, based on

its spiking rate. The response set represented whether a spike occurred or not, and can be

characterized as follows: *R = {0, 1}*, where 1 and 0 represent the occurrence or absence of a

spike, respectively. *P(r)* was then the probability that a unit fired or not a spike across all

trials, whereas *P(r/s)* was the probability of firing to a certain substimulus. The time window

was sufficiently short to assume that, in general, a single spike would occur within each time

segment, and therefore binarized responses were used for MI calculations.

The information provided by joint responses from the FAF and the AC (I_{joint}) was calculated

by taking into account which unit elicited a spike in a merged response (see **Fig. 6B**; also

referred to as "line code" in the literature (Panzeri et al., 2007; Kayser et al., 2009)). That is,

the response set was defined as *R = { (0, 0); (0, 1); (1, 0); (1, 1) }*, where each member of the

set represents whether and which unit fired a spike (e.g. *(0, 1)* could indicate that the FAF unit

did not fire, whereas the AC one did; *(1, 0)* would represent the opposite).

Quantifying information from limited samples

The probabilities in **Eqs. 5** and **6** are estimated empirically from the data, based on the

representation of neuronal responses described above (i.e. the neural codes). These

empirically estimated probabilities (such as *P(r)*, or *P(r/s)*) are biased because it is impossible

in practice to sample all possible values of *R* a sufficiently large number of times (ideally,

infinite). A number of methods have been developed to deal with the sampling bias (Panzeri

et al., 2007). In this study, we used the Quadratic Extrapolation (QE) procedure (Strong et al.,

1998), implemented in the ibTB. In addition to the QE, we subtracted possible remaining

biases by means of a bootstrap procedure (Montemurro et al., 2008; García-Rosales et al., 2018a), using 250 repetitions. For paired responses, we also used the shuffling procedure (Panzeri et al., 2007) implemented in the iBTB together with the bootstrap method. To corroborate that the information estimates presented in the results were not affected by the limited sampling bias, we conducted numerical simulations in order to measure the dependence of the bias on the number of trials. The results of these simulations are shown in **Fig. S8**, and indicate that the number of trials used in this study (50) was sufficient to robustly estimate the information quantities presented.

Statistical analyses

All statistical analyses were conducted in Matlab (version 8.6.0.267246 (R2015b)), with custom-written scripts using the Statistics and Machine Learning Toolbox. Tests for comparisons between the distributions of the quantities described above were always indicated in the main text. When multiple comparisons were done, we performed False-Discovery Rate (FDR) corrections (e.g., comparing across multiple channel pairs in **Fig. 3E**) with the Benjamini and Hochberg procedure (Benjamini and Hochberg, 1995). The significance threshold was set at an alpha of 0.05. If the p values reported were uncorrected, it is stated so in the text. Effect sizes were calculated with the *r* metric, which is defined as follows (Fritz et al., 2012):

$$r = \frac{W}{\sqrt{N}}, \qquad [7]$$

where *r* is the effect size, *W* is the test statistic of the Wilcoxon signed rank test used in this context, and N is the sample size of the quantities being compared (N = 50). Values of $r \leq 0.3$ were considered small effects, while $0.3 \leq r \leq 0.5$ were considered as medium effects, and large effects were considered when r > 0.5 (Fritz et al., 2012).

Acknowledgements

Author Contributions

F.G.R and **J.C.H** designed the study. **F.G.R** collected the data. **F.G.R** analyzed the data and wrote the manuscript. **F.G.R**, **L.L.J**, **E.G.P**, **Y.C.C**, and **J.C.H** discussed the results and reviewed the manuscript.

Declaration of Interests

The authors declare no competing financial or non-financial interests.

Data availability

The data that support the findings of this study are available from the corresponding authors

upon reasonable request.

References

Arnal, L.H., and Giraud, A.L. (2012). Cortical oscillations and sensory predictions. Trends Cogn Sci *16*,
390-398.
Bastos, A.M., and Schoffelen, J.M. (2015). A Tutorial Review of Functional Connectivity Analysis
Methods and Their Interpretational Pitfalls. Front Syst Neurosci *9*, 175.
Benjamini, Y., and Hochberg, Y. (1995). Controlling the False Discovery Rate - a Practical and Powerful
Approach to Multiple Testing. J Roy Stat Soc B Met *57*, 289-300.
Bokil, H., Andrews, P., Kulkarni, J.E., Mehta, S., and Mitra, P.P. (2010). Chronux: a platform for
analyzing neural signals. Journal of neuroscience methods *192*, 146-151.
Buzsaki, G., Anastassiou, C.A., and Koch, C. (2012). The origin of extracellular fields and currents--
EEG, ECoG, LFP and spikes. Nat Rev Neurosci *13*, 407-420.
Carbajal, G.V., and Malmierca, M.S. (2018). The Neuronal Basis of Predictive Coding Along the
Auditory Pathway: From the Subcortical Roots to Cortical Deviance Detection. Trends Hear *22*,
2331216518784822.
Casseday, J.H., Kobler, J.B., Isbey, S.F., and Covey, E. (1989). Central Acoustic Tract in an Echolocating
Bat - an Extralemniscal Auditory Pathway to the Thalamus. Journal of Comparative Neurology *287*,
247-259.
Chase, S.M., and Young, E.D. (2007). First-spike latency information in single neurons increases when
referenced to population onset. Proc Natl Acad Sci U S A *104*, 5175-5180.
Cho, R.Y., Konecky, R.O., and Carter, C.S. (2006). Impairments in frontal cortical gamma synchrony
and cognitive control in schizophrenia. Proc Natl Acad Sci U S A *103*, 19878-19883.
Curic, S., Leicht, G., Thiebes, S., Andreou, C., Polomac, N., Eichler, I.C., Eichler, L., Zollner, C., Gallinat,
J., Steinmann, S.*, et al.* (2019). Reduced auditory evoked gamma-band response and schizophrenia-
like clinical symptoms under subanesthetic ketamine. Neuropsychopharmacology *44*, 1239-1246.
Daume, J., Gruber, T., Engel, A.K., and Friese, U. (2017). Phase-Amplitude Coupling and Long-Range
Phase Synchronization Reveal Frontotemporal Interactions during Visual Working Memory. J
Neurosci *37*, 313-322.
de Ruyter van Steveninck, R.R., Lewen, G.D., Strong, S.P., Koberle, R., and Bialek, W. (1997).
Reproducibility and variability in neural spike trains. Science *275*, 1805-1808.
Debener, S., Herrmann, C.S., Kranczioch, C., Gembris, D., and Engel, A.K. (2003). Top-down
attentional processing enhances auditory evoked gamma band activity. Neuroreport *14*, 683-686.
Durschmid, S., Edwards, E., Reichert, C., Dewar, C., Hinrichs, H., Heinze, H.J., Kirsch, H.E., Dalal, S.S.,
Deouell, L.Y., and Knight, R.T. (2016). Hierarchy of prediction errors for auditory events in human
temporal and frontal cortex. P Natl Acad Sci USA *113*, 6755-6760.

Durschmid, S., Reichert, C., Hinrichs, H., Heinze, H.J., Kirsch, H.E., Knight, R.T., and Deouell, L.Y.
(2018). Direct Evidence for Prediction Signals in Frontal Cortex Independent of Prediction Error.
Cereb Cortex.

Eiermann, A., and Esser, K.H. (2000). Auditory responses from the frontal cortex in the short-tailed
fruit bat Carollia perspicillata. Neuroreport *11*, 421-425.

Esser, K.H., and Eiermann, A. (1999). Tonotopic organization and parcellation of auditory cortex in
the FM-bat Carollia perspicillata. Eur J Neurosci *11*, 3669-3682.

Floresco, S.B., and Ghods-Sharifi, S. (2007). Amygdala-prefrontal cortical circuitry regulates effort-
based decision making. Cerebral Cortex *17*, 251-260.

Fries, P. (2009). Neuronal gamma-band synchronization as a fundamental process in cortical
computation. Annu Rev Neurosci *32*, 209-224.

Fries, P. (2015). Rhythms for Cognition: Communication through Coherence. Neuron *88*, 220-235.

Friston, K. (2018). Does predictive coding have a future? Nat Neurosci *21*, 1019-+.

Fritz, C.O., Morris, P.E., and Richler, J.J. (2012). Effect Size Estimates: Current Use, Calculations, and
Interpretation. J Exp Psychol Gen *141*, 2-18.

Fuster, J.M., Bodner, M., and Kroger, J.K. (2000). Cross-modal and cross-temporal association in
neurons of frontal cortex. Nature *405*, 347-351.

García-Rosales, F., Beetz, M.J., Cabral-Calderin, Y., Kössl, M., and Hechavarria, J.C. (2018a). Neuronal
coding of multiscale temporal features in communication sequences within the bat auditory cortex.
Communications Biology *1*, 200.

García-Rosales, F., Martin, L.M., Beetz, M.J., Cabral-Calderin, Y., Kossl, M., and Hechavarria, J.C.
(2018b). Low-Frequency Spike-Field Coherence Is a Fingerprint of Periodicity Coding in the Auditory
Cortex. iScience *9*, 47-62.

Garcia-Rosales, F., Rohrig, D., Weineck, K., Rohm, M., Lin, Y.H., Cabral-Calderin, Y., Kossl, M., and
Hechavarria, J.C. (2019a). Laminar specificity of oscillatory coherence in the auditory cortex. Brain
Struct Funct *224*, 2907-2924.

Garcia-Rosales, F., Rohrig, D., Weineck, K., Rohm, M., Lin, Y.H., Cabral-Calderin, Y., Kossl, M., and
Hechavarria, J.C. (2019b). Laminar specificity of oscillatory coherence in the auditory cortex. Brain
Struct Funct.

Gilmartin, M.R., Balderston, N.L., and Helmstetter, F.J. (2014). Prefrontal cortical regulation of fear
learning. Trends Neurosci *37*, 455-464.

Giraud, A.L., and Poeppel, D. (2012). Cortical oscillations and speech processing: emerging
computational principles and operations. Nat Neurosci *15*, 511-517.

Gourley, S.L., Olevska, A., Zimmermann, K.S., Ressler, K.J., Dileone, R.J., and Taylor, J.R. (2013). The
orbitofrontal cortex regulates outcome-based decision-making via the lateral striatum. Eur J Neurosci
38, 2382-2388.

Gurtubay, I.G., Alegre, M., Labarga, A., Malanda, A., and Artieda, J. (2004). Gamma band responses to
target and non-target auditory stimuli in humans. Neurosci Lett *367*, 6-9.

Hage, S.R., and Nieder, A. (2015). Audio-vocal interaction in single neurons of the monkey
ventrolateral prefrontal cortex. J Neurosci *35*, 7030-7040.

Hechavarria, J.C., Beetz, M.J., Macias, S., and Kossl, M. (2016a). Distress vocalization sequences
broadcasted by bats carry redundant information. J Comp Physiol A Neuroethol Sens Neural Behav
Physiol *202*, 503-515.

Hechavarria, J.C., Beetz, M.J., Macias, S., and Kossl, M. (2016b). Vocal sequences suppress spiking in
the bat auditory cortex while evoking concomitant steady-state local field potentials. Sci Rep *6*,
39226.

Helfrich, R.F., Huang, M., Wilson, G., and Knight, R.T. (2017). Prefrontal cortex modulates posterior
alpha oscillations during top-down guided visual perception. Proc Natl Acad Sci U S A *114*, 9457-9462.
Helfrich, R.F., and Knight, R.T. (2016). Oscillatory Dynamics of Prefrontal Cognitive Control. Trends
Cogn Sci *20*, 916-930.
Hwang, J., and Romanski, L.M. (2015). Prefrontal neuronal responses during audiovisual mnemonic
processing. J Neurosci *35*, 960-971.
Hyafil, A., Fontolan, L., Kabdebon, C., Gutkin, B., and Giraud, A.L. (2015). Speech encoding by coupled
cortical theta and gamma oscillations. Elife *4*, e06213.
Imada, A., Morris, A., and Wiest, M.C. (2012). Deviance detection by a P3-like response in rat
posterior parietal cortex. Front Integr Neurosci *6*, 127.
Insanally, M.N., Carcea, I., Field, R.E., Rodgers, C.C., DePasquale, B., Rajan, K., DeWeese, M.R.,
Albanna, B.F., and Froemke, R.C. (2019). Spike-timing-dependent ensemble encoding by non-
classically responsive cortical neurons. Elife *8*.
Kanwal, J.S., Gordon, M., Peng, J.P., and Heinz-Esser, K. (2000). Auditory responses from the frontal
cortex in the mustached bat, Pteronotus parnellii. Neuroreport *11*, 367-372.
Kayser, C., Ince, R.A., and Panzeri, S. (2012). Analysis of slow (theta) oscillations as a potential
temporal reference frame for information coding in sensory cortices. PLoS Comput Biol *8*, e1002717.
Kayser, C., Logothetis, N.K., and Panzeri, S. (2010). Millisecond encoding precision of auditory cortex
neurons. Proc Natl Acad Sci U S A *107*, 16976-16981.
Kayser, C., Montemurro, M.A., Logothetis, N.K., and Panzeri, S. (2009). Spike-phase coding boosts
and stabilizes information carried by spatial and temporal spike patterns. Neuron *61*, 597-608.
Kikuchi, Y., Attaheri, A., Wilson, B., Rhone, A.E., Nourski, K.V., Gander, P.E., Kovach, C.K., Kawasaki,
H., Griffiths, T.D., Howard, M.A.*, et al.* (2017). Sequence learning modulates neural responses and
oscillatory coupling in human and monkey auditory cortex. Plos Biology *15*.
Kim, H., Ahrlund-Richter, S., Wang, X., Deisseroth, K., and Carlen, M. (2016). Prefrontal Parvalbumin
Neurons in Control of Attention. Cell *164*, 208-218.
Kobler, J.B., Isbey, S.F., and Casseday, J.H. (1987a). Auditory Pathways to the Frontal-Cortex of the
Moustache Bat, Pteronotus-Parnellii. Science *236*, 824-826.
Kobler, J.B., Isbey, S.F., and Casseday, J.H. (1987b). Auditory pathways to the frontal cortex of the
mustache bat, Pteronotus parnellii. Science *236*, 824-826.
Lakatos, P., Shah, A.S., Knuth, K.H., Ulbert, I., Karmos, G., and Schroeder, C.E. (2005). An oscillatory
hierarchy controlling neuronal excitability and stimulus processing in the auditory cortex. J
Neurophysiol *94*, 1904-1911.
Leicht, G., Kirsch, V., Giegling, I., Karch, S., Hantschk, I., Moller, H.J., Pogarell, O., Hegerl, U., Rujescu,
D., and Mulert, C. (2010). Reduced early auditory evoked gamma-band response in patients with
schizophrenia. Biol Psychiatry *67*, 224-231.
Levakova, M., Tamborrino, M., Ditlevsen, S., and Lansky, P. (2015). A review of the methods for
neuronal response latency estimation. Biosystems *136*, 23-34.
Li, J.C., Liao, X., Zhang, J.X., Wang, M., Yang, N., Zhang, J., Lv, G.H., Li, H.H., Lu, J., Ding, R.*, et al.*
(2017). Primary Auditory Cortex is Required for Anticipatory Motor Response. Cerebral Cortex *27*,
3254-3271.
Lopez-Jury, L., Mannel, A., Garcia-Rosales, F., and Hechavarria, J.C. (2019). Modified synaptic
dynamics predict neural activity patterns in an auditory field within the frontal cortex. Eur J Neurosci.
Magri, C., Whittingstall, K., Singh, V., Logothetis, N.K., and Panzeri, S. (2009). A toolbox for the fast
information analysis of multiple-site LFP, EEG and spike train recordings. BMC Neurosci *10*, 81.
Masquelier, T. (2013). Neural variability, or lack thereof. Front Comput Neurosci *7*, 7.

Medalla, M., and Barbas, H. (2014). Specialized prefrontal "auditory fields": organization of primate
prefrontal-temporal pathways. Front Neurosci *8*, 77.

Miller, E.K. (2000). The prefrontal cortex and cognitive control. Nat Rev Neurosci *1*, 59-65.

Montemurro, M.A., Rasch, M.J., Murayama, Y., Logothetis, N.K., and Panzeri, S. (2008). Phase-of-
firing coding of natural visual stimuli in primary visual cortex. Curr Biol *18*, 375-380.

Mulert, C., Leicht, G., Pogarell, O., Mergl, R., Karch, S., Juckel, G., Moller, H.J., and Hegerl, U. (2007).
Auditory cortex and anterior cingulate cortex sources of the early evoked gamma-band response:
relationship to task difficulty and mental effort. Neuropsychologia *45*, 2294-2306.

Newman, J.D., and Lindsley, D.F. (1976). Single Unit Analysis of Auditory Processing in Squirrel-
Monkey Frontal Cortex. Experimental Brain Research *25*, 169-181.

Nolte, G., Bai, O., Wheaton, L., Mari, Z., Vorbach, S., and Hallett, M. (2004). Identifying true brain
interaction from EEG data using the imaginary part of coherency. Clin Neurophysiol *115*, 2292-2307.

Panzeri, S., Senatore, R., Montemurro, M.A., and Petersen, R.S. (2007). Correcting for the sampling
bias problem in spike train information measures. J Neurophysiol *98*, 1064-1072.

Park, H., Ince, R.A., Schyns, P.G., Thut, G., and Gross, J. (2015). Frontal top-down signals increase
coupling of auditory low-frequency oscillations to continuous speech in human listeners. Curr Biol *25*,
1649-1653.

Parras, G.G., Nieto-Diego, J., Carbajal, G.V., Valdes-Baizabal, C., Escera, C., and Malmierca, M.S.
(2017). Neurons along the auditory pathway exhibit a hierarchical organization of prediction error.
Nat Commun *8*, 2148.

Percival, D.B., and Walden, A.T. (1993). Spectral analysis for physical applications (cambridge
university press).

Pezze, M., McGarrity, S., Mason, R., Fone, K.C., and Bast, T. (2014). Too little and too much:
hypoactivation and disinhibition of medial prefrontal cortex cause attentional deficits. J Neurosci *34*,
7931-7946.

Plakke, B., and Romanski, L.M. (2014). Auditory connections and functions of prefrontal cortex. Front
Neurosci-Switz *8*.

Polomac, N., Leicht, G., Nolte, G., Andreou, C., Schneider, T.R., Steinmann, S., Engel, A.K., and Mulert,
C. (2015). Generators and Connectivity of the Early Auditory Evoked Gamma Band Response. Brain
Topogr *28*, 865-878.

Popa, D., Duvarci, S., Popescu, A.T., Lena, C., and Pare, D. (2010). Coherent amygdalocortical theta
promotes fear memory consolidation during paradoxical sleep. Proc Natl Acad Sci U S A *107*, 6516-
6519.

Risterucci, C., Terramorsi, D., Nieoullon, A., and Amalric, M. (2003). Excitotoxic lesions of the
prelimbic-infralimbic areas of the rodent prefrontal cortex disrupt motor preparatory processes. Eur J
Neurosci *17*, 1498-1508.

Romanski, L.M. (2007). Representation and integration of auditory and visual stimuli in the primate
ventral lateral prefrontal cortex. Cereb Cortex *17 Suppl 1*, i61-69.

Romanski, L.M., and Goldman-Rakic, P.S. (2002). An auditory domain in primate prefrontal cortex.
Nat Neurosci *5*, 15-16.

Runyan, C.A., Piasini, E., Panzeri, S., and Harvey, C.D. (2017). Distinct timescales of population coding
across cortex. Nature *548*, 92-96.

Sakata, S., and Harris, K.D. (2009). Laminar structure of spontaneous and sensory-evoked population
activity in auditory cortex. Neuron *64*, 404-418.

Shannon, C.E. (2001). A mathematical theory of communication. ACM SIGMOBILE Mobile Computing
and Communications Review *5*, 3-55.

Song, E.Y., Boatman, J.A., Jung, M.W., and Kim, J.J. (2010). Auditory cortex is important in the
extinction of two different tone-based conditioned fear memories in rats. Front Behav Neurosci *4*.
St Onge, J.R., Abhari, H., and Floresco, S.B. (2011). Dissociable Contributions by Prefrontal D-1 and D-
2 Receptors to Risk-Based Decision Making. J Neurosci *31*, 8625-8633.
Strong, S.P., de Ruyter van Steveninck, R.R., Bialek, W., and Koberle, R. (1998). On the application of
information theory to neural spike trains. Pac Symp Biocomput, 621-632.
Teng, X., Tian, X., Rowland, J., and Poeppel, D. (2017). Concurrent temporal channels for auditory
processing: Oscillatory neural entrainment reveals segregation of function at different scales. PLoS
Biol *15*, e2000812.
Vianney-Rodrigues, P., Iancu, O.D., and Welsh, J.P. (2011). Gamma oscillations in the auditory cortex
of awake rats. Eur J Neurosci *33*, 119-129.
Werchan, D.M., Collins, A.G., Frank, M.J., and Amso, D. (2016). Role of Prefrontal Cortex in Learning
and Generalizing Hierarchical Rules in 8-Month-Old Infants. J Neurosci *36*, 10314-10322.
Winkowski, D.E., Bandyopadhyay, S., Shamma, S.A., and Kanold, P.O. (2013). Frontal cortex activation
causes rapid plasticity of auditory cortical processing. J Neurosci *33*, 18134-18148.
Winkowski, D.E., Nagode, D.A., Donaldson, K.J., Yin, P., Shamma, S.A., Fritz, J.B., and Kanold, P.O.
(2018). Orbitofrontal Cortex Neurons Respond to Sound and Activate Primary Auditory Cortex
Neurons. Cereb Cortex *28*, 868-879.
Womelsdorf, T., and Everling, S. (2015). Long-Range Attention Networks: Circuit Motifs Underlying
Endogenously Controlled Stimulus Selection. Trends Neurosci *38*, 682-700.
Yger, P., Spampinato, G.L.B., Esposito, E., Lefebvre, B., Deny, S., Gardella, C., Stimberg, M., Jetter, F.,
Zeck, G., Picaud, S.*, et al.* (2018). A spike sorting toolbox for up to thousands of electrodes validated
with ground truth recordings in vitro and in vivo. Elife *7*.
1007

 Figures and captions

1009

Fig. 1. LFP stimulus-related activity in the frontal auditory field (FAF) precedes that of the auditory cortex (AC). (**A**) *Left column:* Grand average across all 50 penetrations of LFPs recorded from the FAF (blue) and the AC at a depth of 450 μm (orange) in response to the four stimuli tested (ordered from top to bottom: natural sequence (*nat*), 5.28 Hz train, 97 Hz train, and the Poisson syllabic sequence (*poisson*); grey traces). *Right column*: zoom into the first 100 ms after stimulus onset. Negative peaks in the evoked potential are marked with vertical dashed lines. Note that peaks in the FAF occur earlier than in the AC. (**B**) Cross-correlation between traces in A (*left column*). Peaks in negative lags indicate that FAF field-potentials lead those in the AC. (**C**) Peak lags between the cross-correlation of FAF LFPs and AC LFPs, for all penetrations and across recording depths. Next to each heatmap, log-scaled corrected p values testing that the peak distribution is significantly below 0 (FDR corrected tailed Wilcoxon signed rank tests; $p_{corr} < 0.05$ for significance).

1023

1024

Fig. 2. Spiking activity suggests the presence of fast inputs into the FAF. (**A**) Spiking responses from two simultaneously recorded units in the FAF (blue) and the AC (at 450 μm; blue), in response to all stimuli tested (top to bottom). (**B**) Zoom-in into the first 100 ms after stimulus onset of the examples shown in **A**. Note that, for this pair, the peak response for the FAF unit was at least as fast as the for auditory cortical one. (**C**) Latency distribution of FAF (blue) units and AC units at 450 μm, for all stimuli. The FAF was, overall, sluggish in comparison to the AC. (**D**) Response latency difference between simultaneously recorded spiking for FAF and AC at different depths (positive difference, FAF slower than AC; negative difference indicates the opposite). In some cases, FAF spiking responses occurred earlier than AC responses, although the AC was in general significantly faster than the FAF across channels, except in the case of the most superficial contact (FDR-corrected Wilcoxon signed rank tests, significance when $p_{corr} <$ 0.05). Log-converted p values and significance threshold are shown to the right of the latency distributions. The threshold is indicated as a red dashed line.

1042

Fig. 3. LFPs from FAF and AC are low-frequency coherent during spontaneous activity

1043

in a depth-dependent manner. (**A**) Simultaneously recorded LFP trace from the FAF

1044

(blue) and the AC at a depth of 700 μm (orange). Raw (top pair) and low-frequency

1045

filtered (bottom pair) traces are shown. (**B**) Frequency-dependent average imaginary

1046

coherence (iCoh), z-normalized to a surrogate distribution, across recording depths in the

1047

AC. Deep channels showed, on average, the strongest coherence values at low

1048

frequencies. (**C**) Time-resolved iCoh using the same segments as in **B**, with a sliding

1049

window of 200 ms (see Methods), the same used for analyzing stimulus-related

1050

synchronization. (**D**) *Top*: depth-dependent population z-normalized iCoh from **B,** for

1051

distinct frequency bands (delta, theta, alpha, beta and low gamma, see Methods;

1052

frequency ranges indicated in the plot), across all penetrations (shown as mean ± SEM).

1053

Bottom: log-scaled corrected p values after testing, per frequency band, whether z-

1054

normalized iCoh values were significantly higher than 0 across penetrations, per AC

1055

depth (FDR-corrected Wilcoxon signed rank tests, $p_{corr} < 0.05$ for significance; threshold

1056

indicated as a horizontal red dashed line). (**E**) Significance matrices comparing, per

1057

1058   frequency band, z-normalized iCoh values across different depths. Each cell (i, j) in a

1059   matrix depicts the log-scaled p_{corr} obtained from statistically comparing coherence at

1060   channels with depths i and j in the AC. Red contour lines delimit regions of statistical

1061   significance (FDR-corrected Wilcoxon signed rank tests, significance when $p_{corr} < 0.05$).

1062

Fig. 4. Interareal phase synchrony during acoustic sequence processing. (**A-D**) Mean time-resolved coherence between LFPs from the FAF and the AC at three representative depths (50, 450 and 700 μm), in response to the natural sequence (**A**), a syllabic train of 5.28 Hz (**B**), a syllabic train of 97 Hz (**C**), and the syllabic train with a Poisson structure (**D**). Note that low frequency synchrony is high even without acoustic stimulation, and the appearance of gamma-band evoked synchronization at the stimulus onset (time 0), albeit more weakly in response to the natural call in **A**. (**E-H**) LFP recordings from the AC (orange) and FAF (blue) around the time of stimulus onset (at 0 s; order in **E-H** corresponds to order in **A-D**), trial-averaged in a single penetration. Left column depicts the raw LFP, whereas middle and right columns depict field-potentials filtered in 4-12 and 25-45 Hz low-frequency and gamma-bands, respectively.

1077

Fig. 5. Acoustic stimulation alters FAF-AC coherence mostly in the gamma-band. (**A**)
Top: average time course of iCoh while animals listened to the natural sequence (left)
across recording depths for low frequencies (4-12 Hz), and percentage increase of
coherence in that range relative to the spontaneous activity (right). *Bottom*: same as *Top*,
but for iCoh values in the gamma range (25-45 Hz). Black contour lines delimit regions
with average increase of coherence > 50%. (**B**) Population onset-related iCoh increase
(median in the period of 0-150 ms after stimulus onset) across depths in the AC (black
traces, low-frequency band iCoh; grey traces, gamma-band iCoh; shown as mean +-
SEM). On the bottom subpanel, log-scaled corrected p values obtained after testing that

such increase was significantly different from 0% (black, low-frequency band; grey, gamma-band; FDR-corrected Wilcoxon signed rank tests, significance when $p_{corr} < 0.05$, indicated as a red dashed line). (**C**) Time-resolved effect size of population iCoh percentage increase (r; see Methods) for the low-frequency band (top) and the gamma-range (bottom). Grey contour lines delimit regions of $r > 0.3$, whereas red contours mark regions of $r > 0.5$ (medium and large effect sizes, respectively). r values are only shown for time points, across channels, where the coherence increase was significantly higher than 0% (Wilcoxon signed rank test, $p < 0.05$). (**D-F**) Same as **A-C** but considering a syllabic train at 5.28 Hz as stimulus. (**G-I**) Same as **A-C**, the stimulus being a syllabic train at 97 Hz. (**J-L**) Same as **A**-**C**, except the stimulus was the Poisson syllabic train.

Fig. 6. Information in rate codes of the FAF-AC circuit. (A) Spiking activity in an exemplary simultaneous recording from the FAF (blue) and the AC (at 450 μm, red). Note the difference in the response patterns between the two structures. (B) Schematic representation of the joint code used for information theoretic calculations. (C) Number of units used to calculate I_{rate} (left heatmap; 1 unit per penetration), for each stimulus (natural call, syllable train at 5.28 Hz, syllable train at 97 Hz, and Poisson syllable train) and depth in the AC (note that the first row in the heatmap corresponds to the FAF). Only units that had at least 0.1 bit/s of information were considered. The right heatmap depicts similar information, showing the number of pairs (FAF-AC spiking; 1 pair per penetration) used to calculate I_{rate} per stimulus and AC depth. In this case, FAF is missing because it is already part of each a pair. (D) Population I_{rate} in the FAF and across AC depths (note that the leftmost values correspond to the FAF), for each of the four stimuli presented (left to right). (E) I_{joint} (black) shown together with I_{rate} from AC (orange) and FAF (blue) units that conformed the pairs, across stimuli (i.e. $I_{rate\_pair\_AC}$ and $I_{rate\_pair\_FAF}$). There were no

1114 consistent significant differences between I_{joint} and I_{rate}, when the latter was calculated for

1115 AC units (Wilcoxon signed rank tests, $p > 0.05$).

1116

1117