Spectral-power associations reflect amplitude modulation and within-frequency interactions on the sub-second timescale and cross-frequency interactions on the seconds timescale

Melisa Menceloglu, Marcia Grabowecky, & Satoru Suzuki
Northwestern university, Evanston, IL, U.S.A.

Send correspondences to:
Satoru Suzuki
Northwestern University
Department of Psychology
Interdepartmental Neuroscience
2029 Sheridan Road, Evanston, IL 60208
Phone: (847)467-1271
Email: satoru@northwestern.edu

Abstract

We investigated the global structure of intrinsic cross-frequency dynamics by systematically examining power-based temporal associations among a broad range of oscillation frequencies both within and across EEG-based current sources (sites). We focused on power-based associations that could reveal unique timescale dependence (independently of interacting frequencies). Large spectral-power fluctuations across all sites occurred at two characteristic timescales, sub-second and seconds, yielding distinct patterns of cross-frequency associations. On the (fast) sub-second timescale, within-site (local) associations were consistently between pairs of β-γ frequencies differing by a constant Δf (particularly Δf~10Hz at posterior sites and Δf~16Hz at lateral sites) suggesting that higher-frequency oscillations are organized into Δf amplitude-modulated packets, whereas cross-site (long-distance) associations were all within-frequency (particularly in the 6-12Hz and >30Hz ranges, suggestive of feedback and feedforward interactions). On the (slower) seconds timescale, within-site (local) associations were characterized by a broad range of frequencies selectively associated with ~10Hz at posterior sites and associations among higher (>20Hz) frequencies at lateral sites, whereas cross-site (long-distance) associations were characterized by a broad range of frequencies at posterior sites selectively associated with ~10Hz at other sites, associations among higher (>20Hz) frequencies among lateral and anterior sites, and prevalent associations at ~10Hz. Regardless of timescale, within-site (local) cross-frequency associations were weak at anterior sites indicative of frequency-specific operations. Overall, these results suggest that the (fast) sub-second-timescale coordination of spectral power is limited to local amplitude modulation and insulated within-frequency long-distance interactions (likely feedforward and feedback interactions), while characteristic patterns of cross-frequency interactions emerge on the (slower) seconds timescale. The results also suggest that the occipital α oscillations play a role in organizing higher-frequency oscillations into ~10Hz amplitude-modulated packets to communicate with other regions. Functional implications of these timescale-dependent cross-frequency associations await future investigations.

Introduction

Because oscillatory dynamics are prevalent in the brain (e.g., Buzsaki, 2006), many EEG/MEG/Electrocorticography (ECoG) studies examined the roles of oscillatory neural activity in perception (e.g., Mathewson et al., 2010; 2011; Voytek et al., 2010; Dehaene & Changeux, 2011), attention (e.g., Busch & VanRullen, 2010; Klimesch, 2012; Bonnefond & Jensen, 2015; Jensen et al., 2014), memory (e.g., Duzel et al., 2010), cognition (e.g., Donner & Siegel, 2011; Engel & Fries, 2010; Palva & Palva, 2007; Palva et al., 2005), and the general control of neural communications (e.g., Fries, 2005). Some studies examined the dynamics of oscillatory activity while people rested with their eyes closed to identify intrinsic spatial networks of oscillatory activity (e.g., Müller et al., 2016; Osipova et al., 2008; Palva & Palva, 2012; Hipp et al., 2012) that may correlate with individual differences (e.g., Scally et al., 2018) or dysfunctions (e.g., Adebimpe et al., 2016; Antonakakis et al., 2016; Gonzalez et al., 2018). The strategies used by most prior studies were to examine phase-phase, power-power, and/or phase-power associations within specific frequency bands or specific combinations of frequency bands to identify spatial networks mediated by those bands.

The goal of the current study was complementary in that, instead of identifying spatial networks based on associations within specific frequency bands, we examined the global distribution of cross-frequency associations, focusing on both the local characteristics reflected in the cross-frequency associations within individual EEG-derived current sources (sites) and the long-distance characteristics reflected in the cross-frequency associations between sites. Importantly, we noted that spectral power universally (across oscillation frequencies and sites) fluctuated on two distinct timescales, sub-second and seconds. Because these fast and slow fluctuations are mathematically orthogonal (see below), distinct cross-frequency mechanisms may operate on these timescales, potentially yielding timescale-dependent patterns of cross-frequency associations at the local and long-distance levels. We thus examined power-power associations that can independently transpire on different timescales; that is, slow cross-frequency co-variations in spectral power may occur irrespective of the presence of fast co-variations, and vice versa. In contrast, the timescale of a phase-phase or phase-power coupling is constrained by the interacting oscillation frequencies. Analyses of spectral-power associations (though less temporally precise than analyses of phase coupling) provided additional advantages for characterizing the overarching structure of cross-frequency interactions.

First, spatial patterns of spectral-power associations may reveal the distribution of particularly consequential cross-frequency interactions because adjusting phase coupling would likely be more impactful for coordinating interactions between oscillatory activities that are concurrently elevated in power, thereby influencing larger neural populations (because larger spectral power implies larger synchronously oscillating populations). Power-based associations may also reveal interactions that are phase insensitive; for example, synchronized oscillatory output from one population may excite another population into generating oscillatory

activity at a different frequency. Second, analyses of spectral-power associations may reveal the global distribution of phase-power couplings. Specifically, consistent covariations of power between pairs of oscillation frequencies differing by a constant Δf at a given current source imply the presence of beating at Δf, that is, the presence of oscillation at the pair-average frequency, $\bar{f}$ Hz, being amplitude-modulated at Δf Hz. This in turn implies phase-power coupling because the periodic Δf Hz modulation of the amplitude (power) of a $\bar{f}$ Hz oscillation is likely mediated by its interaction with the phase of a Δf Hz oscillation.

To facilitate straightforward interpretations of our results, we applied only minimal necessary data transformations: (1) taking the temporal derivative of EEG to reduce the non-oscillatory background spectrum, (2) applying the surface-Laplacian transform to localize neural sources in a purely data-driven manner and to reduce volume conduction and electrode-referencing effects, and (3) applying Morlet-wavelet convolution to extract spectral power as a function of time.

Overall, the results have revealed surprisingly simple local and long-distance patterns of intrinsic spectral-power associations characterized by the oblique (parallel to diagonal), diagonal, and columnar patterns depending on timescale (sub-second or seconds), region (posterior, central, lateral, vs. anterior) and spatial scale (within vs. across EEG-derived current sources). These patterns of spectral-power associations provide a reference for understanding how intrinsic cross-frequency dynamics adjust to behavioral demands and sensory dynamics. Further, while recent studies have demonstrated the α rhythm of visual perception and its association with the occipital α oscillations, the current results suggest that the occipital α oscillations also play a role in organizing higher-frequency oscillations into ~10Hz amplitude-modulated packets to communicate with other areas.

Methods

1. Participants

Twenty-four Northwestern University students (15 women, 1 non-binary; ages 18 to 24 years, *M*=21.25, *SD*=1.57) gave informed consent to participate for monetary compensation ($10/hr). All were right-handed, had normal hearing and normal or corrected-to-normal vision, and had no history of concussion. They were tested individually in a dimly lit room. The study protocol was approved by the Northwestern University Institutional Review Board.

2. EEG recording and pre-processing

While participants engaged in spontaneous thoughts with their eyes closed for approximately 5 minutes, EEG signals were recorded from 60 scalp electrodes (although we used a 64-electrode montage, we excluded

EEG signals from noise-prone electrodes, *Fpz*, *Iz*, *T9*, and *T10* from analyses) at a sampling rate of 512Hz using a BioSemi ActiveTwo system (see www.biosemi.com for details). Two additional electrodes were placed on the left and right mastoid area. The EEG data were preprocessed using EEGLAB and ERPLAB toolboxes for MATLAB (Delorme & Makeig, 2004; Lopez-Calderon & Luck, 2014). The data were re-referenced offline to the average of the two mastoid electrodes, bandpass-filtered at 0.01Hz-80Hz, and notch-filtered at 60Hz (to remove power-line noise that affected the EEG data from some participants). To reduce any effects of volume conduction and reference electrode choices, as well as to facilitate data-driven EEG current source discrimination, we applied the surface-Laplacian transform to all EEG data (Hjorth, 1980; Kayser and Tenke, 2006; Tenke and Kayser, 2012) using the Perrin and colleagues' method (e.g., Perrin et al., 1987; Perrin et al., 1989a; 1989b) with a typical set of parameter values (Cohen, 2014).

3. EEG analysis

3.1. The use of EEG temporal derivative. We refer to the surface-Laplacian transformed EEG signals simply as EEG signals. In all figures, whenever units are not shown, they are arbitrary (a.u.), and the shaded regions indicate ±1 standard error of the mean. An example 1s EEG waveform at a central site *FCz* from one participant is shown in Figure 1A (black curve). The waveform reflects the synchronized electrical activity from a large neural population that generates a distinct current source at *FCz*. The mean spectral-amplitude profile (i.e., fast Fourier transform, FFT) computed on 59 consecutive 5s waveforms for the same participant is shown in Figure 1B (black curve; the shaded region represents ±1 standard error of the mean). The general linear decrease in the spectral amplitude for higher frequencies with a slope of approximately 1 (in log-log scale) reflects the $1/f$ background profile largely explained by the neuronal Ornstein-Uhlenbeck process that exhibits a random-walk type behavior (e.g., Koch, 1999; Mazzoni et al., 2008; see He, 2014 for a review of the various factors that contribute to the $1/f^{\beta}$ background). The spectral "bumps" seen around 10Hz, 20Hz, and 30Hz indicate the characteristic bands of oscillation frequencies that the neural population reflected at this site for this person may utilize for communication and/or information processing. Taking the temporal derivative of EEG ($\frac{\Delta EEG}{\Delta t}$, where Δt is the temporal resolution, i.e., 1/512s; see black curve in Figure 1C) largely removes the $1/f$ background (due to trigonometric properties) to highlight the oscillation bumps (see black curve in Figure 1D). While Figure 1D shows an example at one site from one participant, we confirmed that the background spectral-amplitude profiles were generally flattened after taking the temporal derivative. Because we wished to investigate the dynamics of oscillatory activity (over and above the general $1/f^{\beta}$ background), we used the EEG temporal derivative, which we call EEGd.

3.2. Computing spectral power as a function of time. The spectral-amplitude profiles shown in Figure 1B and 1D are time-averaged (standard fast Fourier transforms). As we wished to understand how the brain

dynamically coordinates oscillatory activity, we used a Morlet wavelet-convolution method (e.g., Cohen, 2014) to extract spectral amplitudes as a function of time to investigate how spectral power (amplitude squared) fluctuated over time. Specifically, each EEGd waveform was decomposed into a time series of spectral power using 200 Morlet wavelets with their center frequencies, f_c's, and factor n's (roughly the number of cycles per wavelet, which is related to the temporal standard deviation of the wavelet by, $n = 2\pi f \cdot SD$), both logarithmically spaced (because neural temporal-frequency tunings tend to be approximately logarithmically scaled; e.g., Hess & Snowden, 1992; Lui et al., 2007). The f_c's spanned the range of 3Hz to 60Hz and the n's spanned the rage of 3 to 16, resulting in the temporal resolutions of *SD*=159ms (at 3Hz) to *SD*=42ms (at 60Hz) and spectral resolutions of *FWHM* (full width at half maximum) =2.36Hz (at 3Hz) to *FWHM*=8.83Hz (at 60Hz). These values struck a good balance for the temporal/spectral-resolution trade-off, and are typically used in the literature (e.g., Cohen, 2014).

  3.3. Generating phase-scrambled controls. To remove spurious cross-frequency associations between proximate f_c's due to partial spectral overlaps of Morlet wavelets, we generated phase-scrambled controls whose spectral power fluctuated stochastically (i.e., unpredictably in a memory free manner) while time-averaged spectral-amplitude profiles matched those of the real data. While phase-scrambling can be performed using several different methods, we chose discrete cosign transform, DCT (e.g., Kiya et al., 2010). In short, we transformed each 5min EEG waveform with type-2 DCT, randomly shuffled the signs of the coefficients, and then inverse-transformed it with type-3 DCT, which yielded a phase-scrambled version. DCT phase-scrambling is similar to DFT (discrete Fourier transform) phase scrambling except that it is less susceptible to edge effects. We verified that DCT phase-scrambling yielded a desired outcome, generating waveforms whose spectral-power fluctuations conformed to exponential distributions (Figure 1E) indicative of a Poisson point process (i.e., a stochastic process), with virtually no distortions to the time-averaged spectral-amplitude profiles of EEG or EEGd (e.g., the blue and black curves overlap in Figure 1B and 1D). In passing, it is noteworthy that the distributions of spectral-power fluctuations of the real data deviated from exponential in a U-shaped manner with disproportionately frequent occurrences of near-zero and high values (Figure 1E), indicative of intermittent bursts (relative to stochastic variations).

  We used EEGd from 60 sites in conjunction with their DCT-phase-scrambled controls to extract intrinsic spectral-power associations over and above any artifact due to partial wavelet overlaps. Because of the 5min length of the data (containing 153,600 time-points at the 512Hz sampling rate), 200 wavelet center frequencies, and 60 sites per participant, even one set of phase-scrambled data would be unlikely to generate accidental patterns of spectral-power associations. Nevertheless, to be cautious, we used four sets of phase-scrambled data (per frequency per site per participant), and verified for a few examples that the control patterns of spectral-power associations were virtually indistinguishable across repetitions. We are thus

reasonably certain that the control patterns accurately captured the spurious associations due to partial wavelet overlap.

Figure 1. The use of the temporal derivative of EEG, EEGd, and DCT-phase-scrambled controls for examining intrinsic cross-frequency spectral-power associations. A. An example of 1s EEG waveform (black) and its DCT-phase-scrambled control (blue) at *FCz* from one participant. **B.** Mean fast Fourier transforms (FFTs) computed on the 59 5s waveforms (same site and participant) for the real EEG (black) and its DCT-phase-scrambled control (blue) plotted in a log-log format. **C.** The temporal derivatives, which we call EEGd, of the example EEG waveform (black) and its DCT-phase-scrambled control (blue) shown in A. **D.** Mean FFTs computed on the 59 5s waveforms (same site and participant) for the real EEGd (black) and its DCT-phase-scrambled control (blue) plotted in a semi-log format. For B and D, the shaded regions represent ±1 standard error of the mean based on the FFTs computed on multiple 5s waveforms. **E.** Temporal distributions of EEGd spectral power for representative wavelet-center frequencies for the real data and their DCT-phase-scrambled controls, plotted as deviations from exponential fits to the DCT-phase-scrambled controls (averaged across all sites). The deviations are shown as ratios in log scale, and spectral power (*x*-axis) has been normalized to the median (per frequency per site per participant). The shaded regions represent ±1 standard error of the mean with participants as the random effect. Note that the DCT-phase-scrambled data provide suitable stochastic controls because their exponential spectral-power distributions imply a Poisson point process.

3.4. Computing spectral-power associations. For assessing power-based cross-frequency coupling, we chose not to use a conventional correlation measure. One reason is that the stochastic distribution of EEGd spectral power is not normal but exponential (Figure 1E). The other reason is that it is difficult to remove artifacts due to wavelet overlap in the frequency domain using a conventional correlation measure (see below). Instead, we computed the *top-bottom-percentile based* temporal associations. This method has advantages including (1) not being susceptible to outliers and (2) the straightforwardness of the computed association values that directly indicate the log power modulation in frequency *Y* that is temporally associated with statistically large power variation in frequency *X*. We computed spectral-power associations at individual scalp-based current sources—*within-site* associations—as well as between pairs of current sources—*cross-site* associations.

3.4.1. Within-site (local) spectral-power associations. To evaluate a within-site spectral-power association from a probe frequency, f_{probe}, to a test frequency, f_{test}, we first identified the time-points corresponding to the top and bottom 15% in the f_{probe} power series. This criterion was reasonable for an approximate exponential distribution (Figure 1E), capturing a good proportion (accounting for approximately 70% of the total variability in the sum of squares) of statistically large variations. The f_{test} power was averaged separately over the time-points corresponding to the top-15% and bottom-15% for the f_{probe} power, and the strength of f_{probet}-to-f_{test} spectral-power association was computed as the natural-log (Ln) ratio of these averages (thus normalizing for absolute power). Thus, a larger association value indicates that the top/bottom-15% variation in the probe frequency power was associated with greater modulation in the test-frequency power in Ln-ratio. In this way, we computed the strengths of probe-frequency-to-test-frequency spectral-power associations for all combinations of wavelet-center frequencies to generate a 2-dimensional, 200-probe-frequency-(*y*-axis)-by-200-test-frequency-(*x*-axis), association matrix per site per participant and averaged across participants. A cross-frequency association matrix computed in this way need not be symmetric about the diagonal. That is, *X*-Hz power modulation coincident with the top/bottom-15% *Y*-Hz power variation may be stronger/weaker than the *Y*-Hz power modulation coincident with the top/bottom-15% *X*-Hz power variation.

As mentioned above, because the wavelets used to extract spectral-power values had non-negligible spectral widths, proximate frequencies would appear to be associated due to partial wavelet overlap. This artifact would generate spurious positive associations near the diagonal (with the diagonal representing the Ln-ratio of the top-15% to bottom-15% power for each frequency). To remove this artifact, spectral-power associations were computed in the same way for the corresponding DCT-phase-scrambled data. Taking the difference (in Ln-ratio) between the real and phase-scrambled associations removes any spurious associations due to partial wavelet overlap (note that removing this artifact would not be as straightforward using a conventional correlation measure). This procedure also made the diagonal meaningful because values along

the diagonal indicate the magnitudes of the top/bottom-15% variations in the real data relative to those expected by stochastic variation.

   3.4.2. Cross-site (long-distance) spectral-power associations. Cross-site spectral-power associations were similarly computed. For example, to evaluate the spectral-power association from a probe frequency at site *S1*, **S1-f$_{probe}$**, to a test frequency at site *S2*, **S2-f$_{test}$**, we identified the time-points corresponding to the top and bottom 15% in the **S1-f$_{probe}$** power time series. Then, the **S2-f$_{test}$** power was averaged separately over the time-points corresponding to the top-15% and bottom-15% for the **S1-f$_{probe}$** power, and the strength of **S1-f$_{probe}$**-to-**S2-f$_{test}$** spectral-power association was computed as the Ln-ratio of these averages. A larger association value indicates that the top/bottom-15% variation in the probe frequency power at *S1* was associated with greater modulation in the test-frequency power at *S2* in Ln-ratio. In this way, we computed the strengths of *S1*-probe-frequency-to-*S2*-test-frequency spectral-power associations for all combinations of *S1* and *S2* wavelet-center frequencies to generate a 2-dimensional, 200-*S1*-probe-frequency-(*y*-axis)-by-200-*S2*-test-frequency (*x*-axis), association matrix per site-pair per participant and averaged across participants. Note that the diagonal indicates cross-site *within-frequency* spectral-power associations. The use of DCT-phase-scrambled controls was unnecessary in this case because partial wavelet overlap would not generate any spurious associations between data from separate sites.

   The within-site and cross-site spectral-power associations were computed for the sub-second timescale (within a 500ms interval) and the seconds timescale (across 500ms intervals). The justification for examining spectral-power associations on these specific timescales is provided in the results section (see 1. Spectral power intrinsically fluctuates on two distinct timescales). Each 5min EEG recording was divided into 600 500ms intervals. The sub-second timescale spectral-power associations were computed at 512Hz temporal resolution within each 500ms interval and averaged across all intervals (per site or site-pair per participant). The seconds timescale associations were computed at 500ms resolution (with the data temporally averaged within each 500ms interval) across the entire 5min period (using each 500ms interval as time unit). Thus, the sub-second-timescale and seconds-timescale spectral-power associations were mathematically independent.

Results

1. Spectral power intrinsically fluctuates on two distinct timescales

Half a second is a landmark timescale in that consciously accessible perceptual representations are thought to form through feedforward and feedback interactions within this timescale (e.g., Lamme et al., 2002; Fahrenfort et al., 2007; Dahaene & Changeux, 2011), and typical motor behavior such as spontaneous tapping, walking, and natural saccades have periodicities in this timescale (e.g., Collyer et al., 1994; Pachi & Ji, 2005; Pelz & Rothkopf, 2007). It is thus feasible that distinct neural interactions may transpire on (1) *within-500ms* timescales—potentially generating the basic building blocks of perceptual and motor processing—and (2) *across-500ms* timescales—potentially chaining these building blocks into cognition and action. Consistent with this reasoning, our data suggest that spectral power intrinsically fluctuates on these timescales.

Spectral-power fluctuations during a 500ms interval from a posterior site, *PO7*, from one participant is shown in Figure 2A. As we focused on large (±15th percentile) variations (see the Methods section), the top-15% power is indicated in red, the bottom-15% power is indicated in blue, and intermediate power is shown as blank. This example clearly shows that spectral power goes through about 1-2 (red-blue) cycles per frequency within 500ms. To confirm this observation across all 500ms intervals for all sites and participants, we quantified the average duration of a top/bottom state (per 500ms interval) as follows. For each frequency (i.e., for each wavelet center frequency, f_c), we identified the state sequence; in the upper example shown in Figure 2A, the sequence is, *bottom-15% → in-between → top-15% → in-between → bottom-15% → in-between → top-15%*, or [**B–T–B–T**] where "–" indicates "in-between." We binarized the T/B states by ignoring the in-between states, and only counted states that began within the 500ms interval of interest (to avoid redundant counting of states across 500ms intervals). Thus, this example included 3 states, T, B and T, so that the estimated average duration of a T/B state for this frequency would be 500ms/3 = 167ms (Figure 2A). When the same (T or B) state recurred across an in-between state, we considered them to be a single state. In the lower example shown in Figure 2A, the identified sequence is, [**–B–B–T**], but the number of states would be 2, that is, a B followed by a T (combining the two B's across the in-between state), so that the estimated average duration of a T/B state for this frequency would be 500ms/2 = 250ms (Figure 2A). We computed the average T/B-state duration in this way for each of the 600 500ms intervals (over the 5min EEG recording period) and averaged them across the 600 intervals per frequency per participant per site. We then generated a histogram of average within-500ms-interval, T/B-state durations per site using the 4,800 values computed for the 200 frequencies and 24 participants; the histograms for the 60 sites are overlaid in Figure 2C. It is clear that the distributions of average T/B-state durations were globally similar (i.e., similar across all 60 sites) and tightly peaked at ~230ms with a negative tail that pulled the mean down to ~215ms. This indicates that a 500ms interval consistently contained a little over one cycle of substantial power fluctuation, confirming that 500ms

provides an appropriate sub-second timescale to examine rapid power fluctuations whose low/high states last ~230ms.

An equivalent analysis was conducted for spectral-power fluctuations across 500ms intervals over the 5min period with the spectral power averaged within each 500ms interval. The spectral-power-fluctuation data at *PO7* from the same participant is shown in Figure 2B with the time axis indicating the serial number of 500ms intervals. This example clearly shows that the spectral power fluctuated between the top-15% (red) and bottom-15% (blue) states at a relatively stable rate. We computed the average T/B-state duration by dividing the entire duration (600 500ms intervals) by the number of T/B states (counted in the same way as above) per frequency per participant per site. We again generated a histogram of average T/B-state durations per site using the 4,800 values computed for the 200 frequencies and 24 participants, and overlaid the histograms for the 60 sites (Figure 2D). It is clear that the distributions of average T/B-state durations across 500ms intervals were globally similar (i.e., similar across all 60 sites) and tightly peaked at about 7.5 500ms-intervals or ~3.75s with a positive tail that pushed the mean up to ~5.44s. Thus, slower spectral-power fluctuations occurred on the timescale of several seconds.

These results indicate that intrinsic spectral-power fluctuations are characterized by at least two distinct timescales, the *sub-second timescale* (within a 500ms interval) with a typical T/B-state lasting ~230ms and the *seconds timescale* (across 500ms intervals) with a typical T/B-state lasting ~3.75s. Note that these power fluctuations on the sub-second and seconds timescales are mathematically independent. As shown below, the spectral-power variations on these timescales yielded distinct patterns of within-site and cross-site spectral-power associations.

Figure 2. Intrinsic spectral-power variations on the characteristic sub-second (~230ms) and seconds (~3.75s) timescales. A. An example of the top-15% (red) and bottom-15% (blue) spectral-power variations within a 500ms interval (taken from a 5min EEG recording; see B) at a posterior site, *PO7*, from one participant. Note that spectral power tends to peak in pairs of frequencies that are ~10Hz apart (the vertical arrows indicating Δ*f*~10Hz). The average duration of the top and bottom states was estimated per frequency by identifying the state sequence ("B" for bottom, "T" for top, and "–" for in-between states in the illustration), counting the top and bottom states that started within the interval while discounting immediate repetitions, and dividing the interval duration (500ms in this case) by the number of T/B states. Two examples are shown for two different frequencies (see text for details). The average T/B-state duration was computed for each of the 600 500ms intervals over the 5min EEG recording period and averaged across those 600 intervals per frequency per participant per site. **B.** An example of the top-15% (red) and bottom-15% (blue) power variations occurring across 500ms intervals (spectral power averaged within each 500ms interval) over the 5min period. The average duration of the top and bottom states was estimated in the same way as for the 500ms interval (see A) but using 500ms intervals as time unit. **C.** Histograms of average T/B-state durations (within 500ms intervals) based on the 4,800 values computed for 200 frequencies and 24 participants per site; histograms from the 60 sites are overlaid. The mode of ~230ms indicates that each brief high/low-power state typically lasted about a quarter of a second. **D.** Histograms of average T/B-state durations (across 500ms intervals) based on the 4,800 values computed for 200 frequencies and 24 participants per site; histograms from the 60 sites are overlaid. The mode of ~3.75s indicates that each longer (across-500ms-interval) high/low-power state typically lasted several seconds. Note that these power fluctuations on the sub-second (with the mode of ~230ms per state) and seconds (with the mode of ~3.75s per state) timescales are mathematically independent. These timescales yielded distinct patterns of spectral-power associations (see text).

2. Within-site (local) spectral-power associations on the (fast) sub-second timescale

The within-site spectral-power associations (in Ln-ratio relative to the phase-scrambled controls; see the Methods section: *3.4. Computing spectral-power associations*) on the sub-second timescale (within a 500ms interval) are marked by strong associations along the 45° lines parallel to the diagonal (see the 2D cross-frequency association plots in Figure 3A, B, D). This indicates that the associations are characterized by specific frequency differences, particularly, Δf~3Hz, Δf~10Hz, and Δf~16Hz. The representative association patterns are shown in Figure 3A-C. Posterior, lateral, and anterior sites yielded distinct patterns.

A representative posterior site shows systematic associations for the θ-α frequencies along the Δf~3Hz lines and particularly for the β-γ frequencies along the Δf~10Hz lines (e.g., Figure 3A, dashed ellipses). Note that the Δf~10Hz associations can be seen within a single 500ms interval as frequent co-occurrences of top-15% states in pairs of frequencies separated by ~10Hz (e.g., vertical arrows in Figure 2A). We evaluated the inter-participant consistency of these patterns in three ways. One way was by plotting the association strength as a function of Δf for each major frequency band (labeled θ, α, β_1, β_2, β_3, γ_1 and γ_2 in the figures). In this way, the associations for the θ-α frequencies along the Δf~3Hz lines (e.g., the main panel in Figure 3A) correspond to the θ and α curves both peaking at Δf~3Hz (e.g., the upper-right panel in Figure 3A), while the associations for the β-γ frequencies along the Δf~10Hz lines (e.g., the main panel in Figure 3A) correspond to the β_1, β_2, β_3, γ_1 and γ_2 curves all peaking at Δf~10Hz (e.g., the upper-right panel in Figure 3A). The tall peaks compared with the relatively small error regions (±1 standard error of the mean with participants as the random effect) indicate that the peaked associations along Δf~3Hz and Δf~10Hz at posterior sites are consistent across participants (the conventional *t*-value is the ratio of the height of each peak to the width of the corresponding error region).

A representative lateral site shows associations for the θ-α frequencies along the Δf~3Hz lines, for the β_1 frequencies along the Δf~8Hz lines, and particularly for the γ_2 frequencies along the Δf~16Hz lines (combined with negative associations along the Δf~8Hz lines) (e.g., the main panel in Figure 3B). The inter-participant consistency of these associations is reflected in the θ and α curves peaking at Δf~3Hz, the β_1 curve peaking at Δf~8Hz, and the γ_2 curve substantially peaking at Δf~16Hz and dipping at Δf~8Hz (e.g., the upper-right panel in Figure 3B) relative to the corresponding error regions.

A representative anterior site shows the lack of any notable spectral-power associations (e.g., the main panel in Figure 3C) reflected in the relatively flat curves hovering around zero for all frequency bands (the upper-right panel in Figure 3C).

A second way in which we evaluated the consistency of cross-frequency association patterns was to confirm within-region similarity. In particular, the associations characterized by the θ-α frequencies peaking at Δf~3Hz (see the posterior region of Figure 3D, 3E) and the β-γ frequencies peaking at Δf~10Hz (see the posterior region of Figure 3D, 3F-H) are shared among posterior sites, those characterized by the γ_2 frequencies peaking at Δf~16Hz (see the lateral region of Figure 3D, 3H) are shared among lateral sites, and the relative lack of spectral-power associations (see the anterior region of Figure 3D-H) are shared among anterior sites. A third way in which we evaluated data consistency was to confirm that the same conclusions about the spectral-power association patterns could be drawn based on the data from the odd or even numbered participants (see Supplementary Figure S1A-C). We did not compute conventional *p*-values adjusted in various ways to more or less "control for" multiple comparisons because those would not add substantively to the above methods of evaluating reliability for the purpose of identifying characteristic patterns of spectral-power associations.

Within-site spectral-power associations on the sub-second timescale (within a 500ms interval)

Figure 3. Within-site spectral-power associations on the sub-second timescale (within a 500ms interval). The sub-second-timescale spectral-power associations were computed at 512Hz temporal resolution within each 500ms interval and averaged across all intervals (per site per participant) and averaged across participants. Each 2D-association plot shows the strengths of power modulation at all *test* frequencies (*x*-axis) that temporally coincided with the top/bottom-15% power variation at each *probe* frequency (*y*-axis), computed as Ln-ratio relative to the DCT-phase-scrambled control (to remove artifacts due to partial wavelet overlap; see text for details). Any asymmetry across the diagonal indicates directional differences; *X*-Hz power modulation coincident with the top/bottom-15% *Y*-Hz power variation may be stronger/weaker than the *Y*-Hz power modulation coincident with the top/bottom-15% *X*-Hz power variation. **A-C.** Representative association patterns. The strong associations along the 45° lines (A and B) indicate that spectral-power associations occurred at constant frequency differences, Δf's. The accompanying line plots show the association strengths for major frequency bands as a function of Δf (warmer-colored curves representing higher-frequency bands), averaged across the *y*-side and *x*-side of the diagonal as the associations were approximately symmetric about the diagonal. The plots clearly show that the association strengths peaked at specific Δf values. **A.** An example from a representative posterior site (*PO8*) characterized by the $\Delta f\sim3$Hz associations for the θ-α frequencies (small dashed ellipse) and particularly by the $\Delta f\sim10$Hz associations for the β-γ frequencies (large dashed ellipse), suggesting that the θ-α and β-γ frequencies are amplitude-modulated at ~3Hz and~10Hz, respectively, at posterior sites (see text for details). **B.** An example from a representative lateral site (*C6*) primarily characterized by the $\Delta f\sim16$Hz associations for the higher γ frequencies (large dashed ellipse), suggesting that the higher γ frequencies are amplitude-modulated at ~16Hz at lateral sites. **C.** An example from a representative anterior site (*AFz*) characterized by the lack of notable associations, suggesting that different frequency bands operate relatively independently at anterior sites. **D-H.** Association patterns at all sites. **D.** 2D-association plots. **E-H.** Corresponding line plots showing the association strengths for major frequency bands as a function of Δf. The line plots are shown separately for the θ-α, β (β_1, β_2, β_3), γ_1, and γ_2 bands to reduce clutter. The lower panels show representative 2D-association plots to highlight the specific bands included in the line plots. **E.** Line plots of association strengths for the θ and α frequencies, peaking at $\Delta f\sim3$Hz at posterior sites (especially in the regions shaded in gray). **F.** Line plots of association strengths for the β (β_1, β_2, β_3) frequencies, peaking at $\Delta f\sim10$Hz at posterior sites (especially in the region shaded in gray). **G.** Line plots of association strengths for the γ_1 frequencies, peaking at $\Delta f\sim10$Hz at posterior sites (especially in the region shaded in gray). **H.** Line plots of association strengths for the γ_2 frequencies, peaking at $\Delta f\sim10$Hz at posterior sites and $\Delta f\sim16$Hz at lateral sites (especially in the regions shaded in gray). In all parts the shading on the line plots represents ±1 standard error of the mean with participants as the random effect.

3. Within-site (local) spectral-power associations on the (slower) seconds timescale

The within-site spectral-power associations on the seconds timescale (across 500ms intervals) are characterized by vertical and horizontal directions. The representative association patterns are shown in Figure 4A-C. At a representative posterior site, large (top/bottom-15%) power variations in the θ-lowγ frequencies (the *y*-axis indicating probe frequencies) were selectively associated with the power modulation in the α band and also β band to a lesser degree (the *x*-axis indicating test frequencies), forming a vertical column at the α band and to a lesser degree at the β band (e.g., the dashed rectangles in the lower panel in Figure 4A). The inter-participant consistency of these associations is reflected in the accompanying line plots in which the association strengths are averaged within each probe-frequency band (labeled with "*p*") and plotted as a function of test frequency. The α-band column (α-column) and the lesser β-band column are reflected in the $p\theta$, $p\alpha$, $p\beta_1$, $p\beta_2$, $p\beta_3$, and $p\gamma_1$ curves consistently peaking at the α band and also at β band to a lesser degree (e.g., the upper panel in Figure 4A).

At a representative lateral site, power variations in the midβ-γ frequencies were broadly associated with one another (e.g., the dashed square in the lower panel in Figure 4B), with the inter-participant consistency of these associations reflected in the $p\beta_2$, $p\beta_3$, $p\gamma_1$, and $p\gamma_2$ curves consistently elevated across the midβ-γ range (e.g., the upper panel in Figure 4B).

At a representative anterior site, there were no notable spectral-power associations (e.g., the lower panel in Figure 4C), reflected in the curves representing all probe-frequency bands being relatively flat and hovering around zero (e.g., the upper panel in Figure 4C).

Figure 4D-H shows that these characteristic patterns of spectral-power associations are consistent within each region. Specifically, the associations marked by the α-column (and the β-column to a lesser degree) characterized by the $p\theta$, $p\alpha$, $p\beta_1$, $p\beta_2$, $p\beta_3$, and $p\gamma_1$ curves consistently peaking at the α band (and at the β band to a lesser degree) are shared among posterior sites (see the posterior region of Figure 4D, 4E-G). The associations marked by the broad square-shaped relationship across the midβ-γ frequencies characterized by the $p\beta_2$, $p\beta_3$, $p\gamma_1$, and $p\gamma_2$ curves consistently elevated across the midβ-γ range are shared among lateral sites (see the lateral regions of Figure 4D, 4F-H). The lack of notable spectral-power associations characterized by the curves for the entire range of probe frequencies being relatively flat and hovering around zero is shared among anterior sites (see the anterior region of Figure 4D, 4E-H). Further, these characteristic patterns of spectral-power associations are evident in the data from the odd or even numbered participants (Supplementary figure S1 D-F).

Within-site spectral-power associations on the seconds timescale (across 500ms intervals)

Figure 4. Within-site spectral-power associations on the seconds timescale (across 500ms intervals). The seconds-timescale spectral-power associations were computed at 500ms temporal resolution across the entire 5min period (per site per participant) and averaged across participants. Each 2D-association plot shows the strengths of power modulation at all *test* frequencies (*x*-axis) that temporally coincided with the top/bottom-15% power variation at each *probe* frequency (*y*-axis), computed as Ln-ratio relative to the DCT-phase-scrambled control (to remove artifacts due to partial wavelet overlap; see text for details). Any asymmetry across the diagonal indicates directional differences; *X*-Hz power modulation coincident with the top/bottom-15% *Y*-Hz power variation may be stronger/weaker than the *Y*-Hz power modulation coincident with the top/bottom-15% *X*-Hz power variation. **A-C.** Representative association patterns. The strong associations along the vertical and horizontal directions indicate that spectral-power associations are characterized by multiple frequencies being associated with a specific frequency band or with one another. The accompanying line plots show the association strengths of each probe-frequency band (labeled with "*p*"; warmer-colored curves representing higher-probe-frequency bands) with all test frequencies (*x*-axis). The plots clearly show that the association strengths peaked at specific test frequencies. **A.** An example from a representative posterior site (*POz*) characterized by the associations of the θ-lowγ frequencies with the α band and to a lesser degree with the midβ band (dashed rectangles), suggesting that the α band and to a lesser degree the midβ band play a role in coordinating cross-frequency interactions at posterior sites. **B.** An example from a representative lateral site (*FC6*) characterized by the broad associations among the midβ-γ frequencies (dashed square). **C.** An example from a representative anterior site (*AFz*) characterized by the lack of notable associations, suggesting that different frequency bands operate relatively independently at anterior sites. **D-H.** Association patterns at all sites. **D.** 2D-association plots. **E-H.** Corresponding line plots showing the association strengths of each probe-frequency band with all test frequencies (*x*-axis). The line plots are shown separately for the θ-α, β (β_1, β_2, β_3), γ_1, and γ_2 bands to reduce clutter. The lower panels show representative 2D-association plots to highlight the specific probe-frequency bands included in the line plots. **E.** Line plots showing the association strengths of the θ and α probe-frequency bands (labeled "$p\theta$" and "$p\alpha$") with all test frequencies. The θ and α bands are both associated with the α band while the α band is additionally associated with the midβ band at posterior sites (especially in the region shaded in gray). **H.** Line plots showing the association strengths of the β (β_1, β_2, β_3) probe-frequency bands (labeled "$p\beta_1$," "$p\beta_3$," and "$p\beta_3$") with all test frequencies. The β (β_1, β_2, β_3) bands are primarily associated with the α band at posterior sites, while the β_2 and β_3 bands are broadly associated with the midβ-γ bands at lateral sites (especially in the regions shaded in gray). **I.** Line plots showing the association strengths of the γ_1 probe-frequency band (labeled "$p\gamma_1$") with all test frequencies. The γ_1 band is associated with the α and midβ bands at posterior sites, while it is broadly associated with the midβ-γ bands at lateral sites (especially in the regions shaded in gray). **J.** Line plots showing the association strengths of the γ_2 probe-band (labeled "$p\gamma_2$") with all test-frequency bands. The γ_2 band is broadly associated with the midβ-γ bands at lateral sites (especially in the regions shaded in gray). In all parts the shading on the line plots represents ±1 standard error of the mean with participants as the random effect.

In summary, the patterns of within-site (local) spectral-power associations were distinct for the sub-second (within a 500ms interval) and seconds (across 500ms intervals) timescales. The (fast) sub-second-timescale associations were characterized by 45° lines parallel to the diagonal, indicative of associations at constant Δf's, whereas the (slower) seconds-timescale associations were characterized by columns, indicative of multiple frequencies being selectively associated with a specific band or with one another. In particular, the (fast) sub-second-timescale oblique associations were primarily characterized by the θ-α frequencies associated at Δf~3Hz and the β-γ frequencies associated at Δf~10Hz at posterior sites (e.g., Figure 3A; also see the posterior region of Figure 3D, 3E-H), and the β-γ frequencies associated at Δf~16Hz at lateral sites (e.g., Figure 3B; also see Figure the lateral regions of 3D, 3H). The (slower) seconds-timescale columnar associations were primarily characterized by the θ-lowγ frequencies associated with the α band (also β band to a lesser degree) at posterior sites (e.g., Figure 4A; also see the posterior region of Figure 4D, 4E-G), and the midβ-γ frequencies broadly associated with one another at lateral sites (e.g., Figure 4B; also see the lateral regions of Figure 4D, 4F-H). No notable spectral-power associations were found on either timescale at anterior sites (e.g., Figures 3C and 4C; also see the anterior region of Figure 3D, 3E-H, and Figure 4D, 4E-H).

4. Cross-site (long-distance) spectral-power associations on the (fast) sub-second timescale

The cross-site spectral-power associations (in Ln ratio) on the sub-second-timescale (within a 500ms interval) are characterized by the diagonal, indicative of within-frequency interactions, while the ranges of associated frequencies varied from site-pair to site-pair (representative examples shown in Figure 5). While there are 60x59 (3,540) site combinations, characteristic patterns of cross-site associations can be identified by examining the associations from all sites to representative sites: *Oz* for the posterior region, *Cz* for the central region, *AFz* for the anterior region, and *T7* and *T8* for the left-lateral and right-lateral regions, respectively. Examining cross-site associations in this way (i.e., from all sites to a target site) allowed us to directly compare the impact of each site on a target site by evaluating the spectral-power modulation (in Ln-ratio) at the target site coincident with large (top/bottom-15%) spectral-power variations at each of the other sites.

Figure 5. Representative examples of cross-site spectral-power associations on the sub-second timescale (within a 500ms interval). Each 2D spectral-power association plot shows the strengths of power modulation (in Ln-ratio) for all test-site frequencies (*x*-axis) that temporally coincided with the top/bottom-15% power variation at each probe-site frequency (*y*-axis). The sub-second-timescale spectral-power associations were computed at 512Hz temporal resolution within each 500ms interval, averaged across all intervals and then across participants. The associations are characteristically diagonal, indicative of within-frequency associations, while the ranges of associated frequencies varied from site-pair to site-pair. **A.** Within-frequency associations in the lower diagonal involving the θ-lowβ frequencies from a posterior site *P4* to a central site *Cz*. **B.** Within-frequency associations in the upper diagonal involving the γ frequencies from a posterior site *Oz* to a lateral site *T7*. **C.** Within-frequency associations in the lower and upper diagonal involving the θ-α and γ frequencies from a posterior site *P6* to a lateral site *T8*. **D.** Stronger within-frequency associations in the higher frequencies from a lateral site *FC8* to an anterior site *AFz*.

The spectral-power associations to *Oz* (a representative posterior site) from all other sites are shown in Figure 6A. The inter-participant consistency of the association patterns was evaluated in three ways. Because all associations were characteristically diagonal (Figure 6A), we computed the diagonal magnitudes (Figure 6B) with the gray regions indicating ±1 standard error of the mean (with participants as the random effects). Large frequency-dependent variations relative to the widths of the error regions indicate statistical reliability (the conventional *t*-value being their ratio). A second way in which we evaluated data consistency was to note bilateral symmetry. While large-scale neural interactions are expected to show general bilateral symmetry, spurious patterns would not. A third way was to confirm that the same conclusions about the association patterns could be drawn based on the data from the odd or even numbered participants (see Supplementary figures S2 and S3).

Although we applied the surface-Laplacian transform to all EEG data to reduce the influences of volume conduction, diagonal associations could reflect volume conduction especially between adjacent sites (e.g., Cohen, 2014). Nevertheless, any spurious contributions from volume conduction would unlikely be strongly frequency dependent because spectral-power profiles tended to be similar between adjacent sites. For example, although the overall strong diagonal associations to *Oz* from its lateral neighbors, *O1* and *O2*, may potentially reflect volume conduction (Figure 6A-B), the fact that the associations were relatively weak in the α band (Figure 6B) may reveal a characteristic of cross-site neural interactions.

Overall, the sub-second-timescale cross-site spectral-power associations to *Oz* (a representative posterior site) from other sites were all diagonal (within-frequency) and diminished with distance (Figure 6A-B), except that the γ-band associations from lateral sites (especially from *T7* [Figure 6C] and *T8*) remained strong. In general, the within-frequency associations to *Oz* were dominated by the α or θ-α bands (e.g., Figure 6D, F) or by combinations of the θ-α and γ bands (e.g., Figure 6C, E), but were never dominated by the β band (also see Figure 6A-B).

Cross-site spectral-power associations on the sub-second timescale (within a 500ms interval) from all sites to *Oz* (posterior)

A

anterior

lateral

lateral

Ln ratio

±0.4   ±0.8   ±0.4

±0.8   Oz   ±0.8

posterior

B

Fp1   Fp2

AF7   AF3   AFz   AF4   AF8

F7   F5   F3   F1   Fz   F2   F4   F6   F8

FT7   FC5   FC3   FC1   FCz   FC2   FC4   FC6   FT8

T7   C5   C3   C1   Cz   C2   C4   C6   T8

TP7   CP5   CP3   CP1   CPz   CP2   CP4   CP6   TP8

P7   P5   P3   P1   Pz   P2   P4   P6   P8

PO7   PO3   POz   PO4   PO8

O1   Oz   O2

Lateral to posterior
Within-frequency associations in θ−α and highβ−γ

Central to posterior
Within-frequency associations especially in α

Within posterior
Within-frequency associations especially in θ−α and γ

Within posterior (proximate)
Within-frequency associations especially in low/high α through β

C   D   E   F

Oz power modulation (Ln ratio)

θ α β₁ β₂ β₃ γ₁ γ₂

T7 frequency (Hz)   Cz frequency (Hz)   P1 frequency (Hz)   POz frequency (Hz)

γ₂   γ₁   β₃   β₂   β₁   α   θ

Oz frequency (Hz)   *Oz* frequency (Hz)   *Oz* frequency (Hz)   *Oz* frequency (Hz)

Figure 6. Cross-site spectral-power associations on the sub-second timescale (within a 500ms interval) from all sites to *Oz* (a representative posterior site). A. 2D spectral-power association plots. All associations are characteristically diagonal, indicative of within-frequency associations, while the ranges of associated frequencies varied across site-pairs. **B.** The values along the diagonal with the shaded regions indicating ±1 standard error of the mean (with participants as the random effect). **C-F.** Representative associations. **C.** *T7* (a left-lateral site) to *Oz* spectral-power associations, characterized by the within-frequency associations in the θ-α and highβ-γ bands, skipping the middle (β band). **D.** *Cz* (a central site) to *Oz* spectral-power associations, characterized by the within-frequency associations primarily in the α band. **E.** *P1* (a posterior site) to *Oz* spectral-power associations, characterized by the within-frequency associations particularly in the θ-α and γ bands, skipping the middle (β band). **F.** *POz* (an adjacent site) to *Oz* spectral-power associations, characterized by the within-frequency associations particularly in the low/high α through β bands. The color scale is shown at the top of part A (also indicated within association plots when different; for example, "±0.4" indicates that the color scale for the corresponding association plot ranges from –0.4 to +0.4).

The sub-second-timescale cross-site spectral-power associations to *Cz* (a representative central site) from other sites were also all diagonal (within-frequency) and diminished with distance (Figure 7A-B), except that the α-band associations from posterior sites remained strong (e.g., Figure 7D; also see the posterior region of Figure 7A-B). The within-frequency associations to *Cz* were generally dominated by the α band (e.g., Figure 7C-F), while some associations from within the central region were relatively frequency independent (e.g., from *FC3*, *FC4*, *C3*, *C4*; also see Figure 7A-B).

The sub-second-timescale cross-site spectral-power associations to *AFz* (a representative anterior site) from other sites were also all diagonal (within-frequency) and diminished with distance (Figure 8A-B), except that the α-band associations from some posterior sites remained strong (e.g., from *P7*, *PO7*, *P8* [Figure 8F], *PO8*). The within-frequency associations to *AFz* were generally dominated by the α band (e.g., Figure 8C, 8F), the β-γ bands (e.g., Figure 8D), or combinations of the α and β-γ bands (e.g., Figure 8E), but were never dominated by the β band (also see Figure 8A-B). It is noteworthy that the associations to *AFz* from a pair of neighboring sites, *Fp1* (Figure 8C) and *AF7* (Figure 8D) were opposite, that is, the associations from *Fp1* were dominated by the α band whereas those from *AF7* were dominated by the β-γ bands; this spectrally opposite relationship was replicated on the right side for the associations from *Fp2* and *AF8* (Figure 8A-B) and obtained from both the odd and even numbered participants (Figure S2 G-I). These spectrally opposite association patterns from neighboring sites indirectly confirm that the surface-Laplacian transform was reasonably effective at revealing distinct neural sources.

The sub-second-timescale cross-site spectral-power associations to *T7* and *T8* (representative left and right lateral sites) from other sites were also all diagonal (within-frequency) and diminished with distance (Figure 9A-B, 9H-I), except that the α-band associations from some contralateral sites (e.g., *C6* [Figure 9G] and *P8* for *T7* and *C5* [Figure 9J] and *P7* for *T8*) and the highβ-γ associations from *Oz* (Figure 9F, K) remained strong. The within-frequency associations to *T7* and *T8* were generally dominated by the β-γ, highβ-γ, or γ band (primarily from the ipsilateral central and anterior regions; e.g., Figure 9C-D, M-N), the α band (primarily from the contralateral regions; e.g., Figure 9G, J), or combinations of the θ-α or α band and the highβ-γ or γ band (primarily from ipsilateral posterior and central regions; Figure 9E-F, K-L), but were never dominated by the β band (also see Figure 14A-B, 14H-I).

Note that the sub-second-timescale cross-site association patterns to *Oz* (posterior), *Cz* (central), *AFz* (anterior), *T7* (left lateral), and *T8* (right lateral) were generally bilaterally symmetric (Figures 6A-B [posterior], 7A-B [central], 8A-B [anterior], 9A vs. 9H, 9B vs. 9I, 9C-G vs. 9J-N [lateral]). Further, the above conclusions can be drawn based on the data from the even or odd numbered participants (Supplementary Figure S2 A-C [posterior], D-F [central], G-I [anterior], J-L, M-O [lateral]).

Cross-site spectral-power associations on the sub-second timescale (within a 500ms interval) from all sites to *Cz* (central)

Anterior to central
Within-frequency associations especially in α

Posterior to central
Within-frequency associations in α

Within central
Within-frequency associations especially in θ–α through β

Lateral to central
Within-frequency associations in α

Figure 7. Cross-site spectral-power associations on the sub-second timescale (within a 500ms interval) from all sites to *Cz* (a representative central site). A. 2D spectral-power association plots. All associations are characteristically diagonal, indicative of within-frequency associations, while the ranges of associated frequencies varied across site-pairs. **B.** The values along the diagonal with the shaded regions indicating ±1 standard error of the mean (with participants as the random effect). **C-F.** Representative associations. **C.** *Fz* (an anterior site) to *Cz* spectral-power associations, characterized by the within-frequency associations particularly in the α band. **D.** *O1* (a posterior site) to *Cz* spectral-power associations, characterized by the within-frequency associations in the α band. **E.** *CP2* (a central site) to *Cz* spectral-power associations, characterized by the within-frequency associations particularly in the θ-α through β bands. **F.** *C6* (a lateral site) to *Cz* spectral-power associations, characterized by the within-frequency associations in the α band. The color scale is shown at the top of part A (also indicated within association plots when different; for example, "±0.4" indicates that the color scale for the corresponding association plot ranges from –0.4 to +0.4).

Cross-site spectral-power associations on the sub-second timescale (within a 500ms interval) from all sites to *AFz* (anterior)

Figure 8. Cross-site spectral-power associations on the sub-second timescale (within a 500ms interval) from all sites to *AFz* (a representative anterior site). A. 2D spectral-power association plots. All associations are characteristically diagonal, indicative of within-frequency associations, while the ranges of associated frequencies varied across site-pairs. **B.** The values along the diagonal with the shaded regions indicating ±1 standard error of the mean (with participants as the random effect). **C-F.** Representative associations. **C.** *Fp1* (an anterior site) to *AFz* spectral-power associations, characterized by the within-frequency associations particularly in the θ-α through β bands. **D.** *AF7* (an anterior site) to *AFz* spectral-power associations, characterized by the within-frequency associations particularly in the β-γ bands. Note that although *Fp1* and *AF7* are adjacent anterior sites the frequency characteristics of their associations with *AFz* were opposite (the low-to-middle bands for *Fp1* and the middle-to-high bands for *AF7*); this pattern was replicated on the right side at *Fp2* and *AF8* (see A and B). **E.** *FCz* (a central site) to *AFz* spectral-power associations, characterized by the within-frequency associations particularly in the α and midβ-γ bands. **F.** *P6* (a posterior site) to *AFz* spectral-power associations, characterized by the within-frequency associations in the α band. The color scale is shown at the top of part A (also indicated within association plots when different; for example, "±0.4" indicates that the color scale for the corresponding association plot ranges from –0.4 to +0.4).

Cross-site spectral-power associations on the sub-second timescale (within a 500ms interval) from all sites to T7 (left lateral) and T8 (right lateral)

Figure 9. Cross-site spectral-power associations on the sub-second time scale (within a 500ms interval) from all sites to *T7* **(a representative left lateral site) and** *T8* **(a representative right lateral site). A, H.** 2D spectral-power association plots for *T7* and *T8*. All associations are characteristically diagonal, indicative of within-frequency associations, while the ranges of associated frequencies varied across site-pairs. **B, I.** The power-modulation values along the diagonal with the shaded regions indicating ±1 standard error of the mean (with participants as the random effect). **C-G, J-N.** Representative associations for *T7* or *T8*. Note the bilateral symmetry. **C, N.** *AF7/AF8* (ipsilateral anterior sites) to *T7/T8* spectral-power associations, characterized by the within-frequency associations particularly in the β-γ bands. **D, M.** *C3/C4* (ipsilateral sites) to *T7/T8* spectral-power associations, characterized by the within-frequency associations in the highβ-γ bands (D) or the γ band (M). **E, L.** *P5/P6* (ipsilateral posterior sites) to *T7/T8* spectral-power associations, characterized by the within-frequency associations particularly in the α and γ bands. **F, K.** *Oz* (a posterior site) to *T7/T8* spectral-power associations, characterized by the within-frequency associations in the θ-α and highβ-γ bands. **G, J.** *C6/C5* (contralateral sites) to *T7/T8* spectral-power associations, characterized by the within-frequency associations in the α band. The color scale is shown at the top of part A (also indicated within association plots when different; for example, "±0.4" indicates that the color scale for the corresponding association plot ranges from –0.4 to +0.4).

In summary, the (fast) sub-second-timescale (within a 500ms interval) cross-site (long-distance) spectral-power associations are characterized by diagonal, within-frequency, associations dominated by different frequency ranges. Although the frequency dependence varied from site-pair to site-pair, some characteristic patterns emerged. Not surprisingly, the association strengths generally diminished with distance. Nevertheless, some associations remained strong. Those "super" long-distance associations tended to be dominated by the α band, such as the associations from lower posterior sites (*PO7*, *PO3*, *POz*, *PO4*, *PO8*, *O1*, *Oz*, and *O2*) to a representative central site, *Cz* (Figure 7A-B), from lateral posterior sites (*P7*, *P5*, *PO7*, *P6*, *P8*, and *PO8*) to a representative anterior site, *AFz* (Figure 8A-B), and from contralateral sites (*FT8*, *C6*, *TP8*, *P8*, and *PO8*; *FT7*, *C5*, *TP7*, *P8*, and *PO7*) to representative left and right lateral sites *T7* and *T8* (Figure 9A-B, 9H-I). A few super long-distance associations were dominated by the β-γ bands, such as those from a posterior site, *Oz*, to representative left and right lateral sites, *T7* and *T8* (Figure 9A-B, 9H-I). Overall, the associations to *Oz* (a representative posterior site), *AFz* (a representative anterior site), and *T7*/*T8* (representative left and right lateral sites) were dominated by the θ-α bands, β-γ bands, or combinations of the θ-α and β-γ bands, whereas the associations to *Cz* (a representative central site) was dominated by the α band. Notably, no associations were dominated by the β band.

5. Cross-site (long-distance) spectral-power associations on the (slower) seconds timescale

The cross-site spectral-power associations (in Ln-ratio) on the seconds timescale (across 500ms intervals) are characterized by columnar, square, and diagonal patterns. Notably, the associations from posterior sites to other sites are characterized by "α-columns," that is, the posterior spectral-power variations in the θ-lowγ bands were selectively associated with the α-band power modulation at other sites (e.g., Figure 10A-D). Other associations are characterized by the α-band to α-band associations (e.g., Figure 10E-H), broad associations among the β-γ bands (Figure 10F and 10H to some degree), and within-frequency (diagonal) associations (e.g., Figure 10H).

Figure 10. Representative examples of cross-site spectral-power associations on the seconds timescale (across 500ms intervals). Each 2D spectral-power association plot shows the strengths of power modulation (in Ln-ratio) for all test-site frequencies (*x*-axis) that temporally coincided with the top/bottom-15% power variation at each probe-site frequency (*y*-axis). The seconds-timescale spectral-power associations were computed at 500ms temporal resolution across the entire 5min period, and averaged across participants. We obtained several characteristic patterns of associations. **A-D.** The "α-column" associations from posterior sites to other sites characterized by the posterior θ-lowγ bands selectively associated with the α band at other sites. **E-H.** Other patterns of associations (not involving posterior sites) characterized by the α to α associations (**E-H**), broad associations among the β-γ bands (**F** and **H** to some degree), and within-frequency (diagonal) associations (**H**).

As we did above for the sub-second-timescale associations, we examined the associations from all sites to representative sites in the posterior (*Oz*), central (*Cz*), anterior (*AFz*), left-lateral (*T7*), and right-lateral (*T8*) regions. To assess the inter-participant consistency of the association patterns, we generated line plots corresponding to each 2D-association plot, where each curve shows the test-site spectral-power modulation coincident with the probe-site top/bottom-15% power variation in each major frequency band (lower-to-higher frequency bands labeled with cooler-to-warmer colors), with the shaded regions indicating ±1 standard error of the mean (with participants as the random effect). In other words, each curve shows a horizontal slice of the corresponding 2D-association plot for a specific probe-site frequency band (see the rectangular boxes in the bottom panels in Figures 11-14). Overall, spectral-power associations to all five target sites diminished with distance (Figures 11-14) as they did on the sub-second timescale.

The seconds-timescale cross-site spectral-power associations to *Oz* (a representative posterior site) from other sites were characterized by two general patterns depending on the region. The associations from within the posterior region to *Oz* were characterized by (1) the α-$\mathrm{low}\gamma$-band (posterior) to α-band (*Oz*) associations, α-columns, and (2) the α-&-midβ-band (posterior) to midβ-band (*Oz*) associations to a lesser degree (e.g., Figure 11C-D; also see the posterior region of Figure 11A-B). The associations from outside the posterior region to *Oz* were characterized by the α-band (non-posterior) to α-band (and to midβ-band to a lesser degree) (*Oz*) associations (e.g., Figure 11E-F; also see the lower-anterior, central, and lateral regions of Figure 11A-B). In addition, the associations from proximate sites to *Oz* included within-frequency (diagonal) associations such as the θ-β-band associations from *POz* (Figure 11D) and broadband associations from *O1* and *O2* (see the bottom of Figure 11A), though the latter may primarily reflect volume conduction.

Cross-site spectral-power associations on the seconds timescale (across 500ms intervals) from all sites to *Oz* (posterior)

A

anterior

lateral

lateral

Ln ratio
1.8
0
-1.8

Oz

posterior

B

Fp1   Fp2
AF7   AF3   AFz   AF4   AF8
F7   F5   F3   F1   Fz   F2   F4   F6   F8
FT7   FC5   FC3   FC1   FCz   FC2   FC4   FC6   FT8
T7   C5   C3   C1   Cz   C2   C4   C6   T8
TP7   CP5   CP3   CP1   CPz   CP2   CP4   CP6   TP8
P7   P5   P3   P1   Pz   P2   P4   P6   P8
PO7   PO3   POz   PO4   PO8
O1   Oz   O2

Within posterior
(α–lowγ) to α and (α & midβ) to midβ associations
plus, within-frequency associations in θ–β

Within posterior (proximate)

Lateral to posterior
α to (α & midβ) associations

Anterior to posterior

C

Oz power modulation (Ln ratio)

θ α β₁ β₂ β₃ γ₁ γ₂

P1α
P1β₁
P1β₂
P1β₃
P1γ₁

P1α
P1β₂

P1γ₂
P1γ₁
P1β₃
P1β₂
P1β₁
P1α
POzα
P1θ

θ α β₁ β₂ β₃ γ₁ γ₂
Oz frequency (Hz)

D

θ α β₁ β₂ β₃ γ₁ γ₂

POzα
POzβ₁
POzβ₂
POzβ₃
POzγ₁

P1β₂
P1α

POzγ₂
POzγ₁
POzβ₃
POzβ₂
POzβ₁
POzα
POzθ

θ α β₁ β₂ β₃ γ₁ γ₂
Oz frequency (Hz)

E

θ α β₁ β₂ β₃ γ₁ γ₂

C5α

C5α

C5γ₂
C5γ₁
C5β₃
C5β₂
C5β₁
C5α
C5θ

θ α β₁ β₂ β₃ γ₁ γ₂
Oz frequency (Hz)

F

θ α β₁ β₂ β₃ γ₁ γ₂

Fzα

Fzα

Fzγ₂
Fzγ₁
Fzβ₃
Fzβ₂
Fzβ₁
Fzα
Fzθ

θ α β₁ β₂ β₃ γ₁ γ₂
Oz frequency (Hz)

Figure 11. Cross-site spectral-power associations on the seconds timescale (across 500ms intervals) from all sites to *Oz* (a representative posterior site). A. 2D spectral-power association plots. Some associations are columnar, indicating multiple frequencies associated with a specific (primarily α) band, and some are diagonal, indicating within-frequency associations. **B.** Replotting of A. Each curve shows the spectral-power modulation at *Oz* associated with probe-site power variation in each major frequency band (lower-to-higher frequency bands labeled with cooler-to-warmer colors), with the shaded regions indicating ±1 standard error of the mean (with participants as the random effect). In other words, each curve shows a horizontal slice of a 2D-association plot for a specific probe-site frequency band (see the rectangular boxes in the bottom panels). **C-F.** Representative associations. **C.** *P1* (a posterior site) to *Oz* spectral-power associations, characterized by the α-lowγ bands at *P1* associated with the α-band at *Oz* (α-column), and the α-&-midβ bands at *P1* somewhat associated the midβ band at *Oz*. **D.** *POz* (an adjacent site) to *Oz* spectral-power associations, characterized by the α-lowγ bands at *POz* associated with the α band at *Oz* (α-column), the α-&-midβ bands at *POz* somewhat associated with the midβ band at *Oz* (as in C, but stronger), and the diagonal (within-frequency) associations in the θ-β bands. **E.** *C5* (a lateral site) to *Oz* spectral-power associations, characterized by the α band at *C5* associated with the α band (and the midβ-band to some degree) at *Oz*. **F.** *Fz* (an anterior site) to *Oz* spectral-power associations, characterized by the α band at *Fz* associated with the α band (and the midβ band to some degree) at *Oz* (as in E). The color scale is shown at the top of part A. Note that spectral-power associations from most posterior sites to *Oz* contain α-columns. The color scale is shown at the top of part A.

The seconds-timescale cross-site spectral-power associations to *Cz* (a representative central site) from posterior sites were characterized by the θ-lowγ-band (posterior) to α-band (*Cz*) associations, α-columns (e.g., Figure 12F; also see the posterior region of Figure 12A-B). The associations from non-posterior sites to *Cz* generally included the α-band (non-posterior) to α-band (*Cz*) associations (e.g., Figure 12C-E; also see the anterior, central, and lateral regions of Figure 12A-B). In addition, the associations from proximate sites to *Cz* included within-frequency (diagonal) associations in the θ-β bands (e.g., Figure 12E; also see the sites surrounding *Cz* in Figure 12A-B).

The seconds-timescale cross-site spectral-power associations to *AFz* (a representative anterior site) from posterior sites were characterized by the θ-lowγ-band (posterior) to α-band (*AFz*) associations, α-columns (e.g., Figure 13F; also see the posterior region of Figure 13A-B). The associations from non-posterior sites generally included the α-band (non-posterior) to α-band (*AFz*) associations (e.g., Figure 13E; also see the anterior, central, and lateral regions of Figure 13A-B). In addition, the associations from anterior and lateral sites to *AFz* included broad associations in the highβ-γ band as well as within-frequency (diagonal) associations (e.g., Figure 13C-D; also see the anterior and upper lateral regions of Figure 13A-B).

The seconds-timescale cross-site spectral-power associations to *T7* and *T8* (representative left and right lateral sites) from posterior sites were characterized by the θ-lowγ-band (posterior) to α-band (*T7/T8*) associations, α-columns (e.g., Figure 14E, L; also see the posterior region of Figure 14A-B, 14H-I). The associations from non-posterior sites to *T7* and *T8* generally included the α-band (non-posterior) to α-band (*T7/T8*) associations (e.g., Figure 14C-D, F-G, J-K, M-N; also see the anterior, central, and lateral regions of Figure 14A-B, 14H-I). In addition, the associations from the ipsilateral and contralateral sites to *T7* and *T8* included broad associations in the highβ-γ bands (e.g., Figure 14C-D, G, J, M-N; also see the lateral regions of Figure 14A-B, 14H-I) as well as within-frequency (diagonal) associations from the ipsilateral sites (e.g., Figure 14C-D, M-N).

Note that the seconds-timescale cross-site association patterns to *Oz* (posterior), *Cz* (central), *AFz* (anterior), *T7* (left lateral), and *T8* (right lateral) were generally bilaterally symmetric (Figures 11A-B [posterior], 12A-B [central], 13A-B [anterior], 14A vs. 14H, 14B vs. 14I, 14C-G vs. 14J-N [lateral]). Further, the above conclusions can be drawn based on the data from the even or odd numbered participants (Supplementary Figure S3A-C [posterior], D-F [central], G-I [anterior], J-L, M-O [lateral]).

Cross-site spectral-power associations on the seconds timescale (across 500ms intervals) from all sites to *Cz* (central)

A

anterior

Ln ratio

lateral

Cz

lateral

posterior

B

Fp1   Fp2
AF7   AF8
AF3   AFz   AF4
F7   F5   F3   F1   Fz   F2   F4   F6   F8
FT7   FC5   FC3   FC1   FCz   FC2   FC4   FC6   FT8
T7   C5   C3   C1   Cz   C2   C4   C6   T8
TP7   CP5   CP3   CP1   CPz   CP2   CP4   CP6   TP8
P7   P5   P3   P1   Pz   P2   P4   P6   P8
PO7   PO3   POz   PO4   PO8
O1   Oz   O2

Anterior to central
α to *α* associations

Lateral to central
α to *α* associations

Within central
Within-frequency associations
in *θ–β*, especially *α*

Posterior to central
(*θ–lowγ*) to *α* association

C

θ α β₁ β₂ β₃ γ₁ γ₂

Cz power modulation (Ln ratio)

AF4*α*

AF4 frequency (Hz)

AF4*γ₂*
AF4*γ₁*
AF4*β₃*
AF4*β₂*
AF4*β₁*
AF4*α*
AF4*θ*

θ α β₁ β₂ β₃ γ₁ γ₂
Cz frequency (Hz)

D

θ α β₁ β₂ β₃ γ₁ γ₂

T7*α*

T7 frequency (Hz)

T7*γ₂*
T7*γ₁*
T7*β₃*
T7*β₂*
T7*β₁*
T7*α*
T7*θ*

θ α β₁ β₂ β₃ γ₁ γ₂
Cz frequency (Hz)

E

θ α β₁ β₂ β₃ γ₁ γ₂

FCz*α*
FCz*θ*   FCz*β₁*   FCz*β₂*
FCz*β₃*

FCz frequency (Hz)

FCz*γ₂*
FCz*γ₁*
FCz*β₃*
FCz*β₂*
FCz*β₁*
FCz*α*
FCz*θ*

θ α β₁ β₂ β₃ γ₁ γ₂
Cz frequency (Hz)

F

θ α β₁ β₂ β₃ γ₁ γ₂

PO8*α*
PO8*β₂*
PO8*β₁*
PO8*β₃*
PO8*γ₁*
PO8*θ*

PO8 frequency (Hz)

PO8*γ₂*
PO8*γ₁*
PO8*β₃*
PO8*β₂*
PO8*β₁*
PO8*α*
PO8*θ*

α-column

θ α β₁ β₂ β₃ γ₁ γ₂
Cz frequency (Hz)

Figure 12. Cross-site spectral-power associations on the seconds timescale (across 500ms intervals) from all sites to *Cz* (a representative central site). A. 2D spectral-power association plots. Some associations are columnar, indicating multiple frequencies associated with a specific (primarily α) band, and some are diagonal, indicating within-frequency associations. **B.** Replotting of A. Each curve shows the spectral-power modulation at *Cz* associated with the probe-site power variation in each major frequency band (lower-to-higher frequency bands labeled with cooler-to-warmer colors), with the shaded regions indicating ±1 standard error of the mean (with participants as the random effect). In other words, each curve shows a horizontal slice of a 2D-association plot for a specific probe-site frequency band (see the rectangular boxes in the bottom panels). **C-F.** Representative associations. **C.** *AF4* (an anterior site) to *Cz* spectral-power associations, characterized by the α band at *AF4* associated with the α band at *Cz*. **D.** *T7* (lateral) to *Cz* spectral-power associations, characterized by the α band at *T7* associated with the α band at *Cz* (as in C). **E.** *FCz* (an adjacent site) to *Cz* spectral-power associations, characterized by the diagonal (within-frequency) associations in the θ-β (especially α) bands. **F.** *PO8* (a posterior site) to *Cz* spectral-power associations, characterized by the θ-lowγ bands at *PO8* associated with the α band at *Cz*—α-column. Note that spectral-power associations from most posterior sites to *Cz* are characterized by α-columns, that is, the θ-lowγ bands at most posterior sites were associated with the α band at *Cz* (see the posterior region of A and B). The color scale is shown at the top of part A.

**Cross-site spectral-power associations on the seconds timescale (across 500ms intervals)
from all sites to *AFz* (anterior)**

Figure 13. Cross-site spectral-power associations on the seconds timescale (across 500ms intervals) from all sites to *AFz* (a representative central site). A. 2D spectral-power association plots. Some associations are columnar, indicating multiple frequencies associated with a specific (primarily α) band, some are square, indicating broad associations among multiple frequencies, and some are diagonal, indicating within-frequency associations. **B.** Replotting of A. Each curve shows the spectral-power modulation at *AFz* associated with the probe-site power variation in each major frequency band (lower-to-higher frequency bands labeled with cooler-to-warmer colors), with the shaded regions indicating ±1 standard error of the mean (with participants as the random effect). In other words, each curve shows a horizontal slice of a 2D-association plot for a specific probe-site frequency band (see the rectangular boxes in the bottom panels). **C-F.** Representative associations. **C.** *AF3* (an adjacent anterior site) to *AFz* spectral-power associations, characterized by the diagonal (within-frequency) associations (especially in the α band) as well as the broad associations among the highβ-γ bands. **D.** *T7* (lateral) to *AFz* spectral-power associations, characterized by the diagonal (within-frequency) associations (especially in the α band) as well as the broad associations among the highβ-γ bands (as in C, but weaker). **E.** *Cz* (a central site) to *AFz* spectral-power associations, characterized by the α band at *Cz* associated with the α band at *AFz*. **F.** *P8* (a posterior site) to *AFz* spectral-power associations, characterized by the θ-lowγ bands at *P8* associated with the α band at *AFz*—α-column. Note that spectral-power associations from most posterior sites to *AFz* are characterized by α-columns, that is, the θ-lowγ bands at most posterior sites were associated with the α band at *AFz* (see the posterior region of A and B). The color scale is shown at the top of part A.

Cross-site spectral-power associations on the seconds timescale (across 500ms intervals) from all sites to *T7* (left lateral) and *T8* (right lateral)

Figure 14. Cross-site spectral-power associations on the seconds timescale (across 500ms intervals) from all sites to *T7* (a representative left lateral site) and *T8* (a representative right lateral site). A, H. 2D spectral-power association plots for *T7* and *T8*. Some associations are columnar, indicating multiple frequencies associated with a specific (primarily α) band, some are square, indicating broad associations among multiple frequencies, and some are diagonal, indicating within-frequency associations. **B, I.** Replotting of A. Each curve shows the spectral-power modulation at *T7* or *T8* associated with the probe-site power variation in each major frequency band (lower-to-higher frequency bands labeled with cooler-to-warmer colors), with the shaded regions indicating ±1 standard error of the mean (with participants as the random effect). In other words, each curve shows a horizontal slice of a 2D-association plot for a specific probe-site frequency band (see the rectangular boxes in the bottom panels). **C-G, J-N.** Representative associations for *T7* and *T8*. Note the bilateral symmetry. **C, N.** *AF7*/*AF8* (ipsilateral anterior sites) to *T7*/*T8* spectral-power associations, characterized by the diagonal (within-frequency) associations (especially in the α band) as well as the broad associations among the highβ-γ bands. **D, M.** *FT7*/*FT8* (adjacent sites) to *T7*/*T8* spectral-power associations, characterized by the diagonal (within-frequency) associations (especially in the α band) as well as the broad associations among the highβ-γ bands (similar to C, N, but stronger). **E, L.** *PO3*/*PO4* (posterior sites) to *T7*/*T8* spectral-power associations, characterized by the θ-lowγ band at *PO3*/*PO4* associated with the α band at *T7*/*T8*—α-column. **F, K.** *FCz* (a central site) to *T7*/*T8* spectral-power associations, characterized by the α band at *FCz* associated with the α-band at *T7*/*T8*. **G, J.** *TF8*/*TF7* (contralateral sites) to *T7*/*T8* associations, characterized by the α band at *TF8*/*TF7* associated with the α band at *T7*/*T8* as well as the broad associations among the highβ-γ bands. Note that spectral-power associations from most posterior sites to *T7*/*T8* are characterized by α-columns, that is, the θ-lowγ bands at most posterior sites were associated with the α band at *T7*/*T8* (see the posterior region of A,B and H,I). The color scale is shown at the top of part A.

In summary, the (slower) seconds-timescale (across 500ms intervals) cross-site (long-distance) spectral-power associations are characterized by the α-band to α-band associations prevalent across most site pairs (Figures 11-14), within-frequency (diagonal) associations from proximate sites (Figures 11-14), broad highβ-γ-band associations involving lateral and anterior targets (Figures 13, 14), and notably by the θ-lowγ-band to α-band associations, α-columns, from posterior sites to other sites (Figures 12-14).

Discussion

Spectral power intrinsically fluctuated on at least two distinct timescales, the sub-second timescale (within a 500ms interval) with the low and high states typically lasting ~230ms, and the seconds timescale (across 500ms intervals) with the low and high states typically lasting ~3.75s (Figure 2). Distinct local and long-distance patterns of intrinsic spectral-power associations were observed on these timescales characterized by region—anterior, lateral, central, versus posterior—and spatial scale—within versus across EEG-derived current sources. While future research is necessary to understand the functional implications of these intrinsic association patterns on perceptual, attentional and cognitive processes, we consider some straightforward interpretations.

Overall, the results suggest that the (fast) sub-second-timescale coordination of spectral power is limited to local amplitude modulation and insulated within-frequency long-distance interactions, while the characteristic columnar patterns of cross-frequency interactions emerge on the (slower) seconds timescale.

In particular, the consistent sub-second associations of the β-γ frequencies at Δf~10Hz at posterior sites suggest that the β-γ oscillations, implicated in a variety of attentional and cognitive processes (e.g., Fries, 2005; Palva & Palva, 2007; Duzel et al., 2010; Engel & Fries, 2010; Donner & Siegel, 2011; Klimesch, 2012; Michalareas et al., 2016), are amplitude modulated at ~10Hz in the occipital region. In general, the detection of consistent co-occurrences of f_1 Hz and f_2 Hz oscillations at a single source implies the presence of a $(f_1+f_2)/2$ Hz oscillation being amplitude-modulated at $|f_2-f_1|$ Hz. Thus, the consistent co-occurrences of the β-γ oscillations at Δf~10Hz at posterior sites suggest that the β-γ oscillations are organized into ~10Hz amplitude-modulated packets in the occipital region. If so, it is reasonable to expect a phase-power coupling where the ~10Hz amplitude-modulated power of the β-γ oscillations interacts with the phase of the α (~10Hz) oscillations in the occipital region.

Indeed, a human MEG study reported that the γ (30-70Hz) power variations were phase-coupled to the α (8-13Hz) oscillations primarily in the occipital area during rest with the eyes closed (Osipova et al., 2008). A monkey unit-recording study also reported that the γ (30-200Hz) power variations were phase-coupled to the α (7-14Hz) oscillations in V1 during rest (Spaak et al., 2012). Nevertheless, we found consistent Δf~10Hz associations for the β as well as γ power (e.g., Figure 3A). A possible reason why the prior studies did not find evidence of phase-coupling of the β power variations to the α oscillations is that any α-band amplitude-modulation of the β power, which we have inferred based on the consistent co-occurrences of β-frequency oscillations at Δf~10Hz, would have been difficult to directly observe because of the closeness of the α and β frequencies; for example, a conventional Morlet-wavelet tuned to extract β power would not have sufficient

temporal resolution to reveal its amplitude-modulation at α frequencies. Nevertheless, these prior results are consistent with the interpretation that the posterior α oscillations may play a role in organizing the β-γ oscillations into α-band amplitude-modulated (AM) packets. This implies that the α power may covary with the β-γ power in the posterior region because extensively synchronized (high power) α oscillations may be required to organize extensively synchronized (high power) β-γ oscillations into α-band AM packets.

We did not find this association on the sub-second timescale, but that may not be surprising. The fact that the β-γ associations were confined along the 45° lines at Δf~10Hz suggests that the α-band AM packets were generated relatively independently for different β-γ frequency pairs; otherwise, the spectral power across the β-γ frequencies would have been broadly associated. This means that the α-band AM packets for different frequency pairs were temporally dispersed. Therefore, even if the α oscillations played a role in organizing the β-γ oscillations into α-band AM packets, the α power would not necessarily fluctuate with the β-γ power on the sub-second timescale. For example, within any given sub-second interval, the α power would have likely been consistently high when the β-γ oscillations (to be organized into α-band AM packets) were broadly elevated and consistently low when the β-γ oscillations were broadly reduced. This reasoning predicts that the associations between the α power and the β-γ power should be observed on a longer timescale. Indeed, on the seconds timescale, posterior sites yielded vertical columns at the α band—α-columns, indicating that the β-lowγ power covaried with the α power over the slower timescale. Thus, the Δf~10Hz characteristic of the sub-second-timescale associations and the α-column characteristic of the seconds-timescale associations at posterior sites are together consistent with the interpretation that the occipital α oscillations may play a role in organizing the β-γ oscillations into α-band AM packets.

This interpretation raises the possibility that the posterior processes mediated by the β-γ oscillations may be transmitted to other regions as α-band AM packets. If so, the posterior β-γ oscillations may generate α oscillations at the receiving neural populations through non-linear interactions involving rectification. Examples of such rectifying interactions have been seen as binocular beats (e.g., Baitch & Levi, 1989), heard as binaural beats (e.g., Licklider et al., 1950), and observed in visual and auditory evoked EEG potentials (e.g., Baitch & Levi, 1988; Pratt et al., 2009). Thus, the β-γ power variations organized into α-band AM packets at posterior sites may be associated with the α power at other sites. Our results support this prediction. The cross-site spectral-power associations from posterior sites to other sites were consistently characterized by α-columns (e.g., Figure 10A-D; also see the posterior region of Figures 11-14), indicating that the θ-lowγ power (including the β-γ power) variations at posterior sites selectively coincided with the α power modulation at other sites on

the seconds timescale. The fact that these associations were columnar rather than square-shaped (which would have indicated broad associations across the β-γ frequencies) is consistent with the above interpretation that different β-γ frequencies in the posterior region are relatively independently organized into α-band AM packets. Thus, the occipital operations involving the β-γ oscillations may be frequency-wise organized into α-band AM packets to coordinate their interactions with other regions.

Recent studies have shown that visual perception, awareness, and/or attention may oscillate in the α rhythm (e.g., VanRullen et al., 2005; Mathewson et al., 2011). For example, stimulus visibility has been shown to correlate with the specific phase of the posterior EEG α oscillations (e.g., Mathewson et al., 2010, but see Busch & VanRullen, 2010). It has also been proposed that the α-band modulation of early visual representations carried by the γ-band oscillations may play a role in temporally prioritizing their downstream processing according to their strengths (e.g., Jensen et al., 2014). The current results corroborate these findings/ideas by providing evidence suggesting that the occipital α oscillations play a role in organizing the intrinsic (at rest with the eyes closed) β-γ oscillations into α-band AM packets to communicate with other regions.

We have also obtained some evidence of ~3Hz (δ-band) amplitude modulation of the θ-α-frequency oscillations at posterior sites (e.g., Figure 3A) and ~16Hz (β-band) amplitude modulation of the γ-frequency (40-55Hz) oscillations at lateral sites (e.g., Figure 3B). However, the current results do not provide a coherent interpretation for these cases of potential phase-power coupling as to how they may be related to the local and long-distance cross-frequency associations on the longer (seconds) timescale. Explanations are also required as to why the (fast) sub-second-timescale cross-site (long-distance) diagonal associations were dominated by the α (8-15hz), β-γ (>30Hz), or a combination of the α and β-γ frequencies, but never dominated by the β (15-30Hz) frequencies (e.g., Figure 5; also see Figures 6-9). Given that diagonal associations indicate insulated within-frequency interactions (i.e., independent interactions for different frequencies), the fast, long-distance diagonal associations may reflect feedforward (dominated by frequencies above ~40Hz; Michalareas et al., 2016) and feedback (dominated by 5-20Hz while peaking at ~10Hz; Michalareas et al., 2016) interactions. Note that, although our participants rested with their eyes closed, they continuously received and processed environmental sensory stimuli. The fact that the fast diagonal long-distance associations to *Cz* (a representative central site) were never dominated by the β-γ frequencies (Figures 7) may potentially suggest that central sites do not strongly engage in feedforward interactions while people rest with their eyes closed.

The cross-site associations generally diminished with distance. However, there were cases where strong associations persisted between distant sites (with weaker associations at intermediate distances). Those "super" long-distance associations were typically α-band to α-band on both the sub-second and seconds

timescales, but there were some exceptions, including the fast within-frequency β-γ associations from lateral sites, *T7*/*T8*, to the lower posterior site, *Oz*, and vice versa, on the sub-second timescale (e.g., Figure 6C; Figure 9F, 9K), and the slower broad β-γ associations from distant contralateral sites such as *TF8*/*TF7* to lateral sites, *T7*/*T8*, on the seconds timescale (e.g., Figure 14G, 4J; also see 14A-B and 14H-I). The former may be relevant to hierarchical visual processing occurring on the (fast) sub-second timescale whereas the latter may be relevant to cross-hemisphere coordination occurring on the (slower) seconds timescale.

Finally, the distinct patterns of intrinsic spectral-power associations characterized by the parallel-to-diagonal, diagonal, columnar, and square associations may provide a useful reference for understanding how intrinsic global dynamics adjust to sensory dynamics and behavioral demands. For example, we obtained some preliminary results suggesting that, while people watch a silent nature video, the intrinsic posterior associations of the β-γ power at Δf~10Hz on the sub-second timescale (obtained while participants rested with their eyes closed) strengthen but Δf shifts to the lower-α/upper-θ frequencies (leaving the lateral Δf~16Hz associations for the γ frequencies unchanged), while the α-column associations from posterior sites to other sites on the seconds timescale disappear (Menceloglu, Grabowecky, & Suzuki, unpublished data). While these preliminary results suggest that the intrinsic patterns of spectral-power associations undergo characteristic adjustments from rest to free viewing, they need to be confirmed and the sources of the adjustments investigated, for example, by determining whether they are due to the eyes being open per se, the presence of visual stimulation, and/or the act of free viewing. Investigating such adjustments in relation to various sensory dynamics and behavioral demands may contribute to an understanding of how internal neural dynamics are optimized for interacting with environmental dynamics.

In summary, we examined the global distribution of spectral-power associations, focusing on both the local characteristics reflected in the cross-frequency associations within individual EEG-derived current sources (sites) and the long-distance characteristics reflected in the cross-frequency associations between sites. Distinct association patterns emerged on the (fast) sub-second and (slower) seconds timescales, suggesting that the fast coordination of spectral power appears to be limited to local amplitude modulation and insulated within-frequency long-distance interactions (dominated by the α and γ bands, likely reflecting feedforward and feedback processes), while the characteristic columnar patterns of cross-frequency interactions emerge on the slower timescale. While the functional significance of these spectral-power associations awaits future research, the associations within the posterior region and its associations with other regions suggest that the intrinsic occipital dynamics are structured in such a way that the β-γ oscillations are organized into α-band (~10Hz) amplitude-modulated packets to interact with other regions.

References

Adebimpe, A., Arabi, A., Bourel-Ponchel, E., Mahmoudzadeh, M., & Wallois, F. (2016). EEG resting state functional connectivity analysis in children with benign epilepsy with centrotemporal spikes. *Frontiers in Neuroscience, 10, Article 143*, 1-9.

Antonakakis, M., Dimitriadis, S. I., Zervakis, M., Micheloyannis, S., Resaie, R., Babajani-Feremi, A., Zouridakis, G., & Papanicolaou, A. C. (2016). Altered cross-frequency coupling in resting-state MEG after mild traumatic brain injury. *International Journal of Psychophysiology, 102*, 1-11.

Baitch, L. W. & Levi, D. (1988). Evidence for nonlinear binocular interactions in human visual cortex. *Vision Research, 28(10)*, 1139-1143.

Baitch, L. W. & Levi, D. (1989). Binocular beats: psychophysical studies of binocular interaction in normal and stereoblind humans. *Vision Research, 29(1)*, 27-35.

Bonnefond, M, & Jensen, O. (2015). Gamma activity coupled to alpha phase as a mechanism for top-down controlled gating. *PLoS ONE, 10(6)*: e0128667, 1-11.

Busch, N. A., & VanRullen, R. (2010). Spontaneous EEG oscillations reveal periodic sampling of visual attention. *Proceedings of the National Academy of Sciences, 107(37)*, 16048-16053.

Buzsaki, G. (2006). *Rhythms of the Brain*, Oxford University Press.

Cohen, M. X. (2014). *Analyzing Neural Time Series Data: Theory and Practice*, MIT Press.

Collyer, C. E., Broadbent, H. E., & Church, R. M. (1994). Preferred rates of repetitive tapping and categorical time production. *Perception & Psychophysics, 55(4)*, 443-453.

Dehaene, S., & Changeux, J.-P. (2011). Experimental and theoretical approaches to conscious processing. *Neuron, 70*, 200-227.

Delorme, A., & Makeig, S. (2004). EEGLAB: an open source toolbox for analysis of single-trial EEG dynamics including independent component analysis. *Journal of neuroscience methods*, *134*(1), 9-21.

Donner, T. H., & Siegel, M. (2011). A framework for local cortical oscillation patterns. *Trends in Cognitive Sciences, 15(5)*, 191-199.

Duzel, E., Penny, W. D., & Burgess, N. (2010). Brain oscillations and memory. *Current Opinion in Neurobiology, 20*, 143-149.

Engel, A. K., & Fries, P. (2010). Beta-band oscillations—signaling the status quo? *Current Opinion in Neurobiology, 20*, 156-165.

Fahrenfort, J. J., Scholte, H. S., & Lamme, V. A. (2007). Masking disrupts reentrant processing in human visual cortex. *Journal of cognitive neuroscience*, *19*(9), 1488-1497.

Fries, P. (2005). A mechanism for cognitive dynamics: neural communication through neural coherence. *Trends in Cognitive Sciences, 9(10)*, 474-480.

Gonzalez, G. F., Simt, D. J. A., van der Molen, M. J. W., Tijms, J., Stam, C. J., de Geus, E. J. C., & van der Molen, M. W. (2018). EEG resting state functional connectivity in adult dyslexics using phase lag index and graph analysis. *Frontiers in Human Neuroscience, 12, Article 341*, 1-12.

He, B. J. (2014). Scale-free brain activity: past, present, and future. *Trends in Cognitive Sciences, 18(9)*, 480-487.

Hess R. F. & Snowden R. J., (1992) Temporal properties of human visual filters: Number, shapes and spatial covariance, *Vision Research, 32*, 47-60.

Hipp, J. F., Hawellek, D. J., Corbetta, M., Siegel, M., & Engel, A. K. (2012). Large-scale cortical correlation structure of spontaneous oscillatory activity. *Nature Neuroscience, 15(6)*, 884-890.

Hjorth, B. (1980). Source derivation simplifies topographical EEG interpretation. *American Journal of EEG Technology 20*, 121-132.

Jensen, O., Gips, B., Bergmann, T. O., & Bonnefond, M. (2014). Temporal coding organized by coupled alpha and gamma oscillations prioritize visual processing. *Trends in Neurosciences, 37(7)*, 357-369.

Kayser, J., Tenke, C. E. (2006). Principal components analysis of Laplacian waveforms as a generic method for identifying ERP generator patterns: I. Evaluation with auditory oddball tasks. *Clinical Neurophysiology, 117*, 348-368.

Kiya, H., Ito, I., & Miron, S. (2010). "Phase scrambling for image matching in the scrambled domain" in Signal Processing, *InTech*, 97-414.

Klimesch, W. (2012). Alpha-band oscillations, attention, and controlled access to stored information. *Trends in Cognitive Sciences, 16(12)*, 606-617.

Koch, C. (1999). *Biophysics of Computation: Information Processing in Single Neurons*. Oxford.

Lamme, V. A., Zipser, K., & Spekreijse, H. (2002). Masking interrupts figure-ground signals in V1. *Journal of cognitive neuroscience*, *14*(7), 1044-1053.

Licklider, J. C., Webster, J. C., & Hedlun, J. M. (1950). On the frequency limits of binaural beats. *Journal of the Acoustical Society of America, 22*, 468-473.

Lopez-Calderon, J., & Luck, S. J. (2014). ERPLAB: an open-source toolbox for the analysis of event-related potentials. *Frontiers in human neuroscience*, *8*, 213.

Lui, L. L., Bourne, J. A., Rosa, M. G. P. (2007). Spatial and temporal frequency selectivity of neurons in the middle temporal visual area of new world monkeys (Callithrix jacchus). *European Journal of Neuroscience, 25*, 1780-1792.

Mathewson, K. E., Gratton, G., Fabiani, M., Beck, D. M., & Ro, T. (2010). To see or not to see: prestimulus alpha phase predicts visual awareness. *Journal of Neuroscience, 29*, 2725-2732.

Mathewson, K. E., Lleras, A., Beck, D. M., Fabiani, M., Ro, T., Gratton, G. (2011). Pulsed out of awareness. EEG alpha oscillations represent a pulsed-inhibition of ongoing cortical processing. *Frontiers in Psychology, 2, A99*, 1-15.

Mazzoni, A., Panzeri, S., Logothetis, N. K., & Brunel, N. (2008). Encoding of naturalistic stimuli by local field potential spectra in networks of excitatory and inhibitory neurons. *PLoS Computational Biology, 4(12)*: e1000239. doi:10.1371/journal.pcbi.1000239.

Michalareas, G., Vezoli, J., van Pelt, S., Schoffelen, J.-M., Kennedy, H., & Fries, P. (2016). Alpha-beta and gamma rhythms subserve feedback and feedforward influences among human visual cortical areas. *Neuron, 89*, 384-397.

Müller, V., Perdikis, D., Oertzen, T., Sleimen-Malkoun, R, Jirsa, V., & Lindenberger, U. (2016). Structure and topology dynamics of hyper-frequency networks during rest and auditory oddball performance. *Frontiers in Computational Neuroscience, 10, Article 108*, 1-25.

Osipova, D., Hermes, D., & Jensen, O. (2008). Gamma-power is phase-locked to posterior alpha activity. *PLoS ONE, 3(12), e3990*, 1-7.

Palva, S., & Palva, M. (2007). New vistas for a-frequency band oscillations. *Trends in Neurosciences, 30(4)*, 150-158.

Palva, S., & Palva, J. M. (2012). Discovering oscillatory interaction networks with M/EEG: challenges and breakthroughs. *Trends in Cognitive Sciences, 16(4)*, 219-230.

Palva, J. M., Palva, S., & Kaila, K. (2005). Phase synchrony among neuronal oscillations in the human cortex. *Journal of Neuroscience, 25(15)*, 3962-3972.

Pachi, A., & Ji, T. (2005). Frequency and velocity of people walking. *Structural Engineering, 83(3)*, 36-40.

Pelz, J. B., & Rothkopf, C. (2007). Oculomotor behavior in natural and man-made environments. In van Gompel, R., Fischer, M., Murray, W., & Hill, R. (Eds.), Eye Movements: a window on Mind and Brain (first., pp. 661–676). Amsterdam: Elsevier.

Perrin, F., Pernier, J., Bertrand, O., & Echallier, J. F. (1989a). Corrigenda EEG 02274. *Electroencephalography and Clinical Neurophysiology 76*, 565.

Perrin, F., Pernier, J., Bertrand, O., & Echallier, J. F. (1989b). Spherical Splines for Scalp Potential and Current Density Mapping. *Electroencephalography and Clinical Neurophysiology 72(2)*: 184-187.

Perrin, F., Pernier, J., Bertrand, O., Giard, M. H., & Echallier, J. F. (1987). Mapping of Scalp Potentials by Surface Spline Interpolation. *Electroencephalography and Clinical Neurophysiology, 66 (1)*, 75-81.

Pratt, H., Starr, A., Michalewski, H. J., Dimitrijevic, A., Bleich, N., & Mittleman, N. (2009). Cortical evoked potentials to an auditory illusion: binaural beats. *Clinical Neurophysiology, 120(8)*, 1514-1524.

Scally, B., Burke, M. R., Bunce, D., & Delvenne, J.-F. (2018). Resting-state EEG power and connectivity are associated with alpha peak frequency slowing in healthy aging. *Neurology of Aging, 71*, 149-155.

Spaak, E., Bonnefond, M., Maier, A., Leopold, D. A., & Jensen, O. (2012). Layer-specific entrainment of gamma-band neural activity by the alpha rhythm in monkey visual cortex. *Current Biology, 22(24)*, 2313–2318.

Tenke, C. E., & Kayser, J. (2012). Generator localization by current source density (CSD): Implications of volume conduction and field closure at intracranial and scalp resolutions. *Clinical Neurophysiology, 123*, 2328–2345.

VanRullen, R., Reddy, L., & Koch, C. (2005). Attention-driven discrete sampling of motion perception. Proceedings of the National Academy of Sciences, 102(14), 5291-5296.

Voytek, B., Canolty, R. T., Shestyuk, A., Crone, N. E., Parvizi, J., & Knight, R. T. (2010). Shifts in gamma phase-amplitude coupling frequency theta to alpha over posterior cortex during visual tasks. Frontiers in Human Neuroscience, 4, A191, 1-9.

Supplementary figures

Figure S1. Inter-participant consistency of the within-site spectral-power associations on the sub-second and seconds timescales.

Figure S2. Inter-participant consistency of the cross-site spectral-power associations on the sub-second timescale (within a 500ms interval) from all sites to representative posterior (*Oz*), central (*Cz*), anterior (*AFz*), and lateral (*T7/T8*) sites.

Figure S3. Inter-participant consistency of the cross-site spectral-power associations on the seconds timescale (across 500ms intervals) from all sites to representative posterior (*Oz*), central (*Cz*), anterior (*AFz*), and lateral (*T7/T8*) sites.

Inter-participant consistency of the within-site spectral-power associations on the sub-second and seconds timescales for all sites

Figure S1. Inter-participant consistency of the within-site spectral-power associations on the sub-second and seconds timescales. A-C. The sub-second-timescale (within a 500ms interval) spectral-power associations for all sites, averaged across odd-numbered participants (**A**), averaged across all participants (**B**, identical to Figure 3D), and averaged across even-numbered participants (**C**). **D-F.** The seconds-timescale (across 500ms intervals) spectral-power associations for all sites, averaged across odd-numbered participants (**D**), averaged across all participants (**E**, identical to Figure 4D), and averaged across even-numbered participants (**F**). Note that both the even and odd numbered participants show the characteristic spectral-power association patterns in the posterior and lateral regions and the relative lack of spectral-power associations in the anterior region on both the sub-seconds (A-C) and seconds (D-F) timescales.

Inter-participant consistency of the cross-site spectral-power associations on the sub-second timescale (within a 500ms interval) from all sites to representative posterior (*Oz*), central (*Cz*), anterior (*AFz*), and lateral (*T7* and *T8*) sites

Figure S2. Inter-participant consistency of the cross-site spectral-power associations on the sub-second timescale (within a 500ms interval) from all sites to representative posterior (*Oz*), A-C, central (*Cz*), D-F, anterior (*AFz*), G-I, and lateral (*T7*/*T8*), J-L/M-O, sites. The data are averaged across all participants in the middle column (identical to Figures 6A, 7A, 8A, 9A, and 9H), averaged across the even-numbered participants in the left column, and averaged across the odd-numbered participants in the right column. Note that both the even and odd numbered participants show the characteristic patterns of diagonal (within-frequency) associations discussed in the main text.

Inter-participant consistency of the cross-site spectral-power associations on the seconds timescale (across 500ms intervals) from all sites to representative posterior (*Oz*), central (*Cz*), anterior (*AFz*), and lateral (*T7* and *T8*) sites

Figure S3. Inter-participant consistency of the cross-site spectral-power associations on the seconds timescale (across 500ms intervals) from all sites to representative posterior (*Oz*), A-C, central (*Cz*), D-F, anterior (*AFz*), G-I, and lateral (*T7/T8*), J-L/M-O, sites. The data are averaged across all participants in the middle column (identical to Figures 11A, 12A, 13A, 14A, and 14H), averaged across the even-numbered participants in the left column, and averaged across the odd-numbered participants in the right column. Note that both the even and odd numbered participants show the characteristic α-columns (the θ-lowγ-band to α-band) associations from posterior to other sites, the broad associations among the β-γ bands particularly involving the lateral and anterior targets, and the prevalent α to α associations discussed in the main text.