Low frequency traveling waves in the human cortex coordinate neural activity across spatial scales

Running title: Multi-scale human cortical traveling waves

Vishnu Sreekumar[1], John H. Wittig Jr.[1], Sara K. Inati[2], and Kareem A. Zaghloul[1] [†]

[1] Surgical Neurology Branch, NINDS, National Institutes of Health, Bethesda, MD 20892, USA

[2] Office of the Clinical Director, NINDS, National Institutes of Health, Bethesda, MD 20892, USA

Draft Date: March 4, 2020
Number of Figures: 5
Number of Supplemental Figures: 5
Number of Supplemental Videos: 2

Number of words (approximate):
  Abstract 150 words
  Introduction 840 words
  Discussion 1263 words

Author Contributions: VS: Conceptualization, Methodology, Validation, Formal Analysis, Writing - Original Draft, Visualization. JHW: Data Curation, Resources, Writing - Review & Editing. SKI: Investigation, Resources. KAZ: Conceptualization, Writing - Review & Editing, Supervision, Project administration.

Acknowledgements: This work was supported by the Intramural Research Program of the National Institute for Neurological Disorders and Stroke. We are indebted to all patients who have selflessly volunteered their time to participate in this study. This work utilized the computational resources of the NIH HPC Biowulf cluster (http://hpc.nih.gov) and we thank Chris Zawora for help with running the analysis code on the supercomputer. We thank Alex Vaz, Julio Chapeton, and Zane Xie for helpful comments on the manuscript.

The authors declare no competing financial interests.

[†]**Correspondence should be addressed to:**
Kareem A. Zaghloul
Surgical Neurology Branch, NINDS, National Institutes of Health Building 10, Room 3D20
10 Center Drive Bethesda, MD 20892-1414
Office: (301) 496-2921
Email: kareem.zaghloul@nih.gov

Abstract

Traveling waves of oscillatory activity are thought to influence neuronal spiking, providing a spatiotemporal framework for neural communication. However, no direct link has been established between traveling waves and single unit spiking in humans. We examined traveling waves in the human lateral temporal lobe by using recordings from intracranial electrodes implanted in twenty participants for seizure monitoring as they performed a paired-associates verbal memory task. We observed ubiquitous low frequency traveling waves across the temporal lobe. Long-range alpha waves were more likely to occur during word pairs that were subsequently remembered relative to those that were not. In a subset of participants with microelectrode recordings, macro-scale waves co-occurred with micro-scale waves, which in turn were temporally locked to single unit spiking. This temporal coordination between traveling waves at different spatial scales and between waves and neuronal spiking in the human brain suggests a role for traveling waves in neural communication.

Keywords: traveling waves, single unit spiking, neuronal communication, coherence, human cortex

Introduction

Brains are complex dynamical systems that enable us to sense, perceive, and generate meanings in a changing world. Both spontaneous and stimulus-driven brain activity show signatures of flexible transitions between different metastable states (Roberts et al., 2019). One such important state is organized as traveling plane waves of neural activity at both mesoscopic (local/single-area, ~ 1 millimeter) and macroscopic (global, extending over several centimeters) scales (Muller et al., 2018). Traveling waves in the brain have been reported extensively in several species, including rabbit, cat, dog, monkey, and turtle (Ermentrout and Kleinfeld, 2001), and have been shown to be functionally relevant, especially in the domains of vision and motor behavior (Rubino et al., 2006; Zanos et al., 2015). Evidence for macroscopic traveling waves in the human brain has primarily come from electroencephalography (EEG) recordings but confounds due to volume conduction have made it difficult to interpret the results (Muller et al., 2018). More recently, intracranial EEG (iEEG) recordings from human clinical patients have revealed macroscopic traveling waves of low frequency oscillatory activity (Muller et al., 2016; Zhang et al., 2018).

Information processing within this complex multi-scale system is thought to rely on coordinated interactions between neuronal populations both within small brain regions and across larger spatial scales. Phase synchronization between participating groups of neurons has been proposed to be the specific mechanism underlying such interactions (Varela et al., 2001). Traditionally, the focus of such analyses has been on a precise temporal alignment of oscillatory activity across brain regions, but based on recent studies, it appears that phase offsets organized systematically in space are a common feature of both cortical and subcortical neural activity. These propagating spatiotemporal patterns include traveling plane waves (Zhang et al., 2018), spiral waves (Muller et al., 2016), and other complex waves (Rubino et al., 2006; Townsend et al., 2015). A cortical repertoire of such time-lagged phase synchrony patterns may provide a more flexible mechanism for functional interactions between neural populations, and recent evidence has demonstrated that these patterns can transiently appear over durations of as little as tens to hundreds of milliseconds. For example, visual information processing induces "perceptual echoes" in the form of posterior-anterior alpha traveling waves that recur periodically across cycles once every ~ 100 ms (Lozano-Soldevilla and VanRullen, 2019). Similarly, spontaneous cortical activity measured using resting-state MEG transiently organizes into phase-coupled networks, and these transient states are visited repeatedly with the dwell times in each state lasting an average of 50 to 100 ms (Vidaurre et al., 2018).

In addition to providing a framework for time-lagged phase synchronization, traveling waves may also play an active role in information processing by influencing the probability of neuronal firing. In this manner, traveling waves could coordinate spiking activity between brain regions in space and time (Wu et al., 2008). Studies have suggested such a link between traveling waves and neuronal activity at smaller scales (mesoscopic and single unit levels) by using high frequency activity at the macro-scale as a proxy for spiking (Bahramisharif et al., 2013). In addition, previous evidence has explicitly demonstrated human single unit spiking activity locked to the phase of theta and delta oscillations (Jacobs et al., 2007; Rutishauser et al., 2010), raising the possibility that traveling waves within these frequencies may coordinate spiking activity. However, there is currently no direct evidence for such a coordinating role of traveling waves across spatial scales all the way down to single-unit spiking activity in humans.

Here, we investigated how traveling waves are orchestrated across spatial scales (the macro-scale ones covering several centimeters of the lateral temporal lobe and the micro-scale ones covering a smaller extent of ~ 4 mm) in the human brain by examining concurrent iEEG and microelectrode (MEA) recordings from the human temporal cortex. We detected traveling plane waves at both spatial scales using optical flow, which estimates motion (instantaneous velocities) from sequences of images which in our case were instantaneous phase maps of neural activity in theta and alpha frequency bands. At the macro-scale, we found traveling waves with speeds and directions consistent with previous reports (Zhang et al., 2018) and with durations that lasted anywhere between tens of milliseconds to a few hundred milliseconds depending on the extent of cortical space covered by the waves. Furthermore, participants in our study performed a long-term associative memory task and we found that long-range macro-scale alpha traveling waves were linked to successful memory encoding and retrieval. We also identified micro-scale traveling waves in the MEA recordings captured from the human middle temporal gyrus, and obtained direct evidence that low frequency micro-scale traveling waves, especially in the alpha band, and single unit spiking activity are tightly coupled. Macro-scale wave times were correlated with both micro-scale wave times and spike times. Taken together, these results establish a link between macro-scale traveling waves, micro-scale traveling waves, and single-unit spiking activity in the human brain, suggesting that traveling waves may play a role in information processing in the brain by coordinating spiking activity both across different brain regions and within local patches of the cortex.

Results

Macro-scale traveling waves

We investigated macro-scale cortical traveling waves in twenty participants with drug-resistant epilepsy who underwent surgery for placement of intracranial electrodes for seizure monitoring (intracranial EEG, iEEG; Fig. 1A). We examined traveling waves while participants were attentive and repeatedly engaged in the same behavior in order to explore the potential role of traveling waves in human cognition. We therefore restricted our analyses to data that had been collected while participants performed a verbal paired-associates memory task that required similar cognitive processing during every trial of the task rather than analyze data from random times during the day (Fig. 1B).

We used an algorithm based on optic flow to determine epochs where activity in the theta (4-8 Hz) and alpha (8-16 Hz) bands propagated across the cortical surface as traveling plane waves (macro-scale traveling waves detected using iEEG electrode contacts; see Methods). To ensure that the algorithm is not biased in any direction due to asymmetry of the electrode arrangement, we limited our analysis only to electrodes arranged in a grid on the cortical surface and applied the detection algorithm separately to three overlapping 4×4 square subgrids overlying the lateral temporal lobe (Fig. 1C; see Methods). Once waves were detected separately on the anterior, middle, and posterior square subgrids, we identified waves that propagated in the same direction concurrently across the three subgrids, and designated these as long-range waves (~ 8 cm) that traveled across the full length of the 8×4 temporal lobe grid (Fig. 1C; Supplemental Movie S1). To demonstrate the lagged phase relationship that is typically observed during a traveling wave, we picked five electrodes along the direction of an exemplar traveling wave and plotted the filtered iEEG traces of those electrodes (Fig. 1D). Within an epoch identified by the algorithm as a traveling plane wave, there is a clear progressive phase lag between adjacent electrodes.

Figure 1 Detecting traveling waves at the macro- and micro-scale through iEEG and microelectrode array (MEA) recordings from the temporal lobe. (*A*) Locations of the 8×4 iEEG macro-electrode grid (red) and MEA (yellow) on the temporal lobe of an example participant. (*B*) During encoding, pairs of words are sequentially presented on the screen. Subsequently during retrieval, one word from each pair is randomly chosen and presented, and participants are instructed to vocalize the associated word. (*C*) The macro-electrode grid is divided as shown into three overlapping square grids. Traveling waves are detected separately on each square sub-grid. Traveling waves that are concurrently detected on all three sub-grids are combined to identify waves that travel the entire extent of the 8×4 grid. An example long-range traveling wave is shown below and in Supplemental Movie S1. (*D*) EEG waveforms (theta-band filtered) from five electrodes (indicated in *C*) that lie along the path of an example traveling wave. The gray highlight denotes the duration of this traveling wave and the red dots indicate sequentially arriving peaks of the EEG waveform at these five electrodes across two oscillation cycles. (*E*) A raster demonstrating the ubiquity of waves detected on the anterior square sub-grid in an example participant. Each of fifty trials is represented in each row, and the time points during which a traveling wave is detected on the sub-grid are indicated by horizontal lines. The red vertical dotted line indicates the time at which the word-pair appeared on the screen.

We confirmed that the detection algorithm only identifies traveling waves when there are true lagged phase relationships between multiple channels on the grid by comparing the detected traveling waves to those detected using surrogate iEEG data. We generated surrogate iEEG data by preserving autocorrelations in the true data but reducing cross-correlations between electrode channels by $26.6 \pm 0.6\%$ (Supplementary Fig. S1A,B; see Methods). We only partially distorted the cross-correlations in order to provide a more conservative test. In both the theta and alpha band, the true data exhibited a significantly greater number of traveling waves per second detected

on each subgrid than the surrogate data across participants (theta 6.1 ± 0.1 versus 5.2 ± 0.1 waves per second; $t(19) = 11.8$, $p = 3.4 \times 10^{-10}$; alpha 11.8 ± 0.1 versus 9.9 ± 0.2; $t(19) = 8.7$, $p = 5.2 \times 10^{-8}$; Supplementary Fig. S1C). Because instantaneous phases are only well defined when there is sufficient power in the frequency band of interest, we confirmed that the average estimate of instantaneous power across all electrodes in each subgrid was significantly greater during wave epochs compared to non-wave epochs (theta, $t(19) = 16.5, p = 9.7 \times 10^{-13}$; alpha, $t(19) = 26.1, p = 2.4 \times 10^{-16}$; Supplementary Fig. S1D). This difference in power is consistent with previous proposals that oscillations propagate as traveling waves (Zhang et al., 2018).

In each participant, we identified traveling waves during both encoding and retrieval trials of the experimental session. On each temporal lobe 4×4 subgrid, we found ubiquitous traveling waves that did not appear time locked to the onset of the word pairs (Fig. 1E, 50 encoding trials from an example participant). Because traveling waves occurred frequently in both the alpha and theta bands, we investigated whether the traveling waves we identified in one frequency band were related to those detected in the other. Across participants, we found that when we detected a theta traveling wave, we also detected an overlapping alpha wave $45.5 \pm 1.1\%$ of the time (Supplementary Fig. S1E). These data suggest that in some cases, the wave detection algorithm may be detecting the same phenomenon captured in both frequency bands due to overlap in the filters.

Across participants, we found that both theta and alpha traveling waves were more frequent on the anterior subgrid compared to the posterior subgrid (theta, 5.1 ± 0.2 versus 4.0 ± 0.1 waves per second; alpha, 11.2 ± 0.4 versus 9.4 ± 0.3 waves per second; $t(19) \geq 5.27$, $p \leq 4.35 \times 10^{-5}$). The higher rate of occurrence of alpha waves relative to theta waves is expected given the shorter duration of the alpha cycle. We also found that traveling waves detected on the anterior subgrid lasted slightly but consistently longer than those on the posterior subgrid in both frequency bands (theta: 57.7 ± 1.4 ms versus 52.1 ± 0.8 ms; alpha: 28.8 ± 0.6 ms versus 26.7 ± 0.5 ms; $t(19) \geq 3.90$, $p \leq .001$).

We examined the direction of the identified traveling waves and found that both theta and alpha traveling waves generally propagated from a posterior to anterior direction in any given local area of the temporal cortex (Rayleigh's test $p < 0.02$ for alpha and $p < 0.00013$ for theta in all participants and both anterior and posterior subgrids; Figs. 2A,B). Across participants, the distribution of wave directions was consistently and significantly non-uniform (length of mean resultant vector of all anterior temporal lobe (ATL) wave directions for theta $r = 0.22 \pm 0.03$; alpha $r = 0.18 \pm 0.03$; and of posterior temporal lobe (PTL) wave directions for theta $r = 0.12 \pm 0.02$; alpha $r = 0.12 \pm 0.01$; Hodges-Ajne test for non-uniformity within each participant, frequency band, and local area of the temporal lobe max $p = 6.9 \times 10^{-6}$). Traveling waves in the anterior subgrid were more directional than those in the posterior subgrid ($t(19) \geq 2.29$, $p \leq .035$).

Given prior reports of periodic traveling waves (Lozano-Soldevilla and VanRullen, 2019), we investigated whether macro-scale traveling waves were periodic. We examined the inter-wave intervals (IWIs) measured as the time between the beginning of one wave to the beginning of the next. In all participants, we found a similarly shaped distribution of IWIs for traveling waves in both theta and alpha frequency bands (Fig. 2C). However, the shapes of these IWI distributions closely resemble the IWI distributions that would arise assuming a Poisson process with a refractory period that is equal to the wave durations in our data (see Fig. S2A). Therefore, these IWI distributions

Figure 2 Macro-scale traveling waves on 4×4 macroelectrode subgrids. (*A*) The distribution of directions of macro-scale waves on the anterior temporal lobe in two example participants. (*B*) The preferred directions of traveling waves in the anterior temporal lobe (ATL) and posterior temporal lobe (PTL) across all 20 participants showing a posterior-anterior preference. (*C*) Inter-wave interval distributions for theta (blue) and alpha (red) waves in four example participants showing clear peaks. All participants show similar peaks. (*D*) The distribution of instantaneous phases collected over all 16 electrodes at the onset of a detected wave on the 4×4 ATL subgrid in three example participants. The phases take on all values, but show weak biases to certain phases in most participants as revealed through statistical tests (see Results). (*E*) The preferred phase at the onset of macro-scale waves across all participants who demonstrated a significant bias in the phase distribution ($n = 14/20$). (*F*) Distribution of directions of long-range cortical theta waves in two example participants showing a strong preference for the posterior-anterior direction.

suggest that macro-scale waves are not periodic.

Next, we wanted to ensure that the wave detection algorithm was able to detect propagation patterns (if they existed) at any phase of the oscillation cycle. Therefore, we examined the initial phase of each wave, accumulated over all electrodes of the subgrid. The distribution of these initial phases was weakly but significantly non-uniform ($p < 0.001$ for 14/20 participants in the theta band and 13/20 participants in the alpha band; Hodges-Ajne tests; Fig. 2D for three example participants). In most participants, the alpha waves preferred to begin with a peak in the alpha oscillation (Fig. 2E). Across participants, the mean resultant vector length of these initial phase distributions was 0.012 ± 0.002. However, because we found that all phases were well represented in these distributions, this analysis suggests that traveling waves can in fact initiate with any phase and confirms that the wave detection algorithm had no difficulty in detecting waves that begin with any phase.

Long-range traveling waves

While traveling waves detected on the iEEG subgrids were ubiquitous, less frequently, we observed waves that propagated over the full length of the temporal macro-scale electrode grid. We restricted our analysis to waves that lasted for a minimum of one cycle of theta and alpha bands (i.e., 167 ms corresponding to 6 Hz in the theta range, and 83 ms corresponding to 12 Hz in the alpha range). Though the overlap between alpha and theta band waves was around 45% on the smaller subgrids, there was only a 6% overlap between the long-range waves detected in the two frequency bands. These long-range traveling waves preferred the posterior-to-anterior direction over anterior-to-posterior in all but one participant (two example participants shown in Fig. 2F; Rayleigh's test of uniformity $p < 4.7 \times 10^{-6}$ and z-statistic > 12.2 in the alpha band across the 19 participants who showed this posterior-anterior preference and $p < 2.3 \times 10^{-5}$ and z-statistic > 10.7 in the theta band across all 20 participants). Across all participants, $74.8 \pm 2.8\%$ of the long-range alpha waves traveled in the posterior-anterior direction ($t(19) = 3.94, p = 0.0009$, paired t-test). We found similar results for theta waves, with $76.5 \pm 3.2\%$ of waves propagating in the posterior-anterior direction ($t(19) = 4.89, p = 0.0001$). Long-range posterior-anterior waves occurred at the rate of 0.20 ± 0.02 per second in the alpha band and 0.090 ± 0.007 in theta whereas the corresponding rates for anterior-posterior waves were 0.060 ± 0.007 and 0.030 ± 0.004 per second in the alpha and theta bands respectively. Long-range traveling waves that propagated in the posterior-anterior direction were significantly longer lasting than those traveling in the anterior-posterior direction in both frequency bands ($t(19) \geq 4.96$, $p \leq 8.6 \times 10^{-5}$ for all comparisons; theta: 209 ± 2 ms posterior-anterior waves versus 201 ± 2 ms anterior-posterior waves; alpha: 108 ± 1 ms posterior-anterior versus 103 ± 1 ms anterior-posterior waves; see Supplementary Fig. S2B for the full distributions of durations in six example participants). Alpha long-range waves propagated at 0.50 ± 0.02 m/s and theta long-range waves propagated at 0.29 ± 0.01 m/s.

We were interested in whether and how such waves of neural activity may be related to behavior. When we examined alpha long-range waves, we found patterns of activity that related to successful associative memory processing. We considered long-range traveling waves during two time periods while participants performed the paired associates task, a 0.5 s baseline period before the onset of the word-pair (at study) or cue word (at test) and a 4 s task period, ting 0.5 s after the onset of the word pair or cue (see Methods). We first considered all long-range traveling waves during the task periods regardless of direction and found that alpha waves were more likely during correct encoding ($20.9 \pm 1.6\%$) than incorrect encoding trials ($18.9 \pm 1.5\%$; $t(19) = 2.497, p = 0.020$). There was a 10.6% increase in the likelihood of occurrence of long-range alpha waves from incorrect to correct encoding trials. Conversely, retrieval trials were marked by an approximately 8.9% decrease in the likelihood of alpha long-range waves during correct compared to incorrect trials ($18 \pm 1.4\%$ vs $19.6 \pm 1.4\%$; $t(19) = -2.2, p = 0.04$). We did not find a significant difference in the likelihood of long-range theta band waves between correct and incorrect trials ($t(19) \leq 1.27$, $p \geq 0.22$). Next, restricting our analysis to just the posterior-to-anterior long-range waves, we also found these differences between correct and incorrect encoding trials in the alpha-band ($t(19) = 2.59, p = 0.02$ and a 13.2% increase in likelihood of finding a wave during correct encoding trials). During retrieval, there was no significant difference in the likelihood of occurrence of posterior-to-anterior alpha long-range waves between correct

and incorrect trials ($t(19) = -1.63, p = 0.12$). Together, these data suggest a consistent relationship between the presence of long-range alpha waves during encoding trials and associative memory performance.

Micro-scale traveling waves

We wanted to understand how the identified macro-scale traveling waves relate to spatiotemporal patterns of neural activity at a smaller spatial scale. In six participants, we had the opportunity to examine micro-scale traveling waves in the local field potentials captured by a grid of 10×10 micro-electrodes (microelectrode array, MEA; see Methods). Because each MEA is a symmetric grid of micro-electrodes, we directly applied the optic flow detection algorithm to data recorded on each MEA in order to identify micro-scale traveling waves without the concern that geometric asymmetry would bias our results (see Methods).

An example micro-scale wave traveling from an inferior-posterior to superior-anterior direction is shown in Fig.3A (and Supplemental Movie S2). We found fewer micro-scale traveling waves per second than the macro-scale waves detected using iEEG contacts (1.48 ± 0.45 theta waves per second across participants; 1.51 ± 0.72 alpha waves per second). The mean duration of theta micro-scale waves was 49 ± 2 ms and of alpha waves was 35 ± 2 ms (Supplementary Fig. S2C). Though less frequently, we did observe longer lasting waves on the order of 100 ms. The mean maximum duration across subjects was 303 ± 34 ms (theta) and 182 ± 25 ms (alpha). We found that both theta and alpha micro-scale traveling waves were slower than their larger macro-scale counterparts, propagating at 0.10 ± 0.05 ms (theta) and 0.18 ± 0.06 ms (alpha), but alpha band micro-scale waves were significantly faster than their theta band counterparts ($t(5) = 18.5, p = 8.43 \times 10^{-6}$). When we examined the IWIs between successive micro-scale waves in each participant, we found that the distribution of IWIs for the micro-scale alpha, but not theta, waves showed clear peaks in three of the six participants with MEA arrays (Fig. S2D; at 85, 115, and 125 ms respectively). Such peaks that are clearly separate from an exponential distribution cannot be reproduced by a Poisson-process assuming refractoriness as before, and therefore these IWI distributions suggest that alpha micro-scale waves may be periodic. Furthermore, signatures of this periodicity are also found when examining spiking activity locked to these alpha micro-scale waves, as we show in the next section.

Similar to their macro-scale counterparts, the micro-scale waves tended to propagate along a specific direction (Fig. 3B). For each participant, we found that the directions of both theta and alpha micro-wave traveling waves were significantly non-uniform (Hodge-Ajne omnibus test $p \leq 1.03 \times 10^{-20}$ for all tests; the mean resultant vector length of direction distributions $= 0.38\pm0.08$ for alpha and 0.32 ± 0.05 for theta micro-scale waves). The directions of propagation of the micro-scale waves, however, were not strictly aligned with the directions of the macro-scale waves (Fig.3A). Together with the lower rate of occurrence and the slower velocity of waves observed at the micro-scale compared to the macro-scale, these data raise the possibility that the waves detected at the micro-scale are not the same waves detected at the macro-scale.

Figure 3 Micro-scale traveling waves. (*A*) An example of a micro-scale alpha traveling wave captured at three different time points on a 96-channel microelectrode array (MEA). Supplemental Movie S2 shows the full wave. (*B*) The distribution of directions of alpha micro-scale waves detected in each participant with an MEA is plotted in red. The blue arrow in each participant demonstrates the preferred direction of the macro-scale waves detected on the larger macroelectrode grid in the same participant. Theta-band waves take on very similar directions and are not shown.

Single unit spiking is locked to micro-scale traveling waves

We examined single unit spiking data from the MEA locked to the beginning of each micro-scale traveling wave (Fig. 4A; see Methods), and found a clear peak in spiking activity around wave onset in two participants who had a relatively large number of well isolated single units recorded on the MEA (Fig. 4B; Supplementary Fig. S3; see Table 1 for counts of well isolated units recorded in different participants and experimental sessions). In order to examine this relation between micro-scale traveling waves and spiking activity across all participants, we computed high frequency broadband power ($70 - 200$ Hz, HFB, see Methods) as a proxy for multiunit spiking activity (Manning et al., 2009) (see Methods). We confirmed that the spike times identified in this manner using HFB power were a good proxy for local multiunit spiking by computing the cross-correlation between HFB spike events and single unit spike events in every participant. (Supplementary Fig. S4A).

Table 1 Number of well isolated-units detected in each experimental session and participant.

Participant	Session 1	Session 2	Session 3	Session 4
P1	74	72		
P2	12			
P3	13	7	13	
P4	15	44	57	113
P5	12	10	10	
P6	48	41	92	

In every participant, we found a clear peak in HFB spiking activity that was locked to and followed the onset

Figure 4 Single unit spiking activity locked to micro-scale traveling waves. (*A*) A schematic of the analysis to identify the relation between micro-scale waves and neuronal spiking. Each orange line represents the duration of a detected micro-scale wave in time. We captured the time points of single unit spiking (blue) lines) locked to the beginning of each of these waves in both backward and forward directions. (*B*) Two example participants show increased likelihood of spiking after the onset of micro-scale traveling waves. Spike rasters accumulated over waves and units are shown on the bottom. The sum of spikes at each millisecond is summarized in the plots on top. The blue trace represents a smoothed version (using a Gaussian window of 50 ms) of the continuous time series of summed spiking events. (*C*) Summary of micro-scale wave-locked spiking across all six participants using high frequency broadband (HFB) proxies for spiking (see Methods). The mean wave-locked spike rate (z-scored within each experimental session and then averaged across sessions for each participant) across participants is shown in the black trace and the corresponding mean over surrogate wave-locked spikes is shown in grey. Micro-scale waves are followed by a significant peak in spiking activity ($p < .01$).

of micro-scale traveling waves (see Supplementary Figs. S4B and S4C). Of note, the same participants that showed clear peaks in the IWI distributions of alpha micro-scale waves also demonstrated periodic spiking activity locked to alpha micro-scale wave onset (Supplementary Fig. S4C, participants P2, P4, and P5). Increases in z-scored HFB spike events were clearly locked to the onset of the alpha micro-scale traveling waves (Fig. S4C). We compared this peak in the true data to a surrogate dataset in which we randomly shuffled the onset times of the micro-scale waves in each participant and computed the wave-locked spike trains. Since the micro-scale IWI peaks were around 100 ms, we restricted this comparison to a 100 ms period locked to wave-onset. Across participants, the peak in the true data was significantly larger than the peak identified using the surrogate data in the alpha band ($t(5) = 4.33, p = .0075$; Fig. 4C). The increased likelihood of spiking following the onset of the micro-scale traveling waves indicates that micro-scale waves recruit more units as they propagate. In the theta band, we found that the likelihood of spiking increases with the micro-scale waves in several sessions but with a slower time course (Supplementary Fig. S4B). Across participants we therefore did not see a significant sharp rise in spiking activity within the first 100 ms after

the onset of the waves ($t(5) = -0.201, p = .85$). This slower rise of spiking activity observed in the theta band may be related to the slower propagation of theta waves.

Relation between traveling waves at the macro- and micro-scales

Traveling waves detected at the macro and micro scales appear to propagate in different directions and at different speeds, suggesting that they are separate wave phenomena. Yet it is possible that the wave phenomena at the two different spatial scales are temporally related. We examined this possibility directly by computing the cross-correlation between macro-scale and micro-scale wave times averaged across all trials, in each participant (Fig. 5A; see Methods).

We found a clear peak in the average cross-correlogram across participants between macro- and micro-scale alpha waves (Fig. 5B). Both within and across participants, we compared the true correlograms to a distribution of shuffled correlograms in which we permuted the trial labels (see Methods). In four of the six participants, we found a significant peak in the average cross-correlograms between macro- and micro-scale alpha waves when compared to the shuffled distribution ($p < 0.05$, t-statistic > 2.02; across 447 ± 83 trials that had at least one wave at each spatial scale; Supplementary Fig. S5A). We found that this difference between the true correlograms describing the temporal relation betwen alpha macro- and micro-scale waves and the shuffled distribution was consistent across participants ($t(5) = 3.050, p = 0.028$; Fig. 5B). We found a similar relation when examining theta macro- and micro-scale waves, although the difference between the true correlograms and the shuffled distribution was only significant in two participants and was not significant across participants ($t(5) = 1.46, p = 0.20$; Supplementary Fig. S5B).

Given the temporal relation between macro- and micro-scale waves demonstrated by these data, we next investigated whether spiking activity is also temporally related to macro-scale traveling waves. We computed the cross-correlation between alpha band macro-scale waves and high frequency broadband (HFB) spikes as before, and compared the true correlograms to a distribution of shuffled correlograms (see Methods). In four of the six participants we again found a significant peak in the correlogram capturing the temporal relation between alpha macro-scale traveling waves and underlying spiking activity when compared to the shuffled distribution ($p < 1.02 \times 10^{-6}$, t-statistic > 7.46, across 596 ± 87 trials; Supplementary Fig. S5C), although across participants the difference between the true and shuffled distribution was not statistically significant (alpha band: $t(5) = 1.97, p = 0.11$). We found a similar relation when examining the individual correlograms between theta macro-scale traveling waves and spiking activity in four of the six participants (t-statistic > 2.16, $p < 0.05$; Supplementary Fig. S5D), suggesting that low-frequency macro-scale waves are consistently and temporally related to spiking activity recorded along their path of propagation.

Figure 5 Relation between macro-scale traveling waves and micro-scale traveling waves and spiking activity (*A*) A schematic of the analysis. We calculated the cross-correlation between the time series representing the time points during which a macro-scale (blue) or a micro-scale (orange) traveling wave was detected. We similarly computed the cross-correlation between the macro-scale wave time series and the time series of high frequencey (HFB) activity (not shown; see Methods). (*B*) The average cross-correlogram between alpha-band macro-scale wave times and micro-scale wave times across participants (blue). The average of the trial-shuffled surrogate correlograms across participants is shown in red. (*C*) The average cross-correlogram between alpha-band macro-scale wave times and the high frequency broadband (HFB) spike time series across participants (blue). The average of the trial-shuffled surrogate correlograms across participants is shown in red.

Discussion

Our data demonstrate a direct link between traveling waves at the macro-scale, traveling waves at the micro-scale, and neuronal spiking activity. Although macro-scale and micro-scale waves appear to be temporally coordinated, our data suggest that they are not the same phenomenon. Micro-scale waves propogate along a different direction and with a slower velocity than macro-scale waves. Critically, spiking activity is tightly linked to the propagation of micro-scale traveling waves. As micro-scale waves are temporally coordinated with macro-scale waves, our data show that macro-scale waves are also closely linked to spiking activity.

The link between traveling waves at two different spatial scales and neuronal spiking suggests that traveling waves may provide a spatiotemporal framework for neuronal firing, and consequently information processing, in the human brain. For example, lower frequency traveling waves may underlie how spiking activity propagates across the cortex during individual tasks (Wu et al., 2008; Zhang et al., 2018). As high frequency activity is often taken as a surrogate for underlying local spiking activity (Manning et al., 2009), such coordinated activity is consistent with studies demonstrating the emergence of cross-frequency coupling during behavior (Axmacher et al., 2010; Canolty

et al., 2006). In addition, the presence of traveling waves that coordinate local spiking activity is also consistent with theoretical accounts regarding communication between brain regions. Both empirical evidence and computational models suggest that communication may rely on coherent low frequency oscillations that coordinate the propagation of higher frequency bouts of spiking activity (Chapeton et al., 2019; Fries, 2005; Haegens et al., 2011). Brief bouts of coordinated traveling waves across brain regions could provide a mechanistic account for how such communication could arise.

If traveling waves therefore participate in coordinating neural processing across brain regions, it is not surprising then that we found traveling waves that were ubiquitious at both the macro- and micro-scales. The awake brain is always active, processing external stimuli or generating internal thought. We found a small but robust relation between the presence of long range alpha traveling waves and successful memory formation. However, even during trials in which participants fail to successfully encode or retrieve a particular memory, they are likely engaged in some cognitive processing. The ubiquitous nature of traveling waves and their possible general role in coordinating information between brain regions may therefore explain why it has been difficult to identify such clear differences in traveling waves related to memory. Our data suggest that traveling waves may contribute to memory formation, but the specific role that traveling waves play in the service of behavior still requires further exploration.

Although our data demonstrate that traveling waves at the macro- and micro-scales are temporally coordinated, they also suggest that the waves at the two different spatial scales are not the same phenomenon. Waves captured using the micro-scale LFP recordings exhibit slower speeds and propagate in a different direction than the macro-scale waves captured through the iEEG contacts. This distinction in velocity between the two spatial scales is consistent with prior observations (Muller et al., 2018). For example, the slower propagation speeds we observed at the micro-scale are similar to prior reports of slower speeds in the human motor cortex at a similar spatial scale (e.g. 0.1 ms in the $15 - 30$ Hz range) (Takahashi et al., 2011). Similarly, the faster speeds at the macro-scale are consistent with previous studies of traveling waves using iEEG recordings (Zhang et al., 2018). The differences observed between the dynamics of waves at the two different spatial scales suggest that distinct axonal fibre tracts carry waves at the two scales (Muller et al., 2018). Specifically, the faster macro-scale speeds are more consistent with axonal conduction speeds of myelinated cortical white matter fibres whereas the slower micro-scale speeds are more consistent with axonal conduction speeds of unmyelinated long-range horizontal fibres within the superficial layers of the cortex (Muller et al., 2018). Therefore, while it may initially seem counterintuitive that waves that co-occur at the two different spatial scales propagate in different directions at different speeds, one possible explanation is that waves at the micro-scale are governed by the architecture of local neural circuits, which may impose different constraints on the propagation velocity and direction of traveling waves than the constraints that govern larger scale traveling waves between brain regions. Yet despite these differences, we also found that traveling waves at the micro-scale were temporally coordinated with waves at the macro-scale. One possible mechanism by which this coordination could occur is via large-scale waves of depolarization that increase the probability of spiking (Wu et al., 2008), which in turn could trigger waves at the micro-scale (Nauhaus et al., 2009).

A similar coordination between traveling waves at two different spatial scales in humans occurs during epileptic

seizures (Smith et al., 2016) where the propagating edge of the seizing territory (i.e., the ictal wavefront) is the source of traveling waves of ictal discharges that propagate out into the local cortical area at the micro-scale. These micro-scale traveling waves in turn depolarize the local cortical region and recruit more neuronal firing, consistent with our observation of micro-scale wave-locked spiking increases. In these hypersynchronous brain states however, the directions of ictal discharge propagation align across spatial scales prior to the recruitment of the MEA into the seizure, and the micro-scale directions of propagating discharges reverse after the passage of the ictal wavefront over the MEA zone. These dynamics and patterns of traveling waves during hypersynchronous pathological states suggest that wave activity in the context of seizures are fundamentally different from the wave propagation we observe during the more physiological non-seizing states we observe here.

The traveling waves we observed predominantly traveled from a posterior to anterior direction along the lateral temporal lobe. This direction of propagation at the macro-scale is also consistent with previous reports of traveling waves across the human cortex (Zhang et al., 2018). Importantly, we used an optic flow algorithm to automatically detect time periods of traveling wave activity. This approach detects and classifies traveling waves on a millisecond by millisecond basis, thereby allowing us to characterize the precise temporal locking of spatiotemporal activity across spatial scales and with underlying neuronal spiking. Our algorithm, however, requires the lagged-phase relationship between adjacent spatial sites to exist across the entire electrode grid. Hence, the algorithm only detects a traveling wave when most of the activity in the underlying cortical regions participates in the spatial phase gradient. It is possible, therefore, that additional traveling waves that involve only a subset of these larger cortical regions may be present but undetected by our algorithm. Similarly, it is also possible that even the identified traveling waves may have longer temporal durations but only involving a smaller region of cortex. Due to the constraints of our algorithm, these would also not be detected. Developing approaches that can identify these lagged-phase relationships with high spatial and temporal precision can help reconcile these issues.

Large-scale distributed cell assemblies are thought to be important for long-term memory. One mechanism by which these assemblies can be formed and maintained is via macro-scale waves that can spatiotemporally coordinate neuronal activity. Similarly, micro-scale traveling waves may recruit neuronal activity at a smaller spatial scale. While the direction of causality between spiking and waves is yet to be established, our data establishes the temporal relationships between traveling waves across different spatial scales and single unit spiking in the human brain that are necessary for such a role for traveling waves in neuronal communication. Therefore, traveling waves at multiple scales may underlie neuronal coordination and communication that is at the core of cognition and behavior.

Methods

Participants

20 participants (9 males, age 34.8 ± 2.1 years) with drug resistant epilepsy underwent a surgical procedure in which platinum recording contacts were implanted on the cortical surface. The clinical team determined the placement of the contacts in each participant so as to best localize epileptogenic regions. Data were collected at the Clinical Center at the National Institutes of Health (NIH; Bethesda, MD). The research protocol was approved by the NIH Institutional Review Board, and informed consent was obtained from the participants and their guardians. All testing was performed in the participants' rooms during their stay in the Epilepsy Monitoring Unit. All analyses were performed using custom code written in Matlab (Natick, MA). We report standard errors of means unless otherwise specified.

Paired associates task

Each participant performed a paired associates task (Fig. 1B). Participants studied lists of pairs of words and later were cued by one word of the pair and had to remember the associated word they had learned earlier. Each participant performed one of two versions of the task that had slight differences in the experimental details as described below. As the tasks did not differ in the fundamental objectives and performance was indistinguishable between groups, we combined the data from both sets of tasks for subsequent analyses.

A single experimental session for each participant consisted of 15 or 25 lists, where each list contained either four or six pairs of common nouns shown on the center of a laptop screen, depending on whether the participant completed the first ($N = 8$ participants) or second version ($N = 12$ participants) of the task respectively. Words were chosen at random without replacement from a pool of high-frequency nouns and were presented sequentially and appeared in capital letters at the center of the screen. During the study period (encoding), each word pair was preceded by an orientation stimulus (either a '+' or a row of capital X's) that appeared on the screen for $250 - 300$ ms followed by a blank interstimulus interval (ISI) between $500 - 750$ ms (with a jitter of 75 ms). Word pairs were then presented stacked in the center of the screen for 2500 ms followed by a blank ISI of 1500 ms with a jitter of 75 ms in the first version of the task, or for 4000 ms followed by a blank ISI of 1000 ms in the second version. Following the presentation of the list of words pairs in the second version of the task, participants completed an arithmetic distractor task of the form A + B + C = ? for 20 seconds.

In both task versions, during the test period (retrieval), one word was randomly chosen from each of the presented pairs and presented in random order, and the participant was asked to recall the other word from the pair by vocalizing a response. Study word pairs were separated from their corresponding recall cue by a minimum lag of two study or test items. Each cue word was preceded by an orientation stimulus (a row of question marks) that appeared on the screen for $250 - 300$ ms followed by a blank ISI of $500 - 750$ ms. Cue words were then presented on the screen for 3000 ms followed by a blank period of 4500 ms in the first version of the task, or for 4000 ms followed by a blank

period of 1000 ms in the second version. Participants could vocalize their response any time during the recall period after cue presentation. We manually designated each recorded response as correct, intrusion (when an incorrect word was vocalized), or pass. A response was designated as pass when no vocalization was made or when the participant vocalized the word 'pass'. We defined all intrusion and pass trials as incorrect trials. A single experimental session therefore contained 60, 100, or 150 total word pairs, or study trials, depending on the task version and the same number of test trials, each cued by one of the two words in the pair.

Intracranial EEG (iEEG) Processing

We recorded intracranial EEG (iEEG) data from subdural electrodes (PMT Corporation, Chanhassen, MN) sampled at 1000 Hz using a Nihon Kohden (Irvine CA) EEG data acquisition system. Subdural macroelectrode contacts were arranged in both grid and strip configurations with an intercontact (center-center) spacing of 10 mm. The large scale traveling wave analyses in this study required an extended grid of electrodes. Therefore, we selected participants from a larger pool, with the requirement that each participant in this study has an 8×4 contact macro-electrode grid (Fig. 1A). Additionally, we only analyzed data from participants with fewer than 5 missing electrodes from the grid in order to get stable characterizations of traveling wave activity. Since the majority of these participants had temporal lobe grids, we restricted our analyses to the temporal lobe ($N = 20$ across both versions of the task). We filtered all iEEG traces using a notch filter (a fourth order butterworth filter with a narrow $59 - 61$ stop band) to remove 60 Hz line noise.

We note here that since all behavioral and electrophysiological data come from participants with epilepsy, the results must be interpreted cautiously. In particular, it is possible that epileptic activity could contaminate our signals and may even manifest as the specific phenomenon we undertake to study here, i.e., traveling waves of activity. However, we took several steps to mitigate the effects of these confounds. First, we eliminated electrodes identified by the clinical teams during the monitoring period as being part of the ictal onset zone. Next, we removed trials that showed transient noise or epileptic activity using an automated algorithm tuned to match the assessment of the clinical team. The automated iterative procedure to eliminates trials and channels that exhibited excessive variance or kurtosis (Wittig et al., 2018). We implemented this procedure by first extracting each trial's data 600 ms before the word pair (for encoding) or cue (for retrieval) onset extending up to 4000 ms after onset, comprising a single trial. For each channel and trial, we computed the variance of the voltage trace during the 4.6 s surrounding the encoding or retrieval period. We used the resulting two-dimensional (trial $\times$ channel) matrix of variances to compute the maximum variance for each trial and channel. We calculated a threshold based on the quartiles of the resultant distribution of trial and channel variances as follows: $3^{rd} quartile + w_{thresh} \times IQR$, where IQR is the interquartile range and w_{thresh} is a user-specified parameter. If any trials exceeded the threshold, the maximum variance trials were iteratively removed and the quartiles were recomputed at each step. If any of the removed trials caused a change in the number of channels that exceeded the threshold, that trial was flagged for exclusion. Otherwise, if any channels exceeded threshold after all noisy trials were removed, those noisy trials were put back into the matrix and instead noisy channels were iteratively removed. This procedure of identifying noisy trials, and

then channels, was iterated until all trials and channels were within the threshold limits. We used a w_{thresh} of 0.5 (approximately 2 s.d. from the mean) for excluding trials as this was found to detect timepoints that were judged as noise by the epileptologist on our clinical team. However, we used a slightly more liberal criterion of $w_{thresh} = 2.3$ for excluding channels because we wanted to keep as many channels as possible for the spatial analysis while being more strict about keeping clean trials for analysis. We did not analyze any dataset with five or more electrodes that were either detected by the clinical team as being in the ictal onset zone or flagged by this iterative algorithm as being noisy and we removed $14.2 \pm 1.5\%$ of trials using this cleaning procedure.

After removing noisy channels and trials as described above, we performed a global common average referencing by subtracting a common average computed across all channels separately for each trial and timepoint. One practical reason for this choice of reference, as opposed to a bipolar referencing scheme, was to retain phase information at each individual channel for the spatial wave analysis. We filtered the referenced data using finite impulse response (FIR) filters in the theta (4-8 Hz) and alpha (8-16 Hz) ranges. We performed the Hilbert transform on each electrode's filtered data to extract instantaneous phase values at each time point. This procedure provided a spatial map of instantaneous phase values at each time point.

Local field potentials (LFPs) and single unit spiking activity recorded by microelectrode arrays

We analyzed a previously reported dataset (Jang et al., 2017) to understand the relationship between the spatiotemporal patterns of traveling wave activity on the larger scale and the dynamic patterns of micro-scale local field potential and single unit activity on the smaller scale. Six participants (4 male; age 34.8 ± 11.5 years) were implanted with one or two 96-channel microelectrode arrays (MEAs, 4×4 mm, Cereplex I; Blackrock Microsystems, Salt Lake City, UT, USA) in the middle temporal gyrus (MTG) (see 1A for an example of placement of the MEA relative to the temporal grid electrodes). All six participants performed the second version of the paired associates task. MEAs were implanted only in participants with presurgical evaluation indicating seizure localization in the temporal lobe. Across participants, MEAs were implanted 14.6 ± 3.7 mm away from the closest macroelectrode with any ictal or interictal activity identified by the clinical team. MEAs arranged in a 10×10 grid structure had an inter-electrode spacing of 400 μm and extended 1.5 mm into the cortical surface for five participants and 1 mm for one participant. We obtained informed consent from participants explicitly for the MEA implants.

We digitally recorded microelectrode signals at 30 kHz using a Cerebus acquisition system (Blackrock Microsystems, Inc.), with 16-bit precision and a range of ± 8 mV. To obtain micro-local field potential (LFP) signals, we re-referenced each microelectrode's raw voltage data by subtracting the average signal across all microelectrode channels, low-pass filtering the signal at 500 Hz, and downsampling at 1000 Hz. We used the same notch filter and automated iterative procedure described above for cleaning the iEEG data to remove line noise, and noisy trials and channels from the micro-LFP signals.

To extract neuronal spiking activity, we re-referenced each microelectrode's signal offline by subtracting the mean signal of all the electrodes in the MEA, and then used a second order Butterworth filter to band pass the signal

between 0.3 to 3 kHz. Using an offline spike-sorting software package (Plexon Offline Sorter, Inc., Dallas, TX, USA), we identified spike waveforms by manually setting a negative or positive voltage threshold depending on the direction of putative action potentials. The voltage threshold was set to include noise signals used in calculating unit isolation quality. Waveforms (duration, 1.067 ms; 32 samples per waveform) that crossed the voltage threshold were stored for spike sorting. Spike clusters were manually identified by viewing the first two principal components and the difference in peak-to-trough voltage of the waveforms. We manually drew a boundary around clusters of waveforms that were differentiable from noise throughout the experimental session. In this manner, we initially identified a total of 1469 putative single units.

Chronic extracellular electrodes have the potential to record from the same unit for multiple days. Therefore, one cannot assume that units recorded in different experimental sessions represent independent samples. To address this, we implemented a metric of unit identification to determine whether any units recorded across two consecutive experimental sessions were the same (Fraser and Schwartz, 2012). The metric assumes that distinct units can be separated using four characteristics of spiking activity: 1) waveform shape, 2) autocorrelation of the spike times, 3) mean firing rate, and 4) pairwise cross-correlation of spike times between units in the same recording session. Each pair of units recorded across two consecutive sessions was therefore represented by a single point in four-dimensional space using the four metrics above. Each four-dimensional similarity score, computed using a pair of units from different experimental sessions, can represent the similarity of either two units on different electrodes, which cannot be identical, or two units recorded from the same electrode, which may or may not be identical. We used a quadratic classifier to determine the decision boundary between different-electrode and same-electrode clusters in this four-dimensional space. This method identified 62 units that were putatively recorded for multiple sessions. The low number of overlapping units is expected, as sessions were on average at least two days apart (76 ± 19 hours), and because over such long periods, units may appear or disappear from recordings due to micromotion, changes in brain state, or other factors(Fraser and Schwartz, 2012). We removed these 62 units from all subsequent analyses to ensure independent samples across sessions.

Due to variability in the signal quality across recordings and the subjective nature of spike sorting, we quantified the quality of each unit by calculating an isolation score and signal to noise ratio (SNR)(Joshua et al., 2007). The isolation score quantifies the distance between the spike and noise clusters in a 32-dimensional space, where each dimension corresponds to a sample in the spike waveform. The spike cluster consisted of all waveforms that were classified as belonging to that unit, and the noise cluster consisted of all waveforms that crossed the threshold that were not classified as belonging to any unit. The isolation score is normalized to be between 0 and 1, and serves as a measure to compare the isolation quality of all units across all experimental sessions and participants. 1200 units (82%) had an isolation score of at least 0.9 which is the minimum threshold we used to include units in the analysis.

In addition to isolation quality, we computed the SNR for each unit using the following equation:

$$SNR = \frac{V_{peak} - V_{trough}}{Noise * C} \tag{1}$$

where V_{peak} and V_{trough} are the maximum and minimum voltage values of the mean waveform, and C is a scaling

factor (set as 5)(Joshua et al., 2007). To obtain *Noise*, we subtracted the mean waveform from each individual waveform for each identified unit, concatenated these waveform residuals, and then computed the standard deviation of this long vector. Therefore, the noise term quantifies the within-unit variability in waveform shape. 1207 units (82%) had an SNR of at least 1.0. We additionally characterized the mean spike rate for each unit, and found that 914 units (62%) had a mean spike rate of at least 1 Hz. Overall, we retained a total of 633 units (43%) that had an isolation score of at least 0.9, a SNR of at least 1.0, and a mean spike rate of at least 1 Hz. The mean firing rate of all units was 3.24 ± 0.11, and the firing rate for the selected units was 4.24 ± 0.16 Hz.

To examine the temporal relation between micro-LFP traveling waves and spiking activity, we identified the starting time point of each micro-LFP traveling wave and collected spike trains that extended from -300 to $+300$ ms from this starting time point. We computed the sum of spikes at each millisecond over all micro-LFP waves across trials to get a summary picture of the micro-LFP wave-locked spike rasters in Fig. 4B and Supplementary Fig. S3.

Since high quality single unit data could not be obtained for every participant, in order to facilitate comparisons across all participants, we constructed high frequency broadband (HFB) proxies for spiking. To do this, we first computed spectral power at 8 different log-spaced frequencies between $70 - 200$ Hz using Morlet wavelets (number of cycles $= 6$) and then averaged the power across these frequencies. HFB proxies for spiking (henceforth called "HFB spikes") were then constructed by identifying time points when HFB power z-scored within a microelectrode and trial exceeded $z = 1.96$. We confirmed that these HFB spikes reflected underlying single unit spiking by computing the cross-correlation between HFB spike events and single unit spike events in every participant. (Supplementary Fig. S4A).

Identification of traveling plane waves

Optical flow is defined to be the distribution of apparent velocities of movement of brightness patterns in an image (Horn and Schunck, 1981). For our purposes, we defined brightness at each electrode as the instantaneous phase value at that electrode. Optical flow therefore determines the velocities of movements of these phases across the electrode grid. We computed optical flow based on frame by frame spatial maps of instantaneous phase in theta and alpha frequency bands thought to be important for associative memory processing.

We used the opticFlow function from the MATLAB toolbox published by Townsend and Gong (2018) available at https://github.com/BrainDynamicsUSYD/NeuroPattToolbox to compute the velocity vector fields. The optic flow algorithm follows the Horn-Schunck method (Horn and Schunck, 1981). We provide a brief overview of the original approach here and refer readers to the original paper for further technical details (Horn and Schunck, 1981). Also see Afrashteh et al. (2017) for an overview of the different optical flow algorithms and comparisons of how well angle and velocity estimates match simulated ground truth. The Horn-Schunck algorithm works well for traveling plane waves (Afrashteh et al., 2017), which is the topic of our investigation here. A more recently described method performs slightly better when estimating speed (Bruhn et al., 2002). However, that method is a hierarchical algorithm that finds solutions from coarse to refined spatial scales that, in order to allow for spatial downsampling, requires a greater spatial coverage than we have access to in our data.

The first step in the Horn-Schunck method is to derive an equation to relate change in image brightness at a given point to the motion of the brightness pattern. The algorithm was developed based on two constraints. The first constraint, called brightness constancy, assumes that the brightness of a given pixel (x, y) is constant from one frame to next frame when it has moved to $(x + u, y + v)$, leading to the equation:

$$I(x + u, y + v, t + 1) = I(x, y, t) \tag{2}$$

where $I(x, y, t)$ is the brightness of pixel (x, y) at time t and $I(x + u, y + v, t + 1)$ is the brightness of the same pixel when it has moved u in the x direction and v in the y direction in one time step (i.e., at time $t+1$). The Horn-Schunck method also assumes that the apparent velocity of the brightness pattern in an image varies smoothly across the image because if neighboring pixels all move in unrelated ways, there is little hope of recovering the velocities (Horn and Schunck, 1981). This leads to the second constraint, called spatial smoothness, which prevents discontinuities in the flow field. The spatial smoothness constraint is expressed as a minimization of the magnitude of the gradient of the optical flow velocity:

$$|\nabla u|^2 = \left(\frac{\partial u}{\partial x} \right)^2 + \left(\frac{\partial u}{\partial y} \right)^2$$

$$\text{and}$$

$$|\nabla v|^2 = \left(\frac{\partial v}{\partial x} \right)^2 + \left(\frac{\partial v}{\partial y} \right)^2. \tag{3}$$

Both constraints are expressed together as a single minimization problem given by:

$$min_{u,v} \left\{ \int \int (I_t + I_x u + I_y v)^2 \, \rho dx dy + \int \int \left(\alpha \rho \left(|\nabla u|^2 + |\nabla v|^2 \right) dx dy \right\} \tag{4}$$

where I_t, I_x, and I_y are derivatives of brightness $I(x, y, t)$ with respect to time, direction x, and direction y. α is a smoothness regularization parameter that scales the global spatial smoothness term with respect to the brightness constancy term such that increasing α increases the influence of the spatial smoothness constraint on the solution for $[u, v]$, producing a smoother velocity vector field. ρ is a penalty function. Horn and Schunck (1981) used a quadratic penalty $(\rho(x^2) = x^2)$. However, similar to Townsend and Gong (2018), we used the Charbonnier penalty, $\rho(x^2) = \sqrt{x^2 + \beta^2}$, where β is a small positive constant. The Charbonnier penalty leads to more accurate velocity vector fields whereas the original quadratic penalty can lead to inaccuracies in the presence of hard edges (which are likely not an issue in neural data) or when adjacent regions move in different directions (which is certainly a possibility, for instance, when two concurrent traveling waves moving in different directions are present on adjacent regions of the temporal cortex). Equation 4 is solved by linearizing its corresponding Euler-Lagrange equations, to

get a unique velocity vector field, $[u, v]$ for each pixel (i.e., electrode) in the image (i.e., spatial map of instantaneous phase; see Townsend and Gong (2018) for more details). These velocity vectors therefore provide information about instantaneous speed as well as directions of motion of each pixel in the image.

The specific value of α and β for the optic flow model was determined by visually comparing the flow vectors obtained against movies of spatiotemporal changes in phase and choosing the values that provided the best visual match between the flow vectors and the apparent motion of activity in the phase movies ($\alpha = 1; \beta = 0.1$). The resulting velocity vector fields were robust to small changes in these parameter values. These choices cannot be automated but previously published simulations suggest that patterns were better localized in space when using smaller values of $\alpha \leq 1$ (Townsend and Gong, 2018).

A requirement for detecting traveling plane waves is that all vectors in the phase velocity field (PVF) point in the same direction. We used the average normalized phase velocity (Townsend et al., 2015):

$$\bar{v_\phi}(t) = \frac{1}{Nv_0(t)} \left| \sum_{xy} v_\phi(x, y, t) \right|, \tag{5}$$

where N is the number of vectors in the PVF. For the macro-scale wave analysis, we split the 8×4 macroelectrode grid into three overlapping square 4×4 sub-grids (Fig. 1C) because of concerns that asymmetry in the geometry of the grid may cause the algorithm to have a directional bias simply due to the input 2D data having more information along one dimension than the other. Therefore, waves were detected on each sub-grid separately, and then eventually combined across the sub-grids to detect macro-scale waves that traveled across the entire 8×4 grid. Given that we identified an instantaneous phase at each electrode, where each electrode is analogous to each pixel in an image, this resulted in 16 velocity vectors for the macroelectrode 4×4 sub-grid data and 96 in the case of the microelectrode data arranged as 10×10 grids. v_0 is the mean speed over all electrodes. Normalized phase velocity $\bar{v_\phi}$ ranges from 0 to 1. $\bar{v_\phi}$ approaches 1 as all the vectors point in the same direction. We first imposed a threshold of $\bar{v_\phi} \geq 0.7$ to detect all the timepoints where the vectors in the PVF align in the same direction. This by itself however does not capture waves traveling in the same direction across any extended duration because all the vectors may be aligned, but in different directions at different time points. Hence, this first step only flags long epochs during which sub-epochs contain velocity vectors that are aligned, but does not require that the velocity vectors identified in each sub-epoch be aligned in the same direction from one sub-epoch to the next.

In order to identify plane waves, we therefore imposed the additional constraint that plane waves must be comprised of uninterrupted timepoints during which the PVF points in the same direction. To identify such plane waves, we examined each identified long epoch that contained normalized phase velocities exceeding our threshold of 0.7. From each time point in each identified epoch, we calculated the distribution of directions in which the PVF pointed. To be considered a plane wave, we required that the PVF align with a fixed direction for a sufficient number of contiguous time points. We defined the minimum time duration for a plane wave to be one quarter of a cycle of the frequency band of interest. Hence, for the theta band, we used the highest frequency of 8 Hz, which has a period

of 125 ms, to derive a minimum duration of 31 ms. For the alpha band, we used the highest frequency of 16 Hz, to derive a minimum duration of 15 ms. Given the possibility that the PVF may exhibit brief changes in direction due to noise, we considered a PVF as part of the same plane wave as long as the PVF returned to the same direction within 5 ms for theta and 3 ms for alpha waves. Finally, to ensure that the PVF points in the same direction within each identified plane wave, we required that the mean directions across time points within that identified plane wave have a circular kurtosis of at least 0.7 and a median absolute deviation less than 15 degrees. These parameters were determined by trial and error, plotting movies of phase maps and ensuring that the detected wave epochs indeed look like traveling plane waves in the phase movies. All parameters were fixed before any of the other analyses reported in this study were performed.

Surrogate iEEG data

In order to compare the identified plane waves to any waves that would be identified by chance, we generated surrogate iEEG data with autocorrelations and spectral content that were similar to the original data, but with reduced cross-correlations between channels. Our goal was to generate surrogate data with cross-correlations between electrode channels reduced by approximately 25%. We ran the wave detection algorithm on these surrogate data. If the surrogate data revealed a significantly reduced number of waves compared to the original data, then this would suggest that the traveling plane waves identified in the original data are indeed due to the specific phase-lagged relationship between spatial locations on the electrode array and are not an artifact of the analysis method itself.

To generate the surrogate iEEG data, we used the Prichard-Theiler method (Prichard and Theiler, 1994) which was also used as a control in a previous study of traveling waves (Townsend et al., 2015). The Prichard-Theiler method strives to preserve the cross-spectrum in multivariate data in addition to the power spectrum of each individual channel. We produced such phase-randomized surrogate data by multiplying the Fourier phases of each channel by a uniform random phase. Specifically, we added the same random phase, chosen from the uniform distribution $0 - 2\pi$, to the phase values for each frequency component of the discrete Fourier transformed signal in each electrode. This approach preserves the cross-spectrum between channels since the cross-spectrum reflects only the relative phase differences between them. In addition, we shifted the phase at each frequency f by another random phase which was chosen from a normal distribution (mean $= 0$, SD $= \pi/4$) (Townsend et al., 2015). We applied this same random phase shift to the data from each electrode channel. This surrogate iEEG data thus produced preserves autocorrelations and power spectra but reduces the cross-correlation between channels by an average of $26.6 \pm 0.6\% (mean \pm SEM)$ across participants (see Fig. S1).

Velocity calculation

The output of the optic flow computation provides both directions and magnitudes of flow. We verified the directions by visually examining movies of identified traveling waves superimposed with the flow fields but we observed that the algorithm tended to underestimate the magnitudes (or speeds). We found several discussions of the same issue faced by other users of the built-in MATLAB function opticalFlowHS. One possibility is that the algorithm due to

the emphasis on minimization of gradients tends to underestimate spatial gradients. Indeed the original paper by Horn and Schunck (1981) mentions this possibility, noting that the velocity estimates "tend to be too small, rather than too large" (pp. 196).

For this reason, we implemented a method to compute velocities of the identified traveling waves, based on the method used in a recent publication on iEEG traveling waves (Zhang et al., 2018). We first computed the temporal frequency f of a traveling wave by first taking the average phase across electrodes at each time point and then calculating the temporal derivative of this average phase. This generates an estimate of instantaneous temporal frequency at each time point within the wave. We took the mean temporal frequency across time points to get f for each wave. We calculated the spatial frequency ξ by first taking a reference electrode and identifying the relative phases at all electrodes with respect to that reference phase. We then regressed the relative phases on Euclidean distance from the reference electrode to get an estimate of spatial frequency. We averaged this spatial frequency over all time points to get ξ for the wave. We did this directly on the time points known to exhibit phase progression across electrodes because the optic flow algorithm already identified the time points of interest. We then estimated the wave speed as $\frac{f}{\xi}$.

Statistical testing

We performed statistical tests of circular distributions (e.g. directions or phases) on the identified waves using Hodges-Ajne tests when the null hypothesis was that the angles are uniformly distributed (e.g., where the alternative can be unimodal, bimodal, or anything other than uniform) and using Rayleigh's tests when the alternative hypothesis was a preference for a specific angle (i.e., a unimodal distribution). We used the CircStat toolbox for MATLAB for directional statistics (Berens, 2020).

In order to determine whether HFB spikes locked to micro-scale waves increased at time $= 0$ relative to other time points, we first computed the micro-scale wave-locked HFB spike rasters, and computed the proportion of HFB spikes at each millisecond across all waves and trials in each experimental session. We z-scored these microscale wave-locked probabilities of HFB spikes within each session and averaged this over sessions to get a wave-locked HFB spiking probability for each participant (Supplementary Figs. S4B and S4C). We then repeated this procedure by choosing random onset times for the microscale waves (but keeping the number and duration of waves the same as in the true data) in order to construct a surrogate microscale wave-locked HFB spiking probability for each participant.

To examine the relation between traveling waves at the macro- and micro- spatial scales, we computed the cross-correlation between the vectors representing the time points at which traveling waves were identified at both spatial scales. In each trial we constructed a binary vector that took on a value of 1 for each time point at which a traveling wave was identified at the macro-scale, and a separate binary vector identifying time points of traveling wave activity at the micro-scale. These binary vectors represent a time series that captures, at each time point, whether a traveling wave was detected at either the macro- or micro-scale respectively. In order to examine the relation between macro-scale traveling waves and spiking, we followed a similar procedure, but used the HFB spike time series which facilitated the quantification of this relation in all participants. In both cases (macro-scale waves

vs micro-scale waves and macro-scale waves vs HFB spikes), we then computed the cross-correlation between the two binary vectors to generate a cross-correlogram for each trial.

For each participant, we compared the true correlograms across trials to a distribution of correlograms in which we permuted the trial labels. Specifically, in each of 50 permutations, we performed a cross-correlation between the macro-scale time series in each trial with the micro-scale time series, or HFB spike time series, from a randomly selected different trial, and then averaged the correlograms across permutations to generate one surrogate correlogram for each trial. We then compared the true correlograms and surrogate correlograms across trials by performing a t-test comparing the average value of the true and surrogate correlograms over a 30 ms and 50 ms window centered around zero, corresponding to the average duration of an alpha and theta macro-scale wave on a macroelectrode subgrid, respectively. Finally, a true and surrogate correlogram for each participant was created by averaging the correlograms across trials. Across participants, we compared the true trial-averaged correlograms and surrogate trial-averaged correlograms, again by taking the average value of the participant-level correlograms over the 30 ms and 50 ms windows centered around zero as described above.

Data and Software Availability

Processed data are available by request to the authors.

References

Afrashteh, N., Inayat, S., Mohsenvand, M., and Mohajerani, M. H. (2017). Optical-flow analysis toolbox for characterization of spatiotemporal dynamics in mesoscale optical imaging of brain activity. *NeuroImage*, 153:58–74.

Axmacher, N., Henseler, M., Jensen, O., Weinreich, I., Elger, C., and Fell, J. (2010). Cross-frequency coupling supports multi-item working memory in the human hippocampus. *Proceedings of the National Academy of Sciences, USA*, 107(7):3228.

Bahramisharif, A., Gerven, M. A. J. v., Aarnoutse, E. J., Mercier, M. R., Schwartz, T. H., Foxe, J. J., Ramsey, N. F., and Jensen, O. (2013). Propagating Neocortical Gamma Bursts Are Coordinated by Traveling Alpha Waves. *J. Neurosci.*, 33(48):18849–18854.

Berens, P. (2020). *Circular Statistics Toolbox* (directional statistics). *https://www.mathworks.com/ matlabcentral/fileexchange/10676-circular-statistics-toolbox-directional-statistics* [Accessed: January 13, 2020].

Bruhn, A., Weickert, J., and Schnörr, C. (2002). Combining the Advantages of Local and Global Optic Flow Methods. In *Proceedings of the 24th DAGM Symposium on Pattern Recognition*, pages 454–462, London, UK, UK. Springer-Verlag.

Canolty, R. T., Edwards, E., Dalal, S. S., Soltani, M., Nagarajan, S. S., Kirsch, H. E., Berger, M. S., Barbaro, N. M., and Knight, R. T. (2006). High gamma power is phase-locked to theta oscillations in human neocortex. *Science*, 313(5793):1626–1628.

Chapeton, J. I., Haque, R., Wittig, J. H., Inati, S. K., and Zaghloul, K. A. (2019). Large-Scale Communication in the Human Brain Is Rhythmically Modulated through Alpha Coherence. *Current Biology*, 29(17):2801–2811.e5.

Ermentrout, G. B. and Kleinfeld, D. (2001). Traveling Electrical Waves in Cortex: Insights from Phase Dynamics and Speculation on a Computational Role. *Neuron*, 29(1):33–44.

Fraser, G. W. and Schwartz, A. B. (2012). Recording from the same neurons chronically in motor cortex. *Journal of Neurophysiology*, 107(7):1970–1978.

Fries, P. (2005). A mechanism for cognitive dynamics: neuronal communication through neuronal coherence. *Trends Cogn Sci*, 9(10):474–480.

Haegens, S., Nácher, V., Luna, R., Romo, R., and Jensen, O. (2011). -Oscillations in the monkey sensorimotor network influence discrimination performance by rhythmical inhibition of neuronal spiking. *PNAS*, 108(48):19377–19382.

Horn, B. K. P. and Schunck, B. G. (1981). Determining optical flow. *Artificial Intelligence*, 17(1):185–203.

Jacobs, J., Kahana, M. J., Ekstrom, A. D., and Fried, I. (2007). Brain oscillations control timing of single-neuron activity in humans. *J Neurosci*, 27(14):3839–3844.

Jang, A. I., Wittig, J. H., Inati, S. K., and Zaghloul, K. A. (2017). Human Cortical Neurons in the Anterior Temporal Lobe Reinstate Spiking Activity during Verbal Memory Retrieval. *Current Biology*, 27(11):1700–1705.e5.

Joshua, M., Elias, S., Levine, O., and Bergman, H. (2007). Quantifying the isolation quality of extracellularly recorded action potentials. *Journal of Neuroscience Methods*, 163(2):267–282.

Lozano-Soldevilla, D. and VanRullen, R. (2019). The Hidden Spatial Dimension of Alpha: 10-Hz Perceptual Echoes Propagate as Periodic Traveling Waves in the Human Brain. *Cell Reports*, 26(2):374–380.e4.

Manning, J. R., Jacobs, J., Fried, I., and Kahana, M. J. (2009). Broadband shifts in LFP power spectra are correlated with single-neuron spiking in humans. *J Neurosci*, 29(43):13613 – 13620.

Muller, L., Chavane, F., Reynolds, J., and Sejnowski, T. J. (2018). Cortical travelling waves: mechanisms and computational principles. *Nat Rev Neurosci*, 19(5):255–268.

Muller, L., Piantoni, G., Koller, D., Cash, S. S., Halgren, E., and Sejnowski, T. J. (2016). Rotating waves during human sleep spindles organize global patterns of activity that repeat precisely through the night. *eLife*, 5:e17267.

Nauhaus, I., Busse, L., Carandini, M., and Ringach, D. L. (2009). Stimulus contrast modulates functional connectivity in visual cortex. *Nat Neurosci*, 12(1):70–76.

Prichard, D. and Theiler, J. (1994). Generating surrogate data for time series with several simultaneously measured variables. *Phys. Rev. Lett.*, 73(7):951–954.

Roberts, J. A., Gollo, L. L., Abeysuriya, R. G., Roberts, G., Mitchell, P. B., Woolrich, M. W., and Breakspear, M. (2019). Metastable brain waves. *Nat Commun*, 10(1):1–17.

Rubino, D., Robbins, K. A., and Hatsopoulos, N. G. (2006). Propagating waves mediate information transfer in the motor cortex. *Nature Neuroscience*, 9(12):1549.

Rutishauser, U., Ross, I., Mamelak, A., and Schuman, E. (2010). Human memory strength is predicted by theta-frequency phase-locking of single neurons. *Nature*, 464(7290):903–907.

Smith, E. H., Liou, J.-y., Davis, T. S., Merricks, E. M., Kellis, S. S., Weiss, S. A., Greger, B., House, P. A., McKhann II, G. M., Goodman, R. R., et al. (2016). The ictal wavefront is the spatiotemporal source of discharges during spontaneous human seizures. *Nature communications*, 7:11098.

Takahashi, K., Saleh, M., Penn, R. D., and Hatsopoulos, N. (2011). Propagating Waves in Human Motor Cortex. *Front. Hum. Neurosci.*, 5.

Townsend, R. G. and Gong, P. (2018). Detection and analysis of spatiotemporal patterns in brain activity. *PLOS Computational Biology*, 14(12):e1006643.

Townsend, R. G., Solomon, S. S., Chen, S. C., Pietersen, A. N. J., Martin, P. R., Solomon, S. G., and Gong, P. (2015). Emergence of Complex Wave Patterns in Primate Cerebral Cortex. *J. Neurosci.*, 35(11):4657–4662.

Varela, F., Lachaux, J.-P., Rodriguez, E., and Martinerie, J. (2001). The brainweb: Phase synchronization and large-scale integration. *Nature Reviews Neuroscience*, 2(4):229.

Vidaurre, D., Hunt, L. T., Quinn, A. J., Hunt, B. A. E., Brookes, M. J., Nobre, A. C., and Woolrich, M. W. (2018). Spontaneous cortical activity transiently organises into frequency specific phase-coupling networks. *Nature Communications*, 9(1):2987.

Wittig, J. H., Jang, A. I., Cocjin, J. B., Inati, S. K., and Zaghloul, K. A. (2018). Attention improves memory by suppressing spiking-neuron activity in the human anterior temporal lobe. *Nature Neuroscience*, 21(6):808–810.

Wu, J.-Y., Huang, X., and Zhang, C. (2008). Propagating Waves of Activity in the Neocortex: What They Are, What They Do. *Neuroscientist*, 14(5):487–502.

Zanos, T. P., Mineault, P. J., Nasiotis, K. T., Guitton, D., and Pack, C. C. (2015). A Sensorimotor Role for Traveling Waves in Primate Visual Cortex. *Neuron*, 85(3):615–627.

Zhang, H., Watrous, A. J., Patel, A., and Jacobs, J. (2018). Theta and Alpha Oscillations Are Traveling Waves in the Human Neocortex. *Neuron*, 98(6):1269–1281.e4.

 # Supplemental Figures

Figure S1 Surrogate data construction and comparison of waves detected in the real versus surrogate data. (*A*) An example voltage trace (blue) and the corresponding phase-scrambled surrogate trace (orange), illustrating the constructed surrogate that mimics the original trace very closely except for the phase information. The power spectral density for the original and surrogate data is shown on the right. (*B*) The spatial cross-correlations between voltage traces on pairs of electrodes (total 32 electrodes arranged as an 8x4 grid). The cross-correlations are decreased by around 27% in this example surrogate data constructed by the Prichard-Theiler method (see Methods). (*C*) The distribution of the number of waves per second detected in the original data compared with the number detected in the surrogate data. A clear and significant decrease is observed in the number of waves detected in the distorted surrogates ($p < .01$). Greater distortions in the phase information that would reduce the spatial cross-correlations between electrodes would result in an even greater separation (*D*) Percent change in log power from non-wave to wave epochs in the theta and alpha bands. (theta, $t(19) = 16.5, p = 9.7 \times 10^{-13}$; alpha, $t(19) = 26.1, p = 2.4 \times 10^{-16}$). (*E*) Temporal overlap between macro-scale traveling waves detected in the theta and alpha frequency bands. Twenty example trials from a participant are shown. The horizontal blue and red lines indicate the extents of waves detected in the theta and alpha band respectively. The black vertical line indicates the time at which the word-pair or a word cue appears on the screen.

Figure S2 Simulated inter-wave interval distribution and distribution of durations of traveling waves at the macro- and micro- scales. (*A*) The distribution of macro-scale inter-wave intervals (IWIs) simulated by assuming a Poisson process with a refractory period that is drawn from an exponential distribution of wave durations and with a rate that is similar to the rate of occurrence of alpha macro-scale (4×4 macro-subgrid) waves in our data of ~ 11 per second. The shape of this distribution resembles that of the IWI distributions presented in Fig. 2C. (*B*) The distributions of durations of long-range theta and alpha traveling waves in six example participants. (*C*) The distributions of durations of microLFP-scale theta and alpha traveling waves in all six participants with MEA recordings. (*D*) The distributions of inter-wave intervals (IWIs) of micro-scale alpha traveling waves in all six participants with MEA recordings. Three participants exhibt a clear peak in the IWI (red dotted lines; 85, 115, and 125 ms for participants P2, P4, and P5 respectively).

microLFP wave-locked spike rasters

Figure S3 Examples of spike rasters locked to the onset of micro-scale traveling waves. The onsets of both alpha and theta micro-scale traveling waves are followed by increases in spiking activity.

Figure S4 High-frequency broadband (HFB) proxy for spiking is locked to the onset of micro-scale traveling waves in all participants. (*A*) Cross-correlations between binarized continuous time high frequency broadband power and multiunit spiking activity in each participant (see Results). Single unit spike trains and HFB spike trains are cross-correlated at 300 different lags in both forward and backward directions within trials, and then averaged over trials and sessions. The correlograms peaked at time = 0 suggest that high frequency power can be used as a proxy for spiking activity. (*B*) We detected time points at which HFB power exceeded a threshold within each trial and micro-electrode and called these HFB spikes. Probability of detecting an HFB spike in each participant and in each session was computed as the proportion of HFB spikes at each millisecond across all waves and trials locked to the onset of micro-scale traveling theta waves (time = 0), and is plotted in gray. A smoothed version (using a Gaussian window of 50 ms) of the probability is overlaid in red. (*C*) Probability of detecting an HFB spike locked to the onset of micro-scale traveling alpha waves (time = 0) in each participant and in each session.

Figure S5 Cross-correlations between the time series of detected macro-scale traveling waves and the traveling waves and spiking activity at the micro-scale (*A*) Cross-correlation between the time series of detected alpha band macro-scale and alpha band micro-scale traveling waves in each participant (blue). We compared the true correlogram to the average of a trial-shuffled distribution (red) and found a significant peak in the cross-correlation between the two traveling waves in 4 out of 6 participants ($p < 0.05$, t-statistic > 2.02) (*B*) Cross-correlation between the time series of detected theta band macro-scale and theta band micro-scale traveling waves in each partcipant (blue). Correlograms only demonstrated a significant peak as compared to the shuffled distribution (red) in two participants. (*C*) Cross-correlation between the time series of detected alpha band macro-scale and the time series of detected HFB events (blue). We compared the true correlogram to the average of a shuffled distribution (red) and found a significant peak in the cross-correlation in 4 out of 6 participants ($p < 1.02 \times 10^{-6}$, t-statistic > 7.46). (*D*) Cross-correlation between the time series of detected theta band macro-scale and the time series of detected HFB events (blue) and found a significant peak in the cross-correlation in 4 out of 6 participants ($p < 0.05$, t-statistic > 2.16).