Mathematical framework for place coding in the auditory system

Alex D. Reyes[1]

[1]Center for Neural Science, New York University, New York, NY, USA

Abstract

In the auditory system, tonotopy is postulated to be the substrate for a place code, where sound frequency is encoded by the location of the neurons that fire during the stimulus. Though conceptually simple, the computations that allow for the representation of intensity and complex sounds are poorly understood. Here, a mathematical framework is developed in order to define clearly the conditions that support a place code. To accommodate both frequency and intensity information, the neural network is described as a topological space with elements that represent individual neurons and clusters of neurons. A bijective mapping is then constructed from acoustic space to neural space so that frequency and intensity are encoded, respectively, by the location and size of the clusters. Algebraic operations -addition and multiplication- are derived to elucidate the rules for representing, assembling, and modulating multi-frequency sound in networks. The predicted outcomes of these operations are consistent with network simulations as well as with electrophysiological and psychophysical data. The analyses show that acoustic information can be encoded with a purely place code, without the need for rate or temporal coding schemes. The mathematical approach complements experimental and computational approaches and provides a foundation for interpreting data and constructing models.

Author Summary

One way of encoding sensory information in the brain is with a so-called place code. In the auditory system, tones of increasing frequencies activate sets of neurons at progressively different locations along an axis. The goal of this study is to elucidate the mathematical principles for representing tone frequency and intensity in neural networks. The rigorous, formal process ensures that the conditions for a place code and the associated computations are defined precisely. This mathematical approach offers new insights into experimental data and a framework for constructing network models.

Introduction

Many sensory systems are organized topographically so that adjacent neurons have small differences in the receptive fields. The result is that minute changes in the sensory features causes an incremental shift in the spatial distribution of active neurons. This is has led to the notion of a place code where the location of the active neurons provides information about sensory attributes. In the auditory system, the substrate for a place code is tonotopy, where the preferred frequency of each neuron varies systematically along one axis [1]. Tonotopy originates in the cochlea [2, 3] and is inherited by progressively higher order structures along the auditory pathway [4]. The importance of a place code [5] is underscored by the fact that cochlear implants, arguably the most successful brain-machine interface, enable deaf patients to discriminate tone pitch simply by delivering brief electrical pulses at points of the cochlea corresponding to specific frequencies [6].

Although frequency and intensity may be encoded in several ways [7], there are regimes where place-coding seems advantageous. Humans are able to discriminate small differences in frequencies and intensities even for stimuli as brief as 5-10 ms [8, 9, 10, 11]. Therefore, the major computations have already taken place within a few milliseconds. This is of some significance because in this short time interval, neurons can fire only bursts of 1-2 action potentials [12, 13], indicating that neurons essentially function as binary units. Therefore, it seems unlikely that neither frequency nor intensity can be encoded via the firing rate of cells since the dynamic range would be severely limited. Similarly, coding schemes based on temporal or 'volley' schemes is difficult to implement at the level of cortex because neurons can phase-lock only to low frequency sounds [14, 15, 16].

There are, however, several challenges with implementing a place coding scheme. First, the optimal architecture for representing frequency is not well-defined. Possible functional units include individual neurons, cortical columns [17, 18], or overlapping neuron clusters [19]. The dimension of each unit ultimately determines the range and resolution at which frequencies and intensities that can be represented and discriminated. Second, how both frequency and intensity can be encoded with a place code is unclear, particularly for brief stimuli when cells function mostly as binary units. Other variables such as firing rate or spike timing are commonly incorporated into models [20]. Third, the rules for combining multiple stimuli is lacking. Physiological sounds are composed of pure tones with differing frequencies and intensities, resulting in potentially complex

spatial activity patterns in networks. Finally, the role of inhibition in a place coding scheme has not been established.

Here, a mathematical model is developed in order to gain insights into: 1) the functional organization of the auditory system that supports a place coding scheme for frequency and intensity: and 2) the computations that can be performed in networks. The approach is to use principles from set theory and topology to construct the acoustic and neural spaces, find a mapping between the spaces, and then develop the algebraic operations. The predictions of the math model are then tested with simulations.

Results

Figure 1: **Computations with a place code**. ***a, left***, hypothetical neural representation of a low frequency (f_α), small amplitude (p_α) pure tone stimulus in a two-dimensional neural network. A stimulus-evoked synaptic field covers a circular area (cyan disk) and causes a subset of cells to fire (filled circles). Projection of the synaptic field onto the tonotopic axis (cyan bar) gives the location and size of the activated area. ***right***, synaptic field generated by a tone with higher frequency (f_β) and sound pressure (p_β). ***b***, synaptic field generated by a sound composed of the two tones. ***c***, modulation by inhibition (red).

The mathematical model is subject to the following biological constraints. First, the neural network inherits the tonotopic organization of the cochlea [2, 3] so that the preferred frequency of neurons changes systematically with location along one axis. Second, a pure tone activates a population of neurons within a confined area [21], with the location of the area varying with the tone frequency. Third, the area grows with sound intensity [21], paralleling the increase in the response area of the basilar membrane [22, 23]. The model is broadly related to the "spread-of-

excitation" class of models [7, 24]

The basic computations that can be performed using a place code are shown schematically in

a 2-dimensional network of neurons (Fig. 1). In response to a pure tone stimulus, a synaptic field

from a presynaptic population of neurons is generated within an enclosed area of the network (a, left

panel, cyan disk), causing a population of cells to fire (filled circles). A tone with a higher frequency

and intensity activates a larger area at a different location (right panel). A sound composed of the

two pure tones activates both regions simultaneously; the regions may overlap if the difference in

frequencies is small (Fig. 1b). Finally, excitatory synaptic fields and the activated neuron clusters

are modulated by inhibition (Fig. 1c). The mathematical basis for these computations is developed

below. For clarity, only the main results are shown (details in appendix).

Neural Space

Although the brain has three spatial dimensions, only one dimension -that corresponding to the

tonotopic axis- is relevant for a place code. Thus, the circular synaptic field in Fig. 1 is projected

onto the tonotopic axis (bars). For simplicity, the neural space is defined as a single row of neurons

(Fig. 2a). In the presence of sound, afferents from an external source generates a synaptic field

that covers a contiguous subset of neurons. In the following, a mathematical description of the

neural space will be developed that accommodates the neural elements and synaptic fields.

The neural space is defined as an interval, bounded by minimum and maximum values x_{min}

and x_{max} (Fig. 2b, magenta). To incorporate neurons, the neural space is partitioned into N_{cell}

sections. Both the neural space and the cells are 'half-open' intervals, which are closed ("[") on

one end and open on the other (")"). This is convenient mathematically because neurons can be

packed next to each other with no space in between, allowing for a formal definition of a partition

(see appendix). Each neuron can therefore be expressed as non-overlapping subintervals of the

form $[x, x + \Delta x)$, where Δx is the width of each neuron. Note that each neuron can be uniquely

identified by the point at the closed end, which also gives its location along the tonotopic axis. The

set containing these points is:

Figure 2: **Mathematical representation of neural and acoustic Spaces.** ***a***, neurons on the tonotopic axis are positioned next to each other with no space in between. Pure tone stimuli activate afferents onto a subset of neurons (cyan, blue). ***b***, mathematical representation of neural space. The tonotopic axis is a half-open interval (magenta) partitioned into smaller intervals that represent the space (Δx) taken up by neurons. The synaptic fields ($h_{x_\alpha,\lambda_\alpha}, h_{x_\beta,\lambda_\beta}$) are also half-open intervals. ***c***, The acoustic space has two dimensions, with frequency as one axis and pressure as the other. The frequency and pressure spaces are partitioned into half-open intervals of length $\Delta f, \Delta p$, respectively. ***d***, Mapping two tones in the acoustic space to intervals in neural space via a function ψ.

$$\mathcal{X} = \{x_1, x_2, \ldots, x_{N_{cell}}\} \tag{1}$$

A synaptic field spans an integral number (n_λ) of neurons and is also defined as a half-open interval with length $\lambda = n_\lambda \Delta x$. The length λ ranges from Δx (1 cell) to a maximum $\lambda_{max} = n_{\lambda,max} \Delta x$. Each synaptic interval, designated as $h_{x,\lambda} = [x, x + \lambda)$, is uniquely identified by the location of the cell at the closed end (x_α, x_β in Fig. 2b) and by its length ($\lambda_\alpha, \lambda_\beta$). The set of starting points $\mathcal{X}_\lambda$ and the set of achievable lengths Λ are given by:

$$\mathcal{X}_\lambda = \{x_1, x_2, \ldots, x_{N_\lambda}\}, N_\lambda = N_{cell} - n_{\lambda,max} \tag{2}$$
$$\Lambda = \{\lambda_1, \lambda_2, \ldots, \lambda_{max}\}$$

As will be shown below, $\mathcal{X}_\lambda$ will contain information about the frequency while Λ will contain information about the sound pressure.

102   The set of all synaptic intervals in neural space is a basis for topology on the neural space,

103   which will be used to define algebraic operations and construct mapping from acoustic space (see

104   below, appendix).

Representing sound in neural space

The elements of acoustic space $\mathcal{A}$ are pure tones, each of which is characterized by a sine wave of a

given frequency (f) and amplitude corresponding to sound pressure (p). Theoretically, frequencies

and pressures can take an uncountable number of values but physiologically, the audible range is

bounded by minimum and maximum values.

The acoustic space has two dimensions with frequency as one axis and sound pressure as the

other. As was done for neural space, the frequency and pressure axes are defined as a half-open

intervals and divided into non-overlapping subintervals expressed as $[f, f + \Delta f)$ and $[p, p + \Delta p)$,

respectively (Fig. 2c). Physiologically, Δf and Δp may be viewed as the minimum frequency and

pressure difference that can be discriminated [8, 9, 10, 11]). For example, two tones with frequencies

f_α, f_β that are in the interval $[f_1, f_1 + \Delta f)$ will both be 'assigned' to f_1 (see appendix). Therefore,

the sets of audible frequencies and pressures are given by the first points of each interval:

$$\mathcal{F} = \{f_1, f_2, \ldots, f_{N_f}\} \tag{3}$$

$$\mathcal{P} = \{p_1, p_2, \ldots, p_{N_p}\}$$

117   Features of the acoustic space are represented in neural space via a mapping ψ (Fig. 2d; see

118   appendix for formal treatment). A pure tone $a_{f,p} \in \mathcal{A}$ is mapped to an interval $h_{x,\lambda}$ by first

119   mapping the components f to x and p to λ via $\psi_f(f) = x$ and $\psi_p(p) = \lambda$.

$$\psi(a_{f,p}) = h_{\psi_f(f),\psi_p(p)} = h_{x,\lambda} \tag{4}$$

120   By adjusting the number of elements in each space appropriately, the mapping becomes bijective

121   (one-to-one, onto).

¹²² A mapping from acoustic space to intervals that are inhibitory can be similarly defined. The
¹²³ mapping is complicated by the fact that the number and receptive field properties of excitatory ($\boldsymbol{E}$
¹²⁴) and inhibitory ($\boldsymbol{I}$) cells differ. The mapping is under ongoing investigation but for purposes of
¹²⁵ the present analyses, the mapping is taken to be identical to that for $\boldsymbol{E}$.

Algebraic operations with synaptic intervals

¹²⁷ Having formally described the mathematical structure of neural space, it is now possible to define
¹²⁸ the algebraic operations -addition and multiplication- for combining and modulating synaptic in-
¹²⁹ tervals (Fig.1b,c). An important condition that must be satisfied is that operations be 'closed'; that
¹³⁰ is, the result obtained with addition or multiplication is an interval (or intervals) that remains in
¹³¹ neural space. To simplify notation, the intervals will henceforth be identified with a single subscript
¹³² or superscript.

Figure 3: **Addition and Multiplication.** *a*, schematic of network receiving three excitatory afferent inputs. *i*, half-open intervals representing the synaptic fields. *ii*, addition (union) of different combinations of intervals. **b**, schematic of network receiving two excitatory inputs (orange, cyan) and an inhibitory input (red). *i*, half-open intervals associated with the activated afferents. *ii*, multiplication (set minus) of each excitatory intervals by the inhibitory interval.

To satisfy closure, 'addition' of synaptic intervals is defined as their union. Let h_α, h_β be two synaptic intervals. Then,

$$h_\alpha + h_\beta \stackrel{\text{def}}{=} h_\alpha \cup h_\beta \tag{5}$$

¹³³ The addition operation yields two possible results (see appendix for details). If the two synaptic

intervals do not overlap (h_β, h_γ in Fig. 3ai), the union yields a set with the same two intervals (Fig. 3aii, bottom). If the two intervals overlap (h_α and h_β, h_α and h_γ), the result is a single interval whose length depends on the amount of overlap (Fig. 3aii, top two traces). Note that summation is sublinear: e.g. $|h_\alpha + h_\gamma| < |h_\alpha| + |h_\gamma|$. Moreover, if the starting points are the same (h_α and h_β), the length is equal to that of longer summand ($|h_\alpha + h_\beta| = |h_\alpha|, |h_\alpha| \geq |h_\beta|$).

It is noteworthy that there is some ambiguity from a decoding perspective because the addition operation will fuse overlapping intervals into a larger, single interval (e.g. $h_\alpha + h_\gamma$ in Fig. 3a). It would not be possible to determine whether a synaptic interval is a result of a single high intensity pure tone, multiple low intensity pure tones with small differences in frequencies, or band limited noise (see Discussion).

Closure is satisfied because the union of an arbitrary number of overlapping intervals results in an interval that is always within the neural space. The union of any number of disjoint intervals is also within the neural space (more accurately, is a subset of the topology defined in neural space, see appendix). A notable property that will be important later is that there is no additive inverse that can decrease the interval length.

One example of addition that occurs under biological conditions is when a pure tone arrives simultaneously to the two ears. The signal propagates separately through the auditory pathway but eventually converges at some brain region. Because each input is due to the same tone, the resultant synaptic intervals will be at same location (i.e. have the same starting points) on the tonotopic axis, though their lengths may differ because of interaural intensity differences (orange and blue intervals in Fig. 3a). Fig. 4a (top panel) shows the predicted total length when two intervals with different lengths are added (the length of the cyan interval is fixed while that of the blue is increased). The total length is equal to the length of the longer interval: hence, it is initially constant and equal to that of the cyan interval but then increases linearly when the length of the blue interval becomes longer.

Addition also takes place when the sound is composed of two pure tones with different frequencies. This would generate two synaptic intervals with different starting points and possibly different lengths (e.g. orange and cyan intervals in Fig. 3a). The total length depends on the degree of overlap between the intervals. In Fig. 4a (bottom panel), the location of one interval (cyan) is fixed while the other (blue) is shifted rightward. When the two intervals completely overlap, the

Figure 4: **Predicted effects of addition and multiplication**. **a**, **top**, addition of two intervals (cyan, blue) when the length of one interval (blue) is increased (top). **bottom**, one interval (blue) is shifted to the right of the other (cyan). **b, top**, multiplication of an excitatory interval (blue) by an inhibitory interval of increasing length (red). **bottom**, multiplication when the inhibitory interval is shifted to the right. **c, top**, effects of inhibition (red) on two excitatory intervals (blue, cyan). With the inhibitory interval at a fixed location, the distance between the excitatory intervals is increased systematically. **bottom**, Effects of two inputs configured as center-surround where the excitatory intervals (blue, cyan) are each flanked by two inhibitory intervals (red, magenta). One of the inputs is shifted systematically to the right of the other. Predicted product length when the inputs occur simultaneously (orange) and when calculated with inputs delivered sequentially.

total length is equal to the length of one interval. As the blue interval is shifted, the total length

increases linearly and plateaus when the two intervals become disjoint.

Inhibition decreases the excitability of the network and would be expected to reduce the size

of the synaptic interval. This is not possible with the addition operation because there is no

inverse (i.e. 'subtraction' is not defined). Therefore, to incorporate the effects of inhibition, a

'multiplication' operation is introduced (Fig. 3b). Multiplication ('·') of an excitatory synaptic

interval h^E by an inhibitory interval h^I is defined as:

$$h^I \cdot h^E \overset{\text{def}}{=} h^E \setminus h^I \tag{6}$$

The set minus operation "\" eliminates the points from the multiplicand h^E that it has in

common with the multiplier h^I (Fig. 3b*i,ii*) thereby decreasing the multiplicand's length. Note

that this differs from the more common set theoretic definition of multiplication, where the product

of sets is given by their intersection. Multiplication yields several results, depending on the relative

locations and size of the multiplicand and the multiplier (see appendix). If the excitatory ($\boldsymbol{E}$) and

inhibitory ($\boldsymbol{I}$) intervals do not overlap, then the $\boldsymbol{E}$ interval is unaffected. If the intervals overlap

(h_α^E and h^I), then the $\boldsymbol{E}$ interval is shortened ($h^I \cdot h_\alpha^E$ in *ii*). If the $\boldsymbol{E}$ interval (h_β^E) is completely

within the $\boldsymbol{I}$ interval, the product is the empty set, indicating complete cancellation ($h^I \cdot h_\beta^E$ in *ii*).

Multiplication can also change the starting points of the intervals and split an interval into two

separate intervals (not shown, see appendix). Multiplication satisfies the closure property as the

resulting interval is a half-open interval that is always in neural space. Other algebraic properties

are discussed in appendix.

If the excitatory and inhibitory inputs are co-activated (as in feedforward circuits), then the

$\boldsymbol{E}$ and $\boldsymbol{I}$ intervals will be at the same location (same starting points) on the tonotopic axis but

may have different lengths. Fig. 4b (top panel) plots the predicted length of the product when

the $\boldsymbol{E}$ interval is multiplied by $\boldsymbol{I}$ intervals of increasing lengths. The product length decreases and

becomes zero when length of the $\boldsymbol{I}$ interval exceeds that of the $\boldsymbol{E}$ interval.

If the $\boldsymbol{E}$ and $\boldsymbol{I}$ inputs are independent of each other, the synaptic intervals could be at different

locations on the tonotopic axis. Figure 4b (bottom panel) plots the length of the product when

the starting point of the $\boldsymbol{I}$ interval (red) is shifted systematically to the right of the $\boldsymbol{E}$ interval

(blue). The product length is zero when the $\boldsymbol{E}$ and $\boldsymbol{I}$ intervals overlap completely (separation =

0) and increases linearly as the overlap decreases, eventually plateauing to a constant value when

the intervals become disjoint.

With addition and multiplication defined, the rules for combining the two operations can now

be determined. A simple case is when a network receives two excitatory inputs that results in

synaptic intervals (h_α^E, h_β^E) and a single inhibitory input that result in an inhibitory interval (h^I).

This scenario would occur if binaural excitatory inputs that converge in a network are then acted

on by local inhibitory neurons. When all three inputs are activated simultaneously, the intervals

combine in neural space as $h^I \cdot (h_\alpha^E + h_\beta^E)$. It can be shown that multiplication is *left* distributive

so that (see appendix):

$$h^I \cdot (h_\alpha^E + h_\beta^E) = (h^I \cdot h_\alpha^E) + (h^I \cdot h_\beta^E) \tag{7}$$

Intuitively, this means that the effect of a single inhibitory input on two separate excitatory inputs can be calculated by computing the inhibitory effects on each separately and then adding the results. Multiplication, however, is not *right* distributive. Thus, given two inhibitory intervals (h_α^I and h_β^I) acting on a single excitatory interval (h^E):

$$(h_\alpha^I + h_\beta^I) \cdot h^E \neq (h_\alpha^I \cdot h^E) + (h_\beta^I \cdot h^E) \tag{8}$$

Fig. 4 c (top panel) plots the predicted length when two **E** intervals are multiplied by an **I** interval as per eq. 7 ($|h^I \cdot (h_\alpha^E + h_\beta^E)|$). The two **E** intervals (blue, cyan) are shifted, respectively, left- and rightward relative to the **I** interval (red). The product length is zero as long as the two **E** intervals are within the **I** interval. When the two **E** intervals reach and exceed the borders of the **I** interval, the product length increases and reaches a plateau when the **E** and **I** intervals become disjoint.

A common physiological scenario is when sound is composed of two pure tones and each tone results in an excitatory synaptic field surrounded by an inhibitory field (center surround inhibition, Fig. 4c, bottom panel). The corresponding composite interval contains an excitatory interval that is flanked by two inhibitory intervals (inset). Letting the **I** -**E** -**I** interval triplet generated by each tone be $(h_\alpha^I + h_\beta^I) \cdot h_\alpha^E$ and $(h_\gamma^I + h_\delta^I) \cdot h_\beta^E$, the expression when both occur simultaneously is:

$$(h_\alpha^I + h_\beta^I + h_\gamma^I + h_\delta^I) \cdot (h_\alpha^E + h_\beta^E) \tag{9}$$

In Fig. 4c (bottom panel, orange curve), the location of one composite interval is shifted rightward. When the composite intervals coincide (separation $=0$), the product length is equal to that of a single excitatory interval. With increasing separation, the product length decreases towards zero but then increases, reaching a plateau when the excitatory and inhibitory components of each

220 composite interval no longer overlap.

221 It is worth noting that the effect of introducing two tones simultaneously cannot be predicted
222 by introducing each separately and then combining the results (see Appendix). That is,

$$(h_\alpha^I + h_\beta^I + h_\gamma^I + h_\delta^I) \cdot (h_\alpha^E + h_\beta^E) \neq (h_\alpha^I + h_\beta^I) \cdot h_\alpha^E + (h_\gamma^I + h_\delta^I) \cdot h_\beta^E \qquad (10)$$

The green curve in Fig. 4 c (bottom panel) is the predicted product length when the I -E -I
triplet pairs are delivered separately and their product lengths subsequently summed. Intuitively,
the curves differ because the effects of inhibition on the adjacent excitatory interval is absent;
indeed, the result resembles that of adding two excitatory intervals (Fig. 4a, bottom panel). A
practical implication is that the intervals due to complex sound cannot be predicted by presenting
individual tones separately (see Discussion).

Simulations with spiking neurons

Key features of the mathematical model were examined with simulations performed on a 2 dimen-
sional network model of spiking excitatory and inhibitory neurons [25]. Both E and I neuron
population receive a Gaussian distributed excitatory drive from an external source (Fig. 5a); the E
cells in addition receive feedforward inhibitory inputs from the I cells. Stimulation evokes Gaussian
distributed excitatory inward currents in both populations and also inhibitory currents in the E
cells (profiles of currents shown in insets). With brief stimuli, the recurrent connections between
neurons [26] do not contribute significantly to activity in auditory cortical circuits [25] and were
omitted. The region encompassing neurons that fire is henceforth referred to as the activated area
(Fig. 5b, top panel). The underlying synaptic field (bottom panel) is described by the area of the
network where the *net* synaptic inputs to cells exceeded (were more negative than) rheobase, the
minimum current needed to evoke an action potential (I_{Rh}, inset). As defined, the synaptic field
is a composite of all the inputs, both excitatory and inhibitory, that are evoked during a stimulus.
Both the activated area and the synaptic field are quantified either by the diameters of circles fitted
to the boundary points (magenta) or by the length of their projections to one axis (orange bar).

 Note that the spatial dimensions have units of *cell number* (see Methods to convert to microns).

Figure 5: **Simulations with spiking neurons.** a, Network consists of excitatory and inhibitory neuron populations. An external drive evokes excitatory inputs in both populations (blue disks) and inhibitory inputs to the E cells (red disk). $insets$, profiles of excitatory (blue) and inhibitory (red) currents evoked in the E and I populations. b, $bottom$, synaptic field evoked in the network during a stimulus. The spatial extent of the synaptic field is quantified either by the diameter of a circle fitted to its outermost points (magenta) or by the length of its projection to the tonotopic axis (orange bar). $inset$, profile of net synaptic current generated in the E cell population. The perimeter of the synaptic field encompasses cells whose net synaptic current input exceeded rheobase (I_{Rh}). top, activated area contains cells that fired action potentials (dots).

To test the addition operation, two external excitatory drives were delivered to the center of the network simultaneously (without inhibition). Increasing the width (by increasing the standard deviation σ_α of the external drive) of one stimulus, while keeping that (σ_β) of the other fixed, increased the diameters of the synaptic field and activated areas (Fig. 6a, top panel, i-iii). As predicted, the diameters of the synaptic field (bottom panel, orange) and activated area (black) initially did not change when σ_α was smaller than σ_β ($\frac{\sigma_\alpha}{\sigma_\beta} < 0.5$) but then increased as σ_α continued to widen. However, because the synaptic currents were Gaussian distributed (Fig. 5b, bottom panel), the curve started to increase before σ_α became equal to σ_β ($\frac{\sigma_\alpha}{\sigma_\beta} = 1$). When delivered simultaneously, the magnitude of the composite current increased, causing the region that exceeded rheobase to widen (Fig 6 a, top panel, compare synaptic field evoked with a single stimulus (i) to

 that evoked with 2 stimuli (*ii*)). The diameter can be calculated from the standard deviations of

256 the two inputs (diameter $\propto \sqrt{\sigma_\alpha^2 + \sigma_\beta^2}$, not shown).

Figure 6: **Test of addition. *a, top***, Activated area (top; 1 sweep) and underlying synaptic field (bottom; average of 25 sweeps). ***i***, one stimulus. ***ii-iii***, two stimuli delivered to the center of the network. The width of one input was systematically increased (σ_α: 2- 45 cells) while that of the other ($\sigma_\beta = 20$ cells) was kept constant. ***bottom***, plot of synaptic field (orange) and activated area (black) diameters vs $\frac{\sigma_\alpha}{\sigma_\beta}$. Dashed curve is predicted relation. ***b***, addition of two spatially separated excitatory inputs ($\sigma_\alpha = \sigma_\beta = 10$). ***top, i - iii***, activated areas and synaptic fields with increasing stimulus separation. Inset in ***ii*** shows example of excitatory synaptic current profiles. ***bottom***, projection length vs. separation distance for synaptic field (orange) and activated area (black). Dashed curves are predicted changes.

To examine the addition of spatially disparate synaptic fields, two excitatory inputs were deliv-

ered at different distances from each other (Fig. 6b, top panel). Consistent with the prediction, the

projection lengths of the synaptic field (bottom panel, orange) and activated areas (black) increased

with stimulus separation and reached a plateau when the two inputs became disjoint (*iii*). The

projection lengths were greater than predicted (dashed lines) when the separation was small (< 10

cells) and when the intervals were just becoming disjoint (at separation ~ 40 cells, *ii*) due to the

summation properties of the Gaussian distributed inputs discussed above.

To test the multiplication operation, the ***E*** and ***I*** neurons were stimulated simultaneously,

resulting in excitatory and inhibitory synaptic currents in the **E** cells (inset in top panel of Fig.

7a *ii*). The width of the excitatory input (σ_{exc}) was kept constant while that of the inhibitory

input (σ_{inh}) was increased systematically. As predicted, the diameter of the synaptic field (bottom

panel, orange) and activated area (black) decreased with increasing σ_{inh}. However, the diameter

asymptoted towards a non-zero value. Because the network was feedforward, the inhibitory input

was delayed relative to excitation by about 10-15 ms; as a result, there was always a time win-

dow where excitation dominated. The excitatory synaptic input was not canceled even when the

inhibition was twice as wide (top panel, *iii*).

Figure 7: **Test of multiplication. *a, top, i-iii*** activated areas and synaptic fields evoked with excitatory ($\sigma_{exc} = 20$) and inhibitory ($\sigma_{inh} = 2 - 45$) inputs. The spatial extent of the inhibition is demarcated by the red circles (inner circle: 1 σ_{inh}; outer: 2 σ_{inh}). Inset in ***ii*** shows an example of excitatory (blue) and inhibitory (red) synaptic current profiles. ***bottom***, plot of activated area (black) and synaptic field (orange) vs $\frac{\sigma_{inh}}{\sigma_{exc}}$. ***b***, Same as in ***a*** except that the excitatory input ($\sigma_{exc} = 10$) was shifted systematically to the right of inhibition ($\sigma_{inh} = 10$). ***bottom***, Diameters of activated area (black) and synaptic field (orange) plotted against separation between excitatory and inhibitory synaptic fields

.

273 To examine multiplication of spatially disparate **E** and **I** inputs, the excitatory input was

274 shifted systematically to the right of the inhibitory input (Fig. 7b). As predicted, the diameters

275 of the synaptic field (bottom panel, orange) and activated area (black) increased with the **E** -**I**

separation and plateaued when the $\boldsymbol{E}$ and $\boldsymbol{I}$ inputs became disjoint (*iii*).

To examine how multiplication distributes over addition, two excitatory inputs and one inhibitory input were delivered simultaneously to the network (Fig. 8a). This is the analog of the left hand side of (eq. 7). All three inputs were initially at the center and then with the inhibition stationary, the two excitatory inputs were shifted left and right (Fig. 8a, top panel, *i-iii*). As predicted, the projection length of the synaptic field increased towards an asymptotic value (bottom panel, orange). To reproduce the right hand side of eq. 7, simulations were performed with inhibition, first with one of the excitatory inputs and then with the other; the resultant projection lengths of each were then summed (green). As was observed with simultaneous stimulation, the projection length increased with separation. The match was poor at small separations <10 cells (*i*) and at separation of ∼ 30 cells (*ii*) because the interaction between the Gaussian excitatory currents (see above) did not factor in when each input was delivered separately. The two curves were nearly identical at separations of 40-80 cells. In this range the $\boldsymbol{E}$ inputs were disjoint (as indicated by the plateauing of the excitation-only curve (dashed orange)) but still overlapped with the inhibitory synaptic field (the orange and green curves were below the excitation-only curve).

Finally, the interaction of inputs with center-surround inhibition (eq. 9) was examined by delivering two excitatory inputs, each with associated inhibitory components (inset in Fig, 8b, top panel, *iii*), to the network. The distance between the inputs were then increased systematically and the projection lengths measured (bottom panel, orange curve). At separations > 20 cells, the projection length of the synaptic field decreased to a minimum (*ii*) and then increased towards a plateau (*iii*), consistent with the prediction (Fig. 4c, bottom panel). However, at separations < 20 cells, the length increased instead of decreasing; this is likely due to the interaction of the Gaussian distributed excitatory fields discussed above. To confirm that the same result cannot be obtained by presenting each stimulus separately (right hand side of eq. 10), each $\boldsymbol{E}$ -$\boldsymbol{I}$ pair was delivered sequentially and the individual projection lengths summed. Unlike with simultaneous stimulation and consistent with the prediction (green curve in Fig. 4c,bottom panel), the projection length increased monotonically to a plateau without a dip (green curve).

Figure 8: **Test of distributive properties. *a, top, i-iii*** Representative activated areas and synaptic fields generated by two excitatory inputs and a single inhibitory input ($\sigma_{exc} = \sigma_{inh} = 10$). With the location of inhibition fixed, the two excitatory inputs were separated systematically. The spatial extent of the inhibition is demarcated by the red circles (inner circle: $1\ \sigma_{inh}$; outer: $2\ \sigma_{inh}$). Inset in ***iii*** shows the excitatory (blue) and inhibitory (red) synaptic current profiles. ***bottom***, plot of synaptic field projection lengths (orange) vs separation of the excitatory inputs. Green symbols are projection lengths obtained with the sequential stimulation protocol (see text). Dotted curve is with no inhibition. ***b***, Simulations with two excitatory-inhibitory pairs, each with center-surround configuration (see inset in ***iii***). ***bottom***, legend as in ***a*** except that the green traces plot the projected lengths obtained when each ***E*** - ***I*** pair ($\sigma_{exc} = 10, \sigma_{inh} = 17$) was delivered sequentially (see text).

Discussion

The aim of this study was to develop a mathematical framework for a place-code and derive the underlying principles for how tones of varying frequencies and intensities are represented, assembled, and modulated in networks of excitatory and inhibitory neurons. The analyses are not intended to replicate the detailed aspects of biological networks but rather to clarify the minimal conditions that must be met for a viable place coding scheme, to aid in the interpretation of experimental data, and to provide a blueprint for developing computational models. Taking a mathematical approach ensures that the terms and variables are clearly defined.

Key findings are as follows (detailed below). First, the 'functional unit' of neural space is a set of contiguous neurons that have flexible borders. The associated mathematical architecture, or topology, is a collection of half-open intervals of varying lengths. The frequency and intensity of pure tones are encoded solely by the location and length of the intervals. Second, the architecture dictate the range and resolution of tone frequencies and intensities that can be represented in neural space. Finally, operations in neural space for combining and modulating units are 'addition' defined as the union and 'multiplication' defined as the set minus operation. Together, they form the algebraic structure that determine the type of computations that can be performed within a place-coding scheme.

Significance

Implications for place code

In order to encode both frequency and intensity, the 'functional' units in the model have flexible, expanding borders. Each is a contiguous set of neurons that receive tone-evoked synaptic inputs (synaptic field) represented by synaptic intervals. Encoding sound involves mapping a point in acoustic space (pure tone with frequency f and pressure p) to an element in neural space (interval at location x with length λ). It is noteworthy that a tone is represented by a population of neurons and that it is not possible to decode the tone frequency or intensity from the firing of a single neuron.

The study suggest that a purely place coding scheme is sufficient for representing sound. Other variables such as firing rate and spike timing [7, 24, 11] are not essential and may in fact be unavailable for brief stimuli (see Introduction). These variables may, however, play important complementary roles in improving coding and perception: for example, frequency and intensity discrimination improves with stimulus duration [8, 9, 10, 11] and when phase-locking is factored in [27].

The expanding synaptic intervals is crucial for maintaining simultaneously high resolution frequency and pressure representation. To see this, consider an alternate model with functional units that are non-overlapping clusters of neurons with fixed dimensions, similar to the classical cortical columns ([17], see appendix). In this version, frequency is encoded by the location of the active

column along the tonotopic axis and pressure by the number of active neurons within the column (population rate code; for brief stimuli where neurons are binary). As shown in the appendix, the number of frequency levels that can be represented is inversely proportional to the number of pressure levels ($|\mathcal{F}| = \frac{N_{cell}}{|\mathcal{P}|}$, where N_{cell} is the number of cells in the network). In contrast, for an expanding synaptic interval, the relation is linear: $|\mathcal{F}| = N_{cell} - |\mathcal{P}|$. Thus, compared with columns, the number of frequency levels drops off at a slower rate with the number of pressure levels.

The mathematical analyses confirms that an inherent problem with the place coding scheme is that it is not possible to completely decode features of multi-component sound stimulus. Another consequence of addition is that two intervals generated by two tones that have similar frequencies and/or high intensities can fuse into a single interval. In such a case, the inverse mapping (ψ^{-1}) yields a single tone. Ambiguities are in fact manifested in psychophysical experiments: subjects perceive tones with small differences in frequencies as a single, louder tone [28] and have difficulties distinguishing the individual components of a multi-frequency stimulus [29, 30].

Implications for experimental data and computational models

The algebraic operations determine the computations that can be performed with a place code. An important property for addition and multiplication is that the results remain within the neural space (closure property). This would not be true, for example, if addition is defined as the standard sum of the interval lengths ($|h_\alpha| + |h_\beta|$) because the result could exceed the boundaries of the neural space if each interval is too long or located near the edge of the tonotopic axis. To ensure closure, addition is defined as the union and multiplication as the set difference operation. Compared with the more familiar vector space, the number of allowable computations is relatively limited (see appendix); many of the linear algebraic operations used commonly for analyses and computational models are generally not permitted.

The representation of complex sound cannot generally be predicted by examining the tonal components individually and then combining them, particularly if inhibition is involved. As shown in Eq. 10 and Fig. 4, the response of two tones presented simultaneously is not a simple combination of the responses to each tone separately. This is in line with experimental data showing that the response of neurons to pure tones and white noise stimuli differ [31]. The implication is that the neural representations of naturalistic sound cannot be reconstructed by presenting pure tones and

then assembling the responses.

The distributive properties dictates how data from separate experiments may be combined.
The effect of inhibition acting on two excitatory inputs can be predicted by examining the effects
of inhibition on each input separately and then summing the results (eq. 7). Auditory networks
often have inhibitory neurons that act locally to modulate external excitatory inputs [32]. Thus,
the responses of binaural inputs can be predicted by adding the responses to monaural inputs even
when each are acted on separately by common inhibition. However, this distributive property does
not apply for two sources of inhibition acting on a single excitatory interval (eq. 8). In cortical
circuits, for example, excitatory neurons can be innervated by several classes of local inhibitory
interneurons [33]. In this case, the model suggests that accurately determining the overall effect
of inhibition requires that the inhibitory interneurons be stimulated simultaneously along with the
excitatory inputs; estimating the effect by sequential stimulation of each excitatory-inhibitory pair
is generally incorrect.

An important prediction is that the result of adding two overlapping intervals is always sublinear.
If the intervals also have the same starting point, as would occur during binaural stimulation, the
resulting length is equal to that of the longer summand (i.e. $|h_\alpha| + |h_\beta| = |h_\alpha|, |h_\alpha| \geq |h_\beta|$).
Therefore, the responses evoked during binaural stimulation should always be less than twice the
responses evoked with each ear. This prediction is supported by electrophysiological experiments
where the response evoked binaurally is in fact equal to larger of two responses evoked monaurally
[34] (see figure in appendix). Similarly, assuming that loudness perception is linked to the length
of the interval, a possible psychophysical analog is that a tone presented binaurally is perceived to
be less than twice as loud as monaural stimulation [35]. In both examples, the apparent sublinear
effects arises from the properties of addition operation, and may not necessarily be due to inhibitory
processes.

The functional unit was defined as the synaptic interval rather than the activated area, which
reflects the number of neurons that actually fired. This facilitated analyses because multiplication
by inhibitory synaptic intervals could be more easily incorporated into the mathematical framework.
Though measuring the intracellular potentials of a large population of cells is currently not feasible
experimentally, the extent of the synaptic field may be estimated from the activated area (Figs.
5,6,7,8), which can, in principle, be measured with imaging techniques [36, 37, 38]. Also, as

mentioned above, the size of the synaptic field can also be inferred indirectly from the receptive fields of individual neurons.

For mathematical convenience, the location of the synaptic intervals was identified by the left-most point (closed end) of the interval with increases in intensity signaled by a lengthening of the interval in the rightward (high frequency) direction. Similar behavior has been observed in the cochlea albeit in the opposite direction: an increase in the intensity causes response area to increase towards low frequency region of the basilar membrane while the high frequency cutoff remains fixed [39, 23, 3]. The choice of the leftmost point to tag the interval is arbitrary and any point in the interval will suffice provided an analogous point can be identified uniquely in each interval in the set. Experimentally, using the center of mass of active neurons as the identifier might be more practical.

Assumptions and limitations

The mathematical model is based on two salient features of the auditory system. One is that the neural space is organized tonotopically. Tonotopy has been described in most neural structures in the auditory pathway, from brainstem areas [4, 40, 41] to at least layer 4 of primary auditory cortex. Whether tonotopy is maintained throughout cortical layers is controversial, with some studies (all in mice) showing clear tonotopy [42, 43, 38, 36] and others showing a more 'salt-and-pepper' organization [37, 44, 36]. A salt-and-pepper organization suggests that the incoming afferents are distributed widely in the neural space rather than confined to a small area. The model needs a relatively prominent tonotopy to satisfy the requirement that synaptic intervals encompass a contiguous set of cells.

A second requirement is that the size of the synaptic interval and activated area increase with the intensity of the sound. Intensity-related expansion of response areas occurs in the cochlea [22, 23, 39] and can also be inferred from the excitatory frequency-response areas (FRAs) of individual neurons. The FRAs, which document the firing of cells to tones of varying frequencies and intensi-ties, are typically "V-shaped" (see Figure in appendix for examples). At low intensities, neurons fire only when the tone frequencies are near its preferred frequency (tip of the V). At higher intensities, the range of frequencies that evoke firing increases substantially [45, 43]. If adjacent neurons have comparably-shaped FRAs but have slightly different preferred frequencies, an increase in intensity

would translate to an increase in the spatial extent of activated neurons.

The algebraic operations were derived from set theoretic operations and the magnitude of the underlying synaptic inputs were irrelevant. Under biological conditions, the input magnitude determines the degree to which biophysical, synaptic, and network processes become engaged, which will affect the length of the synaptic intervals and activated areas. Not surprisingly, the results of the network simulations deviated quantitatively from the mathematical predictions in some regimes (compare Fig. 4 to Figs 6, 7). Most of the discrepancies in the simulations were because the magnitudes of the synaptic inputs were Gaussian distributed along the tonotopic axis. In biological networks, the discrepancies may be exacerbated by the presence of threshold processes such as regenerative events [46, 47]. The underlying algebraic operations may be obscured in regimes such as these.

The model incorrectly assumes that the strength of inhibition is sufficiently strong to fully cancel excitation. This facilitated analysis because the effect of multiplication depends solely on the overlap between the multiplicand and multiplier. As the simulations with the feedforward network showed, the excitation cannot be fully canceled by inhibition owing to synaptic delay. Moreover, the balance may be spatially non-homogeneous: in center-surround suppression, excitation dominates at the preferred frequency with inhibition becoming more prominent at non-preferred frequencies [45, 48, 49]. To apply multiplication to biological systems, it may be necessary to define empirically an "effective" inhibitory field that takes into account for E -I imbalances.

Methods and Materials

Simulations were performed with a modified version of a network model used previously [25]. Briefly, the model is a 200 x 200 cell network composed of 75% excitatory (E) and 25% inhibitory (I) neurons. The connection architecture, synaptic amplitudes/dynamics, and intrinsic properties of neurons were based on experimental data obtained from paired whole-cell recordings of excitatory pyramidal neurons and inhibitory fast-spiking and low threshold spiking interneurons [26]. For this study, the low-threshold spiking interneurons and the recurrent connections between the different cell types were removed, leaving only the inhibitory connections from fast spiking interneurons to pyramidal neurons. The connection probability between the inhibitory fast-spiking cells and the

excitatory pyramidal cells was Gaussian distributed with a standard deviation of 75 μm and peak of 0.4 [26].

Both $\boldsymbol{E}$ and $\boldsymbol{I}$ cells received excitatory synaptic barrages from an external source. The synaptic barrages to each cell (50 ms duration) represented the activity of a specified number of presynaptic neurons; the number was Gaussian distributed in space (Fig. 5 a, bottom). This resulted in excitatory synaptic currents in the $\boldsymbol{E}$ and $\boldsymbol{I}$ cell populations and inhibitory synaptic currents in the $\boldsymbol{E}$ cell population after the $\boldsymbol{I}$ cells fired (insets in Fig. 5a). The spatial extents of the synaptic inputs were varied by changing the standard deviations of the external drive. In some simulations, the $\boldsymbol{E}$ and $\boldsymbol{I}$ cell populations were uncoupled and received separate inputs that could be varied independently of each other.

The neurons are adaptive exponential integrate-and-fire units with parameters adjusted to replicate pyramidal and fast spiking inhibitory neuron firing (see [25] for the parameter values). The cells fired at most one action potential when stimulated with the synaptic barrage. The synaptic barrages were randomized so that the synaptic fields and activated areas varied from trial to trial.

The synaptic field was defined as the area of the network where the net synaptic currents to the cells exceeded rheobase, the minimum current needed to evoke an action potential in the $\boldsymbol{E}$ cells (I_{Rh}, inset in Fig. 5b, bottom panel). I_{Rh} was estimated by calculating the net synaptic current near firing threshold (V_θ): $I_{\text{net}} = g_{exc} * (V_\theta - E_{exc}) + g_{inh} * (V_\theta - E_{inh})$ where g_{exc}, g_{inh} are the excitatory and inhibitory conductances, respectively, and $E_{exc} = 0$ mV, $E_{inh} = -80$ mV are the reversal potentials. For the $\boldsymbol{E}$ cells, rheobase is approximately -0.27 nA.

The spatial extent of the synaptic field or activated area was quantified as the diameter of a circle fitted to the outermost points (maroon circles in Fig. 5b). In simulations with multiple components, the spatial extents were quantified as the total length of the projection onto the tonotopic axis (orange bar in Fig. 5b, bottom panel). The diameters and lengths have units of cell number but can be converted to microns by multiplying by 7.5 μm, the distance between $\boldsymbol{E}$ cells in the network. For all plots, the data points are plotted as mean +/- standard deviation compiled from 20-100 sweeps.

Acknowledgements

I thank L-S Young and A. Bose for reading the manuscript and providing helpful comments. This work was supported by DARPA- Lifelong Learning Machines

 # Appendix

 ## Acoustic Space

The general approach for defining acoustic space is as follows. The elements of acoustic space are pure tones of varying frequencies and sound pressures and may be expressed as a product of frequency space $S_{\mathcal{F}}$ and pressure space $S_{\mathcal{P}}$: $S_{\mathcal{A}} = S_{\mathcal{F}} \times S_{\mathcal{P}}$. Biologically, the range of audible and discriminable frequencies and sound pressures are limited. To reflect this, the frequency and pressure spaces will each be defined as a topological space where the underlying set is an interval but the topology is coarser than the usual topology.

The frequency space $(S_{\mathcal{F}})$ is defined as a half-open interval on the positive real line: $S_F = [f_{min}, f_{max}) \subset \mathbb{R}^+$, where f_{min}, f_{max} are the minimum and maximum audible frequencies, respectively. To account for the fact that discriminability is limited (i.e. tones of similar frequencies are perceived as the same), $S_{\mathcal{F}}$ is partitioned into N_f half-open intervals $h_f = [f_\alpha, f_\beta) = [f_\alpha, f_\alpha + \Delta f)$ where $\Delta f = \frac{1}{N_f}$ is the length of the interval and represents biologically the minimum frequency difference that can be discriminated. The use of half-open intervals ensures that there is no 'gap' between adjacent frequency intervals. The set of all half-open intervals is:

$$\mathcal{H}_{\mathcal{F}} = \{h_f = [f_{min} + i\Delta f, f_{min} + (i+1)\Delta f) \mid f \in S_{\mathcal{F}}, i \in \mathbb{N}_0, i < N_f\} \qquad (1)$$

The topology $\tau_{\mathcal{F}}$ is generated by the elements of $\mathcal{H}_f$:

$$\tau_{\mathcal{F}} = \{\bigcup H_f \mid H_f \subseteq \mathcal{H}_{\mathcal{F}}\} \qquad (2)$$

The set of intervals is a partition where each interval is an equivalence class $[f_j]$: for $f_\alpha, f_\beta \in S_F$, $f_\alpha \sim f_\beta$ if $f_\alpha, f_\beta \in [f_i, f_i + \Delta f)$. This may be extended so that $f_\alpha \sim f_\beta$ if $f_\alpha, f_\beta > f_{max}$ and $f_\alpha \sim f_\beta$ if $f_\alpha, f_\beta \leq f_{min}$. Frequencies f_α, f_β are 'assigned' to f_i if they are between f_i and $f_i + \Delta f$. Thus, f_α, f_β are indistinguishable from each other since both are classified as f_i. Each frequency interval is uniquely identified by the minimum point at the closed end. The set of these points is:

$$\mathcal{F} = \{f_i \mid f_i = f_{min} + i\Delta f, i \in \mathbb{N}_0, i < N_f\} \subset S_{\mathcal{F}} \tag{3}$$

$$= \{f_0, f_1, \ldots, f_{N_f - 1}\}$$

$\mathcal{F}$ is a discretization of $S_{\mathcal{F}}$ and may be thought of as a set of audible frequencies.

The sound pressure space is constructed similarly to yield:

a. $\quad \mathcal{H}_{\mathcal{P}} = \{h_p = [p_{min} + i\Delta p, p_{min} + (i+1)\Delta p) \mid p \in S_{\mathcal{P}}, i \in \mathbb{N}_0, i < N_p\}$ (4)

b. $\quad \tau_{\mathcal{P}} = \{\bigcup H_p \mid H_p \subseteq \mathcal{H}_{\mathcal{P}}\}$ (topology of $S_{\mathcal{P}}$)

c. $\quad \mathcal{P} = \{p_0, p_1, \ldots, p_{N_P - 1}\} \subset S_{\mathcal{P}}$ (set of physiological pressures)

The basis for a topology in $\mathcal{A} = S_{\mathcal{F}} \times S_{\mathcal{P}}$ is:

$$\mathcal{B}_{\mathcal{A}} = \{U_f \times U_p \mid U_f \subset \mathcal{H}_{\mathcal{F}}, U_p \subset \mathcal{H}_p\} \tag{5}$$

The topology for $\mathcal{A}$ is:

$$\tau_{\mathcal{A}} = \{\bigcup B_A \mid B_A \subseteq \mathcal{B}_{\mathcal{A}}\} \tag{6}$$

If only the sets of audible frequencies and pressures are considered, then the discretized acoustic space is:

$$\mathcal{A} = \mathcal{F} \times \mathcal{P} \tag{7}$$

with the discrete topology.

Neural Space

The neural space $S_\mathcal{X}$ is constructed in a similar fashion as $\mathcal{F}$ and $\mathcal{P}$, though the topology is slightly different. The idea is to partition $S_\mathcal{X}$ into subintervals that represent neurons and then to combine the subintervals contiguously to form synaptic intervals.

The neural space $S_\mathcal{X} \subset \mathbb{R}^+$ is a half-open interval representing the one dimensional tonotopic axis: $S_\mathcal{X} = [x_{min}, x_{max})$. $S_\mathcal{X}$ is partitioned into N_{cell} half-open intervals, each of width Δx and expressed as $[x_\alpha, x_\beta), x_\beta > x_\alpha$ or $[x_\alpha, x_\alpha + \Delta x)$. Each interval represents the length (Δx) of a single cell on the tonotopic axis. The set of intervals is expressed as:

$$\mathcal{H}_{x,1} = \{h_{x,1} = [x_{min} + i\Delta x, x_{min} + (i+1)\Delta x) \mid i \in \mathbb{N}_0, i < N_{cell}\} \tag{8}$$

The set $\mathcal{H}_{x,1}$ is a partition, which effectively discretizes $S_\mathcal{X}$ (see section above for a similar treatment). Each interval is uniquely identified by the point at the closed end, which also gives it's location along the tonotopic axis. The set $\mathcal{X}$ containing these points is:

$$\mathcal{X} = \{x_i \mid x_i = x_{min} + i\Delta x \mid x_i \in S_\mathcal{X}, 0 < i < N_{cell}\}$$
$$= \{x_0, x_1, \ldots, x_{N_{cell}-1}\} \tag{9}$$

A synaptic interval is also a half-open interval with length λ expressed as:

$$h_{x,\lambda} = [x, x + \lambda), \, x \in \mathcal{X}, \lambda \in S_\Lambda$$

where $S_\Lambda = [\lambda_{\min}, \lambda_{\max}] \subset \mathbb{R}^+$ is the range of values that the length can take. The length of the synaptic interval is defined to be a contiguous set of cells so that $h_{x,\lambda}$ is an integral multiple of cell length Δx. Letting $n_\lambda \in \mathbb{N}^+$ be the number of cells in the interval, the intervals may be re-expressed as:

$$h_{x,\lambda} = [x, x + \lambda), \; x \in \mathcal{X}, \lambda = n_\lambda \Delta x, n_\lambda \leq n_{\lambda,max} \leq N_{cells} \tag{10}$$

where $n_{\lambda,max}$ is the maximum number of cells in the interval. The set containing all possible interval lengths is :

$$\Lambda = \{\lambda_{n_\lambda} \mid \lambda_{n_\lambda} = n_\lambda \Delta x, n_\lambda \leq n_{\lambda,max} \leq N_{cell}\} \subset S_\Lambda \tag{11}$$
$$= \{\lambda_1, \lambda_2, \ldots, \lambda_{max}\}$$

As shown in the next section, sound pressure will be encoded as the length of the intervals. In order to ensure a full representation of sound pressure, a 'buffer' of $N_{cell} - n_{\max}$ cells is needed. Without the buffer, the maximum value of last interval is 1 cell. The set of identifying points for synaptic intervals is then:

$$\mathcal{X}_\lambda = \{x_1, x_2, \ldots, x_{N_\lambda}\} \subset \mathcal{X}; N_\lambda = N_{cell} - n_{max} \tag{12}$$

The set of synaptic intervals is expressed as:

$$\mathcal{H}_{x,\lambda} = \{h_{x,\lambda} = [x, x + \lambda) \mid x \in \mathcal{X}, \lambda \in \Lambda\} \tag{13}$$

The topology of $S_\mathcal{X}$ generated by the elements of $\mathcal{H}_{x,\lambda}$ is:

$$\tau_\mathcal{X} = \{\bigcup H_{x,\lambda} \mid H_{x,\lambda} \subseteq \mathcal{H}_{x,\lambda}\} \tag{14}$$

Mapping from acoustic space to neural space

The aim is to construct a mapping between the acoustic and neural spaces in such a way that allows for both encoding and decoding sounds in neural space.

Note that a pure tone $a_{f,p}$ corresponds to the ordered pair $(f,p) \in S_\mathcal{F} \times S_\mathcal{P}$ and an interval $h_{x,\lambda} = [x, x+\lambda)$ corresponds to the ordered pair $(x, \lambda) \in S_\mathcal{X} \times S_\Lambda$. The mapping (ψ) from acoustic to neural space is obtained by first defining mappings from frequency space $(S_\mathcal{F})$ to neural space $(S_\mathcal{X})$ and from pressure space $(S_\mathcal{P})$ to interval length space (S_Λ):

$$\psi_f : S_\mathcal{F} \to S_\mathcal{X}, \psi_f(f) = x; \tag{15}$$

$$\psi_p : S_\mathcal{P} \to S_\Lambda, \psi_p(p) = \lambda;$$

$$\psi : S_\mathcal{F} \times S_\mathcal{P} \to S_\mathcal{X} \times S_\Lambda; \psi(f,p) = (\psi_f(f), \psi_p(p)) = (x, \lambda)$$

533   After partitioning, the spaces are effectively discretized into $\mathcal{F} \subset S_\mathcal{F}, \mathcal{P} \subset S_\mathcal{P}, \mathcal{X}_\lambda \subset S_\mathcal{X}, \Lambda \subset S_\Lambda$.

534 These are the functionally and biological relevant sets as they contain the audible frequencies and

535 pressures that can be mapped into the compartmentalized neural space. Therefore, the mapping

536 can be restricted to these sets:

$$\psi_f{\restriction}_\mathcal{F} : \mathcal{F} \to \mathcal{X}_\lambda, \psi_f{\restriction}_\mathcal{F}(f) = x; \tag{16}$$

$$\psi_p{\restriction}_\mathcal{P} : \mathcal{P} \to \lambda, \psi_p{\restriction}_\mathcal{P}(p) = \lambda;$$

$$\psi{\restriction}_{\mathcal{F},\mathcal{P}} : \mathcal{F} \times \mathcal{P} \to \mathcal{X} \times \Lambda; \psi{\restriction}_{\mathcal{F},\mathcal{P}}(f,p)$$

$$= (\psi_f{\restriction}_\mathcal{F}(f), \psi_p{\restriction}_\mathcal{P}(p)) = (x, \lambda)$$

537 The maps are bijective if $|\mathcal{F}| = |\mathcal{X}_\lambda|$ and $|\mathcal{P}| = |\Lambda|$ and continuous because the restricted spaces

538 have the discrete topology.

539 Algebraic operations

540 In the following, addition and multiplication operations for combining elements in acoustic and

541 neural spaces are defined.

542 Operations in acoustic space

543 Complex sounds are composed of multiple pure tones of varying frequencies and intensities. The

544 analyses will be limited to sets of audible frequencies $(\mathcal{F})$ and pressures $(\mathcal{P})$. Pure tones are

545 combined with an addition ("+") operation defined as the 'union'.

$$+ : \mathcal{A} \times \mathcal{A} \rightarrow \mathcal{A}; a_{f_\alpha, p_\alpha} + a_{f_\beta, p_\beta} \overset{\text{def}}{=} a_{f_\alpha, p_\alpha} \cup a_{f_\beta, p_\beta} \tag{17}$$

One property that is potentially problematic is that the addition operation can produce a sound

with the same frequency but different pressures, which is physically impossible (e.g. $a_{f_\alpha, p_\gamma} \cup a_{f_\alpha, p_\delta} =$

$\{a_{f_\alpha, p_\gamma}, a_{f_\alpha, p_\delta}\}$). This may actually be a desirable property because the sound information may

propagate through different channels in the auditory pathway before converging to a neural space

(e.g. binaural stimuli). Nevertheless, assigning multiple pressure values to a single frequency may

be avoided as follows. For $a_{f_\alpha, p_\alpha}, a_{f_\beta, p_\beta} \in \mathcal{A}$,

$$a_{f_\alpha, p_\alpha} + a_{f_\beta, p_\beta} = \tag{18}$$

$$\begin{cases} \{a_{f_\alpha, p_\alpha}, a_{f_\beta, p_\beta}\}, & f_\alpha \neq f_\beta \\ a_{f, p_\gamma}, \ p_\gamma = \max(p_\alpha, p_\beta), & f_\alpha = f_\beta \end{cases}$$

552 **Operations in Neural Space**

In neural space, addition ("+") is also defined as the union. For $h_{x_\alpha \lambda_\alpha}, h_{x_\beta \lambda_\beta} \in (S_\mathcal{X}, \tau_\mathcal{X})$

$$+ : (S_\mathcal{X}, \tau_\mathcal{X}) \times (S_\mathcal{X}, \tau_\mathcal{X}) \rightarrow (S_\mathcal{X}, \tau_\mathcal{X}); \tag{19}$$

$$h_{x_\alpha \lambda_\alpha} + h_{x_\beta \lambda_\beta} \overset{\text{def}}{=} h_{x_\alpha \lambda_\alpha} \cup h_{x_\beta \lambda_\beta}$$

553 Generally, for any two synaptic intervals $(h_{x \lambda_\alpha}, h_{x \lambda_\beta})$, the addition operation yields two possi-

554 bilities:

$$h_{x_\alpha \lambda_\alpha} + h_{x_\beta \lambda_\beta} =$$

$$\begin{cases} h_{x\lambda}, x = \min(x_\alpha, x_\beta), \lambda = |h_{x\lambda_\alpha} \cup h_{x\lambda_\beta}|, & h_{x\lambda_\alpha} \cap h_{x\lambda_\beta} \neq \emptyset \\ \{h_{x_\alpha \lambda_\alpha}, h_{x_\beta \lambda_\beta}\}, & h_{x\lambda_\alpha} \cap h_{x\lambda_\beta} = \emptyset \end{cases} \tag{20}$$

For more than 2 synaptic intervals, the total length λ is given by the Inclusion-Exclusion principle.

The algebraic structure on $(S_\mathcal{X}, \tau_\mathcal{X})$ with the addition operation is a monoid since it inherits the

algebraic properties of the union operation. In particular, addition is closed because the result is

either a longer, half-open interval or two disjoint half-open intervals, either of which is an element

of $\tau_\mathcal{X}$. Addition is commutative, associative, has the empty set as the identity element, and does

not have an inverse.

Multiplication "·" of synaptic intervals is defined as the set minus operation ($\setminus$). Given two

intervals $h_{x_\alpha, \lambda_\alpha}, h_{x_\beta, \lambda_\beta} \in (S_\mathcal{X}, \tau_\mathcal{X})$ where $h_{x_\alpha, \lambda_\alpha}$ is the multiplier and $h_{x_\beta, \lambda_\beta}$ is the multiplicand,

$$\bullet : (S_\mathcal{X}, \tau_\mathcal{X}) \times (S_\mathcal{X}, \tau_\mathcal{X}) \to (S_\mathcal{X}, \tau_\mathcal{X}); \tag{21}$$

$$h_{x_\alpha, \lambda_\alpha} \cdot h_{x_\beta, \lambda_\beta} \overset{\text{def}}{=} h_{x_\beta, \lambda_\beta} \setminus h_{x_\alpha, \lambda_\alpha}$$

563   Letting $\hat{\lambda} = |h_{x_\beta, \lambda_\beta} \setminus h_{x_\alpha, \lambda_\alpha}|$, the possible results of multiplication are:

$$h_{x_\alpha,\lambda_\alpha} \cdot h_{x_\beta,\lambda_\beta} =$$

$$
\begin{cases}
1.\, h_{x_\beta,\lambda_\beta}, & h_{x_\alpha,\lambda_\alpha} \cap h_{x_\beta,\lambda_\beta} = \emptyset \\[2ex]
2.\, [x_\beta, x_\alpha) = [x_\beta, x_\beta + \hat{\lambda}), & h_{x_\alpha,\lambda_\alpha} \cap h_{x_\beta,\lambda_\beta} \neq \emptyset, x_\beta < x_\alpha, h_{x_\alpha,\lambda_\alpha} \not\subset h_{x_\beta,\lambda_\beta} \\[2ex]
3.\, [x_\delta, x_\delta + \hat{\lambda}), & h_{x_\alpha,\lambda_\alpha} \cap h_{x_\beta,\lambda_\beta} \neq \emptyset, x_\beta \geq x_\alpha, h_{x_\beta,\lambda_\beta} \not\subset h_{x_\alpha,\lambda_\alpha} \\[1ex]
\quad x_\delta = x_\beta + (\lambda_\beta - \hat{\lambda}) & \\[2ex]
4.\, \emptyset, & h_{x_\beta,\lambda_\beta} \subset h_{x_\alpha,\lambda_\alpha} \\[2ex]
5.\, \{[x_\beta, x_\alpha), [x_\alpha + \lambda_\alpha, x_\beta + \lambda_\beta)\}, & h_{x_\alpha,\lambda_\alpha} \subset h_{x_\beta,\lambda_\beta}
\end{cases}
$$

$$(22)$$

The algebraic structure on $(S_\mathcal{X}, \tau_X)$ with the multiplication operation is a magma, with properties inherited from the set minus operation. Multiplication is closed because the set minus operation yields an interval that is either the empty set or a half-open interval(s) with a minimum length(s) of Δx and maximum length of λ_{max}. In either case, the resulting interval is in $(S_\mathcal{X}, \tau_\mathcal{X})$. While the $\emptyset$ is a left identity element, there is no unique inverse element since the result is the $\emptyset$ whenever the length of multiplier is greater than or equal to that of the multiplicand. It is also neither commutative nor associative.

Proposition 0.0.1. The *multiplication* operation is left but not right distributive over addition.

Proof. **Left distributive**: Let $h_{x_\alpha,\lambda_\alpha}, h_{x_\beta,\lambda_\beta}, h_{x_\gamma,\lambda_\gamma} \in (S_\mathcal{X}, \tau_\mathcal{X})$

$$
\begin{aligned}
&= h_{x_\gamma,\lambda_\gamma} \cdot (h_{x_\alpha,\lambda_\alpha} + h_{x_\beta,\lambda_\beta}) \\
&= (h_{x_\alpha,\lambda_\alpha} \cup h_{x_\beta,\lambda_\beta}) \setminus h_{x_\gamma,\lambda_\gamma} \\
&= h_{x_\gamma,\lambda_\gamma}^c \cap (h_{x_\alpha,\lambda_\alpha} \cup h_{x_\beta,\lambda_\beta}), \text{ 'c' is complement} \\
&= (h_{x_\gamma,\lambda_\gamma}^c \cap h_{x_\alpha,\lambda_\alpha}) \cup (h_{x_\gamma,\lambda_\gamma}^c \cap h_{x_\beta,\lambda_\beta}) \\
&= h_{x_\alpha,\lambda_\alpha} \setminus h_{x_\gamma,\lambda_\gamma} \cup h_{x_\beta,\lambda_\beta} \setminus h_{x_\gamma,\lambda_\gamma} \\
&= h_{x_\gamma,\lambda_\gamma} \cdot h_{x_\alpha,\lambda_\alpha} + h_{x_\gamma,\lambda_\gamma} \cdot h_{x_\beta,\lambda_\beta}
\end{aligned}
$$

Not Right distributive:

$$(h_{x_\alpha,\lambda_\alpha} + h_{x_\beta,\lambda_\beta}) \cdot h_{x_\gamma,\lambda_\gamma}$$

$$= h_{x_\gamma,\lambda_\gamma} \setminus (h_{x_\alpha,\lambda_\alpha} \cup h_{x_\beta,\lambda_\beta})$$

$$= (h_{x_\gamma,\lambda_\gamma} \setminus h_{x_\alpha,\lambda_\alpha}) \cap (h_{x_\gamma,\lambda_\gamma} \setminus h_{x_\beta,\lambda_\beta})$$

$$\neq h_{x_\alpha,\lambda_\alpha} \cdot h_{x_\gamma,\lambda_\gamma} + h_{x_\beta,\lambda_\beta} \cdot h_{x_\gamma,\lambda_\gamma}$$

 □

Proposition 0.0.2. Let the representation of a pure tone in neural space be an excitatory interval (h_α^E) flanked by two inhibitory intervals (h_α^I, h_β^I) and that of another pure tone be also an excitatory (h_β^E) flanked by two inhibitory intervals (h_γ^I, h_δ^I), then the combined effect when both tones are introduced simultaneously is not equal to presenting each tone separately and then combining the result. That is, $(h_\alpha^I + h_\beta^I + h_\gamma^I + h_\delta^I) \cdot (h_\alpha^E + h_\beta^E) \neq (h_\alpha^I + h_\beta^I) \cdot h_\alpha^E + (h_\gamma^I + h_\delta^I) \cdot h_\beta^E$.

Proof. $(h_\alpha^I + h_\beta^I + h_\gamma^I + h_\delta^I) \cdot (h_\alpha^E + h_\beta^E)$ can be re-expressed as:

$$(h_\alpha^E \cup h_\beta^E) \setminus (h_\alpha^I \cup h_\beta^I \cup h_\gamma^I \cup h_\delta^I)$$

$$= (h_\alpha^I \cup h_\beta^I \cup h_\gamma^I \cup h_\delta^I)^c \cap (h_\alpha^E \cup h_\beta^E)) \text{ where "c" is the complement}$$

Using a similar argument, $(h_\alpha^I + h_\beta^I) \cdot h_\alpha^E + (h_\gamma^I + h_\delta^I) \cdot h_\beta^E$ may be re-expressed as:

$$(h_\alpha^E \setminus (h_\alpha^I \cup h_\beta^I)) \cup (h_\beta^E \setminus (h_\gamma^I \cup h_\delta^I))$$

$$= ((h_\alpha^I \cup h_\beta^I)^c \cap h_\alpha^E) \cup ((h_\gamma^I \cup h_\delta^I)^c \cap h_\beta^E)$$

For an element $y \in ((h_\alpha^I \cup h_\beta^I)^c \cap h_\alpha^E)$, the following statements are true:

$$1. \, y \in (h_\alpha^I \cup h_\beta^I)^c$$

$$2. \, y \in (h_\alpha^I \cup h_\beta^I)^c \cup ((h_\gamma^I \cup h_\delta^I)^c \cap h_\beta^E)$$

$$3. \, y \in (h_\alpha^I \cup h_\beta^I)^c \cup (h_\gamma^I \cup h_\delta^I)^c$$

$$4. \, y \in h_\alpha^E$$

$$5. \, y \in h_\alpha^E \cup ((h_\gamma^I \cup h_\delta^I)^c \cap h_\beta^E)$$

$$6. \, y \in h_\alpha^E \cup h_\beta^E$$

Since $y \in ((h_\alpha^I \cup h_\beta^I)^c \cap h_\alpha^E)$, then from lines 3 and 6, $y \in ((h_\alpha^I \cup h_\beta^I)^c) \cup ((h_\gamma^I \cup h_\delta^I)^c) \cap (h_\alpha^E \cup h_\beta^E)$.

Therefore,

$$((h_\alpha^I \cup h_\beta^I)^c \cap h_\alpha^E) \cup ((h_\gamma^I \cup h_\delta^I)^c \cap h_\beta^E) = ((h_\alpha^I \cup h_\beta^I)^c) \cup ((h_\gamma^I \cup h_\delta^I)^c) \cap (h_\alpha^E \cup h_\beta^E)$$

$$= ((h_\alpha^I \cup h_\beta^I) \cap (h_\gamma^I \cup h_\delta^I))^c \cap (h_\alpha^E \cup h_\beta^E)$$

$$\neq (h_\alpha^I \cup h_\beta^I \cup h_\gamma^I \cup h_\delta^I)^c \cap (h_\alpha^E \cup h_\beta^E))$$

Therefore, $(h_\alpha^I + h_\beta^I + h_\gamma^I + h_\delta^I) \cdot (h_\alpha^E + h_\beta^E) \neq (h_\alpha^I + h_\beta^I) \cdot h_\alpha^E + (h_\gamma^I + h_\delta^I) \cdot h_\beta^E$ $\qquad \square$

Comparison with columnar organization

In the mathematical model, the 'functional' unit is an interval that can vary in size, depending on the sound intensity. The indistinct borders are consistent with topographical organization of afferents [19]. The expanding border facilitates high resolution representation of both frequency and pressure. Assuming a bijective mapping between acoustic and neural spaces, the maximum number of frequency levels that can be represented is proportional to the number of cells along the tonotopic axis (N_{cell} and the maximum number of pressure levels is proportional to the maximum number of cells in each interval ($n_{\lambda,max}$). The relation between the number of frequency and pressure levels is then given by $|\mathcal{F}| = |\mathcal{A}| - |\mathcal{P}| = N_{cell} - n_{\lambda,max}$ (see eq. 12 in appendix). Hence, the number of frequency levels decreases linearly with the number of pressure levels.

In contrast, consider an alternative neural space that consists of classical columns [17]. The definition of a column has evolved [50] but for illustrative purposes, columns are defined here as having distinct borders; the enclosed neurons have identical receptive fields and hence function as a single unit. In this scheme, the location of the active column encodes frequency and sound pressure is encoded as the number of neurons that become active during the stimulus (assuming a brief stimulus so that neurons are effectively binary).

Construction of the neural space is as above except that the flexible synaptic intervals are replaced with half-open intervals, termed columns, spanning a *fixed* number of cells n_{col}. The number of columns that fit into the neural space with N_{cell} neurons is therefore $N_{col} = \frac{N_{cell}}{n_{col}}$. Assuming a bijective mapping from frequency space to neural space, the number of frequency levels $N_{\mathcal{F}} = N_{col} = \frac{N_{cell}}{n_{col}}$. Because the number of cells in a column (n_{col}) is fixed, pressure will be encoded as the number of cells that become active within a column during a stimulus. Assuming a bijective map, the number of pressure levels is $N_{\mathcal{P}} = n_{col}$.

Hence, the number of frequency levels is inversely proportional to the number of pressure levels: $N_{\mathcal{F}} = \frac{N_{cell}}{n_{col}} = \frac{N_{cell}}{N_{\mathcal{P}}}$. Compared with the model with flexible synaptic intervals, the number of frequency levels drops off much faster with the number of pressure levels.

 # Experimental evidence

Frequency (kHz)

Experimental evidence for Addition operation Data adapted from reference [34]. Extracellular (top) and whole-cell voltage clamp (middle, bottom) recording from the central nucleus of the Inferior colliculus, which receives binaural inputs. The frequency response areas (FRA) were constructed by presenting pure tones of varying frequencies (abscissas) and intensities (ordinates) and documenting the responses. Tones were delivered ipsilaterally (left column), contralaterally (middle), and binaurally (right). The FRAs can be taken as an indicator of the spatial extent of synaptic field and activated area in the following manner. Note that the FRAs are "V-shaped". At low intensities, neurons fire only when the tone frequencies are near its preferred frequency (tip of the V). At higher intensities, the range of frequencies that evoke firing increases substantially . If adjacent neurons have comparably-shaped FRAs but have slightly different preferred frequencies, an increase in intensity would translate to an increase in the spatial extent of activated neurons. The model predicts that because the contralateral response is greater than the ipsilateral response, the response evoked with binaural stimulation should equal that of contralateral stimulation. In all cases, the binaural FRAs was nearly identical to the contralateral FRAs. *Permission pending.*

References

[1] William M Siebert. "Frequency discrimination in the auditory system: Place or periodicity mechanisms?" In: *Proceedings of the IEEE* 58.5 (1970), pp. 723–730.

[2] Georg Von Bekesy and Ernest Glen Wever. *Experiments in hearing.* Vol. 8. McGraw-Hill New York, 1960.

[3] Jozef J Zwislocki and My Nguyen. "Place code for pitch: A necessary revision". In: *Acta oto-laryngologica* 119.2 (1999), pp. 140–145.

[4] Troy A Hackett et al. "Linking topography to tonotopy in the mouse auditory thalamocortical circuit". In: *Journal of Neuroscience* 31.8 (2011), pp. 2983–2995.

[5] Brian CJ Moore and Stephan MA Ernst. "Frequency difference limens at high frequencies: evidence for a transition from a temporal to a place code". In: *The Journal of the Acoustical Society of America* 132.3 (2012), pp. 1542–1547.

[6] Robert P Carlyon et al. "Pitch comparisons between electrical stimulation of a cochlear implant and acoustic stimuli presented to a normal-hearing contralateral ear". In: *Journal of the Association for Research in Otolaryngology* 11.4 (2010), pp. 625–640.

[7] Bertrand Delgutte. "Physiological models for basic auditory percepts". In: *Auditory computation.* Springer, 1996, pp. 157–220.

[8] JM Doughty and WR Garner. "Pitch characteristics of short tones. II. Pitch as a function of tonal duration." In: *Journal of Experimental Psychology* 38.4 (1948), p. 478.

[9] Brian CJ Moore. "Frequency difference limens for short-duration tones". In: *The Journal of the Acoustical Society of America* 54.3 (1973), pp. 610–619.

[10] Christophe Micheyl, Li Xiao, and Andrew J Oxenham. "Characterizing the dependence of pure-tone frequency difference limens on frequency, duration, and level". In: *Hearing Research* 292.1-2 (2012), pp. 1–13.

[11] Christophe Micheyl, Paul R Schrater, and Andrew J Oxenham. "Auditory frequency and intensity discrimination explained using a cortical population rate code". In: *PLoS computational biology* 9.11 (2013), e1003336.

[12] Brenda J Hefti and Philip H Smith. "Anatomy, Physiology, and Synaptic Responses of Rat Layer V Auditory Cortical Cells and Effects of Intracellular GABAABlockade". In: *Journal of Neurophysiology* 83.5 (2000), pp. 2626–2638.

[13] Anne-Marie M Oswald and Alex D Reyes. "Maturation of intrinsic and synaptic properties of layer 2/3 pyramidal neurons in mouse auditory cortex". In: *Journal of neurophysiology* 99.6 (2008), pp. 2998–3008.

[14] AD Reyes, EW Rubel, and WJ Spain. "Membrane properties underlying the firing of neurons in the avian cochlear nucleus". In: *Journal of Neuroscience* 14.9 (1994), pp. 5352–5364.

[15] Xiaoqin Wang et al. "Neural coding of temporal information in auditory thalamus and cortex". In: *Neuroscience* 154.1 (2008), pp. 294–303.

[16] Mounya Elhilali et al. "Dynamics of precise spike timing in primary auditory cortex". In: *Journal of Neuroscience* 24.5 (2004), pp. 1159–1172.

[17] Vernon B Mountcastle. "Modality and topographic properties of single neurons of cat's somatic sensory cortex". In: *Journal of neurophysiology* 20.4 (1957), pp. 408–434.

[18] David H Hubel and Torsten N Wiesel. "Receptive fields, binocular interaction and functional architecture in the cat's visual cortex". In: *The Journal of physiology* 160.1 (1962), pp. 106–154.

[19] Arnold L Towe. "Notes on the Hypothesis of Columnar Organization in Somatosensory Cerebral Cortex; pp. 32–47". In: *Brain, Behavior and Evolution* 11.1 (1975), pp. 32–47.

[20] Andrew J Oxenham. "Revisiting place and temporal theories of pitch". In: *Acoustical science and technology* 34.6 (2013), pp. 388–396.

[21] Christoph E Schreiner. "Spatial distribution of responses to simple and complex sounds in the primary auditory cortex". In: *Audiology and Neurotology* 3.2-3 (1998), pp. 104–122.

[22] Tianying Ren, Wenxuan He, and David Kemp. "Reticular lamina and basilar membrane vibrations in living mouse cochleae". In: *Proceedings of the National Academy of Sciences* 113.35 (2016), pp. 9910–9915.

[23] Monita Chatterjee and Jozef J Zwislocki. "Cochlear mechanisms of frequency and intensity coding. I. The place code for pitch". In: *Hearing research* 111.1-2 (1997), pp. 65–75.

[24] William M Siebert et al. "Stimulus transformations in the peripheral auditory system". In: *Recognizing patterns* 104.133 (1968), pp. 602–615.

[25] Robert B Levy and Alex D Reyes. "Coexistence of lateral and co-tuned inhibitory configurations in cortical networks". In: *PLoS computational biology* 7.10 (2011), e1002161.

[26] Robert B Levy and Alex D Reyes. "Spatial profile of excitatory and inhibitory synaptic connectivity in mouse primary auditory cortex". In: *Journal of Neuroscience* 32.16 (2012), pp. 5609–5619.

[27] Andrew J Oxenham. "How we hear: The perception and neural coding of sound". In: *Annual review of psychology* 69 (2018).

[28] WR Thurlow and S Bernstein. "Simultaneous Two-Tone Pitch Discrimination". In: *The Journal of the Acoustical Society of America* 29.4 (1957), pp. 515–519.

[29] Willard R Thurlow and Irving L Rawlings. "Discrimination of number of simultaneously sounding tones". In: *The Journal of the Acoustical Society of America* 31.10 (1959), pp. 1332–1336.

[30] Christophe NJ Stoelinga and Robert A Lutfi. "Discrimination of the spectral density of multitone complexes". In: *The Journal of the Acoustical Society of America* 130.5 (2011), pp. 2882–2890.

[31] Xiaoqin Wang et al. "Sustained firing in auditory cortex evoked by preferred stimuli". In: *Nature* 435.7040 (2005), pp. 341–346.

[32] Max L Schiff and Alex D Reyes. "Characterization of thalamocortical responses of regular-spiking and fast-spiking neurons of the mouse auditory cortex in vitro and in silico". In: *Journal of neurophysiology* 107.5 (2012), pp. 1476–1488.

[33] Alex Reyes et al. "Target-cell-specific facilitation and depression in neocortical circuits". In: *Nature neuroscience* 1.4 (1998), pp. 279–285.

[34] Xiaorui R Xiong et al. "Interaural level difference-dependent gain control and synaptic scaling underlying binaural computation". In: *Neuron* 79.4 (2013), pp. 738–753.

[35] Michael Epstein and Mary Florentine. "Binaural loudness summation for speech presented via earphones and loudspeaker with and without visual cues". In: *The Journal of the Acoustical Socient of America* 131 (2012), pp. 3981–3988.

[36] Daniel E Winkowski and Patrick O Kanold. "Laminar transformation of frequency organization in auditory cortex". In: *Journal of Neuroscience* 33.4 (2013), pp. 1498–1508.

[37] Gideon Rothschild, Israel Nelken, and Adi Mizrahi. "Functional organization and population dynamics in the mouse primary auditory cortex". In: *Nature neuroscience* 13.3 (2010), p. 353.

[38] John B Issa et al. "Multiscale optical Ca2+ imaging of tonal organization in mouse auditory cortex". In: *Neuron* 83.4 (2014), pp. 944–959.

[39] JJ Zwislocki. "What is the cochlear place code for pitch?" In: *Acta oto-laryngologica* 111.2 (1991), pp. 256–262.

[40] Imme Stiebler and Gunter Ehret. "Inferior colliculus of the house mouse. I. A quantitative study of tonotopic organization, frequency representation, and tone-threshold distribution". In: *Journal of Comparative Neurology* 238.1 (1985), pp. 65–76.

[41] Feng Luo et al. "Three-dimensional tonotopic organization of the C57 mouse cochlear nucleus". In: *Hearing research* 257.1-2 (2009), pp. 75–82.

[42] I Stiebler et al. "The auditory cortex of the house mouse: left-right differences, tonotopic organization and quantitative analysis of frequency representation". In: *Journal of Comparative Physiology A* 181.6 (1997), pp. 559–571.

[43] Wei Guo et al. "Robustness of cortical topography across fields, laminae, anesthetic states, and neurophysiological signal types". In: *Journal of Neuroscience* 32.27 (2012), pp. 9159–9172.

[44] Sharba Bandyopadhyay, Shihab A Shamma, and Patrick O Kanold. "Dichotomy of functional organization in the mouse auditory cortex". In: *Nature neuroscience* 13.3 (2010), p. 361.

[45] ML Sutter et al. "Organization of inhibitory frequency receptive fields in cat primary auditory cortex". In: *Journal of Neurophysiology* 82.5 (1999), pp. 2358–2371.

[46] Rishidev Chaudhuri and Ila Fiete. "Computational principles of memory". In: *Nature neuroscience* 19.3 (2016), p. 394.

[47]   Jeremie Barral, Xiao-Jing Wang, and Alex D Reyes. "Propagation of temporal and rate signals in cultured multilayer networks". In: *Nature communications* 10.1 (2019), pp. 1–14.

[48]   Jian Wang, Donald Caspary, and Richard J Salvi. "GABA-A antagonist causes dramatic expansion of tuning in primary auditory cortex". In: *Neuroreport* 11.5 (2000), pp. 1137–1140.

[49]   Fiona EN LeBeau, Manuel S Malmierca, and Adrian Rees. "Iontophoresis in vivo demonstrates a key role for GABAA and glycinergic inhibition in shaping frequency response areas in the inferior colliculus of guinea pig". In: *Journal of Neuroscience* 21.18 (2001), pp. 7303–7312.

[50]   Jonathan C Horton and Daniel L Adams. "The cortical column: a structure without a function". In: *Philosophical Transactions of the Royal Society B: Biological Sciences* 360.1456 (2005), pp. 837–862.