Modeling the variability of the electromotor command system of pulse mormyrids

Ángel Lareo[1*], Pablo Varona[1], Francisco B. Rodríguez[1*]

1 Grupo de Neurocomputación Biológica, Departamento de Ingeniería Informática, Escuela Politécnica Superior, Universidad Autónoma de Madrid, Spain

* angel.lareo@gmail.com, f.rodriguez@uam.es

Abstract

The electromotor neural system in weakly electric fish is a network responsible for active electroreception and electrolocation. This system controls the timing of pulse generation in the electrical signals used by these fish for extracting information from the environment and communicating with other specimens. Ethological studies related to fish mating, exploratory, submissive or aggressive behaviors have described distinct sequences of pulse intervals (SPIs). Accelerations, scallops, rasps, and cessations are four patterns of SPIs reported in pulse mormyrids, each showing characteristic temporal structures and large variability both in timing and duration. This paper presents a biologically plausible computational model of the electromotor command circuit that reproduces these four SPI patterns as a function of the input to the model while keeping the same internal parameter configuration. The topology of the model is based on a simplified representation of the network as described by morphological and electrophysiological studies. An initial *ad hoc* tuned configuration (S-T) was build to reproduce all four SPI patterns. Then, starting from S-T, a genetic algorithm (GA) was developed to automatically find the parameters of the model connectivity. Two different configurations obtained from the GA are presented here: one optimized to a set of synthetic examples of SPI patterns based on experimental observations in mormyrids (S-GA), and another configuration adjusted to patterns recorded from freely-behaving *Gnathonemus Petersii* specimens (R-GA). A robustness analysis to input variability of these model configurations was performed to discard overfitting and assess validity. Results showed that the four SPI patterns are consistently reproduced, both with synthetic (S-GA) data and with signals recorded from behaving animals (R-GA). This new model can be used as a tool to analyze the electromotor command chain during electrogeneration and assess the role of temporal structure in electroreception.

Author summary

Weakly electric fish are a convenient system to study information processing in the nervous system. These fish have a remarkable sense of active electroreception, which allows them to generate and detect electrical fields for locating objects and communicating with other specimens in their surroundings. The electrical signal generated by these fish can be easily monitored noninvasively in freely-behaving animals. Activity patterns in this signal have been associated to different fish behaviors, like aggression or mating, for some species of the mormyridae family. In this work we use discharge patterns recorded from specimens of the *Gnathonemus Petersii* species along

with synthetic data to develop a model of the electromotor command network. The model network is based on morphological and physiological studies in this type of weakly electric fish. The parameters of this model were tuned using a genetic algorithm to fit both synthetic and recorded activity patterns. This computational model allows to simulate the electromotor network behavior under controlled conditions and to test new hypotheses on the generation and function of temporal structure in the signals produced by weakly electric fish.

Introduction

Pulse mormyriforms, a group of weakly electric fish, produce electric pulses with high temporal precision. These fish have the ability of polarize their body in fast voltage transients whose deflection in the fish surroundings is detected by the fish using a specialized electric organ [5]. The electric organ discharges (EODs) occur as a result of the synchronous activation of modified muscle or nerve cells named electrocytes. This ability, known as active electroreception is a well-suited sensory modality to study information processing in a living neural system as the signal from a freely-behaving fish can be monitored during long time periods.

Information is encoded in the fish signal using a multiplexed temporal coding [2]. The pulse shape, with a mean duration of ∼1 ms, is stereotyped, although there are variations among species [16], sex [3] or relative dominance [11]. The interval between EODs, known as the inter-pulse interval (IPI), is much larger and variable than the duration of the EOD. At rest, IPIs are around 100 to 300 ms, but they fluctuate from less than 10 to more than 400 ms [31]. IPIs and sequences of pulse intervals (SPIs) are also relevant to information processing in these animals, as complex higher-level information can be encoded using this kind of temporal coding [2,16]. For instance, IPIs decrease when the fish is actively probing their environment [32]. The timing flexibility of IPIs in this system gives rise to an interesting set of SPI patterns with behavioral relevance, as we will discuss below.

The neural system responsible for controlling the timing of the EODs is the electromotor system, located at the central nervous system of the fish [6]. A neural ensemble known as the command nucleus (CN) initiates the EOD. Action potentials in CN are correlated with EODs (i.e., each action potential in CN leads to an EOD). Nevertheless, CN is not a pacemaker but an integrator system. It mainly receives synaptic input from the mesencephalic precommand nucleus (PCN) and the adjacent thalamic dorsal posterior nucleus (DP) (Fig. 1). Nuclei DP and PCN receive projections from multiple sources, but they are both inhibited by the ventroposterior nucleus (VPd). This inhibition is mediated by the activation of VPd through a feedback mechanism, the corollary discharge pathway (see E_{PCN} in Fig. 1). Inhibition feedback is a mechanism for avoiding responses to the fish own EOD and seems to regulate the resting electromotor rhythm [9]. This is also emphasized by the fact that the IPI of DP/PCN nuclei last, at least, as much as VPd bursts [8].

We have developed a model of the electromotor command system of pulse mormyrids. The model design was driven by the aim of reproducing the variability of temporal firing patterns showed by pulse mormyrids. It is noteworthy that the model reproduces the network's ability to evoke different SPI patterns (related to different fish behaviors) without modifying its internal parameters and due only to changes in the electrical inputs to the network based on those described in [6].

Samples of these patterns were obtained for this work from experimental data recordings of living *Gnathonemus Petersii* specimens [13,14,20] for the first time. These types of patterns have been previously characterized in another species of the *Mormyridae* family [10]. The model topology and nucleus dynamics are based in the

Figure 1. Abridged schematic of the electromotor command network based on [4,8] and used for developing the computational model discussed in this paper. An EOD occurs after each action potential in CN [15], so CN activations represent the output of the model. CN receives excitatory projections from DP (E_{DP}) and PCN (E_{PCN}). Inhibitory afferents are driven to DP and PCN through VPd (I_{DP} and I_{PCN} respectively) triggered by the corollary discharge pathway (E_{CDP}), which makes VPd to fire a burst of action potentials right after the production of an EOD [7]. This inhibition feedback seems to regulate the rythm of EOD output [33]. Current inputs to the electromotor model (In_{VPd}, In_{DP}, In_{PCN}) can be tuned to simulate different behavioral conditions.

results from previous physiological studies of the pulse mormyrid electromotor system [6].

An automated method based on genetic algorithms (GA), with the development of a multiobjective fitness function specifically adapted to this system, was applied for synaptic parameter setting. Patterns recorded from *Gnathonemus petersii* and synthetic samples generated from previously described behavioral patterns in pulse mormyrids were used to fit the model parameters. Finally, the robustness of the model was tested under systematic variations of network inputs to assess validity and discard overfitting to these inputs.

Computational model of the electromotor command network

Figure 1 illustrates the model of the electromotor command network described in the following subsections. We also describe below the genetic approach used to fit the connectivity parameters that give rise to the generation of distinct activity patterns as a function of the stimuli.

Characteristic pulse interval sequences: Synthetic and experimental data

Pulse mormyrids generate a wide variety of electrical activity patterns using different sequences of pulse intervals (SPIs). Previous studies have described several stereotyped SPIs related to distinctive social behaviors [10]. Accelerations, scallops, rasps and cessations are four relevant SPIs that have been described [6,10,21].

Accelerations are sustained interval shortenings to a series of regular smaller IPIs with variable duration. Accelerations (see Fig. 2) are related to the activation of the neural ensemble known as the adjacent thalamic dorsal posterior nucleus (DP, see Fig. 1) [9]. According to [19], this kind of SPI is related with aggressive behaviors.

Figure 2. Characteristic SPI patterns recorded from freely-behaving *Gnathonemus Petersii* specimens (top) and examples of corresponding synthetic SPIs to evolve and validate the electromotor command network model (bottom). Signals were recorded using the platform and the methodology explained in the Experimental Methods section (see also [20]). Synthetic SPIs were constructed preserving the characteristic temporal structure of reported experimental observations [6, 9, 25].

Scallops (see Fig. 2) are sudden drops to very short IPIs followed by an almost immediate recovery to regular resting IPIs. Contrary to what occurs in accelerations, the emmission of shorter IPIs is not sustained. An scallop pattern in CN takes place after the activation of the mesencephalic precommand nucleus (PCN, see Fig. 1), and this kind of firing pattern may serve as an advertisement signal [28].

Rasps (see Fig. 2) are a type of IPI pattern that has an initial sudden decrease to very short IPIs, similar to the one observed in scallops, followed by a step increase of IPIs duration for a sustained series of IPIs, like a long tail of short regular IPIs similar to the ones observed in the acceleration pattern [17]. Rasps occur as a result of the activation of both DP and PCN (see Fig. 1. This SPI is evoked during male courtship behavior [10].

Finally, cessations (see Fig. 2) correspond to activity dropping in the EOD generation for time periods up to one second. A cessation is evoked by the activation of the ventroposterior nucleus (VPd, see Fig. 1). Submissive behavior has been associated with this SPI [24, 25].

Nuclei model

Four different neuron ensembles in the electromotor command chain were modeled: The medullary command nucleus (CN), the mesencephalic precommand nucleus (PCN), the adjacent thalamic dorsal posterior nucleus (DP) and the dorsal region of the ventroposterior nucleus (VPd). Each nucleus was simulated using the neuron model developed by Izhikevich (2003) [18]. This model combines biologically plausibility and computational performance characteristic of integrate-and-fire neuron modeling approaches [22]. It is based in a two-dimensional system of ordinary differential equations:

$$\frac{dv}{dt}(t) = 0.04v^2 + 5v + 140 - u + I_{syn}(t), \tag{1}$$

$$\frac{du}{dt}(t) = a(bv - u), \tag{2}$$

with an auxiliary after-spike resetting:

$$\text{if } v \geq 30\text{mV, then } \begin{cases} v = c \\ u = u + d \end{cases}, \tag{3}$$

where v represents the neuron's membrane voltage and u represents the combined action of ionic current dynamics. The parameters a, b, c and d set the working regime of the neuron model. I_n is the model external input.

A wide range of neuron dynamics, and in particular firing temporal structures, can be reproduced by selecting different values of the parameters a, b, c and d, as shown in [18]. The parameters of the neuron model were adjusted to exhibit the dynamics described by previous neurophysiological studies of the electromotor command network. The activity of each modeled nucleus was compared to the activity of the corresponding ensemble (see table 1). The following firing regimes of the nuclei model were used:

- Low-threshold spiking (LTS): A type of low firing threshold activity for inhibitory cells. In this mode, a neuron can fire high-frequency trains of spikes (burst) and it also shows frequency adaptation while the stimulation is sustained (see table 1). The parameters of VPd in the model correspond to this kind of behavior.

- Regular frequency spiking (RFS): This mode correspond to spike firing at a regular frequency when stimulation amplitude is held constant (see table 1). It is the firing regime in which DP operates.

- Regular Spiking (RS): This mode increases its regular firing frequency when stimulated (see table 1). Adaptation to the stimulus results in a recovery from short interspike intervals to the regular firing frequency. PCN follows this behavior.

- Phasic Spiking (PS): This firing regime operates as an integrate and fire model, although it fires only a single spike as a response to the input, and remain quiescent afterwards. In the model, it is the firing regime used for CN.

Figures in table 1 show the activity of the individual dynamics of all nucleus types considered in the model.

The VPd nucleus exhibits an activity that was modelled using a *low-threshold spiking* firing regime. As recorded VPd bursts last as long as the IPI of DP/PCN nuclei, the initial synaptic parameters were selected in order to reproduce this behavior. The DP nucleus was adjusted to show *regular frequency spiking*, as it evokes a firing pattern in CN which showed prolonged decreases to regular shorter IPIs. The PCN nucleus was modelled to show a decreasing frequency as a response to a spiking input, as this kind of adaptation is observed in the pattern it evokes (scallop). The *regular spiking* firing regime in the model showed that kind of firing behavior. Finally, the CN nucleus was configured to a *phasic spiking* firing pattern as it mainly integrates inputs from DP and PCN. The specific parameter values chosen for the different firing regimes of the nuclei model are listed in S1 Appendix.

Synapses model

We reproduce neural projections using a model of chemical synapses as chemical inter-nuclei communication takes place in the real electromotor command network. In these synapses, when the pre-synaptic target generates an action potential a certain amount of neurotransmitters are released and bind to the postsynaptic receptors. The mathematical description used to model this behavior is based in a description of the receptor bindings [12]. These equations define a simple method for computing synaptic currents with low computational expense. The ratio of bound chemical receptors in the post-synaptic target (r) during a pulse ($t_f < t < t_r$) and after the pulse ($t_r < t$) was calculated as follows:

$$\dot{r} = \begin{cases} \alpha[T](1-r) - \beta r, & \text{if } t_f < t < t_r \\ -\beta r, & \text{otherwise} \end{cases}, \tag{4}$$

Table 1. Dynamic properties of the model nuclei chosen in this study to match their biological counterparts. Values for the parameters of the model by [18] were tuned to replicate the desired experimental dynamic (parameter values are detailed in S1) Appendix. Last column shows the activity of each isolated nucleus model in response to an input current step ($I_{syn}(t)$ in Eq. 1).

Nucleus	Desired dynamic	Nucleus model response
VPd	Low threshold spiking	
PCN	Frequency adaptation	
DP	Regular frequency	
CN	Integrate and fire	

where α and β are the forward and backward rate constants for transmitter binding and [T] is the neurotransmitter concentration.

The beginning of a pulse (t_f) was detected when presynaptic neuron's membrane potential crossed a given *threshold*. Time between t_f and t_r was defined as the maximum release time (t_{max}). Both *threshold* and t_{max} were tuned as a parameter of the synapsis.

From the ratio of bound receptors is given by equation 4, the current received by the post-synaptic target, I_{syn}, at any time t was then calculated as follows:

$$I_{syn}(t) = g \cdot r(t) \cdot (V_{\text{post}}(t) - E_{\text{syn}}), \tag{5}$$

where g is the synaptic conductance, $V_{\text{post}}(t)$ is the post-synaptic potential at time t, and E_{syn} is the synaptic reversal potential at the same time.

The topology of the model was set up using a standard configuration of the model of chemical synapses (E_{DP}, E_{PCN},I_{DP}, I_{PCN}, E_{CDP} in Fig 1). The adjustment of the aprameters of these synapses is essential to generate the four types of SPI patterns generated by the electromotor command network. First, an ad hoc tuning of the parameters of the model was performed, which included an analysis of the simulation results iteratively. Due to the intrinsic complexity of this task, the automatic selection method described in the next section was then developed and applied.

Automatic selection of synapse parameters

An automatic approach was used to tune the parameters of the model synapses. This approach was followed to overcome the lack of specific physiological information about the characteristics of the synapses in the real system. A genetic algorithm (GA) was developed and applied to evolve the parameters of the synapses in order to reproduce the variability of the electromotor command system patterns.

Each individual I in the population of the GA was conformed by a set of 20 parameter values: α, β, g, t_{max} for each of the 5 synapses of the model (see Fig. 1, Eq. 4 and Eq. 5). Each I in a generation had different randomly modified values from the initial ad hoc tuned model. Alterations for each parameter were constrained under different ranges in different executions of the GA.

Each generation, starting from the initial one, was formed by 100 different individuals. The GA follows an steady state GA scheme [1], although other GA schemes [21] were also tested. In this scheme, a temporary population was created by cross and mutation and it was added to the original population. All individuals were then evaluated (using the fitness function described in the next section) and ranked according to their grade. The worst individuals were discarded in order to return the population to its original size. The best individuals (10%) were maintained between generations. This process continued for a predefined number of generations or until a certain fitting value was reached.

Fitness function

Each individual, defined by a set of values for the previously specified parameters, was evaluated being simulated under a predefined set of 4 different simulation cases (S) , each one corresponding to a target SPI: Acceleration (S_{acc}), scallop (S_{sca}), rasp (S_{rasp}), cessation (S_{cess}). Simulation cases (S_{pat}) established the current inputs required to reproduce the *pat* pattern. Each individual I was modeled under all four simulation cases. The fitness function of the overall individual $(f(I))$ was defined as the sum of the fitness results under each case:

$$f(I) = f_{acc}(I) + f_{sca}(I) + f_{rasp}(I) + f_{cess}(I), \tag{6}$$

The four target patterns (acceleration, scallop, rasp and cessation) were defined in terms of an ordered sequence of IPIs $(p_0, ..., p_m)$ where p_i is each IPI in temporary order. The output of a simulation case was also defined in terms of an ordered sequence of IPIs. To compare sequences, they were normalized to the same duration (1000 arbitrary units), regularly interpolated (every 20 arbitrary units, obtaining $n = 50$ points) to detect the pattern shape, and differentiated, as SPI patterns are better defined by the increasing/decreasing slopes between IPIs better than the absolute timing values (see Fig. 4 for an example). The pseudocode of this fitness function is shown in Table 3.

Finally, the fitting value $f_{pat}(I)$ was calculated by comparing the target SPI patterns after these transformations $(p_0^t, ..., p_n^t)$ with the SPI model outputs after the same transformations $(p^S(I)_0, ..., p^S(I)_n)$ using the mean squared error (MSE) as follows:

$$MSE(I) = \frac{\sum_{i=0}^{n}(p_i^t - p^S(I)_i)^2}{n}, \tag{7}$$

$$f_{pat}(I) = \frac{100}{1 + MSE(I)}, \tag{8}$$

Figure 3 Pseudocode of the fitness function, which relies on three different procedures: First, *tranformSPI* procedure considers the list of sequential IPIs that form one SPI and applies the transformations showed in Fig. 4. Then, *evalPattern* procedure applies *tranformSPI* to both the simulated SPI (*simulSPI* procedure) and the target pattern (*targetSPI*) to compare them by calculating the mean squared error between both (*msePattern*, calculated as described in Eq. 7). The *evalPattern* procedure returns the fitting value of a pattern (*fitValuePattern*) calculated as described in Eq. 8. Finally, *evaluate* procedure invokes *evalPattern* for each of the four patterns (scallop, acceleration, rasp and cessation) and adds them to return the fitness value of the overall individual (*fitValue*, equivalent to $f(I)$ in Eq. 6).

procedure TRANSFORMSPI(SPI)
    $SPI \leftarrow$ normalize(SPI)
    $SPI \leftarrow$ interpolate(SPI)
    $SPI \leftarrow$ diff(SPI)
    return SPI
end procedure

procedure EVALPATTERN(I,S_{pat})
    $simulSPI \leftarrow$ transformSPI(simulate(I, S_{pat}))
    $targetSPI \leftarrow$ transformSPI($targetSPIs_{pat}$)
    $msePattern \leftarrow$ MSE($targetSPI$, $simulSPI$)
    $fitValuePattern \leftarrow 1/(1 + msePattern)$
    return $fitValuePattern$
end procedure

procedure EVALUATE(I)
    $fitValue \leftarrow 0$
    for S_{pat} in $Simulations$ **do**
        $fitValue \leftarrow fitValue +$ evalPattern(I, S_{pat})
    end for
    return $fitValue$
end procedure

Figure 4. Steps for SPI output fitness evaluation in a rasp pattern example comparing a target SPI (top) and a simulated SPI (bottom). The input current step function is injected at 500 ms and lasts for 400 ms. First, the SPI is normalized to 1000 arbitrary units (in the figure, it is represented starting at the first IPI). Normalized IPIs are then interpolated every 20 ms and differentiated ($\dot{g}(IPI)$). Finally, the mean squared error is calculated between the target SPI pattern and the simulated one.

Model simulation

Since the model presented here is multi-objective (i.e., it reproduces different SPI patterns when modifying only the model inputs), a set of four different simulation cases (each one related to a distinct SPI pattern) was determined. Each simulation case was defined by the input current values received by the model (In_{VPd}, In_{DP}, In_{PCN} in Fig. 1) during the simulation of the four SPI patterns shown in Fig. 5. This predefined inputs were step functions that represent projections received by VPD, DP and PCN nuclei from other sources of the nervous system. Input values for each SPI case are described in S2 Appendix. The electromotor command network model and the source code of the model and the multi-objective genetic algorithm is provided (see S3 Appendix) and can be easily adapted to other animal data and network models.

Robustness to input variability and overfitting analysis

An analysis for all the different configurations of the model was conducted to assess robustness to input variability and discard overfitting to the predefined stimulation cases. The step functions used as inputs in the simulations are meant to reproduce the nuclei activation associated with each SPI (see S2 Appendix). As a consequence, similar SPIs were expected to result from distinct inputs as long as the appropriate nucleus was stimulated. According to this hypothesis, a robustness analysis to input variability was conducted.

To perform this analysis, a set of different simulations was conformed by modifying the intensity and duration of the predefined model inputs (i.e., the inputs used in the GA for simulating the patterns showed in Fig. 5) up to a 50%. Being $\text{In}_p^0(n)$ the predefined value of the input received by nucleus n in the p pattern simulation case (see S2 Appendix), and $t_p^0(n)$ the duration of the step, the set of simulations to assess robustness is built by modifying intensity from $-0.5 \cdot \text{In}_p^0(n)$ to $0.5 \cdot \text{In}_p^0(n)$ in steps of 0.05, and also modifying duration from $-0.5 \cdot t_p^0(n)$ to $0.5 \cdot t_p^0(n)$ using the same interval steps (see Fig. 6 - Right). Then, the reproducibility of the patterns under this set of

stimulation cases was evaluated using the fitting function. In this case, a relative fitting value was defined as the change ratio of the fitting value from the default stimulation case. Being f^0 the fitness value of the model under predefined stimulation, and f^i the fitness value under a given stimulation case of the set, then, the relative fitting value ($\Delta f(i)$) was given by:

$$\Delta f(i) = 100 \frac{f^i - f^0}{f^0} \tag{9}$$

where negative results mean a decrement in the fitting value when varying the stimulation inputs. When $f^i = f^0$, $\Delta f(i) = 0$, which is the case in the central point of robustness charts that we will discuss later (see Fig. 6 - Left and Fig. 7)

Robustness of the model is evaluated below in terms of the relative increments and decrements of this value. Strong robustness is defined as the ability to maintain $\Delta f(i) > 0$. Note that, here, the fitness function was used again to measure the distance to target patterns, but no GA was employed.

Results

Three different configurations of the model were analyzed (see Table 2 and also S1 Appendix), first the ad hoc tuned configuration (S-T) and the other two from GA-tuning of synaptic parameters, one fitted to synthetic SPI patterns (S-GA) and the other one fitted to reproduce SPI patterns recorded from *Gnathonemus Petersii* specimens (R-GA) (See Fig. 2). Each configuration reproduced all four SPI patterns with a different level of accuracy and robustness, but due only to changes in the inputs (In_{VPd}, In_{DP}, In_{PCN} in Fig. 1), and without modifying any internal parameters. GA configurations showed some shared characteristics between them when compared with the S-T configuration, as the increases in the absolute value of the synaptic conductances (g_{syn}). Note that some of these parameters noticeable change, this is the case of the g_{syn} parameter for the E_{PCN} synapsis (an increase of four times for S-GA and five times R-GA from its initial value in S-T, as it can be seen in Table 2 and S1 Appendix). These similarities are remarkable as network parameters are fitted to a different set of samples of the same SPI patterns. Also remarkable is that S-GA showed similar α, β and t_{max} parameters for both E_{DP} and E_{PCN} projections (Fig. 1), which means that the timing of the synapses is almost symmetrical for both excitatory pathways (Fig. 1).

Four different SPIs patterns were simulated (Fig. 5) using the three configurations of the model: S-R, S-GA and R-GA. In all three configurations, accelerations (Fig. 5 - B) showed a series of almost regular reduced-duration IPIs. In S-T, short IPIs during acceleration were around 20 ms. In S-GA and R-GA short IPIs during acceleration were larger (around 60 ms. in S-GA and 90 ms in R-GA), better complying with the SPI recorded from the fish (which are highly variable, but consistently larger than 20 ms and larger than shorter IPIs observed in scallops). Regarding IPIs regularity during the acceleration, the shorter IPIs within a burst had approximately the same duration. Both R-GA and S-GA configurations showed regularity in the sequence of short IPIs that define acceleration, although the starting IPI tended to be slightly shorter.

Regarding S-T results, scallop and rasp SPI patterns cannot be easily distinguished, as both showed acceleration-like short regular IPIs (Fig. 5). The total SPI duration was different for each pattern, but rasps and scallops lacked their own characteristic internal structure in S-T.

Scallop simulations in both S-GA and R-GA showed the typical behavior associated to this pattern (which is a sudden drop to short IPIs (around 40 ms) followed by an almost immediate recovery). The shorter IPI reached in S-T was slightly fastest ($\sim$25 ms), although the burst duration in all three configurations remained almost the same.

Table 2. Relevant synapse parameters of the GA adjusted to synthetic patterns (S-GA) and GA adjusted to recorded *Gnathonemus Petersii* patterns (R-GA, see Fig. 2) configurations of the model (*threshold* = 0; $E_{syn} = -80$; T = 1; see Eq. 4 and Eq. 5).

S-GA				
Synapse	α	β	g_{syn}	t_{max}
I_{DP}	9.05623	0.00272207	-0.1251	223.097
I_{PCN}	7.50072	0.0270961	-0.27628	169.763
E_{DP}	4.949	0.127261	0.179499	78.9001
E_{PCN}	4.949	0.148451	0.259499	78.9001
E_{CDP}	4.79499	0.00327418	0.705623	396.811

R-GA				
Synapse	α	β	g_{syn}	t_{max}
I_{DP}	0.537866	0.0052969	-0.165774	177.288
I_{PCN}	5.94833	0.00129492	-0.307652	167.175
E_{DP}	5.98168	0.120037	0.238086	9.51458
E_{PCN}	5.02672	0.218571	0.199753	84.4537
E_{CDP}	4.43346	0.0137051	0.647143	428.988

Both in S-GA and R-GA it was true that the shorter IPI in the scallop pattern was shorter than the shorter in the acceleration pattern, in accordance with the activity recorded in the fish.

In S-GA and R-GA, rasps (Fig. 5 - C) showed an initial scallop-type decrease to IPIs around 40 ms, followed by a sustained burst of regular short IPIs like in accelerations. As mentioned before, in S-T the pattern was not fully identifiable. In S-GA the IPIs were shorter, so the SPI was formed by a larger number of IPIs. Also, the recovery to larger IPIs was more abrupt in this case.

Finally, cessations (Fig. 5 - D) showed the expected stop in the generation of pulses during long time periods (of around 500 ms) in all three configurations.

Results for the robustness analysis to input variability of R-GA are depicted in Fig. 6 using a color representation of $\Delta f(i)$ as described by Eq. 9. Results did not show relevant decreases in the fitting value for alterations of up to 50% in the intensity and duration of the default simulation values. Conversely, they showed a limited increase of the fitting value when slight decreases in duration were balanced with slight increases of intensity and, similarly, when slight increases in duration were balanced with slight decreases of intensity.

To discard overfitting to any of the SPI patterns, results of this analysis disaggregated by pattern are also shown in Fig. 7 (rightmost column). No relevant drops in the fitness results stands out in these panels for variations of up to 50% in the intensity and duration of the predefined stimulation inputs. Quite the opposite, better evaluation results (depicted in dark red) were usually obtained, for example, in R-GA scallops, specially for increases in the input duration. For comparison, we also depict in Fig. 7 the robustness results of the other two configurations of the model (those adjusted to synthetic patterns: S-T, S-GA). S-T moderately improved the fitness results in accelerations, and also in cessations when a increase in the duration of the inputs were compensated with a decrease in the input duration. S-GA, in general, showed greater robustness to input variability, maintaining or improving fitness in all SPI patterns.

In Fig. 8, IPIs mean and standard deviation of each SPI pattern simulated during

the robustness analysis of the R-GA model are depicted. In this figure, the SPI depicted in red is the mean SPI of the several executions with variable inputs and the red shade represents the standard deviation of the results. Finally, the SPI represented in black is the closer target pattern used to calculate the fitness. The simulation of each SPI pattern were divided in three partitions according to its fitting value: Worse fit than the one obtained with default inputs ($\Delta f < -100$); similar fit ($-100 < \Delta f < 100$) and worse fit ($\Delta f > 100$).

Figure 5. Simulation of three different models under the simulation conditions associated with all the four SPI patterns. The model parameters are described in S1 Appendix. Simulation parameters are described in S2 Appendix.

Discussion and conclusions

Computational models has been previously used to answer different questions in the study of electroreception and electrogenesis. Regarding electrogenesis, authors in [23, 26, 30] used an anatomically detailed model of the pacemaker of *Apteronotus leptorhynchus* to study the electric organ signal and its spatiotemporal features in wave-type fish. In [29] a model for the *Eigenmannia* was employed to address the jamming avoidance response in these fish. Electroreceptor models are of particular interest as they have a relevant role in understanding the electrical sense, even in non-electroactive species. Finally, bioinspired approaches intend to mimic electrolocation by building robotic electrosensory systems at different abstraction levels. Aiming to develop an underwater autonomous robot with electric sense, a robotic model of the electric fish fins was developed to study fish manoeuvrability [27].

Figure 6. Left: Robustness analysis to input variability of the R-GA electromotor model tuned to recorded *Gnathonemus Petersii* SPI patterns. The central point in the left panel represents the reference fitness value, the one obtained simulating the model under the predetermined simulation conditions (i.e. ΔDuration = 0 and ΔIntensity = 0). Duration and intensity of the step function current input is variated from -0.5 to 0.5 from their initial values and the relative change in the fitness value is calculated as described by Eq. 9. White and lighter yellowish colors represent decreases in the fitness value under variable stimulation. Orange colors represent an equivalent result to the reference fitness value. Darker red colors represent an improvement in the fitness value. Right: Example of distinct current inputs in the simulation at different places of the chart.

Despite the variety of models regarding signal generation in weakly electric fish, the development of a computational model of the electromotor command network (more precisely, a model that can produce the variability of SPIs observed in behaving animals) had not been attempted until now for the mormyrid pulse-type electromotor system. The model presented here assesed the relevance of different parameters in the electromotor command chain and pointed out to the importance of the synaptic parameters (and not only the nucleus dynamics or the network topology) for reproducing the temporal structure of output patterns displayed by the electromotor system. Actually, the diverse temporal organization of SPIs is possible due to a precise balance of strength intensity and timing between the synapses of the network.

The development of this model started by a systematic ad hoc tuning of the nucleus parameters to match the variability of SPIs observed in experimental data. It soon became clear that it was nearly impossible to accomplish this task without changing the synaptic parameters for each target pattern, although it served to gain insight about how certain nucleus parameters altered the dynamical properties of the overall network. This highlighted the hypothesis that relevant synaptic parameters play an important role in the generation of the structure of temporal patterns by the electromotor system.

A multi-objective genetic algorithm was developed and applied to tune the synaptic parameters of the model. Attending to the results, automatic parameter optimization allowed to prove that it is possible to reproduce the four preselected SPI patterns using the described topology by tuning the synapses parameters.

Regarding the resulting model configurations (described in S1 Appendix), they all indicate that the corollary discharge must have a larger maximum release time than any other of the synapses in the model. This characteristic is always present in all best individuals obtained from the GA and is coherent with the idea that it might be an indirect pathway. Also, the fact that S-GA showed similar α, β and t_{max} parameters for both E_{DP} and E_{PCN} projections (see table 2) reinforces the hypothesis of synaptic intensity being the decisive parameter in the elicitation of accelerations or scallops.

Figure 7. Deviation from the f_P^0 (reference fitness value) of each model configuration (S-T, S-GA and R-GA) modifying default current input intensity ($\text{In}_p^0(n)$) from $-0.5 \cdot \text{In}_p^0(n)$ to $0.5 \cdot \text{In}_p^0(n)$ in steps of 0.05, and also modifying default current input duration ($t_p^0(n)$) from $-0.5 \cdot t_p^0(n)$ to $0.5 \cdot t_p^0(n)$ using the same step. The color scheme is the same as the one described in Fig 4. See Fig. 8 for a representation of the IPIs (mean and variance) resulting from worse (light yellow), similar (orange) and better (dark red) fitness results in R-GA.

Nevertheless, the conductance ratio between these synapses is not the same in R-GA. It denotes that the relation between synaptic strengths determines the output of the system in a non-linear manner.

Robustness results show that overfitting to the stimulation inputs was avoided. Although there are considerable drops in fitness for certain combinations of inputs, the general tendency was to maintain (and sometimes even improve) the performance of the model under distinct stimulation (as shown in Fig. 6 and Fig. 7). S-GA and S-T configurations showed a strong robustness to changes in the stimulation inputs (both in terms of intensity and duration), which is coherent with the fact that synthetic target patterns showed less richness and thus were more easily reproduced. In R-GA, rasps were the least robust SPI patterns, but even those with the worsts fitting results kept a recognizable, though slightly flattened, rasp shape. These robustness results give credit to the idea that SPI generation depends on which nucleus is activated and not so much on the intensity or the duration of the inputs.

Figure 8. Mean and variance of simulated SPIs using the R-GA model under the variated simulation conditions of the robustness analysis (see Fig. 7). As in the GA fitness function, the duration of each simulation was normalized to 1000 arbitrary units for representation, starting at its first IPI. Red SPI is the mean SPI from the executions with variated inputs, red shade represents the standard deviation. Finally, the SPI represented in black is the closer target pattern. Simulations of each SPI pattern were divided in three partitions according to its fitting value: the ones that obtains better fitting (upper row: $\Delta f < -100$), those that obtains similar results to the reference fitness value (center row: $-100 < \Delta f < 100$) and the ones that yield worse fitting results (bottom row: $100 < \Delta f$).

The implemented model and its computational efficiency also enables closer-to-natural stimulation to perform more realistic closed-loop experiments with the real system (as pulse mormyrids have been previously used in several closed-loop studies where stimulation is guided by the fish own activity [13, 14, 20]). In this context, we can expect these experiments to benefit from a more realistic stimulator based in the described model [20]. The model can also allow further studies of the underlying mechanisms of electrocommunication, although the internal relationship between fish skin electroreceptors and the electromotor system has yet to be further studied.

All the software developed and used in the analysis presented here (the model, the multi-objective GA used for parameter adjustment with the fitness function used to represent and compare different sequences of temporal firing patterns and the robustness analysis) is provided for future studies of this network and similar networks of other animal models (see S7 supplementary material). This tools can deepen our understanding about the role of the ensemble connectivity and the synaptic mechanisms shaping functional neural temporal structures.

Experimental Methods

Characteristic SPI recordings

The SPIs were recorded from three different freely-behaving *Gnathonemus Petersii* specimens in a 80 l water tank, using four differential dipoles placed in the tank forming

45º angles between them. The grounding electrode was also located in the aquarium. The signal from the dipoles was amplified (TL082 JFET-Input Dual Operational Amplifier), summed (LM741 Operational Amplifiers), squared (using AD633 Analog Multiplier) and then digitized at 15 Khz by a DAQ board (NI PCI-6251, National Instruments Corporation).

IPIs detection was performed using an spike detection algorithm as described in [20]. Examples of SPI recorded from *Gnathonemus Petersii* specimens are depicted in Fig 2 (top).

SPI synthetic data

SPI synthetic data was used for S-GA tuning as it allows for large number of different cases of each pattern to be generated for the evolution of the GA. Synthetic SPIs were constructed preserving the characteristic temporal structure of reported behavioral patterns [6, 10, 25]. Four different synthetic SPIs were generated for each behavioral pattern (scallop, acceleration, rasp and cessation) by randomly altering the timing and amplitude of the IPIs while preserving the characteristic SPI temporal structure. Figure 2 (bottom) shows only one set of the patterns.

Supporting information

S1 Appendix. Model parameters The electromotor system was modeled using four nuclei and five synapses. The nuclei VPd, DP, PCN and CN were simulated using the neuron model developed by Izhikevich (2003) [18], where a wide range of neuron dynamics can be evoked by selecting different values of the parameters a, b, c and d. Table 2 show the parameter values used in the electromotor model. These values were tuned ad hoc to reproduce dynamics described by previous neurophysiological studies. The synapses (I_{DP}, I_{PCN}, E_{DP}, E_{PCN} and E_{CDP}) were simulated using the model described by [12]. The most relevant parameters of the model (α, β, gsyn and t_{max}) were automatically adjusted to the target SPI patterns using the genetic algorithm (GA) described in this paper. Table 2 showed the initial ad hoc tuned configuration (S-T).

S1 Table. Neuron parameters of the model to reproduce the dynamics of the electromotor nuclei as described by previous neurophysiological studies [6] (see Eq. 1, Eq. 2 and Eq. 3).

Neuron	Dynamics	a	b	c	d
VPd	Low-threshold spiking (LTS)	0.02	0.25	-65	2
DP	Regular frequency spiking (RFS)	0.1	0.26	-65	2
PCN	Regular spiking (RS)	0.02	0.2	-65	8
CN	Phasic spiking (PS)	0.02	0.25	-65	6

S2 Table. Relevant synapse parameters of the ad hoc tuning to synthetic patterns (S-T) configuration of the model (*threshold* = 0; $E_{syn} = -80$; T = 1; see Eq. 4 and Eq. 5).

| Synapse | S-T | | | |
	α	β	g_{syn}	t_{max}
I_{DP}	5	0.005	-0.12	160
I_{PCN}	5	0.005	-0.15	160
E_{DP}	5	0.1	0.1	30
E_{PCN}	5	0.18	0.05	30
E_{CDP}	5	0.02	0.3	400

S2 Appendix. Simulation parameters To simulate the electromotor command system, VPd, DP and PCN received external currents, which represent inputs. These predefined values represent current inputs received by the nuclei from other sources of the nervous system. The following tables show the current input values for simulating scallops (S3 Table), accelerations (S4 Table), rasps (S5 Table) and cessations (S6 Table). The first row in each table represents simulation time (in milliseconds), and subsequent rows represents neuron current input for each nucleus model (VPd, DP, PCN) during this time. These inputs were step functions used to simulate the SPIs shown in Fig. 5. Also, these are the predefined simulation parameters for the GA evolution and the $In_p^0(n)$ robustness analysis (center values in Fig. 6 and Fig. 7).

S3 Table. Scallop simulation parameters. This SPI pattern is evoked by increasing current input to PCN neuron. VPd input (-0.5 mA) and DP input (1.7 mA) are constant in this pattern.

Time (ms)	[0, 520]	[520, 680]	[680, 1200]
PCN input	6.5	14	6.5

S4 Table. Acceleration simulation parameters. This SPI pattern is evoked by increasing current input to DP neuron. VPd input (-0.5 mA) and PCN input (6.5 mA) are constant in this pattern.

Time (ms)	[0, 800]	[800, 1200]	[1200, 2000]
DP input	1.7	4	1.7

S5 Table. Rasp simulation parameters. This SPI pattern is evoked by increasing current input to both DP and PCN neurons. VPd input (-0.5 mA) is constant in this pattern.

Time (ms)	[0, 500]	[500, 580]	[580, 830]	[830, 1330]
DP input	1.7	4.5	4	1.7
PCN input	6.5	15	7	6.5

S6 Table. Cessation simulation parameters. This SPI pattern is evoked by increasing current input to VPd neuron. DP input (1.7 mA) and PCN input (6.5 mA) are constant in this pattern.

Time (ms)	[0, 250]	[250, 650]	[650, 1000]
VPd input	-0.5	8	-0.5

S3 Appendix.   Source code All the software used to develop and run the model, as well as the model itself, are publicly available under an open-source license in the following github repository: https://github.com/angellareo/electromotor-nmodel.

The repository includes C++ code needed to run the model, which makes use of Neun dynamical-systems library[1]. The genetic algorithm applied to automatically tune the parameters of the model, implemented using GAlib[2], it is also provided. Some examples of the recorded and synthetic patterns used as targets to tune the model are also included. Finally, the repository also includes detailed instructions to compile and use the software.

References

1. A. Agapie and A. H. Wright. Theoretical analysis of steady state genetic algorithms. *Applications of Mathematics*, 59(5):509–525, 2014.

2. C. A. Baker, T. Kohashi, A. M. Lyons-Warren, X. Ma, and B. A. Carlson. Multiplexed temporal coding of electric communication signals in mormyrid fishes. *The Journal of Experimental Biology*, 216(13):2365–2379, July 2013.

3. A. H. Bass and C. D. Hopkins. Hormonal control of sexual differentiation: Changes in electric organ discharge waveform. *Science*, 220(4600):971–974, 1983.

4. C. Bell, S. Libouban, and T. Szabo. Pathways of the electric organ discharge command and its corollary discharges in mormyrid fish. *Journal of Comparative Neurology*, 216(3):327–338, 1983.

5. A. A. Caputi. The electric organ discharge of pulse gymnotiforms: The transformation of a simple impulse into a complex spatio-temporal electromotor pattern. *Journal of Experimental Biology*, 202(10):1229–1241, 1999.

6. A. A. Caputi, B. A. Carlson, and O. Macadar. Electric organs and their control. In *Electroreception*, pages 410–451. Springer, 2005.

7. B. A. Carlson. Neuroanatomy of the mormyrid electromotor control system. *Journal of Comparative Neurology*, 454(4):440–455, 2002.

8. B. A. Carlson. Single-unit activity patterns in nuclei that control the electromotor command nucleus during spontaneous electric signal production in the mormyrid Brienomyrus brachyistius. *The Journal of Neuroscience*, 23(31):10128–10136, 2003.

9. B. A. Carlson and C. D. Hopkins. Central control of electric signaling behavior in the mormyrid Brienomyrus brachyistius: Segregation of behavior-specific inputs and the role of modifiable recurrent inhibition. *Journal of Experimental Biology*, 207(7):1073–1084, 2004.

---

[1]https://code.launchpad.net/~elferdo/neun/trunk
[2]http://lancet.mit.edu/ga/

10. B. A. Carlson and C. D. Hopkins. Stereotyped temporal patterns in electrical communication. *Animal Behaviour*, 68(4):867–878, 2004.

11. B. A. Carlson, C. D. Hopkins, and P. Thomas. Androgen correlates of socially induced changes in the electric organ discharge waveform of a mormyrid fish. *Hormones and Behavior*, 38(3):177–186, 2000.

12. A. Destexhe, Z. F. Mainen, and T. J. Sejnowski. An efficient method for computing synaptic conductances based on a kinetic model of receptor binding. *Neural computation*, 6(1):14–18, 1994.

13. C. G. Forlim and R. D. Pinto. Automatic realistic real time stimulation/recording in weakly electric fish: Long time behavior characterization in freely swimming fish and stimuli discrimination. *PLoS ONE*, 9(1):e84885+, Jan. 2014.

14. C. G. Forlim, R. D. Pinto, P. Varona, and F. B. Rodriguez. Delay-dependent response in weakly electric fish under closed-loop pulse stimulation. *PloS one*, 10(10):e0141007, 2015.

15. K. Grant, C. Bell, S. Clausse, and M. Ravaille. Morphology and physiology of the brainstem nuclei controlling the electric organ discharge in mormyrid fish. *Journal of Comparative Neurology*, 245(4):514–530, 1986.

16. C. Hopkins and A. Bass. Temporal Coding of Species Recognition Signals in an Electric Fish. *Science*, 212:85–92, May 1981.

17. C. D. Hopkins. On the diversity of electric signals in a community of mormyrid electric fish in West Africa. *American Zoologist*, 21(1):211–222, 1981.

18. E. M. Izhikevich et al. Simple model of spiking neurons. *IEEE Transactions on neural networks*, 14(6):1569–1572, 2003.

19. B. Kramer. The attack frequency of Gnathonemus petersii towards electrically silent (denervated) and intact conspecifics, and towards another mormyrid (Brienomyrus niger). *Behavioral Ecology and Sociobiology*, 1(4):425–446, 1976.

20. A. Lareo, C. G. Forlim, R. D. Pinto, P. Varona, and F. Rodriguez. Temporal Code-Driven Stimulation: Definition and Application to Electric Fish Signaling. *Frontiers in Neuroinformatics*, 10:41, 2016.

21. A. Lareo, P. Varona, and F. Rodriguez. Evolutionary Tuning of a Pulse Mormyrid Electromotor Model to Generate Stereotyped Sequences of Electrical Pulse Intervals. In *International Conference on Artificial Neural Networks*, pages 359–368. Springer, 2018.

22. L. N. Long and G. Fang. A review of biologically plausible neuron models for spiking neural networks. *AIAA InfoTech@ Aerospace*, 2010.

23. K. M. Lucas, J. Warrington, T. J. Lewis, and J. E. Lewis. Neuronal dynamics underlying communication signals in a weakly electric fish: Implications for connectivity in a pacemaker network. *Neuroscience*, 401:21–34, 2019.

24. P. Moller. Communication in weakly electric fish, Gnathonemus niger (mormyridae) I. Variation of electric organ discharge (EOD) frequency elicited by controlled electric stimuli. *Animal Behaviour*, 18:768–786, 1970.

25. P. Moller, J. Serrier, and D. Bowling. Electric organ discharge displays during social encounter in the weakly electric fish Brienomyrus niger L.(Mormyridae). *Ethology*, 82(3):177–191, 1989.

26. K. T. Moortgat, T. H. Bullock, and T. J. Sejnowski. Precision of the pacemaker nucleus in a weakly electric fish: Network versus cellular influences. *Journal of Neurophysiology*, 83(2):971–983, 2000.

27. I. D. Neveln, Y. Bai, J. B. Snyder, J. R. Solberg, O. M. Curet, K. M. Lynch, and M. A. MacIver. Biomimetic and bio-inspired robotics in electric fish research. *Journal of experimental Biology*, 216(13):2501–2514, 2013.

28. J. Serrier and P. Moller. Patterns of electric organ discharge activity in the weakly electric fish Brienomyrus niger L.(Mormyridae). *Experimental biology*, 48(5):235–244, 1989.

29. A. R. Shifman and J. E. Lewis. The complexity of high-frequency electric fields degrades electrosensory inputs: Implications for the jamming avoidance response in weakly electric fish. *Journal of The Royal Society Interface*, 15(138):20170633, 2018.

30. A. R. Shifman, A. Longtin, and J. E. Lewis. Ultrafast traveling wave dominates the electric organ discharge of Apteronotus leptorhynchus: An inverse modelling study. *Scientific Reports*, 5:15780, 2015.

31. C. Teyssedre and M. Boudinot. Rhythmicity as an intrinsic property of the mormyrids electromotor command system. *Physiology & behavior*, 41(3):201–207, 1987.

32. G. von der Emde and H. Bleckmann. Differential responses of two types of electroreceptive afferents to signal distortions may permit capacitance measurement in a weakly electric fish, Gnathonemus petersii. *Journal of Comparative Physiology A*, 171(5):683–694, 1992.

33. G. Von der Emde, L. G. Sena, R. Niso, and K. Grant. The midbrain precommand nucleus of the mormyrid electromotor network. *The Journal of Neuroscience*, 20(14):5483–5495, 2000.

Evaluation Function Steps

Models

S-T S-GA R-GA

Patterns

Scallop

Acceleration

Rasp

Cessation