A non-spiking neuron model with dynamic leak to avoid instability in recurrent networks

Udaya B. Rongala[1*], Jonas M.D. Enander[1], Matthias Kohler[2], Gerald E. Loeb[3], Henrik Jörntell[1]

[1] Department of Experimental Medical Science, Faculty of Medicine, Lund University, Lund, Sweden

[2] Department of Informatics, Technical University of Munich, 85748 Garching, Germany

[3] Department of Biomedical Engineering, Viterbi School of Engineering, University of Southern California, Los Angeles, CA, USA

*Corresponding author

E-mail: udaya_bhaskar.rongala@med.lu.se (UBR)

Abstract

Recurrent circuitry components are distributed widely within the brain, including both

excitatory and inhibitory synaptic connections. Recurrent neuronal networks have potential

stability problems, perhaps a predisposition to epilepsy. More generally, instability risks

making internal representations of information unreliable. To assess the inherent stability

properties of such recurrent networks, we tested a linear summation, non-spiking neuron model

with and without a 'dynamic leak', corresponding to the low-pass filtering of synaptic input

current by the RC circuit of the biological membrane. We first show that the output of this

neuron model, in either of its two forms, follows its input at a higher fidelity than a wide range

of spiking neuron models across a range of input frequencies. Then we constructed fully

connected recurrent networks with equal numbers of excitatory and inhibitory neurons and

randomly distributed weights across all synapses. When the networks were driven by

pseudorandom sensory inputs with varying frequency, the recurrent network activity tended to

induce high frequency self-amplifying components, sometimes evident as distinct transients,

which were not present in the input data. The addition of a dynamic leak based on known

membrane properties consistently removed such spurious high frequency noise across all

networks. Furthermore, we found that the neuron model with dynamic leak imparts a network

stability that seamlessly scales with the size of the network, conduction delays, the input

density of the sensory signal and a wide range of synaptic weight distributions. Our findings

suggest that neuronal dynamic leak serves the beneficial function of protecting recurrent

neuronal circuitry from the self-induction of spurious high frequency signals, thereby

permitting the brain to utilize this architectural circuitry component regardless of network size

or recurrency.

Author Summary

It is known that neurons of the brain are extensively interconnected, which can result in many recurrent loops within its neuronal network. Such loops are prone to instability. Here we wanted to explore the potential noise and instability that could result in recurrently connected neuronal networks across a range of conditions. To facilitate such simulations, we developed a non-spiking neuron model that captures the main characteristics of conductance-based neuron models of Hodgkin-Huxley type, but is more computationally efficient. We found that a so-called dynamic leak, which is a natural consequence of the way the membrane of the neuron is constructed and how the neuron integrates synaptic inputs, provided protection against spurious, high frequency noise that tended to arise in our recurrent networks of varying size. We propose that this linear summation model provides a stable and useful tool for exploring the computational behavior of recurrent neural networks.

Introduction

Recurrent excitatory loops are a common feature in the central nervous system, such as in neocortical circuits [1–4], thalamocortical loops [5,6], cerebrocerebellar and spinocerebellar loops [7,8]. Inhibitory interneurons have been described to provide lateral inhibition [9–12] and feed-forward inhibition [13,14], but they also make synapses on other inhibitory neurons, thereby potentially forming recurrent disinhibitory loops as well [15–17]. Furthermore, such excitatory and inhibitory connectivity has been reported to be balanced [18–20]. Functionally, recurrent connections enable a network to use preceding states to impact the processing of the present state. Such state memory can, for example, improve learning performance [21]. However, due to the many potential positive feedback loops in larger networks with extensive recurrent connections, imbalances in excitatory (E) and inhibitory (I) synaptic activity could lead to activity saturation [22,23], such as observed in epilepsy [24,25], or, in milder cases, a noise-like perturbation of the information content of internal signals, which would be disadvantageous for learning.

We explored potential noise and stability issues that could arise in recurrent neuronal networks. In order to focus on the network architecture aspect of this problem, we used a non-spiking neuron model designed to be simple and computationally efficient, while embodying fundamental properties of Hodgkin-Huxley conductance-based models. The relevance of a non-spiking neuron model stems from the stochasticity inherent in neuronal spike generation [26–28], which renders the spiking output of the individual neuron to some degree unreliable in terms of information content. To compensate for such unreliability, the brain could encode each representation across a population of neurons (below referred to as an ensemble of redundant neurons), as has been observed in the brain *in vivo* [29]. The input-output relationships across a range of neuron types in the central nervous system *in vivo* indicate that overall, each neuron's spike output is a probability density function (PDF) of the underlying

membrane potential of the neuron [27]. That PDF thereby approximates the membrane

potential and could be considered to correspond to the spike output of an ensemble of neurons

with similar inputs. Thus, simulating a non-spiking neuron and providing the PDF of the neuron

as its output avoids the extreme resource demands of both simulating the highly complex spike

generation stochasticity [28] and compensating for that stochasticity by simulating large

populations of redundant neurons. Synaptic input creates modulation of the neuronal

membrane potential, hence its PDF, by temporarily activating conductances that are added to

the static leak conductances. The synaptic conductances and currents can modulate very rapidly

but the membrane capacitance together with the static leak channels forms an RC circuit that

constitutes a low-pass filter (herein, dynamic leak) for the resultant membrane potential. We

hypothesized that this dynamic leak would improve network stability without compromising

information transfer.

To test this hypothesis, we constructed a highly recurrent, two-layer neuronal network,

with five excitatory and five inhibitory neurons in the first layer and four excitatory and four

inhibitory neurons in the second layer. All neurons in both layers were reciprocally connected

with randomized gains. All first layer neurons were provided with six randomized and broadly

distributed input signals. A striking finding was that for all tested network configurations,

synaptic weight distributions, various conduction delays and input density of sensory inputs,

recurrent networks tended to generate high frequency components that were not present in the

sensory input data. In all cases these transients were eliminated by incorporating a dynamic

leak in the neuron models without compromising the representation of the input signals.

We note that the fully reciprocal connectivity employed in the networks described

herein encompasses the wide range of connectivity that has been identified experimentally in

cortical and other central neural structures (see above). The strictly layered connectivity of

many popular neural network models for deep learning reflects only a small subset of the

known complexity of biological networks. Attempts to add limited recurrency into such models

have encountered stability problems [22,23], for which dynamic leak appears to offer

substantial mitigation.

Methods

Neuron model

Linear summation neuron model (LSM): The neuron model implemented for this study was

a non-spiking, linear input summation model with an additional dynamic leak component. For

the version without dynamic leak, the activity ($A_{No_{Dyn}}$) was given by the total weighted input

activity ($w * a$) (where a is the activity of each individual input and w is the weight of that

input) across all individual synapses (i) (Eq. 1). Electrotonic compactness in the neuron is

assumed, so that all synapses have equal impact on the activity of the neuron. This simplified

model of synaptic input activity integration can be shown to be closely related to a Hodgkin-

Huxley (H-H) model (see Appendix 1), for example resulting in the preservation of two key

dependencies of EPSPs and IPSPs on membrane biophysics: *i*) input response magnitude

depends on the difference between the membrane potential and the reversal potentials for the

relevant corresponding 'ion channels' (i.e. depending on if the input is provided through an

excitatory or an inhibitory synapse); *ii*) input response magnitude depends on relative shunting

of synaptic currents by conductances resulting from the background of synaptic input activity

(Eq. 1). The responsive properties of the LSM and the H-H neuron model are shown to be

highly similar in S1 Fig.

The LSM implemented a degree of activity normalization (denominator of Eq. 1) by

introducing a static leak, which was calculated as the product of a constant (k_{static}) multiplied

by the number of synapses on the neuron, plus a term reflecting the total number of open

channels, which is activity dependent.

To mimic the effect of the RC circuit created by the ion channels and the capacitance

of the membrane, we added a dynamic leak function to the neuron. To test the impact of the

dynamic leak on network dynamics, we compared the networks composed of neurons with the

dynamic leak with the same network when the neuron model did not include this dynamic leak.

The neuron activity for the neuron model variant with dynamic leak (A_{Dyn}) is given by the

linear summation model with an additional leak time constant (τ_{Dyn}). Larger neurons with

more synapses tend to have longer time constants [30], so we tried various ways of scaling

τ_{Dyn} with number of synapses i. Thereby, the dynamic leak integrates the function of the

capacitance in the RC circuit of the biological neuron into the LSM (Eq. 2). The neuron activity

of this model is given by the following equations,

$$A_{No_{Dyn}} = \frac{\sum(w_i * a_i)}{(k_{static} * i) + \sum|w_i * a_i|} \tag{1}$$

$$\frac{\tau_{Dyn} * dA_{Dyn}}{dt} = -A_{Dyn}(t) + A_{No_{Dyn}}(t) \tag{2}$$

$$0 \leq A_{No_{Dyn}}$$
$$0 \leq A_{Dyn} \tag{3}$$

Figure 1 illustrates the output activity of individual LSM neurons (Eq. 1-3), which were

isolated in the sense that they were not connected to any neuronal network other than the

provided inputs, for different input combinations of emulated excitatory and inhibitory synaptic

inputs (Fig 1A, B). The input spike trains were convoluted using a kernel function in order to

emulate post-synaptic-potential inputs (detailed below, Eq. 6), that were fed to the LSM neuron

(Fig 1C-E). The LSM activity without dynamic leak ($A_{No_{Dyn}}$, Fig 1F) shows the activity

normalization resulting from the static leak constant ($k_{static} = 1$, for this illustration), along

with the effect of the neuron output activity threshold at zero (Eq. 3). The activity of the LSM

neuron would also be expected to fall back towards this zero level of activity without any

external or internal input. This level hence corresponds to a threshold for spike initiation among

a population of similarly connected neurons that are typically represented by the one modeled

neuron. The output activity for the LSM neuron with dynamic leak (A_{Dyn}, Fig 1G) exhibits a

low pass filtering effect on the output activity, which is reflective of the effect of the RC

component integrated in the LSM neuron model with the dynamic leak.

Figure 2 illustrates the impact of various static and dynamic leaks. As indicated in Fig

2A, the static leak constant acts as a normalization factor for the total neuron activity, without

diminishing the underlying dynamics of that activity (S2 Fig). At very low values of the static

leak constant, the mean activity reached sufficiently high levels for the reversal potential to

start having a significant dampening effect on the activity dynamics (see uppermost trace in

Fig 2A), substantially reducing the coefficient of variation (CV in Fig 2B). Fig 2C, D illustrates

the additional impact of various values of the dynamic leak constant. Fig 2C and S3 Fig

demonstrate the filtering effect of the dynamic leak constant on the total neuron activity. A

high value of this dynamic leak constant substantially smoothens the activity dynamics, which

was reflected in the resulting low CV value (Fig 2D). The dynamic leak constant (τ_{Dyn}) was

set to 1/100 for the rest of this study, unless otherwise specified.

In Appendix 1, we show that the LSM neuron model can be derived from a simplified

H-H type conductance-based neuron model. In the H-H model, the leak is proportional to the

membrane voltage and the synaptic currents are scaled depending on the membrane voltage,

so that the voltage is limited to a fixed range. The differential equation describing this model

suffers from numerical instability, therefore we solve it with the implicit Euler method. The

model is simple enough so that an analytical solution can be obtained. Key H-H model features

that are captured by the LSM neuron: *i*) the response to a given input scales with the difference

between the current activity level (membrane potential *V*) and the reversal potentials of the

excitatory/inhibitory inputs (which have been normalized to +1 and -1, respectively); and *ii*)

the impact of a given input is scaled by the degree of the shunting caused by the total synaptic

activity the neuron receives at that time.

Izhikevich neuron model (IZ): For the Izhikevich neuron model [31], the membrane potential

(IZ_v) and the adaptation variable (IZ_u) were updated via the following nonlinear differential

equations discretized using Euler's method.

$$\dot{IZ}_v = IZ_A IZ_v^2 + IZ_B IZ_v + IZ_C - IZ_u + (IZ_{input} * IZ_k)$$

$$(4)$$

$$\dot{IZ}_u = IZ_a(IZ_b IZ_v - IZ_u)$$

183   When the membrane potential reached the spike depolarization threshold of 30 mV, one spike

184   was produced followed by a reset:

$$if\ IZ_v \geq 30mV, then \begin{cases} IZ_v \leftarrow IZ_c \\ IZ_u \leftarrow IZ_u + IZ_d \end{cases} \quad (5)$$

The IZ_A, IZ_B & IZ_C parameters and the spiking threshold were the standard ones of the

Izhikevich artificial neuron model, whereas the parameters IZ_a, IZ_b, IZ_c & IZ_d were selected

(Table 1, Fig 3E, F) to mimic a regular spiking behavior [31,32]. IZ_{input} was the input current

to the neuron model, that was weighted synaptic activity $(w * a)$ in this article and IZ_k is the

input gain factor.

Table 1. Izhikevich neuron model parameters used in the evaluation of this study. For the IZ

model responses presented in Fig 3E-F and S3 Fig.

IZ_A	IZ_B	IZ_C	IZ_a	IZ_b	IZ_c	IZ_d	IZ_k
0.04	5	140	0.02	0.2	-65	8	300

Further, to analyze the IZ model behavior across different spiking and bursting

behaviors, we have explored the parametric space (Table 2, Fig 3G) of

IZ_a, IZ_b, IZ_c, IZ_d & IZ_k (parameters in Eq. 4-5) within the boundaries identified in

Izhikevich, 2003 [31]. We investigated the IZ neuron model responses (Fig 3G) across 405

different parameter settings for each given input spike frequency. The parameter space was

defined by the possible combinations of parameters listed in Table 2.

Table 2. Izhikevich neuron model parametric space explored in the evaluation of this study

(for the IZ model presented in Fig 3G).

IZ_a	0.02	0.07	0.1	-	-
IZ_b	0.2	0.225	0.25	-	-
IZ_c	-65	-55	-50	-	-
IZ_d	2	4	8	-	-
IZ_k	100	200	300	400	500

Network connectivity

Our network was a two-layer fully connected neuronal network that comprised both

inhibitory neurons (IN) and excitatory neurons (EN) (Fig 4A). The network architecture is

defined based on the following two rules: (*a*) The sensory inputs are projected as excitatory

synapses to all neurons in layer 1 only; (*b*) All excitatory and inhibitory neurons were fully

reciprocally connected both within and between layers. Most of the analysis reported here

utilized a "5 × 4" network architecture (5 ENs and 5 INs in layer 1 and 4 ENs and 4 INs in

layer 2). In the analysis of Fig 8, where different network sizes were explored, we simply scaled

up the number of neurons in each layer using the same connectivity rules (Fig 8).

A two-layer, fully reciprocally connected neuronal network architecture with self-recurrent

connections (autapses) was also investigated. In this specific network architecture, in addition

to the network connectivity defined above, the excitatory neurons projected excitatory synaptic

connections onto themselves, and inhibitory neurons projected inhibitory synaptic connections

onto themselves (S7A Fig).

Sensory inputs

In this article, we investigated the individual neuron responses (Figs 2, 3 and S1-4 Figs)

and network dynamics (Figs 4-8 and S6-7 Figs, except Fig 7C, D) based on six sensory inputs.

These sensory inputs were pseudo-randomly generated (see below) and provided as excitatory

input to both excitatory and inhibitory neurons. We also tested our recurrent networks with

higher input sensor density (#sensors = 6, 15, 30 and 50, Fig 7C, D), the inputs of which were

also pseudo-randomly generated.

Pseudo-random inputs: For the sensory inputs to the LSM and the IZ neurons, we generated

223   pseudorandom spike trains for several different average frequencies (50, 100, 150 & 200 Hz,

224   Fig 3A and S4 Fig) with uniform normal distributions. We used an inbuilt MATLAB® function

225   *"randi"* to generate the spike time distributions in these spike trains. Furthermore, these spikes

226   were convoluted to resemble post-synaptic-potentials (time continuous activity) using the

227   following kernel equation [33],

$$a_i = \frac{\tau_{km}}{\tau_{kd} - \tau_{kr}} * \left[exp\left(\frac{-t - \tau_{kl} - t^*}{\tau_{kd}} \right) - exp\left(\frac{-t - \tau_{kl} - t^*}{\tau_{kr}} \right) \right] \qquad (6)$$

Where, t^* is the input spike time, τ_{kd} is the decay time (4 ms), τ_{kr} is the rise time (12.5

ms) and τ_{km} is the constant to calculate ration between rise time and decay time (21.3 ms), and

τ_{kl} is the latency time which is zero in this case. These values were chosen based on the

previous work [12]. The convoluted sensor signal was then provided as synaptic input to the

neuronal network.

In order to analyze the network dynamics, we provided 50 presentations of the same

pseudorandom spike trains (for each given average frequency). Each input presentation

differed by an addition of random noise of $\pm$ 10 ms to individual spike times (Fig 3C, D, E,

black lines) to the reference pseudorandom spike train (Fig 3A, for spike frequency of 50 Hz).

These presentations were concatenated without pause or reset between them, so the input

subdivided into 50 presentations was in effect one long presentation lasting for 50,000 ms.

To allow a comparison with the output of the LSM, we convoluted the output spike trains also

of the spiking neuron model (IZ). The process of convolution emulated a post synaptic response

that would have been generated in a receiving neuron, whereas the LSM output itself directly

corresponded to such a signal.

Synaptic weights

All excitatory and inhibitory synaptic weights in the network were randomly

distributed, including the excitatory sensory inputs to only the layer 1 neurons. The synaptic

weight distributions were either normal, lognormal or binary. The normal and the log-normal

distributions were generated for different mean weights (μ) (values between $0.1 - 0.5$) each

with a fixed coefficiency of variation (cv) of 20% (where sigma (σ) = (cv / 100) $* \mu$). For

binary distributions, we tested different probabilities of high weight synapses ($w = 1$)

(probability varied between 10% - 50%), whereas the remainder of the synapses were set to

zero weight (Fig 5A, B, C).

Statistical analysis

Cross-correlation: The correlation index measure was used to compute the similarity of the responses of the neuron models (Fig 3F, G and S4E Fig). The correlation between two signals was computed with an inbuilt MATLAB® function "*xcorr*" (with zero lag), which produces values from 0 (uncorrelated) to 1 (identical).

Frequency analysis: We performed a continuous wavelet transform (using an inbuilt MATLAB® function *'cwt'*) in order to define the frequency composition of the input signal over time. The wavelet transform was used to extract the power of each frequency band as a function of time for the continuous neuron activity signal. Here, we reported (Figs 4 – 8 and S5-7 Figs), for each frequency band, the maximum power of the signal within each input presentation time window (1 second).

In S5 Fig, the frequency analysis was performed on the sensory input signals (on the convoluted signal for each given average spiking frequency) across all the 6 sensory inputs for all 50 presentations (see Methods). The maximum power was computed for each sensory input and each presentation, and the average across all 6 input sensors was reported in this figure.

In Fig 4, the frequency analysis was performed on the activity of one excitatory and one inhibitory neuron in layer 1 (Fig 4B, C, F and G) across all frequencies and presentations. S6 Fig display the frequency analysis performed on the activity of all excitatory and inhibitory neurons in the network of Fig 4A. A similar frequency analysis was carried out in Figs 5-8 and S5 Fig, which show the average maximum power calculated across all neurons in all layers and across all 50 presentations.

Results

Comparison to Spiking Neuron Models

We first characterized the input-output relationship of the neuron model in isolation (Fig 3) for a standardized sensor input, consisting of randomized spike times in six sensor neurons that were convoluted to time-continuous input signals. These were synaptically integrated by a single modeled neuron (Fig 3A, B). The activity of the non-spiking LSM (linear summation neuron model) was compared with that of a spiking neuron model (Izhikevich, IZ), in terms of how well their output (Fig 3C-E) correlated with the input (Fig 3F). The IZ neuron model was chosen for this comparison, as it was created to mimic a rich neuronal response dynamics with computational efficiency [31]. The spikes generated by the IZ neuron model were convoluted (see Methods) to a time continuous signal (Fig 3E) in order for it to be comparable with the output of the LSM.

Both neuron models (LSM & IZ) were provided with the same pseudo-random sensory inputs (average firing frequency of 50 Hz in each of six sensors, see Methods) connected via six different synapses (Fig 3B). The IZ neuron model parameters for this particular comparison (Fig 3E, F) were chosen to mimic the regular spiking behavior (hypothesized to be a common neuron behavior in cortex [31,32]). The LSM neuron without dynamic leak reproduced on average a close representation of the source convolution signal for the input but the individual traces were considerably noisier without dynamic leak (Fig 3C) than with dynamic leak (Fig 3D). The main difference between the LSM and the IZ neuron model responses was that the IZ neuron model tended to create output dynamic behavior that was not present in the input signal (Fig 3B, E), a consequence of the binary nature of the spike output. A cross-correlation analysis between the neurons' responses (Fig 3F) showed that the IZ neuron model reflected the input signal less faithfully than the LSM. Note that the cross-correlation is slightly poorer for the

LSM with dynamic leak than without, which is due to that the some of the fine-timing details

of the high frequency components of the underlying convoluted signal is slightly filtered by

the dynamic leak.

We tested if this observation depended on the frequency of the spiking in the sensory

inputs. The LSM consistently showed a higher correlation with the input signal than the IZ

neuron model across a range of input spike frequencies (S3 Fig). Next we tested if the specific

parameters chosen for the IZ neuron model (Fig 3E, also indicated by an asterisk in Fig 3G)

were responsible for these results (Fig 3F). Therefore, we tested a range of parameter settings

(405 different parameter combinations), which are known to reproduce specific output

dynamics (bursting, for example) observed in a variety of neuron types *in vitro* [31]. The

correlation analysis showed that LSM was more consistent than the IZ model in maintaining

high correlation with the sensory inputs across the full range of sensory input spike frequencies

(Fig 3G). The exception was the highest sensory input frequencies, but that can be explained

by that the dynamics of the sensory input diminishes due to the density of the inputs (S3A-D

Fig), as previously described also for neurons *in vivo* [34]. This effect, which we will refer to

as the input density problem, is also evident in Fig 3G.

Network dynamics (with and without Neuronal Dynamic Leak)

We next investigated the activity dynamics of a standardized recurrent neuronal

network implemented using the LSM (Fig 4A). The sensory input was fed as excitatory input

to both the excitatory and inhibitory neurons of the first layer for 50 presentations, where the

sequential presentation differed by added Gaussian noise to the sensory signal (see Methods).

In the network with the neuron model without dynamic leak, there was initially a gradual

increase in the power across the higher frequency components of the activity in both excitatory

and inhibitory neurons (Fig 4B, C) (more extensively illustrated in S6 Fig, where the first few

presentations of sensory input evoked a lower power response). These high frequency

components were not present in the sensory input (S5A Fig) and were therefore generated by

the network, most likely as a consequence of the parallel excitatory and inhibitory connections,

which would be expected to lead to some degree of signal derivation [20]. Interestingly, in the

illustrated IN1 the high frequency components gradually built up (until presentation #10,

approximately) and then faded away (after presentation #20, approximately), despite that the

average intensity of the sensory input did not vary over time, which suggests a relatively rich

internal dynamics in this type of recurrent network, despite its limited size. In neurons of the

second layer, high frequency components typically faded away more slowly (S6 Fig). The

appearance of these high frequency components was sometimes associated with the appearance

of transients in the neuron activity (Fig 4D, E). In contrast, in the same network but with the

neuron model including the dynamic leak, the transients and the high-frequency components

of the neuron activity disappeared (Fig 4F -I). Hence, the low-pass filtering effect of the

dynamic leak 'rescued' the recurrent network from generating spurious high-frequency

components.

The recurrent connections of the network were likely strongly contributing to these

high-frequency components. An extreme case of recurrent connectivity is when a neuron makes

synapse on itself (autapse). It is not clear to what extent autapses exist in adult neuronal

circuitry, but they have been shown to be present in early development [35,36] and they are

widely used in the field of RNN/computational neuroscience [37]. To explore the impact of

autapses we used the exact same network architecture used in Fig 4 but added autapses to all

neurons (S7A Fig). In this scenario, the high-frequency components were strongly amplified

(S7B-E Fig). However, in the same network with the neuron model with the dynamic leak, the

transients and the high-frequency components of the neuron activity were again effectively

removed (S7F-I Fig). We did not explore networks with autapses any further.

We next compared the frequency power distributions of the neuronal activity in this

recurrent network across a range of different synaptic weight distributions (Fig 5). We studied

three different types of synaptic weight distributions (Gaussian, log-normal and binary

distributions). For each type of distribution, we tested five different mean synaptic weights (Fig

5A-C). Moreover, for each given synaptic weight distribution and mean weight, we generated

5 random weight distributions. The average signal of these 5 random weight distributions was

used to calculate each frequency power distribution illustrated (Fig 5D, E), where each line

represents the average activity across all the neurons of the network (Fig 5D, E). In the network

with the neuron model without dynamic leak (Fig 5D), the relative power of the high-frequency

components was amplified for synaptic weight distributions at mean synaptic weights of 0.3-

0.4 or above ($\mu \geq 0.4$ for Gaussian and $\mu \geq 0.3$ for log-normal distributions) and for p > 10%

for binary distribution, compared to the sensory input (S5 Fig). For other synaptic weight

distributions ($\mu = 0.1$ for Gaussian and log-normal distributions and for p = 10% for binary

distributions, for example), there was much lower overall activity in the network, which could

be the reason why the high frequency components were not induced in these networks. In the

network with the neuron model with the dynamic leak component, the transients and the high-

frequency components of the neuron activity disappeared for all settings (Fig 5E), though the

setting of the dynamic leak component used also appeared to over-dampen the sensory input

dynamics between 20-200 Hz.

To further explore if the high-frequency components observed were induced by the

recurrent network, we tested if we could affect the 'center of gravity' of the high-frequency

components by introducing different conduction delays in signal transmission between the

neurons (Fig 6). In the brain *in vivo*, these would correspond to the axonal conduction delays

and synaptic delays combined. The delays were randomized between all the neurons, and

several different mean delays were tested in different simulations. Interestingly, the peak

frequency of the high-frequency component observed without dynamic leak (Fig 6A) was

approximately inversely proportional to the mean conduction delay. These peaks were removed

by adding dynamic leak (Fig 6B).

The high frequency components also appeared for lower average sensor input spike

frequency (50 & 100 Hz, Fig 7A) and for lower number of sensory inputs per neuron (nSensors

= 6 & 15, Fig 7C). In contrast, for higher input spike frequencies (150 & 200 Hz) and higher

number of sensory inputs (nSensors = 30 & 50) the increased density of the inputs resulted in

a paradoxical decrease in the power of the neuron activity across all frequencies analyzed (i.e.

as shown in S1 Fig), most likely due to the large number of randomized inputs regressing

toward the constant mean frequency of each sensory signal. In each case, in the network with

the neuron model with the dynamic leak component, the high-frequency components of the

neuron activity disappeared for the sensor input configurations where it had been present (Fig

7B, D).

We also explored if the size of the network could be a factor for the appearance of the

high frequency components. We found that these high frequency components appeared for

different network sizes and that in those cases the network activity was 'rescued' when the

LSM was implemented with the dynamic leak (Fig 8). Depending on the specific synaptic

weight distribution, the high frequency components became unequally dominant for different

network sizes (Fig 8A, E) according to unclear relationships. The largest network as a rule had

the weakest overall dynamics, which could be due to the same input density problem discussed

above, where the density of synaptic input increased as the larger network has a higher number

of recurrent synaptic inputs per neuron, which caused the dynamics of the neuron activity to

go down. As there is a tendency for membrane time constants to grow with the size of the

neuron [30], we scaled the τ_{Dyn} with the network size (as the neurons of the larger networks

had a higher number of synapses) (Fig 8C-D, and Fig 8G-H, for two different weight

distributions). A moderate scaling of the τ_{Dyn} (with the square root of the number of synapses,

Fig 8C, G) actually increased the dynamics of some network sizes, while eliminating high

frequency components. In contrast, a linear scaling (Fig 8D, H) instead appeared to dampen

such dynamics and, unsurprisingly, low pass-filtered also signals well below 100 Hz for the

largest networks.

Discussion

In the present paper, we explored the properties of a non-spiking neuronal model, which

was derived from the differential conductance-based H-H model, in various recurrent neuronal

networks. We found that in these recurrent networks, many different factors would tend to

trigger network induction of high frequency signal components of a somewhat unpredictable

magnitude and distribution (i.e. Figs 5-8). These signal components were not present in the

input data (S5 Fig) and sometimes peaked to create overt spurious transients (Fig 4B, C). The

dynamic leak in our neuron model invariably 'rescued' the recurrent networks from their

tendency to self-generate these high-frequency signal components (Figs 4-8; S7 Fig).

Corresponding to the capacitive component and the ion channels of the membrane circuit,

dynamic leak is an inevitable feature of real neurons. Furthermore, this low-pass filter

component made the behavior of recurrent networks more predictable for networks of different

sizes.

We worked under the scenario that neuronal networks in the brain are recurrent and that

excitatory and inhibitory connections are both pervasive, without any a priori assumed

structure. Our network architecture contained the circuitry elements of previously reported

'classical' network connectivity patterns (feedback and feedforward inhibition, for example).

Feed-forward and feedback inhibition running in parallel with excitatory connections was

likely the main network feature that caused the signal derivation effects/the high frequency

components in the networks without the dynamic leak. The inclusion of autapses in the

recurrent network strongly amplified these high frequency components (S7 Fig), presumably

primarily through self-amplification of excitatory neurons. But note that in a recurrent network,

any local circuity feature will at the global level automatically result in other functional

network features as well. Hence, in contrast to a non-recurrent, feed forward neuronal network,

in a recurrent network these circuitry features will hence become less clear-cut from a

functional point of view, which could cause additional dynamic network effects that for

example could explain our observations of gradual build-up of high frequency power

components (Fig 4 and S5 Fig) while there was steady sensory input level to keep the network

activity up. However, understanding such network dynamics at a deeper level was outside the

scope of this paper, but would need to be addressed if such networks are to be used in a

functional setting.

In our recurrent networks, apparently spurious high frequency components could be

induced for different types of synaptic weight distributions, delays between neurons, sensory

input densities and network sizes. It was hard to predict under what exact conditions such high

frequency components would become more or less dominant (i.e. Fig 8), but in each case the

dynamic leak effectively cancelled them out. From the point of view of the functionality of a

processing recurrent network, the fact that the frequency distribution of any given network did

not match that of the sensory input is not automatically to be considered a disadvantage because

the goal of a processing network would not be to perfectly replicate the sensory input. However,

the fact that these high frequency components sometimes took the shape of clear-cut transients

with no obvious counterpart in the sensor signal suggests that, at least in part, they should be

considered spurious, i.e. noise injected into the signal due to the dynamics of the specific

network.

In some cases, the activity of the network became highly suppressed relative to the

sensory input (i.e. for low mean weights in Fig 5 and for the largest network in Fig 8). This

effect can be ascribed to the input density problem, i.e. when too many unrelated but

continuously active synaptic inputs converge on the same neuron, their signal dynamics would

tend to cancel out, leaving the neuron with very little signal dynamics [34]. As these signals,

due to the network structure, are paralleled by inhibitory connections, when the signal

dynamics is lost, inhibition and excitation cancel each other out and the activity dynamics is
lost in the network as a whole.

How would spiking neuron networks fare with respect to rescuing a recurrent network
from spurious high frequency components? The phasic nature of discrete spike output would
be expected to worsen the problem, whereas refractoriness would tend to dampen it.
Refractoriness could certainly rescue the system from the extreme transients observed in
networks that included autapses. Refractoriness, however, would not rescue the system from
high frequency components generated through longer range recurrent excitatory loops.

Recurrent neuronal networks with balanced excitatory and inhibitory synaptic
connections have been extensively studied previously [22,23,38,39], using spiking neuron
models (employing integrate-and-fire or related mechanisms for the spike generation). In these
studies, the recurrent connections were sparsely distributed with an overall connection
probability of 1-2%, and a ratio of 4:1 excitatory to inhibitory interneurons. These studies point
out that factors such as high connection probability and unbalanced excitation-inhibition tend
to produce network instability [39] and in some cases failure in signal propagation across the
layers of those neuronal networks [22]. From the stability we observed across a wide range of
recurrent network configurations, always at 100% connection probability (though weighted),
it would seem that the LSM with dynamic leak would be beneficial for ensuring stable recurrent
neuronal network behavior across a range of network sizes and density of connectivity.

The present findings suggest that the biological feature of neuronal dynamic leak, which causes
the polarization (i.e. the activity) of the neuron to settle towards resting potential with a time
constant, is an important functional feature. It allows brain networks to fully utilize recurrent
neuronal network architectures with variable numbers of participating neurons without risking
self-generated noise embodied as high frequency components and spurious transients.

Acknowledgments: Funding: This work was supported by the EU Grant FET 829186 ph-

coding (Predictive Haptic COding Devices In Next Generation interfaces), the Swedish

Research Council (project grant no. K2014-63X-14780-12-3).

References

1.   Binzegger T, Douglas RJ, Martin KAC. A quantitative map of the circuit of cat

primary visual cortex. J Neurosci. 2004. doi:10.1523/JNEUROSCI.1400-04.2004

2.   Kar K, DiCarlo JJ. Fast recurrent processing via ventral prefrontal cortex is needed by

the primate ventral stream for robust core visual object recognition. bioRxiv. 2020.

doi:10.1101/2020.05.10.086959

3.   Koestinger G, Martin KAC, Rusch ES. Translaminar circuits formed by the pyramidal

cells in the superficial layers of cat visual cortex. Brain Struct Funct. 2018.

doi:10.1007/s00429-017-1588-7

4.   Song S, Sjöström PJ, Reigl M, Nelson S, Chklovskii DB. Highly nonrandom features

of synaptic connectivity in local cortical circuits. PLoS Biology. 2005.

doi:10.1371/journal.pbio.0030068

5.   Hooks BM, Mao T, Gutnisky DA, Yamawaki N, Svoboda K, Shepherd GMG.

Organization of cortical and thalamic input to pyramidal neurons in mouse motor

cortex. J Neurosci. 2013. doi:10.1523/JNEUROSCI.4338-12.2013

6.   Steriade M. Synchronized activities of coupled oscillators in the cerebral cortex and

thalamus at different levels of vigilance. Cereb Cortex. 1997.

doi:10.1093/cercor/7.6.583

7.   Allen GI, Tsukahara N. Cerebrocerebellar communication systems. Physiological

Reviews. 1974. doi:10.1152/physrev.1974.54.4.957

8.   Jörntell H. Cerebellar physiology: links between microcircuitry properties and

sensorimotor functions. Journal of Physiology. 2017. doi:10.1113/JP272769

9.   Obermayer J, Heistek TS, Kerkhofs A, Goriounova NA, Kroon T, Baayen JC, et al.

Lateral inhibition by Martinotti interneurons is facilitated by cholinergic inputs in

human and mouse neocortex. Nat Commun. 2018. doi:10.1038/s41467-018-06628-w

10.   Douglas RJ, Martin KAC. Inhibition in cortical circuits. Current Biology. 2009.

doi:10.1016/j.cub.2009.03.003

11.   Zhu JJ, Lo FS. Recurrent inhibitory circuitry in the deep layers of the rabbit superior

colliculus. J Physiol. 2000. doi:10.1111/j.1469-7793.2000.00731.x

12.   Rongala UB, Spanne A, Mazzoni A, Bengtsson F, Oddo CM, Jörntell H. Intracellular

dynamics in cuneate nucleus neurons support self-stabilizing learning of generalizable

tactile representations. Front Cell Neurosci. 2018. doi:10.3389/fncel.2018.00210

13.   Swadlow HA. Fast-spike interneurons and feedforward inhibition in awake sensory

neocortex. Cerebral Cortex. 2003. doi:10.1093/cercor/13.1.25

14.   Isaacson JS, Scanziani M. How inhibition shapes cortical activity. Neuron. 2011.

doi:10.1016/j.neuron.2011.09.027

15.   Jörntell H, Ekerot CF. Receptive Field Plasticity Profoundly Alters the Cutaneous

Parallel Fiber Synaptic Input to Cerebellar Interneurons In Vivo. J Neurosci. 2003.

doi:10.1523/jneurosci.23-29-09620.2003

16.   Pi HJ, Hangya B, Kvitsiani D, Sanders JI, Huang ZJ, Kepecs A. Cortical interneurons

that specialize in disinhibitory control. Nature. 2013. doi:10.1038/nature12676

17.   Sultan KT, Shi SH. Generation of diverse cortical inhibitory interneurons. Wiley

Interdisciplinary Reviews: Developmental Biology. 2018. doi:10.1002/wdev.306

18.   Okun M, Lampl I. Instantaneous correlation of excitation and inhibition during

ongoing and sensory-evoked activities. Nat Neurosci. 2008. doi:10.1038/nn.2105

19.   Anderson JS, Carandini M, Ferster D. Orientation tuning of input conductance,

531   excitation, and inhibition in cat primary visual cortex. J Neurophysiol. 2000.

532   doi:10.1152/jn.2000.84.2.909

533   20.   Wehr M, Zador AM. Balanced inhibition underlies tuning and sharpens spike timing in

534   auditory cortex. Nature. 2003. doi:10.1038/nature02116

535   21.   Sutskever I, Vinyals O, Le Q V. Sequence to sequence learning with neural networks.

536   Advances in Neural Information Processing Systems. 2014.

537   22.   Vogels TP, Abbott LF. Signal propagation and logic gating in networks of integrate-

538   and-fire neurons. J Neurosci. 2005. doi:10.1523/JNEUROSCI.3508-05.2005

539   23.   Brunel N. Dynamics of sparsely connected networks of excitatory and inhibitory

540   spiking neurons. J Comput Neurosci. 2000. doi:10.1023/A:1008925309027

541   24.   Liou JY, Smith EH, Bateman LM, Bruce SL, McKhann GM, Goodman RR, et al. A

542   model for focal seizure onset, propagation, evolution, and progression. Elife. 2020.

543   doi:10.7554/eLife.50927

544   25.   Chakravarthy N, Tsakalis K, Sabesan S, Iasemidis L. Homeostasis of brain dynamics

545   in epilepsy: A feedback control systems perspective of Seizures. Ann Biomed Eng.

546   2009. doi:10.1007/s10439-008-9625-6

547   26.   Naundorf B, Wolf F, Volgushev M. Unique features of action potential initiation in

548   cortical neurons. Nature. 2006. doi:10.1038/nature04610

549   27.   Spanne A, Geborek P, Bengtsson F, Jörntell H. Spike generation estimated from

550   stationary spike trains in a variety of neurons In vivo. Front Cell Neurosci. 2014.

551   doi:10.3389/fncel.2014.00199

552   28.   Saarinen A, Linne ML, Yli-Harja O. Stochastic differential equation model for

553   cerebellar granule cell excitability. PLoS Comput Biol. 2008.

554   doi:10.1371/journal.pcbi.1000004

555 29. Spanne A, Jörntell H. Questioning the role of sparse coding in the brain. Trends in

556   Neurosciences. 2015. doi:10.1016/j.tins.2015.05.005

557 30. Zhang ZW. Maturation of Layer V Pyramidal Neurons in the Rat Prefrontal Cortex:

558   Intrinsic Properties and Synaptic Function. J Neurophysiol. 2004.

559   doi:10.1152/jn.00855.2003

560 31. Izhikevich EM. Simple model of spiking neurons. IEEE Trans Neural Networks.

561   2003;14: 1569–1572. doi:10.1109/TNN.2003.820440

562 32. Izhikevich EM. Which model to use for cortical spiking neurons? IEEE Trans Neural

563   Networks. 2004;15: 1063–1070. doi:10.1109/TNN.2004.832719

564 33. Mazzoni A, Panzeri S, Logothetis NK, Brunel N. Encoding of naturalistic stimuli by

565   local field potential spectra in networks of excitatory and inhibitory neurons. PLoS

566   Comput Biol. 2008;4. doi:10.1371/journal.pcbi.1000239

567 34. Bengtsson F, Ekerot CF, Jörntell H. In vivo analysis of inhibitory synaptic inputs and

568   rebounds in deep cerebellar nuclear neurons. PLoS One. 2011.

569   doi:10.1371/journal.pone.0018822

570 35. Lübke J, Markram H, Frotscher M, Sakmann B. Frequency and dendritic distribution

571   of autapses established by layer 5 pyramidal neurons in the developing rat neocortex:

572   Comparison with synaptic innervation of adjacent neurons of the same class. J

573   Neurosci. 1996. doi:10.1523/jneurosci.16-10-03209.1996

574 36. Tamás G, Buhl EH, Somogyi P. Massive autaptic self-innervation of GABAergic

575   neurons in cat visual cortex. J Neurosci. 1997. doi:10.1523/jneurosci.17-16-

576   06352.1997

37.   Graves A. Supervised Sequence Labelling. 2012. doi:10.1007/978-3-642-24797-2_2

38.   Vogels TP, Sprekeler H, Zenke F, Clopath C, Gerstner W. Inhibitory plasticity

balances excitation and inhibition in sensory pathways and memory networks. Science

(80-). 2011. doi:10.1126/science.1211095

39.   Rubin R, Abbott LF, Sompolinsky H. Balanced excitation and inhibition are required

for high-capacity, noise-robust neuronal selectivity. Proc Natl Acad Sci U S A. 2017.

doi:10.1073/pnas.1705841114

40.   Hodgkin a L, Huxley a F. A quantitative description of membrane current and its

applicaiton to conduction and excitation in nerve. J Physiol. 1952. pp. 500–544.

doi:10.1016/S0092-8240(05)80004-7

41.   Tougaard J. Signal detection theory, detectability and stochastic resonance effects.

Biol Cybern. 2002. doi:10.1007/s00422-002-0327-0

42.   Lindner B. Low-pass filtering of information in the leaky integrate-and-fire neuron

driven by white noise. Understanding Complex Systems. 2014. doi:10.1007/978-3-

319-02925-2_22

APPENDIX 1

Neuron model derivation from H-H model

We first describe the rationale for our Linear Summation neuron model (LSM). In brief, the LSM aims to provide a simple and computationally efficient neuron model, while capturing important characteristics of H-H conductance models [12,40]. The membrane potential in the LSM model is normalized between +1 and -1 with a resting potential of zero. The output of an LSM neuron is a continuous, non-spiking signal that reflects the portion of the membrane potential that exceeds some threshold, which we assumed to be the zero resting potential. This would be suitable to represent one neuron or a population of similarly connected neurons that is biased by background activity to be at or near spontaneous activity (such as is hypothesized for stochastic resonance to prevent dead bands)[41]. This continuous output signal is intended to reflect the mean spike rate that a population of similarly connected neurons would transmit to other centers in the nervous system.

In H-H models the various ion channels associated with ionic pumps and leaks define a resting membrane potential where there are no net currents. Any change in membrane potential away from this resting potential will settle back to the resting potential according to the combined conductance of all of these ion channels, which is called the static leak. Synaptic activation leads to opening of specific ion channels, which in the H-H models as a change of synaptic conductance. The ion(s) that are made permeable by the synapse have a reversal potential that is different from the resting membrane potential. When the ion channels of a particular synapse are open, the membrane potential will be driven towards that reversal potential, with a strength that depends on the strength of the synaptic conductance relative to the static leak conductance.

The synaptic currents charge the neuron, which is modeled as a single capacitor

(assuming that the electrotonic distances between different parts of the neuron are negligible).

Various synaptic signals are thus integrated and converted into a dynamically changing

membrane potential. The static leak is in parallel with this capacitor, thereby defining a time-

constant τ for these dynamic changes. The effect is that of low-pass filtering of the integrated

synaptic currents [42] to produce the membrane potential that defines the output state of the

neuron. In an H-H model, the output state is created by converting the membrane voltage into

patterns of spike output, with the help of a threshold for spike generation. Spike generation is

omitted in the LSM model and the output of the neuron is instead the part of the membrane

potential that exceeds some threshold (herein equal to the resting membrane potential).

First, we describe a conductance-based model similar to previously presented models

[12,40] and then show how a model similar to the LSM model can be derived. In this category

of ion channel conductance-based models, the dynamics of one type of ion channel is lumped

together into one single conductance. Compared to other conductance-based models, no spike

generation is modeled and the neurons resting potential is set to zero. The neuron is modeled

as a capacitor with capacitance (C) and is charged by excitatory ($I_{syn,exc}$) and inhibitory

synaptic currents ($I_{syn,inh}$) and discharged by a leak current (I_{leak}). Therefore, the neurons

membrane potential (V) measured across the capacitor follows the following equation.

$$C\frac{dV}{dt} = I_{leak} + I_{syn,exc} + I_{syn,inh} \qquad (A1)$$

635   The leak current is set proportional to the membrane potential by constant conductance

636   g_L according to Ohm's law:

$$I_{leak} = -g_L V \qquad (A2)$$

If the synaptic currents are zero, the neuron's membrane potential will decay to zero.

Therefore, this model neuron's resting membrane potential is zero. At each excitatory synapse

i the firing rate of the presynaptic neuron (v_i^+) produces a current. The synapse has a baseline

conductance (w_i^+), called synaptic weight. This conductance is scaled by the presynaptic

neuron's firing rate. The direction and magnitude of the current is determined by the difference

between the constant reversal potential (E_{exc}) and the neuron's membrane potential. For an

excitatory synapse, the current would reverse if the membrane potential rose above the positive

reversal voltage, so synaptic activity can never produce a membrane potential about the

reversal potential. Therefore if the neuron has already reached this voltage, the neuron's voltage

cannot increase further. The current contributed by an individual synapse can be modeled as

$$I_{syn,exc_i} = -(V - E_{exc})w_i^+ v_i^+ \qquad (A3)$$

647   The same model is applied for the current generated by an inhibitory synapse i, with

648   reversal potential (E_{inh}), synaptic weight (w_i^-) and presynaptic firing rate (v_i^-). The reversal

649   potential of an inhibitory synapse is set so that the neurons potential cannot decrease below this

650   potential.

$$I_{syn,inh_i} = -(V - E_{inh})w_i^- v_i^- \qquad (A4)$$

651   Summing all synaptic currents and plugging in the current equations into the

652   membrane potential equation we obtain

$$C\frac{dV}{dt} = -g_L V - \sum_i (V - E_{exc})w_i^+ v_i^+ + \sum_i (V - E_{inh})w_i^- v_i^- \qquad (A5)$$

where the first sum is over all excitatory synapses and the second sum over all inhibitory

synapses. In order, to show the relationship of this equation to the LSM model, we set the leak

conductance to one and replace leak conductance and membrane capacitance by a time constant

τ. The reversal potentials are set to +1 and -1 for the excitatory and the inhibitory synapses,

respectively. Hence the range of possible membrane potential is between +1 and -1, assuming

that the initial voltage is also in that range.

The resulting differential equation is

$$\tau \frac{dV}{dt} = -V + (1-V)\sum w_j^+ v_j^+ + (1+V)\sum w_k^- v_k^- \qquad \text{(A6)}$$

660   This equation can be solved by applying the implicit Euler method. Let V_t be the

661   membrane voltage in timestep t and h the stepsize. The following equation must be solved

662   for V_{t+1}

$$V_{t+1} = V_t + h\frac{1}{\tau}\left(-V_{t+1} + (1-V_{t+1})\sum w_j^+ v_j^+ + (1+V_{t+1})\sum w_k^- v_k^-\right) \qquad \text{(A7)}$$

663   In this case an analytic solution is possible:

$$V_{t+1} = \frac{V_t + \dfrac{h}{\tau}\sum w_i v_i}{1 + \dfrac{h}{\tau} + \dfrac{h}{\tau}\sum |w_i| v_i} \qquad \text{(A8)}$$

where both sums are over all synapses.

The parameters of this model are also listed in S1 Table. This new system has

components not commonly found in neuron models. The reason is that usually the differential

equation describes an instantaneous effect of the inputs and the state of the neuron. In this

system the effect of the input on how the input is processed by the neuron in a future time step

is already considered.

From the above derivation (Eq. A8) we could observe that the excitatory ($I_{syn,exc}$) and

inhibitory ($I_{syn,inh}$) synaptic currents from a conductance based neuron model (Eq. A1), can

be reduced to a total synaptic weight summation $\left(\frac{\sum wV}{1+\sum |w|V}\right)$, and that the leak current (I_{leak})

(Eq. A1), which is a dynamic leak because it occurs across capacitor, can be reduced to h/τ (a

dynamic leak constant, Eq. A8; if this constant is larger than zero and smaller than one, it can

be disregarded in this expression). Based on this neuron model derivation, we propose the

simplified linear summation neuron model (LSM, A10) to capture the essential dynamics of

the original H-H conductance-based model (S1 Fig). The LSM is given by two equations: LSM

without dynamic leak (Eq. A9) and LSM with dynamic leak (Eq. A10).

$$A_{No_{Dyn}} = \frac{\sum(w_i a_i)}{1 + \sum|w_i a_i|} \tag{A9}$$

$$\frac{\tau_{Dyn} * dA_{Dyn}}{dt} = -A_{Dyn}(t) + A_{No_{Dyn}}(t) \tag{A10}$$

Fig 1. LSM responses to emulated synaptic inputs. (**A**) The activation times of three

different excitatory synaptic inputs are indicated as spike trains. (**B**) The activation times of

one inhibitory synaptic input. (**C-D**) The excitatory and inhibitory sensory input spike trains

were convoluted using a kernel function (see Methods) to create input that resembles post-

synaptic potentials. Note that the input to the LSM neuron can exceed 1 a.u., while the output

of the LSM neuron cannot. Calibration applies to C –E (traces in the shaded region). (**E**) The

input from summation of the excitatory and inhibitory inputs. (**F**) LSM (without dynamic

leak, $k_{static} = 1$) output activity for the given PSP inputs. Calibration applies to F-G. (**G**) LSM

(with dynamic leak, $k_{static} = 1, \tau_{dyn} = 1/100 \, s$) output activity for the given PSP inputs.

Fig 2. Impact of static leak (k_{static}) and dynamic leak constant (τ_{dyn}) in LSM. (A) Impact

of the value of k_{static} in the LSM (for $\tau_{dyn} = 1/100$) for a given pseudo-random sensory input

at 50 Hz for each of six sensors (see Fig 3). **(B)** The perseverance of dynamics in the neuron

activity (A) for varying k_{static} value as assessed by the coefficient of variation (CV = $\sigma(A)/\text{Á}$)

. A higher value of CV indicates a higher activity variance relative to the mean activity. **(C)**

Impact of the value of τ_{dyn} in the LSM (for $k_{static} = 1$) for the same pseudo-random sensory

input as in **A**. **(D)** The CV as a function of the value of the dynamic leak (τ_{dyn}) in the LSM.

The arrow indicates the value of τ_{dyn} used in rest of this paper unless otherwise specified.

Fig 3. Comparing the properties of different neuron models in isolation. (A) Pseudo-random input spike trains (six spike trains corresponding to the six sensory inputs, with an average spike frequency of 50 Hz in each sensor) **(B)** The sensory input spike trains were convoluted using a kernel function (see Methods). The convoluted input responses were fed as weighted (randomly generated, mu = 0.4) EPSP inputs to the neuron model. **(C)** Output responses of the LSM without dynamic leak. The red line is the mean across 50 presentations

(each presentation made different by adding Gaussian noise, black lines). In this and all panels

below, tests were made for the neuron in isolation, without network connections. (**D**) Similar

display as in **C**, but for LSM with dynamic leak. (**E**) Similar display as in **C**, but for output

responses of Izhikevich neuron model. The spike output of the Izhikevich neuron model were

convoluted using a kernel function (same kernel parameters setting as in **B**). (**F**) Cross-

correlations between the sensory input and the output responses of neuron models (illustrated

in **C-E**). (**G**) Cross-correlation between different sensory input frequencies and neuron model

outputs across a range of IZ model settings, compared to the LSM with dynamic leak. Thin

blue lines indicate the cross-correlation with the sensory input for the IZ neuron model

responses for each of the 405 IZ model parameter settings (IZ_a, IZ_b, IZ_c, IZ_d and IZ_k see

methods) tested. Thick blue line indicates the mean of those cross-correlations. The red line

indicates the cross-correlation between the sensory inputs and the LSM outputs. Asterisk

indicates the cross-correlation measure for the parameters chosen in Fig 3F.

Fig 4. Activity dynamics in a sample recurrent network. (**A**) Principles of the connectivity structure in the recurrent network studied. Note that the default network, and the one used in panels **B-I** of this figure, contained excitatory neurons (5 in the input layer, 4 in the output layer) and inhibitory neurons (same numbers) with the same connectivity whereas only the neurons in layer 1 also received sensory inputs (the same 6 sensory inputs to each neuron) with all synapses having randomly generated gaussian weights (mu = 0.4). (**B**) Frequency plot of

730   the activity in an excitatory neuron. (**C**) Similar plot for an inhibitory neuron. (**D**) Raw data

731   plots for sample signals in the excitatory neuron generated at the indicated presentation #. (**E**)

732   Similar plot for the inhibitory neuron. (**F**)-(**I**) Similar plots as in (**B**)-(**E**) but when all the

733   neurons were modelled to include the neuronal dynamic leak.

Fig 5. High frequency components and the effect of dynamic leak across different synaptic weight distributions. (**A-C**) The three types of synaptic weight distributions that were explored (Gaussian, Log-Normal and Binary) and the average weight distributions for each mean weight value (five weight distributions were generated for each mean weight). (**D**) The frequency power distributions across all the above synaptic weight distributions. Color keys for the different average synaptic weights are in A-C. (**E**) Similar display as in C, for the same networks but with the neuron model with dynamic leak. Dashed orange traces in D, E show the corresponding frequency power distribution for the sensory inputs at 50 Hz, averaged across the six sensory inputs, for comparison.

Fig 6. Impact of conduction delays on the frequency distribution. (**A**) Frequency

distributions for the same network (network settings as in Fig 4) with different average

conduction delays between neurons. (**B**) Data for the same networks and delays when the

neuron model included dynamic leak.

Fig 7. Network activity dynamics increased when sensor input density decreased. (**A**) The

high frequency components became more prominent with lower average spike frequencies in

the sensor input. (**B**) Neuronal dynamic leak resulted in disappearance of the high-frequency

components across all input spike frequencies. (**C**) The high frequency components also

became more prominent with lower number of sensory inputs, while a very high number of

sensor inputs substantially reduced overall neuron activity dynamics. (**D**) Introduction of

neuronal dynamic leak resulted in disappearance of the high-frequency components

irrespective of the number of sensory inputs. The network settings for this analysis were similar

to Fig 4, except for sensory input.

Fig 8. Activity frequency distributions altered with the scale of the networks. (**A, E**) For

networks with Gaussian synaptic weight distribution of mean weight mu = 0.3 and 0.4,

respectively, the high frequency components could appear without dynamic leak, regardless

of network size. (**B, F**) Introduction of the neuronal dynamic leak ($\tau_{dyn} = 1/100$) 'rescued'

the networks from these high-frequency components. (**C, G**) The dynamic leak constant was

adapted based on the square root of number of synapses (i). (**D, H**) The dynamic leak

constant was adapted based on the total number of synapses (i). Dashed orange traces in all

plots show the corresponding frequency power distribution for the sensory inputs at 50 Hz,

averaged across the six sensory inputs, for comparison.

Supporting Information

775
776
777

S1 Fig. Signal similarity between the LSM **and H-H model.** A comparison between the

output responses for LSM (green line is the mean across 50 presentations) and the H-H (derived

using backward Euler method, blue line is the mean across 50 presentations), for a given

pseudo-random sensory input at 50 Hz for each of six sensors (see Fig 3). The responses of the

LSM output were offset by 0.1 activity (a.u.) in order to visualize the coherence between the

responses of both neuron models. The cross correlation (with zero lag) was 0.99.

S2 Fig. Impact of the value of k_{static} on the internal activity of the LSM for a given sensory

input.

S3 Fig. Impact of the value of τ_{dyn} on the internal activity of the LSM for a given sensory

input.

S4 Fig. Comparison of the non-spiking and the spiking neuron model outputs for different

sensory input frequencies. (**A-D**) Neuron outputs in response to different sensory input

frequencies. (**E**) Cross-correlation between sensory inputs and the neuron model outputs.

S5 Fig. Frequency analysis of the sensory inputs. (**A**) Time-continuous frequency power

analysis for each of the six sensory inputs (spike frequency = 50Hz) across the 50 presentations

used in the analysis of the network activity. (**B**) Frequency power analysis (using continuous

wavelet transform, see Methods), of sensory inputs. The plots show the average power of the

activity across all the six sensors, for each of the four mean sensor firing frequencies, across

all 50 presentations used in the analysis of the network activity.

S6 Fig. Frequency analysis plots of the activity in all excitatory neurons $(EN_1 - EN_9)$ and

inhibitory neurons $(IN_1 - IN_9)$ for the network shown in Fig 4A.

S7 Fig. Activity in recurrent networks with autapses. (**A**) Principles of the connectivity

structure in the recurrent network studied. The network presented here is a fully connected

network as in Fig 4, with the addition of self-recurrent excitatory and inhibitory synapses (in

excitatory and inhibitory neurons, respectively). (**B**) Frequency plot of the activity in an

excitatory neuron. (**C**) Similar plot for an inhibitory neuron. (**D**) Raw data plots for sample

signals in the excitatory neuron generated at the indicated presentation #. (**E**) Similar plot for

the inhibitory neuron. **(F)**-**(I)** Similar plots as in **(B)**-**(E)** but when all the neurons were

modelled with the dynamic leak.

Parameter	Symbol	Units
Membrane potential	V	[V]
Membrane capacitance	C	[F]
Membrane time constant	τ	[s]
Time step	h	[s]
Neuron output	v	[V]
Excitatory weights	w_i	[1]
Inhibitory weights	w_j	[1]
Presynaptic excitatory neuron activity	V_i^+	[V]
Presynaptic inhibitory neuron activity	V_j^-	[V]
Excitatory currents	I_{exc}	[A]
Inhibitory currents	I_{inh}	[A]
Leak currents	I_{leak}	[A]

821   **S1 Table.** H-H Model variable definitions (for the H-H neuron model derivation, presented in

822   APPENDIX 1).