Electrical match between initial segment and somatodendritic compartment for action potential backpropagation in retinal ganglion cells

Sarah Goethals[1]*, Martijn C. Sierksma[1,2]*, Xavier Nicol[1], Annabelle Réaux-Le Goazigo[1] and Romain Brette[1]

1. Sorbonne Université, INSERM, CNRS, Institut de la Vision, 17 rue Moreau, F-75012 Paris, France

2. Department of Neuroscience, Erasmus MC, Erasmus University Medical Center Rotterdam, 3000 CA, Rotterdam, The Netherlands

* These two authors contributed equally.

Corresponding author: Romain Brette, romain.brette@inserm.fr

Abstract

The action potential of most vertebrate neurons initiates in the axon initial segment (AIS), and is then transmitted to the soma where it is regenerated by somatodendritic sodium channels. For successful transmission, the AIS must produce a strong axial current, so as to depolarize the soma to the threshold for somatic regeneration. Theoretically, this axial current depends on AIS geometry and Na^+ conductance density. We measured the axial current of mouse RGCs using whole-cell recordings with post-hoc AIS labeling. We found that this current is large, implying high Na^+ conductance density, and carries a charge that co-varies with capacitance so as to depolarize the soma by $\sim$30 mV. Additionally, we observed that the axial current attenuates strongly with depolarization, consistent with sodium channel inactivation, but temporally broadens so as to preserve the transmitted charge. Thus, the AIS appears to be organized so as to reliably backpropagate the axonal action potential.

Introduction

In most vertebrate neurons, action potentials (APs) initiate in the axon initial segment (AIS), a highly organized structure near the soma (Bender & Trussell, 2012), then propagate forward to the axon terminals and backward to the soma and dendrites (Debanne *et al.*, 2011). This backward transmission is functionally important for synaptic plasticity, which requires a precisely timed signal of firing activity at the synapse (Caporale & Dan, 2008). It is also important for long-term intrinsic plasticity since the soma holds the genetic material (Daoudal & Debanne, 2003), and presumably also for structural plasticity of the AIS, which depends on somatic voltage-gated calcium channels (Evans *et al.*, 2013).

At spike initiation, the soma receives an axial current from the AIS, which depolarizes the membrane. When the somatic membrane potential is depolarized about 30 mV above firing threshold, the AP is regenerated by somatic sodium channels (Kole & Stuart, 2008). Hamada et al. (2016) found indirect evidence that the axial current matches the capacitance of the somatodendritic compartment, as they observed that larger cortical pyramidal cells tend to have a more proximal AIS, which should theoretically produce a stronger current. However, the axial current was not directly measured.

Such a measurement could also allow estimating the conductance density of AIS sodium channels, in particular using resistive coupling theory (Brette, 2013; Kole & Brette, 2018). The fact that the AIS, a small structure, must produce a current able to charge a much larger piece of membrane (soma and proximal dendrites), suggests that conductance density is high, in agreement with immunochemical observations (Lorincz & Nusser, 2010). However, this has remained a somewhat contentious issue (Fleidervish *et al.*, 2010) because direct patch-clamp measurements in the intact AIS indicate low conductance density (Colbert & Pan, 2002), which could be an artifact due to the anchoring of channels to the cytoskeleton (Kole *et al.*, 2008).

Finally, it is known that sodium channels can inactivate substantially below threshold, resulting in spike threshold adaptation (Azouz & Gray, 2000; Platkiewicz & Brette, 2011; Fontaine *et al.*, 2014). This suggests that the axial current at spike initiation may also vary substantially. If this is the case, then how can spikes be reliably transmitted to the soma?

To address these questions, we measured the axial current and spontaneous action potentials in ganglion cells of isolated mouse retina followed by ankyrin-G-antibody labeling to measure AIS geometry. We examined the axial current at spike initiation, just below threshold, and with threshold adaptation, and compared these results to theoretical predictions.

Results

The axial current at spike initiation

Action potentials of retinal ganglion cells

Early work on vertebrate motoneurons showed that APs recorded in the soma typically consist of two components (Fatt, 1957; Coombs *et al.*, 1957): an abrupt depolarization due to the axial current originating from the axon initial segment, followed by a regeneration of the AP at a higher potential, by the opening of somatic sodium channels. These two components are clearly distinguished in recordings of spontaneous APs of retinal ganglion cells (RGC). Figure 1A illustrates a typical AP, rising abruptly from threshold. The voltage derivative dV/dt shows two distinct components, which appear most clearly when plotted against the membrane potential V (Fig. 1B). We define the regeneration

67   threshold as the potential when the acceleration d^2V/dt^2 is maximal. In n = 10 cells (see Methods for
68   the inclusion criteria), we observed that the spike threshold of spontaneous APs was -49 ± 3.8 mV (s.d.)
69   while the regeneration threshold is -16 ± 4.6 mV (s.d.), about 33 ± 5 mV (s.d.) higher (Fig. 1C). This is
70   similar to previous measurements in layer 5 cortical pyramidal cells (Kole & Stuart, 2008).

Figure 1. *Spontaneous APs of retinal ganglion cells consist of two components. A, Spontaneous AP of a RGC,*
highlighting spike onset (blue), point of maximum dV/dt of the first component (yellow), somatic regeneration
threshold (red), point of maximum dV/dt of the second component (green). B, Phase plot showing dV/dt vs. V.
The double arrow shows the difference ΔV between spike onset and regeneration threshold. C, Statistics of ΔV.

Transmission of the axial current to the soma

We measured the axial current with whole-cell voltage clamp by stepping the command potential from
$V_0 = -60$ mV to a variable potential V. Voltage steps above a threshold value evoke large spikes of
inward current (Fig. 2A). When the peak current is plotted against voltage, a sharp discontinuity is
seen (Fig. 2B). Similar recordings have been reported in several cell types in whole-cell patch
(Magistretti *et al.*, 2006; Diwakar *et al.*, 2009; Milescu *et al.*, 2010), and also in two-electrode voltage
clamp recordings of cat motoneurons (Barrett & Crill, 1980). As argued by Milescu et al. (2010), this
abrupt increase in current most likely reflects the axial current produced by the AIS AP. Indeed, the
current-voltage curve shows a plateau reflecting the all-or-none axonal spike, followed by an increase
at higher potential, most likely reflecting the somatic sodium current. These currents were eliminated
by 1 μM tetrodotoxin, a potent sodium channel blocker (2 ±0.4 % current remaining, *n* = 4 cells, paired
$t_3 = 4.5$, p = 0.02). For further analysis, the current measurements were corrected for the errors
introduced by the series resistance, as described by Traynelis (1998) (see Methods).

Figure 2. *Transmission of the axial current to the soma. A, Raw current recordings (with leak current correction, and only online correction series resistance) in response to voltage steps from -60 mV to different target potentials (-55 mV to -38 mV). B, Peak current vs. step command potential. The peak current increases abruptly when the potential exceeds some threshold. C, Corrected peak axial current at spike initiation measured in voltage clamp vs. capacitive current measured in current clamp (n = 15; 5 cells were excluded because spontaneous APs or capacitance were not measured). The dashed diagonal line represents the identity $-I_p = CdV/dt$ (not a regression line). D, Total transmitted charge vs. somatic capacitance (n = 17). The solid line is the best linear fit, with slope 31 mV. C, Peak axial current measured in voltage clamp vs. somatic capacitance measured in current clamp (n = 17). The solid line is the best linear fit (not affine; i.e., of the form $-I_p = a.C$). E, Axial current duration t_{50} measured at 50% of peak current, vs. capacitance, with regression line (n= 17); t_{50} = 0.36 ±0.05 ms, excluding one clear outlier.*

When the soma is not voltage-clamped, the axial current at spike initiation charges the somatic capacitance (and proximal dendrites). Therefore, we expect that the axial current measured in voltage clamp is approximately equal to the capacitive current $C.dV/dt$ during the initial rise of an AP recorded in current clamp. We estimated the effective capacitance on the first ms of the response to a small current pulse, and measured dV/dt in the initial phase of a spontaneous AP (see Methods). We found that for most cells, the axial current measured in voltage clamp was indeed close to the capacitive current of a spontaneous AP (Fig. 2C). The somatic depolarization due to the axial current is $\Delta V = Q/C$, where Q is the total charge Q transmitted to the soma, i.e., the integral of the axial current. We found a linear correlation between Q and C (Fig. 2D; Pearson correlation r = 0.56, p = 0.02), with a slope $\Delta V = 31$ mV. This is remarkably close to the difference between spike threshold and regeneration threshold

we observed on spontaneous APs (33 mV; Fig. 1C). Thus, the transmitted charge appears to be just
enough to bring the somatic potential to the voltage where somatic sodium channels open and
regenerate the AP.

This correlation was likely due to a linear relation between axial current and capacitance, because axial
current increased with capacitance (Fig. 2E) while current duration was essentially constant (Fig. 2F).
However, the relation with current was statistically less strong than with charge (Pearson correlation
r= 0.47, p = 0.06), possibly because the measurement of Q is more reliable than that of I_p, as integration
reduces noise and charge is not affected by electrode filtering.

Axial current and AIS geometry

Theoretically, axial current depends on AIS geometry (Hamada *et al.*, 2016). We measured the
geometry of the AIS of n = 14 cells by immunolabeling ankyrin-G, while identifying recorded cells using
biocytin in the patch pipette (see Methods) (Fig. 3A). The AIS was on average 31 μm long ($\pm$ 6 μm s.d.)
and started at 8.6 ± 3.3 μm from the soma (Fig. 3B), with no statistically significant correlation between
the two measurements (p = 0.59, Pearson test). We also measured the axon diameter at the proximal
and distal ends of the AIS. Keeping in mind that these measurements approach the limits of
conventional light microscopy, the proximal and distal diameters were 0.9 ± 0.3 μm and 0.5 ± 0.2 μm,
respectively. For comparison, Raghuram et al. (2019) found by a similar method 1 μm and 0.6 μm on
average in α S RGCs of mice, with substantial variability.

Figure 3. *Geometry of the AIS. A left, Fluorescence image of a RGC labelled with biocytin (pink). The start and*
end position of the AIS are indicated by green arrowheads. Note that the biocytin staining extends beyond the
AIS. Scale bar is 5 μm. A middle left, Fluorescence image of AISs labeled with ankyrin-G antibodies (green). A
middle right, Fluorescence image of the AIS masked by the neuron morphology. A right, Merge of the first and
third panels. B, Distance Δ of the AIS from the soma vs. AIS length L, with the regression line (p = 0.59, Pearson
test).

The axial current was on average I_p = -6.7 nA (s.d. 1.8 nA). A conservative estimate of Na⁺ conductance
density g_{min} in the AIS can be estimated by noting that the axial current cannot be greater than the
maximum current that all Na⁺ channels can pass. This maximum Na⁺ current is $G(E_{Na} - V)$, where E_{Na}
$\approx$ 70 mV is the reversal potential of Na⁺, G is the total Na⁺ conductance and $V \approx$ -15 mV is the local
membrane potential at which the current through a Na⁺ channel is maximal (based on Na⁺ channel
properties measured at the AIS of cortical pyramidal cells (Kole *et al.*, 2008)). Therefore, a lower bound
for the total Na⁺ conductance is $G_{min} = -I_p/(E_{Na} - V) \approx$ 79 nS. Using the high estimate of 1 μm for

the diameter, the average AIS area was therefore 97 μm² (± 19 μm² s.d.), which implies a minimum
conductance density of 814 S/m². With a diameter of 0.7 μm, we find a minimum of 1159 S/m².

Figure 4. *Predictions of axial current with resistive coupling theory. A, Light green curve: membrane potential*
along the axon of a simple model when all Na⁺ channels are open along the AIS, starting at distance Δ (gray
shading), with a voltage clamp of the soma. Solid dark green line: idealized voltage profile for an AIS clamped
at E_{Na}. The axial current produced by the model is the same as the current produced by an AIS clamped at E_{Na}
and starting at distance Δ + δ (dashed line). B, Axial current at spike initiation vs. AIS position Δ in a simple
model (solid) compared to theory (dashed). C, Mean squared error between predicted and measured current,
as a function of conductance density g (with d = 1 μm). D, Measured axial current vs. Δ, with the theoretical
relations for d = 0.8 μm, d = 1 μm and d = 1.2 μm (using g = 5400 S/m², the minimum in C; n = 14).

This is a conservative estimate because it ignores the conditions of propagation of the action potential.
Resistive coupling theory provides a quantitative estimate of the axial current as a function of AIS
geometry and *g*, by assuming that current entering the axonal membrane flows resistively towards the
soma, which acts as a current sink (Brette, 2013; Hamada *et al.*, 2016; Kole & Brette, 2018; Goethals &
Brette, 2020). Suppose first that conductance density is very high, such that the AIS is clamped at E_{Na}
when sodium channels open (Fig. 4A, dark green). Then by Ohm's law, the AIS will produce an axial
current $I_p = (E_{Na}-V_t)/R_a$, where R_a is axial resistance between the soma and the proximal end of the AIS.
Thus, we obtain an inverse relation between axial current and AIS position. However, conductance
density is finite, which implies that the proximal side of the AIS is pulled towards the somatic potential
(Fig. 4A, light green). This is electrically equivalent to shifting the AIS distally by an amount δ:

166
$$I_p = \frac{1}{r_a}\frac{E_{Na} - V_t}{\Delta + \delta}$$

167 where *Δ* is the distance of the AIS from the soma, r_a is the axial resistance per unit length, V_t is the
168 somatic spike threshold ($E_{Na} - V_t \approx 120$ mV) and

169
$$\delta = \sqrt{\frac{d}{4R_i g}}$$

where R_i is intracellular resistivity. Here, AIS length L can be neglected provided that it is substantially
larger than δ (see Methods). This is clearly the case because L was 31 μm on average, while an upper
estimate of δ using d = 1.2 μm and g = 1000 S/m^2 is 17 μm. Thus, in our cells, AIS length should have no
impact on axial current. The formula above agrees well with simulations of a simplified model with
non-inactivating Na$^+$ channels (Fig. 4B), except when the AIS is very proximal, where it gives an
overestimation.

This analysis shows that it is the proximal geometry of the AIS that matters for the calculation of the
axial current. Using d = 1 μm, we find that the error between the predicted and the measured current
varies with g, with a broad minimum at about 5500 S/m^2 (Fig. 4C). This is close to the value that Guo
et al. (2013) obtained by model optimization on current-clamp recordings (5000 S/m^2). Figure 4D
shows the axial current measured in our cells as a function of AIS position, together with the theoretical
predictions using g = 5500 S/m^2 with diameters d = 0.8 μm, d = 1 μm and d = 1.2 μm. Although the
magnitude of the recorded axial currents is consistent with the theoretical prediction, the correlation
between axial current and AIS position did not reach significance (p = 0.66, Pearson test). This may
simply reflect the variability of AIS diameter, which has a strong impact on this relation.

This estimate relies on the precision of AIS geometry measurements. However, even if AIS position and
length were different, high conductance density would still be necessary to account for the measured
axial current. This can be shown by calculating the maximum axial current that can be generated across
all possible AIS geometries for a given conductance density, and then deducing the minimum
conductance density necessary to produce a given axial current I (see Methods). Taking R_i = 100 Ω.cm,
we find g_{min} = 1263 S/m^2 for d = 1 μm and g_{min} = 2467 S/m^2 for d = 0.8 μm (as argued above, it is mostly
the geometry of the proximal side that matters for this calculation). With a higher value for R_i, the
lower bound on conductance density would be proportionally higher.

Overall, this analysis shows that the strong axial current produced at spike initiation requires a Na$^+$
conductance density in the AIS of at least about 1000 S/m^2 using the most conservative estimates, and
plausibly several thousand S/m^2 based on our measurements of AIS location and standard values of
R_i.

The threshold axial current

Variation of axial current near threshold

In a model where the AIS is reduced to a single point, theory predicts that spikes initiate when the
sodium current, and therefore the axial current, reaches a threshold $I_t = k/R_a$, where k is the
activation slope factor of sodium channels ($k \approx 5$ mV) (Brette, 2013). This makes spike initiation distal
from the soma efficient because the Na$^+$ flux below threshold is low. We show in the Methods that the
formula is approximately correct in an extended AIS model, if R_a is measured between soma and the
middle of the AIS. Thus, the threshold axial current is determined by AIS geometry. We tried to
estimate I_t in our cells.

To give an order of magnitude, with d = 1 μm and given that the middle position of the AIS is 24 μm on
average, we obtain $R_a \approx 31$ MΩ, which gives $I_t \approx 160$ pA (assuming k = 5 mV), a small current. Figure
5A shows a recording of the axial current at threshold, which is noisy. We measure the peak current
after smoothing. In addition, theory predicts that the axial current increases very steeply near
threshold (dI/dV is infinite at threshold, see Methods), as shown in Figure 5B. This makes the threshold
current difficult to measure, and likely leads to an underestimation of the threshold current. We

measured the current at different step voltages in steps of 0.5 mV ($n = 12$). In the example shown in Fig. 5C, a small but noticeable current appears at 3 mV below threshold, which increases at higher subthreshold potentials. More precisely, theory predicts that $V-V_t$ is proportional to $(I/I_t - 1)^2$. This relation is shown in a biophysical model in Figure 5D. In a simplified model (no sodium channel inactivation or potassium channels), the slope β is predicted to be equal to $k/2$ (see Methods). This slope is found to be larger in the more realistic model shown in Figure 5D, $\beta \approx 4.7$ mV, close to k. Our data fitted this quadratic relation well (Fig. 5E), with slopes $\beta \approx 4.2$ mV (± 1.7 mV), in the expected range (Fig. 5F). Thus, the axial current increases steeply just below threshold, in agreement with theory.

Figure 5. Axial current near threshold. A, Current recorded at threshold (gray). After smoothing (black), I_t is the peak value. B, Peak current vs. V in a biophysical model with extended AIS. Threshold was measured by bisection for better precision. The shaded box represents the region 3 mV below threshold. C, Peak current vs. V measured below threshold in a RGC. D, Difference between membrane potential and voltage threshold vs. quadratic normalized current in the biophysical model, with the regression line (slope $\beta = 4.7$ mV). E, Same as D in the RGC (slope of regression line: $\beta = 4.4$ mV). F, Slope of linear regressions shown in E over all cells.

Threshold vs. AIS geometry

Both the voltage and axial current at threshold are predicted to depend on AIS geometry, namely to
decrease when the AIS is shifted away from the soma, all else being equal. We analyzed these relations
in n = 10 cells (cells were excluded either because AIS geometry was not measured or reference
potential drifted). There was no significant linear correlation in our data between voltage threshold
and either AIS start position (Fig. 6A, p = 0.54, Pearson test) or length (Fig. 6B, p = 0.14, Pearson test).
However, voltage threshold varies theoretically with both quantities as $-k \log(x_{1/2}L)$. The correlation
was stronger with $\log(x_{1/2}L)$, although still weak (Pearson correlation r = 0.62, p = 0.06). The
regression slope was k = 4.3 mV, a plausible value (Fig. 6C). We note that diameter and perhaps
conductance density, which both contribute to the voltage threshold, may also vary across cells.

We observed an inverse correlation between axial current threshold and AIS position (Fig. 6D, p = 0.04,
Pearson test). Theory makes a quantitative prediction: $I_t = k/R_a$, with R_a measured from the soma to
the middle of the AIS. This may differ by a constant factor in a complex biophysical model (Fig. 6E,
compare dashed and solid lines). Measured currents are lower than predicted and the inverse
correlation is barely significant (Pearson correlation r = -0.65, p = 0.08). As explained above,
underestimation and limited precision were expected. Nonetheless, the magnitude of measured
currents was reasonably close to theoretical estimations (92 pA vs. 160 pA on average, with all but two
cells between 70 and 150 pA).

Figure 6. Threshold vs. AIS geometry. A, Voltage threshold vs. AIS position Δ is RGCs. B, Voltage threshold vs.
AIS length L. C, Voltage threshold vs $x_{1/2}L$ in logarithmic space, with logarithmic regression line (slope k = 4.3
mV; p = 0.06, Pearson test). D, Current at threshold vs. AIS position, with regression line (p = 0.04, Pearson test).
E, Current at threshold vs. AIS middle position $x_{1/2}$, with theoretical prediction using d = 1 μm (dashed green)
and simulation in a biophysical model (solid).

Adaptation of the axial current

Properties of adaptation

We observed that the axial current at spike initiation has just the right magnitude to depolarize the
soma to the somatic regeneration threshold. What would happen if the availability of sodium channels
varied? In many neurons, sodium channels can inactivate substantially below threshold, producing
voltage threshold adaptation (Azouz & Gray, 2000; Platkiewicz & Brette, 2011; Fontaine *et al.*, 2014).
Threshold adaptation has been observed in current-clamp recordings of salamander RGCs (Mitra &
Miller, 2007). If this phenomenon reflects the inactivation of AIS sodium channels, it may compromise
the transmission of the AIS spike to the soma.

We examined this issue by holding the neuron at different potentials V_0 before measuring the voltage
threshold. We observed that the threshold increases substantially with V_0 (Fig. 7A). The relation
between V_t and V_0 follows the theoretical expectation for threshold adaptation due to sodium channel
inactivation (Platkiewicz & Brette, 2011; Fontaine *et al.*, 2014), where the threshold starts increasing
above the baseline V_{min} when V_0 exceeds the half-inactivation voltage V_i of sodium channels, with a
slope $k_i/k_a \approx 1$ in the depolarized range (where k_i and k_a are the inactivation and activation slope
factors, respectively). By fitting the theoretical relation, we find $V_i \approx -55.8 \pm 3.1$ mV (Fig. 7B), $V_i -$
$V_{min} \approx -0.7 \pm 2.9$ mV (Fig. 7C), $k_a \approx 4.1 \pm 2.2$ mV (Fig. 7D), and $k_i/k_a \approx 0.9 \pm 0.18$ (Fig. 7E). These
values are consistent with expectations if threshold adaptation is due to sodium channel inactivation.

We then measured the axial current at spike initiation (just above threshold) as a function of V_0 (note
that there are fewer data points because current recordings were discarded when R_s changed by more
than 30%). We observed that the current decreased considerably with increasing V_0 (Fig. 7F). On
average, it attenuates by a factor 12.3 ± 5.1 when V_0 increases from -60 to -40 mV (Fig. 7G). At V_i, the
current is 32 ± 10 % smaller than the maximum current (Fig. 7H).

If adaptation of voltage threshold and axial current are both due to sodium channel inactivation, then
axial current and voltage threshold should co-vary with V_0. Theoretically, V_t varies with available
conductance g as $-k \log g$ (Platkiewicz & Brette, 2011). For low g, the axial current I_p is proportional
to $\sqrt{g}$. Therefore, V_t should vary with I_p as $-k \log I_p^2$, or equivalently, $-2k \log |I_p|$.

We first note that the potential V_i^* at which the axial current is attenuated by $\sqrt{2}$ is indeed close to the
half-inactivation voltage V_i estimated from threshold adaptation ($V_i^* = -56.5 \pm 1.9$ mV vs. -55.8 mV)
(Fig. 7I). Then when we compare V_t with I_p, we find a logarithmic relation (Fig. 7J, K) with half-slope
$k_a = 2.4 \pm 2.7$ mV (Fig. 7L). Note that this average includes one outlier; the median k_a is 3.4 mV (the
smaller number of points is due to the fact that exclusion criteria for both V_t and I_p are applied). This
strongly suggests that both threshold and axial current adaptation are due to the same phenomenon,
sodium channel inactivation.

Figure 7. *Adaptation of the axial current at spike initiation. A, Voltage threshold vs. initial holding potential V_0 in a RGC. The dashed line is the identity $V_t = V_0$, and the solid curve is a fit to the theoretical relation. B, Statistics of half-inactivation voltage V_i from theoretical fits. C, Statistics of V_i-V_{min} from fits. D, Statistics of activation slope k_a. E, Statistics of k_i/k_a. F, Axial current I_p at spike initiation vs. initial holding potential V_0 in a RGC. The dashed line shows the potential V_i^* where I_p is attenuated by $\sqrt{2}$. G, Current attenuation I_{60}/I_{40} from -60 to -40 mV, over all cells. H, Current at half-inactivation voltage V_i, relative to the maximum current. I, Comparison between V_i^* obtained from current attenuation and V_i obtained from voltage threshold adaptation (the diagonal line is the identity). J, Voltage threshold V_t vs. axial current in logarithmic space, over all RGCs (n = 9; each color corresponds to one cell). K, Voltage threshold V_t vs. axial current for one RGC, with logarithmic regression line (half-slope k = 3.4 mV, r = 0.99). L, Statistics of k_a from logarithmic regressions over all cells.*

While the axial current above threshold is strongly modulated by the available Na$^+$ conductance, resistive coupling theory predicts that the threshold axial current depends on AIS geometry but not on sodium conductance ($I_t = k/R_a$). Figure 8A shows current-voltage relations for different V_0 in the same cell. The curves appear to shift horizontally when V_0 is changed, so that the voltage threshold increases with V_0 but the axial current at threshold does not, as shown specifically on Figure 8B. Over all measured cells (*n* = 6; voltage threshold and current threshold were only measurable with a stable R_s in a few cells), I_t varied by a factor smaller than 2.5 (1.2 $\pm$ 0.6) between -60 and -40 mV (Fig. 8C), whereas I_p varied by a factor 12.3 on average.

Figure 8. Adaptation of the axial current at threshold. A, Current vs. somatic potential V a few mV below threshold, shown for different initial holding potentials V_0 (-70, dark purple to -40 mV, light green) in the same RGC. B, Current at threshold vs. V_0 in the same cell. C, Attenuation of threshold current I_t^{60}/I_t^{40}.

Compensation of axial current attenuation

Figure 9A shows the attenuation of I_p as a function of V_0 in one cell. Here I_p attenuates by a factor 7.3 between -60 and -40 mV. If the axial current at spike initiation attenuates by a factor 7, then we expect the induced somatic depolarization to also attenuate by a factor 7, to about 4 mV, which seems insufficient to reach the threshold for somatic regeneration. However, this is not what we found. In this cell, the total transmitted charge, obtained by integrating the current, attenuates only by a factor 1.7 (Fig. 9B). This occurs because current duration increases at high V_0 (Fig. 9C). Over all measured cells (n = 7), transmitted charge attenuated by a factor 3.1 ± 1.4 from -60 to -40 mV, compared to 12.3 ± 5.1 for the axial current (Fig. 9D). The increase in current duration was observed consistently above -50 mV (Fig. 9E).

Figure 9. Compensation of axial current attenuation. A, Axial current at spike initiation vs. initial potential V_0 in a RGC. B, Total transmitted charge Q vs. V_0 in the same cell. C, Current duration t_{50} vs. V_0 in the same cell. Top traces: normalized axial currents measured at V_0 = -60 mV (light gray), -50 mV (dark gray) and -40 mV (black). D, Current attenuation vs. charge attenuation between -60 and -40 mV, over all cells. E, Current duration t_{50} vs. V_0 in all cells.

Indeed, we could occasionally observe spontaneous bursts on top of a depolarizing wave, with APs triggered at potentials up to -40 mV, with no sign of transmission failure. An example is shown in Figure 10A, with a selection of individual APs shown in Figure 10B, and corresponding phase plots in Figure 10C. During this burst, spike onset increased up to about -40 mV while the somatic regeneration threshold was stable (Fig. 10D).

Figure 10. Changes in AP properties during a spontaneous burst. A, Spontaneous burst of APs in a RGC. B, Individual APs marked in A. C, Phase plot of Aps marked in A. D, Spike onset and somatic regeneration threshold of the successive APs in A. Somatic regeneration threshold could only be accurately measured for the first 12 spikes because of noise.

Thus, detailed properties of the axial current appear to be such as to ensure reliable AP transmission to the soma in changing conditions.

Discussion

Summary

In summary, we have observed that the AIS of RGCs produces a large axial current at spike initiation (about 7 nA), which requires a high Na+ conductance density (most likely several thousand S/m²). The charge that this current transmits to the soma co-varies with somatic capacitance, in such a way as to produce a depolarization of about 30 mV, the amount necessary to bring the somatic potential to spike regeneration threshold. Theory shows that the axial current is mainly determined by AIS position and diameter, and to some extent by Na+ conductance density, but perhaps counter-intuitively not by AIS length.

In agreement with resistive coupling theory (Brette, 2013; Kole & Brette, 2018), the axial current is small below threshold (on the order of 100 pA at threshold, and undetectable a few mV below) and decreases when the AIS is further away from the soma, which reduces energy consumption.

We have also observed that the voltage threshold for spike initiation adapts to depolarization, in a way
compatible with Na+ channel inactivation. Consistently, the axial current at spike initiation also
decreases when the threshold adapts. This attenuation can reach a factor of 10 or more for large
depolarizations, which could potentially compromise spike transmission to the soma. However, we
found that this attenuation is compensated by a broadening of the axial current.

Overall, our results are in good agreement with predictions of resistive coupling theory. The inferred
Na+ channel activation slope factor, which was found consistently to be $k \approx 4$ mV in several distinct
data sets, may seem to be on the low end of Boltzmann fits to patch-clamp recordings, typically 4-8 mV
(Angelino & Brenner, 2007). However, this is likely because this parameter is generally obtained from
fits on a broad voltage range, while an exponential fit around the spike initiation voltage yields lower
values (Platkiewicz & Brette, 2010). For example, Hodgkin and Huxley (1952) found that the Na+
current-voltage curve of the squid axon was well fitted by an exponential of slope 4 mV; Baranauskas
and Martina (2006) also noted that in cortical pyramidal cells, the slope was lower when estimated
around spike threshold than on a broader range (5.4 mV vs. 6.4 mV).

Limitations

One of the main technical limitations to interpret the results of this study is that axonal diameter d
cannot be measured precisely with conventional optical microscopy. This is an important limitation
because theory shows that key properties are very sensitive to diameter. Specifically, axial resistance
is inversely proportional to d^2. This results in an error in resistance estimation of around 50% for a
200 nm error in axon diameter estimation (assuming $d \approx 1$ μm). This translates to comparable errors
in axial current predictions. This limitation should also be kept in mind when interpreting other
studies where changes in AIS geometry are observed (see below). The best way to overcome this
limitation would be to measure axonal diameter precisely using either electron microscopy or super-
resolution microscopy.

Two other limitations are the measurement of intracellular resistivity R_i and axonal tapering. Axial
resistance is proportional to intracellular resistivity R_i, but this parameter is difficult to estimate.
Ideally, it should be measured by simultaneous recordings in the axon and soma, and a precise estimate
requires a precise measurement of axon diameter. Stuart and Spruston (1998) estimated R_i = 70-100
Ω.cm in dendrites of cortical pyramidal cells, based on simultaneous recordings in soma and apical
dendrite. Although this value is mainly determined by the concentration of the most mobile ions (i.e.,
mainly K+), which is not expected to vary widely across the cell, it is conceivable that it is higher in thin
crowded structures such as the proximal axon. Higher values, up to 150 Ω.cm, have been used in
modeling studies of RGCs (Sheasby & Fohlmeister, 1999; Fohlmeister *et al.*, 2010), but these are based
on model optimization using somatic recordings.

In the theory, we did not take into account axonal tapering. However, in RGCs, axon diameter decreases
from soma to AIS, then decreases again along the AIS (Raghuram *et al.*, 2019). The theory assumes a
uniform diameter, because general analytical solutions do not exist with variable diameter. For the
calculation of the axial current at spike initiation, taking into account tapering would tend to reduce
the axial resistance between soma and AIS, as if the AIS were closer to the soma. The diameter in the
calculation of δ should be the diameter of the proximal AIS.

We were not able to confirm the inverse relation between AIS position and axial current at spike
initiation that theory predicts. A plausible reason is that the axial current is very sensitive to diameter,
which might have varied substantially across cells. It is also possible that the available Na+ conductance

density varied across cells. Indeed, our data on adaptation show that half-inactivation voltage (about -57 mV) is close to the initial potential used in our voltage clamp measurements of axial current (-60 mV). Another potential source of variability is that we have studied mice at an age where there are developmental changes in the expression of Na^+ channel subtypes (Boiko *et al.*, 2003; Van Wart *et al.*, 2007), which might have contributed some variability. Finally, series resistance introduces errors that may have been incompletely corrected offline. This issue could be addressed by measuring currents with two electrode voltage-clamp (Barrett & Crill, 1980).

Na^+ conductance density

Whether the AIS has high Na^+ conductance density has been controversial (Colbert & Pan, 2002; Kole *et al.*, 2008; Fleidervish *et al.*, 2010). This question has been typically considered from the viewpoint of excitability: high conductance density has been proposed to account for the fact that the AIS spike initiates about 30 mV below the somatic regeneration threshold. Other contributing factors are the lower activation threshold of axonal sodium channels (Kole & Stuart, 2008; Hu *et al.*, 2009) and the axial resistance between soma and AIS (Brette, 2013). Here we examined another empirical constraint on Na^+ conductance density, the axial current that the AIS generates at spike initiation.

By just considering the area of the AIS, to produce a current of 6.7 nA requires a conductance density of about 1150 S/m^2 with $d = 0.7$ μm (average diameter across the AIS in our data) or 800 S/m^2 with an upper estimate of $d = 1$ μm. This is a lower bound that neglects considerations of cable theory, namely the fact that the axial current flows from the distal end of the AIS to the soma.

It is possible to calculate the maximum axial current produced by an axon of diameter d and conductance density g. This calculation shows that, to account for a current of 6.7 nA, g must be at least 1200 S/m^2 if $d = 1$ μm, and about 2500 S/m^2 if $d = 0.8$ μm, independently of AIS position. Here the relevant diameter is the diameter of the proximal AIS (about 0.9 μm in our data). Finally, taking into account measured AIS position, the data are consistent with g around 5000 S/m^2 (with $d = 1$ μm), although the minimum is broad. Overall, this analysis indicates that g should be several thousand S/m^2. This estimate is independent of Na^+ channel kinetics, and in particular it holds even if Na^+ channels cooperate (Naundorf *et al.*, 2006).

Lorincz and Nusser (2010) counted 187 Nav1.6 channels per $μm^2$ in the AIS of CA1 pyramidal cells. Assuming a unitary conductance of 10-20 pS per channel (Hille, 2001), this amounts to 1870-3740 S/m^2. However, this is an estimate of the structural density, not necessarily of the functional density. In a computational model of layer 5 pyramidal cells, a density of 2500 S/m^2 was necessary to account for the measured initial depolarization speed of somatic APs (Kole *et al.*, 2008). Similarly, optimization of a model of RGCs for AP shape yielded a conductance density of about 5000 S/m^2 (Guo *et al.*, 2013). Our analysis provides an estimation that is less dependent on model specifics, and confirms these previous studies.

The theoretical analysis indicates that a high conductance density is likely a necessary condition to transmit the AIS spike to the soma in a variety of cell types, due to the drastic geometrical variation at the axosomatic boundary. The minimum conductance density to produce an axial current I is proportional to I^2/d_{AIS}^3. If we assume that the current must scale with the area of the soma, then the minimum g is proportional to d_{soma}^4/d_{AIS}^3. This ratio appears to be approximately conserved across cell types (Goethals & Brette, 2020), and therefore most neurons should face the same constraint requiring a similar conductance density in the AIS.

It should be noted that, despite a high conductance density at the AIS, the total Na⁺ influx through the
AIS should theoretically have the same order of magnitude as through the soma and proximal
dendrites, as observed (Fleidervish *et al.*, 2010). Indeed, the total Na⁺ influx at the AIS should match
the charge necessary to depolarize the soma by about 30 mV, while the total Na⁺ influx at the soma
(and proximal dendrites) should account for a further depolarization of a few tens of mV (about 45 mV
in our cells). The AIS influx should occur preferentially in the proximal AIS, even if conductance density
is uniform, because the driving force of the Na⁺ channel is larger there (see Fig. 4A). This has indeed
been observed in cortical pyramidal cells (Baranauskas *et al.*, 2013).

Structural tuning of the AIS

In layer 5 cortical pyramidal cells, Hamada et al. (2016) observed that AIS position was inversely
related to the diameter of the apical dendrite. Quantitatively, this relation was consistent with a
proportionality relation between the axial current produced by the AIS and the somatodendritic
capacitance. Here we showed more directly that, in RGCs, the charge transmitted by the AIS covaries
with the somatodendritic capacitance, in such a way as to depolarize the soma to the threshold for
somatic spike regeneration.

Overall, our measurements are in line with quantitative predictions of resistive coupling theory.
However, we did not observe a correlation between AIS position and capacitance. Theoretically, the
structural parameters that determine the axial current are AIS position and diameter (and not AIS
length, at least not in the range of observed lengths). Therefore, one would expect a negative
correlation between AIS position and capacitance if diameter were homogeneous across cells, or at
least uncorrelated to capacitance. In fact, Raghuram et al. (2019) observed a positive correlation
between AIS position and soma size in α S RGCs. Such a correlation would be expected if AIS diameter
scaled with soma size. The authors did observe a positive correlation between soma size and the
diameter of the proximal axon (we note that observing such correlations for the AIS proper, which is
below 1 µm in diameter, may not be feasible). It cannot be excluded that the lack of significant inverse
correlation between AIS position and capacitance is due to the limited precision of our measurements,
especially as we did observe an inverse correlation between AIS position and threshold axial current.
It is possible that the availability of Na⁺ channels varied across cells. In any case, we stress that axon
diameter is a key structural parameter in setting the axial current as well as excitability, and therefore
it must be considered to correctly interpret experimental results.

It remains that, in order to produce an axial current of appropriate magnitude from an AIS of a given
diameter and conductance density, the AIS must be positioned appropriately. A number of studies have
shown that AIS position can vary across cells (Kuba *et al.*, 2006; Hamada *et al.*, 2016; Höfflin *et al.*,
2017), during development (Galiano *et al.*, 2012; Kuba *et al.*, 2014; Gutzmann *et al.*, 2014), and with
activity (Kuba *et al.*, 2010; Grubb & Burrone, 2010; Grubb *et al.*, 2011; Kuba, 2012; Evans *et al.*, 2015;
Jamann *et al.*, 2017, 2020). These changes have often been suggested to reflect a homeostatic
regulation of excitability, but theory predicts a small effect of AIS position on excitability (Goethals &
Brette, 2020), and a large effect on axial current. Therefore, it is conceivable that these changes reflect
a homeostatic regulation not of excitability *per se*, but of the axial current required to transmit the AIS
spike to the soma. For example, Grubb and Burrone (2010) report that when cultured hippocampal
neurons are depolarized with 15 mM KCl, capacitance decreases by about 10% while the AIS shifts
away from the soma. This distal shift is consistent a decrease in axial current required to match the
decrease in capacitance. In the same way, developmental changes in AIS position may also be
consecutive of changes in somatic diameter or dendritic area. Finally, in neurons where

backpropagation of the AP to the soma may be undesirable, such as some types of auditory neurons
(Kuba *et al.*, 2006; Scott *et al.*, 2007), a distal placement of the AIS may be beneficial.

Adaptation

Threshold adaptation has been observed in current-clamp recordings of salamander RGCs (Mitra &
Miller, 2007), as well as in many other cell types (reviewed in (Platkiewicz & Brette, 2011)). We also
observed it in mouse RGCs and quantified it precisely. The voltage threshold starts increasing when
the membrane is depolarized above ≈ -56 mV, and for large depolarizations the slope of the relation
between potential and threshold is close to 1. That is, the threshold tracks the membrane potential so
as to remain a few mV above it. These observations are consistent with theoretical expectations based
on Na^+ channel inactivation (Platkiewicz & Brette, 2011). In layer 5 pyramidal cells, half-inactivation
voltage of AIS Na^+ channels is about -61 mV (Kole & Stuart, 2008), which is in line with our
observations.

To our knowledge, adaptation of the axial current had not been reported before. Our quantitative
analysis shows that the co-variation of axial current and threshold is consistent with AIS Na^+ channel
inactivation being the cause of both phenomena. The axial current attenuated by a factor 12 on average
over a 20 mV depolarization. This would reduce the charge transmitted to the soma by the same factor
and possibly compromise spike transmission to the soma, if the current spike shape were unchanged.
However, we observed that this attenuation was largely compensated by a broadening of axial
currents. This means that the AP at the AIS broadens when the soma is depolarized. In fact, such
broadening has been observed in layer 5 pyramidal cells and attributed to the inactivation of Kv1
channels (Kole *et al.*, 2007). As Kv1.2 is expressed in the distal AIS of RGCs (Van Wart *et al.*, 2007), this
might explain our observations.

In conclusion, our observations indicate that structural and channel properties of the AIS are
functionally organized in such a way as to ensure reliable transmission of the AP to the soma.

Materials and Methods

All data are available at https://zenodo.org/record/4005629#.X00H9y3pP-Z. Code for both data
analysis and model simulations is available at https://github.com/romainbrette/AIS-geometry-and-
axial-current.

Ethical statement

Timed-pregnant Swiss and C57BL/6NRj mice were purchased from Janvier Labs (Le Genest Saint Isle,
France) and housed under controlled conditions (22 ± 1°C, 60 ± 10% relative humidity, 12/12h
light/dark cycle, food and water *ad libitum*). All animal procedures were performed in strict
accordance with institutional guidelines and approved by local ethics committees (C2EA-05: Comité
d'éthique en expérimentation animale Charles Darwin) and by European Communities Council
Directive 2010/63/UE.

Whole-cell electrophysiology of RGCs

Mice were taken at postnatal day 10-12 (P10-12). The pup was rapidly decapitated, the eyes were
removed and placed in Ringer's medium containing (in mM): 119 NaCl, 2.5 KCl, 1.0 KH$_2$PO$_4$, 11 glucose,
26.2 NaHCO$_3$, 2 CaCl$_2$ and 1 MgCl$_2$ (290-295 mOsm), bubbled with carbogen (95% O$_2$/5% CO$_2$). The
retina was dissected and fixed on filter paper over a small hole (N8895, Sigma-Aldrich) with the RGC
layer upwards and continuously perfused with Ringer's solution warmed to 32 degrees Celsius.

Thick-walled borosilicate pipettes (OD/ID of 1.5/0.87 mm; 30-0060, Harvard Apparatus) were pulled
on a P-1000 Flaming/Brown puller (Sutter Instruments). Pipettes were filled with intracellular
solution containing (in mM): 128 K-gluconate, 10 HEPES, 16 KCl, 1 EGTA, 2 Mg-ATP, 0.5 Na$_2$-GTP, pH
7.25 with KOH (275 mOsm) and 1-2 mg/mL biocytin (B4261, Sigma-Aldrich). Open tip resistance was
2.5-4 MΩ. Reported potentials were corrected for a liquid junction potential of -11 mV. Whole-cell
recordings were made with a Multiclamp 700B amplifier (Axon Instruments), filtered at 10 kHz and
digitized at 50 kHz using a DigiData 1440A (Axon Instruments) and Clampex 10.7 running on Windows
10. High-resistance patch seals (>1 GΩ) were obtained before breaking into the cell. Recordings with
a series resistance R_s above 25 MΩ, or with a residual R_s (after compensation) above 5 MΩ, were
discarded. The resting membrane potential of the cell was recorded in the first minute after breaking
in.

Passive cell properties were recorded by stepping from -70 to -80 mV in voltage-clamp mode without
whole-cell compensation. Series resistance was electronically compensated 80-95% with a lag of 18
μs. Between protocols we repeated the voltage step without compensation to monitor changes in
series resistance, and series resistance compensation was adjusted if necessary. Passive currents were
subtracted using a P/n protocol (5 steps of 5 mV) that preceded each protocol. The P/n protocol was
missing for a few recordings; we then subtracted the passive response using a 10 mV step.

Adaptation protocols started with a long adaptation step at V_0 (0.5 s, V_0 varied by steps of 5 mV)
followed by an activation step (resolution of 1 mV) to elicit an AIS spike. We ensured that the
adaptation step was long enough by varying the step duration in a few cells.

In current-clamp mode, bridge balance and pipette capacitance cancellation (6.2-7.1 pF) were used.
Hyperpolarizing current pulses were injected to measure the cell's capacitance (see
Electrophysiological data analysis). Next, for n = 16 cells, 5-20 minutes of spontaneous activity were
recorded to analyze spontaneous APs.

At the end of the experiment, the pipette was retracted to obtain an outside-out patch. Outside the
retina the tip was cleaned with brief, positive pressure to remove the remaining membrane patch and
the potential offset was noted to check for any drift in the reference potential.

The retina was rinsed in 0.12 M PBS, fixed for 15 minutes in 4% paraformaldehyde in 0.12 M phosphate
buffer, rinsed again 2 times with 0.12 M PBS and kept in 0.12 M PBS at 4 degrees Celsius for
immunolabeling procedure at a later stage.

Immunohistochemistry

A few days after recording, retinas were washed during 5 minutes in PBS and permeabilized overnight
at 4°C in 5% normal goat serum (NGS, Sigma Aldrich) and 1% Triton-X100 in PBS. Retinas were then
incubated with a solution of 0.1M PBS containing the mouse monoclonal anti-ankyrin-G (clone
N106/36; 1:250; NeuroMab; ID: AB_2749806) and 1% normal donkey serum (NDS) for 24h at 4°C.
Retinas were washed 4 x 15 minutes in 0.1M PBS and then incubated with a PBS solution containing
donkey anti-mouse Alexa Fluor 488 (1:500, Thermo Fisher; ID: AB_141607), Streptavidin Alexa Fluor

594 (1:500, Thermo Fisher, ref. S11227) , 5% NGS and 0.1% Triton-X100 overnight at 4°C. Retinas
were washed 4x15 minutes in PBS and mounted onto Superfrost™ slides and coverslipped with
Fluoromount. Mounted retinas were stored at 4°C until confocal imaging.

Confocal imaging

The retinas labelled for biocytin and ankyrin-G were sequentially captured with an inverted laser
scanning confocal microscope (FV1000, Olympus) equipped with an Argon (488nm) ion laser and laser
diode (555 nm), filter cubes appropriate for Alexa Fluor 488 and Alexa Fluor 594, and a 40x objective
(oil, NA 1.3). Acquisition settings were optimized for each cell. Z-stacks were obtained with a step size
of 0.5 µm. Confocal x-y sampling resolution was 0.155 µm, except for three cells for which it was 0.207
µm.

Electrophysiological data analysis

Data were analyzed with custom Python scripts.

Estimation of passive properties

The raw series resistance $R_s{}^*$ was measured from responses to a test pulse in voltage clamp: $R_s =$
$\Delta V / I_0$, where ΔV is the voltage pulse amplitude and I_0 is the amplitude of the first transient peak. The
residual series resistance R_s during a given recording is $R_s = R_s^* - R_{rec}\%_{comp}$ where R_{rec} is the series
resistance used for compensation during the experiment and $\%_{comp}$ is the amount of compensation.
Effective capacitance is estimated from the response to current pulses, by fitting an exponential to the
first ms, which is the time scale of the axial current. This estimation was done in n = 17 cells.

Analysis of APs

The first AP recorded during spontaneous activity was used to measure AP features (Fig. 1).
Spontaneous activity was recorded in 16 cells; 6 of them were excluded from this analysis because the
reference potential drifted by more than 3 mV. To compute the phase plots (*dV/dt* vs *V*), we ensured
that the plotted points are isochronic, by considering that *dV/dt* corresponds to the derivative midway
between two consecutive points, and interpolating the values of *V* at that midpoint. Spike onset was
defined as the potential when *dV/dt* crosses 20 mV/ms for the last time before the AP peak. The value
of *dV/dt* for the initial segment component was defined as the first local maximum between spike onset
and the global maximum of *dV/dt*. In a few cells, this was equal to the global maximum. The
regeneration threshold is defined as the potential at the point of maximal acceleration d^2V/dt^2 after
the initial segment component.

Correction of series resistance error

Axial currents were corrected using a minor adjustment of the method described by Traynelis (1998).
The presence of the series resistance results in an error in clamping the somatic potential equal to -
$R_s.I_e$, where I_e is the current through the electrode. This produces a capacitive current through the
somatic membrane equal to *C.dV/dt = -R_sC dI_e/dt*, which results in filtering the axial current through a

low-pass filter with time constant $\tau = R_sC$. We correct the recorded current by subtracting this capacitive current:

$$I^* = I_e + \tau\frac{dI_e}{dt}$$

where I* is the corrected current. The time constant is estimated directly by fitting an exponential to the first 0.5 ms of the response to a small voltage step (with the same amplifier tunings as for subsequent recordings) (Fig. 11A). Note that as the whole cell compensation circuit of the amplifier was used, this must be understood as a residual time constant, which can be negative. We used the steps from the P/n protocol, except for a few cells with no P/n protocol, where we used a -10 mV test pulse before the axial current recording. We then correct for the loss in driving force due to imperfect clamping as in Traynelis (1998):

$$I = I^*\left(\frac{V_c - E_{Na}}{V_c - I_eR_{res} - E_{Na}}\right)$$

where V_c is the command potential. In practice, this was a minor correction.

Figure 11*. Correction of axial current recordings. A, Passive response to a +5 mV voltage step. An exponential function is fitted on the first 0.5 ms, starting from the peak, to estimate the decay time constant (dashed red). B, A recorded axial current (black) is corrected by defiltering (red), with residual R_s = 2.1 MΩ and τ = 70 μs. C, Peak current correction in a biophysical model with an extended AIS (5 to 30 μm from the soma), as a function of series resistance R_s. Dashed line: peak current in the ideal situation with no series resistance. D, Change in*

measured and actual voltage threshold as a function of R_s in a biophysical model. E, Corrected peak axial
current at spike initiation vs. series resistance in RGCs (n = 20), showing a weak correlation (Pearson
correlation r =0.43, p = 0.06). F, Corrected voltage threshold vs. R_s in RGCs (n = 14; 6 cells excluded because the
reference potential drifted), with the regression line (p = 0.25, Pearson test).

Figure 11B shows a recording from a retinal ganglion cell (black). After correction, the peak current is
larger (red). We tested the effect of series resistance and the correction in a simple biophysical model
of a RGC with an extended AIS, with the electrode modeled as a resistance (see *Biophysical Model*).
Figure 11C shows that the peak recorded current decreases substantially when increasing R_s, but this
error is well corrected by the method described above. The spike threshold is only marginally affected
by the series resistance (Fig. 11D; the exact value of the threshold depends on model parameters). We
selected cells with residual series resistance smaller than 5 MΩ ($n = 20$). There was a correlation
between measured peak axial current I_p and R_s (Fig. 11E, Pearson correlation r = 0.43, p = 0.06), but it
remained small. We observed no correlation between spike threshold and R_s (Fig. 11F, p = 0.25,
Pearson test). Therefore, the impact of R_s on our measurements should be moderate.

Threshold

The voltage threshold V_t is defined as the highest command potential where no axonal spike is elicited.
The membrane potential at the soma differs slightly from the command potential by $-R_{res}I_e$. As the
axial current at threshold is about 100 pA, this error is smaller than 0.5 mV. 6 cells for which the
reference potential drifted by more than 3 mV during the recordings were discarded from voltage
threshold analyses.

As the current at threshold is small, we used only the recordings with P/n protocol (n = 15) to ensure
accurate leak subtraction. Three additional cells were excluded from the analysis of threshold current
because the recordings were either too noisy or with unstable baseline current. Thus, n= 12 cells were
used. The current traces below threshold were smoothed with a sliding window (half-window size is
50 points, 1 ms) before peak detection (Fig. 5A). The threshold current was then measured as the
largest peak current for the data points between V_t - 1mV and V_t.

Charge and current duration

The charge Q transferred to the soma at spike initiation is estimated as the integral of I_e in the time
window where the current is greater than 10% of its peak value (to avoid integrating noise). Current
duration t_{50} is the duration during which the current is greater than 50% of the peak value.

Adaptation

Relations between V_t and V_0 (Fig. 7A) were fitted to the theoretical formula for threshold adaptation
with sodium channel inactivation (Platkiewicz & Brette, 2011; Fontaine *et al.*, 2014):

663
$$V_t = V_{min} + k_a \log\left(1 + \exp\left(\frac{V - V_i}{k_i}\right)\right)$$

For the current adaptation analysis, cells were discarded if R_s increased by more than 30% during the
protocol. In a few cells, the threshold could not be clearly measured at -40 mV and therefore I_{40} is
missing.

Morphological data analysis

Axon tracing in 3D was performed automatically with Vaa3D (Peng *et al.*, 2010) (version 3.2 64-bit ran
on MacOSX10.13.6) based on biocytin Z-stacks. The start and end position of the axon tracing was
manually chosen by the researcher to include the entire AIS. Axon coordinates (*x*, *y*, *z*, radius) were
stored in SWC files and analyzed with custom Python scripts. Coordinates were interpolated with a
finer spacing corresponding to the pixel size (including in the *z* direction also). Interpolation was
performed with B-splines using Scipy (Virtanen *et al.*, 2020) to evaluate the spline at each pixel
comprised in the axon profile, and coordinates were rounded at the nearest pixel. The ankyrin-G
images were then loaded as a 3D stack to get the fluorescence intensity at the interpolated coordinates
along the axon profile. The intensity profile was smoothed with a sliding mean (half-width 15 pixels).
The AIS start and end position were manually defined using the normalized intensity profile, the 3D
stacks and the maximal intensity projection in Fiji (Schindelin *et al.*, 2012). Several cells for which the
start or end position were considered too unclear to be determined accurately, were discarded from
the analyses, so that morphological measurements were available for n = 14 cells.

Statistics

The box plots display the distribution of data in the following way. The central bar shows the median.
The lower and upper limit of the box shows the first and third quartiles (Q1 and Q3), respectively. The
lower and upper whisker bars show Q1-1.5 IQR (interquartile range, the range between Q1 and Q3)
and Q3 + 1.5 IQR, respectively. The data points outside the whiskers are outliers and indicated by
diamonds marker.

Theory

Axial current at spike initiation

The axial current at spike initiation has been derived previously based on resistive coupling theory
(Hamada *et al.*, 2016):

694
$$I_p = \frac{E_{Na} - V_t}{r_a(\Delta + \delta)}$$

695 with

696
$$\delta = \delta' / \tanh(L/\delta')$$

697
$$\delta' = \sqrt{\frac{d}{4R_i g}}$$

698 where Δ is AIS distance from the soma, *L* is AIS length, *d* is AIS diameter, *g* is Na$^+$ conductance density,
699 R_i is intracellular resistivity and

$$700 \qquad\qquad\qquad\qquad r_a = \frac{4R_i}{\pi d^2}$$

is axial resistance per unit length. The derivation makes the following assumptions: all Na+ channels
are open; channel kinetics are neglected; capacitive and leak currents are considered negligible. These
assumptions all tend to overestimate the axial current, but the approximation is generally good (see
Fig. 4B). When L is much greater than δ' (which was the case in our measurements), $\delta \approx \delta'$ and the
axial current is essentially insensitive to L. Intracellular resistivity has not been measured directly in
the RGC axons. In dendrites of cortical pyramidal cells, it was estimated to be R_i = 70-100 Ω.cm (Stuart
& Spruston, 1998). Modeling studies in RGCs assume somewhat higher values, up to about 150 Ω.cm
(Sheasby & Fohlmeister, 1999; Fohlmeister *et al.*, 2010), but these are based on model optimization.
We chose R_i = 100 Ω.cm (higher values would yield a higher estimate of Na+ channel conductance
density).

The maximum current across all possible AIS geometries can be calculated by setting Δ =0 and $L = \infty$
(AIS of infinite length starting from the soma):

$$713 \qquad\qquad\qquad\qquad I_p^{\max} = \frac{\pi}{2} d^{3/2} \sqrt{\frac{g}{R_i}} (E_{Na} - V_t)$$

714   Therefore, the minimum conductance density necessary to produce an axial current I is:

$$715 \qquad\qquad\qquad g_{\min} \quad = \frac{4R_i I^2}{\pi^2 (E_{Na} - V_t)^2 d_{AIS}^3}$$

Axial current at threshold

718   In a model where the spatial extent of the AIS is neglected (all axonal Na+ channels clustered at a single
719   point), the axial current at threshold is k/R_a, where k is the Boltzmann activation slope of Na+ channels
720   and R_a is the axial resistance between soma and AIS (Brette, 2013). It is possible to calculate this
721   current for an AIS of length L starting from the soma.

722   The axial current at threshold is:

$$723 \qquad\qquad\qquad\qquad I_t = \frac{V'(0)}{r_a}$$

724   where r_a is resistance per unit length. To obtain $V'(0)$, we solve the cable equation in a simple axon
725   model where only the axial current and the Na+ current are considered, as in (Goethals & Brette, 2020).
726   We consider a cylindrical axon of diameter d. The AIS has length L and starts from the somatic end. It
727   has a uniform density of Nav channels. The total Nav conductance is

$$728 \qquad\qquad\qquad\qquad G = g \times \pi dL$$

729   where g is the surface conductance density. We neglect leak and K+ currents, Nav channel inactivation,
730   as well as all time-varying phenomena. The cable equation then becomes:

$$731 \qquad\qquad\qquad \frac{d^2 V}{dx^2} = -\pi d r_a g (E_{Na} - V) e^{(V - V_{1/2})/k}$$

732 where $V_{1/2}$ is the half-activation voltage of Nav channels. The boundary conditions are $V(0) = V_s$
733 (somatic potential) and $V'(L) = 0$ (no axial current flowing towards the distal axon). In units of the AIS
734 length L, this equation reads approximately:

735
$$\frac{d^2V}{d(x/L)^2} = -\pi dr_a gL^2(E_{Na} - V_{1/2})e^{(V-V_{1/2})/k}$$

736 Here the driving force $(E_{Na} - V)$ has been approximated by $(E_{Na} - V_{1/2})$ as in (Brette, 2013). We now
737 write the following change of variables:

738
$$U = (V-V_{1/2})/k + \log(\pi dr_a gL^2(E_{Na} - V_{1/2}))$$

739
$$y = x/L$$

740 and we note $U' = dU/dy$. That is, voltage is in units of k and space is in units of AIS length L. The
741 rescaled cable equation is:

742
$$U'' + e^U = 0$$

743 with the boundary conditions:

744
$$U(0) = U_0 = (V_s-V_{1/2})/k + \log(\pi dr_a gL^2(E_{Na} - V_{1/2}))$$

745
$$U'(1) = 0$$

746 This equation is analytically solvable, with general solution

747
$$U(y) = \log\frac{c_1}{2} - 2\log\left(\cosh\left(\frac{1}{2}\sqrt{c_1(c_2 + y)^2}\right)\right)$$

748 From $U'(1) = 0$, it follows that $c_2 = -1$. We then obtain for the boundary condition at 0:

749
$$U(0) = U_0 = \log\frac{c_1}{2} - 2\log\left(\cosh\left(\frac{\sqrt{c_1}}{2}\right)\right)$$

750 which defines c_1 as an implicit function of U_0. We look for a bifurcation, that is, a value of U_0 when the
751 number of solutions changes. This is obtained by setting the derivative of the right hand-side to 0,
752 which gives:

753
$$\frac{\sqrt{c_1}}{2}\tanh\left(\frac{\sqrt{c_1}}{2}\right) = 1$$

754 The solution can be calculated: $\sqrt{c_1}/2 \approx 1.2$, giving $c_1 \approx 5.8$. We have $V'(0) = \frac{k}{L} U'(0)$ and

755
$$U'(y) = \sqrt{c_1(1 - y)}\tanh\left(\frac{\sqrt{c_1(y - 1)^2}}{2}\right)$$

756 so $U'(0) = 2$ and we obtain:

757
$$I_t = \frac{2k}{r_a L}$$

758 A simple extrapolated formula consistent with the formulae for both point AIS away from the soma
759 and extended AIS starting from the soma is:

$$I_t = \frac{k}{r_a x_{1/2}}$$

where $x_{1/2} = \Delta + L/2$ is the middle position of the AIS, relative to the soma. In simulations, we find
that this is a good approximation (Fig. 12).

Figure 12. *Theoretical estimation of axial current at threshold compared to simulations. The simple model (no*
inactivation, no Kv channels) is simulated with L = 10 μm (dark green dots) and L = 30 μm (light green dots),
and the start position is varied from 0 to 20 μm. The theoretical curve is shown as a dashed line.

Axial current near threshold

We calculate the axial current just below threshold as a function of somatic voltage in a point AIS
model. We consider a cylindrical axon of diameter *d* where all the Nav channels are located at a single
location. The AIS contains a total Na⁺ conductance *G*. The axial current is

$$I = \frac{V - V_s}{R}$$

773 where *V* is the axonal voltage, V_s is the somatic voltage, and *R* is the axial resistance between the soma
774 and the AIS. It must equal the Na⁺ current:

$$I_{Na} = G(E_{Na} - V)\exp\left(\frac{V - V_{\frac{1}{2}}}{k}\right)$$

776 which is the exponential approximation near threshold. Near threshold, we have $(E_{Na} - V) \approx$
777 $(E_{Na} - V_s)$. We consider this driving force as a constant ΔV. We then absorb $V_{1/2}$ into *G* and take *k* as
778 the units of voltage. Thus, the equation reads:

$$I = I_{Na} = G\Delta V e^V$$

780 Using $V = V_s + RI$, we obtain:

$$I = G\Delta V \exp(V_s + RI)$$

782 At the bifurcation (threshold), we have (differentiation with respect to *I*):

783
$$1 = GR\Delta V \exp(V_s^* + RI^*)$$

784 where V_s^* is the somatic voltage threshold and I^* is the axial current at threshold. We divide the two
785 previous equations and obtain:

786
$$I = \frac{1}{R} \exp(V_s - V_s^* + RI - RI^*)$$

787 In a point AIS, the axial current at threshold is:

788
$$I^* = 1/R$$

789 Therefore:

790
$$I = I^* \exp\left(V_s - V_s^* + \frac{I}{I^*} - 1\right)$$

791 This can be rewritten as:

792
$$V_s = V_s^* + 1 - \frac{I}{I^*} + \log\frac{I}{I^*}$$

793 A Taylor expansion gives:

794
$$V_s \approx V_s^* - \frac{1}{2}\left(1 - \frac{I}{I^*}\right)^2$$

795 In original voltage units, we then obtain:

796
$$V_s \approx V_s^* - \frac{k}{2}\left(1 - \frac{I}{I^*}\right)^2$$

Relation between voltage threshold and axial current at spike initiation

Theoretically, voltage threshold varies as $-k\log g$, where g is the available Na+ conductance
(Platkiewicz & Brette, 2011; Brette, 2013; Goethals & Brette, 2020). The axial current at spike initiation
also depends on g, and therefore voltage threshold and axial current co-vary when g is varied. The
general relation is complicated, but a simple approximated relation can be obtained by considering the
equation for the maximum current $I_p^{\max}$. Since $I_p^{\max} \propto \sqrt{g}$, it follows that with this approximation the
threshold varies as $-k\log I_p^2$, i.e., as $-2k\log I_p$.

Simplified model

In Fig. 4A-B and Fig. 12, we used a simplified model with only non-inactivating Nav channels to check
analytical expressions, similar to Brette (2013). A spherical soma of diameter 30 μm is attached to an
axonal cylinder of diameter 1 μm and length 500 μm (soma diameter is in fact irrelevant as the soma
is voltage-clamped). Specific membrane capacitance is $C_m = 0.9$ μF/cm²; specific membrane resistance
is $R_m = 15\,000$ Ω.cm²; leak reversal potential is $E_L = -75$ mV; intracellular resistivity is $R_i = 100$ Ω.cm. If
not specified, Nav channels are placed from 5 μm to 35 μm on the axon. In Fig. 12, the length ranges
from 10 μm to 30 μm and the start position from 0 μm to 20 μm. We used simple single gate activation
dynamics with fixed time constant:

$$I_{Na} = Gm(E_{Na} - V)$$

$$\tau_m \cdot \frac{dm}{dt} = m_\infty(V) - m$$

$$m_\infty(V) = \frac{1}{1 + \exp((V_{1/2} - V)/k)}$$

where E_{Na} = 70 mV, k = 5 mV, $V_{1/2}$ = -35 mV and τ_m = 53.6 μs (corresponding to 150 μs before
temperature correction, see (Goethals & Brette, 2020)). For Fig. 4A and B, Na⁺ conductance density
was g = 5000 S/m². For Fig. 12, the total Na⁺ conductance was fixed (G = 350 nS) to keep the total
number of Na⁺ channels fixed when AIS length is varied. This corresponds to conductance densities of
about 11 100 and 3700 S/m² for a 10 and 30 μm long AIS, respectively. The model is simulated in
voltage-clamp and the threshold is measured with the bisection method. We used the Brian 2 simulator
(Stimberg *et al.*, 2019) with 10 μs time step and 1 μm spatial resolution.

Biophysical model

In Fig. 5B, 5D, 6E, 11C and 11D, we used a biophysical model of an AP with inactivating Nav channels
and non-inactivating Kv channels, similar to (Goethals & Brette, 2020). The biophysical model has a
simple geometry, consisting of a spherical soma (30 μm diameter), a long dendrite (diameter: 6 μm,
length: 1000 μm) and a thin unmyelinated axon (diameter: 1 μm, length; 500 μm). The dendrite is
irrelevant to most simulations because the soma is voltage-clamped, electrically isolating the dendrites
from the axon. It only contributes an additional somatodendritic capacitance when an electrode model
is added (Fig. 2). When not specified, the AIS extends from 5 μm to 35 μm from the soma. Specific
membrane capacitance is C_m = 0.9 μF/cm²; specific membrane resistance is R_m = 15 000 Ω.cm²; leak
reversal potential is E_L = -75 mV; intracellular resistivity is R_i = 100 Ω.cm.

In Fig. 5B and 5D, the AIS start position was 10 μm, close to the mean AIS start position in our cell
population. The threshold was approached with 0.01 mV precision using the bisection method. In Fig.
6E, the AIS start position was varied from 0 to 20 μm and the AIS length was 30 μm. In these three
panels, the Na⁺ conductance density was g = 3700 S/m².

In Fig. 11C-D, we inserted an electrode model, which consists of a resistance R_s (0 to 5 M Ω) between
the amplifier and the soma, such that a current $(V_c-V)/R_s$ is injected into the soma (where V_c is the
voltage command). The Na⁺ conductance density g was 7400 S/m², to obtain peak axonal currents and
thresholds comparable to measurements in RGCs.

Passive properties	R_m	15 000 Ω.cm²
	E_L	-75 mV
	R_i	100 Ω.cm
	C_m	0.9 μF/cm²
Nav channels	g_{Na}, soma	250 S/m²
	g_{Na}, dendrite and axon (non AIS)	50 S/m²
	g_{Na}, AIS	variable (3500-7400 S/m²)
	E_{Na}	70 mV
	$V_m^{1/2}$, soma	-30 mV
	$V_h^{1/2}$, soma	-60 mV
	$V_m^{1/2}$, AIS	-35 mV
	$V_h^{1/2}$, AIS	-65 mV
	k_m	5 mV

	k_h	5 mV
	τ_m^*	150 µs (corrected: 54 µs)
	τ_h^*	5 ms (corrected: 1.8 ms)
Kv1 channels	g_K, soma and dendrite	100 S/m²
	g_K, AIS	1500 S/m²
	E_K	-90 mV
	$V_n^{1/2}$	-70 mV
	k_n	20 mV
	τ_n^*	1 ms

Table 1. Parameters values of the biophysical model. Time constants corrected for temperature are indicated in brackets.

Acknowledgments

We thank Marcel Stimberg for assistance with simulations, Elaine Orendorff for assistance with immunochemistry, Stéphane Fouquet for advice and assistance with confocal microscopy, Serge Picaud for access to the electrophysiology setup, and Boris Barbour and Christophe Leterrier for discussions.

Funding information

This work was supported by a grant from Agence Nationale de la Recherche (ANR-14-CE13-0003) to R.B., by a grant from UNADEV (17UU1166-00) to X.N., and by the Programme Investissements d'Avenir IHU FOReSIGHT (ANR-18-IAHU-01). S.G. is supported by the Ecole des Neurosciences de Paris.

Competing interests

The authors have no competing interests to declare.

References

Angelino E & Brenner MP (2007). Excitability constraints on voltage-gated sodium channels. *PLoS Comput Biol* **3,** 1751–1760.

Azouz R & Gray C (2000). Dynamic spike threshold reveals a mechanism for synaptic coincidence detection in cortical neurons in vivo. *PNAS* **97,** 8110.

Baranauskas G, David Y & Fleidervish IA (2013). Spatial mismatch between the Na+ flux and spike initiation in axon initial segment. *PNAS* **110,** 4051–4056.

Baranauskas G & Martina M (2006). Sodium Currents Activate without a Hodgkin and Huxley-Type Delay in Central Mammalian Neurons. *J Neurosci* **26,** 671–684.

Barrett JN & Crill WE (1980). Voltage clamp of cat motoneurone somata: properties of the fast inward current. *The Journal of Physiology* **304,** 231–249.

Bender KJ & Trussell LO (2012). The Physiology of the Axon Initial Segment. *Annual Review of Neuroscience* **35,** 249–265.

872   Boiko T, Van Wart A, Caldwell JH, Levinson SR, Trimmer JS & Matthews G (2003). Functional
873   specialization of the axon initial segment by isoform-specific sodium channel targeting. *J
874   Neurosci* **23,** 2306–2313.

875   Brette R (2013). Sharpness of Spike Initiation in Neurons Explained by Compartmentalization. *PLoS
876   Comput Biol* **9,** e1003338.

877   Caporale N & Dan Y (2008). Spike Timing–Dependent Plasticity: A Hebbian Learning Rule. *Annu Rev
878   Neurosci* **31,** 25–46.

879   Colbert CM & Pan E (2002). Ion channel properties underlying axonal action potential initiation in
880   pyramidal neurons. *Nat Neurosci* **5,** 533–538.

881   Coombs JS, Curtis DR & Eccles JC (1957). The interpretation of spike potentials of motoneurones. *J
882   Physiol* **139,** 198–231.

883   Daoudal G & Debanne D (2003). Long-term plasticity of intrinsic excitability: learning rules and
884   mechanisms. *Learn Mem* **10,** 456–465.

885   Debanne D, Campanac E, Bialowas A, Carlier E & Alcaraz G (2011). Axon Physiology. *Physiol Rev* **91,**
886   555–602.

887   Diwakar S, Magistretti J, Goldfarb M, Naldi G & D'Angelo E (2009). Axonal Na+ Channels Ensure Fast
888   Spike Activation and Back-Propagation in Cerebellar Granule Cells. *Journal of Neurophysiology*
889   **101,** 519–532.

890   Evans MD, Dumitrescu AS, Kruijssen DLH, Taylor SE & Grubb MS (2015). Rapid Modulation of Axon
891   Initial Segment Length Influences Repetitive Spike Firing. *Cell Reports* **13,** 1233–1245.

892   Evans MD, Sammons RP, Lebron S, Dumitrescu AS, Watkins TBK, Uebele VN, Renger JJ & Grubb MS
893   (2013). Calcineurin Signaling Mediates Activity-Dependent Relocation of the Axon Initial
894   Segment. *J Neurosci* **33,** 6950–6963.

895   Fatt P (1957). Sequence of events in synaptic activation of a motoneurone. *J Neurophysiol* **20,** 61–80.

896   Fleidervish IA, Lasser-Ross N, Gutnick MJ & Ross WN (2010). Na+ imaging reveals little difference in
897   action potential-evoked Na+ influx between axon and soma. *Nat Neurosci* **13,** 852–860.

898   Fohlmeister JF, Cohen ED & Newman EA (2010). Mechanisms and Distribution of Ion Channels in
899   Retinal Ganglion Cells: Using Temperature as an Independent Variable. *Journal of
900   Neurophysiology* **103,** 1357–1374.

901   Fontaine B, Pena JL & Brette R (2014). Spike-threshold adaptation predicted by membrane potential
902   dynamics in vivo. *PLoS Comput Biol* **10,** e1003560.

903   Galiano MR, Jha S, Ho TS-Y, Zhang C, Ogawa Y, Chang K-J, Stankewich MC, Mohler PJ & Rasband MN
904   (2012). A Distal Axonal Cytoskeleton Forms an Intra-Axonal Boundary that Controls Axon
905   Initial Segment Assembly. *Cell* **149,** 1125–1139.

906   Goethals S & Brette R (2020). Theoretical relation between axon initial segment geometry and
907   excitability ed. Skinner FK, Calabrese RL, Skinner FK & Nadim F. *eLife* **9,** e53432.

908   Grubb MS & Burrone J (2010). Activity-dependent relocation of the axon initial segment fine-tunes
909   neuronal excitability. *Nature* **465,** 1070–1074.

910   Grubb MS, Shu Y, Kuba H, Rasband MN, Wimmer VC & Bender KJ (2011). Short- and Long-Term
911   Plasticity at the Axon Initial Segment. *J Neurosci* **31,** 16049–16055.

Guo T, Tsai D, Morley JW, Suaning GJ, Lovell NH & Dokos S (2013). Cell-specific modeling of retinal
ganglion cell electrical activity. In *2013 35th Annual International Conference of the IEEE
Engineering in Medicine and Biology Society (EMBC)*, pp. 6539–6542.

Gutzmann A, Ergül N, Grossmann R, Schultz C, Wahle P & Engelhardt M (2014). A period of structural
plasticity at the axon initial segment in developing visual cortex. *Front Neuroanat*; DOI:
10.3389/fnana.2014.00011.

Hamada MS, Goethals S, de Vries SI, Brette R & Kole MHP (2016). Covariation of axon initial segment
location and dendritic tree normalizes the somatic action potential. *Proc Natl Acad Sci USA*
113, 14841–14846.

Hille B (2001). *Ion Channels of Excitable Membranes*. Sinauer Associates.

Hodgkin AL & Huxley AF (1952). Currents carried by sodium and potassium ions through the
membrane of the giant axon of Loligo. *J Physiol* **116,** 449–472.

Höfflin F, Jack A, Riedel C, Mack-Bucher J, Roos J, Corcelli C, Schultz C, Wahle P & Engelhardt M (2017).
Heterogeneity of the Axon Initial Segment in Interneurons and Pyramidal Cells of Rodent
Visual Cortex. *Front Cell Neurosci* **11,** 332.

Hu W, Tian C, Li T, Yang M, Hou H & Shu Y (2009). Distinct contributions of Na(v)1.6 and Na(v)1.2 in
action potential initiation and backpropagation. *Nat Neurosci* **12,** 996–1002.

Jamann N, Dannehl D, Wagener R, Corcelli C, Schultz C, Staiger J, Kole MHP & Engelhardt M (2020).
Sensory input drives rapid homeostatic scaling of the axon initial segment in mouse barrel
cortex. *bioRxiv*2020.02.27.968065.

Jamann N, Jordan M & Engelhardt M (2017). Activity-dependent axonal plasticity in sensory systems.
Neuroscience; DOI: 10.1016/j.neuroscience.2017.07.035.

Kole MH & Brette R (2018). The electrical significance of axon location diversity. *Curr Opin Neurobiol*
51, 52–59.

Kole MHP, Ilschner SU, Kampa BM, Williams SR, Ruben PC & Stuart GJ (2008). Action potential
generation requires a high sodium channel density in the axon initial segment. *Nat Neurosci*
11, 178–186.

Kole MHP, Letzkus JJ & Stuart GJ (2007). Axon initial segment Kv1 channels control axonal action
potential waveform and synaptic efficacy. *Neuron* **55,** 633–647.

Kole MHP & Stuart GJ (2008). Is action potential threshold lowest in the axon? *Nat Neurosci* **11,** 1253–
1255.

Kuba H (2012). Structural tuning and plasticity of the axon initial segment in auditory neurons. *J
Physiol (Lond)* **590,** 5571–5579.

Kuba H, Adachi R & Ohmori H (2014). Activity-Dependent and Activity-Independent Development of
the Axon Initial Segment. *J Neurosci* **34,** 3443–3453.

Kuba H, Ishii TM & Ohmori H (2006). Axonal site of spike initiation enhances auditory coincidence
detection. *Nature* **444,** 1069–1072.

Kuba H, Oichi Y & Ohmori H (2010). Presynaptic activity regulates Na+ channel distribution at the axon
initial segment. *Nature* **465,** 1075–1078.

Lorincz A & Nusser Z (2010). Molecular Identity of Dendritic Voltage-Gated Sodium Channels. *Science*
328, 906–909.

Magistretti J, Castelli L, Forti L & D'Angelo E (2006). Kinetic and functional analysis of transient,
persistent and resurgent sodium currents in rat cerebellar granule cells in situ: an
electrophysiological and modelling study. *J Physiol* **573,** 83–106.

Milescu LS, Bean BP & Smith JC (2010). Isolation of Somatic Na+ Currents by Selective Inactivation of
Axonal Channels with a Voltage Prepulse. *J Neurosci* **30,** 7740–7748.

Mitra P & Miller RF (2007). Mechanism underlying rebound excitation in retinal ganglion cells. *Visual*
Neuroscience **24,** 709–731.

Naundorf B, Wolf F & Volgushev M (2006). Unique features of action potential initiation in cortical
neurons. *Nature* **440,** 1060–1063.

Peng H, Ruan Z, Long F, Simpson JH & Myers EW (2010). V3D enables real-time 3D visualization and
quantitative analysis of large-scale biological image data sets. *Nature Biotechnology* **28,** 348–
353.

Platkiewicz J & Brette R (2010). A threshold equation for action potential initiation. *PLoS Comput Biol*
6, e1000850.

Platkiewicz J & Brette R (2011). Impact of fast sodium channel inactivation on spike threshold
dynamics and synaptic integration. *PLoS Comput Biol* **7,** e1001129.

Raghuram V, Werginz P & Fried SI (2019). Scaling of the AIS and Somatodendritic Compartments in α
S RGCs. *Front Cell Neurosci*; DOI: 10.3389/fncel.2019.00436.

Schindelin J, Arganda-Carreras I, Frise E, Kaynig V, Longair M, Pietzsch T, Preibisch S, Rueden C,
Saalfeld S, Schmid B, Tinevez J-Y, White DJ, Hartenstein V, Eliceiri K, Tomancak P & Cardona A
(2012). Fiji: an open-source platform for biological-image analysis. *Nature Methods* **9,** 676–
682.

Scott LL, Hage TA & Golding NL (2007). Weak action potential backpropagation is associated with high-
frequency axonal firing capability in principal neurons of the gerbil medial superior olive. *The*
Journal of Physiology **583,** 647–661.

Sheasby BW & Fohlmeister JF (1999). Impulse Encoding Across the Dendritic Morphologies of Retinal
Ganglion Cells. *Journal of Neurophysiology* **81,** 1685–1698.

Stimberg M, Brette R & Goodman DF (2019). Brian 2, an intuitive and efficient neural simulator ed.
Skinner FK. *eLife* **8,** e47314.

Stuart G & Spruston N (1998). Determinants of voltage attenuation in neocortical pyramidal neuron
dendrites. *J Neurosci* **18,** 3501–3510.

Traynelis SF (1998). Software-based correction of single compartment series resistance errors.
Journal of Neuroscience Methods **86,** 25–34.

Van Wart A, Trimmer JS & Matthews G (2007). Polarized distribution of ion channels within
microdomains of the axon initial segment. *J Comp Neurol* **500,** 339–352.

Virtanen P et al. (2020). SciPy 1.0: fundamental algorithms for scientific computing in Python. *Nature*
Methods **17,** 261–272.