Delta- and theta-band cortical tracking and phase-amplitude coupling to sung speech by infants

Adam Attaheri*, Áine Ní Choisdealbha, Giovanni M. Di Liberto, Sinead Rocha, Perrine Brusini, Natasha Mead, Helen Olawole-Scott, Panagiotis Boutris, Samuel Gibbon, Isabel Williams, Christina Grey, Sheila Flanagan & Usha Goswami

Keywords: EEG, Language, Neural Oscillations, TRF, Infant

1 Significance

We report the first longitudinal infant EEG study of speech envelope tracking. Here we demonstrate for the first time that delta and theta oscillatory networks in the infant brain show developmental differences in the cortical tracking of speech. We provide the first evidence for phase amplitude coupling (PAC) in response to speech by the infant brain.

Our data indicate important differences compared to prior adult studies, with a significant role for delta-band tracking and delta-driven PAC. Accordingly, the relative weighting of speech encoding mechanisms as revealed by adult neuroimaging studies, where theta-band tracking is emphasized, may not show fundamental age-independent neural mechanisms regarding speech processing. Adult studies may reflect the end state of a system that functions differently earlier in development.

2 Abstract

The amplitude envelope of speech carries crucial low-frequency acoustic information that assists linguistic decoding at multiple time scales. Neurophysiological signals are known to track

the amplitude envelope of adult-directed speech (ADS), particularly in the theta-band. Acoustic analysis of infant-directed speech (IDS) has revealed significantly greater modulation energy than ADS in an amplitude-modulation (AM) band centered on ~2 Hz. Accordingly, cortical tracking of IDS by delta-band neural signals may be foregrounded in infancy, and may be key to language acquisition. Speech also contains acoustic information within its higher-frequency bands (beta, gamma). Adult EEG and MEG studies reveal an oscillatory hierarchy, whereby low-frequency (delta, theta) neural phase dynamics temporally organize the amplitude of high-frequency signals (phase amplitude coupling, PAC). Whilst consensus is growing around the role of PAC in the matured adult brain, its role in the *development* of speech processing is unexplored.

Here, we examined the presence and maturation of low-frequency (<12Hz) cortical speech tracking in infants by recording EEG longitudinally from 60 participants when aged 4-, 7- and 11- months as they listened to nursery rhymes. After establishing stimulus-induced neural signals in delta and theta, cortical tracking at each age was assessed in the delta, theta and alpha [control] bands using a multivariate temporal response function (mTRF) method. Delta-beta, delta-gamma, theta-beta and theta-gamma phase-amplitude coupling (PAC) was also assessed. Significant delta and theta but not alpha tracking was found, the earliest such demonstration for speech. Significant PAC was present at all ages, with stronger delta-driven coupling observed, as hypothesised.

3 Introduction

Neural signals synchronise to the auditory envelope during speech listening. This cortical tracking phenomenon has an important functional role for speech comprehension in adults (1, 2).

The speech envelope is the low-frequency amplitude modulation that carries crucial acoustic information required for perceptual encoding and linguistic decoding at multiple temporal scales. Theorists in speech perception have argued for special roles for syllable-level acoustic rhythmic information (slower temporal modulations centred on ~5 Hz) and phoneme-level acoustic information (rapid temporal modulations centred on ~ 40 Hz) (3). It is proposed that intrinsic neural signals in cortex at matching frequencies (theta, 4-8 Hz; low gamma, 30-50 Hz) provide one mechanism for encoding this acoustic information, parsing speech signals into temporal chunks or windows for subsequent analysis and comprehension (multiple time resolution (2)). Low-frequency (delta, theta) phase and high-frequency (gamma) amplitudes also track acoustic rhythms in the speech signal by operating together as an integrated representational mechanism via phase-amplitude coupling, PAC (4–6), where the phase dynamics of low-frequency neural signals temporally organize the amplitude of high-frequency signals (7–9). Adult studies have demonstrated the functional importance of PAC for speech encoding, with delta and theta phase coupling with gamma amplitude during stimulus-specific speech sampling (4). The role of cortical tracking for speech intelligibility has also been demonstrated by intra-cranial measurements in adult patients using electrocorticography (ECoG) (10–12). Studies measuring adult cortical tracking of unintelligible speech report reduced tracking compared to intelligible speech (13–16). However, to date almost all available studies of PAC and cortical tracking at different frequencies rely on adult neural imaging, indicating a reasonable degree of consensus concerning neural mechanisms, with a core role established for theta tracking (17, 18).

While theta tracking may be a core feature of adult speech encoding, it is important to remember that the adult participants in neural studies are highly literate. It is well-established by developmental studies that learning to read changes the brain (19). Accordingly, investigators

may be studying the end state of development rather than fundamental mechanisms for speech processing which are present from birth. Studies of children suggest that the weighting of different speech encoding mechanisms may change with development (Goswami, 2018, for review). For example, data from children with developmental dyslexia show core cognitive impairments in processing phonological (speech-sound) information, and associated atypical neural synchronisation to, and tracking of, speech input in the *delta band*, not in the theta band (15, 16, 20–22). Regarding degraded speech, typically-developing children show delta-band tracking of speech-in-noise, but not efficient theta-band tracking (23).

In adult studies, delta-band tracking is frequently thought to be related to auditory attentional mechanisms linked to the processing of sequential attributes of speech sounds, for example grouping (24). However, there is an alternative developmental linguistic analysis regarding delta-band tracking (25). Cross-language linguistic data show that strong syllables are produced approximately twice per second (2 Hz) in all languages, both stress-timed and syllable-timed (26). Strong (stressed) syllables may provide a set of acoustic landmarks at a delta-band rate with which the infant brain can begin to represent the acoustic structure of human speech. Even newborn infants can discriminate languages from different rhythm classes (stress timed [e.g. English], syllable timed [e.g. French] or mora timed [Japanese]) (27). Rhythm perception has thus been described in the cognitive literature as a language-universal precursor to language acquisition (28). Accordingly, delta-band cortical tracking may play a fundamental role in language acquisition, particularly regarding the acquisition of phonology (29). Further, the role of PAC in the *development* of speech processing by children and infants is not yet explored.

There are two previous infant language-based cortical tracking studies of speech, both with 7 month-old infants (30, 31). These prior studies tested English-learning participants and

adopted a forward linear modelling approach (detailed methods; 37) to estimate how well the amplitude envelope of IDS was represented in the cortical activity. Both studies reported significant cortical tracking, however neither study was able to address the potential developmental roles of delta- versus theta-band tracking regarding language processing, nor examine possible developmental changes for delta versus theta tracking. To date, there are two PAC studies in infants. Both have focused on clinical applications, specifically the role of PAC in functional connectivity (32, 33). For example, one study measuring PAC in sleeping newborns during active versus quiet sleep reported hierarchical nesting of oscillations in both sleep states (32). Accordingly, current data suggests that PAC mechanisms in the infant brain may be online at birth. However, no study to date has looked at the functional relevance of infant PAC when processing sensory stimuli, leaving PAC during language processing yet to be explored.

Here we assess infant cortical tracking of the temporal modulation information in IDS present in both delta- and theta-rate AM bands. We analysed cortical tracking of nursery rhymes, originally recorded being sung or chanted to an alert infant. Although the center frequencies of canonical EEG bands may shift during infancy (34, 35), the delta band is relatively stable, and there is no consensus on the exact boundaries of different EEG bands at specific time points in development (35). There are also no infant data from studies utilizing speech stimuli. Accordingly, the EEG delta and theta bands were defined following the prior speech processing literature (delta, 0.5-4 Hz; theta, 4-8 Hz). These bands have also been identified by modelling the temporal modulation architecture of IDS (36). Leong et al. theorised that the amplitude envelope of spoken IDS contains a nested oscillatory hierarchy of amplitude modulations (AMs) in three temporal bands, corresponding to the timing of delta, theta and beta/low gamma cortical neural signals. Furthermore, they demonstrated that the low-frequency AM bands in IDS showed

different degrees of coupling with each other compared to adult-directed speech (ADS). IDS both had significantly more modulation energy in the delta band than ADS (which had significantly more modulation energy in the theta band), and significantly greater phase synchronisation between the delta-rate and theta-rate bands of AM than ADS. Based on this computational modelling (36), we therefore hypothesised that delta neural signals would track the speech envelope most strongly early in infant development. We also tentatively hypothesised that theta tracking may come online later. In child studies of cortical tracking, the strength of theta entrainment has been related to reading ability (21).

64-channel EEG was recorded from a sample of 60 infants as they watched and listened passively to a video of nursery rhymes being sung or rhythmically chanted by a female "talking head". The video lasted approximately 20 minutes (see Figure 2a), and was followed by a resting "silent state" recording. Prominent modulation spectrum peaks were identifiable in the nursery rhyme stimuli at rates corresponding to adult delta and theta neural signals (Supplementary Figures S2 and S3). The neural data presented here were recorded from the first half of infants recruited to an ongoing longitudinal study of 122 infants, who listened to nursery rhymes at the ages of 4-, 7- and 11-months. Data collection with the other infants is still ongoing. Our approach allows for subsequent confirmatory testing of the current results with the second half of the sample.

Multivariate temporal response functions (mTRFs) were employed to measure cortical tracking (37). mTRFs are encoding models that describe how the inputs and outputs of a system are linearly related. Forward models provide researchers with information regarding the precise spatial and temporal patterns reflecting the neural processing of a stimulus, as used previously with infants (30, 31). A backward 'stimulus reconstruction' version of the TRF linear modelling

technique, not yet used with infants, was employed here. The backward mTRF uses information from all EEG channels simultaneously to reconstruct the speech envelope, thereby enabling increased sensitivity to signal differences between highly correlated response channels. This provides a single summary measure of speech-EEG coupling for data recorded over long periods of time by assessing the fidelity of the reconstruction (37). Here, we reconstructed the heard speech in the delta and theta bands, using stimulus reconstruction in the alpha band as a control condition. Although alpha band responses may be important in adult speech tracking (38–40), alpha-band AMs did not play a role in the prior computational modelling of IDS (36). Accordingly, we do not predict significant cortical tracking in the alpha band for the infant brain. Finally, we hypothesised that low-frequency oscillatory phase, specifically within the delta band, would couple with high-frequency amplitudes in the infant brain during speech processing. On the developmental hypothesis that delta neural signals would track the speech envelope most strongly early in infant development, we predicted that delta-driven PAC should emerge prior to theta-driven PAC. If individual differences in sensory processing drive cognitive development rather than individual differences in brain mechanisms (41), the basic neural mechanisms for speech encoding should be present at birth.

4 Results:

4.1 Both delta and theta EEG frequency bands respond to nursery rhymes

Prior to investigating cortical tracking and PAC, the distribution of low-frequency neural signals within our data was established using spectral decomposition of the signal, achieved using the periodogram power spectral density (PSD) estimate. After preprocessing, PSD was obtained for each of the remaining 60 electrodes in response to audio-visually presented nursery

rhymes and during a five minute period of silence. A grand average across channels and ages revealed two frequency peaks centered around 2.18Hz and 4.4 Hz for the nursery rhyme period (Supplementary Figure S1). These peak responses corresponded to the frequency peaks found in the acoustic envelope of the nursery rhymes (Supplementary Figures S2 and S3). Separating the data by age revealed 2.18Hz PSD peaks were consistently present at 4-, 7- and 11-months (Figure 1), whereas, the mean values of the 4.40 Hz peaks displayed an age-related increase in PSD.

Figure 1, Spectral decomposition of the EEG signal (0.5-12 Hz) in response to nursery rhyme stimulation. A periodogram was used to obtain a power spectral density (PSD) estimate separately for 4- (red), 7- (green) and 11- (blue) months data. Bold lines indicate the mean values and pale shading plots the standard deviation of the data. Outlier analysis was also conducted to remove extreme data points that would compromise the LMEM (detailed rejection criteria given

in methods). The data plotted included, N=44 4-month, N=47 7-month and N=50 11-month old infants.

To investigate whether the PSD was significantly higher in response to the nursery rhymes compared to the silent state, and whether this relationship was affected by the age of the participants, a linear mixed effects model (LMEM) was conducted separately for the 2.18Hz and 4.40 Hz frequency peaks (see methods). The average PSD across all 60 electrodes was used, with the peak value submitted to the model for each participant. Fixed effects of recording type (nursery rhyme stimulus period, silent state), age (4-, 7- or 11-months) and a recording type by age interaction were included in the model. Silent state data and 11-months data were set as the respective base cases for each effect in the model. Individual differences across the 3 recording sessions (at 4-, 7- and 11-months) were accounted for by including a random intercept (AR1) per participant.

For the 2.18Hz peak, tests of fixed effects revealed that recording type had a significant effect ($F(1, 98.560) = 15.513$, $P = 1.53\text{x}10^{-4}$) on PSD, as the ~2Hz PSD increased significantly during the stimulus period ($M = 29.782$, $SE \pm 1.670$) vs the silent state ($M=23.832$, $SE \pm1.751$). Neither age ($F(2, 137.925) = 2.780$, $P = 0.066$) nor age by recording type ($F(2, 98.427) = 0.045$, $P = 0.956$) showed an effect on PSD. Accordingly, the stimulus effect present at 11-months is also present at 4- and 7-months (see Table 1a).

For the 4.40Hz peak, recording type again showed a significant effect ($F(1, 154.963) = 5.560$, $P = 0.020$) on PSD, increasing during the stimulus period ($M = 21.428$, $SE \pm 2.180$) vs silent state ($M=15.111$, $SE \pm 2.341$). Furthermore, both age ($F(2, 201.747) = 6.406$, $P = 0.002$) and age by recording type ($F(2, 154.883) = 4.005$, $P = 0.020$) exerted a significant effect on PSD. Exploration of the estimates of fixed effects showed that the significant interaction between

recording type by age was driven by a greater effect at 11-months (Table 1b). Bonferroni-corrected pairwise comparisons showed that PSD increased significantly between 4- and 11-months (*M* increase = 12.869, *SE* ± 3.793, *P* = 0.002) and 7- and 11-months (*M increase* = 9.902, *SE* ± 3.783, *P* = 0.029). Hence regardless of recording type, there was a developmental increase in 4.40Hz PSD. This may indicate age-related maturation of theta activity. Importantly, we also observed a stimulus-driven interaction with age for the 4.40Hz PSD peaks, with the largest increase observed at 11-months (silent state, *M* = 17.404, *SE* ± 3.909; nursery rhymes, *M* = 34.316, *SE* ± 3.437).

a, 2.18Hz

	β	SE_b	df	t	P	95% CI
Recording type (stim. rel. to silent)	6.580	2.607	98.912	2.524	.013	[1.407 11.752]
Age 4mo (rel. 11mo)	-5.769	3.459	233.264	-1.668	.097	[-12.584 1.045]
Age 7mo (rel. 11mo)	-2.976	3.472	179.022	-.857	.392	[-9.828 3.876]
Recording type * 4mo (rel. 11mo)	-1.077	3.795	100.233	-.284	.777	[-8.599 6.446]
Recording type * 7mo (rel. 11mo)	-.812	3.599	96.824	-.226	.822	[-7.956 6.332]

b, 4.40Hz

	β	SE_b	df	t	P	95% CI
Recording type (stim. rel. to silent)	16.913	4.615	157.232	3.665	3.38×10^{-4}	[7.797 26.028]
Age 4mo (rel. 11mo)	-4.037	5.364	238.194	-.753	.452	[-14.606 6.531]
Age 7mo (rel. 11mo)	-2.840	5.137	241.386	-.553	.581	[-12.959 7.280]
Recording type * 4mo (rel. to 11mo)	-17.664	6.710	156.221	-2.633	.009	[-30.918 -4.410]
Recording type * 7mo (rel. to 11mo)	-14.125	6.392	154.641	-2.210	.029	[-26.752 -1.497]

Table 1, Parameter information detailing estimates of fixed effects on periodogram PSD peaks at a, 2.18Hz and b, PSD peaks at 4.40Hz, taken from the LMEM described in the text. The base cases for the LMEM were set as 11-months for age and silent state for recording type.

The data indicate that the nursery rhymes induced a ~2Hz PSD response as early as 4-months of age whereas the nursery rhyme-induced ~4Hz response developed between 4- and 11-months.

4.2 Delta and theta EEG frequency bands track nursery rhyme envelopes

Power spectral density (PSD) analysis confirmed that the nursery rhyme stimuli induced power in the delta (~2.18 Hz) and theta (~4.40Hz) bands. To investigate the presence and strength of cortical tracking, backward mTRFs (Figure 2a) (37) were trained with either delta (0.5-4 Hz), theta (4-8Hz) or alpha (8-12 Hz) EEG signals. The quality of the stimulus reconstruction was then compared to randomly permuted data. The decoding model was fit separately to the Hilbert envelope of each of the 83 nursery rhyme trials for each participant, using a leave-one-out cross-validation procedure (see methods). Pearson's correlation (r) was used to test the quality of the reconstruction (Figure 2b). This provided an objective metric of envelope tracking at the individual level. To test the correlation (r) values against chance, random permutation statistics were created for each participant (N = 100 permutations).

Figure 2, mTRF stimulus reconstruction. a) Schematic of the experimental procedure along with a summary of the mTRF analysis pipeline. The EEG signal and the stimulus envelope (absolute value of the Hilbert envelope) were submitted to the mTRF stimulus reconstruction. For the cross validation procedure, 83 nursery rhyme trials were rotated M-1 times each serving once as the "test set" with the remainder of the trials being the "training set". The process was repeated at 12 ridge regressions (λ values, 1×10^{-3}:1×10^{8}) with the average model convolved with the test data to reconstruct the stimulus envelope at the optimal λ. b) Example of one of the 83 mTRF stimulus reconstructions for one participant along with the original acoustic stimulus envelope. . The black line depicts the reconstruction (in arbitrary units) and the orange line illustrating the absolute value of the Hilbert envelope of the stimulus (in arbitrary units).

The reconstruction analyses showed that cortical delta and theta neural signals significantly tracked the envelopes of the nursery rhyme stimuli, but alpha signals did not (Figure 3).

A LMEM was conducted to investigate potential developmental changes. Main effects of data type (real r values, random permutation r values), frequency band (delta, theta or alpha) and age (4-, 7- or 11-months) were investigated along with interactions between data type by frequency band, data type by age and age by frequency band. Random permutation r values, alpha frequency band and 11-month data were set as the respective base cases for each variable in the model. A random intercept (AR1) per participant was included to account for individual differences across the 3 recording sessions (4-, 7- and 11-months).

Tests of fixed effects showed a significant effect of data type ($F(1, 901.802) = 118.656$, $P = 4.806 \times 10^{-26}$), as the real data values were significantly higher than the random permutation values (Figure 3). A significant effect of frequency band ($F(2,903.216) = 401.939$, $P = 1.399$

x10^{-125}) highlighted that cortical tracking (r values) differed by frequency band, with the estimates of fixed effects confirming greater tracking in both delta and theta bands compared to the alpha base case (Table 2). Furthermore, estimates of fixed effects for the alpha base case (Table 2) confirmed that alpha band itself did not produce significant cortical tracking above the randomly permuted values. A significant interaction between data type and frequency band ($F(2,901.802) = 47.657$, $P = 2.114$ x10^{-20}) indicated that cortical tracking in the delta and theta bands was driven by their values being significantly above the randomly permuted r values (as compared to the alpha base case; Table 2). A significant effect of age ($F(2,755.514) = 5.079$, $P = 0.006$) showed that the strength of the cortical tracking values changed with age. There were significant interactions between age by data type ($F(2,901.802) = 3.413$, $P = 0.033$) and age by frequency band ($F(4,902.774) = 3.372$, $P = 0.009$). Inspecting the estimates of fixed effects (Table 2), the data shows that the significant difference between random permutation and real r values is strongest in the 4 month data and the frequency band differences between the age groups is predominantly driven by greater cortical tracking in the delta band at 4 months (as compared to 11 months).

Figure 3, Grand averaged stimulus reconstruction values (Pearson's r) per frequency band. Each

bar represents the grand average r value across the participants at the 3 age points; 4-months

(red), 7-months (green) and 11-months (blue). Age responses are grouped along the X axis by

EEG frequency band, delta (0.5-4Hz) theta (4-8Hz) and alpha (8-12Hz). Light grey boxes signify

the average random permutation value across subjects. Outlier analysis was conducted to remove

extreme values which would compromise the LMEM, full rejection numbers detailed in

methods.

To highlight the relative contribution of delta and theta to the LMEM, the model's base

case within frequency band was changed from alpha to theta. Estimates of fixed effects revealed

that delta produced significantly larger cortical tracking (r values) than theta (Table S1). This

increase was again driven by the real rather than the random permutation data.

LMEM estimates of fixed effects for Pearson correlation (r) values

	β	SE_b	df	t	P	95% CI
Data type (real rel. to rand for alpha base case)	-9.48×10^{-4}	.001	901.802	-.816	.415	[-.003 .001]
Delta (rel. to alpha)	.010	.001	904.662	7.531	1.22×10^{-13}	[.007 .012]
Theta (rel. to alpha)	.005	.001	902.980	4.005	6.70×10^{-5}	[.003 .008]
Age (4mo rel. 11mo)	-.002	.001	907.156	-1.365	.173	[-.004 7.63×10^{-4}]
Age (7mo rel.11mo)	-2.84×10^{-4}	.001	886.784	-.221	.825	[-.003 .002]
Data type * delta (rel. to alpha)	.012	.001	901.802	9.549	1.19×10^{-20}	[.010 .015]
Data type * theta (rel. to alpha)	.004	.001	901.802	3.039	.002	[.001 .006]
Data type * 4mo (rel. to 11mo)	.003	.001	901.802	2.471	.014	[.001 .006]
Data type * 7mo (rel. to 11mo)	6.36×10^{-4}	.001	901.802	.501	.617	[-.002 .003]
4mo * Delta (rel. to 11mo)	.005	.002	903.729	3.391	.001	[.002 .008]
4mo * Theta (rel. to 11mo)	.001	.002	902.587	.803	.422	[-.002 .004]
7mo * Delta (rel. to 11mo)	.001	.002	903.407	.901	.368	[-.001 .004]
7mo * Theta (rel. to 11mo)	8.70×10^{-5}	.002	902.608	.056	.955	[-.003 .003]

Table 2. Parameter estimates from the LMEM. Individual subject person correlations (r

values) derived from 3 frequency bands (delta 0.5-4Hz, theta 4-8Hz and alpha 8-12Hz), 3 ages

(4-, 7- or 11-months) and 2 data types (random or real). Random permutation r values, alpha and

11-months data were set as the respective base cases data type, frequency band and age in the

model.

The mTRF stimulus reconstruction data show that delta and theta EEG responses track

the acoustic envelope of rhythmic speech from the age of 4-months, supporting our hypothesis

that delta-band neural signals play a key role in speech envelope tracking during early infant

language processing. Furthermore, 4-month infants showed significantly greater tracking than

older infants, and this was strongly influenced by the strength of the delta-band response. Theta-

band neural signals also track the speech envelope, but at a significantly lower level. In contrast

to the developmental maturation observed in theta power (Figure 1), there was no evidence for a

developmental change in theta envelope tracking during the first year of life. Significant theta

tracking was observed as early as 4-months, the age at which infants are thought to recognize

their first word (42) (their own name). In accordance with our sensory hypothesis (41), as infants

become more efficient speech comprehenders, top-down processes may be expected to increase

the degree of theta tracking beyond that observed here. Increased attention to speech content

with increasing comprehension may also introduce alpha tracking, perhaps during the second

year of life.

4.3 Phase Amplitude Coupling (PAC)

Modulation index (MI) was determined following the method used by Canolty et al. to

measure PAC, as it is the most tolerant to signal noise (43), a common issue in infant EEG. This

measure combines the amplitude envelope of a selected high-frequency band with the phase time

series of a low-frequency band, creating a complex-valued signal referred to as the modulation

index (8).

For each participant low-frequency phases from 2 to 8Hz (1 Hz steps) and high-

frequency amplitudes from 15 to 45Hz (5 Hz steps) were extracted from the EEG signal from

each of the 60 electrode channels. For each of these PAC steps, multiple MI's were calculated

per infant via a 5-second sliding window. The significant windows, as compared to surrogate

statistical iterations (N=200), were averaged per participant before a grand average (Figure 4)

was calculated for each phase amplitude pairing (see methods).

Figure 4, Violin plots of phase amplitude coupling (Canolty's modulation index). Significant MI's were averaged for each individual infant before being plotted as a grand average violin plot across infants. Outlier analysis was conducted to remove extreme data points that would compromise the LMEM, therefore data plotted consisted of the following number of data points (4-months, N=54; 7-months N=50; 11-months N=54).

To investigate whether the MI values were significantly different when either delta or theta was the low-frequency carrier phase plus when either beta or gamma were the high-frequency amplitudes, and if this relationship was affected by the age of the infants, a LMEM was conducted. Fixed effect factors of low-frequency phase (delta or theta), high-frequency amplitude (beta or gamma) and age (4-, 7- or 11-months) were inputted to the LMEM. Theta, gamma and 4-months data were defined as the respective base cases. The maximum MI value from the four PAC band pairings (delta/beta, delta/gamma, theta/beta and theta/gamma), from

pre-defined frequency band groupings (delta 2-4Hz, theta 4-8Hz, beta 15-30Hz and gamma 30-45Hz) were extracted per participant and submitted to the model. Interactions of low-frequency phase by age and high-frequency amplitude by age were also included in the model, with a random intercept (AR1) per participant included to account for individual differences across the 3 ages of recording (see methods).

Tests of fixed effects showed a significant effect of low-frequency phase ($F(1, 572) =$ 201.915, $P = 1.827$ x10^{-39}) and high-frequency amplitude ($F(1, 572) = 11.308$, $P = 8.23$ x10^{-4}). The estimates of fixed effects (see Table 3) show that changing the low-frequency phase (delta vs theta) has a greater effect on the MI value than changing the high-frequency amplitude (beta vs gamma). Bonferroni-corrected pairwise comparisons showed MI values were larger when delta ($M = 1.513$, $SE \pm 0.053$) rather than theta ($M = 0.596$, $SE \pm 0.053$) was the low-frequency carrier phase. MI values were also larger when beta (M = 1.163, $SE \pm 0.053$) rather than gamma ($M = 0.946$, $SE \pm 0.053$) was the high-frequency amplitude. Age ($F(2, 190.459) = 0.387$, $P =$ 0.680), age by low-frequency phase ($F(2, 572) = 1.448$, $P = 0.236$) and age by high-frequency amplitude ($F(2, 572) = 2.047$, $P = 0.130$) were not significant.

Accordingly, delta plays a greater role than theta as a carrier phase for coupling with higher-frequency amplitudes in the infant brain. Indeed, the importance of delta as the carrier phase does not alter between 4- and 11-months, with delta-beta PAC producing larger values than delta-gamma PAC at all ages (*Mean diff.* $= 0.386$, $SE \pm 0.070$). Given the importance of canonical babbling in the first year of life, enhanced delta-beta PAC may indicate the importance of motor prediction of speech for the language-learning brain (44). Early infant babbling is known to reflect the rhythmic properties of the adult language, as behavioural studies show that the babble of Arabic-, French- and Cantonese-learning infants are distinguishably different (45)**.**

LMEM estimates of fixed effects for PAC values

	β	SE $_b$	df	t	P	95% CI
Low-frequency phase (rel. to θ)	.872	.110	572.000	7.920	1.245x10^{-14}	[.656 1.088]
High-frequency amplitude (rel. to γ)	.330	.110	572.000	2.994	0.003	[.113 .546]
Age (11mo rel. to 4mo)	.005	.135	572	.035	.972	[-.260 .270]
Age (7mo rel. to 4mo)	-.042	.161	261.842	-.263	.792	[-.359 .274]
LFP * 7mo (rel. to 4mo)	.197	.159	572	1.243	.214	[-.115 .509]
LFP * 11mo (rel. to 4mo)	-.063	.156	572.000	-.406	.685	[-.370 .243]
HFA * 7mo (rel. to 4mo)	-.298	.159	572	-1.877	.061	[-.610 .014]
HFA * 11mo (rel. to 4mo)	-.0402	.156	572	-.258	.797	[-.347 .266]

Table 3. Parameter estimates from the LMEM. Maximum MI values from the four PAC band pairings (delta/beta, delta/gamma, theta/beta and theta/gamma), from pre-defined frequency band groupings (beta 2-4Hz, theta 4-8Hz, beta 15-30Hz and gamma 30-45Hz) were submitted to the model. The base cases for the LMEM were set as 4-months for age, theta (θ) for LFP and gamma (γ) for HFA.

5 Discussion

Here we show, for the first time, that infant delta and theta cortical signals track the rhythmic fluctuations of the speech envelope of sung IDS. We demonstrate that delta tracking of the speech envelope is significantly stronger than theta tracking during the first year of life, a different pattern to that found in adults, and that delta tracking is particularly strong at 4 months. The stimulus-induced delta signal power (PSD) is large and constant from 4-months, whilst theta power develops continuously between 4- and 11-months. Also for the first time, we demonstrate PAC in response to speech input, at all ages studied. We show that delta rather than theta neural signals act as the dominant carrier phase for the temporal organisation of higher frequency amplitudes in the infant brain, again different to adults, with delta-beta PAC greater than theta-gamma PAC. These data suggest that the relative weighting of speech encoding mechanisms revealed by adult neuroimaging studies reflect the end state of a system that has fully matured,

rather than representing fundamental age-independent relations. By contrast to adult studies, alpha cortical tracking was not observed for infants in the current paradigm.

Significant cortical tracking was already evident in our sample at 4-months of age, the youngest age yet reported in the speech literature. Indeed, non-speech studies with newborn infants (using amplitude-modulated noise) have shown that delta cortical tracking of rhythm is present at birth (46). Accordingly, language experience may not be required for efficient delta-band cortical tracking of speech rhythm (41). Although it remains possible that early delta tracking provides a foundation for the attentional and grouping mechanisms indicated by some adult studies (24), delta is a temporal frequency that reflects important linguistic information in all languages, via the acoustic landmarks provided by stressed syllable placement (26). Indeed, animal studies have also demonstrated cortical tracking of rhythmically-structured acoustic input in both delta and theta bands (7, 47), possibly suggesting that these are general auditory perceptual abilities conserved across mammalian species. Nevertheless, animals do not learn spoken language, while IDS is highly rhythmic and optimally-structured to support infant language learning. IDS has increased delta-band modulation energy and significantly stronger delta-theta phase synchronization of AMs than ADS (48). Accordingly, it seems plausible that infants, who are exposed to maternal speech rhythms while in the womb, may use these general perceptual abilities to entrain to human speech. Following birth, they may rapidly augment low-frequency cortical tracking with the higher-frequency information perceived by the human ear, for example via PAC.

It has been demonstrated in adult studies that adding more acoustic features (such as spectral features) to the envelope information studied here improves the performance of TRF models (15, 49). In a similar vein, the infant brain may rapidly augment basic delta-band tracking

with a rich repertoire of other linguistic elements as language comprehension grows. It is known from fMRI studies that by age 3 months the infant cortex is already structured into several regions of functional importance for speech processing, for example Broca's area and anterior temporal regions (50). While the neural mechanisms underlying synchronization with the auditory envelope during speech listening are actively debated in the adult literature (1), there is gathering evidence that the alignment of cortical neural signals to specific stimulus parameters of the speech plays a key role in language processing and comprehension (4, 11, 51). The current findings will enable us to see whether individual differences in the cortical tracking observed here will predict individual differences in language outcomes as our infants acquire language. If this were the case, it would support the view that the infant brain synchronises with attended speech in order to learn language. The likelihood that our infants were not yet comprehending the nursery rhymes may explain the absence of alpha tracking, as alpha tracking may reflect both attention to and comprehension of speech (54) . As our sample age, we plan to investigate these possibilities.

6 Methods

6.1 Infant participants

Data from the first half (N=60) of a larger longitudinal cohort (N=122) were used in all analyses. From this initial cohort, four participants withdrew without providing any data and one withdrew after the first session so was also excluded. The remaining sample of 55 infants provided data at ~4-months (115.6 ± 5.3 days), ~7-months (212.2 ± 7.2 days) and ~11-months (333.1 ± 5.6 days) [mean $\pm$ standard deviation (*SD*)]. Due to missed appointments (7-months

N=2), technical issues with the data file (4-months, N=1) the final number of data points at each month was, ~4-months (N=54), ~7-months (N=53), ~11-months (N=55).

Infants were recruited from a medium sized city in the United Kingdom and surrounding areas via multiple means including flyers in hospitals, schools and antenatal classes, research presentations at maternity classes and online advertising. All infants were born full term (37-42 gestational weeks) and had no diagnosed developmental disorder. The study was reviewed by the Psychology Research Ethics Committee of the University of Cambridge. Parents gave written informed consent after a detailed explanation of the study and families were repeatedly reminded that they could withdraw from the study at any point during the repeated appointments.

6.2 Stimuli

A selection of 18 typical English language nursery rhymes were chosen as the stimuli. Audio-visual stimuli of a singing head were recorded using a Canon XA20 video camera at 1080p, 50fps and with audio at 4800Hz. A native female speaker of British English used infant directed speech to melodically sing (for example "Mary Mary Quite Contrary") or rhythmically chant (for nursery rhymes like "There was an old woman who lived in a shoe") the nursery rhymes whilst listening to a 120 bpm metronome. The beat was not present on the stimulus videos but it ensured that a consistent quasi-rhythmic production was maintained throughout the 18 nursery rhymes. To ensure natural vocalizations the nursery rhyme videos were recorded sung, or rhythmically chanted, live to an alert infant or sung again immediately afterwards if the infant fussed out.

6.3 EEG data collection

Infants were seated in a highchair, approximately one meter in front of their primary care giver, within a sound-proof acoustic chamber. EEG data was recorded at a sampling rate of 1000Hz using a GES 300 amplifier connected to a correctly sized 64 channel infant electrode net (Geodesic Sensor Net, Electrical Geodesics Inc., Eugene, OR, USA). The infant was seated ~650mm away from the presentation screen and sounds were presented at 60dB (checked by sound level meter) from speakers (Q acoustics 2020i driven by a Cambridge Audio Topaz AM5 Stereo amplifier) placed either side of the screen. Whilst the infant attended to the screen, the 18 nursery rhyme videos played sequentially, each repeated 3 times (54 videos, with a presentation time of 20' 33'' in total). If the infant lost attention to the screen an attention grabber video was played at the end of that nursery rhyme. If the infant became too fussy a short break was allowed before continuing, otherwise the session was ended. All infants included in analysis listened to at least 2 repetitions of each nursery rhyme (minimum of 36 nursery rhymes, lasting 13' 42''). This stimulus period was followed by 5 minutes of silent recording (silent state). To ensure compliance from the infant, and therefore a good EEG signal during the silent state, it was necessary for a researcher to sit alongside the infant during the silent state recording. To ensure consistency across participants, the researcher performed the same action of silently blowing bubbles and showing the same picture book to the infant.

6.4 EEG preprocessing

All analyses were conducted with custom-made scripts in Matlab 2017a (The MathWorks, Inc., Natick, MA) incorporating the EEGLab toolbox (55).

The four (channels 61, 62, 63 and 64) facial electrodes were excluded from all analyses because they do not exist on the infant-sized EGI Geodesic sensor nets. The EEG data, from the

remaining 60 channels, was filtered (*pop_eegfiltnew* function of EEGLab toolbox) into a

broadband signal (0.5-45Hz for PSD and PAC) or the frequency band of interest (0.5-4Hz, 4-

8Hz or 8-12Hz for the mTRF analysis) using zero-phase bandpass Hamming windowed FIR

filters (transition band widths of 2Hz with cutoff frequencies at -6 dB, 0-5Hz, 3-9Hz and 7-13Hz

respectively). The EEG data was down sampled to 100Hz to reduce the computational load.

Next, the *clean_asr* EEGLab function (55) was used to clean noise artifacts from the data by

identifying and removing bad principal components via a modified PCA procedure (see

supplement for more details). Further bad channels were identified via probability and kurtosis

and were interpolated (via spherical interpolation), if they were 3*SD* away from the mean, before

all channels were re-referenced to a 60-channel average reference.

     EEG responses were epoched into trials aligned to the start and ending at the completion

of a phrase (e.g. "Mary had a little lamb"), producing EEG responses to 83 phrases (*M length* ±

SD: 4.23sec ±0.88) which were repeated a maximum of 3 times in the experiment (249 epochs in

total). This epoching procedure was decided as infant EEG typically contains short, irregular,

movement artifacts and using shorter epochs increases the likelihood of generating a whole

artifact free epoch whilst maintaining long enough epochs for optimising the model fit with the

mTRF toolbox (37). The infants occasionally rested their head or touched the EEG cap in such a

way that specific channels showed short bursts of noise whilst the rest of the channels remained

clean. To account for this, and retain a large volume of the data, epoch by epoch channel

rejection was conducted. Per epoch, probability and kurtosis were used to identify bad channels

and were interpolated (via spherical interpolation) if they were 3*SD* away from the mean.

Finally, bad epochs were rejected with the *pop_autorej* function (EEGLab), removing epochs

with fluctuations above 1000uV and values outside a 3*SD* of the probability threshold.

6.5 Multivariate Temporal Response Function (mTRF)

TRFs are encoding models that can describe how an input and output of a system are related via linear convolution (37). Here, we applied TRFs in a backward direction to assess how strongly a stimulus property, in this case the stimulus envelope, is encoded in the neural response. The backwards, "stimulus reconstruction", mTRF model has important advantages compared to previous forward linear encoding models in infants (30, 31). Specifically, it utilises data from all the EEG channels simultaneously in a multivariate manner, while forward TRF models are fit on individual channels separately.

After preprocessing, the epochs of EEG data in response to each NR trial, were averaged together to improve the signal to noise ratio of the data for the mTRF analysis (4-month, *75.9* ± 13.3 epochs; 7-month, *79.4* ± 6.4 epochs; 11-month, *80.7* ± 5.1 epochs [mean ± standard deviation (*SD*)]). If less than half (42 averaged trials) remained after preprocessing the file was removed from further analysis (minimum numbers at 4-month, 47 epochs; 7-month, 47 epochs and 11-month 65 epochs). The mTRF analysis was conducted using the multivariate temporal response function (mTRF) toolbox (37) through Matlab 2017a (The MathWorks, Inc., Natick, MA). The backwards model can be expressed by the following formula in which the reconstructed stimulus envelope *ŝ(t)* is created by a linear decoder, g*(τ,* n)*, mapping the neural response, *r(t,n)*, back to the stimulus, *s(t)*. The TRF decoder was used to integrate the neural responses at multiple time lags, τ, between 0 and 250ms ($\tau_{min} = 0$ms, $\tau_{max} = 250$ms). These 'stimulus-relevant' time lags where selected in keeping with the previous literature (15, 17, 37)

$$\hat{s}(t) = \sum_{n}\sum_{\tau} r(t+\tau,n)g(\tau,n),$$

The quality of the envelope tracking within each EEG frequency band was assessed by a "leave-one-out" cross-validation per infant [31]. First the average trial EEG epochs (maximum of 83) were normalised via function *nt_normcol* (Noisetools *http://audition.ens.fr/adc/NoiseTools/*). Normalisation, decreased the range of values that were necessary for the regularisation parameter search in the mTRF toolbox, making the cross validation more efficient. Next, the normalized epoch trials were rotated M-1 times, each serving once as the "test set" with the remainder of the trials being the TRF "training set". For each rotation, the resultant M-1 training models were averaged to create one average model from the training set. The average model was subsequently convolved with the test data to reconstruct the stimulus. Pearson's correlation (r) was used to validate how well the reconstructed stimulus correlated to the original. This process was repeated for the M-1 rotations. To avoid overfitting the model to a specific trial, an average r value was taken from the 83 r validation values. This process was repeated at 12 ridge regressions (λ values, $1x10^{-3}:1x10^{8}$) with the lowest λ value, where any increase gave no further improvement to the average r value, was taken (37). Choosing the correct lambda value here again mitigated the potential overfitting of the TRF model. This average r value, at the optimal λ, was used for all further analysis.

6.6 mTRF auditory stimuli preprocessing

The envelope of the auditory signal was extracted by taking the absolute value of the analytic signal generated by the Hilbert transform (Matlab). As the envelope of the lower frequencies is linearly relatable to the EEG signal (10, 11, 51) the envelope of the stimuli was filtered between 0.5Hz and 15Hz (lowpass; 6[th] order Butterworth filter. Highpass; 9[th] order Butterworth filter). The resultant envelopes were normalized using *nt_normcol* (Noisetools). Finally, the stimulus envelopes were down sampled to 100Hz to match the EEG signal.

6.7 mTRF Statistics

Random permutation statistics were created for each participant to measure the average stimulus reconstruction (r) that could be obtained by chance. The random permutation procedure was conducted per participant for each frequency band producing a paired chance stimulus reconstruction (r) per participant. To obtain a random permutation of the data, whilst maintaining phase integrity, each of the stimulus envelopes were first reversed and a random circular shift was applied. Next, the mTRF cross-validation was ran in the same way as the real data (see above for details), to give a stimulus reconstruction (r) value. This procedure was iterated 100 times to create a null distribution and the average of these 100 iterations were used as that participant's random stimulus reconstruction (r) value.

6.8 mTRF Linear mixed effects model

A linear mixed effects model (LMEM), as described in the main text, was conducted in SPSS (IBM SPSS statistics 24), submitting data type (real r values, random permutation r values), frequency band (delta, theta or alpha) and age (4-, 7- or 11-months) along with interactions between data type by frequency band, data type by age and age by frequency band, to the LMEM. Due to the sensitivity of LMEM to outliers in the sample, outlier analysis was conducted to exclude data more than 1.5 interquartile ranges above the upper quartile or below the lower quartile separately per band and per age group, leaving, delta (4-months N=53, 7-months N=53 and 11-months N=51), theta (4-months N=53, 7-months N=52 and 11-months N=55) and alpha (4-months N=53, 7-months N=52 and 11-months N=52) data sets included in the LMEM (Table 2) and Figure 3. Visual inspection of residual plots did not reveal any obvious deviations from homoscedasticity or normality.

The LMEM can be described by the following equation.

R VALUE$_{ij}$ = $β_{0j}$ + $β_{1j}$ AGE$_{ij}$ + $β_2$DATA TYPE$_{ij}$ + $β_3$FREQUENCY BAND$_{ij}$ + $β_4$(DATA TYPE x

AGE)$_{ij}$ + $β_5$(DATA TYPE x FREQUENCY BAND)$_{ij}$ + $β_6$(AGE X FREQUENCY BAND) $_{ij}$ + e_{ij}

6.9 Phase amplitude coupling (PAC)

All remaining epochs after preprocessing were concatenated back into one continual

signal. Due to the increased susceptibility of PAC analysis to noise, manual rejection was

conducted to further remove noisy periods of data from the signal.

To asses PAC, a modified version of the WinPACT plugin (EEGLab) (55) was used to

acquire Canolty and colleagues' modulation index (MI) values (8). The MI method combines the

amplitude envelope time series $A_1(t + τ)$ of a high-frequency with the phase time series $φ_2(t)$ of a

specified low-frequency, creating a composite complex-valued signal $z(t, τ)$. The resulting value

is a widely validated metric of the coupling strength and preferred phase between two

frequencies. For each infant's data, low-frequency phase (LFP) and high-frequency amplitude

(HFA) were extracted with a zero-phase FIR filter (Hamming window), separately for all 60

electrodes. LFP centre frequencies were filtered from 2 to 8Hz, in 1Hz steps, with 1Hz

bandwidth and HFA centre frequencies from 15 to 45Hz, in 5Hz steps, with 5Hz bandwidth. A

sliding 5 second analysis window was implemented with 2.5ms overlaps, with a mean vector

length calculated per window. Next, 200 surrogate statistical iterations were created for each

PAC calculation window, with a generalized family-wise error rate correction implemented for

the multiple PAC calculations. Statistically significant windows were identified if the MI value

exceeded 95% confidence interval of the distribution of the surrogate statistical windows (the

200 iterations created per PAC calculation window). Statistically significant window MIs were

averaged per participant and grand averaged for group level plots.

6.10 PAC Linear mixed effects model (LMEM)

A LMEM was conducted using SPSS (IBM SPSS statistics 24), to investigate whether the MI values (Canolty's modulation index) (8) were significantly different when either delta or theta was the low-frequency carrier phase, when either beta or gamma was the high-frequency amplitude and if this relationship was affected by the age of the infants. Due to the sensitivity of LMEMs to outliers in the sample, outlier analysis was conducted to exclude data more than 1.5 interquartile ranges above the upper quartile or below the lower quartile, leaving, 4-months N=54, 7-months N=50 and 11-months N=54 data sets included in the LMEM Table 3 and Figure 4.

$$PAC_{ij} = \beta_{0j} + \beta_{1j} AGE_{ij} + \beta_2 LFP_{ij} + \beta_3 HFA_{ij} + \beta_4 (AGE \times LFP)_{ij} + \beta_5 (AGE \times HFA)_{ij} + e_{ij}$$

The LMEM can be described by the equation above, in which LFP denotes the band of the low-frequency phase (delta; 2-4Hz or theta; 4-8Hz), HFA is the band of the high-frequency amplitude (beta; 15-30Hz or gamma; 30-45Hz) and age is the age grouping of the infant (~4-months, ~7-months or ~11-months).

6.11 Spectral analysis (periodogram PSD estimate)

The same concatenated data sets created for the PAC analysis were also used for the periodogram Power Spectral Density (PSD) estimates. A one-sided PSD estimate was conducted separately for each electrode channel using the periodogram function (Matlab). The length of the participants data was zero padded to ensure the size of the rectangular window used was equal in length to the number of discrete Fourier transform (DFT) points, ensuring the correct FFT across participants. This resulted in 52,834 equal spaced frequency bins from 0 to 50Hz.

The periodogram can be defined by the following formula. In which the EEG signal, x_n, is sampled at 100Hz, with Δt as the sampling interval.

$$\widehat{P}(f) = \frac{\Delta t}{N} \left| \sum_{n=0}^{N-1} x_n e^{-j2\pi f \Delta t \, n} \right|^2, \quad -1/2\Delta t < f \le 1/2\Delta t,$$

To achieve the one-sided periodogram output reported in Figure 1, values at all frequencies (except 0 and the Nyquist, $1/2\Delta t$), were multiplied by two to conserve the total power.

6.12 PSD Linear mixed effects model

To investigate whether the PSD was significantly higher in response to the nursery rhymes compared to the silent state, and whether this relationship was affected by the age of the participants, a linear mixed effects model (LMEM) was conducted separately for the 2.18Hz and 4.40 Hz frequency peaks (IBM SPSS statistics 24). Fixed effects of recording type (nursery rhymes, silent state), age (4-, 7- or 11-months) and a recording type by age interaction were included in the model. Silent state data and 11-months data were set as the respective base cases for each variable in the model. Due to the sensitivity of LMEMs to outliers in the sample, outlier analysis was conducted to exclude data more than 1.5 interquartile ranges above the upper quartile or below the lower quartile leaving the following data sets included in the LMEM and Figure 1. Final numbers = stimulus period (4-months N=44, 7-months N=47, 11-months N=50) and silent state (4-months N=35, 7-months N=46, 11-months N=38).

The model can be described by the following equation:

$\text{PSDpeak}_{ij} = \beta_{0j} + \beta_{1j}\text{AGE}_{ij} + \beta_2\text{RECORDING TYPE}_{ij} + \beta_3(\text{RECORDING TYPE x AGE})_{ij} + e_{ij}$

7 References

1. J. Obleser, C. Kayser, Neural Entrainment and Attentional Selection in the Listening Brain. *Trends Cogn. Sci.* **23**, 913–926 (2019).

2. A.-L. Giraud, D. Poeppel, Cortical oscillations and speech processing: emerging computational principles and operations. *Nat. Neurosci.* **15**, 511–517 (2012).

3. D. Poeppel, The neuroanatomic and neurophysiological infrastructure for speech and language. *Curr. Opin. Neurobiol.* **28**, 142–149 (2014).

4. J. Gross, *et al.*, Speech Rhythms and Multiplexed Oscillatory Sensory Coding in the Human Brain. *PLOS Biol.* **11**, e1001752 (2013).

5. A. Hyafil, L. Fontolan, C. Kabdebon, B. Gutkin, A.-L. Giraud, Speech encoding by coupled cortical theta and gamma oscillations. *eLife* **4**, e06213 (2015).

6. M. Lizarazu, M. Lallier, N. Molinaro, Phase−amplitude coupling between theta and gamma oscillations adapts to speech rate. *Ann. N. Y. Acad. Sci.* **1453**, 140–152 (2019).

7. P. Lakatos, *et al.*, An oscillatory hierarchy controlling neuronal excitability and stimulus processing in the auditory cortex. *J. Neurophysiol.* **94**, 1904–1911 (2005).

8. R. T. Canolty, *et al.*, High Gamma Power Is Phase-Locked to Theta Oscillations in Human Neocortex. *Science* **313**, 1626–1628 (2006).

9. R. T. Canolty, R. T. Knight, The functional role of cross-frequency coupling. *Trends Cogn. Sci.* **14**, 506–515 (2010).

10. B. N. Pasley, *et al.*, Reconstructing Speech from Human Auditory Cortex. *PLOS Biol.* **10**, e1001251 (2012).

11. E. M. Zion Golumbic, *et al.*, Mechanisms Underlying Selective Neuronal Tracking of Attended Speech at a 'Cocktail Party.' *Neuron* **77**, 980–991 (2013).

12. N. Mesgarani, E. F. Chang, Selective cortical representation of attended speaker in multi-talker speech perception. *Nature* **485** (2012).

13. J. E. Peelle, J. Gross, M. H. Davis, Phase-locked responses to speech in human auditory cortex are enhanced during comprehension. *Cereb. Cortex N. Y. N 1991* **23**, 1378–1387 (2013).

14. H. Blank, M. H. Davis, Prediction Errors but Not Sharpened Signals Simulate Multivoxel fMRI Patterns during Speech Perception. *PLOS Biol.* **14**, e1002577 (2016).

15. G. M. Di Liberto, J. A. O'Sullivan, E. C. Lalor, Low-Frequency Cortical Entrainment to Speech Reflects Phoneme-Level Processing. *Curr. Biol. CB* **25**, 2457–2465 (2015).

16. G. M. Di Liberto, M. J. Crosse, E. C. Lalor, Cortical Measures of Phoneme-Level Speech Encoding Correlate with the Perceived Clarity of Natural Speech. *eNeuro* **5** (2018).

17. N. Ding, J. Z. Simon, Cortical entrainment to continuous speech: functional roles and interpretations. *Front. Hum. Neurosci.* **8** (2014).

18. K. B. Doelling, L. H. Arnal, O. Ghitza, D. Poeppel, Acoustic landmarks drive delta-theta oscillations to enable speech comprehension by facilitating perceptual parsing. *NeuroImage* **85 Pt 2**, 761–768 (2014).

19. U. Frith, Literally changing the brain. *Brain J. Neurol.* **121 (Pt 6)**, 1011–1012 (1998).

20. A. J. Power, L. J. Colling, N. Mead, L. Barnes, U. Goswami, Neural encoding of the speech envelope by children with developmental dyslexia. *Brain Lang.* **160**, 1–10 (2016).

21. A. J. Power, N. Mead, L. Barnes, U. Goswami, Neural entrainment to rhythmic speech in children with developmental dyslexia. *Front. Hum. Neurosci.* **7** (2013).

22. N. Molinaro, M. Lizarazu, M. Lallier, M. Bourguignon, M. Carreiras, Out-of-synchrony speech entrainment in developmental dyslexia. *Hum. Brain Mapp.* **37**, 2767–2783 (2016).

23. M. V. Ghinst, *et al.*, Cortical Tracking of Speech-in-Noise Develops from Childhood to Adulthood. *J. Neurosci.* **39**, 2938–2950 (2019).

24. V. J. Boucher, A. C. Gilbert, B. Jemel, The role of low-frequency neural oscillations in speech processing: Revisiting delta entrainment. *J. Cogn. Neurosci.* **31**, 1205–1215 (2019).

25. V. Leong, U. Goswami, Acoustic-Emergent Phonology in the Amplitude Envelope of Child-Directed Speech. *PLOS ONE* **10**, e0144411 (2015).

26. R. M. Dauer, Stress-timing and syllable-timing reanalyzed**A preliminary version of this paper was read at the Annual Meeting of the Linguistic Society of America, San Antonio, Texas, December 28–30, 1980. The experimental work for this study was carried out at the Phonetics Laboratory, Edinburgh University. *J. Phon.* **11**, 51–62 (1983).

27. T. Nazzi, J. Bertoncini, J. Mehler, Language discrimination by newborns: Toward an understanding of the role of rhythm. *J. Exp. Psychol. Hum. Percept. Perform.* **24**, 756–766 (1998).

28. J. Mehler, *et al.*, A precursor of language acquisition in young infants. *Cognition* **29**, 143–178 (1988).

29. U. Goswami, Speech rhythm and language acquisition: an amplitude modulation phase hierarchy perspective. *Ann. N. Y. Acad. Sci.* **1453**, 67–78 (2019).

30. M. Kalashnikova, V. Peter, G. M. Di Liberto, E. C. Lalor, D. Burnham, Infant-directed speech facilitates seven-month-old infants' cortical tracking of speech. *Sci. Rep.* **8** (2018).

31. S. Jessen, L. Fiedler, T. F. Münte, J. Obleser, Quantifying the individual auditory and visual brain response in 7- month-old infants watching a brief cartoon movie. *bioRxiv*, 610709 (2019).

32. H. Witte, *et al.*, Analysis of the interrelations between a low-frequency and a high-frequency signal component in human neonatal EEG during quiet sleep. *Neurosci. Lett.* **236**, 175–179 (1997).

33. A. Tokariev, M. Videman, J. M. Palva, S. Vanhatalo, Functional Brain Connectivity Develops Rapidly Around Term Age and Changes Between Vigilance States in the Human Newborn. *Cereb. Cortex N. Y. N 1991* **26**, 4540–4550 (2016).

34. P. J. Marshall, Y. Bar-Haim, N. A. Fox, Development of the EEG from 5 months to 4 years of age. *Clin. Neurophysiol.* **113**, 1199–1208 (2002).

35. E. V. Orekhova, T. A. Stroganova, I. N. Posikera, M. Elam, EEG theta rhythm in infants and preschool children. *Clin. Neurophysiol. Off. J. Int. Fed. Clin. Neurophysiol.* **117**, 1047–1062 (2006).

36. V. Leong, M. Kalashnikova, D. Burnham, U. Goswami, The Temporal Modulation Structure of Infant-Directed Speech (2017) https:/doi.org/10.17863/CAM.9089 (July 3, 2020).

37. M. J. Crosse, G. M. Di Liberto, A. Bednar, E. C. Lalor, The Multivariate Temporal Response Function (mTRF) Toolbox: A MATLAB Toolbox for Relating Neural Signals to Continuous Stimuli. *Front. Hum. Neurosci.* **10** (2016).

38. S.-J. Lim, M. Wöstmann, J. Obleser, Selective Attention to Auditory Memory Neurally Enhances Perceptual Precision. *J. Neurosci. Off. J. Soc. Neurosci.* **35**, 16094–16104 (2015).

39. M. Wöstmann, S.-J. Lim, J. Obleser, The Human Neural Alpha Response to Speech is a Proxy of Attentional Control. *Cereb. Cortex* **27**, 3307–3317 (2017).

40. A. Dimitrijevic, M. L. Smith, D. S. Kadis, D. R. Moore, Cortical Alpha Oscillations Predict Speech Intelligibility. *Front. Hum. Neurosci.* **11** (2017).

41. U. Goswami, *Cognitive Development and Cognitive Neuroscience: The Learning Brain* (Routledge, 2019) (July 3, 2020).

42. D. R. Mandel, P. W. Jusczyk, D. B. Pisoni, INFANTS' RECOGNITION OF THE SOUND PATTERNS OF THEIR OWN NAMES. *Psychol. Sci.* **6**, 314–317 (1995).

43. M. J. Hülsemann, E. Naumann, B. Rasch, Quantification of Phase-Amplitude Coupling in Neuronal Oscillations: Comparison of Phase-Locking Value, Mean Vector Length, Modulation Index, and Generalized-Linear-Modeling-Cross-Frequency-Coupling. *Front. Neurosci.* **13** (2019).

44. L. H. Arnal, K. B. Doelling, D. Poeppel, Delta-Beta Coupled Oscillations Underlie Temporal Prediction Accuracy. *Cereb. Cortex N. Y. N 1991* **25**, 3077–3085 (2015).

45. B. D. Boysson-Bardies, L. Sagart, C. Durand, Discernible differences in the babbling of infants according to target language*. *J. Child Lang.* **11**, 1–15 (1984).

46. S. Telkemeyer, *et al.*, Acoustic Processing of Temporally Modulated Sounds in Infants: Evidence from a Combined Near-Infrared Spectroscopy and EEG Study. *Front. Psychol.* **2** (2011).

47. P. Lakatos, *et al.*, Global dynamics of selective attention and its lapses in primary auditory cortex. *Nat. Neurosci.* **19**, 1707–1717 (2016).

48. P. K. Kuhl, Early language acquisition: cracking the speech code. *Nat. Rev. Neurosci.* **5**, 831–843 (2004).

49. C. Daube, R. A. A. Ince, J. Gross, Simple Acoustic Features Can Explain Phoneme-Based Predictions of Cortical Responses to Speech. *Curr. Biol.* **29**, 1924-1937.e9 (2019).

50. G. Dehaene-Lambertz, L. Hertz-Pannier, J. Dubois, Nature and nurture in language acquisition: anatomical and functional brain-imaging studies in infants. *Trends Neurosci.* **29**, 367–373 (2006).

51. J. A. O'Sullivan, *et al.*, Attentional Selection in a Cocktail Party Environment Can Be Decoded from Single-Trial EEG. *Cereb. Cortex N. Y. NY* **25**, 1697–1706 (2015).

52. B. Zoefel, S. T. Oever, A. T. Sack, The Involvement of Endogenous Neural Oscillations in the Processing of Rhythmic Input: More Than a Regular Repetition of Evoked Neural Responses (2018) https:/doi.org/10.17863/CAM.23964 (July 6, 2020).

53. N. Ding, L. Melloni, H. Zhang, X. Tian, D. Poeppel, Cortical tracking of hierarchical linguistic structures in connected speech. *Nat. Neurosci.* **19**, 158–164 (2016).

54. C. Brodbeck, L. E. Hong, J. Z. Simon, Rapid Transformation from Auditory to Linguistic Representations of Continuous Speech. *Curr. Biol.* **28**, 3976-3983.e5 (2018).

55. A. Delorme, S. Makeig, EEGLAB: an open source toolbox for analysis of single-trial EEG dynamics including independent component analysis. *J. Neurosci. Methods* **134**, 9–21 (2004).

Acknowledgements

This project has received funding from the European Research Council (ERC) under the European Union's Horizon 2020 research and innovation programme (grant agreement No. 694786). We would like to thank all the families and infants who kindly donated their time to this project.

Declaration of Interests

The authors do not report any conflicts of interest.

Author Contributions

Adam Attaheri: EEG Paradigm Development, EEG Preprocessing, Investigation - Data Curation, Formal Analysis - design, creation and implementation of analysis, Writing - Original Draft.

Áine Ní Choisdealbha: EEG Preprocessing - Investigation - Data Curation - Writing - Review & Editing

Giovanni Di Liberto: Formal analysis, Writing - Review & Editing

Sinead Rocha: Investigation - Data Curation, Writing - Review & Editing

Perrine Brusini: EEG Paradigm Development, Investigation - Data Curation

Natasha Mead: Investigation - Data Curation

Helen Olawole-Scott: Investigation - Data Curation

Panagiotis Boutris: Investigation - Data Curation

Samuel Gibbon: Investigation - Data Curation

Isabel Williams: Investigation - Data Curation

Christina Grey: Investigation - Data Curation

Sheila Flanagan: Investigation - Modulation analysis

Usha Goswami: Conceptualization - Methodology, Funding Acquisition, Supervision, Project Administration, Writing - Original Draft