Optogenetic analysis of Ca^{++} transients in *Caenorhabditis elegans*

muscle cells during forward and reverse locomotion

Jacob R. Manjarrez[1], Magera Shaw[2], Roger Mailler[2]

1. Department of Biochemistry and Microbiology, Oklahoma State University Center for Health Sciences,

Tulsa, OK 74107

2. Tandy School of Computer Science, University of Tulsa, Tulsa, OK 74104

Corresponding Author:

Roger Mailler

mailler@utulsa.edu

918-631-3140

Tandy School of Computer Science

University of Tulsa

800 South Tucker Dr

Tulsa, OK 74104

Total number of pages; 33

Number of Figures; 7

Word count; Abstract (153), Introduction (610), Discussion (1468)

ABSTRACT

Understanding how an organism generates movement is an important step toward determining how a

system of neurons produces behavior. With only 95 body wall muscles and 302 neurons, *Caenorhabditis*

elegans is an attractive model organism to use in uncovering the connection between neural circuitry and

movement. This study provides a comprehensive examination of the muscle cell activity used by *C.*

elegans during both forward and reverse locomotion. By tracking freely moving worms that express

genetically encoded calcium indicators in their muscle cells, we directly measure the patterns of activity

that occur during movement. We then analyzed these patterns using a variety of signal processing and

statistical techniques. Although our results agree with many previous findings, we also discovered there

is significantly different mean Ca^{++} levels in many of the muscle cells during forward and reverse

locomotion and, when considered independently, the dorsal and ventral muscle activation waves exhibit

classical neuromechanical phase lag (NPL).

INTRODUCTION

One of the primary goals of neuroscience is to uncover the relationship between neural organization and behavior. A key contribution toward achieving this goal occurred with the publication of the first nearly complete connectome of the nematode *Caenorhabditis elegans* (White, et al., 1986). Since that time, researchers have simultaneously worked to fill in the missing details of the neural map (Varshney, et al., 2011; Cook, et al., 2019) and relate its structure to behaviors such as chemotaxis (Chalasani, et al., 2007), touch response (Goodman, 2006), and locomotion (Karbowski, et al., 2008; Boyle, et al., 2007; Wen, et al., 2012; Tolstenkov, et al., 2018; Fouad, et al., 2018).

Traditionally, the activity of the 95 body wall muscles (BWM) that generate locomotive force has been inferred by measuring changes in body posture as the worm moves (Baek, et al., 2002; Cronin, et al., 2005). This has led researchers to hypothesize that *C. elegans* undulating locomotion is generated through alternating dorsal/ventral muscle waves that propagate at the same rate as the body wave from head to tail during forward locomotion and from tail to head during reverse locomotion (Niebur & Erdos, 1991; Boyle, et al., 2007; Haspel, et al., 2011; Wen, et al., 2012). Furthermore, the ventral nerve cord A- and B-type neurons have been implicated as the primary muscle drivers, while the D- and AS-type neurons act to prevent co-activation of opposing dorsal/ventral muscles (Haspel, et al., 2011; Wen, et al., 2012; Tolstenkov, et al., 2018).

In this study, we investigate the behavior of the BWMs during unrestrained forward and reverse locomotion by measuring their Ca^{++} activity using the genetically encoded calcium indicator GCamp3. The data collected during these experiments are then subjected to a battery of statistical and signal analysis techniques. The results of the analysis agree with many previously published findings, but also reveal new important discoveries about the muscle waves generated by *C. elegans*. For example, our results support the conclusions that the head acts nearly independently of the body (Alkema, et al., 2005; Fouad, et al., 2018), that there is a linear drop-off in muscle activation during wave propagation (Xu, et al., 2018), that the wave frequencies of the muscle cells matched those of the bend angles (Karbowski, et al., 2008), and in agreement with the work of Butler et al. (Butler, et al., 2015), that the neuromuscular wave travels faster, and with a fixed phase offset, than the body bend wave.

However, our results also show that dorsal/ventral muscle activation is only truly anti-phasic in the

midbody and shows a larger distribution in other parts of the body than previously reported (Pierce-

Shimomura, et al., 2008; Butler, et al., 2015). The results further show that, when considered individually,

the ventral and dorsal neuromuscular waves propagate down the body at different rates from each other

and exhibit a prototypical neuromechanical phase lag (NPL) like those found in many anguilliform

swimmers (McMillen, et al., 2008; Tytell, et al., 2010). Our analysis shows that the muscle waves are

initially anti-phasic but realign themselves as they progress from head to tail during forward locomotion,

with the exact opposite occurring during reversals.

Finally, when comparing forward to reverse locomotion, our results show that there are significant

differences in the pattern of calcium levels throughout the BWMs. During forward locomotion, for

example, both dorsal and ventral muscle groups exhibit significantly higher mean anterior calcium levels,

which linearly taper off until they become significantly lower in the posterior (Xu, et al., 2018). The exact

opposite phenomena occur during reverse locomotion.

RESULTS

Muscle cell activity decreases linearly as the locomotion wave propagates from anterior to

posterior during forward locomotion and posterior to anterior during reverse locomotion.

Raw intensity measurements (Figures 1B & C) show high levels of calcium activity in the midbody of the

worm during forward locomotion and near the tail during reverse locomotion.   However, when normalized

(see Methods) against measurements taken of worms exposed to 4AP (Figure 1A), the normalized mean

values (Figures 1D & E) reveal that muscle cells rarely exceed 50% of the maximum levels. In addition,

they show that the dorsal and ventral sides have equal mean levels of Ca^{++} intensity ($\alpha=0.01$). During

forward movement, activity in the head is higher than the rest of the body. The average normalize

intensity for forward locomotion is 47.3 ± 9.7% in the head and falls off to 17.3 ± 5.7% in the tail. This

represents a falloff of over 63% over the length of the body and is well fit by the linear equation *foract(x) =*

-0.0094x + 0.469 with an R^2 = 0.83. These results show that during forward locomotion, the dorsal and

ventral mean Ca^{++} levels are highest in the head and decrease distally, and that the mean levels are

simultaneously elevated on both the dorsal and ventral sides.

Figure 1: The normalized average GFP intensity along the AP axis during forward and reverse locomotion.

Average and normalized fluorescence intensities recorded from HBR4 worms. Solid lines indicate the average and bars indicate the standard deviation. A) The average GFP intensities from the dorsal and ventral muscles for worms exposed to 500mM 4-AP. Averages recorded from this data were used to normalize GFP intensities. B) The average (not normalized) GFP intensities for the dorsal and ventral muscles along the AP axis during forward locomotion. C) The average (not normalized) GFP intensities for the dorsal and ventral muscles along the AP axis during reverse locomotion. D) The average normalized GFP intensities recorded from HBR4 worms during forward locomotion. The normalized intensities drop off approximately linearly from head to tail. E) The average normalized GFP intensities recorded from HBR4 worms during reverse locomotion. The normalized intensities drop off approximately linearly from tail to head. E) The average normalized Ca++ intensities for the dorsal muscles during forward and reverse locomotion. The asterisk (*) indicates a significant difference (α = 0.01) between forward and reverse intensities. F) The average normalized Ca++ intensities for the ventral muscles during forward and reverse locomotion. The asterisk (*) indicates a significant difference (α = 0.01) between forward and reverse intensities.

1   The normalized standard deviations of these signals also decrease linearly (decreasing ~41%) over the

2   length of the worm. Since the amplitude of a sine wave is proportional to its standard deviation and can

3   be calculated using the equation (Smith, 1999),

$$\alpha = 2\sqrt{2}\sigma \qquad\qquad\qquad (1)$$

our results show that the peak-to-peak amplitude of the dorsal and ventral waves are highest in the head

and deceases along the length of the body. These results agree with the findings of Xu et al. who

presented a linear model that predicts a deteriorated undulatory wave in the presence of AVB-B gap

junctions (Xu, et al., 2018).

During reverse locomotion (Figure 1E), the pattern is nearly perfectly reversed. Normalized Ca^{++} levels in

the tail are higher than the rest of the body, as are the standard deviations. In the tail, the average

normalized intensity is as high at 49.5 ± 11.2% at muscle row 19 while in the head it falls to just 17.1 ±

7.1%. This represents a 65% falloff in the mean intensity and a 37% decrease in the standard deviation

over the length of the worm. The linear equation *revact(x) = 0.0151x + 0.153* with an R^2 = 0.81 fits the

falloff in mean levels well.

When comparing the amplitudes of the Ca^{++} signals in the ventral and dorsal muscles, the results indicate

that there is a significant (α=0.01) difference between their activity during forward and reverse locomotion.

As Figure 1F & G show, during forward locomotion, dorsal and ventral muscle rows 1-10 show

significantly higher and muscle rows 15-24 show significantly lower mean normalized Ca^{++} intensity levels

when compared to reverse. During reverse locomotion, the opposite is true with muscle rows 1-10

exhibiting significantly lower and muscle rows 15-24 exhibiting significantly higher mean normalized Ca^{++}

levels on both the dorsal and ventral sides.

Figure 2: Muscle activation in the head and tail are in phase while activation in the mid-body is anti-phasic. The ventral side wave also travels faster than the dorsal side wave.

A) Offset between the signals in the dorsal and ventral muscle groups during forward locomotion. Solid line indicates the average offset, while bars indicate the standard deviation. B) The accumulated offset as the wave travels down the AP axis. Solid orange, blue, and green lines are the average accumulated offset for ventral signal, dorsal signal, and bend angle, respectively. The dashed red line shows the difference in activation. C-E) Average cross correlation of the dorsal and ventral muscle activations at the 3rd, 13th and 23rd muscle rows during forward locomotion. F-H) Histogram of the maximum point of dorsal/ventral cross correlation recorded from the 3rd, 13th and 23rd muscle rows. I) Offsets between the signals in the dorsal and ventral muscle groups during reverse locomotion. J) Accumulated drift from tail to head during reverse locomotion. K-M) Average cross correlation of the dorsal and ventral muscle activations at the 3rd, 13th and 23rd muscle rows during reverse locomotion. N-P) Histogram of the maximum point of dorsal/ventral cross correlation recorded from the 3rd, 13th and 23rd muscle rows.

1 The head acts independently of the rest of the body

During forward locomotion, the muscle cells in the head (rows 1-6) have highly correlated Ca^{++} activity,

indicating that they act as a group to control the head position (Figures 2A & B). However, there is an

abrupt shift in the patterns between muscle rows 4 and 6 where the ventral and dorsal sides change from

phasic to anti-phasic behavior.   At muscle row 5, autocorrelation analysis shows alternating patterns of

phasic and anti-phasic behavior, which can be seen in the large standard deviations posterior of the

nerve ring in Figure 2A. These results appear to indicate that two different neural circuits, which overlap

near the nerve ring, are primarily responsible for separate control of the head and body during forward

locomotion. These results agree with experiments conducted by Fouad et al. who demonstrated that the

head can effectively be disconnected from the rest of the body with minimal impact to the generation and

propagation of locomotion waves (Fouad, et al., 2018).

During reverse locomotion, head activation is minimal, but muscle cell activity remains largely correlated.

Figures 2I & J show very small temporal offsets between the ventral and dorsal sides as well as between

subsequent rows of muscles. A pattern transition like the one seen during forward locomotion occurs

between muscle rows 9 and 7 with muscle row 8 showing alternating phasic and off-phasic activity. These

results support the conjecture that the head is controlled using a separate neural circuit from the rest of

the body and previous findings that show that head activity is suppressed during reverse locomotion

(Alkema, et al., 2005).

Muscle activation patterns contain both phasic and anti-phasic components.

Within the head of the worm, dorsal and ventral side intensities are directly in phase with one another. Figure 2A shows that in muscle rows 1-4, the dorsal and ventral sides have no offset in signal when evaluated using autocorrelation. Figure 2C shows the results of the average autocorrelation of the dorsal and ventral muscles in row 3. The point of maximum correlation has a 0 second offset. Additionally, in each of the 315 fragments analyzed (Figure 2F), the signals are in perfect synchronization.

On average, within the mid-body of the worm, the dorsal and ventral sides are out of phase (Figure 2A). However, the non-symmetric cross correlation graph in Figure 2D shows that the activations are not completely anti-phasic. Figure 2G also shows that, unlike the muscles in the head, the offset between the dorsal and ventral sides drift considerably in the mid-body. Among the fragments evaluated for muscle row 13, the activation offset has a mean value of 0.96 ± 0.32 seconds. Given the characteristic frequency of 0.44Hz observed in the muscle cells, the expected dorsal and ventral offset should be 1.14 seconds. While an offset of 1.14 seconds occurs near the nerve ring, more posterior the offset decreases.

At the tail of the worm, the Ca^{++} waves are in phase once again (Figure 2A). This is confirmed in Figures 2E and 2H, which show that the average maximum cross correlation occurs at a 0 second offset and that this happens in nearly all the video fragments evaluated.

Figure 2B shows why the muscle Ca^{++} patterns are in phase, then out of phase, then drift back into phase once again. In the head, the offset between muscle rows 1-5 is nearly 0, meaning they occur at the same time. However, posterior of the nerve ring, the dorsal and ventral muscle activation waves travel down the body at different speeds. The ventral wave takes an average of 1.18 seconds to travel down the body while the dorsal wave takes approximately 59% longer or an average of 1.88 seconds. However, when the two waves are subtracted from one another, the resulting combined signal has an average accumulated offset of 2.66 seconds, which closely approximates the average accumulated offset for the body wave of 2.58 seconds.

In reverse locomotion (Figures 2I-P), the same pattern holds although the accumulated drift between the dorsal and ventral sides is less pronounced (Figure 2J). In the head and tail of the worm, the activation of

1   the dorsal and ventral muscles is nearly perfectly in phase while in the mid-body, they become out of

2   phase (Figures 2K-P). Overall, the reverse wave is nearly twice as fast as the forward wave taking only

3   1.34 versus 2.58 seconds. Like the forward wave, the dorsal and ventral activation waves are twice as

4   fast as the body wave and the difference in the ventral and dorsal activation is also most closely

5   associated with overall body wave propagation.

Figure 3: Correlation between body posture, muscle speed, and muscle activation during forward and reverse locomotion.

A) Average bend angles of the body of an HBR4 worm during forward locomotion. Solid lines indicate the average and bars indicate the standard deviation. B) Average bend speed of the body of an HBR4 worm during forward locomotion. Solid lines indicate the average and bars indicate the standard deviation. C) Correlation of bend angle with the muscle activation during forward locomotion. Dorsal and ventral correlations are indicated with solid lines, where the difference in activation (D-V) is indicated as a dashed line. D) Correlation of the bend speed with muscle activation during forward locomotion. Dorsal and ventral correlations are indicated with solid lines, where the difference in activation (D-V) is indicated as a dashed line. E-G) Frequency analysis of bend angle, muscle activation, and difference in muscle activation at muscle rows 3, 13, and 23. H) Bend angles of the body of HBR4 during reverse locomotion I) Bend speeds of the body of HBR4 during reverse locomotion. J) Correlation of bend angle with muscle activation during reverse locomotion. K) Correlation of bend angle speed and muscle activation. L-N) Frequency analysis of the bend angle, muscle activation, and difference in muscle activation during reverse locomotion.

Body posture is highly correlated with the difference in intensity between ventral and dorsal

muscle activation. Bend speeds are weakly correlated with muscle activity.

During forward locomotion, body bending (Figure 3A) deviates from center nearly equally in the dorsal

and ventral directions. Overall, bend angle is most highly correlated with the difference in the dorsal-

ventral Ca^{++} levels except in the first two muscle rows of the head (Figure 3C). Posterior of the nerve ring,

dorsal and ventral muscle Ca^{++} levels are ~50% correlated with bend angle, however as the wave

propagates further back, the correlation with ventral activation decreases. Additionally, Fourier analysis

(Figures 3E-G) shows that the dominant frequency components (0.11 and 0.44Hz) for dorsal and ventral

activation are nearly equal. However, bending and the difference in Ca^{++} level frequencies are most

highly correlated throughout the worm's body with a single dominant frequency of 0.44Hz. These results

agree with the findings of Karbowski et al. who reported component bend angle frequencies in the range

of 0.45-0.48 Hz (Karbowski, et al., 2008).

In reverse locomotion, the results are similar. Bend angles tend to be the greatest near the tail of the

worm (Figure 3H) and remain most highly correlated with the difference in dorsal-ventral Ca^{++} levels

(Figure 3J). Frequency analysis (Figure 3L-N) shows that bending frequency is most closely associated

with the frequency of the difference between dorsal and ventral Ca^{++} levels.

During forward locomotion, bend angles (Figure 3B) change most quickly in the head and then at nearly

equal speeds throughout the rest of the body. During reverse locomotion, bend speeds (Figure 3I) are

greatest in the tail and at the tip of the head. In both forward and reverse locomotion, bend speeds show

little correlation with muscle Ca^{++} activity (Figure 3D & K).

Dorsal and ventral muscle activation wave combine to create the overall activation pattern

From a mathematical perspective, we can describe the activity of a muscle cell at time t as sine wave

with a wavelength (λ), amplitude (α), and phase (ϕ) using the formula $w(t) = \alpha \sin(\lambda t + \phi)$. Since the

dorsal and ventral muscles work in opposition to one another, the combined activity of these cell can be

calculated by subtracting one from the other. In other words, if we use the function $d(t) =$

$\alpha_d \sin(\lambda_d t + \phi_d)$ to describe the activity of the dorsal side and $v(t) = \alpha_v \sin(\lambda_v t + \phi_v)$ for the

ventral side, the resultant activity for the muscle row becomes $r(t) = d(t) - v(t)$. Substituting in we get

$$r(t) = \alpha_d \sin(\lambda_d t + \phi_d) - \alpha_v \sin(\lambda_v t + \phi_v) \tag{2}$$

3   Based on experimental data we know that the dorsal and ventral wavelengths are equal ($\lambda_d = \lambda_v$).

4   Additionally, and without loss of generality, we can assume that the ventral phase offset can be calculated

5   in relation to the dorsal wave. This simplifies the equation to

$$r(t) = \alpha_d \sin(\lambda t) - \alpha_v \sin(\lambda t + \phi_{v-d}) \tag{3}$$

Since the two sine waves have same wavelength, the results of subtracting them will be a new sine wave

with the same wavelength, but a different amplitude and phase offset. We can determine these values by

treating the dorsal and ventral waveforms as two vectors $\vec{\boldsymbol{d}} = \langle \alpha_d, \angle 0° \rangle$ and $\vec{\boldsymbol{v}} = \langle \alpha_v, \angle \phi_{v-d} \rangle$ and then

calculate the vector $\vec{r} = \vec{\boldsymbol{d}} - \vec{\boldsymbol{v}}$ using the trigonometric technique (Hecht, 2017).

Figure 4A shows a conceptual representation of this method where the vectors $\vec{v}, \vec{r},$ and $\vec{\boldsymbol{d}}$ form a

scalene triangle. To calculate the amplitude and phase offset of $\vec{r}$, the triangle formed by these vectors

can be solved, Using the law of cosines, α_r, the amplitude of $\vec{r}$, can be calculated with the following

equation

$$\|\vec{r}\| = \alpha_r = \sqrt{\alpha_v{}^2 + \alpha_d{}^2 - 2\alpha_v \alpha_d \cos(\phi_{v-d} - \pi)} \tag{4}$$

14   Similarly, the phase offset between $\vec{r}$ and $\vec{\boldsymbol{d}}$, can be computed using the law of sines

$$\theta_{r-d} = \sin^{-1}\left(\frac{\alpha_v \sin(\phi_{v-d} - \pi)}{\alpha_r} \right) \tag{5}$$

15   Since the amplitude of the dorsal and ventral sides are nearly equal to one another, $\alpha_d \approx \alpha_v$, the triangle

16   formed by $\vec{v}, \vec{r},$ and $\vec{\boldsymbol{d}}$ could also be treated as isosceles. Under this assumption, the equation for

17   determining the amplitude of $\vec{r}$ becomes much simpler

$$\|\vec{r}\| = \alpha_r = \alpha_d \cos\left(\frac{\phi_{v-d} - \pi}{2}\right) \qquad (6)$$

2   and the equation for determining the phase offset simplifies to

$$\theta_{r-d} = \frac{\phi_{v-d} - \pi}{2} \qquad (7)$$

Using standard deviation information from Figures 1B & C, we determined the average peak-to-peak

amplitude of the dorsal and ventral sine waves for the muscle cells by using the well know conversion

method from Equation 1 (Smith, 1999).

Figure 4B shows a comparison of waveforms recorded for the dorsal and ventral muscles in the 13th

muscle row and sine waves that were generated from the computed amplitude, frequency, and phase

offset collected during this study. The results are a very close approximation to the actual data. We also

generated the sine waves that result from subtracting the ventral from dorsal signals using both the

scalene and isosceles trigonometric methods presented in Equations 2-7. Figure 4C shows the

comparison between the recorded difference and the computed differences using these two methods.

Again, the results show a very close approximation to the actual data. Finally, Figure 4D-6G show the

recorded amplitudes and accumulated drift for muscle rows 6-24 during forward and reverse locomotion

and the calculated approximations. The calculated results for forward locomotion amplitude and drift,

along with the reverse amplitude, are a very close fit to the actual data. However, the accumulated drift in

reverse deviates from recorded values, although the calculated values are still a reasonable

approximation.

These results confirm that the overall muscle activation pattern seen in *C. elegans* could result from

muscle activation waves that travel down the dorsal and ventral sides at different rates.

Figure 4: Mathematical analysis of forward and reverse body wave propagation.

A) Trigonometric method for determining the resultant phase shift θ_{r-d} and amplitude $\|\vec{r}\|$ of the muscle activity that results from off-

phase dorsal and ventral muscle activation. The vector $\vec{d}$ represents dorsal activity, $\vec{v}$ represents ventral activity, ϕ_{v-d} is the phase

difference between $\vec{d}$ and $\vec{v}$, and $\vec{r}$ represents the resultant vector. B) Comparison between actual dorsal and ventral signals

recorded from muscle row 13 (solid lines) and signals that were generated using the mean, standard deviation, and mean phase

shift information computed in this study (dashed lines). The generated signals very closely approximate the recorded activity. C)

Comparison of recorded muscle row 13 dorsal-ventral activity and the generated signals that result from applying the scalene and

isosceles methods for computing the resultant vector $\vec{r}$. The results of both methods agree well with the recorded activity. D)

Comparison of the recorded mean amplitude during forward locomotion and the values computed using the scalene and isosceles

methods. E) Comparison of the recorded accumulated drift and calculated accumulated drift during forward locomotion. In

agreement with Figure 5B, body wave propagation results from the combined activity of the dorsal and ventral sides. F)

Comparison of the recorded mean amplitude during reverse locomotion and the values computed using the scalene and isosceles

methods. G) Comparison of the recorded accumulated drift and calculated accumulated drift during reverse locomotion. In

agreement with Figure 5J, reverse body wave propagation results from the combined activity of the dorsal and ventral sides.

DISCUSSION

Using high-resolution wavelength switching to measure calcium transients in freely moving

worms

There are several advantages and disadvantages to using wavelength switching as the basis for

measuring calcium transients in freely moving worms. Unlike other techniques that require projecting

multiple images onto the imaging sensor (Butler, et al., 2015), one of the key advantages of performing

wavelength switching is the ability to take very high-resolution images of the specimen. Our system, for

instance, uses a Zyla-4.2P-CL10 sCMOS camera that can take images at a resolution of up to 4

megapixels (2048 X 2048). If we assume that the length of the worm's body fills half of the viewable area

of the camera, this provides approximately 1024 pixels of resolution along the A-P axis. At such a high

resolution, the worm's body can be partitioned according to the location of the individual muscle cells

making it much easier to attribute intensity changes to muscle activity. In addition, by taking large spatial

samples of each cell, we can compensate for camera noise by averaging (filtering) the recorded

intensities over many pixels. At the resolution and zoom used in collecting our data, for example, each

muscle cell is spatially sampled using an average of about 4,500 pixels.

Obtaining images at such high resolution comes at the expense of temporal resolution. Switching

between just two wavelengths can cause a significant drop in the frame rate especially if one of the

wavelengths comes from a mechanically shuttered light source. On our system, the mechanical shutter

on the transmitted brightfield source takes approximately 12 ms to open or close. When combined with

the exposure, transfer, processing, compression and storage time, this leads to a sample rate of just 14.2

samples per second.

For measuring calcium transients in muscle cells, this sampling rate is more than adequate. Muscle cells

have a calcium transient frequency of approximately 0.45 – 0.48 Hz (Karbowski, et al., 2008). With a

sample rate of 14.2 samples per second, our system captures 31 measurements during each wavelength

of a muscle cell's oscillation. Given that the sampling criteria (also known as the Nyquist criteria) only

requires a sampling rate that is twice the signal frequency (Shannon, 1949) in order to be identified, our

system is more than capable of accurately capturing and characterizing muscle calcium transients.

However, if the goal were to capture muscle cell action potentials in freely moving worms using

optogenetic techniques with faster kinetics, like the genetically encoded voltage indicator QuasAr

(Hashemi, et al., 2019), then the sample rate would need to be increased. According to

electrophysiological measurements, a BWM action potential has a duration of 96.3 ± 5.7 ms (Liu, et al.,

2011). Therefore, the sample rate would need to be increased to at least 21 samples per second in order

to meet the sampling criteria. This could easily be achieved in our system by using binning to reduce

image resolution, replacing the mechanically shuttered light source, and/or reducing the exposure time.

Varying rigidity through muscle activity

It is certainly not unheard of for invertebrates to use their muscles to alter body rigidity. For example, it is

believed that lampreys modulate their stiffness using appropriately timed muscle contractions to create

rigidity in their tail while swimming. This strategy allows the organism to transfer positive work from

anterior muscles through the tail to the surrounding fluid (Tytell, et al., 2010).

Although we do not believe that *C. elegans* uses a similar strategy during crawling, our results suggest

that the worm uses its muscles to selectively alter rigidity in areas that are being used to produce the

greatest amount of locomotive force. Because our measurements were normalized using maximum,

F_{4AP}, instead of mean, F_0, fluorescence intensity, we were able to see that 1) mean intensities are the

same in dorsal/ventral contralateral muscle pairs throughout the entire body during both forward and

reverse locomotion and 2) there are significantly elevated anterior (posterior) mean intensity levels that

linearly decrease to significantly lower posterior (anterior) mean intensity levels during forward (reverse)

locomotion. When these results are combined with the findings that GCaMP fluorescence intensity is

associated with muscle length (Liu, et al., 2011)*,* that muscle length is associated with cuticle stiffness

(Petzold, et al., 2011)*,* and that muscle waves decrease as they travel through the body (Xu, et al., 2018),

they support this conclusion.

Our results in no way suggest that previously measured values of the Young's modulus of *C. elegans* are

inaccurate (Park, et al., 2007; Fang-Yen, et al., 2010; Sznitman, et al., 2010). They do, however, highlight

that current techniques used to measure this value produce a mean (whole body) value that does not

account for varying stiffness due to muscle activity.

Figure 5: Kymographs of forward and reverse locomotion

A) Sample kymograph of body wave propagation over time during forward locomotion of the same worm and video segment as

Figure 7A-I. B) Sample kymograph of the dorsal – ventral Ca++ activation over time during forward locomotion of the same worm

and video segment as Figure 7A-I. C) Kymograph of body wave propagation over time during reverse locomotion of the same worm

and video segment as Figure 7J-R. D) Kymograph of the dorsal – ventral Ca++ activation over time during reverse locomotion of the

same worm and video segment as Figure 7J-R.

Dorsal and Ventral Neuromechanical Phase Lag

Neuromechanical Phase Lag (NPL) is characterized by an increase in the phase difference between body

bending and muscle activation as a locomotion wave travels from source to destination (McMillen, et al.,

2008). NPL have been discovered in several organisms including eels, lampreys, and sandfish

(McMillen, et al., 2008; Tytell, et al., 2010; Ding, et al., 2013).

Previous theoretical and empirical studies show that *C. elegans* lacks a NPL and instead has a fixed

phase offset between bend angle and muscle activation throughout the entire body during forward

locomotion (Fang-Yen, et al., 2010; Butler, et al., 2015). Our results agree with these findings and extend

them to include reverse locomotion as well. Figure 2B & J show the results of comparing the propagation

of the body and combined muscle activation waves for forward and reverse. Because these results are

not adjusted for the kinetics of GCaMP, they show an equal accumulated drift over the entire propagation

of the wave. These results agree with the raw results recorded by Butler et al. during forward crawling

(Butler, et al., 2015).   Figure 5 shows kymographs for the bend angle and difference in Ca^{++} intensity

between the dorsal and ventral sides for both forward and reverse locomotion. The red lines are overlaid

to show zero crossing of each body wave and are copied onto the calcium activation kymographs for

reference. Note that the lines are nearly perfectly aligned with the zero crossings of the activation graphs

indicating a phase offset of 0 degrees.

Our results, however, also show a previously unreported phenomena where the dorsal and ventral

activation waves travel at different rates in relationship to both body bending and each other. Figure 2B,

for instance, shows that during forward locomotion, the dorsal activation waves travels 41% faster (1.88s

versus 2.66s) than the body bending wave. In addition, the ventral wave travels 57% faster than the

dorsal wave (1.18s versus 1.88s). This graph, along with Figure 2J for reverse, show clear NPLs when

the two sides of the worm are considered independently of each other.

Given that it is currently believed that the presence of an NPL indicates that wave propagation is primarily

driven by one or more CPGs (Tytell, et al., 2010; Denham, et al., 2018), these results lend considerable

support to the hypothesis that CPGs play a significant role in the generation and propagation of

locomotive waves in *C. elegans*. Our findings suggest that there may be independent dorsal and ventral

CPGs that are coordinated with one another during both forward and reverse locomotion.

Several studies have reported finding CPG activity in the ventral nerve cord. Two studies, for example,

reported that B-type motor neurons (MN) may function as oscillators to drive forward locomotion (Wen, et

al., 2012; Fouad, et al., 2018). Additional studies have reported that AS MNs may form oscillators with

DA and DB neurons (Olivares, et al., 2017; Tolstenkov, et al., 2018) and that A-type MNs (particularly

DA9) may also be rhythmic in nature (Gao, et al., 2017).

It has also been shown that proprioception plays an important role in regulating the activity of these CPGs

(Wen, et al., 2012) and that D and AS MNs work to coordinate the dorsal and ventral sides. For example,

AS MNs have been shown to drive dorsal BWMs while simultaneously activating VD MNs that down

regulate the activity of ventral BWMs (Tolstenkov, et al., 2018). A recent study of D-type MNs has also

shown that impairing the function of the cells leads to decreased coordination, undulation frequencies,

and locomotion speed (Deng, et al., 2020).

These impairments could certainly be explained using a model where the two sides of the worm exhibit

proprioceptive modulated CPGs that are coordinated with one another. By recognizing that muscle

activity in different regions of the body become potentiated and/or attenuated by a lack of proper phase

alignment, it is easy to see that removing coordination between the dorsal and ventral sides would result

in decreased speed, increases and decreases in bend angles, and altered bend angle frequencies.

Figure 6: Image processing steps used to quantify bend angles and muscle calcium signals.

A) Series of brightfield images of *C. elegans* during forward locomotion. Images are taken at an interval of 191ms. B) Series of

corresponding GFP images of *C. elegans* during forward locomotion. Images are taken at an interval of 191ms. C) Series of

brightfield images of *C. elegans* during reverse locomotion. Images are taken at an interval of 191ms. D) Series of corresponding

GFP images of *C. elegans* during reverse locomotion. Images are taken at an interval of 191ms. E) Bright field image of a freely

moving *C. elegans*. F) Bright field image converted to a binary image with the border outline and skeleton. The blue outer border

indicates the dorsal side and the red outer border indicates the ventral side. The midline (cyan) is segmented according to the

midpoints of the muscle cells (green). Note that muscles 1 and 2 are located directly on top of each other. G) The outline and

midline are used as a template for the GFP image. H) Individual outlines for each of the muscle cells are analyzed to determine

their Ca++ concentration. To account for cell overlap, a distance weighted average is computed.

MATERIALS & METHODS

***C. elegans* Growth Conditions and Strains:** *C. elegans* were grown at 20˚C on NGM lite plates containing streptomycin and nystatin; seeded with OP50-1 as a bacteria food source (Brenner, 1974). All experiments were completed with young adults, age-synchronized by picking L4 stage animals to fresh food plates 12-24 h before the experiment. Strains used in this study were N2 and HBR4: goels3[myo-3p::SL1::GCamP3.35::SL2::unc54 3'UTR + unc-119(+)] (Schwartz, et al., 2012).

Single Worm Tracking Protocol: A worm was transferred using a platinum worm pick into an 80μL drop of H_2O on a glass microscope slide at room temperature to remove residual bacteria. After 30 seconds, the worm was transferred to a 1.5μL drop of H_2O on a modified NGM lite plate (1/20 w/w reduction in peptone). The plate was immediately transferred to the microscope for tracking. The 1.5μL drop of water absorbs into the plate within 2 min allowing for transfer and focusing prior to tracking. Worms were tracked under rapid wavelength switching conditions at room temperature, explained below, and each experiment was concluded after four minutes of recording.

Image Capture: Images were acquired using a Leica DMi8, X-Cite XLED1 (Lumen Technologies), Zyla-4.2P-CL10 sCMOS camera (Andor), and in-house software (CNAS tracker). During recording, subsequent images were captured under brightfield and GFP (~470 nm) illumination. The synchronization of image capture and wavelength switching was accomplished using an Arduino-based sequencer that triggered the XLED1, brightfield shutter on the DMi8, and Zyla-4.2P. To account for the delay associated with the mechanical shutter on the brightfield light source, a 12 ms delay was introduced between wavelength changes. Images were captured at 2048 x 2048 using a 10x objective and an exposure time of 9.8 ms. Brightfield and fluorescence intensities and aperture settings were unchanged between samples. Frames were stored on a hard drive using a custom video format called Rapid Video Compression (RVC). Each frame was annotated with a time stamp, stage position, and the lighting conditions. Average frame time was 36 ms. Figure 6A – D shows the results of this process for both forward and reverse locomotion. In Figure 6A & C, the brightfield images are shown, while in Figure 6B & D the corresponding GFP images are shown. To emphasis the changing patterns seen in the GFP signal as the worm moves, these images show every third frame pair (191 ms interval) captured by our system.

Worm tracking: Worms were tracked using in-house software (CNAS tracker), which controlled the

stage on the DMi8. The worm was identified in each brightfield frame by searching from the center of the

last bounding region in expanding concentric circles for a seed pixel (a pixel below a given threshold).

Once a seed pixel was identified, a threshold-based scan line flood fill algorithm was used to determine a

bounding region. An offset between the center of the frame and the center of the bounding region was

then calculated and if greater than 50 pixels, the stage was repositioned.

Video Analysis: Videos were hand partitioned into segments of forward and reverse locomotion using in-

house video editing software (RVC editor). Each video segment was then analyzed using in house video

analysis software (Worm Analyzer). During video processing, brightfield and GFP frames were analyzed

in pairs. Brightfield images (Figure 6E) were converted to binary using a threshold algorithm. Holes were

filled in and small objects were removed using a combination of dilation and erosion operations. A seed

pixel was then located in a similar manner to the method used for worm tracking.

To determine the shape of the worm's body, a border following algorithm was used to trace the worm's

outline. The head and tail were then located by finding the maximum point of curvature along the outline,

which was identified as the tail, and the second maximum point of curvature, which was identified as the

head. The outline was then partitioned into left and right sides based on the head and tail location.

These sides were then manually identified as dorsal/ventral using the vulva location as a guide.

The centerline was created by tracing one side of the border and calculating the perpendicular to the

curvature at each point. This perpendicular was then intersected with the opposing side of the worm and

the center point of this line segment calculated. The center points were added to a data structure that

ordered them based on X and Y location and finally, gaps in the centerline were filled in between

subsequent centerline points as needed.

The skeleton was constructed by partitioning the centerline into 25-line segments using the head, tail, and

midpoints of the BWMs as end points. The midpoint locations of the muscle cells were used to calculate

the angles of the body (Figure 6F).

Because the stage can move between the brightfield and GFP images, analysis of the GFP frames began

by realigning the outline of the worm with the GFP image. This was accomplished using a template

matching algorithm that maximizes the fluorescence signal within the outline (Figure 6G). A bounding

region for each muscle was then determined using the outer border, the anterior and posterior extents of

the muscle cell, and an inset border. The inset border mirrored the curvature of the outer border and was

placed 25 micrometers from the outer border but did not cross the centerline of the worm (Figure 6H).

Once the muscle regions were determined, the average intensity of each muscle cell was calculated

using a modified scanline flood fill algorithm. To account for the shape of the muscle cells, weights were

assigned to each pixel's value based on its distance from the center of the muscle cell. This technique

placed higher weight on the pixels in the thickest and least overlapping portions of the muscle cell.

Relative fluorescence Intensity (RFI) was then calculated by subtracting the average background

fluorescence from the weighted fluorescence intensity of the region.

Results of the image analysis were stored in Comma Separated Values (CSV) format files. For each pair

of frames, a single line was recorded with the timestamp, X and Y stage location, the 24 angles, and 48

intensities of the muscle cells along the body. Figure 7A-R show traces of the bend angles and muscle

cell activation during forward and reverse locomotion for the 3rd, 13th, and 23rd muscle groups.

Forward

Muscle Row 3   Muscle Row 13   Muscle Row 23

Reverse

Muscle Row 3   Muscle Row 13   Muscle Row 23

Figure 7: Trace of the bend angles and calcium concentrations for three locations along the AP axis during forward and reverse locomotion.

A-C) Forward locomotion bend angle data for the 3rd, 13th, and 23rd muscle rows, which are located in the head, mid-body and tail, respectively. The head moves rapidly from side to side, while the pattern at the mid-body and tail are very sinusoidal and have nearly the same amplitude. D-F) The normalized GFP intensity of the ventral and dorsal muscles during forward locomotion at the 3rd, 13th, and 23rd muscle row. At the head, the signals are nearly perfectly in phase and bare a close resemblance to the changes in bend angle. At the mid-body, the pattern becomes clearly anti-phasic with the same amplitude as the head muscles. At the tail, the signals are nearly in phase again, but considerably less intense than the head or mid-body. G-I) The normalized difference between the dorsal and ventral GFP intensities at the 3rd, 13th, and 23rd muscle rows during forward locomotion. Within the head, the difference in intensity is only weakly correlated with the bend angle. However, at muscle rows 13 and 23, the bend angles and difference in intensities are highly correlated. J-L) Bend angle data for the 3rd, 13th, and 23rd muscle rows during reverse locomotion. The bend angles are clearly sinusoidal throughout the body. Rapid head movement, however, is suppressed. M-O) Normalized

4-Aminopyridine inhibition: To normalize for the expression pattern of myo3p::GCamp3, we conducted

experiments to measure the Ca^{++} levels in worms (n=10) that were exposed to the K^+ channel blocker 4-

AP. Exposure to 4-AP causes dramatic and sustained activation of the muscle cells throughout the body

because the cells lose the ability to repolarize. This allowed us to record "maximum" Ca^{++} levels for the

BWMs (Figure 1A).

One day old adults were incubated in a 60 µL drop of 500 mM 4-Aminopyridine (4-AP) on a glass slide for

6 minutes in a humidified chamber. Following the 6-minute incubation, the worms were transferred

directly to a 1.5 µL drop of 500 mM 4-AP on a tracking plate. Once the 500 mM 4-AP absorbed into the

plate (this process takes approx. 1 minute), tracking was started and continued for 45 seconds (n=10).

Data Analysis: The data files produced from the image analysis were batch analyzed using a

combination of the Worm Analyzer and Microsoft Excel. During analysis, aggregate amplitude statistics

were gathered for each individual body bend angle, body bend speed, muscle cell activation, and the

difference between activation of the ventral and dorsal muscle cells in the same muscle row. These

statistics included minimum, maximum, mean, and standard deviation (Figures 1A-C and Figures 3A, B,

H & I).

The data was analyzed for a second time to generate normalized intensity levels (Figures 1D & E).

During this pass, recorded intensity levels were divided by the mean intensity level of the muscle cell

recorded during the 4-AP experiment. These values are reported as F/F_{4AP} in the figures.

These files were then processed using custom software written in Java for frequency and correlation

information. Frequency information was gathered using a Fast Fourier Transform (FFT) over discrete

segments of the input files. Frequency information was aggregated and normalized, so the magnitude

reported for each frequency component is the mean magnitude across the segments divided by the

maximum mean frequency component.

Correlation analysis was also conducted between ventral, dorsal, activation difference and bend angles

(Figure 3C & J). Additionally, autocorrelation was conducted between ventral and dorsal muscles

(Figures 2A, C-H and Figures 2I, K-P), and between subsequent muscle rows (Figures 2B & J).

This aggregate data was saved in a text file for further processing in Excel.

Experimental design and statistical analysis: For HBR4 experiments n=25 worms were tracked. This

produced 96 video files of forward locomotion and 111 files of reverse locomotion. In total, 46,226 frame

pairs or 3,316.15 seconds of forward locomotion and 6,610 frame pairs or 472.59 seconds of reverse

locomotion were analyzed. Average frame rate was ~28 frames per second.

For HBR4 worms exposed to 4-AP, n=10 worms were tracked. Since these worms are paralyzed, the

videos did not need to be partitioned between forward and reverse. Therefore, 10 files consisting of

3,570 frame pairs or 303.85 seconds of video were produced. This video averaged ~25 frames per

second.

Statistical means and deviations were computed in the standard way. Values were normalized using

either the maximum recorded value (for frequency normalization) or the mean value recorded from 4-AP

experiments (normalized intensities). FFT analysis was conducted using a window size of 128 samples

for forward locomotion resulting in 315 fragments, each about 9 seconds in length. With this window size

and an average sample rate of 14.24 samples/second, the maximum detectable frequency is about 7Hz

with a frequency resolution of 0.11 Hz.

Because of the short duration of reverse locomotion, the window size of the FFT was reduced to 32

samples. This resulted in 149 fragments that were each approximately 2.2 seconds in length. The

average sample rate of this data was 14.6 samples/sec resulting in a maximum detectable frequency of

about 7Hz with a frequency resolution of 0.45Hz.

Correlation was computed using the formula for the Pearson correlation coefficient over the data within

window (128 for forward and 32 for reverse).

$$r_{x,y} = \frac{\sum_{i=1}^{n}(x_i - \bar{x})(y_i - \bar{y})}{\sqrt{\sum_{i=1}^{n}(x_i - \bar{x})^2 * \sum_{i=1}^{n}(y_i - \bar{y})^2}} \tag{8}$$

Autocorrelation was conducted by sliding one signal over the other within the window and calculating the

correlation coefficient at each offset. The offset was limited to one-half the wavelength in both positive

and negative directions. Ventral and dorsal offsets and accumulated drift were calculated using the

average offset with the maximum correlation coefficient.

Statistical significance testing was performed using paired, two-tailed t-tests. Data is presented as mean

± SEM using Microsoft Excel unless otherwise noted.

Code, Software, and Data Accessibility: All code and software developed during this study are

available from the corresponding author upon request. All videos and data collected used in this article

may also be requested. However, due to the size of the video files they will not be available for

download. Under these circumstances, special arrangements can be made.

ACKNOWLEGEMENTS

12 Some strains were provided by the CGC, which is funded by NIH Office of Research Infrastructure

13 Programs (P40 OD010440). Special thanks to James Rand for his helpful input and assistance. This

14 work was supported by US Air Force Office of Sponsored Research under grants FA9550-15-1-0060 and

15 FA9550-18-1-0308.

COMPETING INTERESTS

17 The authors of this article declare that they have no financial or non-financial competing interests.

REFERENCES

Alkema, M. J., Hunter-Ensor, M., Ringstad, N. & Horvitz, H. R., 2005. Tyramine Functions Independently

of Octopamine in the Caenorhabditis elegans Nervous System. *Neuron,* 46(2), pp. Pages 247-260.

Baek, J.-H.et al., 2002. Using machine vision to analyze and classify Caenorhabditis elegans behavioral

phenotypes quantitatively. *Journal of Neuroscience Methods,* 118(1), pp. 9-21.

Boyle, J. H., Bryden, J. & Cohen, N., 2007. *An Integrated Neuro-mechanical Model of C. elegans Forward*

Locomotion. s.l., s.n.

Brenner, S., 1974. The genetics of Caenorhabditis elegans. *Genetics,* 77(1), pp. 71-94.

Butler, V. J. et al., 2015. A consistent muscle activation strategy underlies crawling and swimming in

Caenorhabditis elegans.. *Journal of the Royal Society, Interface,* 12(102).

Chalasani, S. et al., 2007. Dissecting a circuit for olfactory behaviour in Caenorhabditis elegans. *Nature,*

Volume 450, p. 63–70.

Cook, S. J. et al., 2019. Whole-animal connectomes of both Caenorhabditis elegans sexes. *Nature,*

Volume 571, pp. 63-71.

Cronin, C. J. et al., 2005. An automated system for measuring parameters of nematode sinusoidal

movement. *BMS Genetics,* Volume 6.

Deng, L. et al., 2020. Inhibition underlies fast undulatory locomotion in C. elegans. *bioRxiv.*

Denham, J. E., Ranner, T. & Cohen, N., 2018. Signatures of proprioceptive control in Caenorhabditis

elegans locomotion. *Philosophical transations B,* Volume 373.

Ding, Y., Sharpe, S. S., Wiesenfeld, K. & Goldman, D. I., 2013. Emergence of the advancing

neuromechanical phase in a resistive force dominated medium. *PNAS,* 110(25), pp. 10123-10128.

Fang-Yen, C. et al., 2010. Biomechanical analysis of gait adaptation in the nematode Caenorhabditis

elegans. *PNAS,* 107(47), pp. 20323-20328.

Fouad, A. D. et al., 2018. Distributed rhythm generators underlie Caenorhabditis elegans forward

locomotion. *eLife,* 7(e29913).

Gao, S. et al., 2017. Excitatory motor neurons are local oscillators for backward locomotion. *eLife,*

Volume 6, p. e29915.

Goodman, M., 2006. Mechanosensation. In: *WormBook.* s.l.:s.n., pp. 1-14.

Hashemi, N. A. et al., 2019. Rhodopsin-based voltage imaging tools for use in muscles and neurons of

Caenorhabditis elegans. *PNAS,* 116(34), pp. 17051-17060.

Haspel, G., O'Donovan, M. J. & Hart, A. C., 2011. Motorneurons dedicated to either forward or backward

locomotion in the nematode C. elegans. *Journal of Neuroscience,* 30(33), pp. 11151-11156.

Hecht, E., 2017. *Optics.* 5th ed. s.l.:Peason Education.

Karbowski, J. et al., 2008. Systems level circuit model of C. elegans undulatory locomotion: mathematical

modeling and molecular genetics.. *J. Comput. Neurosci.,* Volume 24, p. 253–276.

Liu, P. et al., 2011. Genetic dissection of ion currents underlying all-or-none action potentials in C.

elegans body-wall muscle cells. *Journal of Physiology,* Volume 589.1, pp. 101-107.

McMillen, T., Williams, T. & Holmes, P., 2008. Nonlinear muscles, passive viscoelasticitiy and body taper

conspire to create neuromechanical phase lags in anguilliform swimmers. *PLoS Computational Biology,*

4(8).

Niebur, E. & Erdos, P., 1991. Theory of the locomtion of nematodes. *Journal of Biophysics,* pp. 1132-

1146.

Olivares, E. O., Izquierdo, E. J. & Beer, R. D., 2017. Potential role of ventral nerve cord central pattern

generator in forward and backward locomotion in Caenorhabditis elegans. *Network Neuroscience,* 2(3),

pp. 323-343.

Park, S.-J., Goodman, M. B. & Pruitt, B. L., 2007. Analysis of nematode mechanics by piezoresistive

displacement clamp. *PNAS,* 104(44), pp. 17376-17381.

Petzold, B. C. et al., 2011. Caenorhabditis elegans Body Mechanics are Regulated by Body Wall Muscle

Tone. *Biophysical Journal,* Volume 100, pp. 1977-1985.

Pierce-Shimomura, J. T. et al., 2008. Genetic analysis of crawling and swimming locomotory patterns in

C. elegans.. *Proceedings of the National Academy of Sciences,* 105(52), pp. 20982-7.

Schwartz, J., Spies, J.-P. & Bringmann, H., 2012. Reduced muscle contraction and a relaxed posture

during sleep-like Lethargus. *Worm,* 1(1), pp. 12-14.

Shannon, C. E., 1949. Communication in the presence of noise. *Proceedingf of the Institute of Radio*

Engineers, 37(1), pp. 10-21.

Smith, S. W., 1999. *The Scientist and Engineer's Guide to Digital Signal Processing.* 2nd ed.

s.l.:California Technical Publishing.

Sznitman, J. et al., 2010. Material Properties of Caenorhabditis elegans Swimming at Low Reynolds

Number. *biophysical Journal,* 98(4), pp. 617-626.

Tolstenkov, O. et al., 2018. Functionally asymmetric motor neurons contribute to coordinating locomotion

of Caenorhabditis elegans. *eLife,* Issue e34997.

Tytell, E. D. et al., 2010. Interations between internal forces, body stiffness, and fluid environment in a

neuromechanical model of lamprey swimming. *PNAS,* 107(46), pp. 19832-19837.

Varshney, L. R. et al., 2011. Structural Properties of the Caenorhabditis elegans Neuronal Network.

PLOS Computational Biology.

Wen, Q. et al., 2012. Proprioceptive Coupling within motor Neurons Drives C. elegans Forward

Locomotion. *Neuron,* Volume 76, pp. 750-761.

White, J. G., SouthGate, E., Thomas, J. N. & Brenner, S., 1986. The Structure of the Nervous System of

the Nematode Caenorhabditis elegans. *Philosphical Transations of the Royal Society of London,* Volume

Series B, Biological Sciences, pp. 1-340.

Xu, T. et al., 2018. Descending pathway facilitates undulatory wave propagation in Caenorhabditis

elegans through gap junctions. *Proceedings of the National Academy of Sciences,* 115(19), pp. E4493--

E4502.

A

B

Muscle Row 13

Ventral — Dorsal — Calc Ventral — — Calc Dorsal — —

Intensity (F)

Time (sec)

C

Muscle Row 13

Difference — — Calc (Scalene) ·········· Calc (Isosceles) ··········

Dorsal - Ventral

Time (sec)

D

Forward Amplitude

Difference — — Calc (Scalene) ·········· Calc (Isosceles) ··········

Intensity (F)

Muscle Row

E

Forward Accumulated Drift

Difference — — Calc (Scalene) ·········· Calc (Isosceles) ··········

Offset (sec)

Muscle Row

F

Reverse Amplitude

Difference — — Calc (Scalene) ·········· Calc (Isosceles) ··········

Intensity (F)

Muscle Row

G

Reverse Accumulated Drift

Difference — — Calc (Scalene) ·········· Calc (Isosceles) ··········

Offset (sec)

Muscle Row

Forward

A   Normalized Angle

B   Normalized Difference (D-V)

Reverse

C   Normalized Angle

D   Normalized Difference (D-V)

Forward

	Muscle Row 3	Muscle Row 13	Muscle Row 23
Bend Angle	A	B	C
Muscle Activation	D	E	F
D-V Activation	G	H	I

Reverse

	Muscle Row 3	Muscle Row 13	Muscle Row 23
Bend Angle	J	K	L
Muscle Activation	M	N	O
D-V Activation	P	Q	R