Title: Reliability of neural entrainment in the human auditory system

Abbreviated title: Reliability of neural entrainment

Authors: Yuranny Cabral-Calderin[1]* & Molly J. Henry[1]*

Affiliations: [1]Max Planck Institute for Empirical Aesthetics, 60322, Frankfurt am Main,
Germany.

* Corresponding author email address:

yuranny.cabral-calderin@ae.mpg.de

molly.henry@ae.mpg.de

Acknowledgments: This work was supported by a European Research Council Starting
Grant (BRAINSYNC) and a Max Planck Society Research Group granted to MJH. We
thank Nicole Huizinga for helping with the data collection. We thank Hanna Kadel,
Dominik Thiele, and Johannes Messerschmidt for technical support and for helping with
the EEG preparation and participants recruitment. We also thank Cornelius Abel for
technical support.

Abstract

Auditory stimuli are often rhythmic in nature. Brain activity synchronizes with auditory rhythms via neural entrainment, and entrainment seems to be beneficial for auditory perception. However, it is not clear to what extent neural entrainment in the auditory system is reliable over time – a necessary prerequisite for targeted intervention. The current study aimed to establish the reliability of neural entrainment over time and to predict individual differences in auditory perception from associated neural activity. Across two different sessions, human listeners detected silent gaps presented at different phase locations of a 2-Hz frequency modulated (FM) noise while EEG activity was recorded. As expected, neural activity was entrained by the 2-Hz FM noise. Moreover, gap detection was sinusoidally modulated by the phase of the 2-Hz FM into which the gap fell. Critically, both the strength of neural entrainment as well as the modulation of performance by the stimulus rhythm were highly reliable over sessions. Moreover, gap detection was predictable from pre-gap neural 2-Hz phase and alpha amplitude. Our results demonstrate that neural entrainment in the auditory system and the resulting behavioral modulation are reliable over time, and that both entrained delta and non-entrained alpha oscillatory activity contribute to near-threshold stimulus perception. The latter suggests that improving auditory perception might require simultaneously targeting entrained brain rhythms as well as the alpha rhythm.

Introduction

Auditory stimuli, such as music and speech, are often (quasi-)rhythmic in nature. As such, one neural mechanism that has received much recent attention for its contribution to auditory perception is synchronization of brain activity to sound rhythms: *neural entrainment* (Obleser and Kayser, 2019). Neural entrainment is the process by which neural activity phase locks to sensory rhythms, and has been proposed to be a key mechanism for controlling sensory gain (Lakatos et al., 2008; Obleser and Kayser, 2019), attention, and parsing (Giraud and Poeppel, 2012) sensory information that is extended in time.

Neural entrainment has been described for different sensory modalities (Henry and Obleser, 2012; Mathewson et al., 2012; Ten Oever et al., 2017) and different species (Lakatos et al., 2016; Garcia-Rosales et al., 2018). In humans, low-frequency delta/theta activity synchronizes to the rhythms of speech and music, and synchronization success seems to be critical for successful auditory perception (Doelling et al., 2014; Doelling and Poeppel, 2015), in particular in noisy listening situations (Horton et al., 2013; Zion Golumbic et al., 2013; Brodbeck et al., 2020).

If neural entrainment does play a critical mechanistic role for auditory perception, *improving* synchrony between brain activity and stimulus rhythms should result in benefits for perception. In fact, recent work using transcranial electrical stimulation (TES) with alternating current (tACS) to interfere with entrainment reported significant modulation of speech comprehension and stream segregation (Riecke et al., 2015; Riecke et al., 2018; Wilsch et al., 2018; Zoefel et al., 2018; Cabral-Calderin and Wilke, 2020). However, there is uncertainty in tACS results (Erkens et al., 2020), and its efficacy for modulating neural entrainment is still under debate. This is at least in part because TES effects are state-dependent and variable across participants (Cabral-Calderin et al., 2016; Kasten et al., 2019), meaning that the same TES parameters might not be optimal for all participants, or even for one participant under all circumstances. In particular, successfully interfering with neural entrainment likely depends on targeting the right frequency (Stecher and Herrmann, 2018) and stimulus–brain phase relationship (van Bree et al., 2021), which may vary from person to person or from day to day. Here, we aimed to establish the reliability of neural entrainment over time. In doing so, our goal was to demonstrate the viability of an approach

whereby individualized TES protocols can be based on entrainment signatures measured

in a separate EEG session without the need for concurrent electrophysiological measures

while the electrical stimulation is applied, which is very challenging.

Not all stimuli are rhythmic. Thus, multiple neural processing modes have been proposed:

"rhythmic-mode" and "continuous-mode" processing (Schroeder and Lakatos, 2009;

Henry and Herrmann, 2012), only the former of which relies on neural entrainment. Even

in the case of rhythmic stimulation, entrainment lapses are associated with periods of high-

amplitude alpha oscillations (Lakatos et al., 2016), and higher alpha amplitude has also

been related to reduced entrainment-driven behavioral modulation (Henry et al., 2017).

Taken together, these findings suggest that alpha activity and entrainment represent

interacting neural strategies that can comodulate behavior. Here, in addition to examining

the influence of entrained neural activity on auditory perception (Henry et al., 2014; Bauer

et al., 2018), we took the influence of alpha activity into account in order to provide a more

complete picture of the neural mechanisms underlying auditory perception in a vigilance

task utilizing rhythmic stimuli.

Across two EEG sessions, participants detected silent gaps in ongoing frequency-

modulated (FM) stimuli (**Fig. 1,** Henry and Obleser, 2012). We expected that the 2-Hz

stimulus rhythm would entrain delta oscillations and, as such, gap detection would be

modulated by the phase of both the stimulus and the entrained neural oscillation in which

gaps occurred. We show that, while neural entrainment and stimulus-driven behavioral

modulation are highly reliable across sessions, auditory perception cannot be exclusively

explained by entrained low-frequency neural activity: both entrained delta phase and non-

entrained alpha activity contribute to moment-by-moment variations in auditory

perception.

Materials and Methods

Main experiment

Participants

Forty-one healthy participants took part in the study. Three participants were excluded from further analysis due to noisy EEG data (1 participant) and poor task performance (i.e., detection rate < 0.25, 2 participants). Results presented in this manuscript include data from 38 participants (21 females, four left-handed, mean age = 26.03 with SD = 4.6 years old). Each participant took part in two sessions separated by 2–42 days (median: 7 days). All participants self-reported normal-hearing and normal or corrected-to-normal vision. All participants were either native German speakers (n = 37) or spoke German with high proficiency (n = 1). At the time of the experiment no participant was taking medication for any neurological or psychiatric disorder.

Participants received financial compensation for their participation in the study. Written informed consent was obtained from all participants. The procedure was approved by the Ethics Council of the Max Planck Society and in accordance with the declaration of Helsinki.

Stimuli

Auditory stimuli were generated by MATLAB software at a sampling rate of 44,100 Hz. Stimuli were 20-s long complex tones frequency modulated at a rate of 2 Hz and with a center-to-peak depth of 67% (**Fig. 1**). The center frequency for the complex carrier signals was randomly chosen for each stimulus within the range of 1000-1400Hz. The complex carrier comprised 30 components sampled from a uniform distribution with a 500-Hz range. The amplitude of each component was scaled linearly based on its inverse distance from the center frequency; that is, the center frequency itself was the highest-amplitude component, and component amplitudes decreased with increasing distance from the center frequency. The onset phase of the stimulus was randomized from trial to trial, taking on one of eight values (0, $\pi/4$, $\pi/2$, $3\pi/4$, π, $5\pi/4$, $3\pi/2$, $7\pi/4$) with the constraint that each trial would always start with a phase different from its predecessor. All stimuli were rms-amplitude normalized. Three, four, or five silent gaps were inserted into each 20-s stimulus (gap onset and offset were gated with 3-ms half-cosine ramps) without changing the duration of the stimulus. Each gap was chosen to be centered in 1 of 18 equally spaced phase bins into which each single cycle of the frequency modulation was divided. No gaps

were presented either in the first or the last second of the stimulus. A minimum of 1.5 s

separated consecutive gaps.

Procedure

The experiment was conducted in an electrically shielded and acoustically isolated

chamber and under normal-illumination conditions. Sound-level thresholds were

determined for each participant according to the method of limits. All stimuli were then

presented at 55 dB above the individual hearing threshold (55 dB sensation level, SL).

Gap duration was individually adjusted to detection-threshold levels using an adaptive-

tracking procedure comprising two interleaved staircases and a weighted up-down

technique with custom weights. During this procedure, participants detected a gap within

a 4-s FM sound. Except for the duration, the sound had the same characteristics as in the

main experiment. The descending staircase started with a gap duration of 150 ms and the

ascending staircase started with a gap duration of 1 ms. If the participant detected the gap,

gap duration was decreased by some percent (5% for 10 ms ≤ gaps ≤ 35 ms, 20% for 35

ms < gaps ≤ 70 ms, or 50% for 70 ms < gaps || gaps < 10 ms) in the following trial of the

current staircase. On the contrary, if the participant did not detect the gap, gap duration was

increased by some percent (following the same convention as before) of the current gap

duration, in the following trial of the current staircase. Each staircase ended when four

reversals occurred in a span of six trials. The mean final gap duration across the two

staircases was chosen as the gap size for that participant in the main task. This resulted in

gap durations ranging from 11–28 ms across subjects and sessions (session 1: mean = 17.26

ms, SD = 3.42 ms, range = 12–28 ms; session 2: mean = 15.55, SD = 2.78, range = 11-21

ms).

Before starting the main experiment, participants performed practice trials to make sure

they understood the task. For the main experiment, EEG was recorded while listeners

detected gaps embedded in the 20-s long FM stimuli. Listeners were instructed to respond

as quickly as possible when they detected a gap via button-press. Overall, each listener

heard 216 stimuli (27 per starting phase). The number of gaps per stimulus was

counterbalanced (72 stimuli each included 3 gaps, 4 gaps, and 5 gaps) for a total of 864

gaps. For each of the 18 FM-phase bins, 48 gaps were presented. The number of phase bins

was chosen to balance having a good sampling resolution and a high number of trials per

condition without making the task too long. This combination of phase bins and trials

exceeds the recommendation for estimating the sinusoidal modulation of behavior with

high sensitivity (Zoefel et al., 2019). Including the EEG preparation, each experimental

session lasted about 3 hours.

Data Acquisition and Analysis

Behavioral data. Behavioral data were recorded online by MATLAB 2017a (MathWorks)

in combination with Psychtoolbox. Sounds were presented at a rate of 44.1kHz, via an

external soundcard (RME Fireface UCX 36-channel, USB 2.0 & FireWire 400 audio

interface) using ASIO drivers. Participants listened to the sounds via over-ear headphones

(Beyerdynamic DT-770 Pro 80 Ohms, Closed-back Circumaural Dynamic Diffuse field

equalization Impedance: 80 Ohm SPL: 96 dB Frequency range: 5–35,000 Hz). Button

presses were collected using a Cedrus response pad (RB-740). Hits were defined as button-

press responses that occurred no earlier than 100 ms and no later than 1.5 s after the

occurrence of a gap (Henry et al., 2014). This window was chosen because the upper limit

represents the minimum separation between gaps and therefore the response can easily be

assigned to a specific gap. Decreasing this window to maximum 1 s after gap onset

produced qualitatively similar results. Hit rates and RTs were calculated separately for each

of the 18 FM-phase bins. To estimate the FM-induced sinusoidal modulation of gap

detection behavior, a cosine function was fitted to hit rates as a function of FM phase for

each participant and session. From the fitted function, the amplitude parameter quantifies

the strength of behavioral modulation by 2-Hz FM phase, while the phase parameter

indexes the FM-stimulus–brain lag. Significance of the sinusoidal modulation was tested

using a permutation approach, whereby 1000 surrogate datasets were created for each

participant and session by shuffling the single-gap accuracy values (0,1) with respect to

their stimulus-condition labels. Cosine functions were also fitted to the surrogate datasets.

Gap detection was considered to be sinusoidally modulated for each participant if the

individual amplitude value was higher than the 99.9 percentile of the distribution of

amplitude values from the surrogate data, corresponding to $p < 0.05$, *Bonferroni* corrected

for 76 comparisons -i.e., 38 subjects x 2 sessions). Optimal FM phase was defined as the

FM-stimulus phase with highest hit rate in the fitted function.

We aimed to test the influence of FM phase on gap detection while simultaneously testing

and controlling for stimulus characteristics, as well as the passage of time. To do this, we

fit mixed-effects logistic regression models using the MATLAB function '*fitglme*'. Each

model was fitted using a binomial distribution, logit link function, and Laplace fitting

method. Different models were tested evaluating whether gap detection could be predicted

as a function of 1) FM phase, 2) stimulus center carrier frequency (1000–1400Hz), 3)

stimulus carrier at gap onset, 4) global time (1–864, indicating the gap position within the

whole experiment), 5) local time (1–12 equally spaced time bins, excluding the first and

last second of the 20-s stimulus, indicating gap location within the stimulus), 6) cochlear

entropy (see below) and the interactions of 7) FM phase * stimulus carrier frequency, 8)

FM phase * global time and 9) FM phase * local time. Each predictor, excepting interaction

terms, was modeled as a fixed factor plus a random intercept and slope to estimate the

group-level effect while allowing for inter-individual variability in the predictor effect size.

Due to computational limitations, interaction terms were modelled only with fixed terms.

All predictors were transformed to z-scores prior to model fitting. Ten different models

were fitted, each including a different combination of regressors, and the best model was

selected using the Akaike's information criterium (AIC, **Table 2**) and the Likelihood Ratio

Test (LRT). All predictors involving circular data (phase angles) were linearized by

calculating their sine and cosine. The separate beta estimates for the sine (sinb) and cosine

(cosb) of the phase predictor were recombined into a single beta corresponding to the

amplitude of the phasic behavioral modulation:

$$b = \sqrt{(sinb^2 + cosb^2)}$$

Cochlea-scaled spectral entropy is an index of spectral change and represents the relative

unpredictability of acoustic signals (Henry et al., 2016; Teng et al., 2018). Since our

perceptual systems are more driven to detect change than stability, it is possible that the

instantaneous rate of frequency change at gap onset could affect gap detection. For

calculating cochlea-scaled entropy (Stilp and Kluender, 2010; Henry et al., 2016; Teng et

al., 2018), each 20-s auditory stimulus was divided into 16 ms "slices". Each slice was

filtered by a bank of 15 symmetrical rounded-exponential filters with center frequencies

equally spaced between 300 and 2400 Hz in equivalent-rectangular-bandwidth (ERB)

units. The result was a 15-bin frequency histogram where the height of each bar was the
amplitude of the corresponding filter output. Pairwise Euclidean distances were then
calculated for frequency histograms belonging to neighboring slices. For each gap,
cochlea-scaled entropy was finally computed by calculating the Euclidean distance values
averaged in a 27-ms time window right before gap onset. This duration was chosen because
it corresponds to the duration of each phase bin.

To test the classification significance of the winning model, 1000 surrogate datasets were
created for each session by shuffling the single-gap accuracy values (0,1) for each
participant while keeping all condition labels the same. The same mixed-effects models
were fitted to the surrogate datasets and the response operator characteristic (ROC) curve
and the area under the curve (AUC) for the winning model and each surrogate model were
computed. The winning model was considered to be significant if its AUC value fell above
the 95 percentile of the distribution of AUC from the surrogate models ($p < 0.05$).

Electroencephalogram data. The EEG was recorded with an actiCAP active electrode
system in combination with Brainamp DC amplifiers (Brain Products GmbH). The
electrode system included 64 Ag–AgCl electrodes mounted on a standard cap, actiCAP
64Ch Standard-2 (Brain Products GmbH). Signals were recorded continuously with a
passband of 0.1 to 1000 Hz and digitized at a sampling rate of 1000 Hz. For recording, the
reference electrode was placed over FCz and the ground electrode over AFz. For better
stimulus marking, in addition to standard EEG triggers from the LPT port, stimulus
markers were also sent via soundcard and collected in the EEG using a Stimtrak (Brain
Products GmbH). Electrode resistance was kept under 20 kΩ. All EEG data were analyzed
offline by using Fieldtrip software (www.ru.nl/fcdonders/fieldtrip; version 20200130) and
custom MATLAB scripts.

Two different preprocessing pipelines were implemented. One was tailored to assess
entrainment characteristics and reliability, and focused on the complete 20-s stimulus
periods; the second pipeline was tailored to test the effect of pre-target (pre-gap) activity
on gap detection, and focused on the periods around each gap's occurrence. In the first
preprocessing pipeline, the continuous EEG data were high-pass filtered at 0.6 Hz. Filtered
data were then epoched into 21.5-s trials (1 s before stimulus onset and 0.5 s after stimulus

offset). The trial data were low-pass filtered at 80 Hz and the 50-Hz line noise was removed using discrete Fourier transform (dft) with spectrum interpolation as implemented in Fieldtrip. Data were re-referenced to the average reference. Extreme artifacts were removed based on visual inspection. Noisy electrodes were then interpolated (1 electrode in 3 participants and 2 electrodes in one participant). Eye-blinks, muscle, heartbeat, and remaining line noise or faulty contact artifacts were removed using ICA. Next, data were low-pass filtered to 30 Hz and trials for which the range exceeded 200 µV were automatically removed. If more than 30% of the trials had to be removed because of artifacts, the participant was removed for further analysis (1 participant). Preprocessed data were resampled to 500 Hz.

The second preprocessing pipeline included the same steps excepting the initial high-pass filter. To maximize comparability with the first pipeline, all the same trials and ICA components that were identified based on the first pipeline were removed in the second pipeline. After all preprocessing steps and before resampling, 3-s long trials were defined around each gap onset (i.e., 1.5 s before and 1.5 s after gap onset). Trials exceeding a range of 200 µV were excluded and data were resampled to 500 Hz.

Frequency and time-frequency analysis of full-stimulus periods. Full-stimulus epochs were analyzed in the frequency and time-frequency domains to examine brain responses entrained by the 2-Hz stimulation. Since the starting phase of the FM stimulus was randomized from trial to trial, before conducting frequency-domain analyses, single-trial brain responses were realigned so that the FM stimulus phases would be perfectly phase-locked across trials after the realignment. A fast Fourier transform (FFT) was performed on the trial-averaged time-domain data at each electrode, after multiplication with a Hann window. Evoked amplitude in each frequency band was calculated as the absolute value of the complex output, while the phase angle of the complex FFT output at 2 Hz provided an estimate of stimulus–brain phase lag. An FFT was also applied on each single trial, and the resulting single-trial amplitude spectra were averaged over trials as an indicator of total amplitude of neural activity that was not necessarily phase-locked to the stimulus. Inter-trial phase coherence (ITPC) was calculated as the resultant vector length of phase angles from the complex FFT output across trials separately for each frequency and electrode. In addition, the single-trial time-domain data were submitted to a time–frequency analysis by

using the Fieldtrip-implemented version of the Wavelet approach using Fourier output.
Here, wavelet size varied with frequency linearly from three to seven cycles over the range
from 1 to 15 Hz. The resulting complex values were used to estimate time-resolved ITPC
for each channel separately.

Nonparametric Wilcoxon signed-rank tests were conducted to statistically test spectral
amplitudes and ITPC at frequencies of interest (2 Hz, 4 Hz, alpha). For each condition,
participant, and session, data were averaged over all channels (and over time for time-
resolved ITPC) and amplitudes/ITPC of the two target frequencies (2 Hz and 4 Hz) were
then tested against the average amplitude/ITPC of the neighboring ±8 frequency bins
(0.16Hz) (Henry and Obleser, 2012; Bauer et al., 2018). In the case of alpha amplitude,
data were averaged across all bins including frequencies between 7-12 Hz and were tested
against the average amplitude of the neighboring ±100 frequency bins (2 Hz).

Based on the topography of the 2/4 Hz and alpha (7-12 Hz) amplitude spectra, further
analyses involving the extraction of ITPC and/or amplitude values were done in two
separate clusters of electrodes including *F3, Fz, F4, FC1, FC2, C3, Cz, C4, F1, F2, FC3,*
FC4, C1, C2 for 2/4 Hz activity and *P8, P6, P4, P2, Pz, P1, P3, P5, P7, PO9, PO10, PO8,*
PO4, POz, PO3, PO7, O1, Oz, O2 for alpha activity. First, ITPC or amplitude values were
extracted from each electrode and then averaged over electrodes within the relevant cluster.

Pre-gap activity. Before analysis of pre-gap activity, single-trial time-domain data around
the gap period (1.5 s before and 1.5 s after) were detrended (using linear regression). It is
possible that the smearing of the evoked response back into pre-stimulus period by wavelet
convolution could produce spurious pre-stimulus phase effects. To minimize this, gap-
evoked responses were removed from the post-stimulus period by multiplication with half
of a Hann window that ranged between 0 and 50 ms after gap onset and was zero thereafter
(Henry et al., 2014). To estimate neural amplitude and phase, the time-domain data were
submitted to a wavelet convolution yielding complex output as implemented in Fieldtrip.
Wavelet size varied with frequency linearly from three to seven cycles over the range from
1 to 15 Hz with 10-ms temporal resolution. Alpha amplitude as well as 2-Hz amplitude
were averaged within the 100-ms time window preceding gap onset. Neural phase was
computed as the phase angle of the complex output for the specific frequency. Time

windows for extracting pre-gap 2-Hz and alpha phases were adjusted to include 1/5 of a

cycle of the relevant frequency, i.e., 100 ms preceding gap onset for 2-Hz phase and 22 ms

for alpha phase (assuming center frequency 9 Hz). Since different electrodes can have

different phase profiles, computing circular means over different electrodes can lead to

phase cancellation and an imprecise estimation of phase effects on gap perception. To

circumvent this problem, phase values were realigned to a group reference per electrode,

prior to calculating the circular mean across electrodes within the relevant electrode cluster

(fronto-central cluster for 2-Hz phase estimation and parieto-occipital cluster for alpha

phase estimation). This way we hoped to minimize inter-electrode variability within the

cluster, while maintaining inter-participant and inter-session variability. First, trials were

binned according to their pre-gap 2-Hz/alpha phase and hit rates calculated for each bin.

Cosine functions were fitted to binned hit-rate data for each single participant and session

and the optimal phase for gap detection estimated. The group phase references ($\emptyset ref$) were

estimated for each electrode by computing the circular mean optimal phase over sessions

and participants. For each electrode, single trial phase ($\emptyset_{(tr)}$) values were then realigned

($\emptyset r_{(tr)}$) as:

$$\emptyset r_{(tr)} = \emptyset_{(tr)} + (2\pi - \emptyset ref)$$

The influence of pre-gap 2-Hz phase and amplitude, alpha phase and amplitude, and their

interactions on gap detection was evaluated using mixed-effects logistic regression models,

similar to the behavioral analysis, using the MATLAB function *'fitglme'*, specifying the

distribution as binomial, the link function as logit, and the fitting method as Laplace.

Fourteen different logistic regression models were fitted to the data including different

combinations of the regressors, and the best model was chosen based on the AIC value

(**Table 1**) and the LRT. Phase regressors were linearized by computing their sine and

cosine. The phase–phase interaction between 2-Hz phase and alpha phase was assessed

using two predictors, i.e., the product of the sines and the product of the cosines. The

interaction between 2-Hz phase and alpha amplitude was assessed also using two

predictors, i.e., the product of alpha amplitude and the sine and the cosine of 2-Hz phase.

All predictors were transformed to z-scores prior to model fitting. To test the significant

classification performance of the winning model, 1000 surrogate datasets were created for

each participant and session by shuffling the single-gap accuracy values (0,1) across trials while preserving trial correspondence across regressors. The same regression models were fitted to the surrogate datasets. ROC and AUC values were computed for both the winning model and the surrogate models. The winning model was considered to be significant if its AUC value fell above the 95 percentile of the distribution of AUC from the surrogate models ($p < 0.05$).

To investigate optimal 2-Hz phase for gap detection, trials were sorted into 18 equally spaced phase bins based on realigned pre-gap 2-Hz phase angle, and hit rates were calculated for each bin. Optimal 2-Hz, defined as the phase with highest detection rate, was estimated based on separate cosine fits to hit rates binned by either delta phase.

Estimating 2-Hz phase–alpha amplitude coupling. To investigate 2-Hz phase–alpha amplitude coupling, generalized linear mixed-effects models were used to predict pre-gap alpha amplitude from 2-Hz pre-gap phase (its sine and cosine). The model included fixed terms as well as random intercept and slope. Individual beta estimates for the effect of 2-Hz phase on alpha amplitude (here interpreted as cross-frequency coupling) were recombined into a single beta for the phase effect, as described above. To test for statistical significance of the coupling, 1000 surrogate datasets were created for each participant and session by shuffling the trial order for the response variable (alpha amplitude) while keeping the order fixed for the predictor (2-Hz phase). The same generalized linear mixed effects models were fitted to each surrogate dataset and the beta coefficients were estimated just as described for the real data. Cross-frequency coupling was considered to be significant if the beta coefficients from the real model fell above the 95 percentile of the distribution of beta coefficients from the surrogate models ($p < 0.05$).

Questionnaires

To evaluate musical skills, all participants from the main experiment completed the Goldsmiths Musical Sophistication Index (Gold-MSI) (Mullensiefen et al., 2014). Scores were computed using the documents and templates provided in https://www.gold.ac.uk/music-mind-brain/gold-msi/download/. Accordingly, individual scores were used to calculate the general sophistication index as well as scores on five main

factors: active engagement, perceptual abilities, musical training, emotions, singing
abilities.

Statistical Analysis

Unless otherwise specified, correlation analyses between linear variables were done using
Spearman rank correlation coefficient. In case of circular data, circular–circular or
circular–linear correlations were computed using the respective functions in the circular
statistics toolbox for MATLAB (Berens, 2009). Significant differences between sessions
were evaluated using Wilcoxon signed-rank tests. Significant p-values were corrected
using *Bonferroni* method. All statistics values in the text are rounded to max 3 decimal
points.

Control study

Twenty-five participants took part in the control experiment (seventeen females, mean age
26.08 (SD = 4.62)). Seventeen of them received financial compensation and signed written
informed consent (10 also participated in the main study). The other eight participants were
colleagues in our research group/institute (including one author-YCC), and participated
voluntarily without compensation.

Unless otherwise specified, stimuli and procedures were the same as for the main
experiment. In contrast to the main experiment, gap thresholds were not individually
estimated, but gap duration was fixed at 16 ms (mean threshold in session 2 in the main
experiment) for all participants. FM stimuli were created as for the main experiment but
modulated at four different frequencies: 1.5, 2, 2.5, and 3 Hz. Gaps could be presented at
15 different bins of the FM cycle. Subjects heard 224 stimuli (56 per FM) for a total of 932
gaps (233 per FM rate). Stimuli were presented in 8 different blocks (2 per FM rate) of 28
stimuli each. Each block comprised only one FM rate but the FM order was randomized
within session and across participants. The number of gaps per stimulus (3, 4, or 5) was
randomized. For each of the 15 FM-phase bins*FM rate combination, 14-16 gaps were
presented.

Hits were defined as button-press responses that occurred no earlier than 100 ms and no
later than 1.5 s after the occurrence of a gap. Hit rates were calculated separately for each

of the 15 FM-phase bins and each FM rate. To estimate the FM-induced sinusoidal

modulation of gap detection behavior, a cosine function was fitted to hit rates as a function

of FM-phase for each participant. For each participant and FM rate, the mean hit rate (i.e.,

fitted intercept), the fitted amplitude parameter, and the optimal phase (same definition as

in the main experiment) were estimated. The effect of FM rate on hit rates and amplitude

parameters was tested using separate one-way Analyses of Variance (ANOVAs). To test

whether the concentration of optimal stimulus phases changed with FM rate, resultant

vector lengths were computed for distributions of individual optimal phases, weighted by

individual amplitude parameters, separately for each FM rate. A linear model was fitted to

the data, predicting resultant vector length from FM rate and an intercept. The model was

fitted to the data using the Matlab function *"fitglm"* and statistical significance was

estimated using permutation tests. For comparison, the test distribution was created by

computing 1000 resultant vector lengths calculated with the individual optimal phases

while shuffling the FM rate information at the individual level.

Data   and   Matlab   codes   will   be   made   publicly   available   in

https://edmond.mpdl.mpg.de/imeji/collection/9UoanSkXciMEK_v?q= after publication.

Results

In two different sessions, EEG activity was recorded while listeners detected silent gaps

embedded in 20-s long complex tones that were frequency modulated at 2 Hz (**Fig. 1**).

Based on previous literature, we predicted that delta oscillations would be entrained by the

2-Hz FM. We aimed to quantify how reliable entrainment would be across sessions, both

in terms of entrainment strength and in terms of the phase relationship between stimulus

and brain.

Auditory entrainment to FM sounds has high inter-session reliability

We evaluated entrainment using four converging analyses: (1) total and (2) evoked

amplitudes of EEG data, (3) inter-trial phase coherence (ITPC) across the full epoch based

on complex Fourier output, and (4) in a time-resolved way based on the output of a wavelet

convolution (see Methods).

For evoked spectra, we observed high-amplitude peaks at the stimulus FM frequency and its first harmonic (2 Hz and 4 Hz respectively, **Fig. 2a**), consistent with neural tracking of the rhythm of the FM stimulus (Henry and Obleser, 2012; Henry et al., 2014). Relatively high spectral amplitude was also observed in the alpha frequency band (7-12 Hz). For all further analyses on alpha activity, we considered activity between 7 Hz and 12 Hz, because this frequency range best captured the observed range of alpha evoked amplitude (**Fig. 2a**). Evoked amplitudes for 2 Hz, 4 Hz, and alpha frequencies were significantly different than the average amplitude of the neighboring frequency bins (all $z \geq 5.344$, $p \leq 5.452e-07$, see Methods) in both sessions. Total amplitude spectra showed high amplitude in alpha frequency band, while 2-Hz and 4-Hz amplitudes were less visible in the spectra due to high 1/f power (**Fig. 2b**). Nevertheless, compared to the average amplitude of the neighboring frequency bins, 2 Hz, 4 Hz, and alpha amplitudes were also significant in the total amplitude spectra (all $z \geq 4.445$, $p \leq 5.275e-05$). Moreover, the ITPC analysis showed clear peaks at 2 Hz and 4 Hz, again suggesting neural tracking at the stimulus FM frequency and its first harmonic (**Fig. 2c**). In both sessions, ITPC at 2 Hz and 4 Hz was significantly different than the neighboring frequency bins (same neighboring frequency bins as defined for the evoked amplitude analysis, all $z \geq 5.330$, $p \leq 3.938e-07$). Finally, time-resolved ITPC at 2 Hz and 4 Hz, averaged over electrodes and time was significantly different than for the neighboring frequency bins (± 8 frequency bins/0.81Hz, all $z \geq 5.069$, $p \leq 1.604e-06$, **Fig. 2c**, right). FM-stimulus-evoked amplitude at 2 Hz (and also at 4Hz, data not shown) was mostly observed in a fronto-central cluster including electrodes F3, Fz, F4, FC1, FC2, C3, Cz, C4, F1, F2, FC3, FC4, C1 and C2 (**Fig. 2a**, insets). Therefore, all further analyses involving 2 Hz and 4 Hz frequencies were done first independently by electrode and then averaged over this subset of electrodes; the one exception was the examination of neural phase effects of performance, where averaging over electrodes can lead to phase cancellation (see below). The same procedure was followed for all further analyses involving alpha frequencies but data were extracted from the cluster of electrodes exhibiting the highest stimulus-evoked alpha amplitude, i.e., P8, P6, P4, P2, Pz, P1, P3, P5, P7, PO9, PO10, PO8, PO4, POz, PO3, PO7, O1, Oz, O2 (**Fig. 2a**, insets).

Moving a step past previous literature, we next asked whether FM-induced entrainment is reliable over time by correlating the amplitude of the stimulus-evoked activity at 2 Hz, 4

Hz, and in the alpha frequency band, as well as the stimulus-brain lag (i.e., the phase angle of the 2-Hz complex output of the FFT calculated for the full stimulus epoch) across sessions. Inter-session correlations were high and significant for evoked amplitudes at 2 Hz (rho = 0.701, p = 2.238e-06), 4 Hz (rho = 0.764, p = 2.846e-07), and in the alpha band (rho = 0.738, p = 5.962e-07; **Fig. 3a**). Significant difference between sessions was observed for 4-Hz amplitude (session 1 vs session 2: z = 2.632, p = 0.026, *Bonferroni* corrected) but not for the other frequencies (all |z| ≤ 1.429, p ≥ 0.153, uncorrected). Despite individual variability, stimulus–brain phase lags were not uniformly distributed as reported in previous work, but were significantly phase clustered for both sessions (Rayleigh test, session 1: z = 23.004, p = 9.513e-13; session 2: z = 16.087, p = 1.559e-08, **Fig. 3b**). Moreover, phase lags were reliable across sessions as indexed by the high circular–circular correlation (rho = 0.624, p = 0.003) and a circular distance between sessions clustered around zero (V-Test for nonuniformity with known mean direction, v = 30.981, p = 5.905e-13). Taken together, amplitude spectra and phase lags suggested that neural entrainment to FM stimuli is reliable across sessions, which is the first vital prerequisite for targeted interventions of auditory-cortex neural oscillations.

Stimulus-induced behavioral modulation is sinusoidal and shows high inter-session reliability

While listening to the FM sounds, participants responded with a button press each time they detected a silent gap. Each 20-s long stimulus contained three, four, or five gaps. Gaps were distributed uniformly around the 2-Hz FM cycle in 18 possible phase positions (**Fig. 1**). A response was considered to be a "hit" if a button press occurred within a window of 0.1-1.5 s after gap onset.

We hypothesized that, as a consequence of the stimulus-induced entrainment of delta oscillations, hit rates for gap detection would be sinusoidally modulated by the FM stimulus phase. To go a step past previous studies, we also asked whether this modulation is reliable across sessions. While several studies have focused on analyzing oscillatory modulation of perception at the group level by aligning single-participant data to the phase with best or worst performance (see (Zoefel et al., 2019) for recommendations), here we took a different approach and investigated whether the magnitude of stimulus-driven

behavioral modulation and the optimal (best) FM-stimulus phase were consistent across
sessions within an individual.

For each session separately, hit rates were calculated for each FM-phase bin (**Fig. 4a**).
Then, we fitted a cosine function to hit rates as a function of phase for each participant and
each session. The resulting amplitude parameter from the cosine fit was taken as an index
of the strength of the behavioral modulation. Compared to surrogate datasets, significant
behavioral modulation was observed for 31/38 participants in session 1 and 34/38 in
session 2 ($p < 0.05$, Bonferroni corrected, **Fig. 4b**).

The fitted modulation amplitude values were higher in session 2 compared to session 1 (z
$= 3.299$, $p = 9.694e\text{-}04$), however, they were also highly correlated between sessions (rho
$= 0.849$, $p < 0.001$, **Fig. 4b**), indicating that FM-induced behavioral modulation was
reliable, but increased across sessions overall. Individual optimal FM phases (the FM-
stimulus phase yielding highest performance) were estimated from the fitted cosine
functions per participant and per session (**Fig. 4b**). Optimal phases were not uniformly
distributed, but clustered in one half of the FM cycle (Rayleigh test; session 1: $z = 34.440$,
$p = 1.003e\text{-}22$; session 2: $z = 35.734$, $p = 1.759e\text{-}24$). Optimal phases were also highly
correlated between sessions (circular–circular correlation; rho $= 0.620$, $p = 0.036$, **Fig. 4b**).
Moreover, circular distance between optimal phases in session 1 and session 2 was
clustered around zero (V test; $v = 36.772$, $p < 0.001$), suggesting that optimal phase is also
a reliable attribute of FM-induced behavioral modulation.

We recognized that high reliability in optimal FM phase across sessions may have been at
least partially attributable to clustering of optimal phases across participants in the first
place – since optimal phases were significantly clustered across participants, we wanted to
be careful not to overinterpret similar optimal phase across sessions as reflecting within-
participant reliability. In order to test this possibility, we conducted a permutation test in
which the order of participants in session 2 was permuted 1000 times relative to the session-
1 order, and the circular–circular correlation between individual optimal phases in session
1 and (permuted) 2 was computed. If inter-session correlations are driven by the similarity
between participants, permuting the participant order in session 2 should not have affected
inter-session correlations. However, demonstrating the reliability of optimal phase, the

inter-session correlation in the original data was higher than all values in the distribution

of inter-session correlations from the permuted samples (p <0.001).

In addition to the fitted amplitude parameters and optimal FM phases for gap-detection

performance, hit rates (over the entire session), false-alarm rates, reaction times, and

threshold gap durations were also highly correlated across sessions (all rho $\geq$ 0.447, p $\leq$

0.005, **Fig. 4c**). When each of the dependent measures was directly compared across

sessions, a significant difference was observed only for the gap duration (*Wilcoxon signed*

rank test, z = 2.987, p = 0.011, *Bonferroni* corrected). Individually adjusted gap durations

estimated using our threshold procedure were shorter in session 2 than in session 1. Since

hit rates were not significantly different between sessions, the decrease in threshold gap

duration suggests that participants experienced some degree of learning or practice effect,

and could recognize shorter gaps in session 2. The reduction in threshold gap duration

between session 1 and 2 was significantly correlated with music perceptual abilities (rho =

0.385, p = 0.017), as measured with the Goldsmiths Musical Sophistication Index (Gold-

MSI, (Mullensiefen et al., 2014)), very tentatively suggesting that individuals with stronger

music skills might have experienced a greater benefit of repeated exposure across sessions.

Pre-stimulus neural 2-Hz phase and alpha amplitude predict gap detection

In the previous sections, we showed that the 2-Hz FM stimulus entrained neural activity at

the modulation frequency and that gap-detection performance was sinusoidally modulated

by FM phase. Therefore, we expected that pre-gap brain activity should also predict gap-

detection performance. We examined the effects of pre-gap neural phase and amplitude in

the FM stimulus frequency band (2 Hz), pre-gap neural phase and amplitude in the alpha

frequency band (7-12 Hz), and their interactions, on gap detection performance (see

Methods). Both entrained 2-Hz and non-entrained alpha activity were taken into account

since our initial FFT analysis showed stimulus-driven modulation of both, and because it

has previously been shown that entrainment lapses are accompanied by increases in alpha

amplitude (Lakatos et al., 2016), which led us to the hypothesis that both delta and alpha

frequencies might contribute to gap detection (**Fig. 2a-b**). Prior to averaging 2-Hz phase

and alpha phase across the relevant electrodes within each cluster, single trial phase values

were realigned to each electrode's reference phase (see Methods). This was implemented

because averaging over electrodes can lead to phase cancellation and imprecise estimation

of phase effects on performance. Fourteen mixed-effects logistic regression models were

fitted to the data using different combinations of regressors aiming to predict trial-based

gap detection performance (hit/miss). In both sessions, the winning model (smallest AIC

values) included the predictors pre-gap neural 2-Hz phase and pre-gap alpha amplitude

(**Fig. 5a;** winning model vs. next best model, session 1: ΔAIC = 1.682, LRStat = 14.318,

ΔDF = 8, p = 0.074; session 2: ΔAIC = 2.870, LRTstat = 13.13, ΔDF = 8, p = 0.107). While

ΔAIC between the winning model (2-Hz phase + alpha amplitude) and the next best model

(2-Hz phase + alpha amplitude + alpha phase) was smaller than 2 in session 1, we decided

to take this model because 1) it showed the lowest AIC in both sessions, 2) it was the

simplest model of the two and 3) the LRT suggested that the more complex model was not

better at fitting our data. Adding the predictors 2-Hz amplitude, alpha phase, or the

interactions 2-Hz phase*alpha amplitude and 2-Hz phase*alpha phase produced higher

AIC values. **Table 1** shows the AIC and ΔAIC values for all tested models.

To test whether the winning model had a classification accuracy higher than chance, the

ROC and corresponding AUC were calculated. AUC values were then compared to the

distribution of AUCs obtained when fitting the same model to surrogate data (see

Methods). For both sessions, the winning model showed higher AUC than all values in the

surrogate distribution, demonstrating that pre-gap neural 2-Hz phase and alpha amplitude

predicted gap detection accuracy significantly better than chance (AUC S1 = 0.675, S2 =

0.677, p <0.001).

Beta coefficients for 2-Hz phase effect in session 2 were higher than in session 1 (z = 2.444,

p = 0.029, *Bonferroni* corrected, **Fig. 5a**). No significant difference between sessions was

observed for the effect of alpha amplitude (z = 0.051, p = 0.960, uncorrected). For most

participants, beta coefficient for the effect of alpha amplitude were positive in both

sessions, indicating that alpha amplitude was higher for hits than for misses.

Next, we evaluated the clustering across participants of optimal neural 2-Hz phase, both

within and across sessions. Trials were sorted into 18 equally spaced bins according to the

realigned instantaneous neural 2-Hz phase (**Fig. 5b**). Hit rates were calculated for each bin

and cosine functions were fitted to each individual participant's data in order to estimate

optimal neural phase, similar to the behavioral analysis. In both sessions, optimal 2-Hz

neural phases were significantly clustered across participants (all $z \geq 14.667$, $p \leq 9.441e$-

08, **Fig. 5c**). Circular distances between optimal phases for both sessions were also

clustered around zero ($v = 18.258$, $p = 1.404e-05$, **Fig. 5c**). Unexpectedly, the circular–

circular correlation for optimal phases between sessions was not significant ($rho = -0.124$,

$p = 0.429$). Plotting session-wise optimal phase shifts suggested that while mean phase

distances were around zero, optimal phase for different participants changed but in

different directions (**Fig. 5d**). Interestingly, the absolute optimal-phase distance between

sessions correlated with the overall (mean) magnitude of the 2-Hz phase effect on behavior

(beta coefficients; $rho = -0.339$, $p = 0.038$): participants with strongest phase effect showed

higher optimal phase consistency across sessions. No significant association between phase

distance and inter-session interval or time of the day was observed (all $|rho| \leq 0.216$, $p \geq$

0.193, uncorrected).

Pre-gap 2-Hz phase predicts alpha amplitude

In the previous section, we showed that both 2-Hz phase and alpha amplitude predict

single-trial gap detection performance. However, it is not clear whether they represent two

independent mechanisms or if the two neural signatures might be coupled. A natural

question here would then be whether there is a significant phase–amplitude coupling

between 2-Hz and alpha activity. To answer this question, a generalized mixed effects

model was implemented with single-trial pre-gap alpha amplitude as the dependent

variable and pre-gap 2-Hz phase as the predictor (sine and cosine), using both fixed effects

terms as well as random intercept and slope. We expected that if 2-Hz phase and alpha

amplitude are coupled, 2-Hz phase should significantly predict alpha amplitude. To test for

the significance of the phase–amplitude relationship relative to chance, beta estimates for

each session were compared to the beta estimates obtained from fitting the same model to

surrogate datasets, which were created by shuffling single-trial alpha amplitudes while

keeping 2-Hz phase fixed. For both sessions, beta estimates from the real model were

higher than all values in the distribution of beta estimates from the surrogate data ($p < 0.001$,

Fig. 6), indicating that pre-gap 2-Hz neural phase significantly predicted pre-gap alpha

amplitude.

Control Experiment: Gap detection is modulated by the FM rate.

Here, we found that optimal FM phases were clustered in one half of the FM cycle (although we did observe some variability across participants). This was somewhat surprising because previous studies using the same task and very similar stimuli reported that optimal phases were uniformly distributed around the FM cycle (Henry and Obleser, 2012). One major difference between the two studies was the FM frequency (rate): 3 Hz in the previous study (Henry and Obleser, 2012) and 2 Hz in the current study. We hypothesized that individual variability in stimulus-driven behavioral modulation might be influenced by the FM frequency: slower FM frequencies (in this case 2 Hz) should be easier to track and therefore participants should synchronize to such stimuli more similarly, while individual differences are more pronounced for higher FM frequencies, which might be more difficult to track and therefore result in phase slips.

We tested this hypothesis in a control experiment, where 25 participants performed the same gap-detection task as in the main experiment, but FM rate varied between blocks and took on values of 1.5 Hz, 2 Hz, 2.5 Hz, or 3 Hz (see Methods, **Fig. 7**). Overall hit rates were significantly modulated by FM rate (repeated measures ANOVA, $F_{(3,72)} = 13.374$, $p = 4.980\text{e-}07$); lower hit rates were observed for higher FM rates (**Fig. 7a**). Note that here, overall hit rates are a useful performance measure, because we did not titrate gap duration to match hit rates across FM rates or across individuals. FM rate also significantly affected the amplitude of the stimulus-induced behavioral modulation, albeit in opposite direction to the hit-rate effect; amplitude values increased as a function of FM rate ($F_{(3,72)} = 6.336$, $p = 7.128\text{e-}04$, **Fig. 7b**)). To test whether the clustering of individual optimal phases was dependent on the FM rate, individual optimal phases were estimated from cosine fits **(Fig. 7c)**, and the resultant vector length across participants was calculated for each FM rate (**Fig. 7c**). For this calculation, individual optimal phases were weighted using the amplitude parameter of the fit. We did this because estimation of optimal phase is less accurate the lower the amplitude parameter (i.e., weaker sinusoidal modulation of behavior), therefore we reduced the weight of optimal phases from low-amplitude fits in the resultant vector calculation. A linear model was used to predict resultant vector length from FM rate and an intercept parameter. A significant fit for the linear term would suggest that indeed, phase clustering significantly decreased (or increased) with increasing FM rate. Significance was

evaluated using permutation tests. The permutation distribution was created by 1)

computing resultant vector lengths over 1000 iterations (in each iteration the FM rate labels

where permuted for each participant) and fitting the same linear model to the simulated

vector lengths as for the original data. The *t-statistic* for the effect of FM rate on vector

length in the original data was compared to the distribution of *t-statistics* obtained from the

permuted datasets. Contrary to our prediction, the phase clustering increased with

increasing FM rate (*t-stat* = 4.419, permutation p = 0.047). In sum, FM rate affected hit

rates, amplitude of the stimulus-induced sinusoidal modulation, as well as optimal phase

clustering across participants.

Gap detection is also influenced by stimulus carrier and time of occurrence

Although we tried to minimize the possibility that the FM phase effects may have

unknowingly been driven by acoustic confounds, we nonetheless tested which stimulus

characteristics beyond FM phase influenced gap-detection hit rates. Fitting different

mixed-effects logistic regression models, we examined the extent to which single-trial gap

detection accuracy in the main experiment was influenced by 1) FM phase, 2) global

experiment time (when the gap occurred over the whole experiment, quantified as the gap

number within a session), 3) local time (when the gap occurred within a stimulus), 4) the

center carrier frequency of the stimulus in which the gap was presented, 5) the center

frequency at gap onset, 6) cochlear-scaled entropy at gap onset, 7) the interaction of FM

phase with global time, quantifying the extent to which stimulus-driven behavioral

modulation changed over the course of the experiment, and 8) with local time, quantifying

the extent to which stimulus-driven behavioral modulation changed over the course of each

individual stimulus. Each predictor was modeled as a fixed factor with a random intercept

and slope. The winning model was chosen based on AIC and the LRT. To assess the

winning model's significance relative to chance, surrogate datasets were created by

permuting, for each participant, accuracies (1/0) across trials while keeping all other

parameters the same. This procedure was repeated for 1000 iterations. The same model

was fitted to each permuted dataset. ROC and AUC were computed for the real model and

those fitted to the permuted datasets. The model was considered to be significant if the

AUC values was above 95% percent of the AUC values from the permuted samples, for a

corresponding p value of 0.05.

For session 1, the winning model included FM stimulus phase, global time, local time, main stimulus carrier and the interactions of phase * global time and phase * local time (**Fig. 8, Table 2**). In contrast, for session two, the best model did not include any interaction term but only main effects FM stimulus phase, global time, local time, and main stimulus carrier (**Fig. 8**).

Mean beta values for global time, local time, and main carrier frequency were negative, indicating that gap detection performance decreased with increasing global time, local time, and main carrier frequency (**Fig. 8a**). That is, gap detection was better earlier in the session as would be expected from fatiguing over the experiment, earlier in each stimulus, and for relatively low carrier frequencies (**Fig. 8b**). Interestingly, when we plotted the local-time effect, we realized that it arose from two distinct groups of participants: a bigger group who better detected gaps early in the stimulus, and a smaller group who better detected gaps later in the stimulus (**Fig. 8b**). To visualize the interaction effects observed in session 1, trials were grouped in four bins according to their time of occurrence within the session (global time) or within each 20-s stimulus (local time). Hit rates were computed for each FM phase and time bin, and cosine functions were fitted to each bin's data. Visual inspection of this analysis showed that the amplitude of the stimulus-driven behavioral modulation was higher later in the session and earlier within the stimulus (**Fig. 8b**). Beta estimates for the effect of FM stimulus phase were significantly higher in session 2 compared to session 1 (z = 3.836, p = 5.005e-04, *Bonferroni* corrected). No significant difference between sessions were observed for any of the other predictors ($|z| \leq 1.240$, $p \geq 0.215$, uncorrected).

As already mentioned, additional mixed effects logistic regression models were fitted to the individual data using other combination of parameters, including cochlear-scaled entropy and/or the carrier frequency at the exact time the gap was presented, taking into account the sinusoidal modulation. All such models showed higher AIC values than the winning model (**Table 2**, winning model vs. next best model, session 1: ΔAIC = 2.520, LRTstat = 5.480, ΔDF = 4, p = 0.241; session 2: ΔAIC = 4.025, LRTstat = 3.975, ΔDF = 4, p = 0.409). Interestingly, the model with the highest AIC (and therefore worst performance; ΔAIC relative to winning model; session 1: > 2483.513; session 2: > 3200.484, see **Table 2**) was the one including acoustic parameters (including gap onset

696   carrier frequency) but excluding FM stimulus phase information, suggesting that in fact,

697   FM phase was the best predictor of gap detection accuracy. For both sessions, the winning

698   model had AUC values higher than all values in the distribution of surrogate datasets,

699   proving a classification accuracy higher than chance (AUC; S1 = 0.744, S2 = 0.758; p

700   <0.001).

Discussion

In the present study, we investigated the test–retest reliability of neural entrainment and its

relevance for auditory perception. Participants detected silent gaps embedded in 2-Hz FM

stimuli while EEG activity was recorded in two separate sessions. We showed that: 1)

neural activity was entrained by the FM stimuli, and perception was modulated in a

sinusoidal manner by both stimulus and brain phase; 2) both entrainment strength and the

magnitude of stimulus-driven behavioral modulation were reliable across sessions; 3) pre-

gap delta phase and alpha amplitude predicted moment-by-moment fluctuations in

performance.

Neural entrainment is reliable over time

Over the past years, a great deal of attention has been paid to entrainment, and arguments

range from the existence of entrainment per se (Rimmele et al., 2018; Obleser and Kayser,

2019; Meyer et al., 2020) to its role for auditory perception specifically (Ng et al., 2012;

Sameiro-Barbosa and Geiser, 2016; Lakatos et al., 2019). Neural entrainment to rhythmic

stimuli has been observed across a range of sounds, including simple stimuli such as tone

sequences, amplitude-modulated or frequency-modulated sounds, and more complex

auditory stimuli such as music and speech (Henry and Obleser, 2012; Doelling et al., 2014;

Henry et al., 2014; Doelling and Poeppel, 2015; Lakatos et al., 2016; Henry et al., 2017;

Ten Oever et al., 2017; Riecke et al., 2018). However, until now, little attention has been

paid to the reliability of neural entrainment. This is despite the fact that the reliability of

entrainment is of paramount importance both for understanding its contribution to auditory

perception and for developing effective targeted interventions. Here, we showed that neural

entrainment to FM sounds is reliable over time: we observed high inter-session correlations

for metrics of entrainment strength, such as the spectral amplitude of neural activity at the

stimulus frequency, and perhaps more importantly, the phase lag between stimulus and

brain. Interestingly, while no differences in either stimulus–brain phase lag or optimal

stimulus phase were observed between sessions, both the effect of FM-stimulus phase and

the effect of pre-gap 2-Hz neural phase on gap detection were stronger in session 2 than in

session 1. This suggests that while highly reliable, the degree to which behavior is

influenced by auditory rhythms can potentially be trained.

Entrained delta and ongoing alpha activity influenced gap-detection performance

Here, we observed that trial-by-trial gap-detection performance was mainly predicted by

pre-gap neural 2-Hz phase and alpha amplitude. These results are in line with previous

studies showing that the phase of neural oscillations prior to target occurrence predicts

perception in different sensory domains (Hanslmayr et al., 2007; Vanrullen et al., 2011;

Mathewson et al., 2012; Weisz et al., 2014; Wostmann et al., 2019a). For example,

enhanced detection or faster reaction times have been reported for sensory stimuli

presented at the optimal phase of delta (Stefanics et al., 2010), theta (Busch et al., 2009;

Busch and VanRullen, 2010), or alpha oscillations (Busch et al., 2009; Vanrullen et al.,

2011). Our results also showed that, in a rhythmic listening context, gap-detection

performance was not just a product of the entrained delta activity but also depended on

non-entrained (ongoing) alpha activity. Comodulation of behavior by different frequencies

has previously been reported (Henry et al., 2014). Critically, such comodulation was

specific to the entrained frequencies, which led the authors to conclude that environmental

rhythms reduce dimensionality of neural dynamics. Here we expand this view by showing

that both entrained and ongoing brain oscillations could potentially comodulate behavioral

performance. We interpret the contributions of both entrained and ongoing activity to

perception as potentially reflecting an interplay between stimulus driven (sensory, bottom-

up) and internally driven (top-down) processes.

Although our paradigm was not designed to provide a time-resolved look at the interplay

between delta and alpha oscillations, we observed that single-trial 2-Hz pre-gap phase

predicted single-trial alpha amplitudes, which we interpret as delta–alpha phase-amplitude

cross-frequency coupling. In the current context, we are unable to tease apart the

possibilities that, on the one hand, entrained delta oscillations drove alpha-amplitude

fluctuations, or on the other hand, the rhythmic auditory stimulus drove both delta

oscillations as well as alpha-amplitude fluctuations, but that the two neural signatures are

functionally independent. At first glance, the observed delta-alpha coupling seems to

contradict the finding that both delta-phase and alpha amplitude predict gap detection: if

delta-alpha coupling is perfect, including only one of the two predictors should be enough

to explain gap detection. The fact that the winning model includes both predictors however

indicates that delta-alpha coupling is not perfect. Our time-resolved ITPC analysis showed

that coherence (entrainment) at the stimulus frequency fluctuates over time (Lakatos et al.,

2016). We speculate that delta-alpha coupling is higher when delta activity successfully

entrains to the FM stimulus compared to when entrainment is poor. The contribution of

alpha amplitude to gap detection might then be stronger in those trials. Therefore, both

predictors are necessary in the winning model. In other words, our results are consistent

with alternating influences that might occur as a result of "lapses" of entrainment during

which alpha oscillations might have a stronger effect on perception (Lakatos et al., 2016).

It is possible that when entrainment is high, auditory perception is mostly modulated by

the entrained activity, however, during entrainment lapses, perception is shaped by internal

ongoing activity. Or conversely, participants could have adopted the strategy of trying to

ignore the rhythm in order to perform the task, but as their alpha–attention system lapsed,

they were forced into a rhythmic–entrainment mode.

Quite a bit of previous work has demonstrated the importance of alpha activity for "gating"

near-threshold stimuli into awareness (Mathewson et al., 2009; Mathewson et al., 2012),

which goes beyond the idea of alpha activity indexing lapses of entrainment. However, the

vast majority of these studies have been conducted in the visual modality (Spaak et al.,

2014; Fodor et al., 2020; Hutchinson et al., 2020), and it has been argued that alpha activity

does not contribute to near-threshold auditory perception (VanRullen et al., 2014). Thus,

one open question relates to the precise role of alpha oscillations in shaping near-threshold

auditory perception, in particular in a rhythmic auditory context. Answering this question

requires respecting the observation of different alpha rhythms with different neural

generators (Isaichev et al., 2001; Weisz et al., 2011; Billig et al., 2019; Keitel et al., 2019).

Moreover, several studies linking alpha oscillations to attention have suggested that alpha

oscillations could play at least two different roles: i.e., a facilitatory role where it can

enhance target processing, or a suppressive role where alpha activity can suppress the
processing of distractors (Bonnefond and Jensen, 2012; Wostmann et al., 2019b; Schneider
et al., 2020). We hypothesize that the alpha effect observed in our study is reflecting
something like distractor suppression. While delta oscillatory activity entrained to the FM
stimulus facilitates target processing at the optimal delta phase, we speculate that ongoing
alpha activity might play a role in suppressing the distracting stimulus itself (complex
noise), in an attempt to also maximize target detection. In this case, gap detection
performance would be predicted by both mechanisms, in line with the current results.

Behavioral entrainment depends on modulation rate

In the current study, we were surprised to observe that the optimal *stimulus* phase that
yielded best gap-detection performance was consistent across participants. In previous
work, optimal stimulus phase was uniformly distributed across participants, and this
observation was critical to our argument that stimulus-driven behavioral modulation was
the result of neural entrainment and not an artifact of stimulus acoustics (Henry and
Obleser, 2012). One main difference between the current study and previous work was the
FM rate, which was slower here (2 Hz) than in previous work (3 Hz). This led us to conduct
a control experiment where we examined gap-detection performance for stimuli with FM
rates varying between 1.5 and 3 Hz (in 0.5-Hz steps). We observed that hit rates and the
amplitude of the stimulus-driven behavioral modulation were significantly modulated by
FM rate. Contrary to our initial hypothesis, we found that, when controlling for the
modulation amplitude, optimal phase became more consistent as FM rate increased. Such
findings were unexpected to us and suggest that while FM rate plays a major role on
behavioral entrainment to FM stimuli, it does not explain the difference in phase clustering
between the current study and (Henry and Obleser, 2012). In addition to, and perhaps more
importantly than, the FM rate, the two studies also used different FM-modulation depths:
67% (center-to-peak) here and 37.5% in (Henry and Obleser, 2012). It remains to be tested
in future studies whether such modulation depth influences phase clustering across
participants or not.

Conclusion

Taken together, our results showed that FM stimuli entrained neural activity and sinusoidally modulated near-threshold target detection: both signatures of entrainment as well as its behavioral consequences were reliable across sessions. This demonstration is a critical prerequisite for research lines focused on targeted interventions for entrainment but has to our knowledge gone untested until now. Moreover, gap-detection performance was predicted by entrained neural delta phase and ongoing alpha amplitude, suggesting that delta phase and alpha amplitude underpin different but potentially simultaneously active neural mechanisms and together shape perception.

References

Allen GD (1975) Speech rhythm: its relation to performance universals and articulatory timing. Journal of Phonetics 3:75-86.

Assaneo MF, Rimmele JM, Sanz Perl Y, Poeppel D (2020) Speaking rhythmically can shape hearing. Nat Hum Behav.

Bauer AR, Bleichner MG, Jaeger M, Thorne JD, Debener S (2018) Dynamic phase alignment of ongoing auditory cortex oscillations. Neuroimage 167:396-407.

Berens P (2009) CircStat: A MATLAB Toolbox for Circular Statistics. J Stat Softw 31:1-21.

Billig AJ, Herrmann B, Rhone AE, Gander PE, Nourski KV, Snoad BF, Kovach CK, Kawasaki H, Howard MA, 3rd, Johnsrude IS (2019) A Sound-Sensitive Source of Alpha Oscillations in Human Non-Primary Auditory Cortex. J Neurosci 39:8679-8689.

Bonnefond M, Jensen O (2012) Alpha oscillations serve to protect working memory maintenance against anticipated distracters. Curr Biol 22:1969-1974.

Brodbeck C, Jiao A, Hong LE, Simon JZ (2020) Neural speech restoration at the cocktail party: Auditory cortex recovers masked speech of both attended and ignored speakers. PLoS Biol 18:e3000883.

842   Busch NA, VanRullen R (2010) Spontaneous EEG oscillations reveal periodic sampling
843   of visual attention. Proc Natl Acad Sci U S A 107:16048-16053.

844   Busch NA, Dubois J, VanRullen R (2009) The phase of ongoing EEG oscillations predicts
845   visual perception. J Neurosci 29:7869-7876.

846   Cabral-Calderin Y, Wilke M (2020) Probing the Link Between Perception and
847   Oscillations: Lessons from Transcranial Alternating Current Stimulation.
848   Neuroscientist 26:57-73.

849   Cabral-Calderin Y, Anne Weinrich C, Schmidt-Samoa C, Poland E, Dechent P, Bahr M,
850   Wilke M (2016) Transcranial alternating current stimulation affects the BOLD
851   signal in a frequency and task-dependent manner. Hum Brain Mapp 37:94-121.

852   Calabro RS, Naro A, Filoni S, Pullia M, Billeri L, Tomasello P, Portaro S, Di Lorenzo G,
853   Tomaino C, Bramanti P (2019) Walking to your right music: a randomized
854   controlled trial on the novel use of treadmill plus music in Parkinson's disease. J
855   Neuroeng Rehabil 16:68.

856   Collyer CE, Broadbent HA, Church RM (1994) Preferred rates of repetitive tapping and
857   categorical time production. Percept Psychophys 55:443-453.

858   Ding N, Patel AD, Chen L, Butler H, Luo C, Poeppel D (2017) Temporal modulations in
859   speech and music. Neurosci Biobehav Rev 81:181-187.

860   Doelling KB, Poeppel D (2015) Cortical entrainment to music and its modulation by
861   expertise. Proc Natl Acad Sci U S A 112:E6233-6242.

862   Doelling KB, Arnal LH, Ghitza O, Poeppel D (2014) Acoustic landmarks drive delta-theta
863   oscillations to enable speech comprehension by facilitating perceptual parsing.
864   Neuroimage 85 Pt 2:761-768.

865   Drake C, Jones MR, Baruch C (2000) The development of rhythmic attending in auditory
866   sequences: attunement, referent period, focal attending. Cognition 77:251-288.

867   Erkens J, Schulte M, Vormann M, Herrmann CS (2020) Lacking Effects of Envelope
868   Transcranial Alternating Current Stimulation Indicate the Need to Revise Envelope

Transcranial Alternating Current Stimulation Methods. Neurosci Insights
15:2633105520936623.

Fodor Z, Marosi C, Tombor L, Csukly G (2020) Salient distractors open the door of
perception: alpha desynchronization marks sensory gating in a working memory
task. Sci Rep 10:19179.

Fraisse P (1982) Rhythm and Tempo. In: Psychology of Music (Deutsch D, ed), pp 149-
180: Academic Press.

Garcia-Rosales F, Beetz MJ, Cabral-Calderin Y, Kossl M, Hechavarria JC (2018) Neuronal
coding of multiscale temporal features in communication sequences within the bat
auditory cortex. Commun Biol 1:200.

Giraud AL, Poeppel D (2012) Cortical oscillations and speech processing: emerging
computational principles and operations. Nat Neurosci 15:511-517.

Hanslmayr S, Aslan A, Staudigl T, Klimesch W, Herrmann CS, Bauml KH (2007)
Prestimulus oscillations predict visual perception performance between and within
subjects. Neuroimage 37:1465-1473.

Harrington MO, Ashton JE, Ngo HV, Cairney SA (2020) Phase-locked Auditory
Stimulation of Theta Oscillations during Rapid Eye Movement Sleep. Sleep.

Henry MJ, Obleser J (2012) Frequency modulation entrains slow neural oscillations and
optimizes human listening behavior. Proc Natl Acad Sci U S A 109:20095-20100.

Henry MJ, Herrmann B (2012) A precluding role of low-frequency oscillations for auditory
perception in a continuous processing mode. J Neurosci 32:17525-17527.

Henry MJ, Herrmann B, Obleser J (2014) Entrained neural oscillations in multiple
frequency bands comodulate behavior. Proc Natl Acad Sci U S A 111:14935-
14940.

Henry MJ, Herrmann B, Obleser J (2016) Neural Microstates Govern Perception of
Auditory Input without Rhythmic Structure. J Neurosci 36:860-871.

Henry MJ, Herrmann B, Kunke D, Obleser J (2017) Aging affects the balance of neural
entrainment and top-down neural modulation in the listening brain. Nat Commun
8:15801.

Horton C, D'Zmura M, Srinivasan R (2013) Suppression of competing speech through
entrainment of cortical oscillations. J Neurophysiol 109:3082-3093.

Horton C, Srinivasan R, D'Zmura M (2014) Envelope responses in single-trial EEG
indicate attended speaker in a 'cocktail party'. J Neural Eng 11:046015.

Hutchinson BT, Pammer K, Jack B (2020) Pre-stimulus alpha predicts inattentional
blindness. Conscious Cogn 87:103034.

Isaichev SA, Derevyankin VT, Koptelov Yu M, Sokolov EN (2001) Rhythmic alpha-
activity generators in the human EEG. Neurosci Behav Physiol 31:49-53.

Kasten FH, Duecker K, Maack MC, Meiser A, Herrmann CS (2019) Integrating electric
field modeling and neuroimaging to explain inter-individual variability of tACS
effects. Nat Commun 10:5427.

Keitel C, Keitel A, Benwell CSY, Daube C, Thut G, Gross J (2019) Stimulus-Driven Brain
Rhythms within the Alpha Band: The Attentional-Modulation Conundrum. J
Neurosci 39:3119-3129.

Lakatos P, Gross J, Thut G (2019) A New Unifying Account of the Roles of Neuronal
Entrainment. Curr Biol 29:R890-R905.

Lakatos P, Karmos G, Mehta AD, Ulbert I, Schroeder CE (2008) Entrainment of neuronal
oscillations as a mechanism of attentional selection. Science 320:110-113.

Lakatos P, Barczak A, Neymotin SA, McGinnis T, Ross D, Javitt DC, O'Connell MN
(2016) Global dynamics of selective attention and its lapses in primary auditory
cortex. Nat Neurosci 19:1707-1717.

MacDougall HG, Moore ST (2005) Marching to the beat of the same drummer: the
spontaneous tempo of human locomotion. J Appl Physiol (1985) 99:1164-1173.

Mathewson KE, Gratton G, Fabiani M, Beck DM, Ro T (2009) To see or not to see:
prestimulus alpha phase predicts visual awareness. J Neurosci 29:2725-2732.

Mathewson KE, Prudhomme C, Fabiani M, Beck DM, Lleras A, Gratton G (2012) Making
waves in the stream of consciousness: entraining oscillations in EEG alpha and
fluctuations in visual awareness with rhythmic visual stimulation. J Cogn Neurosci
24:2321-2333.

McAuley JD, Henry MJ (2010) Modality effects in rhythm processing: Auditory encoding
of visual rhythms is neither obligatory nor automatic. Atten Percept Psychophys
72:1377-1389.

McAuley JD, Jones MR, Holub S, Johnston HM, Miller NS (2006) The time of our lives:
life span development of timing and event tracking. J Exp Psychol Gen 135:348-
367.

Meyer L, Sun Y, Martin AE (2020) Synchronous, but not entrained: exogenous and
endogenous cortical rhythms of speech and language processing. Lang Cogn
Neurosci 35:1089-1099.

Mullensiefen D, Gingras B, Musil J, Stewart L (2014) The musicality of non-musicians:
an index for assessing musical sophistication in the general population. PLoS One
9:e89642.

Ng BS, Schroeder T, Kayser C (2012) A precluding but not ensuring role of entrained low-
frequency oscillations for auditory perception. J Neurosci 32:12268-12276.

Notbohm A, Kurths J, Herrmann CS (2016) Modification of Brain Oscillations via
Rhythmic Light Stimulation Provides Evidence for Entrainment but Not for
Superposition of Event-Related Responses. Front Hum Neurosci 10.

Obleser J, Kayser C (2019) Neural Entrainment and Attentional Selection in the Listening
Brain. Trends Cogn Sci 23:913-926.

Patel AD, Iversen JR, Chen Y, Repp BH (2005) The influence of metricality and modality
on synchronization with a beat. Exp Brain Res 163:226-238.

Riecke L, Sack AT, Schroeder CE (2015) Endogenous Delta/Theta Sound-Brain Phase
Entrainment Accelerates the Buildup of Auditory Streaming. Curr Biol 25:3196-
3201.

Riecke L, Formisano E, Sorger B, Baskent D, Gaudrain E (2018) Neural Entrainment to
Speech Modulates Speech Intelligibility. Curr Biol 28:161-169 e165.

Rimmele JM, Morillon B, Poeppel D, Arnal LH (2018) Proactive Sensing of Periodic and
Aperiodic Auditory Patterns. Trends Cogn Sci 22:870-882.

Ruspantini I, Saarinen T, Belardinelli P, Jalava A, Parviainen T, Kujala J, Salmelin R
(2012) Corticomuscular coherence is tuned to the spontaneous rhythmicity of
speech at 2-3 Hz. J Neurosci 32:3786-3790.

Sameiro-Barbosa CM, Geiser E (2016) Sensory Entrainment Mechanisms in Auditory
Perception: Neural Synchronization Cortico-Striatal Activation. Front Neurosci
10:361.

Schneider D, Herbst SK, Klatt L, Wöstmann M (2020) Target Enhancement or Distractor
Suppression? Functionally Distinct Alpha Oscillators form the Basis of Attention.
PsyArXiv.

Schroeder CE, Lakatos P (2009) Low-frequency neuronal oscillations as instruments of
sensory selection. Trends Neurosci 32:9-18.

Spaak E, de Lange FP, Jensen O (2014) Local entrainment of alpha oscillations by visual
stimuli causes cyclic modulation of perception. J Neurosci 34:3536-3544.

Stecher HI, Herrmann CS (2018) Absence of Alpha-tACS Aftereffects in Darkness
Reveals Importance of Taking Derivations of Stimulation Frequency and
Individual Alpha Variability Into Account. Front Psychol 9:984.

Stefanics G, Hangya B, Hernadi I, Winkler I, Lakatos P, Ulbert I (2010) Phase entrainment
of human delta oscillations can mediate the effects of expectation on reaction speed.
J Neurosci 30:13578-13585.

Ten Oever S, Schroeder CE, Poeppel D, van Atteveldt N, Mehta AD, Megevand P, Groppe
DM, Zion-Golumbic E (2017) Low-Frequency Cortical Oscillations Entrain to
Subthreshold Rhythmic Auditory Stimuli. J Neurosci 37:4903-4912.

Teng X, Tian X, Doelling K, Poeppel D (2018) Theta band oscillations reflect more than
entrainment: behavioral and neural evidence demonstrates an active chunking
process. Eur J Neurosci 48:2770-2782.

van Bree S, Sohoglu E, Davis MH, Zoefel B (2021) Sustained neural rhythms reveal
endogenous oscillations supporting speech perception. PLoS Biol 19:e3001142.

van Noorden L, Moelants D (1999) Resonance in the Perception of Musical Pulse. Journal
of New Music Research 28:43-66.

VanRullen R, Zoefel B, Ilhan B (2014) On the cyclic nature of perception in vision versus
audition. Philos Trans R Soc Lond B Biol Sci 369:20130214.

Vanrullen R, Busch NA, Drewes J, Dubois J (2011) Ongoing EEG Phase as a Trial-by-
Trial Predictor of Perceptual and Attentional Variability. Front Psychol 2:60.

Weisz N, Hartmann T, Muller N, Lorenz I, Obleser J (2011) Alpha rhythms in audition:
cognitive and clinical perspectives. Front Psychol 2:73.

Weisz N, Wuhle A, Monittola G, Demarchi G, Frey J, Popov T, Braun C (2014)
Prestimulus oscillatory power and connectivity patterns predispose conscious
somatosensory perception. Proc Natl Acad Sci U S A 111:E417-425.

Wilsch A, Neuling T, Obleser J, Herrmann CS (2018) Transcranial alternating current
stimulation with speech envelopes modulates speech comprehension. Neuroimage
172:766-774.

Woodrow H (1951) Chapter: Time perception. In: Handbook of experimental psychology,
pp 1224-1236. Oxford, England: Wiley; England.

Wostmann M, Waschke L, Obleser J (2019a) Prestimulus neural alpha power predicts
confidence in discriminating identical auditory stimuli. Eur J Neurosci 49:94-105.

Wostmann M, Alavash M, Obleser J (2019b) Alpha Oscillations in the Human Brain
Implement Distractor Suppression Independent of Target Selection. J Neurosci
39:9797-9805.

Zion Golumbic EM, Ding N, Bickel S, Lakatos P, Schevon CA, McKhann GM, Goodman
RR, Emerson R, Mehta AD, Simon JZ, Poeppel D, Schroeder CE (2013)

Mechanisms underlying selective neuronal tracking of attended speech at a
"cocktail party". Neuron 77:980-991.

Zoefel B, Archer-Boyd A, Davis MH (2018) Phase Entrainment of Brain Oscillations
Causally Modulates Neural Responses to Intelligible Speech. Curr Biol 28:401-408
e405.

Zoefel B, Davis MH, Valente G, Riecke L (2019) How to test for phasic modulation of
neural and behavioural responses. Neuroimage 202:116175.

1012

1013 **Figures**

1014

Figure 1. Auditory stimuli. Stimuli were 20-s long frequency modulated (FM) sounds
whose frequency fluctuated rhythmically at 2 Hz (bottom), without periodic fluctuations
in amplitude (top). Participants detected short silent gaps (middle left: Gap waveform)
embedded in the sound in one of 18 possible phase bins, uniformly distributed around the
2 Hz FM cycle. Each sound had 3, 4, or 5 gaps. Participants responded with a button press
each time they detected a silent gap. Circular histograms in the figure (middle right:
Distribution of gaps per FM phase bin) show the distribution of gaps per phase bin across
participants, separated by session. S1: session 1; S2: session 2. Hand icon was downloaded
from https://www.stockio.com/.

1024

1025

Figure 2. Neural entrainment to 2-Hz FM stimulus. (a) Evoked amplitude spectra from the fast Fourier transform (FFT) of the time-domain EEG signal. Red solid lines indicate the group average spectrum, gray lines show single participants' spectra, averaged over all electrodes. Inset plots show the topography for 2 Hz and alpha amplitude spectra averaged across participants, separately for session 1 and session 2. (b) Total amplitude spectra. The spectra were computed independently for each trial and then averaged over trials for each subject. Red solid lines indicate the group average spectrum, gray lines show single participants' spectra, averaged over all electrodes. (c) Inter-trial phase coherence (ITPC) indicating the degree of phase clustering across trials for each frequency (left), averaged over all electrodes. Gray lines show individual values and red lines show group average. (right) ITPC shown over time, again averaged across participants and all electrodes. S1: session 1; S2: session 2. Arrows in (a) and (b) indicate the peaks in amplitude and ITPC at the 2-Hz FM stimulus frequency and its first harmonic. Rectangles in (a) indicate the frequency range considered for further alpha analyses.

1042

Figure 3. Reliability of neural entrainment. (a) Inter-session correlation of 2 Hz (left), 4

Hz (middle) and alpha (right) amplitudes. Correlation coefficients and associated p-values

are given in each plot. Each dot represents a single participant. Solid black lines represent

the diagonal for each graph. (b) Circular histograms show neural phase lag relative to the

2-Hz FM stimulus for session 1 (blue, left) and session 2 (orange, middle). Circular

distance between phase lags in the different sessions is shown in the circular histogram in

the right. Z-values and associated p-values from the Rayleigh test are given in each session

plot and the v and p-value from the V-test is given for the circular-distance between

sessions. S1: session 1; S2: session 2.

1052

Figure 4. Stimulus-driven behavioral modulation and its reliability. (a) Hit rates as a function of 2-Hz FM stimulus phase. Dashed blue and orange lines represent the fitted cosine functions for sessions 1 and 2, respectively. Numbers on top of each graph show the mean hit rate across phase bins for each session. Each graph shows data for a different participant. In all panels, blue represents session 1 (S1) and orange represents session 2 (S2). (b) The plot on the left shows the distribution and spread of the amplitude of the observed sinusoidal modulation for each session. The box plot shows median (black horizontal line), 25th and 75th percentiles (box edges) and extreme datapoints (whiskers). Each circle represents a single participant. Horizontal blue and orange lines represent the 0.999 quantile (corresponding to p < 0.05, *Bonferroni* corrected) from the distribution of amplitude parameters from the surrogate datasets, for session 1 and session 2 respectively. Scatter plot in the middle shows the correlation between the fit amplitudes for the 2 sessions. Solid line is the diagonal. Circular histograms on the right of the panel show

individual optimal phases (i.e., FM-stimulus phase with highest hit rate in the cosine fit)

separated by session (left and middle histograms) and the circular distance between the two

(right histogram). Z and P-values in the plots refer to the results from the Rayleigh test. V

and p-value for the inter-session circular distance corresponds to the V test results. (c)

Scatter plots show inter-session correlations for hit rates, reaction times, false alarms rates,

and gap durations. Solid lines are the diagonal. *p = 9.69e-04. Distribution plots were

created using a modified version of the toolbox *distributionPlot* by Dorn J, 2008.

1074

Figure 5. Effect of pre-gap neural activity on gap detection. (a) Beta estimates (including distribution and spread) for 2-Hz phase (left) and alpha amplitude (right) from the winning mixed-effects logistic regression models fitted to the EEG data. Box plots show median (horizontal line), 25th and 75th percentiles (box edges) and extreme datapoints (whiskers). Black crosses represent outlier values. Each circle represents a single participant. Horizontal dashed lines mark the zero line. (b) Hit rates as a function of pre-gap 2-Hz neural phase for one representative participant. Solid lines represent actual data and dashed lines represent the cosine fits. Two cycles are concatenated for visualization purposes. (c) Circular histograms show the distribution of optimal neural 2-Hz phases across participants for each session (left/middle graphs) and the circular distance between both sessions (right). Z and p-values in the plots refer to the results from the Rayleigh test. V and p-value for the inter-session circular distance corresponds to the V test results. (d) Optimal 2-Hz neural phase for session 1 (blue) and session 2 (orange). Black arrows show the phase shift from session 1 to session 2. The Radius in the plot represents the absolute circular distance between sessions. Each circle represents a single

1091   participant and session. S1: session 1 (blue); S2: session 2 (orange). *p = 0.03, *Bonferroni*

1092   corrected.

1093

1094

Figure 6. Predicting alpha amplitude from 2-Hz neural phase. The graph shows the
distribution and spread of the beta coefficients from the generalized linear mixed effects
model predicting pre-gap alpha amplitude from pre-gap 2-Hz neural phase (left). Box plots
show median (colored horizontal lines), 25th and 75th percentiles (box edges) and extreme
datapoints (whiskers). Each circle represents a single participant. S1 (blue colors): session
1, S2 (orange colors): session 2.

1101

1102

Figure 7. Control experiment. (a) The graph shows the distribution and spread of
individual hit rates as a function of stimulus FM rate. Box plots show median (black
horizontal line), 25th and 75th percentiles (box edges) and extreme datapoints (whiskers).
Each circle represents a single participant. (b) Same as in (a) but for the amplitude of the
sinusoidal modulation. (c) Circular histograms showing the distribution of optimal FM-
stimulus phases for each FM rate. The inset on the right shows the resultant vector length
computed across individual optimal phases separated by FM rate.

1110

Figure 8. Effect of stimulus properties on gap detection. (a) Distribution plots showing the beta estimates resulting from mixed effect logistic regression models. Box plots show median (horizontal solid black line), 25th and 75th percentiles (box border), extreme values (whiskers) and outliers (black cross). (b) Visualization of the main effects shown in (a), i.e., difference of hits vs misses in terms of FM-stimulus phase, global time, local time and stimulus center carrier frequency. The two plots in the bottom right show the interaction phase * global time and phase * local time. In the plots, the amplitude of the sinusoidal

1119 modulation (fit amplitude) is shown after fitting cosine function to hit rates by FM-stimulus

1120 phase independently to four global/local time bins. S1: session 1; S2: session 2. * p =

1121 0.006, *Bonferroni* corrected.

1122