The visual cortex produces gamma band echo in response to broadband visual flicker

Alexander Zhigalov[1], Katharina Duecker[1] and Ole Jensen[1]

[1]Centre for Human Brain Health, School of Psychology, University of Birmingham, B15 2TT
Birmingham, United Kingdom

Abstract

The aim of this study is to uncover the network dynamics of the human visual cortex by
driving it with a broadband random visual flicker. We here applied a broadband flicker (1–
720 Hz) while measuring the MEG and then estimated the temporal response function (TRF)
between the visual input and the MEG response. This TRF revealed an early response in the
40–60 Hz gamma range as well as in the 8–12 Hz alpha band. While the gamma band
response is novel, the latter has been termed the alpha band perceptual echo. The gamma
echo preceded the alpha perceptual echo. The dominant frequency of the gamma echo was
subject-specific thereby reflecting the individual dynamical properties of the early visual
cortex. To understand the neuronal mechanisms generating the gamma echo, we
implemented a pyramidal-interneuron gamma (PING) model that produces gamma
oscillations in the presence of constant input currents. Applying a broadband input current
mimicking the visual stimulation allowed us to estimate TRF between the input current and
the population response (akin to the local field potentials). The TRF revealed a gamma echo
that was similar to the one we observed in the MEG data. Our results suggest that the visual
gamma echo can be explained by the dynamics of the PING model even in the absence of
sustained gamma oscillations.

Author Summary

The properties of the neuronal dynamics governing the visual system are highly debated.
While some emphasize the neuronal firing rate and evoked activity in response to visual
stimuli, others emphasize the oscillatory neuronal dynamics. To investigate the dynamical
properties of the visual system, we recorded the magnetoencephalography while stimulating
the visual system using a broadband (1–720 Hz) visual flicker. By estimating the temporal
response function (similar to cross-correlation) between the visual input and neuronal
activity, we demonstrated a clear response in the gamma band that we term the gamma
echo. We then constructed a physiologically realistic network model that could generate
gamma-band oscillations by a pyramidal-interneuron gamma (PING) mechanism. This
model allowed us to account for empirically observed response in the gamma band, and to
provide novel insight on the neuronal dynamics governing the early visual system. The stage
is now set for further investigating how the gamma echo is modulated by tasks such as
spatial attention as well as uncovering how the echo might propagate in the visual hierarchy.

Introduction

The properties of the neuronal dynamics governing the visual system are highly debated.
Some emphasize the neuronal firing rate [1–3] and evoked activity [4] in response to visual
stimuli. Others emphasize the oscillatory neuronal dynamics. In particular, neuronal
oscillations in the gamma band have been proposed to bind visual features by means of

synchronized spiking [5,6] as well as supporting communication between different brain
regions [7,8].

In this paper we are applying a new tool for investigating the dynamical properties of the
visual cortex in humans. We are making use of a new type of LED/DLP projector (Propixx,
VPixx Technologies Inc., Canada) that has a refresh-rate of up to 1440 Hz. The projector
makes it possible to stimulate the visual system with broadband flickering stimuli while
measuring the brain response using magnetoencephalography (MEG). This approach allows
for estimating the temporal response function (TRF). The TRF is the kernel that best
explains the brain response when convolved to the broadband input signal. In other words,
the TRF can be considered a simple model capturing the filter properties of the visual cortex.
In previous studies, such an approach has been used to investigate the dynamical properties
of the visual system at lower frequencies. Using a broadband flicker (1–80 Hz), the TRF was
approximated from the cross-correlation between the EEG and the input signal [9]. This
approach revealed a robust response in the alpha range termed "the perceptual echo". Yet,
the authors did not report dynamical properties in the gamma range most likely due to the
limited refresh rate of the monitor [9]. The aim of this study was to ask if the TRF also has a
band-limited response at higher frequencies, to uncover the faster dynamical properties of
the visual system. As we will show, the TRF function has a clear response at higher
frequencies which is limited to the gamma band.

The oscillatory dynamical properties of the cortical tissue have also been investigated by
means of computational modelling. This has resulted in the notion that neuronal gamma
oscillations are generated by the so-called pyramidal interneuron gamma (PING) mechanism
[10–12]. According to this mechanism, GABAergic interneurons play an essential role in
determining the frequency and synchronization properties for the generation of gamma
oscillations. Basically, the decay of the GABAergic feedback is a key variable determining
the period of each gamma cycle as the GABAergic hyperpolarization prevents neuronal firing
of both pyramidal and interneurons of about 10-20 ms [13]. Furthermore, the GABAergic
feedback also serves to synchronize the population activity [14,15]. In each cycle, the firing
of the pyramidal cells serve to excite the interneurons thus initiating the next oscillatory
cycle. This mechanism was first uncovered in hippocampal rat slices [16] and supported by
computational modelling [10–12]. Later, the GABAergic based mechanism was also
investigated using optogenetic studies in the somatosensory cortex [17,18] and the visual
system [19] in mice. A human MEG study demonstrated that gamma oscillations are strongly
modulated after the GABAergic feedback was manipulated by the GABAergic agonist
lorazepam in a double-blind study. As predicted by the PING model, the visual gamma
oscillations decreased in frequency while they increased in power as the GABAergic
feedback increased with the administration of lorazepam [20]. Other studies have reported a
link between gamma frequency and the GABA concentration as measured by magnetic
resonance spectroscopy (MRS) in both visual and somatosensory regions [21–23] (but see
[24]). Finally a PET study measuring GABA(A) receptor density found a link to gamma
frequency [25].

The PING mechanism can be implemented using different biophysical models [26–28].
Several of these implementations are based on Hodgkin–Huxley type of models. In this
work, we based our simulations on the Izhikevich model [29] which has reasonable realistic
dynamics and computational efficiency of integrate-and-fire neurons. This model is capable
to produce variety of spiking dynamics such as regular spiking, fast spiking, low threshold
spiking and other by adjusting only four parameters. In contrast to other more complex
models, e.g., [30] that require tuning of multiple parameters, the Izhikevich model is relatively

simple yet capable of explaining a wide range of phenomena pertaining neuronal
synchronization and oscillations [31–33].

In this study, we asked if the dynamical properties of the PING model can account for the
gamma response in the TRF we observed in the MEG data. The basic idea was to simulate
a network model for gamma oscillations with a broadband signal. This allowed us to estimate
the TRF of the network model and relate it to the TRF from MEG study. If the network model
can procure a TRF similar to the one observed in the MEG data, then we have provided
novel insight on the neuronal dynamics governing the early visual system.

In short, to investigate the dynamical properties of the visual system, we recorded the MEG
while stimulating the visual system using a broadband (1–720 Hz) visual flicker. This allowed
us to estimate the TRF of the visual system. As we will demonstrate, this resulted in a clear
band-limited response in the gamma band. We then constructed a physiologically realistic
network model that could generate gamma-band oscillations by a PING-type mechanism.
This model allowed us to account for empirically observed TRF in the gamma band.

Methods

Participants

109 Five participants (mean age: 33; age range: 28-38; 1 female) with no history of neurological
110 disorders partook in the study. The study was approved by the local ethics committee
111 (University of Birmingham, UK) and written informed consent was acquired before enrolment
112 in the study. All participants conformed to standard inclusion criteria for MEG experiments.
113 Participants had normal or corrected-to-normal vision.

Experimental paradigm

Two grating stimuli were presented bilaterally (Fig. 1A). After 0.5 s from the stimuli onset, the
left and right gratings started contracting for 3 s either coherently (same direction) or
incoherently (different directions). The direction of the motion (up / down) of the left and right
grating stimuli was random in consequent trials. The grating stimuli moved at a constant
speed of 0.5 degree/s. The participants were instructed to focus on the fixation point and
press the button when a cue indicating the direction of motion (i.e. coherent or incoherent)
occurred at the fixation point.

The key novelty of the experiment is that the luminance of the left and right stimuli was
modulated by two uncorrelated broadband (i.e., noise with uniform distribution) flickering
signals (Fig. 1B) at 1440 Hz. To this end, the grating stimuli were converted into textures
using Psychophysics toolbox [34], and then the luminance of these textures was modulated
by the flickering signals. We used the PROPixx DLP LED projector (VPixx Technologies Inc.,
Canada) to present the grayscale visual stimuli at a high refresh rate of 1440 Hz with a
resolution of 960 x 600 pixels (see, [35]). Such refresh rate was achieved by presenting
twelve frames within one refresh cycle of 120 Hz graphics card. The experimental paradigm
was implemented in MATLAB 2018a (Mathworks Inc., Natick, USA), and the scripts are
available on the OSF website (https://osf.io/fe8x5/).

Fig. 1. Experimental paradigm. (A) Grating stimuli were presented for 0.5 s and then the left
and right gratings started contracting for 3 s either coherently (same direction) or
incoherently (different directions). Yellows arrows on this figure (were not visible in the
experiment) indicate coherent motion downwards. The cue ('=') indicates coherent motion.
(B) Luminance of the left and right grating stimuli was modulated by two independent
broadband signals. The modulation (visual flicker) started at the time -0.5 s, together with the
onset of grating stimuli.

Magnetoencephalography data acquisition and processing

The MEG data were acquired using a 306-sensor TRIUX Elekta Neuromag system (Elekta,
Finland). The magnetic signals were bandpass filtered from 0.1 and 330 Hz using embedded
anti-aliasing filters and then sampled at 1000 Hz. The acquired time series were segmented
into 4 s epochs; −1 to 3 s relative to the onset of the stimuli motion. Note that the stimuli were
flickering during the -0.5 to 3 s time interval. Simultaneously with the MEG, we also acquired
the eye-movements and blinks using an EyeLink eye-tracker (SR Research, Canada). Eye
blinks were detected in the X-axis and Y-axis channels of the eye tracker by applying a
threshold of 5 SD. The saccades were detected using a scatter diagram of X-axis and Y-axis
time series of the eye-tracker for each trial. An event was classified as a saccade if the focus
away from the fixation point by 2° and lasted longer than 500 ms. Trials contaminated by blinks
and saccades were removed from further analysis. We also rejected trials containing large-
amplitude events (above 5 SD) in MEG which are mainly associated with motion and muscle
artefacts. As a result, the number of trials that remained after exclusion was 142 ± 10 (mean ±
SD) per participant. For each participant, the number of trials per condition was equalized by
randomly selecting the same number of trials. Such equalising serves to avoid a potential bias
in TRF estimation related to unbalanced number of trials.

Power spectral density

The power spectral density was estimated using Welch's method as implemented in the
SciPy toolbox [36]. To this end, 4 s epochs of data were divided in 1 s segments with 50%
overlap and weighted by a Hanning taper. The Fourier transform was applied to each
segment and squared Fourier coefficients were averaged over the segments.

163 The same approach was applied to estimate the power spectral density of the modelled
164 data.

Temporal response functions

166 Temporal response functions (TRF) were estimated using ridge regression as implemented
167 in mTRF toolbox [37]:

$$TRF = (S^T S + \lambda I)^{-1} S^T x$$

where S is the lagged time series of the stimulus, x denotes neuronal response, I is the
identity matrix, and λ is the smoothing constant or "ridge parameter". In this study, the
smoothing constant λ was set to 1. Note that TRF is similar to a linear cross-correlation
function if the stimulus is a random (temporally uncorrelated) signal.

The TRFs were computed between the broadband flickering signal and the MEG
gradiometer with the strongest visual flicker response. Note that the TRF in Figure 3 was
computed for an occipital gradiometer that captures signals in both the alpha and gamma
bands. In order to assess the contribution of the 50 Hz line noise to the TRF, we also
computed the TRF for MEG magnetometer with strongest response to the visual flicker
before and after applying source space separation (SSS) method [38] for noise reduction.
For the modelled data we calculated the TRF between the broadband input current and the
average membrane potential for the E-cells.

Time-frequency analysis

The time-frequency representations of power of the TRF were computed using the Hanning
taper approach as implemented in the Fieldtrip toolbox [39]. We used time-windows of
different length spanning 5 cycles at the specific frequency. The analysed frequency range
was 5 – 100 Hz with steps of 1 Hz and the time ranged from -0.1 to 0.2 s (or 0.7 s as in
Figure 1) with steps of 5 ms. In case of the induced gamma oscillations (see, Fig. 5), we
reported a relative change in MEG power during the -0.5 to 3 s stimulation interval compared
to the -1.0 to -0.5 s baseline as follows, $P_{rel} = (P_{ST} - P_{BL}) / (P_{ST} + P_{BL})$, where P_{ST} and P_{BL}
denote MEG power during stimulation and baseline, respectively.

MRI data acquisition

191 A high-resolution T1-weighted anatomical image (TR/TE of 7.4/3.5 ms, a flip angle of 7°, FOV
192 of 256×256×176 mm, 176 sagittal slices, and a voxel size of 1×1×1 mm^3) was acquired using
193 3-Tesla Phillips Achieva scanner.

Source reconstruction

To build a forward model, we first manually aligned the MRI images to the head shape
digitization points acquired with the Polhemus Fastrak. Then, the MRI images were
segmented, and a single shell head model was prepared using spherical harmonics fitted to
the brain surface [40]. The individual anatomy was warped into standard MNI template using
the Fieldtrip toolbox [39].

To localise power of the of induced gamma rhythm in source space, we used the Dynamical
Imaging of Coherent Sources (DICS; [41]) approach as implemented in thr Fieldtrip toolbox.
The time-frequency analysis was applied to the MEG data in the -0.5 to 3 s interval that covers
the entire duration of the flickering stimuli.

To localise the gamma echo response, we used Linearly Constrained Minimum Variance
(LCMV) beamformer [42] as implemented in the Fieldtrip toolbox. To this end, we first

reconstructed time series in source space by applying LCMV beamformer to MEG data, and
then estimated TRF (see, above) for each source point. The covariance matrix for the LCMV
beamformer was estimated for bandpass filtered MEG data (40 – 100 Hz) in the -0.5 to 3 s
time interval.

The location differences between sources of induced gamma and gamma echo response were
assessed by extracting the coordinates (along the interior-superior z-axis) of these sources
for each participant separately, and then applied the t-test over participants.

Model

We modelled the neuronal populations of cortical areas as a network of interconnected
excitatory and inhibitory neurons (Fig. 7A). The network model was composed of 400 regular
spiking excitatory pyramidal neurons (E-cells), and 100 fast-spiking inhibitory interneurons
neurons (I-cells). The number of neurons as well as ratio between E-cells and I-cells (4 to 1)
are consistent with previous studies [29,31].

Neuronal model

We used the neuronal model proposed by Izhikevich [29] to simulate the membrane
potentials of the excitatory and inhibitory neurons.

$$v' = 0.04v^2 + 5v + 140 - u + I + I_{syn} \tag{1}$$

$$u' = a(bv - u) \tag{2}$$

$$s'_{AMPA} = \alpha_{AMPA}F(v)(1 - s_{AMPA}) - \beta_{AMPA}s_{AMPA} \tag{3}$$

$$s'_{GABA} = \alpha_{GABA}F(v)(1 - s_{GABA}) - \beta_{GABA}s_{GABA} \tag{4}$$

where *v* represents the membrane potential of the simulated neuron, *I* determines the input
current, *u* is a slow recovery variable. The model also includes a reset: when *v* exceeds 30
mV, an action potential is assumed, and the variables are reset: *v* = *c* and u = u + d. The
coefficients a = 0.02 and b = 0.2, c = -65 and d = 8 define the regular spiking E-cells, while a
= 0.1 and b = 0.2 c = -65 and d = 2 define the fast spiking I-cells. The variable *s* represents
the gating for synaptic input and includes both s_{AMPA} and s_{GABA} defined for each sending E-
cell and I-cell, respectively.

To model the kinetics of the AMPA and GABA neurons, we followed the formalism from
Wang and Buszaki [11].

The term I_{syn} reflects the synaptic current in the receiving neurons whereas *s* reflects the
gating variable in the sending neuron,

$$I_{syn} = \sum_{i=1}^{N} C_{(:,i)} \cdot s_{AMPA} \cdot (v_{AMPA} - v) + \sum_{j=1}^{M} C_{(:,j)} \cdot s_{GABA} \cdot (v_{GABA} - v) \tag{5}$$

where N is the number of excitatory neurons, M is the number of inhibitory neurons, C is the
connectivity matrix, v_{AMPA} and v_{GABA} are reversal potentials of AMPA (v_{AMPA} = 0 mV) and GABA
receptors (v_{GABA} = -70 mV on E-cells and v_{GABA} = -75 mV on I-cells), respectively. The
differential equation (3 and 4) includes parameters channel opening rate α_{AMPA} = 12 (ms^{-1})
and the channel closing rate β_{AMPA} = 0.5 (ms^{-1}) for AMPA receptors, and α_{GABA} = 12 (ms^{-1})
and β_{GABA} = 0.1 (ms^{-1}) for GABA receptors; *F* denotes a sigmoid function: $F(v) = $
$1/(1 + exp(-v/2))$.

We specified the connectivity strength between different types of cells based on prior
experimental results [43]. These connection strengths represented the amount of current
that enters the receiving neuron after a spike of the sending neuron [31]. To make sure that
the model connectivity was selected adequately, we assessed the model output frequency
(firing rate) as a function of connectivity between I-cells for several input currents to E-cells
and I-cells (Fig. 2). The plot shows a decrease in frequency with increasing inhibitory
connectivity strength as predicted by the PING mechanism [11].

Fig. 2. Model output frequency as a function of connectivity strength between I-cells.

We further adjusted the connectivity matrix while preserving the connectivity strength ratio
between different type of cells, to obtain robust oscillations at 48 Hz for given input currents.
The connectivity between cells was as follows: connectivity between I-cells (c_{ii} = 0.004),
connectivity from I-cells to E-cells (c_{ie} = 0.006), and connectivity from E-cells to I-cells (c_{ei} =
0.003). Since the connectivity strength between E-cells is much lower compared to other
cells, ~0.25 * c_{ii} [31], we set connectivity between E-cells to 0 (c_{ee} = 0.0).

Population activity and local field potential produced by the model

The population activity of the model reflecting the local field potentials was computed by
averaging the membrane potentials of the E-cells. This somehow approximates the fields
measured by MEG which are generated by the sum of dendritic currents in pyramidal cells
[44].

To solve the differential equations (1-4) numerically, we used the Euler method with the
time-step Δt = 1 ms.

Data and code availability

Data and code are available on the OSF website (https://osf.io/fe8x5/).

Results

We used a moving grating paradigm in which the left and right visual stimuli were generated
using orthogonal broadband random signals while we recorded the ongoing MEG (Fig. 1).

Broadband visual stimulation reveals alpha and gamma echoes in the visual system

The TRF of a system can be estimated by deconvolving its input and output [11]. We used
ridge regression (see, Methods) to compute the TRF for the MEG signals from sensors over
visual cortex while stimulating with a broadband random visual input. Figure 3 shows the
TRF for an occipital sensor for a representative participant. The TFR has a rich temporal
structure (Fig. 3A, black line). Applying a bandpass filter in the gamma band (40–100 Hz) to
the TRF revealed an early response (Fig. 3A, blue line) at about 40 ms. A bandpass filter in
the alpha band (8–13 Hz) revealed a later response comprising several cycles. A time-
frequency analysis of power further demonstrated the presence of band-limited responses in
the alpha and gamma band in the TRF (Fig. 3B). While the late response – the "alpha
perceptual echo" – was reported in the previous studies (e.g. [9], the early response – the
"gamma echo" – is so far unobserved property of the visual system.

Fig. 3. TRF of the human visual cortex derived from a random broadband visual input train.
(A) The TFR filtered in the broad band (1–100 Hz; black line), the gamma band (40–100 Hz;
blue line) and the alpha band (8–13 Hz; gray line). (B) Time-frequency representation of
power of the TRF. Note that the TRF was computed for an occipital gradiometer that
captures both the alpha band and gamma band TRF.

TRF show individual resonance frequency of gamma echo

To further evaluate the characteristics of the gamma echo, we computed TRF for five
individual participants using the MEG gradiometers with strongest response to the
broadband input signal. The frequencies of the individual gamma echoes ranged from 46 to
56 Hz and were close to 48 Hz on average (Fig. 4). The responses in the gamma band were
strongest at 50 – 100 ms and spanned over 2 – 3 cycles. To ensure that the 50 Hz line noise
does not contribute to the gamma echo, we assessed the power spectral density and TRF
for magnetometers before and after applying the source space separation (SSS) method
[38] as implemented in MNE Python toolbox [45]. SSS removes artifacts caused by external
disturbances such as line noise, and hence, provides possibility to evaluate contribution of
50 Hz noise to the gamma echo. We performed the analysis on the magnetometers as they
are particularly sensitive to 50 Hz line noise and hence, they provide a worst-case setting.
The results clearly showed that suppression of 50 Hz noise in data did not change the
characteristics of gamma echo (Fig. S1) in any of the participants. This demonstrates that
the gamma echo is not biased by the line noise.

Fig. 4. TRF and the associated time-frequency representation of power for individual
participants. Note the robust response in 40–60 Hz gamma range. Gray lines depict the TFR
at 1–100 Hz while the black lines show the response filtered at 40–100 Hz.

Induced gamma oscillations

To relate the gamma echo response and visually induced gamma oscillations, we computed
a time-frequency representation of power at the occipital sensor with the strongest response

to flicker (see, Fig. 5). The grating induced gamma oscillations at around 57 Hz (grand
average). Interestingly, the individual frequencies of the induced gamma oscillations were
faster than frequencies of the gamma-echo (Fig. 5). These results suggested that the
gamma echo and induced gamma oscillations are produced by different generators.

Fig. 5. Time-frequency representation of the power (relative change) induced by the
gratings. The dashed line indicates frequency of the induced gamma oscillations, and for
comparison, the solid line indicates frequency of the gamma echo. Curves next to the time-
frequency plots represent power averaged over the -0.5 to 3 s time interval.

Localization of gamma echoes and induced gamma oscillations in sensor and source spaces

To identify the generators of the gamma echo and induced gamma oscillations, we
computed their spatial characteristics at the sensor and source levels. Both sensor and
source space topographies of the gamma echo clearly showed that the response was mainly
localized in the primary visual cortex (Fig. 6A, B). Similarly, induced gamma oscillations were
originated in the visual cortex as suggested by sensor and source space topographies (Fig.
6C). The sources of the gamma echo response and induced gamma oscillations were
largely overlapped (Fig. 6), although, sources of the gamma echo appeared more lateralised
and superior. We assessed their spatial overlap by extracting coordinates along z-axis and
comparing these coordinates across subjects using t-test (see, Methods). Although, the
sources of induced gamma oscillations were slightly superior (~11 mm on average)
compared those of the gamma echo, the difference was not significant ($p > 0.19$, t-test).
These results suggest that the gamma echo response and induced gamma oscillations are
produced by neighbouring but not necessarily the same sources.

Fig. 6. Topographies and source modelling of the gamma echo and induced gamma oscillations. (A) The topography and the source modelling (LCMV beamformer) of the peak amplitude of the gamma echo (0.04 – 0.08 s) for the right flickering stimuli. (B) Same as (A) but for left flickering stimuli. (C) The topography and source modelling of the power (DICS beamformer) of the induced gamma oscillations within range 40 – 100 Hz.

PING based model of gamma oscillations

We implemented a pyramidal-interneuron gamma (PING) [10,12,16] network model with biologically plausible synaptic currents [11] attempting to account for the TRF in the gamma band. The model consisted of interconnected excitatory (E) and inhibitory (I) cells (Fig. 7A). The connectivity matrix in Fig. 7B describes the connection strengths between all the cells. In this model, the connectivity strength between different type of cells was set based on prior empirical findings [43], see Methods. The connection strength was weighted by random values drawn from a uniform distribution [0, 1], to ensure heterogeneous connectivity. For the connectivity matrix in Fig. 7B and constant input currents of 12.25 µA and 5.25 µA to the E-cells and I-cells, respectively, the model produced synchronous spiking activity (Fig. 7C). The membrane potentials of the excitatory neurons were averaged to approximate the local field potentials, i.e., the population activity (Fig. 7D). Spectral analysis revealed robust oscillations in the local field potentials at 48 Hz (Fig. 7E). The PSD was computed and subsequently averaged over 20 trials, to reduce random variations in the model output.

Fig. 7. The PING model with constant input currents produces robust neuronal oscillations at
around 48 Hz. (A) Neuronal architecture; the simulated network consisted of interconnected
E-cells (N=400) and I-cells (N=100). (B) Connectivity matrix between E-cells and I-cells. (C)
Spike rastergram for E-cells (blue) and I-cells (orange) shows temporal synchronization
among the cells in the presence of constant input current. (D) The average membrane
potential of the E-cells exhibited prominent oscillations. (E) Power spectral density of the
average membrane potential for the E-cells shows a clear peak at 48 Hz. Note that PSD was
averaged over 20 trials.

In accordance with the PING mechanism, the model firing rate is determined by the input
currents and the connectivity strength [11], suggesting that the resonance frequency of 48
Hz can be obtained for different combinations of the input currents and connectivity. To
further explore this possibility, we assessed the model output power (at the spectral peak)
and corresponding frequency (Fig. 8A) by varying the input currents to E-cells and I-cells
while preserving the connectivity parameters and the network size. The 2D parameter space
diagram (Fig. 8B, C) indicated that resonance frequency of 48 Hz can be obtained for
several combinations of the input currents. Considering this, in addition to the input currents
used in our simulations above (I_E = 12.25 µA and I_I = 5.25 µA; black circle in Fig. 8B,C), we
also explored two pairs of the input currents: I_E = 8.75 µA and I_I = 5.25 µA (red circle in Fig.
8B,C), I_E = 12.75 µA and I_I = 7.25 µA (blue circle in Fig. 8B,C), which produce oscillations at
the resonance frequency. Temporal characteristics of the spiking activity and mean field
potentials for three pairs of the input currents are shown in Fig. 8D. These results suggested
that our initial model parameters (I_E = 12.25 µA and I_I = 5.25 µA) provided more stable
oscillations compared to the other pairs of the input currents.

Fig. 8. (A) The PSD with spectral peak at 48 Hz for input currents I_E = 12.25 µA and I_I = 5.25
µA. (B, C) Power at the spectral peak (B) and corresponding frequency (C) of the network
oscillations as a function of input current to E-cells and I-cells. Black, red, and blue circles
indicate pairs of the currents producing oscillations at 48 Hz. (D) Spiking activity and
corresponding average membrane potentials for three selected input currents that produce
oscillations at 48 Hz.

To ensure that the model was operating in a stable regime, we estimated the duration of
transient effect after the input current was applied (Fig. 9A). The time diagram of spiking
activity and mean field potentials showed that the transient effect lasted less than 0.5 s. In
the further analyses, we discarded the first 1 s of the signal to make sure that the remaining
signal is stationary.

Fig. 9. (A) Transients in spiking activity and average membrane potential after applying
constant input currents to E-cells and I-cells. (B) The power (at the spectral peak) and
corresponding frequency of the network as a function of the network size. The labels indicate
the number of neurons in the network. Bars indicate standard deviation estimated in 20
trials.

Finally, we evaluated the impact of the network size on frequency and power of the mean-
field potentials (Fig. 9B). Importantly, while changing the network size, we preserved the
ratio between E-cells and I-cells as 4 to 1 following our original model [29]. The results
suggested that an increase in the network size from 200 to 1000 neurons was associated
with a slight decrease in the frequency from 50 to 46 Hz, and an increase in the power. Such
a relatively small change in the output characteristics suggested robustness of the model.

Broadband input to the model produces a gamma echo at the resonance frequency

In order to estimate the TRF of the network dynamics, we applied broadband input current to
the model. The input current was modelled as a sum of constant current of 12.25 µA and
random (uniform) noise with amplitude of 4 µA to the E-cells and a constant current of 5.25
µA to I-cells (Fig. 10A). This simulates the LGN input to the area V1 in the visual cortex. For
the broadband input current, the model produced neuronal activity (Fig. 10A-D) similar to
those of the constant input currents (see, Fig. 7). In the presence of broadband input, spiking
activity of E-cells remained highly synchronised (Fig. 10B), so that average membrane
potentials showed oscillations that can be readily observed in population response (Fig.
10C) and as well as in the power-spectral density (Fig. 10D). By computing the TRF
between the input broadband current and output voltage, we observed a gamma echo (Fig.
10E) similar to that in MEG data. Importantly, the frequency of the echo matched the
resonance frequency of the model (Fig. 10F). To obtain more robust results, the PSD and
TRF were averaged over 20 trials.

Fig. 10. Broadband input current to E-cells produces damped oscillations in the TRF – the
gamma echo. (A) Broadband input current to E-cells (black line) and constant input current
to I-cells (orange line). (B) Spike rastergram for E-cells and I-cells for broadband input
current. (C) The average membrane potential of the E-cells in response to fluctuating input
currents. (D) Power spectral density of average membrane potentials of the E-cells averaged
over 20 trials. (E) TRF assessed for the average membrane potentials of the E-cells with
respect to the broadband input current. Note the clear "gamma echo". Gray and black lines
depict respectively raw and the filtered TRF (40 – 100 Hz) averaged over 20 trials. (F) Time-
frequency representation of power of the TRF.

We further assessed the impact of the amplitude of the broadband input current on
characteristics of the gamma echo. The input current was modelled as a sum of constant
current of 12.25 µA and random (uniform) noise with amplitude ranged from 2 to 9 µA to the
E-cells and a constant current of 5.25 µA to I-cells. The gamma echo revealed by MEG was
resembling the model gamma echo for broadband input current of 4 µA (Fig. 11). In case of
lower currents (2 µA and 3 µA), the response at resonance frequency showed much longer
decay. Conversely, the higher currents (5 µA to 9 µA) produced a response with shorter
decay time.

Fig. 11. The amplitude of the broadband input current determines temporal characteristics of the gamma echo. TRF (*top panel*) and its time-frequency representation (*bottom panel*). I_{BB} denotes amplitude of the broadband input current.

Oscillatory inputs produce maximum power at the resonance frequency

We further explored the model response by applying an oscillatory input current to E-cells in a similar manner as the broadband input current. The oscillatory input was modelled as a sum of constant current of 12.25 µA and a sine wave with amplitude of 9 µA to E-cells, while keeping the current to I-cells constant at 5.25 µA (Fig. 12A). The oscillatory input increased synchronization among the E-cells in the gamma band (Fig. 12B) compared to the absence of oscillatory input (see, Fig. 7C). The average membrane potential of the E-cells also showed a larger amplitude (Fig. 12C) compared to that of the constant input current (Fig. 7D). The oscillatory input current (mimicking visual stimulation) at the resonance frequency (48 Hz) produced stronger response compared to a response at non-resonance (e.g. 78 Hz)

frequency input (Fig. 12D). To assess the spectral profile of the model in response to input
currents of different frequencies, we applied a sinusoidal input current ranging from 1 to 100
Hz with 1 Hz steps and amplitude of 9 µA. The results showed an amplified peak in the
power spectral density near the resonance frequency of 48 Hz (Fig. 12E). Consistently with
earlier findings [46], the spectral profile peaked at the resonance frequency and showed a
decay towards higher frequencies.

Fig. 12. Oscillatory input current reveals an amplification of oscillatory dynamics at the ~48
Hz resonance frequency. (A) Oscillatory input current to E-cells (black line) and constant
current to I-cells (orange line). (B) Spike rastergram for E-cells and I-cells. (C) The average
membrane potential of the E-cells. (D) Example of power spectral density for input current at
48 Hz (resonance frequency, black line) and at 78 Hz (non-resonance, orange line). (E)
Power spectral density of the average membrane potential for oscillatory input over multiple
frequencies, 1–100 Hz, and amplitude of 9 µA.

To further investigate the model response to an oscillatory input, we computed the model
output power (at the spectral peak) and corresponding frequency as a function of the input
current, by systematically varying its frequency (1 – 100 Hz) and amplitude (0.5 – 10 µA).
The results showed that the peak frequency in the spectral profile increased with the
amplitude of input current (Fig. 13A), meaning that the peak at around 48 Hz can be
obtained for a specific input current of 9 µA (corresponds to Fig. 12E). This suggests that the
amplitude of visual input may differently affect frequency of the neuronal response.
Interestingly, there was a minimum input current of 5 µA, above which, the frequency of the
network oscillations matched the frequency of the input current (Fig. 13B). This suggests
that the frequency of external stimulation may not be directly translated to the firing rate.

Fig. 13. Network output power at the spectral peak (A) and corresponding frequency (B) as a function of the oscillatory input. The amplitude and frequency of the input current varied within 0.5 – 10 µA and 5 – 100 Hz, respectively. Note that the spectral profile on A (right panel) for $I_E = 9$ µA corresponds to the spectral profile shown on Fig. 12E.

Discussion

In this study, we used broadband visual stimulation combined with MEG to assess the dynamical properties of the human visual cortex. We did this by estimating the temporal response function (TRF), i.e. the kernel best explaining the MEG signal from visual cortex when convolved to the broadband visual input. The TRF is similar to the cross-correlation function [37] in case of a random temporally uncorrelated input. In the TRF we observed an early response limited to the gamma band that we term the *gamma echo*. We also observed the known *perceptual echo* in the alpha band [9]. To explore the neuronal mechanisms producing the gamma echo, we implemented a biophysically plausible pyramidal-interneuron-gamma (PING) model. When driving the model by a broadband input current and estimating the respective TRF, we observed a gamma echo similar to that in the MEG data. Based on these simulations, we suggest that the gamma echo is produced by a network in which the dynamical properties are largely determined by GABAergic interneurons and their interaction with pyramidal cells; i.e. a PING-type network adjusted to produce damped oscillations in the gamma band can account for the gamma echo.

Relationship between alpha and gamma echoes

Our findings reveal that both the alpha and gamma echo reflect the intrinsic properties of the
visual system. However, there are several differences between the alpha and gamma band
echoes. First, while alpha echo occurs at around 0.2 s, gamma echo has a much earlier
onset at 40 ms. Second, the gamma echo is largely localized in the primary visual cortex,
whereas the alpha echo propagates over the cortex [47]. Third, the alpha-echo spans for up
to 10 cycles, while gamma-echo vanishes after 2–3 cycles. These different characteristics
suggest that the echoes are generated by different mechanisms and may not always occur
in the brain concurrently.

At the same time the alpha and gamma echoes share similar properties. Earlier studies have
demonstrated that the alpha echo shows maximum power at the individual alpha frequency
[9]. Similarly, we found that the central frequencies of the gamma echo were specific to the
participants. Our simulation results showed that the gamma echo of the model was strongly
related to the resonance properties of the neuronal network. Thus, we suggest that the
gamma echo reflects the intrinsic resonance properties of the early visual system.

Our results show that the gamma echo originates in the primary visual cortex and does not
appear to propagate outside of this area. Conversely, a recent study showed that alpha
echoes have the characteristics of travelling waves [47]. The authors further suggest that
the spatio-temporal dynamics of the alpha echo is consistent with the timing of the neuronal
activity that one might expect for feedforward and feedback communication associated with
predictive coding. Indeed, both alpha and gamma oscillations might play a key role for
predictive coding [48,49], and thus, propagation properties associated with the gamma echo
may provide crucial insight on the feedforward dynamics associated with predictive coding.

In contrast to the alpha echo, the gamma echo has not been observed in previous studies
that applied broadband visual stimulation (e.g. [9,50]), most likely since these studies relied
on projectors with a relatively low refresh rate of 100 to 160 Hz. The resulting temporal
resolution of 6 – 10 ms corresponds to at least 3 samples for a 48 Hz-cycle, and thus, it does
not allow to fully capture gamma-band activity. In this study, we used a projector with a
refresh rate of 1440 Hz which allows presenting stimuli with a sub-millisecond temporal
resolution allowing for optimally estimating the gamma echo.

Induced gamma oscillations and gamma echo

In this study, we presented grating stimuli concurrently with the broadband visual flicker, and
hence, both the grating stimuli and the flicker can potentially induce a response in the
gamma band. Analysing time-frequency representation of MEG power and the gamma echo,
we found that the visual grating induces gamma oscillations at around 57 Hz (grand
average) whereas central frequency of the gamma echo was near 48 Hz, indicating that
these phenomena do not overlap in the frequency domain. Furthermore, we did source
localization of the induced gamma oscillations and the gamma echo. Although, the sources
were located in the primary visual cortex closely to each other, there was an indication that
sources of the induced gamma are slightly superior (~11 mm) than the sources of gamma
echo. Consistently with our findings, previous studies [21,51–54] also demonstrated that
static and dynamic gratings induce gamma oscillations in the primary visual cortex. Indeed,
the gamma echo and induced gamma oscillations may originate from neighbouring but
different areas (for instance, V1 and V2), which might not be easily dissociated due to limited
spatial resolution of MEG. Based on the findings, we conclude that the gamma echo and the
induced gamma oscillations are produced by different neuronal populations. This is

consistent with the work of Duecker et al, 2020 demonstrating the visual flicker does not
entrain endogenous gamma oscillations but they are rather coexisting phenomena.

Mechanism of the gamma echo

We implemented a biophysically realistic computational model based on the PING
mechanism to clarify the underlying mechanism of the gamma echo. As we discussed
earlier, the gamma echo and induced gamma oscillations are likely to be produced by
different generators. This explains the absence of a resonant frequency in our recent study
(Duecker et al., 2020) which however was reported by Gulbinaite and colleagues [46]. In
their study, the resonance frequency at about 47 Hz was observed when driving the visual
system with rhythmic stimuli in a wide range of frequencies (3 to 80 Hz). We were able to
reproduce this finding using our model and we therefore suggest that the rhythmic
stimulation in study by Gulbinaite et al. did not affect the network producing endogenous
gamma oscillations *per se*, but rather a network in V1 producing damped gamma
oscillations. This way, the gamma echo does not reflect the dynamics of the endogenous
gamma oscillations, but rather co-exists with endogenous gamma oscillations in different
frequency bands.

Computational model

In this study we used a relatively simple model to describe dynamics of the early visual
cortex in response to the broadband and rhythmic stimulation. Our model was based on the
Izhikevich framework [29] and thus, combined biologically plausibility of Hodgkin–Huxley
type dynamics and the computational efficiency of integrate-and-fire neurons. In addition, we
improved the model by incorporating the kinetics of the AMPA and GABA neurons based on
the formalism from Wang and Buszaki [11]. Since the gamma echo is well localised in the
primary visual cortex (V1), and hence, the underlying mechanism does not require a
complex interplay between areas in the visual system, our model adequately describe this
phenomenon. In future work more complex multicompartment models [26] could also be
utilised to describe gamma echo and perhaps provide some insight into the mechanism.

Our model was tuned to account for the gamma echo, and in future work it would interesting
to extend the model framework such that the network can produce alpha oscillations as well.
This would allow addressing more complex relationship between the gamma and alpha
echoes from mechanistic perspective. Yet an avenue to explore would be to extend the
models with a second network capable of producing endogenous gamma oscillations. This
would allow for exploring the conditions when the network producing the gamma echo could
also entrain that network producing the endogenous gamma oscillations.

Implication of the findings

Our findings can provide new insight into the mechanism of evoked responses. It seems
plausible that the characteristics of the early evoked responses in the visual system might be
determined by the properties of the endogenous gamma activity. Indeed evoked gamma
oscillations in response to visual stimuli have been identified in a previous study [55].
Importantly these oscillations increased with hypocapnia which is known to also increase
GABAergic conductivity. In future work it would also be interesting to further uncover which

components of visual evoked fields can be explained by the neuronal dynamics also
producing the gamma echo [56].

The gamma echo is not related to 50 Hz line noise.

One might be concerned that the gamma echo is partly a consequence of the 50 Hz line
noise given the similar frequencies. However, our analysis on magnetometers (see, Fig. S1)
clearly demonstrates that suppression of the 50 Hz line noise does not change the
characteristics of the gamma echo in any of the participants. Moreover, the gamma echo did
vary from 46 to 56 Hz over participants. We conclude that the gamma echo is not biased by
the 50 Hz line noise.

Conclusion

Using broadband visual input stimuli we here provide evidence for a band-limited temporal
response function in the gamma that we term the gamma echo. A computational model
showed that a PING type of mechanism based on a network producing damped oscillations
in the gamma band could account for the gamma echo. Nevertheless, the gamma echo is
distinct from the mechanism producing endogenous gamma oscillations. The stage is now
set for further investigating how the gamma echo is modulated by tasks such as spatial
attention as well as uncovering how the echo might propagate in the visual hierarchy.

References

[1]   Shadlen MN, Newsome WT. The variable discharge of cortical neurons: Implications
for connectivity, computation, and information coding. Journal of Neuroscience
1998;18:3870–96. https://doi.org/10.1523/jneurosci.18-10-03870.1998.

[2]   Stein RB, Gossen ER, Jones KE. Neuronal variability: Noise or part of the signal?
Nature Reviews Neuroscience 2005;6:389–97. https://doi.org/10.1038/nrn1668.

[3]   Shadlen MN. Rate versus Temporal Coding Models. Encyclopedia of Cognitive
Science, Chichester: John Wiley & Sons, Ltd; 2006.
https://doi.org/10.1002/0470018860.s00372.

[4]   Mangun GR, Hillyard SA, Luck SJ. Electrocortical substrates of visual selective
attention. In: Meyer DE, Kornblum S, editors. Attention and performance 14:
Synergies in experimental psychology, artificial intelligence, and cognitive
neuroscience. 1st ed., The MIT Press; 1993, p. 219–43.

[5]   Engel AK, Singer W. Temporal binding and the neural correlates of sensory
awareness. Trends in Cognitive Sciences 2001;5:16–25.
https://doi.org/10.1016/S1364-6613(00)01568-0.

[6]   von der Malsburg C. The what and why of binding: The modeler's perspective.
Neuron 1999;24:95–104. https://doi.org/10.1016/S0896-6273(00)80825-9.

[7]   Bressler SL. Interareal synchronization in the visual cortex. Behavioural Brain
Research 1996;76:37–49. https://doi.org/10.1016/0166-4328(95)00187-5.

[8] Varela F, Lachaux JP, Rodriguez E, Martinerie J. The brainweb: Phase
synchronization and large-scale integration. Nature Reviews Neuroscience
2001;2:229–39. https://doi.org/10.1038/35067550.

[9] Vanrullen R, MacDonald JSP. Perceptual echoes at 10 Hz in the human brain.
Current Biology 2012;22:995–9. https://doi.org/10.1016/j.cub.2012.03.050.

[10] Tiesinga P, Sejnowski TJ. Cortical Enlightenment: Are Attentional Gamma
Oscillations Driven by ING or PING? Neuron 2009;63:727–32.
https://doi.org/10.1016/j.neuron.2009.09.009.

[11] Wang XJ, Buzsáki G. Gamma oscillation by synaptic inhibition in a hippocampal
interneuronal network model. Journal of Neuroscience 1996;16:6402–13.
https://doi.org/10.1523/jneurosci.16-20-06402.1996.

[12] Whittington MA, Traub RD, Kopell N, Ermentrout B, Buhl EH. Inhibition-based
rhythms: Experimental and mathematical observations on network dynamics.
International Journal of Psychophysiology, vol. 38, Int J Psychophysiol; 2000, p. 315–
36. https://doi.org/10.1016/S0167-8760(00)00173-2.

[13] Traub R, Whittington M. Cortical Oscillations in Health and Disease. Oxford
University Press; 2010. https://doi.org/10.1093/acprof:oso/9780195342796.001.0001.

[14] van Vreeswijk C, Abbott LF, Bard Ermentrout G. When inhibition not excitation
synchronizes neural firing. Journal of Computational Neuroscience 1994;1:313–21.
https://doi.org/10.1007/BF00961879.

[15] Gerstner W, van Hemmen JL, Cowan JD. What Matters in Neuronal Locking?
Neural Computation 1996;8:1653–76. https://doi.org/10.1162/neco.1996.8.8.1653.

[16] Whittington MA, Traub RD, Jefferys JGR. Synchronized oscillations in interneuron
networks driven by metabotropic glutamate receptor activation. Nature 1995;373:612–
5. https://doi.org/10.1038/373612a0.

[17] Cardin JA, Carlén M, Meletis K, Knoblich U, Zhang F, Deisseroth K, et al. Driving
fast-spiking cells induces gamma rhythm and controls sensory responses. Nature
2009;459:663–7. https://doi.org/10.1038/nature08002.

[18] Tiesinga PHE. Motifs in health and disease: The promise of circuit interrogation by
optogenetics. European Journal of Neuroscience 2012;36:2260–72.
https://doi.org/10.1111/j.1460-9568.2012.08186.x.

[19] Adesnik H, Scanziani M. Lateral competition for cortical space by layer-specific
horizontal circuits. Nature 2010;464:1155–60. https://doi.org/10.1038/nature08935.

[20] Lozano-Soldevilla D, ter Huurne N, Cools R, Jensen O. GABAergic modulation of
visual gamma and alpha oscillations and its consequences for working memory
performance. Current Biology 2014;24:2878–87.
https://doi.org/10.1016/j.cub.2014.10.017.

[21] Muthukumaraswamy SD, Edden RAE, Jones DK, Swettenham JB, Singh KD.
Resting GABA concentration predicts peak gamma frequency and fMRI amplitude in
response to visual stimulation in humans. Proceedings of the National Academy of
Sciences of the United States of America 2009;106:8356–61.
https://doi.org/10.1073/pnas.0900728106.

681 [22] Gaetz W, Edgar JC, Wang DJ, Roberts TPL. Relating MEG measured motor cortical
682    oscillations to resting γ-Aminobutyric acid (GABA) concentration. NeuroImage
683    2011;55:616–21. https://doi.org/10.1016/j.neuroimage.2010.12.077.

684 [23] Edden RAE, Muthukumaraswamy SD, Freeman TCA, Singh KD. Orientation
685    discrimination performance is predicted by GABA concentration and gamma
686    oscillation frequency in human primary visual cortex. Journal of Neuroscience
687    2009;29:15721–6. https://doi.org/10.1523/JNEUROSCI.4426-09.2009.

688 [24] Cousijn H, Haegens S, Wallis G, Near J, Stokes MG, Harrison PJ, et al. Resting
689    GABA and glutamate concentrations do not predict visual gamma frequency or
690    amplitude. Proceedings of the National Academy of Sciences of the United States of
691    America 2014;111:9301–6. https://doi.org/10.1073/pnas.1321072111.

692 [25] Kujala J, Jung J, Bouvard S, Lecaignard F, Lothe A, Bouet R, et al. Gamma
693    oscillations in V1 are correlated with GABAA receptor density: A multi-modal MEG
694    and Flumazenil-PET study. Scientific Reports 2015;5:16347.
695    https://doi.org/10.1038/srep16347.

696 [26] Lee S, Jones SR. Distinguishing mechanisms of gamma frequency oscillations in
697    human current source signals using a computational model of a laminar neocortical
698    network. Frontiers in Human Neuroscience 2013;7.
699    https://doi.org/10.3389/fnhum.2013.00869.

700 [27] Börgers C, Kopell N. Synchronization in networks of excitatory and inhibitory
701    neurons with sparse, random connectivity. Neural Computation 2003;15:509–38.
702    https://doi.org/10.1162/089976603321192059.

703 [28] Börgers C, Epstein S, Kopell NJ. Background gamma rhythmicity and attention in
704    cortical local circuits: A computational study. Proceedings of the National Academy of
705    Sciences of the United States of America 2005;102:7002–7.
706    https://doi.org/10.1073/pnas.0502366102.

707 [29] Izhikevich EM. Simple model of spiking neurons. IEEE Transactions on Neural
708    Networks 2003;14:1569–72. https://doi.org/10.1109/TNN.2003.820440.

709 [30] Ainsworth M, Lee S, Cunningham MO, Roopun AK, Traub RD, Kopell NJ, et al. Dual
710    gamma rhythm generators control interlaminar synchrony in auditory cortex. Journal
711    of Neuroscience 2011;31:17040–51. https://doi.org/10.1523/JNEUROSCI.2209-
712    11.2011.

713 [31] Quax S, Jensen O, Tiesinga P. Top-down control of cortical gamma-band
714    communication via pulvinar induced phase shifts in the alpha rhythm. PLoS
715    Computational Biology 2017;13. https://doi.org/10.1371/journal.pcbi.1005519.

716 [32] Brette R, Gerstner W. Adaptive exponential integrate-and-fire model as an effective
717    description of neuronal activity. Journal of Neurophysiology 2005;94:3637–42.
718    https://doi.org/10.1152/jn.00686.2005.

719 [33] Wacongne C, Changeux JP, Dehaene S. A neuronal model of predictive coding
720    accounting for the mismatch negativity. Journal of Neuroscience 2012;32:3665–78.
721    https://doi.org/10.1523/JNEUROSCI.5003-11.2012.

722 [34] Kleiner M, Brainard D, Pelli D, Ingling A, Murray R, Broussard C. What's new in
723    psychtoolbox-3. vol. 36. [Pion Ltd.]; 2007.

[35] Zhigalov A, Jensen O. Alpha oscillations do not implement gain control in early
visual cortex but rather gating in parieto-occipital regions. Human Brain Mapping
2020;41:5176–86. https://doi.org/10.1002/hbm.25183.

[36] Virtanen P, Gommers R, Oliphant TE, Haberland M, Reddy T, Cournapeau D, et al.
SciPy 1.0: fundamental algorithms for scientific computing in Python. Nature Methods
2020;17:261–72. https://doi.org/10.1038/s41592-019-0686-2.

[37] Crosse MJ, di Liberto GM, Bednar A, Lalor EC. The multivariate temporal response
function (mTRF) toolbox: A MATLAB toolbox for relating neural signals to continuous
stimuli. Frontiers in Human Neuroscience 2016;10:604.
https://doi.org/10.3389/fnhum.2016.00604.

[38] Taulu S, Simola J. Spatiotemporal signal space separation method for rejecting
nearby interference in MEG measurements. Physics in Medicine and Biology
2006;51:1759–68. https://doi.org/10.1088/0031-9155/51/7/008.

[39] Oostenveld R, Fries P, Maris E, Schoffelen J-M. FieldTrip: Open source software for
advanced analysis of MEG, EEG, and invasive electrophysiological data.
Computational Intelligence and Neuroscience 2011;2011:156869.
https://doi.org/10.1155/2011/156869.

[40] Nolte G. The magnetic lead field theorem in the quasi-static approximation and its
use for magnetoenchephalography forward calculation in realistic volume conductors.
Physics in Medicine and Biology 2003;48:3637–52. https://doi.org/10.1088/0031-
9155/48/22/002.

[41] Gross J, Kujala J, Hamalainen M, Timmermann L, Schnitzler A, Salmelin R.
Dynamic imaging of coherent sources: Studying neural interactions in the human
brain. Proceedings of the National Academy of Sciences of the United States of
America 2001;98:694–9. https://doi.org/10.1073/pnas.98.2.694.

[42] van Veen BD, van Drongelen W, Yuchtman M, Suzuki A. Localization of brain
electrical activity via linearly constrained minimum variance spatial filtering. IEEE
Transactions on Biomedical Engineering 1997;44:867–80.
https://doi.org/10.1109/10.623056.

[43] Binzegger T, Douglas RJ, Martin KAC. A quantitative map of the circuit of cat
primary visual cortex. Journal of Neuroscience 2004;24:8441–53.
https://doi.org/10.1523/JNEUROSCI.1400-04.2004.

[44] Hämäläinen M, Hari R, Ilmoniemi RJ, Knuutila J, Lounasmaa O v.
Magnetoencephalography theory, instrumentation, and applications to noninvasive
studies of the working human brain. Reviews of Modern Physics 1993;65:413–97.
https://doi.org/10.1103/RevModPhys.65.413.

[45] Gramfort A, Luessi M, Larson E, Engemann DA, Strohmeier D, Brodbeck C, et al.
MEG and EEG data analysis with MNE-Python. Frontiers in Neuroscience 2013;7.
https://doi.org/10.3389/fnins.2013.00267.

[46] Gulbinaite R, Roozendaal DHM, VanRullen R. Attention differentially modulates the
amplitude of resonance frequencies in the visual cortex. NeuroImage
2019;203:116146. https://doi.org/10.1016/j.neuroimage.2019.116146.

[47]   Alamia A, VanRullen R. Alpha oscillations and traveling waves: Signatures of
767   predictive coding? PLoS Biology 2019;17.
768   https://doi.org/10.1371/journal.pbio.3000487.

769   [48]   Bastos AM, Lundqvist M, Waite AS, Kopell N, Miller EK. Layer and rhythm specificity
770   for predictive routing. Proceedings of the National Academy of Sciences
771   2020;117:202014868. https://doi.org/10.1073/pnas.2014868117.

772   [49]   Bastos AM, Usrey WM, Adams RA, Mangun GR, Fries P, Friston KJ. Canonical
773   Microcircuits for Predictive Coding. Neuron 2012;76:695–711.
774   https://doi.org/10.1016/j.neuron.2012.10.038.

775   [50]   Jia J, Liu L, Fang F, Luo H. Sequential sampling of visual objects during sustained
776   attention. PLoS Biology 2017;15. https://doi.org/10.1371/journal.pbio.2001903.

777   [51]   Swettenham JB, Muthukumaraswamy SD, Singh KD. Spectral properties of induced
778   and evoked gamma oscillations in human early visual cortex to moving and stationary
779   stimuli. Journal of Neurophysiology 2009;102:1241–53.
780   https://doi.org/10.1152/jn.91044.2008.

781   [52]   Muthukumaraswamy SD, Singh KD. Visual gamma oscillations: The effects of
782   stimulus type, visual field coverage and stimulus motion on MEG and EEG
783   recordings. NeuroImage 2013;69:223–30.
784   https://doi.org/10.1016/j.neuroimage.2012.12.038.

785   [53]   van Pelt S, Fries P. Visual stimulus eccentricity affects human gamma peak
786   frequency. NeuroImage 2013;78:439–47.
787   https://doi.org/10.1016/j.neuroimage.2013.04.040.

788   [54]   Hoogenboom N, Schoffelen JM, Oostenveld R, Parkes LM, Fries P. Localizing
789   human visual gamma-band activity in frequency, time and space. NeuroImage
790   2006;29:764–73. https://doi.org/10.1016/j.neuroimage.2005.08.043.

791   [55]   Jensen O, Hari R, Kaila K. Visually evoked gamma responses in the human brain
792   are enhanced during voluntary hyperventilation. NeuroImage 2002;15:575–86.
793   https://doi.org/10.1006/nimg.2001.1013.

794   [56]   David O, Kilner JM, Friston KJ. Mechanisms of evoked and induced responses in
795   MEG/EEG. NeuroImage 2006;31:1580–91.
796   https://doi.org/10.1016/j.neuroimage.2006.02.034.

Supporting information

Fig. S1. Suppression of line noise in data does not change the characteristics of the gamma
echo in representative magnetometers. Each panel shows the power spectral density (PSD)
and TRF for individual participants before (blue line) and after (orange line) applying the SSS
method to suppress 50 Hz line noise. The echoes remain strong after the 50 Hz line noise is
suppressed.