Numerical Simulation of Concussive-generated Cortical Spreading Depolarization to
Optimize DC-EEG Electrode Spacing for Non-invasive Visual Detection

Samuel J. Hund, PhD [1,2]
Benjamin R. Brown, PhD [1]
Coline L. Lemale, MSc [3,4]
Prahlad G. Menon, PhD [1,5]
Kirk A. Easley, MS, MApStat [6]
Jens P. Dreier, MD [3,4,7,8,9]
Stephen C. Jones, PhD [1*]
10

[1] CerebroScope, the dba entity of SciencePlusPlease LLC, 1936 Fifth Avenue, Pittsburgh, PA
15219-5544, USA
[2] SimulationSolutions, LLC, 5707 Jackson St., Pittsburgh, PA, 15206, USA
[3] Center for Stroke Research, Charité – Universitätsmedizin Berlin, corporate member of Freie
Universität Berlin, Humboldt-Universität zu Berlin, and Berlin Institute of Health, Berlin,
Germany
[4] Department of Experimental Neurology, Charité – Universitätsmedizin Berlin, corporate
member of Freie Universität Berlin, Humboldt-Universität zu Berlin, and Berlin Institute of
Health, Berlin, Germany
[5] Previous address:
Electrical & Computer Engineering, SYSU-CMU Joint Institute of Engineering, Sun Yat-sen
University - Carnegie Mellon University (SYSU-CMU), 5000 Forbes Ave., Pittsburgh, PA,
15213, USA
Current address:
Department of Bioengineering, University of Pittsburgh, 302 Benedum Hall, Ohara St.,
Pittsburgh, PA, 15213, USA
[6] Department of Biostatistics and Bioinformatics, Rollins School of Public Health, Emory
University, 1518 Clifton Road NE, Atlanta, GA, 30322, USA
[7] Department of Neurology, Charité – Universitätsmedizin Berlin, corporate member of Freie
Universität Berlin, Humboldt-Universität zu Berlin, and Berlin Institute of Health, Berlin,
Germany
[8] Bernstein Center for Computational Neuroscience Berlin, Berlin, Germany
[9] Einstein Center for Neurosciences Berlin, Berlin, Germany
34

Word count: 7480 words
Number of Figures: 6 (plus one supplemental movie and one supplemental figure)
Number of Tables: 2

* Correspondence:
Stephen C. Jones
CerebroScope, the dba entity of SciencePlusPlease LLC
1936 Fifth Avenue
Pittsburgh, PA 15219-5544, USA
ph: 412-208-3397
sjones@cerebro-scope.com

1 Abstract

Background: Cortical Spreading Depolarization (SD) is a propagating depolarization wave of

neurons and glial cells in the cerebral gray matter. SD occurs in all forms of severe acute brain

injury as documented using invasive detection methods. Based on many experimental studies of

mechanical brain deformation and concussion, the occurrence of SDs in human concussion has

often been hypothesized. However, this hypothesis cannot be confirmed in humans as SDs can

only be detected with invasive detection methods that would require either a craniotomy or a

burr hole to be performed on athletes. Typical electroencephalography (EEG) electrodes, placed

on the scalp, can detect the possible presence of SD but have not been able to accurately and

reliably identify SDs.

Methods: To explore the possibility of a non-invasive method to resolve this hurdle, we

developed a finite element numerical model that simulates scalp voltage changes that are induced

by a brain-surface SD. We then compared our simulation results with retrospectively evaluated

data in aneurysmal subarachnoid hemorrhage (aSAH) patients from Drenckhahn et al. (Brain

135:853, 2012).

Results: The ratio of peak scalp to simulated peak cortical voltage, Vscalp/Vcortex, was 0.0735,

whereas the ratio from the retrospectively evaluated data was 0.0316 (0.0221, 0.0527) [median

(1st quartile, 3rd quartile), n = 161, p < 0.001, one sample Wilcoxon signed rank test]. These

differing values provide validation because their differences can be attributed to differences in

shape between concussive- and aSAH-SDs, as well as the inherent limitations in human study

voltage measurements. This simulated scalp surface potential was used to design a virtual scalp

detection array. Error analysis and visual reconstruction showed that 1 cm is the optimal

electrode spacing to visually identify the propagating scalp voltage from a cortical SD. Electrode

spacings of 2 cm and above produce distorted images and high errors in the reconstructed image.

Conclusion: Our analysis suggests that concussive (and other) SDs can be detected from the

scalp, which could confirm SD occurrence in human concussion, provide concussion diagnosis

based on an underlying physiological mechanism, and lead to non-invasive SD detection in the

setting of severe acute brain injury.

Keywords: full-band EEG; DC-EEG; Cortical Spreading Depolarization; Brain Concussion;

Mild   Traumatic   Brain   Injury;   Finite   Element   Analysis;   Numerical   Simulation;

Electroencephalography; Electrocorticography

1   Introduction

Concussion, also known as mild traumatic brain injury (not to be confused with severe traumatic brain injury), affects 1.6-3.8 million individuals per year in the United States [1-3], and the actual number is likely higher because of underreporting and misdiagnosis [4]. In particular, sports concussion has garnered major public attention in recent years [5-9]. Concussions during military [10-12], automotive, occupational, and bicycle accidents have increasingly added to the public consciousness. Diagnosis of concussion depends on highly variable and often non-specific symptoms that include physical, cognitive, behavioral, emotional, and sleep-related aspects [13]. Immediate diagnostic methods rely on psychometric, reaction time, and balance assessments, but the accuracy, reliability, and repeatability of these assessments have come into question [14-21]. Health professionals typically test for potential sports-related concussions during the acute phase using the Sport Concussion Assessment Tool 5th Edition, SCAT 5, [22], which includes many of the aforementioned components. The assessment of acute concussion to prevent serious consequences of inappropriate return-to-play decisions [23, 24] is a well-established process that is based on multiple symptoms but without an underlying pathophysiological mechanism.

The historical [25] and emerging experimental [26, 27] evidence that concussion is accompanied by cortical Spreading Depolarization (SD) suggest that SD might be the underlying cause of, or at the least contribute to, acute concussion symptomatology in the immediate minutes after concussion. Currently, diffuse axonal injury (DAI) is the most widely accepted anatomical mechanism accounting for the acute and chronic symptoms of concussion. DAI has been proposed as an objective diagnostic criteria based on axonal pathophysiology assessed by MRI and the increased blood concentration of axonal proteins [28]. However, the effects of DAI and SD are separated both by where they occur anatomically, with DAI affecting axons and SD

occurring in neurons and glia, and the timing of their effects. Concussion is thought to induce a

brain network dysfunction, in which white matter damage and DAI are implicated in

characteristic symptoms such as slowed information processing at one day [29] and five years

[30] post-concussion, time periods which are not relevant to the immediate occurrence of SD

following concussion.

1.1   What are SDs?

SDs are regions (typically 3 mm width or diameter [31, 32]) of large amplitude direct-current

(DC, 5 - 30 mV) negative *en mass* depolarization of neuronal and glial cells in gray matter that

persist over several minutes [33-37]. The hallmark of SD is the near-complete breakdown of the

neuronal transmembrane ion gradients [38] that leads to influx of water and cytotoxic edema

[39]. Secondarily, glutamate is released in large amounts [40]. SDs are slow-moving waves (1 - 9

mm/min) that lead to depression of electroencephalographic (EEG) amplitudes for 0.5 - 3

minutes, with normal function grossly restored after 5 - 10 minutes if the vasculature is not

compromised [31, 41, 42]. Although SDs were originally discovered in rabbits in the 1940s [31],

it was not until the 1990s that they were initially observed in a single severe acute brain trauma

patient [43]. In the early 2000s, Strong and colleagues presented the first robust bedside method

that used subdural electrodes to detect SDs in approximately 50% of individuals with traumatic

brain injury [36].

SDs occur abundantly, periodically, and repetitively in severe acute brain injury,

including malignant hemispheric stroke, subarachnoid hemorrhage (SAH), spontaneous

intracerebral hemorrhage, and severe traumatic brain injury [41, 44-49]. The transition from

long-lasting SDs in severely ischemic tissue to short-lasting SDs in less ischemic or normal

tissue has been described as "the SD continuum" [50, 51]. Terminal SDs during the development

of stroke, brain death and death from circulatory arrest represent the extreme end of the SD

continuum [34, 52-58]. In addition, short-lasting SD in otherwise healthy tissue is assumed to be

the underlying cause of migraine aura [35, 59, 60], which is the only clinical manifestation of SD

in which the wave-like nature of SD becomes clinically apparent, leading to the fallacy for many

decades that migraine aura is the only clinical manifestation of SD [50]. In the first phase of

ischemic strokes due to arterial occlusion, and most likely in concussion, the SD spreads

concentrically from the ischemic core [61] or the point of impact [31]. The consequences of SD

occurrence in both migraine and concussion, if it does occur in human concussion, are

temporary, in stark contrast to the "continuum" pathological role of SD in severe acute brain

injury [50].

1.2   Rationale for SD Occurring in Concussion

SD and concussion were first linked by observation that a firm, non-damaging touch of the brain

elucidated an SD [31]. This initial observation of brain deformation causing SD was the basis for

extensive studies using controlled brain deformation [62-64]. These studies of brain deformation

were not focused on human concussion but rather the mechanical parameters of brain

deformation, including the speed, area, and depth of the depression that elicited SD. The direct

link between concussion and SD was suggested based on a comparison of the energies required

to elicit SD and experimental concussion [65]. This comparison is weakened by concern that: 1)

the calculation of energies was not described or referenced; 2) only experimental, non-human

studies provided evidence; and 3) the rate of deformation, a parameter that determines SD

initiation, was not used. These concerns make the presumption that human concussion is always

accompanied by SD a hypothesis that needs testing.

Many experimental studies have noted the similar features of concussion and SD,

including high metabolic rate [66] and high $[K^+]_o$ [67]. In particular, EEG suppression [68-70]

and negative DC-potential [70] in experimental models of concussion were consistent with the

original observations of EEG suppression [31] and negative DC-potential during SD [37].

Studies demonstrating the presence of SD in mouse models of concussion strongly

suggest that SD might be a common feature of concussion [26, 27]. The behavioral effects

associated with SD after controlled cortical impact without craniotomy are similar to the diverse

symptoms used to diagnose human concussion [26]. All of these experimental studies used

models of concussion that excluded cerebral contusion or intra-cranial hematomas.

Several clinical studies [71, 72] and reviews [73-75] have presented compelling

arguments suggesting that SD could explain concussion symptomatology. In particular, Oka et

al. [71] reported that patients with non-convulsive concussion-like injury showed symptoms of

"headache, nausea and vomiting, pale complexion, somnolence, irritability or restless confusion"

that are "also characteristic symptoms of classical migraine attacks." Although this experimental

and clinical evidence that a blow to the cranium could trigger SD is scientifically valid, the

mechanism of SD initiation by brain deformation has not been explored and the

electrophysiological confirmation of this scenario in humans [25; page 1083] is missing.

1.3   Mechanisms of Mechanical Brain Deformation Induced SD

Although the mechanisms of SD initiation and propagation have been extensively explored [25,

76], there has been no attention devoted to the mechanism of SD elicited by brain deformation.

Strangely, brain deformation has been ascribed to many modes of eliciting SD, as thoroughly

described by Marshall [77], including pinprick, pledget application of compounds that elicit SD

to the cortical surface, neurosurgical procedures that involve brain deformation or compression,

and others. However, many studies have been performed using *in vitro* models of neuronal

stretch that show both permeability and ion channel changes [78, 79] whose time scale is

relevant to concussive SD initiation. In this same time scale, there is evidence that cells do

partially depolarize after stretch due to permeability increases [80, 81]. These issues could be

explored for their connection to the mechanism of SD generation by brain deformation. A recent

study suggests spontaneous SDs in an "intracortical hemorrhage model are triggered by the

mechanical distortion of tissue by rapidly growing hematomas" [82].

To explore the possibility of non-invasive detection methods that might resolve the

conundrum between the scientific evidence for, and missing confirmation of, SD in human

concussion, we performed a numerical simulation to model the spatial and temporal

characteristics, as well as the magnitude, of the scalp DC-voltage from an assumed brain-surface

concussive SD. We then compared the computational model with retrospectively evaluated

human results from aneurysmal SAH (aSAH) patients, given that human concussion data are not

available. Finally, we used this simulated scalp DC-potential to investigate the ideal spatial

separation of the electrodes in a sensor array for scalp DC-EEG detection of SD.

Our hypotheses are that our simulated scalp DC-potential: 1) compares with existing

experimental data; 2) can be used to determine the electrode configuration, specifically the

electrode spacing, that enables, and is sufficient for, the accurate reconstruction of a scalp DC

potential image that aids in the visual detection of SD; and 3) is consistent with the detection

limits of DC-EEG. The implications of these hypotheses are that if propagating SDs can be

noninvasively detected, concussion detection using SD is possible, the role of SD in concussion

could be explored, and noninvasive SD detection in severe acute brain injury patients might be

possible.

2   Methods

2.1   DC-EEG Forward Problem using a Finite Element Model

Various authors have conducted numerical simulations of EEG phenomena in the brain and head

directed both at the forward problem [83] and inverse source localization of the focus of epileptic

seizures [84, 85] and of regions of suppressed neural activity [86]. Most models focused on the

number of tissue layers and geometry [83, 84, 87-90] but others have been concerned with

material properties and constitutive equations [91-93]. However, all these models used clinical

EEG frequencies greater than 0.5 Hz, except for the inverse source localization effort by Miller

et al. [85] which used frequencies of 0 to 70 Hz in contrast to the clinical frequency range. Our

forward problem simulation is unique as it deals with the near-zero frequencies of an SD that can

be modeled with just a brain-surface DC-potential without any underlying cortical structure and

depends on DC-EEG, not the normal clinical EEG frequencies above 0.5 Hz.

2.1.1 SD modeled as a brain surface voltage field

To implement our simulation, we first mathematically describe the SD voltage waveform. The

cortex was not modeled as the SD can be described as an electric field on the cortical surface.

The SD voltage waveform on the brain-surface is instead implemented into the model with the

boundary condition:

$$V_{cortex} = \Delta V_{SD}\chi(r,t),$$ [1]

where ΔV_{SD} is the cortical surface voltage potential of SD (-20 mV) and χ is a shape function

describing the spatio-temporal behavior of the spreading, namely an expanding ring with a

thickness or width of 3 mm [31, 32] and a velocity of 3 mm/min appearing within 1 min after

impact [26, 27].

Two different shape functions were used to describe the SD, whose initial inner radius is

zero at the concussive focus. The first shape function is a square wave:

$$\chi(r,t) = \begin{cases} 1 & r_{inner} \leq r \leq r_{outer} \\ 0 & \text{elsewhere} \end{cases},$$ [2]

where r is the distance from the focus of the concussion. The radius of the ring expands outward

as:

$$r(t) = \frac{W}{2} + v_{CSD}t,$$ [3]

where W is the constant ring thickness of the wave (3 mm), and v_{SD} is the propagation speed of

the SD (3 mm/min). The inner (trailing) edge of the ring, r_{inner}, and outer (leading) edge of the

ring, r_{outer}, are then

$$r_{inner} = r(t) - \frac{W}{2}, \text{ and}$$ [4]

$$r_{outer} = r(t) + \frac{W}{2}.$$ [5]

The second shape function is a triangular wave:

$$\chi(r,t) = \begin{cases} \dfrac{r - r_{inner}}{r(t) - r_{inner}} & r_{inner} \leq r \leq r(t) \\ \dfrac{r_{outer} - r}{r_{outer} - r(t)} & r(t) < r \leq r_{outer} \\ 0 & \text{elsewhere} \end{cases},$$ [6]

where r(t) is the radius of the expanding ring, and r_{inner} and r_{outer} are again the inner and outer

radii of the ring. These two shapes bracket the largest and smallest transmission of signal to the

scalp (or most optimistic and least optimistic signal estimates), including the more typical shape

1   observed using ECoG methods and the shape of an SD DC shift in an experimental model of

2   concussion [26], for a given SD voltage, ΔV_{SD}, and width, W. These boundary conditions

3   (Equations 1-6) define the spatial extent of the modeled SD that are needed to determine the

4   solutions to Equation 7 below.

5   ***2.1.2 Layers between the brain surface and scalp through which the SD electric field***

6   ***must pass***

Our next step was to model the layers between the brain surface and the scalp through which

these brain surface voltage fields must travel to reach the scalp. A five-layer model was used for

this project, focusing on 1) cerebrospinal fluid (CSF); 2) dura matter; 3) skull; 4) muscle; and 5)

skin (see Fig. 1b). Ramon et al. [84] showed that the CSF was the major factor in a quality

model. Muscle was included to account for the portions of the frontal bellies of the

occipitofrontalis muscle that attach to the *galea aponeurotica* [94]. Although the muscle layer is

thin, it was included for completeness and adds to the truthfulness of the model. The total

thickness is 1.02 cm and the thickness of each layer can be found in Table 1. The values for layer

thickness, relative permittivity (dielectric constant), and conductance, as presented in Table 1,

were obtained from various literature sources [83, 84, 93, 95, 96]. The frontal bone of the skull

was chosen as the reference because this is the area where athletic concussions are most likely to

occur, and it is also the thickest part of the skull on average, resulting in the greatest attenuation

of the signal [97]. Furthermore, the results will be compared to clinical research data collected by

Drenckhahn et al. [34] for SDs occurring primarily in the frontal cortex of aSAH patients (see

below for details). Instead of relying on a multilayer model of the skull, i.e., hard and soft bone

[83, 98-100], the theory of interacting continua was used to determine the parameters through

mixture theory [101].

2.1.3 Calculation of the SD electric field propagating from the brain surface to the

scalp

Our further step was to calculate the propagation of the electric field through these layers from

the brain surface to the scalp using Poisson's equation:

5
$$-\nabla \bullet \left[\left(\sigma + \varepsilon_o \varepsilon_r \frac{\partial}{\partial t} \right) \nabla V \right] = Q,$$
[7]

where t is time, σ is the conductivity, ε_o is the permittivity in a vacuum, ε_r is the relative

permittivity, V is voltage potential, and Q is a source term. The boundary condition at the scalp

was zero normal current density or Q = 0. No other current sources (Q) were used; however, Q

could be used to produce noise and additional signal generation such as that of the transdermal

epithelial potential (TEP) or the galvanic skin potential. The model ignores the TEP, i.e.,

assumes the skin is abraded [102, 103]. In more detail, Poisson's equation relates the

contributions from the voltage field on the cortical surface, V_{cortex}, defined by the boundary

condition (Equation 1) and its associated shape functions (Equations 2 and 6), as it propagates

through the various layers from the brain surface to the scalp. The calculation was implemented

using finite element modeling, a method that creates a mesh of cells between which these

equations are solved numerically. These equations of electrodynamic theory and their use in

finite element modeling are inherent in computational neuroscience tools such as FieldTrip [104,

105] that are used to study the forward and inverse problems. These tools are focused on clinical

EEG frequencies in contrast to our focus on SDs DC potential.

2.2   Simulation Details and Parameters

The simulation was performed on a cylindrical domain with a radius of 10 cm (see Fig. 1a and

1c). This radius was chosen to be large to prevent interference effects of the boundary condition.

Due to the slow propagation velocity of SDs, the total time simulated was 15 minutes as a pilot

study showed little change in the basic structure of the propagation after this time. The

simulation was performed using COMSOL 4.3 (COMSOL, Inc.) with a structured hexagonal

mesh, which uses an adaptive time solver with a relative error below 1e-6. The spatial resolution

of the mesh was evaluated using the grid convergence index (GCI) method, which is the

American Society of Mechanical Engineers standard [106]. The mesh element sizes were 0.886,

0.481, and 0.246 mm for the coarse, medium, and fine meshes, respectively. The coarse mesh

had some elements with GCI qualities as low as 0.4 (<10% of elements) and the fine mesh

elements all had quality values above 0.95; all elements had GCI qualities above the level of

concern (0.1). Furthermore, the simulation was validated against an analytical solution for a

constant voltage drop of 20 mV applied between the scalp and the cortex. The layer resistances,

R, can be calculated as:

$$R = \frac{h}{A\sigma},$$ [8]

where h is the thickness and A the cross-sectional area of the layer. The current and voltage drop

can then be calculated from Ohm's law. The resulting errors were less than 3e-7 mA and

1e-5 mV for current and voltage, respectively, between the closed-form solution and the

numerical results.

The shape of the potential of the SD as it propagates through the various layers was

characterized through a relative voltage, V_{rel}:

$$V_{rel} = \frac{V_i}{\min(V_i)},$$ [9]

which compares the voltage of the i^{th} layer, V_i, to the minimum voltage on that layer occurring

between the time of 5 and 15 minutes, $\min(V_i)$. A value of 0.2 was set for the threshold of V_{rel} in

order to determine the thickness or width of the SD-based DC-potential and to tag times for

analyzing sensor data.

2.3   Scalp Potential Image Reconstruction, Simulated Scalp Detector Construction, and Reconstruction Error

This simulation/modeling process of an SD's DC electric field on the brain surface that

transverses the various tissue layers from the brain to the scalp results in an estimate of the

electric field on the scalp. This electric field is then "sampled" by an array of electrode sensors at

various spacings. The final step is then the reconstruction of the scalp electric field from this

electrode data so that the scalp electric field can be presented as a heat-map image. The errors

between the known scalp electric field and its reconstruction from the electrode sensors can then

be evaluated. Errors in velocity were determined in a subsequent study using the scalp electric

field calculated as a results of the simulation, but with a limited electrode array.

The scalp surface signal over a 10 cm x 10 cm square (Figure 1a) was reconstructed from

simulated electrode readings by sampling the predicted voltages at various electrode spacings.

The simulated SD was centered at 2.5 cm from the left of the center of the sensor array as shown

in Figure 1d. The relative location of the sensor grid to the simulation or sensor domain and focal

point of the SD can be seen in Figure 1a. Figure 1d shows a sample grid with 1-cm spacing.

Reconstruction of the scalp electric field was performed with bilinear interpolation between four

electrodes [107]. The root-mean-squared error (or the L2 norm),

20
$$\left\| V_n(x,y) - V_{0.5}(x,y) \right\|_{L2} = \int_\Omega \left(V_n(x,y) - V_{0.5}(x,y) \right)^2 d\Omega, \qquad [10]$$

where Ω is the domain, was used to compare the error between the voltage reconstruction at 0.5-

mm electrode spacing ($V_{0.5}$) and the other arrays with electrode spacing of 1, 5, 10, 15, 20, 25,

30, 40, and 50 mm (V_n). The reconstruction was also performed by averaging the voltage

potential over circular areas (0.5, 0.75, 1, 1.5, 2, 2.5, 3, 4, and 5 mm radii) representing various

sizes of the active area of the electrode. Results were compared with the infinitesimal or point

values of voltage.

2.4   Errors in Velocity and Ring Thickness Evaluated using Detection Array

Offsets

A second study, independent of the regular grid study above, was performed to understand how

different offsets (see Fig. 1e) influenced SD velocity calculations from the simulated scalp data.

To simplify this error analysis, a subset of the full electrode array was used composed of a linear

electrode array. Errors in the velocity of the SD will occur if a linear sensor array is not aligned

with the velocity field, which occurs for a concentrically expanding wave when the sensors are

offset from a given radius. Therefore, velocity and ring thickness calculations were performed

for a 1 x 7 array of electrodes with the sensor array situated so that the first electrode is located

over the focus of the SD, and then with 3 additional linear 2 x 7 arrays that were separated by

0.1, 0.5, and 1 cm. All arrays had an electrode spacing of 0.5 cm and length of 3 cm (see Fig.

1e). An apparent velocity, v_{app}, was calculated using the formula:

$$v_{app} = \frac{D_{sensor}}{t_{i+1} - t_i},$$ [11]

where D_{sensor} is the spacing between two electrodes and t_i is the time at which V_{rel} of the i^{th}

electrode either first exceeds (onset) or is first restored below the threshold of 0.2 (abatement).

Velocities were calculated using each electrode pair (i and i+1), with the first pair consisting of

the two electrodes closest to the focus and so forth. A scalp depolarization time (t_d), where the

threshold value was exceeded, was defined to be the time between onset and abatement. The

scalp ring thickness (W_s) was calculated using the equation:

$$W_s = \frac{t_d}{v_{app}} \, .$$ [12]

For this second study, the scalp DC potential of a brain surface expanding ring SD was simulated

with a velocity of 3 mm/min, a ring thickness of 30.8 mm, and a depolarization time of 10.3

minutes, values derived from the FEM simulation and the time needed to transverse the length of

the simulated linear electrode array.

2.5   Retrospective Evaluation of Human Data [34]

We retrospectively evaluated the amplitude of SDs in three aSAH patients with sufficient quality

subdural full-band ECoG (fbECoG) and scalp full-band EEG (fbEEG) recordings from

Drenckhahn et al. [34]. Patient recruitment and characteristics, fbEEG and fbECoG recording,

data processing and analysis are detailed in Drenckhahn et al. [34]. Research protocols were

approved by the institutional review board and surrogate informed consent was obtained for all

patients. All research was conducted in accordance with the Declaration of Helsinki.

In brief, a single, linear, six-contact (platinum) recording strip (Wyler, 5 mm diameter;

Ad-Tech Medical) was placed on the surface of the cortex for ECoG recordings [36, 44, 45].

Both fbECoG and fbEEG recordings were performed (bandpass: 0–1000 Hz, sampling rate: 2500

Hz) using a BrainAmp amplifier. The electrodes were attached with Collodion adhesive

(Mavidon) after abrasive electrode gel (Abralyt 2000, EasyCap) and conductive electrode cream

(Synapse, Med-Tek) were applied to minimize electrode impedance (<5 kV) and ensure long-

term stability of the signal. Data were recorded and reviewed with the use of LabChart 7

software (ADInstruments) and BrainVision Recorder 1.05 software (Brain Products),

respectively. For each pair of subdural fbECoG and scalp fbEEG recordings from the same SD,

the maximum voltage of each was recorded. The ratio of these subdural and scalp voltages was

compared with the ratio determined from our simulation.

2.6   Statistics

Statistical tests were performed using SAS/STAT version 15.1 (SAS institute Inc, Cary, NC). A

nonparametric statistical test was used because the voltage ratio measurements deviated

significantly from a normal distribution. The one sample Wilcoxon signed rank test was used to

compare our simulation derived voltage ratio with the voltage ratio determined from data

retrospectively extracted from the work of Drenckhahn et al. [34]. Data are reported as medians

(1^{st} quartile, 3^{rd} quartile) and $p < 0.05$ was accepted as statistically significant.

3   Results

The simulation results for the voltage and current density distributions in the various layers from

the cortex to the scalp for a cortical triangular wave after 5 seconds and 10 minutes are shown in

Fig. 2. The voltage field and ring shape at the interface between each layer of the model starting

at the cortex and continuing to the scalp are summarized in Table 2. Early in the migration of the

voltage depression, the voltage requires more time to return to rest after passage of the wave

peak when compared to later time points. On the scalp, the relative voltage exceeded the 0.2

threshold at 14.6 mm ahead of the peak voltage and remained elevated 16.2 mm behind the peak

value. Figures 2b and 2d show that the largest current densities occur in the first layer composed

of CSF, as it is the most conductive, peaking at 35.6 mA/m^2 at the point of peak voltage on the

cortical surface and weakening to below 2.1 mA/m^2 at locations 2 mm before and after the value

of SD radius, r(t), at the peak cortical voltage. The muscle tissue also shows an elevated current

density (20 mA/m^2), though much smaller than that in the CSF.

3.1   Voltage Decrease

The voltage detectable at the scalp is attenuated to 0.0735 of its strength at the cortex as shown

in Table 2. The voltage is attenuated through each layer, while the affected region grows larger.

The largest amplitude drop, $\Delta V = 8.18$ mV, occurs in the skull. A drop of 5.10 and 5.01 mV

occurred in the CSF and dura matter, respectively. The total voltage amplitude drop across the

skin and muscle taken together was only 0.240 mV. Figure 3 compares the voltage at the cortex

to that of the scalp, and at each interface between layers.

3.2   Dimensional Changes

The area above the threshold voltage grew most in the skull (595%) and least in the muscle

(0.74%). The thickness of the voltage ring was 2.4 mm at the cortical surface and increases to

30.8 mm (x 12.8) at the scalp. There is also a spatial lag between the locations of the peak

voltage on the cortex and the scalp of 0.474 mm, which corresponds to a time delay of 0.16

minutes. Supplemental Movie S1 presents a movie of the scalp voltage from a cortical SD with

both top and side views.

3.3   Voltage Ratios from the Simulated Square and Triangle Waves

This study investigated two types of propagation waves: a square wave and a triangular wave.

Their peak voltages from the scalp electrode sampling results were noticeably different: V_{peak}

was 3.6 and 1.47 mV for the square and triangle waves, respectively, giving relative voltages of

0.18 and 0.0735.

In addition to simulating the scalp signal with tissues having electromagnetic properties

as measured in Penn and Bell [95], we also simulated the triangle wave profile with tissue having

properties as reported by Gabriel et al. [96]. Though the estimates of these parameters were

different, some by several orders of magnitude, the resulting peak scalp voltage ratio was 0.09,

as opposed to 0.0735, suggesting that signal detectability at the scalp is not sensitive to the

variation of tissue properties between (or within) subjects.

3.4   Voltage Ratio Comparison with Clinical Research Results

We compared the voltage ratio from our simulation results with the voltage ratio retrospectively

evaluated from the data collected by Drenckhahn et al. [34]. Paired and identifiable fbECoG

subdural and fbEEG scalp recordings were available for 161 SDs. In the pooled analysis, the

maximum fbECoG subdural peak amplitude among all electrodes for each individual SD was

-9.3 (-7.2, -10.1) mV. In the scalp fbEEG recordings of the same SDs, the maximum peak

amplitude among all electrodes was -273 (-376, -176) μV. The ratio of peak scalp to peak

subdural voltage was 0.0316 (0.0221, 0.0527) in the pooled data analysis (n=161). The

simulation results differed from the retrospectively evaluated data; the ratio of peak scalp to

simulated peak cortical voltage, V_{scalp}/V_{cortex} = 0.0735 versus 0.0316 (0.0221, 0.0527), n =

161, $p < 0.001$, one sample Wilcoxon signed rank test.

3.5   Effect of Electrode Spacing on Visualization of Scalp Voltage

Figure 4 shows the reconstruction of the surface signal using regularly spaced sensor arrays with

varying separation distance. The voltage reconstructions are visually consistent with the true

field up to a sensor grid spacing of 1.0 cm. At larger electrode grid spacings of 2 cm and above, a

breakdown of the ring structure occurs, and at even greater spacings the structure could not be

discerned. Figure 5 illustrates how the loss of structure occurs due to the change in grid spacing

starting at the 2 cm spacing (Figure 5c) and continuing at the 3 cm spacing (Figure 5d).

Supplemental Fig. S1 shows the dependence of the degradation of the true scalp voltage on the

electrode spacing and the time after SD initiation.

3.6   Effect of Electrode Spacing on the Error in the Reconstruction of Scalp

Voltage

Figure 6 shows the root-mean-squared error of the reconstructed scalp voltage as a function of

electrode spacing: the error approaches 5% for electrode spacing of 1.5 cm and increases to 25%

for electrode spacing above 2.5 cm. When taking into account differences in possible electrode

diameter from 0.1 to 1 cm, we found that the reconstructions only varied by 2% even when

comparing a point electrode to one that was 1 cm in diameter. The error in reconstructing the

brain-surface field from an electrode grid could be further reduced by application of more

complex and computationally expensive interpolation methods.

3.7   Errors in Velocity and Ring Thickness

The simulation results allowed the velocity, as one of the characteristic parameters of SD, to be

estimated from the simulated scalp potential, but as previously noted, errors were dependent on a

misalignment of the strip electrode and the origin and path of the spreading wave. The velocity

and ring thickness predictions were dependent on the sensor offset from the velocity vector, as

well as on the proximity to the focus of the SD, and reached values less than 10% and 4% for

velocity and thickness, respectively.

The velocity was consistently over predicted. The error in the velocity calculation (in

relation to the simulation velocity of 3 mm/min) using the onset time (V_{rel} exceeding 0.2) was

highest near the focal point of the concussion, being 127%, 127%, 117%, and 284% for the 4

different offsets, and decreasing to 7.5%, 6.4%, 8.7%, and 19% for the final electrode pairing,

i.e., the two electrodes furthest from the focus of the SD. The errors in the velocity calculation

were smaller using the abatement times (V_{rel} returns to less than 0.2) with two electrodes closest

to the focus predicting errors of 82%, 82%, 88.7%, and 122%, but the velocity errors were

similar at the final electrode pairing to those predicted using the onset time.

The average time of electrode activation for $V_{rel} > 0.2$ was 9.66 (9.12, 9.9) minutes

excluding electrodes for which the wave did not completely pass within the 15-minute time

frame. The error in ring thickness increased as the array was offset; the error between predicted

and actual thickness was 3.51% to 9.8% for the zero and 1 cm offset arrays, respectively.

4   Discussion

We simulated the scalp voltage produced by a concentrically traveling SD on the cortex of the

brain and estimated that an electrode spacing of 1.0 cm is required to accurately collect the

spatio-temporal data of the SD with image reconstruction errors of less than 5%, whereas an

electrode spacing of 2 cm gives reconstruction errors greater the 15% at 15 min (see Figure 6).

The results showed that the SD wave detectability is dependent on electrode grid spacing, with

loss of structure as grid spacing increases. The ratio of simulated peak scalp to peak cortical

voltage (Vscalp/Vcortex = 0.0735) was approximately double compared to the retrospectively

evaluated clinical research observations of Drenckhahn et al. [34]. This difference is acceptable

as its due to differences in SD shape and configuration between our simulated concussive and

aSAH SDs. Although the amplitude from the simulated concussive SD is diminished to ~7% of

that at the brain surface through resistive dissipation, it is large enough to be detected by current

DC-coupled amplifiers. The spatial expansion of the negative DC-potential at the scalp of a

brain-surface SD, which occurs mostly in the skull (low current but high resistance), aids in the

non-invasive detection of a SD as it enlarges the ring thickness at the scalp.

Our simulation results were highly accurate (peak errors < 1e-3%) when compared to the

closed-form solutions. This accuracy suggests that imaging principles that were used in this work

could be applied to detection and tracking of SDs. Therefore, systematic errors due to our

model's simplified geometry and assumed uniform thickness of the layers and to the effect of

variations in material properties (conductivity and relative permittivity) used in our simulation

will not detract from the accuracy and reliability of the simulated data for its potential use in

future designs.

4.1   Existing Methods of SD Detection

The current method for detecting and measuring SDs using electrocorticography (ECoG) with

strip electrodes directly placed on the cortical surface [36, 47] is invasive. This method is only

used on patients where the electrodes are placed concurrently with a prior necessitated

craniotomy or a burr hole trepanation for placement of a ventricular drain or oxygen sensor [108]

as performed for the planning of resective epilepsy surgery [109; see section 'Burr Holes for

Placement of Strip Electrodes' (4th page) and Figure 4]. Often, publications using ECoG SD

detection highlight the lack of a scalp detection method to reliably detect SD non-invasively [35,

108].

4.2   Previous Non-Invasive Detection Attempts

To answer this need for non-invasive SD detection, there have been two efforts directed at scalp

SD detection using simultaneous ECoG at the cortical surface and EEG at the scalp with

clinically-based electrode positions [34, 110] the spacings of which are typically estimated as ~8

cm for the 10-20 and ~2 cm for the 10-5 system [111, 112]. Stationary residual negative scalp

DC voltages between 65 μV and 1 mV associated with propagating SDs using ECoG have been

measured on the scalp by Drenckhahn et al. [34]; however, SD propagation was not observed on

the scalp (see Fig. 1A, traces 1-3 and 10-12, in Drenckhahn et al. [34]). The widened DC-

potential at the scalp shown by our simulation is possibly the reason Drenckhahn et al. [34]

observed that the scalp DC-voltage surface appeared at multiple electrodes simultaneously.

In another study, scalp observations of EEG suppression and DC-potential changes in

patients whose bone-flap had been removed (except for 1 of 18 subjects) were guided by ECoG-

detected SDs. However, unguided scalp SD detection was not established [110]. A replication of

this study [113] and a follow-up rebuttal [114] did not provide evidence of unguided non-

invasive SD detection.

Recently a case study has been reported of spreading depression correlates in the EEG

delta band (0-4 Hz) visually identified in retrospectively examined 12-hr time-compressed scalp

EEG records that were time-associated with depth electrode ECoG suppressions and DC shifts of

a SD [115], suggesting another possible method of non-invasive SD detection.

4.3   SD modeling, trajectories, and simulation

Although tracking [116], modeling [117, 118], and observational [119] studies of SDs

have been made in or used gyrencephalic brains, our model of an SD propagating on a flat sheet

replicates the brain surface electric field of an SD appropriately and does represent the most

likely situation of SD propagation along a gyrus, based on Woitzik et al.'s [41] data that 17 out

of 19 SDs observed in human malignant hemispheric stroke patients travelled on gyral ridges,

and on the reasoning that a gyrus can be represented as a segment of a flat sheet. One effort by

Chamanzar et al. [120] provides simulations for detecting SDs based on modeling their EEG

suppressions in the clinical EEG frequencies with silent cortical dipoles imbedded in a realistic

brain model. This work used the well-known variation in EEG suppression duration and width as

a determinant of detectability. This effort is clearly complementary to our work concerning the

brain surface electric field produced from the DC-shift associated with SD depolarization, its

propagation to the scalp and reconstruction as a heat-map image of the associated scalp electric

field: Both SDs DC-shift, as modeled in this work, and EEG suppression, as modeled by

Chamanzar et al. [120], are recognized as essential markers of SD identification using the

invasive ECoG method [108].

4.4   Velocity and Size Errors Using Estimates from a Limited Electrode Array

The relative position of the SD focus and the electrode array affect the prediction of the size and

speed of the SD. Electrodes nearest to the focal point of the SD showed the most significant

errors in the velocity calculation (> 100%). This is because directly above the focus, the scalp

voltage is affected by the entire ring. This effect becomes less pronounced as the ring expands

outwards. The apparent velocity approaches the expansion velocity of the SD as the leading edge

(scalp) propagates away from the focal point (temporally and spatially). Electrodes further from

the focus had relatively small errors (~6%) but increased (by 20%) as the electrode-sensor row

was offset from the radial projection of the SD focus. Despite the large variability in velocity

predictions, the thickness of the SD was more reliably calculated with errors of approximately 4 -

10% or 0.2 - 1.0 cm. The model showed that the post-SD scalp voltage recovered at a slower rate

due to the same axisymmetric influence of the ring structure with the more closely spaced

electric field lines at the trailing edge of the ring. This sustains the decreased voltage of the

depolarization for a longer duration (t_d) at this trailing edge. These effects may not be indicative

of the truly active system, where biofluidic pathways, i.e., blood and CSF, may serve to restore

voltage potentials more efficiently than a passive material. For example, blood flow can increase

post-SD [41] and may remove excess ions [121; page 156]. In addition, massive amounts of K^+

appear in the CSF [122] and their clearance via the glymphatic route [123] could alter the voltage

potential.

4.5   Estimated Surface Characteristics and Voltage Ratio - Comparison of

Simulated Square and Triangle Waves

The simulated DC-potential on the scalp has identifiable shape and magnitude characteristics.

The spatial extent of the voltage change due to the SD wave expands considerably, from 2.4 mm

to 30.8 mm, as it passes through tissue, allowing it to be detected by multiple electrodes

simultaneously. The voltage data presented here are discussed in terms of V_{ratio}, the peak scalp

electrode sampled voltage scaled by the peak voltage of the SD. The simulation predicted

voltage ratios of 0.18 and 0.0735 for the square wave and triangular wave, respectively.

Aesthetically, the triangle wave offers a better fit to the waveforms observed by Drenckhahn et

al. [34], but would result in less voltage at the scalp than the concussive-SD observed by Pacheco

et al. [26; Figure 4H top], suggesting that it provides a conservative estimate of SD-detectability.

The primary reason that the square wave shows better propagation of voltage (higher $|V|$) is that

it produces more power (V^2/R) for a given resistance.

4.6   Comparison of Voltage Ratios – Simulation vs. Clinical Research

The median value of the voltage ratio from the retrospective analysis of data from Drenckhahn et

al. [34] was 0.0316 (0.0221, 0.0527), which is significantly different from our voltage ratio value

of 0.0735 ($p < 0.001$). This difference is within the same general range and is acceptable for our

purposes, especially because data from human concussive SDs is not available. The higher

voltage ratio from our simulation of an expanding ring concussive SD can be attributed to the

different shape, size, and propagating configuration of its electric field as compared to that of an

aSAH SD. The strength of signal predicted at the scalp surface is stronger for an expanding ring

SD compared to a globular SD because the contributions of the electric field from adjacent

portions of the expanding ring add together to produce a net increase in the electric filed at the

scalp. Analytic models of the expanding ring SD and an aSAH SD-like globular-region model

were compared. The globular-SD had a triangular voltage profile with a width of 3 mm. These

analytic models allow predictions of the scalp surface DC-voltage ratios, which are 0.093 for the

expanding ring, compared to 0.010 for the globular-region model with triangular waveform.

This analysis explains why our simulated concussive SD voltage ratio of 0.0735 is much larger

than the ratio from our retrospective data analysis of human aSAH SDs. Furthermore, there are

inherent limitations in calculating a ratio of human voltage measurements due to misalignment of

the subdural electrode strip and the scalp electrodes. In the human case, there are also

complications in the estimation of an SD's maximum voltage as sensed by a limited one-

dimensional ECoG electrode array and the widely separated scalp EEG electrodes in relation to

an SD's trajectory, especially as the effect of fresh craniotomy in these patients with aneurismal

SAH is unknown [34].

4.7   SD Detectability and Practicality

Because the conductivity equation is linear and material properties are constant, the relative

voltage is independent of the peak voltage (ΔV_{SD}), but not the voltage waveform used to model

the SD. Therefore, a single numerical experiment can be used to evaluate a full range of

voltages. If we apply our simulated triangle wave voltage ratio of 0.0735 to the minimum voltage

of the retrospectively determined brain-surface voltages from Drenckhahn et al. [34] of -800 µV,

we obtain an estimated scalp voltage of -59 µV. This voltage is within the sensitivity threshold of

currently available DC-coupled biosignal amplifiers. This suggests that the threshold of

sensitivity for DC-EEG is an important consideration and that all but the weakest scalp voltages

from a SD would be detectable with the caveat that noise and artifacts might interfere. It also

might be possible that an SD could be non-invasively detected with an algorithm without

visualization with greater than 1 cm electrode spacing.

The practical implementation of non-invasive SD detection for concussion will depend

on the development of a non-invasive method in a known source of SD's in severe acute brain

injury patients in the Neurointensive Care Unit. The initial phase of this development cycle has

been reported using an 8x6 cm 1-cm spaced 29 electrode array [124, 125] placed over the edge

of the lesion.

4.8   Limitations

The SD spreads uniformly in the simulation since there is no biochemical, physical, or

anatomical variation in the simulated (lissencephalic) cortex [119, 126] or in the modeled

material layers that would serve to distort the shape of the wave, thus our simulation results have

limited applicability to those SDs that might enter sulci of a gyrencephalic cortex and to

situations where there are anatomical variations in the layers. However, the simulation suggests

the design parameters of a preliminary sensor array can be used to obtain the experimental

results necessary to refine the numerical model and SD detection algorithms that could be

developed for such a scalp SD sensor unit. Another limitation of this current study is that the

effect oof local drift such as the TEP [127, 128] and artifacts resulting from improper electrode-

skin contact were not included. Another limitation applies to using our results to predict SD

detection success of different SD widths and morphologies. If a globular SD, such as is typical

for ischemic stroke, were modeled travelling along the edge of a lesion or separated from the

lesion edge [129], a low error image reconstruction and faithful visualization might require

different electrode spacing.

A sensor array with electrode spacings of 1.0 cm will enable, and is sufficient for, the

reconstruction of an image of the concentrically spreading electric field on the scalp from a

brain-surface SD with low error and high visual fidelity. Obviously, the addition of large-scale

background noise and/or artifacts will hinder the reconstruction of the signal, as will the local

failure of a single electrode depending on the overall effectiveness of the interpolation

algorithms used to process the incoming signals. Other issues to be considered include the

relative electrode sensor sensitivities and relative motion to the scalp.

Non-invasive SD detection is often stated as a goal in those publications where SDs are

detected in acute brain injury patients using invasive ECoG [34-36], but applying our simulation

results for the detection of concussion-SDs, with this being in far future, directly to acute brain

injury SDs might be inappropriate, as suggested by our comparison of voltage ratios between our

simulated expanding ring SDs to the SAH-SD data gleaned from Drenckhahn et al.'s work [34].

This is because our results are based on the expanding ring SD morphology, whereas SDs in

acute brain injury are most likely globular with variable trajectories and dimensions including

width as suggested by the SD trajectory data of Woitzik et al. [41] in malignant hemispheric

stroke patients.

4.9   Conclusion

This simulation study suggests that propagating SDs can be visually detected on the scalp with

properly configured DC-EEG. If our simulation results were used to implement successful non-

invasive SD scalp detection, the link between SD and concussion could be confirmed. The

confirmation of this link would involve a large clinical trial using a deployable non-invasive SD

detection system that could be placed on an athlete's head at or near the concussive focus starting

within 10 minutes of the suspected concussion for a data collection period of at least 20 minutes.

SD could then provide a unifying concept for the wide-ranging symptoms of concussion; the

varying symptoms used to diagnose concussion could be a result of SD occurring in different

cortical locations, depending on where the head-hit occurred. In addition, our results imply that

the noninvasive detection of SDs in severe acute brain injury patients in the Neurointensive Care

Unit is possible with the proper electrode array configuration. This implication is supported by

our proof-of-concept validation data [124, 125].

Acknowledgements We thank Thomas Ferguson, Richard Kraig, Douglas Smith, and Joel

Greenberg for reading and commenting on the manuscript and Hiba Al-Ashtal for editorial

services.

Funding Information This project was conducted for CerebroScope, a medical device

company developing a scalp DC-EEG system for detecting SDs in severe acute brain injury,

concussion, and migraine. This work was partially supported by grants from the: US Public

Health Service National Institutes of Health: NS30839; NS30839-14S1; and NS66292 to the SCJ

while at the Allegheny-Singer Research Institute; and 5R43NS092181 and 3R43NS092181-02S1

to SCJ for CerebroScope; DFG Deutsche Forschungsgemeinschaft, German Research Council:

DFG DR 323/5-1 and DFG DR 323/10-1 to JPD; and BMBF Bundesministerium fuer Bildung

und Forschung (Era-Net Neuron EBio2), with funds from BMBF (0101EW2004) to JPD.

Compliance with Ethical Standards All ethical standards have been met. See section

"Retrospective Evaluation of Human Data".

Competing interests Samuel J. Hund, Prahlad G. Menon, and Stephen C. Jones are founding

partners and shareholders of CerebroScope. Benjamin R. Brown is a consultant to and

shareholder of CerebroScope.

Intellectual Property Disclosures Parts of this work are disclosed in U.S. Patent No.

10,028,694, published and publically available on May 26, 2016 and issued July 24, 2018; and in

U.S. Published Patent Application No. 2019/0038167, published February 7, 2019.

1 References

1.   Langlois JA, Rutland-Brown W, Wald MM. The epidemiology and impact of traumatic
brain injury: a brief overview. J Head Trauma Rehabil. 2006;21:375-378.

2.   Coronado VG, McGuire LC, Sarmiento K, et al. Trends in Traumatic Brain Injury in the
U.S. and the public health response: 1995-2009. J Safety Res. 2012;43:299-307.

3.   Lefevre-Dognin C, Cogné M, Perdrieau V, Granger A, Heslot C, Azouvi P. Definition
and epidemiology of mild traumatic brain injury. Neurochirurgie. 2020;67:218-221.

4.   Mansell JL, Tierney RT, Higgins M, McDevitt J, Toone N, Glutting J. Concussive signs
and symptoms following head impacts in collegiate athletes. Brain Inj. 2010;24:1070-
1074.

5.   Costello DM, Kaye AH, O'Brien TJ, Shultz SR. Sport related concussion - Potential for
biomarkers to improve acute management. J Clin Neurosci. 2018;56:1-6.

6.   Davis GA, Ellenbogen RG, Bailes J, et al. The Berlin International Consensus Meeting
on Concussion in Sport. Neurosurgery. 2018;82:232-236.

7.   Master CL, Mayer AR, Quinn D, Grady MF. Concussion. Ann Intern Med.
2018;169:ITC1-ITC16.

8.   Provencher MT, Frank RM, Shubert DJ, Sanchez A, Murphy CP, Zafonte RD.
Concussions in Sports. Orthopedics. 2019;42:12-21.

9.   Hobbs JG, Young JS, Bailes JE. Sports-related concussions: diagnosis, complications,
and current management strategies. Neurosurg Focus. 2016;40:E5:
https://doi.org/10.3171/2016.1.FOCUS15617.

10. Shively SB, Perl DP. Traumatic brain injury, shell shock, and posttraumatic stress
disorder in the military--past, present, and future. J Head Trauma Rehabil. 2012;27:234-
239.

11. Wells TS, Miller SC, Adler AB, Engel CC, Smith TC, Fairbank JA. Mental health impact
of the Iraq and Afghanistan conflicts: a review of US research, service provision, and
programmatic responses. Int Rev Psychiatry. 2011;23:144-152.

12. Guskiewicz KM, Marshall SW, Bailes J, et al. Association between recurrent concussion
and late-life cognitive impairment in retired professional football players. Neurosurgery.
2005;57:719-726.

13. Harmon KG, Drezner JA, Gammons M, et al. American Medical Society for Sports
Medicine position statement: concussion in sport. Br J Sports Med. 2013;47:15-26.

14. Bruce J, Echemendia R, Meeuwisse W, Comper P, Sisco A. 1 year test-retest reliability
of ImPACT in professional ice hockey players. Clin Neurophysiol. 2013;28:14-25.

15. Lichtenstein JD, Moser RS, Schatz P. Age and Test Setting Affect the Prevalence of Invalid Baseline Scores on Neurocognitive Tests. Am J Sports Med. 2013;42:479-484.

16. Resch J, Driscoll A, McCaffrey N, et al. ImPact Test-Retest Reliability: Reliably Unreliable? J Athl Train. 2013;48:506-511.

17. Barlow M, Schlabach D, Peiffer J, Cook C. Differences in change scores and the predictive validity of three commonly used measures following concussion in the middle school and high school aged population. Inter J Sports Phys Ther. 2011;6:150-157.

18. McClure DJ, Zuckerman SL, Kutscher SJ, Gregory AJ, Solomon GS. Baseline Neurocognitive Testing in Sports-Related Concussions: The Importance of a Prior Night's Sleep. Am J Sports Med. 2014;42:472-478.

19. Cole WR, Arrieux JP, Schwab K, Ivins BJ, Qashu FM, Lewis SC. Test-retest reliability of four computerized neurocognitive assessment tools in an active duty military population. Arch Clin Neuropsychol. 2013;28:732-742.

20. Thiagarajan P, Ciuffreda KJ, Ludlam DP. Vergence dysfunction in mild traumatic brain injury (mTBI): a review. Ophthalmic Physiol Opt. 2011;31:456-468.

21. Echemendia RJ, Putukian M, Mackin RS, Julian L, Shoss N. Neuropsychological test performance prior to and following sports-related mild traumatic brain injury. Clin J Sport Med. 2001;11:23-31.

22. Echemendia RJ, Meeuwisse W, McCrory P, et al. The Sport Concussion Assessment Tool 5th Edition (SCAT5): Background and rationale. Br J Sports Med. 2017;51:848-850.

23. Ochiai H, Abe T. Clinical features and early detection of sport-related concussion. Acute Med Surg. 2019;6:49-53.

24. Broglio SP, Cantu RC, Gioia GA, et al. National Athletic Trainers' Association position statement: management of sport concussion. J Athl Train. 2014;49:245-265.

25. Somjen GG. Mechanisms of spreading depression and hypoxic spreading depression-like depolarization. Physiol Rev. 2001;81:1065-1096.

26. Pacheco JM, Hines-Lanham A, Stratton C, et al. Spreading Depolarizations Occur in Mild Traumatic Brain Injuries and Are Associated with Postinjury Behavior. eNeuro. 2019;6:1-17.

27. Bouley J, Chung DY, Ayata CY, Brown RH, Jr., Henninger N. Cortical spreading depression denotes concussion injury. J Neurotrauma. 2019;36:1008-1017.

28. Smith DH, Stewart W. 'Concussion' is not a true diagnosis. Nat Rev Neurol. 2020;16:457-458.

29. McCuddy WT, España LY, Nelson LD, Birn RM, Mayer AR, Meier TB. Association of acute depressive symptoms and functional connectivity of emotional processing regions following sport-related concussion. Neuroimage Clin. 2018;19:434-442.

30. O'Jile JR, Ryan LM, Betz B, et al. Information processing following mild head injury. Arch Clin Neuropsychol. 2006;21:293-296.

31. Leao AAP. Spreading depression of activity in the cerebral cortex. J Neurophysiol. 1944;7:359-390.

32. Reid KH, Marrannes R, Wauquier A. Spreading depression and central nervous system pharmacology. J Pharmacol Methods. 1988;19:1-21.

33. Leao AA. The slow voltage variation of cortical spreading depression of activity. Electroencephalogr Clin Neurophysiol. 1951;3:315-321.

34. Drenckhahn C, Winkler MK, Major S, et al. Correlates of spreading depolarization in human scalp electroencephalography. Brain. 2012;135:853-868.

35. Lauritzen M, Dreier JP, Fabricius M, Hartings JA, Graf R, Strong AJ. Clinical relevance of cortical spreading depression in neurological disorders: migraine, malignant stroke, subarachnoid and intracranial hemorrhage, and traumatic brain injury. J Cereb Blood Flow Metab. 2011;31:17-35.

36. Strong AJ, Fabricius M, Boutelle MG, et al. Spreading and synchronous depressions of cortical activity in acutely injured human brain. Stroke. 2002;33:2738-2743.

37. Leao AAP. Further observations on the speading depression of activity in the cerebral cortex. J Neurophysiol. 1947; 10:409-414.

38. Kraig RP, Nicholson C. Extracellular ionic variations during spreading depression. Neuroscience. 1978;3:1045-1059.

39. Dreier JP. The role of spreading depression, spreading depolarization and spreading ischemia in neurological disease. Nat Med. 2011;17:439-447.

40. Enger R, Tang W, Vindedal GF, et al. Dynamics of Ionic Shifts in Cortical Spreading Depression. Cereb Cortex. 2015;25:4469-4476.

41. Woitzik J, Hecht N, Pinczolits A, et al. Propagation of cortical spreading depolarization in the human cortex after malignant stroke. Neurology. 2013;80:1095-1102.

42. Grafstein B. Locus of propagation of spreading cortical depression. J Neurophysiol. 1956;19:308-316.

43. Mayevsky A, Doron A, Manor T, Meilin S, Zarchin N, Ouaknine GE. Cortical spreading depression recorded from the human brain using a multiparametric monitoring system. Brain Res. 1996;740:268-274.

44. Dohmen C, Sakowitz OW, Fabricius M, et al. Delayed secondary phase of peri-infarct depolarizations after focal cerebral ischemia: relation to infarct growth and neuroprotection. Ann Neurol. 2008;63:720-728.

45. Dreier JP, Woitzik J, Fabricius M, et al. Delayed ischaemic neurological deficits after subarachnoid haemorrhage are associated with clusters of spreading depolarizations. Brain. 2006;129:3224-3237.

46.   Dreier JP, Major S, Manning A, et al. Cortical spreading ischaemia is a novel process
involved in ischaemic damage in patients with aneurysmal subarachnoid haemorrhage.
Brain. 2009;132:1866-1881.

47.   Fabricius M, Fuhr S, Bhatia R, et al. Cortical spreading depression and peri-infarct
depolarization in acutely injured human cerebral cortex. Brain. 2006;129:778-790.

48.   Hartings JA, Bullock MR, Okonkwo DO, et al. Spreading depolarisations and outcome
after traumatic brain injury: a prospective observational study. Lancet Neurol.
2011;10:1058-1064.

49.   Helbok R, Schiefecker AJ, Friberg C, et al. Spreading depolarizations in patients with
spontaneous intracerebral hemorrhage: Association with perihematomal edema
progression. J Cereb Blood Flow Metab. 2017;37:1871-1882.

50.   Dreier JP, Reiffurth C. The stroke-migraine depolarization continuum. Neuron.
2015;86:902-922.

51.   Hartings JA, Shuttleworth CW, Kirov SA, et al. The continuum of spreading
depolarizations in acute cortical lesion development: Examining Leao's legacy. J Cereb
Blood Flow Metab. 2017;37:1571-1594.

52.   Oliveira-Ferreira AI, Milakara D, Alam M, et al. Experimental and preliminary clinical
evidence of an ischemic zone with prolonged negative DC shifts surrounded by a
normally perfused tissue belt with persistent electrocorticographic depression. J Cereb
Blood Flow Metab. 2010;30:1504-1519.

53.   Hartings JA, York J, Carroll CP, et al. Subarachnoid blood acutely induces spreading
depolarizations and early cortical infarction. Brain. 2017;140:2673-2690.

54.   Luckl J, Lemale CL, Kola V, et al. The negative ultraslow potential, electrophysiological
correlate of infarction in the human cortex. Brain. 2018;141:1734-1752.

55.   Dreier JP, Major S, Foreman B, et al. Terminal spreading depolarization and electrical
silence in death of human cerebral cortex. Ann Neurol. 2018;83:295-310.

56.   Dreier JP, Major S, Lemale CL, et al. Correlates of Spreading Depolarization, Spreading
Depression, and Negative Ultraslow Potential in Epidural Versus Subdural
Electrocorticography. Front Neurosci. 2019;13:373.

57.   Carlson AP, Shuttleworth CW, Major S, Lemale CL, Dreier JP, Hartings JA. Terminal
spreading depolarizations causing electrocortical silencing prior to clinical brain death:
case report. J Neurosurg. 2018;131:1773-1779.

58.   Menyhárt Á, Frank R, Farkas AE, et al. Malignant astrocyte swelling and impaired
glutamate clearance drive the expansion of injurious spreading depolarization foci. J
Cereb Blood Flow Metab. 2021;Online ahead eprint.

59.   Hadjikhani N, Sanchez Del Rio M, Wu O, et al. Mechanisms of migraine aura revealed
by functional MRI in human visual cortex. Proc Natl Acad Sci USA. 2001;98:4687-4692.

60. Major S, Huo S, Lemale CL, et al. Direct electrophysiological evidence that spreading depolarization-induced spreading depression is the pathophysiological correlate of the migraine aura and a review of the spreading depolarization continuum of acute neuronal mass injury. Geroscience. 2020;42:57-80.

61. Kumagai T, Walberer M, Nakamura H, et al. Distinct spatiotemporal patterns of spreading depolarizations during early infarct evolution: evidence from real-time imaging. J Cereb Blood Flow Metab. 2011;31:580-592.

62. Zachar J, Zacharova D. [Mechanical energy as causative agent of spreading depression]. Cesk Fysiol. 1958;7:189-190.

63. Zachar J, Zacharova D. [Mechanism of the origin of spreading cortical depression] (in Slovak). Lek Pr. 1963;3:3-110.

64. Zachar J, Zacharova D. Subthreshold changes at the site of initiation of spreading cortical depression by mechanical stimuli. Electroencephalogr Clin Neurophysiol. 1961;13:896-904.

65. Bures J, Buresova O, Krivanek J. Initiation of Spreading Depression: Mechanical Stimuli. The Mechanism and Application of Leao's Spreading Depression of Electroencephalographic Activity. Prague: Academia; 1974:26-30.

66. Shah KR, West M. The effect of concussion on cerebral uptake of 2-deoxy-D-glucose in rat. Neurosci Lett. 1983;40:287-291.

67. Takahashi H, Manaka S, Sano K. Changes in extracellular potassium concentration in cortex and brain stem during the acute phase of experimental closed head injury. J Neurosurg. 1981;55:708-717.

68. West M, Parkinson D, Havlicek V. Spectral analysis of the electroencephalographic response in experimental concussion in the rat. Electroencephalogr Clin Neurophysiol. 1982;53:192-200.

69. Meyer JS, Denny-Brown D. Studies of cerebral circulation in brain injury. II. Cerebral concussion. Electroencephalogr Clin Neurophysiol. 1955;7:529-544.

70. Watanabe N, Noriaki W. The Mechanism and Pathophysiology of Rat Cerebral Concussion: Changes in rCBF, ECoG, SPC Following Skull Impact. Journal of the Medical Society of Toho University. 2002;49:23-30.

71. Oka H, Kako M, Matsushima M, Ando K. Specific type of head injury in children. Report of 5 cases. Brain. 1977;100:287-298.

72. Takahashi H, Nakazawa S. Specific type of head injury in children. Report of 5 cases. Childs Brain. 1980;7:124-131.

73. Barkhoudarian G, Hovda DA, Giza CC. The molecular pathophysiology of concussive brain injury. Clin Sports Med. 2011;30:33-48.

74. Sakas DE, Whitwell HL. Neurological episodes after minor head injury and trigeminovascular activation. Med Hypotheses. 1997;48:431-435.

75. The editor. Vasodilatation and migraine. Lancet. 1990;335:822-823.

76. Pietrobon D, Moskowitz MA. Chaos and commotion in the wake of cortical spreading depression and spreading depolarizations. Nat Rev Neurosci. 2014;15:379-393.

77. Marshall WH. Spreading cortical depression of Leao. Physiol Rev. 1959;39:239-279.

78. Geddes-Klein DM, Schiffman KB, Meaney DF. Mechanisms and consequences of neuronal stretch injury in vitro differ with the model of trauma. J Neurotrauma. 2006;23:193-204.

79. Keating CE, Cullen DK. Mechanosensation in traumatic brain injury. Neurobiol Dis. 2021;148:105210, Online ahead of print: https://doi.org/10.1016/j.nbd.2020.105210.

80. Tavalin SJ, Ellis EF, Satin LS. Mechanical perturbation of cultured cortical neurons reveals a stretch-induced delayed depolarization. J Neurophysiol. 1995;74:2767-2773.

81. Hibino M, Itoh H, Kinosita K, Jr. Time courses of cell electroporation as revealed by submicrosecond imaging of transmembrane potential. Biophys J. 1993;64:1789-1800.

82. Fischer P, Sugimoto K, Chung DY, et al. Rapid hematoma growth triggers spreading depolarizations in experimental intracortical hemorrhage. J Cereb Blood Flow Metab. 2021;41:1264-1276.

83. Hallez H, Vanrumste B, Grech R, et al. Review on solving the forward problem in EEG source analysis. J Neuroeng Rehabil. 2007;4: https://doi.org/10.1186/1743-0003-4-46.

84. Ramon C, Schimpf PH, Haueisen J. Influence of head models on EEG simulations and inverse source localizations. BioMed Eng OnLine. 2006;5:1-13: http://dx.doi.org/10.1186/1475-925X-5-10.

85. Miller JW, Kim W, Holmes MD, Vanhatalo S. Ictal localization by source analysis of infraslow activity in DC-coupled scalp EEG recordings. Neuroimage. 2007;35:583-597.

86. Chamanzar A, Behrmann M, Grover P. Neural silences can be localized rapidly using noninvasive scalp EEG. Commun Biol. 2021;4:429.

87. Cuffin BN. Effects of local variations in skull and scalp thickness on EEG's and MEG's. IEEE Trans Biomed Eng. 1993;40:42-48.

88. Cuffin BN. Effects of head shape on EEG's and MEG's. IEEE Trans Biomed Eng. 1990;37:44-52.

89. Stavtsev AI, Ushakov VL, Verkhliutov VM. [Modeling the effect of the layer thickness and tissue conductivities of the head and the brain on the EEG potentials using finite element method][Article in Russian]. Zh Vyssh Nerv Deiat Im I P Pavlova. 2007;57:742-752.

90. Baillet S, Mosher JC, Leahy RM. Electromagnetic brain mapping. IEEE Signal
Processing Magazine. 2001;18:14-30.

91. Leahy RM, Mosher JC, Spencer ME, Huang MX, Lewine JD. A study of dipole
localization accuracy for MEG and EEG using a human skull phantom.
Electroencephalogr Clin Neurophysiol. 1998;107:159-173.

92. Wen P. The impact of inhomogeneous tissue anisotropy on potential distribution within
head model. Australas Phys Eng Sci Med. 2003;26:115-118.

93. Plis SM, George JS, Jun SC, Ranken DM, Volegov PL, Schmidt DM. Probabilistic
forward model for electroencephalography source analysis. Phys Med Biol.
2007;52:5309-5327.

94. Seery GE. Surgical anatomy of the scalp. Dermatol Surg. 2002;28:581-587.

95. Penn JW, Bell EL. Electrical Parameter Values of Some Human Tissues in the
Radiofrequency Radiation Range. 1978; Defense Technical Information Center, Report #
SAM-TR-78-38: https://apps.dtic.mil/sti/pdfs/ADA064202.pdf

96. Gabriel C, Peyman A, Grant EH. Electrical conductivity of tissue at frequencies below 1
MHz. Phys Med Biol. 2009;54:4863-4878.

97. Pellman EJ, Viano DC, Tucker AM, Casson IR. Concussion in professional football:
location and direction of helmet impacts-Part 2. Neurosurgery. 2003;53:1328-1340.

98. Dannhauer M, Lanfer B, Wolters CH, Knosche TR. Modeling of the human skull in EEG
source analysis. Hum Brain Mapp. 2011;32:1383-1399.

99. Petrov Y. Anisotropic spherical head model and its application to imaging electric
activity of the brain. Phys Rev E Stat Nonlin Soft Matter Phys. 2012;86:011917-011917:
https://10.1103/PhysRevE.86.011917.

100. Bruno P, Vatta F, Mininel S, Inchingolo P. Referenced EEG and head volume conductor
model: geometry and parametrical setting. Conf Proc IEEE Eng Med Biol Soc.
2004;2:833-836.

101. Johnson G, Massoudi M, Rajagopal KR. Flow of a fluid-solid mixture between flat
plates. Chemical Engineering Science. 1991;46:1713-1723.

102. Tallgren P, Vanhatalo S, Kaila K, Voipio J. Evaluation of commercially available
electrodes and gels for recording of slow EEG potentials. Clin Neurophysiol.
2005;116:799-806.

103. Voipio J, Tallgren P, Heinonen E, Vanhatalo S, Kaila K. Millivolt-scale DC shifts in the
human scalp EEG: evidence for a nonneuronal generator. J Neurophysiol. 2003;89:2208-
2214.

104. Oostenveld R, Fries P, Maris E, Schoffelen JM. FieldTrip: Open source software for
advanced analysis of MEG, EEG, and invasive electrophysiological data. Comput Intell
Neurosci. 2011;2011:156869.

105. Vorwerk J, Oostenveld R, Piastra MC, Magyari L, Wolters CH. The FieldTrip-SimBio pipeline for EEG forward solutions. Biomed Eng Online. 2018;17:37.

106. Roache PJ. Verification and Validation in Computational Science and Engineering. Albuquerque, New Mexico: Hermosa Publishers; 1998.

107. Press WH, Teukolsky SA, Vetterling WT, Flannery BP. **3.6 Interpolation on a Grid in Multidimensions**. Numerical Recipes 3rd Edition: The Art of Scientific Computing. Cambridge University Press, The Edinburgh Building, Cambridge, UK; 2007:132-134.

108. Dreier JP, Fabricius M, Ayata C, et al. Recording, analysis, and interpretation of spreading depolarizations in neurointensive care: Review and recommendations of the COSBID research group. J Cereb Blood Flow Metab. 2017;37:1595-1625.

109. Voorhies JM, Cohen-Gadol A. Techniques for placement of grid and strip electrodes for intracranial epilepsy surgery monitoring: Pearls and pitfalls. Surg Neurol Int. 2013;4:98: https://www.ncbi.nlm.nih.gov/pmc/articles/PMC3740610/.

110. Hartings JA, Wilson JA, Hinzman JM, et al. Spreading depression in continuous electroencephalography of brain trauma. Ann Neurol. 2014;76:681-694.

111. Klem GH, Luders HO, Jasper HH, Elger C. The ten-twenty electrode system of the International Federation. The International Federation of Clinical Neurophysiology. Electroencephalogr Clin Neurophysiol. 1999;52:3-6.

112. Oostenveld R, Praamstra P. The five percent electrode system for high-resolution EEG and ERP measurements. Clin Neurophysiol. 2001;112:713-719.

113. Hofmeijer J, van Kaam CR, van de Werff B, Vermeer SE, Tjepkema-Cloostermans MC, van Putten MJAM. Detecting Cortical Spreading Depolarization with Full Band Scalp Electroencephalography: An Illusion? Front Neurol. 2018;9: https://www.frontiersin.org/articles/10.3389/fneur.2018.00017/full.

114. Hartings JA, Ngwenya LB, Watanabe T, Foreman B. Commentary: Detecting Cortical Spreading Depolarization with Full Band Scalp Electroencephalography: An Illusion? Front Syst Neurosci. 2018;12: https://www.frontiersin.org/articles/10.3389/fnsys.2018.00019/full.

115. Robinson D, Hartings J, Foreman B. First Report of Spreading Depolarization Correlates on Scalp EEG Confirmed with a Depth Electrode. Neurocrit Care. 2021.

116. Milakara D, Grozea C, Dahlem M, et al. Simulation of spreading depolarization trajectories in cerebral cortex: Correlation of velocity and susceptibility in patients with aneurysmal subarachnoid hemorrhage. Neuroimage Clin. 2017;16:524-538.

117. Dahlem MA, Graf R, Strong AJ, et al. Two-dimensional wave patterns of spreading depolarization: Retracting, re-entrant, and stationary waves. Physica D. 2010;239:889-903.

118. Kenny A, Plank MJ, David T. The effects of cerebral curvature on cortical spreading depression. J Theor Biol. 2019;472:11-26.

119. Santos E, Sanchez-Porras R, Sakowitz OW, Dreier JP, Dahlem MA. Heterogeneous propagation of spreading depolarizations in the lissencephalic and gyrencephalic brain. J Cereb Blood Flow Metab. 2017;37:2639-2643.

120. Chamanzar A, George S, Venkatesh P, et al. An algorithm for automated, noninvasive detection of cortical spreading depolarizations based on EEG simulation. faIEEE Trans Biomed Eng. 2019;66:1115-1126.

121. Bures J, Buresova O, Krivanek J. The Mechanism and Application of Leao's Spreading Depression of Electroencephalographic Activity. Prague: Academia; 1974.

122. Brinley FJ, Jr., Kandel ER, Marshall WH. Potassium outflux from rabbit cortex during spreading depression. J Neurophysiol. 1960;23:246-256.

123. Mestre H, Du T, Sweeney AM, et al. Cerebrospinal fluid influx drives acute ischemic tissue swelling. Science. 2020;367: https://doi.org/10.1126/science.aax7171.

124. Jones SC, Hund SJ, Singer E, Brown BR. Non-invasive detection of spreading depolarization: Initial results. 3rd International Conference on Spreading Depolarization (iCSD-2019); Yokohama, Japan: http://www.cosbid.org/wp-content/uploads/2019/07/iCSD-2019-Program.pdf.

125. Jones SC, Hund SJ, Singer E, Brown BR. Non-invasive detection of spreading depolarization: further results. 4th International Conference on Spreading Depolarization (iCSD-2021); Sep 20, 2021; Lyon, France: Not yet available.

126. James MF, Smith MI, Bockhorst KH, et al. Cortical spreading depression in the gyrencephalic feline brain studied by magnetic resonance imaging. J Physiol. 1999;519 Pt 2:415-425.

127. Picton TW, Hillyard SA. Cephalic skin potentials in electroencephalography. Electroencephalogr Clin Neurophysiol. 1972;33:419-424.

128. Tallgren P. DC-stable electrode-skin interface for human EEG recording. 2005; University of Helsinki, Department of Biological and Environmental Sciences, Finland: Report # E5: http://lib.tkk.fi/Diss/2006/isbn9512269562/article4.pdf

129. Jones SC, Kharlamov A, Chung DY, Boada F, Yushmanov VE. **Types of peri-infarct depolarization trajectories in experimental ischemic stroke**. 4th International Conference on Spreading Depolarization (iCSD-2021); Sep 20, 2021; Lyon, France: Not yet available.

130. Dahnke R, Yotter RA, Ziegler G, Gaser C. Brain Tissue Thickness Estimation using a
Projection Scheme. 16th Annual Meeting of the Organization for Human Brain Mapping,
Program #1458; Jun 6, 2010; Barcelona: Organization of Human Brain Mapping:
https://www.researchgate.net/profile/Robert_Dahnke/publication/336513396_Brain_Tiss
ue_Thickness_Estimation_Using_a_Projection_Scheme/links/5da45dde45851553ff8f658
d/Brain-Tissue-Thickness-Estimation-Using-a-Projection-Scheme.pdf.

131. Bashkatov AN, Genina EA, Sinichkin YP, Kochubey VI, Lakodina NA, Tuchin VV.
Glucose and mannitol diffusion in human dura mater. Biophys J. 2003;85:3310-3318.

132. Mahinda HAM, Murty OP. Variability in thickness of human skull bones and sternum –
An autopsy experience. J Forensic Med Toxicol. 2009;26:26-31.

133. Hori H, Moretti G, Rebora A, Crovato F. The thickness of human scalp: normal and bald.
J Invest Dermatol. 1972;58:396-399.

Figure Captions

Fig. 1 The associated geometry and locations for the numerical analysis. **a**) The overlay of the

20-cm diameter computational domain (dark gray) and the sensor domain (white square with red

border) showing the focal point of the spreading depolarization (SD) as a red dot. **b**) A slice view

of the model layers with thickness representing cerebrospinal fluid (CSF), Dura Mater, Skull,

Muscle, and Skin. **c**) The three-dimensional computational domain with a 90° quadrant removed

to show the layers and focal point of the SD. **d**) An example of the 10 cm x 10 cm sensor grid

(red border) with 1-cm spacing and electrode locations indicated by crosses and the focal point

of the SD as a red dot. **e**) The sensor offset for velocity and geometric calculations with the ideal

sensor position with gray crosses, an offset array in black, and the focal point of the SD as a red

dot. The offsets used were 0.1, 0.5, and 1.0 cm

Fig. **2** Simulation results for electrical voltage and current density at 5 sec and 10 min after

spreading depolarization (SD) initiation in the 10-cm disk. Panels **a** and **b** (dashed border) show

the numerical results at 5 seconds, and panels **c** and **d** (solid border) show them at 10 minutes

after initiation of the SD for a concentrically spreading SD propagating radially. Panels **a** and **c**

show the electrical potential (voltage in mV), and panels **c** and **d** show the current density

(mA/m^2). The numerical pseudo-color scales for voltage and current density are shown below

panels **a** and **c,** and panels **b** and **d**, respectively. The insert in panel **c** shows the relative location

of the views of the SD depicted in panels **a** and **b** (5 seconds) as well as **c** and **d** (10 min). Also

included in the insert are the location of the scalp, cortex, and focal point of the SD

Fig. 3 The simulated voltage potential of a cortical spreading depolarization diminishes in

amplitude at the scalp (**b**) but increases in effective width (**c**). The voltages in the cortex and

scalp are shown with identical scales in (**a**) and (**b**) to highlight the change in amplitude. The

scalp voltage map is rescaled in **c** to highlight the increase in ring diameter

Fig. 4   The scalp voltage was sampled and reconstructed using simulated sensor grids with

electrode spacings of 0.5, 5, 10, 20, and 30 mm. These voltage maps represent the signal at 10

minutes after the onset of the spreading depolarization (SD). They illustrate the degradation of

the reconstruction with increasing electrode spacing, and the preservation of the scalp voltage at

electrode spacings of less than 1 cm.   The white X indicates the focal point of the SD.

Reconstruction was performed using bilinear interpolation between four electrodes

Fig. 5   Numerical simulation results of the scalp voltage reconstruction of a spreading depolarization (SD) expanding ring with different electrode spacings. (**a**) Estimated scalp voltage intensity map at 10 min after SD initiation in a 10 cm x 10 cm simulation domain. The symbol X marks the focal point of the SD on the underlying brain surface. The region within the dashed orange box is expanded to show the detail of the detected signal degradation with increased electrode spacing in (**b**), (**c**), and (**d**), with electrode spacings of 1, 2, and 3 cm, respectively. (**b**) Only the 1 cm spacing shows the full ring structure of the scalp voltage (~2.5% error). (**c**) The 2-cm sensor spacing shows a recognizable ring but a low voltage wedge has broken the structure (~15% error). The dark cross (**b** and **c**) indicates the locations of sensors that are removed from the 1 cm design to obtain the 2-cm design, which result in the breakdown of the ring. With the removal of the signal from the electrode sensors within this cross, the reconstructed heat map image losses data points that contribute to the ring structure. (**d**) The 3-cm spacing fails to reconstruct the ring structure in the intensity map (~25% error). The lost of the signal from the electrode marked with a surrounding square, located on the ring of the SD (depressed voltage), and from the two electrodes marked with surrounding triangles, on the normal tissue (baseline voltage), results in the development of a notch, thus breaking the ring structure. The white circles (**b** and **d**) indicate the sensors from the 1-cm design that remain in the 3-cm array

1   **Fig. 6**   The root-mean-squared error in the reconstruction, using the 0.05-cm spacing as the

2   baseline, for each of the sensor designs as a function of sensor electrode spacing and time. The

3   error is reported at 0.5, 1, 5, 10, and 15 minutes

Movie S1   (see mpg file) Movie of a simulation of an expanding ring cortical Spreading

Depolarization (SD) showing: (a) a top view of the simulated propagating scalp voltage,

represented by a 200-mm diameter disk and mapped to the pseudo-color scale, between 5

seconds and 15 minutes from the concentrically expanding SD. The 3-mm wide, expanding ring

SD on the cortical surface is shown in white against black in the lower left quadrant. (b) A radial

section, or cross-section of a side view, showing the propagating SD through the 5 layers [skin,

muscle, skull, dura mater (DM), and cerebrospinal fluid (CSF)] from the brain surface to the

scalp (thickness 10.2 mm) with a timer below. (c) The pseudo-color scale showing with the

voltage scaled to 20% of the maximum voltage of each layer

3   **Supplemental Fig. 1**   The scalp voltage intensity maps from a cortical spreading

4   depolarization (SD) onset as a function of sensor spacing and time after onset. Top row: The

5   exact voltage field is provided for reference at 0.5, 1, 5, 10, and 15 minutes after SD initiation.

6   The bottom three rows show the simulated voltages at the scalp for the electrode spacings of 1, 3,

7   and 4 cm