Predicting Composition of Genetic Circuits with Resource Competition: Demand and Sensitivity

Cameron D. McBride* and Domitilla Del Vecchio*

Department of Mechanical Engineering, MIT, 77 Massachusetts Ave, Cambridge, MA, USA

E-mail: cmcbride@mit.edu; ddv@mit.edu

Abstract

The design of genetic circuits typically relies on characterization of constituent modules in isolation to predict the behavior of modules' composition. However, it has been shown that the behavior of a genetic module changes when other modules are in the cell due to competition for shared resources. In order to engineer multi-module circuits that behave as intended, it is thus necessary to predict changes in the behavior of a genetic module when other modules load cellular resources. Here, we introduce two characteristics of circuit modules: the demand for cellular resources and the sensitivity to resource loading. When both are known for every genetic module in a circuit, they can be used to predict any module's behavior upon addition of any other module to the cell. We develop an experimental approach to measure both characteristics for any circuit module using a resource sensor module. Using the measured resource demand and sensitivity for each module in a library, the outputs of the modules can be accurately predicted when they are inserted in the cell in arbitrary combinations. These resource competition characteristics may be used to inform the design of genetic circuits that perform as predicted despite resource competition.

Keywords

Resource Competition, Modular Composition, Experiment Design

1   Introduction

Genetic circuits are typically designed in a bottom-up fashion by combining previously characterized modules together to create new behaviors for particular applications (*1*). However, genetic modules often behave differently depending on the cellular context resulting in a lengthy design process and significant trial-and-error in designing genetic circuits (*2–4*). One major aspect of context dependence is resource competition between genetic circuit modules due to the fact that cellular resources such as RNAP and ribosomes are finite and shared among modules within a genetic circuit (*5–7*). It has previously been shown that resource competition between genes may result in more than a 60% decrease in expression levels (*6*), and that resource competition may cause significant changes in the qualitative behavior of genetic circuits (*7*). It has also been shown in (*8*) that using the gene expression levels of a module's output helps to improve the accuracy of mathematical models in two-node transcriptional cascades, which indicates that resource competition may play a significant role in these circuits. Resource competition has also been observed in cell-free systems (*9*), mammalian cells (*10*), and in computational models (*11–13*). Much work has gone into developing strategies to improve genetic circuits' robustness to changes in cellular resources (*14–20*). In these strategies, resource competition is assumed to be an unknown disturbance and a controller (feedback or feedforward) is implemented to decrease the effects of resource competition on the system. However, characterization of genetic circuits with resource competition for prediction has remained largely unexplored.

Consider a situation where multiple genetic circuit modules are initially characterized in isolation. When the modules are combined to form a multi-module system, each module behaves differently since the modules must compete for resources with every other module,

and, therefore, each module has access to a different amount of resources than when it was initially characterized. Therefore, to accurately design multi-module genetic circuits, the behavior of every module must be able to be predicted in the context of the final application despite resource competition effects. Additionally, it is highly desirable to characterize modules individually with a minimum number of experiments needed to characterize resource competition effects.

Here, we present an experimental method to estimate the effects of resource competition in genetic circuits that can be used to predict circuit behavior in new contexts. We first present the high-level method of estimating two key resource competition characteristics for a genetic circuit module of interest: resource demand and sensitivity. Using a mechanistic model of resource competition in genetic circuits (6, 7), we define these key characteristics of any genetic circuit module that characterize a module's demand for resources and sensitivity to changes in available resources. These characteristics can be used to predict a module's output with resource competition, which enables bottom-up design of genetic circuits. To experimentally measure the resource competition characteristics, we first characterize two resource sensors, which are then used to estimate the resource competition characteristics for any module of interest. Accordingly, we characterize the resource competition characteristics of a library of genetic circuit modules in *E. coli* and show that predictions using the resource competition characteristics quantitatively match measurements of genetic circuit outputs in new contexts.

2 Results

2.1 Using Resource Competition Properties to Predict Outputs

When genetic circuit modules are inserted into a cell, they use cellular resources for protein production and change the availability of cellular resources to other circuit modules in the cell. As shown in Figure 1a, the input-output response of a genetic circuit module of interest

may be characterized in isolation. When the module of interest is in the same cell as other (perturbing) modules, the modules compete for cellular resources and, therefore, the output of the module of interest cannot be accurately predicted based only on its behavior in isolation (6, 7).

In order to predict the effect of resource competition on genetic circuit modules, we demonstrate a method to estimate two key *resource competition characteristics* of a genetic circuit module, which may be used to predict changes in the module's input-output response due to resource competition in new situations.

For a module of interest M, the resource competition characteristics are the *resource demand* Q_{M}, ("quantity" of resources used by the module) and *resource sensitivity* (sensitivity of the module's output to resource loads), S_{M}. As shown in Figure 1b, the output of the module of interest is predicted by a function of the module's output when measured alone y_{M}, the module of interest's resource sensitivity S_{M}, and the resource demand of both the module of interest Q_{M} and of the other, perturbing modules in the cell Q_{P}. Thus, by estimating Q and S for all modules, the changes in module outputs due to resource competition effects can be predicted as explained next.

The resource competition characteristics Q_{M} and S_{M} are defined based on a previously proposed model describing resource competition in cells, which we recall here (6, 7). We consider the concentration of a protein y, which is considered as the output of a genetic circuit module of interest M where the circuit module's output is measured in the presence of another circuit module P. Based on this model, the ordinary differential equation (ODE) describing the output of the rate of change of y is given as

$$\frac{dy}{dt} = \frac{\alpha_y F_y(u_y)}{1 + \underbrace{\sum_{j \in \mathcal{M}} w_j F_j(u_j)}_{(a)} + \underbrace{\sum_{k \in \mathcal{P}} w_k F_k(u_k)}_{(b)}} - \gamma y, \tag{1}$$

where α_y represents the maximum production rate of y and is proportional to the total

Figure 1: **Overview of the resource competition characteristics for a module of interest.** **(a)** The input-output response of a genetic circuit module of interest is characterized in isolation within the cell. When a new module is added to the cell, this module perturbs the pool of available cellular resources. This results in an unpredictable change in the input-output response of the module of interest. **(b)** A resource sensor module enables the estimation of the resource competition characteristics Q_M (resource demand) and S_M (resource sensitivity) for a module of interest by measuring the input-output response of the module of interest with the resource sensor in the cell. **(c)** Knowledge of the resource competition characteristics Q_M and S_M and of the Q_P for a perturbing module enables the prediction of the module's input-output response in new contexts such as with the perturbing module.

cellular resources, the functions $F_i(u_i)$ represent the regulation function of the gene i by its input(s) u_i (e.g. Hill function (21)) and, for a single regulator is of the form $F_i(u_i) = \frac{1+a_y u_i^{n_i}}{1+b_i u_i^{n_i}}$ for some constants a_i, b_i, and n_i. This model can be derived by applying the conservation of gene expression resources in the process of protein production, and is derived in SI Section S1.1 as well as in (7). The quantity $w_j F_j(u_j)$ represents the resource demand of the individual gene j and is nondimensional (7) with w_j representing the resource demand coefficient of gene j and is a lumped parameter of biochemical binding constants that depends

on the promoter strength, ribosome binding site (RBS), and plasmid copy number. Further, γ represents the protein degradation and dilution rate, and $\mathcal{M}$ represents the set of genes in module M with y in $\mathcal{M}$, while $\mathcal{P}$ represents the set of genes in module P. Term (a) represents the resource demand of all the genes in module M and term (b) represents the resource demand of all genes in module P. This model assumes that total cellular resources are finite, constant, and independent of cell growth. More discussion on how these assumptions affect our experimental measurements is presented in Section 3.

Based on Eq. (1), the resource demand of the module of interest M, is defined as

$$Q_{\mathrm{M}} = \sum_{j \in \mathcal{M}} w_j F_j(u_j), \tag{2}$$

where $\mathcal{M}$ is all genes contained in the module of interest M. Note that the resource demand Q_{M} is the sum of the resource demands of all the constituent genes within the module.

The second resource competition characteristic is the sensitivity of the regulation function of the module's output, $F_y(u_y)$, to changes in cellular resources, which we call *resource sensitivity*, and is defined as

$$S_{\mathrm{M}} = \frac{dF_y(u_y)}{dQ_{\mathrm{P}}} \frac{1}{F_y(u_y)|_{Q_{\mathrm{P}}=0}}, \tag{3}$$

where Q_{P} is the resource demand of a module that is perturbing the resource pool, in other words, term (b) in Eq. (1). The resource sensitivity S_{M} determines how disturbances in the pool of cellular resources imparted by a perturbing module affect the regulation function of the module's output. In response to a resource perturbation, genes within the module of interest that regulate the module's output change, resulting in a change in the expression of the output of the module of interest.

As shown in Figure 1b, in order to estimate the resource demand Q_{M} and resource sensitivity S_{M} of a generic module, a special module called a *resource sensor* is used, where the resource demand Q_{RS} of the resource sensor was previously characterized. The output

of the module of interest in new situations when the resource pool is perturbed by other modules can be predicted using the estimated $\hat{Q}_{\mathrm{M}}$ and $\hat{S}_{\mathrm{M}}$ for all modules in the circuit, as shown in Figure 1c. Specifically, by combining the two resource competition characteristics Q_{M} and S_{M} based on their definitions, the output of a genetic circuit module can be predicted as other modules compete for resources through their own resource demand Q_{P} according to the equation

$$\hat{y}_{\mathrm{M}}^{p} \approx y_{\mathrm{M}} \left(1 + S_{\mathrm{M}} Q_{\mathrm{P}}\right) \frac{1 + Q_{\mathrm{M}}}{1 + Q_{\mathrm{M}} + Q_{\mathrm{P}}}, \tag{4}$$

where y_{M} is the output of the module of interest in isolation and $\hat{y}_{\mathrm{M}}^{p}$ is the predicted output of the module when perturbed due to the depletion of the resource pool by the presence of the module P. For the derivation of Eq. (4), see the SI Section S1.

2.2   Characterization of a Resource Sensor

To estimate the resource competition characteristics Q_{M} and S_{M} for a generic module M, a special module called a *resource sensor* must be first characterized, which will be used to probe modules of interest. The resource sensor module consists of a single constitutively expressed fluorescent protein. Since the resource sensor is a single constitutive gene, Q_{RS} fully characterizes the resource competition characteristics of the resource sensor.

The resource demand of the resource sensor can be estimated from a procedure of three experiments as shown in Figure 2a. First, the outputs of two resource sensor modules are each measured in isolation. Then, both resource sensor modules are placed in the same cell, where they compete for resources, and their outputs are measured together. By comparing the change in output of each sensor under the resource perturbation by the other sensor, the resource demand Q_{RS} for both resource sensors 1 and 2 (RS1 and RS2) can be found according to the Resource Sensor Demand Estimation equations in Figure 2a.

These equations were derived by expressing the output of each sensor using the model of Eq. (1) and using the fact that they are constitutive genes. See SI Section S1.4 for the

derivation of these equations. The system was set to its steady state, and solved for the resource demand characteristics Q_{RS1} and Q_{RS2} from the corresponding equations. Then, the estimators for the resource demand of the resource sensors are given by

$$\hat{Q}_{RS1} = \frac{1 - \frac{y_{RS2}^p}{y_{RS2}}}{\frac{y_{RS1}^p}{y_{RS1}} + \frac{y_{RS2}^p}{y_{RS2}} - 1} \tag{5a}$$

$$\hat{Q}_{RS2} = \frac{1 - \frac{y_{RS1}^p}{y_{RS1}}}{\frac{y_{RS1}^p}{y_{RS1}} + \frac{y_{RS2}^p}{y_{RS2}} - 1}, \tag{5b}$$

where y_{RS1} and y_{RS2} are the outputs of resource sensors 1 and 2 measured in isolation and y_{RS1}^p and y_{RS2}^p are the outputs of resource sensors 1 and 2 when they are measured together. In the experiments, the output fluorescent protein production rate per cell is used as the output of each module or resource sensor. The protein production rate is proportional to the steady state of the protein concentration per cell and independent of growth rate (see SI Section S1.2). For figures showing module and resource sensor outputs against time, see SI Section S5.3.

As in Figure 2b, the constitutive mTagBFP (BFP) gene with a weak ribosome binding site (RBS) was chosen as resource sensor 1, and a constitutive mRFP (RFP) gene with a strong RBS was chosen as resource sensor 2. The normalized output of resource sensors 1 and 2 are given in Figure 2c. These measurements are then used to calculate the resource demands Q_{RS1} and Q_{RS2} according to Eq. (5), with the resulting resource demands Q_{RS1} and Q_{RS2} for each resource sensor shown in Figure 2c. The resource demand of the RS2 is significantly larger than the resource demand of resource sensor 1 since resource sensor 2 causes a larger decrease in the output of resource sensor 1 than resource sensor 1 causes in resource sensor 2. Detailed plasmid maps of all resource sensor constructs are shown in the SI, Figure S11. For additional experimental details on the design of the resource sensor modules and specific considerations for controlling for transcriptional effects (*22*), see Methods Section 4.2.

Figure 2: **Experimental procedure to measure resource demand for a pair of resource sensors. (a)** The outputs of two resource sensors, y_{RS1} and y_{RS2} when each sensor's output is measured in isolation (Experiments 1 and 2) are compared to their respective outputs y_{RS1}^p and y_{RS1}^p when they are in the same cell together (Experiment 3). The superscript y^p represents the output of a sensor under a resource perturbation. **(b)** Genetic constructs used for implementing the resource sensors. See SI Section S4 for sequence details and Figures S11 for plasmid maps. The constitutive mTagBFP (BFP) gene with a weak RBS was chosen as resource sensor 1 (RS1), and a constitutive mRFP (RFP) gene with a strong RBS was chosen as resource sensor 2 (RS2). **(c)** From the measurements of the resource sensors outputs in isolation and together, the resource demands of both resource sensors are able to be estimated according to the Resource Sensor Demand Estimation Equations (Panel (a) or Eq. (5)). The fluorescent protein production rate per cell at steady state was used as the output of each resource sensor module. See Methods Section 4.4 for details on how production rate per cell was calculated. All measurements are the average of three technical replicates. Error bars represent one standard deviation from the mean and were propagated through relevant equations using the standard error. Measurements were made using a microplate reader, see Methods Section 4.1 and Section 4.3 for details on cellular growth conditions and measurement conditions.

2.3   Characterization of a Module

Using the estimated resource demand of the resource sensors $\hat{Q}_{RS}$, the resource competition characteristics Q_M and S_M of an arbitrary genetic module, M, may be estimated by following a similar set of experiments used to characterize the resource sensor. As shown in Figure 3a, the output of the module of interest is measured both with and without the presence of the

resource sensor and similarly, the output of the resource sensor is measured both with and without the module of interest. These four measurements along with the measured resource demand $\hat{Q}_{\text{RS}}$ of the resource sensor are used to estimate the module's resource competition characteristics $\hat{Q}_{\text{M}}$ and $\hat{S}_{\text{M}}$.

As with the resource sensors, the resource demand characteristic Q_{M} of a module represents the resource competition term in Eq. (1) for all genes associated with the particular module. The resource competition characteristics are estimated by expressing the module output in isolation (Experiment 1) and the output perturbed by the resource sensor (Experiment 2) according to the resource competition model, Eq. (1). Then, the resource demand $\hat{Q}_{\text{M}}$ and resource sensitivity $\hat{S}_{\text{M}}$ are solved for using an approximation for the derivative in the definition of S_{M}, Eq. (3). The formulas for estimating the resource demand $\hat{Q}_{\text{M}}$ and resource sensitivity $\hat{S}_{\text{M}}$ of a module of interest M are given as

$$\hat{Q}_{\text{M}} = \left(\frac{y_{\text{RS}}}{y_{\text{RS}}^p} - 1 \right) (1 + \hat{Q}_{\text{RS}}) \tag{6a}$$

$$\hat{S}_{\text{M}} = \frac{\left(1 - \frac{y_{\text{M}}}{y_{\text{M}}^p} \right) (1 + \hat{Q}_{\text{RS}}) + \hat{Q}_{\text{RS}} \frac{y_{\text{RS}}^p}{y_{\text{RS}}}}{\hat{Q}_{\text{RS}} \left(1 + \hat{Q}_{\text{RS}} \left(1 - \frac{y_{\text{RS}}^p}{y_{\text{RS}}} \right) \right)}, \tag{6b}$$

where y_{RS} is the output of the resource sensor measured in isolation, $\hat{Q}_{\text{RS}}$ is the estimate for the resource demand of the resource sensor, y_{RS}^p is the output of the resource sensor with the module of interest, y_{M} is the output of the module in isolation, and y_{M}^p is the output of the module when measured with the resource sensor. For the derivation of these formulas, see SI Section S1.5.

As shown in Figure 3b, four genetic circuit modules were characterized using both resource sensors. Each module consists of a constitutive gene with a fluorescent protein output, but could represent a more complex module in practice. The output of each module was measured both in isolation and with the resource sensors. Resource sensors 1 and 2 were used depending on whether the resource sensor's output is a different color from the module's

Figure 3: Caption on next page.

Figure 3: **Estimation of the resource characteristics $\hat{Q}_\mathrm{M}$ and $\hat{S}_\mathrm{M}$ of a genetic circuit module.** **(a)** Experiments to characterize the resource competition characteristics of the module of interest. The input-output responses of the resource sensor and of the module of interest are measured in isolation (Experiment 0 and 1). Then, the module is measured with the resource sensor (Experiment 2). **(b)** Genetic constructs for implementing the circuit modules. See SI Section S4 for sequence details and Figures S12 and S13 for plasmid maps. Module 1 consists of a constitutive mTagBFP (BFP) gene with a strong RBS, modules 2 and 3 consist of a constitutive GFPop1 (GFP) gene with a weak and strong RBS, respectively, and module 4 consists of a constitutive mRFP gene (RFP) with a weak RBS. The outputs of these modules were measured in isolation according to Experiment 1 and with resource sensors 1 and 2 according to Experiment 2, where the resource sensors were previously characterized resource demand as in Figure 2 with known $\hat{Q}_\mathrm{RS1}$ and $\hat{Q}_\mathrm{RS2}$. **(c)** Measurements of the outputs of the resource sensors and modules according to Experiments 0, 1, and 2. Measurements are normalized such that the output of the module in isolation is set to 1. Superscripts ^{pi} indicate that the measurement is the perturbed output by module or resource sensor i for resource sensors $i \in \{1, 2\}$ or modules $i \in \{1, 2, 3, 4\}$. The resource competition characteristics $\hat{Q}_\mathrm{M}$ and $\hat{S}_\mathrm{M}$ for each module are estimated according to the Module Resource Properties Estimation equations (Eq. (6)). The resource competition characteristics for module 1 was calculated using resource sensor 2 and the resource competition characteristics for module 4 were calculated using resource sensor 1. The resource demand and resource sensitivity for modules 2 and 3 are taken as the average of the respective resource demands and resource sensitivities found using both resource sensors 1 and 2. Non-averaged resource demands and sensitivities are shown in Figure S2. All measurements represent the average of three technical replicates. Error bars represent one standard deviation from the mean. Error estimates of $\hat{Q}_\mathrm{M}$ and $\hat{S}_\mathrm{M}$ were obtained by propagating error estimates through Eq. (6) using the standard error. Measurements were made using a microplate reader, see Methods Section 4.1 and Section 4.3 for details on cellular growth conditions and measurement conditions.

output. The outputs for each resource sensor alone and in the presence of the modules along with the outputs of the module alone and with the resource sensors are shown in Figure 3c. These data are then used to calculate the corresponding Q_M and S_M of the module of interest with the resource demand $\hat{Q}_{RS}$ for the corresponding resource sensor following the Module Resource Estimation equations. The estimated values of $\hat{Q}_M$ and $\hat{S}_M$ for each module are shown in Figure 3c. Due to the overlap of fluorescent proteins between the resource sensors and modules, the resource competition characteristics for module 1 was calculated using resource sensor 2 and the resource competition characteristics for module 4 were estimated using resource sensor 1. The resource demand and resource sensitivity for modules 2 and 3 are taken as the average of the resource competition characteristics estimated using resource sensor 1 and 2.

2.4   Prediction and Validation

Having estimated $\hat{Q}_M$ and $\hat{S}_M$ for each module, the module's input-output response in new contexts accounting for resource competition can now be predicted. To verify that the resource sensor measurements are accurate and provide good predictions, predictions of the module outputs are compared to measured outputs when pairs of modules are measured together in the cell. The four previously characterized modules were used, as shown in Figure 4a.

Each module was measured with every other module and resource sensor, resulting in a new cellular context due to the resource competition between the modules, as shown in Figure 4b. The output of each module when perturbed by another module was predicted using the estimated $\hat{Q}_M$ and $\hat{S}_M$ for each module along with its output in isolation y_M. The predicted output of a module under resource competition from another, perturbing module P is given as

$$\hat{y}_M^p \approx y_M \left(1 + \hat{S}_M \hat{Q}_P\right) \frac{1 + \hat{Q}_M}{1 + \hat{Q}_M + \hat{Q}_P}, \tag{7}$$

Figure 4: **Validation of the method by prediction of module outputs under resource loads. (a)** The four constitutive modules previously characterized in Figure 3 with known $\hat{Q}_M$ and $\hat{S}_M$ were used to validate the method. **(b)** Based on each module's output in isolation and the estimated resource competition characteristics $\hat{Q}_M$ and $\hat{S}_M$, the outputs of the modules when measured together are predicted using the Prediction of Module Outputs equations (Eq. (7)). The superscript ^{p} indicates that the output is perturbed and the $\hat{}$ indicates that it is an estimated (or predicted) quantity. Additionally, the outputs of the modules are measured when they are together in pairs to compare with the predictions. See SI Section S4 for sequence details and Figure S14 for plasmid maps. **(c)** Comparison of the measured outputs of modules 1, 2, 3, and 4 with the predicted outputs based on $\hat{Q}_M$ and $\hat{S}_M$ for each module when perturbed by another module or resource sensor. Measurement results are shown in darker colored bars and predictions shown with lighter colored bars. All measurements are the average of three technical replicates. Error bars represent one standard deviation from the mean. Error estimates of the predicted outputs were obtained by propagating the error estimates through Eq. (7) using the standard error. Measurements were made using a microplate reader, see Methods Sections 4.1 and 4.3 for details on cellular growth conditions and measurement conditions.

which is found by comparing the resource competition model, Eq. (1) with and without the perturbing module Q_{P} and combining with the definition of S_{M} (Eq. (3)). Further details can be found in the SI, Section S1.3. The measured outputs of the modules when measured with other modules were compared to the predictions using the resource competition characteristics of each module $\hat{Q}_{\mathrm{M}}$ and $\hat{S}_{\mathrm{M}}$, shown in Figure 4c. Most predictions are within one standard deviation from the measured value with the exceptions of modules 2 and 3 with resource sensor 2 and module 4 measured with module 1, where the predictions are within two standard deviations from the measured values. Therefore, the predicted outputs of the modules using the resource competition characteristics are able to accurately predict the outputs of the constitutive modules in new contexts arising from resource competition between modules. For a detailed discussion on potential sources of systemic error, see the Discussion, Section 3.

2.5   Application to Inducible Genetic Modules

To verify that the resource sensor method gives accurate predictions for more complex modules, the resource sensor method was applied to an inducible module. The resource sensor method for an inducible module is the same as that presented for the constitutive modules except that the resource competition characteristics Q_{M} and S_{M} must be estimated for each value of the input inducer concentration, u. We created module 5, consisting of an EYFP (YFP) gene and PhlF repressor, as shown in Figure 5a.

Using the resource sensor outputs and module outputs for each inducer concentration, as in Figure 5b, the module's resource demand $\hat{Q}_{\mathrm{M}}(u)$ and resource sensitivity $\hat{S}_{\mathrm{M}}(u)$ were estimated for each inducer concentration, giving maps of the module output $y_{\mathrm{M}}(u)$, the resource demand $Q_{\mathrm{M}}(u)$, and the resource sensitivity $S_{\mathrm{M}}(u)$ as functions of the inducer concentration u as shown in Figure 5b. The output maps of the module with resource competition can be predicted for each input using these maps, as shown in Figure 5c. All predictions are within 1.5 standard deviations to the corresponding measurements except

Figure 5: **Application to predict an inducible module's input-output response under resource loads.** **(a)** Module 5 consists of a PhlF repressor and EYFP fluorescent protein output. The inducer 2,4-Diacetylphloroglucinol (DAPG) is used to vary the level of repression of the pPhlF promoter regulating EYFP by PhlF. See SI Section S4 for sequence details and Figure S15 for plasmid maps. **(b)** The outputs of module 5 and resource sensors 1 and 2 were measured for each module in isolation and when module 5 was measured with resource sensors 1 and 2 for each inducer concentration 0 nM, 0.1 nM, 1 nM, and 10 nM. The resource competition characteristics of the module were estimated for each value of the input using the Module Resource Properties Estimation equations (Eq. (5)). The resource demand and resource sensitivity were calculated using both resource sensor 1 and 2 and the average of each was taken for each input concentration. Non-averaged resource demand and sensitivity are shown in Figure S2. **(c)** Prediction of the behavior of module 5 when measured in new contexts with other modules based on its output in isolation and $\hat{Q}_{\mathrm{M}}$ and $\hat{S}_{\mathrm{M}}$. Solid bars represent measured data and dashed bars represent predictions made using the resource sensor method. All measurements are the average of three technical replicates. Error bars represent one standard deviation from the mean and were propagated through relevant equations using the standard error. Measurements were made using a microplate reader, see Methods Sections 4.1 and 4.3 for details on cellular growth conditions and measurement conditions.

for the output of module 5 with module 4, where module 5's output is not predicted to significantly decrease under the perturbation, since $\hat{Q}_\mathrm{M}$ for module 4 is less than 0.1. This may be a result of transcriptional context effects.

3 Discussion

In this paper, the resource demand Q_M and sensitivity S_M were defined based on a mathematical model describing resource competition in genetic circuits. These quantities describe how modules behave in the presence of other modules that perturb the pool of cellular resources. Knowledge of Q_M and S_M for every module in a collection of modules enables the quantitative prediction of changes in module outputs due to resource competition between modules. Estimation of Q_M and S_M for a module of interest requires measuring the module of interest with a resource sensor module. This method was experimentally validated where predictions of module outputs using Q_M and S_M were compared with measurements of module outputs when pairs of modules were measured together, and predictions showed good agreement with measurements.

Here we discuss some considerations when implementing the method to measure Q_M and S_M for a module. The characteristics Q_M and S_M can predict large changes in module output due to resource competition effects, but care must be taken to detect or predict small changes in module behavior due to resource competition. The best resource sensors should have a large enough resource demand Q_RS to impose a measurable change in the output of the module of interest, but a small enough Q_RS to avoid creating a large stress response from the host cell. Based on our experimental results, it is recommended that the resource sensor demand Q_RS be between approximately 0.2 and 0.8. It should be noted that the resource competition characteristics are nondimensional quantities, so microplate readers do not need to use absolute units of fluorescence to obtain accurate estimates of the resource demand and resource sensitivity.

Differences in transcriptional context were controlled for by including all modules on the same plasmid and turning off modules by using a very weak RBS (TIR approximately 1.0) for the corresponding coding sequence. It was verified that no significant fluorescence was observed from modules when they were turned off through the use of a very weak RBS, as shown in SI Section S3.1, Figures S5-S10. Transcriptional resource competition may also be measured, although care needs to be taken to ensure effects such as terminator read-through between resource sensors and modules are not significant. Additionally, spatial transcriptional context effects such as super-coiling of DNA or transcriptional blocking of promoters by neighboring terminators may cause significant changes in circuit behavior (*22*), which are not accounted for in the estimation of Q_{M} and S_{M}, and can therefore disrupt the estimates. Therefore, care must be taken to control for transcriptional context effects when finding Q_{M} and S_{M} for a module of interest. This includes eliminating leaky termination between the resource sensor and module of interest as well as adding spacers separating terminators from the downstream promoter between the module of interest and the resource sensor. Failure to account for these effects may result in the estimation of unphysical resource competition characteristics.

One possible source of error in the validation of module 5 is the fact that transcriptional context was not held constant across all constructs in the same way as for the constitutive modules. Therefore, a possible reason for the difference between prediction and measurement when module 4 and 5 were measured together (Figure 5) is that the spacer between the terminator for module 4 and the promoter of module 5 was only 19 bp, while for the other modules, the spacer was larger than 55 bp (see SI Section S4 for details on the plasmid maps). This may have resulted in a change in the activity of the EYFP promoter due to transcriptional context differences such as supercoiling (*22*).

Theoretically, the estimated values of Q_{M} should be independent of the resource sensor used to perform the estimation; however, when the resource sensor has a large demand $\hat{Q}_{\mathrm{RS}}$, the estimated $\hat{Q}_{\mathrm{M}}$ of the module of interest was found to be larger than when measured using

a resource sensor with smaller $\hat{Q}_{RS}$, see SI, Figure S4. This is likely due to the regulation of the cellular resources or stress response by the host cell (*13*, *23*). The model on which the method is based assumes that cellular resources are constant. However, if the cell undergoes a stress response due to the presence of a genetic circuit module, the measurements of resource demand and sensitivity may not be accurate. This is one possible source of systemic error in the method and is especially likely to cause inaccuracies in the estimates for modules where the resource demand Q_M is large (greater than approximately 0.8).

For a constitutive module, no approximations were made in deriving the expressions for estimating $\hat{Q}_M$ and $\hat{S}_M$, but some approximations were necessary when the resource demand Q_M of a module of interest depends on unmeasured protein concentrations, such as in a more complex module (SI Section S1.5). This may explain why the predictions for the constitutive Modules 1-4 (Figure 4) were closer to the measurements than for the inducible module (Figure 5).

Growth rate is subject to change due to burden of the synthetic circuit on the host cell, which may cause additional unexpected changes in circuit behavior due to changes in dilution rate (*24–28*). In SI Section S2, we demonstrate that the cellular growth rate and the resource demand Q_M are closely related and show that estimation of the resource demand may be used to predict changes in growth rate due to metabolic burden on the host cell. This shows that the resource demand Q_M can be used to predict total cellular output and may be useful in metabolic engineering applications (*29–31*).

The resource competition characteristics may also be used to indicate whether resource competition effects can safely be ignored in genetic circuit design or need to be included for accurate circuit design. Note that the resource demand estimation only depends on the resource sensor measurement, so it can be estimated even for modules whose output is not measured. When the resource demands for all modules in a genetic circuit are small, e.g. $\hat{Q}_M < 0.2$, resource competition effects can safely be ignored as long as the number of modules is sufficiently small. When some module resource demands are moderate, e.g.

$0.2 \leq \hat{Q}_\mathrm{M} < 0.8$, resource competition should be accounted for to make accurate predictions of module outputs and overall system behavior. When any module resource demand is large, e.g. $\hat{Q}_\mathrm{M} \geq 0.8$, significant resource competition effects can be expected and the cellular growth rate will likely decrease due to the burden on the host cell. For an analysis of the experimental dependence of growth rate on the resource demand, see SI Section S2.

When designing genetic circuits, it should be noted that, in general, the output of a module with a large resource demand Q_M will change less in response to the same resource perturbation than a similar module with a smaller resource demand, as can be seen from Eq. (7). However, modules with large resource demand will cause other modules to experience more significant changes in their behavior due to resource competition. Additionally, unexpected changes in behavior may occur due to resource competition, such as a change in the number of equilibria of a system (*32*, *33*). The method assumes that disturbances due to resource competition are small enough such that these qualitative changes do not occur.

A simplified set of experiments may be used to estimate resource competition by using a constitutive fluorescent reporter gene integrated into the chromosome such as in (*24*) as the resource sensor. This modified procedure decreases the number of experiments necessary to perform from 2 experiments per module to 1 experiment per module, but also decreases the accuracy of predictions of module outputs. Here, we discuss how this modified procedure would work in practice. In this case, since the resource sensor is chromosomally integrated, it will impart a much smaller resource demand compared to genes on the plasmid, giving $Q_\mathrm{RS} \approx 0$. Then, the resource demand for a module of interest, Q_M, can be estimated by measuring the resource sensor output with and without the presence of the module of interest and using Eq. (6a) with $Q_\mathrm{RS} = 0$. In this setup, the sensitivity S_M will not be accurately estimated since the effect of the resource sensor is too small to significantly change the module's output. Assuming that each module behaves approximately like a constitutive gene, the sensitivity may be approximated as $S_\mathrm{M} = 0$. Then, the predicted module outputs with resource competition follow according to Eq. (7) with $\hat{S}_\mathrm{M} = 0$.

Other recent work has attempted to better characterize genetic circuits for improved predictions. In (34), the authors used RNA sequencing and ribosome profiling to characterize a single genetic circuit to inform a mathematical model for predicting its behavior; however, their model does not include resource competition between parts. Therefore, the estimates for promoter and ribosome binding strengths depend on the concentration of available RNAP and ribosomes and are subject to change when the availability of cellular resources changes.

Future work may address how changes in media or temperature changes the resource demand Q_{M} and sensitivity S_{M}, and some of the following applications. The resource competition characteristics Q_{M} and S_{M} may be applied to circuits with feedback or feedforward controllers implemented such as in (15, 16), so both improved robustness from the controller and improved prediction of module behavior can be obtained. Software that predicts the values of Q_{M} and S_{M} based on DNA sequences or the strength of promoters and ribosome binding sites may be designed as well. The values of Q_{M} and S_{M} may also be used to give conditions when it is advantageous to distribute genetic circuits across multiple cells within a consortium due to excessive burden on the host cell such as in (35). Additionally, an extension of Q_{M} and S_{M} to situations where there are multiple pools of resources such as transcriptional resources in mammalian cells (10) or synthetic orthogonal ribosomes as in (14) would be valuable. Finally, Q_{M} and S_{M} may be used to investigate more complex models for resource competition such as when the pool of resources is regulated by the host cell.

4   Methods

4.1   Strain and Growth Medium

The Top10 strain of bacterium *E. coli* was used to perform all experiments. M9610 supplemented media and was used to test the constitutive plasmids was made by modifying M9 supplemented media (15). The recipe for 5x M9610 salt stock is 33.36 mM $Na_2HPO_4 \cdot 7H_2O$,

220.40 mM of KH_2PO_4, 8.56 mM of NaCl, and 18.69 mM of NH_4Cl. The recipe for 50 mL of M9610 supplemented medium is 10 mL of 5x M9610 salt stock, 1 mL of 10% (w/v) casamino acid, 1 mL of 20% (w/v) glucose, 50 uL of 0.1 M $CaCl_2$, 100 uL of 1M $MgSO_4$, 333 uL of 50 g/L thiamine, 50 uL of 100x ampicillin, and the remainder of the 50 mL is sterile water.

4.2   Genetic Circuit Design and Construction

PCR, Gibson assembly and Golden Gate assembly were used to construct the plasmids. DNA fragments were amplified with PCR. Gibson assembly was performed using NEBuilder HiFi DNA Assembly Master Mix (NEB #E2621S) or Golden Gate master mix (NEB #E1601). Plasmids were incubated on ice for 30 min with competent cells which were prepared using CCMB80 buffer (TekNova, C3132) and were transformed by heat shocking competent cells at 42°C for 1 min. Plasmid DNA was prepared using the miniprep kit (Zymo Research, D4015), and sequencing was performed using the Quintarabio basic DNA sequencing service.

To control for transcriptional effects such as super-coiling (*22*, *36*), transcription read-through, or promoter blocking by nearby terminators, all constitutive plasmids contained the coding sequences for all of BFP, GFP, and RFP proteins. Gene translation was turned off for the unwanted coding sequences by using extremely weak (TIR < 1.0) ribosome binding site strength (RBS) for the constitutive module experiments. This was verified by fluorescence measurements for the relevant genes and were observed to have no significant fluorescence. Translation initiation rates (TIR) values for each module were calculated using the RBS calculator 2.0 (*37*). Multiple strong terminators at the end of each coding sequence were used to minimize transcriptional read-through and spacers were introduced between termina-tors and promoters to minimize DNA-context-related effects between modules and resource sensors (see plasmid maps in the SI, Section S4, Figures S11-S15). Since ribosomes are the limiting resource in bacteria (*6*, *11*, *38*), and all promoters used for the constitutive modules were strong and of similar strength, varying the strength of the RBS gives a good estimation of the different resource competition effects between the modules. The strong

constitutive promoters J23100, J23119, and J23104 were used for the constitutive modules and resource sensors to ensure resource competition effects would be significant enough to be easily measurable.

For the inducible EYFP module (module 5) experiments, only the coding sequence for the resource sensor/perturbing module of interest was included in the plasmids. It was found that there were only minor differences between the output of the module without a coding sequence of a fluorescent protein and one with the coding sequence of a fluorescent protein but a very weak RBS due to transcriptional context effects. The module 5 was taken from the pAJM.847 plasmid in (*39*) (Addgene #108524, additional details in the SI of (*39*), page 42). The molecule 2,4-diacetylphloroglucinol (DAPG) was used as the inducer for module 5.

Controlling for transcriptional context does not appear to be necessary in applications since module 5 predictions were still good even though the resource sensor or module on the plasmid with module 5 was different for different experiments. It is necessary to use multiple strong terminators to eliminate transcriptional read-through between the module and resource sensor and to use a long enough spacer (at least approximately 40 bp) between the resource sensor and the module of interest to ensure that terminators do not block nearby promoter activity.

4.3   Plate Reader

Cells with the relevant plasmids were streaked on LB agar plates with carbenicillin and grown in an incubator at $37°C$ for 20-24 hrs. Cells were then picked and inoculated into $800\,\mu L$ of M9610 liquid media with ampicillin in a loose cap culture tube (VWR, 13 mL culture tube, cat #60818-667) and grown in an air shaker (New Brunswick Scientific Excella E24 M1352-0000) at $30°C$ with at 200 rpm for 7-9 hrs. Cells were then inoculated into a 96-well plate (Falcon #351172) and diluted to an initial optical density at 600 nm (OD_{600}) reading of approximately 0.02 in $200\,\mu L$ of M9610 liquid media. Cells were grown in a plate reader (Synergy MX, Biotek, Winooski, VT) at $30°C$ for 10 hrs with measurements every 5 mins.

The plate was shaken for 3 sec before OD_{600} and fluorescence measurements. Excitation (EX) and emission (EM) wavelengths for the plate reader were chosen to maximize difference between the different fluorescence channels while keeping a strong signal. The plate reader settings for each measurement are as follows. OD_{600} channel settings: absorbance at 600 nm; BFP channel settings: EX = 400 nm (bandwidth = 9 nm), EM = 460 nm (bandwidth = 9 nm), Sensitivity = 80; GFP channel settings: EX 485 nm (bandwidth = 9 nm), EM 513 nm (bandwidth = 9 nm), Sensitivity = 90; RFP channel settings: EX 584 nm (bandwidth = 9 nm), EM 619 nm (bandwidth = 13.5 nm), Sensitivity = 100; YFP channel settings: EX 520 nm (bandwidth = 9 nm), EM 545 nm (bandwidth = 13.5 nm), Sensitivity = 100. At least three wells filled with 200 uL M9610 liquid media were used to subtract background OD_{600} and fluorescence measurements. All experimental measurements consisted of three technical replicates. Measurements of the cells in the 96-well plate were spatially separated with at least one empty well between active wells to reduce cross-talk between neighboring wells (*40*).

4.4 Data Analysis

The protein production rate was used as the output of each circuit module, since it is independent of growth rate, see SI Section S1.2 for theoretical justification or (*24*). The protein production rate of a protein X per cell is given as

$$\frac{1}{OD}\frac{dX}{dt} \qquad (8)$$

where OD is the optical density of the cells. Fluorescence measurements were taken every 5 minutes using the microplate reader. The numerical time derivative $\frac{dX}{dt}$ was found after subtracting background fluorescence and absorbance by using a 5-pt centered Savitzky-Golay filtered first derivative and then applying a (zero-phase) moving average filter with window size of 9 points. The steady state production rate was selected for each construct as a time

window of at least 2 hours when the cells were in exponential phase where the protein production rate per cell was approximately constant and the fluorescent protein measurements were above the lower detection limit of the plate reader. This usually occurred between approximately 2 and 6 hours after the start of the experiment. Module output was calculated as the average production rate over the time window for each technical replicate and then averaged across all three replicates. Error bars on the module's output represent one standard deviation in the difference of the means across the three replicates. Error estimates were propagated through all equations using the standard error estimates. Growth rate for each construct was determined using a robust nonlinear least squares logistic curve fit, utilizing the Levenberg-Marquardt algorithm. All computations were completed using custom scripts written in MATLAB R2020a, which are available in the Supporting Information. Corrections for fluorescence scattering due to cells and bleed-through across fluorescence channels were corrected for based off the raw fluorescence measurements. Graphs of fluorescent protein production rate against time are available in the SI, Figures S25-S34.

4.5   Fluorescence Scattering Correction

As the optical density cells of the well change, the background fluorescence readings also change due to light scattering. To correct for this phenomena, correlations were measured for determining the relationship between background fluorescence measurements and OD_{600}. Linear regression was applied between OD_{600} and the relevant raw fluorescence measurements for cells not expressing the relevant proteins. The correlation between BFP fluorescence and OD_{600} was $C_{OD,B} = -2385 BFP/OD(a.u.)$, and the correlation between GFP fluorescence and OD_{600} was $C_{OD,G} = 1300 GFP/OD(a.u.)$. These correlations are negligible for YFP and RFP measurement channels. Each was subtracted off of BFP and GFP fluorescence signals according to the equations $B_{new} = B_{raw} - C_{OD,B}OD$ and $G_{new} = G_{raw} - C_{OD,G}OD$. The magnitude of this correction is less than 10% of the signal. Data used to estimate this effect and find correlations is shown in the SI, Figure S20.

Multiple scattering effects within the microplate reader become significant at larger optical densities (*41*, *42*), so steady state data was selected for OD_{600} lower than this value before protein production rate was observed to drop, which normally occurred below $OD_{600} < 0.05$.

4.6 Bleed-Through Correction

Correction for fluorescence bleed between channels using linear unmixing (*43*) is applied to each fluorescence channel. The correlation between fluorescence intensities was found by applying linear regression between pairs of fluorescent measurement channels for a cell expressing only one protein to find the correction (correlation) matrix. Then, the measured fluorescent values may be expressed as a linear combinations of the true fluorescence values given by

$$F_{measured} = CF_{true} \tag{9}$$

where C is the correlation matrix, which can be found by applying linear regression between measurement channels when only one type of fluorescent protein is expressed (I can't find this treatment in the plate reader literature, only in the microscopy literature), and $F_{measured}$ is the observed fluorescence intensity for each channel with cross-talk and F_{true} is the actual fluorescence intensity. For our data, the correlation matrix is

$$C = \begin{bmatrix} 1. & 0.0024 & 0.0110 & 0.0157 \\ 0.0011 & 1. & 0.0076 & 0.1053 \\ 0.0011 & 0.0003 & 1. & 0.0011 \\ -0.0005 & 0.2547 & -0.0004 & 1. \end{bmatrix} \tag{10}$$

where first column encodes the correlation of the readings of the channels BFP, GFP, RFP, and YFP, respectively, when only mTagBFP2 is expressed and the correlation was found using linear regression. A similar procedure is used to populate the 2nd (GFP), 3rd (RFP), and 4th (YFP) columns with their respective proteins. Plots of pairs of fluorescence mea-

surements against each other for purely expressed BFP, GFP, RFP, and YFP are given in the SI, Figures S6-S19. Entries in C less than 0.01 are set to 0. Note that the is no significant fluorescence bleed between channels except for between the YFP and GFP channels. The compensated fluorescence measurements are given as

$$F_{compensated} = C^{-1} F_{measured} \tag{11}$$

where $F_{measured}$ is a column vector containing the fluorescent channels in the order BFP, GFP, RFP, and YFP. Eq. (11) is applied for each well at each time-step.

Acknowledgement

The authors thank Yili Qian for helpful discussions and Hsin-Ho Huang for help proofreading the manuscript. We also thank Massimo Bellato for his contributions to earlier versions of the constructs. This work was supported by NSF Expeditions in Computing Award #1521925.

Author Contributions

All authors designed experiments and interpreted the data; CM preformed the research, cloned constructs, performed experiments, developed the mathematical models, wrote the paper; DDV designed the research and edited the paper.

Conflicts of Interest

The authors declare no conflicts of interest.

Supporting Information Available

The following files are freely available.

- Filename: Supporting Information

- Filename: MATLAB code and and experimental data zip folder

References

1. Purnick, P. E. M., and Weiss, R. (2009) The second wave of synthetic biology: from modules to systems. *Nature Reviews Molecular Cell Biology 10*, 410–422.

2. Cardinale, S., and Arkin, A. P. (2012) Contextualizing context for synthetic biology– identifying causes of failure of synthetic biological systems. *Biotechnology Journal 7*, 856–866.

3. Brophy, J. A., and Voigt, C. A. (2014) Principles of Genetic Circuit Design. *Nature methods 11*, 508–520.

4. Del Vecchio, D. (2015) Modularity, context-dependence, and insulation in engineered biological circuits. *Trends in Biotechnology 33*, 111–119.

5. Vind, J., Sørensen, M. A., Rasmussen, M. D., and Pedersen, S. (1993) Synthesis of Proteins in Escherichia coli is Limited by the Concentration of Free Ribosomes: Expression from Reporter Genes does not always Reflect Functional mRNA Levels. *Journal of Molecular Biology 231*, 678–688.

6. Gyorgy, A., Jiménez, J., Yazbek, J., Huang, H.-H., Chung, H., Weiss, R., and Del Vecchio, D. (2015) Isocost Lines Describe the Cellular Economy of Genetic Circuits. *Biophysical Journal 109*, 639–646.

7. Qian, Y., Huang, H.-H., Jiménez, J. I., and Del Vecchio, D. (2017) Resource Competition Shapes the Response of Genetic Circuits. *ACS Synthetic Biology 6*, 1263–1272.

8. Gómez-Schiavon, M., Dods, G., El-Samad, H., and Ng, A. H. (2020) Multidimensional Characterization of Parts Enhances Modeling Accuracy in Genetic Circuits. *ACS Synthetic Biology*

9. Borkowski, O., Bricio, C., Murgiano, M., Rothschild-Mancinelli, B., Stan, G.-B., and Ellis, T. (2018) Cell-free prediction of protein expression costs for growing cells. *Nature Communications 9*, 1457.

10. Frei, T., Cella, F., Tedeschi, F., Gutiérrez, J., Stan, G.-B., Khammash, M., and Siciliano, V. (2020) Characterization and mitigation of gene expression burden in mammalian cells. *Nature Communications 11*, 4641.

11. Gorochowski, T. E., Avcilar-Kucukgoze, I., Bovenberg, R. A. L., Roubos, J. A., and Ignatova, Z. (2016) A Minimal Model of Ribosome Allocation Dynamics Captures Trade-offs in Expression between Endogenous and Synthetic Genes. *ACS Synthetic Biology 5*, 710–720.

12. Sabi, R., and Tuller, T. (2019) Modelling and measuring intracellular competition for finite resources during gene expression. *Journal of The Royal Society Interface 16*, 20180887.

13. Weiße, A. Y., Oyarzún, D. A., Danos, V., and Swain, P. S. (2015) Mechanistic links between cellular trade-offs, gene expression, and growth. *Proceedings of the National Academy of Sciences of the United States of America 112*, E1038–E1047.

14. Darlington, A. P. S., Kim, J., Jiménez, J. I., and Bates, D. G. (2018) Dynamic allocation of orthogonal ribosomes facilitates uncoupling of co-expressed genes. *Nature Communications 9*, 695.

15. Huang, H.-H., Qian, Y., and Vecchio, D. D. (2018) A quasi-integral controller for adaptation of genetic modules to variable ribosome demand. *Nature Communications 9*, 5415.

16. Jones, R. D., Qian, Y., Siciliano, V., DiAndreth, B., Huh, J., Weiss, R., and Del Vecchio, D. (2020) An endoribonuclease-based feedforward controller for decoupling resource-limited genetic modules in mammalian cells. *Nature Communications 11*, 5690.

17. Aoki, S. K., Lillacci, G., Gupta, A., Baumschlager, A., Schweingruber, D., and Khammash, M. (2019) A universal biomolecular integral feedback controller for robust perfect adaptation. *Nature 570*, 533–537.

18. Lillacci, G., Benenson, Y., and Khammash, M. (2018) Synthetic control systems for high performance gene expression in mammalian cells. *Nucleic Acids Research 46*, 9855–9863.

19. Aleksashin, N. A., Szal, T., d'Aquino, A. E., Jewett, M. C., Vázquez-Laslop, N., and Mankin, A. S. (2020) A fully orthogonal system for protein synthesis in bacterial cells. *Nature Communications 11*, 1858.

20. Venturelli, O. S., Tei, M., Bauer, S., Chan, L. J. G., Petzold, C. J., and Arkin, A. P. (2017) Programming mRNA decay to modulate synthetic circuit resource allocation. *Nature Communications 8*, 15128.

21. Hill, A. (1910) The possible effects of the aggregation of the molecules of haemoglobin on its dissociation curves. *The Journal of Physiology 40*, iv–vii.

22. Yeung, E., Dy, A. J., Martin, K. B., Ng, A. H., Del Vecchio, D., Beck, J. L., Collins, J. J., and Murray, R. M. (2017) Biophysical Constraints Arising from Compositional Context in Synthetic Gene Networks. *Cell Systems 5*, 11–24.e12.

23. Ceroni, F., Boo, A., Furini, S., Gorochowski, T. E., Borkowski, O., Ladak, Y. N., Awan, A. R., Gilbert, C., Stan, G.-B., and Ellis, T. (2018) Burden-driven feedback control of gene expression. *Nature Methods 15*, 387–393.

24. Ceroni, F., Algar, R., Stan, G.-B., and Ellis, T. (2015) Quantifying cellular capacity identifies gene expression designs with reduced burden. *Nature Methods 12*, 415.

25. Dai, X., Zhu, M., Warren, M., Balakrishnan, R., Patsalo, V., Okano, H., Williamson, J. R., Fredrick, K., Wang, Y.-P., and Hwa, T. (2016) Reduction of translating ribosomes enables Escherichia coli to maintain elongation rates during slow growth. *Nature microbiology 2*, 16231.

26. Klumpp, S. (2011) Growth-Rate Dependence Reveals Design Principles of Plasmid Copy Number Control. *PLOS ONE 6*, e20403.

27. Bienick, M. S., Young, K. W., Klesmith, J. R., Detwiler, E. E., Tomek, K. J., and Whitehead, T. A. (2014) The Interrelationship between Promoter Strength, Gene Expression, and Growth Rate. *PLoS ONE 9*.

28. Hintsche, M., and Klumpp, S. (2013) Dilution and the theoretical description of growth-rate dependent gene expression. *Journal of Biological Engineering 7*, 22.

29. Ceroni, F., Blount, B. A., and Ellis, T. (2016) Sensing the Right Time to Be Productive. *Cell Systems 3*, 116–117.

30. Doong, S. J., Gupta, A., and Prather, K. L. J. (2018) Layered dynamic regulation for improving metabolic pathway productivity in Escherichia coli. *Proceedings of the National Academy of Sciences 115*, 2964–2969.

31. Jagadevan, S., Banerjee, A., Banerjee, C., Guria, C., Tiwari, R., Baweja, M., and Shukla, P. (2018) Recent developments in synthetic biology and metabolic engineering in microalgae towards biofuel production. *Biotechnology for Biofuels 11*, 185.

32. Zhang, R., Goetz, H., Melendez-Alvarez, J., Li, J., Ding, T., Wang, X., and Tian, X.-J. (2021) Winner-takes-all resource competition redirects cascading cell fate transitions. *Nature Communications 12*, 853.

33. McBride, C., and Del Vecchio, D. (2020) The number of equilibrium points of perturbed nonlinear positive dynamical systems. *Automatica 112*, 108732.

34. Espah Borujeni, A., Zhang, J., Doosthosseini, H., Nielsen, A. A. K., and Voigt, C. A. (2020) Genetic circuit characterization by inferring RNA polymerase movement and ribosome usage. *Nature Communications 11*, 5001.

35. McCarty, N. S., and Ledesma-Amaro, R. (2019) Synthetic Biology Tools to Engineer Microbial Communities for Biotechnology. *Trends in Biotechnology 37*, 181–197.

36. Hatfield, G. W., and Benham, C. J. (2002) DNA Topology-Mediated Control of Global Gene Expression in Escherichia coli. *Annual Review of Genetics 36*, 175–203.

37. Salis, H. M., Mirsky, E. A., and Voigt, C. A. (2009) Automated design of synthetic ribosome binding sites to control protein expression. *Nature Biotechnology 27*, 946–950.

38. Jens, M., and Rajewsky, N. (2015) Competition between target sites of regulators shapes post-transcriptional gene regulation. *Nature Reviews Genetics 16*, 113–126.

39. Meyer, A. J., Segall-Shapiro, T. H., Glassey, E., Zhang, J., and Voigt, C. A. (2019) Escherichia coli "Marionette" strains with 12 highly optimized small-molecule sensors. *Nature Chemical Biology 15*, 196–204.

40. Mauri, M., Vecchione, S., and Fritz, G. (2019) Deconvolution of Luminescence Cross-Talk in High-Throughput Gene Expression Profiling. *ACS Synthetic Biology 8*, 1361–1370.

41. Stevenson, K., McVey, A. F., Clark, I. B. N., Swain, P. S., and Pilizota, T. (2016) General calibration of microbial growth in microplate readers. *Scientific Reports 6*, 38828.

42. Krishnamurthi, V. R., Niyonshuti, I. I., Chen, J., and Wang, Y. (2021) A new analysis method for evaluating bacterial growth with microplate readers. *PLoS ONE 16*.

43. Garini, Y., Young, I. T., and McNamara, G. (2006) Spectral imaging: Principles and applications. *Cytometry Part A 69A*, 735–747.

TOC Graphic