Behaviourally modulated hippocampal theta oscillations in the ferret persist during

both locomotion and immobility

Dunn S.L.S.[1,2], Town S.M.[1], Bizley J.K.[1]*, Bendor D.[2]*

* equal senior author contribution

1. Ear Institute, University College London

2. Institute of Behavioural Neuroscience, University College London

Abstract

Theta oscillations are a hallmark of hippocampal activity across mammals and play a critical

role in many hippocampal models of memory and spatial navigation. To reconcile the cross-

species differences observed in the presence and properties of theta, we recorded

hippocampal local field potentials in rats and ferrets during auditory and visual localisation

tasks designed to vary locomotion and sensory attention. Here, we show that theta oscillations

occur during locomotion in both ferrets and rats, however during periods of immobility, theta

oscillations persisted in the ferret, contrasting starkly with the switch to large irregular activity

(LIA) in the rat. Theta during immobility in the ferret was identified as Type 2 theta due to its

sensitivity to atropine, and was modulated by behavioural state, with the strongest theta

observed during reward epochs. These results demonstrate that even under similar

behavioural conditions, differences exist between species in the relationship between theta

and behavioural state.

Introduction

The hippocampal formation plays a central role in creating a cognitive map, critical for both memory and navigation. Studies in rodents, including the discovery of place[1], grid[2], and head direction[3] cells, have laid the foundation for our understanding of the neural basis of these functions. Hippocampal neurons operate within a framework of several types of oscillatory rhythms, the most dominant being the theta oscillation[4–7] - a rhythmic disinhibition of the network that is observed as a 5-12 Hz sawtooth wave in the local field potential (LFP). Disruption of theta in rodents has been shown to impair memory and navigation[8–11], and artificially restoring theta-like rhythmic activity can partially recover these functions[12]. Theta oscillations are believed to play an important role in organisation of hippocampal activity[13–16] and coordination between hippocampus and cortex[17–19], and are important features of many models of hippocampal function[20–22].

In rats, two types of theta oscillations have been described, each with distinct behavioural correlates and pharmacology[23,24]. Type 1 theta is observed continuously during active locomotor behaviours[25] and is resistant to anticholinergic drugs such as atropine[24,26]. The properties of Type 1 theta and its interactions with neuronal spiking and higher frequency LFP oscillations are well characterized in the rat[27–32]. Type 2 theta is rare in the awake rat, sensitive to anticholinergic drugs[24,26,33], and occurs in short bouts during immobility, typically at a lower frequency (4-7 Hz) than Type 1 theta[23–25,34]. Whereas Type 1 theta has been closely linked to spatial and mnemonic functions of the hippocampus, Type 2 theta has typically been elicited by noxious stimuli[34–37] while also being associated with several cognitive processes including arousal/attention[34], sensorimotor integration[38], and emotional processing[39.].

Intracranial EEG in epilepsy patients have recently allowed insights into neural activity in the human hippocampus, and comparison across species. These data indicate that the properties of human theta oscillations differ from those observed in the rat: Human theta does not appear continuously during locomotion, but rather in transient bursts[40,41]. The frequency of human theta has been reported be lower (1-5 Hz) than in rats[40,42–44] or with functionally distinct low and high frequency components (~3 Hz and ~8 Hz)[45].

Short bouts of theta activity, like that seen in the human hippocampus, have been described

in the bat[46–48] and other non-human primates[49–51]. In some of these studies, the occurrence of

hippocampal theta oscillations was linked to active sensation: in the primate, theta was phase

locked to saccades[50]; in the bat, it was found to co-occur with bouts of echolocation[46]. Whether

these oscillatory bouts correspond to Type 1 or Type 2 theta has not yet been determined,

however they *do not* appear to be directly linked to locomotion. It is worth noting that while

bats and primates rely on distal senses (e.g. vision and audition), rodents instead rely mainly

on proximal senses (whisking and sniffing). Because rodents whisk and sniff continuously at

a theta rhythm during locomotion, it is challenging to dissociate whether theta is truly linked to

locomotion or to active sensation. There is thus value in studying theta in other species with

comparable locomotory behaviour to rodents, but who's sensory strategies rely on distal

senses more akin to those used by primates.

To investigate the relationship between hippocampal theta, locomotion, and sensory strategy,

we studied the hippocampus of the ferret (*Mustela putorios furo*), a predator of the order

Carnivora, which has a comparable locomotory behaviour to rodents, but who rely more

heavily on both vision and hearing than rats. Ferrets have approximately twice the visual acuity

of rats[52,53] and more developed binocular vision, including the presence of ocular dominance

columns in visual cortex[54,55] and saccadic activity[56]. Ferrets, who have excellent low frequency

hearing, also show superior sound localisation abilities to rodents, particularly when locating

distant sound sources[57,58].

We recorded the hippocampal LFP from ferrets while they performed a behavioural task

designed to independently manipulate locomotion and sensory attention. Parallel experiments

were performed in rats to directly compare theta activity under similar conditions. With this

behavioural task, we sought to determine whether theta oscillations are present during

locomotion in ferrets, and if they share similar locomotor-related modulations with rat theta.

Furthermore, we investigated the effect of changing sensory attentional load on the

hippocampal LFP, which could potentially be influenced by a species' dominant mode of

sensation (e.g. whisking vs. hearing).

Results

LFP recording during behaviour in rats and ferrets

To investigate the prevalence of hippocampal theta across species, we recorded hippocampal

neural activity from three rats (R1, R2, R3) and three ferrets (F1, F2, F3) while they performed

an approach-to-target localisation task designed to vary locomotion and sensory attentional

load (Fig. 1). Rats performed a two-choice task with two peripheral stimuli locations (approx.

-60° and 60°; Fig. 1a) while ferrets performed a 5-choice task with stimuli presented at 30°

intervals (Fig. 1c). The task structure was identical across species (Fig. 1b); animals initiated

a trial by holding a nose-poke at the centre of the arena for a pseudorandom time between

2.5 and 3.5 seconds. Once triggered, an auditory (A; broadband noise burst) or visual stimulus

(V; white LED flash) was presented in a noisy background at the periphery of the arena.

Individual testing sessions contained only auditory or visual trials. To receive reward, animals

were required to approach the location at which the stimulus was presented.

All animals performed above chance for both stimulus modalities (rats Fig. 1d; proportion

correct, mean ± standard deviation (S.D.) across sessions A: R1 0.87 ± 0.08, R3 0.90 ± 0.08;

R2 was not tested with auditory stimuli, see Methods; V: R1 0.94 ± 0.03, R2 0.84 ± 0.09, R3

0.99 ± 0.01; ferrets Fig. 1g; A: F1 0.79 ± 0.15, F2 0.70 ± 0.26, F2 0.83 ± 0.16; V: F1 0.74 ±

0.09, F2 0.72 ± 0.10, F3 0.81 ± 0.09). Both rats and ferrets moved at similar speeds while

performing the behavioural task (rats Fig. 1e,f; mean session speeds ± S.D. excluding speeds

< 10 cms^{-1} R1 26.6 ± 1.4 cms^{-1}, R2 32.0 ± 2.1 cms^{-1}, R3 31.3 ± 1.6 cms^{-1}; ferrets Fig 1h,i; F1

29.4 ± 1.3 cms^{-1}, F2 28.0 ± 1.2 cms^{-1}, 31.7 ± 2.3 cms^{-1}).

During performance of the behavioural task, we recorded the local field potential (LFP) from

the dorsal hippocampus of rats and the homologous septal pole of the ferret hippocampus

using 32 channel linear probes (Neuronexus). The distinct laminar structure of the

hippocampal formation is conserved in the ferret (Fig. 2a,b) and 3D models of gross

Figure 1: Localisation behaviour in rats and ferrets.
a-c, Schematics of the behavioural tasks. **a**, Behavioural arena used with rats showing the two peripheral target locations, with the animal holding at the centre initiation spout. **b**, Time-course of the behavioural trial for both the rat and the ferret. **c**, Behavioural arena used with ferrets showing the five peripheral target locations, with the animal holding at the centre initiation spout. **d-f**, Summary of rat behavioural performance. **d**, Proportion of correct trials for and visual sessions for each rat. Each marker represents one session, shown with the mean and standard deviation across sessions. Grey dashed line represents performance at chance level (1/2). **e**, Cumulative speed distribution across sessions for each rat. The mean and standard deviation of the session speed distributions are shown as line and shaded area. **f**, Mean session speed of 'moving' data (defined as speeds > 10 cms^{-1}) for each rat. Each marker represents one session, shown with the mean and standard deviation across sessions. **g-i**, as in **d-f** but for ferret data (chance level: 1/5).

hippocampal anatomy were generated to target electrode implantations (Extended Data Fig. 1,3). We implanted electrodes in the rat in the right hemisphere only (Fig 2c; Extended Data Fig. 2), while ferrets received bilateral electrode implants (Fig 2d, Extended Data Fig. 3). Most probes entered the hippocampal formation directly (R1, R2, F1$_L$, F3$_L$, F3$_R$), crossing the pyramidal cell layer. The remaining implants (R3, F1$_R$, F2$_L$) did not cross the pyramidal cell layer, however hippocampal LFP oscillations were still detected on all channels (Extended Data Fig. 2,3). Typical examples of the data obtained during a single behavioural trial are shown in Figure 2e for one rat (R2) and Figure 2f for one ferret (F3$_R$).

Rat-like theta oscillations during locomotion in the ferret hippocampus at 4-7Hz

We first sought to determine whether the ferret hippocampus showed rat-like theta oscillations during locomotion. Theta oscillations in the rat have two important hallmarks: (1) distinct anatomical profiles in which theta power increases and theta phase shifts while travelling through the hippocampal cell layer[5,26], and (2) strong correlations of frequency and power with speed/acceleration[59–61]. We initially characterised these properties in the rat (Fig. 3 a-f, Extended Data Fig. 4a,b) to obtain baseline measurements from which to compare across species. Theta oscillations were evident in rats as a prominent peak between 6-13 Hz in the power spectral density (PSD) of the LFP during locomotion (speed > 10 cms^{-1}; Fig. 3a). We used a peak-trough detection method that operated on the theta-filtered trace (4-14 Hz) to estimate the instantaneous amplitude, power, phase, and frequency of theta (Fig. 3b). Using these metrics, we quantified the speed-theta relationships: we observed a strong positive correlation between speed and theta frequency (Fig. 2c; $\beta_1 = 2.9 \times 10^{-2}$, $p = 4.1 \times 10^{-4}$, $R^2 = 0.96$) and a negative correlation between speed and theta power (Fig. 3d; $\beta_1 = -1.9 \times 10^{-2}$, $p = 6.3 \times 10^{-3}$, $R^2 = 0.68$) for the example channel with the highest overall LFP power along the probe. We estimated these parameters across every channel of the probe to obtain the theta depth profile (Fig. 3e,f). As expected, theta power increased across the hippocampal cell layer, and this increase was accompanied by shifts in theta phase. Locomotion speed and theta frequency were highly positively correlated along all channels. Speed and power were

Figure 2: Hippocampal formation and electrode position across species.
a-b, Nissl-stained coronal sections from rat (**a,** -3.12 relative to Bregma) and ferret (**b,** -14.4 mm relative to occipital crest) brain. Insets show magnified images of the dorsal pole of the hippocampal formation (CA: cornu ammonis, DG: dentate gyrus, S: subiculum). **c-d,** Single trial examples of behavioural and neural data recorded from one rat (**c**) and one ferret (**d**). *Top left:* Head position tracking of a single recording session (grey line) with a single trial highlighted in colour and coded by time. *Top right:* The speed of the highlighted trial, coloured with the same scale. Shaded area indicates stimulus activation. *Bottom left:* Nissl-stained section of the hippocampus showing the estimated position of electrode recording sites (grey bar). *Bottom right:* Corresponding LFP traces for the example trial for each channel on the probe (n = 32 channels, 100 μm spacing). **e-f,** Estimated electrode implant locations for each rat (**e**) and ferret (**f**). Brain section outlines were generated from the Allen Rat Brain Atlas[90] and the Ferret Brain Atlas[62]. Left (L) and right (R) hemispheres are indicated for each section. The left section is most anterior; the anterior-posterior position of the section is given in millimetres relative to bregma (rat) or the occipital crest (ferret).

positively correlated along the probe, except in the region of highest theta power (Fig. 3f;

Extended Data Fig. 4 for data across all sessions/rats).

In ferrets, a prominent low-frequency peak (4-7 Hz) was evident in PSDs of the LFP during

locomotion (Fig. 3g). We therefore filtered the ferret LFP between 2-8 Hz and used the same

peak-trough approach to estimate the instantaneous amplitude, power, phase, and frequency

of this oscillation (Fig. 3h) and quantified its relationship with speed (Fig. 3i,j). Across the

hippocampus, we found similar depth profiles to those observed in the rat, with increases in

power and shifts in phase through the cell layer (Fig. 3k,l). The patterns of speed-frequency

and speed-power relationships were also like those observed in the rat. Thus, we concluded

that this low-frequency oscillation in the ferret was equivalent to rodent hippocampal theta.

The slope of the speed-theta frequency relationship was consistently positive for both species,

although roughly half that in the ferret compared to the rat (Fig. 3f vs Fig. 3l *Speed vs freq.*;

Mean ± SD across all channels and sessions: rat: 0.026 ± 0.007, ferret: 0.010 ± 0.003). The

depth profiles of theta properties in each animal (both rat and ferret) were determined by probe

position. Only probes that entered the hippocampal formation directly and crossed through the

cell layer and apical dendrites show the modulation of theta power, phase, and speed-power

correlation with depth as seen in Figure 3 (Extended Data Fig. 4).

To group data across varied implant locations, we used histological images and the properties

of theta oscillations along the probe to estimate the anatomical location of electrodes along

the probe for further analysis (Fig. 3f,l, Extended Data Fig. 4a-d). The pyramidal cell layer

(pyr.) was defined by a dip in theta power and the beginning of the theta phase shift. In the

rat, we confirmed the position of the cell layer using the ripple power (Extended Data Fig. 4e).

As theta oscillations have relatively low power in the pyramidal cell layer, we estimated the

location of the stratum oriens (or.) and, where appropriate, the stratum radiatum (rad.) along

each probe. Channels we estimated to be within the stratum oriens consistently showed

positive correlations between theta power and locomotion speed, while channels in the

stratum radiatum were found to have high theta power, occur below the theta phase shift, and

displayed consistent negative speed-power correlation (Fig. 3f,l, Extended Data Fig. 4).

Figure 3: Rat-like theta oscillation in the ferret hippocampus during locomotion occur at 4-7 Hz

a-d, Measuring theta characteristics in the rat. **a,** Power spectral density of the hippocampal LFP recorded from the channel with highest overall power during locomotion in rat R1 in a single session. Orange shading indicates 4-7 Hz range. **b,** Peak-trough method for estimating theta properties. A one second example of neural data during locomotion (from the same channel and session as shown in **a**) with LFP (1 Hz high-pass filtered) shown in grey and theta filtered activity (4-14 Hz) shown in blue. Dashed lines indicate positions of extrema detected on the filtered signal used to estimate the instantaneous amplitude (top), phase (middle) and instantaneous frequency (bottom). Theta frequency is shown overlaid on spectrogram of the above LFP signal (normalised to maximum). **c-d,** Relationship between locomotor speed and theta frequency (**c**) or theta power (**d**) for the same channel as shown in **a** for one recording session. Data points in black represent median values in 250 ms epochs; grey markers show excluded data when the animal was not moving (< 10 cms⁻¹). Box plots show median, interquartile range and 9th to 91st percentile of frequency/power binned by speed (5 cms⁻¹ bins). Speeds over the 90th percentile of head speed were excluded (>55 cms⁻¹) due to small sample sizes and are not shown for clarity. Regression line fitted to median values in each speed bin are shown in pink; text shows regression parameters. **e,** Nissl-stained section of the hippocampus of rat R1 showing the estimated electrode track position (grey bar). **f,** Depth profile of theta characteristics for a single recording session of rat R1. *Theta filtered:* LFP signal filtered between 4 and 14 Hz shown for each channel as a function of probe depth.

Figure 3: Rat-like theta oscillation in the ferret hippocampus during locomotion occur at 4-7 Hz cont.

f cont., *Theta power:* power profile across the probe. Data shown as medians across probe with interquartile (filled line) and 9th to 91st percentile (dashed) range. *Theta phase:* phase shift for each channel relative to the top channel on the probe. Data shown as circular mean and standard deviation[91]. *Speed vs freq.:* Regression slope of locomotion speed and theta frequency across the probe. *Speed vs pow.:* Regression slope of locomotion speed and theta power across the probe. Filled markers indicate significant regressions (Bonferroni corrected p < 0.0016). Estimated position of hippocampal layers based on theta depth profiles shown with grey shading (stratum oriens, or.; stratum pyramidale, pyr., stratum radiatum, rad.) **g-j,** Measuring theta characteristics in the ferret, same as **a-d** but with data from one recording session of ferret F3$_L$; theta filter bandwidth for the ferret is 2-8 Hz and is shown in orange. **k,** Nissl-stained section of the hippocampus of ferret F3$_L$ showing the estimated electrode track position (grey bar). **l,** As in **f** but showing depth profile of theta characteristics (filtered 2-8 Hz) for a single recording session of ferret F3$_L$.

Low-frequency oscillatory activity persists during immobility in the ferret

When rats stop moving, the LFP typically transitions from the theta state to large irregular

activity (LIA), characterised by a large irregular amplitude and broadband low frequency

activity (Fig. 4a). However, in the ferret, we observed robust low-frequency oscillatory activity

regardless of the locomotor state of the animal (Fig. 4b). When identifying theta oscillations in

the rat, the delta-theta power ratio is often used to distinguish theta from high power periods

of LIA as there would still be power in the theta band after filtering (see Fig. 3d). The low

frequency range of theta in ferrets meant we were unable to use the delta-theta ratio. To

directly compare theta oscillations across species, we therefore adopted a metric designed to

measure the regularity of an oscillatory signal by parameterising autocorrelograms of LFP

epochs (Extended Data Fig. 5).

We first segmented LFP data into 1 second epochs and calculated the autocorrelations of

each epoch (see Fig. 4c,d and f,g for examples). We then compared the epoch

autocorrelogram with the autocorrelations obtained for sinusoids of varying frequency (4-14

Hz for rats, 2-14 Hz for ferrets, 0.1 Hz increments) and identified the sinusoid that mostly

closely matched the epoch data (defined as the minimum Euclidean distance; Extended Data

Fig. 5a-f). From the autocorrelogram of this best-fitting sinusoid, we estimated the frequency

of the signal present in the original LFP epoch. We also used the best-fitting sinusoid to

Figure 4: Low frequency oscillatory activity persists during immobility in the ferret hippocampal LFP

a-b, 20 seconds of example data from one rat (**a**, R2) and one ferret (**b**, F1ₗ). *Top:* Head speed showing multiple periods of immobility and movement. *Middle:* LFP traces from stratum oriens (or.) and stratum radiatum (rad.) corresponding to the speed trace above. *Bottom:* Spectrogram of rad. LFP above, normalised to maximum power. **c-d,** Example data segments illustrating the autocorrelation-based method of quantifying oscillatory activity from LFP recorded during locomotion (**c**) and immobility (**d**) in R2 rad. (*top*: blue line) and corresponding autocorrelation (*bottom*: black). The matched sinusoid wave autocorrelation (grey) is used for frequency estimation and peak range estimation. Green line indicates the uncorrected peak range measurement for this example, vertical grey line indicates peak range of matched sinusoid used for normalisation. Text shows mean speed in example epochs. **e,** Scatter plot and marginal histograms showing estimated frequency and peak range for all epochs from one session recorded in rat R2. Each marker represents one epoch and is coloured by mean head speed. Green markers show the position of the example epochs from **c** (diamond) and **d** (square).

Figure 4: Low frequency oscillatory activity persists during immobility in the ferret hippocampal LFP cont.
f-h, Quantification of oscillatory activity in ferret F1$_L$ shown as in c-e. **i,** Comparison of peak range for immobile (mean speed < 5 cms^{-1}, grey markers) vs. moving (mean speed > 20 cms^{-1}, blue markers) epochs for each rat for data from stratum oriens (or.) and stratum radiatum (rad.). Note that not every probe crossed the stratum radiatum. Each marker represents median for all epochs data from one recording session. Box plots show median, interquartile range and 9th to 91st percentile across sessions. **j,** Difference in peak range (moving – immobile) for data shown in **i** (rat data, blue) and **k** (ferret data, orange). **k,** as in **i** but for each ferret probe.

measure the range of the first autocorrelogram peak (green lines in Fig. 4c,d,f,g; Extended

Data Fig. 5g). The peak range measured from the epoch autocorrelogram was then

normalised by the peak range of the matched sinusoid. Using this method, highly periodic

signals in the theta range would result in peak range values approaching one, whereas white

noise (or signals with uniform spectra) would produce peak range values near zero. The

transition from theta oscillations to LIA that occurs during immobility in rats should therefore

be indicated by a reduction in autocorrelation range. To test this, we also measured the mean

speed of head movement in each epoch for which theta oscillations were analysed.

In the moving rat, theta oscillatory activity was indeed reflected by high values for the

autocorrelation peak range (Fig. 4c,e), with frequencies of 9.6 ± 0.6 Hz (mean ± SD; Fig. 4e).

In contrast at low speeds, autocorrelograms were flatter, and thus the peak range lower (Fig.

4d,e), over a broader range of frequencies (7.7 ± 1.6 Hz; Fig. 4e), as would be expected for

LIA. The increase in peak range values associated with locomotion in the rat was consistent

across animals for theta recorded in both the stratum oriens and radiatum (Fig 4i,j), and indeed

across all channels (Extended Data Fig. 6a).

In the ferret, we did not see the same consistent locomotor-related increases in peak range

that were clearly observed in rats (Fig. 4f-j; Extended Data Fig. 6b). The difference between

peak range values during locomotion and immobility were smaller in ferrets compared to rats,

particularly in the stratum radiatum, where a small increase was observed in immobility

compared to locomotion for one site (F3$_L$; Fig. 4k). In the stratum oriens, two sites from probes

which crossed the pyramidal cell layer (F1$_L$, F3$_R$), showed low peak range values during both

locomotion and immobility (Fig 4k). The low values in these sites may be due to the relatively

low theta power observed during both locomotion and immobility (Extended Data Fig. 6b). The

frequency of ferret theta during movement was lower than that found in the rat, consistent with

our earlier findings (5.7 ± 0.5 Hz; Fig. 4h). The frequency range associated with activity during

immobility (4.6 ± 0.7 Hz) was ~ 1 Hz lower than that during locomotion and was less variable

than that found in the rat.

As in the rat, Type 1 theta in the ferret showed a characteristic saw-tooth shape, as indicated

by the large harmonic peak in PSDs of the LFP during locomotion (Fig. 3a,g, Extended Data

Figure 6c-h). Further investigation of the immobility-related oscillatory activity in the ferret

suggested that this activity was more sinusoidal (Extended Data Fig. 6d-h).

Using a linear mixed-effects model to compare effects of locomotion between rats and ferrets,

we found a significant interaction between locomotor state and species in predicting peak

range values (LMM, t = 152.0, p < 0.001; Table 1). We then modelled the species data

independently to better estimate the single-factor fixed effect of locomotion on peak range

values. Both rats and ferrets showed a significant increase in peak range values during

locomotion, however the rat (β_1 = 0.19, t = 270.8, p < 0.001) had a far greater coefficient, an

order of magnitude higher than the ferret (β_1 = 0.017, t = 19.3, p < 0.001). These data indicate

that while theta oscillations generally disappear during immobility in the rat, they often persist

throughout immobile periods in the ferret.

Immobility-related oscillatory activity in the ferret is abolished by atropine

Next, we sought to determine whether oscillations observed during immobility in the ferret

were sensitive to the anticholinergic drug atropine and thus might reflect the occurrence of

Type 2 theta. These experiments included an additional ferret (F4; Extended Data Fig. 7)

implanted with a microdrive that allowed tetrodes to be positioned in the hippocampus. Two

ferrets (F1, F4) were given atropine sulphate (i.p., >0.6 mg kg^{-1}) prior to recording. Testing

was limited to localisation of auditory but not visual stimuli (due to the effects of atropine on

pupil dilation).

Figure 5: Immobility-related oscillatory activity in the ferret is abolished by atropine

a-b, 20 seconds of example data from ferret F4 in a control session (**a**) where no atropine was administered (No-drug control, -A) and test session (**b**) with atropine administered (+A). *Top:* Head speed showing multiple periods of immobility and movement. *Middle:* LFP trace (1 Hz highpass filtered, 50Hz notch filtered) from a channel estimated to be below the cell layer. *Bottom:* LFP spectrogram, normalised to maximum power. **c-d,** Examples of autocorrelation peak range during (**c**) immobility (speed < 5 cms⁻¹) and (**d**) locomotion (speed >20 cms⁻¹), without (-A; immobile: grey, moving: orange) and with (+A; green) administration of atropine *Top:* One second example LFPs. The mean head speed in the example epochs are indicated. *Bottom:* Corresponding autocorrelograms of the LFP epochs above (black line) overlaid on the matched sinusoid wave autocorrelograms (grey line). Black vertical line indicates the uncorrected peak range measurement for these examples, vertical grey line indicates peak range of matched sinusoid used for normalisation. **E,** Comparison of autocorrelation peak range for data during locomotion without (-A; grey) and with (+A, green) atropine for 3 channels across 2 ferrets. Each marker represents a 1 second data epoch. Box plots show median, interquartile range and 9th to 91st percentile. **f,** β₁ coefficients for linear mixed-effects models predicting peak range values based on drug condition for immobile and moving data independently. Lines indicate 5-95% confidence intervals. **g,** as in (**e**) but for moving data.

We estimated the position of the tetrodes in F4 using the theta power-speed relationship (Extended Data Fig. 7) and identified recording sites near the cell layer (F4$_{periCL}$: consistently positive theta power-speed relationship) or below the cell layer (F4$_{subCL}$: consistently negative theta power-speed relationship). Figure 5a shows example data from a F4$_{subCL}$ channel during a drug-free control session in which robust theta oscillations were visible both during movement and immobility. However, when atropine was administered, theta oscillations at the same recording location were selectively disrupted when the animal was immobile, but not during movement (Fig. 5b).

To quantify the effects of atropine on theta oscillations, we used the same autocorrelation-based method described above to measure instantaneous theta power in movement and immobility for all recordings (e.g. Fig. 5c,d). Atropine suppressed theta oscillations during immobility, as reflected by significant reductions in peak range for recordings in both animals and both regions around the cell layer (Fig. 5e). During movement (epochs with mean speed >20 cms^{-1}), atropine administration had no effect on the abundance of theta oscillations (Fig. 5g). A linear mixed-effects model on peak range confirmed a significant interaction between locomotor state and drug condition (Supplementary Table 3). Modelling the peak range for each locomotor state individually showed that atropine administration significantly reduced peak range during immobility but had no significant effect during locomotion (Fig. 5f). Together, these results are consistent with the properties of Type 2 theta and reflect its widespread occurrence in the ferret hippocampus during periods of stillness.

Type 2 theta in the ferret is modulated by behavioural state

We next explored how Type 1 and Type 2 theta may be modulated in the rat and ferret during the behavioural task. We selected three epochs of interest (Fig. 6a,b: when the animals were immobile and holding at the centre spout to initiate a trial (Hold); locomotion to the goal location (Run); and when the animals were immobile and receiving reward (Reward).

Autocorrelograms were calculated for each epoch, and we measured the peak range as

before to quantify the theta oscillations (Fig. 6c,d).

In the rat, we observed that, consistent with the earlier locomotor-related increase in theta,

theta measured using peak range was greater during Run epochs than Hold and Reward

epochs, both for individual recording areas (e.g. stratum radiation in R1: Fig. 6e) and across

all channels (Fig. 6f). Run values were consistently higher than Hold and Reward epochs for

all rats, in both the stratum oriens (LMM, Hold vs Run β_1 = -0.285, t = -74.07, p < 0.001;

Reward vs Run β_1 = -0.31, t = -79.54, p < 0.001) and stratum radiatum (LMM, Hold vs Run β_1

= -0.211, t = -53.37, p < 0.001; Reward vs Run β_1 = -0.23, t = -59.10, p < 0.001; Fig. 6g;

Extended Data Fig. 8a; Supplementary Table 4). We did see some evidence of trials with Type

2 theta in the rat, particularly in rat R1 (Fig. 6e, Extended Data Fig. 9a), however these were

in the minority compared with trials where the peak range values were lower, indicating a

switch to LIA.

Surprisingly, in the ferret's stratum radiatum, peak range (i.e. theta power) was significantly

higher in immobile Reward epochs than during Run (Fig. 6h-j; LMM β_1 = 0.11, t = 24.82, p <

0.001; Supplementary Table 5). This effect was observed across all radiatum channels (Fig.

6j; Extended Data Fig. 8b). Hold epochs were consistently lower than Run in the ferret stratum

radiatum (LMM: β_1 = -0.09, t = -20.24, p < 0.001), however the difference between Hold and

Run was smaller for the ferrets than for the rats, indicating the presence of robust Type 2 theta

during the Hold period in the ferret. This can also clearly be observed in trial average

spectrograms (Extended Data Fig. 9). Despite the abundance of Type 2 theta in the ferret

during this behavioural task, we found no impact of task parameters, including stimulus

modality, task difficulty, or performance, on the peak range values in any of the trial epochs

(Extended Data Figure 10g).

Figure 6: Type 2 theta in the ferret is modulated by behavioural state

a-b, Example trials from (**a**) rat R1 and (**b**) ferret F3ʟ. *Top:* Head speed across example trials with Hold (grey shading), Run (rat: blue shading; ferret: orange shading), and Reward (purple shading) epochs highlighted. *Bottom:* Corresponding neural trace (rat: 2 Hz high pass filtered, 50 Hz notch filtered; ferret: 1 Hz high pass filtered, 50 Hz notch filtered) recorded from the stratum radiatum. **c-d,** Autocorrelograms of the LFP segments during the trial epochs highlighted in **a-b:** Hold (grey, *left plot*), Run (blue/orange, *middle plot*), Reward (purple, *right plot*); overlaid on the matched sinusoid wave autocorrelation (light grey lines). The black vertical lines illustrate the uncorrected peak range measurement for each epoch, vertical grey line indicates peak range of matched sinusoid used for normalisation. **e,** Scatter plot and marginal histograms showing relationship between LFP trial epoch frequency and normalised autocorrelation peak range for Hold (grey), Run (blue), and Reward (purple) epochs in rat R1. Each marker represents data from a one second epoch from a single trial; data are from all sessions. The markers edged with black show the position of the example epochs shown in **c**. **f,** Autocorrelation peak range for Hold (grey), Run (blue), and Reward (purple) epochs across all probe channels for rat R1; data are from all sessions and are presented as median (solid line) and interquartile range (shaded area).

Figure 6: Type 2 theta in the ferret is modulated by behavioural state cont.

f cont., Channels in the stratum oriens (or.) and stratum radiatum (rad.) are highlighted with horizontal light grey shading. **g,** Normalised autocorrelation peak range for Hold (grey), Run (blue), and Rwd (reward; purple) epochs for each rat (R1 n = 1081, R2 n = 368, R3 = 427 trials) in the stratum oriens (or., *left plot*) and stratum radiatum (rad., *right plot*). Data are presented as median (marker position) and interquartile range (solid line) and normalised to the median Run value; data are from all sessions.

h-i, as in **e-f** but for ferret F3L. **j,** as in **g** but for ferret probes (F1L n = 430, F1R n = 236, F2L n = 421, F3L n = 272, F3R n = 682 trials). For **h-j** ferret Run data are presented in orange.

The enhancement observed in the ferret stratum radiatum was specific to Reward epochs and

was not observed during immobility outside of the task (i.e. spontaneous stillness of ferret

away from centre or peripheral spouts; Extended Data Fig. 8c) or due to spout approach

behaviour (Extended Data Fig. 8e). We also confirmed that there was no relation of reward

enhancement to stimulus activation when behavioural responses overlapped with long-

duration (2 s) stimuli (Extended Data Fig. 8f). Interestingly, error trials showed a very similar

pattern of peak range values across the probe (Extended Data Fig. 8d) which suggests that

consumption of reward may not be necessary for the observed enhancement.

The enhancement of peak range in Reward over Run epochs may be due to the wave shape:

The Reward epochs PSDs did not show harmonic peaks that were evident in Run epoch PSDs

(Extended Data Fig. 10a-f) and skew in a signal reduces the peak range measurement

(simulations, data not shown). The changing frequency of theta during Run, as the animal

rapidly accelerates and decelerates travelling towards the peripheral spout, may have also

acted to decrease peak range values relative to the Reward epochs. Hold epoch PSDs also

did not show the harmonic peaks that were evident in Run epoch PSDs (Extended Data Fig.

10a-f) which suggests that the oscillations observed during both Hold and Reward epochs had

similar wave shapes and were thus likely to emerge from common mechanisms. The

enhancement of peak range in the Reward epochs compared to Hold epochs in the ferret

stratum radiatum appears to be driven by increased theta power during Reward epochs

(Extended Data Fig. 10a). Together these data illustrate behavioural modulation of Type 2

theta oscillations in the ferret specific to particular hippocampal layers.

Discussion

Here we provide the first characterisation of theta oscillations in the ferret hippocampus, with

parallel behavioural and electrophysiological experiments in rats providing ground data for

direct comparison between species. In both species, theta was present during locomotion,

and possessed similar properties including the relationship of theta frequency with running

speed, and a theta phase shift observed passing through the pyramidal cell layer. However,

the frequency of theta in the ferret during locomotion (4-7 Hz), was lower than that typically

observed in the rat (5-12 Hz). It has been suggested that the frequency of theta oscillations

decreases with brain size across species to facilitate interregional communication across the

brain[63]. Our results do not directly contradict this theory as ferret brains are considerably larger

than rat brains; however, the frequency of theta we observe in ferrets is similar to that reported

in earlier studies in the cat[64] and dog[65]; species phylogenetically closer to the ferret, but with

significantly larger brain sizes[66]. This raises the possibility that species of the same Order or

Family share similar hippocampal theta characteristics, rather than simply a direct relationship

between theta frequency and brain size.

We found a remarkable difference between the behavioural states eliciting theta between the

two species in this study. Whereas theta oscillations in rats give way to large irregular activity

during immobility (a finding we replicate from numerous earlier studies[24,25]), theta oscillations

in ferret hippocampus remain robust across both movement and immobility. The effectiveness

of atropine in disrupting theta oscillations during immobility in ferrets strongly suggest that

oscillatory activity during this period reflects Type 2 theta previously described in the rat[24]. The

dose of atropine required to abolish Type 2 theta in the ferret (0.6 mg/kg) was considerably

lower than previously used in rodents[24,26,33] (25-50 mg/kg), in keeping with the typical dosages

of atropine used clinically in humans and carnivores, compared with the high doses needed

to compensate for rodents' high levels of atropinase activity. The physiological differences

between rodents and carnivores that give rise to species differences in the effective dose of

atropine may also explain the abundant theta activity in ferret hippocampus. The theta

generation network has several control points at which neuromodulator (cholinergic) tone may

influence the propensity to oscillate, including membrane oscillations[67], firing resonance[68], and

intra-hippocampal network oscillations[69]. It may be that for ferrets, higher cholinergic tone

keeps the hippocampus in a predominantly oscillatory state.

Recent work has reported respiration-coupled oscillatory activity in the hippocampus of

rodents that occurs at a similar frequency to, but independently of, theta oscillations[70,71]. While

the olfactory system is a dominant sense for ferrets, their breathing rate is ~0.5 Hz[72], and so

we do not believe that theta is directly tied to a respiratory related signal. Sniffing however,

would occur at a higher frequency than respiration and we are currently unable to quantify

sniffing in our animals. We do not believe that sniffing accounts fully for the abundance of

theta we observe in the ferret: it is unlikely that ferrets are sniffing continually during the ballistic

approach to peripheral targets, or while drinking water rewards.

With the exception of primates and bats, all mammals studied to date have shown robust theta

oscillations during locomotion[73]. Species differences have previously been observed in the

occurrence of Type 2 theta. The proportion of Type 2 theta observed in the rat is broadly

representative of rodents in general, with one notable exception being the rabbit[24,74], where

atropine-sensitive Type 2 theta has been reliably evoked by sensory stimulation. During

immobile periods distinct from sensory stimulation in the rabbit, LIA was reported to occur.

The key difference between the ferret and the rabbit seems to be the default mode of the

hippocampal LFP during stillness; whereas rabbit Type 2 theta is evoked during immobility

related periods of LIA, in the ferret, theta seems to be the dominant mode of activity regardless

of locomotor state, at least in the behavioural task in this study. This may also be true of dogs,

who are the closest phylogenetic relative to ferrets that have been studied; the example traces

in the few papers recording from dogs show robust oscillatory activity resembling that

observed in ferrets[65,75,76]. Cats, another close relative, also showed an abundance of Type 2

theta which was correlated to visual attention and was reported to be larger in amplitude than

theta during locomotion[64,77,78].

The broader reasons why Type 2 theta is so much more prevalent in ferrets than rats are

unclear. Active sensation cannot account for the abundance of theta observed in the ferret nor

the behavioural modulation of Type 2 theta we observe. Given the link between Type 2 theta

and attention/arousal, one might expect increased theta power during the hold period as

animals are attentive and waiting for the stimulus. However, this was not what we observed,

rather the Type 2 theta oscillations in the ferret were strongest during receipt of reward. We

looked to ferrets for an intermediate animal in terms of sensory strategy between experts of

proximal (rat) and distal (bat, primate) sensation, yet the ferret has proved to be at an extreme

of theta abundance. This places ferrets as an interesting counterpoint to the bat in particular,

where non-oscillatory phase coding[79] indicates that oscillatory activity is not necessary for the

temporal organisation of hippocampal processing.

One surprising consequence of persistent theta in the ferret is the absence of widespread LIA

normally seen in rodents, during which sharp wave ripples and hippocampal replay occur. The

two-stage model of memory formation[80] posits that switches between theta and sharp wave

states in rodents reflect shifts between memory encoding and reactivation, respectively. This

leaves open the question of whether ferrets use the same reactivation strategy as rats, or if

Type 2 theta can serve a similar function to the sharp wave state during immobility in the ferret;

the enhancement of theta during a period of reward consumption could support such a

hypothesis. One avenue that will be important to explore in future is sleep in ferrets, as well

an extensive search for the presence of sharp-wave ripples during both sleep and awake

states.

Ferrets are a valuable addition to the repertoire of model species in hippocampal research in

which it will be interesting to explore the contribution to natural behaviours. For example,

ferrets can navigate over large home ranges in feral colonies[81,82] while their proclivity for

exploration is reflected in the verb "to ferret" (aptly meaning "to industriously search"). As

obligate carnivores that rely on predation for survival, ferrets display prey tracking behaviours

that can be evoked in a laboratory setting[83]. It will be interesting to explore the contribution of

the hippocampal formation to these natural behaviours.

Together our results show that ferrets offer a valuable model organism for hippocampal

research that compliments and builds upon insights gained through studies with rodents. Both

rats and ferrets demonstrated Type 1 theta during movement, indicating a degree of

conserved function across species; however, the theta frequency in ferrets was lower than

rats, and thus closer to that observed in humans and other primates. Ferrets also show

widespread Type 2 theta during immobility that is relatively rare in rodents. This suggests that

ferrets may provide a vital window into functions of the hippocampal formation that have been

difficult to isolate in more commonly used species and thus open new avenues to expand our

understanding of oscillatory activity in behaviour.

Methods

Rats

Three adult male Lister Hooded rats were used in this study, during which they performed behavioural tasks and received hippocampal implants for chronic electrophysiological recording. Rats were supplied from Charles River at 250 g at 7 weeks old and were acclimatized for at least one week prior to the onset of behavioural training. Animals were typically housed in groups of 2 to 4 prior to surgery and then housed individually following electrode implantation. Access to water in the home cage was ad libitum. Access to food in the home cage was ad libitum except during periods of behavioural sessions during which food intake was restricted. During food restriction, rats received a minimum of 15 g of food per day as rewards during testing; if the minimum amount food was not eaten during testing, the remaining food was supplemented at the end of the day. The animals' weight was monitored throughout the course of behavioural training and testing. If animals dropped below 90 % of their target weight, they were taken off study and given free access to food. Animals were housed under a 12:12 hr light-dark cycle (lights on 12:30 pm to 11:30 am; dusk 11:30 pm to 12:30 pm; lights off 12:30am to 11:30am; dawn 11:30 am to 12:30 pm).

All rat experimental procedures performed were first approved by a local ethical review committee. Procedures were carried out under license from the UK Home Office in accordance with the Animals (Scientific Procedures) Act 1986 and PPLs 70/8636 and 70/8637.

Rat surgical procedures

Rats were unilaterally implanted with 32 channel linear probes (NeuroNexus, A1x32-Edge-5mm-100-177). Contacts were positioned down the edge of the shank and had 100 µm spacing. Implants were targeted at the right dorsal hippocampus: 2.6 mm lateral and 3.48 mm posterior to Bregma and were implanted 3.4 mm below the cortical surface.

All surgical tools were sterilized using high temperature steam in an autoclave, or with ethanol

where necessary. Aseptic technique was used throughout the surgical procedures. General

anaesthesia was initially induced via 3% isofluroane in oxygen in an anaesthetic chamber.

Anaesthesia was maintained throughout the surgery with 2% isofluorane in oxygen. Body

temperature was maintained at 37 degrees using a heat mat positioned underneath the

animal. Animals were held in a stereotaxic frame (DigiW Wireless Digital Stereotaxic frame,

Neurostar, Tubingen, Germany) during surgical procedures. An incision was made down the

midline to expose the central crest of the skull; retracted skin was held in place with hemostat

clamps. The exposed skull was cleaned using a scalpel blade and then hydrogen peroxide.

Stereotaxic coordinates were used to mark the position of the craniotomy. Using a high-speed

drill (Foredom 1474 micromotor high-speed drill) and a 1.2 mm burr (Fine Science Tools

GmbH, Germany), five holes were drilled outside of the marked craniotomy locations into

which small stainless steel bone screws were placed. Another screw was inserted into the

interparietal bone near the lambdoid suture and was used as a ground reference for the

electrode. A dental adhesive resin cement (Super-Bond, C&B, Sun Medical Company Ldt.,

Japan) was applied around the five bone screws. A craniotomy of approximately 1 mm

diameter was then performed with the drill and a 0.7 mm burr (Fine Science Tools GmbH,

Germany). A needle was used to make a small hole in the dura at the target implantation

region. The electrode was positioned above the exposed cortex using the stereotaxic arm and

then carefully inserted into the brain. The craniotomy was then filled with sterile Vaseline, and

the implant was built up around the electrode with bone cement (Simplex Rapid, Kemdent,

Associated Dental Products Ltd, UK). Once the electrode was initially secured, the ground

wire was wrapped around the ground screws. Bone cement was further used to build up the

implant, into which the ground wire was embedded. A custom-designed, 3D-printed plastic rail

was also secured onto the implant with dental acrylic, which was used to mount a custom 3D

printed cone and secure the headstage in place. Finally, the wound was sutured to obtain a

smooth margin around the implant.

Immediately following surgery, animals were closely observed in a heated chamber until the

full recovery of motor function, and the rat had been seen to eat and drink. Under veterinary

advice, oral administration of meloxicam (0.5mg/ml; Metacam, Norbrook Labs Ldt., UK) was

given to the animals for three days following the surgery to reduce inflammation. Animals were

given a 7-day recovery period post-surgery during which they did not perform any behavioural

sessions.

Rat histology

Following the completion of recordings, rats were administered a terminal overdose of Euthatal

(400mg/kg of pentobarbital sodium; Merial Animal Health Ltd, Harlow, UK) prior to transcardial

perfusion. During perfusion, the blood vessels were washed with 0.9% saline followed by 400-

500 ml 100% formalin. Brains were then extracted and stored in 100% formalin for at least 24

hours. The extracted brains were immersed in a 30% sucrose solution for three days until they

sank. Brains were then coronally sectioned at 40 µm using a freezing microtome (Leica

CM1850). Every section was stained for Nissl substance to allow the electrode tracks to be

observed. Sections were mounted and imaged using an Axio Scan slide scanner (Zeiss).

Rat equipment and data acquisition

Rats were trained and tested in a custom-built sound-proof chamber (IAC Acoustics). Within

this chamber was a raised track composed of 3 segments: a centre platform and two response

arms. The custom-built centre platform was designed to hold an infra-red (IR) sensor (Sharp)

at approximate rat head height. There were two additional IR sensors fixed under the response

arms. Reward ports were positioned at the ends of the response arms into which food rewards

were dispensed using a pellet dispenser (Campden Instruments Ltd., UK). Light emitting

diodes (LEDs; Kingbright Whites) were mounted within a diffusive plastic case above the

reward port at the end of the response arms. Loudspeakers were mounted adjacent to the

track, positioned to face the centre platform. Stimulus generation and task automation was

performed using custom written MATLAB (MathWorks) scripts which communicated with a

Tucker-Davis Technologies (TDT) signal processor (RZ6, Tucker-Davis Technologies,

Alachua, FL) and an Arduino Uno.

Rat neural data were recorded during behavioural sessions using a Neuralynx Digital Lynx

acquisition system. Voltage signals were recorded at 30 kHz, then digitised and amplified

directly on the headstage. Signals were band-pass filtered between 0.1 Hz and 10 kHz and

transmitted to a personal computer running Neuralynx Cheetah acquisition software. The

behavioural metadata (e.g. stimulus and nose poke times) were also transmitted to the

Cheetah acquisition software from the TDT signal processor and the Arduino via TTL pulses

sent to the Digital Lynx. A video camera was installed in the ceiling of the chamber which

communicated with the Neuralynx Cheetah processor, allowing for real-time monitoring of the

animal during the task. Video data were collected at 25 frames per second. A red and green

LED were attached to the wireless headstage and the positions of these LEDs were tracked

online during recordings with the Neuralynx Cheetah software.

Ferret

Four adult female pigmented ferrets (*Mustela putorius furo*) were used in this study, during

which they performed behavioural tasks and received hippocampal implants for chronic

electrophysiological recording. Ferrets were obtained at 7 weeks of age. Behavioural training

began when the animals were at least 16 weeks old and weighed a minimum of 700 g.

Animals were typically housed in groups of 2 to 8 and were given ad libitum access to high-

protein food pellets; ferrets with free access to water (i.e. not undergoing behavioural testing)

were housed in separate groups to those under water restriction (i.e. undergoing behavioural

testing). During testing, water was removed from the home cage on the evening prior to the

first testing day; training typically began on Mondays and thus water restriction began on

Sunday evening. Ad libitum access to water in the home cage was reinstated at the end of a

testing run. Testing runs typically lasted 5 days, and so access to water was typically given on

Friday evenings. During water restriction, ferrets received a minimum of 60 ml/kg of water per

day either as water rewards during testing or supplemented as wet food (a mixture of ground

high-protein pellets and water) and/or a small volume of water at the end of the day. Animals

were weighed daily during behavioural testing to ensure that body weight did not drop below

85% of the starting weight measured on the first day of the testing run. Animals were housed

under a 14:10 hr light-dark cycle in summer (lights on 06:00 to 20:00) and a 10:14 hr light-

dark cycle in winter (lights on 08:00 to 18:00). During change over periods the light times were

moved by 1 hr per week. All animals underwent regular otoscopic examinations to ensure their

ears were clean and healthy.

All ferret experimental procedures performed were first approved by a local ethical review

committee. Procedures were carried out under license from the UK Home Office in accordance

with the Animals (Scientific Procedures) Act (1986) and PPL 70/7278 and 70/7267.

Hippocampal targeting in ferrets

At the time of this project, there was no atlas to guide electrode implantation in the ferret,

therefore target positions were estimated prior to the surgeries by constructing three

dimensional (3D) reconstructions of two ferret brains. Nissl-stained coronal sections (50 μm

thick, 200 μm spacing) were imaged using a Zeiss AxioScan Z1 slide scanner. Rigid-body

registration was performed using a custom written MATLAB script to align the images. 3D

models were then constructed using IMOD, an open-source image processing program

(Kremer et al., 1996). The 3D models allowed for the gross anatomy of the ferret hippocampus

to be visualised. The implantation target was the septal (dorsal) pole of the hippocampus, as

the majority of rodent studies have recorded from this region of the hippocampus. Target

implant positions in the dorsal hippocampus were visualised in the 3D models and measurements were made with reference to other brain landmarks (Table 1).

Due to the unreliable nature of landmarks on the ferret skull (He et al., 2002), and considerable inter-animal variability in the gross anatomical structure of the brain and skull, defining stereotaxic coordinates for hippocampal implantation was best achieved using the pattern of gyral and sulcal curvature. As the lab has developed reliable landmarks for exposing the middle ectosylvian gyrus (MEG; 11 mm from midline, 12 mm from back of skull), where the auditory cortex (AC) is located, it was decided that the top of the MEG would serve as a reference landmark for the location of the hippocampal craniotomy. Using the 3D models, measurements of the implant target position were taken with reference to the top of the MEG. The hippocampal implant target was on the lateral gyrus (LG) and so the midline and the lateral sulcus were chosen as additional reference landmarks to guide the position of the implant. The 3D model was also used to measure the depth on the dorsoventral axis needed to reach the hippocampus from the cortical surface.

Reference location	Distance (mm)
Medial from MEG	6.6 ± 1.0
Dorsal from MEG	4.6 ± 0.4
Rostral from MEG	2.3 ± 0.3
Lateral from midline	3.3 ± 0.2
Medial from LG	1.8 ± 0.3
Depth of cell layer below cortical surface	5.4 ± 0.3

Table 1: Measurements from 3D model of ferret brain for electrode implant target. Distance is

reported as mean ± standard deviation, n = 4.

Ferret surgical procedures

All surgical tools were sterilized using high temperature steam in an autoclave, via ethylene

oxide, or with cold sterilant where necessary. Aseptic technique was used throughout the

surgical procedures. General anaesthesia was initially induced via an intramuscular injection

of medetomidine (Dormitor, 0.022 mg/kg, Pfizer) and ketamine (Ketaset, 5 mg/kg, Fort Dodge

Animal Health). Animals were then intubated and ventilated; anaesthesia was maintained

throughout the surgery with 1.5 % isofluorane in oxygen. An intravenous (I.V.) line was

inserted, and a saline solution was continuously infused. Heart rate, end-tidal C02, and body

temperature were monitored throughout the surgery. Body temperature was maintained at

37°C using a heat mat positioned underneath the animal, which was controlled via closed-

loop feedback of the animal's body temperature. Animals were held in a stereotaxic frame

(Kopf Instruments, USA) and the area around the midline over the skull was infused with the

local anaesthetic bupivacaine (Marcain, AstraZeneca, UK). An incision was made down the

midline to expose the central crest of the skull; retracted skin was held in place with hemostat

clamps. Unilaterally, a section of temporal muscle was separated from the skull and then

removed using electrocautery tongs. The exposed skull was cleaned using 1% citric acid

solution (0.1 g in 10 ml H_2O) to prevent muscle regrowth, and a dental adhesive resin cement

(Super-Bond, C&B, Sun Medical Company Ldt., Japan) was applied. The location of the AC

craniotomy was marked on the skull, and as this was used as a reference for the approximate

location of the hippocampal craniotomy. Using a drill (DREMEL 4000 rotary tool), two holes

were made outside of the marked craniotomy locations, into which small stainless steel bone

screws were placed, which both anchored the implant and provided an electrical ground for

recordings.

To determine the location of the MEG, an AC craniotomy of approximately 3 x 3 mm was

performed. The portion of skull removed was retained in sterile saline; upon localisation of the

implantation target with reference to the MEG (see Section 2.3.1), the skull segment was

returned to the AC craniotomy. The hippocampal craniotomy location was marked around the

implantation target, and a second craniotomy (3 x 3 mm) was then performed. This craniotomy

location was mirrored and marked on the other side of the skull for the contralateral implant.

To implant each probe, a small hole was made in the dura at the target implantation region.

The electrode was positioned above the exposed cortex using a micromanipulator and then

carefully inserted into the brain. The craniotomy was then filled with a silicone elastomer

adhesive (KwiK-Sil, World Precision Instruments, UK), and the implant was built up around

the electrode with bone cement (Palacos R+G, Heraeus Medical, UK). Once the electrode

was initially secured, the ground wire was wrapped around two of the small screws in the skull,

which functioned as reference for the electrode. Bone cement was further used to build up the

implant, into which the ground wire was embedded. This procedure was then repeated on the

other side of the skull, although no AC craniotomy was performed as the hippocampal

craniotomy location was already determined. Once complete, the implant was built up further

with bone cement and small metal hooks were embedded, which served to secure the

headstage during neural recordings. Excess skin was then removed, and the wound was

sutured to obtain a smooth margin around the implant.

Microdrive Implantation

The surgical procedure for implantation of the tetrode microdrive was similar to that outlined

above for the linear probes. However, this implant was unilateral due to the large footprint of

the microdrive. Upon localisation of the unilateral hippocampal craniotomy in the same manner

as described above, the contralateral temporal muscle was retracted. The exposed skull was

then cleaned with citric acid, and Super-Bond was applied. Two bone screws were then

inserted into the skull. The drive was then implanted, grounded, and secured in bone cement

as detailed above.

 Post-operative care

Immediately following surgery, animals were closely observed until the full recovery of motor

function and had been seen to eat and drink. Under veterinary advice, post-operative

medication was given to the animals for up to 5 days: subcutaneous (S.C.) injections of 0.5

ml/kg buprenorphine (0.3 mg/ml; Vetergesic, Alstoe Animal Health Ldt, UK) for analgesia; oral

administration of 0.1 mg/kg meloxicam (0.5mg/ml; Loxicom, Norbrook Labs Ldt., UK) to reduce

inflammation; and antibiotics were given as S.C. injections of 0.1 ml/kg amoxicillin (150 mg/ml;

Amoxycare, LA). Animals were given a minimum of 7 days recovery post-surgery during which

they did not undergo any procedures. Animals were housed singularly for the initial 3-4 days

following the surgery and then housed in a pair for the remainder of the recovery period. After

the recovery period, animals were again housed in groups of 2-8, with grouping determined

by whether the animals were undergoing behavioural testing (and thus water restriction) or

whether they had free access to water.

Ferret histology

Following the completion of recordings, ferrets were administered a terminal overdose of

Euthatal (400mg/kg of pentobarbital sodium; Merial Animal Health Ltd, Harlow, UK) prior to

transcardial perfusion. For ferret implants F2 L, F3 L and F4 L electrolytic lesions were

performed prior to perfusion using a current generator (A365 Stimulus Isolator, World

Precision Instruments, FL, US); a unipolar current of 30 µA was passed through electrodes

for 10 s, after which the polarity was reversed and another 10 s of 30 µA current was passed.

In animals with linear probe implants (F2 L and F3 L), pairs of electrodes at the top, middle

and tip of the probes were lesioned. For the tetrode animal (F4 L), one wire on each tetrode

was lesioned. During perfusion, the blood vessels were washed with 0.9% saline followed by

1.5 to 2L 4% paraformaldehyde in 0.1 M phosphate buffer. Brains were then extracted and

stored in 4% paraformaldehyde for at least 24 hours. The extracted brains were immersed in

a 30% sucrose solution for three days until they sank. Brains were then coronally sectioned at

50 μm using a freezing microtome (Leica CM1850). Every 4th section was stained for Nissl

substance to allow the electrode tracks to be observed. Sections were mounted and imaged

using an Axio Scan slide scanner (Zeiss).

Ferret equipment and data acquisition

Ferrets were trained and tested in a custom-built sound-proof chamber. Within this chamber

was a circular arena of 50 cm radius, with walls and ceiling made with strong plastic mesh. In

the centre of the arena floor, an acrylic spout was mounted at approximate ferret head height

onto a plastic platform. The spout was connected to tubing, through which a water reward

could be given, and also contained an infra-red (IR) sensor (OB710, TT electronics, UK) to

detect nose-pokes. Eleven additional acrylic spouts, all with water tubing and IR sensors, were

inserted through the wire mesh wall at equidistant locations (30° separation) around the

periphery of the arena, with the exception of the position directly behind the centre spout. Light

emitting diodes (King bright White 8 mm) were attached to the back of the spouts in such a

way that the acrylic acted as waveguides; when the LEDs were active, the spouts themselves

emitted light. This LED positioning was implemented to make responding at the spout more

intuitive by combining stimuli and response locations. Loudspeakers (Visaton FRS 8) were

mounted 3.5 cm behind the arena wall, in line with each spout. For the localisation task, only

the 5 front spouts (-60°, -30°, 0°, +30° and +60°) were used to allow for both auditory and

visual testing.

Stimulus generation and task automation was performed using custom written MATLAB

(MathWorks Inc., Natick, USA) scripts which communicated with TDT signal processors (RX8,

RS8, and RZ2). Two cameras were installed in the ceiling of the chamber: a webcam, for

monitoring of the animal during the task; and a Prosilica GC650C camera (Allied Vision

Technologies) with a wide angle lens (1.8 mm 3.6 mm FL, Varifocal Video Lens, Edmund

Optics) which communicated with a TDT RV2 video processor to track red and green LEDs attached to the animal's headstage, and thus the head position of the animal, with high precision (30 frames per second).

Ferret neural data were recorded during behavioural sessions using a wireless recording system (Wirelss-2100-System, Multi Channel Systems GmbH, Germany). Voltage signals were recorded at 20 kHz, then digitised and amplified 100 times directly on the headstage. Signals were band-pass filtered between 0.1 Hz and 10 kHz, and transmitted to a wireless receiver which communicated with a personal computer running Multi Channel Suite software. The wireless system was synchronised with the TDT signal processors via a TTL pulse sent from the TDT RX8 signal processor to the MCS interface board.

Atropine administration in the ferret

Ferrets F1 and F4 received I.P. injections of atropine sulphate. Atropine sulphate has been used to abolish Type II theta in the rat[24,26,33,84], rabbit[24], guinea pig[85] and cat[86]. However, no protocol was found for the administration of atropine to investigate the effects on neural signals in the hippocampus of the ferret. Therefore, a protocol was developed based on the previous literature and with consultation of a veterinarian.

The most common route of atropine delivery in the literature was intra-peritoneal (I.P.) injection. The dose of atropine given in previous studies to rats and guinea pigs was relatively high (25-50 mg/kg) compared to the pre-anaesthetic dose given to ferrets prior to surgery (0.05 mg/kg). Cats received a dose of 1 mg/kg[86] and as fellow Carnivorans, cats are phylogenetically closer to ferrets than rats. Therefore, a gradually increasing dose of I.P. atropine sulphate from 0.05 mg/kg to 1 mg/kg was administered to the ferrets over the course of several weeks. The impact of atropine administration at each dose on the animal's health and general behaviour was monitored, both within and outside of behavioural testing, using a specifically developed score sheet. A dose of 0.6 mg/kg was found to be effective in

manipulating neural activity in the ferret hippocampus. We therefore included only sessions

with doses of 0.6 mg/kg and higher for analysis.

For behavioural testing following the administration of atropine, the task was modified with

removal of visual stimuli and a reduction of the background illumination level in the testing

chamber. Light levels were lowered as atropine is known to cause dilation of pupils and so

animals may have become abnormally light sensitive. The length of time the animal had to

hold its head in place at the centre spout to trigger a trial was also reduced to make trial

initiation easier. In some early sessions following atropine administration, locomotion was

elicited by experimenter interaction with the ferret; in later sessions the animals acclimated to

the drug effects and did not need additional motivation for movement. The drug-free control

sessions used for comparison were interleaved with atropine sessions, typically recorded one

to three days after any given atropine session, and used the same modified task as the

atropine sessions.

Common methods

Behavioural training and testing

<u>Behavioural training</u>

Behavioural training procedures for the rat and ferret were broadly similar (Table 2). Due to

equipment and licensing constraints across the two labs in which this work was performed,

the rats received food reward and the ferrets received water reward. Both reward types were

sufficient motivation for the animals to perform the behavioural task.

Rats and ferrets were trained to perform approach-to-target localisation tasks with auditory (A;

white noise burst) and visual (V; LED flash) stimuli. Rats performed a two-choice task with two

peripheral stimuli locations (approx. -60° and 60°) while ferrets performed a 5-choice task with

stimuli presented at 30° intervals.

Training stage	Rat	Ferret
Pre-training	Association of centre nose-poke spout with reward.	Association of centre nose-poke spout with reward.
Stage 1	Centre nose-poke triggered flashing AV stimuli (250ms duration) which was presented continuously until animals responded correctly. Incorrect response had no effect. Hold time gradually increased from 10 to 300 ms. Centre nose-poke gives no direct reward.	Centre nose-poke triggered flashing A or V stimuli (250ms duration) which was presented continuously until animals responded. Incorrect trials triggered noise burst and light flash from all peripheral locations. Hold time gradually increased from 500 to 1000 ms. Gradual decrease to zero in centre reward probability.
Stage 2	Unimodal (A or V) stimuli gradually introduced, incorrect response ends trial and triggered 250 ms error sound (10 kHz pure tone) Hold time gradually increased to between 2.5 and 3.5 seconds.	Stimulus presented as 2 second single stimulus. Hold time gradually increased to between 2.5 and 3.5 seconds.

730 Table 2. Protocols used to train rats and ferrets

Behavioural testing

Once trained, both rats and ferrets performed approach-to-target localisation tasks. The task structure was identical across species. To trigger a trial, the animal was required to hold in a nose-poke at the centre spout for a hold time, the duration of which was pseudorandomly chosen from five possibilities between 2.5 s and 3.5 s. Once triggered, an auditory (A; broadband noise burst) or visual stimulus (V; white LED flash) was presented in a noisy background at the periphery of the arena. The location and modality of stimulus was pseudorandomly chosen for each trial.

Within a session, stimuli presented were unimodal (A or V). To receive reward, animals were required to approach the location at which the stimulus was presented. Incorrect responses triggered error responses (rat: 250 ms 20 kHz pure tone; ferret: 100 ms sound and light noise burst). To prevent biasing in ferret's responses to particular spouts, incorrect responses were followed by "correction trials", where the stimulus from the previous trial was repeated until the animal made a correct response. Ferrets could receive up to five correction trials before the trial was aborted and the next trial was initiated. Rats did not receive correction trials. If either species did not respond within 60 s, the trial was aborted, and the animal was then able to trigger the next trial. Aborted trials were excluded from the current analysis because the animals were not engaged with the behavioural task.

During testing, the task switched between blocks of easy trials and blocks of hard trials; blocks were 15 trials long. Difficulty was increased by either reducing stimulus duration ("Duration task") or reducing the signal-to-noise ratio (SNR; "SNR task"; see Table 3 for stimuli used). Only one method of increasing difficulty was employed within a session (i.e. stimulus SNR was fixed while duration was varied and vice versa). Difficulty was gradually increased as the animals' performance increased. Within a stimulus modality, the easy condition was identical for both Duration and SNR tasks.

Auditory SNR was calculated as the difference between target signal and background noise

in dB SPL. Sound levels were calibrated using a measuring amplifier (Bruel & Kjær Type

2610). For the ferret, the background noise level was increased to reduce stimulus SNR, while

for the rat the target sound level was decreased. Visual SNR was calculated as the ratio of

the luminous intensity of the target signal, to the luminosity of the background signal.

Luminosity measurements were taken using a photometer (Chroma meter CS-100 A). For

both species, visual SNR was reduced by increasing background light level.

Species	Rat				Ferret			
Task type	Duration (ms)		SNR (dB SPL / a.u.)		Duration (ms)		SNR (dB SPL / a.u.)	
Modality	A	V	A	V	A	V	A	V
Easy	2000	2000	24.7	768.5	2000	2000	22.9 to 28.9	30.8
Hard	40 to 1000	10 to 1000	1.0 to 17.5	2.5 to 20.4	40 to 1000	80 to 1000	-0.1 to 11.1	1.5 to 6.9

766   Table 3: Summary of stimuli used for all behavioural testing

768   All animals were trained on both visual and auditory stimuli, however rat R2 suffered damage

769   to his hearing during implant surgery and therefore was only tested with visual stimuli.

Data cleaning

Head tracking

A red and green LED were attached to the head along the midline of both species and the positions of these LEDs were tracked. Position data for the rat was tracked online using the Neuralynx Cheetah software. Ferret position data was tracked offline with custom written MATLAB scripts. For both species, the tracking data were processed and cleaned offline with custom written MATLAB scripts. Large reflections were removed from tracking data using the following constraints: (1) an LED was not permitted to travel over 50 pixels in one frame, (2) the two LEDs were required to be within 30-50 pixels of each other (depending on the exact headstage configuration). Linear interpolation was used to fill gaps of less than 660 ms in the data and traces were smoothed using a median filter (width = 5). For the rat, tracking data were excluded when the door to the sound chamber was open, measured through average intensity of the image, and when the LEDs were out of the field of view for > 0.5 s. The average position of the two LEDs was used to estimate the head position of the animal, and subsequently the animal's head speed across frames.

Neural data cleaning

Neural data were extracted and processed using custom written MATLAB (MathWorks Inc., Natick, USA) scripts. Neural data were downsampled to 1 kHz. As large amplitude movement artefacts and other noise artefacts (e.g. due to wireless signal dropping out, headstage becoming unplugged etc.) were observed during recordings, a cleaning algorithm was implemented to detect and remove noise artefacts. The cleaning algorithm was run over data from each session individually.

Channels were excluded from analysis on the basis of the power spectral density (PSD; Welch's method, Hanning window, nfft = 4096) if (1) the power in the theta band was below a certain threshold (< 2 dB for ferrets, < 4 dB for rats), or (2) the 50 Hz noise power was too high (threshold set relative to the theta power). Sessions were excluded if all channels were

removed at this stage of cleaning. For the atropine sessions, the channels selected for

analysis were based on the PSDs from control sessions without atropine.

Large amplitude movement artefacts and other noise artefacts on the remaining channels

were removed using an algorithm which used the fact that noise artefacts were present on all

channels of the probe. The mean amplitude across all channels was found and peaks in this

were identified by thresholding. To calculate the noise threshold, the mode of the distribution

of mean channel amplitudes was found and multiplied by an empirically chosen factor of 10.

Identified noise artefacts were then replaced with NaNs. Zeros and saturation points (for digital

systems) were also identified and removed.

Further cleaning steps were developed for the rat neural data, as scratching artefacts were

observed that were not always detected with the initial cleaning algorithm. Furthermore, the

scratching artefacts occurred within the hippocampal theta range at 8-12 Hz, so accurate

removal of these was imperative. During scratching artefacts, power in the 6-13 Hz band was

high across all channels of the probe, including the third of recording sites at the top of the

probe that were positioned in the cortex above the hippocampus (channels 1 to 10). During

periods of clean neural recording, the power in this band was usually much lower on these

channels than during scratching artefacts and so the following protocol was implemented:

(1) A 1 kHz resampled signal from each channel within a session was filtered between 6-13

Hz using a zero-lag FIR filter (order = 500 ms), and the 6-13 Hz power across each channel

was found using the Hilbert transform.

(2) The median 6-13 Hz power of the cortical channels was calculated across the session.

(3) A power threshold was calculated using the mode of the distribution of median power

calculated in (2).

(4) Sections of the signal where the median 6-13 Hz power for cortical channels exceeded the

threshold were removed from all channels on the probe and replaced with NaNs.

The scratching artefact removal algorithm also identified and removed putative epochs of high-

voltage spike-wave (HVS) events as described by Haggerty and Ji (2014). These epochs were

characterised by a high amplitude 8 Hz oscillation in the cortex and the hippocampus, with

higher power in the cortex than the hippocampus. A smooth power profile across the probe

was also observed, suggesting it reflected a biological process as opposed to a noise artefact.

The waveform of the observed oscillatory events closely resembled those described for HVS

(Haggerty and Ji 2014; data not shown). As the waveform and power profile of these events

did not resemble theta oscillations, the epochs were deemed not appropriate for inclusion in

the current study and were removed from the signals.

Data Analysis

The theta filter parameters used in this study were: rat 4-14 Hz, Finite Impulse Response (FIR)

filter of order 500 ms; ferret: 2-8 Hz, FIR filter of order 1000 ms.

<u>Peak-trough detection method</u>

Peak-trough detection has been used previously to calculate the instantaneous frequency and

phase of hippocampal theta oscillations in the rat[32]. A recently published toolbox also employs

peak-trough detection to detect and characterise neural oscillations[87].

Here, the instantaneous frequency, phase, and power of the filtered signal was estimated

using a custom written peak-trough detection method. A peak-trough detection algorithm was

used to estimate the instantaneous frequency, phase, and power of filtered signals. Signals

were scanned on a point-by-point basis, searching for extrema within a voltage range

(empirically set to 0.25 x median amplitude of the signal across the session). The detected

extrema were constrained to look for alternate peaks and troughs. Instantaneous frequency

was estimated by calculating the mean between the peak frequency (i.e. the inverse of the

time between peaks) and the trough frequency. Instantaneous amplitude was calculated as

the mean of the absolute values of the peak amplitude and the trough amplitude, from which

the power was calculated. Instantaneous phase was found by setting the peaks at 0° and the

troughs at 180° and interpolating the phase between these points.

<u>Determination of hippocampal layers</u>

To group data across varied implant locations, electrode sites in three hippocampal layers

were estimated using the depth properties of theta oscillations (Fig. 3, Extended Data Fig. 4)

and histological data. In probes where the hippocampal formation was entered directly, the

pyramidal cell layer (pyr.) was defined by a dip in theta power and the beginning of the theta

phase shift. In the rat, the position of the cell layer was confirmed using the ripple power

(Extended Data Fig. 4). As theta oscillations have relatively low power in the pyramidal cell

layer, the location of the stratum oriens (or.) and, where appropriate, the stratum radiatum

(rad.) were then estimated. In probes that crossed the pyramidal cell layer, an electrode site

200 μm above the pyramidal cell layer was selected as the stratum oriens. For the estimation

of an electrode within the stratum radiatum, the distance between the cell layer and the stratum

radiatum/lacunosum-moleculare border was measured (which can be clearly observed in Nissl

staining) for each probe and used this distance (typically 400 μm) to select a channel for

analysis. The area of stratum radiatum recorded from would thus be close to the stratum

radiatum/lacunosum-moleculare border and have high theta power. In probes that did not

cross the cell layer, and thus did not show theta modulation, the stratum oriens channel was

typically chosen as the channel with the highest theta power, which also aligned with the

estimates of the stratum oriens location from histological data.

<u>Autocorrelation metric of oscillatory activity</u>

The LFP was first high-pass filtered using IIR (Infinite Impulse Response) filters (rat: 6th-order

high-pass Chebyshev Type II filter with 80 dB of stopband attenuation and a passband edge

frequency of 2 Hz; ferret: 4th-order high-pass Chebyshev Type II filter with 80 dB of stopband

attenuation and a passband edge frequency of 1Hz) and 50 Hz notch filtered (14th-order band-

stop Chebyshev Type II filter with 60 dB of stopband attenuation, pass-band edge frequencies

of 48 and 52 Hz and stop-band frequencies of 49 and 51 Hz). The signal was then segmented

into one second epochs and autocorrelograms were calculated for each epoch. For each

autocorrelogram, the Euclidean distance (ED) to the autocorrelations of sine waves of varying

frequency (4-14 Hz for the rat, 2-14 Hz for the ferret, 0.1 Hz increments) was calculated. The

ED between the data and the sine autocorrelograms was normalised by the ED of the

individual ED of each sine autocorrelogram. The 'matched' sine autocorrelogram (i.e. with the

minimum Euclidean distance from the data epoch autocorrelogram) was used to identify the

first autocorrelogram peak. The range of this peak was measured from the maxima of the first

peak to the average of the two surrounding troughs. This peak range measurement was then

normalised by the peak range of the matched sine, as the peak range was found to vary as a

function of frequency. The frequency of the signal in the data epoch was estimated as the

frequency of the sine wave that was used to calculate the matched sine autocorrelogram.

The head speed signal was also segmented into corresponding 1 second epochs, for which

the mean speed was found for each epoch. For comparison of moving vs. immobile epochs

(Figure 4, 5) conservative speed thresholds were chosen to ensure good separation of

locomotor contingencies (moving vs. immobile) given that speeds were averaged over a one

second window.

Detection of trial epochs

Hold windows were defined as -1.05 to -0.05 seconds prior to stimulus onset. Run windows

were taken as the 1 s prior to peripheral response. Reward windows were defined as the first

1 second window following peripheral response with speed consistently below 5 cms^{-1}. For

the rat, reward windows had the additional constraint of being on the maze arm where the

peripheral spout was located. Only correct trials were used for the analysis in Figure 6.

Statistics

Linear mixed-effects models (R, LME4[88,89]) were used for statistical analysis to account for the

nested structure of the data. For all LMMs we modelled the peak range for each 1 second

epoch as the response variable.

For the data in Figure 4, locomotor state (MovFlag: moving vs immobile) and species (rat vs

ferret) were modelled as fixed effects with an interaction, and ID (R1, R2, R3, F1, F2, F3) and

session as random effects. Channel (oriens vs radiatum) was also included as a fixed effect.

The full model was as follows:

906   PeakRange ~ MovFlag * Species + Chan + (1 | Species/ID/Session)

907   A significant interaction was observed (see Table 1) so the data were then split by species to

908   get an accurate estimate of the effect of locomotor state on peak range:

909               $PeakRange_{RAT}$ ~ MovFlag + Chan + (1 | ID/Session)

910               $PeakRange_{FERRET}$ ~ MovFlag + Chan + (1 | ID/Session)

911   For the atropine data (Figure 5), we modelled the interaction between locomotor state and

912   drug condition (DrugFlag: atropine vs control) with ID, channel, and session modelled as

913   random effects:

914   PeakRange ~ MovFlag * DrugFlag + (1 | ID/Chan/Session)

915   A significant interaction between locomotor condition and drug condition was found, and so

916   the data were then split by locomotor condition to get an accurate estimate of the effect of

917   atropine on peak range:

918               $PeakRange_{MOV}$ ~ DrugFlag + (1 | ID/Chan/Session)

919               $PeakRange_{IMM}$ ~ DrugFlag + (1 | ID/Chan/Session)

920   For trial data (Figure 6), we modelled the effect of trial epoch on peak range values (Table 3)

921   for rats and ferrets separately. For each species, trial epoch (Hold, Run, Reward) and channel

922   were modelled as fixed effects with an interaction, with ID and session as random effects. The

Run epoch was selected as the reference factor. Only correct trials were included in this analysis.

$$PeakRange \sim Epoch * Chan + (1 \mid ID/Session)$$

A significant interaction between channel and epoch was observed, and so the data were then split by channel to get an accurate estimate of the effect of trial epoch on peak range:

$$PeakRange_{OR} \sim Epoch + (1 \mid ID/Session)$$

$$PeakRange_{RAD} \sim Epoch + (1 \mid ID/Session)$$

Behavioural tasks were fully automated and controlled by custom software such that the experimenter did not influence either the order in which trials were presented and the behavioural outcome of a trial. Neural data collection was also fully automated. Experimenters were not blind to the species, or to whether drug or no drug were given in the atropine experiments. Data analysis pipelines were fully automated. Criteria and rational for exclusion of data (e.g. movement artefacts) are stated throughout the methods and were implemented automatically in MATLAB.

Data and code are available at https://github.com/slsdunn/theta-paper-code

Author Contributions: S.D., J.K.B., and D.B. designed the experiment; S.D. and S.T. collected and analysed data; S.D., S.T., J.K.B., and D.B., wrote and revised the manuscript.

Acknowledgments:

S.D. UCL SenSyt

J.B. Royal Society/Wellcome Sir Henry Dale Fellowship (098418/Z/12/Z), ERC Consolidator award (SOUNDSCENE)

D.B. ERC starter grant (CHIME) and HFSP Young Investigator Award (RGY0067/2016)

946   We thank Katherine Wood, Gareth Jones, and Huriye Atilgan for assistance with data

947   collection, and the members of the Bizley and Bendor labs for valuable discussion. We also

948   thank Suzanne Radtke-Schuller for up-to-date anatomical subdivisions of the ferret

949   hippocampus and Noelia Lopez for her help in developing the atropine protocol.

References

1.   O'Keefe, J. & Dostrovsky, J. The hippocampus as a spatial map. Preliminary evidence

from unit activity in the freely-moving rat. *Brain Res.* **34**, 171–175 (1971).

2.   Hafting, T., Fyhn, M., Molden, S., Moser, M.-B. & Moser, E. I. Microstructure of a

spatial map in the entorhinal cortex. *Nature* **436**, 801–806 (2005).

3.   Taube, J. S., Muller, R. U. & Ranck, J. B. *Head-Direction Cells Recorded from the

Postsubiculum in Freely Moving Rats. I. Description and Quantitative Analysis. The

Journal of Neuroscience* http://www.cogsci.ucsd.edu/~sereno/201/readings/08.04-

HeadDirCells.pdf (1990).

4.   O'Keefe, J. Hippocampus, theta, and spatial memory. *Curr. Opin. Neurobiol.* **3**, 917–

924 (1993).

5.   Buzsáki, G. Theta oscillations in the hippocampus. *Neuron* **33**, 325–340 (2002).

6.   Buzsáki, G. & Moser, E. I. Memory, navigation and theta rhythm in the hippocampal-

entorhinal system. *Nature Neuroscience* vol. 16 130–138 (2013).

7. Colgin, L. L. Mechanisms and Functions of Theta Rhythms. *Annu. Rev. Neurosci.* **36**,
295–312 (2013).

8. Winson, J. Loss of hippocampal theta rhythm results in spatial memory deficit in the
rat. *Science (80-.).* **201**, 160–163 (1978).

9. Mitchell, S. J., Rawlins, J. N., Steward, O. & Olton, D. S. Medial septal area lesions
disrupt theta rhythm and cholinergic staining in medial entorhinal cortex and produce
impaired radial arm maze behavior in rats. *J. Neurosci.* **2**, 292–302 (1982).

10. M'Harzi, M. & Jarrard, L. E. Effects of medial and lateral septal lesions on acquisition
of a place and cue radial maze task. *Behav. Brain Res.* **49**, 159–165 (1992).

11. Wang, Y., Romani, S., Lustig, B., Leonardo, A. & Pastalkova, E. Theta sequences are
essential for internally generated hippocampal firing fields. *Nat. Neurosci.* **18**, 282–
288 (2015).

12. McNaughton, N., Ruan, M. & Woodnorth, M. A. Restoring theta-like rhythmicity in rats
restores initial learning in the Morris water maze. *Hippocampus* **16**, 1102–1110
(2006).

13. Hasselmo, M. E., Bodelón, C. & Wyble, B. P. A proposed function for hippocampal
theta rhythm: Separate phases of encoding and retrieval enhance reversal of prior
learning. *Neural Comput.* **14**, 793–817 (2002).

14. Mizuseki, K., Sirota, A., Pastalkova, E. & Buzsáki, G. Theta Oscillations Provide
Temporal Windows for Local Circuit Computation in the Entorhinal-Hippocampal
Loop. *Neuron* **64**, 267–280 (2009).

15. Jezek, K., Henriksen, E. J., Treves, A., Moser, E. I. & Moser, M. B. Theta-paced
flickering between place-cell maps in the hippocampus. *Nature* **478**, 246–249 (2011).

16.   Kay, K. *et al.* Constant Sub-second Cycling between Representations of Possible
Futures in the Hippocampus. *Cell* **180**, 552-567.e25 (2020).

17.   Jones, M. W. & Wilson, M. A. Theta Rhythms Coordinate Hippocampal and Prefrontal
Interactions in a Spatial Memory Task. *PLoS Biol.* **3**, e402 (2005).

18.   Siapas, A. G., Lubenov, E. V. & Wilson, M. A. Prefrontal phase locking to
hippocampal theta oscillations. *Neuron* **46**, 141–151 (2005).

19.   Grion, N., Akrami, A., Zuo, Y., Stella, F. & Diamond, M. E. Coherence between Rat
Sensorimotor System and Hippocampus Is Enhanced during Tactile Discrimination.
PLoS Biol. **14**, e1002384 (2016).

20.   Bush, D., Barry, C., Manson, D. & Burgess, N. Using Grid Cells for Navigation.
Neuron **87**, 507–520 (2015).

21.   Lisman, J. E. & Jensen, O. The Theta-Gamma Neural Code. *Neuron* vol. 77 1002–
1016 (2013).

22.   Hasselmo, M. E. & Stern, C. E. Theta rhythm and the encoding and retrieval of space
and time. *NeuroImage* vol. 85 656–666 (2014).

23.   Bland, B. H. The physiology and pharmacology of hippocampal formation theta
rhythms. *Prog. Neurobiol.* **26**, 1–54 (1986).

24.   Kramis, R., Vanderwolf, C. H. & Bland, B. H. Two types of hippocampal rhythmical
slow activity in both the rabbit and the rat: Relations to behavior and effects of
atropine, diethyl ether, urethane, and pentobarbital. *Exp. Neurol.* **49**, 58–85 (1975).

25.   Vanderwolf, C. H. Hippocampal electrical activity and voluntary movement in the rat.
Electroencephalogr. Clin. Neurophysiol. **26**, 407–418 (1969).

26.   Buzsáki, G., Czopf, J., Kondákor, I. & Kellényi, L. Laminar distribution of hippocampal
rhythmic slow activity (RSA) in the behaving rat: Current-source density analysis,

effects of urethane and atropine. *Brain Res.* **365**, 125–137 (1986).

27.   O'Keefe, J. & Recce, M. L. Phase relationship between hippocampal place units and

the EEG theta rhythm. *Hippocampus* **3**, 317–330 (1993).

28.   Klausberger, T. *et al.* Brain-state- and cell-type-specific firing of hippocampal

interneurons in vivo. *Nature* **421**, 844–848 (2003).

29.   Bragin, a *et al.* Gamma (40-100 Hz) oscillation in the hippocampus of the behaving

rat. *J. Neurosci.* **15**, 47–60 (1995).

30.   Colgin, L. L. & Moser, E. I. Hippocampal theta rhythms follow the beat of their own

drum. *Nat. Neurosci.* **12**, 1483–1484 (2009).

31.   Scheffer-Teixeira, R. *et al.* Theta phase modulates multiple layer-specific oscillations

in the CA1 region. *Cereb. Cortex* **22**, 2404–2414 (2012).

32.   Belluscio, M. A., Mizuseki, K., Schmidt, R., Kempter, R. & Buzsáki, G. Cross-

frequency phase-phase coupling between θ and γ oscillations in the hippocampus. *J.*

Neurosci. **32**, 423–35 (2012).

33.   Lai-Wo Stan Leung. Spectral analysis of hippocampal EEG in the freely moving rat:

Effects of centrally active drugs and relations to evoked potentials.

Electroencephalogr. Clin. Neurophysiol. **60**, 65–77 (1985).

34.   Sainsbury, R. S., Heynen, A. & Montoya, C. P. Behavioral correlates of hippocampal

type 2 theta in the rat. *Physiol. Behav.* **39**, 513–519 (1987).

35.   Whishaw, I. Q. Hippocampal electroencephalographic activity in the Mongolian gerbil

during natural behaviours and wheel running and in the rat during wheel running and

conditioned immobility. *Can. J. Psychol.* **26**, 219–239 (1972).

36.   Montoya, C. P., Heynen, A. J., Faris, P. D. & Sainsbury, R. S. Modality Specific Type

2 Theta Production in the Immobile Rat. *Behav. Neurosci.* **103**, 106–111 (1989).

37.   Seidenbecher, T., Laxmi, T. R., Stork, O. & Pape, H. C. Amygdalar and hippocampal

1042   theta rhythm synchronization during fear memory retrieval. *Science (80-.).* **301**, 846–

1043   850 (2003).

1044   38.   Bland, B. H. & Oddie, S. D. Theta band oscillation and synchrony in the hippocampal

1045   formation and associated structures: The case for its role in sensorimotor integration.

1046   *Behav. Brain Res.* **127**, 119–136 (2001).

1047   39.   Mikulovic, S. *et al.* Ventral hippocampal OLM cells control type 2 theta oscillations and

1048   response to predator odor. *Nat. Commun.* **9**, 1–15 (2018).

1049   40.   M. Aghajan, Z. *et al.* Theta Oscillations in the Human Medial Temporal Lobe during

1050   Real-World Ambulatory Movement. *Curr. Biol.* **27**, 3743-3751.e3 (2017).

1051   41.   Bush, D. *et al.* Human hippocampal theta power indicates movement onset and

1052   distance travelled. *Proc. Natl. Acad. Sci. U. S. A.* **114**, 12297–12302 (2017).

1053   42.   Watrous, A. J. *et al.* A Comparative Study of Human and Rat Hippocampal Low-

1054   Frequency Oscillations During Spatial Navigation. *Hippocampus* **23**, 656–661 (2013).

1055   43.   Jacobs, J. Hippocampal theta oscillations are slower in humans than in rodents:

1056   Implications for models of spatial navigation and memory. *Philos. Trans. R. Soc. B*

1057   *Biol. Sci.* **369**, 20130304 (2014).

1058   44.   Bohbot, V. D., Copara, M. S., Gotman, J. & Ekstrom, A. D. Low-frequency theta

1059   oscillations in the human hippocampus during real-world and virtual navigation. *Nat.*

1060   *Commun.* **8**, 14415 (2017).

1061   45.   Goyal, A. *et al.* Functionally distinct high and low theta oscillations in the human

1062   hippocampus. *Nat. Commun.* **11**, 2469 (2020).

1063   46.   Ulanovsky, N. & Moss, C. F. Hippocampal cellular and network activity in freely

1064   moving echolocating bats. *Nat. Neurosci.* **10**, 224–233 (2007).

47.   Yartsev, M. M., Witter, M. P. & Ulanovsky, N. Grid cells without theta oscillations in

the entorhinal cortex of bats. *Nature* **479**, 103–107 (2011).

48.   Yartsev, M. M. & Ulanovsky, N. Representation of three-dimensional space in the

hippocampus of flying bats. *Science (80-.).* **340**, 367–372 (2013).

49.   Stewart, M. & Fox, S. E. Hippocampal theta activity in monkeys. *Brain Res.* **538**, 59–

63 (1991).

50.   Jutras, M. J., Fries, P. & Buffalo, E. A. Oscillatory activity in the monkey hippocampus

during visual exploration and memory formation. *Proc. Natl. Acad. Sci. U. S. A.* **110**,

13144–13149 (2013).

51.   Courellis, H. S. *et al.* Spatial encoding in primate hippocampus during free navigation.

PLoS Biol. **17**, e3000546 (2019).

52.   Srinivasan, S., Carlo, C. N. & Stevens, C. F. Predicting visual acuity from the structure

of visual cortex. *Proc. Natl. Acad. Sci. U. S. A.* **112**, 7815–7820 (2015).

53.   Veilleux, C. C. & Kirk, E. C. Visual acuity in mammals: Effects of eye size and

ecology. *Brain. Behav. Evol.* **83**, 43–53 (2014).

54.   Law, M. I., Zahs, K. R. & Stryker, M. P. *Organization of Primary Visual Cortex (Area*

17) in the Ferret. THE JOURNAL OF COMPARATIVE NEUROLOGY vol. 278 (1988).

55.   Hein, A., Courjon, J. H., Flandrin, J. M. & Arzi, M. Optokinetic nystagmus in the ferret:

including selected comparisons with the cat. *Exp. Brain Res.* **79**, 623–632 (1990).

56.   Stitt, I., Zhou, Z. C., Radtke-Schuller, S. & Fröhlich, F. Arousal dependent modulation

of thalamo-cortical functional interaction. *Nat. Commun.* **9**, 1–13 (2018).

57.   Kavanagh, G. L. & Kelly, J. B. Midline and lateral field sound localization in the albino

rat (Rattus norvegicus). *Behav. Neurosci.* **100**, 200–205 (1986).

58.   King, A. J. & Parsons, C. H. Improved auditory spatial acuity in visually deprived

ferrets. *Eur. J. Neurosci.* **11**, 3945–3956 (1999).

59.   McFarland, W. L., Teitelbaum, H. & Hedges, E. K. Relationship between hippocampal

1091   theta activity and running speed in the rat. *J. Comp. Physiol. Psychol.* **88**, 324–328

1092   (1975).

1093   60.   Sławińska, U. & Kasicki, S. The frequency of rat's hippocampal theta rhythm is related

1094   to the speed of locomotion. *Brain Res.* **796**, 327–331 (1998).

1095   61.   Kropff, E., Carmichael, J. E., Moser, E. I. & Moser, M. B. Frequency of theta rhythm is

1096   controlled by acceleration, but not speed, in running rats. *Neuron* **109**, 1029-1039.e8

1097   (2021).

1098   62.   Radtke-Schuller, S. *Cyto- and Myeloarchitectural Brain Atlas of the Ferret (Mustela*

1099   *putorius) in MRI Aided Stereotaxic Coordinates. Cyto- and Myeloarchitectural Brain*

1100   *Atlas of the Ferret (Mustela putorius) in MRI Aided Stereotaxic Coordinates* (Springer

1101   International Publishing, 2018). doi:10.1007/978-3-319-76626-3.

1102   63.   Buzsáki, G., Logothetis, N. & Singer, W. Scaling brain size, keeping timing:

1103   Evolutionary preservation of brain rhythms. *Neuron* **80**, 751–764 (2013).

1104   64.   Grastyán, E., Lissák, K., Madarász, I. & Donhoffer, H. Hippocampal electrical activity

1105   during the development of conditioned reflexes. *Electroencephalogr. Clin.*

1106   *Neurophysiol.* **11**, 409–430 (1959).

1107   65.   Arnolds, D. E. A. T., Lopes da Silva, F. H., Aitink, J. W. & Kamp, A. Hippocampal EEG

1108   and behaviour in dog. I. Hippocampal EEG correlates of gross motor behaviour.

1109   *Electroencephalogr. Clin. Neurophysiol.* **46**, 552–570 (1979).

1110   66.   Jardim-Messeder, D. *et al.* Dogs Have the Most Neurons, Though Not the Largest

1111   Brain: Trade-Off between Body Mass and Number of Neurons in the Cerebral Cortex

1112   of Large Carnivoran Species. *Front. Neuroanat.* **11**, (2017).

67.   Alonso, A. & Llinás, R. R. Subthreshold Na+-dependent theta-like rhythmicity in

stellate cells of entorhinal cortex layer II. *Nature* **342**, 175–177 (1989).

68.   Zemankovics, R., Káli, S., Paulsen, O., Freund, T. F. & Hájos, N. Differences in

subthreshold resonance of hippocampal pyramidal cells and interneurons: The role of

h-current and passive membrane characteristics. *J. Physiol.* **588**, 2109–2132 (2010).

69.   Goutagny, R., Jackson, J. & Williams, S. Self-generated theta oscillations in the

hippocampus. *Nat. Neurosci.* **12**, 1491–1493 (2009).

70.   Nguyen Chi, V. *et al.* Hippocampal Respiration-Driven Rhythm Distinct from Theta

Oscillations in Awake Mice. *J. Neurosci.* **36**, 162–177 (2016).

71.   Lockmann, A. L. V., Laplagne, D. A., Leão, R. N. & Tort, A. B. L. A Respiration-

Coupled Rhythm in the Rat Hippocampus Independent of Theta and Slow

Oscillations. *J. Neurosci.* **36**, 5338–5352 (2016).

72.   *Biology and Diseases of the Ferret. Biology and Diseases of the Ferret* (Wiley-

Blackwell, 2014). doi:10.1002/9781118782699.

73.   Robinson, T. E. Hippocampal rhythmic slow activity (RSA, theta): A critical analysis of

selected studies and discussion of possible species-differences. *Brain Res. Rev.* **2**,

69–101 (1980).

74.   Green, J. D. & Arduini, A. A. Hippocampal Electrical Activity in Arousal. *J.*

Neurophysiol. **17**, 533–557 (1954).

75.   Arnolds, D. E. A. T., Lopes da Silva, F. H., Aitink, J. W. & Kamp, A. Hippocampal EEG

and behaviour in dog. II. Hippocampal EEG correlates with elementary motor acts.

Electroencephalogr. Clin. Neurophysiol. **46**, 571–580 (1979).

76.   Arnolds, D. E. A. T., Lopes da Silva, F. H., Aitink, J. W. & Kamp, A. Hippocampal EEG

and behaviour in dog. III. Hippocampal EEG correlates of stimulus-response tasks

and of sexual behaviour. *Electroencephalogr. Clin. Neurophysiol.* **46**, 581–591 (1979).

77. Whishaw, I. Q. & Vanderwolf, C. H. Hippocampal EEG and behavior: Change in

amplitude and frequency of RSA (Theta rhythm) associated with spontaneous and

learned movement patterns in rats and cats. *Behav. Biol.* **8**, 461–484 (1973).

78. Frederickson, C. J., Smylie, C. S., Howell, G. A. & Lenig, R. B. Movement-dependent

and movement-independent changes in hippocampal RSA in cats11 Preliminary

results from this work were presented at the Society for Neuroscience, Anaheim, CA,

1977. *Brain Res. Bull.* **3**, 559–562 (1978).

79. Eliav, T. *et al.* Nonoscillatory Phase Coding and Synchronization in the Bat

Hippocampal Formation. *Cell* **175**, 1119-1130.e15 (2018).

80. Buzsáki, G. Two-stage model of memory trace formation: A role for 'noisy' brain

states. *Neuroscience* **31**, 551–570 (1989).

81. Norbury, G. I., Norbury, D. C. & Heyward, R. P. Space use and denning behaviour of

wild ferrets and cats. *N. Z. J. Ecol.* **22**, 149–159 (1998).

82. Young, J. B. Movement patterns of two New Zealand mustelids: Implications for

predator pest management. (Lincoln, 1998).

83. Apfelbach, R. & Wester, U. The quantitative effect of visual and tactile stimuli on the

prey-catching behaviour of ferrets (Putorius furo L.). *Behav. Processes* **2**, 187–200

(1977).

84. Robinson, T. E. & Vanderwolf, C. H. H. Electrical stimulation of the brain stem in

freely moving rats: II. Effects on hippocampal and neocortical electrical activity, and

relations to behavior. *Exp. Neurol.* **61**, 485–515 (1978).

85. Sainsbury, R. S. & Montoya, C. P. The relationship between type 2 theta and

behavior. *Physiol. Behav.* **33**, 621–626 (1984).

86. Olmstead, C. E. & Villablanca, J. R. Hippocampal theta rhythm persists in the

permanently isolated forebrain of the cat. *Brain Res. Bull.* **2**, 93–100 (1977).

87.   Cole, S. & Voytek, B. Cycle-by-cycle analysis of neural oscillations. *J. Neurophysiol.*
1164   **122**, 849–861 (2019).

1165   88.   Bates, D., Mächler, M., Bolker, B. & Walker, S. Fitting Linear Mixed-Effects Models
1166   Using lme4. *J. Stat. Softw.* **67**, 1–48 (2015).

1167   89.   Hlavac, M. stargazer: Well-Formatted Regression and Summary Statistics Tables.
1168   (2018).

1169   90.   Paxinos, G. & Watson, C. *The rat brain in stereotaxic coordinates*. (Elsevier Academic
1170   Press, 2005).

1171   91.   Berens, P. CircStat : A MATLAB Toolbox for Circular Statistics. *J. Stat. Softw.* **31**, 1–
1172   21 (2009).

1173